



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- 122A (L166)
- 122A-1 (L166-A)
- Cone Kit: C8R129H
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 6
- Sweep Frequency Hz: 20-1200
- D.C. Resistance Ohms: 4.5 min/5.5 max
- Gap Gauge: .053"
- Notes: Mass Ring. Cone Kit
may have aquaplas on cone instead of mass ring.
- If Not Serviceable, Replace With: 128H-1
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Use as last resort.
Replace both units in a stereo pair.
- Additional Parts Currently Available*:
 - Dome: 31385
 - Mounting Gasket: 20253
 - Trim Gasket: 52806

MID RANGE DRIVER:

- LE5-8
- Cone Kit: C8RLE510
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 4
- Sweep Frequency Hz: 75-3000
- D.C. Resistance Ohms: 5.6 min/6.8 max
- Gap Gauge: .040"
- Notes:
 - If Not Serviceable, Replace With: LE5-12
 - Visual Change: No

MID RANGE DRIVER (Cont'd)

- Baffle Modification: No
 - Exact Acoustic Replacement: Yes
 - Additional Parts Currently Available*:
 - Dome: 51868
 - Trim Gasket: 29931
- HIGH FREQUENCY DRIVER:**
- 066
 - Diaphragm Kit: D8R066
 - Nom. Impedance: 8 Ohm
 - Dynamic Test Input V: 5
 - Sweep Frequency Hz: 200-1200
 - D.C. Resistance Ohms: 3.5 min/4.4 max
 - Gap Gauge: .031"
 - Notes: Test With Network
If Not Serviceable, Replace With: Currently Available.
Can Also Be Replaced With 044.
 - Visual Change: Yes
 - Baffle Modification: Yes
 - Exact Acoustic Replacement: No. Slightly different.
Replace both units in a stereo pair.

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 Ohm
- Power Capacity: 75 Watts Continuous Program
- Crossover Frequencies: 1000 Hz, 6000 Hz
- Sensitivity: 76dB (1 Watt @ 15 Feet)
- Enclosure Dim: 14-1/4" x 23-1/2" x 13" D
36.2cm x 59.7cm x 33cm
- Shipping Weight: 55 lbs. - 25 kg.

*Other parts may also be available. Check with JBL for details.