



SYSTEM COMPONENTS:

- LOW FREQUENCY DRIVER:** 310G-3
 Cone Kit: Kit not available.
 Defective driver should be replaced.
 Nom. Impedance: 4 Ohm
 Dynamic Test Input V: 5
 Sweep Frequency Hz: 30-1200
 D.C. Resistance Ohms: 3.8 min/4.8 max
 Gap Gauge: N/A
 Notes:
 If Not Serviceable, Replace With: Currently Available.
 Can also be replaced with 510G.
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No. Slightly different.
 Replace both units in a stereo pair.
 Additional Parts Currently Available*:
 Mounting Gasket: 60979
- MID RANGE DRIVER:** 305G-3
 Cone Kit: Kit not available.
 Defective driver should be replaced.
 Nom. Impedance: 4 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 3.8 min/4.6 max
 Gap Gauge: N/A
 Notes:
 If Not Serviceable, Replace With: Currently Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A
- HIGH FREQUENCY DRIVER:** 012
 Diaphragm Kit: Kit not available.
 Defective driver should be replaced.

HIGH FREQUENCY DRIVER (Cont'd)

- Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 1000-2000
 D.C. Resistance Ohms: 3.6 min/4.4 max
 Gap Gauge: N/A
 Notes:
 If Not Serviceable, Replace With: Currently Available.
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A
- PASSIVE RADIATOR:** PR310-3
 Cone Kit: Kit Not Available.
 Defective driver should be replaced.
 Notes:
 If Not Serviceable, Replace With: Currently Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A
 Additional Parts Currently Available*:
 Mounting Gasket: 60979

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 Ohm
 Rec. Amp Power Range: 10-150 Watts Per Channel
 Crossover Frequencies: 1100 Hz, 3400 Hz
 Sensitivity: 91dB (1 Watt @ 1 Meter)
 Enclosure Dim: 38-1/16" x 18-1/2" x 12-1/2" D
 987mm x 470mm x 318mm
 Shipping Weight: 65 lbs. - 29.5 kg.
 Additional Parts Currently Available*:
 Grill: GJ350A
 Binding Posts: Red: 63635
 Black: 63636

*Other parts may also be available. Check with JBL for details.