



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:	128H
Cone Kit:	C8R128H
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	6
Sweep Frequency Hz:	20-1200
D.C. Resistance Ohms:	5.1 min/6.3 max
Gap Gauge:	.057"
Notes:	Aquaplas
If Not Serviceable, Replace With:	128H-1
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	Yes
Additional Parts Currently Available*:	
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806
MID RANGE DRIVER:	LE5-12
Cone Kit:	C8RLE510
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	4
Sweep Frequency Hz:	75-3000
D.C. Resistance Ohms:	4.9 min/6.1 max
Gap Gauge:	.040"
Notes:	
If Not Serviceable, Replace With:	Currently Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	51686
Terminal Board:	53225

MID RANGE DRIVER (Cont'd)

Mounting Gasket:	21771
Trim Gasket:	29931
HIGH FREQUENCY DRIVER:	044
Diaphragm Kit:	D8R044
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	2
Sweep Frequency Hz:	2000-12000
D.C. Resistance Ohms:	5.4 min/6.6 max
Gap Gauge:	.032"
Notes:	Test With Network
If Not Serviceable, Replace With:	Currently Available.
Can Also Be Replaced With 034.	
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No. Use as last resort.
Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Mounting Gasket:	62551
Screen:	60424
Screen Gasket:	60752

SYSTEM SPECIFICATIONS:

Nom. Impedance:	8 Ohm
Max Rec. Amp Power::	300 Watts Per Channel
Crossover Frequencies:	1100 Hz, 3700 Hz
Sensitivity:	89dB (1 Watt @ 1 Meter)
Enclosure Dim:	24-1/2" x 14-1/4" x 13" D 622mm x 362mm x 333mm
Shipping Weight:	56 lbs. - 25.5 kg.
Additional Parts Currently Available*:	
Binding Posts: Red:	56131
Black:	56130

*Other parts may also be available. Check with JBL for details.