



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:
 128H
 Cone Kit: C8R128H
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 6
 Sweep Frequency Hz: 20-1200
 D.C. Resistance Ohms: 5.6 min/6.3 max
 Gap Gauge: .057"
 Notes: Aquaplas
 If Not Serviceable, Replace With: 128H-1
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes
 Additional Parts Currently Available*:
 Dome: 31385
 Mounting Gasket: 20253
 Trim Gasket: 52806

MID RANGE DRIVER:
 LE5-10
 Cone Kit: C8RLE510
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 4.9 min/6.1 max
 Gap Gauge: .040"
 Notes:
 If Not Serviceable, Replace With: Currently Available
 or LE5-12
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes
 Additional Parts Currently Available*:
 Dome: 51686
 Mounting Gasket: 21771
 Trim Gasket: 29931

HIGH FREQUENCY DRIVER:
 033
 Diaphragm Kit: D8R033
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 5

HIGH FREQUENCY DRIVER (Cont'd)

Sweep Frequency Hz: 200-1200
 D.C. Resistance Ohms: 3.6 min/4.4 max
 Gap Gauge: .031"
 Notes: Test With Network
 If Not Serviceable, Replace With: 034
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.

Additional Parts Currently Available*:
 Mounting Gasket: 57754

PASSIVE RADIATOR:
 PR300
 Cone Kit: CRPR300

Notes:
 If Not Serviceable, Replace With: No Replacement Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A
 Additional Parts Currently Available*:
 Dome: 31385
 Mounting Gasket: 20253
 Trim Gasket: 52806

SYSTEM SPECIFICATIONS:

Nom. Impedance: 8 Ohm
 Max Rec. Amp Power: 300 Watts Per Channel
 Crossover Frequencies: 1000 Hz, 4000 Hz
 Sensitivity: 88dB (1 Watt @ 1 Meter)
 Enclosure Dim: 41-1/2" x 17" x 13" D
 1054mm x 432mm x 330mm
 Shipping Weight: 90 lbs. - 41 kg.
 Additional Parts Currently Available*:
 Grill: G150BR
 Binding Posts: Red: 56131
 Black: 56130

*Other parts may also be available. Check with JBL for details.