



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:	128H
Cone Kit:	C8R128H
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	6
Sweep Frequency Hz:	20-1200
D.C. Resistance Ohms:	5.1 min/6.3 max
Gap Gauge:	.057"
Notes:	Aquaplas
If Not Serviceable, Replace With:	128H-1
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	Yes
Additional Parts Currently Available*:	
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806
MID RANGE DRIVER:	LE5-12
Cone Kit:	C8RLE510
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	4
Sweep Frequency Hz:	75-3000
D.C. Resistance Ohms:	4.9 min/6.1 max
Gap Gauge:	.040"
Notes:	
If Not Serviceable, Replace With:	Currently Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	51686
Terminal Board:	53225
Mounting Gasket:	21771
Trim Gasket:	29931
HIGH FREQUENCY DRIVER:	O44
Diaphragm Kit:	D8R044
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	2

HIGH FREQUENCY DRIVER (Cont'd)

Sweep Frequency Hz:	2000-12000
D.C. Resistance Ohms:	5.4 min/6.6 max
Gap Gauge:	.032"
Notes:	Test With Network
If Not Serviceable, Replace With:	Currently Available
Can Also Be Replaced With:	034
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No. Use as last resort.
	Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Mounting Gasket:	62511
Screen:	60424
PASSIVE RADIATOR:	PR300
Cone Kit:	CRPR300
Notes:	
If Not Serviceable, Replace With:	No Replacement Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806

SYSTEM SPECIFICATIONS:

Nom. Impedance:	8 Ohm
Max Rec. Amp Power:	300 Watts Per Channel
Crossover Frequencies:	1100 Hz, 3700 Hz
Sensitivity:	89dB (1 Watt @ 1 Meter)
Enclosure Dim:	41-1/2" x 17" x 13" D
	1054mm x 432mm x 330mm
Shipping Weight:	80 lbs. - 36.4 kg.
Additional Parts Currently Available*:	
Grill:	G150BR
Binding Posts:	Red: 56131
	Black: 56130

*Other parts may also be available. Check with JBL for details.