



**SYSTEM COMPONENTS:**

**LOW FREQUENCY DRIVER:** 125A  
 Cone Kit: C8R127A  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 5  
 Sweep Frequency Hz: 30-1200  
 D.C. Resistance Ohms: 4.7 minimum  
 5.7 maximum  
 Gap Gauge: .044"  
 Notes: Dome Inverted

If Not Serviceable,  
 Replace With: 125HR  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No.  
 Slightly different. Replace both units  
 in a stereo pair.

Additional Parts Currently Available\*:  
 Dome: 50201  
 Terminal Board: 52348  
 Mounting Gasket: 52089  
 Trim Gasket: 52315

**HIGH FREQUENCY DRIVER:** LE25-2  
 Diaphragm Kit: D8RLE252  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 3  
 Sweep Frequency Hz: 500-1200

**HIGH FREQUENCY DRIVER (Cont'd)**

D.C. Resistance Ohms: 3.6 minimum  
 4.4 maximum

Gap Gauge: .029"  
 Notes: Kit includes parts  
 for similar models. Use required parts only.

If Not Serviceable,  
 Replace With: 035TiA  
 Visual Change: Yes  
 Baffle Modification: Yes  
 Exact Acoustic Replacement: No. Use as a last  
 resort. Replace both units in a stereo pair.

Additional Parts Currently Available\*:  
 Trim Ring: 53363  
 Mounting Gasket: 50949-01  
 Dome: 21606

**SYSTEM SPECIFICATIONS:**

Nominal Impedance: 8 Ohm  
 Power Capacity: 35 Watts  
 Continuous Program  
 Crossover Frequency: 2000 Hz  
 Sensitivity: 76dB (1 Watt @ 15 Feet)  
 Enclosure Dim: 12-3/4" x 24" x 13-1/4" D  
 324mm x 610mm x 336mm  
 Shipping Weight: 42 lbs. - 19 kg.

Additional Parts Currently Available\*:  
 Binding Posts: Red: 56131  
 Black: 56130

\*Other parts may also be available. Check with JBL for details.