



## SYSTEM COMPONENTS:

### LOW FREQUENCY DRIVER:

127A  
 Cone Kit: C8R127A  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 5  
 Sweep Frequency Hz: 30-1200  
 D.C. Resistance Ohms: 4.8 minimum  
 5.6 maximum

Gap Gauge: .044"

Notes:

If Not Serviceable,

Replace With: 125HR

Visual Change: Yes

Baffle Modification: No

Exact Acoustic Replacement: No.

Slightly different. Replace both units in a stereo pair.

Additional Parts Currently Available\*:

Dome: 50201

Mounting Gasket: 52089

Trim Gasket: 52315

### MID RANGE DRIVER:

LE5-10  
 Cone Kit: C8RLE510  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 4  
 Sweep Frequency Hz: 75-3000  
 D.C. Resistance Ohms: 4.9 minimum  
 6.1 maximum

Gap Gauge: .040"

Notes:

If Not Serviceable,

Replace With: Currently Available or LE5-12

Visual Change: Yes

Baffle Modification: No

Exact Acoustic Replacement: Yes

### MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available\*:

Dome: 51686

Mounting Gasket: 21771

Trim Gasket: 29931

### HIGH FREQUENCY DRIVER:

LE26  
 Diaphragm Kit: D8RLE26  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 3  
 Sweep Frequency Hz: 500-1200  
 D.C. Resistance Ohms: 3.4 minimum  
 4.3 maximum

Gap Gauge: .029"

Notes:

If Not Serviceable,

Replace With: 035TiA

Visual Change: Yes

Baffle Modification: Yes

Exact Acoustic Replacement: No. Use as last resort. Replace both units in a stereo pair.

Additional Parts Currently Available\*:

Trim Ring: 57732

Mounting Gasket: 50949-02

Dome: 21606

## SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm  
 Max Recommended Amp Power: 70 Watts  
 Crossover Frequencies: 800 Hz, 3000 Hz  
 Sensitivity: 88dB (1 Watt @ 1 Meter)  
 Enclosure Dim: 24-1/2" x 14-1/4" x 12-11/32" D  
 622mm x 362mm x 314mm  
 Shipping Weight: 47 lbs. - 21 kg.  
 Additional Parts Currently Available\*:  
 Binding Posts: Red: 56131  
 Black: 56130

\*Other parts may also be available. Check with JBL for details.