



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER: 127H
 Cone Kit: C8R127A
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 5
 Sweep Frequency Hz: 30-1200
 D.C. Resistance Ohms: 4.8 minimum
 5.6 maximum

Gap Gauge: .044"
 Notes:
 If Not Serviceable,
 Replace With: 125HR
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.

Additional Parts Currently Available*:

Dome: 50201
 Terminal Board: 52348
 Mounting Gasket: 52089
 Trim Gasket: 52315

MID RANGE DRIVER: LE5-10
 Cone Kit: C8RLE510
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 4.9 minimum
 6.1 maximum

Gap Gauge: .040"
 Notes:
 If Not Serviceable,
 Replace With: Currently Available or LE5-12
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available*:

Dome: 51686
 Mounting Gasket: 21771
 Trim Gasket: 29931

HIGH FREQUENCY DRIVER: LE26
 Diaphragm Kit: D8RLE26
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 3
 Sweep Frequency Hz: 500-1200
 D.C. Resistance Ohms: 3.4 minimum
 4.3 maximum

Gap Gauge: .029"
 Notes: Plastic Flange

If Not Serviceable,
 Replace With: 035TiA
 Visual Change: Yes
 Baffle Modification: Yes
 Exact Acoustic Replacement: No. Use as last
 resort. Replace both units in a stereo pair.

Additional Parts Currently Available*:

Trim Ring: 57732
 Mounting Gasket: 50949-02
 Dome: 21606

SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm
 Max Recommended
 Amp Power: 200 Watts
 Crossover Frequencies: 800 Hz, 3000 Hz
 Sensitivity: 88dB (1 Watt @ 1 Meter)
 Enclosure Dim: 24-1/2" x 14-1/4" x 12-11/32" D
 622mm x 362mm x 314mm
 Shipping Weight: 47 lbs. - 21 kg.
 Additional Parts Currently Available*:
 Binding Posts: Red: 56131
 Black: 56130

*Other parts may also be available. Check with JBL for details.