



N/A

SYSTEM COMPONENTS:

FULL RANGE DRIVER: LE8T
 Cone Kit: C8RLE8T
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 20-1200
 D.C. Resistance Ohms: 5.1 minimum
 5.9 maximum
 Gap Gauge: .048"
 Notes: Aquaplas On Cone.
 Bond 2 foam pads to underside of dome.
 If Not Serviceable,
 Replace With: LE8T-H
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.
 Additional Parts Currently Available*:
 Dome: 21219
 Mounting Gasket: 21769
 Trim Gasket: 21812

PASSIVE RADIATOR

Cone Kit: PR8
 Notes: CRPR8
 If Not Serviceable,
 Replace With: No Replacement Available
 Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic
 Replacement: N/A
 Additional Parts Currently Available*:
 Dome: 21219
 Mounting Gasket: 21769
 Trim Gasket: 21812

SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm (Originally Rated
 16 Ohm)
 Power Capacity: 25 Watts
 Crossover Frequency: N/A
 Sensitivity: Not Published
 Enclosure Dim: 23-3/4" x 20" x 5-1/8" D
 603mm x 508mm x 130mm
 Shipping Weight: 34 lbs. - 15.4 kg.
 Additional Parts Currently Available*:

SYSTEM NOTES:

System was also available with JBL Solid State Energizer installed. No parts available for Energizer.

*Other parts may also be available. Check with JBL for details.