

SCHEMATIC
NOT AVAILABLE

N55 SCHEMATIC

SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER: 123A-1
 Cone Kit: C8R2212
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 6
 Sweep Frequency Hz: 20-1200
 D.C. Resistance Ohms: 4.5 minimum
 5.5 maximum
 Gap Gauge: .044"
 Notes: Aquaplas
 If Not Serviceable,
 Replace With: 2213H
 (Reverse Polarity)
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.
 Additional Parts Currently Available*:
 Dome: 31385
 Trim Gasket: 32756

MID RANGE DRIVER: LE5-5
 Cone Kit: C8RLE59
 Nom. Impedance: 8 Ohm
 Dynamic Test Input V: 4
 Sweep Frequency Hz: 75-3000
 D.C. Resistance Ohms: 5.6 minimum
 6.6 maximum
 Gap Gauge: .040"
 Notes:

MID RANGE DRIVER (Cont'd):
 If Not Serviceable,
 Replace With: LE5-11
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: No.
 Slightly different. Replace both units
 in a stereo pair.
 Additional Parts Currently Available*:
 Dome: Was 54721 (Paper); Now 51868 (Alum.)
 Trim Gasket: 29931

HIGH FREQUENCY DRIVER: 077
 Diaphragm Kit: D16R2405
 Nom. Impedance: 16 Ohm
 Dynamic Test Input V: 7
 Sweep Frequency Hz: 1000-3000
 D.C. Resistance Ohms: 5.7 minimum
 6.7 maximum
 Gap Gauge: .025"
 Notes: Test With Network.
 Do not crease diaphragm.
 If Not Serviceable,
 Replace With: 2405H
 Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes
 Additional Parts Currently Available*:
 Mounting Gasket: 51795

SYSTEM SPECIFICATIONS:

NOT AVAILABLE

*Other parts may also be available. Check with JBL for details.