



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- 118H
- Cone Kit: C8R118
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 5
- Sweep Frequency Hz: 30-1200
- D.C. Resistance Ohms: 5.1 minimum
6.1 maximum
- Gap Gauge: .051"
- Notes: Aquaplas On Cone
- If Not Serviceable, Replace With: 125HR
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No. Slightly different. Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Dome: 62112
- Terminal Board: 52348
- Mounting Gasket: 52089
- Trim Gasket: 62012

HIGH FREQUENCY DRIVER:

- 034
- Diaphragm Kit: D8R034
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 2.5
- Sweep Frequency Hz: 200-2000
- D.C. Resistance Ohms: 5.4 minimum
6.6 maximum

HIGH FREQUENCY DRIVER (Cont'd)

- Gap Gauge: .031"
- Notes: Test With Network
- If Not Serviceable, Replace With: Currently Available
- Visual Change: N/A
- Baffle Modification: N/A
- Exact Acoustic Replacement: N/A
- Additional Parts Currently Available*:
- Mounting Gasket: 57754
- Screen: 60424
- Screen Gasket: 60752

SYSTEM SPECIFICATIONS:

- Nominal Impedance: 8 Ohm
- Max. Recommended Amp Power: 150 Watts
- Crossover Frequency: 2200 Hz
- Sensitivity: 90dB (1 Watt @ 1 Meter)
- Enclosure Dim: 22-1/4" x 14" x 11-3/4" D
565mm x 356mm x 298mm
- Shipping Weight: 44 lbs. - 20 kg.
- Additional Parts Currently Available*:
- Binding Posts: Red: 56131
Black: 56130

*Other parts may also be available. Check with JBL for details.