



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- Cone Kit: 122A C8R129H
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 6
- Sweep Frequency Hz: 20-1200
- D.C. Resistance Ohms: 4.5 minimum
5.5 maximum

Gap Gauge:

- Notes: .053"
Mass Ring.
Cone kit may have aqua plas on cone instead of mass ring.

If Not Serviceable,

- Replace With: 128H-1
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: No.
Use as last resort. Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Dome: 31385
- Mounting Gasket: 20253
- Trim Gasket: 52806

MID RANGE DRIVER:

- Cone Kit: LE5-5 C8RLE59
- Nom. Impedance: 8 Ohm
- Dynamic Test Input V: 4
- Sweep Frequency Hz: 75-3000
- D.C. Resistance Ohms: 5.6 minimum
6.6 maximum

Gap Gauge:

- Notes: .040"

If Not Serviceable,

- Replace With: LE5-11
- Visual Change: Yes
- Baffle Modification: No

MID RANGE DRIVER (Cont'd)

- Exact Acoustic Replacement: No.
- Slightly different. Replace both units in a stereo pair.
- Additional Parts Currently Available*:
Dome: Was 54721 (Paper); Now 51868 (Alum.)
Trim Gasket: 29931

HIGH FREQUENCY DRIVER:

- Diaphragm Kit: 077 D16R2405
- Nom. Impedance: 16 Ohm
- Dynamic Test Input V: 7
- Sweep Frequency Hz: 1000-3000
- D.C. Resistance Ohms: 5.7 minimum
6.7 maximum
- Gap Gauge: .025"
- Notes: Test With Network.
Do not crease diaphragm.

If Not Serviceable,

- Replace With: 2405H
- Visual Change: Yes
- Baffle Modification: No
- Exact Acoustic Replacement: Yes
- Additional Parts Currently Available*:
Mounting Gasket: 51795

SYSTEM SPECIFICATIONS:

- Nominal Impedance: 8 Ohm
- Max. Recommended Amp Power: 200 Watts
- Crossover Frequencies: 1000 Hz, 6500 Hz
- Sensitivity: 89dB (1 Watt @ 1 Meter)
- Enclosure Dim: 24-1/2" x 17-1/2" x 13-1/8" D
622mm x 445mm x 333mm
- Shipping Weight: 67 lbs. - 30 kg.
- Additional Parts Currently Available*:
Binding Posts: Red: 56131
Black: 56130

*Other parts may also be available. Check with JBL for details.