



**SYSTEM COMPONENTS:**

**LOW FREQUENCY DRIVER:**

LE10A  
 Cone Kit: C8RLE10A  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 6  
 Sweep Frequency Hz: 20-1200  
 D.C. Resistance Ohms: 4.4 minimum  
 5.0 maximum  
 Gap Gauge: .048"  
 Notes: Aquaplas On Cone.  
 Dome Inverted.

If Not Serviceable,  
 Replace With: LE10H-1  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No.  
 Slightly different. Replace both units  
 in a stereo pair.

**Additional Parts Currently Available\*:**

Dome: 21514  
 Mounting Gasket: 21770  
 Trim Gasket: 21813

**HIGH FREQUENCY DRIVER:**

LE20-1  
 Diaphragm Kit: D8RLE20  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 6  
 Sweep Frequency Hz: 1000-6000  
 D.C. Resistance Ohms: 3.7 minimum  
 4.2 maximum  
 Gap Gauge: .029"  
 Notes: Test With Network

**HIGH FREQUENCY DRIVER (Cont'd)**

If Not Serviceable,  
 Replace With: 035TiA  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No. Use as a last  
 resort. Replace both units in a stereo pair.

**Additional Parts Currently Available\*:**

Trim Ring: 21600

**PASSIVE RADIATOR:**

PR10  
 Cone Kit: CRPR10  
 Notes: Dome Inverted  
 If Not Serviceable, No Replacement  
 Replace With: Available  
 Visual Change: N/A  
 Baffle Modification: N/A  
 Exact Acoustic Replacement: N/A

**Additional Parts Currently Available\*:**

Dome: 50201  
 Mounting Gasket: 21770  
 Trim Gasket: 21813

**SYSTEM SPECIFICATIONS:**

Nominal Impedance: 8 Ohm  
 Power Capacity: 30 Watts  
 Crossover Frequency: 2500 Hz  
 Enclosure Dim: 14" x 23-1/2" x 12" D  
 356mm x 597mm x 305mm

Shipping Weight: 49 lbs. - 22.2 kg.

**Additional Parts Currently Available\*:**

\*Other parts may also be available. Check with JBL for details.