



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

- Cone Kit: 123A-1
- Nom. Impedance: C8R2212
- Dynamic Test Input V: 8 Ohm
- Sweep Frequency Hz: 6
- D.C. Resistance Ohms: 20-1200
- Gap Gauge: 4.5 min/5.5 max
- Notes: .044"
- If Not Serviceable, Replace With: Aquaplas

- Visual Change: 2213H (Reverse Polarity)
- Baffle Modification: Yes
- Exact Acoustic Replacement: No
- Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Dome: 31385
- Trim Gasket: 32756

MID RANGE DRIVER:

- Cone Kit: LE5-2
- Nom. Impedance: C8RLE52
- Dynamic Test Input V: 8 Ohm
- Sweep Frequency Hz: 4
- D.C. Resistance Ohms: 75-3000
- Gap Gauge: 5.5 min/6.5 max
- Notes: .040"
- If Not Serviceable, Replace With: Dome Inverted

- Visual Change: LE-5-10
- Baffle Modification: Yes
- Exact Acoustic Replacement: No
- Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Dome: 54721
- Trim Gasket: 29931

HIGH FREQUENCY DRIVER:

- Diaphragm Kit: LE20-1
- Nom. Impedance: D8RLE20
- Dynamic Test Input V: 8 Ohm
- Sweep Frequency Hz: 6
- D.C. Resistance Ohms: 1000-6000
- Gap Gauge: 3.7 min/4.2 max
- Notes: .029"
- If Not Serviceable, Replace With: Test With Network

- Visual Change: 035TiA
- Baffle Modification: Yes
- Exact Acoustic Replacement: No
- Use as last resort. Replace both units in a stereo pair.

Additional Parts Currently Available*:

- Trim Ring: 21600

PASSIVE RADIATOR:

- Cone Kit: PR12
- Notes: Kit Not Available
- Unit not serviceable. No

- replacement available.
- If Not Serviceable, Replace With: N/A
- Visual Change: N/A
- Baffle Modification: N/A
- Exact Acoustic Replacement: N/A

SYSTEM SPECIFICATIONS:

- Nom. Impedance: 8 ohm
- Power Handling: 50 Watts Continuous Program
- Crossover Frequencies: 7000 Hz, 1200 Hz
- Enclosure Dim: 26 1/2" x 35" x 17 1/8" D
- Shipping Weight: 673mm x 889mm x 448mm
- 230 lbs. - 104 kg. (pair)

*Other parts may also be available. Check with JBL for details.