

Component	Description	Equivalent
1 GA109	50V, 0,015A	AA 113, 1N34, 1N54, 1N60
2 GA113	35V, 0,03A	AA 113, AA 119, 1N34, 1N54, 1N60
3 OA646	GA 109	GA 109
4 GA114	35V, 0,03A	4x GA 113
5 1006	1600/1700V, 2,3mA	E800C2,3
6 896	880/950V, 3,3mA	E400C3,3
7 972	1100/1200V, 3mA	E500C3
8 992	1300/1450V, 2,7mA	E600C2,7
9 100	75V, 0,125A	BA 157....159, BAY 19....21, BAY 87....89
10 101	0100, 150V	BA 157....159, BAY 20....21, BAY 88....89
11 102	0100, 300V	BA 157....159, BAY 21, BAY 88....89
12 110	100	BA 157....159, BAY 19....21, BAY 87....89
13 111	0100, 150V	BA 157...159, BAY 20...21, BAY 88...89
14 112	0100, 300V	BA 157...159, BAY 21, BAY 88...89
15 114	0100, 500V	BA 158...159, BA 199/550, BAY 89...91
16 241	100V, 3A(Tc100°)	BYX 38/300R, BYX 39/600R
17 0241..48R	0241..0248, 800V	BYX 38/..., BYX 39/...
18 242	0241, 200V	BYX 38/300R, BYX 39/600R
19 243	0241, 300V	BYX 38/300R, BYX 39/600R
20 245	0241, 500V	BYX 38/600R, BYX 39/600R
21 248	0241, 800V	BYX 38/900R, BYX 39/800R
22 300	75V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
23 301	0300, 150V	BY 126...127, BY 133...135, 1N4003...07
24 302	0300, 300V	BY 126...127, BY 133...134, 1N4004...07
25 304	0300, 500V	BY 126...127, BY 133...134, 1N4005...07
26 307	0300, 800V	BY 127, BY 133, BY 227, 1N4006...07
27 310	300	BY 126...127, BY 133...135, 1N4002...07
28 311	0300, 150V	BY 126...127, BY 133...135, 1N4003...07
29 312	0300, 300V	BY 126...127, BY 133...134, 1N4004...07
30 314	0300, 500V	BY 126...127, BY 133...134, 1N4005...07
31 317	0300, 800V	BY 127, BY 133, BY 227, 1N4006...07
32 320	300	BY 126...127, BY 133...135, 1N4002...07
33 321	0300, 150V	BY 126...127, BY 133...135, 1N4003...07
34 322	0300, 300V	BY 126...127, BY 133...134, 1N4004...07
35 324	0300, 500V	BY 126...127, BY 133...134, 1N4005...07
36 327	0300, 800V	BY 127, BY 133, BY 227, 1N4006...07
37 400	75V, 0,25A	BA 157...159, BA 199/250, BAY 19...21
38 401	0400, 150V	BA 157...159, BA 199/250, BAY 20...21
39 402	0400, 300V	BA 157...159, BA 199/350, BAY 21
40 404	0400, 500V	BA 158...159, BA 199/550, BAY 89...91
41 410	400	BA 157...159, BA 199/250, BAY 19...21
42 411	0400, 150V	BA 157...159, BA 199/250, BAY 20...21
43 412	0400, 300V	BA 157...159, BA 199/350, BAY 21
44 414	0400, 500V	BA 158...159, BA 199/550, BAY 89...91

45	500	75V, 0,25A	BA 157...159, BA 199/250, BAY 19...21
46	501	0500, 150V	BA 157...159, BA 199/250, BAY 20...21
47	502	0500, 300V	BA 157...159, BA 199/350, BAY 21
48	503	0500, 400V	BA 157...159, BA 199/550, BAY 89...91
49	504	0500, 500V	BA 158...159, BA 199/550, BAY 89...91
50	507	0500, 800V	BA 159, BAY 90...91, BY 204/8
51	601	200V, 17,5A(Tc100°)	BYX 25/600R, SSiE2040
52	0601..08R	0601..0608	BYX 25/...
53	602	0601, 300V	BYX 25/600R, SSiE2040
54	604	0601, 600V	BYX 25/600R, SSiE2040
55	606	0601, 900V	BYX 25/1000R, SSiE2060
56	608	0601, 1200V	BYX 25/1200R, SSiE2080
57	612	300V, 40A(Tc100°)	D 60/400, DS 42-04A
58	614	0612, 600V	D 60/800, DS 42-07A
59	616	0612, 900V	D 60/1200, DS 42-11A
60	618	0612, 1200V	D 60/1200, DS 42-14A
61	619	0612, 1500V	D 60/1600, DS 42-16A
62	622	300V, 100A(Tc100°)	D 160/400, DS 85-04C
63	624	0622, 600V	D 160/800, DS 85-06C
64	626	0622, 900V	D 160/1200, DS 85-10C
65	628	0622, 1200V	D 160/1200, DS 85-12C
66	629	0622, 1500V	D 160/1600, DS 85-16C
67	632	300V, 20A(Tc100°)	D 21S/1000, D 24/400
68	634	0632, 600V	D 21S/1000, D 24/800
69	636	0632, 900V	D 21S/1000, D 24/1200
70	638	0632, 1200V	D 21S/1200, D 24/1200
71	639	0632, 1500V	D 24/1600
72	700	1N4002	1N4002
73	701	1N4003	1N4003
74	702	1N4004	1N4004
75	704	1N4005	1N4005
76	707	1N4006	1N4006
77	708	1N4007	1N4007
78	710	1N4001	1N4001
79	771	150V, 1,5A	BY 226...227, BY 251...255, 1N5393...99
80	772	0771, 300V	BY 226...227, BY 252...255, 1N5394...99
81	774	0771, 500V	BY 226...227, BY 253...255, 1N5397...99
82	776	0771, 800V	BY 227, BY 254...255, 1N5398...99
83	778	0771, 1000V	BY 227, BY 228, BY 255, 1N5399
84	779	0771, 1200V	BY 227, BY 228, BY 255, BYX 87
85	1101(c)	2,7V, 0,25W, 10%(c5%)	BZX55/..., BZX79/..., ZPD..., 1N4682...4714
86	1102(c)	1101(c), 3,3V	
87	1103(c)	1101(c), 3,9V	
88	1104(c)	1101(c), 4,7V	
89	1105(c)	1101(c), 5,6V	

90	1106(c)	1101(c), 6,8V	
91	1107(c)	1101(c), 7,5V	
92	1108(c)	1101(c), 8,2V	
93	1109(c)	1101(c), 9,1V	
94	1110(c)	1101(c), 10V	
95	1111(c)	1101(c), 11V	
96	1112(c)	1101(c), 12V	
97	1113(c)	1101(c), 13V	
98	1115(c)	1101(c), 15V	
99	1116(c)	1101(c), 16V	
100	1118(c)	1101(c), 18V	
101	1120(c)	1101(c), 20V	
102	1122(c)	1101(c), 22V	
103	1124(c)	1101(c), 24V	
104	1127(c)	1101(c), 27V	
105	1130(c)	1101(c), 30V	
106	1133(c)	1101(c), 33V	
107	1203(c)	3,9V, 15W(Tc45°), 10%(c5%)	BZX 98/..., BZY 93/...
108	1204(c)	1203(c), 4,7V	
109	1205(c)	1203(c), 5,6V	
110	1206(c)	1203(c), 6,8V	
111	1207(c)	1203(c), 7,5V	
112	1208(c)	1203(c), 8,2V	
113	1209(c)	1203(c), 9,1V	
114	1210(c)	1203(c), 10V	
115	1211(c)	1203(c), 11V	
116	1212(c)	1203(c), 12V	
117	1213(c)	1203(c), 13V	
118	1301(c)	2,7V, 1W, 10%(c5%)	BZW22/..., BZX61/..., ZPY..., 1N4728...4743
119	1302(c)	1301(c), 3,3V	
120	1303(c)	1301(c), 3,9V	
121	1304(c)	1301(c), 4,7V	
122	1305(c)	1301(c), 5,6V	
123	1306(c)	1301(c), 6,8V	
124	1307(c)	1301(c), 7,5V	
125	1308(c)	1301(c), 8,2V	
126	1309(c)	1301(c), 9,1V	
127	1310(c)	1301(c), 10V	
128	1311(c)	1301(c), 11V	
129	1312(c)	1301(c), 12V	
130	1313(c)	1301(c), 13V	
131	1315(c)	5324(c)	
132	1316(c)	5325(c)	
133	1318(c)	5326(c)	
134	1320(c)	5327(c)	

135	1322(c)	5328(c)	
136	1324(c)	5329(c)	
137	1327(c)	5330(c)	
138	1330(c)	5331(c)	
139	1333(c)	5332(c)	
140	1336(c)	5333(c)	
141	1339(c)	5334(c)	
142	1343(c)	5335(c)	
143	1347(c)	5336(c)	
144	1405	1305	
145	1406	1306	
146	1408	1308	
147	1410	1310	
148	1412	1312	
149	1415	5324	
150	1418	5326	
151	1422	5328	
152	1427	5330	
153	1433	5332	
154	1439	5334	
155	1447	5336	
156	2301	220V, 0,05A, 1,5 $\mu$ s	BA 147/230, BAY 21, BAY 46, 1N5196
157	2302	2301	BA 147/230, BAY 21, BAY 46, 1N5196
158	2303	2301, 100V, 0,5A	BA 157...159, BA 193...194, BY 402...405
159	2304	2301, 50V	BA 147/50, BAY 18...21, 1N5194...96
160	2401	25V, 0,1A, <2,5 $\mu$ s	BA 147/50, BAY 18...21, 1N5194...96
161	2403	2401, 55V	BA 147/50, BAY 18...21, 1N5194...96
162	2405	2401, 80V	BA 147/100, BAY 19...21, 1N5195...96
163	2410	2401, 150V	BA 147/150, BAY 20...21, 1N5195...96
164	2415	2401, 200V	BA 147/230, BAY 21, 1N5195...96
165	2420	2401, 250V	BA 147/300, BAY 21, BAY 46, 1N5196
166	2502	200V, 0,6A, 5 $\mu$ s	BY 126...127, BY 133...134, 1N4003...07
167	2504	2502, 400V	BY 126...127, BY 133...134, 1N4004...07
168	2506	2502, 600V	BY 126...127, BY 133...134, 1N4005...07
169	2602	200V, 3A(Tc100°)	BYX 38/300R, BYX 39/600R
170	2602..06R	2602	BYX 38/..., BYX 39/...
171	2604	2602, 400V	BYX 38/600R, BYX 39/600R
172	2606	2602, 600V	BYX 38/600R, BYX 39/600R
173	2611	100V, 6A(Tc100°)	BYX 38/300R, BYX 39/600R
174	2611..14R	2611	BYX 38/..., BYX 39/...
175	2612	2611, 200V	BYX 38/300R, BYX 39/600R
176	2614	2611, 400V	BYX 38/600R, BYX 39/600R
177	2702	20V, 3A(Tc100°)	BYX 38/300R, BYX 39/600R
178	2702..10R	2702	BYX 38/..., BYX 39/...
179	2705	2702, 50V	BYX 38/300R, BYX 39/600R

180	2710	2702, 100V	BYX 38/300R, BYX 39/600R
181	2912	500V, 0,1A, <2,5μs	BA 158...159, BAY 89...91, BY 203/12
182	2913	2912, 750V	BA 159, BAY 90...91, BY 203/12
183	2914	2912, 1000V	BA 159, BAY 90...91, BY 203/12
184	2915	2912, 1250V	BAY 91, BY 203/12, RGP 01-12, SHG 1,5
185	2916	2912, 1500V	BAY 91, BY 203/16, RGP 01-16, SHG 1,5
186	2917	2912, 1750V	BAY 91, BY 203/20, BY 584, SHG 2
187	2918	2912, 2000V	BAY 91, BY 203/20, SHG 2
188	3377	1V(1,5A), 1,5W	ZY 1
189	3390	1V(0,1A), 0,4W	BA 315, BZX 62, BZX 97/C0V8
190	3391	3390, 0,25W	BA 315, BZX 62, BZX 97/C0V8
191	3392	1,5V(2A), 15W	-
192	3393	1,2V(0,5A), 1W	-
193	3396	+1V(+0,1A), 0,25W	-
194	3397	+0,56..0,68V(+1mA), 2,5W	-
195	3398	+0,6..0,72V(+1mA), 2,5W	-
196	3701(G)	5,9..6,5V	BZV 13, BZV 30, BZX 93, 1N828, 1N4583
197	3702(G)	5,9..6,5V	BZV 19, BZV 29, BZX 92, 1N825, 1N4582
198	3703(G)	5,9..6,5V	BZV 11, BZV 28, BZX 91, 1N823, 1N4581
199	3704(G)	5,9..6,5V	BZV 10, BZV 27, BZX 90, 1N821, 1N4580
200	3705	6,1..6,5V	-
201	3706	6,1..6,5V	1N4894, 1N4895
202	3707	6,1..6,5V	1N4893, 1N4894
203	3710	6,1..6,5V	-
204	3711	6,1..6,5V	-
205	3712	6,1..6,5V	BZV 14, BZV 31, BZX 94, 1N829, 1N4584
206	3713	6,6V	-
207	3714	6,6V	-
208	3722	8..8,8V	BZX 51, 1N4780
209	3723	8..8,8V	BZX 52, 1N4781
210	3724	8..8,8V	BZX 53, 1N4782
211	3725	8..8,8V	BZX 54, 1N4783
212	3731	8..8,8V	-
213	3732	8..8,8V	-
214	3733	8..8,8V	-
215	4120(c)	10V, 15W, 10%(c5%)	BZX 98/..., BZY 93/...
216	4121(c)	4120(c), 11V	
217	4122(c)	4120(c), 12V	
218	4123(c)	4120(c), 13V	
219	4124(c)	4120(c), 15V	
220	4125(c)	4120(c), 16V	
221	4126(c)	4120(c), 18V	
222	4127(c)	4120(c), 20V	
223	4128(c)	4120(c), 22V	
224	4129(c)	4120(c), 24V	

225	4130(c)	4120(c), 27V	
226	4131(c)	4120(c), 30V	
227	4132(c)	4120(c), 33V	
228	4133(c)	4120(c), 36V	
229	4134(c)	4120(c), 39V	
230	4135(c)	4120(c), 43V	
231	4136(c)	4120(c), 47V	
232	4137(c)	4120(c), 51V	
233	4138(c)	4120(c), 56V	
234	4139(c)	4120(c), 62V	
235	4140(c)	4120(c), 68V	
236	4141(c)	4120(c), 75V	
237	4142(c)	4120(c), 82V	
238	4143(c)	4120(c), 91V	
239	4144(c)	4120(c), 100V	
240	4145(c)	4120(c), 110V	
241	4146(c)	4120(c), 120V	
242	4147(c)	4120(c), 135V	
243	4148(c)	4120(c), 150V	
244	4149(c)	4120(c), 165V	
245	4150(c)	4120(c), 180V	
246	4151(c)	4120(c), 200V	
247	4220..51	4120..4151(c)	BZY 93/...R
248	4320..51	4120..4151(c), 20W	BZY 93/...
249	4420..51	4120..4151(c), 20W	BZY 93/...R
250	4520..51	4120..4151(c), 30W	BZY 91/..., 1N3309R...3350R
251	4620..51	4120..4151(c), 30W	BZY 91/...R, 1N3309...3350
252	4720..51	4120..4151(c), bidirecional	-
253	4820..51	4320..4151(c), bidirecional	-
254	4920..51	4520..4151(c), bidirecional	-
255	5120..51	5320..5351(c)	5320...5331
256	5220..51	5320..5351(c), bidirecional	
257	5320(c)	10V, 1W, 10%(c5%)	BZW22/..., BZX61/..., ZPY..., 1N4740...4764
258	5321(c)	5320(c), 11V	
259	5322(c)	5320(c), 12V	
260	5323(c)	5320(c), 13V	
261	5324(c)	5320(c), 15V	
262	5325(c)	5320(c), 16V	
263	5326(c)	5320(c), 18V	
264	5327(c)	5320(c), 20V	
265	5328(c)	5320(c), 22V	
266	5329(c)	5320(c), 24V	
267	5330(c)	5320(c), 27V	
268	5331(c)	5320(c), 30V	
269	5332(c)	5320(c), 33V	

270	5333(c)	5320(c), 36V	
271	5334(c)	5320(c), 39V	
272	5335(c)	5320(c), 43V	
273	5336(c)	5320(c), 47V	
274	5337(c)	5320(c), 51V	
275	5338(c)	5320(c), 56V	
276	5339(c)	5320(c), 62V	
277	5340(c)	5320(c), 68V	
278	5341(c)	5320(c), 75V	
279	5342(c)	5320(c), 82V	
280	5343(c)	5320(c), 91V	
281	5344(c)	5320(c), 100V	
282	5345(c)	5320(c), 110V	
283	5346(c)	5320(c), 120V	
284	5347(c)	5320(c), 135V	
285	5348(c)	5320(c), 150V	
286	5349(c)	5320(c), 165V	
287	5350(c)	5320(c), 180V	
288	5351(c)	5320(c), 200V	
289	5420..51	5320..5351(c), bidirecional	
290	5501	NT 55/C0V7	NT 55/C0V7
291	5502	NT 55/C1V4	NT 55/C1V4
292	5503	NT 55/2V1	NT 55/C2V1
293	5506(G)	2,7V, 0,5W, 5%, (NT 55/C..)	BZX55/..., BZX83/..., ZPD..., 1N5223...81
294	5507(G)	5506(G), 3V	
295	5508(G)	5506(G), 3,3V	
296	5509(G)	5506(G), 3,6V	
297	5510(G)	5506(G), 3,9V	
298	5511(G)	5506(G), 4,3V	
299	5512(G)	5506(G), 4,7V	
300	5513(G)	5506(G), 5,1V	
301	5514(G)	5506(G), 5,6V	
302	5515(G)	5506(G), 6,2V	
303	5516(G)	5506(G), 6,8V	
304	5517(G)	5506(G), 7,5V	
305	5518(G)	5506(G), 8,2V	
306	5519(G)	5506(G), 9,1V	
307	5520(G)	5506(G), 10V	
308	5521(G)	5506(G), 11V	
309	5522(G)	5506(G), 12V	
310	5523(G)	5506(G), 13V	
311	5524(G)	5506(G), 15V	
312	5525(G)	5506(G), 16V	
313	5526(G)	5506(G), 18V	
314	5527(G)	5506(G), 20V	

315	5528(G)	5506(G), 22V	
316	5529(G)	5506(G), 24V	
317	5530(G)	5506(G), 27V	
318	5531(G)	5506(G), 30V	
319	5532(G)	5506(G), 33V	
320	5533(G)	5506(G), 36V	
321	5534(G)	5506(G), 39V	
322	5535(G)	5506(G), 43V	
323	5536(G)	5506(G), 47V	
324	5537(G)	5506(G), 51V	
325	5538(G)	5506(G), 56V	
326	5539(G)	5506(G), 62V	
327	5540(G)	5506(G), 68V	
328	5541(G)	5506(G), 75V	
329	5542(G)	5506(G), 82V	
330	5543(G)	5506(G), 91V	
331	5544(G)	5506(G), 100V	
332	5545(G)	5506(G), 110V	
333	5546(G)	5506(G), 120V	
334	5547(G)	5506(G), 130V	
335	5548(G)	5506(G), 150V	
336	5549(G)	5506(G), 160V	
337	5550(G)	5506(G), 180V	
338	5551(G)	5506(G), 200V	
339	7701	NT 77/C0V7	NT 77/0V7
340	7702	NT 77/1V4	NT 77/1V4
341	7706	2,7V, 1,5W, 5%, (NT 77/..)	BZV47/..., BZY97/..., ZY..., 1N5913...5956
342	7707	7706, 3V	
343	7708	7706, 3,3V	
344	7709	7706, 3,6V	
345	7710	7706, 3,9V	
346	7711	7706, 4,3V	
347	7712	7706, 4,7V	
348	7713	7706, 5,1V	
349	7714	7706, 5,6V	
350	7715	7706, 6,2V	
351	7716	7706, 6,8V	
352	7717	7706, 7,5V	
353	7718	7706, 8,2V	
354	7719	7706, 9,1V	
355	7720	7706, 10V	
356	7721	7706, 11V	
357	7722	7706, 12V	
358	7723	7706, 13V	
359	7724	7706, 15V	



360	7725	7706, 16V	
361	7726	7706, 18V	
362	7727	7706, 20V	
363	7728	7706, 22V	
364	7729	7706, 24V	
365	7730	7706, 27V	
366	7731	7706, 30V	
367	7732	7706, 33V	
368	7733	7706, 36V	
369	7734	7706, 39V	
370	7735	7706, 43V	
371	7736	7706, 47V	
372	7737	7706, 51V	
373	7738	7706, 56V	
374	7739	7706, 62V	
375	7740	7706, 68V	
376	7741	7706, 75V	
377	7742	7706, 82V	
378	7743	7706, 91V	
379	7744	7706, 100V	
380	7745	7706, 110V	
381	7746	7706, 120V	
382	7747	7706, 130V	
383	7748	7706, 150V	
384	7749	7706, 160V	
385	7750	7706, 180V	
386	7751	7706, 200V	
387	9015		-
388	9605	5,8..6,6V, 0,125W	-
389	9606	9605, 6,4..7,2V	-
390	9607	9605, 7,1..7,9V	-
391	9624	5kV, 0,1A	1N5182
392	9648	200V, 2A	BYX 38/300R, BYX 39/600R
393	9649	1,4kV, 0,1A	1N1732
394	9650	9649, 2,8kV	1N1733
395	9651	9649, 4,2kV	1N1734
396	9652	9649, 5,6kV	BYX 90
397	9689	100V, 6A, <300ns	1N3880...3883
398	9690	9689	1N3880R...3883R
399	9779	9015, 0,25W	-
400	9970	3V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N4683...90
401	9971	9970, 3,6V	
402	9972	9970, 4,3V	
403	9973	9970, 5,1V	
404	9974	9970, 6,2V	

405	9980	3V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...20
406	9981	9980, 3,6V	
407	9982	9980, 4,3V	
408	9983	9980, 5,1V	
409	9984	9980, 6,2V	
410	9992	4,3V, 15W	BZX 98/..., BZY 93/...
411	9993	9992, 5,1V	
412	9994	9992, 6,2V	
413	(s)SF	SP 0610T	SP 0610T
414	(s)SG,SSG	SN 7002	SN 7002
415	(s)SH	BSS 119	BSS 119
416	(SSi)B0510...0580	SSi B 0510..0580	
417	(SSi)B0810...0880	SSi B 0810..0880	
418	(SSi)C1710	SSi C 1710	
419	(SSi)C1720	SSi C 1720	
420	(SSi)C1740	SSi C 1740	
421	(SSi)C1760	SSi C 1760	
422	(SSi)C1780	SSi C 1780	
423	(SSi)C2620	SSi C 2620	
424	(SSi)C2630	SSi C 2630	
425	-1F	PMST 5550	PMST 5550
426	-1J	PMST 2369	PMST 2369
427	-1K	PMST 6428	PMST 6428
428	-1L	PMST 6429	PMST 6429
429	-2L	PMST 5401	PMST 5401
430	-G1	PMST 5551	PMST 5551
431	0	HVU 300(A)	HVU 300(A)
432	0	HVC 300A	HVC 300A
433	0	HVE 300A	HVE 300A
434	010	SO 918R	SO 918R
435	02	BSX 39	BSX 39
436	02	BST 82	BST 82
437	028	SO 3572R	SO 3572R
438	02BZ2.2..4.7	2,2..4,7V, 10%, 0,25W	BZX 46/..., BZX 55/..., BZX 83/..., ZPD...
439	02CZ2.0..47X,Y,Z	2..47V, 5%, 0,2W	BZX 84/..., BZX 88/...
440	02DZ2.0..47Y,Z	4,7..8,2V, 3%, 0,2W	-
441	03N06C	RLD03N06CLE	RLD 03N06CLE
442	03N06CLE	RLP03N06CLE	RLP 03N06CLE
443	03P1M	03 P05M, 100V	BT 149/..., TAG 59-..., 2N6681...85
444	03P2J	200V, 0,3A, Igt/Ih <0,2/<5mA	-
445	03P2M	03 P05M, 200V	BT 149/..., TAG 59-..., 2N6682...85
446	03P3M	03 P05M, 300V	BT 149/..., TAG 59-..., 2N6683...85
447	03P4J	03 P2J, 400V	-
448	03P4M	03 P05M, 400V	BT 149/..., TAG 59-..., 2N6683...85
449	03P4MG(C)	<0,05/<5mA	BT 149/..., MCR 606-..., TAG 59-...

450	03P5J	03 P2J, 500V	-
451	03P5M	03 P05M, 500V	BT 149/..., TAG 59-..., 2N6684...85
452	03P5MG(C)	03 P4MG, 500V	BT 149/..., MCR 606-..., TAG 59-...
453	044	SO 3571R	SO 3571R
454	047	SO 3570R	SO 3570R
455	04AZ2.0..39R..Z	2,0..39V, +-5%, 3W	BZV 16/..., BZV 47/..., BZX 70/..., ZY...
456	05AZ2.2..100R..Z	2,2..100V, +-5%, 0,5W	BZX 46/..., BZX 55/..., BZX 83/..., ZPD...
457	05J25	SS 05J25	SS 05J25
458	066	SO 269R	SO 269R
459	087	SO 502SR	SO 502SR
460	09	1SS377	1SS377
461	09	1SS378	1SS378
462	091	SO 642R	SO 642R
463	1	HVR 187	HVR 187
464	1	HSR 101	HSR 101
465	)	6,8..440V, 1,5kW(1ms)	1N5629...65, 1N6267...6303
466	A		1N6036...72, 1N6138...73
467	1.5J4	SS 1.5J4	SS 1.5J4
468	1.5J5	SS 1.5J5	SS 1.5J5
469	1/4M...Z10	+ -10%	BZX55/..., BZX83/..., ZPD..., 1N5221...81
470	1/4M...Z5	+ -5%	BZX55/..., BZX83/..., ZPD..., 1N5221...81
471	1/4M2.4..200(A)Z	2,4..200V, 0,25W, +-20%	BZX55/..., BZX83/..., ZPD..., 1N5221...81
472	10	MRF 9411	MRF 9411
473	10	SST 110	SST 110
474	10(X,Y,Z)	U 02W10V	Z 02W 10V
475	1006	AEG 1006	
476	100T2	120V, 5A, 85W	BD 245D, BD 550, 2N5759...60, 2SC2706
477	101	FC 101	FC 101
478	102	FC 102	FC 102
479	103	FC 103	FC 103
480	104	FC 104	FC 104
481	104T2	60V, 5A, 85W	BD 245A, BDV 91, 2N4914...15, 2SD895
482	105	FC 105	FC 105
483	106	FC 106	FC 106
484	107	FC 107	FC 107
485	108	FC 108	FC 108
486	108T2	BDY 57	BDY 57
487	109	FC 109	FC 109
488	109T2	BDY 58	BDY 58
489	10B	HZF 10BP	HZF 10BP
490	10C	HZF 10CP	HZF 10CP
491	10D1..D10	100..1000V, 1A	BY 126...127, BY 133...135, 1N4001...4007
492	10DF1..DF8	100..800V, 1A, 100..200ns	BYD 33D...M, BYT 52B...M, RGP 10B...M
493	10E1..E8	100..800V, 1A	BY 126...127, BY 133...135, 1N4001...4007
494	10EF1..EF2	100..200V, 1A, <200ns	BYD 33D...M, BYT 52B...M, RGP 10B...M

495	10ELS1..ELS6	100..600V, 1A, <150ns	BYT 11-..., BYT 52B...M, BYV 26B...E
496	10KF10..KF40	100..400V, 10A, <35..45ns	BYT 79-...
497	10KF10B..KF40B	10 KF10..KF40	-
498	10SP-01..10	50..1000V, 10A	-
499	10Y	BZV 49/C10	BZV 49/C10
500	11	FC 11	FC 11
501	11	MRF 9511	MRF 9511
502	11	MMBD 1501	MMBD 1501
503	11(X,Y,Z)	U 02W11V	Z 02W 11V
504	110	FC 110	FC 110
505	111	FC 111	FC 111
506	111T2	60V, 0,8W	-
507	111T2/18	60V, 0,5W	-
508	112	FC 112	FC 112
509	113	FC 113	FC 113
510	114	FC 114	FC 114
511	115	FC 115	FC 115
512	116	FC 116	FC 116
513	117	FC 117	FC 117
514	118	FC 118	FC 118
515	119	FC 119	FC 119
516	11B	HZF 11BP	HZF 11BP
517	11C	HZF 11CP	HZF 11CP
518	11DF1..DF4	100..400V, 1A, 30ns	EGP 10B...G, FE 1B...H
519	11E1..E4	100..400V, 1A	BY 126...127, BY 133...135, 1N4001...4007
520	11EFS1..EFS4	100..400V, 1A, <30ns	EGP 10B...G, FE 1B...H
521	11ES1..ES2	100..200V, 1A	BY 126...127, BY 133...135, 1N4001...4007
522	11Y	BZV 49/C11	BZV 49/C11
523	12(X,Y,Z)	U 02W12V	Z 02W 12V
524	120	FC 120	FC 120
525	121	FC 121	FC 121
526	12B	HZF 12BP	HZF 12BP
527	12C	HZF 12CP	HZF 12CP
528	12Y	BZV 49/C12	BZV 49/C12
529	13	MMBD 1503	MMBD 1503
530	13	BAS 125	BAS 125
531	13(X,Y,Z)	U 02W13V	Z 02W 13V
532	13B	HZF 13BP	HZF 13BP
533	13C	HZF 13CP	HZF 13CP
534	13Y	BZV 49/C13	BZV 49/C13
535	14	MMBD 1504	MMBD 1504
536	14	BAS 125-04	BAS 125-04
537	1401	ED 1401	
538	1402	ED 1402	
539	142T	BD 142	BD 142

540	14B	BFR 14B	BFR 14B
541	14C	BFR 14C	BFR 14C
542	14N05L	RFD 14N05L	RFD 14N05L
543	14N06L	RFD 14N06L	RFD 14N06L
544	15	MMBT 3960	MMBT 3960
545	15	MMBD 1505	MMBD 1505
546	15	BAS 125-05	BAS 125-05
547	15(X,Y,Z)	U 02W15V	Z 02W 15V
548	1501	ED 1501	
549	1502	ED 1502	
550	15B	HZF 15BP	HZF 15BP
551	15C	HZF 15CP	HZF 15CP
552	15DF4..DF8	400..800V, 1,3A, 150ns	BYD 33G...M, BYV 96D...E, RGP 15G...M
553	15IP-02..10	50..1000V, 15A	-
554	15SP-01..10	50..1000V, 15A	-
555	15Y	BZV 49/C15	BZV 49/C15
556	16	BAS 125-06	BAS 125-06
557	16(X,Y,Z)	U 02W16V	Z 02W 16V
558	1601	ED 1601	
559	1602	ED 1602	
560	16054P	BA 159	BA 159
561	16090	S 3703SF	S 3703SF
562	16091	S 3702S	S 3702S
563	16092	D 2103SF	D 2103SF
564	16093	D 2103S	D 2103S
565	16094	D 2103S	D 2103S
566	16121	S 3703SF	S 3703SF
567	16122	S 3702S	S 3702S
568	16123	D 2103SF	D 2103SF
569	16152	S 3703SF	S 3703SF
570	16157	S 3702S	S 3702S
571	16159	D 2103SF	D 2103SF
572	16207(B)	BD 241A,B	BD 241A,B
573	16305	BD 243C	BD 243C
574	16306	BD 244C	BD 244C
575	16315	BD 595	BD 595
576	16316	BD 596	BD 596
577	16317	BD 245A	BD 245A
578	16318	BD 246A	BD 246A
579	16410	S 3703SF	S 3703SF
580	16411	S 3702S	S 3702S
581	16412	D 2103SF	D 2103SF
582	16413	D 2103S	D 2103S
583	16420	S 3703SF	S 3703SF
584	16421	S 3702S	S 3702S

585	16422	D 2103SF	D 2103SF
586	16423	D 2103S	D 2103S
587	16443	TIC 106M	TIC 106M
588	16461	S 3702S	S 3702S
589	16476	S 3703SF	S 3703SF
590	16477	S 3702S	S 3702S
591	16488	TAG 626/600	TAG 626/600
592	16490	S 3703SF	S 3703SF
593	16491	S 3702S	S 3702S
594	16492	D 2103SF	D 2103SF
595	16493	D 2103S	D 2103S
596	16503	2N3055	2N3055
597	16562	2N5298	2N5298
598	16563	2N6107	2N6107
599	16606	BD 809	BD 809
600	1664	2N3055	2N3055
601	16640	S 3703SF	S 3703SF
602	16641	S 3702S	S 3702S
603	16656	BU 104	BU 104
604	16668	2N3055	2N3055
605	16690	S 3703SF	S 3703SF
606	16691	S 3702S	S 3702S
607	16810	BD 607	BD 607
608	16811	BD 608	BD 608
609	16837	2N4101	2N4101
610	16888	S 3703SF	S 3703SF
611	16889	S 3702S	S 3702S
612	16924	BD 810	BD 810
613	16B	HZF 16BP	HZF 16BP
614	16C	HZF 16CP	HZF 16CP
615	16N03L	RFD 16N03L	RFD 16N03L
616	16Y	BZV 49/C16	BZV 49/C16
617	17	BAS 125-07	BAS 125-07
618	1701	ED 1701	
619	17018	S 3900S	S 3900S
620	17019	S 3901S	S 3901S
621	1702	ED 1702	
622	17020	S 3900S	S 3900S
623	17021	S 3901S	S 3901S
624	17022	S 3900S	S 3900S
625	17023	S 3901S	S 3901S
626	17024	S 3900S	S 3900S
627	17025	S 3901S	S 3901S
628	17026	S 3900S	S 3900S
629	17027	S 3901S	S 3901S

630	17028	S 3900S	S 3900S
631	17029	S 3901S	S 3901S
632	17030	S 3900S	S 3900S
633	17031	S 3901S	S 3901S
634	17032	S 3900S	S 3900S
635	17033	S 3901S	S 3901S
636	17034	S 3900S	S 3900S
637	17035	S 3901S	S 3901S
638	17036	S 3900S	S 3900S
639	17037	S 3901S	S 3901S
640	17040	S 3900S	S 3900S
641	17041	S 3901S	S 3901S
642	17052	S 3900S	S 3900S
643	17053	S 3901S	S 3901S
644	17054	S 3900S	S 3900S
645	17055	S 3901S	S 3901S
646	17056	S 3900S	S 3900S
647	17057	S 3901S	S 3901S
648	17058	S 3900S	S 3900S
649	17058F	S 3900S	S 3900S
650	17059	S 3901S	S 3901S
651	17062	S 3900S	S 3900S
652	17063	S 3901S	S 3901S
653	17065	S 3901S	S 3901S
654	17066	S 3900S	S 3900S
655	17074	S 3900S	S 3900S
656	17075	S 3901S	S 3901S
657	17076	S 3900S	S 3900S
658	17077	S 3901S	S 3901S
659	17078	S 3900S	S 3900S
660	17079	S 3901S	S 3901S
661	17080	S 3900S	S 3900S
662	17086	S 3900S	S 3900S
663	17087	S 3901S	S 3901S
664	17088	S 3900S	S 3900S
665	17089	S 3901S	S 3901S
666	17106	17127	17127
667	17120	17127	17127
668	17122	17127	17127
669	17124	17127	17127
670	17126	17127	17127
671	17127		BStC 1233S11
672	17132	17127	17127
673	17150	17127	17127
674	17154	17127	17127

675	17166	17088..89	17088, 17089
676	17322	BD 203	BD 203
677	17323	BD 204	BD 204
678	17375	BD 243C	BD 243C
679	17389	BD 317	BD 317
680	17390	BD 318	BD 318
681	17391	BD 317	BD 317
682	17520	TIP 135	TIP 135
683	17521	TIP 130	TIP 130
684	17560	RCA 8638C	RCA 8638C
685	17561	RCA 9116C	RCA 9116C
686	17597	BD 243C	BD 243C
687	18	SST 108	SST 108
688	18(X,Y,Z)	U 02W18V	Z 02W 18V
689	1801	ED 1801	
690	1802	ED 1802	
691	18022	S 3900S	S 3900S
692	18052	S 3900S	S 3900S
693	18053	S 3901S	S 3901S
694	180T2	BDY 23	BDY 23
695	181	BFQ 181	BFQ 181
696	18127	17127	17127
697	181T2	BDY 24	BDY 24
698	182	BFQ 182	BFQ 182
699	182T2	BDY 25	BDY 25
700	183T2	BDY 26	BDY 26
701	184T2	BDY 27	BDY 27
702	185T2	BDY 28	BDY 28
703	18B	HZF 18BP	HZF 18BP
704	18C	HZF 18CP	HZF 18CP
705	18Y	BZV 49/C18	BZV 49/C18
706	19	SST 109	SST 109
707	193DT2	210V, 10A, 85W, >5MHz	BD 245F, 2SC1586, 2SD552, 2SD583
708	194	BFQ 194	BFQ 194
709	196	BFQ 196	BFQ 196
710	1A	MA 110	MA 110
711	1A	KST 3904	KST 3904
712	1A	BC 846AW	BC 846R
713	1A	FMMT 3904	FMMT 3904
714	1A	MMBT 3904	MMBT 3904
715	1A	YTS 3904	YTS 3904
716	1A	SXT 3904	SXT 3904
717	1A(p,s)	BC 846A	BC 846
718	1AG	HN1B01FU-GR	HN 1B01FU
719	1AG	HN 1B01F-GR	HN 1B01F



720	1AG	2SC3339-GR	2SC3339
721	1AL	2SC3339-BL	2SC3339
722	1AM	MMBT 3904	MMBT 3904
723	1AO	2SC3339-O	2SC3339
724	1AQ	2SB779-Q	2SB779
725	1AQ	2SB1584-Q	2SB1584
726	1AR	2SB779-R	2SB779
727	1AR	BC 846AR	BC 846R
728	1AR	2SB1584-R	2SB1584
729	1As	BC 846AW	BC 846W
730	1AS	2SB779-S	2SB779
731	1AS	2SB1584-S	2SB1584
732	1AS027	1AS029, 800V	BYD 14K...M, BYW 55...56, 2N5062
733	1AS029	1000V, 1,5A	BUD 14M, BYD 34M, BYV 96E, BYW 56
734	1AY	HN 1B01F-Y	HN 1B01F
735	1AY	HN 1B01FU-Y	HN 1B01FU
736	1AY	2SC3339-Y	2SC3339
737	1AZ6,8..330	6,8..330V, 10%, 1W	BZW22/..., BZX61/..., ZPY....
738	1B	2N2222	2N2222
739	1B	MA 111	MA 111
740	1B	KST 2222	KST 2222
741	1B	MMBT 2222	MMBT 2222
742	1B	YTS 2222	YTS 2222
743	1B	FMMT 2222	FMMT 2222
744	1B	BC 846BW	BC 846R
745	1B(p,s)	BC 846B	BC 846
746	1BG	2SC3340-GR	2SC3340
747	1BL	2SC3340-BL	2SC3340
748	1BR	BC 846BR	BC 846R
749	1Bs	BC 846BW	BC 846W
750	1C	MA 112	MA 112
751	1C	FMMT-A20	FMMT-A20
752	1C	KST 20	KST 20
753	1C	MMBTA 20	MMBTA 20
754	1CL	2SC4082-L	2SC4082
755	1CM	2SC4082-M	2SC4082
756	1CN	2SC4082-N	2SC4082
757	1CO	2SC3341-O	2SC3341
758	1CP	2SC4082-P	2SC4082
759	1CQ	2SC4082-Q	2SC4082
760	1CY	2SC3341-Y	2SC3341
761	1D	MA 113	MA 113
762	1D	BC 846W	BC 846W
763	1D	MMBTA 42	MMBTA 42
764	1D	KST 42	KST 42

765	1D	SXTA 42	SXTA 42
766	1D(p)	BC 846	BC 846
767	1DL	2SC408S-L	2SC4083
768	1DM	2SC4083-M	2SC4083
769	1DN	2SC4083-N	2SC4083
770	1DP	2SC4083-P	2SC4083
771	1DQ	2SC4083-Q	2SC4083
772	1DR	2SD1328-R	2SD1328
773	1DR	2SD2436-R	2SD2436
774	1DS	2SD1328-S	2SD1328
775	1DS	2SD2436-S	2SD2436
776	1DT	2SD1328-T	2SD1328
777	1DT	2SD2436-T	2SD2436
778	1E	MA 114	MA 114
779	1E	MMBTA 43	MMBTA 43
780	1E	BC 847AW	BC 847W
781	1E	KST 43	KST 43
782	1E	FMMT-A43	FMMT-A43
783	1E	SXTA 43	SXTA 43
784	1E(p,s)	BC 847A	BC 847
785	1EL	2SC4084-L	2SC4084
786	1EM	2SC4084-M	2SC4084
787	1EN	2SC4084-N	2SC4084
788	1EP	2SC4084-P	2SC4084
789	1EQ	2SC4084-Q	2SC4084
790	1ER	BC 847AR	BC 847R
791	1Es	BC 847AW	BC 847W
792	1EZ100..200D5,10	100..200V, 1W, D55%, D1010%	BZW 22/..., BZX 61/..., BZX 85/...
793	1F	MA 115	MA 115
794	1F	BC 847BW	BC 847W
795	1F	MMBT 5550	MMBT 5550
796	1F	KST 5550	KST 5550
797	1F	2SC4543	2SC4543
798	1F(p,s)	BC 847B	BC 847
799	1FP	2SK321-P	2SK321
800	1FQ	2SK321-Q	2SK321
801	1FR	2SK321-R	2SK321
802	1FR	BC 847BR	BC 847R
803	1Fs	BC 847BW	BC 847W
804	1FS	2SK321-S	2SK321
805	1G	FMMT-A06	FMMT-A06
806	1G	BC 847C	BC 847
807	1G	KST 06	KST 06
808	1G	BC 847CW	BC 847W
809	1G	MMBTA 06	MMBTA 06

810	1GM	MMBTA 06	MMBTA 06
811	1GR	BC 847CR	BC 847R
812	1Gs	BC 847CW	BC 847W
813	1GT	SOA 06	SOA 06
814	1H	MA 116	MA 116
815	1H	FMMT-A05	FMMT-A05
816	1H	BC 847W	BC 847W
817	1H	MMBTA 05	MMBTA 05
818	1H	KST 05	KST 05
819	1H(p)	BC 847	BC 847
820	1HR	2SD2185-R	2SD2185
821	1HS	2SD2185-S	2SD2185
822	1HT	SOA 05	SOA 05
823	1I	2SB1440	2SB1440
824	1IR	2SB1440-R	2SB1440
825	1IS	2SB1440-S	2SB1440
826	1J	MMBT 2369	MMBT 2369
827	1J	BC 848AW	BC 848W
828	1J	FMMT 2369	FMMT 2369
829	1J(p,s)	BC 848A	BC 848
830	1J2	SS 1J2	SS 1J2
831	1J4	SS 1J4	SS 1J4
832	1J6	SS 1J6	SS 1J6
833	1JA	MMBT 2369A	MMBT 2369A
834	1Jp	BCV 61A	BCV 61
835	1JR	BC 848AR	BC 848R
836	1Js	BCV 61A	BCV 61
837	1Js	BC 848AW	BC 848W
838	1K	KST 6428	KST 6428
839	1K	BC 848B	BC 848
840	1K	MMBT 6428	MMBT 6428
841	1K	BC 848BW	BC 848W
842	1K34(A)	1N34	1N34
843	1K60	1N60	1N60
844	1K90	1N90	1N90
845	1KM	MMBT 6428	MMBT 6428
846	1Kp	BCV 61B	BCV 61
847	1KP	2SK316-P	2SK316
848	1KQ	2SK316-Q	2SK316
849	1KR	BC 848BR	BC 848R
850	1KR	2SD2210-R	2SD2210
851	1Ks	BCV 61B	BCV 61
852	1Ks	BC 848BW	BC 848W
853	1KS	2SD2210-S	2SD2210
854	1KT	2SD2210-T	2SD2210

855	1L	MMBT 6429	MMBT 6429
856	1L	BC 848CW	BC 848W
857	1L	2SB1537	2SB1537
858	1L(p,s)	BC 848C	BC 848
859	1LM	2SC4103-M	2SC4103
860	1LN	2SC4103-N	2SC4103
861	1Lp	BCV 61C	BCV 61
862	1LP	2SC4103-P	2SC4103
863	1LQ	2SC4103-Q	2SC4103
864	1LR	BC 848CR	BC 848R
865	1Ls	BCV 61C	BCV 61
866	1Ls	BC 848CW	BC 848W
867	1M	MMBTA 13	MMBTA 13
868	1M	KST 13	KST 13
869	1M	IMBT 3903	IMBT 3903
870	1M	BC 848W	BC 848W
871	1M	FMMT-A13	FMMT-A13
872	1M	2SD2357	2SD2357
873	1M(p)	BC 848	BC 848
874	1M...ZS10	+ -10%	BZD23/..., BZT03/..., BZX70/...
875	1M...ZS5	+ -5%	BZD23/..., BZT03/..., BZX70/...
876	1M3.3..200ZS	3,3..200V, 2,5W, + -20%	BZD23/..., BZT03/..., BZX70/...
877	1MN	2SC4128-N	2SC4128
878	1Mp	BCV 61	BCV 61
879	1MP	2SJ84-P	2SJ84
880	1MP	2SC4128-P	2SC4128
881	1MQ	2SJ84-Q	2SJ84
882	1MR	2SJ84-R	2SJ84
883	1N	IMBT 3904	IMBT 3904
884	1N	MMBTA 14	MMBTA 14
885	1N	FMMT-A14	FMMT-A14
886	1N	KST 14	KST 14
887	1N	2SB1539	2SB1539
888	1N10	MMFT 1N10E	MMFT 1N10E
889	1N100(A)	100V, 30..70mA	AA 117...118, AA 132...133
890	1N102	125V	AA 133, 1N39
891	1N1028	50V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
892	1N1029	1N1028, 100V	BY 126...127, BY 133...135, 1N4002...07
893	1N103	20V	AA 117...118, AA 132...134, 1N34, 1N54
894	1N1030	1N1028, 150V	BY 126...127, BY 133...135, 1N4003...07
895	1N1031	1N1028, 200V	BY 126...127, BY 133...134, 1N4003...07
896	1N1032	1N1028, 300V	BY 126...127, BY 133...134, 1N4004...07
897	1N1033	1N1028, 400V	BY 126...127, BY 133...134, 1N4004...07
898	1N1034	50V, 1A(Tc100°)	BYX 38/300R, BYX 39/600R
899	1N1035	1N1034, 100V	BYX 38/300R, BYX 39/600R

900	1N1036	1N1034, 150V	BYX 38/300R, BYX 39/600R
901	1N1037	1N1034, 200V	BYX 38/300R, BYX 39/600R
902	1N1038	1N1034, 300V	BYX 38/300R, BYX 39/600R
903	1N1039	1N1034, 400V	BYX 38/600R, BYX 39/600R
904	1N104	25V	AA 117...118, AA 132...134, 1N34, 1N54
905	1N1040	50V, 1A(Tc100°)	BYX 38/300R, BYX 39/600R
906	1N1041	1N1040, 100V	BYX 38/300R, BYX 39/600R
907	1N1042	1N1040, 150V	BYX 38/300R, BYX 39/600R
908	1N1043	1N1040, 200V	BYX 38/300R, BYX 39/600R
909	1N1044	1N1040, 300V	BYX 38/300R, BYX 39/600R
910	1N1045	1N1040, 400V	BYX 38/600R, BYX 39/600R
911	1N1052	50V, 1,5A(Tc100°)	BYW 52...56, BYX 82...87. 1N5391...97
912	1N1053	1N1052, 100V	BYW 52...56, BYX 82...87. 1N5392...97
913	1N1054	1N1052, 150V	BYW 52...56, BYX 82...87. 1N5393...97
914	1N1055	1N1052, 200V	BYW 52...56, BYX 82...87. 1N5393...97
915	1N1056	1N1052, 300V	BYW 53...56, BYX 83...87. 1N5394...97
916	1N1057	1N1052, 400V	BYW 53...56, BYX 83...87. 1N5395...97
917	1N1058	50V, 5A(Tc100°)	BYX 38/300R, BYX 39/600R
918	1N1059	1N1058, 100V	BYX 38/300R, BYX 39/600R
919	1N106	300V	-
920	1N1060	1N1058, 150V	BYX 38/300R, BYX 39/600R
921	1N1061	1N1058, 200V	BYX 38/300R, BYX 39/600R
922	1N1062	1N1058, 300V	BYX 38/300R, BYX 39/600R
923	1N1063	1N1058, 400V	BYX 38/600R, BYX 39/600R
924	1N1064	50V, 5A(Tc100°)	BYX 38/300R, BYX 39/600R
925	1N1065	1N1064, 100V	BYX 38/300R, BYX 39/600R
926	1N1066	1N1064, 150V	BYX 38/300R, BYX 39/600R
927	1N1067	1N1064, 200V	BYX 38/300R, BYX 39/600R
928	1N1068	1N1064, 300V	BYX 38/300R, BYX 39/600R
929	1N1069	1N1064, 400V	BYX 38/600R, BYX 39/600R
930	1N107	10V, 100mA	AA 135...136, AA 139
931	1N108	50V	AA 135...136, AA 139
932	1N109	15V, 50mA	-
933	1N1093	15V, 500ns	AAY 27...28, 1N191...192, 1N3592
934	1N1095	500V, 0,75A(Tc50°)	BY 126...127, BY 133...134, 1N4005...07
935	1N1096	1N1095, 600V	BY 126...127, BY 133...134, 1N4005...07
936	1N1100	100V, 0,75A(Tc50°)	BY 126...127, BY 133...135, 1N4002...07
937	1N1101	1N1100, 200V	BY 126...127, BY 133...134, 1N4003...07
938	1N1102	1N1100, 300V	BY 126...127, BY 133...134, 1N4004...07
939	1N1103	1N1100, 400V	BY 126...127, BY 133...134, 1N4004...07
940	1N1104	1N1100, 500V	BY 126...127, BY 133...134, 1N4005...07
941	1N1105	1N1100, 600V	BY 126...127, BY 133...134, 1N4005...07
942	1N111	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
943	1N1115	100V, 1,5A(Tc85°)	BYX 38/300, BYX 39/600
944	1N1115R...1120R	1N1115..1120	BYX 38/600R, BYX 39/600R

945	1N1116	1N1115, 200V	BYX 38/300, BYX 39/600
946	1N1117	1N1115, 300V	BYX 38/300, BYX 39/600
947	1N1118	1N1115, 400V	BYX 38/600, BYX 39/600
948	1N1119	1N1115, 500V	BYX 38/600, BYX 39/600
949	1N112	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
950	1N1120	1N1115, 600V	BYX 38/600, BYX 39/600
951	1N1124(A)	200V, 3..3,3A(Tc50°)	BYX 38/600, BYX 39/600
952	1N1124R...1128R	1N1124(A)..1128(A)	BYX 38/600R, BYX 39/600R
953	1N1125(A)	1N1124(A), 300V	BYX 38/600, BYX 39/600
954	1N1126(A)	1N1124(A), 400V	BYX 38/600, BYX 39/600
955	1N1127(A)	1N1124(A), 500V	BYX 38/600, BYX 39/600
956	1N1128(A)	1N1124(A), 600V	BYX 38/600, BYX 39/600
957	1N113	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
958	1N1130	1500V, 0,3A	-
959	1N1131	1N1130	-
960	1N1133	1,5kV, 0,075A	1N5181
961	1N1134	1,5kV, 0,1A	1N5181
962	1N1135	1,8kV, 0,065A	1N5181
963	1N1136	1,8kV, 0,085A	1N5181
964	1N1137	2,4kV, 0,05A	1N5181
965	1N1138	2,4kV, 0,06A	1N5181
966	1N1139	3,6kV, 0,065A	1N5181
967	1N114	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
968	1N1140	3,6kV, 0,065A	1N5181
969	1N1141	4,8kV, 0,06A	1N5182
970	1N1142	4,8kV, 0,05A	1N5182
971	1N1143	6kV, 0,05A	1N5183
972	1N1143A	1N1143, 0,065mA	1N5183
973	1N1144	7,2kV, 0,05A	1N5183
974	1N1145	7,2kV, 0,06A	1N5183
975	1N1146	8kV, 0,045A	1N5184
976	1N1147	12kV, 0,045A	1N3052
977	1N1148	14kV, 0,05A	1N3053
978	1N1149	16kV, 0,045A	1N3054
979	1N115	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
980	1N116(A)	60..70V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
981	1N1169	400V, 0,79A	BY 126...127, BY 133...134, 1N4004...07
982	1N1169A	1N1169	BY 126...127, BY 133...134, 1N4004...07
983	1N117(A)	60..70V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
984	1N1170	50V	AA 117...118, AA 132...134, 1N34, 1N54
985	1N118(A)	60V, 30..70mA	AA 117...118, AA 132...134, 1N34, 1N54
986	1N1183	50V, 35A(Tc140°)	1N3765, 1N4525
987	1N1183R...1190R	1N1183..1190	1N3765R
988	1N1183T...1190T	1N1183..1190	1N3765T
989	R	1N1183..1190	1N3765TR

990	1N1184	1N1183, 100V	1N3765, 1N4525
991	1N1185	1N1183, 150V	1N3765, 1N4525
992	1N1186	1N1183, 200V	1N3765, 1N4525
993	1N1187	1N1183, 300V	1N3765, 1N4526
994	1N1188	1N1183, 400V	1N3765, 1N4526
995	1N1189	1N1183, 500V	1N3765, 1N4527
996	1N119	60V, 25mA	AAV 28, 1N191...192, 1N276
997	1N1190	1N1183, 600V	1N3765, 1N4527
998	1N1191(A)	50V, 20A(Tc150°)	1N3765, 1N4525
999	1N1191R...1198R	1N1191..1198	1N3765R
1000	1N1192(A)	1N1191, 100V	1N3765, 1N4525
1001	1N1193(A)	1N1191, 150V	1N3765, 1N4525
1002	1N1194(A)	1N1191, 200V	1N3765, 1N4525
1003	1N1195(A)	1N1191, 300V	1N3765, 1N4526
1004	1N1196(A)	1N1191, 400V	1N3765, 1N4526
1005	1N1197(A)	1N1191, 500V	1N3765, 1N4527
1006	1N1198(A)	1N1191, 600V	1N3765, 1N4527
1007	1N1199(A,B,C)	50V, 12A	
1008	1N120	60V, 25mA	AAV 28, 1N191...192, 1N276
1009	1N1200(A,B,C)	1N1199, 100V	BYW 88/100, BYX 76
1010	1N1201(A,B,C)	1N1199, 150V	BYW 88/200, BYX 77
1011	1N1201R...1206R	1N1199..1206	BYW 88/...R, BYX 75R...79R
1012	1N1202(A,B,C)	1N1199, 200V	BYW 88/200, BYX 77
1013	1N1203(A,B,C)	1N1199, 300V	BYW 88/300, BYX 78
1014	1N1204(A,B,C)	1N1199, 400V	BYW 88/400, BYX 78
1015	1N1205(A,B,C)	1N1199, 500V	BYW 88/500, BYX 79
1016	1N1206(A,B,C)	1N1199, 600V	BYW 88/600, BYX 79
1017	1N1217(A,B)	50V, 1.6A	BY 251...255, BYW 52...56, 1N5060...62
1018	1N1218(A,B)	1N1217, 100V	BY 251...255, BYW 52...56, 1N5060...62
1019	1N1219(A,B)	1N1217, 150V	BY 251...255, BYW 52...56, 1N5060...62
1020	1N1220(A,B)	1N1217, 200V	BY 251...255, BYW 52...56, 1N5060...62
1021	1N1221(A,B)	1N1217, 300V	BY 252...255, BYW 53...56, 1N5060...62
1022	1N1222(A,B)	1N1217, 400V	BY 252...255, BYW 53...56, 1N5060...62
1023	1N1223(A,B)	1N1217, 500V	BY 253...255, BYW 54...56, 1N5061...62
1024	1N1224(A,B)	1N1217, 600V	BY 253...255, BYW 54...56, 1N5061...62
1025	1N1225(A,B)	1N1217, 700V	BY 254...255, BYW 55...56, 1N5062
1026	1N1226(A,B)	1N1217, 800V	BY 254...255, BYW 55...56, 1N5062
1027	1N1227(A,B)	1N1217	BYX 38/300, BYX 39/600
1028	1N1228(A,B)	1N1218	BYX 38/300, BYX 39/600
1029	1N1229(A,B)	1N1219	BYX 38/300, BYX 39/600
1030	1N1230(A,B)	1N1220	BYX 38/300, BYX 39/600
1031	1N1231(A,B)	1N1221	BYX 38/300, BYX 39/600
1032	1N1232(A,B)	1N1222	BYX 38/300, BYX 39/600
1033	1N1233(A,B)	1N1223	BYX 38/600, BYX 39/600
1034	1N1234(A,B)	1N1224	BYX 38/600, BYX 39/600

1035	1N1235(A,B)	1N1225	BYX 38/900, BYX 39/800
1036	1N1236(A,B)	1N1226	BYX 38/900, BYX 39/800
1037	1N1251	50V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
1038	1N1252	1N1251, 100V	BY 126...127, BY 133...135, 1N4002...07
1039	1N1253	1N1251, 200V	BY 126...127, BY 133...134, 1N4003...07
1040	1N1254	1N1251, 300V	BY 126...127, BY 133...134, 1N4004...07
1041	1N1255(A)	1N1251, 400V	BY 126...127, BY 133...134, 1N4004...07
1042	1N1256	1N1251, 500V, 0,32A	BY 126...127, BY 133...134, 1N4005...07
1043	1N1257	1N1251, 600V, 0,3A	BY 126...127, BY 133...134, 1N4005...07
1044	1N1258	1N1251, 700V, 0,28A	BY 127, BY 133, BYX 95, 1N4006...07
1045	1N1259	1N1251, 800V, 0,27A	BY 127, BY 133, BYX 95, 1N4006...07
1046	1N126(A)	60..75V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
1047	1N1260	1N1251, 900V, 0,25A	BY 127, BY 133, BYX 95, 1N4007
1048	1N1261	1N1251, 1000V, 0,24A	BY 127, BY 133, BYX 95, 1N4007
1049	1N127(A)	100..125V, 30mA	AA 117...118, AA 132...133
1050	1N128(A)	40V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
1051	1N1281	50V, 160A	-
1052	1N1282	1N1281, 100V	-
1053	1N1283	1N1281, 150V	-
1054	1N1284	1N1281, 200V	-
1055	1N1285	1N1281, 300V	-
1056	1N1286	1N1281, 400V	-
1057	1N1287	1N1281, 500V	-
1058	1N1291...1297	1N1281..1287	-
1059	1N1301	50V, 37A(Tc120°)	1N3765, 1N4525
1060	1N1302	1N1301, 100V	1N3765, 1N4525
1061	1N1304	1N1301, 200V	1N3765, 1N4525
1062	1N1306	1N1301, 300V	1N3765, 1N4526
1063	1N1313	8,75V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5238...74
1064	1N1313	8,75V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5238...74
1065	1N1313A...1327A	1N1313..1327, 5%	
1066	1N1314	1N1313, 10,5V	
1067	1N1315	1N1313, 12,75V	
1068	1N1316	1N1313, 15,75V	
1069	1N1317	1N1313, 19V	
1070	1N1318	1N1313, 23,5V	
1071	1N1319	1N1313, 28,5V	
1072	1N132		-
1073	1N1320	1N1313, 34,5V	
1074	1N1321	1N1313, 41V	
1075	1N1322	1N1313, 48,5V	
1076	1N1323	1N1313, 58V	
1077	1N1324	1N1313, 71V	
1078	1N1325	1N1313, 87,5V	
1079	1N1326	1N1313, 105V	



1080	1N1327	1N1313, 127,5V	
1081	1N133	5V	-
1082	1N1330	50V, 240A(Tc125°)	-
1083	1N1331	1N1330, 100V	-
1084	1N1332	1N1330, 150V	-
1085	1N1333	1N1330, 200V	-
1086	1N1334	1N1330, 300V	-
1087	1N1335	1N1330, 400V	-
1088	1N1336	1N1330, 500V	-
1089	1N1341(A,B,C)	50V, 6A(Tc150°)	
1090	1N1341R...1348R	1N1341..1348	BYX 38/600R, BYX 39/600R
1091	1N1342(A,B,C)	1N1341, 100V	BYX 38/300, BYX 39/600
1092	1N1343(A,B,C)	1N1341, 150V	BYX 38/300, BYX 39/600
1093	1N1344(A,B,C)	1N1341, 200V	BYX 38/300, BYX 39/600
1094	1N1345(A,B,C)	1N1341, 300V	BYX 38/300, BYX 39/600
1095	1N1346(A,B,C)	1N1341, 400V	BYX 38/600, BYX 39/600
1096	1N1347(A,B,C)	1N1341, 500V	BYX 38/600, BYX 39/600
1097	1N1348(A,B,C)	1N1341, 600V	BYX 38/600, BYX 39/600
1098	1N135	75V	AA 117...118, AA 132...133, 1N34, 1N54
1099	1N1351	10V, 10%, 10W(Tc55°)	BZX 98/..., BZY 93/..., 1N2974...3005
1100	1N1351A...1375A	1N1351..1375, 5%	
1101	1N1351B...1375B	1N1351..1375, 20%	
1102	1N1351C...1375C	1N1351..1375, bidirecional	-
1103	A	1N1351..1375, bidirecional, 5%	-
1104	1N1351R...1375R	1N1351..1375	
1105	1N1352	1N1351, 11V	
1106	1N1353	1N1351, 12V	
1107	1N1354	1N1351, 13V	
1108	1N1355	1N1351, 15V	
1109	1N1356	1N1351, 16V	
1110	1N1357	1N1351, 18V	
1111	1N1358	1N1351, 20V	
1112	1N1359	1N1351, 22V	
1113	1N1360	1N1351, 24V	
1114	1N1361	1N1351, 27V	
1115	1N1362	1N1351, 30V	
1116	1N1363	1N1351, 33V	
1117	1N1364	1N1351, 36V	
1118	1N1365	1N1351, 39V	
1119	1N1366	1N1351, 43V	
1120	1N1367	1N1351, 47V	
1121	1N1368	1N1351, 51V	
1122	1N1369	1N1351, 56V	
1123	1N137	RT 1N137L	RT 1N137L
1124	1N137(A,B)	32..36V, 30..75mA	BA 127, BA 147/50, 1N4148, 1N5194...96

1125	1N1370	1N1351, 62V	
1126	1N1371	1N1351, 68V	
1127	1N1372	1N1351, 75V	
1128	1N1373	1N1351, 82V	
1129	1N1374	1N1351, 91V	
1130	1N1375	1N1351, 100V	
1131	1N1376	50V, 240A(Tc125°C)	-
1132	1N1377	1N1376, 100V	-
1133	1N1378	1N1376, 150V	-
1134	1N1379	1N1376, 200V	-
1135	1N138(A,B)	16..18V, 9..50mA	BA 127, BA 147/25, 1N4148, 1N5194...96
1136	1N1380	1N1376, 300V	-
1137	1N1381	1N1376, 400V	-
1138	1N1382	1N1376, 500V	-
1139	1N139	46V, 70mA	AA 117...118, AA 132...134, 1N34, 1N54
1140	1N1396	50V, 70A(Tc150°)	1N3288
1141	1N1397	2N1396, 100V	1N3288
1142	1N1398	2N1396, 150V	1N3289
1143	1N1399	2N1396, 200V	1N3289
1144	1N140	80V, 85mA	AA 117...118, AA 132...133, 1N34, 1N54
1145	1N1400	2N1396, 300V	1N3290
1146	1N1401	2N1396, 400V	1N3291
1147	1N1402	2N1396, 500V	1N3292
1148	1N1403	2N1396, 600V	1N3293
1149	1N1406	600V, 0,125A	BY 203/12, RGP 01/10, SHG 1
1150	1N1407	1N1406, 800V	BY 203/12, RGP 01/10, SHG 1
1151	1N1408	1N1406, 1000V	BY 203/12, RGP 01/10, SHG 1
1152	1N1409	1N1406, 1200V	BY 203/12, RGP 01/12, SHG 1,5
1153	1N141	80V, 70mA	AA 113, 1N34, 1N54
1154	1N1410	1N1406, 1500V	BY 203/16, RGP 01/16, SHG 1,5
1155	1N1411	1N1406, 1800V	BY 203/20, SHG 2
1156	1N1412	1N1406, 2000V	BY 203/20, SHG 2
1157	1N1413	1N1406, 2400V	SHG 2,5
1158	1N1415	400V, 1A	BY 126...127, BY 133...134, 1N4004...07
1159	1N1416	8,2V, 5%, 10W	BZX98/..., BZY93/..., 1N2972...3011
1160	1N1417	1N1416, 12V	
1161	1N1418	1N1416, 15V	
1162	1N1419	1N1416, 18V	
1163	1N142	115V, 60mA	AA 117...118, AA 132...133
1164	1N1420	1N1416, 22V	
1165	1N1421	1N1416, 27V	
1166	1N1422	1N1416, 68V	
1167	1N1423	1N1416, 100V	
1168	1N1424	1N1416, 150V	
1169	1N1425	8,2V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5923...53

1170	1N1426	1N1425, 12V	
1171	1N1427	1N1425, 15V	
1172	1N1428	1N1425, 18V	
1173	1N1429	1N1425, 22V	
1174	1N143	115V, 85mA	AA 117...118, AA 132...133
1175	1N1430	1N1425, 27V	
1176	1N1431	1N1425, 68V	
1177	1N1432	1N1425, 100V	
1178	1N1433	1N1425, 150V	
1179	1N1434	50V, 30A	1N3765, 1N4525
1180	1N1435	1N1434, 100V	1N3765, 1N4525
1181	1N1436	1N1434, 200V	1N3765, 1N4525
1182	1N1437	1N1434, 400V	1N3765, 1N4526
1183	1N1438	1N1434, 600V	1N3765, 1N4526
1184	1N1439	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
1185	1N144	35V, 150mA	AA 136, 1N270
1186	1N1440	1N1439, 200V	BY 126...127, BY 133...134, 1N4003...07
1187	1N1441	1N1439, 300V	BY 126...127, BY 133...134, 1N4004...07
1188	1N1442	1N1439, 400V	BY 126...127, BY 133...134, 1N4004...07
1189	1N1443(A,B)	1000V, 0,95..1,6A	BY 255, BYW 56, GP 15M, 1N5399
1190	1N1444(A,B)	1N1443(A,B)	-
1191	1N145	40V, 0,7A	AA 117...118, AA 132...134, 1N34, 1N54
1192	1N147(A)	900MHz	-
1193	1N1482	4,7V, 5%, 10W	BZX98/..., BZY93/..., 1N3995...3998
1194	1N1483	6,2V, 5%, 10W	
1195	1N1484	4,7V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5917...20
1196	1N1485	6,2V, 5%, 1W	
1197	1N1486	500V, 0,78A	BY 126...127, BY 133...134, 1N4005...07
1198	1N1487	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
1199	1N1488	1N1487, 200V	BY 126...127, BY 133...134, 1N4003...07
1200	1N1489	1N1487, 300V	BY 126...127, BY 133...134, 1N4004...07
1201	1N1490	1N1487, 400V	BY 126...127, BY 133...134, 1N4004...07
1202	1N1491	1N1487, 500V	BY 126...127, BY 133...134, 1N4005...07
1203	1N1492	1N1487, 600V	BY 126...127, BY 133...134, 1N4005...07
1204	1N1507	3,9V, 10%, 0,75W	BZV85/..., BZW22/..., ZPY..., 1N4730...50
1205	1N1507A...1517A	1N1507..1517, 5%	
1206	1N1508	1N1507, 4,7V	
1207	1N1509	1N1507, 5,6V	
1208	1N1510	1N1507, 6,8V	
1209	1N1511	1N1507, 8,2V	
1210	1N1512	1N1507, 10V	
1211	1N1513	1N1507, 12V	
1212	1N1514	1N1507, 15V	
1213	1N1515	1N1507, 18V	
1214	1N1516	1N1507, 22V	

1215	1N1517	1N1507, 27V	
1216	1N1518	3,9V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5915...35
1217	1N1518A...1528A	1N1518..1528, 5%	
1218	1N1519	1N1518, 4,7V	
1219	1N1520	1N1518, 5,6V	
1220	1N1521	1N1518, 6,8V	
1221	1N1522	1N1518, 8,2V	
1222	1N1523	1N1518, 10V	
1223	1N1524	1N1518, 12V	
1224	1N1525	1N1518, 15V	
1225	1N1526	1N1518, 18V	
1226	1N1527	1N1518, 22V	
1227	1N1528	1N1518, 27V	
1228	1N1537	50V, 1,6A(Tc140°)	BYX 38/300, BYX 39/600
1229	1N1538	1N1537, 100V	BYX 38/300, BYX 39/600
1230	1N1539	1N1537, 150V	BYX 38/300, BYX 39/600
1231	1N1540	1N1537, 200V	BYX 38/300, BYX 39/600
1232	1N1541	1N1537, 300V	BYX 38/300, BYX 39/600
1233	1N1542	1N1537, 400V	BYX 38/600, BYX 39/600
1234	1N1543	1N1537, 500V	BYX 38/600, BYX 39/600
1235	1N1544	1N1537, 600V	BYX 38/600, BYX 39/600
1236	1N1551	100V, 1A(Tc100°)	BYX 38/300, BYX 39/600
1237	1N1552	1N1551, 200V	BYX 38/300, BYX 39/600
1238	1N1553	1N1551, 300V	BYX 38/300, BYX 39/600
1239	1N1554	1N1551, 400V	BYX 38/600, BYX 39/600
1240	1N1555	1N1551, 500V	BYX 38/600, BYX 39/600
1241	1N1556	100V, 0,75A(Tc100°)	BY 126...127, BY 133...135, 1N4002...07
1242	1N1557	1N1556, 200V	BY 126...127, BY 133...134, 1N4003...07
1243	1N1558	1N1556, 300V	BY 126...127, BY 133...134, 1N4004...07
1244	1N1559	1N1556, 400V	BY 126...127, BY 133...134, 1N4004...07
1245	1N1560	1N1556, 500V	BY 126...127, BY 133...134, 1N4005...07
1246	1N1563(A)	100V, 1,5A	BY 251...255, BYW 52...56, 1N5392...99
1247	1N1564(A)	1N1563, 200V	BY 251...255, BYW 52...56, 1N5393...99
1248	1N1565(A)	1N1563, 300V	BY 252...255, BYW 53...56, 1N5394...99
1249	1N1566(A)	1N1563, 400V	BY 252...255, BYW 53...56, 1N5395...99
1250	1N1567(A)	1N1563, 500V	BY 253...255, BYW 54...56, 1N5396...99
1251	1N1568(A)	1N1563, 600V	BY 253...255, BYW 54...56, 1N5398...99
1252	1N1575	100V, 3,5A(Tc25°)	BYX 38/300, BYX 39/600
1253	1N1576	1N1575, 200V	BYX 38/300, BYX 39/600
1254	1N1577	1N1575, 300V	BYX 38/300, BYX 39/600
1255	1N1578	1N1575, 400V	BYX 38/600, BYX 39/600
1256	1N1579	1N1575, 500V	BYX 38/600, BYX 39/600
1257	1N1580	1N1575, 600V	BYX 38/600, BYX 39/600
1258	1N1581	50V, 10A(Tc50°)	BYW 88/50, BYX 42/300, BYX 98/300
1259	1N1581R...1587R	1N1581..1587	BYW 88/...R, BYX 42/...R, BYX 98/...R

1260	1N1582	1N1581, 100V	BYW 88/100, BYX 42/300, BYX 98/300
1261	1N1583	1N1581, 200V	BYW 88/200, BYX 42/300, BYX 98/300
1262	1N1584	1N1581, 300V	BYW 88/300, BYX 42/300, BYX 98/300
1263	1N1585	1N1581, 400V	BYW 88/400, BYX 42/600, BYX 98/600
1264	1N1586	1N1581, 500V	BYW 88/500, BYX 42/600, BYX 98/600
1265	1N1587	1N1581, 600V	BYW 88/600, BYX 42/600, BYX 98/600
1266	1N1588	3,9V, 10%, 3,5W	BZX98/..., BZY93/..., 1N2970...2988
1267	1N1588A...1598A	1N1588..1598, 5%	
1268	1N1589	1N1588, 4,7V	
1269	1N1590	1N1588, 5,6V	
1270	1N1591	1N1588, 6,8V	
1271	1N1592	1N1588, 8,2V	
1272	1N1593	1N1588, 10V	
1273	1N1594	1N1588, 12V	
1274	1N1595	1N1588, 15V	
1275	1N1596	1N1588, 18V	
1276	1N1597	1N1588, 22V	
1277	1N1598	1N1588, 27V	
1278	1N1599	3,9V, 10%, 10W	BZX98/..., BZY93/..., 1N2970...2988
1279	1N1599A...1609A	1N1599..1609, 5%	
1280	1N1600	1N1599, 4,7V	
1281	1N1601	1N1599, 5,6V	
1282	1N1602	1N1599, 6,8V	
1283	1N1603	1N1599, 8,2V	
1284	1N1604	1N1599, 10V	
1285	1N1605	1N1599, 12V	
1286	1N1606	1N1599, 15V	
1287	1N1607	1N1599, 18V	
1288	1N1608	1N1599, 22V	
1289	1N1609	1N1599, 27V	
1290	1N1612(A)	50V, 15A(Tc50°)	
1291	1N1612R..1616R	1N1612..1616	BYX 25/...R, BYX 99/...R, SSi E2040
1292	1N1613(A)	1N1612, 100V	BYX 25/600, BYX 99/300
1293	1N1614(A)	1N1612, 200V	BYX 25/600, BYX 99/300
1294	1N1615(A)	1N1612, 400V	BYX 25/600, BYX 99/600
1295	1N1616(A)	1N1612, 600V	BYX 25/600, BYX 99/600
1296	1N1617	100V, 1,5A	BY 251...255, BY 226...227, 1N5392...99
1297	1N1618	1N1617, 200V	BY 251...255, BY 226...227, 1N5393...99
1298	1N1619	1N1617, 300V	BY 252...255, BY 226...227, 1N5394...99
1299	1N1620	1N1617, 400V	BY 252...255, BY 226...227, 1N5395...99
1300	1N1621	100V, 10A(Tc100°)	BYW 88/100, BYX 76...81, 2N4506...11
1301	1N1622	1N1621, 200V	BYW 88/200, BYX 77...81, 2N4506...11
1302	1N1623	1N1621, 300V	BYW 88/300, BYX 78...81, 2N4507...11
1303	1N1624	1N1621, 400V	BYW 88/400, BYX 78...81, 2N4507...11
1304	1N1625(A)	48V, 0,25..0,5mA	-

1305	1N1626(A)	96V, 0,25..0,5mA	-
1306	1N1627	48V, 3,8mA	-
1307	1N1628	96V, 3,8mA	-
1308	1N1629	144V, 3,8mA	-
1309	1N1630	192V, 3,8mA	-
1310	1N1631	240V, 3,8mA	-
1311	1N1632	288V, 3,8mA	-
1312	1N1633	336V, 3,8mA	-
1313	1N1634	384V, 3,8mA	-
1314	1N1635	48V, 13mA	-
1315	1N1636	96V, 13mA	-
1316	1N1637	144V, 13mA	-
1317	1N1638	192V, 13mA	-
1318	1N1639	240V, 13mA	-
1319	1N1640	48V, 28mA	-
1320	1N1641	96V, 28mA	-
1321	1N1642	144V, 28mA	-
1322	1N1644	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
1323	1N1645	1N1644, 100V	BY 126...127, BY 133...135, 1N4002...07
1324	1N1646	1N1644, 150V	BY 126...127, BY 133...134, 1N4003...07
1325	1N1647	1N1644, 200V	BY 126...127, BY 133...134, 1N4003...07
1326	1N1648	1N1644, 250V	BY 126...127, BY 133...134, 1N4004...07
1327	1N1649	1N1644, 300V	BY 126...127, BY 133...134, 1N4004...07
1328	1N1650	1N1644, 350V	BY 126...127, BY 133...134, 1N4004...07
1329	1N1651	1N1644, 400V	BY 126...127, BY 133...134, 1N4004...07
1330	1N1652	1N1644, 500V	BY 126...127, BY 133...134, 1N4005...07
1331	1N1653	1N1644, 600V	BY 126...127, BY 133...134, 1N4005...07
1332	1N1660	50V, 116A(Tc120°)	1N4587...96
1333	1N1661	1N1660, 100V	1N4587...96
1334	1N1662	1N1660, 150V	1N4588...96
1335	1N1663	1N1660, 200V	1N4588...96
1336	1N1664	1N1660, 300V	1N4589...96
1337	1N1665	1N1660, 400V	1N4590...96
1338	1N1666	1N1660, 500V	1N4591...96
1339	1N1670	50V, 240A(Tc120°)	1N3735...44
1340	1N1671	1N1670, 100V	1N3735...44
1341	1N1672	1N1670, 150V	1N3736...44
1342	1N1673	1N1670, 200V	1N3736...44
1343	1N1674	1N1670, 300V	1N3737...44
1344	1N1675	1N1670, 400V	1N3738...44
1345	1N1676	1N1670, 500V	1N3739...44
1346	1N1680	150V, 50A(Tc150°)	1N3289...97
1347	1N1681	1N1680, 250V	1N3290...97
1348	1N1682	1N1680, 300V	1N3290...97
1349	1N1683	1N1680, 350V	1N3291...97

1350	1N1684	1N1680, 400V	1N3291...97
1351	1N1685	1N1680, 450V	1N3292...97
1352	1N1686	1N1680, 500V	1N3292...97
1353	1N1687	1N1680, 600V	1N3293...97
1354	1N1688	1N1680, 700V	1N3294...97
1355	1N1689	1N1680, 800V	1N3294...97
1356	1N1690	1N1680, 900V	1N3295...97
1357	1N1691	1N1680, 1000V	1N3295...97
1358	1N1692	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
1359	1N1693	1N1692, 200V	BY 126...127, BY 133...134, 1N4003...07
1360	1N1694	1N1692, 300V	BY 126...127, BY 133...134, 1N4004...07
1361	1N1695	1N1692, 400V	BY 126...127, BY 133...134, 1N4004...07
1362	1N1696	1N1692, 500V	BY 126...127, BY 133...134, 1N4005...07
1363	1N1697	1N1692, 600V	BY 126...127, BY 133...134, 1N4005...07
1364	1N1698	6,6kV, 0,062A	1N5183...84
1365	1N1699	10kV, 0,058A	1N5184
1366	1N1700	12kV, 0,05A	1N3052
1367	1N1701	50V, 0,3A	BA 157...159, BY 206...207, BY 401...405
1368	1N1702	1N1701, 100V	BA 157...159, BY 206...207, BY 402...405
1369	1N1703	1N1701, 200V	BA 157...159, BY 206...207, BY 403...405
1370	1N1704	1N1701, 300V	BA 157...159, BY 206...207, BY 404...405
1371	1N1705	1N1701, 400V	BA 157...159, BY 207, BY 404...405
1372	1N1706	1N1701, 500V	BA 158...159, BY 207, BY 405
1373	1N1707	50V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
1374	1N1708	1N1707, 100V	BY 126...127, BY 133...135, 1N4002...07
1375	1N1709	1N1707, 200V	BY 126...127, BY 133...134, 1N4003...07
1376	1N1710	1N1707, 300V	BY 126...127, BY 133...134, 1N4004...07
1377	1N1711	1N1707, 400V	BY 126...127, BY 133...134, 1N4004...07
1378	1N1712	1N1707, 500V	BY 126...127, BY 133...134, 1N4005...07
1379	1N1730	1kV, 0,2A	GP 02-20, HVG 2, MR 250-2
1380	1N1730A	1N1730, 0,35A	-
1381	1N1731	1,5kV, 0,2A	GP 02-20, HVG 2, MR 250-2
1382	1N1731A	1N1731, 0,35A	-
1383	1N1732	2kV, 0,2A	GP 02-20, HVG 2, MR 250-2
1384	1N1732A	1N1732, 0,35A	-
1385	1N1733	3kV, 0,2A	GP 02-30, HVG 3, MR 250-3
1386	1N1733A	1N1733, 0,35A	-
1387	1N1734	5kV, 0,2A	HVG 5, MR 250-5
1388	1N1734A	1N1734, 0,35A	-
1389	1N1735(A)	6,2V, 5%, 0,2W	BZV 10...11, BZV 27...28, 1N4580...81
1390	1N1736(A)	12,4V, 5%, 0,4W	1N4908...09, 1N4912...13
1391	1N1737(A)	18,6V, 5%, 0,6W	-
1392	1N1738(A)	24,8V, 5%, 0,8W	-
1393	1N1739(A)	31V, 5%, 1W	-
1394	1N1740(A)	37,2V, 5%, 1,2W	-



1395	1N1741(A)	43,4V, 5%, 1,4W	-
1396	1N1742(A)	49,6V, 5%, 1,6W	-
1397	1N1743	10V, 5%, 10W	BZX98/C10, BZY93/C10, 1N2974
1398	1N1744	10V, 5%, 1W	BZW22/C10, BZX61/C10, ZPY10, 1N5925
1399	1N1745	1,5kV, 0,38A	1N1731A
1400	1N1746	1,5kV, 0,44A	-
1401	1N1747	1,8kV, 0,36A	1N1732A
1402	1N1748	1,8kV, 0,42A	-
1403	1N1749	2,4kV, 0,23A	1N1733A
1404	1N175	125V,	AA 133
1405	1N1750	2,4kV, 0,38A	-
1406	1N1751	3,6kV, 0,37A	1N1734A
1407	1N1752	3,6kV, 0,36A	1N1734A
1408	1N1753	4,8kV, 0,33A	1N1734A
1409	1N1754	4,8kV, 0,32A	1N1734A
1410	1N1755	6kV, 0,29A	-
1411	1N1756	6kV, 0,36A	-
1412	1N1757	7,2kV, 0,29A	-
1413	1N1758	7,2kV, 0,33A	-
1414	1N1759	8kV, 0,25A	-
1415	1N1760	12kV, 0,25A	-
1416	1N1761	14kV, 0,3A	-
1417	1N1762	16kV, 0,25A	-
1418	1N1763(A)	400V, 0,5..1A	BY 126...127, BY 133...134, 1N4004...07
1419	1N1764(A)	1N1763, 500V	BY 126...127, BY 133...134, 1N4005...07
1420	1N1765	5,6V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1M5919...56
1421	1N1765A...1802A	1N1765..1802, 5%	
1422	1N1766	1N1765, 6,2V	
1423	1N1767	1N1765, 6,8V	
1424	1N1768	1N1765, 7,5V	
1425	1N1769	1N1765, 8,2V	
1426	1N1770	1N1765, 9,1V	
1427	1N1771	1N1765, 10V	
1428	1N1772	1N1765, 11V	
1429	1N1773	1N1765, 12V	
1430	1N1774	1N1765, 13V	
1431	1N1775	1N1765, 15V	
1432	1N1776	1N1765, 16V	
1433	1N1777	1N1765, 18V	
1434	1N1778	1N1765, 20V	
1435	1N1779	1N1765, 22V	
1436	1N1780	1N1765, 24V	
1437	1N1781	1N1765, 27V	
1438	1N1782	1N1765, 30V	
1439	1N1783	1N1765, 33V	



1440	1N1784	1N1765, 36V	
1441	1N1785	1N1765, 39V	
1442	1N1786	1N1765, 43V	
1443	1N1787	1N1765, 47V	
1444	1N1788	1N1765, 51V	
1445	1N1789	1N1765, 56V	
1446	1N1790	1N1765, 62V	
1447	1N1791	1N1765, 68V	
1448	1N1792	1N1765, 75V	
1449	1N1793	1N1765, 82V	
1450	1N1794	1N1765, 91V	
1451	1N1795	1N1765, 100V	
1452	1N1796	1N1765, 110V	
1453	1N1797	1N1765, 120V	
1454	1N1798	1N1765, 130V	
1455	1N1799	1N1765, 150V	
1456	1N1800	1N1765, 160V	
1457	1N1801	1N1765, 180V	
1458	1N1802	1N1765, 200V	
1459	1N1803	5,6V, 10%, 10W	BZX98/..., BZY93/..., 1N2970...3015
1460	1N1803A...1815A	1N1803..1815, 5%	
1461	1N1803B...1815B	1N1803..1815, 20%	
1462	1N1803C...1815C	1N1803..1815, bidirecional	
1463	A	1N1803..1815, bidirecional, 5%	
1464	1N1803R...1815R	1N1803..1815	
1465	1N1804	1N1803, 6,2V	
1466	1N1805	1N1803, 6,8V	
1467	1N1806	1N1803, 7,5V	
1468	1N1807	1N1803, 8,2V	
1469	1N1808	1N1803, 9,1V	
1470	1N1809	1N1803, 110V	
1471	1N1810	1N1803, 120V	
1472	1N1811	1N1803, 130V	
1473	1N1812	1N1803, 150V	
1474	1N1813	1N1803, 160V	
1475	1N1814	1N1803, 180V	
1476	1N1815	1N1803, 200V	
1477	1N1816	13V, 10%, 10W	BZX98/..., BZY93/..., 1N2977...3004
1478	1N1816A...1836A	1N1816..1836, 5%	
1479	1N1816C...1836C	1N1816..1836, bidirecional	
1480	A	1N1816..1836, bidirecional, 5%	
1481	1N1816R...1836R	1N1816..1836	
1482	1N1817	1N1816, 15V	
1483	1N1818	1N1816, 16V	
1484	1N1819	1N1816, 18V	

1485	1N1820	1N1816, 20V	
1486	1N1821	1N1816, 22V	
1487	1N1822	1N1816, 24V	
1488	1N1823	1N1816, 27V	
1489	1N1824	1N1816, 30V	
1490	1N1825	1N1816, 33V	
1491	1N1826	1N1816, 36V	
1492	1N1827	1N1816, 39V	
1493	1N1828	1N1816, 43V	
1494	1N1829	1N1816, 47V	
1495	1N1830	1N1816, 51V	
1496	1N1831	1N1816, 56V	
1497	1N1832	1N1816, 62V	
1498	1N1833	1N1816, 68V	
1499	1N1834	1N1816, 75V	
1500	1N1835	1N1816, 82V	
1501	1N1836	1N1816, 91V	
1502	1N1839	6,8V, 85mA	-
1503	1N1839	6,8V, 85mA	-
1504	1N1840	10V, 77mA	-
1505	1N1841	15V, 63mA	-
1506	1N1842	22V, 50mA	-
1507	1N1843	33V, 40mA	-
1508	1N1844	47V, 30mA	-
1509	1N1845	68V, 23mA	-
1510	1N1846	100V, 16mA	-
1511	1N1847	150V, 11mA	-
1512	1N1848	330V, 7,5mA	-
1513	1N1850	470V, 6mA	-
1514	1N1875	8,2V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5923...49
1515	1N1875A...1888A	1N1875..1888, 5%	
1516	1N1875B...1888B	1N1875..1888, 1%	
1517	1N1876	1N1875, 10V	
1518	1N1877	1N1875, 12V	
1519	1N1878	1N1875, 15V	
1520	1N1879	1N1875, 18V	
1521	1N1880	1N1875, 22V	
1522	1N1881	1N1875, 27V	
1523	1N1882	1N1875, 33V	
1524	1N1883	1N1875, 39V	
1525	1N1884	1N1875, 47V	
1526	1N1885	1N1875, 56V	
1527	1N1886	1N1875, 68V	
1528	1N1887	1N1875, 82V	
1529	1N1888	1N1875, 100V	

1530	1N1889	120V, 10%, 3W	BZX98/..., BZY93/..., 1N3008...3011
1531	1N1889A...1890A	1N1889..1890, 5%	
1532	1N1889B...1890B	1N1889..1890, 1%	
1533	1N1890	1N1889, 145V	
1534	1N1891	8,2V, 10%, 10W	BZX98/..., BZY93/..., 1N2972...3011
1535	1N1891A...1906A	1N1891..1906, 5%	
1536	1N1892	1N1891, 10V	
1537	1N1893	1N1891, 12V	
1538	1N1894	1N1891, 15V	
1539	1N1895	1N1891, 18V	
1540	1N1896	1N1891, 22V	
1541	1N1897	1N1891, 27V	
1542	1N1898	1N1891, 33V	
1543	1N1899	1N1891, 39V	
1544	1N1900	1N1891, 47V	
1545	1N1901	1N1891, 56V	
1546	1N1902	1N1891, 68V	
1547	1N1903	1N1891, 82V	
1548	1N1904	1N1891, 100V	
1549	1N1905	1N1891, 120V	
1550	1N1906	1N1891, 150V	
1551	1N1907	50V, 1,5A	BY 251...255, BY 226...227, 1N5391...99
1552	1N1908	1N1907, 100V	BY 251...255, BY 226...227, 1N5392...99
1553	1N1909	1N1907, 200V	BY 251...255, BY 226...227, 1N5393...99
1554	1N191	90V, 30mA, <100ns	AAV 28
1555	1N1910	1N1907, 300V	BY 252...255, BY 226...227, 1N5394...99
1556	1N1911	1N1907, 400V	BY 252...255, BY 226...227, 1N5395...99
1557	1N1912	1N1907, 500V	BY 253...255, BY 226...227, 1N5396...99
1558	1N1913	1N1907, 600V	BY 253...255, BY 226...227, 1N5397...99
1559	1N1914	1N1907, 700V	BY 254...255, BY 227, 1N5398...99
1560	1N1915	1N1907, 800V	BY 254...255, BY 227, 1N5399
1561	1N1916	1N1907, 900V	BY 255, BY 227, BYW 56, GP 15M
1562	1N1917	50V, 4A	BYX 38/300, BYX 39/600
1563	1N1918	1N1917, 100V	BYX 38/300, BYX 39/600
1564	1N1919	1N1917, 200V	BYX 38/300, BYX 39/600
1565	1N192	1N191, 70V	AAV 28
1566	1N1920	1N1917, 300V	BYX 38/300, BYX 39/600
1567	1N1921	1N1917, 400V	BYX 38/600, BYX 39/600
1568	1N1922	1N1917, 500V	BYX 38/600, BYX 39/600
1569	1N1923	1N1917, 600V	BYX 38/600, BYX 39/600
1570	1N1924	1N1917, 700V	BYX 38/900, BYX 39/800
1571	1N1925	1N1917, 800V	BYX 38/900, BYX 39/800
1572	1N1926	1N1917, 900V	BYX 38/900, BYX 39/1000
1573	1N1927	3,9V, 10%, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5228...71
1574	1N1927A...1944A	1N1927..1944, 5%	

1575	1N1927B...1944B	1N1927..1944, 1%	
1576	1N1928	1N1927, 4,7V	
1577	1N1929	1N1927, 5,6V	
1578	1N1930	1N1927, 6,8V	
1579	1N1931	1N1927, 8,2V	
1580	1N1932	1N1927, 10V	
1581	1N1933	1N1927, 12V	
1582	1N1934	1N1927, 15V	
1583	1N1935	1N1927, 18V	
1584	1N1936	1N1927, 22V	
1585	1N1937	1N1927, 27V	
1586	1N1938	1N1927, 33V	
1587	1N1939	1N1927, 39V	
1588	1N194(A)	40V, 30mA, 200ns	BAV 18...21, BAX 15...17, 1N4148
1589	1N1940	1N1927, 47V	
1590	1N1941	1N1927, 56V	
1591	1N1942	1N1927, 68V	
1592	1N1943	1N1927, 82V	
1593	1N1944	1N1927, 100V	
1594	1N1945	120V, 10%, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5273...81,...
1595	1N1945A..1953A	1N1945..1953, 5%	
1596	1N1945B..1953B	1N1945..1953, 1%	
1597	1N1946	1N1945, 145V	
1598	1N1947	1N1945, 180V	
1599	1N1948	1N1945, 220V	
1600	1N1949	1N1945, 270V	
1601	1N195	40V, 30mA, 300ns	BAV 18...21, BAX 15...17, 1N4148
1602	1N1950	1N1945, 330V	
1603	1N1951	1N1945, 395V	
1604	1N1952	1N1945, 470V	
1605	1N1953	1N1945, 565V	
1606	1N1954	3,95V, 10%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5228...57
1607	1N1954A..1965A	1N1954..1965, 5%	
1608	1N1954B..1965B	1N1954..1965, 1%	
1609	1N1955	1N1954, 4,7V	
1610	1N1956	1N1954, 5,65V	
1611	1N1957	1N1954, 6,85V	
1612	1N1958	1N1954, 8,3V	
1613	1N1959	1N1954, 9,7V	
1614	1N196	40V, 30mA, 100ns	BAV 18...21, BAX 15...17, 1N4148
1615	1N1960	1N1954, 12V	
1616	1N1961	1N1954, 14,5V	
1617	1N1962	1N1954, 18V	
1618	1N1963	1N1954, 22V	
1619	1N1964	1N1954, 27V	

1620	1N1965	1N1954, 33V	
1621	1N1966	39,5V, 10%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5259...81
1622	1N1967	1N1966, 47V	
1623	1N1968	1N1966, 56,5V	
1624	1N1969	1N1966, 68,5V	
1625	1N1970	1N1966, 83V	
1626	1N1971	1N1966, 100V	
1627	1N1972	1N1966, 120V	
1628	1N1973	1N1966, 150V	
1629	1N1974	1N1966, 180V	
1630	1N1975	1N1966, 220V	
1631	1N1976	1N1966, 270V	
1632	1N1977	1N1966, 330V	
1633	1N1978	1N1966, 390V	
1634	1N1979	1N1966, 470V	
1635	1N198(A...N)	100V, 30mA, <300ns	AAY 28, 1N191
1636	1N1980	1N1966, 560V	
1637	1N1981	3,9V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5228...81
1638	1N1981B...2007B	1N1981...2007, 1%	
1639	1N1982	1N1981, 4,7V	
1640	1N1983	1N1981, 5,6V	
1641	1N1984	1N1981, 6,8V	
1642	1N1985	1N1981, 8,2V	
1643	1N1986	1N1981, 10V	
1644	1N1987	1N1981, 12V	
1645	1N1988	1N1981, 15V	
1646	1N1989	1N1981, 18V	
1647	1N1990	1N1981, 22V	
1648	1N1991	1N1981, 27V	
1649	1N1992	1N1981, 33V	
1650	1N1993	1N1981, 39V	
1651	1N1994	1N1981, 47V	
1652	1N1995	1N1981, 56V	
1653	1N1996	1N1981, 68V	
1654	1N1997	1N1981, 82V	
1655	1N1998	1N1981, 100V	
1656	1N1999	1N1981, 120V	
1657	1N200	6,8V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5235...81
1658	1N2000	1N1981, 150V	
1659	1N2001	1N1981, 180V	
1660	1N2002	1N1981, 220V	
1661	1N2003	1N1981, 270V	
1662	1N2004	1N1981, 330V	
1663	1N2005	1N1981, 390V	
1664	1N2006	1N1981, 470V	

1665	1N2007	1N1981, 560V	
1666	1N2008	100V, 10%, 10W	BZX98/..., BZY93/..., 1N3005...3011
1667	1N2008A...2012A	1N2008..2012, 5%	
1668	1N2008C...2012C	1N2008..2012, bidirecional	
1669	A	1N2008..2012, bidirecional, 5%	
1670	1N2008R...2012R	1N2008..2012	
1671	1N2009	1N2008, 110V	
1672	1N201	1N200, 8,2V	
1673	1N2010	1N2008, 120V	
1674	1N2011	1N2008, 130V	
1675	1N2012	1N2008, 150V	
1676	1N2013	50V, 0,2A	BA 157...159, BY 206...207, BY 204/4
1677	1N2014	1N2013, 100V	BA 157...159, BY 206...207, BY 204/4
1678	1N2015	1N2013, 150V	BA 157...159, BY 206...207, BY 204/4
1679	1N2016	1N2013, 200V	BA 157...159, BY 206...207, BY 204/4
1680	1N2017	1N2013, 250V	BA 157...159, BY 206...207, BY 204/4
1681	1N2018	1N2013, 300V	BA 157...159, BY 206...207, BY 204/4
1682	1N2019	1N2013, 350V	BA 157...159, BY 206...207, BY 204/4
1683	1N202	1N200, 10V	
1684	1N2020	1N2013, 400V	BA 157...159, BY 207, BY 204/4
1685	1N2021	150V, 10A(Tc150°)	BYW 88/200, BYX 42/300, BYX 77...81
1686	1N2022	1N2021, 250V	BYW 88/300, BYX 42/300, BYX 78...81
1687	1N2023	1N2021, 300V	BYW 88/300, BYX 42/300, BYX 78...81
1688	1N2024	1N2021, 350V	BYW 88/400, BYX 42/600, BYX 78...81
1689	1N2025	1N2021, 400V	BYW 88/400, BYX 42/600, BYX 78...81
1690	1N2026	50V, 1A(Tc150°)	BYX 38/300, BYX 39/600
1691	1N2027	1N2026, 200V	BYX 38/300, BYX 39/600
1692	1N2028	1N2026, 300V	BYX 38/300, BYX 39/600
1693	1N2029	1N2026, 400V	BYX 38/600, BYX 39/600
1694	1N203	1N200, 12V	
1695	1N2030	1N2026, 500V	BYX 38/600, BYX 39/600
1696	1N2031	1N2026, 600V	BYX 38/600, BYX 39/600
1697	1N2032	4,85V, 10%, 0,75W	BZV85/..., BZW22/..., ZPY..., 1N3016...29
1698	1N2032A...2040A	1N2032..2040, 5%	
1699	1N2033	1N2032, 5,8V	
1700	1N2034	1N2032, 7,1V	
1701	1N2035	1N2032, 8,75V	
1702	1N2036	1N2032, 10,5V	
1703	1N2037	1N2032, 12,7V	
1704	1N2038	1N2032, 15,7V	
1705	1N2039	1N2032, 19V	
1706	1N204	1N200, 15V	
1707	1N2040	1N2032, 23,5V	
1708	1N2041	4,85V, 10%, 10W	BZX98/..., BZY93/..., 1N2970...86
1709	1N2041...49A..D	1N2041..2049, 5%	

1710	1N2041..49-1..-4	1N2041..2049, 5%	
1711	1N2042	1N2041, 5,8V	
1712	1N2043	1N2041, 7,1V	
1713	1N2044	1N2041, 8,75V	
1714	1N2045	1N2041, 10,5V	
1715	1N2046	1N2041, 12,7V	
1716	1N2047	1N2041, 15,7V	
1717	1N2048	1N2041, 19V	
1718	1N2049	1N2041, 23,5V	
1719	1N205	1N200, 18V	
1720	1N2054	50V, 250A(Tc135°)	1N3735...44
1721	1N2055	1N2054, 100V	1N3735...44
1722	1N2056	1N2054, 150V	1N3736...44
1723	1N2057	1N2054, 200V	1N3736...44
1724	1N2058	1N2054, 250V	1N3737...44
1725	1N2059	1N2054, 300V	1N3737...44
1726	1N206	1N200, 22V	
1727	1N2060	1N2054, 350V	1N3738...44
1728	1N2061	1N2054, 400V	1N3738...44
1729	1N2062	1N2054, 450V	1N3739...44
1730	1N2063	1N2054, 500V	1N3739...44
1731	1N2064	1N2054, 600V	1N3740...44
1732	1N2065	1N2054, 700V	1N3741...44
1733	1N2066	1N2054, 800V	1N3741...44
1734	1N2067	1N2054, 900V	1N3742...44
1735	1N2068	1N2054, 1000V	1N3742...44
1736	1N2069(A)	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
1737	1N207	1N200, 27V	
1738	1N2070(A)	1N2069, 400V	BY 126...127, BY 133...134, 1N4004...07
1739	1N2071(A)	1N2069, 600V	BY 126...127, BY 133...134, 1N4005...07
1740	1N2072	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
1741	1N2073	1N2072, 100V	BY 126...127, BY 133...135, 1N4002...07
1742	1N2074	1N2072, 150V	BY 126...127, BY 133...135, 1N4003...07
1743	1N2075	1N2072, 200V	BY 126...127, BY 133...134, 1N4003...07
1744	1N2076	1N2072, 250V	BY 126...127, BY 133...134, 1N4004...07
1745	1N2077	1N2072, 300V	BY 126...127, BY 133...134, 1N4004...07
1746	1N2078	1N2072, 400V	BY 126...127, BY 133...134, 1N4004...07
1747	1N2079	1N2072, 500V	BY 126...127, BY 133...134, 1N4005...07
1748	1N208	1N200, 33V	
1749	1N2080	50V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
1750	1N2081	1N2080, 100V	BY 126...127, BY 133...135, 1N4002...07
1751	1N2082	1N2080, 200V	BY 126...127, BY 133...134, 1N4003...07
1752	1N2083	1N2080, 300V	BY 126...127, BY 133...134, 1N4004...07
1753	1N2084	1N2080, 400V	BY 126...127, BY 133...134, 1N4004...07
1754	1N2085	1N2080, 500V	BY 126...127, BY 133...134, 1N4005...07

1755	1N2086	1N2080, 600V	BY 126...127, BY 133...134, 1N4005...07
1756	1N209	1N200, 39V	
1757	1N2090	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
1758	1N2091	1N2090, 100V	BY 126...127, BY 133...135, 1N4002...07
1759	1N2092	1N2090, 200V	BY 126...127, BY 133...134, 1N4003...07
1760	1N2093	1N2090, 300V	BY 126...127, BY 133...134, 1N4004...07
1761	1N2094	1N2090, 400V	BY 126...127, BY 133...134, 1N4004...07
1762	1N2095	1N2090, 500V	BY 126...127, BY 133...134, 1N4005...07
1763	1N2096	1N2090, 600V	BY 126...127, BY 133...134, 1N4005...07
1764	1N210	1N200, 47V	
1765	1N2103	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
1766	1N2104	1N2103, 100V	BY 126...127, BY 133...135, 1N4002...07
1767	1N2105	1N2103, 200V	BY 126...127, BY 133...134, 1N4003...07
1768	1N2106	1N2103, 300V	BY 126...127, BY 133...134, 1N4004...07
1769	1N2107	1N2103, 400V	BY 126...127, BY 133...134, 1N4004...07
1770	1N2108	1N2103, 500V	BY 126...127, BY 133...134, 1N4005...07
1771	1N2109	50V, 2A	BY 249/300, BYX 38/300, BYX 39/600
1772	1N211	1N200, 56V	
1773	1N2110	1N2109, 100V	BY 249/300, BYX 38/300, BYX 39/600
1774	1N2111	1N2109, 200V	BY 249/300, BYX 38/300, BYX 39/600
1775	1N2112	1N2109, 300V	BY 249/300, BYX 38/300, BYX 39/600
1776	1N2113	1N2109, 400V	BY 249/600, BYX 38/600, BYX 39/600
1777	1N2114	1N2109, 500V	BY 249/600, BYX 38/600, BYX 39/600
1778	1N2115	365V, 0,3A	BA 157...159, BY 206...207, BY 204/4
1779	1N2116	400V, 0,75A	BY 126...127, BY 133...134, 1N4004...07
1780	1N2117	720V, 0,75A	BY 127, BY 133, BYW 42, 1N4006...07
1781	1N212	1N200, 68V	
1782	1N2128	50V, 60A(Tc115°)	-
1783	1N2128A...2138A	1N2128..2138, 60A(Tc140°)	-
1784	1N2128R...2138R	1N2128..2138	DS 75-02B...-16B
1785	1N2129	1N2128, 100V	-
1786	1N213	1N200, 82V	
1787	1N2130	1N2128, 150V	-
1788	1N2131	1N2128, 200V	-
1789	1N2132	1N2128, 250V	-
1790	1N2133	1N2128, 300V	-
1791	1N2134	1N2128, 350V	-
1792	1N2135	1N2128, 400V	-
1793	1N2136	1N2128, 450V	-
1794	1N2137	1N2128, 500V	-
1795	1N2138	1N2128, 600V	-
1796	1N2139	20kV, 0,045A	1N3057
1797	1N214	1N200, 100V	
1798	1N2146	120V, <50ns	BAV 15...16, EGP 10C, FE 1C
1799	1N2147(A)	50V, 6A(Tc150°)	BYX 38/300, BYX 39/600



1800	1N2148(A)	1N2147, 100V	BYX 38/300, BYX 39/600
1801	1N2149(A)	1N2147, 200V	BYX 38/300, BYX 39/600
1802	1N215	1N200, 120V	
1803	1N2150(A)	1N2147, 300V	BYX 38/300, BYX 39/600
1804	1N2151(A)	1N2147, 400V	BYX 38/600, BYX 39/600
1805	1N2152(A)	1N2147, 500V	BYX 38/600, BYX 39/600
1806	1N2153(A)	1N2147, 600V	BYX 38/600, BYX 39/600
1807	1N2154	50V, 25A(Tc145°)	1N3765...68, 1N4525...30
1808	1N2154R...2160R	1N2154..2160	1N3765R...68R
1809	1N2155	1N2154, 100V	1N3765...68, 1N4525...30
1810	1N2156	1N2154, 200V	1N3765...68, 1N4525...30
1811	1N2157	1N2154, 300V	1N3765...68, 1N4526...30
1812	1N2158	1N2154, 400V	1N3765...68, 1N4526...30
1813	1N2159	1N2154, 500V	1N3765...68, 1N4527...30
1814	1N216	1N200, 150V	
1815	1N2160	1N2154, 600V	1N3765...68, 1N4527...30
1816	1N2163(A)	9,4V, 0,75W	-
1817	1N2164(A)	9,4V, 0,75W	-
1818	1N2165(A)	9,4V, 0,75W	-
1819	1N2166(A)	9,4V, 0,75W	-
1820	1N2167(A)	9,4V, 0,75W	-
1821	1N2168(A)	9,4V, 0,75W	-
1822	1N2169(A)	9,4V, 0,75W	-
1823	1N217	1N200, 180V	
1824	1N2170(A)	9,4V, 0,75W	-
1825	1N2171(A)	9,4V, 0,75W	-
1826	1N2172	50V, 50A(Tc150°)	1N3288...97
1827	1N2173	1N2172, 100V	1N3288...97
1828	1N2174	1N2172, 200V	1N3289...97
1829	1N218	1N200, 220V	
1830	1N219	1N200, 270V	
1831	1N2194	50V, 6A	BYX 38/300, BYX 39/600
1832	1N2195	1N2194, 100V	BYX 38/300, BYX 39/600
1833	1N2196	1N2194, 150V	BYX 38/300, BYX 39/600
1834	1N2197	1N2194, 200V	BYX 38/300, BYX 39/600
1835	1N2198	1N2194, 300V	BYX 38/300, BYX 39/600
1836	1N2199	1N2194, 400V	BYX 38/600, BYX 39/600
1837	1N220	1N200, 330V	
1838	1N2200	1N2194, 500V	BYX 38/600, BYX 39/600
1839	1N2201	1N2194, 600V	BYX 38/600, BYX 39/600
1840	1N2202	1N2194, 800V	BYX 38/900, BYX 39/800
1841	1N2203	1N2194, 1000V	BYX 38/1200, BYX 39/1000
1842	1N2204	50V, 12A	BYW 88/50, BYX 75...81, BYX 99/300
1843	1N2205	1N2204, 100V	BYW 88/100, BYX 76...81, BYX 99/300
1844	1N2206	1N2204, 150V	BYW 88/200, BYX 77...81, BYX 99/300

1845	1N2207	1N2204, 200V	BYW 88/200, BYX 77...81, BYX 99/300
1846	1N2208	1N2204, 300V	BYW 88/300, BYX 78...81, BYX 99/300
1847	1N2209	1N2204, 400V	BYW 88/400, BYX 78...81, BYX 99/600
1848	1N221	1N200, 390V	
1849	1N2210	1N2204, 500V	BYW 88/500, BYX 79...81, BYX 99/600
1850	1N2211	1N2204, 600V	BYW 88/600, BYX 79...81, BYX 99/600
1851	1N2212	1N2204, 800V	BYW 88/800, BYX 80...81, BYX 99/900
1852	1N2213	1N2204, 1000V	BYW 88/1000, BYX 81, BYX 99/1200
1853	1N2214	5,5V, 2%, 1W	BZW22/C5V6, BZX61/C5V6, ZPY5,6, 1N5919
1854	1N2216(A)	50V, 1,5A	BYX 38/300, BYX 39/600
1855	1N2217(A)	1N2216	-
1856	1N2218(A)	1N2216, 500V	BYX 38/600, BYX 39/600
1857	1N2219(A)	1N2216, 500V	-
1858	1N222	1N200, 470V	
1859	1N2220(A)	1N2216, 600V	BYX 38/600, BYX 39/600
1860	1N2221(A)	1N2216, 600V	-
1861	1N2222(A)	800V, 1A	BYX 38/900, BYX 39/800
1862	1N2223(A)	1N2222	-
1863	1N2224(A)	1N2222, 1000V	BYX 38/1200, BYX 39/1000
1864	1N2225(A)	1N2222, 1000V	-
1865	1N2226(A)	1N2222, 1200V	BYX 38/1200, BYX 39/1200
1866	1N2227(A)	1N2222, 1200V	-
1867	1N2228(A)	50V, 5A	BYX 38/300, BYX 39/600
1868	1N2229(A)	1N2228	-
1869	1N2230(A)	1N2228, 200V	BYX 38/300, BYX 39/600
1870	1N2231(A)	1N2228, 200V	-
1871	1N2232(A)	1N2228, 300V	BYX 38/300/, BYX 39/600
1872	1N2233(A)	1N2228, 300V	-
1873	1N2234(A)	1N2228, 400V	BYX 38/600, BYX 39/600
1874	1N2235(A)	1N2228, 400V	-
1875	1N2236(A)	1N2228, 500V	BYX 38/600, BYX 39/600
1876	1N2237(A)	1N2228, 500V	-
1877	1N2238(A)	1N2228, 600V	BYX 38/600, BYX 39/600
1878	1N2239(A)	1N2228, 600V	-
1879	1N2240(A)	1N2228, 800V	BYX 38/900, BYX 39/800
1880	1N2241(A)	1N2228, 800V	-
1881	1N2242(A)	1N2228, 1000V	BYX 38/1200, BYX 39/1000
1882	1N2243(A)	1N2228, 1000V	-
1883	1N2244(A)	1N2228, 1200V	BYX 38/1200, BYX 39/1200
1884	1N2245(A)	1N2228, 1200V	-
1885	1N2246(A)	50V, 10A	BYX 42/300, BYX 98/300
1886	1N2247(A)	1N2246	-
1887	1N2248(A)	1N2246, 100V	BYX 42/300, BYX 98/300
1888	1N2249(A)	1N2246, 100V	-
1889	1N225	8,75V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5238...74

1890	1N225	8,75V, 10%, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5238...74
1891	1N2250(A)	1N2246, 200V	BYX 42/300, BYX 98/300
1892	1N2251(A)	1N2246, 200V	-
1893	1N2252(A)	1N2246, 300V	BYX 42/300, BYX 98/300
1894	1N2253(A)	1N2246, 300V	-
1895	1N2254(A)	1N2246, 400V	BYX 42/600, BYX 98/600
1896	1N2255(A)	1N2246, 400V	-
1897	1N2256(A)	1N2246, 500V	BYX 42/600, BYX 98/600
1898	1N2257(A)	1N2246, 500V	-
1899	1N2258(A)	1N2246, 600V	BYX 42/600, BYX 98/600
1900	1N2259(A)	1N2246, 600V	-
1901	1N225A...235A	1N225...235, 5%	
1902	1N226	1N225, 10,5V	
1903	1N2260(A)	1N2246, 800V	BYX 42/900, BYX 98/900
1904	1N2261(A)	1N2246, 800V	-
1905	1N2262(A)	1N2246, 1000V	BYX 42/1200, BYX 98/1200
1906	1N2263(A)	1N2246, 1000V	-
1907	1N2264(A)	1N2246, 1200V	BYX 42/1200, BYX 98/1200
1908	1N2265(A)	1N2246, 1200V	-
1909	1N2266	50V, 1A	BYX 38/300, BYX 39/600
1910	1N2267	1N2266	-
1911	1N2268	1N2266, 500V	BYX 38/600, BYX 39/600
1912	1N2269	1N2266, 500V	-
1913	1N227	1N225, 12,8V	
1914	1N2270	1N2266, 600V	BYX 38/600, BYX 39/600
1915	1N2271	1N2266, 600V	-
1916	1N2272	50V, 6A(Tc150°)	BYX 38/300, BYX 39/600
1917	1N2273	1N2272, 100V	BYX 38/300, BYX 39/600
1918	1N2274	1N2272, 200V	BYX 38/300, BYX 39/600
1919	1N2275	1N2272, 300V	BYX 38/300, BYX 39/600
1920	1N2276	1N2272, 400V	BYX 38/600, BYX 39/600
1921	1N2277	1N2272, 500V	BYX 38/600, BYX 39/600
1922	1N2278	1N2272, 600V	BYX 38/600, BYX 39/600
1923	1N2279	1N2272, 800V	BYX 38/900, BYX 39/800
1924	1N228	1N225, 15,7V	
1925	1N2280	1N2272, 1000V	BYX 38/1200, BYX 39/1000
1926	1N2281	1N2272, 1200V	BYX 38/1200, BYX 39/1200
1927	1N2282	300V, 20A(Tc150°)	1N3765...68, 1N4525...30
1928	1N2283	1N2282, 400V	1N3765...68, 1N4526...30
1929	1N2284	1N2282, 500V	1N3765...68, 1N4527...30
1930	1N2285	1N2282, 600V	1N3765...68, 1N4527...30
1931	1N2286	1N2282, 800V	1N3766...68, 1N4528...30
1932	1N2287	1N2282, 1000V	1N3768, 1N4529...30
1933	1N2288	1N2282, 1200V	1N4530
1934	1N2289...2293	1N2289A..2293A	-

1935	1N2289A	100V, 1,5A	BYX 38/300, BYX 39/600
1936	1N229	1N225, 19V	
1937	1N2290A	1N2289A, 5A	BYX 38/300, BYX 39/600
1938	1N2291A	1N2289A, 200V	BYX 38/300, BYX 39/600
1939	1N2292A	1N2289A, 300V	BYX 38/300, BYX 39/600
1940	1N2293A	1N2289A, 400V	BYX 38/600, BYX 39/600
1941	1N230	1N225, 23,5V	
1942	1N231	1N225, 28,5V	
1943	1N232	1N225, 34,5V	
1944	1N2326	1V, 0,2A	-
1945	1N2327	1100V, 0,4A	BY 127, BY 133, BYX 94...95, GP 10Q
1946	1N2328	1N2327, 2200V	1N1732A, 1N1733A
1947	1N233	1N225, 41V	
1948	1N234	1N225, 48V	
1949	1N2348	50V, 3A(Tc50°)	BYX 38/300, BYX 39/600
1950	1N2349	1N2348, 100V	BYX 38/300, BYX 39/600
1951	1N235	1N225, 58V	
1952	1N2350	1N2348, 150V	BYX 38/300, BYX 39/600
1953	1N2357	1400V, 0,4A	BY 231/1400, BY 268...269, GP 10V
1954	1N2358	1N2357, 1500V	BY 231/1500, BY 269, DM 513, GP 10W
1955	1N2359	1N2357, 1600V	BY 269, DM 513, EM 516, GP 10Y
1956	1N236	71V, 10%, 0,15W	
1957	1N2360	1N2357, 1800V	DM 516, 1N1732A
1958	1N2361	1N2357, 2000V	1N1732A
1959	1N2362	1400V, 1A	-
1960	1N2362A...2371A	1N2362...2371, 5A	-
1961	1N2362B...2371B	1N2362...2371, 10A	-
1962	1N2363	1N2362	-
1963	1N2364	1N2362, 1500V	-
1964	1N2365	1N2362, 1500V	-
1965	1N2366	1N2362, 1600V	-
1966	1N2367	1N2362, 1600V	-
1967	1N2368	1N2362, 1800V	-
1968	1N2369	1N2362, 1800V	-
1969	1N237	1N236, 88V	
1970	1N2370	1N2362, 2000V	-
1971	1N2371	1N2362, 2000V	-
1972	1N2372	1000V, 0,2A(Tc150°)	-
1973	1N2373	600V, 0,25A	BY 126...127, BY 133...134, 1N4005...07
1974	1N2374	1000V, 0,25A	BY 127, BY 133, GP 10Q, 1N4007...07
1975	1N2375	1500V, 0,2A	BY 231/1500, BY 269, DM 513, GP 10W
1976	1N2376	2000V, 0,2A	HVG 2, GP 02-20, MR 250-2, 1N1732(A)
1977	1N2377	2400V, 0,15A	HVG 3, GP 02-30, MR 250-3, 1N1733(A)
1978	1N2378	3000V, 0,15A	HVG 3, GP 02-30, MR 250-3, 1N1733(A)
1979	1N2379	4000V, 0,15A	HVG 4, GP 02-40, MR 250-4, 1N1734(A)

1980	1N238	1N236, 105V	
1981	1N2380	6000V, 0,1A	BYX 90, 1N5183
1982	1N2381	10kV, 0,075A	1N3052
1983	1N2382	4kV, 0,15A	HVG 4, GP 02-40, MR 250-4, 1N1734(A)
1984	1N2382A	1N2382, 0,35A	1N1734A
1985	1N2383	6kV, 0,1A	BYX 90, 1N5183
1986	1N2383A	1N2383, 0,35A	-
1987	1N2384	8kV, 0,07A	1N5184
1988	1N2384A	1N2384, 0,275A	-
1989	1N2385	10kV, 0,07A	1N5184
1990	1N2385A	1N2384, 0,2A	-
1991	1N2387	30V, 10%, 1W	BZW22/C10, BZX61/C10, ZPY10, 1N5925
1992	1N239	1N236, 128V	
1993	1N2426	50V, 100A(Tc75°)	1N3288...97
1994	1N2427	1N2326, 100V	1N3288...97
1995	1N2428	1N2326, 150V	1N3289...97
1996	1N2429	1N2326, 200V	1N3289...97
1997	1N2430	1N2326, 250V	1N3290...97
1998	1N2431	1N2326, 300V	1N3290...97
1999	1N2432	1N2326, 350V	1N3291...97
2000	1N2433	1N2326, 400V	1N3291...97
2001	1N2434	1N2326, 500V	1N3292...97
2002	1N2435	1N2326, 600V	1N3293...97
2003	1N2436	50V, 150A(Tc75°)	1N4587...96
2004	1N2437	1N2436, 100V	1N4587...96
2005	1N2438	1N2436, 150V	1N4588...96
2006	1N2439	1N2436, 200V	1N4588...96
2007	1N2440	1N2436, 250V	1N4589...96
2008	1N2441	1N2436, 300V	1N4589...96
2009	1N2442	1N2436, 350V	1N4590...96
2010	1N2443	1N2436, 400V	1N4590...96
2011	1N2444	1N2436, 500V	1N4591...96
2012	1N2445	1N2436, 600V	1N4592...96
2013	1N2446	50V, 45A(Tc60°)	-
2014	1N2447	1N2446, 100V	-
2015	1N2448	1N2446, 150V	-
2016	1N2449	1N2446, 200V	-
2017	1N2450	1N2446, 250V	-
2018	1N2451	1N2446, 300V	-
2019	1N2452	1N2446, 350V	-
2020	1N2453	1N2446, 400V	-
2021	1N2454	1N2446, 500V	-
2022	1N2455	1N2446, 600V	-
2023	1N2456	1N2446, 700V	-
2024	1N2457	1N2446, 800V	-

2025	1N2458	50V, 60A(Tc60°)	-
2026	1N2459	1N2458, 100V	-
2027	1N2460	1N2458, 150V	-
2028	1N2461	1N2458, 200V	-
2029	1N2462	1N2458, 250V	-
2030	1N2463	1N2458, 300V	-
2031	1N2464	1N2458, 350V	-
2032	1N2465	1N2458, 400V	-
2033	1N2466	1N2458, 500V	-
2034	1N2467	1N2458, 600V	-
2035	1N2468	1N2458, 700V	-
2036	1N2469	1N2458, 800V	-
2037	1N248(A...C)	50..55V, 10..20A	BYX 25/600
2038	1N248(A...C)R	1N248(A..C)	BYX 25/600R, DS 17-02A, SSiE2040
2039	1N2482	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2040	1N2483	1N2482, 400V	BY 126...127, BY 133...134, 1N4004...07
2041	1N2484	1N2482, 600V	BY 126...127, BY 133...134, 1N4005...07
2042	1N2485	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2043	1N2486	1N2485, 300V	BY 126...127, BY 133...134, 1N4004...07
2044	1N2487	1N2485, 400V	BY 126...127, BY 133...134, 1N4004...07
2045	1N2488	1N2485, 500V	BY 126...127, BY 133...134, 1N4005...07
2046	1N2489	1N2485, 600V	BY 126...127, BY 133...134, 1N4005...07
2047	1N249(A...C)	100..110V, 10..20A	BYX 25/600
2048	1N249(A...C)R	1N249(A..C)	BYX 25/600R, DS 17-02A, SSiE2040
2049	1N2491	50V, 6A(Tc150°)	BYX 38/300, BYX 39/600
2050	1N2492	1N2491, 100V	BYX 38/300, BYX 39/600
2051	1N2493	1N2491, 200V	BYX 38/300, BYX 39/600
2052	1N2494	1N2491, 300V	BYX 38/300, BYX 39/600
2053	1N2495	1N2491, 400V	BYX 38/600, BYX 39/600
2054	1N2496	1N2491, 500V	BYX 38/600, BYX 39/600
2055	1N2497	1N2491, 600V	BYX 38/600, BYX 39/600
2056	1N2498	10V, 10%, 10W	BZX98/..., BZY93/..., 1N2974...76
2057	1N2498A...2500A	1N2498..2500, 5%	
2058	1N2498C...2500C	1N2498..2500, bidirecional	
2059	1N2499	1N2498, 11V	
2060	1N250(A...C)	200..220V, 10..20A	BYX 25/600
2061	1N250(A...C)R	1N250(A..C)	BYX 25/600R, DS 17-02A, SSiE2040
2062	1N2500	1N2498, 12V	
2063	1N2501	800V, 0,15A	BA 159, BAY 90, BY 203/12, SHG 1
2064	1N2502	1N2501, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2065	1N2503	1N2501, 1200V	BAY 91, BY 203/12, SHG 1,5
2066	1N2504	1N2501, 1500V	BAY 91, BY 203/15, SHG 1,5
2067	1N2505	800V, 0,3A	BA 159, BAY 90, BY 203/12, GP 10Q
2068	1N2506	1N2505, 1000V	BA 159, BAY 90, BY 203/12, GP 10Q
2069	1N2507	1N2505, 1200V	BAY 91, BY 203/12, EM 513, GP 10Q

2070	1N2508	1N2505, 1500V	BAY 91, BY 203/15, EM 516, GP 10Y
2071	1N251	40V, 75mA, <150ns	BAV 18...21, BAX 15...17, 1N3070
2072	1N2512	100V, 4A(Tc30°)	BYX 38/300, BYX 39/600
2073	1N2512R...2523R	1N2512..2523	BYX 38/...R, BYX 39/...R
2074	1N2513	1N2512, 200V	BYX 38/300, BYX 39/600
2075	1N2514	1N2512, 300V	BYX 38/300, BYX 39/600
2076	1N2515	1N2512, 400V	BYX 38/600, BYX 39/600
2077	1N2516	1N2512, 500V	BYX 38/600, BYX 39/600
2078	1N2517	1N2512, 600V	BYX 38/600, BYX 39/600
2079	1N2518	1N2512	-
2080	1N2519	1N2513	-
2081	1N251A	1N251, 125V, 100mA	BAV 19...21, BAX 15...17, 1N3070
2082	1N252	20V, 100mA, <150ns	BAV 18...21, BAX 15...17, 1N3070
2083	1N2520	1N2514	-
2084	1N2521	1N2515	-
2085	1N2522	1N2516	-
2086	1N2523	1N2517	-
2087	1N2524	50V, 2,5A(Tc150°)	-
2088	1N2525	1N2524, 100V	-
2089	1N2526	1N2524, 200V	-
2090	1N2527	1N2524, 300V	-
2091	1N2528	1N2524, 400V	-
2092	1N2529	1N2524, 500V	-
2093	1N252A	1N252, 125V	BAV 19...21, BAX 15...17, 1N3070
2094	1N253	95V, 1A	BYX 38/300, BYX 39/600
2095	1N2530	1N2524, 600V	-
2096	1N2531	1N2524, 700V	-
2097	1N2532	1N2524, 800V	-
2098	1N2533	1N2524, 900V	-
2099	1N2534	1N2524, 1000V	-
2100	1N2535	50V, 2,5A(Tc150°)	-
2101	1N2536	1N2535, 100V	-
2102	1N2537	1N2535, 200V	-
2103	1N2538	1N2535, 300V	-
2104	1N2539	1N2535, 400V	-
2105	1N254	1N253, 190V, 0,4A	BYX 38/300, BYX 39/600
2106	1N2540	1N2535, 500V	-
2107	1N2541	1N2535, 600V	-
2108	1N2542	1N2535, 700V	-
2109	1N2543	1N2535, 800V	-
2110	1N2544	1N2535, 900V	-
2111	1N2545	1N2535, 1000V	-
2112	1N2546	50V, 2,5A(Tc150°)	-
2113	1N2547	1N2546, 100V	-
2114	1N2548	1N2546, 200V	-



2115	1N2549	1N2546, 300V	-
2116	1N255	1N253, 380V, 0,4A	BYX 38/600, BYX 39/600
2117	1N2550	1N2546, 400V	-
2118	1N2551	1N2546, 500V	-
2119	1N2552	1N2546, 600V	-
2120	1N2553	1N2546, 700V	-
2121	1N2554	1N2546, 800V	-
2122	1N2555	1N2546, 900V	-
2123	1N2556	1N2546, 1000V	-
2124	1N2557	700V, 6A(Tc150°)	-
2125	1N2558	1N2557, 800V	-
2126	1N2559	1N2557, 900V	-
2127	1N256	1N253, 570V, 0,2A	BYX 38/600, BYX 39/600
2128	1N2560	1N2557, 1000V	-
2129	1N2561	700V, 6A(Tc150°)	-
2130	1N2562	1N2561, 800V	-
2131	1N2563	1N2561, 900V	-
2132	1N2564	1N2561, 1000V	-
2133	1N2565	50V, 6A(Tc150°)	-
2134	1N2566	1N2565, 100V	-
2135	1N2567	1N2565, 200V	-
2136	1N2568	1N2565, 300V	-
2137	1N2569	1N2565, 400V	-
2138	1N2570	1N2565, 500V	-
2139	1N2571	1N2565, 600V	-
2140	1N2572	1N2565, 700V	-
2141	1N2573	1N2565, 800V	-
2142	1N2574	1N2565, 900V	-
2143	1N2575	1N2565, 1000V	-
2144	1N2576	50V, 12A(Tc150°)	-
2145	1N2577	1N2576, 100V	-
2146	1N2578	1N2576, 200V	-
2147	1N2579	1N2576, 300V	-
2148	1N2580	1N2576, 400V	-
2149	1N2581	1N2576, 500V	-
2150	1N2582	1N2576, 600V	-
2151	1N2583	1N2576, 700V	-
2152	1N2584	1N2576, 800V	-
2153	1N2585	1N2576, 900V	-
2154	1N2586	1N2576, 1000V	-
2155	1N2587	50V, 12A(Tc150°)	-
2156	1N2588	1N2587, 100V	-
2157	1N2589	1N2587, 200V	-
2158	1N2590	1N2587, 300V	-
2159	1N2591	1N2587, 400V	-



2160	1N2592	1N2587, 500V	-
2161	1N2593	1N2587, 600V	-
2162	1N2594	1N2587, 700V	-
2163	1N2595	1N2587, 800V	-
2164	1N2596	1N2587, 900V	-
2165	1N2597	1N2587, 1000V	-
2166	1N2598	50V, 12A(Tc150°)	-
2167	1N2599	1N2598, 100V	-
2168	1N2600	1N2598, 200V	-
2169	1N2601	1N2598, 300V	-
2170	1N2602	1N2598, 400V	-
2171	1N2603	1N2598, 500V	-
2172	1N2604	1N2598, 600V	-
2173	1N2605	1N2598, 700V	-
2174	1N2606	1N2598, 800V	-
2175	1N2607	1N2598, 900V	-
2176	1N2608	1N2598, 1000V	-
2177	1N2609	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
2178	1N2610	1N2609, 100V	BY 126...127, BY 133...135, 1N4002...07
2179	1N2611	1N2609, 200V	BY 126...127, BY 133...134, 1N4003...07
2180	1N2612	1N2609, 300V	BY 126...127, BY 133...134, 1N4004...07
2181	1N2613	1N2609, 400V	BY 126...127, BY 133...134, 1N4004...07
2182	1N2614	1N2609, 500V	BY 126...127, BY 133...134, 1N4005...07
2183	1N2615	1N2609, 600V	BY 126...127, BY 133...134, 1N4005...07
2184	1N2616	1N2609, 800V	BY 127, BY 133, EM 513, 1N4006...07
2185	1N2617	1N2609, 1000V	BY 127, BY 133, EM 513, 1N4007
2186	1N2618	1N2609, 1200V	BY 127, BY 133, EM 513, GP 10Q
2187	1N2619	1N2609, 1500V	BY 400, BY 448, DM 513, EM 516, GP 10W
2188	1N2620(A,B)	9,3V, 5%, 0,75W	-
2189	1N2621(A,B)	9,3V, 5%, 0,75W	-
2190	1N2622(A,B)	9,3V, 5%, 0,75W	-
2191	1N2623(A,B)	9,3V, 5%, 0,75W	-
2192	1N2624(A,B)	9,3V, 5%, 0,75W	-
2193	1N2625(A,B)	9,3V, 5%, 0,75W	-
2194	1N2626(A,B)	9,3V, 5%, 0,75W	-
2195	1N265	80V	AA 117...118, AA 132...133
2196	1N266	50V	AA 117...118, AA 132...134, 1N34, 1N54
2197	1N267	30V	AA 117...118, AA 132...134, 1N34, 1N54
2198	1N268	30V, 300mA	AA 139, 1N270
2199	1N270	100V, 60mA	AA 117...118, AA 132...133
2200	1N273	32V, 80mA	AA 117...118, AA 132...133, 1N34, 1N54
2201	1N276	100V, 60mA, <300ns	AA 28, AAZ 15
2202	1N2765(A)	6,8V, 5%	-
2203	1N2766(A)	1N2765, 13,6V	-
2204	1N2767(A)	1N2765, 20,4V	-

2205	1N2768(A)	1N2765, 27,2V	-
2206	1N2769(A)	1N2765, 34V	-
2207	1N277(M)	100..125V, 50mA	AA 117...118, AA 132...133
2208	1N2770(A)	1N2765, 40,8V	-
2209	1N2772	700V, 0,75A	BY 127, BY 133, EM 513, 1N4006...07
2210	1N2773	1N2772, 800V	BY 127, BY 133, EM 513, 1N4006...07
2211	1N2774	1N2772, 900V	BY 127, BY 133, EM 513, 1N4007
2212	1N2775	1N2772, 1000V	BY 127, BY 133, EM 513, 1N4007
2213	1N2776	1N2772, 1100V	BY 127, BY 133, EM 513, GP 10Q
2214	1N2777	1N2772, 1200V	BY 127, BY 133, EM 513, GP 10Q
2215	1N2778	1N2772, 1300V	BY 400, BY 448, EM 513, GP 10V
2216	1N2779	1N2772, 1400V	BY 400, BY 448, EM 516, GP 10V
2217	1N278	58V, 0,17A	AA 117...118, AA 132...134, 1N34, 1N54
2218	1N2780	1N2772, 1500V	BY 400, BY 448, EM 516, GP 10Y
2219	1N2781	1N2772, 1600V	BY 400, BY 448, EM 516, GP 10Y
2220	1N2784	200V, 22A(Tc40°)	BYX 96/300
2221	1N2785	1N2784, 400V	BYX 96/600
2222	1N2786	200V, 10A	BYW 88/200, BYX 77...81
2223	1N2787	1N2786, 400V	BYW 88/400, BYX 78...81
2224	1N2788	200V, 50A(Tc40°)	-
2225	1N2789	1N2788, 400V	-
2226	1N279	32V, 70mA	AA 117...118, AA 132...134, 1N34, 1N54
2227	1N2790	8,5V, 5%, 1W	BZX 53, 1N4782
2228	1N2793	50V, 8,5A	BYW 88/50, BYX 75...81
2229	1N2794	1N2793, 100V	BYW 88/100, BYX 76...81
2230	1N2795	1N2793, 150V	BYW 88/200, BYX 77...81
2231	1N2796	1N2793, 200V	BYW 88/200, BYX 77...81
2232	1N2797	1N2793, 250V	BYW 88/300, BYX 78...81
2233	1N2798	1N2793, 300V	BYW 88/300, BYX 78...81
2234	1N2799	1N2793, 350V	BYW 88/400, BYX 78...81
2235	1N2800	1N2793, 400V	BYW 88/400, BYX 78...81
2236	1N2801	20V, <500ns	-
2237	1N2804B..2846B	1N2804..2846, 5%	-
2238	1N2804R..2846R	1N2804..2846	-
2239	1N2805	1N2804, 7,5V	-
2240	1N2806	1N2804, 8,2V	-
2241	1N2807	1N2804, 9,1V	-
2242	1N2808	1N2804, 10V	-
2243	1N2809	1N2804, 11V	-
2244	1N281	75V, 75mA	AA 117...118, AA 132...134, 1N34, 1N54
2245	1N2810	1N2804, 12V	-
2246	1N2811	1N2804, 13V	-
2247	1N2812	1N2804, 14V	-
2248	1N2813	1N2804, 15V	-
2249	1N2814	1N2804, 16V	-

2250	1N2815	1N2804, 17V	-
2251	1N2816	1N2804, 18V	-
2252	1N2817	1N2804, 19V	-
2253	1N2818	1N2804, 20V	-
2254	1N2819	1N2804, 22V	-
2255	1N282	15V	AA 113...119, 1N34, 1N54, 1N60
2256	1N2820	1N2804, 24V	-
2257	1N2821	1N2804, 25V	-
2258	1N2822	1N2804, 27V	-
2259	1N2823	1N2804, 30V	-
2260	1N2824	1N2804, 33V	-
2261	1N2825	1N2804, 36V	-
2262	1N2826	1N2804, 39V	-
2263	1N2827	1N2804, 43V	-
2264	1N2828	1N2804, 45V	-
2265	1N2829	1N2804, 47V	-
2266	1N283	25V	AA 139
2267	1N2830	1N2804, 50V	-
2268	1N2831	1N2804, 51V	-
2269	1N2832	1N2804, 56V	-
2270	1N2833	1N2804, 62V	-
2271	1N2834	1N2804, 68V	-
2272	1N2835	1N2804, 75V	-
2273	1N2836	1N2804, 82V	-
2274	1N2837	1N2804, 91V	-
2275	1N2838	1N2804, 100V	-
2276	1N2839	1N2804, 105V	-
2277	1N2840	1N2804, 110V	-
2278	1N2841	1N2804, 120V	-
2279	1N2842	1N2804, 130V	-
2280	1N2843	1N2804, 150V	-
2281	1N2844	1N2804, 160V	-
2282	1N2845	1N2804, 180V	-
2283	1N2846	1N2804, 200V	-
2284	1N2847(A)	100V, 1,5A(Tc75°)	-
2285	1N2848(A)	1N2847, 200V	-
2286	1N2849(A)	1N2847, 300V	-
2287	1N2850(A)	1N2847, 400V	-
2288	1N2851(A)	1N2847, 500V	-
2289	1N2852(A)	1N2847, 600V	-
2290	1N2858(A)	50V, 0,75..1A	BY 126...127, BY 133...135, 1N4001...07
2291	1N2859(A)	1N2858, 100V	BY 126...127, BY 133...135, 1N4002...07
2292	1N2860(A)	1N2858, 200V	BY 126...127, BY 133...134, 1N4003...07
2293	1N2861(A)	1N2858, 300V	BY 126...127, BY 133...134, 1N4004...07
2294	1N2862(A)	1N2858, 400V	BY 126...127, BY 133...134, 1N4004...07

2295	1N2863(A)	1N2858, 500V	BY 126...127, BY 133...134, 1N4005...07
2296	1N2864(A)	1N2858, 600V	BY 126...127, BY 133...134, 1N4005...07
2297	1N2865	1000V, 0,7A	BY 127, BY 133, GP 10Q, 1N4007
2298	1N2866	1N2865, 1500V	BY 400, BY 448, EM 516, GP 10W
2299	1N287	40V, 60mA	AA 117...118, AA 132...134, 1N34, 1N54
2300	1N2878	700V, 0,25A	BA 158...159, BAY 90, BY 203/12
2301	1N2879	1N2878, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2302	1N288	70V, 0,75A	AA 117...118, AA 132...134, 1N34, 1N54
2303	1N2880	1N2878, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2304	1N2881	1N2878, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2305	1N2882	1N2878, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2306	1N2883	1N2878, 1000V	BA 159, BAY 90, BY 203/12, SHG 1
2307	1N2884	1N2878, 1400V	BAY 91, BY 203/16, GP 10W, SHG 1,5
2308	1N2885	1N2878, 1400V	BAY 91, BY 203/16, GP 10W, SHG 1,5
2309	1N2886	1N2878, 1500V	BAY 91, BY 203/16, GP 10W, SHG 1,5
2310	1N2887	1N2878, 1500V	BAY 91, BY 203/16, GP 10W, SHG 1,5
2311	1N2888	1N2878, 1700V	BAY 91, BY 203/20, DM 516, SHG 2
2312	1N2889	1N2878, 1700V	BAY 91, BY 203/20, DM 516, SHG 2
2313	1N289	80V, 80mA	AA 117...118, AA 132...134, 1N34, 1N54
2314	1N2890	1N2878, 2000V	BAY 91, BY 203/20, SHG 2, 1N1732(A)
2315	1N2891	1N2878, 2000V	BAY 91, BY 203/20, SHG 2, 1N1732(A)
2316	1N2892	1N2878, 2100V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2317	1N2893	1N2878, 2100V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2318	1N2894	1N2878, 2400V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2319	1N2895	1N2878, 2400V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2320	1N2896	1N2878, 2500V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2321	1N2897	1N2878, 2500V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2322	1N2898	1N2878, 2800V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2323	1N2899	1N2878, 2800V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2324	1N290	100V, 0,3A	AA 117...118, AA 132...133
2325	1N2900	1N2878, 3000V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2326	1N2901	1N2878, 3000V	GP 02-30, MR 250-3, SHG 2,5, 1N1733(A)
2327	1N2902	1N2878, 3100V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2328	1N2903	1N2878, 3100V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2329	1N2904	1N2878, 3500V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2330	1N2905	1N2878, 3500V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2331	1N2906	1N2878, 3500V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2332	1N2907	1N2878, 3500V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2333	1N2908	1N2878, 3800V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2334	1N2909	1N2878, 3800V	GP 02-40, HVG 4, MR 250-4, 1N1733(A)
2335	1N291	100V, 0,4A	AA 117...118, AA 132...133
2336	1N2910	1N2878, 4000V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2337	1N2911	1N2878, 4000V	GP 02-40, HVG 4, MR 250-4, 1N1734(A)
2338	1N2912	1N2878, 4200V	HVG 5, MR 250-5, 1N1734(A)
2339	1N2913	1N2878, 4200V	HVG 5, MR 250-5, 1N1734(A)

2340	1N2914	1N2878, 4500V	HVG 5, MR 250-5, 1N1734(A)
2341	1N2915	1N2878, 4500V	HVG 5, MR 250-5, 1N1734(A)
2342	1N2916	1N2878, 4500V	HVG 5, MR 250-5, 1N1734(A)
2343	1N2917	1N2878, 4500V	HVG 5, MR 250-5, 1N1734(A)
2344	1N2918	1N2878, 5000V	HVG 5, MR 250-5, 1N1734(A)
2345	1N2919	1N2878, 5000V	HVG 5, MR 250-5, 1N1734(A)
2346	1N292	70V, 70mA	AA 117...118, AA 132...134, 1N34, 1N54
2347	1N2920	1N2878, 5500V	BYX 90
2348	1N2921	1N2878, 5500V	BYX 90
2349	1N2922	1N2878, 6000V	BYX 90
2350	1N2923	1N2878, 6000V	BYX 90
2351	1N2924	1N2878, 6500V	BYX 90
2352	1N2925	1N2878, 6500V	BYX 90
2353	1N2937	50V, 15%, 10W	BZX98/C51, BZY93/C51, 1N2996
2354	1N2938	0,9V, 15%	-
2355	1N294(A)	60V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
2356	1N295(A,S,X)	30..40V, 20..35mA	AA 117...118, AA 132...134, 1N34, 1N54
2357	1N297(A)	80V, 35mA	AA 117...118, AA 132...134, 1N34, 1N54
2358	1N2970	6,8V, 20%, 10W(Tc55°)	BZX 98/..., BZY 93/..., ZL ..., ZX ...
2359	1N2970A...3015A	1N2970...3015, 10%	
2360	1N2970B...3015B	1N2970...3015, 5%	
2361	1N2970R...3015R	1N2970...3015	
2362	1N2971	1N2970, 7,5V	
2363	1N2972	1N2970, 8,2V	
2364	1N2973	1N2970, 9,1V	
2365	1N2974	1N2970, 10V	
2366	1N2975	1N2970, 11V	
2367	1N2976	1N2970, 12V	
2368	1N2977	1N2970, 13V	
2369	1N2978	1N2970, 14V	
2370	1N2979	1N2970, 15V	
2371	1N298(A)	70V, 30..50mA	AA 117...118, AA 132...134, 1N34, 1N54
2372	1N2980	1N2970, 16V	
2373	1N2981	1N2970, 17V	
2374	1N2982	1N2970, 18V	
2375	1N2983	1N2970, 19V	
2376	1N2984	1N2970, 20V	
2377	1N2985	1N2970, 22V	
2378	1N2986	1N2970, 24V	
2379	1N2987	1N2970, 25V	
2380	1N2988	1N2970, 27V	
2381	1N2989	1N2970, 30V	
2382	1N299	50V	AA 117...118, AA 132...134, 1N34, 1N54
2383	1N2990	1N2970, 33V	
2384	1N2991	1N2970, 36V	

2385	1N2992	1N2970, 39V	
2386	1N2993	1N2970, 43V	
2387	1N2994	1N2970, 45V	
2388	1N2995	1N2970, 47V	
2389	1N2996	1N2970, 50V	
2390	1N2997	1N2970, 51V	
2391	1N2998	1N2970, 52V	
2392	1N2999	1N2970, 56V	
2393	1N300(A,B)	15V, 65..100mA	BA 127, BA 147/25, 1N4148, 1N5194...96
2394	1N3000	1N2970, 62V	
2395	1N3001	1N2970, 68V	
2396	1N3002	1N2970, 75V	
2397	1N3003	1N2970, 82V	
2398	1N3004	1N2970, 91V	
2399	1N3005	1N2970, 100V	
2400	1N3006	1N2970, 105V	
2401	1N3007	1N2970, 110V	
2402	1N3008	1N2970, 120V	
2403	1N3009	1N2970, 130V	
2404	1N3010	1N2970, 140V	
2405	1N3011	1N2970, 150V	
2406	1N3012	1N2970, 160V	
2407	1N3013	1N2970, 175V	
2408	1N3014	1N2970, 180V	
2409	1N3015	1N2970, 200V	
2410	1N3016	6,8V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5921...56
2411	1N3016A...3051A	1N3016...3051, 10%	
2412	1N3016B...3051B	1N3016...3051, 5%	
2413	1N3017	1N3016, 7,5V	
2414	1N3018	1N3016, 8,2V	
2415	1N3019	1N3016, 9,1V	
2416	1N3020	1N3016, 10V	
2417	1N3021	1N3016, 11V	
2418	1N3022	1N3016, 12V	
2419	1N3023	1N3016, 13V	
2420	1N3024	1N3016, 15V	
2421	1N3025	1N3016, 16V	
2422	1N3026	1N3016, 18V	
2423	1N3027	1N3016, 20V	
2424	1N3028	1N3016, 22V	
2425	1N3029	1N3016, 24V	
2426	1N303(A,B)	125V, 40..65mA	BA 147/150, BAY 20, BAY 45, 1N5195...96
2427	1N3030	1N3016, 27V	
2428	1N3031	1N3016, 30V	
2429	1N3032	1N3016, 33V	

2430	1N3033	1N3016, 36V	
2431	1N3034	1N3016, 39V	
2432	1N3035	1N3016, 43V	
2433	1N3036	1N3016, 47V	
2434	1N3037	1N3016, 51V	
2435	1N3038	1N3016, 56V	
2436	1N3039	1N3016, 62V	
2437	1N304	55V	AA 117...118, AA 132...134, 1N34, 1N54
2438	1N3040	1N3016, 68V	
2439	1N3041	1N3016, 75V	
2440	1N3042	1N3016, 82V	
2441	1N3043	1N3016, 91V	
2442	1N3044	1N3016, 100V	
2443	1N3045	1N3016, 110V	
2444	1N3046	1N3016, 120V	
2445	1N3047	1N3016, 130V	
2446	1N3048	1N3016, 150V	
2447	1N3049	1N3016, 160V	
2448	1N305	60V, 125mA	AA 136, 1N270
2449	1N3050	1N3016, 180V	
2450	1N3051	1N3016, 200V	
2451	1N3052	12kV, 0,1A	-
2452	1N3053	1N3052, 14kV	-
2453	1N3054	1N3052, 16kV	-
2454	1N3055	1N3052, 18kV	-
2455	1N3056	1N3052, 20kV	-
2456	1N3057	1N3052, 22kV	-
2457	1N3058	1N3052, 24kV	-
2458	1N3059	1N3052, 26kV	-
2459	1N306	15V, 150mA	AA 135...136, AA 139, 1N270
2460	1N3060	1N3052, 28kV	-
2461	1N3061	1N3052, 30kV	-
2462	1N3062	50V, 0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2463	1N3063	50V, 0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2464	1N3064	50V, 0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2465	1N3065	50V, 0,115A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2466	1N3066	50V, 0,115A, <2ns	BA 218, BAX 13, BAX 91, 1N4148...49
2467	1N3067	30V, 0,115A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2468	1N3068	30V, 0,075A, <50ns	BAV 17...21, BAX 90, BAX 94, BAY 41
2469	1N3069	65V, 0,225A, <50ns	BAV 18...21, BAW 48...50, BAY 72
2470	1N3070	200V, 0,15A, <50ns	BA 197...198, BAV 20...21, BAW 50
2471	1N3071	200V, 0,225A, <50ns	BA 197...198, BAV 20...21, BAW 50
2472	1N3072	50V, 0,2A(Tc150°)	BY 126...127, BY 133...135, 1N4001...07
2473	1N3073	1N3072, 100V	BY 126...127, BY 133...135, 1N4002...07
2474	1N3074	1N3072, 150V	BY 126...127, BY 133...135, 1N4003...07



2475	1N3075	1N3072, 200V	BY 126...127, BY 133...134, 1N4003...07
2476	1N3076	1N3072, 250V	BY 126...127, BY 133...134, 1N4004...07
2477	1N3077	1N3072, 300V	BY 126...127, BY 133...134, 1N4004...07
2478	1N3078	1N3072, 350V	BY 126...127, BY 133...134, 1N4004...07
2479	1N3079	1N3072, 400V	BY 126...127, BY 133...134, 1N4004...07
2480	1N308	8V, 100mA	AA 139
2481	1N3080	1N3072, 500V	BY 126...127, BY 133...134, 1N4005...07
2482	1N3081	1N3072, 600V	BY 126...127, BY 133...134, 1N4005...07
2483	1N3082	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
2484	1N3083	1N3082, 400V	BY 126...127, BY 133...134, 1N4004...07
2485	1N3084	1N3082, 600V	BY 126...127, BY 133...134, 1N4005...07
2486	1N3085	100V, 150A(Tc150°)	1N4587...96
2487	1N3086	1N3085, 200V	1N4588...96
2488	1N3087	1N3085, 300V	1N4589...96
2489	1N3088	1N3085, 400V	1N4590...96
2490	1N3089	1N3085, 500V	1N4591...96
2491	1N309	30V, 100mA	AA 135...136, AA 139, 1N270
2492	1N3090	1N3085, 600V	1N4592...96
2493	1N3091	1N3085, 800V	1N4593...96
2494	1N3092	1N3085, 1000V	1N4594...96
2495	1N3097	30V, 0,05A, <500ns	AAZ 49, AAZ 15, AAZ 17, 1N276
2496	1N3098	120V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5951...56
2497	1N3098A...3101A	1N3098...3101, 10%	
2498	1N3099	1N3098, 145V	
2499	1N310	100V, 40mA	AA 117...118, AA 132...133
2500	1N3100	1N3098, 180V	
2501	1N3101	1N3098, 220V	
2502	1N3102	120V, 10%, 10W	BZX98/..., BZY93/..., ZX..., 1N3008...15
2503	1N3102A...3105A	1N3102...3105, 5%	
2504	1N3103	1N3102, 150V	
2505	1N3104	1N3102, 180V	
2506	1N3105	1N3102, 220V	
2507	1N3106	800V, 0,75A	BY 127, BY 133, BYX 94...95, 1N4006...07
2508	1N3107	1N3106, 1200V, 0,5A	BY 127, BY 133, BYX 94...95, GP 10Q
2509	1N3108	800V, 1,5A	BY 227, BY 254...255, 1N5062, 1N5398
2510	1N3109	1N3108, 1200V, 0,7A	BY 227, BY 255, BY 350/1300, GH 3E
2511	1N3110	12V, 0,05A	AAZ 27, AAZ 18, 1N3592
2512	1N3111	50V, 150A(Tc150°)	1N4587...96
2513	1N3112	7,4V, 5%, 1W	BZW22/C7V5, BZX61/C7V5, ZPY7,5, 1N5922
2514	1N3113		-
2515	1N3114		-
2516	1N3115		-
2517	1N3116		-
2518	1N3117		-
2519	1N3118		-



2520	1N3119		-
2521	1N312	50V, 70mA	AA 117...118, AA 132...134, 1N34, 1N54
2522	1N3120		-
2523	1N3121	50V, 0,11A, <500ns	AAZ 15, AAZ 17
2524	1N3122	20V, 0,18A, <3500ns	AA 139, AAZ 18
2525	1N3123	40V, 0,05A, <4ns	BA 218, BAX 13, BAX91, 1N4148...49
2526	1N3124	40V, 0,05A, <4ns	BA 218, BAX 13, BAX91, 1N4148...49
2527	1N3125	55V, 300ns	AAY 28, 1N631, 1N633
2528	1N313	100V, 40mA	AA 117...118, AA 132...133
2529	1N3139	50V, 70A(Tc150°)	-
2530	1N314	75V, 100mA	1N270
2531	1N3140	1N3139, 100V	-
2532	1N3141	1N3139, 150V	-
2533	1N3142	1N3139, 200V	-
2534	1N3146	25V, <2ns	-
2535	1N3147	60V	BA 127, BA 187...190, BAY 19...21
2536	1N3148	8,5V, 0,4W	1N4779, 1N4784
2537	1N315(A)	200..300V, 75..100mA	-
2538	1N3151	7,2kV, 0,1A	BYX 90, 1N5183
2539	1N3154(A)	8,4V, 5%, 0,4W	BZX 51, 1N4775, 1N4780
2540	1N3155(A)	8,4V, 5%, 0,4W	BZX 52, 1N4776, 1N4781
2541	1N3156(A)	8,4V, 5%, 0,4W	BZX 53, 1N4777, 1N4781
2542	1N3157(A)	8,4V, 5%, 0,4W	BZX 54, 1N4778, 1N4783
2543	1N3159	15V, 0,08A, <300ns	AAY 27...28, AAZ 18, 1N631, 1N633
2544	1N316(A)	50V, 0,25A	BA 157...159, BAY 18...21, BAY 86...90
2545	1N3160	60V, 0,03A	AAY 27...28, AAZ 18, 1N631, 1N633
2546	1N3161	50V, 175A(Tc150°)	1N3735...44
2547	1N3161R...3177R	1N3161...3177	1N3735R...3744R
2548	1N3162	1N3161, 100V	1N3735...44
2549	1N3163	1N3161, 150V	1N3736...44
2550	1N3164	1N3161, 200V	1N3736...44
2551	1N3165	1N3161, 250V	1N3737...44
2552	1N3166	1N3161, 300V	1N3737...44
2553	1N3167	1N3161, 350V	1N3738...44
2554	1N3168	1N3161, 400V	1N3738...44
2555	1N3169	1N3161, 500V	1N3739...44
2556	1N317(A)	1N316, 100V	BA 157...159, BAY 19...21, BAY 87...90
2557	1N3170	1N3161, 600V	1N3740...44
2558	1N3171(A)	1N3161, 700V, 240A	1N3741...44
2559	1N3172(A)	1N3161, 800V, 240A	1N3741...44
2560	1N3173(A)	1N3161, 900V, 240A	1N3742...44
2561	1N3174(A)	1N3161, 1000V, 240A	1N3742...44
2562	1N3175(A)	1N3161, 1200V, 240A	1N3743...44
2563	1N3176(A)	1N3161, 1200V, 240A	1N3744
2564	1N3177(A)	1N3161, 1600V, 240A	-

2565	1N3179	240V	BY 126...127, BY 133...134, 1N4004...07
2566	1N318(A)	1N316, 200V	BA 157...159, BAY 21, BAY 88...90
2567	1N3180	130V	BY 126...127, BY 133...135, 1N4003...07
2568	1N3181	7,7V, 10%, 0,6W	-
2569	1N3181	7,7V, 10%, 0,6W	-
2570	1N3182		-
2571	1N3189	200V, 1A	BY 226...227, BY 251...255, 1N5393...99
2572	1N319(A)	1N316, 350V	BA 157...159, BAY 21, BAY 88...90
2573	1N3190	1N3189, 400V	BY 226...227, BY 252...255, 1N5395...99
2574	1N3191	1N3189, 600V	BY 226...227, BY 253...255, 1N5397...99
2575	1N3193	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2576	1N3194	1N3193, 400V	BY 126...127, BY 133...134, 1N4004...07
2577	1N3195	1N3193, 600V	BY 126...127, BY 133...134, 1N4005...07
2578	1N3196	1N3193, 800V	BY 127, BY 133, BY 227, 1N4006...07
2579	1N3197	30V, 0,08A, <300ns	AAZ 49, AAZ 15, AAZ 17
2580	1N3198	2,25V, 2%, 0,4W	-
2581	1N3199	8,4V, 5%, 0,27W	BZX 52, 1N4776, 1N4781
2582	1N320(A)	1N316, 500V	BA 158...159, BAY 89...90
2583	1N3200	8,4V, 5%, 0,27W	BZX 53, 1N4777, 1N4782
2584	1N3201	8,4V, 5%, 0,27W	BZX 53, 1N4777, 1N4782
2585	1N3202	8,4V, 5%, 0,27W	BZX 54, 1N4778, 1N4783
2586	1N3203	25V, 0,06A, 300ns	AAZ 49, AAZ 15, AAZ 17, 1N276
2587	1N3204	60V, 0,06A, 300ns	AAZ 28, AAZ 15, AAZ 17, 1N276
2588	1N3206	100V, 0,075A, <4ns	BA 219, BAX 96
2589	1N3207	60V, <6ns	BAW 62, BAX 95, 1N4148...49, 1N4151
2590	1N3208	50V, 15A(Tc150°)	1N4525...30
2591	1N3208R...3214R	1N3208..3214	D 24C/...
2592	1N3209	1N3208, 100V	1N4525...30
2593	1N321(A)	1N316, 850V	BA 159, BAY 90...91
2594	1N3210	1N3208, 200V	1N4525...30
2595	1N3211	1N3208, 300V	1N4526...30
2596	1N3212	1N3208, 400V	1N4526...30
2597	1N3213	1N3208, 500V	1N4527...30
2598	1N3214	1N3208, 600V	1N4527...30
2599	1N3215	60V, <250ns	BAW 21, BAX 15...17, 1N4148...49
2600	1N322(A)	1N316, 1000V	BA 159, BAY 90...91
2601	1N3223	150V, 800ns	BA 196...198, BAV 20...21, BAX 15...17
2602	1N3225	40V, 0,03A, <500ns	AAZ 28, 1N276, 1N631, 1N633
2603	1N3227	100V, 0,5A	BY 126...127, BY 133...135, 1N4002...07
2604	1N3228	1N3227, 200V	BY 126...127, BY 133...134, 1N4003...07
2605	1N3229	1N3227, 400V	BY 126...127, BY 133...134, 1N4004...07
2606	1N323(A)	50V, 0,4A	BA 157...159, BY 126...127, 1N4001...07
2607	1N3230	1N3227, 600V	BY 126...127, BY 133...134, 1N4005...07
2608	1N3231	1N3227, 800V	BY 127, BY 133, GP 10Q, 1N4006...07
2609	1N3232	1N3227, 1000V	BY 127, BY 133, GP 10Q, 1N4007

2610	1N3233	1N3227, 1200V	BY 127, BY 133, EM 513, GP 10Q
2611	1N3234	1N3227, 1500V	BY 269, GP 10W, DM 513, EM 516
2612	1N3235	1N3227, 1800V	DM 516
2613	1N3236	1N3227, 2000V	-
2614	1N3237	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
2615	1N3238	1N3237, 100V	BY 126...127, BY 133...135, 1N4002...07
2616	1N3239	1N3237, 200V	BY 126...127, BY 133...134, 1N4003...07
2617	1N324(A)	1N323, 100V	BA 157...159, BY 126...127, 1N4002...07
2618	1N3240	1N3237, 400V	BY 126...127, BY 133...134, 1N4004...07
2619	1N3241	1N3237, 600V	BY 126...127, BY 133...134, 1N4005...07
2620	1N3242	1N3237, 800V	BY 127, BY 133, GP 10Q, 1N4006...07
2621	1N3243	1N3237, 1000V	BY 127, BY 133, GP 10Q, 1N4007
2622	1N3244	1N3237, 1200V	BY 127, BY 133, EM 513, GP 10Q
2623	1N3245	1N3237, 1500V	BY 269, DM 513, EM 516, GP 10W
2624	1N3246	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
2625	1N3247	1N3246, 100V	BY 126...127, BY 133...135, 1N4002...07
2626	1N3248	1N3246, 200V	BY 126...127, BY 133...134, 1N4003...07
2627	1N3249	1N3246, 400V	BY 126...127, BY 133...134, 1N4004...07
2628	1N325(A)	1N323, 200V	BA 157...159, BY 126...127, 1N4003...07
2629	1N3250	1N3246, 600V	BY 126...127, BY 133...134, 1N4005...07
2630	1N3251	1N3246, 800V	BY 127, BY 133, BY 227, 1N4006...07
2631	1N3252	1N3246, 1000V	BY 127, BY 133, BY 227, 1N4007
2632	1N3253	1N3193	1N3193
2633	1N3254	1N3194	1N3194
2634	1N3255	1N3195	1N3195
2635	1N3256	1N3196	1N3196
2636	1N3257	80V, <3ns	BA 219, BAW 62, BAX 95, 1N4148...49
2637	1N3258	80V, <4ns	BA 219, BAW 62, BAX 95, 1N4148...49
2638	1N326(A)	1N323, 350V	BA 157...159, BY 126...127, 1N4004...07
2639	1N3260	50V, 160A(Tc125°)	1N4587...96
2640	1N3260R...3276R	1N3260...3276	1N4587R...4596R
2641	1N3261	1N3260, 100V	1N4587...96
2642	1N3262	1N3260, 150V	1N4588...96
2643	1N3263	1N3260, 200V	1N4588...96
2644	1N3264	1N3260, 250V	1N4589...96
2645	1N3265	1N3260, 300V	1N4589...96
2646	1N3266	1N3260, 350V	1N4590...96
2647	1N3267	1N3260, 400V	1N4590...96
2648	1N3268	1N3260, 500V	1N4591...96
2649	1N3269	1N3260, 600V	1N4592...96
2650	1N327(A)	1N323, 500V	BA 158...159, BY 126...127, 1N4005...07
2651	1N3270	1N3260, 700V	1N4593...96
2652	1N3271	1N3260, 800V	1N4593...96
2653	1N3272	1N3260, 900V	1N4594...96
2654	1N3273	1N3260, 1000V	1N4594...96

2655	1N3274	1N3260, 1200V	1N4595...96
2656	1N3275	1N3260, 1400V	1N4596
2657	1N3276	1N3260, 1600V	-
2658	1N3277	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2659	1N3278	1N3277, 400V	BY 126...127, BY 133...134, 1N4004...07
2660	1N3279	1N3277, 600V	BY 126...127, BY 133...134, 1N4005...07
2661	1N328(A)	1N323, 850V	BA 159, BY 127, BY 133, 1N4007
2662	1N3280	1N3278, 800V	BY 127, BY 133, BY 227, 1N4006...07
2663	1N3281	1N3278, 1000V	BY 127, BY 133, BY 227, 1N4007
2664	1N3282	1000V, 0,1A	BY 203/12, RGP 01-10, SHG 1, 1N5181
2665	1N3283	1N3282, 1500V	BY 203/16, RGP 01-16, SHG 1,5, 1N5181
2666	1N3284	1N3282, 2000V	BY 203/20, HVG 2, SHG 2, 1N5181
2667	1N3285	1N3282, 2500V	HVG 3, SHG 2,5, 1N1733, 1N5181
2668	1N3286	1N3282, 3000V	HVG 3, GP 02-30, 1N1733, 1N5181
2669	1N3287(W)	0,26V, 0,25W	-
2670	1N3288(A)	100V, 100A(Tc130°)	-
2671	1N3288R...3297R	1N3288...3297	DS 85-01C...-12C
2672	1N3289(A)	1N3288, 200V	-
2673	1N329(A)	1N323, 1000V	BA 159, BY 127, BY 133, 1N4007
2674	1N3290(A)	1N3288, 300V	-
2675	1N3291(A)	1N3288, 400V	-
2676	1N3292(A)	1N3288, 500V	-
2677	1N3293(A)	1N3288, 600V	-
2678	1N3294(A)	1N3288, 800V	-
2679	1N3295(A)	1N3288, 1000V	-
2680	1N3296(A)	1N3288, 1200V	-
2681	1N3297(A)	1N3288, 1400V	-
2682	1N3298	60V, <200ns	BAV 18...21, BAX 15...17, BAY 42...43
2683	1N3298A	1N3288, 70V, 0,3A, <20ns	BAV 18...21, BAX 15...17, BAY 42...43
2684	1N3299	Itsm10A	-
2685	1N330	32V	BA 127...128, BA 147/50, BA 222
2686	1N3300	Itsm50A	-
2687	1N3300A	1N3300, Ub16,2..19,8V	-
2688	1N3301	1N3300, Ub17,6..29,4V	-
2689	1N3301A	1N3300, Ub19,8..24,2V	-
2690	1N3302	1N3300, Ub21,6..32,4V	-
2691	1N3302A	1N3300, Ub24,3..29,7V	-
2692	1N3303	1N3300, Ub26,4..39,6V	-
2693	1N3303A	1N3300, Ub29,7..36,3V	-
2694	1N3304	1N3300, Ub31,2..46,8V	-
2695	1N3304A	1N3300, Ub35,1..42,9V	-
2696	1N3305	6,8V, 20%, 50W(Tc75°)	BZY 91/...
2697	1N3305A...3350A	1N3305...3350, 10%	
2698	1N3305B...3350B	1N3305...3350, 5%	
2699	1N3305R...3350R	1N3305...3350	

2700	1N3306	1N3305, 7,5V	
2701	1N3307	1N3305, 8,2V	
2702	1N3308	1N3305, 9,1V	
2703	1N3309	1N3305, 10V	
2704	1N331	16V	BA 127...128, BA 147/25, BA 222
2705	1N3310	1N3305, 11V	
2706	1N3311	1N3305, 12V	
2707	1N3312	1N3305, 13V	
2708	1N3313	1N3305, 14V	
2709	1N3314	1N3305, 15V	
2710	1N3315	1N3305, 16V	
2711	1N3316	1N3305, 17V	
2712	1N3317	1N3305, 18V	
2713	1N3318	1N3305, 19V	
2714	1N3319	1N3305, 20V	
2715	1N332	400V, 1,2A	BYX 38/600, BYX 39/600
2716	1N3320	1N3305, 22V	
2717	1N3321	1N3305, 24V	
2718	1N3322	1N3305, 25V	
2719	1N3323	1N3305, 27V	
2720	1N3324	1N3305, 30V	
2721	1N3325	1N3305, 33V	
2722	1N3326	1N3305, 36V	
2723	1N3327	1N3305, 39V	
2724	1N3328	1N3305, 43V	
2725	1N3329	1N3305, 45V	
2726	1N333	1N332, 0,6A	BYX 38/600, BYX 39/600
2727	1N3330	1N3305, 47V	
2728	1N3331	1N3305, 50V	
2729	1N3332	1N3305, 51V	
2730	1N3333	1N3305, 52V	
2731	1N3334	1N3305, 56V	
2732	1N3335	1N3305, 62V	
2733	1N3336	1N3305, 68V	
2734	1N3337	1N3305, 75V	
2735	1N3338	1N3305, 82V	
2736	1N3339	1N3305, 91V	
2737	1N334	1N332, 300V	BYX 38/300, BYX 39/600
2738	1N3340	1N3305, 100V	
2739	1N3341	1N3305, 105V	
2740	1N3342	1N3305, 110V	
2741	1N3343	1N3305, 120V	
2742	1N3344	1N3305, 130V	
2743	1N3345	1N3305, 140V	
2744	1N3346	1N3305, 150V	

2745	1N3347	1N3305, 160V	
2746	1N3348	1N3305, 175V	
2747	1N3349	1N3305, 180V	
2748	1N335	1N332, 300V, 0,6A	BYX 38/300, BYX 39/600
2749	1N3350	1N3305, 200V	
2750	1N3354	10V, 3A(Tc55°)	BYX 38/300, BYX 39/600
2751	1N3355	1N3354, 15V	BYX 38/300, BYX 39/600
2752	1N3356	1N3354, 25V	BYX 38/300, BYX 39/600
2753	1N3357	1N3354, 50V	BYX 38/300, BYX 39/600
2754	1N3358	1N3354, 75V	BYX 38/300, BYX 39/600
2755	1N3359	1N3354, 100V	BYX 38/300, BYX 39/600
2756	1N336	1N332, 200V	BYX 38/300, BYX 39/600
2757	1N3360	1N3354, 150V	BYX 38/300, BYX 39/600
2758	1N3361	1N3354, 200V	BYX 38/300, BYX 39/600
2759	1N3362	1N3354, 300V	BYX 38/300, BYX 39/600
2760	1N3363	1N3354, 400V	BYX 38/600, BYX 39/600
2761	1N3364	1N3354, 500V	BYX 38/600, BYX 39/600
2762	1N3365	1N3354, 600V	BYX 38/600, BYX 39/600
2763	1N3366	1N3354, 700V	BYX 38/900, BYX 39/800
2764	1N3367	1N3354, 800V	BYX 38/900, BYX 39/800
2765	1N3368	1N3354, 900V	BYX 38/900, BYX 39/1000
2766	1N3369	1N3354, 1000V	BYX 38/1200, BYX 39/1000
2767	1N337	1N332, 200V, 0,6A	BYX 38/300, BYX 39/600
2768	1N3370	1N3354, 1200V	BYX 38/1200, BYX 39/1200
2769	1N3371	1N3354, 1500V	-
2770	1N3372	10V, 20A(Tc100°)	DS 25-01A, 1N3491...95
2771	1N3373	1N3372, 25V	DS 25-01A, 1N3491...95
2772	1N3374	1N3372, 50V	DS 25-01A, 1N3491...95
2773	1N3375	1N3372, 100V	DS 25-01A, 1N3492...95
2774	1N3376	1N3372, 150V	DS 25-02A, 1N3493...95
2775	1N3377	1N3372, 200V	DS 25-02A, 1N3493...95
2776	1N3378	1N3372, 300V	DS 25-03A, 1N3494...95
2777	1N3379	1N3372, 400V	DS 25-05A, 1N3495
2778	1N338	100V, 3A	BYX 38/300, BYX 39/600
2779	1N3380	1N3372, 500V	DS 25-05A
2780	1N339	2N338, 1,2A	BYX 38/300, BYX 39/600
2781	1N34(A)	75V, 50mA	AA 113, 1N60
2782	1N340	2N338, 0,6A	BYX 38/300, BYX 39/600
2783	1N341	2N338, 400V, 1,2A	BYX 38/600, BYX 39/600
2784	1N342	2N338, 400V, 0,6A	BYX 38/600, BYX 39/600
2785	1N343	2N338, 300V, 1,2A	BYX 38/600, BYX 39/600
2786	1N344	300V, 0,6A	BYX 38/300, BYX 39/600
2787	1N345	1N344, 200V, 1,2A	BYX 38/300, BYX 39/600
2788	1N346	1N344, 200V, 0,6A	BYX 38/300, BYX 39/600
2789	1N3464	12kV, 0,06A	1N3052

2790	1N3465	60V, 75mA	AA 117...118, AA 132...134, 1N34, 1N54
2791	1N3466	40V, 75mA	AA 117...118, AA 132...134, 1N34, 1N54
2792	1N3467	18V, <2ns	-
2793	1N3468	18V, <2ns	-
2794	1N3469	35V, 85mA	AA 135...136, 1N634...635
2795	1N347	1N344, 100V, 3A	BYX 38/300, BYX 39/600
2796	1N3470	35V, 85mA	AA 135...136, 1N634...635
2797	1N3477	2,2V, 10%, 0,25W	BZX55/C2V4, BZX79/C2V4, 1N5221
2798	1N3477A	1N3477, 5%	
2799	1N348	1N344, 100V, 1,2A	BYX 38/300, BYX 39/600
2800	1N3483	8V	-
2801	1N3484	75V	AA 117...118, AA 132...133
2802	1N3485	175V, <50ns	BA 197...198, BAV 20...21, 1N3070
2803	1N3486	1000V, 0,4A	BA 159, BY 127, BY 133, BY 204/10
2804	1N3487	1N3486, 1200V	BY 127, BY 133, BYX 94...95, GP 10Q
2805	1N3488		-
2806	1N3489(A)	Itsm10A	-
2807	1N349	1N344, 100V, 0,6A	BYX 38/300, BYX 39/600
2808	1N3490	1N3489	-
2809	1N3491	50V, 25A(Tc130°)	SSi E1205...1240, 1N3659...3665
2810	1N3491R...3495R	1N3491...3495	DS 25-...A, SSi E1105...40, 1N3659R...65R
2811	1N3492	1N3491, 100V	SSi E1210...1240, 1N3660...3665
2812	1N3493	1N3491, 200V	SSi E1220...1240, 1N3661...3665
2813	1N3494	1N3491, 300V	SSi E1220...1240, 1N3662...3665
2814	1N3495	1N3491, 400V	SSi E1230...1240, 1N3663...3665
2815	1N3496	6,2V, 5%, 0,25W	BZV 11, BZV 28, BZX 91, 1N4581
2816	1N3497	6,2V, 5%, 0,25W	BZV 12, BZV 29, BZX 92, 1N4582
2817	1N3498	6,2V, 5%, 0,25W	BZV 13, BZV 30, BZX 93, 1N4583
2818	1N3499	6,2V, 5%, 0,25W	BZV 14, BZV 31, BZX 94, 1N4584
2819	1N350	70V, 15mA	BA 147/100, BAY 19...21, BAY 45...46
2820	1N3500	6,2V, 5%, 0,25W	BZV 10, BZV 27, BZX 90, 1N4580
2821	1N3501	6,35V, 2%, 0,25W	1N4890
2822	1N3502	6,35V, 2%, 0,25W	1N4891
2823	1N3503(A)	6,35V, 2%, 0,25W	1N4890...95
2824	1N3504(A)	6,35V, 2%, 0,25W	1N4890...95
2825	1N3506	3,3V, 5%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5226...61,...
2826	1N3507	1N3506, 3,6V	
2827	1N3508	1N3506, 3,9V	
2828	1N3509	1N3506, 4,3V	
2829	1N351	1N350, 120V	BA 147/150, BAY 20...21, BAY 45...46
2830	1N3510	1N3506, 4,7V	
2831	1N3511	1N3506, 5,1V	
2832	1N3512	1N3506, 5,6V	
2833	1N3513	1N3506, 6,2V	
2834	1N3514	1N3506, 6,8V	



2835	1N3515	1N3506, 7,5V	
2836	1N3516	1N3506, 8,2V	
2837	1N3517	1N3506, 9,1V	
2838	1N3518	1N3506, 10V	
2839	1N3519	1N3506, 11V	
2840	1N352	1N350, 170V	BA 147/230, BAY 20...21, BAY 46
2841	1N3520	1N3506, 12V	
2842	1N3521	1N3506, 13V	
2843	1N3522	1N3506, 15V	
2844	1N3523	1N3506, 16V	
2845	1N3524	1N3506, 18V	
2846	1N3525	1N3506, 20V	
2847	1N3526	1N3506, 22V	
2848	1N3527	1N3506, 24V	
2849	1N3528	1N3506, 27V	
2850	1N3529	1N3506, 30V	
2851	1N353	1N350, 225V	BA 147/300, BAY 21, BAY 46, BAY 88
2852	1N3530	1N3506, 33V	
2853	1N3531	1N3506, 36V	
2854	1N3532	1N3506, 39V	
2855	1N3533	1N3506, 43V	
2856	1N3534	1N3506, 47V	
2857	1N3537	12V, 10%, 1W	BZW22/C12, BZX61/C12, ZPY12, 1N5927
2858	1N354	1N350, 325V	BA 147/300, BAY 21, BAY 46, BAY 88
2859	1N3544	100V, 0,6A	BY 126...127, BY 133...134, 1N4002...07
2860	1N3545	1N3544, 200V	BY 126...127, BY 133...134, 1N4003...07
2861	1N3546	1N3544, 300V	BY 126...127, BY 133...134, 1N4004...07
2862	1N3547	1N3544, 400V	BY 126...127, BY 133...134, 1N4004...07
2863	1N3548	1N3544, 500V	BY 126...127, BY 133...134, 1N4005...07
2864	1N3549	1N3544, 600V	BY 126...127, BY 133...134, 1N4005...07
2865	1N355	80V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
2866	1N3550	180V, 0,08A, <1,5µs	BA 157...159, BA 199/250, BAY 46
2867	1N3551		-
2868	1N3552(A)		-
2869	1N3553	0,25V, 0,25W	-
2870	1N3554		-
2871	1N3555		-
2872	1N3556		-
2873	1N3557		-
2874	1N3559	24V	AA 139, 1N270
2875	1N3563	1000V, 0,4A	BA 159, BY 127, BY 133, 1N4007
2876	1N3564	15V	AA 112...113, AA 116, 1N34, 1N54, 1N60
2877	1N3565	6V, 2A	
2878	1N3566	800V, 1A	BYX 38/900, BYX 39/800
2879	1N3567	75V, 0,06A, <2ns	BA 218, BAX 13, BAX 91, 1N4148...49



2880	1N3568	80V, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2881	1N3569	100V, 3,5A(Tc85°)	BYX 38/300, BYX 39/600
2882	1N3570	1N3569, 200V	BYX 38/300, BYX 39/600
2883	1N3571	1N3569, 300V	BYX 38/300, BYX 39/600
2884	1N3572	1N3569, 400V	BYX 38/600, BYX 39/600
2885	1N3573	1N3569, 500V	BYX 38/600, BYX 39/600
2886	1N3574	1N3569, 600V	BYX 38/600, BYX 39/600
2887	1N3575	60V, 0,15A	BA 147/100, BA 157...159, BAY 19
2888	1N3576	1N3575, 125V	BA 147/150, BA 157...159, BAY 20
2889	1N3577	1N3575, 175V	BA 147/230, BA 157...159, BAY 20
2890	1N3578	1N3575, 225V	BA 147/230, BA 157...159, BAY 21
2891	1N3579	1N3575, 275V	BA 147/300, BA 157...159, BAY 21
2892	1N3580(A,B)	11,7V, 5%, 0,75W	1N941
2893	1N3581(A,B)	11,7V, 5%, 0,75W	1N942
2894	1N3582(A,B)	11,7V, 5%, 0,75W	1N943
2895	1N3583(A,B)	11,7V, 5%, 0,75W	1N944
2896	1N3584(A,B)	11,7V, 5%, 0,75W	1N945
2897	1N3585	50V, 400A(Tc120°)	-
2898	1N3586	1N3585, 100V	-
2899	1N3587	1N3585, 200V	-
2900	1N3588	1N3585, 300V	-
2901	1N3589	1N3585, 400V	-
2902	1N359(A)	50V, 0,15A	BA 147/50, BAY 18...21, 1N4001...07
2903	1N3590	1N3585, 500V	-
2904	1N3591	1N3585, 600V	-
2905	1N3592	30V, 0,05A, <70ns	AAY 27
2906	1N3593	40V, 0,05A, 10ns	BA 218, BAX 13, BAX 91, 1N4148...49
2907	1N3594	60V, 6ns	BA 218, BAX 13, BAX 91, 1N4148...49
2908	1N3595	150V, 0,1A, <3µs	BA 147/150, BA 157...159, 1N5606...07
2909	1N3596	20V, 0,075A, <4ns	BA 217, BA 317, BAY 71, 1N4148...49
2910	1N3597	200V, 0,275A, <300ns	BA 157...159, BA 173, BY 206...207
2911	1N3598	50V, 0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
2912	1N3599	150V, <50ns	BA 196...198, BAV 20...21, BAY 80
2913	1N36	36V, 16mA	AA 113, AA 119, 1N34, 1N60
2914	1N360(A)	1N359, 100V	BA 147/100, BAY 19...21, 1N4002...07
2915	1N3600	50V, 0,2A, <4ns	BAW 62, BAX 95, BAY 95, 1N4148...49
2916	1N3601	75V, <5ns	BAW 62, BAX 95, BAW 76, 1N4148...49
2917	1N3602	75V, 0,115A, <5ns	BAW 62, BAX 95, BAW 76, 1N4148...49
2918	1N3603	1N3602, 45V	BAW 62, BAX 95, BAW 76, 1N4148...49
2919	1N3604	1N4151	1N4151
2920	1N3605	1N4152	1N4152
2921	1N3606	1N4153	1N4153
2922	1N3607	1N4151	1N4151
2923	1N3608	1N4152	1N4152
2924	1N3609	1N4153	1N4153

2925	1N361(A)	1N359, 200V	BA 147/230, BAY 21, 1N4003...07
2926	1N3611(GP)	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
2927	1N3612(GP)	1N3611, 400V	BY 126...127, BY 133...134, 1N4004...07
2928	1N3613(GP)	1N3611, 600V	BY 126...127, BY 133...134, 1N4005...07
2929	1N3614(GP)	1N3611, 800V	BY 127, BY 133, 1N4006...07
2930	1N3615	50V, 16A(Tc150°)	BYX 25/600, BYX 99/600
2931	1N3616	1N3615, 100V	BYX 25/600, BYX 99/600
2932	1N3617	1N3615, 150V	BYX 25/600, BYX 99/600
2933	1N3618	1N3615, 200V	BYX 25/600, BYX 99/600
2934	1N3619	1N3615, 300V	BYX 25/600, BYX 99/600
2935	1N362(A)	1N359, 350V	BAY 21, BAY 88...90, 1N4003...07
2936	1N3620	1N3615, 400V	BYX 25/600, BYX 99/600
2937	1N3621	1N3615, 500V	BYX 25/600, BYX 99/600
2938	1N3622	1N3615, 600V	BYX 25/600, BYX 99/600
2939	1N3623	1N3615, 800V	BYX 25/800, BYX 99/900
2940	1N3624	1N3615, 1000V	BYX 25/1000, BYX 99/1200
2941	1N3625	200V, 0,15A	BA 157...159, BY 204/4, BY 206...207
2942	1N3626	50V	AA 117...118, AA 132...134, 1N34, 1N54
2943	1N3627		-
2944	1N3628		-
2945	1N3629	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
2946	1N363(A)	1N359, 500V	BA 158...159, BAY 89...90, 1N4005...07
2947	1N3630	1N3629, 200V	BY 126...127, BY 133...134, 1N4003...07
2948	1N3631	1N3629, 300V	BY 126...127, BY 133...134, 1N4004...07
2949	1N3632	1N3629, 400V	BY 126...127, BY 133...134, 1N4004...07
2950	1N3633	1N3629, 500V	BY 126...127, BY 133...134, 1N4005...07
2951	1N3634	1N3629, 600V	BY 126...127, BY 133...134, 1N4005...07
2952	1N3635	1N3629, 700V	BY 127, BY 133, BY 227, 1N4006...07
2953	1N3636	1N3629, 800V	BY 127, BY 133, BY 227, 1N4006...07
2954	1N3637	1N3629, 900V	BY 127, BY 133, BY 227, 1N4007
2955	1N3638	1N3629, 1000V	BY 127, BY 133, BY 227, 1N4007
2956	1N3639	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2957	1N364(A)	1N359, 850V	BA 159, BAY 90...91, 1N4007
2958	1N3640	1N3639, 400V	BY 126...127, BY 133...134, 1N4004...07
2959	1N3641	1N3639, 600V	BY 126...127, BY 133...134, 1N4005...07
2960	1N3642	1N3639, 800V	BY 127, BY 133, BY 227, 1N4006...07
2961	1N3643	1000V, 0,25A	BA 159, BY 127, BY 133, 1N4007
2962	1N3644	1N3643, 1500V	BAY 91, BY 203/16, BY 269, GP 10W
2963	1N3645	1N3643, 2000V	BAY 91, BY 203/20, GP 02-20, MR 250-2
2964	1N3646	1N3643, 2500V	GP 02-30, MR 250-3, 1N1733A
2965	1N3647	1N3643, 3000V	GP 02-30, MR 250-3, 1N1733A
2966	1N3648	10kV, 0,35A	-
2967	1N3649	800V, 3,3A(Tc50°)	BYX 38/900, BYX 39/800
2968	1N3649R...3650R	1N3649...3650	BYX 38/...R, BYX 39/...R
2969	1N365(A)	1N359, 1000V	BA 159, BAY 90...91, 1N4007

2970	1N3650	1N3649, 1000V	BYX 38/1200, BYX 39/1000
2971	1N3656	200V, 0,75A	BY 126...127, BY 133...134, 1N4003...07
2972	1N3657	1N3656, 400V	BY 126...127, BY 133...134, 1N4004...07
2973	1N3658	1N3656, 600V	BY 126...127, BY 133...134, 1N4005...07
2974	1N3659	50V, 30A(Tc100°)	SSi E1105...1140
2975	1N3659R...3665R	1N3659...3665	SSi E1205...1240
2976	1N3660	1N3659, 100V	SSi E1110...1140
2977	1N3661	1N3659, 200V	SSi E1120...1140
2978	1N3662	1N3659, 300V	SSi E1120...1140
2979	1N3663	1N3659, 400V	SSi E1130...1140
2980	1N3664	1N3659, 500V	SSi E1130...1140
2981	1N3665	1N3659, 600V	SSi E1140
2982	1N3666	80V, 0,07A, <300ns	AAZ 28, AAZ 15, 1N633
2983	1N3668	30V, 0,075A, <150ns	BAX 85, BAX 89...90, BAX 94, 1N4148...49
2984	1N3669	70V, 0,4A, <200ns	BA 157...159, BAV 15...16, BAX 12
2985	1N367	60V	AA 117...118, AA 132...134, 1N34, 1N54
2986	1N3670(A)	700V, 12A(Tc150°)	BYW 88/800, BYX 80...81, 1N4509...11
2987	1N3670R...3673R	1N3670...3673	BYW 88/...R, BYX 80R...81R
2988	1N3671(A)	1N3670, 800V	BYW 88/800, BYX 80...81, 1N4509...11
2989	1N3672(A)	1N3670, 900V	BYW 88/1000, BYX 81, 1N4510...11
2990	1N3673(A)	1N3670, 1000V	BYW 88/1000, BYX 81, 1N4510...11
2991	1N3675	6,8V, 20%, 0,75W	BZV85/..., BZW22/..., ZPY..., 1N3016...51
2992	1N3675A...3710A	1N3675...3710, 10%	
2993	1N3675B...3710B	1N3675...3710, 5%	
2994	1N3676	1N3675, 7,5V	
2995	1N3677	1N3675, 8,2V	
2996	1N3678	1N3675, 9,1V	
2997	1N3679	1N3675, 10V	
2998	1N368(A)	200V, 0,1A	-
2999	1N3680	1N3675, 11V	
3000	1N3681	1N3675, 12V	
3001	1N3682	1N3675, 13V	
3002	1N3683	1N3675, 15V	
3003	1N3684	1N3675, 16V	
3004	1N3685	1N3675, 18V	
3005	1N3686	1N3675, 20V	
3006	1N3687	1N3675, 22V	
3007	1N3688	1N3675, 24V	
3008	1N3689	1N3675, 27V	
3009	1N3690	1N3675, 30V	
3010	1N3691	1N3675, 33V	
3011	1N3692	1N3675, 36V	
3012	1N3693	1N3675, 39V	
3013	1N3694	1N3675, 43V	
3014	1N3695	1N3675, 47V	

3015	1N3696	1N3675, 51V	
3016	1N3697	1N3675, 56V	
3017	1N3698	1N3675, 62V	
3018	1N3699	1N3675, 68V	
3019	1N370	1,85V, 20%, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5221...36
3020	1N3700	1N3675, 75V	
3021	1N3701	1N3675, 82V	
3022	1N3702	1N3675, 91V	
3023	1N3703	1N3675, 100V	
3024	1N3704	1N3675, 110V	
3025	1N3705	1N3675, 120V	
3026	1N3706	1N3675, 130V	
3027	1N3707	1N3675, 150V	
3028	1N3708	1N3675, 160V	
3029	1N3709	1N3675, 180V	
3030	1N371	1N370, 2,35V, 15%	
3031	1N3710	1N3675, 200V	
3032	1N3711	6kV, 0,15A	BYX 90
3033	1N3712		-
3034	1N3713		-
3035	1N3714		-
3036	1N3715		-
3037	1N3716		-
3038	1N3717		-
3039	1N3718		-
3040	1N3719		-
3041	1N372	1N370, 2,9V, 15%	
3042	1N3720		-
3043	1N3721		-
3044	1N3722	50V, <10ns	BA 218, BAX 13, BAX 91, 1N4148...49
3045	1N3723	1000V, 0,75A	BY 127, BY 133, BY 227, 1N4007
3046	1N3724	1N3723, 1200V	BY 127, BY 133, BY 227, GP 10Q
3047	1N3725	1N3723, 1400V	BY 400, BY 448, EM 516, GP 10W
3048	1N3726	1N3723, 1600V	BY 400, DM 513, EM 516, GP 10Y
3049	1N3727	1N3723, 1800V	DM 516
3050	1N3728	550V, 0,2A	BA 158...159, BA 199/550, BAY 89...90
3051	1N3729	600V, <500ns	BY 208/600, BY 295/600, BY 407
3052	1N373	1N370, 3,5V, 15%	
3053	1N3730	80V, <15ns	BAW 26...27
3054	1N3731	100V, 0,175A, <3ns	-
3055	1N3732	5,1V, 5%, 1W	BZW22/C5V1, BZX61/C5V1, ZPY5,1, 1N5918
3056	1N3735	100V, 250A(Tc130°)	-
3057	1N3735R...3744R	1N3735...3744	DS 40-...A
3058	1N3736	1N3735, 200V	-
3059	1N3737	1N3735, 300V	-

3060	1N3738	1N3735, 400V	-
3061	1N3739	1N3735, 500V	-
3062	1N374	1N370, 4,1V, 10%	
3063	1N3740	1N3735, 600V	-
3064	1N3741	1N3735, 800V	-
3065	1N3742	1N3735, 1000V	-
3066	1N3743	1N3735, 1200V	-
3067	1N3744	1N3735, 1400V	-
3068	1N3748	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
3069	1N3749	1N3748, 400V	BY 126...127, BY 133...134, 1N4004...07
3070	1N375	1N370, 4,1V, 5%	
3071	1N3750	1N3748, 600V	BY 126...127, BY 133...134, 1N4005...07
3072	1N3751	1N3748, 800V	BY 127, BY 133, BY 227, 1N4006...07
3073	1N3752	1N3748, 1000V	BY 127, BY 133, BY 227, 1N4007
3074	1N3753	55V	AA 117...118, AA 132...134, 1N34, 1N54
3075	1N3754	100V, 0,125A	BA 157...159, BY 204/4, BY 206...207
3076	1N3755	1N3754, 200V	BA 157...159, BY 204/4, BY 206...207
3077	1N3756	1N3754, 400V	BA 157...159, BY 204/4, BY 206...207
3078	1N3757	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
3079	1N3758	1N3757, 400V	BY 126...127, BY 133...134, 1N4004...07
3080	1N3759	1N3757, 600V	BY 126...127, BY 133...134, 1N4005...07
3081	1N376	1N370, 4,95V, 5%	
3082	1N3760	1N3757, 800V	BY 127, BY 133, BY 227, 1N4006...07
3083	1N3761	1N3757, 1000V	BY 127, BY 133, BY 227, 1N4007
3084	1N3762	7,5kV, 0,065A	BYX 90, 1N5183
3085	1N3763	20V, 5%, 1,5W	-
3086	1N3764	3kV, 0,4A	1N1733A
3087	1N3765	700V, 35A(Tc140°)	1N4528
3088	1N3765T...3768T	1N3765...3768	-
3089	1N3766	1N3765, 800V	1N4528
3090	1N3767	1N3765, 900V	1N4529
3091	1N3768	1N3765, 1000V	1N4529
3092	1N3769	90V	AA 117...118, AA 132...133
3093	1N377	1N370, 5,9V, 5%	
3094	1N3771	Ub>170V	-
3095	1N3772	Ub15..25V, Ib<0,4mA, Itsm10A	-
3096	1N3773	25V, <40ns	-
3097	1N3774	1,15V, 2%, 0,34W	-
3098	1N3775	1500V, 3,3A(Tc50°)	-
3099	1N3776	10V, 10%, 6W	BZX98/C10, BZY93/C10, ZL10, 1N2974
3100	1N3777	800V, 35A(Tc140°)	1N3766...68, 1N4528...30
3101	1N3779	6,5V, 3%, 0,4W	BZV 10, BZV 27, BZX 90, 1N4580
3102	1N378	1N370, 7,15V, 5%	
3103	1N3780	6,5V, 3%, 0,4W	BZV 10, BZV 27, BZX 90, 1N4580
3104	1N3781	6,5V, 3%, 0,4W	BZV 11, BZV 28, BZX 91, 1N4581

3105	1N3782	6,5V, 3%, 0,4W	BZV 12, BZV 29, BZX 92, 1N4582
3106	1N3783	6,5V, 3%, 0,4W	BZV 13, BZV 30, BZX 93, 1N4583
3107	1N3784	6,5V, 3%, 0,4W	BZV 14, BZV 31, BZV 94, 1N4584
3108	1N3785	6,8V, 20%, 1,5W	-
3109	1N3785B...3820B	1N3785...3820, 5%	
3110	1N3786	1N3785, 7,5V	
3111	1N3787	1N3785, 8,2V	
3112	1N3788	1N3785, 9,1V	
3113	1N3789	1N3785, 10V	
3114	1N379	8,2V, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5237...81,...
3115	1N3790	1N3785, 11V	
3116	1N3791	1N3785, 12V	
3117	1N3792	1N3785, 13V	
3118	1N3793	1N3785, 15V	
3119	1N3794	1N3785, 16V	
3120	1N3795	1N3785, 18V	
3121	1N3796	1N3785, 20V	
3122	1N3797	1N3785, 22V	
3123	1N3798	1N3785, 24V	
3124	1N3799	1N3785, 27V	
3125	1N38	120V, 50mA	AA 117...118, AA 132...133
3126	1N380	1N379, 10V	
3127	1N3800	1N3785, 30V	
3128	1N3801	1N3785, 33V	
3129	1N3802	1N3785, 36V	
3130	1N3803	1N3785, 39V	
3131	1N3804	1N3785, 43V	
3132	1N3805	1N3785, 47V	
3133	1N3806	1N3785, 51V	
3134	1N3807	1N3785, 56V	
3135	1N3808	1N3785, 62V	
3136	1N3809	1N3785, 68V	
3137	1N381	1N379, 12V	
3138	1N3810	1N3785, 75V	
3139	1N3811	1N3785, 82V	
3140	1N3812	1N3785, 91V	
3141	1N3813	1N3785, 100V	
3142	1N3814	1N3785, 110V	
3143	1N3815	1N3785, 120V	
3144	1N3816	1N3785, 130V	
3145	1N3817	1N3785, 150V	
3146	1N3818	1N3785, 160V	
3147	1N3819	1N3785, 180V	
3148	1N382	1N379, 15V	
3149	1N3820	1N3785, 200V	

3150	1N3821	3,3V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...22
3151	1N3821A...3830A	1N3821...3830, 5%	
3152	1N3822	1N3821, 3,6V	
3153	1N3823	1N3821, 3,9V	
3154	1N3824	1N3821, 4,3V	
3155	1N3825	1N3821, 4,7V	
3156	1N3826	1N3821, 5,1V	
3157	1N3827	1N3821, 5,6V	
3158	1N3828	1N3821, 6,2V	
3159	1N3829	1N3821, 6,8V	
3160	1N383	1N379, 18V	
3161	1N3830	1N3821, 7,5V	
3162	1N3831	I <sub>tsm</sub> 5A	4E20..., 4E20M...
3163	1N3832	1N3831, Ub21..29V	-
3164	1N3833	1N3831, Ub26..34V	4E30..., 4E30M...
3165	1N3834	1N3831, Ub31..39V	4E40..., 4E40M...
3166	1N3835	1N3831, Ub36..44V	4E40..., 4E40M...
3167	1N3836	1N3831, Ub41..49V	4E50..., 4E50M...
3168	1N3837	1N3831, Ub46..54V	4E50..., 4E50M...
3169	1N3838	1N3831, Ub90..110V	4E100..., 4E100M...
3170	1N3839	1N3831, Ub16..24V	4E20..., 4E20M...
3171	1N384	1N379, 22V	
3172	1N3840	1N3831, Ub21..29V	-
3173	1N3841	1N3831, Ub26..34V	4E30..., 4E30M...
3174	1N3842	1N3831, Ub31..39V	4E40..., 4E40M...
3175	1N3843	1N3831, Ub36..44V	4E40..., 4E40M...
3176	1N3844	1N3831, Ub41..49V	4E50..., 4E50M...
3177	1N3845	1N3831, Ub46..54V	4E50..., 4E50M...
3178	1N3846	1N3831, Ub90..110V	4E100..., 4E100M...
3179	1N385	1N379, 27V	
3180	1N386	1N379, 33V	
3181	1N3864	125V, <900ns	BA 173, BAV 19...21, BAX 15...17
3182	1N3865	80V	1N270
3183	1N3866	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
3184	1N3867	1N3866, 400V	BY 126...127, BY 133...134, 1N4004...07
3185	1N3868	1N3866, 600V	BY 126...127, BY 133...134, 1N4005...07
3186	1N3869	1000V, 0,5A	BA 159, BY 127, BY 133, 1N4007
3187	1N387	1N379, 39V	
3188	1N3870	1N3879, 1500V	BY 269, DM 513, EM 516, GP 10W
3189	1N3871	1N3879, 2000V, 0,25A	BAY 91, BY 203/20, SHG 2
3190	1N3872	90V, <15ns	BA 202...203, BAV 16, BAY 43
3191	1N3873	90V, 0,15A, <4ns	BA 219, BAW 47
3192	1N3874	1N3879	-
3193	1N3875	1N3880	-
3194	1N3876	1N3881	-



3195	1N3877	1N3882	-
3196	1N3878	1N3883	-
3197	1N3879(A)	50V, 6A(Tc100°), <200ns	
3198	1N3879R...3883R	1N3879	BYX 62/800R
3199	1N388	1N379, 47V	
3200	1N3880(A)	1N3879, 100V	BYX 62/800
3201	1N3881(A)	1N3879, 200V	BYX 62/800
3202	1N3882(A)	1N3879, 300V	BYX 62/800
3203	1N3883(A)	1N3879, 400V	BYX 62/800
3204	1N3884	1N3889	-
3205	1N3885	1N3890	-
3206	1N3886	1N3891	-
3207	1N3887	1N3892	-
3208	1N3888	1N3893	-
3209	1N3889(A)	50V, 12A(Tc100°), <200ns	
3210	1N3889R...3893R	1N3889	BYX 62/800R
3211	1N389	1N379, 56V	
3212	1N3890(A)	1N3889, 100V	BYX 62/800
3213	1N3891(A)	1N3889, 200V	BYX 62/800
3214	1N3892(A)	1N3889, 300V	BYX 62/800
3215	1N3893(A)	1N3889, 400V	BYX 62/800
3216	1N3894	400V, 0,4A	BA 157...159, BY 204/4, BY 207
3217	1N3895	350V, 0,4A	BA 157...159, BY 204/4, BY 206...207
3218	1N3896	0,775V, 5%, 0,25W	-
3219	1N3897	1,5V, 5%, 0,25W	-
3220	1N3898	2V, 5%, 0,25W	-
3221	1N3899	50V, 20A(Tc100°), <200ns	BYT 65/600, 1N3909...13
3222	1N3899R...3903R	1N3899, 400V	BYT 65/600R, 1N3909R...13R
3223	1N39	200V, 50mA	-
3224	1N390	1N379, 68V	
3225	1N3900	1N3899, 100V	BYT 65/600, 1N3910...13
3226	1N3901	1N3899, 200V	BYT 65/600, 1N3911...13
3227	1N3902	1N3899, 300V	BYT 65/600, 1N3912...13
3228	1N3903	1N3899, 400V	BYT 65/600, 1N3913
3229	1N3904	1N3899	1N3914...18
3230	1N3905	1N3900	1N3915...18
3231	1N3906	1N3901	1N3916...18
3232	1N3907	1N3902	1N3917...18
3233	1N3908	1N3903	1N3918
3234	1N3909	50V, 30A(Tc100°), <200ns	MR 860...866
3235	1N3909R...3913R	1N3909...3913	MR 864R...866R
3236	1N391	1N379, 82V	
3237	1N3910	1N3909, 100V	MR 861...866
3238	1N3911	1N3909, 200V	MR 862...866
3239	1N3912	1N3909, 300V	MR 864...866



3240	1N3913	1N3909, 400V	MR 864...866
3241	1N3914	1N3909	-
3242	1N3915	1N3910	-
3243	1N3916	1N3911	-
3244	1N3917	1N3912	-
3245	1N3918	1N3913	-
3246	1N3919	1000V, 5A(Tc100°)	BYX 38/1200, BYX 39/1200
3247	1N392	1N379, 100V	
3248	1N3920	1N3919, 1500V	-
3249	1N3921	1N3919, 2000V	-
3250	1N3922	1N3919, 2500V	-
3251	1N3923	1N3919, 3000V	-
3252	1N3924	1000V, 10A(Tc100°)	BYX 42/1200, BYX 98/1200
3253	1N3925	1N3924, 1500V	-
3254	1N3926	1N3924, 2000V	-
3255	1N3927	1N3924, 2500V	-
3256	1N3928	1N3924, 3000V	-
3257	1N3929	1000V, 1A	BY 127, BY 133, BY 227, 1N4007
3258	1N393	1N379, 120V	
3259	1N3930	1N3929, 1500V	BY 269, DM 513, EM 516, GP 10W
3260	1N3931	1N3929, 2000V	-
3261	1N3932	1N3929, 2500V	-
3262	1N3933	1N3929, 3000V	-
3263	1N3934	1200V, 10A	BYX 42/1200, BYX 98/1200
3264	1N3935	Ub26..34V, Ib<15µA, Itsm10A	-
3265	1N3936	Itsm10A	-
3266	1N3937	Itsm10A	-
3267	1N3938	200V, 2A	BYW 52...56, 1N5060...62
3268	1N3939	1N3938, 400V	BYW 53...56, 1N5060...62
3269	1N394	1N379, 150V	
3270	1N3940	1N3938, 600V	BYW 54...56, 1N5061...62
3271	1N3941	1N3938, 800V	BYW 55...56, 1N5062
3272	1N3942	1N3938, 1000V	BYW 56
3273	1N3943	2,5V, 0,75W	-
3274	1N3944	15V, <12ns	AAAY 48, 1N995
3275	1N3945		-
3276	1N3946		-
3277	1N3947		-
3278	1N3949	20V, 5%, 10W	BZX98/C20, BZY93/C20, ZX20, 1N2984
3279	1N395	1N379, 180V	
3280	1N3950	20V, 5%, 1,5W	-
3281	1N3951	25V, 5%, 1,5W	-
3282	1N3952	130V, 0,2A	BA 189...190, BAY 20...21, BAY 45...46
3283	1N3953	40V, <300ns	AAAY 28, 1N631, 1N633
3284	1N3954	50V, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49

3285	1N3955	100V, 70A(Tc150°)	-
3286	1N3956	30V, 2ns	BA 218, BAX 13, BAX 91, 1N4148...49
3287	1N3957(GP)	1N3611, 1000V	BY 127, BY 133, BY 227, 1N4007
3288	1N3958(C)	100V, 3,5A	BYX 38/300, BYX 39/600
3289	1N3959(C)	1N3958, 200V	BYX 38/300, BYX 39/600
3290	1N396	1N379, 220V	
3291	1N3960(C)	1N3958, 300V	BYX 38/300, BYX 39/600
3292	1N3961(C)	1N3958, 400V	BYX 38/600, BYX 39/600
3293	1N3962(C)	1N3958, 500V	BYX 38/600, BYX 39/600
3294	1N3963(C)	1N3958, 600V	BYX 38/600, BYX 39/600
3295	1N3964	200V, 22A(Tc120°)	BYX 25/600
3296	1N3965	1N3964, 400V	BYX 25/600
3297	1N3966	1N3964, 600V	BYX 25/600
3298	1N3967	1N3964, 800V	BYX 25/800
3299	1N3968	200V, 50A(Tc120°)	-
3300	1N3969	1N3968, 400V	-
3301	1N397	1N379, 270V	
3302	1N3970	1N3968, 600V	-
3303	1N3971	1N3968, 800V	-
3304	1N3972	200V, 104A(Tc120°)	-
3305	1N3973	1N3972, 400V	-
3306	1N3974	1N3972, 600V	-
3307	1N3975	1N3972, 800V	-
3308	1N3976	200V, 250A(Tc120°)	-
3309	1N3977	1N3976, 400V	-
3310	1N3978	1N3976, 600V	-
3311	1N3979	1N3976, 800V	-
3312	1N398	1N379, 330V	
3313	1N3981	200V, 3A	BY 251...255, BYW 17/200, 1N5402...08
3314	1N3982	1N3981, 400V	BY 252...255, BYW 17/400, 1N5404...08
3315	1N3983	1N3981, 600V	BY 253...255, BYW 17/400, 1N5406...08
3316	1N3984	5,5V, 5%, 10W	BZX98/C5V6, BZY93/C5V6, ZX5,6, 1N3997
3317	1N3985	1N3984, 6V	BZX98/C6V2, BZY93/C6V2, ZX6,2, 1N3998
3318	1N3986	1N3984, 6,2V	BZX98/C6V2, BZY93/C6V2, ZX6,2, 1N3998
3319	1N3987	700V, 6A(Tc150°)	BYX 38/900, BYX 39/800
3320	1N3987R...3990R	1N3987..3990	BYX 38/...R, BYX 39/...R
3321	1N3988	1N3987, 800V	BYX 38/900, BYX 39/800
3322	1N3989	1N3987, 900V	BYX 38/900, BYX 39/1000
3323	1N399	1N379, 390V	
3324	1N3990	1N3987, 1000V	BYX 38/1200, BYX 39/1000
3325	1N3991	35V	AA 117...118, AA 132...134, 1N34, 1N54
3326	1N3992	4kV	GP 02-40, MR 250-4, 1N1734A
3327	1N3993	3,9V, 10%, 10W(Tc55°)	BZX98/..., BZY93/..., ZL..., ZX...
3328	1N3993A...4000A	1N3993..4000, 5%	
3329	1N3994	1N3993, 4,3V	

3330	1N3995	1N3993, 4,7V	
3331	1N3996	1N3993, 5,1V	
3332	1N3997	1N3993, 5,6V	
3333	1N3998	1N3993, 6,2V	
3334	1N3999	1N3993, 6,8V	
3335	1N400	1N379, 470V	
3336	1N4000	1N3993, 7,5V	
3337	1N4001		BY 126...127, BY 133...135, 1N5614...22
3338	1N4002(..)	1N4001, 100V	BY 126...127, BY 133...135, 1N5614...22
3339	1N4003(..)	1N4001, 200V	BY 126...127, BY 133...134, 1N5614...22
3340	1N4004(..)	1N4001, 400V	BY 126...127, BY 133...134, 1N5616...22
3341	1N4005(..)	1N4001, 600V	BY 126...127, BY 133...134, 1N5618...22
3342	1N4006(..)	1N4001, 800V	BY 127, BY 133, BY 227, 1N5620...22
3343	1N4007(..)	1N4001, 1000V	BY 127, BY 133, BY 227, 1N5622
3344	1N4007KH	1N4001, 1600V	DM 513, DM 516, EM 516, GP 10Y
3345	1N4007KS	1N4001, 1250V	BY 133, BYX 95, EM 513, GP 10V
3346	1N4008	12V, 0,1A, <70ns	AAZ 18
3347	1N4009	35V, 0,1A, <4ns	BA 318, BAY 38, BAX 80, 1N4148...49
3348	1N401	1,5V	-
3349	1N4010	6,2V, 5%, 0,4W	BZV 10, BZV 27, BZX 90, 1N4580
3350	1N4011	1000V, 0,5A	BA 159, BY 127, BY 133, 1N4007
3351	1N4012	700V, 12A(Tc150°)	BYW 88/800, BYX 80...81, 1N4509...11
3352	1N4013	1N4012, 800V	BYW 88/800, BYX 80...81, 1N4509...11
3353	1N4014	1N4012, 900V	BYW 88/1000, BYX 81, 1N4510...11
3354	1N4015	1N4012, 1000V	BYW 88/1000, BYX 81, 1N4510...11
3355	1N4016	8,2V, 20%, 5W	BZX98/..., BZY93/..., ZX..., 1N2972...3005
3356	1N4016A...4042A	1N4016..4042, 10%	
3357	1N4016B...4042B	1N4016..4042, 5%	
3358	1N4017	1N4016, 9,1V	
3359	1N4018	1N4016, 10V	
3360	1N4019	1N4016, 11V	
3361	1N402	2V	-
3362	1N4020	1N4016, 12V	
3363	1N4021	1N4016, 13V	
3364	1N4022	1N4016, 15V	
3365	1N4023	1N4016, 16V	
3366	1N4024	1N4016, 18V	
3367	1N4025	1N4016, 20V	
3368	1N4026	1N4016, 22V	
3369	1N4027	1N4016, 24V	
3370	1N4028	1N4016, 27V	
3371	1N4029	1N4016, 30V	
3372	1N403	2,5V	-
3373	1N4030	1N4016, 33V	
3374	1N4031	1N4016, 36V	

3375	1N4032	1N4016, 39V	
3376	1N4033	1N4016, 43V	
3377	1N4034	1N4016, 47V	
3378	1N4035	1N4016, 51V	
3379	1N4036	1N4016, 56V	
3380	1N4037	1N4016, 62V	
3381	1N4038	1N4016, 68V	
3382	1N4039	1N4016, 75V	
3383	1N404	3,1V	-
3384	1N4040	1N4016, 82V	
3385	1N4041	1N4016, 91V	
3386	1N4042	1N4016, 100V	
3387	1N4043	25V, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
3388	1N4044	50V, 275A(Tc120°)	-
3389	1N4044R..4056R	1N4044..4056	-
3390	1N4045	1N4044, 100V	-
3391	1N4046	1N4044, 150V	-
3392	1N4047	1N4044, 200V	-
3393	1N4048	1N4044, 250V	-
3394	1N4049	1N4044, 300V	-
3395	1N405	3,7V	-
3396	1N4050	1N4044, 400V	-
3397	1N4051	1N4044, 500V	-
3398	1N4052	1N4044, 600V	-
3399	1N4053	1N4044, 700V	-
3400	1N4054	1N4044, 800V	-
3401	1N4055	1N4044, 900V	-
3402	1N4056	1N4044, 1000V	-
3403	1N4057(A)	12,4V, 5%, 1,5W	-
3404	1N4058(A)	1N4057, 14,6V	-
3405	1N4059(A)	1N4057, 16,8V	-
3406	1N406	4,3V	-
3407	1N4060(A)	1N4057, 18,5V	-
3408	1N4061(A)	1N4057, 21V	-
3409	1N4062(A)	1N4057, 23V	-
3410	1N4063(A)	1N4057, 27V	-
3411	1N4064(A)	1N4057, 30V	-
3412	1N4065(A)	1N4057, 33V	-
3413	1N4066(A)	1N4057, 37V	-
3414	1N4067(A)	1N4057, 43V	-
3415	1N4068(A)	1N4057, 47V	-
3416	1N4069(A)	51V, 5%, 2W	-
3417	1N407	5,2V	-
3418	1N4070(A)	1N4069, 56V	-
3419	1N4071(A)	1N4069, 62V	-

3420	1N4072(A)	1N4069, 68V	-
3421	1N4073(A)	1N4069, 75V	-
3422	1N4074(A)	1N4069, 82V	-
3423	1N4075(A)	1N4069, 87V	-
3424	1N4076(A)	1N4069, 91V	-
3425	1N4077(A)	1N4069, 100V	-
3426	1N4078(A)	1N4069, 105V	-
3427	1N4079(A)	1N4069, 110V	-
3428	1N408	6,2V	-
3429	1N4080(A)	1N4069, 120V	-
3430	1N4081(A)	130V, 5%, 2,5W	-
3431	1N4082(A)	1N4081, 140V	-
3432	1N4083(A)	1N4081, 150V	-
3433	1N4084(A)	1N4081, 175V	-
3434	1N4085(A)	1N4081, 200V	-
3435	1N4086	70V, <200ns	BAW 49...50, BAX 15...17, BAY 72
3436	1N4087	50V, <2,5ns	BA 318, BAY 38, BAY 95, 1N4148...49
3437	1N4088	30V	AA 117...118, AA 132...14, 1N34, 1N54
3438	1N4089	400V, 1,1A	BY 126...127, BY 133...134, 1N4004...07
3439	1N409		-
3440	1N4090		-
3441	1N4092	50V	BA 127, BA 187...190, 1N4148...49
3442	1N4093	50V	BA 127, BA 187...190, 1N4148...49
3443	1N4095	5V, 10%, 0,33W	BZX55/C5V1, BZX79/C5V1, ZPD5,1, 1N5231
3444	1N4096	90V, 5%, 3W	BZT03/...
3445	1N4097	1N4096, 100V	
3446	1N4098	1N4096, 150V	
3447	1N4099	6,8V, 5%, 0,4W,	BZV 39/...
3448	1N4100	1N4099, 7,5V	
3449	1N4101	1N4099, 8,2V	
3450	1N4102	1N4099, 8,7V	
3451	1N4103	1N4099, 9,1V	
3452	1N4104	1N4099, 10V	
3453	1N4105	1N4099, 11V	
3454	1N4106	1N4099, 12V	
3455	1N4107	1N4099, 13V	
3456	1N4108	1N4099, 14V	
3457	1N4109	1N4099, 15V	
3458	1N411(A,B)	50V, 25..50A	BYX 56/600, BYX 97/300
3459	1N4110	1N4099, 16V	
3460	1N4111	1N4099, 17V	
3461	1N4112	1N4099, 18V	
3462	1N4113	1N4099, 19V	
3463	1N4114	1N4099, 20V	
3464	1N4115	1N4099, 22V	

3465	1N4116	1N4099, 24V	
3466	1N4117	1N4099, 25V	
3467	1N4118	1N4099, 27V	
3468	1N4119	1N4099, 28V	
3469	1N4120	1N4099, 30V	
3470	1N4121	1N4099, 33V	
3471	1N4122	1N4099, 36V	
3472	1N4123	1N4099, 39V	
3473	1N4124	1N4099, 43V	
3474	1N4125	1N4099, 47V	
3475	1N4126	1N4099, 51V	
3476	1N4127	1N4099, 56V	
3477	1N4128	1N4099, 60V	
3478	1N4129	1N4099, 62V	
3479	1N4130	1N4099, 68V	
3480	1N4131	1N4099, 75V	
3481	1N4132	1N4099, 82V	
3482	1N4133	1N4099, 87V	
3483	1N4134	1N4099, 91V	
3484	1N4135	1N4099, 100V	
3485	1N4136	200V, 70A(Tc100°)	-
3486	1N4137	1N4136, 400V	-
3487	1N4138	1N4136, 600V	-
3488	1N4139	50V, 3A	BY 251...255, BYW 17/100, 1N5400...08
3489	1N4140	1N4139, 100V	BY 251...255, BYW 17/100, 1N5401...08
3490	1N4141	1N4139, 200V	BY 251...255, BYW 17/200, 1N5402...08
3491	1N4142	1N4139, 400V	BY 252...255, BYW 17/400, 1N5404...08
3492	1N4143	1N4139, 600V	BY 253...255, BYW 17/600, 1N5406...08
3493	1N4144	1N4139, 800V	BY 254...255, BYW 17/800, 1N5407...08
3494	1N4145	1N4139, 1000V	BY 255, BYW 17/1000, 1N5408
3495	1N4146	1N4139, 1200V	BY 255, BY 228, BYW 17/1200
3496	1N4147	30V, 10ns	BA 218, BAX 13, BAX 91, 1N4148...49
3497	1N4148	100V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4446...49
3498	1N4149	100V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4446...49
3499	1N4150	50V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3500	1N4151	75V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3501	1N4152	40V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3502	1N4153	75V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3503	1N4154	35V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3504	1N4155	400V, 0,2A, <10µs	BA 157...159, BA 199/450, BAY 89
3505	1N4156	1,41V(1mA), 0,4W	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
3506	1N4157	2,05V(1mA), 0,4W	BZ 102/2V1, BZX 75/C2V1, ZTE 1
3507	1N4158	6,8V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5921...56
3508	1N4158A...4193A	1N4158..4193, 10%	
3509	1N4158B...4193B	1N4158..4193, 5%	

3510	1N4159	1N4158, 7,5V	
3511	1N4160	1N4158, 8,2V	
3512	1N4161	1N4158, 9,1V	
3513	1N4162	1N4158, 10V	
3514	1N4163	1N4158, 11V	
3515	1N4164	1N4158, 12V	
3516	1N4165	1N4158, 13V	
3517	1N4166	1N4158, 15V	
3518	1N4167	1N4158, 16V	
3519	1N4168	1N4158, 18V	
3520	1N4169	1N4158, 20V	
3521	1N417	60V, 60mA, <300ns	AAZ 15, AAZ 17, 1N276
3522	1N4170	1N4158, 22V	
3523	1N4171	1N4158, 24V	
3524	1N4172	1N4158, 27V	
3525	1N4173	1N4158, 30V	
3526	1N4174	1N4158, 33V	
3527	1N4175	1N4158, 36V	
3528	1N4176	1N4158, 39V	
3529	1N4177	1N4158, 43V	
3530	1N4178	1N4158, 47V	
3531	1N4179	1N4158, 51V	
3532	1N418	60V, 16mA, <300ns	AAY 28, 1N191...192
3533	1N4180	1N4158, 56V	
3534	1N4181	1N4158, 62V	
3535	1N4182	1N4158, 68V	
3536	1N4183	1N4158, 75V	
3537	1N4184	1N4158, 82V	
3538	1N4185	1N4158, 91V	
3539	1N4186	1N4158, 100V	
3540	1N4187	1N4158, 110V	
3541	1N4188	1N4158, 120V	
3542	1N4189	1N4158, 130V	
3543	1N419	80V, 60mA, <300ns	AAZ 15
3544	1N4190	1N4158, 150V	
3545	1N4191	1N4158, 160V	
3546	1N4192	1N4158, 180V	
3547	1N4193	1N4158, 200V	
3548	1N4194	6,8V, 20%, 10W	BZX98/..., BZY93/..., ZX..., 1N2970...3015
3549	1N4194A...4239A	1N4194..4239, 10%	
3550	1N4194B...4239B	1N4194..4239, 5%	
3551	1N4195	1N4194, 7,5V	
3552	1N4196	1N4194, 8,2V	
3553	1N4197	1N4194, 9,1V	
3554	1N4198	1N4194, 10V	

3555	1N4199	1N4194, 11V	
3556	1N4200	1N4194, 12V	
3557	1N4201	1N4194, 13V	
3558	1N4202	1N4194, 14V	
3559	1N4203	1N4194, 15V	
3560	1N4204	1N4194, 16V	
3561	1N4205	1N4194, 17V	
3562	1N4206	1N4194, 18V	
3563	1N4207	1N4194, 19V	
3564	1N4208	1N4194, 20V	
3565	1N4209	1N4194, 22V	
3566	1N4210	1N4194, 24V	
3567	1N4211	1N4194, 25V	
3568	1N4212	1N4194, 27V	
3569	1N4213	1N4194, 30V	
3570	1N4214	1N4194, 33V	
3571	1N4215	1N4194, 36V	
3572	1N4216	1N4194, 39V	
3573	1N4217	1N4194, 43V	
3574	1N4218	1N4194, 45V	
3575	1N4219	1N4194, 47V	
3576	1N4220	1N4194, 50V	
3577	1N4221	1N4194, 51V	
3578	1N4222	1N4194, 52V	
3579	1N4223	1N4194, 56V	
3580	1N4224	1N4194, 62V	
3581	1N4225	1N4194, 68V	
3582	1N4226	1N4194, 75V	
3583	1N4227	1N4194, 82V	
3584	1N4228	1N4194, 91V	
3585	1N4229	1N4194, 100V	
3586	1N4230	1N4194, 105V	
3587	1N4231	1N4194, 110V	
3588	1N4232	1N4194, 120V	
3589	1N4233	1N4194, 130V	
3590	1N4234	1N4194, 140V	
3591	1N4235	1N4194, 150V	
3592	1N4236	1N4194, 160V	
3593	1N4237	1N4194, 175V	
3594	1N4238	1N4194, 180V	
3595	1N4239	1N4194, 200V	
3596	1N4240	5V, 2%, 10W	BZX 98/5V1, BZY 93/C5V1, ZX 5,1
3597	1N4241	6V, 2%, 10W	BZX 98/C6V2, BZY 93/C6V2, ZX 6,2
3598	1N4242	2x SS, 40V, <2ns	-
3599	1N4244	10V, 0,05A, <0,75ns	BAY 82, 1N4376



3600	1N4245(GP)	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
3601	1N4246(GP)	1N4245, 400V	BY 126...127, BY 133...134, 1N4004...07
3602	1N4247(GP)	1N4245, 600V	BY 126...127, BY 133...134, 1N4005...07
3603	1N4248(GP)	1N4245, 800V	BY 127, BY 133, BY 227, 1N4006...07
3604	1N4249(GP)	1N4245, 1000V	BY 127, BY 133, BY 227, 1N4007
3605	1N424A	150V, 0,225A	BA 147/150, BA 190, 1N5195...96
3606	1N4250	800V, 0,5A	BY 127, BY 133, BY 227, 1N4006...07
3607	1N4251	1N4250, 1000V	BY 127, BY 133, BY 227, 1N4007
3608	1N4252	1N4250, 1200V	BY 127, BY 133, BY 227, BY 268, GP 10Q
3609	1N4253	1N4250, 1500V	BY 269, DM 513, EM 516, GP 10W
3610	1N4254	1500V, 0,25A	BAY 91, BY 203/16, GP 02-20, SHG 1,5
3611	1N4255	1N4254, 2000V	BAY 91, BY 203/20, GP 02-20, SHG 2
3612	1N4256	1N4254, 2500V	GP 02-30, MR 250-3, SHG 2,5
3613	1N4257	1N4254, 3000V	GP 02-30, MR 250-3, SHG 2,5
3614	1N4258	6,8V, 20%, 10W	BZX98/..., BZY93/..., ZX..., 1N2970...3015
3615	1N4258A...4293A	1N4258..4293, 10%	
3616	1N4258B...4293B	1N4258..4293, 5%	
3617	1N4259	1N4258, 7,5V	
3618	1N4260	1N4258, 8,2V	
3619	1N4261	1N4258, 9,1V	
3620	1N4262	1N4258, 10V	
3621	1N4263	1N4258, 11V	
3622	1N4264	1N4258, 12V	
3623	1N4265	1N4258, 13V	
3624	1N4266	1N4258, 15V	
3625	1N4267	1N4258, 16V	
3626	1N4268	1N4258, 18V	
3627	1N4269	1N4258, 20V	
3628	1N4270	1N4258, 22V	
3629	1N4271	1N4258, 24V	
3630	1N4272	1N4258, 27V	
3631	1N4273	1N4258, 30V	
3632	1N4274	1N4258, 33V	
3633	1N4275	1N4258, 36V	
3634	1N4276	1N4258, 39V	
3635	1N4277	1N4258, 43V	
3636	1N4278	1N4258, 47V	
3637	1N4279	1N4258, 51V	
3638	1N4280	1N4258, 56V	
3639	1N4281	1N4258, 62V	
3640	1N4282	1N4258, 68V	
3641	1N4283	1N4258, 75V	
3642	1N4284	1N4258, 82V	
3643	1N4285	1N4258, 91V	
3644	1N4286	1N4258, 100V	

3645	1N4287	1N4258, 110V	
3646	1N4288	1N4258, 120V	
3647	1N4289	1N4258, 130V	
3648	1N429	6,2V, 5%, 0,2W	BZV 10, BZV 27, BZX 90, 1N821, 1N4580
3649	1N4290	1N4258, 150V	
3650	1N4291	1N4258, 160V	
3651	1N4292	1N4258, 180V	
3652	1N4293	1N4258, 200V	
3653	1N4295(A)	10V, 0,4W	-
3654	1N4296(A)	10V, 1W	-
3655	1N4297(A,B)	8,8V, 5%, 10W	-
3656	1N4298(A,B)	8,8V, 5%, 10W	-
3657	1N4299(A,B)	11,3V, 5%, 10W	-
3658	1N43	70V, 40mA	AA 117...118, AA 132...134, 1N34, 1N54
3659	1N4300(A,B)	11,3V, 5%, 10W	-
3660	1N4301(A,B)	8,8V, 5%, 50W	-
3661	1N4302(A,B)	8,8V, 5%, 50W	-
3662	1N4303(A,B)	11,3V, 5%, 50W	-
3663	1N4304(A,B)	11,3V, 5%, 50W	-
3664	1N4305	75V, 0,1A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3665	1N4306	2x SS, 75V, 0,2A, <4ns	-
3666	1N4308	100V, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3667	1N4309	50V, <2ns	BAW 24...27
3668	1N431(B)	68..75V, 10mA	BA 147/100, BA 188, 1N5194...96
3669	1N4310	75V, <2ns	BAW 26...27
3670	1N4311	100V, <2ns	BAV 14
3671	1N4312	150V, <2ns	BAV 14
3672	1N4313	100V, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3673	1N4314	1N4308	1N4308
3674	1N4315	1N4309	1N4309
3675	1N4316	1N4310	1N4310
3676	1N4317	1N4311	1N4311
3677	1N4318	1N4312	1N4312
3678	1N4319	1N4313	1N4313
3679	1N4321	50V, 10%, 3W	BZT03/C51, BZV40/C51, BZV48/C51
3680	1N4322	75V, <6ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3681	1N4323	6,8V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5921...56
3682	1N4323A...4358A	1N4323..4358, 10%	
3683	1N4323B...4358B	1N4323..4358, 5%	
3684	1N4324	1N4323, 7,5V	
3685	1N4325	1N4323, 8,2V	
3686	1N4326	1N4323, 9,1V	
3687	1N4327	1N4323, 10V	
3688	1N4328	1N4323, 11V	
3689	1N4329	1N4323, 12V	

3690	1N4330	1N4323, 13V	
3691	1N4331	1N4323, 15V	
3692	1N4332	1N4323, 16V	
3693	1N4333	1N4323, 18V	
3694	1N4334	1N4323, 20V	
3695	1N4335	1N4323, 22V	
3696	1N4336	1N4323, 24V	
3697	1N4337	1N4323, 27V	
3698	1N4338	1N4323, 30V	
3699	1N4339	1N4323, 33V	
3700	1N4340	1N4323, 36V	
3701	1N4341	1N4323, 39V	
3702	1N4342	1N4323, 43V	
3703	1N4343	1N4323, 47V	
3704	1N4344	1N4323, 51V	
3705	1N4345	1N4323, 56V	
3706	1N4346	1N4323, 62V	
3707	1N4347	1N4323, 68V	
3708	1N4348	1N4323, 75V	
3709	1N4349	1N4323, 82V	
3710	1N4350	1N4323, 91V	
3711	1N4351	1N4323, 100V	
3712	1N4352	1N4323, 110V	
3713	1N4353	1N4323, 120V	
3714	1N4354	1N4323, 130V	
3715	1N4355	1N4323, 150V	
3716	1N4356	1N4323, 160V	
3717	1N4357	1N4323, 180V	
3718	1N4358	1N4323, 200V	
3719	1N4359	200V	-
3720	1N4360	2,4V, 5%, 0,25W	BZX55/C2V4, BZX79/C2V4, 1N5221
3721	1N4361	900V, 0,5A	BY 127, BY 133, BY 227, 1N4007
3722	1N4362	0,65V(1mA), 0,4W	BZ102/0V7, BZX55/C0V8, ZPD1
3723	1N4363	120V, 0,1A, <40ns	BA 197...198, BAV 19...21, 1N3070
3724	1N4364	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
3725	1N4364R...4369R	1N4364..4369	1N4364...4369
3726	1N4365	1N4364, 200V	BY 126...127, BY 133...134, 1N4003...07
3727	1N4366	1N4364, 300V	BY 126...127, BY 133...134, 1N4004...07
3728	1N4367	1N4364, 400V	BY 126...127, BY 133...134, 1N4004...07
3729	1N4368	1N4364, 500V	BY 126...127, BY 133...134, 1N4005...07
3730	1N4369	1N4364, 600V	BY 126...127, BY 133...134, 1N4005...07
3731	1N4370	2,4V, 10%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5221...25
3732	1N4370A...4372A	1N4370..4372, 5%	
3733	1N4371	1N4370, 2,7V	
3734	1N4372	1N4370, 3V	

3735	1N4374	1500V, 0,75A	BY 269, BY 350/1500, DM 513, GP 10W
3736	1N4375	60V, <6ns	BA 218, BAX 13, BAX 91, 1N4148...49
3737	1N4376	10V, 0,05A, <6ns	BAY 82, 1N4244
3738	1N4379		-
3739	1N4380	50V, 0,05A, <1,8ns	-
3740	1N4381	25V, <100ns	AAZ 27, AAZ 18, 1N3592
3741	1N4382	55V, <5,5ns	BAW 76
3742	1N4383(GP)	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
3743	1N4384(GP)	1N4383, 400V	BY 126...127, BY 133...134, 1N4004...07
3744	1N4385(GP)	1N4383, 600V	BY 126...127, BY 133...134, 1N4003...07
3745	1N4386	PQ>32,5W(150MHz)	-
3746	1N4387	PQ>15W(450MHz)	-
3747	1N4388	PQ>11W(1000MHz)	-
3748	1N4389	5V	-
3749	1N4390	20V, <0,5ns	-
3750	1N4391	20V, <0,5ns	-
3751	1N4392	15V, <0,5ns	-
3752	1N4393(A,B)		-
3753	1N4394(A,B)		-
3754	1N4395(A,B)		-
3755	1N4396(A,B)		-
3756	1N4397(A,B)		-
3757	1N4398(A,B)		-
3758	1N4399(A,B)		-
3759	1N44	115V, 35mA	AA 117...118, AA 132...134, 1N34, 1N54
3760	1N440(B)	100V, 0,3..0,75A	BY 126...127, BY 133...135, 1N4002...07
3761	1N4400	6,8V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5921...56
3762	1N4400A...4435A	1N4400..4435, 10%	
3763	1N4400B...4435B	1N4400..4435, 5%	
3764	1N4401	1N4400, 7,5V	
3765	1N4402	1N4400, 8,2V	
3766	1N4403	1N4400, 9,1V	
3767	1N4404	1N4400, 10V	
3768	1N4405	1N4400, 11V	
3769	1N4406	1N4400, 12V	
3770	1N4407	1N4400, 13V	
3771	1N4408	1N4400, 15V	
3772	1N4409	1N4400, 16V	
3773	1N441(B)	1N440(B), 200V	BY 126...127, BY 133...134, 1N4003...07
3774	1N4410	1N4400, 18V	
3775	1N4411	1N4400, 20V	
3776	1N4412	1N4400, 22V	
3777	1N4413	1N4400, 24V	
3778	1N4414	1N4400, 27V	
3779	1N4415	1N4400, 30V	

3780	1N4416	1N4400, 33V	
3781	1N4417	1N4400, 36V	
3782	1N4418	1N4400, 39V	
3783	1N4419	1N4400, 43V	
3784	1N442(B)	1N440(B), 300V	BY 126...127, BY 133...134, 1N4004...07
3785	1N4420	1N4400, 47V	
3786	1N4421	1N4400, 51V	
3787	1N4422	1N4400, 56V	
3788	1N4423	1N4400, 62V	
3789	1N4424	1N4400, 68V	
3790	1N4425	1N4400, 75V	
3791	1N4426	1N4400, 82V	
3792	1N4427	1N4400, 91V	
3793	1N4428	1N4400, 100V	
3794	1N4429	1N4400, 110V	
3795	1N443(B)	1N440(B), 400V	BY 126...127, BY 133...134, 1N4004...07
3796	1N4430	1N4400, 120V	
3797	1N4431	1N4400, 130V	
3798	1N4432	1N4400, 150V	
3799	1N4433	1N4400, 160V	
3800	1N4434	1N4400, 180V	
3801	1N4435	1N4400, 200V	
3802	1N444(B)	1N440(B), 500V	BY 126...127, BY 133...134, 1N4005...07
3803	1N4441	1500V, 25mA, <300ns	BY 203/16, BY 269, SHG 1,5
3804	1N4442	30V, 1ns	BA 218, BAX 13, BAX 91, 1N4148...49
3805	1N4444	70V, 0,225A, <7ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3806	1N4445	125V, <4ns	BA 219, BAX 96
3807	1N4446	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3808	1N4447	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3809	1N4448	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3810	1N4449	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3811	1N445(B)	1N440(B), 600V	BY 126...127, BY 133...134, 1N4005...07
3812	1N4450	30V, 0,2A, <4ns	BA 221, BAY 74, 1N4148...49, 1N4154
3813	1N4451	30V, 0,2A, <10ns	BA 221, BAY 74, 1N4148...49, 1N4154
3814	1N4452	40V, <20ns	BAV 15...16, BAV 44, BAW 24...27
3815	1N4453	0,8V(10mA), 0,5W	BA220, BZ102/0V7, BZX55/C0V8, ZPD1
3816	1N4454	50V, 0,2A, <10ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3817	1N4455	50V	BA 128, BA 147/50, BA 222, 1N5194
3818	1N4456	35V, <1,5ns	-
3819	1N4457	50V, <1,5ns	-
3820	1N4458	800V, 5A(Tc150°)	BYX 38/900, BYX 39/800
3821	1N4458R...4459R	1N4458..4459	BYX 38/...R, BYX 39/...R
3822	1N4459	1N4458, 1000V	BYX 38/1200, BYX 39/1000
3823	1N4460	6,2V, 5%, 1,5W	BZV47/..., BZY97/..., ZY..., 1N5920...56
3824	1N4461	1N4460, 6,8V	

3825	1N4462	1N4460, 7,5V	
3826	1N4463	1N4460, 8,2V	
3827	1N4464	1N4460, 9,1V	
3828	1N4465	1N4460, 10V	
3829	1N4466	1N4460, 11V	
3830	1N4467	1N4460, 12V	
3831	1N4468	1N4460, 13V	
3832	1N4469	1N4460, 15V	
3833	1N447	40V, 60mA	AA 117...118, AA 132...134, 1N34, 1N54
3834	1N4470	1N4460, 16V	
3835	1N4471	1N4460, 18V	
3836	1N4472	1N4460, 20V	
3837	1N4473	1N4460, 22V	
3838	1N4474	1N4460, 24V	
3839	1N4475	1N4460, 27V	
3840	1N4476	1N4460, 30V	
3841	1N4477	1N4460, 33V	
3842	1N4478	1N4460, 36V	
3843	1N4479	1N4460, 39V	
3844	1N448	100V, 60mA	AA 117...118, AA 132...133
3845	1N4480	1N4460, 43V	
3846	1N4481	1N4460, 47V	
3847	1N4482	1N4460, 51V	
3848	1N4483	1N4460, 56V	
3849	1N4484	1N4460, 62V	
3850	1N4485	1N4460, 68V	
3851	1N4486	1N4460, 75V	
3852	1N4487	1N4460, 82V	
3853	1N4488	1N4460, 91V	
3854	1N4489	1N4460, 100V	
3855	1N449	40V, 60mA	AA 117...118, AA 132...134, 1N34, 1N54
3856	1N4490	1N4460, 110V	
3857	1N4491	1N4460, 120V	
3858	1N4492	1N4460, 130V	
3859	1N4493	1N4460, 150V	
3860	1N4494	1N4460, 160V	
3861	1N4495	1N4460, 180V	
3862	1N4496	1N4460, 200V	
3863	1N4499	6,2V, 5%, 1W	BZW22/C6V2, BZX61/C6V2, ZPY6,2, 1N5920
3864	1N45	75V, 35mA	AA 113, AA 117...118, 1N34, 1N60
3865	1N450	100V, 60mA	AA 117...118, AA 132...133
3866	1N4500	80V, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3867	1N4501	7V, 5%, 0,21W	-
3868	1N4502	20V	AA 117...119, AA 132...134, 1N34, 1N54
3869	1N4503	33V, 10%, 3W	BZT 03/C,D33

3870	1N4504	200V, 10%, 3W	BZT 03/C,D200
3871	1N4505	6kV, 0,1A	BYX 90, 1N5183
3872	1N4506	200V, 12A(Tc135°)	BYX 25/600
3873	1N4507	1N4506, 400V	BYX 25/600
3874	1N4508	1N4506, 600V	BYX 25/600
3875	1N4509	1N4506, 800V	BYX 25/800
3876	1N451	175V, 60mA	1N39
3877	1N4510	1N4506, 1000V	BYX 25/1000
3878	1N4511	1N4506, 1200V	BYX 25/1200
3879	1N4512	10V	BA 128, BA 147/25, BA 222, 1N5194
3880	1N4513	2000V, 0,25A	BAY 91, BY 203/20, HVG 2, SHG 2
3881	1N4514	800V, 1,1A	BY 127, BY 133, BY 227, 1N4006...07
3882	1N4517	200V, 2A	BY 251...255, BY 259/300, 1N5060...62
3883	1N452	35V	AA 136
3884	1N4523	15V, <8ns	AAAY 21
3885	1N4524	10V, <3ns	1N995
3886	1N4525	200V, 35A(Tc115°)	BYX 56/600
3887	1N4526	1N4525, 400V	BYX 56/600
3888	1N4527	1N4525, 600V	BYX 56/600
3889	1N4528	1N4525, 800V	BYX 56/800
3890	1N4529	1N4525, 1000V	BYX 56/1000
3891	1N453	115V	1N270
3892	1N4530	1N4525, 1200V	BYX 56/1200
3893	1N4531	75V, 0,15A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3894	1N4532	75V, 0,15A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3895	1N4533	40V, 0,075A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3896	1N4534	75V, 0,075A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
3897	1N4535	3,45V, 5%, 0,5W	-
3898	1N4536	25V, 0,075A, <2ns	BA 218, BAX 13, BAX 91, 1N4148...49
3899	1N4537	1800V, 3A	-
3900	1N4538	1N4537, 2400V	-
3901	1N4539	1N4537, 3000V	-
3902	1N454	60V	AA 136, 1N270
3903	1N4540	1N4537, 3600V	-
3904	1N4541	225V, 0,4A	BA 157...159, BY 204/4, BY 206...207
3905	1N4542	1N4541, 400V	BA 157...159, BY 204/4, BY 207
3906	1N4543	1N4541, 600V	BA 158...159, BY 204/8, BY 207
3907	1N4544	1N4541, 800V	BA 159, BY 204/8, BY 208/800
3908	1N4545	1N4541, 1000V	BA 159, BY 204/10, BY 208/1000
3909	1N4548	25V, <2ns	BA 217, BA 317, BAY 71, 1N4148...49
3910	1N4549	3,9V, 20%, 50W(Tc75°)	-
3911	1N4549A...4556A	1N4549..4556, 10%	
3912	1N4549B...4556B	1N4549..4556, 5%	
3913	1N4549R...4556R	1N4549..4556	
3914	1N455	35V	AA 136, AA 139, 1N270



3915	1N4550	1N4549, 4,3V	
3916	1N4551	1N4549, 4,7V	
3917	1N4552	1N4549, 5,1V	
3918	1N4553	1N4549, 5,6V	
3919	1N4554	1N4549, 6,2V	
3920	1N4555	1N4549, 6,8V	
3921	1N4556	1N4549, 7,5V	
3922	1N4557	3,9V, 20%, 50W(Tc75°)	-
3923	1N4557A...4564A	1N4557..4564, 10%	
3924	1N4557B...4564B	1N4557..4564, 5%	
3925	1N4557R...4564R	1N4557..4564	
3926	1N4558	1N4557, 4,3V	
3927	1N4559	1N4557, 4,7V	
3928	1N456(A)	35V, 0,09..0,2A	BA 127, BA 187...190, BA 215, 1N484A
3929	1N4561	1N4557, 5,6V	
3930	1N4562	1N4557, 6,2V	
3931	1N4563	1N4557, 6,8V	
3932	1N4564	1N4557, 7,5V	
3933	1N4565(A,B)	6,4V, 5%, 0,4W	BZV 10, BZV 27, BZX 90
3934	1N4566(A,B)	6,4V, 5%, 0,4W	BZV 11, BZV 28, BZX 91
3935	1N4567(A,B)	6,4V, 5%, 0,4W	BZV 12, BZV 29, BZX 92
3936	1N4568(A,B)	6,4V, 5%, 0,4W	BZV 13, BZV 30, BZX 93
3937	1N4569(A,B)	6,4V, 5%, 0,4W	BZV 14, BZV 31, BZX 94
3938	1N457(A)	75V, 0,075..0,2A	BA 188...190, BAY 45, BAY 73, 1N484A
3939	1N4570(A,B)	6,4V, 5%, 0,4W	
3940	1N4571(A,B)	6,4V, 5%, 0,4W	
3941	1N4572(A,B)	6,4V, 5%, 0,4W	
3942	1N4573(A,B)	6,4V, 5%, 0,4W	
3943	1N4574(A,B)	6,4V, 5%, 0,4W	
3944	1N4575(A,B)	6,4V, 5%, 0,4W	
3945	1N4576(A,B)	6,4V, 5%, 0,4W	
3946	1N4577(A,B)	6,4V, 5%, 0,4W	
3947	1N4578(A,B)	6,4V, 5%, 0,4W	
3948	1N4579(A,B)	6,4V, 5%, 0,4W	
3949	1N458(A)	150V, 0,055..0,2A	BA 189...190, BAY 45, BAW 52, 1N484A
3950	1N4580(A,B)	6,4V, 5%, 0,4W	
3951	1N4581(A,B)	6,4V, 5%, 0,4W	
3952	1N4582(A,B)	6,4V, 5%, 0,4W	
3953	1N4583(A,B)	6,4V, 5%, 0,4W	
3954	1N4584(A,B)	6,4V, 5%, 0,4W	
3955	1N4585(GP)	800V, 1A	BY 127, BY 133, BY 227, 1N4006...07
3956	1N4586(GP)	1N4585, 1000V	BY 127, BY 133, BY 227, 1N4007
3957	1N4587	100V, 150A(Tc110°)	-
3958	1N4587R...4596R	1N4587..4596	-
3959	1N4588	1N4587, 200V	-



3960	1N4589	1N4587, 300V	-
3961	1N459(A)	200V, 0,04..0,2A	BA 190, BAY 46, BAW 52, BAY 20...21
3962	1N4590	1N4587, 400V	-
3963	1N4591	1N4587, 500V	-
3964	1N4592	1N4587, 600V	-
3965	1N4593	1N4587, 800V	-
3966	1N4594	1N4587, 1000V	-
3967	1N4595	1N4587, 1200V	-
3968	1N4596	1N4587, 1400V	-
3969	1N4598(A)	90V	-
3970	1N4599(A)	110V	-
3971	1N46	60V, 40mA	AA 117...118, AA 132...134, 1N34, 1N54
3972	1N4606	85V, 0,35A, <6ns	BAV 10, BAW 55, BAW 76, BAX 81
3973	1N4607	85V, 0,35A, <15ns	BAV 10, BAW 55, BAW 76, BAX 81
3974	1N4608	85V, 0,35A, <15ns	BAV 10, BAW 55, BAW 76, BAX 81
3975	1N4609(A)		-
3976	1N461(A)	30V, 0,06..0,2A	BA 127, BA 187...190, BA 215, 1N484A
3977	1N4610	80V, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
3978	1N4611(A,B,C)	6,6V, 5%, 0,25W	BZV 11...14, BZV 28...31, 1N4575...84
3979	1N4612(A,B,C)	6,6V, 5%, 0,25W	
3980	1N4613(A,B,C)	6,6V, 5%, 0,25W	
3981	1N4614	1,8V, 5%, 0,25W	-
3982	1N4615	1N4614, 2V	-
3983	1N4616	1N4614, 2,2V	-
3984	1N4617	1N4614, 2,4V	-
3985	1N4618	1N4614, 2,7V	-
3986	1N4619	1N4614, 3V	-
3987	1N462(A)	70V, 0,05..0,2A	BA 127, BA 188...190, BA 215, 1N484A
3988	1N4620	1N4614, 3,3V	-
3989	1N4621	1N4614, 3,6V	-
3990	1N4622	1N4614, 3,9V	-
3991	1N4623	1N4614, 4,3V	-
3992	1N4624	1N4614, 4,7V	-
3993	1N4625	1N4614, 5,1V	-
3994	1N4626	1N4614, 5,6V	-
3995	1N4627	1N4614, 6,2V	-
3996	1N4628	6,8V, 5%, 0,6W	BZX55/..., BZX83/..., ZPD..., 1N5235...61
3997	1N4629	1N4628, 7,5V	
3998	1N463(A)	200V, 0,03..0,2A	BA 190, BAW 52, BAY 46, BAY 21
3999	1N4630	1N4628, 8,2V	
4000	1N4631	1N4628, 9,1V	
4001	1N4632	1N4628, 10V	
4002	1N4633	1N4628, 11V	
4003	1N4634	1N4628, 12V	
4004	1N4635	1N4628, 13V	

4005	1N4636	1N4628, 15V	
4006	1N4637	1N4628, 16V	
4007	1N4638	1N4628, 18V	
4008	1N4639	1N4628, 20V	
4009	1N464(A)	150V, 0,04..0,2A	BA 189...190, BAW 52, BAY 45, 1N484A
4010	1N4640	1N4628, 22V	
4011	1N4641	1N4628, 24V	
4012	1N4642	1N4628, 27V	
4013	1N4643	1N4628, 30V	
4014	1N4644	1N4628, 33V	
4015	1N4645	1N4628, 36V	
4016	1N4646	1N4628, 39V	
4017	1N4647	1N4628, 43V	
4018	1N4648	1N4628, 47V	
4019	1N4649	3,3V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...41
4020	1N465	2,6V, 10%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5221...36
4021	1N4650	1N4649, 3,6V	
4022	1N4651	1N4649, 3,9V	
4023	1N4652	1N4649, 4,3V	
4024	1N4653	1N4649, 4,7V	
4025	1N4654	1N4649, 5,1V	
4026	1N4655	1N4649, 5,6V	
4027	1N4656	1N4649, 6,2V	
4028	1N4657	1N4649, 6,8V	
4029	1N4658	1N4649, 7,5V	
4030	1N4659	1N4649, 8,2V	
4031	1N465B...470B	1N465..470, 1%	
4032	1N466	1N465, 3,5V	
4033	1N4660	1N4649, 9,1V	
4034	1N4661	1N4649, 10V	
4035	1N4662	1N4649, 11V	
4036	1N4663	1N4649, 12V	
4037	1N4664	1N4649, 13V	
4038	1N4665	1N4649, 15V	
4039	1N4666	1N4649, 16V	
4040	1N4667	1N4649, 18V	
4041	1N4668	1N4649, 20V	
4042	1N4669	1N4649, 22V	
4043	1N467	1N465, 4,1V	
4044	1N4670	1N4649, 24V	
4045	1N4671	1N4649, 27V	
4046	1N4672	1N4649, 30V	
4047	1N4673	1N4649, 33V	
4048	1N4674	1N4649, 36V	
4049	1N4675	1N4649, 39V	

4050	1N4676	1N4649, 43V	
4051	1N4677	1N4649, 47V	
4052	1N4678	1,8V, 5%, 0,25W	BZX79/..., BZX55/..., ZPD..., 1N5221...60
4053	1N4679	1N4678, 2V	
4054	1N468	1N465, 4,85V	
4055	1N4680	1N4678, 2,2V	
4056	1N4681	1N4678, 2,4V	
4057	1N4682	1N4678, 2,7V	
4058	1N4683	1N4678, 3V	
4059	1N4684	1N4678, 3,3V	
4060	1N4685	1N4678, 3,6V	
4061	1N4686	1N4678, 3,9V	
4062	1N4687	1N4678, 4,3V	
4063	1N4688	1N4678, 4,7V	
4064	1N4689	1N4678, 5,1V	
4065	1N469	1N465, 5,8V	
4066	1N4690	1N4678, 5,6V	
4067	1N4691	1N4678, 6,2V	
4068	1N4692	1N4678, 6,8V	
4069	1N4693	1N4678, 7,5V	
4070	1N4694	1N4678, 8,2V	
4071	1N4695	1N4678, 8,7V	
4072	1N4696	1N4678, 9,1V	
4073	1N4697	1N4678, 10V	
4074	1N4698	1N4678, 11V	
4075	1N4699	1N4678, 12V	
4076	1N47	150V, 30mA	AA 133, 1N39
4077	1N470	1N465, 7,1V	
4078	1N4700	1N4678, 13V	
4079	1N4701	1N4678, 14V	
4080	1N4702	1N4678, 15V	
4081	1N4703	1N4678, 16V	
4082	1N4704	1N4678, 17V	
4083	1N4705	1N4678, 18V	
4084	1N4706	1N4678, 19V	
4085	1N4707	1N4678, 20V	
4086	1N4708	1N4678, 22V	
4087	1N4709	1N4678, 24V	
4088	1N471	3,5V, 10%, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5221...36
4089	1N4710	1N4678, 25V	
4090	1N4711	1N4678, 27V	
4091	1N4712	1N4678, 28V	
4092	1N4713	1N4678, 30V	
4093	1N4714	1N4678, 33V	
4094	1N4715	1N4678, 36V	

4095	1N4716	1N4678, 39V	
4096	1N4717	1N4678, 43V	
4097	1N4718	50V, <180ns	BYT 52A, BYX 92/50, MR 810, RGP 10A
4098	1N4719	50V, 3A	BY 396...399, RGP 30A, BY 205/100
4099	1N4719R...4725R	1N4719..4725	1N4719...4725
4100	1N471B...475B	1N471..475, 1%	
4101	1N472	1N471, 4,1V	
4102	1N4720	1N4719, 100V	BY 396...399, RGP 30B, BY 205/100
4103	1N4721	1N4719, 200V	BY 397...399, RGP 30D, BY 205/200
4104	1N4722	1N4719, 400V	BY 398...399, RGP 30G, BY 205/400
4105	1N4723	1N4719, 600V	BY 228, BY 399, RGP 30J, BY 205/600
4106	1N4724	1N4719, 800V	BY 228, BY 399, RGP 30K, BY 205/800
4107	1N4725	1N4719, 1000V	BY 228, BY 438, RGP 30M, BY 206/1000
4108	1N4726	20V, 0,06A	-
4109	1N4727	20V, 0,075A	-
4110	1N4728	3,3V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...49
4111	1N4728A...4764A	1N4728..4764, 5%	
4112	1N4729	1N4728, 3,6V	
4113	1N473	1N471, 4,85V	
4114	1N4730	1N4728, 3,9V	
4115	1N4731	1N4728, 4,3V	
4116	1N4732	1N3728, 4,7V	
4117	1N4733	1N4728, 5,1V	
4118	1N4734	1N4728, 5,6V	
4119	1N4735	1N4728, 6,2V	
4120	1N4736	1N4728, 6,8V	
4121	1N4737	1N4728, 7,5V	
4122	1N4738	1N4728, 8,2V	
4123	1N4739	1N4728, 9,1V	
4124	1N474	1N471, 5,8V	
4125	1N4740	1N4728, 10V	
4126	1N4741	1N4728, 11V	
4127	1N4742	1N4728, 12V	
4128	1N4743	1N4728, 13V	
4129	1N4744	1N4728, 15V	
4130	1N4745	1N4728, 16V	
4131	1N4746	1N4728, 18V	
4132	1N4747	1N4728, 20V	
4133	1N4748	1N4728, 22V	
4134	1N4749	1N4728, 24V	
4135	1N475	1N471, 7,1V	
4136	1N4750	1N4728, 27V	
4137	1N4751	1N4728, 30V	
4138	1N4752	1N4728, 33V	
4139	1N4753	1N4728, 36V	

4140	1N4754	1N4728, 39V	
4141	1N4755	1N4728, 43V	
4142	1N4756	1N4728, 47V	
4143	1N4757	1N4728, 51V	
4144	1N4758	1N4728, 56V	
4145	1N4759	1N4728, 62V	
4146	1N476	90V, 50mA	AA 117...118, AA 132...133
4147	1N4760	1N4728, 68V	
4148	1N4761	1N4728, 75V	
4149	1N4762	1N4728, 82V	
4150	1N4763	1N4728, 91V	
4151	1N4764	1N4728, 100V	
4152	1N4765(A,B)	9,1V, 5%, 0,25W	1N935
4153	1N4766(A,B)	9,1V, 5%, 0,25W	1N936
4154	1N4767(A,B)	9,1V, 5%, 0,25W	1N937
4155	1N4768(A,B)	9,1V, 5%, 0,25W	1N938
4156	1N4769(A,B)	9,1V, 5%, 0,25W	1N939
4157	1N477	90V, 50mA	AA 117...118, AA 132...133
4158	1N4770(A,B)	9,1V, 5%, 0,25W	
4159	1N4771(A,B)	9,1V, 5%, 0,25W	
4160	1N4772(A,B)	9,1V, 5%, 0,25W	
4161	1N4773(A,B)	9,1V, 5%, 0,25W	
4162	1N4774(A,B)	9,1V, 5%, 0,25W	
4163	1N4775(A,B)	8,5V, 5%, 0,25W	1N3154
4164	1N4776(A,B)	8,5V, 5%, 0,25W	1N3155
4165	1N4777(A,B)	8,5V, 5%, 0,25W	1N3156
4166	1N4778(A,B)	8,5V, 5%, 0,25W	1N3157
4167	1N4779(A,B)	8,5V, 5%, 0,25W	-
4168	1N478	90V, 50mA	AA 117...118, AA 132...133
4169	1N4780(A,B)	8,5V, 5%, 0,25W	1N3154
4170	1N4781(A,B)	8,5V, 5%, 0,25W	1N3155
4171	1N4782(A,B)	8,5V, 5%, 0,25W	1N3156
4172	1N4783(A,B)	8,5V, 5%, 0,25W	1N3157
4173	1N4784(A,B)	8,5V, 5%, 0,25W	-
4174	1N4785	320V, 7A	AY 102
4175	1N4786(A...D)		-
4176	1N4787(A...D)		-
4177	1N4788(A...D)		-
4178	1N4789(A...D)		-
4179	1N479	90V, 50mA	AA 117...118, AA 132...133
4180	1N4790(A...D)		-
4181	1N4791(A...D)		-
4182	1N4792(A...D)		-
4183	1N4793(A...D)		-
4184	1N4794(A...D)		-

4185	1N4795(A...D)		-
4186	1N4796(A...D)		-
4187	1N4797(A...D)		-
4188	1N4798(A...D)		-
4189	1N4799(A...D)		-
4190	1N48	80V, 50mA	AA 117...118, AA 132...133
4191	1N480	60V, 35mA, <500ns	AAZ 28, AAZ 15, AAZ 17, 1N276
4192	1N4800(A...D)		-
4193	1N4801(A...D)		-
4194	1N4802(A...D)		-
4195	1N4803(A...D)		-
4196	1N4804(A...D)		-
4197	1N4805(A...D)		-
4198	1N4806(A...D)		-
4199	1N4807(A...D)		-
4200	1N4808(A...D)		-
4201	1N4809(A...D)		-
4202	1N4810(A...D)		-
4203	1N4811(A...D)		-
4204	1N4812(A...D)		-
4205	1N4813(A...D)		-
4206	1N4814(A...D)		-
4207	1N4815(A...D)		-
4208	1N4816(A)	50V, 1,5A	BY 226...227, BY 251...255, 1N5391...99
4209	1N4817(A)	1N4816, 100V	BY 226...227, BY 251...255, 1N5392...99
4210	1N4818(A)	1N4816, 200V	BY 226...227, BY 251...255, 1N5393...99
4211	1N4819(A)	1N4816, 300V	BY 226...227, BY 252...255, 1N5394...99
4212	1N482(A...C)	40V, 0.1..0.2A	BA 127, BA 187...190, BA 215, BAY 45
4213	1N4820(A)	1N4816, 400V	BY 226...227, BY 252...255, 1N5395...99
4214	1N4821(A)	1N4816, 500V	BY 226...227, BY 253...255, 1N5396...99
4215	1N4822(A)	1N4816, 600V	BY 226...227, BY 253...255, 1N5397...99
4216	1N4823	100V, 1A, <100ns	BYV 12...16, BYX 92/100, EGP 10B
4217	1N4824	1N4823, 200V	BYV 13...16, BYX 92/200, EGP 10D
4218	1N4825	1N4823, 400V	BYT 52G, BYV 13...16, BYX 92/400
4219	1N4826	1N4823, 600V	BYT 52J, BYV 14...16, BYV 36C
4220	1N4827	30V, 200ns	AAZ 28, 1N631, 1N633
4221	1N4828	1,1V(100mA), 0,4W	-
4222	1N4829	1N4828, 1,87V(100mA)	-
4223	1N483(A...C)	1N482(A..C), 80V	BA 188...190, BAW 52, BAY 19, BAY 45
4224	1N4830	1N4828, 2,69V(100mA)	-
4225	1N4831	9,1V, 20%, 1,2W	-
4226	1N4831A...4860A	1N4831..4860, 10%	
4227	1N4831B...4860B	1N4831..4860, 5%	
4228	1N4832	1N4831, 10V	
4229	1N4833	1N4831, 11V	

4230	1N4834	1N4831, 12V	
4231	1N4835	1N4831, 13V	
4232	1N4836	1N4831, 15V	
4233	1N4837	1N4831, 16V	
4234	1N4838	1N4831, 18V	
4235	1N4839	1N4831, 20V	
4236	1N484(A...C)	1N482(A..C), 150V	BA 189...190, BAW 52, BAY 20, BAY 45
4237	1N4840	1N4831, 22V	
4238	1N4841	1N4831, 24V	
4239	1N4842	1N4831, 27V	
4240	1N4843	1N4831, 30V	
4241	1N4844	1N4831, 33V	
4242	1N4845	1N4831, 36V	
4243	1N4846	1N4831, 39V	
4244	1N4847	1N4831, 43V	
4245	1N4848	1N4831, 47V	
4246	1N4849	1N4831, 51V	
4247	1N485(A...C)	1N482(A..C), 200V	BA 190, BAW 52, BAY 21, BAY 46
4248	1N4850	1N4831, 56V	
4249	1N4851	1N4831, 62V	
4250	1N4852	1N4831, 68V	
4251	1N4853	1N4831, 75V	
4252	1N4854	1N4831, 82V	
4253	1N4855	1N4831, 91V	
4254	1N4856	1N4831, 100V	
4255	1N4857	1N4831, 110V	
4256	1N4858	1N4831, 120V	
4257	1N4859	1N4831, 130V	
4258	1N486(A,B)	225V, 0,1..0,2A	BA 157...159, BAY 21, BAY 46, BAY 88...90
4259	1N4860	1N4831, 150V	
4260	1N4861	40V, <1μs	BA 127, BA 147/50, BA 187...190
4261	1N4862	70V, <1μs	BA 127, BA 147/100, BA 188...190
4262	1N4863	70V, 0,2A, <7ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4263	1N4864	125V, 0,2A, <4ns	BA 203
4264	1N487(A,B)	1N486(A,B), 300V	BA 157...159, BAY 21, BAY 46, BAY 88...90
4265	1N4878	100V, 100A(Tc120°)	1N3288...97
4266	1N4879	100V, 160A(Tc120°)	1N4587...96
4267	1N488(A,B)	1N486(A,B), 380V	BA 158...159, BAY 21, BAY 88...90
4268	1N4880	250V, 160A(Tc120°)	1N3735...44
4269	1N4881	20V, 10%, 3W	BZT 03/C,D20
4270	1N4882	36V, 10%, 3W	BZT 03/C,D,36
4271	1N4883	12V, 5%, 3W	BZT 03/C12
4272	1N4884	1N4881, 5%	BZT 03/C20
4273	1N4885		-
4274	1N4886		-

4275	1N4888	12V, <0,5ns	BAY 82, 1N4244, 1N4376
4276	1N4889	62V, 5%, 5W	BZV40/C62, BZV 48/C62, 1N5372
4277	1N4890(A)	6,35V, 5%, 0,4W	-
4278	1N4891(A)	6,35V, 5%, 0,4W	-
4279	1N4892(A)	6,35V, 5%, 0,4W	-
4280	1N4893(A)	6,35V, 5%, 0,4W	-
4281	1N4894(A)	6,35V, 5%, 0,4W	-
4282	1N4895(A)	6,35V, 5%, 0,4W	-
4283	1N4896(A)	12,8V, 5%, 0,4W	-
4284	1N4897(A)	12,8V, 5%, 0,4W	-
4285	1N4898(A)	12,8V, 5%, 0,4W	-
4286	1N4899(A)	12,8V, 5%, 0,4W	-
4287	1N49	75V	AA 117...118, AA 132...133, 1N34, 1N54
4288	1N490	60V, 35mA, <500ns	AAY 28, AAZ 15, AAZ 17, 1N276
4289	1N4900(A)	12,8V, 5%, 0,4W	-
4290	1N4901(A)	12,8V, 5%, 0,4W	-
4291	1N4902(A)	12,8V, 5%, 0,4W	-
4292	1N4903(A)	12,8V, 5%, 0,4W	-
4293	1N4904(A)	12,8V, 5%, 0,4W	-
4294	1N4905(A)	12,8V, 5%, 0,4W	-
4295	1N4906(A)	12,8V, 5%, 0,4W	-
4296	1N4907(A)	12,8V, 5%, 0,4W	-
4297	1N4908(A)	12,8V, 5%, 0,4W	-
4298	1N4909(A)	12,8V, 5%, 0,4W	-
4299	1N4910(A)	12,8V, 5%, 0,4W	-
4300	1N4911(A)	12,8V, 5%, 0,4W	-
4301	1N4912(A)	12,8V, 5%, 0,4W	-
4302	1N4913(A)	12,8V, 5%, 0,4W	-
4303	1N4914(A)	12,8V, 5%, 0,4W	-
4304	1N4915(A)	12,8V, 5%, 0,4W	-
4305	1N4916(A)	19,2V, 5%, 0,4W	-
4306	1N4917(A)	19,2V, 5%, 0,4W	-
4307	1N4918(A)	19,2V, 5%, 0,4W	-
4308	1N4919(A)	19,2V, 5%, 0,4W	-
4309	1N4920(A)	19,2V, 5%, 0,4W	-
4310	1N4921(A)	19,2V, 5%, 0,4W	-
4311	1N4922(A)	19,2V, 5%, 0,4W	-
4312	1N4923(A)	19,2V, 5%, 0,4W	-
4313	1N4924(A)	19,2V, 5%, 0,4W	-
4314	1N4925(A)	19,2V, 5%, 0,4W	-
4315	1N4926(A)	19,2V, 5%, 0,4W	-
4316	1N4927(A)	19,2V, 5%, 0,4W	-
4317	1N4928(A)	19,2V, 5%, 0,4W	-
4318	1N4929(A)	19,2V, 5%, 0,4W	-
4319	1N4930(A)	19,2V, 5%, 0,4W	-



4320	1N4931(A)	19,2V, 5%, 0,4W	-
4321	1N4932(A)	19,2V, 5%, 0,4W	-
4322	1N4933(GP)	50V, 1A, <200ns	BYT 52A, BYX 92/50, EGP 10A, RGP 10A
4323	1N4934(GP)	1N4933, 100V	BYT 52B, BYX 92/100, EGP 10B, RGP 10B
4324	1N4935(GP)	1N4933, 200V	BYT 52D, BYX 92/200, EGP 10D, RGP 10D
4325	1N4936(GP)	1N4933, 400V	BY 201/4, BYT 52G, BYX 92/400, RGP 10G
4326	1N4937(GP)	1N4933, 600V	BY 201/6, BYT 52J, BYX 92/600, RGP 10J
4327	1N4938	1N3070	1N3070
4328	1N4942(GP)	200V, 1A, <150ns	BYT 52D, BYX 92/200, EGP 10D, RGP 10D
4329	1N4943(GP)	1N4942, 300V	BYT 52G, BYX 92/300, RGP 10G
4330	1N4944(GP)	1N4942, 400V	BYT 52G, BYX 92/400, RGP 10G
4331	1N4945(GP)	1N4942, 500V	BY 201/6, BYT 52J, RGP 10J
4332	1N4946(GP)	1N4942, 600V, <250ns	BY 201/6, BYT 52J, RGP 10J
4333	1N4947(GP)	1N4942, 800V, <250ns	BYV 15...16, BYT 52K, RGP 10K
4334	1N4948(GP)	1N4942, 1000V, <500ns	BYV 16, BYV 38, BYT 52M, RGP 10M
4335	1N4949	35V, <0,3ns	-
4336	1N4950	30V, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
4337	1N4951	20V, 25mA	-
4338	1N4952	1N4951, 50V	-
4339	1N4954	6,8V, 5%, 5W	BZV 40/..., BZV 48/..., 1N5342...5388
4340	1N4954A...4996A	1N4954..4996, 10%	
4341	1N4954B...4996B	1N4954..4996, 20%	
4342	1N4955	1N4954, 7,5V	
4343	1N4956	1N4954, 8,2V	
4344	1N4957	1N4954, 9,1V	
4345	1N4958	1N4954, 10V	
4346	1N4959	1N4954, 11V	
4347	1N4960	1N4954, 12V	
4348	1N4961	1N4954, 13V	
4349	1N4962	1N4954, 15V	
4350	1N4963	1N4954, 16V	
4351	1N4964	1N4954, 18V	
4352	1N4965	1N4954, 20V	
4353	1N4966	1N4954, 22V	
4354	1N4967	1N4954, 24V	
4355	1N4968	1N4954, 27V	
4356	1N4969	1N4954, 30V	
4357	1N497	25V, 80mA	AA 135...136, 1N270
4358	1N4970	1N4954, 33V	
4359	1N4971	1N4954, 36V	
4360	1N4972	1N4954, 39V	
4361	1N4973	1N4954, 43V	
4362	1N4974	1N4954, 47V	
4363	1N4975	1N4954, 51V	
4364	1N4976	1N4954, 56V	

4365	1N4977	1N4954, 62V	
4366	1N4978	1N4954, 68V	
4367	1N4979	1N4954, 75V	
4368	1N498	46V, 70mA	AA 136, 1N270
4369	1N4980	1N4954, 82V	
4370	1N4981	1N4954, 91V	
4371	1N4982	1N4954, 100V	
4372	1N4983	1N4954, 110V	
4373	1N4984	1N4954, 120V	
4374	1N4985	1N4954, 130V	
4375	1N4986	1N4954, 150V	
4376	1N4987	1N4954, 160V	
4377	1N4988	1N4954, 180V	
4378	1N4989	1N4954, 200V	
4379	1N499	62V, 80mA	AA 136, 1N270
4380	1N4990	1N4954, 220V	
4381	1N4991	1N4954, 240V	
4382	1N4992	1N4954, 270V	
4383	1N4993	1N4954, 300V	
4384	1N4994	1N4954, 330V	
4385	1N4995	1N4954, 360V	
4386	1N4996	1N4954, 390V	
4387	1N50	75V	AA 117...118, AA 132...133, 1N34, 1N54
4388	1N500	70V, 80mA	1N270
4389	1N5004	100V, 1A	BY 126...127, BY 133...134, 1N4002...07
4390	1N5005	1N5004, 200V	BY 126...127, BY 133...134, 1N4003...07
4391	1N5006	1N5004, 400V	BY 126...127, BY 133...134, 1N4004...07
4392	1N5007	1N5004, 600V	BY 126...127, BY 133...134, 1N4005...07
4393	1N5008	3,3V, 10%, 2,5W	BZD 23/..., BZT 03/..., BZX 70/...
4394	1N5008A...5051A	1N5008..5051, 5%	
4395	1N5009	1N5008, 3,6V	
4396	1N501	92V, 80mA	1N270
4397	1N5010	1N5008, 3,9V	
4398	1N5011	1N5008, 4,3V	
4399	1N5012	1N5008, 4,7V	
4400	1N5013	1N5008, 5,1V	
4401	1N5014	1N5008, 5,6V	
4402	1N5015	1N5008, 6,2V	
4403	1N5016	1N5008, 6,8V	
4404	1N5017	1N5008, 7,5V	
4405	1N5018	1N5008, 8,2V	
4406	1N5019	1N5008, 9,1V	
4407	1N502	115V, 70mA	1N270
4408	1N5020	1N5008, 10V	
4409	1N5021	1N5008, 11V	

4410	1N5022	1N5008, 12V	
4411	1N5023	1N5008, 13V	
4412	1N5024	1N5008, 14V	
4413	1N5025	1N5008, 15V	
4414	1N5026	1N5008, 16V	
4415	1N5027	1N5008, 17V	
4416	1N5028	1N5008, 18V	
4417	1N5029	1N5008, 19V	
4418	1N5030	1N5008, 20V	
4419	1N5031	1N5008, 22V	
4420	1N5032	1N5008, 24V	
4421	1N5033	1N5008, 25V	
4422	1N5034	1N5008, 27V	
4423	1N5035	1N5008, 30V	
4424	1N5036	1N5008, 33V	
4425	1N5037	1N5008, 36V	
4426	1N5038	1N5008, 39V	
4427	1N5039	1N5008, 43V	
4428	1N5040	1N5008, 45V	
4429	1N5041	1N5008, 47V	
4430	1N5042	1N5008, 50V	
4431	1N5043	1N5008, 51V	
4432	1N5044	1N5008, 52V	
4433	1N5045	1N5008, 56V	
4434	1N5046	1N5008, 62V	
4435	1N5047	1N5008, 68V	
4436	1N5048	1N5008, 75V	
4437	1N5049	1N5008, 82V	
4438	1N5050	1N5008, 91V	
4439	1N5051	1N5008, 100V	
4440	1N5052(A)	700V, 1,5A	BY 227, BYX 85...86, GP 15K, 1N5398...99
4441	1N5053(A)	1N5052, 800V	BY 227, BYX 85...86, GP 15K, 1N5398...99
4442	1N5054(A)	1N5052, 1000V	BY 227, BYX 86, GP 15M, 1N5399
4443	1N5055	100V, 1A	BY 126...127, BY 133...135, 1N4002...07
4444	1N5056	1N5055, 200V	BY 126...127, BY 133...134, 1N4003...07
4445	1N5057	1N5055, 300V, 0,8A	BY 126...127, BY 133...134, 1N4004...07
4446	1N5058	1N5055, 400V, 0,8A	BY 126...127, BY 133...134, 1N4004...07
4447	1N5059(GP)	200V, 2A	BYD 14D...M, BYW 52...56
4448	1N5060(GP)	1N5059, 400V	BYD 14G...M, BYW 53...56
4449	1N5061(GP)	1N5059, 600V	BYD 14J...M, BYW 54...56
4450	1N5062(GP)	1N5059, 800V	BYD 14K...M, BYW 55...56
4451	1N5063	6,8V, 5%, 3W	BZT 03/...
4452	1N5064	1N5063, 7,5V	
4453	1N5065	1N5063, 8,2V	
4454	1N5066	1N5063, 9,1V	

4455	1N5067	1N5063, 10V	
4456	1N5068	1N5063, 11V	
4457	1N5069	1N5063, 13V	
4458	1N5070	1N5063, 14V	
4459	1N5071	1N5063, 15V	
4460	1N5072	1N5063, 16V	
4461	1N5073	1N5063, 18V	
4462	1N5074	1N5063, 22V	
4463	1N5075	1N5063, 24V	
4464	1N5076	1N5063, 27V	
4465	1N5077	1N5063, 30V	
4466	1N5078	1N5063, 33V	
4467	1N5079	1N5063, 36V	
4468	1N5080	1N5063, 39V	
4469	1N5081	1N5063, 40V	
4470	1N5082	1N5063, 43V	
4471	1N5083	1N5063, 45V	
4472	1N5084	1N5063, 47V	
4473	1N5085	1N5063, 50V	
4474	1N5086	1N5063, 51V	
4475	1N5087	1N5063, 56V	
4476	1N5088	1N5063, 60V	
4477	1N5089	1N5063, 62V	
4478	1N5090	1N5063, 68V	
4479	1N5091	1N5063, 70V	
4480	1N5092	1N5063, 75V	
4481	1N5093	1N5063, 80V	
4482	1N5094	1N5063, 82V	
4483	1N5095	1N5063, 91V	
4484	1N5096	1N5063, 110V	
4485	1N5097	1N5063, 120V	
4486	1N5098	1N5063, 130V	
4487	1N5099	1N5063, 140V	
4488	1N51	46V, 30mA	AA 113, 1N34, 1N54, 1N60
4489	1N5100	1N5063, 160V	
4490	1N5101	1N5063, 170V	
4491	1N5102	1N5063, 180V	
4492	1N5103	1N5063, 190V	
4493	1N5104	1N5063, 200V	
4494	1N5105	1N5063, 220V	
4495	1N5106	1N5063, 240V	
4496	1N5107	1N5063, 260V	
4497	1N5108	1N5063, 270V	
4498	1N5109	1N5063, 280V	
4499	1N5110	1N5063, 300V	

4500	1N5111	1N5063, 320V	
4501	1N5112	1N5063, 330V	
4502	1N5113	1N5063, 340V	
4503	1N5114	1N5063, 360V	
4504	1N5115	1N5063, 380V	
4505	1N5116	1N5063, 390V	
4506	1N5117	1N5063, 400V	
4507	1N5118	14V, 5%, 5W	BZV 40/..., BZV 48/..., 1N5351...5388
4508	1N5119	1N5118, 40V	
4509	1N5120	1N5118, 45V	
4510	1N5121	1N5118, 50V	
4511	1N5122	1N5118, 60V	
4512	1N5123	1N5118, 70V	
4513	1N5124	1N5118, 80V	
4514	1N5125	1N5118, 90V	
4515	1N5126	1N5118, 140V	
4516	1N5127	1N5118, 170V	
4517	1N5128	1N5118, 190V	
4518	1N5129	1N5118, 260V	
4519	1N5130	1N5118, 280V	
4520	1N5131	1N5118, 320V	
4521	1N5132	1N5118, 340V	
4522	1N5133	1N5118, 380V	
4523	1N5134	1N5118, 400V	
4524	1N5136(A)		-
4525	1N5137(A)		-
4526	1N5138(A)		-
4527	1N5139(A)		-
4528	1N5140(A)		-
4529	1N5141(A)		-
4530	1N5142(A)		-
4531	1N5143(A)		-
4532	1N5144(A)		-
4533	1N5145(A)		-
4534	1N5146(A)		-
4535	1N5147(A)		-
4536	1N5148(A)		-
4537	1N5158	Ub8..10V, Ib<0,05mA, Itsm10A	-
4538	1N5159	1N5158, Ub9..11V	-
4539	1N5160	1N5158, Ub10..12V	-
4540	1N5161		-
4541	1N5162	1200V, 150A(Tc150°)	1N4595...96
4542	1N5163	35V, <0,5ns	-
4543	1N5164	35V, <0,4ns	-
4544	1N5165(A)	30V	-

4545	1N5166(A)	30V	-
4546	1N5167(A)	20V	-
4547	1N5168		-
4548	1N5169		-
4549	1N5170	15V, 2A	BY 251...255, BYW 52...56, 1N5400...08
4550	1N5171	1N5170, 50V	BY 251...255, BYW 52...56, 1N5400...08
4551	1N5172	1N5170, 100V	BY 251...255, BYW 52...56, 1N5401...08
4552	1N5173	1N5170, 300V	BY 252...255, BYW 53...56, 1N5404...08
4553	1N5174	1N5170, 400V	BY 252...255, BYW 53...56, 1N5404...08
4554	1N5175	1N5170, 500V	BY 253...255, BYW 54...56, 1N5406...08
4555	1N5176	1N5170, 600V	BY 253...255, BYW 54...56, 1N5406...08
4556	1N5177	1N5170, 800V	BY 254...255, BYW 55...56, 1N5407...08
4557	1N5178	1N5170, 1000V	BY 255, BYW 56, GP 20M, 1N5408
4558	1N5179	2,8V(1mA), 0,4W	BZ 102/2V8, BZV 86/2V6, BZX 75/C2V8
4559	1N5180	120V, 4A	BY 500/200, MR 752...760, MR 822...826
4560	1N5181	4kV, 0,1A	HVG 4, 1N1734
4561	1N5182	1N5181, 5kV	HVG 5, 1N1734
4562	1N5183	1N5181, 7,5kV	BYX 90
4563	1N5184	1N5181, 10kV	1N3052
4564	1N5185(A)	50V, 3..4A, <250..400ns	BY 500/100, BYV 61...63, MR 820...826
4565	1N5186(A)	1N5185, 100V	BY 500/100, BYV 62...63, MR 821...826
4566	1N5187(A)	1N5185, 200V	BY 500/200, EGP 50D, FE 5D, MR 822...826
4567	1N5188(A)	1N5185, 400V	BY 500/400, MR 824...826
4568	1N5189(A)	1N5185, 500V	BY 500/600, MR 826
4569	1N5190(A)	1N5185, 600V	BY 500/600, MR 826
4570	1N5194	80V, 0,2A	BA 157...159, BA 188...190, BAY 19...20
4571	1N5195	1N5194, 200V	BA 157...159, BA 190, BAY 21
4572	1N5196	1N5194, 250V	BA 157...159, BAY 46, BAY 88...90
4573	1N5197	50V, 3A	BY 251...255, BYW 17/100, 1N5400...08
4574	1N5198	1N5197, 100V	BY 251...255, BYW 17/100, 1N5401...08
4575	1N5199	1N5197, 200V	BY 251...255, BYW 17/200, 1N5402...08
4576	1N52(A)	80V, 50mA	AA 117...118, AA 132...133
4577	1N5200	1N5197, 400V	BY 252...255, BYW 17/400, 1N5404...08
4578	1N5201	1N5197, 600V	BY 253...255, BYW 17/600, 1N5406...08
4579	1N5206	440V, 2A	BY 253...255, BYW 54...56, 1N5061...62
4580	1N5207	440V, 4A	BY 500/600, MR 756...760, MR 826
4581	1N5208	70V, 0,075A	BA 147/100, BA 188...190, 1N5606...09
4582	1N5209	150V, 0,055A	BA 147/150, BA 189...190, 1N5606...07
4583	1N5210	200V, 0,04A	BA 147/230, BAY 21, BAY 88...90
4584	1N5211	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
4585	1N5212	1N5211, 400V	BY 126...127, BY 133...134, 1N4004...07
4586	1N5213	1N5211, 600V	BY 126...127, BY 133...134, 1N4005...07
4587	1N5214	1N5211, 800V	BY 127, BY 133, BY 227, 1N4006...07
4588	1N5215	1N5211	1N5211
4589	1N5216	1N5212	1N5212

4590	1N5217	1N5213	1N5213
4591	1N5218	1N5214	1N5214
4592	1N5219	30V, <2ns	BA 218, BAX 13, BAX 91, 1N4148...49
4593	1N5220	30V, <0,7ns	-
4594	1N5221	2,4V, 20%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5985...6031
4595	1N5221A...5281A	1N5221..5281, 10%	
4596	1N5221B...5281B	1N5221..5281, 5%	
4597	1N5222	1N5221, 2,5V	
4598	1N5223	1N5221, 2,7V	
4599	1N5224	1N5221, 2,8V	
4600	1N5225	1N5221, 3,0V	
4601	1N5226	1N5221, 3,3V	
4602	1N5227	1N5221, 3,6V	
4603	1N5228	1N5221, 3,9V	
4604	1N5229	1N5221, 4,3V	
4605	1N5230	1N5221, 4,7V	
4606	1N5231	1N5221, 5,1V	
4607	1N5232	1N5221, 5,6V	
4608	1N5233	1N5221, 6,0V	
4609	1N5234	1N5221, 6,2V	
4610	1N5235	1N5221, 6,8V	
4611	1N5236	1N5221, 7,5V	
4612	1N5237	1N5221, 8,2V	
4613	1N5238	1N5221, 8,7V	
4614	1N5239	1N5221, 9,1V	
4615	1N5240	1N5221, 10V	
4616	1N5241	1N5221, 11V	
4617	1N5242	1N5221, 12V	
4618	1N5243	1N5221, 13V	
4619	1N5244	1N5221, 14V	
4620	1N5245	1N5221, 15V	
4621	1N5246	1N5221, 16V	
4622	1N5247	1N5221, 17V	
4623	1N5248	1N5221, 18V	
4624	1N5249	1N5221, 19V	
4625	1N5250	1N5221, 20V	
4626	1N5251	1N5221, 22V	
4627	1N5252	1N5221, 24V	
4628	1N5253	1N5221, 25V	
4629	1N5254	1N5221, 27V	
4630	1N5255	1N5221, 28V	
4631	1N5256	1N5221, 30V	
4632	1N5257	1N5221, 33V	
4633	1N5258	1N5221, 36V	
4634	1N5259	1N5221, 39V	

4635	1N5260	1N5221, 43V	
4636	1N5261	1N5221, 47V	
4637	1N5262	1N5221, 51V	
4638	1N5263	1N5221, 56V	
4639	1N5264	1N5221, 60V	
4640	1N5265	1N5221, 62V	
4641	1N5266	1N5221, 68V	
4642	1N5267	1N5221, 75V	
4643	1N5268	1N5221, 82V	
4644	1N5269	1N5221, 87V	
4645	1N527	10V	AA 112...114, AA 116, AA 119, 1N60
4646	1N5270	1N5221, 91V	
4647	1N5271	1N5221, 100V	
4648	1N5272	1N5221, 110V	
4649	1N5273	1N5221, 120V	
4650	1N5274	1N5221, 130V	
4651	1N5275	1N5221, 140V	
4652	1N5276	1N5221, 150V	
4653	1N5277	1N5221, 160V	
4654	1N5278	1N5221, 170V	
4655	1N5279	1N5221, 180V	
4656	1N5280	1N5221, 190V	
4657	1N5281	1N5221, 200V	
4658	1N5282(A)	80V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4659	1N5283...5314		-
4660	1N530	100V, 0,3A	BA 157...159, BY 402...405, 1N4002...07
4661	1N531	1N530, 200V	BA 157...159, BY 403...405, 1N4003...07
4662	1N5315	100V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4663	1N5316	100V, 0,135A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4664	1N5317	80V, 0,125A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4665	1N5318	75V, 0,125A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4666	1N5319	40V, 0,1A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4667	1N532	1N530, 300V	BA 157...159, BY 404...405, 1N4004...07
4668	1N5320	120V, 1A, <250ns	BY 201/2, BY 296...299, BYX 58/200
4669	1N5321	30V	-
4670	1N5322	30V	-
4671	1N5323	20V	-
4672	1N5324	15k, 0,01A	HS 10
4673	1N5326	200V, 12A	-
4674	1N5329	6kV, 0,135A	BYX 90, 1N5183
4675	1N533	1N530, 400V	BA 157...159, BY 404...405, 1N4004...07
4676	1N5330	1500V, 0,54A	BY 269, DM 513, EM 516, GP 10W
4677	1N5331	1200V, 12A(Tc150°)	BYW 88/1200, 1N4511
4678	1N5332	1200V, 35A(Tc140°)	1N4530
4679	1N5333	3,3V, 20%, 5W	BZV 40/..., BZV 48/...



4680	1N5333A...5388A	1N5333..5388, 10%	
4681	1N5333B...5388B	1N5333..5388, 5%	
4682	1N5334	1N5333, 3,6V	
4683	1N5335	1N5333, 3,9V	
4684	1N5336	1N5333, 4,3V	
4685	1N5337	1N5333, 4,7V	
4686	1N5338	1N5333, 5,1V	
4687	1N5339	1N5333, 5,6V	
4688	1N534	1N530, 500V	BA 158...159, BY 405, 1N4005...07
4689	1N5340	1N5333, 6V	
4690	1N5341	1N5333, 6,2V	
4691	1N5342	1N5333, 6,8V	
4692	1N5343	1N5333, 7,5V	
4693	1N5344	1N5333, 8,2V	
4694	1N5345	1N5333, 8,7V	
4695	1N5346	1N5333, 9,1V	
4696	1N5347	1N5333, 10V	
4697	1N5348	1N5333, 11V	
4698	1N5349	1N5333, 12V	
4699	1N535	1N530, 600V	BA 158...159, BY 405, 1N4005...07
4700	1N5350	1N5333, 13V	
4701	1N5351	1N5333, 14V	
4702	1N5352	1N5333, 15V	
4703	1N5353	1N5333, 16V	
4704	1N5354	1N5333, 17V	
4705	1N5355	1N5333, 18V	
4706	1N5356	1N5333, 19V	
4707	1N5357	1N5333, 20V	
4708	1N5358	1N5333, 22V	
4709	1N5359	1N5333, 24V	
4710	1N536	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
4711	1N5360	1N5333, 25V	
4712	1N5361	1N5333, 27V	
4713	1N5362	1N5333, 28V	
4714	1N5363	1N5333, 30V	
4715	1N5364	1N5333, 33V	
4716	1N5365	1N5333, 36V	
4717	1N5366	1N5333, 39V	
4718	1N5367	1N5333, 43V	
4719	1N5368	1N5333, 47V	
4720	1N5369	1N5333, 51V	
4721	1N537	1N536, 100V	BY 126...127, BY 133...135, 1N4002...07
4722	1N5370	1N5333, 56V	
4723	1N5371	1N5333, 60V	
4724	1N5372	1N5333, 62V	

4725	1N5373	1N5333, 68V	
4726	1N5374	1N5333, 75V	
4727	1N5375	1N5333, 82V	
4728	1N5376	1N5333, 87V	
4729	1N5377	1N5333, 91V	
4730	1N5378	1N5333, 100V	
4731	1N5379	1N5333, 110V	
4732	1N538	1N536, 200V	BY 126...127, BY 133...134, 1N4003...07
4733	1N5380	1N5333, 120V	
4734	1N5381	1N5333, 130V	
4735	1N5382	1N5333, 140V	
4736	1N5383	1N5333, 150V	
4737	1N5384	1N5333, 160V	
4738	1N5385	1N5333, 170V	
4739	1N5386	1N5333, 180V	
4740	1N5387	1N5333, 190V	
4741	1N5388	1N5333, 200V	
4742	1N5389	40kV	-
4743	1N539	1N536, 300V	BY 126...127, BY 133...134, 1N4004...07
4744	1N5390	5V	-
4745	1N5391(A,GP)	50V, 1,5A	BY 251...255, BY 226...227, BYW 52...56
4746	1N5392(A,GP)	1N5391, 100V	BY 251...255, BY 226...227, BYW 52...56
4747	1N5393(A,GP)	1N5391, 200V	BY 251...255, BY 226...227, BYW 52...56
4748	1N5394(A,GP)	1N5391, 300V	BY 252...255, BY 226...227, BYW 53...56
4749	1N5395(A,GP)	1N5391, 400V	BY 252...255, BY 226...227, BYW 53...56
4750	1N5396(A,GP)	1N5391, 500V	BY 253...255, BY 226...227, BYW 54...56
4751	1N5397(A,GP)	1N5391, 600V	BY 253...255, BY 226...227, BYW 54...56
4752	1N5398(A,GP)	1N5391, 800V	BY 254...255, BY 227, BYW 55...56
4753	1N5399(A,GP)	1N5391, 1000V	BY 255, BY 227, BYW 56, GP 15M
4754	1N54(A)	75V, 50mA	AA 113, AA 117...118, 1N34
4755	1N540	1N536, 400V	BY 126...127, BY 133...134, 1N4004...07
4756	1N5400(K)	50V, 3A	BY 251...255, BYW 17/100, BYW 82
4757	1N5401(K)	1N5400, 100V	BY 251...255, BYW 17/100, BYW 82
4758	1N5402(K)	1N5400, 200V	BY 251...255, BYW 17/200, BYW 82
4759	1N5403(K)	1N5400, 300V	BY 252...255, BYW 17/400, BYW 83
4760	1N5404(K)	1N5400, 400V	BY 252...255, BYW 17/400, BYW 83
4761	1N5405(K)	1N5400, 500V	BY 253...255, BYW 17/600, BYW 84
4762	1N5406(K)	1N5400, 600V	BY 253...255, BYW 17/600, BYW 84
4763	1N5407(K)	1N5400, 800V	BY 254...255, BYW 17/800, BYW 85
4764	1N5408(K)	1N5400, 1000V	BY 255, BYW 17/1000, BYW 86
4765	1N5409	300V, 40A(Tc100°)	BYX 97/300
4766	1N541	50V, 30mA	AA 113, AA 119, 1N34, 1N54, 1N60
4767	1N5410	300V, 12A(Tc100°)	BYW 88/300, BYX 78...81, 1N4507...11
4768	1N5411	Ub29..35V, Ib<0,05mA, Itsm2A	1N5761, N413M, BR 100, D3202Y, DO201YR
4769	1N5412	40V, 0,2A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49

4770	1N5413	80V, 0,2A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4771	1N5414	100V, 0,2A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
4772	1N5415	50V, 3A, <150ns	BYW 16/100, BYW 72...78, RGP 30A
4773	1N5416	1N5415, 100V	BYW 16/100, BYW 72...78, RGP 30B
4774	1N5417	1N5415, 200V	BYW 16/200, BYW 72...78, RGP 30D
4775	1N5418	1N5415, 400V	BYW 16/400, BYW 74...78, RGP 30G
4776	1N5419	1N5415, 500V, <250ns	BYW 16/600, BYW 76...78, RGP 30K
4777	1N5420	1N5415, 600V, <400ns	BYW 16/600, BYW 76...78, RGP 30K
4778	1N5421	200V	-
4779	1N5422	200V	-
4780	1N5423	200V	-
4781	1N5424	100V	-
4782	1N5425	100V	-
4783	1N5427	75V, <4ns	-
4784	1N5428	200V, <50ns	-
4785	1N5429	200V	-
4786	1N543(A)	1500V, 10..35mA	DM 513, EM 516, RGP 01-16, SHG 1,5
4787	1N5430	75V, <4ns	-
4788	1N5431	80V, <4ns	-
4789	1N5432	20V, <0,75ns	-
4790	1N5433	720V, 2mA, <400ns	BA 158...159, BY 204/8, BY 203/12
4791	1N5434	720V, 2mA, <400ns	BA 158...159, BY 204/8, BY 203/12
4792	1N5435	720V, 12A(Tc25°)	-
4793	1N544(A)	1200V, 15..75mA	DM 513, EM 516, RGP 01-16, SHG 1,5
4794	1N5441(A...D)		-
4795	1N5442(A...D)		-
4796	1N5443(A...D)		-
4797	1N5444(A...D)		-
4798	1N5445(A...D)		-
4799	1N5446(A...D)		-
4800	1N5447(A...D)		-
4801	1N5448(A...D)		-
4802	1N5449(A...D)		-
4803	1N5450(A...D)		-
4804	1N5451(A...D)		-
4805	1N5452(A...D)		-
4806	1N5453(A...D)		-
4807	1N5454(A...D)		-
4808	1N5455(A...D)		-
4809	1N5456(A...D)		-
4810	1N5461(A...D)		-
4811	1N5462(A...D)		-
4812	1N5463(A...D)		-
4813	1N5464(A...D)		-
4814	1N5465(A...D)		-

4815	1N5466(A...D)		-
4816	1N5467(A...D)		-
4817	1N5468(A...D)		-
4818	1N5469(A...D)		-
4819	1N547(S)	600V, 0,75A	BY 126...127, BY 133...134, 1N4005
4820	1N5470(A...D)		-
4821	1N5471(A...D)		-
4822	1N5472(A...D)		-
4823	1N5473(A...D)		-
4824	1N5474(A...D)		-
4825	1N5475(A...D)		-
4826	1N5476(A...D)		-
4827	1N548	900V, 0,3A	BA 159, BY 127, BY 133, 1N4007
4828	1N5482	2,4kV, 1A	-
4829	1N5483	1N5482, 3,6kV	-
4830	1N5484	1N5482, 4,8kV	-
4831	1N5485	1N5482, 6kV	-
4832	1N549	1N548, 1200V	BY 127, BY 133, BYX 95, EM 513
4833	1N55(A,B)	150..180V, 30..50mA	-
4834	1N550	100V, 0,5A	BYX 38/300, BYX 39/600
4835	1N551	1N550, 200V	BYX 38/300, BYX 39/600
4836	1N5510A...5546A	1N5518..5546, 10%	
4837	1N5510B...5546B	1N5518..5546, 5%	
4838	1N5510C...5546C	1N5518..5546, 2%	
4839	1N5510D...5546D	1N5518..5546, 1%	
4840	1N5518	3,3V, 20%, 0,4W	BZX55/..., BZX55/..., ZPD..., 1N5226...57
4841	1N5519	1N5518, 3,6V	
4842	1N552	1N550, 300V	BYX 38/300, BYX 39/600
4843	1N5520	1N5518, 3,9V	
4844	1N5521	1N5518, 4,3V	
4845	1N5522	1N5518, 4,7V	
4846	1N5523	1N5518, 5,1V	
4847	1N5524	1N5518, 5,6V	
4848	1N5525	1N5518, 6,2V	
4849	1N5526	1N5518, 6,8V	
4850	1N5527	1N5518, 7,5V	
4851	1N5528	1N5518, 8,2V	
4852	1N5529	1N5518, 9,1V	
4853	1N553	1N550, 400V	BYX 38/600, BYX 39/600
4854	1N5530	1N5518, 10V	
4855	1N5531	1N5518, 11V	
4856	1N5532	1N5518, 12V	
4857	1N5533	1N5518, 13V	
4858	1N5534	1N5518, 14V	
4859	1N5535	1N5518, 15V	

4860	1N5536	1N5518, 16V	
4861	1N5537	1N5518, 17V	
4862	1N5538	1N5518, 18V	
4863	1N5539	1N5518, 19V	
4864	1N554	1N550, 500V	BYX 38/600, BYX 39/600
4865	1N5540	1N5518, 20V	
4866	1N5541	1N5518, 22V	
4867	1N5542	1N5518, 24V	
4868	1N5543	1N5518, 25V	
4869	1N5544	1N5518, 28V	
4870	1N5545	1N5518, 30V	
4871	1N5546	1N5518, 33V	
4872	1N555	1N550, 600V	BYX 38/600, BYX 39/600
4873	1N5550	200V, 3A	BY 251...255, BYW 17/200, BYW 82...86
4874	1N5551	1N5550, 400V	BY 252...255, BYW 17/400, BYW 83...86
4875	1N5552	1N5550, 600V	BY 253...255, BYW 17/600, BYW 84...86
4876	1N5553	1N5550, 800V	BY 254...255, BYW 17/800, BYW 85...86
4877	1N5554	1N5550, 1000V	BY 255, BYW 17/1000, BYW 86, 1N5408
4878	1N5555	33V, 1,5kW(1ms)	1N5645
4879	1N5556	1N5555, 43,7V	1N5648
4880	1N5557	1N5555, 54V	1N5651
4881	1N5558	1N5555, 191V	1N5664
4882	1N5559	6,8V, 20%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5921...56
4883	1N5559A...5594A	1N5559...5594, 10%	
4884	1N5559B...5594B	1N5559...5594, 5%	
4885	1N5560	1N5559, 7,5V	
4886	1N5561	1N5559, 8,2V	
4887	1N5562	1N5559, 9,1V	
4888	1N5563	1N5559, 10V	
4889	1N5564	1N5559, 11V	
4890	1N5565	1N5559, 12V	
4891	1N5566	1N5559, 13V	
4892	1N5567	1N5559, 15V	
4893	1N5568	1N5559, 16V	
4894	1N5569	1N5559, 18V	
4895	1N5570	1N5559, 20V	
4896	1N5571	1N5559, 22V	
4897	1N5572	1N5559, 24V	
4898	1N5573	1N5559, 27V	
4899	1N5574	1N5559, 30V	
4900	1N5575	1N5559, 33V	
4901	1N5576	1N5559, 36V	
4902	1N5577	1N5559, 39V	
4903	1N5578	1N5559, 43V	
4904	1N5579	1N5559, 47V	

4905	1N558	1500V, 15mA	BAY 91, RGP 01-16,
4906	1N5580	1N5559, 51V	
4907	1N5581	1N5559, 56V	
4908	1N5582	1N5559, 62V	
4909	1N5583	1N5559, 68V	
4910	1N5584	1N5559, 75V	
4911	1N5585	1N5559, 82V	
4912	1N5586	1N5559, 91V	
4913	1N5587	1N5559, 100V	
4914	1N5588	1N5559, 110V	
4915	1N5589	1N5559, 120V	
4916	1N5590	1N5559, 130V	
4917	1N5591	1N5559, 150V	
4918	1N5592	1N5559, 160V	
4919	1N5593	1N5559, 180V	
4920	1N5594	1N5559, 200V	
4921	1N56(A)	50V, 60mA	AA 117...118, AA 132...134, 1N60
4922	1N560	800V, 0,25A	BY 127, BY 133, BYW 42, G 1K, 1N4006
4923	1N5605	70V	BA 188...190, BAY 19...21, BAY 45...46.
4924	1N5606	150V, 0,1A	BA 189...190, BAY 20...21, BAY 45...46.
4925	1N5607	200V, 0,15A	BA 190, BAW 52, BAY 21, BAY 46.
4926	1N5608	120V, 0,15A, <300ns	BA 157...159, BAV 19...21, BAX 15...17
4927	1N5609	120V, 0,15A, <300ns	BA 157...159, BAV 19...21, BAX 15...17
4928	1N561	1N560, 1000V	BY 127, BY 133, BYW 43, G 1M, 1N4007
4929	1N5610	1N5555	1N5555
4930	1N5611	1N5556	1N5556
4931	1N5612	1N5557	1N5557
4932	1N5613	1N5558	1N5558
4933	1N5614	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
4934	1N5615	200V, 1A, <150ns	BY 201/2, BYT 52D, BYX 92/200
4935	1N5616	1N5614, 400V	BY 126...127, BY 133...134, 1N4004...07
4936	1N5617	1N5615, 400V	BY 201/4, BYT 52G, BYX 92/400
4937	1N5618	1N5614, 600V	BY 126...127, BY 133...134, 1N4005...07
4938	1N5619	1N5615, 600V	BY 201/6, BYT 52J, RGP 10J
4939	1N562	800V, 0,4A	BYX 38/900, BYX 39/800
4940	1N5620	1N5614, 800V	BY 127, BY 133, BY 227, 1N4006...07
4941	1N5620P1..5665P1	1N5629..5665	
4942	1N5621	1N5615, 800V	BYV 15...16, BYT 52K, RGP 10K
4943	1N5622	1N5614, 1000V	BY 127, BY 133, BY 227, 1N4007
4944	1N5623	1N5615, 1000V	BYV 16, BYV 36E, BYT 52M, RGP 10M
4945	1N5624(GP)	200V, 5A	BY 500/200, MR 752...760, MR 822...826
4946	1N5625(GP)	1N5624, 400V	BY 500/400, MR 754...760, MR 824...826
4947	1N5626(GP)	1N5624, 600V	BY 500/600, MR 756...760, MR 826
4948	1N5627(GP)	1N5624, 800V	BY 214/800, MR 758...760
4949	1N5629(A)	6,8V, 1,5kW(1ms)	1N6267...6303, 1N6036...72, 1N6138...73

4950	1N563	1N562, 1000V	BYX 38/1200, BYX 39/1000
4951	1N5630(A)	1N5629, 7,5V	
4952	1N5631(A)	1N5629, 8,2V	
4953	1N5632(A)	1N5629, 9,1V	
4954	1N5633(A)	1N5629, 10V	
4955	1N5634(A)	1N5629, 11V	
4956	1N5635(A)	1N5629, 12V	
4957	1N5636(A)	1N5629, 13V	
4958	1N5637(A)	1N5629, 15V	
4959	1N5638(A)	1N5629, 16V	
4960	1N5639(A)	1N5629, 18V	
4961	1N5640(A)	1N5629, 20V	
4962	1N5641(A)	1N5629, 22V	
4963	1N5642(A)	1N5629, 24V	
4964	1N5643(A)	1N5629, 27V	
4965	1N5644(A)	1N5629, 30V	
4966	1N5645(A)	1N5629, 33V	
4967	1N5646(A)	1N5629, 36V	
4968	1N5647(A)	1N5629, 39V	
4969	1N5648(A)	1N5629, 43V	
4970	1N5649(A)	1N5629, 47V	
4971	1N5650(A)	1N5629, 51V	
4972	1N5651(A)	1N5629, 56V	
4973	1N5652(A)	1N5629, 62V	
4974	1N5653(A)	1N5629, 68V	
4975	1N5654(A)	1N5629, 75V	
4976	1N5655(A)	1N5629, 82V	
4977	1N5656(A)	1N5629, 91V	
4978	1N5657(A)	1N5629, 100V	
4979	1N5658(A)	1N5629, 110V	
4980	1N5659(A)	1N5629, 120V	
4981	1N566	275V	-
4982	1N5660(A)	1N5629, 130V	
4983	1N5661(A)	1N5629, 150V	
4984	1N5662(A)	1N5629, 160V	
4985	1N5663(A)	1N5629, 170V	
4986	1N5664(A)	1N5629, 180V	
4987	1N5665(A)	1N5629, 200V	
4988	1N567	125V, 300ns	-
4989	1N5679	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
4990	1N568	50V, 80ns	-
4991	1N5680	1N5679, 100V	BY 126...127, BY 133...135, 1N4001...07
4992	1N5681(A,B)		-
4993	1N5682(A,B)		-
4994	1N5683(A,B)		-

4995	1N5684(A,B)		-
4996	1N5685(A,B)		-
4997	1N5686(A,B)		-
4998	1N5687(A,B)		-
4999	1N5688(A,B)		-
5000	1N5689(A,B)		-
5001	1N569	25V	AA 139, 1N270
5002	1N5690(A,B)		-
5003	1N5691(A,B)		-
5004	1N5692(A,B)		-
5005	1N5693(A,B)		-
5006	1N5694(A,B)		-
5007	1N5695(A,B)		-
5008	1N5696(A,B)		-
5009	1N5697(A,B)		-
5010	1N5698(A,B)		-
5011	1N5699(A,B)		-
5012	1N57(A)	80V, 40mA	AA 117...118, AA 132...133
5013	1N5700(A,B)		-
5014	1N5701(A,B)		-
5015	1N5702(A,B)		-
5016	1N5703(A,B)		-
5017	1N5704(A,B)		-
5018	1N5705(A,B)		-
5019	1N5706(A,B)		-
5020	1N5707(A,B)		-
5021	1N5708(A,B)		-
5022	1N5709(A,B)		-
5023	1N571	15V, <4μ	-
5024	1N5710(A,B)		-
5025	1N5711	70V, 15mA	BAR 28, HSS 102
5026	1N5712	20V, 35mA	BAR 10, 1S1992, 1SS101, 1SS109
5027	1N5713	12V	-
5028	1N5714	200V	-
5029	1N5715	200V	-
5030	1N5716	200V	-
5031	1N5717	100V	-
5032	1N5718	100V	-
5033	1N5719	100V	BA 188...190, BA 147/100, 1N5606...09
5034	1N5720	30V, <10ns	BA 317, BAW 53, BAY 71, 1N4148...49
5035	1N5721	1N5720, 15V	BA 317, BAW 53, BAY 71, 1N4148...49
5036	1N5726	60V, <10ns	BAV 14, BAW 26...27
5037	1N5727	1N5726, 50V	BAV 14, BAW 24...27
5038	1N5728	4,7V, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5230...67
5039	1N5728A...5757A	1N5728..5757, 5%	



5040	1N5728B...5757B	1N5728..5757, 2%	
5041	1N5728C...5757C	1N5728..5757, 1%	
5042	1N5729	1N5728, 5,1V	
5043	1N5730	1N5728, 5,6V	
5044	1N5731	1N5728, 6,2V	
5045	1N5732	1N5728, 6,8V	
5046	1N5733	1N5728, 7,5V	
5047	1N5734	1N5728, 8,2V	
5048	1N5735	1N5728, 9,1V	
5049	1N5736	1N5728, 10V	
5050	1N5737	1N5728, 11V	
5051	1N5738	1N5728, 12V	
5052	1N5739	1N5728, 13V	
5053	1N5740	1N5728, 15V	
5054	1N5741	1N5728, 16V	
5055	1N5742	1N5728, 18V	
5056	1N5743	1N5728, 20V	
5057	1N5744	1N5728, 22V	
5058	1N5745	1N5728, 24V	
5059	1N5746	1N5728, 27V	
5060	1N5747	1N5728, 30V	
5061	1N5748	1N5728, 33V	
5062	1N5749	1N5728, 36V	
5063	1N5750	1N5728, 39V	
5064	1N5751	1N5728, 43V	
5065	1N5752	1N5728, 47V	
5066	1N5753	1N5728, 51V	
5067	1N5754	1N5728, 56V	
5068	1N5755	1N5728, 62V	
5069	1N5756	1N5728, 68V	
5070	1N5757	1N5728, 75V	
5071	1N5758	Ub16..24V, Ib<0,1mA, Itsm2A	-
5072	1N5758A	Itsm2A	-
5073	1N5759	Ub20..28V, Ib<0,1mA, Itsm2A	-
5074	1N5759A	Itsm2A	-
5075	1N5760	Ub24..32V, Ib<0,1mA, Itsm2A	N 413L, D 3202U
5076	1N5760A	Itsm2A	N 413L, D 3202U
5077	1N5761	Ub28..36V, Ib<0,1mA, Itsm2A	N 413M, BR 100, D 3202Y, D O201 YR
5078	1N5761A	Itsm2A	N 413M, BR 100, D 3202Y, D O201 YR
5079	1N5762	Ub32..40V, Ib<0,1mA, Itsm2A	N 413N, D 3202U
5080	1N5762A	Itsm2A	N 413N, D 3202U
5081	1N5766	110V, 400ns	1N4525...4530
5082	1N5767	100V, <0,4pF(50V)	-
5083	1N5779	1N5158, Ub11..13V	-
5084	1N5780	1N5158, Ub12..14V	-

5085	1N5781	1N5158, Ub13..15V	-
5086	1N5782	1N5158, Ub8..10V, Ib<0,1mA	-
5087	1N5783	1N5158, Ub9..11V, Ib<0,1mA	-
5088	1N5784	1N5158, Ub10..12V, Ib<0,1mA	-
5089	1N5785	1N5158, Ub11..13V, Ib<0,1mA	-
5090	1N5786	1N5158, Ub12..14V, Ib<0,1mA	-
5091	1N5787	1N5158, Ub13..15V, Ib<0,1mA	-
5092	1N5788	1N5158, Ub8..10V, Ib<0,1mA	-
5093	1N5789	1N5158, Ub9..11V, Ib<0,1mA	-
5094	1N5790	1N5158, Ub10..12V, Ib<0,1mA	-
5095	1N5791	1N5158, Ub11..13V, Ib<0,1mA	-
5096	1N5792	1N5158, Ub12..14V, Ib<0,1mA	-
5097	1N5793	1N5158, Ub13..15V, Ib<0,1mA	-
5098	1N5794	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
5099	1N5795	1N5794, 100V	BY 126...127, BY 133...135, 1N4002...07
5100	1N5796	1N5794, 200V	BY 126...127, BY 133...134, 1N4003...07
5101	1N5797	1N5794, 400V	BY 126...127, BY 133...134, 1N4004...07
5102	1N5798	1N5794, 600V	BY 126...127, BY 133...134, 1N4005...07
5103	1N5799	1N5794, 800V	BY 127, BY 133, BY 227, 1N4006...07
5104	1N58(A)	115V, 50mA	AA 117...118, AA 132...133
5105	1N5800	1N5794, 1000V	BY 127, BY 133, BY 227, 1N4007
5106	1N5802	50V, 2,5A, <25ns	BYV 28/50, EGP 30A, FE 3A
5107	1N5803	1N5802, 75V	BYV 28/100, EGP 30B, FE 3B
5108	1N5804	1N5802, 100V	BYV 28/100, EGP 30B, FE 3B
5109	1N5805	1N5802, 125V	BYV 28/150, EGP 30C, FE 3C
5110	1N5806	1N5802, 150V	BYV 28/150, EGP 30C, FE 3C
5111	1N5807	50V, 6A, <30ns	BYV 61...63, FE 6A
5112	1N5808	1N5807, 75V	BYV 62...63, FE 6B
5113	1N5809	1N5807, 100V	BYV 62...63, FE 6B
5114	1N5810	1N5807, 125V	BYV 63, FE 6C
5115	1N5811	1N5807, 150V	BYV 63, FE 6C
5116	1N5812	50V, 20A, <25ns	BYW 77/50
5117	1N5813	1N5812, 75V	BYW 77/100
5118	1N5814	1N5812, 100V	BYW 77/100
5119	1N5815	1N5812, 125V	BYW 77/150
5120	1N5816	1N5812, 150V	BYW 77/150
5121	1N5817		
5122	1N5818	1N5817, 30V	BYS 21, BYV 10-30, SB 130
5123	1N5819	1N5817, 40V	BYS 21, BYV 10-40, SB 140
5124	1N5820	20V, 3A	BYS 26, MBR 320, SB 320
5125	1N5821	1N5820, 30V	BYS 26, MBR 330, SB 330
5126	1N5822	1N5820, 40V	BYS 26, MBR 340, SB 340, HRP 24
5127	1N5823	20V, 5A	BYS 08, SB 520
5128	1N5824	1N5823, 30V	BYS 08, SB 530
5129	1N5825	1N5823, 40V	BYS 08, SB 540

5130	1N5826	20V, 15A(Tc85°)	BYS 15, MBR 1520
5131	1N5827	1N5826, 30V	BYS 15, MBR 1530
5132	1N5828	1N5826, 40V	BYS 15, MBR 1540
5133	1N5829	20V, 25A(Tc85°)	BYS 30...32, BYS 35/20, MBR 2520
5134	1N5830	1N5829, 30V	BYS 30...32, BYS 35/30, MBR 2530
5135	1N5831	1N5829, 40V	BYS 30...32, BYS 35/40, MBR 2540
5136	1N5832	20V, 40A(Tc75°)	BYS 50...51, BYS 60/20, MBR 4020
5137	1N5833	1N5832, 30V	BYS 50...51, BYS 60/30, MBR 4030
5138	1N5834	1N5832, 40V	BYS 50...51, BYS 60/40, MBR 4040
5139	1N5835	30V, 3A, <100ns	BYV 28/50, EGP 30A, FE 3A
5140	1N5836	1N5835, 50V	BYV 28/50, EGP 30A, FE 3A
5141	1N5837	2,4V, 20%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5221...81
5142	1N5837A...5897A	1N5837...5897, 10%	
5143	1N5837B...5897B	1N5837...5897, 5%	
5144	1N5837C...5897C	1N5837...5897, 2%	
5145	1N5837D...5897D	1N5837...5897, 1%	
5146	1N5838	1N5837, 2,5V	
5147	1N5839	1N5837, 2,7V	
5148	1N5840	1N5837, 2,8V	
5149	1N5841	1N5837, 3V	
5150	1N5844	1N5837, 3,9V	
5151	1N5845	1N5837, 4,3V	
5152	1N5846	1N5837, 4,7V	
5153	1N5847	1N5837, 5,1V	
5154	1N5848	1N5837, 5,6V	
5155	1N5849	1N5837, 6V	
5156	1N5850	1N5837, 6,2V	
5157	1N5851	1N5837, 6,8V	
5158	1N5852	1N5837, 7,5V	
5159	1N5853	1N5837, 8,2V	
5160	1N5854	1N5837, 8,7V	
5161	1N5855	1N5837, 9,1V	
5162	1N5856	1N5837, 10V	
5163	1N5857	1N5837, 11V	
5164	1N5858	1N5837, 12V	
5165	1N5859	1N5837, 13V	
5166	1N5860	1N5837, 14V	
5167	1N5861	1N5837, 15V	
5168	1N5862	1N5837, 16V	
5169	1N5863	1N5837, 17V	
5170	1N5864	1N5837, 18V	
5171	1N5865	1N5837, 19V	
5172	1N5866	1N5837, 20V	
5173	1N5867	1N5837, 22V	
5174	1N5868	1N5837, 24V	

5175	1N5869	1N5837, 25V	
5176	1N5870	1N5837, 27V	
5177	1N5871	1N5837, 28V	
5178	1N5872	1N5837, 30V	
5179	1N5873	1N5837, 33V	
5180	1N5874	1N5837, 36V	
5181	1N5875	1N5837, 39V	
5182	1N5876	1N5837, 43V	
5183	1N5877	1N5837, 47V	
5184	1N5878	1N5837, 51V	
5185	1N588	1500V, 0,1A	BAY 91, RGP 01-16
5186	1N5880	1N5837, 60V	
5187	1N5881	1N5837, 62V	
5188	1N5882	1N5837, 68V	
5189	1N5883	1N5837, 75V	
5190	1N5884	1N5837, 82V	
5191	1N5885	1N5837, 87V	
5192	1N5886	1N5837, 91V	
5193	1N5887	1N5837, 100V	
5194	1N5888	1N5837, 110V	
5195	1N5889	1N5837, 120V	
5196	1N589	1500V, 0,25A	BAY 91, DM 513, EM 516, GP 10Y
5197	1N5890	1N5837, 130V	
5198	1N5891	1N5837, 140V	
5199	1N5892	1N5837, 150V	
5200	1N5893	1N5837, 160V	
5201	1N5894	1N5837, 170V	
5202	1N5895	1N5837, 180V	
5203	1N5896	1N5837, 190V	
5204	1N5897	1N5837, 200V	
5205	1N59	280V, 50mA	-
5206	1N590	1500V, 25mA	BAY 91, RGP 01-16
5207	1N5907	1N5629, 6...7V	
5208	1N5908	1N5629, 6...7V	
5209	1N591	1N590	BAY 91, RGP 01-16
5210	1N5913	3,3V, 20%, 1,5W(Tc75°)	BZW22/..., BZX61/..., ZPY..., BZY97/...
5211	1N5913A...5956A	1N5913..5956, 10%	
5212	1N5913A...5956A	1N5913..5956, 10%	
5213	1N5913B...5956B	1N5913..5956, 5%	
5214	1N5913B...5956B	1N5913..5956, 5%	
5215	1N5913C...5956C	1N5913..5956, 2%	
5216	1N5913C...5956C	1N5913..5956, 2%	
5217	1N5913D...5956D	1N5913..5956, 1%	
5218	1N5913D...5956D	1N5913..5956, 1%	
5219	1N5914	1N5913, 3,6V	

5220	1N5915	1N5913, 3,9V	
5221	1N5916	1N5913, 4,3V	
5222	1N5917	1N5913, 4,7V	
5223	1N5918	1N5913, 5,1V	
5224	1N5919	1N5913, 5,6V	
5225	1N5920	1N5913, 6,2V	
5226	1N5921	1N5913, 6,8V	
5227	1N5922	1N5913, 7,5V	
5228	1N5923	1N5913, 8,2V	
5229	1N5924	1N5913, 9,1V	
5230	1N5925	1N5913, 10V	
5231	1N5926	1N5913, 11V	
5232	1N5927	1N5913, 12V	
5233	1N5928	1N5913, 13V	
5234	1N5929	1N5913, 15V	
5235	1N5930	1N5913, 16V	
5236	1N5931	1N5913, 18V	
5237	1N5932	1N5913, 20V	
5238	1N5933	1N5913, 22V	
5239	1N5934	1N5913, 24V	
5240	1N5935	1N5913, 27V	
5241	1N5936	1N5913, 30V	
5242	1N5937	1N5913, 33V	
5243	1N5938	1N5913, 36V	
5244	1N5939	1N5913, 39V	
5245	1N5940	1N5913, 43V	
5246	1N5941	1N5913, 47V	
5247	1N5942	1N5913, 51V	
5248	1N5943	1N5913, 56V	
5249	1N5944	1N5913, 62V	
5250	1N5945	1N5913, 68V	
5251	1N5946	1N5913, 75V	
5252	1N5947	1N5913, 82V	
5253	1N5948	1N5913, 91V	
5254	1N5949	1N5913, 100V	
5255	1N5950	1N5913, 110V	
5256	1N5951	1N5913, 120V	
5257	1N5952	1N5913, 130V	
5258	1N5953	1N5913, 150V	
5259	1N5954	1N5913, 160V	
5260	1N5955	1N5913, 180V	
5261	1N5956	1N5913, 200V	
5262	1N5957	100V, <0,4pF(50V)	-
5263	1N596	600V, 0,15A	BA 158...159, BAY 89...90, BY 207
5264	1N5968	5,6V, 5%, 5W	BZV 40/C5V6, BZV 48/C5V6, 2N5339B

5265	1N5969	6,2V, 5%, 5W	BZV 40/C6V2, BZV 48/C6V2, 2N5341B
5266	1N597	1N596, 800V	BA 159, BAY 90, BY 204/8
5267	1N598	1N596, 1000V	BA 159, BAY 90, BY 204/10
5268	1N5985	2,4V, 20%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5221...81,...
5269	1N5985A...6031A	1N5985..6031, 10%	
5270	1N5985B...6031B	1N5985..6031, 5%	
5271	1N5985C...6031C	1N5985..6031, 2%	
5272	1N5985D...6031D	1N5985..6031, 1%	
5273	1N5986	1N5985, 2,7V	
5274	1N5987	1N5985, 3V	
5275	1N5988	1N5985, 3,3V	
5276	1N5989	1N5985, 3,6V	
5277	1N599(A)	50V, 0,4A	BA 157...159, BY 401...405, 1N4001...07
5278	1N5990	1N5985, 3,9V	
5279	1N5991	1N5985, 4,3V	
5280	1N5992	1N5985, 4,7V	
5281	1N5993	1N5985, 5,1V	
5282	1N5994	1N5985, 5,6V	
5283	1N5995	1N5985, 6,2V	
5284	1N5996	1N5985, 6,8V	
5285	1N5997	1N5985, 7,5V	
5286	1N5998	1N5985, 8,2V	
5287	1N5999	1N5985, 9,1V	
5288	1N60(A)	50V, 50mA	AA 113, AA 138, 1N34, 1N54
5289	1N600(A)	1N599, 100V	BA 157...159, BY 402...405, 1N4002...07
5290	1N6000	1N5985, 10V	
5291	1N6001	1N5985, 11V	
5292	1N6002	1N5985, 12V	
5293	1N6003	1N5985, 13V	
5294	1N6004	1N5985, 15V	
5295	1N6005	1N5985, 16V	
5296	1N6006	1N5985, 18V	
5297	1N6007	1N5985, 20V	
5298	1N6008	1N5985, 22V	
5299	1N6009	1N5985, 24V	
5300	1N601(A)	1N599, 150V	BA 157...159, BY 403...405, 1N4003...07
5301	1N6010	1N5985, 27V	
5302	1N6011	1N5985, 30V	
5303	1N6012	1N5985, 33V	
5304	1N6013	1N5985, 36V	
5305	1N6014	1N5985, 39V	
5306	1N6015	1N5985, 43V	
5307	1N6016	1N5985, 47V	
5308	1N6017	1N5985, 51V	
5309	1N6018	1N5985, 56V	

5310	1N6019	1N5985, 62V	
5311	1N602(A)	1N599, 200V	BA 157...159, BY 403...405, 1N4003...07
5312	1N6020	1N5985, 68V	
5313	1N6021	1N5985, 75V	
5314	1N6022	1N5985, 82V	
5315	1N6023	1N5985, 91V	
5316	1N6024	1N5985, 100V	
5317	1N6025	1N5985, 110V	
5318	1N6026	1N5985, 120V	
5319	1N6027	1N5985, 130V	
5320	1N6028	1N5985, 150V	
5321	1N6029	1N5985, 160V	
5322	1N603(A)	1N599, 300V	BA 157...159, BY 404...405, 1N4004...07
5323	1N6030	1N5985, 180V	
5324	1N6031	1N5985, 200V	
5325	1N6036(A)	1N5630, bidirecional	1N6138...6173
5326	1N6037(A)	1N5631, bidirecional	
5327	1N6038(A)	1N5632, bidirecional	
5328	1N6039(A)	1N5633, bidirecional	
5329	1N604(A)	1N599, 400V	BA 157...159, BY 404...405, 1N4004...07
5330	1N6040(A)	1N5634, bidirecional	
5331	1N6041(A)	1N5635, bidirecional	
5332	1N6042(A)	1N5636, bidirecional	
5333	1N6043(A)	1N5637, bidirecional	
5334	1N6044(A)	1N5638, bidirecional	
5335	1N6045(A)	1N5639, bidirecional	
5336	1N6046(A)	1N5640, bidirecional	
5337	1N6047(A)	1N5641, bidirecional	
5338	1N6048(A)	1N5642, bidirecional	
5339	1N6049(A)	1N5643, bidirecional	
5340	1N605(A)	1N599, 500V	BA 158...159, BY 405, 1N4005...07
5341	1N6050(A)	1N5644, bidirecional	
5342	1N6051(A)	1N5645, bidirecional	
5343	1N6052(A)	1N5646, bidirecional	
5344	1N6053(A)	1N5647, bidirecional	
5345	1N6054(A)	1N5648, bidirecional	
5346	1N6055(A)	1N5649, bidirecional	
5347	1N6056(A)	1N5650, bidirecional	
5348	1N6057(A)	1N5651, bidirecional	
5349	1N6058(A)	1N5652, bidirecional	
5350	1N6059(A)	1N5653, bidirecional	
5351	1N606(A)	1N599, 600V	BA 158...159, BY 405, 1N4005...07
5352	1N6060(A)	1N5654, bidirecional	
5353	1N6061(A)	1N5655, bidirecional	
5354	1N6062(A)	1N5656, bidirecional	

5355	1N6063(A)	1N5657, bidirecional	
5356	1N6064(A)	1N5658, bidirecional	
5357	1N6065(A)	1N5659, bidirecional	
5358	1N6066(A)	1N5660, bidirecional	
5359	1N6067(A)	1N5661, bidirecional	
5360	1N6068(A)	1N5662, bidirecional	
5361	1N6069(A)	1N5663, bidirecional	
5362	1N607(A)	50V, 1A	BYX 38/300, BYX 39/600
5363	1N6070(A)	1N5664, bidirecional	
5364	1N6071(A)	1N5665, bidirecional	
5365	1N6072(A)	1N5665, 220V, bidirecional	
5366	1N6073	50V, 3A, 30ns	BYV 28/50, EGP 30A, FE 3A
5367	1N6074	1N6073, 100V	BYV 28/100, EGP 30B, FE 3B
5368	1N6075	1N6073, 150V	BYV 28/150, EGP 30C, FE 3C
5369	1N6076	50V, 6A, 30ns	BYV 61...63, FE 6A
5370	1N6077	1N6076, 100V	BYV 61...63, FE 6A
5371	1N6078	1N6076, 150V	BYV 61...63, FE 6A
5372	1N6079	50V, 12A, 30ns	-
5373	1N607R...614R	1N607(A)..614(A)	BYX 38/600R, BYX 39/600R
5374	1N608(A)	1N607(A), 100V	BYX 38/300, BYX 39/600
5375	1N6080	1N 6079, 100V	-
5376	1N6081	1N 6079, 150V	-
5377	1N6082	4,3V, 20%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5229...40
5378	1N6082A...6091A	1N6082..6091, 10%	
5379	1N6082B...6091B	1N6082..6091, 5%	
5380	1N6082C...6091C	1N6082..6091, 2%	
5381	1N6082D...6091D	1N6082..6091, 1%	
5382	1N6083	1N6082, 4,7V	
5383	1N6084	1N6082, 5,1V	
5384	1N6085	1N6082, 5,6V	
5385	1N6086	1N6082, 6,2V	
5386	1N6087	1N6082, 6,8V	
5387	1N6088	1N6082, 7,5V	
5388	1N6089	1N6082, 8,2V	
5389	1N609(A)	1N607(A), 150V	BYX 38/300, BYX 39/600
5390	1N6090	1N6082, 9,1V	
5391	1N6091	1N6082, 10V	
5392	1N6095	30V, 25A(Tc70°)	BYS 30...32, BYV 121/35, MBR 2530
5393	1N6096	1N6095, 40V	BYS 30...32, BYV 121/40, MBR 2540
5394	1N6097	30V, 50A(Tc70°)	BYS 50...51, BYS 60/30, MBR 6030
5395	1N6098	1N6098, 40V	BYS 50...51, BYS 60/40, MBR 6045
5396	1N6099	1N3595	1N3595
5397	1N61	140V, 40mA	AA 133, 1N39
5398	1N610(A)	1N607(A), 200V	BYX 38/300, BYX 39/600
5399	1N6102(A)	6,8V, 500W(1ms)	BZW 06/...B



5400	1N6103(A)	1N6102, 7,5V	
5401	1N6104(A)	1N6102, 8,2V	
5402	1N6105(A)	1N6102, 9,1V	
5403	1N6106(A)	1N6102, 10V	
5404	1N6107(A)	1N6102, 11V	
5405	1N6108(A)	1N6102, 12V	
5406	1N6109(A)	1N6102, 13V	
5407	1N611(A)	1N607(A), 300V	BYX 38/300, BYX 39/600
5408	1N6110(A)	1N6102, 15V	
5409	1N6111(A)	1N6102, 16V	
5410	1N6112(A)	1N6102, 18V	
5411	1N6113(A)	1N6102, 20V	
5412	1N6114(A)	1N6102, 22V	
5413	1N6115(A)	1N6102, 24V	
5414	1N6116(A)	1N6102, 27V	
5415	1N6117(A)	1N6102, 30V	
5416	1N6118(A)	1N6102, 33V	
5417	1N6119(A)	1N6102, 36V	
5418	1N612(A)	1N607(A), 400V	BYX 38/600, BYX 39/600
5419	1N6120(A)	1N6102, 39V	
5420	1N6121(A)	1N6102, 43V	
5421	1N6122(A)	1N6102, 47V	
5422	1N6123(A)	1N6102, 51V	
5423	1N6124(A)	1N6102, 56V	
5424	1N6125(A)	1N6102, 62V	
5425	1N6126(A)	1N6102, 68V	
5426	1N6127(A)	1N6102, 75V	
5427	1N6128(A)	1N6102, 82V	
5428	1N6129(A)	1N6102, 91V	
5429	1N613(A)	1N607(A), 500V	BYX 38/600, BYX 39/600
5430	1N6130(A)	1N6102, 100V	
5431	1N6131(A)	1N6102, 110V	
5432	1N6132(A)	1N6102, 120V	
5433	1N6133(A)	1N6102, 130V	
5434	1N6134(A)	1N6102, 150V	
5435	1N6135(A)	1N6102, 160V	
5436	1N6136(A)	1N6102, 180V	
5437	1N6137(A)	1N6102, 200V	
5438	1N6138(A)	6,8V, 1,5kW	1N6036...6072
5439	1N6139(A)	1N6138, 7,5V	
5440	1N614(A)	1N607(A), 600V	BYX 38/600, BYX 39/600
5441	1N6140(A)	1N6138, 8,2V	
5442	1N6141(A)	1N6138, 9,1V	
5443	1N6142(A)	1N6138, 10V	
5444	1N6143(A)	1N6138, 11V	

5445	1N6144(A)	1N6138, 12V	
5446	1N6145(A)	1N6138, 13V	
5447	1N6146(A)	1N6138, 15V	
5448	1N6147(A)	1N6138, 16V	
5449	1N6148(A)	1N6138, 18V	
5450	1N6149(A)	1N6138, 20V	
5451	1N615	300V, 75mA	-
5452	1N6150(A)	1N6138, 22V	
5453	1N6151(A)	1N6138, 24V	
5454	1N6152(A)	1N6138, 27V	
5455	1N6153(A)	1N6138, 30V	
5456	1N6154(A)	1N6138, 33V	
5457	1N6155(A)	1N6138, 36V	
5458	1N6156(A)	1N6138, 39V	
5459	1N6157(A)	1N6138, 43V	
5460	1N6158(A)	1N6138, 47V	
5461	1N6159(A)	1N6138, 51V	
5462	1N616	30V, 30mA	AA 113...114, AA 116, AA 119, 1N60
5463	1N6160(A)	1N6138, 56V	
5464	1N6161(A)	1N6138, 62V	
5465	1N6162(A)	1N6138, 68V	
5466	1N6163(A)	1N6138, 75V	
5467	1N6164(A)	1N6138, 82V	
5468	1N6165(A)	1N6138, 91V	
5469	1N6166(A)	1N6138, 100V	
5470	1N6167(A)	1N6138, 110V	
5471	1N6168(A)	1N6138, 120V	
5472	1N6169(A)	1N6138, 130V	
5473	1N617	90V, 50mA	AA 117...118, AA 132...133
5474	1N6170(A)	1N6138, 150V	
5475	1N6171(A)	1N6138, 160V	
5476	1N6172(A)	1N6138, 180V	
5477	1N6173(A)	1N6138, 200V	
5478	1N618	90V, 50mA	AA 117...118, AA 132...133
5479	1N619	30V	BA 127...128, BA 222, BA 147/50, 1N4148
5480	1N62	140V, 40mA	AA 133, 1N39
5481	1N622	150V	BA 147/150, 1N5195...96, 1N5606...07
5482	1N625(A)	30V, 20mA, <500..1000ns	BA 195, BAW 49, BAX 15...17, 1N3070
5483	1N626(A)	1N625, 50V	BA 195, BAW 49, BAX 15...17, 1N3070
5484	1N6262	200V, 85A(Tc100°)	-
5485	1N6263	60V, 15mA	BAR 28, HSS 100, HSS 102
5486	1N6267(A)	1N5629	1N6036...6072, 1N6138...6173
5487	1N6268(A)	1N5630	
5488	1N6269(A)	1N5631	
5489	1N627(A)	1N625, 100V	BA 195, BAW 49, BAX 15...17, 1N3070

5490	1N6270(A)	1N5632	
5491	1N6271(A)	1N5633	
5492	1N6272(A)	1N5634	
5493	1N6273(A)	1N5635	
5494	1N6274(A)	1N5636	
5495	1N6275(A)	1N5637	
5496	1N6276(A)	1N5638	
5497	1N6277(A)	1N5639	
5498	1N6278(A)	1N5640	
5499	1N6279(A)	1N5641	
5500	1N628(A)	1N625, 150V	BA 195, BAW 50, BAX 15...17, 1N3070
5501	1N6280(A)	1N5642	
5502	1N6281(A)	1N5643	
5503	1N6282(A)	1N5644	
5504	1N6283(A)	1N5645	
5505	1N6284(A)	1N5646	
5506	1N6285(A)	1N5647	
5507	1N6286(A)	1N5648	
5508	1N6287(A)	1N5649	
5509	1N6288(A)	1N5650	
5510	1N6289(A)	1N5651	
5511	1N629(A)	1N625, 200V	BA 195, BA 197, BAW 50, BAX 17
5512	1N6290(A)	1N5652	
5513	1N6291(A)	1N5653	
5514	1N6292(A)	1N5654	
5515	1N6293(A)	1N5655	
5516	1N6294(A)	1N5656	
5517	1N6295(A)	1N5657	
5518	1N6296(A)	1N5658	
5519	1N6297(A)	1N5659	
5520	1N6298(A)	1N5660	
5521	1N6299(A)	1N5661	
5522	1N63(A)	100V, 30..50mA	AA 117...118, AA 132...133
5523	1N6300(A)	1N5662	
5524	1N6301(A)	1N5663	
5525	1N6302(A)	1N5664	
5526	1N6303(A)	1N5665	
5527	1N6304	50V, 70A(Tc100°), <50ns	BYW 07/50, BYW 08/50, BYW 94/50
5528	1N6304R..6306R	1N6304..6306	BYW 07/...R
5529	1N6305	1N6304, 100V	BYW 07/100, BYW 08/100, BYW 94/100
5530	1N6306	1N6304, 150V	BYW 07/150, BYW 08/150, BYW 94/150
5531	1N6307	40V	-
5532	1N631	60V, 60mA, <300ns	AAY 28, 1N276
5533	1N632	60V, <300ns	AAY 28, 1N276
5534	1N633	90V, 60mA, <300ns	AAY 28, 1N276

5535	1N634	125V, 100mA	-
5536	1N635	175V, 150mA	-
5537	1N636	50V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
5538	1N6373	5V, 1,5kW	1N5629...49, 1N6267...6387
5539	1N6374	1N6373, 8V	
5540	1N6375	1N6373, 10V	
5541	1N6376	1N6373, 12V	
5542	1N6377	1N6373, 15V	
5543	1N6378	1N6373, 18V	
5544	1N6379	1N6373, 22V	
5545	1N6380	1N6373, 36V	
5546	1N6381	1N6373, 45V	
5547	1N6382..6389	1N6373..6381, bidirecional	1N6036...55, 1N6138...58
5548	1N6391	45V, 25A(Tc125°)	BYS 31-..., BYS 32, BYV 121-45
5549	1N6392	45V, 60A(Tc115°)	BYS 50, BYS 32-45, MBR 6045
5550	1N64(A)	25V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
5551	1N643(A)	200V, 0,04A, <300ns	BA 195, BA 197...198, BAW 50, BAX 17
5552	1N645(A,B,GP,J)	225V, 0,4A	BA 157...159, BY 206...207, BY 404...405
5553	1N646(GP)	1N645, 300V	BA 157...159, BY 206...207, BY 404...405
5554	1N6461	5V, 2,5W, 500W(1ms)	BZW 06/..., BZW70/..., BZX70/..., BZY93/...
5555	1N6462	1N6461, 6V	
5556	1N6463	1N6461, 12V	
5557	1N6464	1N6461, 15V	
5558	1N6465	1N6461, 24V	
5559	1N6466	1N6461, 30,5V	
5560	1N6467	1N6461, 40,3V	
5561	1N6468	1N6461, 51,6V	
5562	1N647(GP)	1N645, 400V	BA 157...159, BY 207, BY 404...405
5563	1N6478	50V, 1A	BYM 11-50, BYM 12-50
5564	1N6479	1M6478, 100V	BYM 11-100, BYM 12-100
5565	1N648(GP)	1N645, 500V	BA 158...159, BY 207, BY 405, 1N4005
5566	1N6480	1M6478, 200V	BYM 11-200, BYM 12-200
5567	1N6481	1M6478, 400V	BYM 11-400, BYM 12-400
5568	1N6482	1M6478, 600V	BYM 11-600, BYM 12-600
5569	1N6483	1M6478, 800V	BYM 11-800, BYM 12-800
5570	1N6484	1M6478, 1000V	BYM 11-1000, BYM 12-1000
5571	1N649(GP)	1N645, 600V	BA 158...159, BY 207, BY 405, 1N4005
5572	1N6492	45V, 1,2A	BYS 22-45, BYS 26-45, MBR 350
5573	1N65	70V, 50mA	AA 113, 1N34, 1N54, 1N60
5574	1N658(A)	50V, 60mA, <300ns	BA 195, BAW 49, BAX 15...17, 1N3070
5575	1N659(A)	50V, 100mA, <300ns	BA 195, BAW 49, BAX 15...17, 1N3070
5576	1N66	60V, 50mA	AA 117...118, AA 132...134, 1N60
5577	1N660(A)	100V, 100mA, <300ns	BA 195, BAW 49, BAX 15...17, 1N3070
5578	1N661(A)	200V, 100mA, <300ns	BA 195, BA 197...98, BAW 50, BAX 17
5579	1N662(A)	80V, 40mA, <500ns	BA 195, BAW 49, BAX 15...17, 1N3070

5580	1N6620	200V, 1,2A, <30ns	BYD 73D...G, BYV 27/200
5581	1N6621	400V, 1,2A, <30ns	BYD 73G, BYD 74G
5582	1N6622	600V, 1,2A, <30ns	-
5583	1N6623	800V, 1A, <50ns	-
5584	1N6624	900V, 1A, <50ns	-
5585	1N6625	1000V, 1A, <60ns	-
5586	1N6626	200V, 2A, <30ns	BYD 74D...G, BYV 27/200
5587	1N6627	400V, 2A, <30ns	BYD 74G
5588	1N6628	600V, 2A, <30ns	-
5589	1N6629	800V, 1,4A, <50ns	-
5590	1N663(A)	80V, 60mA, <500ns	BA 195, BAW 49, BAX 15...17, 1N3070
5591	1N6630	900V, 1,4A, <50ns	-
5592	1N6631	1000V, 1,4A, <60ns	-
5593	1N6638	150V, 0,3A, <4,5ns	-
5594	1N664	8,2V, 5%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5230...76
5595	1N6642	100V, 0,3A, <5ns	-
5596	1N6643	75V, 0,3A, <6ns	BAV 10, BAW 55, BAW76
5597	1N665	1N664, 12V	
5598	1N666	1N664, 15V	
5599	1N667	1N664, 18V	
5600	1N668	1N664, 22V	
5601	1N669	1N664, 27V	
5602	1N67(A)	92V, 35mA	AA 113, AA 119, 1N34, 1N54, 1N60
5603	1N670	1N664, 68V	
5604	1N671	1N664, 100V	
5605	1N672	1N664, 150V	
5606	1N673	350V, 0,4A	BA 157...159, BY 206...207, BY 404...405
5607	1N674	1N664, 4,7V	1N664...
5608	1N675	1N664, 6,2V	1N664...
5609	1N676	100V, 0,2A	BA 157...159, BA 193...194, BA 199/250
5610	1N677	100V, 0,4A	BA 157...159, BA 193...194, BA 199/250
5611	1N678	200V, 0,2A	BA 157...159, BA 199/250, BAS 11
5612	1N679	200V, 0,4A	BA 157...159, BA 199/250, BAS 11
5613	1N68(A)	100V, 35mA	AA 117...118, AA 132...133
5614	1N681	300V, 0,075A	BA 199/350, BAS 11, BAY 21, BAY 88...90
5615	1N682	300V, 0,15A	BA 199/350, BAS 11, BAY 21, BAY 88...90
5616	1N683	400V, 0,075A	BA 157...159, BA 199/450, BAY 89...90
5617	1N684	400V, 0,15A	BA 157...159, BA 199/450, BAY 89...90
5618	1N685	500V, 0,075A	BA 158...159, BA 199/550, BAY 89...90
5619	1N686	500V, 0,15A	BA 158...159, BA 199/550, BAY 89...90
5620	1N687	600V, 0,075A	BA 158...159, BA 199/550, BAY 89...90
5621	1N689	600V, 0,15A	BA 158...159, BA 199/550, BAY 89...90
5622	1N69(A)	70V, 40mA	AA 117...118, AA 132...134, 1N34, 1N54
5623	1N690	36V, 0,25A, <800ns	BAV 17...21, BAW 48...50, BAY 72, BAX 12
5624	1N691	1N690, 80V	BAV 19...21, BAW 49...50, BAY 72, BAX 12

5625	1N692	1N690, 100V	BAV 19...21, BAW 49...50, BAY 72, BAX 12
5626	1N693	1N690, 130V	BAV 16, BAV 19...21, BAW 50, BAX 15
5627	1N695(A)	20..25V, 0,1..0,15A, 300ns	AAZ 49, AAZ 15, AAZ 17
5628	1N697	120V, 0,25A, <100ns	BA 197...98, BAV 19...21, BAW 50
5629	1N698	15V, 500ns	AAZ 49, AAZ 15, AAZ 18, 1N276
5630	1N699	105V, 30mA, <300ns	AAZ 28, 1N191, 1N633
5631	1N70(A)	120V, 30..50mA	AA 117...118, AA 132...133
5632	1N701	10V, 5%, 0,4W	BZX55/C10, BZX83/C10, ZPD10, 1N5240
5633	1N702	2,6V, 10%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5222...81
5634	1N702A...745A	1N702..745, 5%	
5635	1N702B...745B	1N702..745, 20%	
5636	1N703	1N702, 3,5V	
5637	1N704	1N702, 4,1V	
5638	1N705	1N702, 4,8V	
5639	1N706	1N702, 5,8V	
5640	1N707	1N702, 7,1V	
5641	1N708	1N702, 5,6V	
5642	1N709	1N702, 6,2V	
5643	1N710	1N702, 6,8V	
5644	1N711	1N702, 7,5V	
5645	1N712	1N702, 8,2V	
5646	1N713	1N702, 9,1V	
5647	1N714	1N702, 10V	
5648	1N715	1N702, 11V	
5649	1N716	1N702, 12V	
5650	1N717	1N702, 13V	
5651	1N718	1N702, 15V	
5652	1N719	1N702, 16V	
5653	1N72		-
5654	1N720	1N702, 18V	
5655	1N721	1N702, 20V	
5656	1N722	1N702, 22V	
5657	1N723	1N702, 24V	
5658	1N724	1N702, 27V	
5659	1N725	1N702, 30V	
5660	1N726	1N702, 33V	
5661	1N727	1N702, 36V	
5662	1N728	1N702, 39V	
5663	1N729	1N702, 43V	
5664	1N730	1N702, 47V	
5665	1N731	1N702, 51V	
5666	1N732	1N702, 56V	
5667	1N733	1N702, 62V	
5668	1N734	1N702, 68V	
5669	1N735	1N702, 75V	

5670	1N736	1N702, 82V	
5671	1N737	1N702, 91V	
5672	1N738	1N702, 100V	
5673	1N739	1N702, 110V	
5674	1N740	1N702, 120V	
5675	1N741	1N702, 130V	
5676	1N742	1N702, 150V	
5677	1N743	1N702, 160V	
5678	1N744	1N702, 180V	
5679	1N745	1N702, 200V	
5680	1N746	3,3V, 10%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5226...42
5681	1N746A...759A	1N746..759, 5%	
5682	1N747	1N746, 3,6V	
5683	1N748	1N746, 3,9V	
5684	1N749	1N746, 4,3V	
5685	1N75	100V, 50mA	AA 117...118, AA 132...133
5686	1N750	1N746, 4,7V	
5687	1N751	1N746, 5,1V	
5688	1N752	1N746, 5,6V	
5689	1N753	1N746, 6,2V	
5690	1N754	1N746, 6,8V	
5691	1N755	1N746, 7,5V	
5692	1N756	1N746, 8,2V	
5693	1N757	1N746, 9,1V	
5694	1N758	1N746, 10V	
5695	1N759	1N746, 12V	
5696	1N760	60V, 100ns	1N631, 1N633
5697	1N761	4,85V, 10%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5230...52
5698	1N761A...769A	1N761..769, 5%	
5699	1N762	1N761, 5,8V	
5700	1N763	1N761, 7,1V	
5701	1N764	1N761, 8,75V	
5702	1N765	1N761, 10,5V	
5703	1N766	1N761, 12,7V	
5704	1N767	1N761, 15,7V	
5705	1N768	1N761, 19V	
5706	1N769	1N761, 23,5V	
5707	1N770	20V, 40mA, 350ns	AAY 29, 1N191...192
5708	1N771(A,B)	100V, 50..75mA	AA 117...118, AA 132...133
5709	1N772(A)	80V, 50..65mA	AA 117...118, AA 132...133
5710	1N773(A)	75V, 50..65mA	AA 117...118, AA 132...134, 1N34, 1N54
5711	1N774(A)	70V, 50..65mA	AA 117...118, AA 132...134, 1N34, 1N54
5712	1N775	70V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
5713	1N776	30V, 45mA	AA 117...118, AA 132...134, 1N34, 1N54
5714	1N777	75V, 50mA, 500ns	AAY 28, 1N276, 1N633



5715	1N778	118V, 50mA, 300ns	BA 195, BAV 19...21, BAX 15...17
5716	1N779	200V, 50mA, 300ns	BA 195, BA 197...198, BAV 20...21, BAX 17
5717	1N781(A)	40V, 60mA, <500ns	AA 28, 1N191...192, 1N276
5718	1N788	60V, 200ns	-
5719	1N789	30V, 0,12A, <500ns	BA 195, BAV 17...21, BAX 15...17, 1N3070
5720	1N790	30V, 0,12A, <250ns	BA 195, BAV 17...21, BAX 15...17, 1N3070
5721	1N791	30V, 0,16A, <500ns	BA 195, BAV 17...21, BAX 15...17, 1N3070
5722	1N792	30V, 0,2A, <500ns	BA 195, BAV 17...21, BAX 15...17, 1N3070
5723	1N793	60V, 0,12A, <500ns	BA 195, BAV 18...21, BAX 15...17, 1N3070
5724	1N794	60V, 0,12A, <250ns	BA 195, BAV 18...21, BAX 15...17, 1N3070
5725	1N795	60V, 0,16A, <500ns	BA 195, BAV 18...21, BAX 15...17, 1N3070
5726	1N796	60V, 0,2A, <500ns	BA 195, BAV 18...21, BAX 15...17, 1N3070
5727	1N797	120V, 0,12A, <500ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5728	1N798	120V, 0,12A, <250ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5729	1N799	120V, 0,16A, <500ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5730	1N800	120V, 0,2A, <500ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5731	1N801	150V, 0,12A, <500ns	BA 195, BAV 20...21, BAX 15...17, 1N3070
5732	1N802	150V, 0,16A, <500ns	BA 195, BAV 20...21, BAX 15...17, 1N3070
5733	1N803	200V, 0,12A, <500ns	BA 195, BA 197...198, BAV 20...21
5734	1N804	200V, 0,16A, <500ns	BA 195, BA 197...198, BAV 20...21
5735	1N805	40V	AA 117...118, AA 132...134, 1N34, 1N54
5736	1N806	125V, 60mA, <300ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5737	1N807	200V, 60mA, <300ns	BA 195, BA 197...198, BAV 20...21, BAX 17
5738	1N808	110V, 100mA, <300ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5739	1N809	220V, 100mA, <300ns	BA 195, BA 197...198, BAV 20...21, BAX 17
5740	1N81(A)	50V, 30mA	AA 117...118, AA 132...134, 1N60
5741	1N810	50V, <50ns	BY 208/600, BY 295/150, BY 406...407
5742	1N811	30V, 0,04A, <250ns	BAV 17...21, BAX 15...17, 1N3070
5743	1N812	40V, 0,06A, <250ns	BAV 18...21, BAX 15...17, 1N3070
5744	1N813	20V, 0,075A, <250ns	BAV 17...21, BAX 15...17, 1N3070
5745	1N814	50V, 0,06A, <250ns	BAV 18...21, BAX 15...17, 1N3070
5746	1N815	25V, 0,12A, <250ns	BAV 17...21, BAX 15...17, 1N3070
5747	1N816	0,58..0,7V	BA 220, BZ 102/0V7, BZX55/C0V8, BZX62
5748	1N817	200V, <1µs	BA 147/230, BA 190, 1N5195...96
5749	1N818	80V, 0,055A, <500ns	BA 195, BAV 19...20, BAX 15...17, 1N3070
5750	1N82(A)		-
5751	1N821(A)	6,2V, 5%, 0,25W	BZV 10, BZV 27, BZX 90
5752	1N822(A)	6,2V, 5%, 0,25W	-
5753	1N823(A)	6,2V, 5%, 0,25W	BZV 11, BZV 28, BZX 91
5754	1N824(A)	6,2V, 5%, 0,25W	-
5755	1N825(A)	6,2V, 5%, 0,25W	BZV 12, BZV 29, BZX 92
5756	1N826(A)	6,55V, 5%, 0,25W	BZV 12, BZV 29, BZX 92
5757	1N827(A)	6,2V, 5%, 0,25W	BZV 13, BZV 30, BZX 93
5758	1N828(A)	6,55V, 5%, 0,25W	BZV 13, BZV 30, BZX 93
5759	1N829(A)	6,2V, 5%, 0,25W	BZV 14, BZV 51, BZX 94



5760	1N83	375V	-
5761	1N830(A)		-
5762	1N831(A,B,C)		-
5763	1N832(A,B,C)		-
5764	1N833(A)		-
5765	1N835	30V, 70mA, <500ns	AAZ 49, AAZ 15, AAZ 17
5766	1N836	5V	-
5767	1N837(A)	100V, 0,1A, <500ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5768	1N838	150V, 0,1A, <500ns	BA 195, BAV 20...21, BAX 15...17, 1N3070
5769	1N839	200V, 0,1A, <500ns	BA 195, BA 197...198, BAV 20...21, BAX 17
5770	1N84	25V	AA 113, AA 119, 1N34, 1N54, 1N60
5771	1N840	50V, 0,1A, <300ns	BA 195, BAV 18...21, BAX 15...17, 1N3070
5772	1N841	150V, 0,1A, <300ns	BA 195, BAV 20...21, BAX 15...17, 1N3070
5773	1N842	200V, 0,1A, <300ns	BA 195, BA 197...198, BAV 20...21, BAX 17
5774	1N843	250V, 0,1A, <300ns	BA 198, BAV 21, BAW 173
5775	1N844	100V, 0,2A, <500ns	BA 195, BAV 19...21, BAX 15...17, 1N3070
5776	1N845	200V, 0,2A, <500ns	BA 195, BA 197...198, BAV 19...21, BAX 17
5777	1N846	50V, 0,2A	BA 157...159, BAY 86...90, BY 204/4
5778	1N847	1N846, 100V	BA 157...159, BAY 87...90, BY 204/4
5779	1N848	1N846, 200V	BA 157...159, BAY 88...90, BY 204/4
5780	1N849	1N846, 300V	BA 157...159, BAY 88...90, BY 204/4
5781	1N850	1N846, 400V	BA 157...159, BAY 89...90, BY 204/4
5782	1N851	1N846, 500V	BA 158...159, BAY 89...90, BY 204/8
5783	1N852	1N846, 600V	BA 158...159, BAY 89...90, BY 204/8
5784	1N853	1N846, 700V	BA 158...159, BAY 90...91, BY 204/8
5785	1N854	1N846, 800V	BA 158...159, BAY 90...91, BY 204/8
5786	1N855	1N846, 900V	BA 159, BAY 90...91, BY 204/10
5787	1N856	1N846, 1000V	BA 159, BAY 90...91, BY 204/10
5788	1N857	50V, 0,15A	BA 157...159, BAY 86...90, BY 204/4
5789	1N858	1N857, 100V	BA 157...159, BAY 87...90, BY 204/4
5790	1N859	1N857, 200V	BA 157...159, BAY 88...90, BY 204/4
5791	1N86	70V, 50mA	AA 117...118, AA 132...134
5792	1N860	1N857, 300V	BA 157...159, BAY 88...90, BY 204/4
5793	1N861	1N857, 400V	BA 157...159, BAY 89...90, BY 204/4
5794	1N862	1N857, 500V	BA 158...159, BAY 89...90, BY 204/8
5795	1N863	1N857, 600V	BA 158...159, BAY 89...90, BY 204/8
5796	1N864	1N857, 700V	BA 158...159, BAY 90...91, BY 204/8
5797	1N865	1N857, 800V	BA 158...159, BAY 90...91, BY 204/8
5798	1N866	1N857, 900V	BA 159, BAY 90...91, BY 204/10
5799	1N867	1N857, 1000V	BA 159, BAY 90...91, BY 204/10
5800	1N868	50V, 0,1A	BA 157...159, BAY 86...90, BY 204/4
5801	1N869	1N868, 100V	BA 157...159, BAY 87...90, BY 204/4
5802	1N87(A..T)	25..30V, 30..50mA	AA 112...114, AA 119, 1N34, 1N54, 1N60
5803	1N870	1N868, 200V	BA 157...159, BAY 88...90, BY 204/4
5804	1N871	1N868, 300V	BA 157...159, BAY 88...90, BY 204/4

5805	1N872	1N868, 400V	BA 157...159, BAY 89...90, BY 204/4
5806	1N873	1N868, 500V	BA 158...159, BAY 89...90, BY 204/8
5807	1N874	1N868, 600V	BA 158...159, BAY 89...90, BY 204/8
5808	1N875	1N868, 700V	BA 158...159, BAY 90...91, BY 204/8
5809	1N876	1N868, 800V	BA 158...159, BAY 90...91, BY 204/8
5810	1N877	1N868, 900V	BA 159, BAY 90...91, BY 204/10
5811	1N878	1N868, 1000V	BA 159, BAY 90...91, BY 204/10
5812	1N879	50V, 0,05A	BA 157...159, BAY 86...90, BY 204/4
5813	1N88	100V	AA 117...118, AA 132...133
5814	1N880	1N879, 100V	BA 157...159, BAY 87...90, BY 204/4
5815	1N881	1N879, 200V	BA 157...159, BAY 88...90, BY 204/4
5816	1N882	1N879, 300V	BA 157...159, BAY 88...90, BY 204/4
5817	1N883	1N879, 400V	BA 157...159, BAY 89...90, BY 204/4
5818	1N884	1N879, 500V	BA 158...159, BAY 89...90, BY 204/8
5819	1N885	1N879, 600V	BA 158...159, BAY 89...90, BY 204/8
5820	1N886	1N879, 700V	BA 158...159, BAY 90...91, BY 204/8
5821	1N887	1N879, 800V	BA 158...159, BAY 90...91, BY 204/8
5822	1N888	1N879, 900V	BA 159, BAY 90...91, BY 204/10
5823	1N889	1N879, 1000V	BA 159, BAY 90...91, BY 204/10
5824	1N89	80V, 30mA	AA 117...118, AA 132...133
5825	1N890	80V, 0,1A	BA 147/100, BA 188...190, 1N5606...09
5826	1N891	60V, 0,2A, 300ns	BA 197...198, BAV 18...21, BAX 15...17
5827	1N892	120V, 0,2A, 300ns	BA 197...198, BAV 20...21, BAX 15...17
5828	1N893	240V, 0,2A, 300ns	BA 173, BA 198, BAV 21
5829	1N897	50V, 0,03A, <1μs	BAX 85, BAX 89, BAX 90, BAX 94
5830	1N898	50V, 0,06A, <300ns	BAX 85, BAX 89, BAX 90, BAX 94
5831	1N899	100V, 0,03A, <300ns	BA 197...198, BAV 19...21, BAX 15...17
5832	1N90	60V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
5833	1N900	100V, 0,05A, <300ns	BA 197...198, BAV 19...21, BAX 15...17
5834	1N901	100V, 0,06A, <300ns	BA 197...198, BAV 19...21, BAX 15...17
5835	1N902	200V, 0,03A, <300ns	BA 197...198, BAV 20...21, BAX 17
5836	1N903(A)	20..40V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5837	1N904(A)	30V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5838	1N905(A)	20V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5839	1N906(A)	20V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5840	1N907(A)	30V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5841	1N908(A)	40V, 0,05..0,075A, <4ns	BA 218, BAX 13, BAX 91, 1N4148
5842	1N909	60V, 100mA	AA 136, 1N270, 1N634...635
5843	1N91	100V, 1A	-
5844	1N910	1N909, 30V	AA 135...136, 1N270, 1N634...635
5845	1N911	1N909, 30V	AA 135...136, 1N270, 1N634...635
5846	1N912(A)	0,62V, 0,5W	-
5847	1N913(A)	0,62V, 0,6W	-
5848	1N914(A,B)	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
5849	1N915	65V, 0,075A, <10ns	BAW 62, BAX 95, 1N4148...49, 1N4151

5850	1N916(A,B)	100V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
5851	1N917	40V, 0,05A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4151
5852	1N918		-
5853	1N919	150V, 0,1A, <300ns	BA 195, BAV 20...21, BAX 15...17, 1N3070
5854	1N92	1N91, 200V	-
5855	1N920	36V, 0,25A, <300ns	BA 197...189, BAV 17...21, BAX 15...17
5856	1N921	70V, 0,25A, <300ns	BA 197...189, BAV 19...21, BAX 15...17
5857	1N922	100V, 0,25A, <300ns	BA 197...189, BAV 19...21, BAX 15...17
5858	1N923	130V, 0,25A, <300ns	BA 197...189, BAV 19...21, BAX 15...17
5859	1N924	60V, 2μs	BA 127, BA 188...190, BAY 19...21
5860	1N925	40V, 0,12A, <150ns	BA 195, BAX 16...17, BAY 41...43, 1N3070
5861	1N926	40V, 0,12A, <150ns	BA 195, BAX 16...17, BAY 41...43, 1N3070
5862	1N927	65V, 0,12A, <150ns	BA 195, BAX 16...17, BAY 42...43, 1N3070
5863	1N928	1N927, 120V	BA 195, BAX 16...17, BAV 19...21, 1N3070
5864	1N929	23V, 0,25A	BA 192...194, BAW 51...52, BAY 17...21
5865	1N93(A)	1N91, 300V	-
5866	1N930	58V, 0,25A	BA 193...194, BAW 51...52, BAY 19...21
5867	1N931	115V, 0,25A	BA 194, BAW 52, BAY 20...21, BAY 45
5868	1N932	230V, 0,25A	BA 199/250, BAY 21, BAY 46, BAY 88
5869	1N933	100V, 30mA, <400ns	AAZ 28, AAZ 15, 1N633
5870	1N934	60V, 30mA, 1μs	BA 127, BA 147/100, BA 188...190
5871	1N935(A,B)	9V, 5%, 0,5W	1N4765
5872	1N936(A,B)	9V, 5%, 0,5W	1N4766, 1N4771
5873	1N937(A,B)	9V, 5%, 0,5W	1N4767, 1N4772
5874	1N938(A,B)	9V, 5%, 0,5W	1N4768, 1N4773
5875	1N939(A,B)	9V, 5%, 0,5W	1N4769, 1N4774
5876	1N940(A,B)	9V, 5%, 0,5W	-
5877	1N941(A,B)	11,7V, 5%, 0,5W	1N3580
5878	1N942(A,B)	11,7V, 5%, 0,5W	1N3581
5879	1N943(A,B)	11,7V, 5%, 0,5W	1N3582
5880	1N944(A,B)	11,7V, 5%, 0,5W	1N3583
5881	1N945(A,B)	11,7V, 5%, 0,5W	1N3584
5882	1N946(A,B)	11,7V, 5%, 0,5W	-
5883	1N947	600V, 0,4A	BA 158...159, BY 204/8, BY 207, BY 405
5884	1N948	36V, 0,08A, <1μs	BA 127, BA 147/50, BA 187...190
5885	1N949	50V, 0,5A	AA 117...118, AA 132...134, 1N34, 1N54
5886	1N95	60V, 30mA	AA 117...118, AA 132...134, 1N34, 1N54
5887	1N950(A)	130V, 6..88pF	-
5888	1N951(A)	80V, 12..120pF	-
5889	1N952(A)	60V, 20..170pF	-
5890	1N953(A)	25V, 46..240pF	-
5891	1N954	25V, 14..88pF	-
5892	1N955	25V, 22..120pF	-
5893	1N956	25V, 32..170pF	-
5894	1N957	6,8V, 20%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5235...81

5895	1N957A...992A	1N957..992, 10%	
5896	1N957B...992B	1N957..992, 5%	
5897	1N958	1N957, 7,5V	
5898	1N959	1N957, 8,2V	
5899	1N96(A)	75V, 30..70mA	AA 117...118, AA 132...134, 1N34, 1N54
5900	1N960	1N957, 9,1V	
5901	1N961	1N957, 10V	
5902	1N962	1N957, 11V	
5903	1N963	1N957, 12V	
5904	1N964	1N957, 13V	
5905	1N965	1N957, 15V	
5906	1N966	1N957, 16V	
5907	1N967	1N957, 18V	
5908	1N968	1N957, 20V	
5909	1N969	1N957, 22V	
5910	1N97(A)	80..92V, 30mA	AA 117...118, AA 132...133
5911	1N970	1N957, 24V	
5912	1N971	1N957, 27V	
5913	1N972	1N957, 30V	
5914	1N973	1N957, 33V	
5915	1N974	1N957, 36V	
5916	1N975	1N957, 39V	
5917	1N976	1N957, 43V	
5918	1N977	1N957, 47V	
5919	1N978	1N957, 51V	
5920	1N979	1N957, 56V	
5921	1N98(A)	80V, 30..70mA	1N34, 1N54
5922	1N980	1N957, 62V	
5923	1N981	1N957, 68V	
5924	1N982	1N957, 75V	
5925	1N983	1N957, 82V	
5926	1N984	1N957, 91V	
5927	1N985	1N957, 100V	
5928	1N986	1N957, 110V	
5929	1N987	1N957, 120V	
5930	1N988	1N957, 130V	
5931	1N989	1N957, 150V	
5932	1N99(A)	80..92V, 30mA	AA 117...118, AA 132...133
5933	1N990	1N957, 160V	
5934	1N991	1N957, 180V	
5935	1N992	1N957, 200V	
5936	1N993	20V, 0,02A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
5937	1N994	6,5V, 0,02A, <2ns	-
5938	1N995	10V, 0,03A, <6ns	-
5939	1N996	20V, 0,05A, <300ns	AAY 27...28, 1N631, 1N633, 1N3592

5940	1N997	35V, 0,05A, 150ns	BAX 85, BAX 89...90, BAX 94, 1N4148
5941	1N998	150V	BA 157...159, BA 194, BAS 11, BAW 52
5942	1N999	100V, <4ns	BA 219, BAX 96
5943	1O	2SD2359	2SD2359
5944	1OP	2SK662-P	2SK662
5945	1OP	2SK198-P	2SK198
5946	1OQ	2SK662-Q	2SK662
5947	1OQ	2SK198-Q	2SK198
5948	1OR	2SK198-R	2SK198
5949	1OR	2SK662-R	2SK662
5950	1P	KST 2222A	KST 2222A
5951	1P	MMBT 2222A	MMBT 2222A
5952	1P	YTS 2222A	YTS 2222A
5953	1P	FMMT 2222A	FMMT 2222A
5954	1P137	RT 1P137L	RT 1P137L
5955	1P643	50V, 1A	BY 201/2, BYX 55/350, RGP 10A
5956	1P644	1P643, 100V	BY 201/2, BYX 55/350, RGP 10B
5957	1P645	1P643, 225V	BY 201/3, BYX 55/350, RGP 10G
5958	1P646	1P643, 300V	BY 201/3, BYX 55/350, RGP 10G
5959	1P647	1P643, 400V	BY 201/4, BYX 55/600, RGP 10G
5960	1P648	1P643, 500V	BY 201/5, BYX 55/600, RGP 10J
5961	1P649	1P643, 600V	BY 201/6, BYX 55/600, RGP 10J
5962	1P664	BY 201/12	BY 201/12
5963	1PS181	1PS193	-
5964	1PS184	1PS193	-
5965	1PS193	80V, 0,215A, <4ns	-
5966	1PS226	1PS193	-
5967	1Q	KST 5088	KST 5088
5968	1Q	MMBT 5088	MMBT 5088
5969	1R	KST 5089	KST 5089
5970	1R	MMBT 5089	MMBT 5089
5971	1R	2SC4929	2SC4929
5972	1RQ	2SB1585-Q	2SB1585
5973	1RQ	2SB970-Q	2SB970
5974	1RR	2SB1585-R	2SB1585
5975	1RR	2SB970-R	2SB970
5976	1RS	2SB1585-S	2SB1585
5977	1RS	2SB970-S	2SB970
5978	1S	MMBT 2369A	MMBT 2369A
5979	1S	2SD2413	2SD2413
5980	1S020	100V, 1,5A	BY 251...255, BY 226...227, 1N5392...99
5981	1S021	1S020, 200V	BY 251...255, BY 226...227, 1N5393...99
5982	1S023	1S020, 400V	BY 252...255, BY 226...227, 1N5395...99
5983	1S025	1S020, 600V	BY 253...255, BY 226...227, 1N5397...99
5984	1S027	1S020, 800V	BY 254...255, BY 227, 1N5398...99

5985	1S100	150V, 0,75A	BY 126...127, BY 133...135, 1N4003...07
5986	1S100	150V, 0,75A	BY 126...127, BY 133...135, 1N4003...07
5987	1S1000(A)	890MHz	-
5988	1S1001	20V, 0,05A, <200ns	AA Y 28, 1N631, 1N633
5989	1S1002	25V, 0,1A, <300ns	AA Y 49, AA Z 15, AA Z 17
5990	1S1003	125V, 0,075A	AA 133, 1N634...635
5991	1S1004	100V, 0,05A	AA 117...118, AA 132...133
5992	1S1005	100V, 0,05A	AA 117...118, AA 132...133
5993	1S1006	60V, 0,05A	AA 117...118, AA 132...133
5994	1S1007	60V, 0,075A	AA 117...118, AA 132...133
5995	1S1008	25V, 0,08A	AA 117...118, AA 132...134, 1N60
5996	1S1009	25V, 0,05A	AA 117...118, AA 132...134, 1N60
5997	1S100R...109R	1S100..109	1S100...109
5998	1S101	1S100, 200V	BY 126...127, BY 133...134, 1N4003...07
5999	1S101	1S100, 200V	BY 126...127, BY 133...134, 1N4003...07
6000	1S1010	30V, 0,05A	AA 117...118, AA 132...134, 1N60
6001	1S1011(L,S)	0,2..0,35V, 0,05W	-
6002	1S1012	1S871	1S871
6003	1S1013	1S871A	1S871A
6004	1S1014	1S871B	1S871B
6005	1S1015	1S871C	1S871C
6006	1S1016	1S871D	1S871D
6007	1S1017	1S871E	1S871E
6008	1S1018	1S871F	1S871F
6009	1S1019	1S871G	1S871G
6010	1S102	1S100, 300V	BY 126...127, BY 133...134, 1N4004...07
6011	1S102	1S100, 300V	BY 126...127, BY 133...134, 1N4004...07
6012	1S1020	1S871H	1S871H
6013	1S1021	1S881	1S881
6014	1S1022	1S881A	1S881A
6015	1S1023	1S881B	1S881B
6016	1S1024	1S881C	1S881C
6017	1S1025	1S881D	1S881D
6018	1S1026	1S881E	1S881E
6019	1S1027	1S881	1S881
6020	1S1028	1S881A	1S881A
6021	1S1029	1S881B	1S881B
6022	1S103	1S100, 400V	BY 126...127, BY 133...134, 1N4004...07
6023	1S1030	1S881C	1S881C
6024	1S1031	1S881D	1S881D
6025	1S1032	1S881E	1S881E
6026	1S1033	200V, 200A(Tc110°)	-
6027	1S1034	1S1033, 300V	-
6028	1S1035	1S1033, 400V	-
6029	1S1036	1S1033, 600V	-

6030	1S1037	1S1033, 800V	-
6031	1S1038	1S1033, 1000V	-
6032	1S104	1S100, 500V	BY 126...127, BY 133...134, 1N4005...07
6033	1S1043	400V, 0,75A	BY 126...127, BY 133...134, 1N4004...07
6034	1S1044	1S1043, 600V	BY 126...127, BY 133...134, 1N4005...07
6035	1S1045	1S1043, 800V	BY 127, BY 133, BY 227, 1N4006...07
6036	1S1046	1S1043, 1000V	BY 127, BY 133, BY 227, 1N4007
6037	1S1047	1S1043, 1200V	BY 127, BY 133, BY 227, GP 10Q
6038	1S1048	1S1043, 1400V	BY 400, BY 448, DM 513, GP 10V
6039	1S1049	1S1043, 1600V	BY 400, DM 513, EM 516, GP 10Y
6040	1S105	1S100, 600V	BY 126...127, BY 133...134, 1N4005...07
6041	1S1050	1S1043, 1800V	DM 516
6042	1S1051	1S1043, 2000V	-
6043	1S1052	300V, 3A	BYX 38/300, BYX 39/600
6044	1S1052R...1059R	1S1052..1059	BYX 38/...R, BYX 39/...R
6045	1S1053	1S1052, 400V	BYX 38/600, BYX 39/600
6046	1S1054	1S1052, 600V	BYX 38/600, BYX 39/600
6047	1S1055	1S1052, 800V	BYX 38/900, BYX 39/900
6048	1S1056	1S1052, 1000V	BYX 38/1200, BYX 39/1000
6049	1S1057	1S1052, 1200V	BYX 38/1200, BYX 39/1200
6050	1S1058	1S1052, 1400V	BYX 39/1400
6051	1S1059	1S1052, 1600V	-
6052	1S106	1S100, 700V	BY 127, BY 133, BY 227, 1N4006...07
6053	1S1061	1S1043, 100V, 1A	1S1043
6054	1S1062	1S1043, 200V, 1A	1S1043
6055	1S1063	1S1043, 1A	1S1043
6056	1S1064	1S1044, 1A	1S1044
6057	1S1065	1S1045, 1A	1S1045
6058	1S1066	1S1046, 1A	1S1046
6059	1S1067	1S1047, 1A	1S1047
6060	1S1068	1S1048, 1A	1S1048
6061	1S1069	1S1049, 1A	1S1049
6062	1S107	1S100, 800V	BY 127, BY 133, BY 227, 1N4006...07
6063	1S1070	1S1050, 1A	1S1050
6064	1S1071	100V, 1,5A	BY 226...228, BY 251...255, 1N5392...99
6065	1S1072	1S1071, 200V	BY 226...228, BY 251...255, 1N5393...99
6066	1S1073	1S1071, 400V	BY 226...228, BY 252...255, 1N5395...99
6067	1S1074	1S1071, 600V	BY 226...228, BY 253...255, 1N5397...99
6068	1S1075	1S1071, 800V	BY 227...228, BY 254...255, 1N5398...99
6069	1S1076	1S1071, 1000V	BY227...228, BY255, BYW17/1000, 1N5399
6070	1S1077	1S1071, 1200V	BY 227...228, BY 255, BYW 17/1200
6071	1S1078	1S1071, 1400V	BY 228, BY 400, BY 448
6072	1S1079	1S1071, 1600V	BY 400
6073	1S108	1S100, 900V	BY 127, BY 133, BY 227, 1N4007
6074	1S1080	1S1071, 1800V	-



6075	1S1081	200V, 3A	BYX 38/300, BYX 39/600
6076	1S109	1S100, 1000V	BY 127, BY 133, BY 227, 1N4007
6077	1S1094	6,2..8V, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5234...60
6078	1S1095	1S1094, 7,5..10V	
6079	1S1096	1S1094, 9..12V	
6080	1S1097	1S1094, 11..14,5V	
6081	1S1098	1S1094, 13,5..18V	
6082	1S1099	1S1094, 17..21V	
6083	1S11	60V, 50mA	AA 113, 1N34, 1N60
6084	1S1100	1S1094, 20..27V	
6085	1S1101	1S1094, 25..32V	
6086	1S1102	1S1094, 30..42V	
6087	1S1103	8kV, 0,15A	SMH-08
6088	1S1104	1S1103, 10kV	SMH-10
6089	1S1105	1S1103, 16kV	SMH-16
6090	1S1106	1S1103, 20kV	RMH-20
6091	1S111[Japan]	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
6092	1S111[Texas]	225V, 0,4A	BA 157...159, BY 204/4, 1N4004...07
6093	1S112[Japan]	1S111[Japan], 200V	BY 126...127, BY 133...134, 1N4003...07
6094	1S112[Texas]	1S111[Texas], 300V	BA 157...159, BY 204/4, 1N4004...07
6095	1S113[Japan]	1S111[Japan], 300V	BY 126...127, BY 133...134, 1N4004...07
6096	1S113[Texas]	1S111[Texas], 400V	BA 157...159, BY 204/4, 1N4004...07
6097	1S114[Japan]	1S111[Japan], 400V	BY 126...127, BY 133...134, 1N4004...07
6098	1S1144	90V, 0,4A, <20ns	BAV 14...16
6099	1S1145	90V, 0,9A, <20ns	-
6100	1S1146	40V, 0,1A, <6,9ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6101	1S1147	40V, 0,045A, <6,9ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6102	1S1148	60V, 0,25A, <7ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6103	1S1149	70V, 0,25A, <7ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6104	1S115[Japan]	1S111[Japan], 500V	BY 126...127, BY 133...134, 1N4005...07
6105	1S115[Texas]	1S111[Texas], 600V	BA 158...159, BY 204/8, 1N4005...07
6106	1S1150	400V, 280A(Tc110°)	-
6107	1S1151	1S1150, 800V	-
6108	1S1152	1S1150, 1000V	-
6109	1S1153	1S1150, 1200V	-
6110	1S116[Japan]	1S111[Japan], 600V	BY 126...127, BY 133...134, 1N4005...07
6111	1S1160	3..4,5V, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5225...60
6112	1S1161	1S1160, 4,3..5,4V	
6113	1S1162	1S1160, 5,2..6,4V	
6114	1S1163	1S1160, 6,2..8V	
6115	1S1164	1S1160, 7,5..10V	
6116	1S1165	1S1160, 9..12V	
6117	1S1166	1S1160, 11..14,5V	
6118	1S1167	1S1160, 13,5..18V	
6119	1S1168	1S1160, 17..21V	



6120	1S1169	1S1160, 20..27V	
6121	1S117[Japan]	1S111[Japan], 700V	BY 127, BY 133, BY 227, 1N4006...07
6122	1S117[Texas]	1S111[Texas], 800V	BA 159, BY 204/8, 1N4006...07
6123	1S1170	1S1160, 25..32V	
6124	1S1171	1S1160, 30..42V	
6125	1S1172	4,3..5,4V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5916...43
6126	1S1173	1S1172, 5,2..6,4V	
6127	1S1174	1S1172, 6,2..8V	
6128	1S1175	1S1172, 7,5..10V	
6129	1S1176	1S1172, 9..12V	
6130	1S1177	1S1172, 11..14,5V	
6131	1S1178	1S1172, 13,5..18V	
6132	1S1179	1S1172, 17..21V	
6133	1S118[Japan]	1S111[Japan], 800V	BY 127, BY 133, BY 227, 1N4006...07
6134	1S1180	1S1172, 20..27V	
6135	1S1181	1S1172, 25..32V	
6136	1S1182	1S1172, 30..40V	
6137	1S1183	1S1172, 38,5..47,5V	
6138	1S1184	1S1172, 45,5..57V	
6139	1S1185	4,3..5,4V, 3W	BZX98/..., BZY93..., ZX..., 1N2970...99
6140	1S1186	1S1185, 5,2..6,4V	
6141	1S1187	1S1185, 6,2..8V	
6142	1S1188	1S1185, 7,5..10V	
6143	1S1189	1S1185, 9..12V	
6144	1S119[Japan]	1S111[Japan], 50V	BY 126...127, BY 133...135, 1N4001...07
6145	1S1190	1S1185, 11..14,5V	
6146	1S1191	1S1185, 13,5..18V	
6147	1S1192	1S1185, 17..21V	
6148	1S1193	1S1185, 20..27V	
6149	1S1194	1S1185, 25..32V	
6150	1S1195	1S1185, 30..40V	
6151	1S1196	1S1185, 38,5..47,5V	
6152	1S1197	1S1185, 49,5..57V	
6153	1S1198(A)		-
6154	1S1199(A)		-
6155	1S12	22,5V, 50mA	AA 112...114, 1N34, 1N54, 1N60
6156	1S120[Japan]	50V, 0,6A	BY 126...127, BY 133...135, 1N4001...07
6157	1S120[Texas]	50V, 0,2A	BA 157...159, BY 204/4, BY 206...207
6158	1S1200(A)		-
6159	1S1207	1000V, 10A(Tc120°)	1N4510...11
6160	1S1208	100V, 0,2A	BA 188...190, BAY 19...21, BAY 45...46
6161	1S1209	0,63..0,69V(10mA), 0,1W	BA220, BZ102/0V7, BZX55/C0V8, ZPD1
6162	1S121[Japan]	1S120[Japan], 100V	BY 126...127, BY 133...135, 1N4002...07
6163	1S121[Texas]	1S120[Texas], 150V	BA 157...159, BY 204/4, BY 206...207
6164	1S1210	0,56..0,61V(1,5mA), 0,06W	-

6165	1S1211	0,59..0,64V(1,5mA), 0,06W	-
6166	1S1212	0,62..0,67V(1,5mA), 0,06W	BA220, BZ102/0V7, BZX55/C0V8, ZPD1
6167	1S1213	50V, 0,06A, <250ns	AAZ 15, AAZ 17, 1N276
6168	1S1214	50V, 0,06A, <250ns	AAZ 15, AAZ 17, 1N276
6169	1S1215	40V, 0,06A, <200ns	AAZ 15, AAZ 17, 1N276
6170	1S1216	30V, 0,06A, <150ns	AAZ 15, AAZ 17, 1N276
6171	1S1217	75V, 0,1A, <750ns	AAZ 15
6172	1S1218	100V, 0,1A, <750ns	AAZ 15
6173	1S1219(H)	30V, 0,1A, <4ns	BA 317, BAY 71, 1N4148...49, 1N4151
6174	1S122[Japan]	1S120[Japan], 200V	BY 126...127, BY 133...134, 1N4003...07
6175	1S1220(H)	30V, 0,3A, <4ns	BAW 76
6176	1S1221	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
6177	1S1222	1S1221, 600V	BY 126...127, BY 133...134, 1N4005...07
6178	1S1223	1S1221, 1000V	BY 127, BY 133, BY 227, 1N4007
6179	1S1224	600V, 0,1A	BA 158...159, BAY 89...91, BY 203/12
6180	1S1225	1S1224, 800V	BA 158...159, BAY 90...91, BY 203/12
6181	1S1225A	1S1224, 1000V	BA 159, BAY 90...91, BY 203/12, SHG 1
6182	1S1226	1S1224, 1500V	BAY 91, BY 203/16, BY 584, SHG 1,5
6183	1S123[Japan]	1S120[Japan], 300V	BY 126...127, BY 133...134, 1N4004...07
6184	1S1230(H,N)	400V, 0,5A	BY 126...127, BY 133...134, 1N4004...07
6185	1S1231(H,N)	1S1230, 500V	BY 126...127, BY 133...134, 1N4005...07
6186	1S1232(H,N)	1S1230, 600V	BY 126...127, BY 133...134, 1N4005...07
6187	1S1233(H,N)	1S1230, 800V	BY 127, BY 133, BY 227, 1N4006...07
6188	1S1234(H,N)	1S1230, 1000V	BY 127, BY 133, BY 227, 1N4007
6189	1S1235	75..90V, 1W	BZW22/C82, BZX61/C82, ZPY82, 1N5947
6190	1S1236	Ub18..32V, Ib<0,2mA, Itsm2A	1N5760, N 413L, D 3202U
6191	1S1237	300V, 0,01A, <1,8μs	BA 147/300, BAY 21, BAY 46, BAY 88
6192	1S1238	1S1237, 500V	BA 158...159, BAY 89...90, BAY 92
6193	1S1239	25V, 0,03A	AA 113...114, AA 119, 1N34, 1N54, 1N60
6194	1S124[Japan]	1S120[Japan], 400V	BY 126...127, BY 133...134, 1N4004...07
6195	1S1240		-
6196	1S1241		-
6197	1S1242		-
6198	1S1243		-
6199	1S1244	22,5V, 0,05A	AA 112...114, AA 119, 1N34, 1N54, 1N60
6200	1S1245	115V, 0,05A	AA 117...118, AA 132...133, 1N634...35
6201	1S1246	115V, 0,05A	AA 117...118, AA 132...133, 1N634...35
6202	1S1247	500V, 200A(Tc100°)	-
6203	1S1248	1S247, 600V	-
6204	1S1249	1S247, 800V	-
6205	1S125[Japan]	1S120[Japan], 500V	BY 126...127, BY 133...134, 1N4005...07
6206	1S1250	1S247, 1000V	-
6207	1S1251	1S247, 1300V	-
6208	1S126[Japan]	1S120[Japan], 600V	BY 126...127, BY 133...134, 1N4005...07
6209	1S1260	150V, 3A	BYX 38/300, BYX 39/600

6210	1S1260R...1269R	1S1260..1269	BYX 38/...R, BYX 39/...R
6211	1S1261	1S1260, 200V	BYX 38/300, BYX 39/600
6212	1S1262	1S1260, 300V	BYX 38/300, BYX 39/600
6213	1S1263	1S1260, 400V	BYX 38/600, BYX 39/600
6214	1S1264	1S1260, 500V	BYX 38/600, BYX 39/600
6215	1S1265	1S1260, 600V	BYX 38/600, BYX 39/600
6216	1S1266	1S1260, 700V	BYX 38/900, BYX 39/800
6217	1S1267	1S1260, 800V	BYX 38/900, BYX 39/800
6218	1S1268	1S1260, 900V	BYX 38/900, BYX 39/1000
6219	1S1269	1S1260, 1000V	BYX 38/1200, BYX 39/1000
6220	1S127	75V, 30mA	AA 117...118, AA 132...133, 1N634
6221	1S1270	150V, 6A	BYX 38/300, BYX 39/600
6222	1S1270R...1279R	1S1270..1279	BYX 38/...R, BYX 39/...R
6223	1S1271	1S1270, 200V	BYX 38/300, BYX 39/600
6224	1S1272	1S1270, 300V	BYX 38/300, BYX 39/600
6225	1S1273	1S1270, 400V	BYX 38/600, BYX 39/600
6226	1S1274	1S1270, 500V	BYX 38/600, BYX 39/600
6227	1S1275	1S1270, 600V	BYX 38/600, BYX 39/600
6228	1S1276	1S1270, 700V	BYX 38/900, BYX 39/800
6229	1S1277	1S1270, 800V	BYX 38/900, BYX 39/800
6230	1S1278	1S1270, 900V	BYX 38/900, BYX 39/1000
6231	1S1279	1S1270, 1000V	BYX 38/1200, BYX 39/1000
6232	1S128	6V, <25ns	AA 48, 1N995
6233	1S1280	200V, 10A	1N4525...30
6234	1S1280R...1285R	1S1280..1285	D 24/400C...1200C
6235	1S1281	1S1280, 300V	1N4526...30
6236	1S1282	1S1280, 400V	1N4526...30
6237	1S1283	1S1280, 600V	1N4527...30
6238	1S1284	1S1280, 800V	1N4528...30
6239	1S1285	1S1280, 1000V	1N4529...30
6240	1S1286	100V, 15A(Tc50°)	1N3492...95
6241	1S1286R...1288R	1S1286..1288	1N3492R...95R
6242	1S1287	100V, 20A(Tc50°)	1N3492...95
6243	1S1288	100V, 20A(Tc50°)	1N3492...95
6244	1S1289	150V, 12A	1N4525...30
6245	1S1289R...1292R	1S1289..1292	D 24/C400
6246	1S129[Japan]	50V, 0,1A, <240ns	AA 49, AAZ 15, AAZ 17
6247	1S1290	1S1289, 300V	1N4526...30
6248	1S1291	150V, 25A	1N4525...30
6249	1S1292	1S1291, 300V	1N4526...30
6250	1S1297	70V, 0,4A, <12ns	BAV 14...16, BAW 26...27
6251	1S1298	125V, 0,45A, <12ns	BAV 14...16
6252	1S1299	125V, 0,6A, <12ns	BAV 14...16
6253	1S13	45V, 35mA	AA 113, 1N34, 1N54, 1N60
6254	1S130[Japan]	1S129[Japan], <340ns	AA 49, AAZ 15, AAZ 17

6255	1S130[Texas]	50V, 0,2A	BA 157...159, BY 204/4, BY 206...207
6256	1S1300	1,65..2,2V(2mA)	-
6257	1S1301	35V, 0,045A, <5,3ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6258	1S1302	70V, 0,25A, <7ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6259	1S1303	60V, 0,25A, <7ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6260	1S1304	125V, 0,5A, <20ns	BAV 14...16
6261	1S1305	125V, 0,9A, <20ns	-
6262	1S131[Japan]	8..9,5V	-
6263	1S131[Texas]	1S130[Texas], 100V	BA 157...159, BY 204/4, BY 206...207
6264	1S1314		-
6265	1S1315		BA 124...125, BB 119, 1S2790, 1SV50
6266	1S1316	40V, 0,1A	BA 147/50, BA 187...190, 1N5606...09
6267	1S1317	1S1316, 60V	BA 147/100, BA 188...190, 1N5606...09
6268	1S1318	1S1316, 125V	BA 147/150, BA 189...190, 1N5606...09
6269	1S1319	1S1316, 250V	BA 147/300, BA 157...159, BAY 21
6270	1S132[Japan]	8..9,5V	-
6271	1S132[Texas]	1S130[Texas], 200V	BA 157...159, BY 204/4, BY 206...207
6272	1S1320	1S1316, 400V	BA 157...159, BAY 89...90, BY 207
6273	1S1321	100V, 5A(Tc120°)	BYX 38/300, BYX 39/600
6274	1S1322	1S1321, 200V	BYX 38/300, BYX 39/600
6275	1S1323	1S1321, 300V	BYX 38/300, BYX 39/600
6276	1S1324	1S1321, 400V	BYX 38/600, BYX 39/600
6277	1S1325	1S1321, 500V	BYX 38/600, BYX 39/600
6278	1S1326	1S1321, 600V	BYX 38/600, BYX 39/600
6279	1S1327	1S1321, 700V	BYX 38/900, BYX 39/800
6280	1S1328	1S1321, 800V	BYX 38/900, BYX 39/800
6281	1S1329	1S1321, 900V	BYX 38/1200, BYX 39/1000
6282	1S133[Japan]	8..9,5V	-
6283	1S1330	1S1321, 1000V	BYX 38/1200, BYX 39/1000
6284	1S1331	200V, 500A(Tc130°)	-
6285	1S1332	1S1331, 400V	-
6286	1S1333	1S1331, 600V	-
6287	1S1334	1S1331, 800V	-
6288	1S1335	1S1331, 1000V	-
6289	1S1336	1S1331, 1200V	-
6290	1S1337	1S1331, 1400V	-
6291	1S1338	1S1331, 1600V	-
6292	1S1339	1S1331, 1800V	-
6293	1S134[Japan]	3,8..5,4V, 0,25W	BZX55/C4V7, BZX79/C4V7, ZPD4,7, 1N5230
6294	1S134[Texas]	1S130[Texas], 400V	BA 157...159, BY 204/4, BY 206...207
6295	1S1340	1S1331, 2000V	-
6296	1S1341	50V, 0,8A	BY 126...127, BY 133...134, 1N4001...07
6297	1S1342	1S1341, 100V	BY 126...127, BY 133...134, 1N4002...07
6298	1S1343	1S1341, 200V	BY 126...127, BY 133...134, 1N4003...07
6299	1S1344	1S1341, 300V	BY 126...127, BY 133...134, 1N4004...07

6300	1S1345	1S1341, 400V	BY 126...127, BY 133...134, 1N4004...07
6301	1S1346	1S1341, 600V	BY 126...127, BY 133...134, 1N4005...07
6302	1S1347	1S1341, 800V	BY 127, BY 133, BY 227, 1N4006...07
6303	1S1348	1S1341, 1000V	BY 127, BY 133, BY 227, 1N4007
6304	1S1349	1S1341, 1200V	BY 127, BY 133, BY 227, GP 10Q
6305	1S135[Japan]	1S134[Japan], 5,2..6,2V	BZX55/C5V6, BZX79/C5V6, ZPD5,6, 1N5232
6306	1S1350	50V, 2A	BY 205/100, BY 229/200, BYX 49/300
6307	1S1351	1S1350, 100V	BY 205/100, BY 229/200, BYX 49/300
6308	1S1352	1S1350, 200V	BY 205/200, BY 229/200, BYX 49/300
6309	1S1353	1S1350, 300V	BY 205/400, BY 229/400, BYX 49/300
6310	1S1354	1S1350, 400V	BY 205/400, BY 229/400, BYX 49/600
6311	1S1354	1S1350, 400V	BY 205/400, BY 229/400, BYX 49/600
6312	1S1355	1S1350, 600V	BY 205/600, BY 229/600, BYX 49/600
6313	1S1356	1S1350, 800V	BY 205/800, BY 229/800, BYX 49/900
6314	1S1357	1S1350, 1000V	BY205/1000, BY229/1000, BYX49/1200
6315	1S1358	1S1350, 1200V	BY329/1000, BY359/1300, BYX49/1200
6316	1S1359(A)	200V, 0,2A	BY 126...127, BY 133...134, 1N4003...07
6317	1S136[Japan]	1S134[Japan], 6,0..7,1V	BZX55/C6V8, BZX79/C6V8, ZPD6,8, 1N5235
6318	1S136[Texas]	1S130[Texas], 600V	BA 158...159, BY 204/8, BY 207
6319	1S1360(A)	1S1359, 400V	BY 126...127, BY 133...134, 1N4004...07
6320	1S1361(A)	1S1359, 600V	BY 126...127, BY 133...134, 1N4005...07
6321	1S1362(A)	1S1359, 800V	BY 127, BY 133, BY 227, 1N4006...07
6322	1S1363(A)	1S1359, 1000V	BY 127, BY 133, BY 227, 1N4007
6323	1S1364(A)	1S1359, 1200V	BY 127, BY 133, BY 227, GP 10Q
6324	1S1365(A)	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
6325	1S1366(A)	1S1365, 400V	BY 126...127, BY 133...134, 1N4004...07
6326	1S1367(A)	1S1365, 600V	BY 126...127, BY 133...134, 1N4005...07
6327	1S1368(A)	1S1365, 800V	BY 127, BY 133, BY 227, 1N4006...07
6328	1S1369(A)	1S1365, 1000V	BY 127, BY 133, BY 227, 1N4007
6329	1S137[Japan]	1S134[Japan], 6,9..8,1V	BZX55/C7V5, BZX79/C7V5, ZPD7,5, 1N5236
6330	1S1370(A)	1S1365, 1200V	BY 127, BY 133, BY 227, GP 10Q
6331	1S1371(A)	2..3,2V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5221...61
6332	1S1372(A)	1S1371, 3..4V	
6333	1S1373(A)	1S1371, 3,8..5V	
6334	1S1374(A)	1S1371, 4,8..6V	
6335	1S1375(A)	1S1371, 5,8..7V	
6336	1S1376(A)	1S1371, 6..8V	
6337	1S1377(A)	1S1371, 7,7..9,5V	
6338	1S1378(A)	1S1371, 8,5..11V	
6339	1S1379(A)	1S1371, 10,5..14,5V	
6340	1S138[Japan]	1S134[Japan], 7,9..9,1V	BZX55/C8V2, BZX79/C8V2, ZPD8,2, 1N5237
6341	1S138[Texas]	1S130[Texas], 800V	BA 159, BY 204/8, BY 208/800
6342	1S1380(A)	1S1371, 14..18V	
6343	1S1381(A)	1S1371, 17..23V	
6344	1S1382(A)	1S1371, 22..28V	

6345	1S1383(A)	1S1371, 27..33V	
6346	1S1384(A)	1S1371, 32..38V	
6347	1S1385(A)	1S1371, 37..48V	
6348	1S1386(A)	2..3,2V, 0,5W	BZV85/..., BZX85/..., ZPY..., 1N4728...58
6349	1S1387(A)	1S1386, 3..4V	
6350	1S1388(A)	1S1386, 3,8..5V	
6351	1S1389(A)	1S1386, 4,8..6V	
6352	1S139[Japan]	1S134[Japan], 8,9..10,1V	BZX55/C9V1, BZX79/C9V1, ZPD9,1, 1N5239
6353	1S1390(A)	1S1386, 5,8..7V	
6354	1S1391(A)	1S1386, 6,8..8V	
6355	1S1392(A)	1S1386, 7,7..9,5V	
6356	1S1393(A)	1S1386, 8,5..11V	
6357	1S1394(A)	1S1386, 10,5..14,5V	
6358	1S1395(A)	1S1386, 14..18V	
6359	1S1396(A)	1S1386, 17..23V	
6360	1S1397(A)	1S1386, 22..28V	
6361	1S1398(A)	1S1386, 27..33V	
6362	1S1399(A)	1S1386, 32..38V	
6363	1S14	45V, 35mA	AA 113, 1N34, 1N54, 1N60
6364	1S140[Japan]	1S134[Japan], 9,9..12,2V	BZX55/C11, BZX79/C11, ZPD11, 1N5241
6365	1S140[Texas]	50V, 0,3A	BA 157...159, BY 204/4, BY 206...207
6366	1S1400(A)	1S1386, 37..48V	
6367	1S1401(A)	1S1386, 47..58V	
6368	1S1402	2..3,2V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...38
6369	1S1402R...1415R	1S1402..1415	
6370	1S1403	1S1402, 3..4V	
6371	1S1404	1S1402, 3,8..5V	
6372	1S1405	1S1402, 4,8..6V	
6373	1S1406	1S1402, 5,8..7V	
6374	1S1407	1S1402, 6,8..8V	
6375	1S1408	1S1402, 7,7..9,5V	
6376	1S1409	1S1402, 8,5..11V	
6377	1S141[Japan]	1S134[Japan], 11,8..13,9V	BZX55/C13, BZX79/C13, ZPD13, 1N5243
6378	1S141[Texas]	1S140[Texas], 100V	BA 157...159, BY 204/4, BY 206...207
6379	1S1410	1S1402, 10,5..14,5V	
6380	1S1411	1S1402, 14..18V	
6381	1S1412	1S1402, 17..23V	
6382	1S1413	1S1402, 22..28V	
6383	1S1414	1S1402, 27..33V	
6384	1S1415	1S1402, 32..38V	
6385	1S1417	800V, 25A(Tc135°)	1N4528...30
6386	1S1418	1S1417, 1000V	1N4529...30
6387	1S1419	1S1417, 1200V	1N4530
6388	1S142[Japan]	1S134[Japan], 13,3..15,5V	BZX55/C15, BZX79/C15, ZPD15, 1N5245
6389	1S142[Texas]	1S140[Texas], 200V	BA 157...159, BY 204/4, BY 206...207

6390	1S1420(H)	<2,2V(2mA), 0,1W	-
6391	1S1423	2..3,2V, 3W	BZX98/..., BZY93/..., ZL..., 1N2970...99
6392	1S1423R...1438R	1S1423..1438	
6393	1S1424	1S1423, 3..4V	
6394	1S1425	1S1423, 3,8..5V	
6395	1S1426	1S1423, 4,8..6V	
6396	1S1427	1S1423, 5,8..7V	
6397	1S1428	1S1423, 6,8..8V	
6398	1S1429	1S1423, 7,7..9,5V	
6399	1S143[Japan]	1S134[Japan], 14,7..17,3V	BZX55/C16, BZX79/C16, ZPD16, 1N5246
6400	1S1430	1S1423, 8,5..11V	
6401	1S1431	1S1423, 10,5..14,5V	
6402	1S1432	1S1423, 14..18V	
6403	1S1433	1S1423, 17..23V	
6404	1S1434	1S1423, 22..28V	
6405	1S1435	1S1423, 27..33V	
6406	1S1436	1S1423, 32..38V	
6407	1S1437	1S1423, 37..48V	
6408	1S1438	1S1423, 47..58V	
6409	1S1439	3,8..5V, 10W	BZX98/..., BZY93/..., ZL..., 1N2970...99
6410	1S1439R...1452R	1S1439..1452	
6411	1S144[Japan]		
6412	1S144[Texas]	1S140[Texas], 400V	BA 157...159, BY 204/4, BY 206...207
6413	1S1440	1S1439, 4,8..6V	
6414	1S1441	1S1439, 5,8..7V	
6415	1S1442	1S1439, 6,8..8V	
6416	1S1443	1S1439, 7,7..9,5V	
6417	1S1444	1S1439, 8,5..11V	
6418	1S1445	1S1439, 10,5..14,5V	
6419	1S1446	1S1439, 14..18V	
6420	1S1447	1S1439, 17..23V	
6421	1S1448	1S1439, 22..28V	
6422	1S1449	1S1439, 27..33V	
6423	1S145[Japan]		BA 124...125, BB 119, 1S2790, 1SV50
6424	1S1450	1S1439, 32..38V	
6425	1S1451	1S1439, 37..48V	
6426	1S1452	1S1439, 47..58V	
6427	1S1454	400V, 6A(Tc120°)	BYX 42/600, BYX 98/600
6428	1S1455	1S1454, 800V	BYX 42/900, BYX 98/900
6429	1S1456	1S1454, 1000V	BYX 42/1200, BYX 98/1200
6430	1S1457	1S1454, 1200V	BYX 42/1200, BYX 98/1200
6431	1S1458	60V, 0,1A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6432	1S1459	60V, 0,15A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6433	1S146[Japan]	100V, 0,6A	BY 126...127, BY 133...135, 1N4002...07
6434	1S1460	60V, 0,35A, <2ns	BAW 76



6435	1S1461	800V, 12A(Tc135°)	BYX 25/800R
6436	1S1462	1S1461, 1000V	BYX 25/1000R
6437	1S1463	1S1461, 1200V	BYX 25/1200R
6438	1S1464	800MHz	-
6439	1S1466	60V, 0,08A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6440	1S1467	60V, 0,25A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6441	1S147[Japan]	1S146[Japan], 200V	BY 126...127, BY 133...134, 1N4003...07
6442	1S1471	1000V, 1A	BYV 36E, BYV 96E, BYW 56, 1N4249
6443	1S1472	600V, 0,15A	BA 158...159, BAY 89...90, BY 207
6444	1S1473(H,K)	30V, 0,1A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4151
6445	1S1474	200V, 1,5A	BYV 36A, BYV 95A, BYW 52...56, BYW 95A
6446	1S1475	1S1474, 400V	BYV 36B, BYV 95B, BYW 53...56, BYW 95B
6447	1S1476	1S1474, 600V	BYV 36C, BYV 95C, BYW 54...56, BYW 95C
6448	1S1477	1S1474, 800V	BYV 36D, BYV 96D, BYW 55...56, BYW 96D
6449	1S1478	1S1474, 1000V	BYV 36E, BYV 96E, BYW 56, BYW 96E
6450	1S1479	1S1474, 1200V	SSi B9880A
6451	1S148[Japan]	1S146[Japan], 300V	BY 126...127, BY 133...134, 1N4004...07
6452	1S1480	200V, 20A(Tc90°)	1N4525...30
6453	1S1481	1S1480, 400V	1N4526...30
6454	1S1482	1S1480, 600V	1N4527...30
6455	1S1483	1S1480, 800V	1N4528...30
6456	1S1484	1S1480, 1000V	1N4529...30
6457	1S1485	1S1480, 1200V	1N4530
6458	1S1486	100V, 0,4A	BYV 36A, BYV 95A, BYW 52...56, BYW 95A
6459	1S1487	1S1486, 200V	BYV 36A, BYV 95A, BYW 52...56, BYW 95A
6460	1S1488	200V, 1,5A	BY 226...227, BY 251...255, 1N5393...99
6461	1S1489	1S1488, 400V	BY 226...227, BY 252...255, 1N5395...99
6462	1S149[Japan]	1S146[Japan], 400V	BY 126...127, BY 133...134, 1N4004...07
6463	1S1490	1S1488, 600V	BY 226...227, BY 253...255, 1N5397...99
6464	1S1491	1S1488, 800V	BY 227, BY 254...255, 1N5398...99
6465	1S1492	1S1488, 1000V	BY 227, BY 255, BYW 56, 1N5399
6466	1S1493	200V, 30A	BYX 56/600, BYX 97/300,
6467	1S1493R...1495R	1S1493...1495	BYX 56/...R, BYX 97/...R
6468	1S1494	1S1493, 400V	BYX 56/600, BYX 97/600,
6469	1S1495	1S1493, 600V	BYX 56/600, BYX 97/600,
6470	1S1496	200V, 50A(Tc70°)	1N3289...97
6471	1S1496R...1498R	1S1496...1498	1N3289R...97R
6472	1S1497	1S1496, 400V	1N3291...97
6473	1S1498	1S1496, 600V	1N3293...97
6474	1S15	45V, 35mA	AA 113, 1N34, 1N54, 1N60
6475	1S150[Japan]	1S146[Japan], 500V	BY 126...127, BY 133...134, 1N4005...07
6476	1S1500		BA 124...125, BB 119, 1S2790, 1SV50
6477	1S1501		BA 124...125, BB 119, 1S2790, 1SV50
6478	1S1502		BA 124...125, BB 119, 1S2790, 1SV50
6479	1S1503		BA 124...125, BB 119, 1S2790, 1SV50



6480	1S151	100V, 1,5A	BYX 38/300, BYX 39/600
6481	1S1514(M)	90V, 0,12A, <2ns	BA 219, 1N4148...49, 1N4446...49
6482	1S1515(M)	55V, 0,12A, <2ns	BA 219, 1N4148...49, 1N4446...49
6483	1S1516(M)	55V, 0,12A, <2ns	BA 219, 1N4148...49, 1N4446...49
6484	1S1517(A)	1500V, 0,5A	BY 228, BY 269, BY 400, BY 448
6485	1S1518	200V, 10A	1N3493...95
6486	1S1518R...1522R	1S1518..1522	1N3493R...95R
6487	1S1519	1S1518, 400V	1N3495
6488	1S152	1S151, 200V	BYX 38/300, BYX 39/600
6489	1S1520	1S1518, 500V	-
6490	1S1521	1S1518, 600V	-
6491	1S1522	1S1518, 800V	-
6492	1S153	1S151, 300V	BYX 38/300, BYX 39/600
6493	1S1532	35V, 0,06A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
6494	1S154	1S151, 400V	BYX 38/600, BYX 39/600
6495	1S1540(N)	68..83V, 35W(Tc55°)	-
6496	1S1541(N)	1S1540, 77..103V	
6497	1S1542(N)	1S1540, 103..115V	
6498	1S1543(N)	1S1540, 140..168V	
6499	1S1544(A)	30V, 0,1A, <100ns	BAV 17...21, BAX 90, BAX 94, BAY 41...43
6500	1S1545	30V, 0,1A, <100ns	BAV 17...21, BAX 90, BAX 94, BAY 41...43
6501	1S1546	100V, 0,6A	BY 126...127, BY 133...135, 1N4002...07
6502	1S1547	1S1546, 200V	BY 126...127, BY 133...134, 1N4003...07
6503	1S1548	1S1546, 400V	BY 126...127, BY 133...134, 1N4004...07
6504	1S1549	890MHz	-
6505	1S155	1S151, 500V	BYX 38/600, BYX 39/600
6506	1S1550	1S1540, 162..195V	
6507	1S1551		-
6508	1S1552		-
6509	1S1553	70V, 0,1A	BA 147/100, BA 188...190, 1N5606...09
6510	1S1554	1S1553, 55V	BA 147/100, BA 188...190, 1N5606...09
6511	1S1555	1S1553, 35V	BA 147/50, BA 187...190, 1N5606...09
6512	1S1556		-
6513	1S1557		-
6514	1S1558		-
6515	1S156	1S151, 600V	BYX 38/600, BYX 39/600
6516	1S1565	800V, 350A(Tc90°)	-
6517	1S1566	1S1565, 1000V	-
6518	1S1567	1S1565, 1200V	-
6519	1S1568	1S1565, 1500V	-
6520	1S1569	1S1565, 1800V	-
6521	1S157	100V, 1A	BYX 38/300, BYX 39/600
6522	1S1570	1S1565, 2000V	-
6523	1S1575	400V, 12A(Tc120°)	1N4526...30
6524	1S1576	1S1575, 600V	1N4527...30

6525	1S1577	1S1575, 800V	1N4528...30
6526	1S1578	1S1575, 1000V	1N4529...30
6527	1S1579	60V, 0,05A	-
6528	1S158	1S157, 200V	BYX 38/300, BYX 39/600
6529	1S1580	1S1579, 35V	-
6530	1S1582		BA 124...125, BB 119, 1S2790, 1SV50
6531	1S1583		-
6532	1S1585	90V, 0,15A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6533	1S1586	55V, 0,15A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6534	1S1587	55V, 0,13A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6535	1S1588	35V, 0,12A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6536	1S1589	40V, 0,06A, <4ns	BA 218, BAX 13, BAY 71, 1N4148...49
6537	1S159	1S157, 300V	BYX 38/300, BYX 39/600
6538	1S1591	600V, 0,03A, <300ns	BA 158...159, BY 203/12, SHG 1
6539	1S1592	1S1591, 800V	BA 159, BY 203/12, BY 268...269, SHG 1
6540	1S1593	1S1591, 1000V	BA 159, BY 203/12, BY 268...269, SHG 1
6541	1S1594	1S1591, 1200V	BY 203/12, BY 268...269, SHG 1,5
6542	1S1595	1S1591, 1500V	BY 203/16, BY 269, SHG 1,5
6543	1S1596	1S1591, 1800V	BY 203/20, SHG 2
6544	1S1597	35V, 0,1A	BA 147/50, BA 187...190, 1N5606...09
6545	1S1598	1S1597, 50V	BA 147/50, BA 187...190, 1N5606...09
6546	1S1599	1S1597, 100V	BA 147/100, BA 188...190, 1N5606...07
6547	1S16	45V, 35mA	AA 113, 1N34, 1N54, 1N60
6548	1S160	50V, 10A(Tc120°)	BYX 42/300, BYX 98/300
6549	1S1600	1S1597, 200V	BA 147/230, BA 190, BAY 21, BAY 88...90
6550	1S1601	1S1597, 300V	BA 147/300, BAY 21, BAY 88...90
6551	1S1602	1S1597, 400V	BA 157...159, BAY 89...90, BY 207
6552	1S1604	100V, 1,1A	BY 126...127, BY 133...135, 1N4002...07
6553	1S1605	800V, 0,5A	BY 127, BY 133, BY 227, 1N4006...07
6554	1S1606	200V, 20A(Tc100°)	1N4525...30
6555	1S1606R...1607R	1S1606..1607	D 24/400C
6556	1S1607	1S1606, 300V	1N4526...30
6557	1S1608	1000V, 0,5A	BY 127, BY 133, BY 227, 1N4007
6558	1S1609	1S1608, 1300V	BY 127, BY 133, BY 227, GP 10V
6559	1S161	1S160, 100V	BYX 42/300, BYX 98/300
6560	1S1610	1S1608, 1500V	BY 269, DM 513, EM 516, GP 10W
6561	1S1611	6kV, 0,06A	1N5183
6562	1S1612	1S1611, 12kV	1N3052
6563	1S1613	1S1611, 18kV	1N3055
6564	1S1614	800V, 50A(Tc135°)	1N3294R...97R
6565	1S1615	1S1614, 1000V	1N3295R...97R
6566	1S1616	1S1614, 1200V	1N3296R...97R
6567	1S1617		BA 111, BA 124, 1S2790, 1SV50
6568	1S1618		BA 111, BA 124, 1S2790, 1SV50
6569	1S1619		BA 111, BA 124, 1S2790, 1SV50

6570	1S162	1S160, 200V	BYX 42/300, BYX 98/300
6571	1S1620	50V, 0,115A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6572	1S1621	175V, 0,1A, <400ns	BA 195, BAX 15, BAX 17, 1N3070
6573	1S1622	100V, 0,3A	BA 157...159, BY 204/4, BY 206...207
6574	1S1623	1S1622, 200V	BA 157...159, BY 204/4, BY 206...207
6575	1S1624	1S1622, 400V	BA 157...159, BY 204/4, BY 207
6576	1S1625	1S1622, 600V	BA 158...159, BY 204/8, BY 207
6577	1S1626	800V, 6A(Tc135°)	1N4509...11
6578	1S1627	1S1626, 1000V	1N4510...11
6579	1S1628	1S1626, 1200V	1N4511
6580	1S1629	800V, 3A(Tc135°)	BYX 39/800
6581	1S163	1S160, 300V	BYX 42/300, BYX 98/300
6582	1S1630	1S1629, 1000V	BYX 39/1000
6583	1S1631	1S1629, 1200V	BYX 39/1200
6584	1S1632	150V, 150A(Tc110°)	1N4588...4596
6585	1S1633	1S1632, 300V	1N4589...4596
6586	1S1634	1S1632, 400V	1N4590...4596
6587	1S1635	1S1632, 500V	1N4591...4596
6588	1S1636	1S1632, 600V	1N4592...4596
6589	1S1637	1S1632, 700V	1N4593...4596
6590	1S1638	1S1632, 800V	1N4593...4596
6591	1S1639	1S1632, 1000V	1N4594...4596
6592	1S164	1S160, 400V	BYX 42/600, BYX 98/600
6593	1S1642	400V, 25A(Tc90°)	1N4526...30
6594	1S1642R	1S1642	D 24/400C
6595	1S1643	150V, 50A(Tc120°)	1N3289...97
6596	1S1643R...1644R	1S1643..1644	1N3289R...97R
6597	1S1644	1S1643, 300V	1N3290...97
6598	1S1645	150V, 100A(Tc110°)	1N3289...97
6599	1S1645R...1646R	1S1645..1646	1N3289R...97R
6600	1S1646	1S1645, 300V	1N3290...97
6601	1S1647	150V, 200A(Tc100°)	1N3736...44
6602	1S1647R...1648R	1S1647..1648	1N3736R...44R
6603	1S1648	1S1647, 300V	1N3737...44
6604	1S165	1S160, 500V	BYX 42/600, BYX 98/600
6605	1S1650		BA 124...125, BB 119, 1S2790, 1SV50
6606	1S1651		BA 124...125, BB 119, 1S2790, 1SV50
6607	1S1652	150V, 12A(Tc50°)	1N4525...30
6608	1S1652R...1653R	1S1652..1653	D 24/400C
6609	1S1653	1S1652, 300V	1N4526...30
6610	1S1654	150V, 25A(Tc50°)	1N4525...30
6611	1S1654R...1655R	1S1654..1655	D 24/400C
6612	1S1655	1S1654, 300V	1N4526...30
6613	1S1658		BA 111, BA 124, 1S2790, 1SV50
6614	1S1659	10V, 0,05A, <1ns	BAY 82, 1N4244, 1N4376

6615	1S166	1S160, 600V	BYX 42/600, BYX 98/600
6616	1S1660	150V, 3A	BYX 38/300, BYX 39/900
6617	1S1660R...1661R	1S1660..1661	BYX 38/300R, BYX 39/900R
6618	1S1661	1S1660, 300V	BYX 38/300, BYX 39/900
6619	1S1662	150V, 6A	BYX 38/300, BYX 39/900
6620	1S1662R...1663R	1S1662..1663	BYX 38/300R, BYX 39/900R
6621	1S1663	1S1662, 300V	BYX 38/300, BYX 39/900
6622	1S1664	100V, 1A	BY 126...127, BY 133...135, 1N4002...07
6623	1S1665	1S1664, 200V	BY 126...127, BY 133...134, 1N4003...07
6624	1S1666	1S1664, 400V	BY 126...127, BY 133...134, 1N4004...07
6625	1S1667	1S1664, 600V	BY 126...127, BY 133...134, 1N4005...07
6626	1S1668	1S1664, 800V	BY 127, BY 133, BY 227, 1N4006...07
6627	1S1669	1S1664, 1000V	BY 127, BY 133, BY 227, 1N4007
6628	1S167	100V, 5A(Tc120°)	BYX 38/300, BYX 39/600
6629	1S1670	100V, 1,8A	B100C2000, etc
6630	1S1671	1S1670, 200V	B200C2000, etc
6631	1S1672	1S1670, 400V	B400C2000, etc
6632	1S1673	1S1670, 600V	B600C2000, etc
6633	1S1674	1S1670, 800V	B800C2000, etc
6634	1S1675	1S1670, 1000V	B1000C2000, etc
6635	1S1678	100V, 1,3A	BY 251...255, BY 226...227, 1N5392...99
6636	1S1679	1S1678, 200V	BY 251...255, BY 226...227, 1N5393...99
6637	1S168	1S167, 200V	BYX 38/300, BYX 39/600
6638	1S1680	1S1678, 400V	BY 252...255, BY 226...227, 1N5395...99
6639	1S1681	1S1678, 600V	BY 253...255, BY 226...227, 1N5397...99
6640	1S1682	1S1678, 800V	BY 254...255, BY 227, 1N5398...99
6641	1S1683	1S1678, 1000V	BY 255, BY 227, BYW 56, 1N5399
6642	1S1684	1S1678	1S1678
6643	1S1685	1S1679	1S1679
6644	1S1686	1S1680	1S1680
6645	1S1687	1S1681	1S1681
6646	1S1688	1S1682	1S1682
6647	1S1689	1S1683	1S1683
6648	1S169	1S167, 300V	BYX 38/300, BYX 39/600
6649	1S1690(A)	30V, 0,09A	BA 147/50, BA 187...190, 1N5606...09
6650	1S1691(A)	36V, 0,1A	BA 147/50, BA 187...190, 1N5606...09
6651	1S1692(A)	70V, 0,075A	BA 147/100, BA 188...190, 1N5606...09
6652	1S1693(A)	70V, 0,1A	BA 147/100, BA 188...190, 1N5606...09
6653	1S1694(A)	130V, 0,1A	BA 147/150, BA 189...190, 1N5606...07
6654	1S1695(A)	200V, 0,04A	BA 147/230, BA 190, BAY 21, BAY 88...90
6655	1S1696(A)	225V, 0,1A	BA 147/230, BAY 21, BAY 88...90
6656	1S1697(A)	300V, 0,1A	BA 147/300, BAY 21, BAY 88...90
6657	1S1698(A)	380V, 0,1A	BA 158...159, BA 199/450, BAY 89...90
6658	1S1699	30V, 0,02A, <250ns	BA 157...159, BAV 17...21, BAW 48...50
6659	1S17	115V, 50mA	AA 117...118, AA 132...133

6660	1S170	50V, 20A(Tc120°)	1N4525...30
6661	1S1700	1S1699, 40V, 0,12A	BA 157...159, BAV 17...21, BAW 48...50
6662	1S1701	1S1699, 60V, 0,1A	BA 157...159, BAV 18...21, BAW 49...50
6663	1S1702	1S1699, 65V, 0,12A	BA 157...159, BAV 19...21, BAW 49...50
6664	1S1703	1S1699, 100V, 0,02A	BA 157...159, BAV 19...21, BAW 49...50
6665	1S1704(A)	1S1699, 100V, 0,04A	BA 157...159, BAV 19...21, BAW 49...50
6666	1S1705(A)	1S1699, 120V, 0,2A	BA 157...159, BAV 19...21, BAW 50
6667	1S1706	1S1699, 200V, 0,02A	BA 157...159, BAV 20...21, BAW 50
6668	1S1707(A)	1S1699, 200V, 0,04A	BA 157...159, BAV 20...21, BAW 50
6669	1S1708	1S1699, 200V, 0,1A	BA 157...159, BAV 20...21, BAW 50
6670	1S1709	1S1699, 220V, 0,1A	BA 157...159, BA 198, BAV 21
6671	1S171	1S170, 100V	1N4525...30
6672	1S1710	30V, 0,05A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
6673	1S1711	40V, 0,05A, <4ns	BA 218, BAX 13, BAX 91, 1N4148...49
6674	1S1712(A)	100V, 0,075A, <4ns	BA 219, BAX 96, 1N4148...49, 1N4151
6675	1S1713	50V, 0,075A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6676	1S1714	75V, 0,075A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
6677	1S1715	6..7,1V, 0,3W	BZX55/..., BZX79/..., ZPD..., 1N5234...40
6678	1S1716	1S1715, 6,9..8,1V	
6679	1S1717	1S1715, 7,9..9,1V	
6680	1S1718	1S1715, 8,9..10,1V	
6681	1S1719	Ub28..42V, Ib<0,2mA, Itsm2A	1N5762, N413N, D3202U
6682	1S172	1S170, 200V	1N4525...30
6683	1S1722		-
6684	1S1723	100V, 1,3A	BY 251...255, BY 226...227, 2N5392...99
6685	1S1723R...1733R	1S1723..1733	1S1723...1733
6686	1S1724	1S1723, 150V	BY 251...255, BY 226...227, 2N5393...99
6687	1S1725	1S1723, 200V	BY 251...255, BY 226...227, 2N5393...99
6688	1S1726	1S1723, 250V	BY 252...255, BY 226...227, 2N5394...99
6689	1S1727	1S1723, 300V	BY 252...255, BY 226...227, 2N5394...99
6690	1S1728	1S1723, 400V	BY 252...255, BY 226...227, 2N5395...99
6691	1S1729	1S1723, 500V	BY 253...255, BY 226...227, 2N5396...99
6692	1S173	1S170, 300V	1N4526...30
6693	1S1730	1S1723, 600V	BY 253...255, BY 226...227, 2N5397...99
6694	1S1731	1S1723, 800V	BY 254...255, BY 227, 2N5398...99
6695	1S1732	1S1723, 1000V	BY 255, BY 227, BYX 86...87, 2N5399
6696	1S1733	1S1723, 1200V	BY 255, BY 227, BYW 17/1200, BYX 87
6697	1S1734	4,5..5,5V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5917...53
6698	1S1735	1S1734, 5..6,5V	
6699	1S1736	1S1734, 6..8V	
6700	1S1737	1S1734, 7..10V	
6701	1S1738	1S1734, 9..12V	
6702	1S1739	1S1734, 11..14V	
6703	1S174	1S170, 400V	1N4526...30
6704	1S1740	1S1734, 13..16V	

6705	1S1741	1S1734, 15..19V	
6706	1S1742	1S1734, 18..22V	
6707	1S1743	1S1734, 20..27V	
6708	1S1744	1S1734, 25..35V	
6709	1S1745	1S1734, 30..40V	
6710	1S1746	1S1734, 35..50V	
6711	1S1747	1S1734, 45..60V	
6712	1S1748	1S1734, 55..70V	
6713	1S1749	1S1734, 65..80V	
6714	1S175	1S170, 500V	1N4527...30
6715	1S1750	1S1734, 75..90V	
6716	1S1751	1S1734, 85..100V	
6717	1S1752	1S1734, 95..110V	
6718	1S1753	1S1734, 100..120V	
6719	1S1754	1S1734, 110..130V	
6720	1S1755	1S1734, 120..140V	
6721	1S1756	1S1734, 130..150V	
6722	1S1757		-
6723	1S1758		-
6724	1S1759		-
6725	1S176	1S170, 600V	1N4527...30
6726	1S1760		-
6727	1S1761		-
6728	1S1762		-
6729	1S1763		-
6730	1S1764		-
6731	1S1765		BA 111, BA 124, 1S2790, 1SV50
6732	1S1766	4,5..5,5V, 0,25W	BZX55/..., BZX79/..., ZPY..., 1N5230...59
6733	1S1767	1S1766, 5..6,5V	
6734	1S1768	1S1766, 6..8V	
6735	1S1769	1S1766, 7..10V	
6736	1S177	100V, 15A(Tc120°)	1N4525...30
6737	1S1770	1S1766, 9..12V	
6738	1S1771	1S1766, 11..14V	
6739	1S1772	1S1766, 13..16V	
6740	1S1773	1S1766, 15..19V	
6741	1S1774	1S1766, 18..22V	
6742	1S1775	1S1766, 20..27V	
6743	1S1776	1S1766, 25..35V	
6744	1S1777	1S1766, 30..40V	
6745	1S1778	8..9V	BZX 51, 1N4780
6746	1S1779	8..9V	BZX 52, 1N4781
6747	1S178	1S177, 200V	1N4525...30
6748	1S1780	8..9V	BZX 53, 1N4782
6749	1S1781	8..9,5V	BZX 51, 1N4780

6750	1S1782	8..9,5V	BZX 52, 1N4781
6751	1S1783	8..9,5V	BZX 53, 1N4782
6752	1S1784	62V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5944...56
6753	1S1785	1S1784, 68V	
6754	1S1786	1S1784, 82V	
6755	1S1787	1S1784, 100V	
6756	1S1788	1S1784, 120V	
6757	1S1789	1S1784, 130V	
6758	1S179	1S177, 300V	1N4526...30
6759	1S1790	1S1784, 150V	
6760	1S1791	1S1784, 180V	
6761	1S1792	1S1784, 200V	
6762	1S1793	1S1784, 220V	
6763	1S1794	1S1784, 250V	
6764	1S1795	1S1784, 300V	
6765	1S1796	30V, 0,1A, <4ns	BA 317, BAY 38, BAY 71, 1N4148...49
6766	1S1798	100V, 8A(Tc135°)	BYX 42/300, BYX 98/300
6767	1S1798R...1804R	1S1798..1804	BYX 42/...R, BYX 98/...R
6768	1S1799	1S1798, 200V	BYX 42/300, BYX 98/300
6769	1S18	115V, 50mA	AA 117...118, AA 132...133
6770	1S180	70V, 0,1A	BA 147/100, BA 188...190, BAY 19...21
6771	1S1800	1S1798, 300V	BYX 42/300, BYX 98/300
6772	1S1801	1S1798, 400V	BYX 42/600, BYX 98/600
6773	1S1802	1S1798, 600V	BYX 42/600, BYX 98/600
6774	1S1803	1S1798, 800V	BYX 42/900, BYX 98/900
6775	1S1804	1S1798, 1000V	BYX 42/1000, BYX 98/1000
6776	1S1807	890MHz	-
6777	1S1808	600V, 210A(Tc105°)	1N3740R...44R
6778	1S1809	1S1808, 800V	1N3741R...44R
6779	1S181	1S180, 120V	BA 147/150, BA 189...190, BAY 20...21
6780	1S1810	1S1808, 1000V	1N3742R...44R
6781	1S1811	1S1808, 1200V	1N3743R...44R
6782	1S1812	1S1808, 1400V	1N3744R
6783	1S1813	1S1808, 1600V	-
6784	1S1814	600V, 300A(Tc105°)	-
6785	1S1815	1S1814, 800V	-
6786	1S1816	1S1814, 1000V	-
6787	1S1817	1S1814, 1200V	-
6788	1S1818	1S1814, 1400V	-
6789	1S1819	1S1814, 1600V	-
6790	1S182	1S180, 220V	BA 147/230, BAY 21, BAY 46, BAY 88
6791	1S1820	887MHz	-
6792	1S1821	800V, 1A	BYW 55...56, 1N4248...49, 1N5062
6793	1S1821R...1824R	1S1821..1824	1S1821...1824
6794	1S1822		



6795	1S1823		
6796	1S1824		
6797	1S1825	800V, 12A(Tc130°)	1N4528...30
6798	1S1829	800V, 1A	BY 127, BY 133, BY 227, 1N4006...07
6799	1S183	1S180, 320V	BA 147/300, BAY 21, BAY 46, BAY 88
6800	1S1830	1S1829, 1000V	BY 127, BY 133, BY 227, 1N4007
6801	1S1831	2000V, 0,15A	BAY 91, BY 203/20, SHG 2
6802	1S1832	1800V, 0,7A	DM 516
6803	1S1834	400V, 1A, <350ns	BY 201/4, BYX 55/600, MR 814, RGP 10G
6804	1S1835	1S1834, 600V	BY 201/6, BYX 55/600, MR 816, RGP 10J
6805	1S1836	18kV, 2mA	BY 476, BY 711
6806	1S1837	1S1836, 25kV	BY 478, BY 713
6807	1S1838	1S1836, 45kV	-
6808	1S184	15V, 0,04A	BA 281
6809	1S1841	400V, 25A(Tc110°)	1N3765...68, 1N4526...30
6810	1S1842	1S1841, 600V	1N3765...68, 1N4527...30
6811	1S1843	1S1841, 800V	1N3766...68, 1N4528...30
6812	1S1844	1S1841, 1000V	1N3768, 1N4529...30
6813	1S1845	200V, 0,5A	BY 251...255, BY 226...227, BYW 17/200
6814	1S1845A	1S1845, 400V	BY 252...255, BY 226...227, BYW 17/400
6815	1S1845B	1S1845, 600V	BY 253...255, BY 226...227, BYW 17/600
6816	1S1845C	1S1845, 800V	BY 254...255, BY 227, BYW 17/800
6817	1S1845D	1S1845, 1000V	BY 255, BY 227, BYW 17/1000, BYX 86
6818	1S1845E	1S1845, 1200V	BY 255, BY 227, BYW 17/1200, BYX 87
6819	1S1846(A...E)	1S1845(A..E), 1A	1S1845(A...E)
6820	1S1847(A...E)	200..1200V, 8A(Tc50°)	BYX 42/..., BYX 98/...
6821	1S1848(A...E)	200..1200V, 22A(Tc50°)	BYX 96/...
6822	1S1849(R)	100V, 1,5A	2x BY 226...227, 2x BY 251...255
6823	1S185	15V, 0,04A	BA 281
6824	1S1850(R)	1S1849, 200V	2x BY 226...227, 2x BY 251...255
6825	1S1851(R)	1S1849, 400V	2x BY 226...227, 2x BY 252...255
6826	1S1855		-
6827	1S186	75V, 30mA	AA 117...118, AA 132...133
6828	1S1860	855MHz, 3V, 30mA	BA 480...481, BAR 19, BAT 29
6829	1S1861	1000V, 40A(Tc104°)	BYX 56/1000, BYX 97/1200
6830	1S1862	1000V, 60A(Tc126°)	DS 75-11B
6831	1S1863	100V, 150A(Tc116°)	1N4587...96
6832	1S1864	1S1863, 150V	1N4588...96
6833	1S1865	1S1863, 200V	1N4588...96
6834	1S1866	1S1863, 300V	1N4589...96
6835	1S1867	1S1863, 400V	1N4590...96
6836	1S1868	1S1863, 500V	1N4591...96
6837	1S1869	1S1863, 600V	1N4592...96
6838	1S187(S)	40V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
6839	1S1870	1S1863, 800V	1N4593...96



6840	1S1871	1S1863, 1000V	1N4594...96
6841	1S1872	100V, 250A(Tc107°)	1N3735...44
6842	1S1873	1S1872, 150V	1N3736...44
6843	1S1874	1S1872, 200V	1N3736...44
6844	1S1875	1S1872, 300V	1N3737...44
6845	1S1876	1S1872, 400V	1N3738...44
6846	1S1877	1S1872, 500V	1N3739...44
6847	1S1878	1S1872, 600V	1N3740...44
6848	1S1879	1S1872, 800V	1N3741...44
6849	1S188(AM,FM,G)	25..40V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
6850	1S1880	1S1872, 1000V	1N3742...44
6851	1S1881	1S1872, 1200V	1N3743...44
6852	1S1882	1S1872, 1400V	1N3744
6853	1S1885(A)	100V, 1A, A1,2A	BY 126...127, BY 133...135, 1N4002...07
6854	1S1886(A)	1S1885, 200V	BY 126...127, BY 133...134, 1N4003...07
6855	1S1887(A)	1S1885, 400V	BY 126...127, BY 133...134, 1N4004...07
6856	1S1888(A)	1S1885, 600V	BY 126...127, BY 133...134, 1N4005...07
6857	1S189	50V, 40mA	AA 113, AA 119, 1N34, 1N54, 1N60
6858	1S1890	600V, 1,2A	BY 226...227, BY 253...255, 1N5397...99
6859	1S1891	1S1890, 800V	BY 227, BY 254...255, 1N5398...99
6860	1S1892	1S1890, 1000V	BY 227, BY 255, BYX 86, 1N5398...99
6861	1S1893		BA 124...125, BB 119, 1S2790, 1SV50
6862	1S1894(A...D)		BB 105G, BB 205G, BB 305G, BB 505G
6863	1S1895(A...D)		BB 105G, BB 205G, BB 305G, BB 505G
6864	1S1897	500V, 1,5A, <800ns	BY 258/500, BY 298, BYV 14, RGP 15J
6865	1S1898	1S1897, 800V	BY 258/800, BY 299, BYV 15, RGP 15K
6866	1S1899	1S1897, 1000V	BY 246/1000, BY 299, BYV 16, RGP 15M
6867	1S19	15V, 35mA	AA 112...114, 1N34, 1N54, 1N60
6868	1S190	4,4..5,6V, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5231...50
6869	1S1902	500V, 0,8A, <300ns	BY 201/5, BYX 55/600, RGP 10J, 1N4946
6870	1S1905	100V, 1A	2x BY 126...127, BY 133...135, 1N4002
6871	1S1905R...1907R	1S1905..1907	1S1905...1907
6872	1S1906	1S1905, 200V	2x BY 126...127, BY 133...134, 1N4003
6873	1S1907	1S1905, 400V	2x BY 126...127, BY 133...134, 1N4004
6874	1S191	1S190, 5,4..6,6V	
6875	1S1910	1300V, 1A, <1µs	BY 228, BY 231/1400, BY 400, BY 448
6876	1S1911	1S1910, 1500V	BY 228, BY 231/1500, BY 400, BY 448
6877	1S1912	10kV, 3mA, <300ns	BY 509...510, BY 707...709
6878	1S1914	100V, 1,5A	BY 226...227, BY 251...255, 1N5392...99
6879	1S1915	1S1914, 200V	BY 226...227, BY 251...255, 1N5393...99
6880	1S1916	1S1914, 400V	BY 226...227, BY 252...255, 1N5395...99
6881	1S1917	1S1914, 600V	BY 226...227, BY 253...255, 1N5397...99
6882	1S1918	1S1914, 800V	BY 227, BY 254...255, 1N5398...99
6883	1S1919	1S1914, 1000V	BY 227, BY 255, BYX 87, 1N5399
6884	1S192	1S190, 6,4..7,6V	

6885	1S1920	1200V, 0,8A	BY 133, BY 227, BYX 95, GP 10Q, EM 513
6886	1S1921A	200V, 0,1A	BA 157...159, BA 147/230, BAY 88...91
6887	1S1921B	1S1921A, 400V	BA 157...159, BAY 88...91, BY 203/12
6888	1S1921C	1S1921A, 600V	BA 158...159, BAY 89...91, BY 203/12
6889	1S1921D	1S1921A, 800V	BA 159, BAY 90...91, BY 203/12
6890	1S1921E	1S1921A, 1000V	BA 159, BAY 90...91, BY 203/12
6891	1S1921F	1S1921A, 1200V	BAY 91, BY 203/12, BY 584, RGP 01-12
6892	1S1922		BA 124...125, BB 119, 1SV 114, 1SV125
6893	1S1923		BA 124...125, BB 119, 1SV 114, 1SV125
6894	1S1924		BA 124...125, BB 119, 1SV 114, 1SV125
6895	1S1925	5V, 50mA, 890MHz	-
6896	1S1926	5V, 25mA, 890MHz	BA 480...481, BAR 19, BAT 29
6897	1S1927	2000V, 7A(Tc120°)	-
6898	1S1928	2000V, 12A(Tc120°)	-
6899	1S1929	3000V, 12A(Tc120°)	-
6900	1S193	1S190, 7,4..8,6V	
6901	1S1930	2000V, 24A(Tc120°)	-
6902	1S1931	3000V, 24A(Tc120°)	-
6903	1S1932	2000V, 50A(Tc120°)	-
6904	1S1933	1S1932, 3000V	-
6905	1S1934	100V, 20A	1N3765...3768, 1N4525...4530
6906	1S1934R...1939R	1S1934...1939	D24/...C, 1N3765R...3768R
6907	1S1935	1S1934, 200V	1N3765...3768, 1N4525...4530
6908	1S1936	1S1934, 400V	1N3765...3768, 1N4526...4530
6909	1S1937	1S1934, 600V	1N3765...3768, 1N4527...4530
6910	1S1938	1S1934, 800V	1N3766...3768, 1N4528...4530
6911	1S1939	1S1934, 1000V	1N3768, 1N4529...4530
6912	1S194	1S190, 8,4..9,6V	
6913	1S1941	100V, 0,5A	BY 133...135, BY 226...227, 1N4002...07
6914	1S1942	1S1941, 200V	BY 133...134, BY 226...227, 1N4003...07
6915	1S1943	1S1941, 400V	BY 133...134, BY 226...227, 1N4004...07
6916	1S1944	1S1941, 600V	BY 133...134, BY 226...227, 1N4005...07
6917	1S1948	200V, 1,3A	BY 226...227, BY 251...255, 1N5393...99
6918	1S1949	1S1948, 400V	BY 226...227, BY 252...255, 1N5395...99
6919	1S195	1S190, 9,4..10,6V	
6920	1S1950	1S1948, 600V	BY 226...227, BY 253...255, 1N5397...99
6921	1S1951	31..35V, 1W	BZW22/C33, BZX61/C33, ZPY33, 1N5937
6922	1S1952	1,8..2,6V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...36
6923	1S1953	1S1952, 2,5..3,5V	
6924	1S1954	1S1952, 3,4..4,6V	
6925	1S1955	1S1952, 4,4..5,6V	
6926	1S1956	1S1952, 5,2..6,6V	
6927	1S1957	1S1952, 6,4..7,9V	
6928	1S1958	1S1952, 7,7..8,8V	
6929	1S1959	1S1952, 8,5..9,6V	

6930	1S196	1S190, 10,4..11,6V	
6931	1S1960	1S1952, 9,4..10,6V	
6932	1S1961	1S1952, 10,4..11,6V	
6933	1S1962	1S1952, 11,4..12,7V	
6934	1S1963	1S1952, 12,4..14,1V	
6935	1S1964	1S1952, 13,8..15,6V	
6936	1S1965	1S1952, 15,3..17,1V	
6937	1S1966	1S1952, 16,8..19,1V	
6938	1S1967	1S1952, 18,8..21,2V	
6939	1S1968	1S1952, 20,8..23,3V	
6940	1S1969	1S1952, 22,7..25,6V	
6941	1S197	1S190, 11,4..12,6V	
6942	1S1970	1S1952, 25,1..28,9V	
6943	1S1971	1S1952, 28..32V	
6944	1S1972(M)	75V, 0,2A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
6945	1S1973(M)	35V, 0,1A, <4ns	BA 318, BAY 38, BAX 80, 1N4148...49
6946	1S198	1S190, 12,4..16,1V	
6947	1S199	1S190, 15,9..20V	
6948	1S1991	Ub23..37V, Ib<0,2mA, Itsm2A	DO201 YR
6949	1S1992	30V, 0,02A	BAT 81, HSS 100...102
6950	1S1993	20V, 0,03A	BAT 81, HSS 100...102
6951	1S1994	30V, 0,03A	BAT 81, HSS 100...102
6952	1S1995	20V, 0,05A	BAT 81, HSS 100...102
6953	1S1996	200V, 3A(Tc128°)	BY 251...255, 1N5402...08, BY 205/200
6954	1S1996R...1999R	1S1996..1999	BY 251...255, 1N5402...08, BY 205/...
6955	1S1997	1S1996, 400V	BY 252...255, 1N5404...08, BY 205/400
6956	1S1998	1S1996, 600V	BY 253...255, 1N5406...08, BY 205/600
6957	1S1999	1S1996, 800V	BY 254...255, 1N5407...08, BY 205/800
6958	1S20	30V, <500ns	AA 27...28, 1N276
6959	1S200	35V, 25mA	AA 112...114, AA 119, 1N34, 1N54, 1N60
6960	1S2000	400V, 10A(Tc128°)	1N3765...3768, 1N4526...4530
6961	1S2000R...2002R	1S2000..2002	D24/...C, 1N3765R...3768R
6962	1S2001	1S2000, 600V	1N3765...3768, 1N4527...4530
6963	1S2002	1S2000, 800V	1N3766...3768, 1N4528...4530
6964	1S2003	100V, 10A(Tc125°)	1N3492...3495
6965	1S2003R	1S2003	DS 25-...A, 1N3492R...3495R
6966	1S2005	400V, 20A(Tc100°)	1N3765...3768, 1N4526...4530
6967	1S2005R...2007R	1S2005..2007	D24/...C, 1N3765R...3768R
6968	1S2006	1S2005, 600V	1N3765...3768, 1N4527...4530
6969	1S2007	1S2005, 800V	1N3766...3768, 1N4528...4530
6970	1S2011	1000V, 20A(Tc100°)	1N3768, 1N4529...4530
6971	1S2011R	1S2011	D24/1200C, 1N3768R
6972	1S2012	200V, 100A(Tc104°)	1N3289...3297, 1N4588...4596
6973	1S2013	1S2012, 400V	1N3291...3297, 1N4590...4596
6974	1S2014	1S2012, 600V	1N3293...3297, 1N4592...4596

6975	1S2015	1S2012, 800V	1N3294...3297, 1N4593...4596
6976	1S2016	1S2012, 1000V	1N3295...3297, 1N4594...4596
6977	1S2017	1S2012, 1300V	1N3297, 1N4596
6978	1S2018	1S2012, 1500V	-
6979	1S2019	200V, 100A(Tc90°)	1N3289...3297, 1N4588...4596
6980	1S2020	1S2019, 400V	1N3291...3297, 1N4590...4596
6981	1S2021	1S2019, 600V	1N3293...3297, 1N4592...4596
6982	1S2022	1S2019, 800V	1N3294...3297, 1N4593...4596
6983	1S2023	1S2019, 1000V	1N3295...3297, 1N4594...4596
6984	1S2024	1S2019, 1300V	1N3297, 1N4596
6985	1S2025	1S2019, 1500V	-
6986	1S2029	800V, 30A(Tc95°)	1N3766...3768, 1N4528...4530
6987	1S2029R	1S2029	D34/...C, 1N3766R...3768R
6988	1S2030(A)[Texas]	3V, 0,4W, 10%, (A5%)	BZX55/..., BZX83/..., ZPD..., 1N5225...57
6989	1S2033	800V, 50A(Tc60°)	1N3294...3297
6990	1S2033(A)[Texas]	1S2030[Texas], 3,3V	1S2030
6991	1S2033R	1S2033	1N3294R...3297R
6992	1S2034	200V, 20A(Tc115°)	1N3493...3295
6993	1S2034R...2035R	1S2034	DS 25-...A, 1N3493R...3295R
6994	1S2035	1S2034, 300V	1N3494...3295
6995	1S2036	200V, 10A(Tc125°)	1N3493...3295
6996	1S2036(A)[Texas]	1S2030[Texas], 3,6V	1S2030
6997	1S2036R...2037R	1S2036	DS 25-..., 1N3493R...3295R
6998	1S2037	1S2036, 300V	1N3494...3295
6999	1S2038	2500V, 300A(Tc90°)	-
7000	1S2039	1S2038, 3000V	-
7001	1S2039(A)[Texas]	1S2030[Texas], 3,9V	1S2030
7002	1S204	250V, 0,1A	BA 157...159, BA 199/250, BAY 88...90
7003	1S2040	1S2038, 4000V	-
7004	1S2043(A)[Texas]	1S2030[Texas], 4,3V	1S2030
7005	1S2043[Hitachi]	1,8..2,6V, 10W(Tc115°)	BZX98/..., BZY93/..., ZX..., 1N2970...90
7006	1S2044[Hitachi]	1S2043[Hitachi], 2,5..3,5V	
7007	1S2045[Hitachi]	1S2043[Hitachi], 3,4..4,6V	
7008	1S2046[Hitachi]	1S2043[Hitachi], 4,4..5,4V	
7009	1S2047(A)[Texas]	1S2030[Texas], 4,7V	1S2030
7010	1S2047[Hitachi]	1S2043[Hitachi], 5,2..6,8V	1S2043
7011	1S2048[Hitachi]	1S2043[Hitachi], 6,2..7,9V	
7012	1S2049[Hitachi]	1S2043[Hitachi], 7,7..8,7V	
7013	1S205	1S204, 350V	BA 157...159, BA 199/350, BAY 88...90
7014	1S2050[Hitachi]	1S2043[Hitachi], 8,5..9,6V	
7015	1S2051(A)[Texas]	1S2030[Texas], 5,1V	1S2030
7016	1S2051[Hitachi]	1S2043[Hitachi], 9,4..10,6V	1S2043
7017	1S2052[Hitachi]	1S2043[Hitachi], 10,4..11,6V	
7018	1S2053[Hitachi]	1S2043[Hitachi], 11,4..12,7V	
7019	1S2054[Hitachi]	1S2043[Hitachi], 12,4..14,1V	

7020	1S2055[Hitachi]	1S2043[Hitachi], 13,5..15,6V	
7021	1S2056(A)[Texas]	1S2030[Texas], 5,6V	1S2030
7022	1S2056[Hitachi]	1S2043[Hitachi], 15,3..17,1V	1S2043
7023	1S2057[Hitachi]	1S2043[Hitachi], 16,8..19,1V	
7024	1S2058[Hitachi]	1S2043[Hitachi], 18,8..21,2V	
7025	1S2059[Hitachi]	1S2043[Hitachi], 20,8..23,3V	
7026	1S206	1S204, 450V	BA 158...159, BA 199/450, BAY 89...90
7027	1S2060[Hitachi]	1S2043[Hitachi], 22,7..25,6V	
7028	1S2061[Hitachi]	1S2043[Hitachi], 25,1..28,9V	
7029	1S2062(A)[Texas]	1S2030[Texas], 6,2V	1S2030
7030	1S2062[Hitachi]	1S2043[Hitachi], 28..32V	
7031	1S2063	800V, 1,3A	BY 227, BY 254...255, 1N5398...99
7032	1S2064	Ub28..38V, Ib<0,2mA, Itsm2A	-
7033	1S2067[Njr]	8,5V	BZX 51, 1N4780
7034	1S2068(A)[Texas]	1S2030[Texas], 6,8V	1S2030
7035	1S2068[Njr]	8,5V	BZX 51, 1N4781
7036	1S2069[Njr]	8,5V	BZX 53, 1N4782
7037	1S207	1S204, 550V	BA 158...159, BA 199/550, BAY 89...90
7038	1S2070	50V, 45mA, <3ns	BA 318, BAY 38, 1N4305, 1N4148...49
7039	1S2071	22V, 45mA, <5ns	BA 318, BAY 38, 1N4305, 1N4148...49
7040	1S2072	80V, 0,2A, <6ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7041	1S2074H	50V, 0,15A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7042	1S2075(A)[Texas]	1S2030[Texas], 7,5V	1S2030
7043	1S2075K	35V, 0,1A, <8ns	BA 318, BAY 38, 1N4305, 1N4148...49
7044	1S2076	35V, 0,15A, <8ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7045	1S2076A	1S2076, 70V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7046	1S208	250V, 0,4A	BY 126...127, BY 133...134, 1N4004...07
7047	1S2080[Hitachi]	200V, 1,1A	BY 133...135, BY 226...227, 1N4003...07
7048	1S2081[Hitachi]	1S2080[Hitachi], 400V	BY 133...135, BY 226...227, 1N4003...07
7049	1S2082(A)[Texas]	1S2030[Texas], 8,2V	1S2030
7050	1S2082[Hitachi]	1S2080[Hitachi], 600V	BY 133...135, BY 226...227, 1N4003...07
7051	1S2083	100V, 20A(Tc115°)	1N3492...3495
7052	1S2083R	1S2083	DS 25-..., 1N3492R...3495R
7053	1S2084	1000V, 10A(Tc128°)	1N3768, 1N4529...4530
7054	1S2085(A)		BB 105, BB 205, BB 305, BB 405, BB 505
7055	1S2086(A)		BB 105, BB 205, BB 305, BB 405, BB 505
7056	1S2087(A)		BB 105, BB 205, BB 305, BB 405, BB 505
7057	1S2088(A)		BB 105, BB 205, BB 305, BB 405, BB 505
7058	1S209	1S208, 450V	BY 126...127, BY 133...134, 1N4005...07
7059	1S2090		BA 121, BB 117, BB 417, 1SV89
7060	1S2091(A)[Texas]	1S2030[Texas], 9,1V	1S2030
7061	1S2091[Toshiba]	175V, 0,03A, <100ns	BA 195, BA 197...198, BAV 20...21
7062	1S2092	125V, 0,03A, <100ns	BA 195, BA 197...198, BAV 19...21
7063	1S2093	Ub26..38V, Ib<0,05mA, Itsm2A	1N5761, N413M, BR100, D3202Y, DO201YR
7064	1S2094		BA 121, BB 117, BB 417, 1SV89

7065	1S2095	55V, 0,25A, <8ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7066	1S2095A	1S2095, 75V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7067	1S2097	225V, 0,03A, <4ns	-
7068	1S2098	175V, 0,04A, <4ns	-
7069	1S2099	125V, 0,05A, <4ns	BA 203
7070	1S210	1S208, 650V	BY 127, BY 133, BY 227, 1N4006...07
7071	1S2100(A)[Texas]	1S2030[Texas], 10V	1S2030
7072	1S2107(A)[Tosh.]	3,9V, 0,25W, 10%, (A5%)	BZX55/..., BZX79/..., ZPD..., 1N5228...48
7073	1S2108(A)[Tosh.]	1S2107[Tosh.], 4,3V	
7074	1S2109(A)[Tosh.]	1S2107[Tosh.], 4,7V	
7075	1S211	1S208, 850V	BY 127, BY 133, BY 227, 1N4007
7076	1S2110(A)[Texas]	1S2030[Texas], 11V	1S2030
7077	1S2110(A)[Tosh.]	1S2107[Tosh.], 5,1V	1S2107
7078	1S2111(A)[Tosh.]	1S2107[Tosh.], 5,6V	
7079	1S2112(A)[Tosh.]	1S2107[Tosh.], 6,2V	
7080	1S2113(A)[Tosh.]	1S2107[Tosh.], 6,8V	
7081	1S2114(A)[Tosh.]	1S2107[Tosh.], 7,5V	
7082	1S2115(A)[Tosh.]	1S2107[Tosh.], 8,2V	
7083	1S2116(A)[Tosh.]	1S2107[Tosh.], 9,1V	
7084	1S2117(A)[Tosh.]	1S2107[Tosh.], 10V	
7085	1S2118(A)[Tosh.]	1S2107[Tosh.], 11V	
7086	1S2119(A)[Tosh.]	1S2107[Tosh.], 12V	
7087	1S212	8..9V, 0,3W	-
7088	1S2120(A)[Texas]	1S2030[Texas], 12V	1S2030
7089	1S2120(A)[Tosh.]	1S2107[Tosh.], 13V	1S2107
7090	1S2121(A)[Tosh.]	1S2107[Tosh.], 15V	
7091	1S2122(A)[Tosh.]	1S2107[Tosh.], 16V	
7092	1S2123(A)[Tosh.]	1S2107[Tosh.], 18V	
7093	1S2124	300V, 0,5A	BY 126...127, BY 133...134, 1N4004...07
7094	1S2128[NEC]	5,4..6,6V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5919...53
7095	1S2129[NEC]	1S2128[NEC], 7,5..10V	
7096	1S213	8..9V, 0,3W	-
7097	1S2130(A)[Texas]	1S2030[Texas], 13V	1S2030
7098	1S2130[NEC]	1S2128[NEC], 10,8..13,2V	
7099	1S2131[NEC]	1S2128[NEC], 17..20V	1S2128
7100	1S2132[NEC]	1S2128[NEC], 80..115V	
7101	1S2133[NEC]	1S2128[NEC], 115..140V	
7102	1S2134	40V, 45mA, <7ns	BA 318, BAY 38, 1N4305, 1N4148...49
7103	1S2135	70V, 0,25A, <7ns	BAW 62, BAX 95, 1N4446...49, 1N4148...49
7104	1S2139(A...C)		BB 105, BB 205, BB 305, BB 405, BB 505
7105	1S214	8..9V, 0,3W	-
7106	1S2140	60V, 0,25A, <6ns	BAW 62, BAX 95, 1N4446...49, 1N4148...49
7107	1S2142		BB 104, BB 204, BB 304, MV 104
7108	1S2143		BB 104, BB 204, BB 304, MV 104
7109	1S2144(A...C)	40V, 0,15A, 5ns	BA 200...201, BAW 46, BAX 80, 1N4148...49



7110	1S2145	90V, 0,1A, <5ns	BA 219, 1N4446...49, 1N4148...49
7111	1S2147(A...D)		BA 105, BA 205, BA 305, BA 405, BA 505
7112	1S2148	100V, 1,5A	2x BY226...227, BY251...255, 1N5392...99
7113	1S2148R...2149R	1S2148	2x BY226...227, BY251...255, 1N5393...99
7114	1S2149	1S2148, 200V	2x BY226...227, BY251...255, 1N5393...99
7115	1S215	8,9..9,9V, 0,3W	-
7116	1S2150(A)[Texas]	1S2030[Texas], 15V	1S2030
7117	1S216	8,9..9,9V, 0,3W	-
7118	1S2160(A)[Texas]	1S2030[Texas], 16V	1S2030
7119	1S217	8,9..9,9V, 0,3W	-
7120	1S2176	6kV, 0,1A, <500ns	BYX 90, 1N5183
7121	1S2177	6kV, 0,3A, <500ns	-
7122	1S2178	6kV, 0,5A, <500ns	-
7123	1S2179	1200V, 2A	BY 228, BY 246/1200, BY 448, BY 458
7124	1S218	40V, 0,04A, <2ns	BA 218, BAX 13, BAX 91, 1N4148...49
7125	1S2180(A)[Texas]	1S2030[Texas], 18V	1S2030
7126	1S2180[Origin]	12kV, 0,1A, <500ns	1N3052
7127	1S2181[Origin]	36kV, 0,1A, <500ns	-
7128	1S2186		BA 244, BA 282, BA 284, BA 482
7129	1S2187	2V, 30mA, 900MHz	BA 480...481, BAT 19, BAT 29
7130	1S2188		-
7131	1S219	300V, 10A	-
7132	1S2190	7,7..8,7V	BZX 51, 1N4780
7133	1S2191	7,7..8,7V	BZX 52, 1N4781
7134	1S2192	7,7..8,7V	BZX 53, 1N4782
7135	1S2193	7,7..8,7V	BZX 54, 1N4783
7136	1S2194	5,4..6,6V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5232...43
7137	1S2195	1S2194, 7,5..10V	
7138	1S2196	1S2194, 10,8..13,2V	
7139	1S2197(A)		-
7140	1S2198	5V, 30mA, 855MHz	BA 480...481, BAR 19, BAT 29
7141	1S2199[NEC]		-
7142	1S220	4,5V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5917...53
7143	1S2200(A)[Texas]	1S2030[Texas], 20V	1S2030
7144	1S2200[NEC]		-
7145	1S2204	70V, 0,2A, <7ns	BAW 62, BAX 95, 1N4446...49, 1N4148...49
7146	1S2206		BA 121, BB 117, BB 417, 1SV89
7147	1S2207		BA 125, BB 119, 1SV114, 1SV125
7148	1S2208		BB 105, BB 205, BB 305, BB 405, BB 505
7149	1S2209		BB 105, BB 205, BB 305, BB 405, BB 505
7150	1S221	1S220, 5,5V	
7151	1S2210	11V, 0,02A	BAT 19, 1SS88, 1SS106
7152	1S2211	33V, 35mA	BAT 81
7153	1S2212	30V, 0,1A, <100ns	BAV 17...20, BAX 90, BAX 94, 1N3070
7154	1S222	1S220, 6,5V	



7155	1S2220(A)[Texas]	1S2030[Texas], 22V	1S2030
7156	1S2222		BA 244, BA 282, BA 284, BA 482
7157	1S2223	100V, 1,8A	2x BY251...255, BY259/150, 1N5060...62
7158	1S2223R...2225R	1S2223	2x BY251...255, BY259/..., 1N5060...62
7159	1S2224	1S2223, 200V	2x BY251...255, BY259/300, 1N5060...62
7160	1S2225	1S2223, 400V	2x BY252...255, BY259/600, 1N5060...62
7161	1S2226	100V, 1A	BY 126...127, BY 133...135, 1N4002...07
7162	1S2227	1S2226, 200V	BY 126...127, BY 133...134, 1N4003...07
7163	1S2228	1S2226, 400V	BY 126...127, BY 133...134, 1N4004...07
7164	1S2229	1S2226, 600V	BY 126...127, BY 133...134, 1N4005...07
7165	1S223	1S220, 7,5V	
7166	1S2230	1S2226, 800V	BY 127, BY 133, BY 227, 1N4006...07
7167	1S2231	1S2226, 1000V	BY 127, BY 133, BY 227, 1N4007
7168	1S2233	600V, 1,5A	BY 226...227, BY 253...255, 1N5397...99
7169	1S2234	1S2233, 800V	BY 227, BY 254...255, 1N5398...99
7170	1S2235	1S2233, 1000V	BY 227, BY 255, BYX 86, 1N5399
7171	1S2236		BA 111, BA 124, 1S2790, 1SV50
7172	1S2238[Hitachi]	400V, 1,3A	BYW 53...56, 1N5060...5062
7173	1S2239[Hitachi]	1S2238, 600V	BYW 54...56, 1N5061...5062
7174	1S224	1S220, 8,5V	
7175	1S2240(A)[Texas]	1S2030[Texas], 24V	1S2030
7176	1S2240[Hitachi]	1S2238, 800V	BYW 55...56, 1N5062
7177	1S2241	400V, 1,1A	BYW 53...56, 1N5060...5062
7178	1S2242	1S2241, 600V	BYW 54...56, 1N5061...5062
7179	1S2243	1S2241, 800V	BYW 55...56, 1N5062
7180	1S2244	200V, 0,4A, <800ns	BA 157...159, BY 204/4, BY 206...207
7181	1S2245	1S2244, 400V	BA 157...159, BY 204/4, BY 207
7182	1S2246	1S2244, 600V	BA 158...159, BY 204/8, BY 207
7183	1S225	1S220, 9,5V	
7184	1S226	1S220, 11V	
7185	1S2267		BA 125, BB 119, 1SV114, 1SV125
7186	1S2268		BA 121, BB 117, BB 417, 1SV89
7187	1S2269	400V, 1A	BY 126...127, BY 133...134, 1N4004...07
7188	1S227	1S220, 12V	
7189	1S2270(A)[Texas]	1S2030[Texas], 27V	1S2030
7190	1S2270[Sanken]	200V, 1,3A	BY 226...227, BY 251...255, 1N5393...99
7191	1S2271[Sanken]	1S2270, 400V	BY 226...227, BY 252...255, 1N5395...99
7192	1S2272[Sanken]	1S2270, 600V	BY 226...227, BY 253...255, 1N5397...99
7193	1S2273[Sanken]	1S2270, 800V	BY 227, BY 254...255, 1N5398...99
7194	1S2274[Sanken]	1S2270, 1000V	BY 227, BY 255, BYX 86, 1N5399
7195	1S2277	200V, 0,3A, <800ns	BA 157...159, BY 204/4, BY 206...207
7196	1S2278	1S2277, 400V	BA 157...159, BY 204/4, BY 207
7197	1S2279	1S2277, 600V	BA 158...159, BY 204/8, BY 207
7198	1S228	1S220, 13V	
7199	1S2280	1S2277, 800V	BA 159, BY 204/8, BY 208/800

7200	1S2281	1S2277, 1000V	BA 159, BY 204/10, BY 208/1000
7201	1S2282(A)[Hit.]	2,5..3,5V, 10W(Tc115°)	BZX98/..., BZY93/..., ZX..., 1N2970...89
7202	1S2283(A)[Hit.]	1S2282, 3,4..4,6V	
7203	1S2284(A)[Hit.]	1S2282, 4,4..5,4V	
7204	1S2285(A)[Hit.]	1S2282, 5,2..6,8V	
7205	1S2286(A)[Hit.]	1S2282, 6,2..7,9V	
7206	1S2287(A)[Hit.]	1S2282, 7,7..8,7V	
7207	1S2288(A)[Hit.]	1S2282, 8,5..9,6V	
7208	1S2289(A)[Hit.]	1S2282, 9,4..10,6V	
7209	1S229	1S220, 14V	
7210	1S2290(A)[Hit.]	1S2282, 10,4..11,6V	
7211	1S2291(A)[Hit.]	1S2282, 11,4..12,7V	
7212	1S2292(A)[Hit.]	1S2282, 12,4..14,1V	
7213	1S2293(A)[Hit.]	1S2282, 13,5..15,6V	
7214	1S2294(A)[Hit.]	1S2282, 15,3..17,1V	
7215	1S2295(A)[Hit.]	1S2282, 16,8..19,1V	
7216	1S2296(A)[Hit.]	1S2282, 18,8..21,2V	
7217	1S2297(A)[Hit.]	1S2282, 20,8..23,3V	
7218	1S2298(A)[Hit.]	1S2282, 22,7..25,6V	
7219	1S2299(A)[Hit.]	1S2282, 25,1..28,9V	
7220	1S230	1S220, 15V	
7221	1S2300(A)[Hit.]	1S2282, 28..32V	
7222	1S2300(A)[Texas]	1S2030[Texas], 30V	1S2030
7223	1S2301	1,4..2,6V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5913...18
7224	1S2302	1S2301, 2,4..3,6V	
7225	1S2303	1S2301, 3,4..4,6V	
7226	1S2304	1S2301, 4,4..5,4V	
7227	1S2305	Ub28..38V, Ib<0,2mA, Itsm2A	1N5761, N413M, D3202Y, BR100, DO201YR
7228	1S2306	600V, 1A	BY 126...127, BY 133...134, 1N4005...07
7229	1S2307	1S2306, 800V	BY 127, BY 133, BY 228, 1N4006...07
7230	1S2308	1S2306, 1000V	BY 127, BY 133, BY 228, 1N4007
7231	1S2309	1S2306, 1500V	BY 228, BY 400, BY 448, EM 516, GP 10W
7232	1S231	1S220, 16V	
7233	1S2310	600V, 0,3A	BA 158...159, BY 204/8, BY 208/600
7234	1S2311	1S2310, 800V	BA 159, BY 204/8, BY 208/800
7235	1S2312	1S2310, 1000V	BA 159, BY 204/10, BY 208/1000
7236	1S2313	600V, 0,15A	BA 158...159, BY 204/8, BY 208/600
7237	1S2314	1S2313, 800V	BA 159, BY 204/8, BY 208/800
7238	1S2315	1S2313, 1000V	BA 159, BY 204/10, BY 208/1000
7239	1S2316	400V, 0,13A, <300ns	BA 157...159, BY 204/4, BY 208/600
7240	1S2317	1S2316, 600V	BA 158...159, BY 204/8, BY 208/800
7241	1S2318	1S2316, 800V	BA 159, BY 204/8, BY 208/800
7242	1S2319	1S2316, 1000V	BA 159, BY 204/10, BY 208/1000
7243	1S232	1S220, 17V	
7244	1S2323	800V, 0,4A, <800ns	BA 159, BY 204/8, BY 208/800, BY 228

7245	1S2324	1S2323, 1000V	BA 159, BY 204/10, BY 208/1000, BY 228
7246	1S2325	1S2323, 1300V	BY 228, BY 268...269, BY 400, BY 448
7247	1S2326	1S2323, 1500V	BY 228, BY 269, BY 400, BY 448
7248	1S2329	400V, 0,3A	BA 147...159, BY 204/4, BY 207
7249	1S233	1S220, 18V	
7250	1S2330(A)[Texas]	1S2030[Texas], 33V	1S2030
7251	1S2331	100V, 100A(Tc130°)	D120/400, DS 80-04A, DS 85-01C
7252	1S2332	1S2331, 200V	D120/400, DS 80-04A, DS 85-02C
7253	1S2333	1S2331, 300V	D120/400, DS 80-04A, DS 85-04C
7254	1S2334	1S2331, 400V	D120/400, DS 80-04A, DS 85-04C
7255	1S2335	1S2331, 600V	D120/800, DS 80-07A, DS 85-06C
7256	1S2336	1S2331, 800V	D120/800, DS 80-11A, DS 85-08C
7257	1S2337	1S2331, 1000V	D120/1200, DS 80-14A, DS 85-10C
7258	1S2339		BB 105, BB 205, BB 305, BB 405, BB 505
7259	1S234	1S220, 19V	
7260	1S2340		BA 121, BA 125, BB 117, BB 119
7261	1S2348H	65V, 0,25A, <8ns	BAW 62, BAX 95, 1N4446...48, 1N4148...49
7262	1S2349	200V, 1,8A	2x (BY 226...227, BY 251...255, 1N5060)
7263	1S2349R...2350R	1S2349	2x (BY 226...227, BY 251...255, 1N5060)
7264	1S235	1S220, 20V	
7265	1S2350	1S2349, 400V	2x (BY 226...227, BY 252...255, 1N5060)
7266	1S2351	200V, 0,1A, <1,5µs	BA 157...159, BAY 88...91, BY 203/12
7267	1S2352	1S2351, 600V	BA 158...159, BAY 89...91, BY 203/12
7268	1S2353	1S2351, 800V	BA 159, BAY 90...91, BY 203/12
7269	1S2354	1S2351, 1000V	BA 159, BAY 90...91, BY 203/12
7270	1S2355	1S2351, 1500V	BAY 91, BY 203/16, BY 584, SHG 1,5
7271	1S2356	200V, 0,4A	BYW 52...56, 1N4245...4249
7272	1S2357	1S2356, 400V	BYW 53...56, 1N4246...4249
7273	1S2358	200V, 0,6A	BYW 52...56, 1N4245...4249
7274	1S2359	1S2358, 400V	BYW 53...56, 1N4246...4249
7275	1S236	1S220, 22V	
7276	1S2361	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
7277	1S2362	1S2361, 400V	BY 126...127, BY 133...134, 1N4004...07
7278	1S2363	1S2361, 600V	BY 126...127, BY 133...134, 1N4005...07
7279	1S2364	1S2361, 800V	BY 127, BY 133, BY 227, 1N4006...07
7280	1S2365	1S2361, 1000V	BY 127, BY 133, BY 227, 1N4007
7281	1S2366	200V, 0,1A, <1,5µs	BA 157...159, BAY 88...91, BY 203/12
7282	1S2367	1S2366, 600V	BA 158...159, BAY 89...91, BY 203/12
7283	1S2368	1S2366, 800V	BA 159, BAY 90...91, BY 203/12
7284	1S2369	1S2368, 1000V	BA 159, BAY 90...91, BY 203/12
7285	1S237	1S220, 24V	
7286	1S2370	1S2366, 1500V	BAY 91, BY 203/12, BY 584, SHG 1,5
7287	1S2377	100V, 1,8A	2x (BY 226...227, BY 251...255, 1N5060)
7288	1S2377R...2380R	1S2377	2x (BY 226...227, BY 251...255, 1N5061)
7289	1S2378	1S2377, 200V	2x (BY 226...227, BY 251...255, 1N5060)

7290	1S2379	1S2377, 400V	2x (BY 226...227, BY 252...255, 1N5060)
7291	1S238	1S220, 25V	
7292	1S2380	1S2377, 600V	2x (BY 226...227, BY 253...255, 1N5061)
7293	1S2381	100V, 1A	2x (BY 126...127, BY 133...135, 1N4002)
7294	1S2382	1S2381, 200V	2x (BY 126...127, BY 133...134, 1N4003)
7295	1S2383	1S2381, 400V	2x (BY 126...127, BY 133...134, 1N4004)
7296	1S2384	1S2381, 600V	2x (BY 126...127, BY 133...134, 1N4005)
7297	1S2387H	130V, 0,25A, <10ns	BA 203, BAV 14
7298	1S239	1S220, 27V	
7299	1S2390	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
7300	1S2391	1S2390, 100V	BY 126...127, BY 133...135, 1N4002...07
7301	1S2392	1S2390, 200V	BY 126...127, BY 133...134, 1N4003...07
7302	1S2393	1S2390, 300V	BY 126...127, BY 133...134, 1N4004...07
7303	1S2394	1S2390, 400V	BY 126...127, BY 133...134, 1N4004...07
7304	1S2395	1S2390, 500V	BY 126...127, BY 133...134, 1N4005...07
7305	1S2396	1S2390, 600V	BY 126...127, BY 133...134, 1N4005...07
7306	1S2397	1S2390, 700V	BY 127, BY 133, BY 227, 1N4006...07
7307	1S2398	1S2390, 800V	BY 127, BY 133, BY 227, 1N4006...07
7308	1S2399	1S2390, 900V	BY 127, BY 133, BY 227, 1N4007
7309	1S240	1S220, 30V	
7310	1S2400	1S2390, 1000V	BY 127, BY 133, BY 227, 1N4007
7311	1S2401	100V, 1A	BY 126...127, BY 133...135, 1N4002...07
7312	1S2402	1S2401, 200V	BY 126...127, BY 133...134, 1N4003...07
7313	1S2403	1S2401, 400V	BY 126...127, BY 133...134, 1N4004...07
7314	1S2404	1S2401, 600V	BY 126...127, BY 133...134, 1N4005...07
7315	1S2405	1S2401, 800V	BY 127, BY 133, BY 227, 1N4006...07
7316	1S2406	1S2401, 1000V	BY 127, BY 133, BY 227, 1N4007
7317	1S2407	1S2401, 1200V	BY 127, BY 133, BY 227, GP 10Q
7318	1S2408	50V, 2A	BY 226...227, BY 251...255, 1N5060...62
7319	1S2409	1S2408, 100V	BY 226...227, BY 251...255, 1N5060...62
7320	1S241	1S220, 33V	
7321	1S2410	1S2408, 200V	BY 226...227, BY 251...255, 1N5060...62
7322	1S2411	1S2408, 300V	BY 226...227, BY 252...255, 1N5060...62
7323	1S2412	1S2408, 400V	BY 226...227, BY 252...255, 1N5060...62
7324	1S2413	1S2408, 500V	BY 226...227, BY 253...255, 1N5061...62
7325	1S2414	1S2408, 600V	BY 226...227, BY 253...255, 1N5061...62
7326	1S2415	50V, 2A	BY 226...227, BY 251...255, 1N5060...62
7327	1S2416	1S2415, 100V	BY 226...227, BY 251...255, 1N5060...62
7328	1S2417	1S2415, 200V	BY 226...227, BY 251...255, 1N5060...62
7329	1S2418	1S2415, 300V	BY 226...227, BY 252...255, 1N5060...62
7330	1S2419	1S2415, 400V	BY 226...227, BY 252...255, 1N5060...62
7331	1S242	1S220, 36V	
7332	1S2420	1S2415, 500V	BY 226...227, BY 253...255, 1N5061...62
7333	1S2421	1S2415, 600V	BY 226...227, BY 253...255, 1N5061...62
7334	1S2422	50V, 20A(Tc115°)	1N3491...3495

7335	1S2422R...2427R	1S2422	DS 25-...A
7336	1S2423	1S2422, 100V	1N3492...3495
7337	1S2424	1S2422, 200V	1N3493...3495
7338	1S2425	1S2422, 300V	1N3494...3495
7339	1S2426	1S2422, 400V	1N3495
7340	1S2427	1S2422, 500V	-
7341	1S243	1S220, 39V	
7342	1S2434	50V, 12A(Tc120°)	1N3765...3768, 1N4525...4530
7343	1S2434R...2439R	1S2434	D24/...C, 1N3765R...3768R
7344	1S2435	1S2434, 100V	1N3765...3768, 1N4525...4530
7345	1S2436	1S2434, 200V	1N3765...3768, 1N4525...4530
7346	1S2437	1S2434, 300V	1N3765...3768, 1N4526...4530
7347	1S2438	1S2434, 400V	1N3765...3768, 1N4526...4530
7348	1S2439	1S2434, 500V	1N3765...3768, 1N4527...4530
7349	1S244	1S220, 43V	
7350	1S2440	50V, 25A(Tc120°)	1N3491...3495
7351	1S2440R...2445R	1S2440	DS 25-...A
7352	1S2441	1S2440, 100V	1N3492...3495
7353	1S2442	1S2440, 200V	1N3493...3495
7354	1S2443	1S2440, 300V	1N3494...3495
7355	1S2444	1S2440, 400V	1N3495
7356	1S2445	1S2440, 500V	-
7357	1S2445R...2451R	1S2446	D24/...C, 1N3765R...3768R
7358	1S2446	50V, 25A(Tc120°)	1N3765...3768, 1N4525...4530
7359	1S2447	1S2446, 100V	1N3765...3768, 1N4525...4530
7360	1S2448	1S2446, 200V	1N3765...3768, 1N4525...4530
7361	1S2449	1S2446, 300V	1N3765...3768, 1N4526...4530
7362	1S245	1S220, 45V	
7363	1S2450	1S2446, 400V	1N3765...3768, 1N4526...4530
7364	1S2451	1S2446, 500V	1N3765...3768, 1N4527...4530
7365	1S2452	6..7V, 0,25W	BZV 10, BZV 27, 1N4580
7366	1S2453	6..7V, 0,25W	BZV 11, BZV 28, 1N4581
7367	1S2454	6..7V, 0,25W	BZV 12, BZV 29, 1N4582
7368	1S2455	100V, 2,5A	BY 251...255, BY 259/150, 1N5402...08
7369	1S2456	1S2455, 200V	BY 251...255, BY 259/300, 1N5402...08
7370	1S2457	1S2455, 400V	BY 252...255, BY 259/600, 1N5404...08
7371	1S2458	1S2455, 600V	BY 253...255, BY 259/600, 1N5406...08
7372	1S2459	1S2455, 800V	BY 254...255, BY 259/900, 1N5407...08
7373	1S246	1S220, 47V	
7374	1S2460	70V, 0,1A	BA 147/100, BAY 19...21, 1N5606...09
7375	1S2461	1S2460, 120V	BA 147/150, BAY 20...21, 1N5606...09
7376	1S2462	1S2460, 220V	BA 147/230, BAY 21, BAY 46, BAY 88
7377	1S2463	1S2460, 320V	BA 147/300, BAY 21, BAY 46, BAY 88
7378	1S2469	18kV, 0,02A	CY 20, HS 13
7379	1S247	1S220, 50V	

7380	1S2470	1S2469, 12kV	HS 10
7381	1S2471	90V, 0,13A, <4ns	BA 219, 1N4148...49, 1N4446...4449
7382	1S2472	55V, 0,12A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7383	1S2473	40V, 0,11A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
7384	1S2474	0,6..0,8V, 0,75W	BZW22/..., BZX61/..., ZPY..., 1N5913...56
7385	1S2474R...2530R	1S2474...2530	
7386	1S2475	1S2474, 1,3..1,7V	
7387	1S2476	1S2474, 1,69..1,9V	
7388	1S2477	1S2474, 1,88..2,1V	
7389	1S2478	1S2474, 2,09..2,31V	
7390	1S2479	1S2474, 2,28..2,55V	
7391	1S248	1S220, 52V	
7392	1S2480	1S2474, 2,54..2,85V	
7393	1S2481	1S2474, 2,83..3,15V	
7394	1S2482	1S2474, 3,13..3,47V	
7395	1S2483	1S2474, 3,42..3,78V	
7396	1S2484	1S2474, 3,7..4,1V	
7397	1S2485	1S2474, 4,08..4,52V	
7398	1S2486	1S2474, 4,47..4,94V	
7399	1S2487	1S2474, 4,84..5,36V	
7400	1S2488	1S2474, 5,32..5,9V	
7401	1S2489	1S2474, 5,89..6,51V	
7402	1S249	1S220, 56V	
7403	1S2490	1S2474, 6,46..7,14V	
7404	1S2491	1S2474, 7,12..7,88V	
7405	1S2492	1S2474, 7,79..8,63V	
7406	1S2493	1S2474, 8,62..9,56V	
7407	1S2494	1S2474, 9,5..10,5V	
7408	1S2495	1S2474, 10,4..11,6V	
7409	1S2496	1S2474, 11,4..12,6V	
7410	1S2497	1S2474, 12,3..13,7V	
7411	1S2498	1S2474, 13,2..15,8V	
7412	1S2499	1S2474, 15,2..17V	
7413	1S250	1S220, 62V	
7414	1S2500	1S2474, 16,9..19V	
7415	1S2501	1S2474, 18,8..21V	
7416	1S2502	1S2474, 20,9..23,1V	
7417	1S2503	1S2474, 22,8..25,5V	
7418	1S2504	1S2474, 25,4..28,5V	
7419	1S2505	1S2474, 28,3..31,5V	
7420	1S2506	1S2474, 31,3..34,7V	
7421	1S2507	1S2474, 34,2..37,8V	
7422	1S2508	1S2474, 37..41V	
7423	1S2509	1S2474, 40,8..45,2V	
7424	1S251	1S220, 68V	

7425	1S2510	1S2474, 44,7..49,4V	
7426	1S2511	1S2474, 48,4..53,6V	
7427	1S2512	1S2474, 53,2..59V	
7428	1S2513	1S2474, 58,9..65,1V	
7429	1S2514	1S2474, 64,6..71,4V	
7430	1S2515	1S2474, 71,2..78,8V	
7431	1S2516	1S2474, 77,9..86,3V	
7432	1S2517	1S2474, 86,2..95,6V	
7433	1S2518	1S2474, 95..105V	
7434	1S2519	1S2474, 104..116V	
7435	1S252	1S220, 75V	
7436	1S2520	1S2474, 114..126V	
7437	1S2521	1S2474, 123..137V	
7438	1S2522	1S2474, 132..158V	
7439	1S2523	1S2474, 152..170V	
7440	1S2524	1S2474, 169..190V	
7441	1S2525	1S2474, 188..210V	
7442	1S2526	1S2474, 209..231V	
7443	1S2527	1S2474, 228..255V	
7444	1S2528	1S2474, 254..285V	
7445	1S2529	1S2474, 283..315V	
7446	1S253	1S220, 82V	
7447	1S2530	1S2474, 313..347V	
7448	1S2531	0,6..0,8V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5221...71
7449	1S2531R...2575R	1S2531	
7450	1S2532	1S2531, 1,3..1,7V	
7451	1S2533	1S2531, 1,69..1,9V	
7452	1S2534	1S2531, 1,88..2,1V	
7453	1S2535	1S2531, 2,09..2,31V	
7454	1S2536	1S2531, 2,28..2,55V	
7455	1S2537	1S2531, 2,54..2,85V	
7456	1S2538	1S2531, 2,83..3,15V	
7457	1S2539	1S2531, 3,13..3,47V	
7458	1S254	1S220, 91V	
7459	1S2540	1S2531, 3,42..3,78V	
7460	1S2541	1S2531, 3,7..4,1V	
7461	1S2542	1S2531, 4,08..4,52V	
7462	1S2543	1S2531, 4,47..4,94V	
7463	1S2544	1S2531, 4,84..5,36V	
7464	1S2545	1S2531, 5,32..5,9V	
7465	1S2546	1S2531, 5,89..6,51V	
7466	1S2547	1S2531, 6,46..7,14V	
7467	1S2548	1S2531, 7,12..7,88V	
7468	1S2549	1S2531, 7,79..8,63V	
7469	1S255	1S220, 100V	



7470	1S2550	1S2531, 8,62..9,56V	
7471	1S2551	1S2531, 9,5..10,5V	
7472	1S2552	1S2531, 10,4..11,6V	
7473	1S2553	1S2531, 11,4..12,6V	
7474	1S2554	1S2531, 12,3..13,7V	
7475	1S2555	1S2531, 13,2..15,8V	
7476	1S2556	1S2531, 15,2..17V	
7477	1S2557	1S2531, 16,9..19V	
7478	1S2558	1S2531, 18,8..21V	
7479	1S2559	1S2531, 20,9..23,1V	
7480	1S256	1S220, 105V	
7481	1S2560	1S2531, 22,8..25,5V	
7482	1S2561	1S2531, 25,4..28,5V	
7483	1S2562	1S2531, 28,3..31,5V	
7484	1S2563	1S2531, 31,3..34,7V	
7485	1S2564	1S2531, 34,2..37,8V	
7486	1S2565	1S2531, 37..41V	
7487	1S2566	1S2531, 40,8..45,2V	
7488	1S2567	1S2531, 44,7..49,4V	
7489	1S2568	1S2531, 48,4..53,6V	
7490	1S2569	1S2531, 53,2..59V	
7491	1S257	1S220, 110V	
7492	1S2570	1S2531, 58,9..65,1V	
7493	1S2571	1S2531, 64,6..71,4V	
7494	1S2572	1S2531, 71,2..78,8V	
7495	1S2573	1S2531, 77,9..86,3V	
7496	1S2574	1S2531, 86,2..95,6V	
7497	1S2575	1S2531, 95..105V	
7498	1S258	1S220, 120V	
7499	1S2588		BA 182, BA 243, BA 283, BA 483...484
7500	1S2589	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
7501	1S259	1S220, 130V	
7502	1S2590	1S2589, 100V	BY 126...127, BY 133...135, 1N4002...07
7503	1S2591	1S2589, 200V	BY 126...127, BY 133...134, 1N4003...07
7504	1S2592	800V, 1A, <800ns	BY 231/800, BY 400, MR 817, RGP 10K
7505	1S2593	1S2592, 1000V	BY 231/1000, BY 400, MR 818, RGP 10M
7506	1S2594	1S2592, 1300V	BY 231/1400, BY 228, BY 400, BY 448
7507	1S2595	1S2592, 1500V	BY 231/1500, BY 228, BY 400, BY 448
7508	1S2596	200V, 2A, <600ns	BY 218/200, BY 296...299, BYW 32...36
7509	1S2597	1S2596, 400V	BY 218/400, BY 298...299, BYW 34...36
7510	1S2598	1S2596, 600V	BY 218/600, BY 228, BY 299, BYW 36
7511	1S26	100V, 3,5A	-
7512	1S260	1S220, 140V	
7513	1S2602	200V, 1A	BYW 52...56, 1N4245...49, 1N5060...62
7514	1S2603	1S2602, 300V	BYW 53...56, 1N4246...49, 1N5060...62

7515	1S2604	1S2602, 400V	BYW 53...56, 1N4246...49, 1N5060...62
7516	1S2605	1S2602, 500V	BYW 54...56, 1N4247...49, 1N5061...62
7517	1S2606	1S2602, 600V	BYW 54...56, 1N4247...49, 1N5061...62
7518	1S2607	1S2602, 700V	BYW 55...56, 1N4248...49, 1N5062
7519	1S2608	1S2602, 800V	BYW 55...56, 1N4248...49, 1N5062
7520	1S2609	1S2602, 900V	BYW 56, 1N4249
7521	1S261	1S220, 150V	
7522	1S2610	1S2602, 1000V	BYW 56, 1N4249
7523	1S2611	1S2602, 1100V	SSiB9860A
7524	1S2612	1S2602, 1200V	SSiB9880A
7525	1S2613	1S2602, 1300V	SSiB9880A
7526	1S2614	1S2602, 1400V	SSiB9880A
7527	1S2615	600V, 1A, <250ns	BY 201/6, BYV 14...16, BYX 55/600
7528	1S2616	1S2615, <350ns	BY 201/6, BYV 14...16, BYX 55/600
7529	1S2617	1S2615, <900ns	BY 201/6, BYV 14...16, BYX 55/600
7530	1S2618	800V, 1A, <800ns	BY245/800, BY231/800, MR817, RGP10K
7531	1S2619	8kV, 0,04A	1N5184
7532	1S262	4,5V, 10%, 10W	BZX98/..., BZY93/..., ZL..., 1N2970...3011
7533	1S2620	16kV, 0,04A	1N3054
7534	1S2621	24kV, 0,04A	1N3058
7535	1S2622	32kV, 0,04A	1N3061
7536	1S2628	100V, 5,5A, <300ns	1N3880R...3883R
7537	1S2629	1S2628, 200V	1N3881R...3883R
7538	1S263	1S262, 5,5V	
7539	1S2630	100V, 8A(Tc70°), <300ns	BYV 30/100, BYW 30/100, BYX 61/100
7540	1S2631	1S2630, 200V	BYV 30/200, BYW 30/200, BYX 61/200
7541	1S2632	100V, 16A(Tc70°), <300ns	-
7542	1S2633	1S2632, 200V	-
7543	1S2634	100V, 46A(Tc70°), <400ns	-
7544	1S2635	1S2634, 200V	-
7545	1S2636	100V, 95A(Tc70°), <400ns	-
7546	1S2637	1S2636, 200V	-
7547	1S2638		BA 125, BB 119, 1SV114, 1SV125
7548	1S2639	1400V, 50A(Tc125°)	-
7549	1S264	1S262, 6,5V	
7550	1S2640	1S2639, 1600V	-
7551	1S2641	1S2639, 2000V	-
7552	1S2642	1S2639, 2500V	-
7553	1S2643	1S2639, 3000V	-
7554	1S2644	1400V, 80A(Tc115°)	-
7555	1S2645	1S2644, 1600V	-
7556	1S2646	1S2644, 2000V	-
7557	1S2647	1S2644, 2500V	-
7558	1S2648	1S2644, 3000V	-
7559	1S2649	400V, 100A(Tc90°)	1N3291R...3297R

7560	1S265	1S262, 7,5V	
7561	1S2650	1S2649, 600V	1N3293R...3297R
7562	1S2651	1S2649, 800V	1N3294R...3297R
7563	1S2652	1S2649, 1000V	1N3295R...3297R
7564	1S2653	1S2649, 1200V	1N3296R...3297R
7565	1S2654	600V, 210A(Tc110°)	1N3740R...3744R
7566	1S2655	1S2654, 800V	1N3741R...3744R
7567	1S2656	1S2654, 1000V	1N3742R...3744R
7568	1S2657	1S2654, 1200V	1N3743R...3744R
7569	1S2658	1S2654, 1400V	1N3744R
7570	1S2659	1S2654, 1600V	-
7571	1S266	1S262, 8,5V	
7572	1S2660	600V, 400A(Tc100°)	-
7573	1S2661	1S2660, 800V	-
7574	1S2662	1S2660, 1000V	-
7575	1S2663	1S2660, 1200V	-
7576	1S2664	1S2660, 1400V	-
7577	1S2665	1S2660, 1600V	-
7578	1S2666	100V, 80A, <300ns	-
7579	1S2667	1S2666, 200V	-
7580	1S2668	1S2666, 250V	-
7581	1S267	1S262, 9,5V	
7582	1S2672	200V, 0,8A, <200ns	BY 201/2, BYT 52D, BYX 92/200, RGP 10D
7583	1S2673	1S2672, 300V	BY 201/3, BYT 52G, BYX 92/300, RGP 10G
7584	1S2674	1S2672, 400V	BY 201/4, BYT 52G, BYX 92/400, RGP 10G
7585	1S2675	1S2672, 500V	BY 201/5, BYT 52J, RGP 10J
7586	1S2676	1S2672, 600V	BY 201/6, BYT 52J, RGP 10J
7587	1S2677	1S2672, 700V	BYT 52K, RGP 10K
7588	1S2678	1S2672, 800V	BYT 52K, RGP 10K
7589	1S2679	1S2672, 1000V	BYT 52M, RGP 10M
7590	1S268	1S262, 11V	
7591	1S2685		BB 105, BB 205, BB 305, BB 405, BB 505
7592	1S2686		-
7593	1S2687		-
7594	1S2688		-
7595	1S2689		-
7596	1S269	1S262, 12V	
7597	1S2692		BA 182, BA 243, BA 283, BA 483...484
7598	1S270	1S262, 13V	
7599	1S271	1S262, 14V	
7600	1S2711	1500V, 1,5A	BY 228, BY 255, BY 400, BY 448
7601	1S2712	1800V, 1,4A, <2,2µs	-
7602	1S2714	100V, 6A(Tc100°), <200ns	1N3880...3883
7603	1S2715	1S2714, 200V	1N3881...3883
7604	1S2716	1S2714, 300V	1N3882...3883

7605	1S2717	1S2714, 400V	1N3883
7606	1S2718	1S2714, 600V	-
7607	1S2719	100V, 30A(Tc100°), <200ns	1N3910...3913
7608	1S272	1S262, 15V	
7609	1S2720	1S2719, 200V	1N3911...3913
7610	1S2721	1S2719, 300V	1N3912...3913
7611	1S2722	1S2719, 400V	1N3913
7612	1S2723	1S2719, 600V	-
7613	1S2724	200V, 5A	-
7614	1S2724	200V, 5A	-
7615	1S2724R..2726R	1S2724	-
7616	1S2725	1S2724, 400V	-
7617	1S2725	1S2724, 400V	-
7618	1S2725	1S2724, 400V	-
7619	1S2726	1S2724, 600V	-
7620	1S2726	1S2724, 600V	-
7621	1S2726	1S2724, 600V	-
7622	1S273	1S262, 16V	
7623	1S274	1S262, 17V	
7624	1S2745	750V, 2,5A, <1,3µs	BY 228, BY 438, RGP 30K
7625	1S2746	1S2745, 800V	BY 228, BY 438, RGP 30K
7626	1S2747	1S2745, 1000V	BY 228, BY 438, RGP 30M
7627	1S275	1S262, 18V	
7628	1S2756	400V, 1A, <2,5µs	BY 201/4, BYX 55/600, RGP 10G
7629	1S2757	1S2756, 600V	BY 201/6, BYX 55/600, RGP 10J
7630	1S2758	1000V, 3A	BY 255, BYW 17/1000, G3M, 1N5408
7631	1S2759	1S2758, 1200V	BY 255, BYW 17/1200
7632	1S276	1S262, 19V	
7633	1S2760	1S2758, 50V	BY 251...255, BYW 17/100, 1N5402...08
7634	1S2761	1S2758, 100V	BY 251...255, BYW 17/100, 1N5402...08
7635	1S2762	1S2758, 200V	BY 251...255, BYW 17/200, 1N5402...08
7636	1S2763	1S2758, 300V	BY 252...255, BYW 17/400, 1N5403...08
7637	1S2764	1S2758, 400V	BY 252...255, BYW 17/400, 1N5404...08
7638	1S2765	1S2758, 500V	BY 253...255, BYW 17/600, 1N5406...08
7639	1S2766	1S2758, 600V	BY 253...255, BYW 17/600, 1N5406...08
7640	1S2766A	1S2766	BYM 56C, BYW 18/600, BYW 84...86
7641	1S2767	1S2758, 700V	BY 254...255, BYW 17/800, 1N5407...08
7642	1S2767A	1S2767	BYM 56D, BYW 18/800, BYW 85...86
7643	1S2768	1S2758, 800V	BY 254...255, BYW 17/800, 1N5407...08
7644	1S2768A	1S2768	BYM 56D, BYW 18/800, BYW 85...86
7645	1S2769	6..7V, 0,25W	BZV 10, BZV 27, 1N4580
7646	1S277	1S262, 20V	
7647	1S2770	6..7V, 0,25W	BZV 10, BZV 27, 1N4580
7648	1S2771	6..7V, 0,25W	BZV 11, BZV 28, 1N4581
7649	1S2772	6..7V, 0,25W	BZV 12, BZV 29, 1N4582

7650	1S2773	6..7V, 0,25W	BZV 13, BZV 30, 1N4583
7651	1S2774	6..7V, 0,25W	BZV 14, BZV 31, 1N4584
7652	1S2775	200V, 0,5A, <2 $\mu$ s	BY 295/200, BY 406...407, BYX 55/600
7653	1S2776	1S2775, 400V	BY 295/400, BY 407, BYX 55/600
7654	1S2777	1S2775, 600V	BY 295/600, BY 407, BYX 55/600
7655	1S2778	200V, 2,7A	BY 251...255, GP 30D, MR 502...510
7656	1S2779	1S2778, 400V	BY 252...255, GP 30G, MR 504...510
7657	1S278	1S262, 22V	
7658	1S2780	1S2778, 600V	BY 253...255, GP 30J, MR 506...510
7659	1S2781	1S2778, 800V	BY 254...255, GP 30K, MR 508...510
7660	1S2782	1S2778, 1000V	BY 228, BY 255, GP 30M, MR 510
7661	1S2783		-
7662	1S2784	100V, 0,5A	B100C500, etc.
7663	1S2785	1S2784, 200V	B200C500, etc.
7664	1S2786	1S2784, 400V	B400C500, etc.
7665	1S2787	40V, 0,05A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
7666	1S2788	25V, 0,05A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
7667	1S2789		BB 105, BB 205, BB 305, BB 405, BB 505
7668	1S279	1S262, 24V	
7669	1S2790		BA 125, BB 119, 1SV114, 1SV125
7670	1S2791	5V, 30mA, 887MHz	BA 480...481, BAR 19, BAT 29
7671	1S2792	100V, 20A(Tc90°), <300ns	1N3900R...3903R
7672	1S2793	1S2792, 250V	1N3902R...3903R
7673	1S2794	1S2792, 400V	1N3903R
7674	1S2795	400V, 12A(Tc40°)	-
7675	1S2796	1S2795, 600V	-
7676	1S2797	1S2795, 800V	-
7677	1S2798	1S2795, 1000V	-
7678	1S2799	100V, 150A(Tc76°)	1N4587...4596
7679	1S28	50V, 0,5A	-
7680	1S280	1S262, 25V	
7681	1S2800	1S2799, 200V	1N4588...4596
7682	1S2801	1S2799, 300V	1N4589...4596
7683	1S2802	1S2799, 400V	1N4590...4596
7684	1S2803	1S2799, 600V	1N4592...4596
7685	1S2804	1S2799, 800V	1N4593...4596
7686	1S2805	1S2799, 1000V	1N4594...4596
7687	1S2806	1S2799, 1200V	1N4595...4596
7688	1S2807	1S2799, 1400V	1N4596
7689	1S2808	1S2799, 1600V	-
7690	1S2809	100V, 250A(Tc74°)	1N3735...3744
7691	1S281	1S262, 27V	
7692	1S2810	1S2809, 200V	1N3736...3744
7693	1S2811	1S2809, 300V	1N3737...3744
7694	1S2812	1S2809, 400V	1N3738...3744

7695	1S2813	1S2809, 600V	1N3740...3744
7696	1S2814	1S2809, 800V	1N3741...3744
7697	1S2815	1S2809, 1000V	1N3742...3744
7698	1S2816	1S2809, 1200V	1N3743...3744
7699	1S2817	1S2809, 1400V	1N3744
7700	1S2818	1S2809, 1600V	-
7701	1S2819	600V, 500A(Tc100°)	-
7702	1S282	1S262, 30V	
7703	1S2820	1S2819, 800V	-
7704	1S2821	1S2819, 1000V	-
7705	1S2822	1S2819, 1200V	-
7706	1S2823	1S2819, 1400V	-
7707	1S2824	1S2819, 1600V	-
7708	1S2825	1S2819, 1800V	-
7709	1S2826(A)	100V, 1,5A	BY 226...227, BY 251...255, 1N5401...08
7710	1S2827(A)	1S2826, 200V	BY 226...227, BY 251...255, 1N5402...08
7711	1S2828(A)	1S2826, 400V	BY 226...227, BY 252...255, 1N5404...08
7712	1S2829(A)	1S2826, 600V	BY 226...227, BY 253...255, 1N5406...08
7713	1S283	1S262, 33V	
7714	1S2830(A)	1S2826, 800V	BY 227, BY 254...255, 1N5407...08
7715	1S2831(A)	1S2826, 1000V	BY 227, BY 228, BY 255, 1N5408
7716	1S2832	200V, 1A	BY 126...127, BY 226...227, 1N4003...07
7717	1S2833	1S2832, 800V	BY 127, BY 227, GP 10Q, 1N4006...07
7718	1S2834	1S2832, 1200V	BY 127, BY 227, EM 513, GP 10Q
7719	1S2835	35V, 0,15A, <4ns	MA 151WA, MA 152WA, 1SS181
7720	1S2836	1S2835, 75V	BAW 56, MA 152WA, 1SS181
7721	1S2837	1S2835	MA 151WK, MA 152WK, 1SS184
7722	1S2838	1S2835, 75V	BAV 70, MA 152WK, 1SS184
7723	1S2839	600V, 1A, 1,5µs	BY 201/6, BYX 55/600, RGP 10J
7724	1S284	1S262, 36V	
7725	1S285	1S262, 39V	
7726	1S286	1S262, 43V	
7727	1S287	1S262, 45V	
7728	1S288	1S262, 47V	
7729	1S289	1S262, 50V	
7730	1S29	1S28, 150V	-
7731	1S290	1S262, 52V	
7732	1S291	1S262, 56V	
7733	1S292	1S262, 62V	
7734	1S293	1S262, 68V	
7735	1S294	1S262, 75V	
7736	1S295	1S262, 82V	
7737	1S296	1S262, 91V	
7738	1S297	1S262, 100V	
7739	1S298	1S262, 105V	

7740	1S299	1S262, 110V	
7741	1S30	1S28, 250V	-
7742	1S300	1S262, 120V	
7743	1S3006(A)	6,8V, 1W, 10%, (A5%)	BZW22/..., BZX61/..., ZPY..., 1N5921...56
7744	1S3007(A)	1S3006(A), 7,5V	
7745	1S3008(A)	1S3006(A), 8,2V	
7746	1S3009(A)	1S3006(A), 9,1V	
7747	1S301	1S262, 130V	
7748	1S3010(A)	1S3006(A), 10V	
7749	1S3011(A)	1S3006(A), 11V	
7750	1S3012(A)	1S3006(A), 12V	
7751	1S3013(A)	1S3006(A), 13V	
7752	1S3015(A)	1S3006(A), 15V	
7753	1S3016(A)	1S3006(A), 16V	
7754	1S3018(A)	1S3006(A), 18V	
7755	1S302	1S262, 140V	
7756	1S3020(A)	1S3006(A), 20V	
7757	1S3022(A)	1S3006(A), 22V	
7758	1S3024(A)	1S3006(A), 24V	
7759	1S3027(A)	1S3006(A), 27V	
7760	1S303	1S262, 150V	
7761	1S3030(A)	1S3006(A), 30V	
7762	1S3033(A)	1S3006(A), 33V	
7763	1S3036(A)	1S3006(A), 36V	
7764	1S3039(A)	1S3006(A), 39V	
7765	1S3043(A)	1S3006(A), 43V	
7766	1S3047(A)	1S3006(A), 47V	
7767	1S3051(A)	1S3006(A), 51V	
7768	1S3056(A)	1S3006(A), 56V	
7769	1S306(-M)	35V, 0,06A, <3ns	BA 218, BAX 13, BAY 71, 1N4148...49
7770	1S3062(A)	1S3006(A), 62V	
7771	1S3068(A)	1S3006(A), 68V	
7772	1S307	20V, 0,085A, <100ns	AAY 27, AAZ 18
7773	1S3075(A)	1S3006(A), 75V	
7774	1S308	80V, 0,2A	-
7775	1S3082(A)	1S3006(A), 82V	
7776	1S309	120V, 0,25A	-
7777	1S3091(A)	1S3006(A), 91V	
7778	1S30N06L	RF1S30N06LE	RF 1S30N06LE
7779	1S31	1S28, 300V	-
7780	1S310(H)	50V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
7781	1S3100(A)	1S3006(A), 100V	
7782	1S311(H,N)	1S310, 100V	BY 126...127, BY 133...135, 1N4002...07
7783	1S3110(A)	1S3006(A), 110V	
7784	1S312(A,H)	1S310, 200V	BY 126...127, BY 133...134, 1N4003...07



7785	1S3120(A)	1S3006(A), 120V	
7786	1S313(H)	1S310, 300V	BY 126...127, BY 133...134, 1N4004...07
7787	1S3130(A)	1S3006(A), 130V	
7788	1S314(H,N)	1S310, 400V	BY 126...127, BY 133...134, 1N4004...07
7789	1S315(H)	1S310, 500V	BY 126...127, BY 133...134, 1N4005...07
7790	1S3150(A)	1S3006(A), 150V	
7791	1S316	1S310, 800V	BY 127, BY 133, BY 227, 1N4006...07
7792	1S3160(A)	1S3006(A), 160V	
7793	1S317	1S310, 1000V	BY 127, BY 133, BY 227, 1N4007
7794	1S318	75V, 0,05A	AA 117...118, AA 132...133, 1N634...635
7795	1S3180(A)	1S3006(A), 180V	
7796	1S319	60V, 0,04A	AA 117...118, AA 132...134, 1N34, 1N54
7797	1S32	75V, 30mA	AA 117...118, AA 132...133, 1N634
7798	1S320	40V, 0,05A	AA 113, AA 119, 1N34, 1N54, 1N60
7799	1S3200(A)	1S3006(A), 200V	
7800	1S321	120V, 0,05A	AA 133, 1N635
7801	1S322	75V, 0,04A	AA 117...118, AA 132...133, 1N634...635
7802	1S323	50V, 0,05A	AA 117...118, AA 132...134, 1N34, 1N54
7803	1S324	40V, 0,04A	BA 218, BAX 13, BAX 91, 1N4148...49
7804	1S325	40V, 0,04A	BA 218, BAX 13, BAX 91, 1N4148...49
7805	1S326	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
7806	1S327	1S326, 400V	BY 126...127, BY 133...134, 1N4004...07
7807	1S328	1S326, 600V, 0,4A	BY 126...127, BY 133...134, 1N4005...07
7808	1S329	1S326, 800V, 0,4A	BY 127, BY 133, BY 227, 1N4006...07
7809	1S33	120V, 30mA	AA 132...133, 1N634
7810	1S330	4,4..5,6V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5230...50
7811	1S331	1S330, 5,4..6,6V	
7812	1S332	1S330, 6,4..7,6V	
7813	1S333	1S330, 7,4..8,6V	
7814	1S334	1S330, 8,4..9,6V	
7815	1S335	1S330, 9,4..10,6V	
7816	1S336	1S330, 10,4..11,6V	
7817	1S337	1S330, 11,4..12,6V	
7818	1S338	1S330, 12,4..16,1V	
7819	1S339	1S330, 15,9..20V	
7820	1S34	75V, 30mA	AA 117...118, AA132...133, 1N634
7821	1S340	4,4..5,6V, 1,5W	BZV47/..., BZY97/..., ZY..., 1N5917...32
7822	1S341	1S340, 5,4..6,6V	
7823	1S342	1S340, 6,4..7,6V	
7824	1S343	1S340, 7,4..8,6V	
7825	1S344	1S340, 8,4..9,6V	
7826	1S345	1S340, 9,4..10,6V	
7827	1S346	1S340, 10,4..11,6V	
7828	1S347	1S340, 11,4..12,6V	
7829	1S348	1S340, 12,4..16,1V	

7830	1S349	1S340, 15,9..20V	
7831	1S350	30V, 15mA	AA 113, AA 119, 1N34, 1N54, 1N60
7832	1S351(M,S)		BA 124...125, BB 119, 1S2790, 1SV50
7833	1S352(M,N)		BA 124...125, BB 119, 1S2790, 1SV50
7834	1S353(M)		BA 124...125, BB 119, 1S2790, 1SV50
7835	1S354	75V, 0,04A	AA 117...118, AA 132...133, 1N634...635
7836	1S355	30V, 0,05A	AA 113, AA 119, 1N34, 1N54, 1N60
7837	1S356	50V, 0,06A	AA 113, AA 117...118, 1N34, 1N60
7838	1S357	45V	AA 113, AA 119, 1N34, 1N54, 1N60
7839	1S358	150V, 0,1A	BA 147/150, BA 189...190, 1N5606...07
7840	1S358-S	1S358, 50V	BA 147/50, BA 187...190, 1N5606...09
7841	1S359	400V, 0,5A	BY 126...127, BY 133...134, 1N4004...07
7842	1S36	200V, 0,5A	BY 126...127, BY 133...134, 1N4003...07
7843	1S367	100V, 0,4A	BY 126...127, BY 133...135, 1N4002...07
7844	1S368	1S367, 200V	BY 126...127, BY 133...134, 1N4003...07
7845	1S369	1S367, 300V	BY 126...127, BY 133...134, 1N4004...07
7846	1S37	1S36, 400V	BY 126...127, BY 133...134, 1N4004...07
7847	1S370	1S367, 400V	BY 126...127, BY 133...134, 1N4004...07
7848	1S371	1S367, 500V	BY 126...127, BY 133...134, 1N4005...07
7849	1S372	1S367, 600V	BY 126...127, BY 133...134, 1N4005...07
7850	1S373	100V, 0,3A	BY 126...127, BY 133...135, 1N4002...07
7851	1S374	1S373, 200V	BY 126...127, BY 133...134, 1N4003...07
7852	1S375	1S373, 400V	BY 126...127, BY 133...134, 1N4004...07
7853	1S376	1S373, 500V	BY 126...127, BY 133...134, 1N4005...07
7854	1S377	1S373, 600V	BY 126...127, BY 133...134, 1N4005...07
7855	1S378	100V, 0,3A	BY 126...127, BY 133...135, 1N4002...07
7856	1S379	1S378, 200V	BY 126...127, BY 133...134, 1N4003...07
7857	1S38	1S36, 700V	BY 127, BY 133, BY 227, 1N4006...07
7858	1S380	1S378, 400V	BY 126...127, BY 133...134, 1N4004...07
7859	1S381	1S378, 500V	BY 126...127, BY 133...134, 1N4005...07
7860	1S382	1S378, 600V	BY 126...127, BY 133...134, 1N4005...07
7861	1S383	100V, 0,8A	BY 126...127, BY 133...135, 1N4002...07
7862	1S384	1S383, 200V	BY 126...127, BY 133...134, 1N4003...07
7863	1S385	1S383, 400V	BY 126...127, BY 133...134, 1N4004...07
7864	1S386	1S383, 500V	BY 126...127, BY 133...134, 1N4005...07
7865	1S387	1S383, 600V	BY 126...127, BY 133...134, 1N4005...07
7866	1S388	100V, 0,8A	BY 126...127, BY 133...135, 1N4002...07
7867	1S389	1S388, 200V	BY 126...127, BY 133...134, 1N4003...07
7868	1S39	1S36, 800V, 0,4A	BY 127, BY 133, BY 227, 1N4006...07
7869	1S390	1S388, 400V	BY 126...127, BY 133...134, 1N4004...07
7870	1S391	1S388, 500V	BY 126...127, BY 133...134, 1N4005...07
7871	1S392	1S388, 600V	BY 126...127, BY 133...134, 1N4005...07
7872	1S393	400V, 0,3A	BA 157...159, BY 204/4, BY 206...207
7873	1S394	1S393, 0,4A	BA 157...159, BY 204/4, BY 206...207
7874	1S395	400V, 0,5A	BY 126...127, BY 133...134, 1N4004...07

7875	1S396	1S395, 600V	BY 126...127, BY 133...134, 1N4005...07
7876	1S397	1S395, 800V	BY 127, BY 133, BY 227, 1N4006...07
7877	1S398	1S395, 1000V	BY 127, BY 133, BY 227, 1N4007
7878	1S399[IR]	400V, 0,8A	BY 126...127, BY 133...134, 1N4004...07
7879	1S40	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
7880	1S400[IR]	1S399[IR], 600V	BY 126...127, BY 133...134, 1N4005...07
7881	1S4006..4200(A)	1S3006..3200(A), 1,5W	BZV47/..., BZY97/..., ZY..., 1N5921...56
7882	1S401[IR]	1S399[IR], 800V	BY 127, BY 133, BY 227, 1N4006...07
7883	1S402[IR]	1S399[IR], 1000V	BY 127, BY 133, BY 227, 1N4007
7884	1S403[IR]	1S399[IR], 1200V	BY 127, BY 133, BY 227, GP 10Q
7885	1S404[IR]	600V, 0,1A	BA 157...159, BAY 89...91, BY 203/12
7886	1S405[IR]	1S404[IR], 800V	BA 159, BAY 90...91, BY 203/12
7887	1S406[IR]	1S404[IR], 1000V	BA 159, BAY 90...91, BY 203/12
7888	1S407[IR]	1S404[IR], 1200V	BAY 91, BY 203/12, BY 584, SHG 1,5
7889	1S408[IR]	1,5kV, 0,38A	1N1732A
7890	1S409[IR]	1S408[IR], 1,8kV	1N1732A
7891	1S41	1S40, 200V	BY 126...127, BY 133...134, 1N4003...07
7892	1S410[IR]	1S408[IR], 2,4kV	1N1733A
7893	1S410[Texas]	100V, 3A(Tc125°)	BYX 38/300, BYX 39/600
7894	s]	1S410..419[Texas]	BYX 38/...R, BYX 39/...R
7895	1S411[IR]	1S408[IR], 3,6kV, 0,36A	1N1734A
7896	1S411[Texas]	1S410[Texas], 200V	BYX 38/300, BYX 39/600
7897	1S412[IR]	1S408[IR], 4,8kV, 0,36A	1N1734A
7898	1S413[IR]	1S408[IR], 6kV, 0,36A	-
7899	1S413[Texas]	1S410[Texas], 400V	BYX 38/600, BYX 39/600
7900	1S414[IR]	1S408[IR], 7,2kV, 0,33A	-
7901	1S415[IR]	1S408[IR], 12kV, 0,25A	-
7902	1S415[Texas]	1S410[Texas], 600V	BYX 38/600, BYX 39/600
7903	1S416[IR]	1S408[IR], 16kV, 0,25A	-
7904	1S417[IR]	50V, 3A(Tc70°)	BYX 38/300, BYX 39/600
7905	1S417[Texas]	1S410[Texas], 800V	BYX 38/900, BYX 39/800
7906	1S418[IR]	1S417[IR], 100V	BYX 38/300, BYX 39/600
7907	1S419[IR]	1S417[IR], 150V	BYX 38/300, BYX 39/600
7908	1S419[Texas]	1S410[Texas], 1000V	BYX 38/1200, BYX 39/1000
7909	1S42	1S40, 300V	BY 126...127, BY 133...134, 1N4004...07
7910	1S420[IR]	1S417[IR], 200V	BYX 38/300, BYX 39/600
7911	1S420[Texas]	100V, 10A(Tc100°)	BYW 88/100, BYX 76...81, 1N4506...11
7912	s]	1S420[Texas], 800V	BYW 88/...R, BYX 86R...81R
7913	1S421[IR]	1S417[IR], 250V	BYX 38/300, BYX 39/600
7914	1S421[Texas]	1S420[Texas], 200V	BYW 88/200, BYX 77...81, 1N4506...11
7915	1S422[IR]	1S417[IR], 300V	BYX 38/300, BYX 39/600
7916	1S423[IR]	1S417[IR], 400V	BYX 38/600, BYX 39/600
7917	1S423[Texas]	1S420[Texas], 400V	BYW 88/400, BYX 78...81, 1N4507...11
7918	1S424[IR]	1S417[IR], 500V	BYX 38/600, BYX 39/600
7919	1S425[IR]	1S417[IR], 600V	BYX 38/600, BYX 39/600

7920	1S425[Texas]	1S420[Texas], 600V	BYW 88/600, BYX 79...81, 1N4508...11
7921	1S426(G)[Japan]	15..25V, 20..50mA	AA 112...114, 1N34, 1N54, 1N60
7922	1S427[Japan]	13,5..15V, 0,3W	BZX55/C15, BZX79/C15, ZPD15, 1N5244
7923	1S427[Texas]	1S420[Texas], 800V	BYW 88/800, BYX 80...81, 1N4509...11
7924	1S43	1S40, 400V	BY 126...127, BY 133...134, 1N4004...07
7925	1S431	100V, 100A(Tc105°)	1N3288...97
7926	1S432	1S431, 200V	1N3289...97
7927	1S433	1S431, 300V	1N3290...97
7928	1S434	1S431, 400V	1N3291...97
7929	1S435	1S431, 500V	1N3292...97
7930	1S436	1S431, 600V	1N3293...97
7931	1S437	1S431, 700V	1N3294...97
7932	1S438	1S431, 800V	1N3294...97
7933	1S439	1S431, 900V	1N3295...97
7934	1S44	1S40, 500V	BY 126...127, BY 133...134, 1N4005...07
7935	1S44[Texas]	40V, 0,1A, <8ns	BA 318, BAY 38, 1N4148...49, 1N4151
7936	1S440	1S431, 1000V	1N3295...97
7937	1S441	45V, 30mA	AA 113, AA 119, 1N34, 1N54, 1N60
7938	1S442	43V, 0,1A	AA 113, AA 119, 1N34, 1N54, 1N60
7939	1S443	43V, 0,12A, <2μs	AA 136, AAY 49, AAZ 15, AAZ 17
7940	1S444	30V, 0,09A, <200ns	AAY 49, AAZ 15, AAZ 17
7941	1S445	65V, 0,1A, <450ns	AAZ 15, AAZ 17
7942	1S446	60V, 30mA	AA 113, 1N34, 1N54, 1N60
7943	1S447	75V, 40mA	AA 117...118, AA 132...133
7944	1S448	110V, 40mA	AA 117...118, AA 132...133
7945	1S449	110V, 40mA	AA 117...118, AA 132...133
7946	1S45	1S40, 600V	BY 126...127, BY 133...134, 1N4005...07
7947	1S450	140V, 30mA	AA 133
7948	1S451	60V, 40mA	AA 113, 1N43, 1N54, 1N60
7949	1S452	75V, 40mA	AA 117...118, AA 132...133
7950	1S453	75V, 40mA	AA 117...118, AA 132...133
7951	1S454	45V, 40mA	AA 113, AA 119, 1N34, 1N54, 1N60
7952	1S455	35V, 40mA	AA 113, AA 119, 1N34, 1N54, 1N60
7953	1S456	40V, 0,1A	BA 147/50, BA 187...190, 1N5606...09
7954	1S457	1S456, 80V	BA 147/100, BA 188...190, 1N5606...09
7955	1S458	1S456, 150V	BA 147/150, BA 189...190, 1N5606...07
7956	1S459	1S456, 200V	BA 147/230, BA 190, 1N5606...07
7957	1S46	1S40, 700V	BY 127, BY 133, BY 227, 1N4006...07
7958	1S460	22V, 0,045A, <3ns	BA 317, BAY 71, BAY 94, 1N4148...49
7959	1S461	90V, 0,15A, <3ns	BA 219, 1N4148...49, 1N4446...49
7960	1S462	90V, 0,22A, <3ns	1N4148...49, 1N4151, 1N4446...49
7961	1S463	125V, 0,9A, <30ns	EGP 10C, FE 1C
7962	1S464	0,76..0,84V(10mA)	BA 220, BZ 102/0V7, BZX55/C0V8, ZPD1
7963	1S465	43V, 0,045A, <10ns	BA 218, BAX 13, BAX 91, 1N4148...49
7964	1S466	43V, 0,045A, <1ns	-

7965	1S467	0,64..0,7V(3mA), <6ns	BA 220, BA 315
7966	1S468	40V, 0,115A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4151
7967	1S47	1S40, 800V	BY 127, BY 133, BY 227, 1N4006...07
7968	1S470(H,L,M)	5,5..6,5V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5233...62
7969	1S471(H,L,M)	1S470, 6,5..8V	
7970	1S472(H,L,M)	1S470, 8..10V	
7971	1S473(H,L,M)	1S470, 10..12,5V	
7972	1S474(H,L,M)	1S470, 12,5..16V	
7973	1S475(H,L,M)	1S470, 16..20V	
7974	1S476(H,L,M)	1S470, 20..25V	
7975	1S477(H,L,M)	1S470, 25..31V	
7976	1S478(H,L,M)	1S470, 31..41V	
7977	1S479(H,L,M)	1S470, 41..51V	
7978	1S48		BA 111, BA 124, 1S2790, 1SV50
7979	1S480(H,L,M)	5,5..6,5V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5919...41
7980	1S481(H,L,M)	1S480, 6,5..8V	
7981	1S482(H,L,M)	1S480, 8..10V	
7982	1S483(H,L,M)	1S480, 10..12,5V	
7983	1S484(H,L,M)	1S480, 12,5..16V	
7984	1S485(H,L,M)	1S480, 16..20V	
7985	1S486(H,L,M)	1S480, 20..25V	
7986	1S487(H,L,M)	1S480, 25..31V	
7987	1S488(H,L,M)	1S480, 31..41V	
7988	1S489(H,L,M)	1S480, 41..51V	
7989	1S49		BA 111, BA 124, 1S2790, 1SV50
7990	1S490(H,L,M)	5,5..6,5V, 3W	BZX98/..., BZY93/..., ZX..., 1N2970...97
7991	1S491(H,L,M)	1S490, 6,5..8V	
7992	1S492(H,L,M)	1S490, 8..10V	
7993	1S493(H,L,M)	1S490, 10..12,5V	
7994	1S494(H,L,M)	1S490, 12,5..16V	
7995	1S495(H,L,M)	1S490, 16..20V	
7996	1S496(H,L,M)	1S490, 20..25V	
7997	1S497(H,L,M)	1S490, 25..31V	
7998	1S498(H,L,M)	1S490, 31..41V	
7999	1S499(H,L,M)	1S490, 41..51V	
8000	1S50	40V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
8001	1S500	43V, 0,045A, <3ns	BA 218, BAX 13, BAX 91, 1N4148...49
8002	1S501	43V, 0,075A, <3ns	BA 218, BAX 13, BAX 91, 1N4148...49
8003	1S5015(A)	15V, 10W(Tc100°), 10%, (A5%)	BZX98/..., BZY93/..., ZX..., 1N2979...3011
8004	1S5015C...5150C	1S5015..5150(A), bidirecional	
8005	1S5015R...5150R	1S5015..5150(A)	
8006	1S5016(A)	1S5015(A), 16V	
8007	1S5018(A)	1S5015(A), 18V	
8008	1S501M	1S501, 22V, 0,045A, <1ns	-
8009	1S5020(A)	1S5015(A), 20V	

8010	1S5022(A)	1S5015(A), 22V	
8011	1S5024(A)	1S5015(A), 24V	
8012	1S5027(A)	1S5015(A), 27V	
8013	1S5030(A)	1S5015(A), 30V	
8014	1S5033(A)	1S5015(A), 33V	
8015	1S5036(A)	1S5015(A), 36V	
8016	1S5039(A)	1S5015(A), 39V	
8017	1S5043(A)	1S5015(A), 43V	
8018	1S5047(A)	1S5015(A), 47V	
8019	1S5051(A)	1S5015(A), 51V	
8020	1S5056(A)	1S5015(A), 56V	
8021	1S5062(A)	1S5015(A), 62V	
8022	1S5068(A)	1S5015(A), 68V	
8023	1S5075(A)	1S5015(A), 75V	
8024	1S5082(A)	1S5015(A), 82V	
8025	1S5091(A)	1S5015(A), 91V	
8026	1S51	3,8..4,5V	BZW22/..., BZX61/..., ZPY..., 1N5915...25
8027	1S5100(A)	1S5015(A), 100V	
8028	1S5110(A)	1S5015(A), 110V	
8029	1S5120(A)	1S5015(A), 120V	
8030	1S5130(A)	1S5015(A), 130V	
8031	1S5150(A)	1S5015(A), 150V	
8032	1S52	5,2..6,2V	
8033	1S53	6,0..7,1V	
8034	1S54	6,9..8,1V	
8035	1S542	500V, 0,5A	BY 126...127, BY 133...134, 1N4005...07
8036	1S544	800V, 10A(Tc120°)	BYX 42/900, BYX 98/900
8037	1S545	1S544, 1000V	BYX 42/1200, BYX 98/1200
8038	1S546	800V, 20A(Tc120°)	1N4528...30
8039	1S547	1S546, 1000V	1N4528...30
8040	1S55	7,9..9,1V	
8041	1S550	8..9V	BZX 51, 1N4780
8042	1S551	8..9V	BZX 52, 1N4781
8043	1S552	8..9V	BZX 53, 1N4782
8044	1S553(T)		BA 111, BA 124, 1S2790, 1SV50
8045	1S554(T)		BA 111, BA 124, 1S2790, 1SV50
8046	1S555		BA 111, BA 124, 1S2790, 1SV50
8047	1S556		BA 111, BA 124, 1S2790, 1SV50
8048	1S56	8,9..10,1V	
8049	1S560(H)	15V, 0,04A, <200ns	AAY 27, 1N631, 1N633, 1N3592
8050	1S561..569(A)		-
8051	1S57		
8052	1S60	50V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
8053	1S6006(A)	(A5%)	BZX98/..., BZY93/..., ZX..., 1N5921...56
8054	1S6006R...6200R	1S6006..6200(A)	

8055	1S6007(A)	1S6006(A), 7,5V	
8056	1S6008(A)	1S6006(A), 8,2V	
8057	1S6009(A)	1S6006(A), 9,1V	
8058	1S6010(A)	1S6006(A), 10V	
8059	1S6011(A)	1S6006(A), 11V	
8060	1S6012(A)	1S6006(A), 12V	
8061	1S6013(A)	1S6006(A), 13V	
8062	1S6015(A)	1S6006(A), 15V	
8063	1S6016(A)	1S6006(A), 16V	
8064	1S6018(A)	1S6006(A), 18V	
8065	1S6020(A)	1S6006(A), 20V	
8066	1S6022(A)	1S6006(A), 22V	
8067	1S6024(A)	1S6006(A), 24V	
8068	1S6027(A)	1S6006(A), 27V	
8069	1S6030(A)	1S6006(A), 30V	
8070	1S6033(A)	1S6006(A), 33V	
8071	1S6036(A)	1S6006(A), 36V	
8072	1S6039(A)	1S6006(A), 39V	
8073	1S6043(A)	1S6006(A), 43V	
8074	1S6047(A)	1S6006(A), 47V	
8075	1S6051(A)	1S6006(A), 51V	
8076	1S6056(A)	1S6006(A), 56V	
8077	1S6062(A)	1S6006(A), 62V	
8078	1S6068(A)	1S6006(A), 68V	
8079	1S6075(A)	1S6006(A), 75V	
8080	1S6082(A)	1S6006(A), 82V	
8081	1S6091(A)	1S6006(A), 91V	
8082	1S61	1S60, 100V	BY 126...127, BY 133...135, 1N4001...07
8083	1S6100(A)	1S6006(A), 100V	
8084	1S611	2..3,2V, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5221...37
8085	1S6110(A)	1S6006(A), 110V	
8086	1S612	1S611, 3..3,9V	
8087	1S6120(A)	1S6006(A), 120V	
8088	1S613	1S611, 3,7..4,5V	
8089	1S6130(A)	1S6006(A), 130V	
8090	1S614	1S611, 4,3..5,4V	
8091	1S615	1S611, 5,2..6,4V	
8092	1S6150(A)	1S6006(A), 150V	
8093	1S616	1S611, 6,2..8V	
8094	1S6160(A)	1S6006(A), 160V	
8095	1S617	7,5..10V, 0,15W	BZX55/..., BZX79/..., ZPD..., 1N5236...59
8096	1S618	1S617, 9..12V	
8097	1S6180(A)	1S6006(A), 180V	
8098	1S619	1S617, 11..14,5V	
8099	1S62	1S60, 200V	BY 126...127, BY 133...134, 1N4002...07



8100	1S620	1S617, 13,5..18V	
8101	1S6200(A)	1S6006(A), 200V	
8102	1S621	1S617, 17..21V	
8103	1S622	1S617, 20..27V	
8104	1S623	1S617, 25..32V	
8105	1S624	1S617, 30..39V	
8106	1S63	1S60, 300V	BY 126...127, BY 133...134, 1N4003...07
8107	1S632	3..3,9V, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5225...37
8108	1S633	1S632, 3,7..4,5V	
8109	1S634	1S632, 4,3..5,4V	
8110	1S635	1S632, 5,2..6,4V	
8111	1S636	1S632, 6,2..8V	
8112	1S64	1S60, 400V	BY 126...127, BY 133...134, 1N4004...07
8113	1S65	1S60, 500V	BY 126...127, BY 133...134, 1N4005...07
8114	1S66	1S60, 600V	BY 126...127, BY 133...134, 1N4005...07
8115	1S661	400V, 1A(Tc120°)	BY 252...255, BYW 17/400, 1N5404...08
8116	1S662	1S661, 800V	BY 254...255, BYW 17/800, 1N5407...08
8117	1S663	1S661, 1000V	BY 255, BY 228, BYW 17/1000, 1N5408
8118	1S664	1S661, 1200V	BY 255, BY 228, BYW 17/1200
8119	1S665	400V, 2,5A(Tc120°)	BYX 38/600R, BYX 39/600R
8120	1S666	1S665, 800V	BYX 38/900R, BYX 39/800R
8121	1S667	1S665, 1000V	BYX 38/1200R, BYX 39/1000R
8122	1S668	1S665, 1200V	BYX 38/1200R, BYX 39/1200R
8123	1S669	400V, 10A(Tc120°)	BYX 42/600R, BYX 98/600R
8124	1S670	1S669, 800V	BYX 42/900R, BYX 98/900R
8125	1S671	1S669, 1000V	BYX 42/1200R, BYX 98/1200R
8126	1S672	1S669, 1200V	BYX 42/1200R, BYX 98/1200R
8127	1S673	400V, 20A(Tc120°)	BYX 56/600R, BYX 97/600R
8128	1S674	1S673, 800V	BYX 56/800R, BYX 97/900R
8129	1S675	1S673, 1000V	BYX 56/1000R, BYX 97/1200R
8130	1S676	1S673, 1200V	BYX 56/1200R, BYX 97/1200R
8131	1S677	400V, 82,5A(Tc105°)	1N3291R...97R
8132	1S678	1S677, 800V	1N3294R...97R
8133	1S679	1S677, 1000V	1N3295R...97R
8134	1S680	1S677, 1200V	1N3296R...97R
8135	1S681	400V, 200A(Tc105°)	1N3738R...44R
8136	1S682	1S681, 800V	1N3741R...44R
8137	1S683	1S681, 1000V	1N3742R...44R
8138	1S684	1S681, 1200V	1N3743R...44R
8139	1S685	300V, 0,35A	BA 157...159, BY 204/4, BY 206...207
8140	1S686	1S685, 450V	BA 158...159, BY 204/8, BY 207
8141	1S687	1S685, 750V	BA 158...159, BY 204/8, BY 268...269
8142	1S688	1S685, 1200V	BY 127, BY 133, BY 227, BY 268...269
8143	1S690	3,6..4,3, 1W	BZW22/..., BZX61/..., ZPY..., 1N5914...36
8144	1S691	1S690, 4,3..5,1V	

8145	1S692	1S690, 5,1..6,2V	
8146	1S693	1S690, 6,2..7,5V	
8147	1S694	1S690, 7,5..9,1V	
8148	1S695	1S690, 9,1..11V	
8149	1S696	1S690, 11..13V	
8150	1S697	1S690, 13..16V	
8151	1S698	1S690, 16..20V	
8152	1S699	1S690, 20..24V	
8153	1S700	1S690, 24..30V	
8154	1S701	3,6..4,3V, 3,5W	BZX98/..., BZY93/..., ZX..., 1N2970...89
8155	1S702	1S701, 4,3..5,1V	
8156	1S703	1S701, 5,1..6,2V	
8157	1S7030(A,B)	3V, 0,4W, 10%, (A5%, B15%)	BZX55/..., BZX83/..., ZPD..., 1N5225...46
8158	1S7033(A,B)	1S7030(A,B), 3,3V	
8159	1S7036(A,B)	1S7030(A,B), 3,6V	
8160	1S7039(A,B)	1S7030(A,B), 3,9V	
8161	1S704	1S701, 6,2..7,5V	
8162	1S7043(A,B)	1S7030(A,B), 4,3V	
8163	1S7047(A,B)	1S7030(A,B), 4,7V	
8164	1S705	1S701, 7,5..9,1V	
8165	1S7051(A,B)	1S7030(A,B), 5,1V	
8166	1S7056(A,B)	1S7030(A,B), 5,6V	
8167	1S706	1S701, 9,1..11V	
8168	1S7062(A,B)	1S7030(A,B), 6,2V	
8169	1S7068(A,B)	1S7030(A,B), 6,8V	
8170	1S707	1S701, 11..13V	
8171	1S7075(A,B)	1S7030(A,B), 7,5V	
8172	1S708	1S701, 13..16V	
8173	1S7082(A,B)	1S7030(A,B), 8,2V	
8174	1S709	1S701, 16..20V	
8175	1S7091(A,B)	1S7030(A,B), 9,1V	
8176	1S71	175V, 0,06A	BA 147/230, BA 190, 1N5195...96
8177	1S710	1S701, 20..24V	
8178	1S7100(A,B)	1S7030(A,B), 10V	
8179	1S711	1S701, 24..30V	
8180	1S7110(A,B)	1S7030(A,B), 11V	
8181	1S712	3,6..4,3V, 10W	BZX98/..., BZY93/..., ZX..., 1N2970...89
8182	1S7120(A,B)	1S7030(A,B), 12V	
8183	1S713	1S712, 4,3..5,1V	
8184	1S7130(A,B)	1S7030(A,B), 13V	
8185	1S714	1S712, 5,1..6,2V	
8186	1S715	1S712, 6,2..7,5V	
8187	1S7150(A,B)	1S7030(A,B), 15V	
8188	1S716	1S712, 7,5..9,1V	
8189	1S7160(A,B)	1S7030(A,B), 16V	

8190	1S717	1S712, 9,1..11V	
8191	1S718	1S712, 11..13V	
8192	1S719	1S712, 13..16V	
8193	1S72	1S71, 130V	BA 147/150, BA 189...190, 1N5195...96
8194	1S720	1S712, 16..20V	
8195	1S721	1S712, 20..24V	
8196	1S722	1S712, 24..30V	
8197	1S723	400V, 6A(Tc105°)	BYX 38/600, BYX 39/600
8198	1S724	1S723, 600V	BYX 38/600, BYX 39/600
8199	1S725	1S723, 800V	BYX 38/900, BYX 39/800
8200	1S726	1S723, 1000V	BYX 38/1200, BYX 39/1000
8201	1S73(A)	20..30V, 0,12A, <900ns	AAZ 49, AAZ 15, AAZ 17
8202	1S731	50V, 0,1A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4151
8203	1S732	200V, 250A(Tc105°)	1N3736...44
8204	1S733	1S732, 300V	1N3737...44
8205	1S734	1S732, 400V	1N3738...44
8206	1S735	1S732, 500V	1N3739...44
8207	1S736	1S732, 600V	1N3740...44
8208	1S737	1S732, 700V	1N3741...44
8209	1S738	1S732, 800V	1N3741...44
8210	1S739	1S732, 900V	1N3742...44
8211	1S74	75V, 50mA	AA 117...118, AA 132...133
8212	1S740	1S732, 1000V	1N3742...44
8213	1S741	1S732, 100V	1N3735...44
8214	1S742	1S732, 1200V	1N3743...44
8215	1S743	1S732, 1500V	-
8216	1S744	40V, 40mA	AA 113, AA 119, 1N34, 1N54, 1N60
8217	1S745	50V, 65mA	AA 113, 1N34, 1N54, 1N60
8218	1S746	75V, 45mA	AA 113, 1N34, 1N54, 1N60
8219	1S747	75V, 45mA	AA 113, 1N34, 1N54, 1N60
8220	1S748	20V, 40mA	AA 112...114, 1N34, 1N54, 1N60
8221	1S75	30V, 25mA	AA 117...118, AA 132...134, 1N34, 1N54
8222	1S750(S)	887MHz	-
8223	1S76	45V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
8224	1S77(H)	60V, 60mA	AA 117...118, AA 132...133, AAY 28
8225	1S770	100V, 15A(Tc50°)	1N3492...95
8226	1S770R	1S770	1N3492R...95R
8227	1S773(A)	35V, 0,1A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4151
8228	1S774(A)	35V, 0,12A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4151
8229	1S775(A)	80V, 0,08A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4151
8230	1S776(A)	130V, 0,1A, <3ns	-
8231	1S778	100V, 12A(Tc40°)	BYW 88/100, BYX 76...81
8232	1S779	150V, 40A(Tc104°)	BYX 56/600R, BYX 97/300R
8233	1S78(H)	40V, 80mA	AA 117...118, AA 132...133, AAY 49
8234	1S780	1S779, 200V	BYX 56/600R, BYX 97/300R

8235	1S781	1S778, 250V	BYW 88/300, BYX 78...81
8236	1S782	1S779, 300V	BYX 56/600R, BYX 97/300R
8237	1S783	1S779, 400V	BYX 56/600R, BYX 97/600R
8238	1S784	1S779, 500V	BYX 56/600R, BYX 97/600R
8239	1S785	1S779, 600V	BYX 56/600R, BYX 97/600R
8240	1S786	1S779, 800V	BYX 56/800R, BYX 97/900R
8241	1S787	100V, 60A(Tc126°)	-
8242	1S788	1S787, 150V	-
8243	1S789	1S787, 200V	-
8244	1S79(H)	20V, 0,1A	AA 117...118, AA 132...133, AAY 49
8245	1S790	250V, 18A(Tc40°)	-
8246	1S791	1S787, 300V	-
8247	1S792	1S787, 400V	-
8248	1S793	1S787, 500V	-
8249	1S794	1S787, 600V	-
8250	1S795	1S787, 800V	-
8251	1S796(N)	75V, 5%, 50W(Tc55°)	-
8252	1S797(N)	1S796, 95V	
8253	1S798(N)	1S796, 105V	
8254	1S799(N)	1S796, 150V	
8255	1S80	30V, 40mA	AA 113, AA 119, 1N34, 1N54, 1N60
8256	1S800(N)	1S796, 180V	
8257	1S801	22V, 0,055A, <4ns	BA 217, BA 317, BAY 71, 1N4148...49
8258	1S802	30V, 0,06A, <4ns	BA 217, BA 317, BAY 71, 1N4148...49
8259	1S803	30V, 0,065A, <4ns	BA 217, BA 317, BAY 71, 1N4148...49
8260	1S804	50V, 0,06A, <4ns	BA 218, BA 318, BAY 38, 1N4148...49
8261	1S805	50V, 0,065A, <2ns	BA 218, BA 318, BAY 38, 1N4148...49
8262	1S806	50V, 0,065A, <2ns	BA 218, BA 318, BAY 38, 1N4148...49
8263	1S807	75V, 0,065A, <2ns	BAW 62, BAX 95, BAW 76, 1N4148...49
8264	1S808	100V, 0,065A, <2ns	BA 219, BAX 96, 1N4148...49, 1N4151
8265	1S81	230V, 0,06A	BA 147/230, BA 157...159, BAY 21
8266	1S810	100V, 0,1A	AA 117...118, AA 132...133, 1N634...35
8267	1S811	250V, 0,5A(Tc100°)	BY 126...127, BY 133...134, 1N4004...07
8268	1S812	1S811, 400V	BY 126...127, BY 133...134, 1N4004...07
8269	1S813	1S811, 800V	BY 127, BY 133, BY 227, 1N4006...07
8270	1S814	1S811, 1000V	BY 127, BY 133, BY 227, 1N4007
8271	1S815	1S811, 1200V	BY 127, BY 133, BY 227, GP 10Q
8272	1S816	250V, 1A(Tc120°)	BY 252...255, BYW 17/400, 1N5404...08
8273	1S817	1S816, 400V	BY 252...255, BYW 17/400, 1N5404...08
8274	1S818	1S816, 800V	BY 254...255, BYW 17/800, 1N5407...08
8275	1S819	1S816, 1000V	BY 228, BY 255, BYW 17/1000, 1N5408
8276	1S82	50V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
8277	1S820	1S816, 1200V	BY 228, BY 255, BYW 17/1200
8278	1S821	250V, 2,5A(Tc120°)	BYX 38/300R, BYX 39/600R
8279	1S822	1S821, 400V	BYX 38/600R, BYX 39/600R

8280	1S823	1S821, 800V	BYX 38/900R, BYX 39/800R
8281	1S824	1S821, 1000V	BYX 38/1200R, BYX 39/1000R
8282	1S825	1S821, 1200V	BYX 38/1200R, BYX 39/1200R
8283	1S826	250V, 6A(Tc120°)	BYX 38/300R, BYX 39/600R
8284	1S827	1S826, 400V	BYX 38/600R, BYX 39/600R
8285	1S828	1S826, 800V	BYX 38/900R, BYX 39/800R
8286	1S829	1S826, 1000V	BYX 38/1200R, BYX 39/1000R
8287	1S830	1S826, 1200V	BYX 38/1200R, BYX 39/1200R
8288	1S831	250V, 10A	BYX 42/300R, BYX 98/300R
8289	1S832	1S831, 400V	BYX 42/600R, BYX 98/600R
8290	1S833	1S831, 800V	BYX 42/900R, BYX 98/900R
8291	1S834	1S831, 1000V	BYX 42/1200R, BYX 98/1200R
8292	1S835	1S831, 1200V	BYX 42/1200R, BYX 98/1200R
8293	1S836	250V, 20A(Tc120°)	D 24/400B
8294	1S837	1S836, 400V	D 24/400B
8295	1S838	1S836, 800V	D 24/800B
8296	1S839	1S836, 1000V	D 24/1000B
8297	1S840	1S836, 1200V	D 24/1200B
8298	1S841	100V, 1A	BY 126...127, BY 133...134, 1N4002...07
8299	1S842	1S841, 200V	BY 126...127, BY 133...134, 1N4003...07
8300	1S843	1S841, 300V	BY 126...127, BY 133...134, 1N4004...07
8301	1S844(N)	1S841, 400V	BY 126...127, BY 133...134, 1N4004...07
8302	1S845	1S841, 500V	BY 126...127, BY 133...134, 1N4005...07
8303	1S846(N)	1S841, 600V	BY 126...127, BY 133...134, 1N4005...07
8304	1S847	1S841, 700V	BY 127, BY 133, BY 227, 1N4006...07
8305	1S848(N)	1S841, 800V	BY 127, BY 133, BY 227, 1N4006...07
8306	1S849	1S841, 900V	BY 127, BY 133, BY 227, 1N4007
8307	1S85(H)		BA 124...125, BB 119, 1S2790, 1SV50
8308	1S850(N)	1S841, 1000V	BY 127, BY 133, BY 227, 1N4007
8309	1S851	1S841, 1200V	BY 127, BY 133, BY 227, GP 10Q
8310	1S852	1S841, 1500V	BY 350/1500, BY 400, BY 448, GP 10W
8311	1S86		BA 124...125, BB 119, 1S2790, 1SV50
8312	1S861	100V, 10A(Tc40°)	1N3492...95
8313	1S861R	1S861	1N3492R...95R
8314	1S863	300V, 8A	BYX 42/300, BYX 98/300
8315	1S864	1S863, 400V	BYX 42/600, BYX 98/600
8316	1S865	1S863, 500V	BYX 42/600, BYX 98/600
8317	1S866	1S863, 600V	BYX 42/600, BYX 98/600
8318	1S867	1S863, 700V	BYX 42/900, BYX 98/900
8319	1S868	1S863, 800V	BYX 42/900, BYX 98/900
8320	1S869	1S863, 900V	BYX 42/900, BYX 98/900
8321	1S87	20V, 0,1A, <120ns	AAZ 49, AAZ 15, AAZ 17
8322	1S870	1S863, 1000V	BYX 42/1200, BYX 98/1200
8323	1S871	400V, 0,15A	BA 157...159, BY 203/12, BY 204/4
8324	1S871A	1S871, 600V	BA 158...159, BY 203/12, BY 204/8

8325	1S871B	1S871, 800V	BA 158...159, BY 203/12, BY 204/8
8326	1S871C	1S871, 1000V	BA 159, BAY 90, BY 203/12, BY 204/10
8327	1S871D	1S871, 1200V	BAY 91, BY 203/12, SHG 1,5
8328	1S871E	1S871, 1400V	BAY 91, BY 203/16, SHG 1,5
8329	1S871F	1S871, 1600V	BAY 91, BY 203/16, SHG 2
8330	1S871G	1S871, 1800V	BAY 91, BY 203/20, SHG 2
8331	1S871H	1S871, 2000V	BAY 91, BY 203/20, SHG 2
8332	1S872	400V, 0,25A	BA 157...159, BY 204/4, BY 203/12
8333	1S872A	1S872, 600V	BA 158...159, BY 204/8, BY 203/12
8334	1S872B	1S872, 800V	BA 158...159, BY 204/8, BY 203/12
8335	1S872C	1S872, 1000V	BA 159, BAY 90, BY 204/10, BY 203/12
8336	1S872D	1S872, 1200V	BAY 91, BY 203/12, BY 268...269
8337	1S873	300V, 17A	BYX 96/300
8338	1S874	1S873, 400V	BYX 96/600
8339	1S875	1S873, 500V	BYX 96/600
8340	1S876	1S873, 600V	BYX 96/600
8341	1S877	1S873, 700V	BYX 96/900
8342	1S878	1S873, 800V	BYX 96/900
8343	1S879	1S873, 900V	BYX 96/900
8344	1S88	1S87, <240ns	AAZ 49, AAZ 15, AAZ 17
8345	1S880	1S873, 1000V	BYX 96/1200
8346	1S881	400V, 0,5A	BY 126...127, BY 133...134, 1N4004...07
8347	1S881A	1S881, 600V	BY 126...127, BY 133...134, 1N4005...07
8348	1S881B	1S881, 800V	BY 127, BY 133, BY 227, 1N4006...07
8349	1S881C	1S881, 1000V	BY 127, BY 133, BY 227, 1N4007
8350	1S881D	1S881, 1200V	BY 127, BY 133, BY 227, BY 268...269
8351	1S881E	1S881, 1400V	BY 268...269, GP 10V, DM 513, EM 516
8352	1S882	400V, 0,75A	BY 126...127, BY 133...134, 1N4004...07
8353	1S882A	1S882, 600V	BY 126...127, BY 133...134, 1N4005...07
8354	1S882B	1S882, 800V	BY 127, BY 133, BY 227, 1N4006...07
8355	1S882C	1S882, 1000V	BY 127, BY 133, BY 227, 1N4007
8356	1S882D	1S882, 1200V	BY 127, BY 133, BY 227, BY 268...269
8357	1S882E	1S882, 1400V	BY 268...269, GP 10V, DM 513, EM 516
8358	1S883	300V, 100A	1N3290...97
8359	1S884	1S883, 400V	1N3291...97
8360	1S885	1S883, 500V	1N3292...97
8361	1S886	1S883, 600V	1N3293...97
8362	1S887	1S883, 700V	1N3294...97
8363	1S888	1S883, 800V	1N3294...97
8364	1S889	1S883, 900V	1N3295...97
8365	1S89	1S87, <340ns	AAZ 49, AAZ 15, AAZ 17
8366	1S890	1S883, 1000V	1N3295...97
8367	1S891		BA 124...125, BB 119, 1S2790, 1SV50
8368	1S892		BA 124...125, BB 119, 1S2790, 1SV50
8369	1S893		BA 124...125, BB 119, 1S2790, 1SV50

8370	1S894	6kV, 0,03A	CY 7, HS 6
8371	1S895	1S894, 8kV	CY 10, HS 8
8372	1S896	1S894, 10kV	CY 10, HS 8
8373	1S897	1S894, 12kV	HS 10
8374	1S90	150V, 0,3A	BY 126...127, BY 133...135, 1N4003...07
8375	1S90R..99R	1S90..99	1S90...99
8376	1S91	1S90, 200V	BY 126...127, BY 133...134, 1N4003...07
8377	1S92	1S90, 300V	BY 126...127, BY 133...134, 1N4004...07
8378	1S920[Fch,Tix]	BA 187	BA 187
8379	1S921[Fch,Tix]	BA 188	BA 188
8380	1S921[Japan]	200V, 1,5A	BY 226...227, BY 251...255, 1N5393...99
8381	1S922[Fch,Tix]	BA 189	BA 189
8382	1S922[Japan]	1S921[Japan], 400V	BY 226...227, BY 252...255, 1N5395...99
8383	1S923[Fch,Tix]	BA 190	BA 190
8384	1S923[Japan]	1S921[Japan], 600V	BY 226...227, BY 253...255, 1N5397...99
8385	1S924[Japan]	1S921[Japan], 800V	BY 227, BY 254...255, 1N5398...99
8386	1S925[Japan]	1S921[Japan], 1000V	BY 227, BY 255, BYX 86...87, 1N5399
8387	1S926	200V, 20A(Tc90°)	1N4525...30
8388	1S927	1S926, 400V	1N4526...30
8389	1S928	1S926, 600V	1N4527...30
8390	1S929	1S926, 800V	1N4528...30
8391	1S93	1S90, 400V	BY 126...127, BY 133...134, 1N4004...07
8392	1S930	1S926, 1000V	1N4529...30
8393	1S931	200V, 50A(Tc79°)	1N3289...97
8394	1S932	1S931, 400V	1N3291...97
8395	1S933	1S931, 600V	1N3293...97
8396	1S934	1S931, 800V	1N3294...97
8397	1S935	1S931, 1000V	1N3295...97
8398	1S936[Japan]	200V, 100A(Tc91°)	1N3289...97
8399	1S937[Japan]	1S936 [Japan], 400V	1N3291...97
8400	1S938[Japan]	1S936 [Japan], 600V	1N3293...97
8401	1S939[Japan]	1S936 [Japan], 800V	1N3294...97
8402	1S94	1S90, 500V	BY 126...127, BY 133...134, 1N4005...07
8403	1S940[Japan]	1S936 [Japan], 1000V	1N3295...97
8404	1S940[Texas]	30V, 0,05A	BA 147/50, BA 187...190, 1N5606...09
8405	1S941[Texas]	1S940[Texas], 50V	BA 147/50, BA 187...190, 1N5606...09
8406	1S942[Texas]	1S940[Texas], 75V	BA 147/100, BA 188...190, 1N5606...09
8407	1S946	200V, 0,6A	BY 126...127, BY 133...134, 1N4003...07
8408	1S947	1S947, 400V	BY 126...127, BY 133...134, 1N4004...07
8409	1S948	1S947, 600V	BY 126...127, BY 133...134, 1N4005...07
8410	1S949	1S947, 800V	BY 127, BY 133, BY 227, 1N4006...07
8411	1S95	1S90, 600V	BY 126...127, BY 133...134, 1N4005...07
8412	1S950	1S947, 1000V	BY 127, BY 133, BY 227, 1N4007
8413	1S951	35V, 0,1A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4151
8414	1S952	35V, 0,15A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4151



8415	1S953	35V, 0,1A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4151
8416	1S954	75V, 0,2A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4151
8417	1S955	100V, 0,2A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4151
8418	1S956	200V, 1,5A	BY 226...227, BY 251...255, 1N5393...99
8419	1S957	1S956, 400V	BY 226...227, BY 252...255, 1N5395...99
8420	1S958	1S956, 600V	BY 226...227, BY 253...255, 1N5397...99
8421	1S959	1S956, 800V	BY 227, BY 254...255, 1N5398...99
8422	1S96	1S90, 700V	BY 127, BY 133, BY 227, 1N4006...07
8423	1S960	1S956, 1000V	BY 227, BY 255, BYX 86...87, 1N5399
8424	1S961	200V, 3A	BY 205/200, BY 229/200, BYX 49/300
8425	1S962	1S961, 400V	BY 205/400, BY 229/400, BYX 49/600
8426	1S963	1S961, 600V	BY 205/600, BY 229/600, BYX 49/600
8427	1S964	1S961, 800V	BY 205/800, BY 229/800, BYX 49/900
8428	1S965	1S961, 1000V	BY205/1000, BY229/1000, BYX49/1200
8429	1S966	200V, 20A	1N4525...30
8430	1S967	1S966, 400V	1N4526...30
8431	1S968	1S966, 600V	1N4527...30
8432	1S969	1S966, 800V	1N4528...30
8433	1S97	1S90, 800V	BY 127, BY 133, BY 227, 1N4006...07
8434	1S970	1S966, 1000V	1N4529...30
8435	1S971	500V, 280A	-
8436	1S972	1S971, 600V	-
8437	1S973	1S971, 800V	-
8438	1S974	1S971, 1000V	-
8439	1S975	1S971, 1300V	-
8440	1S976	1S971, 1500V	-
8441	1S977	35V, 0,06A, <2,5ns	BA 318, BAY 38, 1N4148...49, 1N4151
8442	1S978	1S977, 50V	BA 318, BAY 38, 1N4148...49, 1N4151
8443	1S98	1S90, 900V	BY 127, BY 133, BY 227, 1N4007
8444	1S981	30V, 0,045A, <2,5ns	BA 318, BAY 38, 1N4148...49, 1N4151
8445	1S982	30V, 0,05A, <2,5ns	BA 318, BAY 38, 1N4148...49, 1N4151
8446	1S983	30V, 0,06A, <2,5ns	BA 318, BAY 38, 1N4148...49, 1N4151
8447	1S984	50V, 0,05A, <2ns	BA 318, BAY 38, 1N4148...49, 1N4151
8448	1S985	50V, 0,06A, <2ns	BA 318, BAY 38, 1N4148...49, 1N4151
8449	1S986	50V, 0,06A, <2ns	BA 318, BAY 38, 1N4148...49, 1N4151
8450	1S987	100V, 0,06A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
8451	1S988	100V, 0,06A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4151
8452	1S989	17..21V, 3W	BZX98/C18, BZY93/C18, ZL18, 1N2982
8453	1S99	1S90, 1000V	BY 127, BY 133, BY 227, 1N4007
8454	1S990(A)	0,6..0,8V, 0,25W	BA220, BZ102/0V7, BZX55/C0V8, ZPD1
8455	1S991(A)	1S990, 1,3..1,5V	BZ102/1V4, BZX75/C1V4, ZTE1,5
8456	1S992	1S990, 1,4..2,6V	BZ102/2V1, BZX75/C2V1, ZTE2
8457	1S993	1S990, 2,4..3,6V	-
8458	1S994	1S990, 3,4..4,6V	-
8459	1S995	35V	

8460	1S996(A,B)	5..10V, 0,1..0,15A	-
8461	1S997	10V, 0,1A	-
8462	1S998(A,B)	5..10V, 0,1..0,15A	-
8463	1S999	0,55..0,75V, 0,05W	BA 220, BZ102/0V7, BZX55/C0V8, ZPD1
8464	1SP	2SC3935-P	2SC3935
8465	1SP	2SC3130-P	2SC3130
8466	1SQ	2SC3130-Q	2SC3130
8467	1SQ	2SC3935-Q	2SC3935
8468	1SR	2SC3935-R	2SC3935
8469	1SR	2SC3130-R	2SC3130
8470	1SR124-..A	100..400V, 1A, <400ns	BYV 12...16, RGP 10B...M, RGP 15B...M
8471	1SR124-100A	100V, 1A, <400ns	BYT 52B...M, BYV 12...16, RGP 10B...M
8472	1SR139-..	100..600V, 1A	BY 126...127, BY 133...135, 1N4002...07
8473	1SR153-..	100..400V, 0,8A, <400ns	BYT 52B...M, BYV 12...16, RGP 10B...M
8474	1SR154-..	1S35-..., SMD	-
8475	1SR156-..	1S153-..., SMD	-
8476	1SR159-200	200V, 1A, <50ns	-
8477	1SR35-..(A)	100..400V, 1A	BY 126...127, BY 133...135, 1N4002...07
8478	1SS101	70V, 15mA	BAR 28, HSS 102, 1N5711
8479	1SS102	125V, 0,15A, <3ns	BA 203
8480	1SS103		BA 182, BA 243, BA 283, BA 483...484
8481	1SS104	35V, 0,1A	BA 127, BA 147/50, BA 187...190, BA 215
8482	1SS106	11V, 0,03A	BAR 10, BAT 19
8483	1SS107	22V, 15mA	BAR 10, 1N5712
8484	1SS108	35V, 15mA	HSS 100...102, 1S1992
8485	1SS109	90V, 0,15A	BA 147/100, BA 189...190, BAY 19...21
8486	1SS110		BA 182, BA 243, BA 283, BA 483...484
8487	1SS111	20V, 0,15A, <2ns	BAX 80, BAY 95, 1N4148...49, 1N4446...48
8488	1SS112	1SS111, 40V	BAX 80, BAY 95, 1N4148...49, 1N4446...48
8489	1SS113	1SS111, 60V	BAW 62, BAX 95, 1N4148...49, 1N4446...48
8490	1SS114	1SS111, 80V	BAW 62, BAX 95, 1N4148...49, 1N4446...48
8491	1SS115	1SS111, 100V	BAW 62, BAX 95, 1N4148...49, 1N4446...48
8492	1SS116	1SS111, 120V	-
8493	1SS117	35V, 0,1A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8494	1SS118	75V, 0,2A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8495	1SS119	35V, 0,15A, <3,5ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8496	1SS120	1SS119, 70V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8497	1SS121	75V, 0,2A, <50ns	BAV 19...21, BAW 49, BAY 43, BAY 72
8498	1SS122(H)	400V, 0,15A, <10µs	BA 157...159, BA 199/450, BAY 89...91
8499	1SS123	70V, 0,1A, <9ns	BAV 99, HSM 123, MA 157A
8500	1SS130	100V, 0,13A, <4ns	1N4148...49, 1N4446...49, 1SS115...116
8501	1SS131	90V, 0,13A, <4ns	1N4148...49, 1N4446...49, 1SS115...116
8502	1SS132	55V, 0,12A, <4ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8503	1SS133	40V, 0,11A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8504	1SS134	40V, 0,05A, <3ns	BA 318, BAY 38, 1N4148...49, 1N4446...49

8505	1SS135		BA 182, BA 243, BA 283, BA 483...484
8506	1SS136	75V, 0,2A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8507	1SS137	1SS136, 55V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8508	1SS138	1SS136, 40V	BA 318, BAY 38, 1N4148...49, 1N4446...49
8509	1SS139	90V, 0,13A, <50ns	BAV 19...21, BAW 49, BAY 43, BAY 72
8510	1SS140	55V, 0,12A, <50ns	BAV 18...21, BAW 49, BAY 42, BAY 72
8511	1SS141	40V, 0,11A, <50ns	BAV 18...21, BAW 49, BAY 41, BAY 72
8512	1SS142	300V, 0,2A, <400ns	BA 157...159, BY 204/4, BY 206...207
8513	1SS143	1SS142, 250V	BA 157...159, BY 204/4, BY 206...207
8514	1SS144	1SS142, 200V	BA 157...159, BY 204/4, BY 206...207
8515	1SS145	1SS142	BA 157...159, BY 204/4, BY 206...207
8516	1SS146	1SS143	BA 157...159, BY 204/4, BY 206...207
8517	1SS147	1SS144	BA 157...159, BY 204/4, BY 206...207
8518	1SS148	35V, 0,1A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8519	1SS149	250V, 0,15A, <5µs	BA 157...159, BY 204/4, BY 206...207
8520	1SS150		BA 182, BA 243, BS 283, BA 483...484
8521	1SS151	4V, 30mA	BA 480...481, BAR 19, BAT 29
8522	1SS152		BA 182, BA 243, BS 283, BA 483...484
8523	1SS153		BAT 18, MA 57
8524	1SS154	6V, 0,03A, 0,8pF	-
8525	1SS155		-
8526	1SS157	40V, 50mA	AA 113, AA 119, 1N34, 1N54, 1N60
8527	1SS158	50V, 50mA	AA 113, 1N34, 1N54, 1N60
8528	1SS16	855MHz	-
8529	1SS161		BA 182, BA 243, BA 283, BA 483...483
8530	1SS162		BA 244, BA 282, BA 282, BA 482
8531	1SS163	35V, 0,15A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8532	1SS164	1SS 163, 70V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8533	1SS165	12V, 15mA, <1pF(0V)	BAR 10...11, 1N5712
8534	1SS166	1SS165, <1,2pF(0V)	BAR 10...11, 1N5712
8535	1SS166A	1SS165, <0,8pF(0V)	BAR 10...11, 1N5712
8536	1SS168		BA 182, BA 243, BA 283, BA 483...483
8537	1SS172	120V, 0,7A, <20ns	-
8538	1SS173	35V, 0,1A, <12ns	BA 318, BAY 17, 1N4148...49, 1SS113
8539	1SS174	3V, 30mA	BA 480...481, BAR 19, BAT 29
8540	1SS175	75V, 0,15A, <100ns	BA 201, BAV 19...21, 1N4148...4149
8541	1SS175A	1SS175, 100V	BA 202, BAV 19...21, 1N4148...4149
8542	1SS176	35V, 0,1A, <4ns	BA 318, BAY 38, BAY 71, 1N4148...49
8543	1SS177	1SS176, 55V	BA 318, BAX 80, BAY 38, 1N4148...49
8544	1SS178	1SS176, 90V	BA 219, 1SS115, 1N4148...49, 1N4446...49
8545	1SS181	85V, 0,1A, <4ns	BAW 56, MA 152WA, KDS 181, 1S2836
8546	1SS184	1SS181	BAV 70, KDS 184, MA 152WK, 1S2838
8547	1SS187	85V, 0,1A, <4ns	-
8548	1SS190	1SS187	-
8549	1SS193	1SS187	-

8550	1SS196	1SS187	-
8551	1SS197		BA 182, BA 243, BA 283, BA 483...483
8552	1SS198	10V, 30mA	BAR 10...11, 1N5712, 1SS106
8553	1SS199	30V, 15mA	BAT 81, HSS 101, 1S1992, 1SS108
8554	1SS200	85V, 0,1A, <4ns	-
8555	1SS201	1SS200	-
8556	1SS202	35V, 0,1A, <3ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8557	1SS202(1)	1SS202, 100V	1N4148...49, 1N4446...49, 1SS115...116
8558	1SS205	1SS53	1SS53
8559	1SS206	1SS54	1SS54
8560	1SS207	1SS55	1SS55
8561	1SS220	70V, 0,1A, <3ns	-
8562	1SS221	1SS220, 100V	-
8563	1SS222	1SS220	-
8564	1SS223	1SS220, 100V	-
8565	1SS226	85V, 0,1A, <4ns	BAV 99, HSM 123, MA 157A
8566	1SS228	3V, 30mA	BA 480...481, BAR 19, BAT 29
8567	1SS233	35V, 0,1A, <3ns	MC 921
8568	1SS234	1SS233, 75V	MC 921
8569	1SS235	1SS233	MC 911
8570	1SS236	1SS233, 75V	MC 911
8571	1SS237(1)	10V, 35mA, <1pF(0V)	BAT 19, BAT 45, 1SS88, 1SS106
8572	1SS238		BA 182, BA 243, BA 283, BA 483...483
8573	1SS239	6V, 30mA	-
8574	1SS24	40V, 50mA	AA 113, 1N34, 1N54, 1N60
8575	1SS241	30V, 0,1A, <1,2pF, <0,9Ohm	BA 582
8576	1SS242	5V, 30mA	-
8577	1SS244	250V, 0,2A, <75ns	BA 198, BAV 21, 1SS83
8578	1SS245	1SS244	BA 198, BAV 21, 1SS83
8579	1SS247	250V, 0,2A, <60ns	BA 198, BAV 21 BA 157...159, BY 206...207
8580	1SS248	1SS247, 300V	1SS83 BA 157...159, BY 206...207
8581	1SS25	40V, 50mA	AA 113, 1N34, 1N54, 1N60
8582	1SS250	250V, 0,1A, <60ns	BAS 21
8583	1SS252	1SS131	1SS131
8584	1SS253	1SS132	1SS132
8585	1SS254	1SS133	1SS133
8586	1SS26	40V, 50mA	AA 113, 1N34, 1N54, 1N60
8587	1SS265	1SS135	1SS135
8588	1SS268	30V, <0,9Ohm	-
8589	1SS269	1SS268	-
8590	1SS27	40V, 50mA	AA 113, 1N34, 1N54, 1N60
8591	1SS270	30V, 0,15A, <3,5ns	BA 221, BAY 74, 1N4148...49, 1N4154
8592	1SS270A	1SS270, 70V	BAW 62, BAX 95, 1N4148...49, 1N4151
8593	1SS271	VHF/UHF, 6V, 30mA	BAT 68-04
8594	1SS272	85V, 0,1A, <4ns	-

8595	1SS276	3V, 30mA	BA 480...481, BAR 19, BAT 29
8596	1SS277	35V, 0,1A, <0,50hm	BA 282, BA 284, BA 482
8597	1SS279	35V, 0,1A, <10hm	BA 244, BA 282, BA 284, BA 482
8598	1SS28	30V, 50mA	AA 113, 1N34, 1N54, 1N60
8599	1SS280	35V, 0,1A, <0,60hm	BA 244, BA 282, BA 284, BA 482
8600	1SS281	10V, 35mA, <1pF(0V)	BAT 19, BAT 45, 1SS88, 1SS106
8601	1SS282	5V, 50mA, <1pF(0V)	1S1925
8602	1SS283	5V, 30mA, <0,9pF(0V)	BAR 10, BAT 45, 1N5712
8603	1SS285	70V, 15mA, <2pF(0V)	HSS 102
8604	1SS286	25V, 35mA	BAT 81, HSS 101, 1S1992, 1SS108
8605	1SS29	40V, 50mA	AA 113, 1N34, 1N54, 1N60
8606	1SS290	1SS139	1SS139
8607	1SS291	1SS140	1SS140
8608	1SS292	1SS141	1SS141
8609	1SS294	1SS293, SMD	1SS348
8610	1SS295	4V, 0,05A	MA 730, 1SS366
8611	1SS30	75V, 50mA	-
8612	1SS300	1SS181	-
8613	1SS301	1SS184	-
8614	1SS302	1SS226	-
8615	1SS306	250V, 0,1A, <60ns	-
8616	1SS307	35V, 0,1A	BAS 19...21, BAS 29
8617	1SS308	85V, 0,1A, <4ns	-
8618	1SS309	85V, 0,1A, <4ns	-
8619	1SS31	50V, 50mA	AA 113, 1N34, 1N54, 1N60
8620	1SS311	420V, 0,1A, 1,5µs	HSM 122
8621	1SS312	1SS268	-
8622	1SS313	1SS269	-
8623	1SS314	1SS241	BA 592, MA 77, 1SS356
8624	1SS314	1SS241	BA 592, MA 77, 1SS356
8625	1SS315	1SS242	-
8626	1SS315	1SS242	-
8627	1SS317	35V, 0,1A, <0,60hm	BA 244, BA 282, BA 284, BA 482
8628	1SS318		BA 592, 1SS314
8629	1SS319	1SS293, SMD,	-
8630	1SS321	S, 12V, 0,05A	-
8631	1SS322	1SS 294, SMD	-
8632	1SS332	40V, 0,1A, <4ns	1SS354, 1SS355
8633	1SS332	40V, 0,1A, <4ns	1SS354, 1SS355
8634	1SS336	85V, 0,2A, <20ns	-
8635	1SS337	1SS336	-
8636	1SS344	25V, 0,5A, 20ns	1SS349
8637	1SS345	55V, 10mA	-
8638	1SS348	85V, 0,1A	-
8639	1SS349	25V, 1A	-

8640	1SS350	5V, 30mA	BAT 17
8641	1SS351	1SS350	-
8642	1SS352	85V, 0,1A, <4ns	1SS353
8643	1SS352	85V, 0,1A, <4ns	1SS353
8644	1SS353	90V, 0,1A, <4ns	1SS352
8645	1SS353	90V, 0,1A, <4ns	1SS352
8646	1SS354	50V, 0,1A, <4ns	1SS352
8647	1SS354	50V, 0,1A, <4ns	1SS352
8648	1SS355	40V, 0,1A, <4ns	1SS332, 1SS352
8649	1SS355	40V, 0,1A, <4ns	1SS332, 1SS352
8650	1SS356	30V, 0,1A, <1,2pF, <0,9Ohm	BA 592, MA 77, 1SS314
8651	1SS356	30V, 0,1A, <1,2pF, <0,9Ohm	BA 592, MA 77, 1SS314
8652	1SS357	1SS293, SMD	-
8653	1SS357	1SS293, SMD	-
8654	1SS358	1SS345	-
8655	1SS360	1SS181	-
8656	1SS361	1SS184	-
8657	1SS362	1SS184	-
8658	1SS364	1SS268	-
8659	1SS365	10V, 35mA, 0,85pF	MA 704
8660	1SS366	1SS365	MA 730, 1SS295
8661	1SS367	15V, 0,1A	-
8662	1SS368	1SS352	-
8663	1SS369	1SS357	-
8664	1SS370	1SS250	-
8665	1SS371	1SS241	-
8666	1SS372	1SS367	-
8667	1SS373	1SS367	-
8668	1SS374	1SS367	-
8669	1SS375	1SS365	-
8670	1SS377	1SS367	-
8671	1SS378	1SS367	-
8672	1SS379	1SS367	-
8673	1SS382	80V, 0,1A, 1,6ns	-
8674	1SS382	80V, 0,1A, 1,6ns	-
8675	1SS383	40V, 0,1A	-
8676	1SS384	10V, 0,1A	-
8677	1SS385	10V, 0,1A	-
8678	1SS388	40V, 0,1A	-
8679	1SS389	10V, 0,1A	-
8680	1SS41	100V, 0,13A, <4ns	BA 219, 1N4148...49, 1N4446...49
8681	1SS42	5V, 30mA, 900MHz	BA 480...481, BAR 19, BAT 29
8682	1SS43	5V, 30mA	BA 480...481, BAR 19, BAT 29
8683	1SS48	70V, 0,1A	-
8684	1SS49	35V, 0,1A, <10ns	BAY 69, BAY 71, 1N4148...49, 1N4446...49

8685	1SS50	50V, 0,1A, <4ns	BA 318, BAY 38, 1N4148...49, 1N4446...49
8686	1SS51	75V, 0,1A, <10ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8687	1SS53	35V, 0,1A, <100ns	BAX 90, BAX 94, BAY 41...43, 1N4148...49
8688	1SS54	1SS53, 75V	BAW 49, BAY 43, BAY 72, 1N4148...49
8689	1SS55	1SS53, 100V	BAW 49, BAX 12, BAY 72, 1N4148...49
8690	1SS78	5V, 9375MHz	BA 480...481, BAR 19, BAT 29
8691	1SS81	200V, 0,2A, <100ns	BA 197...198, BAV 20...21, BAW 50
8692	1SS82	1SS81, 250V	BA 198, BAV 21
8693	1SS83	1SS81, 300V	-
8694	1SS84	75V, 0,15A, <50ns	BAV 19...21, BAW 49, BAY 43, BAY 72
8695	1SS85		BA 182, BA 243, BA 283, BA 483...484
8696	1SS86	3V, 30mA	-
8697	1SS87	3V, 15mA	-
8698	1SS88	10V, 15mA	BAT 19, 1SS106
8699	1SS90	5V, 30mA	BA 480...481, BAR 19, BAT 29
8700	1SS91(-G,-S)		BA 182, BA 243, BA 283, BA 483...484
8701	1SS92	75V, 0,2A, <2ns	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8702	1SS93	1SS92, 55V	BAW 62, BAX 95, 1N4148...49, 1N4446...49
8703	1SS94	1SS92, 40V	BAW 62, BAY 95, 1N4148...49, 1N4446...49
8704	1SS97(1,2)	10..30V, 35mA	HSS 100...102
8705	1SS98	5V, 50mA	1S1925
8706	1SS99	5V	-
8707	1SV100		BB 112, BB 130, BB 509, 1SV134...135
8708	1SV101		BA 125, BB 119, 1SV114, 1SV125
8709	1SV102	360..450pF(2V)	BB 112, BB 130, BB 509, 1SV134...135
8710	1SV103		BB 104, BB 204, BB 304, MV 104, 1SV109
8711	1SV104		BB 104, BB 204, BB 304, MV 104, 1SV109
8712	1SV109		BB 104, BB 204, BB 304, MV 104, 1SV55
8713	1SV110		BB 105, BB 205, BB 305, BB 405, BB 505
8714	1SV111		BB 105, BB 205, BB 305, BB 405, BB 505
8715	1SV112		BB 105, BB 205, BB 305, BB 405, BB 505
8716	1SV113		BB 105, BB 205, BB 305, BB 405, BB 505
8717	1SV114		BB 119, 1SV50, 1SV114, 1SV125
8718	1SV115		BB 112, BB 130, BB 509, 1SV134...135
8719	1SV116		BB 112, BB 130, BB 509, 1SV134...135
8720	1SV118		BB 112, BB 130, BB 509, 1SV134...135
8721	1SV121	100V, 0,1A	-
8722	1SV123		BB 105, BB 205, BB 305, BB 405, BB 505
8723	1SV124		BB 105, BB 205, BB 305, BB 405, BB 505
8724	1SV125		BA 125, BB 119, 1SV114
8725	1SV126		BB 109, BB 143, BBY 30, MV 109, 1SV50
8726	1SV128	50V, 0,05A, 0,25pF	MA 551, 1SV233
8727	1SV129		BB 112, BB 130, BB 509, 1SV134...135
8728	1SV132		BB 105, BB 205, BB 305, BB 405, BB 505
8729	1SV133		BB 105, BB 205, BB 305, BB 405, BB 505



8730	1SV134		BB 112, BB 130, BB 509, 1SV102, 1SV129
8731	1SV135		BB 112, BB 130, BB 509, 1SV102, 1SV129
8732	1SV136		BB 105, BB 205, BB 305, BB 405, BB 505
8733	1SV138		MA 337, MA 338, MA 353
8734	1SV145	34V	BB 119, 1SV114, 1SV125
8735	1SV146	34V	BB 119, 1SV114, 1SV125
8736	1SV147		BB 104, BB 204, BB304, MV 104, 1SV109
8737	1SV148		BB 105, BB 205, BB 305, BB 405, BB 505
8738	1SV149		BB 509, MV 1401...1404, 1SV134...135
8739	1SV151		BB 119, 1SV114, 1SV125, 1SV145...146
8740	1SV153(A)		BB 515, BB 721, BB 723, BB 729...731
8741	1SV154	65V, 0,1A	-
8742	1SV155		BB 205, BB 305, BB 405, BB 505, 1SV124
8743	1SV156	30V, 0,05A, <0,6pF	-
8744	1SV157	50V, 0,05A, <0,9pF	1SV196
8745	1SV160	15V, 7..14pF	-
8746	1SV161		BB 721, BB 723, BB 729...731
8747	1SV163	30V, 11..17pF(2V)	BB 117, BB 417
8748	1SV164	30V, 11..12,7pF(3V)	BB 405, BB 505, 1SV111, 1SV148
8749	1SV165	30V, 10,3..13pF(3V)	BB 405, BB 505, 1SV111, 1SV148
8750	1SV166	30V, 28..32,5pF(3V)	BB 109, BB 143, BBY 30, MV 109, 1SV50
8751	1SV166(1)	30V, 29..34pF(3V)	BB 109, BB 143, BBY 30, MV 109, 1SV50
8752	1SV166S	30V, 23..36pF(3V)	-
8753	1SV167	30V, 26..32pF(3V)	1SV209
8754	1SV169	30V, 2,1..2,5pF(2V)	BB 405, BB 505, 1SV111, 1SV148
8755	1SV170	30V, 13,7..17pF(2V)	BB 117, BB 417
8756	1SV172	AGC	-
8757	1SV178	65V, 0,15A	-
8758	1SV183	28V, 2..4pF(2V)	1SV210
8759	1SV184	15V, 40..50pF(2V)	BB 109, BB 143, BBY 30, MV 109, 1SV213
8760	1SV186	3,3..4,5pF(2V)	-
8761	1SV187	60V, 0,05A	MI 308, MI 407, 1SV178
8762	1SV188		BB 721, BB 723, BB 729...731
8763	1SV191	30V, 32..37pF(2V)	1SV167, 1SV209
8764	1SV193		BB 721, BB 723, BB 729...731
8765	1SV194		BB 419, BB 619...620
8766	1SV196	50V, 0,05A, <0,9pF	1SV157
8767	1SV200		BB 419, BB 619...620
8768	1SV202		BB 721, BB 723, BB 729...731
8769	1SV203		BB 419, BB 619...620
8770	1SV204	10,5..16pF(2V)	-
8771	1SV205	35V	BB 721, BB 723, BB 729...31, 1SV202
8772	1SV207	30V, 30..33pF(2V)	-
8773	1SV209	30V, 26,6..32pF(2V)	1SV167
8774	1SV210	28V, 2..4pF(2V)	1SV183

8775	1SV211	33..39pF(2V)	-
8776	1SV212	14..16pF(2V)	-
8777	1SV213	15V, 35..41pF(2V)	BB 109, BB 143, BBY 30, MV 109, 1SV184
8778	1SV214	1SV153A	BB 535, MA 360, MA 372, 1SV223
8779	1SV215	1SV161	MA 366, 1SV232
8780	1SV216	1SV204	-
8781	1SV217	1SV211	MA 371
8782	1SV218	30V, 32..37pF(2V)	-
8783	1SV219	30V, 26,6..32pF(2V)	-
8784	1SV220	30V, 9,5..14pF(2V)	BB 515, BB 721, BB 723
8785	1SV221	30V, 14..16,4pF(2V)	BB 515, BB 721, BB 723
8786	1SV222	30V, 13,7..17pF(2V)	-
8787	1SV223	1SV205	BB 535, MA 360, MA 372, 1SV214
8788	1SV224		-
8789	1SV225		-
8790	1SV226		-
8791	1SV227		-
8792	1SV228		-
8793	1SV229	1SV212	-
8794	1SV230	1SV224	-
8795	1SV231	1SV226	BB 639, MA 365, MA 374
8796	1SV232	1SV227	MA 366, 1SV215
8797	1SV233	50V, 0,05A	MA 551, 1SV128
8798	1SV234	1SV233	-
8799	1SV237	AGC	-
8800	1SV238		MA 355, MA 357, MA 366, 1SV269
8801	1SV239		-
8802	1SV241	50V, 0,23pF	-
8803	1SV242	36..42pF	-
8804	1SV242(SM)	1SV242	-
8805	1SV245		MA 368, MA 373
8806	1SV246	1SV233	-
8807	1SV247	1SV233	-
8808	1SV248	1SV250	-
8809	1SV249	1SV251	-
8810	1SV250	50V, 0,23pF	-
8811	1SV251	1SV250	-
8812	1SV252	1SV172	-
8813	1SV254	1SV153A	-
8814	1SV255	1SV161	-
8815	1SV256	1SV204	-
8816	1SV257	1SV212	-
8817	1SV258	1SV224	-
8818	1SV259	1SV227	-
8819	1SV260	1SV239	-

8820	1SV261	1SV245	-
8821	1SV262	33..38pF(2V)	-
8822	1SV263	1SV266	-
8823	1SV264	1SV267	-
8824	1SV265	50V, 0,23pF	-
8825	1SV266	50V, 0,23pF	-
8826	1SV267	1SV266	-
8827	1SV268	50V, 0,7pF	-
8828	1SV269	29..34pF(2V)	MA 355, MA 357, MA 266, 1SV238
8829	1SV270	15..17pF(1V)	-
8830	1SV271	1SV237	-
8831	1SV272	50V, 0,6pF	-
8832	1SV273	1SV270	-
8833	1SV274	1SV262	-
8834	1SV275	1SV269	-
8835	1SV276	1SV270	-
8836	1SV277	10V, 4..4,9(1V)	-
8837	1SV278	1SV153A	-
8838	1SV279	1SV212	-
8839	1SV280	1SV239	-
8840	1SV281	1SV270	-
8841	1SV282	1SV262	-
8842	1SV283	1SV269	-
8843	1SV284	1SV270	-
8844	1SV285	1SV277	-
8845	1SV286	1SV224	-
8846	1SV294	50V, 0,23pF	-
8847	1SV298	50V, 0,23pF	-
8848	1SV32	90V, 350..650MHz	-
8849	1SV33	90V, 250..550MHz	-
8850	1SV34	110V, 0,05A, 10GHz	-
8851	1SV35	110V, 0,05A, 10GHz	-
8852	1SV50(-1,S)		BB 109, BB 143, MV 109, MV 2101...2115
8853	1SV53(A,B)		BA 125, BB 119, 1SV114, 1SV125
8854	1SV54(G)		BA 125, BB 119, 1SV114, 1SV125
8855	1SV55		BB 104, BB 204, BB 304, MV 104, 1SV109
8856	1SV58		BB 105, BB 205, BB 305, BB 405, BB 505
8857	1SV59		BB 105, BB 205, BB 305, BB 405, BB 505
8858	1SV68		BB 101, BB 110, BB 203, MV 310, 1SV84
8859	1SV69		BB 105, BB 205, BB 305, BB 405, BB 505
8860	1SV70		BB 105, BB 205, BB 305, BB 405, BB 505
8861	1SV71		-
8862	1SV72		-
8863	1SV73		-
8864	1SV74		-

8865	1SV75		BB 105, BB 205, BB 305, BB 405, BB 505
8866	1SV76		BB 105, BB 205, BB 305, BB 405, BB 505
8867	1SV77	70V, <800ns	-
8868	1SV80	30V	-
8869	1SV84		BB 101, BB 110, BB 203, MV 310, 1SV68
8870	1SV87		BB 105, BB 205, BB 305, BB 405, BB 505
8871	1SV88		BB 105, BB 205, BB 305, BB 405, BB 505
8872	1SV89		BA 121, BB 117, BB 417
8873	1SV90(A)		BB 112, BB 130, BB 509, 1SV134...135
8874	1SV91		BB 112, BB 130, BB 509, 1SV134...135
8875	1SV92		BB 112, BB 130, BB 509, 1SV134...135
8876	1SV93		BB 112, BB 130, BB 509, 1SV134...135
8877	1SV94		BB 105, BB 205, BB 305, BB 405, BB 505
8878	1SV95		BB 105, BB 205, BB 305, BB 405, BB 505
8879	1SV96		-
8880	1SV97		BB 105, BB 205, BB 305, BB 405, BB 505
8881	1SV98		BB 119, 1SV50, 1SV114, 1SV125
8882	1SV99	50V, 0,05A, 0,3pF, 7Ohm	-
8883	1SZ45A	6,4V, 5%, 0,25W, +-0,01%/°C	BZV 10, BZV 27, BZX 90, 1N4575, 1N4580
8884	1SZ46A	6,4V, 5%, 0,25W, +-0,005%/°C	BZV 11, BZV 28, BZX 91, 1N4576, 1N4581
8885	1SZ47(A)	6,4V, 5%, 0,25W, +-0,002%/°C	BZV 12, BZV 29, BZX 92, 1N4577, 1N4582
8886	1SZ48(A)	6,4V, 5%, 0,25W, +-0,001%/°C	BZV 13, BZV 30, BZX 93, 1N4578, 1N4583
8887	1SZ50	6,2V, 5%, 0,25W, +-0,01%/°C	BZV 10, BZV 27, BZX 90, 1N4575, 1N4580
8888	1SZ51	6,2V, 5%, 0,25W, +-0,005%/°C	BZV 11, BZV 28, BZX 91, 1N4576, 1N4581
8889	1SZ52	6,2V, 5%, 0,25W, +-0,002%/°C	BZV 12, BZV 29, BZX 92, 1N4577, 1N4582
8890	1SZ53	6,2V, 5%, 0,25W, +-0,001%/°C	BZV 13, BZV 30, BZX 93, 1N4578, 1N4583
8891	1T	2SC4975	2SC4975
8892	1T	MMBT 3960A	MMBT 3960A
8893	1T	2SC3077	2SC3077
8894	1T	2SC3933	2SC3933
8895	1T1	SST 5101	SST 5101
8896	1T1	MMST 5101	MMST 5101
8897	1T32(A)	30V	BB 515, BB 721, BB 723, 1SV188, 1SV202
8898	1T33(A)	30V, 27,2..32pF(2V)	-
8899	1T33C	30V, 34,6..42pF(2V)	-
8900	1T359	30V	-
8901	1T360	1T364	MA 371, 1SV217
8902	1T362	1T32	BB 535, MA 360, MA 372, 1SV214, 1SV223
8903	1T363	1T33C	BB 639, MA 355, MA 366, MA 371
8904	1T364	30V, 28..34pF(2V)	MA 355, MA 357, MA 366
8905	1T365	30V, 3,3..4,5pF(2V)	-
8906	1T366	30V, 18,6pF(1V)	-
8907	1TH61	1500V, 0,3A, <6µs	BY 228, DM 513, EM 516, GP 10W...Y
8908	1TZ61	1500V, 1A	BY 228, DM 513, EM 516, GP 10W...Y
8909	1U	KST 2484	KST 2484

8910	1U	2SC3934	2SC3934
8911	1U	2SC3110	2SC3110
8912	1U	MMBT 2484	MMBT 2484
8913	1V	MMBT 6427	MMBT 6427
8914	1V	2SD2441	2SD2441
8915	1V(p)	BF 820	BF 820
8916	1VR	2SD1824-R	2SD1824
8917	1VR	2SD1149-R	2SD1149
8918	1VS	2SD1149-S	2SD1149
8919	1VS	2SD1824-S	2SD1824
8920	1VT	2SD1824-T	2SD1824
8921	1VT	2SD1149-T	2SD1149
8922	1W	FMMT 3903	FMMT 3903
8923	1W(p)	BF 821	BF 821
8924	1X	2SC2845	2SC2845
8925	1X(p)	BF 822	BF 822
8926	1XB	2SC4780-B	2SC4780
8927	1XC	2SC4780-C	2SC4780
8928	1Y	KST 3903	KST 3903
8929	1Y	YTS 3903	YTS 3903
8930	1Y	MMBT 3903	MMBT 3903
8931	1Y(p)	BF 823	BF 823
8932	1YQ	2SD2457-Q	2SD2457
8933	1YR	2SD2457-R	2SD2457
8934	1Z	MMBT 6517	MMBT 6517
8935	1Z6,2..390(A)	6,2..390V, 10%(A5%), 1W	BZW22/..., BZX61/..., ZPY..., 1N5920...56
8936	1ZB6.8..390	6,8..390V, 10%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5920...56
8937	1ZC12..120(A)	12..120V, 10%(A5%), 1W	BZW22/..., BZX61/..., ZPY..., 1N5927...51
8938	1ZF8,2..24	8,2..24V, 5%, 3W	BZT 03/..., BZV 16/..., BZX 70/...
8939	1ZM100	1ZM27, 100V	
8940	1ZM180	1ZM27, 180V	
8941	1ZM27	27V, 20%, 1W, bidirecional	BZW 06/...B, 1N6118...6137
8942	1ZM30	1ZM27, 30V	
8943	1ZM330	1ZM27, 330V	
8944	1ZM390	1ZM27, 390V	
8945	1ZM47	1ZM27, 47V	
8946	1ZM50	1ZM27, 50V	
8947	1ZQ	2SA1890-Q	2SA1890
8948	1ZR	2SD2433-R	2SD2433
8949	1ZR	2SD1030-R	2SD1030
8950	1ZR	2SD2345-R	2SD2345
8951	1ZR	2SD1823-R	2SD1823
8952	1ZR	2SA1890-R	2SA1890
8953	1ZS	2SD2433-S	2SD2433
8954	1ZS	2SD1823-S	2SD1823

8955	1ZS	2SD2345-S	2SD2345
8956	1ZS	2SD1030-S	2SD1030
8957	1ZT	2SD2433-T	2SD2433
8958	1ZT	2SD2345-T	2SD2345
8959	1ZT	2SD1823-T	2SD1823
8960	1ZT	2SD1030-T	2SD1030
8961	2	HVU 200(A)	HVU 200(A)
8962	2	HVC 200A	HVC 200A
8963	2	1SV200	1SV200
8964	2	HVE 200A	HVE 200A
8965	2	HVR 100	HVR 100
8966	2.0B	HZF 2.0BP	HZF 2.0BP
8967	2.0B	HZF 2.0BP	HZF 2.0BP
8968	2.0C	HZF 2.0CP	HZF 2.0CP
8969	2.2B	HZF 2.2BP	HZF 2.2BP
8970	2.2C	HZF 2.2CP	HZF 2.2CP
8971	2.4B	HZF 2.4BP	HZF 2.4BP
8972	2.4C	HZF 2.4CP	HZF 2.4CP
8973	2.7B	HZF 2.7BP	HZF 2.7BP
8974	2.7C	HZF 2.7CP	HZF 2.7CP
8975	20(X,Y,Z)	U 02W20V	Z 02W 20V
8976	20B	HZF 20BP	HZF 20BP
8977	20C	HZF 20CP	HZF 20CP
8978	20E1..E10	100..1000V, 1,7A	BYD 14D...M, GP 20B...M, 1N5060...5062
8979	20Y	BZV 49/C20	BZV 49/C20
8980	22	SM-1XZ02	SM-1XZ02
8981	22(X,Y,Z)	U 02W22V	Z 02W 22V
8982	2221..2222(A)	2N2221...22(A), 0,625W	2N2221...22(A)
8983	22B	HZF 22BP	HZF 22BP
8984	22C	HZF 22CP	HZF 22CP
8985	22C	F 1C2200	F 1C2200
8986	22F	F 1C2250	F 1C2250
8987	22G	F 1C2260	F 1C2260
8988	22H	F 1C2270	F 1C2270
8989	22I	F 1C2280	F 1C2280
8990	22J	F 1C2290	F 1C2290
8991	22Y	BZV 49/C22	BZV 49/C22
8992	23A	F 1C2300	F 1C2300
8993	23B	F 1C2310	F 1C2310
8994	23C	F 1C2320	F 1C2320
8995	24	MMBD 1201	MMBD 1201
8996	24	SM-1XZ04	SM-1XZ04
8997	24(X,Y,Z)	U 02W24V	Z 02W 24V
8998	24B	HZF 24BP	HZF 24BP
8999	24C	HZF 24CP	HZF 24CP

9000	24Y	BZV 49/C24	BZV 49/C24
9001	25SP-01..10	50..1000V, 25A	-
9002	26	MMBD 1203	MMBD 1203
9003	27	MMBD 1204	MMBD 1204
9004	27925	BD 902	BD 902
9005	27A	HZM 27FA	HZM 27FA
9006	27A	HZM 27WA	HZM 27WA
9007	27B	HZF 27BP	HZF 27BP
9008	27C	HZF 27CP	HZF 27CP
9009	27Y	BZV 49/C27	BZV 49/C27
9010	28	BFQ 28	BFQ 28
9011	28	MMBD 1205	MMBD 1205
9012	28025	BD 901	BD 901
9013	29	MMBD 1401	MMBD 1401
9014	2906..2907(A)	2N2906..07(A), 0,625W	2N2906...07(A)
9015	2955	MMFT 2955E	MMFT 2955E
9016	2A	MA 728	MA 728
9017	2A	KST 3906	KST 3906
9018	2A	YTS 3906	YTS 3906
9019	2A	MMBT 3906	MMBT 3906
9020	2A	FMMT 3906	FMMT 3906
9021	2A	SXT 3906	SXT 3906
9022	2AC3T	<40/20mA	TAG 200-..., T 2303-..., TAG 208-...
9023	2AC5T	2 AC3T, 500V	TAG 200-..., T 2303-..., TAG 208-...
9024	2AC6T	2 AC3T, 600V	TAG 200-..., T 2303-..., TAG 208-...
9025	2AQ	2SD1304-Q	2SD1304
9026	2AR	2SD1304-R	2SD1304
9027	2AR	2SC5026-R	2SC5026
9028	2AS	2SD1304-S	2SD1304
9029	2AS	2SC5026-S	2SC5026
9030	2B	2N2907	2N2907
9031	2B	MA 729	MA 729
9032	2B	BC 849BW	BC 849W
9033	2B	YTS 2907	YTS 2907
9034	2B	FMMT 2907	FMMT 2907
9035	2B	KST 2907	KST 2907
9036	2B	MMBT 2907	MMBT 2907
9037	2B(p,s)	BC 849B	BC 849
9038	2BP	2SK374-P	2SK374
9039	2BP	2SK663-P	2SK663
9040	2BQ	2SK663-Q	2SK663
9041	2BQ	2SK374-Q	2SK374
9042	2BR	2SK374-R	2SK374
9043	2BR	BC 849BR	BC 849R
9044	2BR	2SK663-R	2SK663



9045	2Bs	BC 849BW	BC 849W
9046	2BS	2SK374-S	2SK374
9047	2BS	2SK663-S	2SK663
9048	2C	MA 732	MA 732
9049	2C	BC 849CW	BC 849W
9050	2C	FMMT-A70	FMMT-A70
9051	2C	MMBTA 70	MMBTA 70
9052	2C(p,s)	BC 849C	BC 849
9053	2CR	BC 849CR	BC 849R
9054	2Cs	BC 849CW	BC 849W
9055	2D	MA 784	MA 784
9056	2D	BC 849W	BC 849W
9057	2D	KST 92	KST 92
9058	2D	MMBTA 92	MMBTA 92
9059	2D	SXTA 92	SXTA 92
9060	2D(p)	BC 849	BC 849
9061	2E	MA 785	MA 785
9062	2E	KST 93	KST 93
9063	2E	MMBTA 93	MMBTA 93
9064	2E	FMMT-A93	FMMT-A93
9065	2E	SXTA 93	SXTA 93
9066	2EZ3,6..200D..	3,6..200V, 2W, D55%, D1010%	BZV 16/..., BZV 47/..., BZX 70/..., ZY...
9067	2F	MMBT 2907A	MMBT 2907A
9068	2F	YTS 2907A	YTS 2907A
9069	2F	BC 850BW	BC 850W
9070	2F	FMMT 2907A	FMMT 2907A
9071	2F	KST 2907A	KST 2907A
9072	2F	SXT2907A	SXT 2907A
9073	2F	2SB1612	2SB1612
9074	2F(p,s)	BC 850B	BC 850B
9075	2FQ	2SB1583-Q	2SB1583
9076	2FR	2SB1583-R	2SB1583
9077	2FR	2SB792AR	2SB792A
9078	2FR	BC 850BR	BC 850R
9079	2FS	2SB1583-S	2SB1583
9080	2FS	2SB792AS	2SB792A
9081	2Fs	BC 850BW	BC 850W
9082	2G	MMBTA 56	MMBTA 56
9083	2G	KST 56	KST 56
9084	2G	BC 850C	BC 850
9085	2G	BC 850CW	BC 850W
9086	2G	FMMT-A56	FMMT-A56
9087	2GM	MMBTA 56	MMBTA 56
9088	2GR	BC 850CR	BC 850R
9089	2Gs	BC 850CW	BC 850W

9090	2GT	SOA 56	SOA 56
9091	2H	MMBTA 55	MMBTA 55
9092	2H	FMMT-A55	FMMT-A55
9093	2H	KST 55	KST 55
9094	2H	BC 850W	BC 850W
9095	2H(p)	BC 850	BC 850
9096	2HT	SOA 55	SOA 55
9097	2I	2SD2474	2SD2474
9098	2J	MMBT 3640	MMBT 3640
9099	2K	2SB1614	2SB1614
9100	2KBP01..10	50..1000V, 2A	B30...500C2200
9101	2L	MMBT 5401	MMBT 5401
9102	2L	KST 5401	KST 5401
9103	2M	MMBT 404	MMBT 404
9104	2M	FMMT 5087	FMMT 5087
9105	2N	MMBT 404A	MMBT 404A
9106	2N02L	MMFT 2N02EL	MMFT 2N02EL
9107	2N100	25V, 5mA, 0,025W	AC 127, ASY 28...29, 2SD30
9108	2N1000	40V, 0,15W, >7MHz	-
9109	2N1003	35V, 0,12W,	AF 124...127, AF 200
9110	2N1004	35V, 0,12W,	AF 124...127, AF 200
9111	2N1005	15V, 0,025A, 0,15W, B>20	BC 168, BC 183, BC 238, BC 548
9112	2N1006	2N1005, B>45	BC 168, BC 183, BC 238, BC 548
9113	2N1007	40V, 3A, 30W	AD 149, AUY 19...20, 2N1529...48
9114	2N1008	20V, 0,3A, 0,2W	AC 125...126, AC 151, 2N1191...94
9115	2N1008A	2N1008, 40V	ASY 48, ASY 77, 2N1191...94
9116	2N1008B	2N1008, 60V	ASY 48, ASY 77
9117	2N1009	35V, 0,3A, 0,15W	AC 128, AC 152...153
9118	2N101(13)	30V, 1,5A	-
9119	2N1010	10/10/10V, 2mA, 0,02W, 2MHz	-
9120	2N1011	80V, 5A, 90W	AL 102...103, AUY 28, 2N3615...18
9121	2N1012	40V, 0,15W, >3MHz	-
9122	2N1014	100V, 5A, 50W	AL 102...103, AUY 28, 2N3616, 2N3618
9123	2N1017	30V, 1A, 0,2W	AC 128, AC 153, 2SB324, 2SB415
9124	2N1018	30V, 1A, 0,2W	AC 128, AC 153, 2SB324, 2SB415
9125	2N102(13)	25V, 1,5A	-
9126	2N1021(A)	100V, 7A, 150W	2N1552, 2N1556, 2N1560, 2N3616, 2N3618
9127	2N1022(A)	2N1021, 120V	2N2290, 2N2293
9128	2N1023	40V, 10mA, 0,12W, 120MHz	AF 106, AF 109R, AF 306
9129	2N1024	18V, 0,1A, 0,25W, >1MHz	BC 213, BC 258, BC 308, BC 558
9130	2N1025	40V, 0,1A, 0,25W, >1MHz	BC 212, BC 257, BC 307, BC 557
9131	2N1026(A)	40V, 0,1A, 0,25W, >2MHz	BC 212, BC 257, BC 307, BC 557
9132	2N1027	18V, 0,1A, 0,25W, >4MHz	BC 213, BC 258, BC 308, BC 558
9133	2N1028	12V, 0,1A, 0,25W, >7,2MHz	BC 213, BC 258, BC 308, BC 558
9134	2N1029	50V, 15A, 90W, B>20	2N1550...52, 2N1555...56, 2N1559...60

9135	2N1029A	2N1029, 60V	2N1550...52, 2N1555...56, 2N1559...60
9136	2N1029B	2N1029, 90V	2N1552, 2N1556, 2N1560
9137	2N1029C	2N1029, 100V	2N1552, 2N1556, 2N1560
9138	2N103	35V, 0,01A, 0,05W	AC 127, ASY 28, 2SD30
9139	2N1030	50V, 15A, 90W, B>50	2N1550...52, 2N1555...56, 2N1559...60
9140	2N1030A	2N1030, 60V	2N1550...52, 2N1555...56, 2N1559...60
9141	2N1030B	2N1030, 90V	2N1552, 2N1556, 2N1560
9142	2N1030C	2N1030, 100V	2N1552, 2N1556, 2N1560
9143	2N1031	50V, 15A, 90W, B>20	2N1550...52, 2N1555...56, 2N1559...60
9144	2N1031A	2N1031, 60V	2N1550...52, 2N1555...56, 2N1559...60
9145	2N1031B	2N1031, 90V	2N1552, 2N1556, 2N1560
9146	2N1031C	2N1031, 100V	2N1552, 2N1556, 2N1560
9147	2N1032	50V, 15A, 90W, B>50	2N1550...52, 2N1555...56, 2N1559...60
9148	2N1032A	2N1032, 60V	2N1550...52, 2N1555...56, 2N1559...60
9149	2N1032B	2N1032, 90V	2N1552, 2N1556, 2N1560
9150	2N1032C	2N1032, 100V	2N1552, 2N1556, 2N1560
9151	2N1034	50V, 0,05A, 0,25W, $\beta$ >9	BC 212, BC 257, BC 307, BC 557
9152	2N1035	50V, 0,05A, 0,25W, $\beta$ >18	BC 212, BC 257, BC 307, BC 557
9153	2N1036	50V, 0,05A, 0,25W, $\beta$ >36	BC 212, BC 257, BC 307, BC 557
9154	2N1037	50V, 0,05A, 0,25W, $\beta$ >9	BC 212, BC 257, BC 307, BC 557
9155	2N1038	40V, 3A, 20W(Tc25°)	2N2564
9156	2N1038-1	2N1038	2N2552, 2N2560
9157	2N1038-2	2N1038	2N1042, 2N2556
9158	2N1039	60V, 3A, 20W(Tc25°)	2N2565
9159	2N1039-1	2N1039	2N2553, 2N2561
9160	2N1039-2	2N1039	2N1043, 2N2557
9161	2N104	30V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
9162	2N1040	80V, 3A, 20W(Tc25°)	2N2566
9163	2N1040-1	2N1040	2N2554, 2N2562
9164	2N1040-2	2N1040	2N1044, 2N2558
9165	2N1041	100V, 3A, 20W(Tc25°)	2N2567
9166	2N1041-1	2N1041	2N2555, 2N2563
9167	2N1041-2	2N1041	2N1045, 2N2559
9168	2N1042	40V, 3,5A, 20W(Tc25°)	2N1038, 2N2556
9169	2N1042-1	2N1042	2N2552, 2N2560
9170	2N1042-2	2N1042	2N1038, 2N2564
9171	2N1043	60V, 3,5A, 20W(Tc25°)	2N1039, 2N2557
9172	2N1043-1	2N1043	2N2553, 2N2561
9173	2N1043-2	2N1043	2N1039, 2N2565
9174	2N1044	80V, 3,5A, 20W(Tc25°)	2N1040, 2N2558
9175	2N1044-1	2N1044	2N2554, 2N2562
9176	2N1044-2	2N1044	2N1040, 2N2566
9177	2N1045	100V, 3,5A, 20W(Tc25°)	2N1041, 2N2559
9178	2N1045-1	2N1045	2N2555, 2N2563
9179	2N1045-2	2N1045	2N1041, 2N2567

9180	2N1046	100V, 12A, 50W	2N1552, 2N1556, 2N1560
9181	2N1046A,B	2N1046, 130V	AUY 38, 2N2527...28
9182	2N105	25V, 0,015A, 0,035W	AC 125...126, AC 151, 2SB54, 2SB56
9183	2N1051	60V, 0,1A, 0,5W, 3MHz	BC 174, BC 182, BC 190, BC 546
9184	2N1052	180V, 0,2A, 0,6W, 4MHz	BF 258...259, BF 658...659, 2N5058...59
9185	2N1053	2N1052, 200V	BF 258...259, BF 658...659, 2N5058...59
9186	2N1054	2N1052, 125V	BF 257...259, BF 657...659, 2N5058...59
9187	2N1055	2N1052, 100V	BF 257...259, BF 657...659, 2N5058...59
9188	2N1056	70V, 0,3A, 0,24W	ASY 48, ASY 77, 2N2042...43
9189	2N1057	45V, 0,3A, 0,24W	ASY 48, ASY 76...77, 2SB405ST
9190	2N1058	-/20V, 0,05A, 0,05W	AC 127, ASY 28, ASY 73...75
9191	2N1059	40V, 0,1A, 0,18W	AC 127, ASY 28, ASY 73...75
9192	2N106	15V, 0,01A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
9193	2N1060	40V, 0,2A, 0,25W, <50/-ns	BSW 41, BSY 63, 2N708. 2N4123
9194	2N1065	40V, 0,12W, >20MHz	ASY 76...77
9195	2N1066	40V, 10mA, 0,12W, 120MHz	AF 106, AF 109R, AF 306
9196	2N1067	60V, 0,5A, 5W, 1,5MHz	BD 137, BD 167, BD 525, BD 825
9197	2N1068	2N1067, 1,5A, 10W	BD 137, BD 167, BD 525, BD 825
9198	2N1069	60V, 4A, 50W	BD245A, BDV 91, 2N4914...15, 2N5068...69
9199	2N107	12V, 0,01A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
9200	2N1070	60V, 4A, 50V	BD245A, BDV 91, 2N4914...15, 2N5068...69
9201	2N1072	-/30V, 2A, 12W	BD 135, BD 165, BD 509, BD 825
9202	2N1073	40V, 10A, 85W	AL 100...101, AUY 21, 2N3611...18
9203	2N1073A	2N1073, 80V	AL 100...101, AUY 37, 2N3615...18
9204	2N1073B	2N1073, 120V	AL 100, AUY 38, 2N2290, 2N2293
9205	2N1074	50V, 0,05A, 0,25W, B14	BC 167, BC 182, BC 237, BC 547
9206	2N1075	2N1074, B25	BC 167, BC 182, BC 237, BC 547
9207	2N1076	2N1074, B50	BC 167, BC 182, BC 237, BC 547
9208	2N1077	2N1074, B18	BC 167, BC 182, BC 237, BC 547
9209	2N108	20V, 0,015A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
9210	2N1081	40V, 0,75A, 0,6W	BC 140...141, BC 300...302, 2N3053
9211	2N1082	25V, 0,05A, 0,2W, >17MHz	BC 168, BC 183, BC 238, BC 548
9212	2N1084	60V, 2A, 5W(Tc100°)	BC 461, BCX 60, 2N4235...36
9213	2N1085	60V, 2A, 5W(Tc100°)	BC 441, BCX 40, 2N4238...39
9214	2N1086(A)	9V, 0,02A, 0,065W, 8MHz	-
9215	2N1087	9V, 0,02A, 0,065W, 8MHz	-
9216	2N109	35V, 0,15A, 0,165W	AC 125...126, AC 151, 2SB54, 2SB56
9217	2N109/5	25V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
9218	2N1090	25V, 0,4A, 0,12W, 7MHz	ASY 73...75
9219	2N1091	25V, 0,4A, 0,12W, 13MHz	ASY 73...75
9220	2N1092	60V, 0,5A, 1,5MHz	BC 140...141, BC 300...302, 2N1613
9221	2N1093	30V, 0,3A, 0,15Wz	AC 125...126, AC 151...152, 2SB324
9222	2N1094	30V, 0,04A, 0,15W, 645MHz	AF 139, AF 239S
9223	2N1094	30V, 0,04A, 0,15W, 645MHz	AF 139, AF 239S
9224	2N1095	60V, 0,5W, 3MHz	BC 140...141, BC 300...302, 2N3053

9225	2N1096	90V, 0,5W, 3MHz	BC 141, BC 300...301, 2N1889...90
9226	2N1097	-/16V, 0,1A, 0,14W, B>34	AC 125...126, AC 151, 2SB54, 2SB56
9227	2N1098	2N11097, B>25	AC 125...126, AC 151, 2SB54, 2SB56
9228	2N1099	80V, 15A, 170W	2N1982, 2N2075, 2N2079, 2N2492...93
9229	2N110	50V, 0,04A, 0,2W	-
9230	2N1100	2N1099, 100V	2N2493
9231	2N1101	20V, 0,1A, 0,18W	AC 127, ASY 28...29, ASY 73...75
9232	2N1102	2N1101, 40V	-
9233	2N1103	45V, 0,02A, 0,125W, >10MHz	BC 167, BC 182, BC 237, BC 547
9234	2N1104	45V, 0,02A, 0,125W, >20MHz	BC 167, BC 182, BC 237, BC 547
9235	2N1105	60V, 0,5A, 0,8W	BC 140...141, BC 300...302, 2N3053
9236	2N1106	2N1105, 100V	BC 141, BC 300, 2N1889...90, 2N1990
9237	2N1107	16V, 5mA, 0,03W, 40MHz	AF 124...126, AF 200
9238	2N1108	16V, 5mA, 0,03W, 35MHz	AF 124...126, AF 200
9239	2N1109	16V, 5mA, 0,03W, 35MHz	AF 124...126, AF 200
9240	2N111(A)	30V, 0,2A, 0,13W, 3MHz	ASY 26, 2N3323...25
9241	2N1110	16V, 5mA, 0,03W, 35MHz	AF 124...126, AF 200
9242	2N1111(A,B)	20V, 5mA, 0,03W, 35MHz	AF 124...126, AF 200
9243	2N1114	25V, 0,2A, 0,15W, >7MHz	AC 127, ASY 28...29, ASY 73...75
9244	2N1115(A)	20V, 0,125A, 0,15W, >5MHz	AC 125...126, AC 151, ASY 26...27
9245	2N1116	60V, 0,8A, 0,6W, >6MHz	BC 140...141, BC 300...302, 2N3053
9246	2N1117	60V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
9247	2N1118(A)	25V, 0,05A, 0,15W	BC 213, BC 258, BC 308, BC 558
9248	2N1119	10V, 0,05A, 0,15W	BC 213, BC 258, BC 308, BC 558
9249	2N112(A)	30V, 0,2A, 0,13W, 5MHz	ASY 26, 2N3323...25
9250	2N1120	80V, 15A, 90W	2N1551...52, 2N1555...56, 2N1559...60
9251	2N1121	-/15V, 0,02A, 0,065W, 8MHz	-
9252	2N1122	12V, 0,05A, 0,025W	-
9253	2N1122A	2N1122, 15V	-
9254	2N1123	45V, 0,5A, 0,75W	2N1189...90
9255	2N1124	40V, 0,25A, 0,3W	2N1189...90, 2SB405ST
9256	2N1125	40V, 0,25A, 0,3W	2N1189...90, 2SB405ST
9257	2N1126	2N1124, 1W	2N1189...90, 2SB405ST
9258	2N1127	2N1125, 1W	2N1189...90, 2SB405ST
9259	2N1128	25V, 0,25A, 0,15W	AC 128, AC 152...153, AC 188, 2SB324
9260	2N1129	25V, 0,25A, 0,15W	AC 128, AC 152...153, AC 188, 2SB324
9261	2N113	30V, 0,2A, 0,13W, 10MHz	ASY 26, 2N3323...25
9262	2N1130	30V, 0,25A, 0,15W	AC 128, AC 152...153, AC 188, 2SB324
9263	2N1131	50V, 0,6A, 0,6W, >50MHz	BC 161, BC 303...304, 2N2904...05(A)
9264	2N1131A,AS	2N1131, 60V	BC 161, BC 303...304, 2N2904...05(A)
9265	2N1132	50V, 0,6A, 0,6W, >60MHz	BC 161, BC 303...304, 2N2904...05(A)
9266	2N1132A	2N1132, 60V	BC 161, BC 303...304, 2N2904...05(A)
9267	2N1132B	2N1132, 75V	BC 303, BSW 40, 2N4031, 2N4033
9268	2N1135(A)	>5,6MHz	(BC 213, BC 258, BC 308, BC 558
9269	2N1136	60V, 6A, 60W, B>50	AL 102...103, AUY 28, 2N3615...18

9270	2N1136A	2N1136, 90V	AL 102...103, AUY 28, 2N3616, 2N3618
9271	2N1136B	2N1136, 100V	AL 102...103, AUY 37, 2N3616, 2N3618
9272	2N1137	60V, 6A, 60W, B>75	AL 102...103, AUY 28, 2N3615...18
9273	2N1137A	2N1137, 90V	AL 102...103, AUY 28, 2N3616, 2N3618
9274	2N1137B	2N1137, 100V	AL 102...103, AUY 37, 2N3616, 2N3618
9275	2N1138	60V, 6A, 60W, B>100	AL 102...103, AUY 28, 2N3615...18
9276	2N1138A	2N1138, 90V	AL 102...103, AUY 28, 2N3616, 2N3618
9277	2N1138B	2N1138, 100V	AL 102...103, AUY 37, 2N3616, 2N3618
9278	2N1139	15V, 0,1A, 0,5W, >100MHz	BSV 69, 2N3724, 2SC1072, 2SC1385
9279	2N114	30V, 0,2A, 0,13W, 20MHz	ASY 26, 2N3323...25
9280	2N1140	40V, 1W, >35MHz	BSV 69, 2N3724, 2SC1072, 2SC1385
9281	2N1141(A)	35V, 0,1A, 0,3W, >1200MHz	AFY 18
9282	2N1142(A)	35V, 0,1A, 0,3W, >1000MHz	AFY 18
9283	2N1143(A)	35V, 0,1A, 0,3W, >800MHz	AFY 18
9284	2N1144	16V, 0,1A, 0,14W, B55	AC 125...126, AC 151, 2SB54, 2SB56
9285	2N1145	2N1144, B45	AC 125...126, AC 151, 2SB54, 2SB56
9286	2N1146	40V, 15A, 90W	2N1549...60
9287	2N1146A	2N1146, 60V	2N1550...52, 2N1554...56, 2N1558...60
9288	2N1146B	2N1146, 80V	2N1551...52, 2N1555...56, 2N1559...60
9289	2N1146C	2N1146, 100V	2N1552, 2N1556, 2N1560
9290	2N1147	40V, 15A, 90W	2N1549...60
9291	2N1147A	2N1147, 60V	2N1550...52, 2N1554...56, 2N1558...60
9292	2N1147B	2N1147, 80V	2N1551...52, 2N1555...56, 2N1559...60
9293	2N1147C	2N1147, 100V	2N1552, 2N1556, 2N1560
9294	2N1149	45V, 0,025A, 0,15W, 12MHz	BC 167, BC 182, BC 237, BC 547
9295	2N1150	45V, 0,025A, 0,15W, 13MHz	BC 167, BC 182, BC 237, BC 547
9296	2N1151	45V, 0,025A, 0,15W, 14MHz	BC 167, BC 182, BC 237, BC 547
9297	2N1152	45V, 0,025A, 0,15W, 15MHz	BC 167, BC 182, BC 237, BC 547
9298	2N1153	45V, 0,025A, 0,15W, 16MHz	BC 167, BC 182, BC 237, BC 547
9299	2N1154	50V, 0,06A, 0,75W, 1MHz	BC 140...141, BC 300...302, 2N3053
9300	2N1155	2N1154, 80V, 0,05A	BC 140...141, BC 300...301, 2N1889...90
9301	2N1156	2N1154, 120V, 0,04A	BC 300, 2N1883(A), 2N2102, 2N2405
9302	2N1157	60V, 40A, 187W	-
9303	2N1157A	2N1157, 80V	-
9304	2N1158(A)	20V, 0,1A, 0,06..0,075W	-
9305	2N1159	80V, 5A, 90W	AL 102...103, AUY 22, 2N3615...18
9306	2N1160	2N1159, 7A	AL 102...103, AUY 22, 2N3615...18
9307	2N1162(A)	50V, 25A, 106W	2N1651...53, 2N2285...87
9308	2N1163(A)	50V, 25A, 106W	2N1651...53, 2N2285...87
9309	2N1164(A)	80V, 25A, 106W	2N1652...53, 2N2286...87
9310	2N1165(A)	80V, 25A, 106W	2N1652...53, 2N2286...87
9311	2N1166(A)	100V, 25A, 106W	2N1653, 2N2287
9312	2N1167(A)	100V, 25A, 106W	2N1653, 2N2287
9313	2N1168	50V, 5A, 45W	AL 102...103, AUY 22, 2N1545...48
9314	2N1169	40V, 0,4A, 0,12W	-



9315	2N117	45V, 25mA, 0,15W, $\beta > 9$	BC 167, BC 182, BC 237, BC 547
9316	2N1170	40V, 0,4A, 0,12W	-
9317	2N1171	30V, 0,4A, 0,17W, $> 10\text{MHz}$	AC 128, AC 152...153, ASY 26, ASY 76...77
9318	2N1172	40V, 1,5A, 5W	AD 162
9319	2N1173	35V, 0,2A, 0,25W	-
9320	2N1174	35V, 0,2A, 0,25W	-
9321	2N1175(A)	35V, 0,5A, 0,225W, 4,2MHz	AC 128, AC 152...153, ASY 76...77
9322	2N1176	10V, 0,3A, 0,3W	AC 128, AC 152...153, 2SB324, 2SB415
9323	2N1176A	2N1176, 40V	ASY 48, ASY 76...77, 2SB405ST
9324	2N1176B	2N1176, 60V	ASY 48, ASY 77
9325	2N1177	40V, 10mA, 0,08W, 140MHz	AF 106, AF 109R, AF 306
9326	2N1178	40V, 10mA, 0,08W, 140MHz	AF 106, AF 109R, AF 306
9327	2N1179	40V, 10mA, 0,08W, 140MHz	AF 106, AF 109R, AF 306
9328	2N118(A)	2N117, $\beta > 19$	BC 167, BC 182, BC 237, BC 547
9329	2N1180	40V, 10mA, 0,08W, 100MHz	AF 106, AF 109R, AF 306
9330	2N1182	-/60V, 5A, 106W	2N1541...43, 2N1546...48, 2N3615...18
9331	2N1183	45V, 3A, 7,5W, $B > 20$	AUY 18
9332	2N1183A	2N1183, 60V	AUY 18
9333	2N1183B	2N1183, 80V	-
9334	2N1184	45V, 3A, 7,5W, $B > 40$	AUY 18
9335	2N1184A	2N1184, 60V	AUY 18
9336	2N1184B	2N1184, 80V	-
9337	2N1185	45V, 0,5A, 0,2W, 3MHz, $\beta > 190$	ASY 76...77
9338	2N1186	60V, 0,5A, 0,2W, 1,5MHz, $\beta > 30$	ASY 77
9339	2N1187	60V, 0,5A, 0,2W, 2MHz, $\beta > 50$	ASY 77
9340	2N1188	$\beta > 100$	ASY 77
9341	2N1189	45V, 0,5A, 0,2W, 3,5MHz, $\beta > 75$	ASY 76...77, 2SB405ST
9342	2N119	2N117, $\beta > 38$	BC 167, BC 182, BC 237, BC 547
9343	2N1190	$\beta > 125$	ASY 76...77, 2SB405ST
9344	2N1191	40V, 0,2A, 0,2W, 1,5MHz, $\beta > 30$	ASY 48, ASY 76...77, 2SB56A
9345	2N1192	40V, 0,2A, 0,2W, 2MHz, $\beta > 50$	ASY 48, ASY 76...77, 2SB56A
9346	2N1193	$\beta > 100$	ASY 48, ASY 76...77, 2SB56A
9347	2N1194	40V, 0,2A, 0,2W, 3MHz, $\beta > 190$	ASY 48, ASY 76...77, 2SB56A
9348	2N1195	$> 1200\text{MHz}$	2N1141...43
9349	2N1196	70V, 0,1A, 0,35	BC 212, BC 256, BC 266, BC 556
9350	2N1197	70V, 0,1A, 0,35	BC 212, BC 256, BC 266, BC 556
9351	2N1198	25V, 0,075A, 0,065W, 9MHz	ASY 28...29, ASY 73...75
9352	2N1199(A)	20V, 0,1A, 0,15W, 125MHz	BSV 89...92, BSX 92...93, 2N2368...69(A)
9353	2N120	2N117, $\beta > 76$	BC 167, BC 182, BC 237, BC 547
9354	2N1200	20V, 0,1A, 0,1W, 4,3MHz	BC 168, BC 183, BC 238, BC 548
9355	2N1201	2N1200, 12MHz	BC 168, BC 183, BC 238, BC 548
9356	2N1202	80V, 3,5A, 34W	-
9357	2N1203	2N1202, 120V	-
9358	2N1204(A)	20V, 0,5A, 0,3W, 200MHz	2N1495, 2N2099...2100
9359	2N1205	20V, 0,15W, $> 17\text{MHz}$	BC 168, BC 183, BC 238, BC 548



9360	2N1206	>10MHz	BC 140...141, BC 300...302, 2N3053
9361	2N1207	2N1206, 125V	BC 300, 2N1893(A), 2SC959, 2SC2108
9362	2N1208(I)	60V, 5A, 45..80W	2N3487...92
9363	2N1209(I)	45V, 5A, 45..80W	2N3487...92
9364	2N1212(I)	60V, 5A, 45..80W	2N3487...92
9365	2N1217	20V, 0,025A, 0,075W, 9MHz	-
9366	2N1218	45V, 3A, 20W	-
9367	2N1219	30V, 0,1A, 0,25W, >5MHz	BC 213, BC 258, BC 308, BC 558
9368	2N1220	30V, 0,1A, 0,25W, >2MHz	BC 213, BC 258, BC 308, BC 558
9369	2N1221	30V, 0,1A, 0,25W	BC 213, BC 258, BC 308, BC 558
9370	2N1222	30V, 0,1A, 0,25W, >2MHz	BC 213, BC 258, BC 308, BC 558
9371	2N1223	40V, 0,1A, 0,25W, 2MHz	BC 212, BC 257, BC 307, BC 557
9372	2N1224	40V, 10mA, 0,12W, 30MHz	AF 124...126, AF 200
9373	2N1225	40V, 10mA, 0,12W, 100MHz	AF 124...125, AF 200
9374	2N1226	60V, 10mA, 0,12W, 30MHz	AF 118
9375	2N1227	35V, 3A, 50W	AD 149, AUY 19...20, 2N2144...46
9376	2N1228	15V, 0,1A, 0,4W, 1,2MHz, $\beta > 14$	BC 213, BC 258, BC 308, BC 558
9377	2N1229	2N1228, $\beta > 28$	BC 213, BC 258, BC 308, BC 558
9378	2N123	20V, 0,125A, 0,15W	ASY 26...27, ASY 48, ASY 76...77
9379	2N1230	35V, 0,1A, 0,4W, 1,2MHz, $\beta > 14$	BC 213, BC 258, BC 308, BC 558
9380	2N1231	2N1230, $\beta > 28$	BC 213, BC 258, BC 308, BC 558
9381	2N1232	60V, 0,1A, 0,4W, 1MHz, $\beta > 14$	BC 212, BC 256, BC 266, BC 556
9382	2N1232A	2N1232, 90V	2SC1890, 2SC2240, 2SC2459, 2SC3245
9383	2N1233	2N1232, $\beta > 28$	BC 212, BC 256, BC 266, BC 556
9384	2N1234	$\beta > 14$	2SC1890A, 2SC2240, 2SC2459, 2SC3245
9385	2N1235	120V, 2A, 85W	2N3489, 2N3492, 2N5284...85
9386	2N123A(5)	2N123	ASY 26...27, ASY 48, ASY 76...77
9387	2N124	10V, 8mA, 0,05W, 3MHz	ASY 26...27, ASY 48, ASY 76...77
9388	2N1245	30V, 4A, 20W	AD 149, AUY 28, 2N1529...48, 2SB449
9389	2N1246	30V, 4A, 20W	AD 149, AUY 28, 2N1529...48, 2SB449
9390	2N1247	6V, 5mA, 0,03W, 5MHz, $B > 15$	BC 168, BC 183, BC 238, BC 548
9391	2N1248	6V, 5mA, 0,03W, 5MHz, $B > 15$	BC 168, BC 183, BC 238, BC 548
9392	2N1249	6V, 5mA, 0,03W, 5MHz, $B > 20$	BC 168, BC 183, BC 238, BC 548
9393	2N125	10V, 8mA, 0,05W, 5MHz	ASY 26...27, ASY 48, ASY 76...77
9394	2N1251	20V, 0,1A, 0,15W	AC 127, ASY 28...29, ASY 73...75
9395	2N1252	30V, 1A, 0,6W, >40MHz, $B > 15$	BC 140...141, BC 300...302, 2N2218...19
9396	2N1252A	2N1252, 60V	BC 140...141, BC 300...302, 2N2218...19
9397	2N1253	30V, 1A, 0,6W, >50MHz, $B > 30$	BC 140...141, BC 300...302, 2N2218...19
9398	2N1253A	2N1253, 60V	BC 140...141, BC 300...302, 2N2218...19
9399	2N1254	30V, 0,1A, 0,275W, <25/40ns	BC 213, BC 308, BC 558, BSX 36
9400	2N1255	30V, 0,1A, 0,275W, <25/60ns	BC 213, BC 308, BC 558, BSX 36
9401	2N1256	40V, 0,1A, 0,275W, <25/40ns	BC 212, BC 307, BC 557, BSX 36
9402	2N1257	40V, 0,1A, 0,275W, <25/60ns	BC 212, BC 307, BC 557, BSX 36
9403	2N1258	40V, 0,1A, 0,275W, <25/60ns	BC 212, BC 307, BC 557, BSX 36
9404	2N1259	50V, 0,1A, 0,275W, <25/60ns	BC 212, BC 307, BC 557, BSX 36

9405	2N126	10V, 8mA, 0,05W, 5MHz	ASY 26...27, ASY 48, ASY 76...77
9406	2N1261(A)	80V, 3,5A, 34W, B>20	-
9407	2N1262(A)	2N1261(A), B>30	-
9408	2N1263(A)	2N1261(A), B>45	-
9409	2N1264	20V, 10mA, 0,05W, 3MHz	AF 124...127, AF 200
9410	2N1264/13	2N1264	-
9411	2N1265	20V, 0,1A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
9412	2N1265/5	2N1265, 10V, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
9413	2N1266	-/10V, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
9414	2N1267	20V, 0,1A, 0,15W, B>6	BC 168, BC 183, BC 238, BC 548
9415	2N1268	2N1267, B>11	BC 168, BC 183, BC 238, BC 548
9416	2N1269	2N1267, B>28	BC 168, BC 183, BC 238, BC 548
9417	2N127	10V, 8mA, 0,05W, 5MHz	ASY 26...27, ASY 48, ASY 76...77
9418	2N1270	2N1267	BC 168, BC 183, BC 238, BC 548
9419	2N1271	2N1267, B>11	BC 168, BC 183, BC 238, BC 548
9420	2N1272	2N1267, B>28	BC 168, BC 183, BC 238, BC 548
9421	2N1273	15V, 0,2A, 0,25W	AC 125...126, AC 151, 2SB54, 2SB56
9422	2N1274	2N1273, 25V	AC 125...126, AC 151, 2SB54, 2SB56
9423	2N1275	100V, 0,05A, 0,25W	BF 398, BSS 68, BSV 68, 2SB715...716
9424	2N1276	40V, 0,025A, 0,15W, B>9	BC 167, BC 182, BC 237, BC 547
9425	2N1277	2N1276, B>18	BC 167, BC 182, BC 237, BC 547
9426	2N1278	2N1276, B>37	BC 167, BC 182, BC 237, BC 547
9427	2N1279	2N1276, B>76	BC 167, BC 182, BC 237, BC 547
9428	2N128	10V, 5mA, 0,025W, >28MHz	AF 124...127, AF 200
9429	2N1280	16V, 0,4A, 0,2W, >5MHz, B>40	ASY 76...77
9430	2N1281	16V, 0,4A, 0,2W, >7MHz, B>60	ASY 76...77
9431	2N1282	B>70	ASY 76...77
9432	2N1284	20V, 0,4A, 0,15W, 8MHz	ASY 76...77
9433	2N1285	40V, 10mA, 0,12W, 100MHz	AF 124...125, AF 200
9434	2N1287(A)	25V, 0,3A, 0,3W, 1MHz	-
9435	2N1288	15V, 0,05A, 0,075W, 60MHz	-
9436	2N1289	2N1288, 20V	-
9437	2N129	10V, 5mA, 0,03W, 30MHz	AF 124...127, AF 200
9438	2N1291	35V, 3A, 20W	AD 149, AUY 19...20, 2N2143...46
9439	2N1292	35V, 3A, 25W	2N1218
9440	2N1293	2N1291, 60V	AL 102...103, AUY 19...20, 2N2144...46
9441	2N1294	2N1292, 60V	-
9442	2N1295	2N1291, 80V	AL 102...103, AUY 20, 2N2141, 2N2146
9443	2N1296	2N1292, 80V	-
9444	2N1297	2N1291, 100V	AL 102...103, AUY 34, 2N2141, 2N2146
9445	2N1298	2N1292, 100V	-
9446	2N1299	40V, 0,2A, 0,15W, 5MHz	-
9447	2N130	25V, 0,01A, 0,085W	AC 125...126, AC 151, ASY 26...27
9448	2N1300	13V, 0,1A, 0,15W, 40MHz	-
9449	2N1301	2N1300, 60MHz	-

9450	2N1302	25V, 0,3A, 0,15W, 5MHz, B>20	ASY 28...29, ASY 73...75
9451	2N1303	30V, 0,3A, 0,15W, 5MHz, B>20	ASY 26, ASY 76...77
9452	2N1304	B>40	ASY 28...29, ASY 73...75
9453	2N1305	B>40	ASY 26, ASY 76...77
9454	2N1306	B>60	ASY 28...29, ASY 73...75
9455	2N1307	B>60	ASY 26, ASY 76...77
9456	2N1308	B>80	ASY 28...29, ASY 73...75
9457	2N1309(A)	B>80	ASY 26, ASY 76...77
9458	2N130A	45V, 0,1A, 0,1W	ASY 48, ASY 76...77
9459	2N131	25V, 0,01A, 0,085W	AC 125...126, AC 151, ASY 26...27
9460	2N1310	90V, 0,12W	-
9461	2N1311	75V, 0,12W	-
9462	2N1312	50V, 0,12W	-
9463	2N1313	30V, 0,4A, 0,18W, 12MHz	ASY 76...77
9464	2N1314	40V, 3,5A, 12W(Tc70°)	AD 149, AUY 19...20, 2N2143...46
9465	2N1315	32V, 3,5A, 12W(Tc70°)	AD 149, AUY 19...20, 2N2137...46
9466	2N1316	30V, 0,4A, 0,2W, >10MHz	ASY 76...77
9467	2N1317	20V, 0,4A, 0,2W, >10MHz	ASY 76...77
9468	2N1318	10V, 0,4A, 0,2W, >10MHz	ASY 76...77
9469	2N1319	20V, 0,4A, 0,2W, 6MHz	ASY 76...77
9470	2N131A	45V, 0,1A, 0,1W	ASY 48, ASY 76...77
9471	2N132	25V, 0,01A, 0,085W	AC 125...126, AC 151, ASY 26...27
9472	2N1320	35V, 3A, 20W	-
9473	2N1321	35V, 3A, 25W	-
9474	2N1322	2N1320, 60V	-
9475	2N1323	2N1321, 60V	-
9476	2N1324	2N1320, 80V	-
9477	2N1325	2N1321, 80V	-
9478	2N1326	2N1320, 100V	-
9479	2N1327	2N1321, 100V	-
9480	2N1328	2N1320	-
9481	2N1329	2N1321	-
9482	2N132A	35V, 0,1A, 0,1W	ASY 48, ASY 76...77
9483	2N133	25V, 0,01A, 0,085W	AC 125...126, AC 151, ASY 26...27
9484	2N1330	2N1321, 60V	-
9485	2N1331	2N1320, 80V	-
9486	2N1332	2N1321, 80V	-
9487	2N1333	2N1320, 100V	-
9488	2N1334	2N1321, 100V	-
9489	2N1335	120V, 0,3A, PQ>0,25W(70MHz)	-
9490	2N1336	120V, 0,3A, PQ>0,5W(70MHz)	-
9491	2N1337	120V, 0,3A, PQ>0,7W(70MHz)	-
9492	2N1338	80V, 0,3A, PQ>0,5W(70MHz)	-
9493	2N1339	120V, 0,3A, PQ>0,25W(70MHz)	-
9494	2N133A	35V, 0,1A, 0,1W	ASY 48, ASY 76...77

9495	2N1340	150V, 0,3A, PQ>0,5W(70MHz)	-
9496	2N1341	120V, 0,3A, PQ>0,75W(70MHz)	-
9497	2N1342	150V, 0,3A, PQ>1W(70MHz)	-
9498	2N1343	20V, 0,4A, 0,15W, 6MHz	ASY 76...77
9499	2N1344	15V, 0,4A, 0,15W, >7MHz	ASY 76...77
9500	2N1345	10V, 0,4A, 0,15W, >10MHz	ASY 76...77
9501	2N1346	12V, 0,4A, 0,15W, >10MHz	ASY 76...77
9502	2N1347	20V, 0,2A, 0,15W, >5MHz	ASY 26...27, ASY 76...77
9503	2N1348	40V, 0,4A, 0,2W, 5MHz	ASY 76...77
9504	2N1349	40V, 0,4A, 0,2W, 10MHz	ASY 76...77
9505	2N135	20V, 0,05A, 0,1W, 4,5MHz	AF 124...127, AF 200, 2N3323...25
9506	2N1350	50V, 0,4A, 0,2W, 8MHz	ASY 76...77
9507	2N1351	40V, 0,4A, 0,2W, 8MHz	ASY 76...77
9508	2N1352	30V, 0,2A, 0,15W, >2,5MHz	ASY 26...27, ASY 76...77
9509	2N1353	15V, 0,2A, 0,2W, 3,5MHz	ASY 26...27, ASY 76...77
9510	2N1354	30V, 0,2A, 0,2W, 4,5MHz	ASY 26...27, ASY 76...77
9511	2N1355	30V, 0,2A, 0,2W, 8MHz	ASY 26...27, ASY 76...77
9512	2N1356	30V, 0,2A, 0,2W, >5MHz	ASY 26...27, ASY 76...77
9513	2N1357	30V, 0,2A, 0,2W, 12MHz	ASY 26...27, ASY 76...77
9514	2N1358(A,M)	80V, 15A, 150W	2N1982, 2N2075, 2N2079, 2N2492...93
9515	2N1359	50V, 3A, 106W, B>35	2N1540...43, 2N1546...48, 2N3615...18
9516	2N136	20V, 0,05A, 0,1W, 6,5MHz	AF 124...127, AF 200, 2N3323...25
9517	2N1360	2N1359, B>60	2N1540...43, 2N1546...48, 2N3615...18
9518	2N1361(A)	25V, 0,2A, 0,15..0,2W, 4MHz	ASY 26...27, ASY 76...77
9519	2N1362	100V, 3A, 106W, B>35	2N1542...43, 2N1547...48, 2N3616, 2N3618
9520	2N1363	2N1362, B>60	2N1542...43, 2N1547...48, 2N3616, 2N3618
9521	2N1364	2N1362, 120V	2N1543, 2N1548, 2N2290, 2N2293
9522	2N1365	2N1362, 120V, B>60	2N1543, 2N1548, 2N2290, 2N2293
9523	2N1366	18V, 0,025A, 0,1W, >5MHz	-
9524	2N1367	2N1366, >2,5MHz	-
9525	2N137	20V, 0,05A, 0,1W, 10MHz	AF 124...127, AF 200, 2N3323...25
9526	2N1370	25V, 0,2A, 0,25W, B>45	AC 125...126, AC 151, 2SB54, 2SB56
9527	2N1371	2N1370, 45V	2SB56A
9528	2N1372	2N1370, B>30	AC 125...126, AC 151, 2SB54, 2SB56
9529	2N1373	2N1370, 45V	2SB56A
9530	2N1374	2N1370, B>50	AC 125...126, AC 151, 2SB54, 2SB56
9531	2N1375	2N1370, 45V, B>50	2SB56A
9532	2N1376	2N1370, B>75	AC 125...126, AC 151, 2SB54, 2SB56
9533	2N1377	2N1370, 45V, B>75	2SB56A
9534	2N1378	2N1370, 12V, B>95	AC 125...126, AC 151, 2SB54, 2SB56
9535	2N1379	2N1370, B>95	AC 125...126, AC 151, 2SB54, 2SB56
9536	2N138	20V, 0,15A, 0,15W	AC 125...126, AC 151, ASY 26...27
9537	2N1380	2N1370, 12V, B>30	AC 125...126, AC 151, 2SB54, 2SB56
9538	2N1381	2N1370, B>30	AC 125...126, AC 151, 2SB54, 2SB56
9539	2N1382	2N1370, B>50	AC 125...126, AC 151, 2SB54, 2SB56

9540	2N1383	2N1370, B>30	AC 125...126, AC 151, 2SB54, 2SB56
9541	2N1384	30V, 0,5A, 0,24W, 35MHz	-
9542	2N1385	25V, 0,1A, 0,75W, >250MHz	-
9543	2N1386	25V, 0,05A, 0,3W, 60MHz	BC 238, BC 548, BSV 59, 2N2221...22(A)
9544	2N1387	30V, 0,05A, 0,3W, 50MHz	BC 238, BC 548, BSV 59, 2N2221...22(A)
9545	2N1388	45V, 0,05A, 0,3W, >50MHz	BC 237, BC 547, BSV 59, 2N2221...22(A)
9546	2N1389	50V, 0,05A, 0,3W, >25MHz	BC 237, BC 547, BSV 59, 2N2221...22(A)
9547	2N138A,B	2N138, 45V, 0,13W	ASY 48, ASY 76...77
9548	2N139	16V, 15mA, 0,035W, 4,7MHz	AF 124...127, AF 200, 2N3323...25
9549	2N1390	20V, 0,05A, 0,3W, >20MHz	BC 238, BC 548, BSV 59, 2N2221...22(A)
9550	2N1391	25V, 0,15W, >3MHz	AC 127, ASY 28...29, ASY 73...75
9551	2N1395	40V, 10mA, 0,12W, 30MHz	AF 124...126, AF 200
9552	2N1396	2N1395, 100MHz	AF 106, AF 109R, AF 306
9553	2N1397	2N1395, 120MHz	AF 106, AF 109R, AF 306
9554	2N1398	>140MHz	AF 106, AF 109R, AF 306
9555	2N1399	>140MHz	AF 106, AF 109R, AF 306
9556	2N140	16V, 15mA, 0,035W, 7MHz	AF 124...127, AF 200, 2N3323...25
9557	2N1400	>100MHz	AF 106, AF 109R, AF 306
9558	2N1401(A)	>120MHz	AF 106, AF 109R, AF 306
9559	2N1402	>100MHz	AF 106, AF 109R, AF 306
9560	2N1403	15V, 0,1A, 0,25W, >200MHz	AF 109R, AF 139, AF 239(S)
9561	2N1404(A)	25V, 0,3A, 0,15W, >4MHz	ASY 76...77
9562	2N1405	30V, 0,05A, 0,075W, 1100MHz	AF 139, AF 239(S)
9563	2N1406	30V, 0,05A, 0,075W, 1100MHz	AF 139, AF 239(S)
9564	2N1407	30V, 0,05A, 0,075W, 1100MHz	AF 139, AF 239(S)
9565	2N1408	50V, 0,2A, 0,15W	ASY 48, ASY 77
9566	2N1409(A)	30V, 0,5A, 0,6..0,8W, B>15	BC 140...141, BC 300...302, 2N2218...19
9567	2N1410(A)	2N1409(A), B>30	BC 140...141, BC 300...302, 2N2218...19
9568	2N1411	-/50V, 0,025W, 70MHz	-
9569	2N1412(A)	100V, 15A, 150W	2N2493
9570	2N1413	35V, 0,5A, 0,225W, B>25	AC 128, AC 152...153, 2SB324, 2SB415
9571	2N1414	2N1413, B>34	AC 128, AC 152...153, 2SB324, 2SB415
9572	2N1415	2N1413, B>53	AC 128, AC 152...153, 2SB324, 2SB415
9573	2N1417	15V, 0,05A, 0,15W	BC 168, BC 183, BC 238, BC 548
9574	2N1418	2N1417, 30V	BC 168, BC 183, BC 238, BC 548
9575	2N1419	80V, 25A, 87W	2N1652...53, 2N2286...87
9576	2N1420(A)	60V, 1A, 0,6..0,8W, >50MHz	BC 140...141, BC 300...302, 2N1990
9577	2N1421	60V, 3A, 30W	2N5002, 2N5004, 2N5284...85
9578	2N1422	60V, 3A, 30W	AL 102...103, AUY 19...20, 2N2144...46
9579	2N1423	60V, 3A, 60W	AL 102...103, AUY 19...20, 2N2144...46
9580	2N1424	60V, 3A, 60W	2N5002, 2N5004, 2N5284...85
9581	2N1425	24V, 10mA, 0,08W, >6MHz	AF 124...127, AF 200
9582	2N1426	24V, 10mA, 0,08W, >6MHz	AF 124...127, AF 200
9583	2N1427	6V, 0,05A, 0,025W, 60MHz	ASZ 21, 2N705, 2N960...967
9584	2N1428	6V, 0,05A, 0,1W, >18MHz	BC 213, BC 258, BC 308, BC 558

9585	2N1429	2N1428	BC 213, BC 258, BC 308, BC 558
9586	2N1430	100V, 10A, 70W	AL 100...101, AUY 37, 2N2290, 2N2293
9587	2N1431	20V, 0,1A, 0,18W	AC 127, AC 176, AC 187
9588	2N1432	45V, 10mA, 0,1W	AF 124...127, AF 200
9589	2N1433	80V, 3,5A, 12W(Tc75°), B>20	-
9590	2N1434	2N1433, B>45	-
9591	2N1435	2N1433, B>30	-
9592	2N1436	15V, 0,05A, 0,05W, <70/-ns	ASZ 21, 2N705, 2N960...67
9593	2N1437	100V, 3A, 23W	-
9594	2N1438	100V, 3A, 23W	-
9595	2N1439	50V, 0,1A, 0,4W, >1MHz, B9	BC 212, BC 257, BC 307, BC 557
9596	2N1440	2N1439, 60V, B16	BC 212, BC 256, BC 266, BC 556
9597	2N1441	2N1439, B27	BC 212, BC 257, BC 307, BC 557
9598	2N1442	2N1439, B43	BC 212, BC 257, BC 307, BC 557
9599	2N1443	2N1439, B65	BC 212, BC 257, BC 307, BC 557
9600	2N1444	60V, 0,25A, 0,5W, <250/250ns	BC 140...141, BC 300...302, 2N2218...19
9601	2N1445	120V, 0,75A, 0,8W	BC 300, 2N1893, 2SC959, 2SC2108
9602	2N1446	45V, 0,4A, 0,2, B30	2N1189...90, 2SB405ST
9603	2N1447	2N1446, B45	2N1189...90, 2SB405ST
9604	2N1448	2N1446, B65	2N1189...90, 2SB405ST
9605	2N1449	2N1446, B80	2N1189...90, 2SB405ST
9606	2N145	20V, 5mA, 0,065W, B30	-
9607	2N1450	30V, 0,1A, 0,12W, <200/170ns	2N2955...57
9608	2N1451	45V, 0,4A, 0,2W, B>20	2N1189...90, 2SB405ST
9609	2N1452	2N1451, B>30	2N1189...90, 2SB405ST
9610	2N1453	30V, 5A, 43W, B>40	-
9611	2N1454	2N1453, B>70	-
9612	2N1455	2N1453, 60V	-
9613	2N1456	2N1453, 60V, B>70	-
9614	2N1457	2N1453, 80V	-
9615	2N1458	2N1453, 80V, B>70	-
9616	2N146	2N145, B50	-
9617	2N1461	2N1453	-
9618	2N1462	2N1453, B>70	-
9619	2N1463	2N1453, 60V	-
9620	2N1464	2N1453, 60V, B>70	-
9621	2N1465	120V, 3A, 20W	-
9622	2N1466	2N1465	-
9623	2N1468		-
9624	2N1469	40V, 0,1A, 0,25W, >2MHz	BC 212, BC 257, BC 307, BC 557
9625	2N147	2N145, B70	-
9626	2N1470	60V, 3A, 55W	BD 245A, BDV 91, BDX 91, 2N4914...15
9627	2N1471	12V, 0,2A, 0,2W, >3MHz	2N705(A), 2N960...967, 2N2955...57
9628	2N1472	25V, 0,1A, 0,15W, 140MHz	BSW 41, BSY 62...63, 2N706A, 2N708
9629	2N1473	40V, 0,4A, 0,25W, 8MHz	-



9630	2N1474(A)	60/60/60V, 0,1A, 0,25W	-
9631	2N1475	60/60/60V, 0,1A, 0,25W	-
9632	2N1476	100/100/100V, 0,1A, 0,25W	-
9633	2N1477	100/100/100V, 0,1A, 0,25W	-
9634	2N1478	30V, 0,5A, 0,25W, 8MHz	ASY 76...77
9635	2N1479	60V, 1,5A, 5W(Tc25°), B>20	BCX 40, BSS 15...16, 2N5320...21
9636	2N148	16V, 5mA, 0,065W, B35	-
9637	2N1480	2N1479, 100V	BCX 40, BSS 15, BSV 84, 2N5320
9638	2N1481	2N1479, B>35	BCX 40, BSS 15...16, 2N5320...21
9639	2N1482	2N1479, 100V, B>35	BCX 40, BSS 15, BSV 84, 2N5320
9640	2N1483	60V, 3A, 25W(Tc25°), B>20	BD 241A, BD 535, BD 539A, BD 935
9641	2N1484	2N1483, 100V	BD 241C, BD 539C, BD 937, 2SD712
9642	2N1485	2N1483, B>35	BD 241A, BD 535, BD 539A, BD 935
9643	2N1486	2N1483, 100V, B>35	BD 241C, BD 539C, BD 937, 2SD712
9644	2N1487	60V, 6A, 75W, B>15	BD 245A, BDV 91, BDX 91, 2N4914...15
9645	2N1488	2N1487, 100V	BD 245C, BDV 95, BDX 95, 2N5758...60
9646	2N1489	2N1487, B>25	BD 245A, BDV 91, BDX 91, 2N4914...15
9647	2N148A	2N148, 32V	-
9648	2N149	16V, 5mA, 0,065W, B38	-
9649	2N1490	2N1487, 100V, B>25	BD 245C, BDV 95, BDX 95, 2N5758...60
9650	2N1491	30V, 0,1A, 0,5W, 250MHz	BFW 16...17
9651	2N1492	60V, 0,1A, 0,5W, 275MHz	-
9652	2N1493	100V, 0,1A, 0,5W, 300MHz	-
9653	2N1494(A)	20V, 0,5A, 0,75W, >110MHz	2N2096
9654	2N1495(A)	40V, 0,5A, 0,3W, >150MHz	2N2100
9655	2N1496	2N1495, 0,5W	2N2097
9656	2N1499(A)	20V, 0,1A, 0,06W, >100MHz	2N2955...57
9657	2N1499B	30V, 0,1A, 0,075W, >150MHz	2N2955...57
9658	2N149A	2N149, 32V	-
9659	2N150	16V, 5mA, 0,065W, B41	-
9660	2N1500(/18)	30V, 0,1A, 0,075W, >150MHz	ASZ 21, 2N705, 2N960...67, 2N2955...57
9661	2N1501	60V, 3,5A, 34W	-
9662	2N1502	2N1501, 40V	-
9663	2N1504(/10)	80V, 3A, 23W	-
9664	2N1505	50V, 0,5A, PQ1,1W(70MHz)	BFX 55
9665	2N1506	60V, 0,5A, PQ1,3W(70MHz)	BFX 55
9666	2N1506A	2N1506, 80V	BFX 55
9667	2N1507	60V, 1A, 0,6W, >50MHz	BC 140...141, BC 300...302, 2N1990
9668	2N1508	2N1509, 100V	BC 141, BC 300, BSW 39, 2N1990
9669	2N1509	60V, 1A, 1W	BC 140...141, BC 300...302, 2N2218...19
9670	2N150A	2N150, 32V	-
9671	2N1510	75V, 0,02A, 0,075W	-
9672	2N1511	60V, 6A, 75W, B>15	BD 245A, BDV 91, BDX 91, 2N4914...15
9673	2N1512	2N1511, 100V	BD 245C, BDV 95, BDX 95, 2N5758...60
9674	2N1513	2N1511, B>25	BD 245A, BDV 91, BDX 91, 2N4914...15



9675	2N1514	2N1511, 100V, B>25	BD 245C, BDV 95, BDX 95, 2N5758...60
9676	2N1515	20V, 10mA, 0,083W, 70MHz	AF 124...126, AF 200
9677	2N1516	25V, 10mA, 0,083W, 70MHz	AF 124...126, AF 200
9678	2N1517	20V, 10mA, 0,083W, 70MHz	AF 124...126, AF 200
9679	2N1517A	2N1517, 40V, 0,1W	AF 124...126, AF 200
9680	2N1518	50V, 25A, 87,5W	2N2153...55, 2N2157...59
9681	2N1519	2N1518, 80V	2N2155, 2N2159
9682	2N1520	50V, 35A, 87,5W	2N2153...55, 2N2157...59
9683	2N1521	2N1520, 80V	2N2155, 2N2159
9684	2N1522	50V, 50A, 87,5W	2N4049...50, 2N4052...53
9685	2N1523	2N1522, 80V	2N4050, 2N4053
9686	2N1524	24V, 10mA, 0,08W, 33MHz	AF 124...127, AF 200
9687	2N1524/33	2N1524, 0,12W	AF 124...127, AF 200
9688	2N1525	24V, 10mA, 0,08W, 33MHz	AF 124...127, AF 200
9689	2N1526	24V, 10mA, 0,08W, 33MHz	AF 124...127, AF 200
9690	2N1526/33	2N1526, 0,12W	AF 124...127, AF 200
9691	2N1527	24V, 10mA, 0,08W, 33MHz	AF 124...127, AF 200
9692	2N1528	25V, 0,02A, 0,15W, 20MHz	BC 168, BC 183, BC 238, BC 548
9693	2N1529(A)	40V, 5A, 106W, B>20	2N3611...18
9694	2N1530(A)	2N1529, 60V	2N3612, 2N3614, 2N3615...18
9695	2N1531(A)	2N1529, 80V	2N3615...18
9696	2N1532(A)	2N1529, 100V	2N3616, 2N3618
9697	2N1533(A)	2N1529, 120V	-
9698	2N1534(A)	40V, 5A, 106W, B>35	2N3611...18
9699	2N1535(A)	2N1534, 60V	2N3612, 2N3614, 2N3615...18
9700	2N1536(A)	2N1534, 80V	2N3615...18
9701	2N1537(A)	2N1534, 100V	2N3616, 2N3618
9702	2N1538(A)	2N1534, 120V	-
9703	2N1539(A)	40V, 5A, 106W, B>50	2N3611...18
9704	2N1540(A)	2N1539, 60V	2N3612, 2N3614, 2N3615...18
9705	2N1541(A)	2N1539, 80V	2N3615...18
9706	2N1542(A)	2N1539, 100V	2N3616, 2N3618
9707	2N1543(A)	2N1539, 120V	-
9708	2N1544(A)	40V, 5A, 106W, B>75	2N3611...18
9709	2N1545(A)	2N1544, 60V	2N3612, 2N3614, 2N3615...18
9710	2N1546(A)	2N1544, 80V	2N3615...18
9711	2N1547(A)	2N1544, 100V	2N3616, 2N3618
9712	2N1548(A)	2N1544, 120V	-
9713	2N1549(A)	40V, 15A, 106W, B>10	2N1651...53, 2N2285...87
9714	2N155	30V, 3A, 20W	AD 149, AUY 19...20, 2N2137, 2N2142
9715	2N1550(A)	2N1549, 60V	2N1651...53, 2N2285...87
9716	2N1551(A)	2N1549, 80V	2N1652...53, 2N2286...87
9717	2N1552(A)	2N1549, 100V	2N1652...53, 2N2286...87
9718	2N1553(A)	40V, 15A, 106W, B>30	2N1651...53, 2N2285...87
9719	2N1554(A)	2N1553, 60V	2N1651...53, 2N2285...87

9720	2N1555(A)	2N1553, 80V	2N1652...53, 2N2286...87
9721	2N1556(A)	2N1553, 100V	2N1652...53, 2N2286...87
9722	2N1557(A)	40V, 15A, 106W, B>50	2N1651...53, 2N2285...87
9723	2N1558(A)	2N1557, 60V	2N1651...53, 2N2285...87
9724	2N1559(A)	2N1557, 80V	2N1652...53, 2N2286...87
9725	2N1560(A)	2N1557, 100V	2N1652...53, 2N2286...87
9726	2N1561	25V, 0,25A, PQ>0,5W(160MHz)	2N1692
9727	2N1562	25V, 0,25A, PQ>0,4W(160MHz)	2N1693
9728	2N1564	80V, 0,05A, 0,6W, >30MHz	BC 140...141, BC 300...301, 2N1889...90
9729	2N1565	80V, 0,05A, 0,6W, >60MHz	BC 140...141, BC 300...301, 2N1889...90
9730	2N1566	80V, 0,05A, 0,6W, >60MHz	BC 140...141, BC 300...301, 2N1889...90
9731	2N1566A	2N1566, 0,1A, >100MHz	BC 140...141, BC 300...301, 2N1889...90
9732	2N157	60V, 3A, 20W	AUY 19...20, 2N2139...41, 2N2144...46
9733	2N1572	125V, 0,05A, 0,6W, >30MHz	BC 300, 2N1893(A), 2SD755...756(A)
9734	2N1573	125V, 0,05A, 0,6W, >60MHz	BC 300, 2N1893(A), 2SD755...756(A)
9735	2N1574	125V, 0,05A, 0,6W, >60MHz	BC 300, 2N1893(A), 2SD755...756(A)
9736	2N157A	2N157, 90V	AUY 28, AUY 34, 2N2141, 2N2146
9737	2N1585	25V, 0,1A, 0,3W, 400MHz	-
9738	2N1586	15V, 0,025A, 0,125W, >5MHz	BC 168, BC 183, BC 238, BC 548
9739	2N1587	2N1586, 30V	BC 168, BC 183, BC 238, BC 548
9740	2N1588	2N1586, 60V	BC 174, BC 182, BC 190, BC 546
9741	2N1589	15V, 0,025A, 0,125W, >5MHz	BC 168, BC 183, BC 238, BC 548
9742	2N159	50V, 0,01A, 0,08W	ASY 77
9743	2N1590	2N1589, 30V	BC 168, BC 183, BC 238, BC 548
9744	2N1591	2N1589, 60V	BC 174, BC 182, BC 190, BC 546
9745	2N1592	15V, 0,025A, 0,125W, >5MHz	BC 168, BC 183, BC 238, BC 548
9746	2N1593	2N1592, 30V	BC 168, BC 183, BC 238, BC 548
9747	2N1594	2N1592, 60V	BC 174, BC 182, BC 190, BC 546
9748	2N1595	50V, 1A(Tc80°), Igt/Ih<10/5mA	BTX 30/50, T 1N100A, TAG 1-50, S 2600B
9749	2N1595A	50V, 1A(Tc80°C), Igt/Ih<2/5mA	TAG 2-50, MCR 1906-2, TAG 614-100
9750	2N1596	2N1596, 100V	BTX30/100, T1N100A, TAG 1-100, S2600B
9751	2N1596A	2N1595A, 100V	TAG 2-100, MCR 1906-3, TAG 614-100
9752	2N1597	2N1596, 200V	BTX30/200, T1N200A, TAG1-200, S2600B
9753	2N1597A	2N1595A, 200V	TAG 2-200, MCR 1906-4, TAG 614-200
9754	2N1598	2N1596, 300V	BTX30/300, T1N300A, TAG1-300, S2600D
9755	2N1598A	2N1595A, 300V	TAG 2-300, MCR 1906-5, TAG 614-300
9756	2N1599	2N1596, 400V	BTX30/400, T1N400A, TAG1-400, S2600D
9757	2N1599A	2N1595A, 400V	TAG 2-400, MCR 1906-6, TAG 614-400
9758	2N160(A)	40V, 0,025A, 0,15W, B>9	BC 167, BC 182, BC 237, BC 547
9759	2N1605	25V, 0,1A, 0,15W, >4MHz	ASY 28...29, ASY 73...75
9760	2N1605A	2N1605, 40V	-
9761	2N1606	>7,2MHz	-
9762	2N1607	>10MHz	-
9763	2N1608	>25MHz	-
9764	2N1609	80V, 1,5A, 4,5W, B>30	-

9765	2N161(A)	2N160, B>19	BC 167, BC 182, BC 237, BC 547
9766	2N1610	2N1609, B>50	-
9767	2N1611	2N1609, 60V	-
9768	2N1612	2N1609, 60V, B>50	-
9769	2N1613(S)	75V, 0,5A, 0,8W, >60MHz	BC 140...141, BC 300...301, 2N1990
9770	2N1613A,L	2N1613, 1A, 1W	BC 140...141, 2N1990, 2N2102, 2N2405
9771	2N1613B	2N1613, 120V, 1A, 1W	2N2102, 2N2405, 2N3019...20
9772	2N1614	65V, 0,3A, 0,24W, >0,5MHz	ASY 48, ASY 77
9773	2N1615	100V, 0,2A, 0,6W, >2MHz	BC 141, BC 300, 2N1889...90, 2N1893(A)
9774	2N1616(I)	60V, 5A, 60W, >3MHz	2N3487...92
9775	2N1616A	2N1616, 7,5A, 85W	2N3487...92
9776	2N1617(I)	80V, 5A, 60W, >3MHz	2N3487...92
9777	2N1617A	2N1617, 7,5A, 85W	2N3487...92
9778	2N1618(I)	100V, 5A, 60W, >3MHz	2N3488...89, 2N3491...92
9779	2N1618A	2N1618, 7,5A, 85W	2N3488...89, 2N3491...92
9780	2N1619	60V, 5A, 60W, >3MHz	2N3487...92
9781	2N162(A)	2N160, B>19	BC 167, BC 182, BC 237, BC 547
9782	2N1620(I)	100V, 5A, 60W, >3MHz	2N3488...89, 2N3491...92
9783	2N1622	90V, 0,12W, 1MHz	-
9784	2N1623	50V, 0,05A, 0,25W	BC 212, BC 257, BC 307, BC 557
9785	2N1624	25V, 0,15W, >5MHz	ASY 28...29, ASY 73...75
9786	2N163(A)	2N160, B>39	BC 167, BC 182, BC 237, BC 547
9787	2N1631	34V, 10mA, 0,08W, 45MHz	AF 124...126, AF 200
9788	2N1632	2N1631	AF 124...126, AF 200
9789	2N1633	34V, 10mA, 0,08W, 40MHz	AF 124...126, AF 200
9790	2N1634	2N1633	AF 124...126, AF 200
9791	2N1635	34V, 10mA, 0,08W, 45MHz	AF 124...126, AF 200
9792	2N1636	2N1635	AF 124...126, AF 200
9793	2N1637	34V, 10mA, 0,08W, 45MHz	AF 124...126, AF 200
9794	2N1637/33	2N1637, 0,12W	AF 124...126, AF 200
9795	2N1638	35V, 10mA, 0,08W, 40MHz	AF 124...126, AF 200
9796	2N1638/33	2N1638, 0,12W	AF 124...126, AF 200
9797	2N1639	34V, 10mA, 0,08W, 45MHz	AF 124...126, AF 200
9798	2N1639/33	2N1639, 0,12W	AF 124...126, AF 200
9799	2N164(A)	15V, 0,03A, 0,06W, >4MHz	ASY 28...29
9800	2N1640	30V, 0,05A, 0,25W, B>6	2N2946
9801	2N1641	30V, 0,05A, 0,25W, B>10	2N2946
9802	2N1642	30V, 0,05A, 0,25W, B>15	2N2946
9803	2N1643	25V, 0,05A, 0,25W, B>10	2N2946
9804	2N1644(A)	60V, 0,6W, >50MHz	BC 140...141, BC 300...302, 2N3053
9805	2N1645	-/20V, 0,3A, 1W, 600MHz	-
9806	2N1646	15V, 0,05A, 0,15W	AF 106, AF 109R, AF 306
9807	2N1647	80V, 5A, 40W, >3MHz, B>15	2N5002, 2N5004, BD 243B
9808	2N1648	2N1647, 120V	2N5284...85, BD 243C, BD 539D
9809	2N1649	80V, 5A, 40W, >3MHz, B>30	2N5002, 2N5004, 2N5284...85, (BD 243B)

9810	2N165	15V, 0,02A, 0,06W, 5MHz	ASY 28...29
9811	2N1650	2N1647, 120V	2N5284...85, BD 243C, BD 539D
9812	2N1651	60V, 25A, 106W	2N2285...87
9813	2N1652	2N1651, 100V	2N2286...87
9814	2N1653	2N1651, 120V	2N2287
9815	2N1654	100V, 0,05A, 0,25W, B>20	BF 398, 2SA893(A), 2SA970, 2SA1285(A)
9816	2N1655	2N1654, 125V, B>10	BF 398, 2SA893(A), 2SA970, 2SA1285(A)
9817	2N1656	2N1654, 125V, B>20	BF 398, 2SA893(A), 2SA970, 2SA1285(A)
9818	2N1658(/13)	80V, 1A, 15W	-
9819	2N1659(/13)	2N1658, 60V	-
9820	2N166	6V, 0,02A, 0,025W, 5MHz	ASY 28...29
9821	2N1663	20V, 0,1A, 0,15W, -/65ns	BSV 89...92, BSX 92...93, 2N2368...69(A)
9822	2N1664	45V, 0,2A, 0,2W, 5MHz	ASY 48, ASY 76...77
9823	2N1665	15V, 0,05A, 0,15W	AF 109R, AF 139, AF 239(S)
9824	2N1666	80V, 6A, 30W, B>15	AL 102...103, AUY 28, 2N3615...18
9825	2N1667	60V, 6A, 30W, B>35	AL 102...103, AUY 28, 2N3615...18
9826	2N1668	60V, 6A, 30W, B>20	AL 102...103, AUY 28, 2N3615...18
9827	2N1669	80V, 6A, 30W, B>20	AL 102...103, AUY 28, 2N3615...18
9828	2N167(A)	30V, 0,075A, 0,065W	ASY 28
9829	2N1670	100V, 0,12W, >10MHz	ACY 39, 2N2042...43
9830	2N1671A	Ip<25μA, Iv>8mA	-
9831	2N1671A	Ip<25μA, Iv>8mA	-
9832	2N1671AP	2N1671A, Ip<12μA	-
9833	2N1671AP	2N1671A, Ip<12μA	-
9834	2N1671AX	2N1671A	-
9835	2N1671AX	2N1671A	-
9836	2N1671B	2N1671A, Ip<6μA	-
9837	2N1671B	2N1671A, Ip<6μA	-
9838	2N1671BX	2N1671A, Ip<6μA	-
9839	2N1671BX	2N1671A, Ip<6μA	-
9840	2N1671C	2N1671A, Ip<2μA	2N2647
9841	2N1671C	2N1671A, Ip<2μA	2N2647
9842	2N1671CX	2N1671A, Ip<2μA	2N2647
9843	2N1671CX	2N1671A, Ip<2μA	2N2647
9844	2N1672(A)	40V, 0,12W, >2MHz	-
9845	2N1673	35V, 10mA, 0,08W, 5MHz	AF 124...127, AF 200
9846	2N1674	45V, 0,025A, 0,2W, >20MHz	BC 167, BC 182, BC 237, 547
9847	2N1675	100V, 10A, 100W, >120MHz	2SC2527
9848	2N1676	4,5/4,5/4,5V, 0,05A, 0,1W	-
9849	2N1677	4,5/4,5/4,5V, 0,05A, 0,1W	-
9850	2N1678	60V, 0,12W, >25MHz	AF 118
9851	2N1679	100V, 1A, 1W, >50MHz	BC 141, BSW 39, 2N1990, 2SC1069
9852	2N168(A)	15V, 0,02A, 0,065W	ASY 28...29
9853	2N1680	2N1679, 60V	BC 140...141, BSW 27...28, 2SC1069
9854	2N1681	30V, 0,2A, 0,18W, >5MHz	ASY 26, ASY 76...77

9855	2N1682	25V, 0,5W, >200MHz	BFX 96...97, BSY 58, 2N2218...19(A)
9856	2N1683	13V, 0,1A, 0,15W, 80MHz	ASZ 21, 2N705, 2N960...67
9857	2N1684	25V, 0,1A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
9858	2N1685	25V, 0,1A, 0,1W	AC 127, AC 176, AC 187, ASY 28...29
9859	2N1686	30V, 1A, Igt/Ih<1/<5mA	-
9860	2N1687	2N1686, 60V	-
9861	2N1688	2N1686, 100V	-
9862	2N1689	2N1686, 200V	-
9863	2N169(A)	15V, 0,02A, 0,065W	ASY 28...29
9864	2N1692	25V, 0,25A, PQ>0,5W(160MHz)	2N1561
9865	2N1693	25V, 0,25A, PQ>0,4W(160MHz)	2N1562
9866	2N1694	20V, 0,025A, 0,075W, 9MHz	ASY 28...29, ASY 73...75
9867	2N170	6V, 0,02A, 0,025W	ASY 28...29
9868	2N1700	60V, 1A, 5W(Tc25°)	BC 140...141, BSX 45...47, 2N3107...10
9869	2N1701	60V, 2,5A, 25W(Tc25°)	BD 177, BD 239A, BD 437, BD 935
9870	2N1702	60V, 5A, 75W	BD 245A, BDV 91, BDX 91, 2N4914...15
9871	2N1703	2N1702	BD 245A, BDV 91, BDX 91, 2N4914...15
9872	2N1704	45V, 0,05A, 0,5W, 5MHz	BC 140...141, BC 300...302, 2N3053
9873	2N1705	18V, 0,4A, 0,2W, 4MHz	AC 128, AC 152...153, AC 188
9874	2N1706	25V, 0,4A, 0,2W, 3MHz	AC 128, AC 152...153, AC 188
9875	2N1707	30V, 0,4A, 0,2W, 3MHz	AC 128, AC 152...153, AC 188
9876	2N1708	25V, 0,2A, 0,3W, <40/75ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
9877	2N1708A	2N1708, 40V, 0,5A	BSS 10, BSX 26, BSX 39, 2N3261
9878	2N1709	75V, 1,2A, 13W, 100MHz	BD 139, BD 230, 2SC1398, 2SC2690
9879	2N1710	2N1709, 60V	BD 137, BD 228, 2SC1398, 2SC2690
9880	2N1711(S)	75V, 0,5A, 0,8W, >70MHz	BC 140...141, BC 300...301, 2N1990
9881	2N1711A,L	2N1711, 1A, 1W	BC 140...141, 2N1990, 2N2102, 2N2405
9882	2N1711B	2N1711, 120V, 1A, 1W	2N2102, 2N2405, 2N3019...20
9883	2N1713	30V, 10mA, 0,08W, >100MHz	AF 106, AF 109R, AF 306
9884	2N1714	B>20	BC 141, BSS 42...43, BSX 46...47, 2N5320
9885	2N1715	2N1714, 150V	BSS 43, BSW 68
9886	2N1716	B>40	BC 141, BSS 42...43, BSX 46...47, 2N5320
9887	2N1717	2N1714, 150V, B>40	BSS 43, BSW 68
9888	2N1718	2N1714	BD 139, BD 230, BD 237, BD 443
9889	2N1719	2N1715	BD 443A, BD 524, 2SC2481, 2SC2690A
9890	2N172	15V, 5mA, 0,065W	-
9891	2N1720	2N1716	BD 139, BD 230, BD 237, BD 443
9892	2N1721	2N1717	BD 443A, BD 524, 2SC2481, 2SC2690A
9893	2N1724	120V, 5A, 100W, B>20	2N3489, 2N3492
9894	2N1724A	2N1724, 180V	2N5542
9895	2N1725	2N1724, B>50	2N3489, 2N3492
9896	2N1726	20V, 0,05A, 0,06W	AF 124...126, AF 200
9897	2N1727	20V, 0,05A, 0,06W	AF 124...126, AF 200
9898	2N1728	20V, 0,05A, 0,06W	AF 124...126, AF 200
9899	2N1729	25V, 0,3A, 0,15W, <300/600ns	ASY 26...27, ASY 76...77

9900	2N173	60V, 15A, 170W	2N1981, 2N2076, 2N2080, 2N2491...93
9901	2N1730	25V, 0,3A, 0,15W, <300/600ns	ASY 28...29, ASY 73...75
9902	2N1731	30V, 0,3A, 0,15W	ASY 26, ASY 76...77
9903	2N1732	30V, 0,3A, 0,15W	ASY 28, ASY 73...75
9904	2N174(A)	80V, 15A, 150W	2N1982, 2N2075, 2N2079, 2N2492...93
9905	2N1742	20V, 0,05A, 0,06W	AF 139, AF 239(S)
9906	2N1743	20V, 0,05A, 0,06W	AF 139, AF 239(S)
9907	2N1744	20V, 0,05A, 0,06W	AF 139, AF 239(S)
9908	2N1745	20V, 0,05A, 0,06W	AF 106, AF 109R, AF 306
9909	2N1746	20V, 0,05A, 0,06W	AF 106, AF 109R, AF 306
9910	2N1747	20V, 0,05A, 0,06W	AF 106, AF 109R, AF 306
9911	2N1748(A)	25V, 0,05A, 0,06W	AF 106, AF 109R, AF 306
9912	2N1749	40V, 0,01A, 0,075W	AF 106, AF 109R, AF 306
9913	2N175	10V, 2mA, 0,02W	AF 124...127, AF 200
9914	2N1750	14V, 5mA, 0,015W	AF 124...126, AF 200
9915	2N1751	80V, 25A, 106W	2N1652...53, 2N2286...87
9916	2N1752	12V, 0,05A, 0,06W	AF 124...126, AF 200
9917	2N1753	30V, 0,05A, 0,03W	AF 124...126, AF 200
9918	2N1754	13V, 0,1A, 0,05W	ASY 26...27, ASY 76...77
9919	2N176	40V, 3A, 90W	AD 149, AUY 19...20, 2N2143...46
9920	2N1763	40V, 0,05A, 0,3W, <32/58	2N3722...25, 2SC1385
9921	2N1764	2N1763, 20V	2N3722...25, 2SC1385
9922	2N1765	400V, 0,5A, Igt/Ih<10/<5mA	2N1599, BTX 30/400, T 1N400, TAG 1-400
9923	2N1779	25V, 0,1A, 0,1W, 5MHz, B>20	ASY 28...29, ASY 73...75
9924	2N178	30V, 3A, 40W	AD 149, AUY 19...20, 2N2137...46
9925	2N1780	2N1779, 8MHz, B>30	ASY 28...29, ASY 73...75
9926	2N1781	2N1779, 6MHz, B>40	
9927	2N1781	2N1779, 6MHz, B>40	ASY 28...29, ASY 73...75
9928	2N1782	30V, 0,1A, 0,1W, 8MHz, B>30	ASY 26, ASY 76...77
9929	2N1784	2N1782, 12MHz, B>20	ASY 26, ASY 76...77
9930	2N1785	10V, 0,05A, 0,045W, 50MHz	AF 124...126, AF 200
9931	2N1786	10V, 0,05A, 0,045W, 50MHz	AF 124...126, AF 200
9932	2N1787	15V, 0,05A, 0,045W, 50MHz	AF 124...126, AF 200
9933	2N1788	35V, 0,05A, 0,06W, 100MHz	AF 106, AF 109R, AF 306
9934	2N1789	35V, 0,05A, 0,06W, 100MHz	AF 106, AF 109R, AF 306
9935	2N179	-/40V, 1A, 10W(Tc75°)	AD 149, AUY 19...20, 2N2144...46
9936	2N1790	35V, 0,05A, 0,06W, 100MHz	AF 106, AF 109R, AF 306
9937	2N180	30V, 0,15W	ASY 26, ASY 76...77
9938	2N1808	25V, 0,3A, 0,15W, 14MHz	ASY 28...29, ASY 73...75
9939	2N1809	50V, 10A, 250W	-
9940	2N181	2N180	ASY 26, ASY 76...77
9941	2N1810	2N1809, 100V	-
9942	2N1811	2N1809, 150V	-
9943	2N1812	2N1809, 200V	-
9944	2N1813	2N1809, 250V	-



9945	2N1814	2N1809, 300V	-
9946	2N1815	2N1809, 350V	-
9947	2N1816	50V, 15A, 250W	-
9948	2N1817	2N1716, 100V	-
9949	2N1818	2N1716, 150V	-
9950	2N1819	2N1716, 200V	-
9951	2N182	25V, 0,1W, 3,8MHz	ASY 28...29, ASY 73...75
9952	2N1820	2N1716, 250V	-
9953	2N1821	2N1716, 300V	-
9954	2N1822	2N1716, 350V	-
9955	2N1823	50V, 20A, 250W	-
9956	2N1824	2N1823, 100V	-
9957	2N1825	2N1823, 150V	-
9958	2N1826	2N1823, 200V	-
9959	2N1827	2N1823, 250V	-
9960	2N1828	2N1823, 300V	-
9961	2N1829	2N1823, 350V	-
9962	2N183	25V, 0,1W, 7,5MHz	ASY 28...29, ASY 73...75
9963	2N1830	50V, 25A, 250W	-
9964	2N1831	2N1830, 100V	-
9965	2N1832	2N1830, 150V	-
9966	2N1833	2N1830, 200V	-
9967	2N1834	2N1830, 250V	-
9968	2N1835	2N1830, 300V	-
9969	2N1836	2N1830, 350V	-
9970	2N1837(A,B)	80V, 0,5A, 0,6W, <200/500ns	BC 140...141, BC 300...301, 2N2218...19A
9971	2N1838	45V, 0,5A, 0,6W, <200/800ns	BC 140...141, BC 300...301, 2N2218...19
9972	2N1839(A)	45V, 0,5A, 0,6W, <200/600ns	BC 140...141, BC 300...301, 2N2218...19
9973	2N184	25V, 0,1W, 15MHz	ASY 28...29, ASY 73...75
9974	2N1840	25V, 0,5A, 0,6W, <500/1200ns	BC 140...141, BC 300...301, 2N2218...19
9975	2N1841	-/50V, 13W, 78MHz	BD 139, BD 230, BD 379, 2SC1398
9976	2N1842	Igt/Ih<80/40mA	BTW 39/50, BTW 45/200R, TAG 9N400
9977	2N1843	2N1843, 50V	BTW 39/50, BTW 45/200R, TAG 9N400
9978	2N1844	2N1843, 100V	BTW 39/100, BTW 45/200R, TAG 9N400
9979	2N1845	2N1843, 150V	BTW 39/200, BTW 45/200R, TAG 9N400
9980	2N1846	2N1843, 200V	BTW 39/200, BTW 45/200R, TAG 9N400
9981	2N1847	2N1843, 250V	BTW 39/300, BTW 45/300R, TAG 9N400
9982	2N1848	2N1843, 300V	BTW 39/300, BTW 45/300R, TAG 9N400
9983	2N1849	2N1843, 400V	BTW 39/400, BTW 45/400R, TAG 9N400
9984	2N185	20V, 0,15A, 0,15W	AC 125...126, AC 151, ASY 26...27
9985	2N1850	2N1843, 500V	BTW 39/500, BTW 45/500R, TAG 9N600
9986	2N1853(/18)	18V, 0,1A, 0,15W, <800/900ns	ASY 26...27, ASY 76...77
9987	2N1854	18V, 0,1A, 0,15W, >40MHz	ASY 26...27, ASY 76...77
9988	2N186(A)	25V, 0,2A, 0,1W, B24	AC 125...126, AC 151...152
9989	2N1864	20V, 0,05A, 0,06W, 50MHz	AF 124...126, AF 200



9990	2N1865	20V, 0,05A, 0,06W, 180MHz	AF 106, AF 109R, AF 306
9991	2N1866	35V, 0,05A, 0,06W, 180MHz	AF 106, AF 109R, AF 306
9992	2N1867	35V, 0,05A, 0,06W, 180MHz	AF 106, AF 109R, AF 306
9993	2N1868	35V, 0,05A, 0,06W, 400MHz	AF 139, AF 239(S)
9994	2N1869(A)	Igt/Ih<0,2/<5mA	2N2322, 2N6332, TAG 615-100
9995	2N187(A)	2N186, B36	AC 125...126, AC 151...152
9996	2N1870(A)	2N1869, 30V	2N2323, 2N6333, TAG 615-100
9997	2N1871(A)	2N1869, 60V	2N2324, 2N6334, TAG 615-100
9998	2N1872(A)	2N1869, 100V	2N2324, 2N6334, TAG 615-100
9999	2N1873(A)	2N1869, 150V	2N2325, 2N6335, TAG 615-200
10000	2N1874(A)	2N1869, 200V	2N2326, 2N6336, TAG 615-200
10001	2N1875(A)	2N1869, Igt/Ih<0,02/<3mA	2N2322A
10002	2N1876(A)	2N1870, Igt/Ih<0,02/<3mA	2N2323A
10003	2N1877(A)	2N1871, Igt/Ih<0,02/<3mA	2N2324A
10004	2N1878(A)	2N1872, Igt/Ih<0,02/<3mA	2N2324A
10005	2N1879(A)	2N1873, Igt/Ih<0,02/<3mA	2N2325A
10006	2N188(A)	2N186, B54	AC 125...126, AC 151...152
10007	2N1880(A)	2N1874, Igt/Ih<0,02/<3mA	2N2326A
10008	2N1881	Igt/Ih<2,5/<10mA	TAG 2-50, MCR 1906-2, TAG 614-100
10009	2N1882	2N1881, 60V	TAG 2-100, MCR 1906-3, TAG 614-100
10010	2N1883	2N1881, 100V	TAG 2-100, MCR 1906-3, TAG 614-100
10011	2N1884	2N1881, 150V	TAG 2-200, MCR 1906-4, TAG 614-200
10012	2N1885	2N1881, 200V	TAG 2-200, MCR 1906-4, TAG 614-200
10013	2N1889	B>40	BC 141, BC 300, 2N1893(A), 2N1990
10014	2N189	25V, 0,2A, 0,2W, B32	AC 125...126, AC 151...152
10015	2N1890(S)	2N1889, >60MHz, B>100	BC 141, BC 300, 2N1893(A), 2N1990
10016	2N1891	25V, 0,3A, 0,15W, >5MHz	ASY 28...29, ASY 73...75
10017	2N1892	30V, 0,3A, 0,15W, >5MHz	ASY 26...27, ASY 76...77
10018	2N1893(L,S)	120V, 0,5A, 0,8W, 70MHz	BC 300, BSY 55...56, 2N2102, 2N2405
10019	2N1893A	2N1893, 140V, >100MHz	BSS 43, BSW 68, 2N3019...20
10020	2N1894	60V, 2A, 85W	-
10021	2N1895	2N1894, 80V	-
10022	2N1896	60V, 2A, 85W	-
10023	2N1897	2N1896, 80V	-
10024	2N1898	2N1896, 100V	-
10025	2N190	2N189, B42	AC 125...126, AC 151...152
10026	2N1902	2N1899	-
10027	2N1903	2N1899, B>8	-
10028	2N1904	2N1899, B>20	-
10029	2N1905	100V, 6A, 30W(Tc55°)	AL 102...103, AU 108, 2N5324...25
10030	2N1906	2N1905, 130V	AL 102, AU 110, AU 210, 2N5324...25
10031	2N1907(A)	100V, 20A, 60W(Tc70°)	2N1652...53, 2N2286...87
10032	2N1908(A)	2N1907, 130V	2N1653, 2N2287
10033	2N191	2N189, B67	AC 125...126, AC 151...152
10034	2N1917	25/8/25V, 0,05A, 0,25W	-

10035	2N1918	25/8/25V, 0,05A, 0,25W	-
10036	2N1919	40/18/40V, 0,05A, 0,25W	-
10037	2N192	2N189, B90	AC 125...126, AC 151...152
10038	2N1920	40/18/40V, 0,05A, 0,25W	-
10039	2N1921	50/50/50V, 0,05A, 0,25W	-
10040	2N1922	80/80/80V, 0,05A, 0,25W	-
10041	2N1923	85V, 0,06A, 0,75W, 90MHz	BC141, BC300...301, BC546, 2N1889...90
10042	2N1924	B>34	ASY 77
10043	2N1925	2N1924, 2,5MHz, B>53	ASY 77
10044	2N1926	2N1924, 3MHz, B>72	ASY 77
10045	2N193	18V, 0,05A, 0,15W, 3MHz	ASY 28...29, ASY 73...75
10046	2N1936	125/60V, 20A, 200W	2N2817...18, 2N2821...22, 2N5539
10047	2N1937	2N1936, 125/80V	2N2817...18, 2N2821...22, 2N5539
10048	2N194(A)	18V, 0,1A, 0,05W, 3MHz	ASY 28...29, ASY 73...75
10049	2N1940	30V, 0,25A, 3,5W, >350MHz	-
10050	2N1941	45V, 1A, 0,6W, >60MHz	BC 140...141, 2N1990, 2N2102, 2N2405
10051	2N1942	20V, 0,5A, 0,2W, >5MHz	ASY 76...77
10052	2N1943	60V, 0,5A, 0,8W	BC 140...141, BC 300...302, 2N3053
10053	2N1944	B>150	BC 140...141, 2N1990, 2N2101, 2N2405
10054	2N1945	2N1944, 30V	BC 140...141, 2N1990, 2N2101, 2N2405
10055	2N1946	2N1944, 40V	BC 140...141, 2N1990, 2N2101, 2N2405
10056	2N1947	B>500	BC 140...141, 2N1990, 2N2101, 2N2405
10057	2N1948	2N1947, 30V	BC 140...141, 2N1990, 2N2101, 2N2405
10058	2N1949	2N1947, 40V	BC 140...141, 2N1990, 2N2101, 2N2405
10059	2N195	15V, 0,03A, 0,1W	AC 125...126, AC 151
10060	2N1950	B>250	BC 140...141, 2N1990, 2N2101, 2N2405
10061	2N1951	2N1950, 30V	BC 140...141, 2N1990, 2N2101, 2N2405
10062	2N1952	2N1950, 40V	BC 140...141, 2N1990, 2N2101, 2N2405
10063	2N1953	20V, 1A, 0,6W, >40MHz	BC 140...141, 2N1990, 2N2101, 2N2405
10064	2N1954	60/20V, 0,2A, 0,2W	ASY 77
10065	2N1955	60/18V, 0,2A, 0,2W	ASY 77
10066	2N1956	60/16V, 0,2A, 0,2W	ASY 77
10067	2N1957	60/14V, 0,2A, 0,2W	ASY 77
10068	2N1958	B>20	BSS 27, BSV 77, BSV 95, 2N5189
10069	2N1958A	2N1958, 1A, <60/45ns	BSS 27, BSV 77, BSV 95, 2N5189
10070	2N1959	B>40	BSS 27, BSV 77, BSV 95, 2N5189
10071	2N1959A	2N1959, 1A, <60/45ns	BSS 27, BSV 77, BSV 95, 2N5189
10072	2N196	30V, 0,03A, 0,1W	AC 125...126, AC 151
10073	2N1960(/46)	15V, 0,2A, 0,15W, <60/70ns	2N964(A), 2N2635, 2N2955...57
10074	2N1961(/46)	12V, 0,2A, 0,15W, <75/110ns	2N960...2N967, 2N2635, 2N2955...57
10075	2N1962(/46)	40V, 0,2A, 0,4W, <18/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
10076	2N1963(/46)	30V, 0,2A, 0,4W, <20/40ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
10077	2N1964(/46)	60V, 0,5A, 0,4W, <65/45ns	2N4014
10078	2N1965(/46)	60V, 0,5A, 0,4W, <65/45ns	2N4014
10079	2N1969	30V, 0,4A, 0,15W, >10MHz	ASY 76...77

10080	2N197	30V, 0,03A, 0,1W	AC 125...126, AC 151
10081	2N1970	100V, 15A, 170W	2N2493
10082	2N1971	80V, 4A, 38W	AL 102...103, AUY 28, 2N1546...48
10083	2N1972	60V, 1A, 0,8W, >50MHz	BC 140...141, 2N1990, 2N2102, 2N2405
10084	2N1973	100V, 0,8W, >60MHz, B>75	BC 141, BC 300, 2N1889...90, 2N1990
10085	2N1974	100V, 0,8W, >50MHz, B>35	BC 141, BC 300, 2N1889...90, 2N1990
10086	2N1975	100V, 0,8W, >40MHz, B>15	BC 141, BC 300, 2N1889...90, 2N1990
10087	2N1978	60V, 30W(Tc100°), >40MHz	-
10088	2N198	30V, 0,03A, 0,1W	AC 125...126, AC 151
10089	2N1980	50V, 15A, 170W	2N2075...77, 2N2079...81, 2N2490...93
10090	2N1981	70V, 15A, 170W	2N2075...76, 2N2079...80, 2N2492...93
10091	2N1982	90V, 15A, 170W	2N2493
10092	2N1983	50V, 1A, 0,6W, >40MHz, β>80	BC 140...141, 2N1990, 2N2102, 2N2405
10093	2N1984	2N1983, β>40	BC 140...141, 2N1990, 2N2102, 2N2405
10094	2N1985	2N1983, β>20	BC 140...141, 2N1990, 2N2102, 2N2405
10095	2N1986	50V, 1A, 0,6W, >40MHz, B>60	BC 140...141, 2N1990, 2N2102, 2N2405
10096	2N1987	2N1986, B>20	BC 140...141, 2N1990, 2N2102, 2N2405
10097	2N1988	B>35	BC 141, 2N1990, 2N2102, 2N2405
10098	2N1989	2N1988, B>20	BC 141, 2N1990, 2N2102, 2N2405
10099	2N199	30V, 0,03A, 0,1W	AC 125...126, AC 151
10100	2N1990(N,R,W)	2N1990(S), 0,25..0,3W	BC 639, 2N3700...01, 2SD667, 2SD774
10101	2N1990(S)	100V, 1A, 0,6W	
10102	2N1990(S)	100V, 1A, 0,6W	BC 141, 2N1990, 2N2102, 2N2405
10103	2N1991(S)	30V, 0,6A, 0,6W, >40MHz	BC 160...161, BC 303...304, 2N2303
10104	2N1992	-/15V, 0,05A, 0,35W, 430MHz	BSV 89...92, BSX 92...93, 2N2368...69(A)
10105	2N1993	>3MHz	ASY 28, ASY 73...75
10106	2N1994	30V, 0,3A, 0,15W	-
10107	2N1995	2N1994, 25V	-
10108	2N1996	2N1994, 20V	-
10109	2N1997	45V, 0,5A, 0,25W, >3MHz	ASY 77
10110	2N1998	2N1997, 35V	ASY 76...77
10111	2N1999	2N1997, 30V	ASY 76...77
10112	2N200	36V, 0,1A, 0,1W	AC 125...126, AC 151
10113	2N2000	50V, 1A, 0,3A, >2MHz	-
10114	2N2001	2N2000, 30V	-
10115	2N2002	30/5/30V, 0,1A, 0,25W	2N2946
10116	2N2003	30/5/30V, 0,1A, 0,25W	2N2946
10117	2N2004	50/15/50V, 0,1A, 0,25W	2N2946
10118	2N2005	50/15/50V, 0,1A, 0,25W	2N2946
10119	2N2005	50/15/50V, 0,1A, 0,25W	2N2946
10120	2N2006	60/35/60V, 0,1A, 0,25W	-
10121	2N2007	60/35/60V, 0,1A, 0,25W	-
10122	2N2008	175V, 0,5A, 0,8W, >40MHz	BSS 48...49, 2N3439...40
10123	2N2009	Igt/Ih<0,2/<5mA	2N2322, 2N6332, TAG 615-100
10124	2N2010	2N2009, 50V	2N2323, 2N6333, TAG 615-100

10125	2N2011	2N2009, 100V	2N2324, 2N6334, TAG 615-100
10126	2N2012	2N2009, 200V	2N2326, 2N6335, TAG 615-200
10127	2N2013	2N2009, 300V	2N2328, 2N6336, TAG 615-300
10128	2N2014	2N2009, 400V	2N2329, 2N6337, TAG 615-400
10129	2N2015	100V, 10A, 150W	-
10130	2N2016	2N2015, 130V	-
10131	2N2017	80V, 1A, 1W	BC 140...141, 2N1990, 2N2102, 2N2405
10132	2N2018	150V, 2A, 40W, 10MHz	-
10133	2N2019	200V, 2A, 40W, 10MHz	-
10134	2N2020	150V, 2A, 40W, 10MHz	-
10135	2N2021	200V, 2A, 40W, 10MHz	-
10136	2N2022	15V, 0,05A, >250MHz, <60/-ns	ASZ 21, 2N705, 2N964A
10137	2N2033	80V, 3A, 5W(Tc25°)	BSX 64, BUY 41, 2N4238...39, 2SC2214
10138	2N2033S	2N2033, 8,5W	BD 179, BD 241B, BD 441, BD 619
10139	2N2034	80V, 3A, 5W(Tc25°)	BSX 64, BUY 41, 2N4238...39, 2SC2214
10140	2N2034S	2N2034, 8,5W	BD 179, BD 241B, BD 441, BD 619
10141	2N2035	80V, 3A, 14W(Tc25°)	BD 179, BD 241B, BD 441, BD 619
10142	2N2036	80V, 3A, 10W(Tc25°)	BD 179, BD 241B, BD 441, BD 619
10143	2N2038	45V, 0,5A, 0,6W, B>12	BC 140...141, BC 300....302, 2N3053
10144	2N2039	2N3038, 75V	BC 140...141, BC 300....301, 2N1613
10145	2N204	36V, 0,1A, 0,1W, B>50	AC 125...126, AC 151
10146	2N2040	45V, 0,5A, 0,6W, B>30	BC 140...141, BC 300....302, 2N3053
10147	2N2041	2N3040, 75V	BC 140...141, BC 300....301, 2N1613
10148	2N2042(A)	105V, 0,2A, 0,2W, B>20	ACY 39, 2N398
10149	2N2043(A)	105V, 0,2A, 0,2W, B>20	ACY 39, 2N398
10150	2N2048	20V, 0,1A, 0,15W, >150MHz	2N2955...57
10151	2N2048A	2N2048, 30V	2N2955...57
10152	2N2049	75V, 0,5A, 0,8W, >50MHz	BC 140...141, BC 300...302, 2N1711
10153	2N205	2N204, B>15	AC 125...126, AC 151
10154	2N2059	10V, 0,05A, 0,06W, <8/25ns	ASZ 21, 2N705, 2N960...67, 2N2955...57
10155	2N206	30V, 0,05A, 0,075W	AC 125...126, AC 151
10156	2N2061	20V, 3A, 40W	AL 102...103, AUY 28, 2N1529...48
10157	2N2061A	2N2061, 5A, 90W	AL 102...103, AUY 28, 2N1529...48
10158	2N2062	20V, 3A, 40W	AL 102...103, AUY 28, 2N1529...48
10159	2N2062A	2N2062, 5A, 90W	AL 102...103, AUY 28, 2N1529...48
10160	2N2063	40V, 3A, 35W	AL 102...103, AUY 28, 2N1529...48
10161	2N2063A	2N2063, 5A, 90W	AL 102...103, AUY 28, 2N1529...48
10162	2N2064	40V, 3A, 35W	AL 102...103, AUY 28, 2N1529...48
10163	2N2064A	2N2064, 5A, 90W	AL 102...103, AUY 28, 2N1529...48
10164	2N2065	80V, 3A, 35W	AL 102...103, AUY 28, 2N1546...48
10165	2N2065A	2N2065, 5A, 90W	AL 102...103, AUY 28, 2N1546...48
10166	2N2066	80V, 3A, 35W	AL 102...103, AUY 28, 2N1546...48
10167	2N2066A	2N2066, 5A, 90W	AL 102...103, AUY 28, 2N1546...48
10168	2N2069	40V, 12A, 75W	2N1549...60
10169	2N207(A,B)	12/12/12V, 0,02A, 0,068W	ASY 26...27

10170	2N2070	2N2069, 80V	2N1551...52, 2N1555...56, 2N1559...60
10171	2N2071	2N2069	2N1549...60
10172	2N2072	2N2069, 80V	2N1551...52, 2N1555...56, 2N1559...60
10173	2N2075(A)	80V, 15A, 170W, B>20	2N1982, 2N2492...93
10174	2N2076(A)	2N2075, 70V	2N1981...82, 2N2492...93
10175	2N2077(A)	2N2075, 50V	2N1980...82, 2N2490...93
10176	2N2078(A)	2N2075, 40V	2N1980...82, 2N2490...93
10177	2N2079(A)	80V, 15A, 170W, B>35	2N1982, 2N2492...93
10178	2N2080(A)	2N2079, 70V	2N1981...82, 2N2492...93
10179	2N2081(A)	2N2079, 50V	2N1980...82, 2N2490...93
10180	2N2082(A)	2N2079, 40V	2N1980...82, 2N2490...93
10181	2N2083	30V, 10mA, 0,06W, >30MHz	AF 124...126, AF 200
10182	2N2084	40V, 10mA, 0,125W, >100MHz	AF 106, AF 109R, AF 306
10183	2N2085	33V, 0,5A, 0,15W, 8MHz	ASY 28, ASY 73...75
10184	2N2086	B>20	BC 300, 2N1893(A), 2N2102, 2N2405
10185	2N2087	2N2086, B>40	BC 300, 2N1893(A), 2N2102, 2N2405
10186	2N2089	20V, 10mA, 0,1W, >44MHz	AF 124...126, AF 200
10187	2N2090	20V, 10mA, 0,1W, >44MHz	AF 124...126, AF 200
10188	2N2091	20V, 10mA, 0,1W, >44MHz	AF 124...126, AF 200
10189	2N2092	20V, 10mA, 0,1W, >30MHz	AF 124...126, AF 200
10190	2N2093	25V, 10mA, 0,1W, >30MHz	AF 124...126, AF 200
10191	2N2094	60/40V, 0,6W, >200MHz	BFR10, BFX96...97, 2N3722...23, 2SC1385
10192	2N2094A	2N2094, 60/60V	BFR10, BFX96...97, 2N3722...23, 2SC1385
10193	2N2095	30V, 0,3A, >500MHz	-
10194	2N2096	25V, 0,5A, 0,5W, -/130ns	2N1494
10195	2N2097	40V, 0,5A, 0,5W, -/90ns	2N1496
10196	2N2098	30V, 0,3A, 1W, >500MHz	-
10197	2N2099	2N2096, 0,3W	2N1495
10198	2N21(A)	100V, 0,04A, 0,12W	ACY 39, 2N2042...43
10199	2N2100(A)	2N2097, 0,3W	2N1495
10200	2N2101	60V, 3A, 75W	2N3487...92
10201	2N2102(A,L,S)	120V, 1A, 1W, >120MHz	BSS 42...43, BSX 47, 2N2405, 2N3019...20
10202	2N2104	50V, 0,6A, 0,8W, 60MHz, B>25	BC 161, BC 303...304, 2N2303, 2SA606
10203	2N2105	2N2104, B>15	BC 161, BC 303...304, 2N2303, 2SA606
10204	2N2106	60V, 0,5A, 1W, B>12	BC 140...141, BC 300...302, 2N3053
10205	2N2107	2N2106, B>30	BC 140...141, BC 300...302, 2N3053
10206	2N2108	2N2106, B>75	BC 140...141, BC 300...302, 2N3053
10207	2N2109	50V, 30A, 250W(Tc60°)	2N6324...25
10208	2N211	-/10V, 0,05A, 0,05W, 3MHz	ASY 28...29, ASY 73...75
10209	2N2110	2N2109, 100V	2N6324...25
10210	2N2111	2N2109, 150V	2N6324...25
10211	2N2112	2N2109, 200V	2N6324...25
10212	2N2113	2N2109, 250V	2N6324...25
10213	2N2114	2N2109, 300V	2N6324...25
10214	2N2115	2N2109, 350V	2N6324...25

10215	2N2116	50V, 30A, 250W(Tc60°)	2N6324...25
10216	2N2117	2N2116, 100V	2N6324...25
10217	2N2118	2N2116, 150V	2N6324...25
10218	2N2119	2N2116, 200V	2N6324...25
10219	2N212	18V, 0,1A, 0,15W, >4MHz	ASY 28...29, ASY 73...75
10220	2N2120	2N2116, 250V	2N6324...25
10221	2N2121	2N2116, 300V	2N6324...25
10222	2N2122	2N2116, 350V	2N6324...25
10223	2N2123	50V, 30A, 250W(Tc60°)	2N6324...25
10224	2N2124	2N2123, 100V	2N6324...25
10225	2N2125	2N2123, 150V	2N6324...25
10226	2N2126	2N2123, 200V	2N6324...25
10227	2N2127	2N2123, 250V	2N6324...25
10228	2N2128	2N2123, 300V	2N6324...25
10229	2N2129	2N2123, 350V	2N6324...25
10230	2N213(A)	40V, 0,1A, 0,05W	AC 127
10231	2N2130	50V, 30A, 250W(Tc60°)	2N6324...25
10232	2N2131	2N2130, 100V	2N6324...25
10233	2N2132	2N2130, 150V	2N6324...25
10234	2N2133	2N2130, 200V	2N6324...25
10235	2N2134	2N2130, 250V	2N6324...25
10236	2N2135	2N2130, 300V	2N6324...25
10237	2N2136	2N2130, 350V	2N6324...25
10238	2N2137(A)	30V, 3A, 70W, B>30	AL 102...103, AUY 19...20, 2N1529...48
10239	2N2138(A)	2N2137, 45V	AL 102...103, AUY 19...20, 2N1545...48
10240	2N2139(A)	2N2137, 60V	AL 102...103, AUY 19...20, 2N1545...48
10241	2N214(A)	40V, 0,1A, 0,18W	AC 127
10242	2N2140(A)	2N2137, 75V	AL 102...103, AUY 19...20, 2N1546...48
10243	2N2141(A)	2N2137, 90V	AL 102...103, AUY 28, 2N1547...48
10244	2N2142(A)	30V, 3A, 70W, B>50	AL 102...103, AUY 19...20, 2N1529...48
10245	2N2143(A)	2N2142, 45V	AL 102...103, AUY 19...20, 2N1545...48
10246	2N2144(A)	2N2142, 60V	AL 102...103, AUY 19...20, 2N1545...48
10247	2N2145(A)	2N2142, 75V	AL 102...103, AUY 19...20, 2N1546...48
10248	2N2146(A)	2N2142, 90V	AL 102...103, AUY 28, 2N1547...48
10249	2N2147	75V, 5A, 12,5W(Tc81°)	AL 102...103, AUY 22, 2N3617...18
10250	2N2148	2N2147, 60V	AL 102...103, AUY 22, 2N3617...18
10251	2N215	30V, 0,03A, 0,15W	AC 125...126, AC 151
10252	2N2150	125V, 2A, 30W(Tc100°), B>20	2N5284...85
10253	2N2151	2N2150, B>40	2N5284...85
10254	2N2152(A)	45V, 30A, 170W, B>50	-
10255	2N2153(A)	2N2152, 60V	-
10256	2N2154(A)	2N2152, 75V	-
10257	2N2155(A)	2N2152, 90V	-
10258	2N2156(A)	45V, 30A, 170W, B>80	-
10259	2N2157(A)	2N2156, 60V	-



10260	2N2158(A)	2N2156, 75V	-
10261	2N2159(A)	2N2156, 90V	-
10262	2N216	18V, 0,05A, 0,05W, 3MHz	ASY 28...29, ASY 73...75, AC 127
10263	2N2160	2N1671A	-
10264	2N2160	2N1671A	-
10265	2N2161	55V, 0,05A, 0,2W, <350/700ns	BC 167, BC 182, BC 237, BC 547
10266	2N2162	30/-/30V, 0,15W	2N2946
10267	2N2163	15/-/15V, 0,15W	2N2946
10268	2N2164	12/-/12V, 0,15W	2N2946
10269	2N2165	30/-/30V, 0,15W	2N2946
10270	2N2166	15/-/15V, 0,15W	2N2946
10271	2N2167	12/-/12V, 0,15W	2N2946
10272	2N2168	20V, 0,1A, 0,06W, 450MHz	2N2635, 2N2955...57
10273	2N2169	15V, 0,1A, 0,06W, 450MHz	2N705, 2N964(A), 2N2635, 2N2955...57
10274	2N217	35V, 0,15A, 0,165W	AC 125...126, AC 151
10275	2N2170	15V, 0,1A, 0,06W, 350MHz	2N705, 2N964(A), 2N2635, 2N2955...57
10276	2N2171	50V, 0,4A, 0,225W, 7,5MHz	ASY 77, 2N1189...90
10277	2N2172	20V, 0,4A, 0,2W, >5MHz	AC 128, AC 152...153, ASY 77, 2N1189...90
10278	2N2173	25V, 0,75A, 0,24W	AC 128, AC 153
10279	2N2175	6/6/6V, 0,05A, 0,1W, >10MHz	BC 213, BC 258, BC 308, BC 558
10280	2N2176	6/6/6V, 0,05A, 0,1W, >10MHz	BC 213, BC 258, BC 308, BC 558
10281	2N2177	6/6/6V, 0,05A, 0,1W, >8MHz	BC 213, BC 258, BC 308, BC 558
10282	2N2178	6/6/6V, 0,05A, 0,1W, >8MHz	BC 213, BC 258, BC 308, BC 558
10283	2N218	16V, 15mA, 0,035W, 13MHz	AF 124...127, AF 200
10284	2N2180	>60MHz	-
10285	2N2181	25/25/25V, 0,05A, 0,15W	2N2946
10286	2N2182	2N2181	2x 2N2946
10287	2N2183	15/10/15V, 0,05A, 0,15W	2N2946
10288	2N2184	2N2183	2x 2N2946
10289	2N2185	30/30/30V, 0,05A, 0,15W	2N2946
10290	2N2186	2N2185	2x 2N2946
10291	2N2187	2N2185	2x 2N2946
10292	2N2188	40V, 0,03A, 0,125W, >60MHz	AF 124...125, AF 200
10293	2N2189	2N2188, >102MHz	AF 106, AF 109R, AF 306
10294	2N219	16V, 15mA, 0,08W, 13MHz	AF 124...127, AF 200
10295	2N2190	2N2188, 60V	AF 124...125, AF 200
10296	2N2191	2N2188, 60V, >102MHz	AF 106, AF 109R, AF 306
10297	2N2192(A,B)	60V, 1A, 0,8W, >50MHz	BC 140...141, BSW 27...28, 2N3252...53
10298	2N2193(A,AS,B)	80V, 1A, 0,8W, >50MHz	BC 140...141, BSW 39, 2N3444
10299	2N2194(A,B)	60V, 1A, 0,8W, >50MHz	BC 140...141, BSW 27...28, 2N3252...53
10300	2N2195(A,B)	45V, 1A, 0,6W, >50MHz	BC 140...141, BSW 27...28, 2N3252...53
10301	2N2196	80V, 1A, 15W, B>30	BD 139, BD 230, BD 387, BD 829
10302	2N2197	2N2196, B>75	BD 139, BD 230, BD 387, BD 829
10303	2N2198	80V, 0,2A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
10304	2N2199	15V, 0,1A, 0,075W, >120MHz	AFY 18, 2N3323...25



10305	2N220	10V, 2mA, 0,02W	AC 125...126, AC 151
10306	2N2200	15V, 0,1A, 0,075W, >120MHz	AFY 18, 2N3323...25
10307	2N2201	120V, 1A, >10MHz	BD 524, 2SC2690, 2SC3421, 2SD1381...82
10308	2N2202	2N2201	BD 524, 2SC2690, 2SC3421, 2SD1381...82
10309	2N2203	2N2201	BD 524, 2SC2690, 2SC3421, 2SD1381...82
10310	2N2205	25V, 0,2A, 0,3W, 35/60ns, B>20	BSS 11...12, BSX 19...20, 2N2368...69(A)
10311	2N2206	2N2205, B>40	BSS 11...12, BSX 19...20, 2N2368...69(A)
10312	2N2207	70V, 0,05A, 0,26W, >140MHz	AF 118
10313	2N2208	30V, 10mA, 0,12W	AF 124...126, AF 200
10314	2N2209	30V, 0,1A, 0,15W, >6MHz	ASY 26, ASY 76...77
10315	2N2210	100V, 15A, 70W	2N2493
10316	2N2211	80V, 5A, 90W	AL 102...103, AUY 28, 2N1546...48
10317	2N2212	120V, 10A, 102W	AL 100, AUY 38, 2N2290, 2N2293, 2N2527
10318	2N2214	25V, 0,2A, 0,25W, 200MHz	BC 238, BC 548, BSW 41, 2N706A, 2N708
10319	2N2216	150V, 0,25A, 0,8W, 40MHz	2N3636...37, 2N5415, 2SA712
10320	2N2217	B>20	BSW 51...54, BSX 59...61, 2N3444
10321	2N2217A	2N2217, 75V	BSW 51...54, BSX 59...61, 2N3444
10322	2N2218(A)	2N2217, B>40	BSW 51...54, BSX 59...61, 2N3444
10323	2N2219(A)	2N2217, B>100	BSW 51...54, BSX 59...61, 2N3444
10324	2N2220(A)	2N2217, 0,5W	BSS 40...41, BSW 61...64, 2N4014
10325	2N2221(A)	2N2217, 0,5W, B>40	BSS 40...41, BSW 61...64, 2N4014
10326	2N2222(A)	2N2217, 0,5W, B>100	BSS 40...41, BSW 61...64, 2N4014
10327	2N2224	65V, 0,5A, 0,8W, >250MHz	BC 140...141, BC 300...302, 2N2218...19A
10328	2N2225	15V, 0,4A, 0,2W, <100/200ns	-
10329	2N223	-/18V, 0,15A, 0,25W	AC 125...126, AC 151
10330	2N2234	>50MHz	-
10331	2N2235	2N2234, >100MHz	-
10332	2N2236	40V, 0,5A, 0,6W, >50MHz	BC 140...141, BC 300...302, 2N2218...19
10333	2N2237	2N2236, >100MHz	BC 140...141, BC 300...302, 2N2218...19
10334	2N2238	30V, 0,05A, 0,3W, >400MHz	AF 139, AF 239(S), 2N3283...86
10335	2N2239	60V, 0,5A, 2,5MHz	BD 137, BD 167, BD 517, BD 827
10336	2N224	25V, 0,15A, 0,25W	AC 125...126, AC 151...152
10337	2N2240	B>40	BC 140...141, BC 300...302, 2N3053
10338	2N2241	2N2240, B>100	BC 140...141, BC 300...302, 2N3053
10339	2N2242	40V, 0,225A,, 0,36W, <30/50ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
10340	2N2243(A)	120V, 1A, 0,8W, >50MHz	BC 300, 2N1893(A), 2N2102, 2N2405
10341	2N2244	20V, 0,1A, 0,5W, >60MHz, B>5	BC 168, BC 183, BC 238, BC 548
10342	2N2245	2N2244, B>10	BC 168, BC 183, BC 238, BC 548
10343	2N2246	2N2244, B>20	BC 168, BC 183, BC 238, BC 548
10344	2N2247	45V, 0,1A, 0,5W, >60MHz, B>5	BC 167, BC 182, BC 237, BC 547
10345	2N2248	2N2247, B>10	BC 167, BC 182, BC 237, BC 547
10346	2N2249	2N2247, B>20	BC 167, BC 182, BC 237, BC 547
10347	2N225	2N224	AC 125...126, AC 151...152
10348	2N2250	25V, 0,1A, 0,5W, >60MHz, B>5	BC 168, BC 183, BC 238, BC 548
10349	2N2251	2N2250, B>10	BC 168, BC 183, BC 238, BC 548

10350	2N2252	2N2250, B>20	BC 168, BC 183, BC 238, BC 548
10351	2N2253	50V, 0,1A, 0,5W, >60MHz, B>5	BC 167, BC 182, BC 237, BC 547
10352	2N2254	2N2253, B>10	BC 167, BC 182, BC 237, BC 547
10353	2N2255	2N2253, B>20	BC 167, BC 182, BC 237, BC 547
10354	2N2256	7V, 0,1A, 0,3W, <7/7ns, B>20	-
10355	2N2257	2N2256, B>40	-
10356	2N2258	7V, 0,1A, 0,15W, <7/7ns, B>20	-
10357	2N2259	2N2258, B>40	-
10358	2N226	30V, 0,15A, 0,25W	AC 125...126, AC 151...152
10359	2N2266	80V, 5A, 50W	-
10360	2N2267	2N2266, 100V	-
10361	2N2268	2N2266	-
10362	2N2269	2N2267	-
10363	2N227	2N226	AC 125...126, AC 151...152
10364	2N2270(L,S)	60V, 1A, 1W, 250MHz	BC 140...141, 2N1990, 2N2218...19(A)
10365	2N2271	20V, 0,5A, 0,25W	AC 128, AC152...153, AC 188, 2SB405
10366	2N2272	40V, 0,5A, 0,36W, <40/40ns	BSS 10, BSX 26, BSX 39, 2N4013...14
10367	2N2273	25V, 0,1A, 0,15W, >250MHz	AFY 18, 2N3323...25, AF 106, AF 109R
10368	2N2274	25/25/25V, 0,05A, 0,15W	2N2946
10369	2N2275	2N2274	2x 2N2946
10370	2N2276	15/10/10V, 0,05A, 0,15W	2N2945
10371	2N2277	2N2276	2x 2N2945
10372	2N2278	15/15/15V, 0,05A, 0,15W	2N2945
10373	2N2279	2N2278	2x 2N2945
10374	2N228	40V, 0,1A, 0,18W	AC 127
10375	2N2280	10/6/10V, 0,05A, 0,15W	2N2944
10376	2N2281	2N228	2x 2N2944
10377	2N2282	60V, 3A, 5W, >20MHz	-
10378	2N2283	2N2282, 100V	-
10379	2N2284	2N2282, 200V	-
10380	2N2285	60V, 25A, 106W	2N1651...53
10381	2N2286	2N2285, 100V	2N1652...53
10382	2N2287	2N2285, 120V	2N1653
10383	2N2288	40V, 10A, 70W, B>20	AL 100...101, AUY 21, 2N1549...1560
10384	2N2289	2N2288, 80V	AL 100...101, AUY 37, 2N1559...1560
10385	2N229	10V, 0,1A, 0,18W	AC 127, ASY 28...29, ASY 73...75
10386	2N2290	2N2288, 120V	AL 100, AUY 38, 2N2527...28
10387	2N2291	40V, 10A, 70W, B>50	AL 100...101, AUY 21, 2N1549...1560
10388	2N2292	2N2291, 80V	AL 100...101, AUY 37, 2N1559...1560
10389	2N2293	2N2291, 120V	AL 100, AUY 38, 2N2527...28
10390	2N2294	40V, 10A, 60W	AL 100...101, AUY 21, 2N2288...93
10391	2N2295	2N2294, 80V	AL 100...101, AUY 37, 2N2292...93
10392	2N2296	2N2294, 120V	AL 100, AUY 38, 2N2293, 2N2527...28
10393	2N2297(S)	80V, 1A, 0,8W, 10MHz	BC 140...141, BSX 45...47, 2N1990
10394	2N230	60V, 2A, 15W	AUY 18, AUY 35...36

10395	2N2303	50V, 0,5A, 0,6W, >60MHz	BC 161, BC 303...304, BC 361, 2SA606
10396	2N2304	60V, 3A, 25W	BD 241A, BD 535, BD 539A, BD 935
10397	2N2305	60V, 6A, 75W	BD 245A, BDV 91, BDX 91, 2N4914...15
10398	2N2306	75V, 2A, 13W, >175MHz	BD 139, BD 230, BD 379, 2SD1177...78
10399	2N2308	100V, 3A, 25W, >1MHz	BD 241C, BD 539C, BD 937, 2SD712
10400	2N2309	30V, 0,6A, 40MHz	BC 140...141, BC 300...302, 2N3053
10401	2N231	4,5V, 3mA, 9mW, 20MHz	AF 124...127, AF 200
10402	2N2310	B>12	BC 337A, BC 637, BC 639, 2SD667
10403	2N2311	2N2310, 100V	BC 639, BCX 24, 2N3700...01, 2SD667
10404	2N2312	B>30	BC 337A, BC 637, BC 639, 2SD667
10405	2N2313	2N2312, 100V	BC 639, BCX 24, 2N3700...01, 2SD667
10406	2N2314	B>20	BC 337A, BC 637, BC 639, 2SD667
10407	2N2315	B>40	BC 337A, BC 637, BC 639, 2SD667
10408	2N2316	B>40	BCX 22, 2N3700...01, 2SC2235, 2SD667
10409	2N2317	B>40	BC 639, BCX 24, 2N3700...01, 2SD667
10410	2N2318	30V, 0,2A, 0,36W, 45/40ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
10411	2N2319	2N2318, 0,3W	BSS 11...12, BSX 19...20, 2N2368...69(A)
10412	2N232	4,5V, 3mA, 9mW, 30MHz	AF 124...127, AF 200
10413	2N2320	2N2318, 0,6W	BSS 28...29, BSV 69, 2N3724(A), 2SC1385
10414	2N2322	Igt/Ih<0,2/<2mA	2N6332, TAG 615-100, MCR 606-2
10415	2N2322A	2N2322, Igt/Ih<0,02/<2mA	-
10416	2N2323	2N2322, 50V	2N6333, TAG 615-100, MCR 606-2
10417	2N2323A	2N2323, Igt/Ih<0,02/<2mA	-
10418	2N2324	2N2322, 100V	2N6334, TAG 615-100, MCR 606-3
10419	2N2324A	2N2324, Igt/Ih<0,02/<2mA	-
10420	2N2325	2N2322, 150V	2N6335, TAG 615-200, MCR 606-4
10421	2N2325A	2N2325, Igt/Ih<0,02/<2mA	-
10422	2N2326	2N2322, 200V	2N6335, TAG 615-200, MCR 606-4
10423	2N2326A	2N2326, Igt/Ih<0,02/<2mA	-
10424	2N2327	2N2322, 250V	2N6336, TAG 615-300, MCR 606-5
10425	2N2327A	2N2327, Igt/Ih<0,02/<2mA	-
10426	2N2328	2N2322, 300V	2N6336, TAG 615-300, MCR 606-5
10427	2N2328A	2N2328, Igt/Ih<0,02/<2mA	-
10428	2N2329	2N2322, 400V	2N6337, TAG 615-400, MCR 606-6
10429	2N2329A	2N2329, Igt/Ih<0,02/<2mA	-
10430	2N233	10V, 0,1A, 0,15W, >2MHz	AC 127, ASY 28...29, ASY 73...75
10431	2N2330(S)	30V, 0,5A, 0,8W, >100MHz	-
10432	2N2331(S)	2N2330, 0,5W	-
10433	2N2332	15/5/15V, 0,1A, 0,15W	2N2944
10434	2N2333	15/5/15V, 0,1A, 0,15W	2N2944
10435	2N2334	30/15/30V, 0,1A, 0,15W	2N2946
10436	2N2335	30/15/30V, 0,1A, 0,15W	2N2946
10437	2N2336	50/35/50V, 0,1A, 0,15W	2N2946
10438	2N2337	50/35/50V, 0,1A, 0,15W	2N2946
10439	2N2338	60V, 7,5A, 150W	-

10440	2N233A	2N233, 18V	AC 127, ASY 28...29, ASY 73...75
10441	2N234(A)	30V, 3A, 25W	AD 149, AUY 19...20, 2N2137...2146
10442	2N2340	50V, 1A, 15W, B>10	BD 137, BD 167, BD 228, BD 235
10443	2N2341	50V, 1A, 15W, B>40	BD 137, BD 167, BD 228, BD 235
10444	2N2342	2N2340, 100V	BD 139, BD 169, BD 230, BD 237
10445	2N2343	2N2341, 100V	BD 139, BD 169, BD 230, BD 237
10446	2N2344	Igt/Ih<0,02/<1mA	2N2322A
10447	2N2345	2N2344, 50V	2N2323A
10448	2N2346	2N2344, 100V	2N2324A
10449	2N2347	2N2344, 150V	2N2325A
10450	2N2348	2N2344, 200V	2N2326A
10451	2N2349	40V, 0,025A, 0,15W	BF 198...199, BF 224...225, BF 596...597
10452	2N235(A,B)	50V, 3A, 25W	AD 149, AUY 19...20, 2N2144...2146
10453	2N2350(A)	60V, 1A, 0,4W, >50MHz	BC 337A, BC 637, BC 639, 2SD667
10454	2N2351(A)	80V, 1A, 0,4W, >50MHz	BC 639, BCX 24, 2N3700...01, 2SD667
10455	2N2352(A)	60V, 1A, 0,4W, >50MHz	BC 337A, BC 637, BC 639, 2SD667
10456	2N2353(A)	45V, 1A, 0,4W, >50MHz	BC 337(A), BC 635, BC 637, BC 639
10457	2N2354	20V, 0,15A, 0,18W	AC 127, ASY 28...29, ASY 73...75
10458	2N2357	60V, 50A, 170W	2N4280...83, 2N5435...40
10459	2N2358	2N2357, 100V	2N5436, 2N5439
10460	2N2359	2N2357, 120V	2N5437, 2N5440
10461	2N236(A,B)	50V, 3A, 25W	AD 149, AUY 19...20, 2N2144...2146
10462	2N2360	20V, 0,05A, 0,06W	AF 139, AF 239(S), 2N3283...86
10463	2N2361	20V, 0,05A, 0,06W	AF 139, AF 239(S), 2N3283...86
10464	2N2362	20V, 0,05A, 0,06W	AF 139, AF 239(S), 2N3283...86
10465	2N2363	30V, 0,05A, 0,075W	AF 139, AF 239(S), 2N3283...86
10466	2N2364(A)	120V, 1A, 0,4W, >50MHz	BCX 22, 2N3700...01, 2SC2235, 2SD667
10467	2N2368	B>20	BSS 10...11, BSX 19...20, 2N3261, 2SC2901
10468	2N2369(A)	2N2368, B>40	BSS 10...11, BSX 19...20, 2N3261, 2SC2901
10469	2N237	45V, 0,02A, 0,15W	2SB56A
10470	2N2370	15/15/15V, 0,05A, 0,2W	2N2945
10471	2N2371	15/15/15V, 0,05A, 0,2W	2N2945
10472	2N2372	2N2370, 0,15W	2N2945
10473	2N2373	2N2371, 0,15W	2N2945
10474	2N2374	15MHz	ASY 76...77
10475	2N2375	35/35/35V, 0,5A, 0,25W, 9MHz	ASY 76...77
10476	2N2376	2N2375	ASY 76...77
10477	2N2377	25V, 0,05A, 0,15W, >8MHz	BC 213, BC 258, BC 308, BC 558
10478	2N2378	10V, 0,05A, 0,15W, >8MHz	BC 213, BC 258, BC 308, BC 558
10479	2N2379	100V, 15A, 150W	2N2493
10480	2N238	20V, 0,15A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
10481	2N2380(A)	80V, 0,5A, 0,6W, >100MHz	BC 140...141, BC 300...301, 2N2218...19A
10482	2N2381	30V, 0,5A, 0,3W, >300MHz	-
10483	2N2382	2N2381, 45V	-
10484	2N2384	80V, 5A, 85W	2N3487...92, BD 243B, BD 539B, BD 951

10485	2N2386(A)	20V, Idss0,9..15mA, Up<8V	2N2497...2500
10486	2N2387	B>40	BC 382...384, BC 413...414, BC 550
10487	2N2388	2N2387, B>100	BC 382...384, BC 413...414, BC 550
10488	2N2389	B>40	BC 639, 2SD667, 2SD774, 2SD1226
10489	2N2390	2N2389, >70MHz, B>100	BC 639, 2SD667, 2SD774, 2SD1226
10490	2N2391	B>15	BC 213, BC 258, BC 308, BC 558
10491	2N2392	2N2391, B>30	BC 213, BC 258, BC 308, BC 558
10492	2N2393	B>20	BC 327(A), BC 638, BC 640, 2SB647
10493	2N2394	2N2393, >60MHz, B>30	BC 327(A), BC 638, BC 640, 2SB647
10494	2N2395	B>20	BC 337A, BC 637, BC 639, 2SD667
10495	2N2396	2N2395, >50MHz, B>40	BC 337A, BC 637, BC 639, 2SD667
10496	2N2397	35V, 0,2A, 0,3W, <40/70ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
10497	2N2398	20V, 0,05A, 0,06W	AF 139, AF 239(S), 2N3283...86
10498	2N2399	20V, 0,05A, 0,06W	AF 139, AF 239(S), 2N3283...86
10499	2N240	6V, 15mA, 0,03W, >30MHz	AF 124...127, AF 200
10500	2N2400	12V, 0,1A, 0,15W, >150MHz	2N960...967, 2N2635, 2N2955...57
10501	2N2401	15V, 0,1A, 0,15W, >200MHz	2N705(A), 2N964(A), 2N2635, 2N2955...57
10502	2N2402	18V, 0,1A, 0,15W, >250MHz	2N2635, 2N2955...57
10503	2N2403	60V, 1A, 150MHz, B>20	BSW 27...28, BSX 59...61, 2N3252...53
10504	2N2404	2N2403, B>40	BSW 27...28, BSX 59...61, 2N3252...53
10505	2N2405(L,S)	140V, 1A, 1W, >120MHz	2N2102, 2N3019...3020
10506	2N241(A)	25V, 0,2A, 0,1..0,2W	AC 125...126, AC 151, 2SB54, 2SB56
10507	2N2410	60V, 0,8A, 0,8W, 35/40ns	BSS 27, BSV 77, BSV 95, 2N5189
10508	2N2410/51	2N2410, 0,3W	BSS 27, BSV 77, BSV 95, 2N5189
10509	2N2411	25V, 0,1A, 0,3W, 15/74ns, B>20	BSX 36
10510	2N2412	2N2411, B>40	BSX 36
10511	2N2413	40V, 0,2A, 0,3W, >300MHz	BSS 10...11, BSX 19...20, 2N2368...69(A)
10512	2N2415	15V, 0,02A, 0,075W, >550MHz	AF 139, AF 239(S), 2N3283...86
10513	2N2416	15V, 0,02A, 0,075W, >400MHz	AF 139, AF 239(S), 2N3283...86
10514	2N2417	2N489, 0,3W	2N489
10515	2N2418	2N490, 0,3W	2N490
10516	2N2419	2N491, 0,3W	2N491
10517	2N242	45, 5A, 106W	AL 102...103, AUY 28, 2N1539...48
10518	2N2420	2N492, 0,3W	2N492
10519	2N2421	2N493, 0,3W	2N493
10520	2N2422	2N494, 0,3W	2N494
10521	2N2423	100V, 5A, 90W	AL 102...103, AUY 37, 2N1547...48
10522	2N2424	<300/500ns	BC 212, BC 307, BC 557, BCY 77, BCY 79
10523	2N2425	<500/725ns	BC 212, BC 307, BC 557, BCY 77, BCY 79
10524	2N2426	40V, 0,2A, 0,15W, >25MHz	-
10525	2N2427	40V, 0,05A, 0,5W, 50MHz	BC 167, BC 182, BC 237, BC 547
10526	2N2428	32V, 0,1A, 0,165W	AC 125...126, AC 151, 2SB54, 2SB56
10527	2N2429	32V, 0,1A, 0,165W	AC 125...126, AC 151, 2SB54, 2SB56
10528	2N243	60V, 0,06A, 0,75W, β>9	BC 140...141, BC 300...302, BC 637
10529	2N2430	32V, 0,5A, 0,28W	AC 127, AC 176, AC 187

10530	2N2431(MP)	32V, 0,5A, 0,225W	AC 128, AC 152...153, 2SB324, 2SB415
10531	2N2432	30V, 0,1A, 0,3W, >20MHz	2N4138
10532	2N2432A	2N2432, 45V	2N4138
10533	2N2433	75V, 1A, 0,5W, >80MHz, B>40	BC 639, BCX 24, 2N3700...01, 2SD667
10534	2N2434	B>100	BC 639, BCX 24, 2N3700...01, 2SD667
10535	2N2435	B>40	BCX 22, 2N3700...01, 2SC2235, 2SD667
10536	2N2436	B>100	BCX 22, 2N3700...01, 2SC2235, 2SD667
10537	2N2437	B>15	BC 639, BCX 24, 2N3700...01, 2SD667
10538	2N2438	2N2438, >80MHz, B>35	BC 639, BCX 24, 2N3700...01, 2SD667
10539	2N2439	2N2438, >90MHz, B>75	BC 639, BCX 24, 2N3700...01, 2SD667
10540	2N244	2N243, B>25	BC 140...141, BC 300...302, BC 637
10541	2N2440	120V, 0,5A, 0,8W, >90MHz	BC 300, 2N2102, 2N2405, 2N3019...3020
10542	2N2443	120V, 0,8W, >50MHz	BC 300, 2N2102, 2N2405, 2N3019...3020
10543	2N2444	80V, 10A, 85W	AL 100...101, AUY 37, 2N2292...93
10544	2N2445	100V, 15A, 90W	2N1552, 2N1556, 2N1560
10545	2N2446	60V, 7A, 90W	AL 102...103, AUY 22, 2N3615...18
10546	2N2447	45V, 0,1A, 0,075W	2N1191...94, 2SB56A
10547	2N2449	35V, 0,1A, 0,075W	AC 125...125, AC 151, 2SB54, 2SB56
10548	2N2451	>80MHz	-
10549	2N2455	/65ns	-
10550	2N2456	<-/65ns	-
10551	2N2458	Up<5V	
10552	2N2459	B>40	BSS 38, BSX 21, 2SC2240, 2SC2459
10553	2N2460	2N2459, >120MHz, B>70	BSS 38, BSX 21, 2SC2240, 2SC2459
10554	2N2461	2N2459, >140MHz, B>115	BSS 38, BSX 21, 2SC2240, 2SC2459
10555	2N2462	2N2459, >160MHz, B>160	BSS 38, BSX 21, 2SC2240, 2SC2459
10556	2N2463	B>40	BSS 38, BSX 21, 2SC2240, 2SC2459
10557	2N2464	2N2463, >120MHz, B>70	BSS 38, BSX 21, 2SC2240, 2SC2459
10558	2N2465	2N2463, >140MHz, B>115	BSS 38, BSX 21, 2SC2240, 2SC2459
10559	2N2466	2N2463, >160MHz, B>160	BSS 38, BSX 21, 2SC2240, 2SC2459
10560	2N2467	60V, 3A, >20MHz	-
10561	2N2468	2N2467, 100V	-
10562	2N2469	2N2467, 200V	-
10563	2N247	40V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
10564	2N247/33	2N247, 0,12W	AF 124...127, AF 200
10565	2N2472	120V, 1A, >10MHz	BD 524, 2SC2384, 2SC2481, 2SD1381...82
10566	2N2473	2N2472	BD 524, 2SC2384, 2SC2481, 2SD1381...82
10567	2N2474	30V, 0,05A, 0,25W	-
10568	2N2475	15V, 0,1A, 0,3W, <20/15ns	BSV 89...92, BSX 44, 2N2368...69(A)
10569	2N2476	60V, 1A, 0,6W, <25/45ns, B>40	BSS 27, BSV 77, BSV 95, 2N5189
10570	2N2477	2N2476, B>20	BSS 27, BSV 77, BSV 95, 2N5189
10571	2N2478	120V, 0,5A, 0,6W, >200MHz	BC 300, 2N2102, 2N2405, 2N3019...20
10572	2N2479	80V, 0,5A, 0,6W, >150MHz	BC 140...141, BC 300...301, BSW 39
10573	2N248	25V, 5mA, 0,03W, 50MHz	AF 124...127, AF 200
10574	2N2481	<40/55ns	BSS 10...11, BSX 19...20, 2N2368...69(A)



10575	2N2482	20V, 0,1A, 0,15W, >600MHz	-
10576	2N2483	B>40	2N3117, 2SC1775(A), 2SC2240, 2SC2390
10577	2N2483	B>40	2N3117, 2SC1775(A), 2SC2240, 2SC2390
10578	2N2484(A)	2N2483, B>100	2N3117, 2SC1775(A), 2SC2240, 2SC2390
10579	2N2484(A)	2N2483, B>100	2N3117, 2SC1775(A), 2SC2240, 2SC2390
10580	2N2485	>100MHz	BUX 49, BUY 41, 2SC1860
10581	2N2485	>100MHz	BUX 49, BUY 41, 2SC1860
10582	2N2486	2N2485, 140V	BUX 49, BUY 41, 2SC1860
10583	2N2486	2N2485, 140V	BUX 49, BUY 41, 2SC1860
10584	2N2487	15V, 0,1A, 0,06W, >360MHz	2N3283...86
10585	2N2487	15V, 0,1A, 0,06W, >360MHz	2N3283...86
10586	2N2488	15V, 0,1A, 0,06W, >360MHz	2N3283...86
10587	2N2488	15V, 0,1A, 0,06W, >360MHz	2N3283...86
10588	2N2489	20V, 0,1A, 0,06W, >300MHz	2N3283...86
10589	2N2489	20V, 0,1A, 0,06W, >300MHz	2N3283...86
10590	2N249	25V, 0,2A, 0,35W	AC 125...126, AC 151
10591	2N2490	70V, 15A, 170W, B>20	2N1981...82, 2N2075...76, 2N2079...80
10592	2N2491	60V, 15A, 170W, B>35	2N1981...82, 2N2075...76, 2N2079...80
10593	2N2492	80V, 15A, 170W, B>25	2N1982, 2N2075, 2N2079
10594	2N2493	100V, 15A, 170W, B>25	-
10595	2N2494	40V, 10mA, 0,125W, >135MHz	AF 106, AF 109R, AF 306, 2N3323...25
10596	2N2495	2N2494	AF 106, AF 109R, AF 306, 2N3323...25
10597	2N2496	2N2494, 0,1W	AF 106, AF 109R, AF 306, 2N3323...25
10598	2N2497	20V, Idss>1mA, Up<5V	2N2608, 2N3329, 2N5460
10599	2N2497	20V, Idss>1mA, Up<5V	2N2608, 2N3329, 2N5460
10600	2N2498	20V, Idss>2mA, Up<6V	2N2609, 2N3330, 2N5461
10601	2N2498	20V, Idss>2mA, Up<6V	2N2609, 2N3330, 2N5461
10602	2N2499	20V, Idss>5mA, Up<8V	BF 320B, 2N3331, 2N5462
10603	2N2499	20V, Idss>5mA, Up<8V	BF 320B, 2N3331, 2N5462
10604	2N250	30V, 3A, 25W	AD 149, AUY 10...20, 2N2137...46
10605	2N2500	20V, Idss>1mA, Up<6V	2N2608, 2N3332, 2N5460
10606	2N2500	20V, Idss>1mA, Up<6V	2N2608, 2N3332, 2N5460
10607	2N2501	40V, 0,36W, >350MHz	BSS 10...11, BSX 19...20, 2N2368...69(A)
10608	2N2501	40V, 0,36W, >350MHz	BSS 10...11, BSX 19...20, 2N2368...69(A)
10609	2N2509	125V, 0,2A, 0,36W, >45MHz	BFR 86, 2SC2240, 2SC2459, 2SC3245(A)
10610	2N2509	125V, 0,2A, 0,36W, >45MHz	BFR 86, 2SC2240, 2SC2459, 2SC3245(A)
10611	2N250A	40V, 7A, 90W	AL 102...103, AUY 21...22, 2N3611...18
10612	2N251	60V, 3A, 25W	AL 102...103, AUY 19...20, 2N2144...46
10613	2N2510	100V, 0,2A, 0,36W, >45MHz	BFR 86, 2SC2240, 2SC2459, 2SC3245(A)
10614	2N2510	100V, 0,2A, 0,36W, >45MHz	BFR 86, 2SC2240, 2SC2459, 2SC3245(A)
10615	2N2511	80V, 0,2A, 0,36W, >45MHz	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10616	2N2511	80V, 0,2A, 0,36W, >45MHz	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10617	2N2512	70V, 0,03A, 0,15W, >140MHz	AF 118
10618	2N2514	80V, 0,1A, 0,4W, 30MHz, B>15	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10619	2N2514	80V, 0,1A, 0,4W, 30MHz, B>15	BC 546, 2SC2240, 2SC2459, 2SC3245(A)



10620	2N2515	2N2514, 60MHz, B>30	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10621	2N2515	2N2514, 60MHz, B>30	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10622	2N2516	2N2514, 100MHz, B>60	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10623	2N2516	2N2514, 100MHz, B>60	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
10624	2N2517	B>15	BSS 38, BSX 21, 2SC2240, 2SC2459
10625	2N2517	B>15	BSS 38, BSX 21, 2SC2240, 2SC2459
10626	2N2518	2N2517, 60MHz, B>30	BSS 38, BSX 21, 2SC2240, 2SC2459
10627	2N2518	2N2517, 60MHz, B>30	BSS 38, BSX 21, 2SC2240, 2SC2459
10628	2N2519	2N2517, 100MHz, B>60	BSS 38, BSX 21, 2SC2240, 2SC2459
10629	2N2519	2N2517, 100MHz, B>60	BSS 38, BSX 21, 2SC2240, 2SC2459
10630	2N251A	60V, 7A, 90W	AL 102...103, AUY 21...22, 2N3614...18
10631	2N252	-/16V, 5mA, 0,03W	AF 124...127, AF 200
10632	2N2520	B>18	BC 174, BC 182, BC 190, BC 546
10633	2N2520	B>18	BC 174, BC 182, BC 190, BC 546
10634	2N2521	2N2520, B>36	BC 174, BC 182, BC 190, BC 546
10635	2N2521	2N2520, B>36	BC 174, BC 182, BC 190, BC 546
10636	2N2522	2N2520, B>76	BC 174, BC 182, BC 190, BC 546
10637	2N2522	2N2520, B>76	BC 174, BC 182, BC 190, BC 546
10638	2N2523	>70MHz, B>60	2N2483...84, 2N3117, 2SC2240, 2SC2390
10639	2N2523	>70MHz, B>60	2N2483...84, 2N3117, 2SC2240, 2SC2390
10640	2N2524	2N2523, B>150	2N2483...84, 2N3117, 2SC2240, 2SC2390
10641	2N2524	2N2523, B>150	2N2483...84, 2N3117, 2SC2240, 2SC2390
10642	2N2525	100V, 1A, 16W, >56MHz	-
10643	2N2526	80V, 10A, 85W	AL 100...101, 2N2289...90, 2N2292...93
10644	2N2527	2N2526, 120V	AL 100, 2N2290, 2N2293
10645	2N2528	2N2526, 160V	-
10646	2N2529	B>10	BC 167, BC 182, BC 237, BC 547
10647	2N2529	B>10	BC 167, BC 182, BC 237, BC 547
10648	2N253	12V, 5mA, 0,065W	-
10649	2N2530	2N2529, >10MHz, B>12	BC 167, BC 182, BC 237, BC 547
10650	2N2530	2N2529, >10MHz, B>12	BC 167, BC 182, BC 237, BC 547
10651	2N2531	2N2529, >12MHz, B>20	BC 167, BC 182, BC 237, BC 547
10652	2N2531	2N2529, >12MHz, B>20	BC 167, BC 182, BC 237, BC 547
10653	2N2532	2N2529, >16MHz, B>45	BC 167, BC 182, BC 237, BC 547
10654	2N2532	2N2529, >16MHz, B>45	BC 167, BC 182, BC 237, BC 547
10655	2N2533	2N2529, >10MHz, B>20	BC 167, BC 182, BC 237, BC 547
10656	2N2533	2N2529, >10MHz, B>20	BC 167, BC 182, BC 237, BC 547
10657	2N2534	2N2529, >20MHz, B>45	BC 167, BC 182, BC 237, BC 547
10658	2N2534	2N2529, >20MHz, B>45	BC 167, BC 182, BC 237, BC 547
10659	2N2535	60V, 3A, 10W	-
10660	2N2536	2N2535, 80V	-
10661	2N2537	60V, 0,8A, 0,8W, <40/40, B>50	BSS 27, BSV 77, BSV 95, 2N5189
10662	2N2537	60V, 0,8A, 0,8W, <40/40, B>50	BSS 27, BSV 77, BSV 95, 2N5189
10663	2N2538	2N2537, B>100	BSS 27, BSV 77, BSV 95, 2N5189
10664	2N2538	2N2537, B>100	BSS 27, BSV 77, BSV 95, 2N5189

10665	2N2539	2N2537, 0,5W	2N4014
10666	2N2539	2N2537, 0,5W	2N4014
10667	2N254	20V, 5mA, 0,065W	-
10668	2N2540	2N2537, 0,5W, B>100	2N4014
10669	2N2541	30V, 1A, 0,215W, >10MHz	-
10670	2N255	15V, 3A, 20W	AD 149, AUY 19...20, 2N2137...46
10671	2N2551	150V, 1A, 0,4W	BFT 28, 2N3636...37, 2N5415
10672	2N2552	2N1038	2N1038
10673	2N2553	2N1039	2N1039
10674	2N2554	2N1040	2N1040
10675	2N2555	2N1041	2N1041
10676	2N2556	2N1038	2N1038
10677	2N2557	2N1039	2N1039
10678	2N2558	2N1040	2N1040
10679	2N2559	2N1041	2N1041
10680	2N255A	2N255, 5A	AL 102...103, AUY 21...22, 2N1539...48
10681	2N256	30V, 3A, 20W	AD 149, AUY 19...20, 2N2137...46
10682	2N2560	2N1042	2N1042
10683	2N2561	2N1043	2N1043
10684	2N2562	2N1044	2N1044
10685	2N2563	2N1045	2N1045
10686	2N2564(/5)	2N1042	2N1042
10687	2N2565(/5)	2N1043	2N1043
10688	2N2566(/5)	2N1044	2N1044
10689	2N2567(/5)	2N1045	2N1045
10690	2N2568	32V, 0,1A, >1400MHz	-
10691	2N2569	20V, 0,1A, 0,3W, >100MHz	2N2432, 2N4138
10692	2N256A	2N256, 5A	AL 102...103, AUY 21...22, 2N1539...48
10693	2N257	40V, 3A, 30W	AD 149, AUY 19...20, 2N2143.46
10694	2N2570	20V, 0,1A, 0,3W, >100MHz	2N2432, 2N4138
10695	2N2571	20V, 0,5A, 0,3W, >100MHz	-
10696	2N2572	20V, 0,5A, 0,3W, >100MHz	-
10697	2N2573	Igt/Ih<40/10mA	2N3668
10698	2N2574	2N2573, 50V	2N3668
10699	2N2575	2N2573, 100V	2N3668
10700	2N2576	2N2573, 200V	2N3669
10701	2N2577	2N2573, 300V	2N3670
10702	2N2578	2N2573, 400V	2N3670
10703	2N2579	2N2573, 500V	-
10704	2N258	30V, 0,05A, 0,25W, $\beta$ >15	BC 213, BC 258, BC 308, BC 558
10705	2N2580(M)	400/400V, 10A, 150W, B>10	-
10706	2N2581	2N2580, B>25	-
10707	2N2582	500/500V, 10A, 150W, B>10	-
10708	2N2583	2N2582, B>25	-
10709	2N2584	600/600V, 10A, 150W, B>10	-

10710	2N2585	2N2584, B>25	-
10711	2N2586	60V, 0,03A, 0,3W, 63MHz	2N2483...84, 2N3117, 2SC2240, 2SC2390
10712	2N2587	30V, 0,1A, 0,15W, >320MHz	2N3283...86
10713	2N2588	40V, 0,03A, 0,15W, >75MHz	AF 106, AF 109R, AF 306
10714	2N2589	150/150V, 7A, 85W	2N5542
10715	2N259	2N258, B>32	BC 213, BC 258, BC 308, BC 558
10716	2N2590	B>40	BSS 68, BSV 68, 2SA970, 2SB715...16
10717	2N2591	2N2590, >70MHz, B>70	BSS 68, BSV 68, 2SA970, 2SB715...16
10718	2N2592	2N2590, >90MHz, B>115	BSS 68, BSV 68, 2SA970, 2SB715...16
10719	2N2593	2N2590, >110MHz, B>160	BSS 68, BSV 68, 2SA970, 2SB715...16
10720	2N2594	80V, 1A, 1W, >40MHz	BC 140...141, 2N1990, 2N2102, 2N2405
10721	2N2595	B>15	BSS 68, BSV 68, 2SA970, 2SB715...16
10722	2N2596	2N2595, >40MHz, B>30	BSS 68, BSV 68, 2SA970, 2SB715...16
10723	2N2597	2N2595, >60MHz, B>60	BSS 68, BSV 68, 2SA970, 2SB715...16
10724	2N2598	B>20	BF 398, 2SA970, 2SA1049, 2SB716(A)
10725	2N2599(A)	2N2598, >40MHz, B>40	BF 398, 2SA970, 2SA1049, 2SB716(A)
10726	2N260	10V, 0,05A, 0,2W	BC 213, BC 258, BC 308, BC 558
10727	2N2600(A)	2N2598, >60MHz, B>60	BF 398, 2SA970, 2SA1049, 2SB716(A)
10728	2N2601	B>18	BSS 68, BSV 68, 2SA970, 2SB715...716
10729	2N2602	2N2601, >40MHz, B>36	BSS 68, BSV 68, 2SA970, 2SB715...716
10730	2N2603	2N2601, >60MHz, B>76	BSS 68, BSV 68, 2SA970, 2SB715...716
10731	2N2604	60V, 0,03A, 0,4W, >30MHz	2SA970, 2SA1016, 2SA1038...39, 2SA1136
10732	2N2605(A)	60V, 0,03A, 0,4W, >30MHz	2SA970, 2SA1016, 2SA1038...39, 2SA1136
10733	2N2606	30V, Idss>0,1mA, Up<4V	2N5797
10734	2N2607	30V, Idss>0,3mA, Up<4V	2N5020
10735	2N2608	30V, Idss>0,9mA, Up<4V	2N5460
10736	2N2609	30V, Idss>2mA, Up<4V	2N5461
10737	2N260A	2N260, 30V	BC 213, BC 258, BC 308, BC 558
10738	2N261	75V, 0,05A, 0,2W	BC 212, BC 256, BC 266, BC 556
10739	2N2610	45V, 0,025A, 0,15W	BC 167, BC 182, BC 237, BC 547
10740	2N2611	120V, 1A, >4MHz	BD 424, BD 524, 2SC2384, 2SC2481
10741	2N2612	65V, 15A, 75W	2N1551...52, 2N1555...56, 2N1559...60
10742	2N2613	30V, 0,05A, 0,12W	AC 125...126, AC 151, 2SB54, 2SB56
10743	2N2614	40V, 0,05A, 0,12W	2N1191...94, 2SB56A
10744	2N2615	30V, 0,3W, >500MHz	BF 224...225, BFR 37, BFW 30, BFX 73
10745	2N2616	30V, 0,05A, 0,3W, >600MHz	BF 224...225, BFR 37, BFW 30, BFX 73
10746	2N2617	25V, 0,1A, 0,25W	BC 168, BC 183, BC 238, BC 548
10747	2N2618	60V, 0,75A, 0,6W, >200MHz	BC 140...141, BC 300...302, 2N2218...19
10748	2N2618/46	2N2618, 0,4W	BC 337A, BC 637, BC 639, 2SD667
10749	2N262	10V, 0,05A, 0,2W	BC 213, BC 258, BC 308, BC 558
10750	2N2620	50V, Idss<50mA, Up<20V	-
10751	2N2621	B>15	ASY 26...27, 2N1309
10752	2N2622	2N2621, 24V, >15MHz, B>15	ASY 26...27, 2N1309
10753	2N2623	2N2621, 32V, >16MHz, B>20	ASY 26, 2N1309
10754	2N2624	B>15	ASY 26...27, 2N1309

10755	2N2625	2N2624, 24V, >15MHz, B>15	ASY 26...27, 2N1309
10756	2N2626	2N2624, 32V, >16MHz, B>20	ASY 26, 2N1309
10757	2N2627	B>15	ASY 26...27, 2N1309
10758	2N2628	2N2627, 24V, >15MHz, B>15	ASY 26...27, 2N1309
10759	2N2629	2N2627, 32V, >16MHz, B>20	ASY 26, 2N1309
10760	2N262A	2N262, 30V	BC 213, BC 258, BC 308, BC 558
10761	2N263	45V, 0,02A, 0,15W, B>45	BC 167, BC 182, BC 237, BC 547
10762	2N2630	18V, 0,1A, 0,3W, >300MHz	-
10763	2N2631	80V, 1,5A, PQ>3W(150MHz)	BFS 23
10764	2N2632	90/60V, 5A, 40W, >20MHz	2N5002, 2N5004, 2N5284...85
10765	2N2633	2N2632, 120/80V	2N5284...85
10766	2N2634	2N2632, 150/100V	2N5284...85
10767	2N2635	30V, 0,1A, 0,15W, >150MHz	2N2955...57
10768	2N2636	100V, 25A, 100W	2N1652...53, 2N2286...87
10769	2N2637	100V, 25A, 100W	2N1652...53, 2N2286...87
10770	2N2638	100V, 25A, 100W	2N1652...53, 2N2286...87
10771	2N264	2N263, B>20	BC 167, BC 182, BC 237, BC 547
10772	2N2645	75V, 0,5A, 0,5W, >50MHz	BC 639, BCX 24, 2N3700...01, 2SD667
10773	2N2646	Ip<5μA, Iv>4mA	
10774	2N2646P	Ip<12μA, Iv>4mA	-
10775	2N2647	2N2646, Ip<2μA, Iv>8mA	-
10776	2N2648	30V, 1A, 0,3W, >10MHz	-
10777	2N2649	65V, 1A, 0,7W, >100MHz	-
10778	2N265	25V, 0,05A, 0,075W	AC 125...126, AC 151, ASY 26...27
10779	2N2650	2N2649, 140V	-
10780	2N2651	40V, 0,5A, 0,36W, >350MHz	BSS 10, BSX 26, BSX 39, 2N3261
10781	2N2654	25V, 10mA, 0,1W, 250MHz	AF 109R, AF 139, AF 239(S)
10782	2N2655	100V, 0,5A, 15W(Tc25°)	BUX 49, BUY 41, 2SC1860
10783	2N2656	25V, 0,2A, 0,36W, >250MHz	BC 168, BC 183, BC 238, BC 548
10784	2N2657	80V, 5A, 4W(Tc100°), >20MHz	BFT 32...34, 2N4895...97, 2N5336...39
10785	2N2658	2N2657, 100V	BFT 33...34, 2N4895...97, 2N5339
10786	2N2659	50V, 3A, 15W(Tc25°)	2N1039
10787	2N266	18V, 0,2A, 0,075W	AC 125...126, AC 151, ASY 26...27
10788	2N2660	2N2659, 70V	2N1040
10789	2N2661	2N2659, 90V	2N1041
10790	2N2662	50V, 3A, 15W(Tc25°)	2N2553, 2N2561
10791	2N2663	2N2662, 70V	2N2554, 2N2562
10792	2N2664	2N2662, 90V	2N2555, 2N2563
10793	2N2665	50V, 3A, 15W(Tc25°)	2N1039
10794	2N2666	2N2665, 70V	2N1040
10795	2N2667	2N2665, 90V	2N1041
10796	2N2668	50V, 3A, 15W(Tc25°)	2N2553, 2N2561
10797	2N2669	2N2668, 70V	2N2554, 2N2562
10798	2N267	35V, 10mA, 0,035W, 30MHz	AF 124...127, AF 200
10799	2N2670	2N2668, 90V	2N2555, 2N2563

10800	2N2671	25V, 10mA, 0,1W, >200MHz	AF 106, AF 109R, AF 306
10801	2N2672(A)	25..32V, 10mA, 0,1W, >18MHz	AF 124...127, AF 200
10802	2N2673	B>8	BC 174, BC 182, BC 190, BC 546
10803	2N2674	2N2673, B>12	BC 174, BC 182, BC 190, BC 546
10804	2N2675	2N2673, B>22	BC 174, BC 182, BC 190, BC 546
10805	2N2676	2N2673, B>45	BC 174, BC 182, BC 190, BC 546
10806	2N2677	2N2673, 45V, B>20	BC 167, BC 182, BC 237, BC 547
10807	2N2678	2N2673, 45V, B>45	BC 167, BC 182, BC 237, BC 547
10808	2N2679	Igt/Ih<0,02/<0,5mA	2N2323A
10809	2N2679A...2686A	2N2679..2686, <10µs	-
10810	2N268(A)	80V, 3A, 30W	AL 102...103, AUY 20, 2N2141, 2N2146
10811	2N2680	2N2679, 60V	2N2324A
10812	2N2681	2N2679, 100V	2N2324A
10813	2N2682	2N2679, 200V	2N2326A
10814	2N2682	2N2679, 200V	2N2326A
10815	2N2683	Igt/Ih<0,02/<1mA	2N2323A
10816	2N2684	2N2683, 60V	2N2324A
10817	2N2685	2N2683, 100V	2N2324A
10818	2N2686	2N2683, 200V	2N2326A
10819	2N2687	Igt/Ih<0,2/<2mA	2N6605, TAG 06Y, 2N2323, TAG 615-100
10820	2N2688	2N2687, 60V	2N6606, TAG 06YY, 2N2324, TAG 615-100
10821	2N2689	2N2687, 100V	2N6607, TAG 06A, 2N2324, TAG 615-100
10822	2N269(A)	20V, 0,1A, 0,12W, >4MHz	ASY 26...27, ASY 48, ASY 76...77
10823	2N2690	2N2687, 200V	2N6608, TAG 06B, 2N2326, TAG 615-200
10824	2N2691	100V, 20A, 100W	2N1652...53, 2N2286...87
10825	2N2691A	2N2691, 120V	2N1653, 2N2287
10826	2N2692	B>90	BC 167, BC 182, BC 237, BC 547
10827	2N2693	2N2692, B>60	BC 167, BC 182, BC 237, BC 547
10828	2N2694	2N2692, B>30	BC 167, BC 182, BC 237, BC 547
10829	2N2695	25V, 0,5A, 0,36W, >100MHz	BC 327...328, BC 636, 2N2906...07(A)
10830	2N2696	25V, 0,5A, 0,36W, >100MHz	BC 327...328, BC 636, 2N2906...07(A)
10831	2N2699	15V, 0,1A, 0,15W, >300MHz	2N705A, 2N964(A), 2N2635, 2N2955...57
10832	2N27	35V, 0,05W, >1MHz	AC 127, ASY 28
10833	2N270	25V, 0,075A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
10834	2N2706(MP)	32V, 0,2A, 0,28W	AC 128, AC 152...153, 2SB324, 2SB415
10835	2N2707	2N2430+2N2706	AC 127AC 128, AC 127AC 152
10836	2N2708	>700MHz	BF 377...378, BF 689, BF 763, 2N2857
10837	2N2709	50V, 0,05A, 0,24W	BC 212, BC 257, BC 307, BC 557
10838	2N271(A)	30V, 0,2A, 0,15W, 10MHz	ASY 26...27, 2N3323...25
10839	2N2710	40V, 0,5A, 0,36W, <20/35ns	BSS 10, BSX 26, BSX 39, 2N3261
10840	2N2711	18V, 0,1A, 0,12W, B>30	BC 168, BC 183, BC 238, BC 548
10841	2N2712	2N2711, B>75	BC 168, BC 183, BC 238, BC 548
10842	2N2713	B>30	BC 168, BC 183, BC 238, BC 548
10843	2N2714	2N2713, B>75	BC 168, BC 183, BC 238, BC 548
10844	2N2715	18V, 0,05A, 0,2W, B>30	BC 168, BC 183, BC 238, BC 548

10845	2N2716	2N2715, B>75	BC 168, BC 183, BC 238, BC 548
10846	2N2717	25V, 15mA, 0,1W, >300MHz	ASZ 21, 2N2635, 2N2955...57
10847	2N2718	20V, 0,4A, 0,24W, >150MHz	-
10848	2N2719	25V, 0,2A, 0,3W, 200MHz	BC 238, BC 548, BSY 62, 2N706A
10849	2N272	-/20V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
10850	2N2723	80V, 0,04A, 0,5W, B>2000	-
10851	2N2724	2723, B>7000	-
10852	2N2725	2723, 45V	-
10853	2N2726	B>30	BSS 48, 2N2440, 2SD413, 2SD576, 2SD624
10854	2N2727	2N2726, B>75	BSS 48, 2N2440, 2SD413, 2SD576, 2SD624
10855	2N2728	15V, 50A, 170W	2N4048...4053
10856	2N2729	30V, 0,05A, 0,3W, >600MHz	BF 377...378, BF 689, BF 763, 2N2857
10857	2N273	-/12V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
10858	2N2730	80V, 65A, 170W	2N4050, 2N4053
10859	2N2731	2N2730, 60V	2N4049...4050, 2N4052...4053
10860	2N2732	2N2730, 40V	2N4048...4050, 2N4051...4053
10861	2N2733	80V, 65A, 170W	2N4050, 2N4053
10862	2N2734	2N2733, 60V	2N4049...4050, 2N4052...4053
10863	2N2735	2N2733, 40V	2N4048...4050, 2N4051...4053
10864	2N2736	80V, 65A, 170W	2N4050, 2N4053
10865	2N2737	2N2736, 60V	2N4049...4050, 2N4052...4053
10866	2N2738	2N2736, 40V	2N4048...4050, 2N4051...4053
10867	2N274	40V, 10mA, 0,12W, 30MHz	AF 124...127, AF 200
10868	2N2757	50V, 30A, 200W	2N6324...25
10869	2N2758	2N2757, 100V	2N6324...25
10870	2N2759	2N2757, 150V	2N6324...25
10871	2N2760	2N2757, 200V	2N6324...25
10872	2N2761	2N2757, 250V	2N6324...25
10873	2N2762	2N2757, 300V	2N6324...25
10874	2N2763	50V, 30A, 200W	2N6324...25
10875	2N2764	2N2763, 100V	2N6324...25
10876	2N2765	2N2763, 150V	2N6324...25
10877	2N2766	2N2763, 200V	2N6324...25
10878	2N2767	2N2763, 250V	2N6324...25
10879	2N2768	2N2763, 300V	2N6324...25
10880	2N2769	50V, 30A, 200W	2N6324...25
10881	2N277	40V, 15A, 170W	2N1980...82, 2N2075...82, 2N2491
10882	2N2770	2N2769, 100V	2N6324...25
10883	2N2771	2N2769, 150V	2N6324...25
10884	2N2772	2N2769, 200V	2N6324...25
10885	2N2773	2N2769, 250V	2N6324...25
10886	2N2774	2N2769, 300V	2N6324...25
10887	2N2775	50V, 30A, 200W	2N6324...25
10888	2N2776	2N2775, 100V	2N6324...25
10889	2N2777	2N2775, 150V	2N6324...25



10890	2N2778	2N2775, 200V	2N6324...25
10891	2N2779	2N2775, 250V	2N6324...25
10892	2N278	2N277, 50V	2N1980...82, 2N2075...77, 2N2491
10893	2N2780	2N2775, 300V	2N6324...25
10894	2N2781	75V, 2A, 15W, >140MHz	-
10895	2N2782	100V, 2A, 15W, >140MHz	-
10896	2N2783	100V, 2A, 15W, >140MHz	-
10897	2N2784	15V, 0,3W, <9/9ns	-
10898	2N2785	60V, 0,2A, 0,5W, B>2000	BFX 67, 2N999
10899	2N2786(A)	35V, 0,15A, >225MHz	-
10900	2N2787	B>20	BC 140...141, BSW 39, 2N2218...19A
10901	2N2789(S)	2N2787, B>100	BC 140...141, BSW 39, 2N2218...19A
10902	2N279	-/20V, 0,05A, 0,125W, $\beta$ >20	AC 125...126, AC 151, 2SB54, 2SB56
10903	2N2790	2N2787, 0,5W	BC 639, BSW 63...64, 2N2221...22A
10904	2N2791	2N2787, 0,5W, B>40	BC 639, BSW 63...64, 2N2221...22A
10905	2N2792	2N2787, 0,5W, B>100	BC 639, BSW 63...64, 2N2221...22A
10906	2N2793	75V, 60A, 170W	2N4050, 2N4053
10907	2N2794	20V, Idss>1,5mA	2N2497...98, 2N2500
10908	2N2795	25V, 0,1A, 0,075W, 450MHz	2N2635, 2N2955...57
10909	2N2796	25V, 0,1A, 0,075W, 450MHz	2N2635, 2N2955...57
10910	2N2797	40V, 0,1A, 0,075W, >150MHz	2N2955...57
10911	2N2798	60V, 0,1A, 0,075W, >120MHz	-
10912	2N2799	30V, 0,1A, 0,075W, >120MHz	2N2635, 2N2955...57
10913	2N28	30V, 0,08A, 0,12W	AC 127, ASY 28
10914	2N280	2N279, B>47	AC 125...126, AC 151, 2SB54, 2SB56
10915	2N2800(S)	B>30	BSW 40, 2N2904...05(A), 2N3468, 2SA717
10916	2N2801(S)	2N2800, B>75	BSW 40, 2N2904...05(A), 2N3468, 2SA717
10917	2N2808	30V, 0,025A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, 2N2857
10918	2N2808A	2N2808, >1,5GHz	BF 377...378, BF 689, BF 763, 2N2857
10919	2N2809	30V, 0,025A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, 2N2857
10920	2N2809A	2N2809, >1,3GHz	BF 377...378, BF 689, BF 763, 2N2857
10921	2N281	16V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
10922	2N2810	24V, 0,025A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, 2N2857
10923	2N2810A	2N2810, >1,3GHz	BF 377...378, BF 689, BF 763, 2N2857
10924	2N2811	80V, 10A, 70W, >15MHz, B>20	2N5288...89, 2N5542
10925	2N2812	2N2811, B>40	2N5288...89, 2N5542
10926	2N2813	2N2811, 120V	2N5288...89, 2N5542
10927	2N2814	2N2811, 120V, B>40	2N5288...89, 2N5542
10928	2N2815	80V, 20A, 200W	2N6324...25
10929	2N2816	2N2815, 100V	2N6324...25
10930	2N2817	2N2815, 150V	2N6324...25
10931	2N2818	2N2815, 200V	2N6324...25
10932	2N2819	80V, 25A, 200W	2N6324...25
10933	2N282	2x 2N281, .	AC 125...126, AC 151, 2SB54, 2SB56
10934	2N2820	2N2819, 100V	2N6324...25



10935	2N2821	2N2819, 150V	2N6324...25
10936	2N2822	2N2819, 200V	2N6324...25
10937	2N2823	80V, 30A, 200W	2N6324...25
10938	2N2824	2N2823, 100V	2N6324...25
10939	2N2825	2N2823, 150V	2N6324...25
10940	2N2826	-/15V, 1A, 7,5W	AD 162
10941	2N2827	40V, 1,5A, 7,5W	-
10942	2N2828	80V, 3A, 40W	2N5002, 2N5004, 2N5284...85
10943	2N2829	80V, 3A, 40W	2N5002, 2N5004, 2N5284...85
10944	2N283	20V, 0,01A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
10945	2N2831	40V, 0,2A, 0,36W, >250MHz	BC 547, BFX 94...95, 2N2221...22(A)
10946	2N2832	80V, 20A, 85W	2N1652...53, 2N2286...87
10947	2N2833	2N2832, 120V	2N1653, 2N2287
10948	2N2834	2N2832, 140V	-
10949	2N2835	32V, 1A, 16W(Tc50°)	AD 162
10950	2N2836	55V, 3,5A, 37W	AD 149, AUY 19...20, 2N1545...48
10951	2N2837	2N2800, 0,5W	2N2906...07(A), 2N4026...29
10952	2N2838	2N2801, 0,5W	2N2906...07(A), 2N4026...29
10953	2N284	32V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
10954	2N2840	Ip<10μA, Iv>0,24mA	-
10955	2N2841	30V, Idss>0,025mA, Up<1,7V	2N5471...72
10956	2N2842	30V, Idss>0,065mA, Up<1,7V	2N5472...73
10957	2N2843	30V, Idss>0,2mA, Up<1,7V	2N5265
10958	2N2844	30V, Idss>0,44mA, Up<1,7V	2N5020, 2N5266...67
10959	2N2845	B>30	2N4014
10960	2N2846	2N2845, 0,8W	BSS 27, BSV 77, BSV 95, 2N5189
10961	2N2847	2N2845, B>40	2N4014
10962	2N2848	2N2845, 0,8W, B>40	BSS 27, BSV 77, BSV 95, 2N5189
10963	2N2849(-1)	100V, 3A, 0,85W, B>100	BSX 64, 2N4239, 2SC696, 2SC2214
10964	2N2849-2..2856-2	2N2849(-1)..2N2856(-1)	2N5002, 2N5004, 2N5284...85
10965	2N2849-3..2856-3	2N2849(-1)..2N2856(-1)	BD 241C, BD 539C, BD 937, 2SD712
10966	2N284A	2N284, 60V	ASY 48, ASY 77
10967	2N285(A,B)	-/40V, 3A, 25W(Tc45°)	AD 149, AUY 19...20, 2N2143...46
10968	2N2850(-1)	2N2849, B>40	BSX 64, 2N4239, 2SC696, 2SC2214
10969	2N2851(-1)	2N2849, B>40	BSX 64, 2N4239, 2SC696, 2SC2214
10970	2N2852(-1)	2N2849, B>20	BSX 64, 2N4239, 2SC696, 2SC2214
10971	2N2853(-1)	60V, 3A, 0,85W, B>40	BSX 62...64, 2N4238...39, 2SC696, 2SC2214
10972	2N2854(-1)	2N2853, B>100	BSX 62...64, 2N4238...39, 2SC696, 2SC2214
10973	2N2855(-1)	2N2853, B>40	BSX 62...64, 2N4238...39, 2SC696, 2SC2214
10974	2N2856(-1)	2N2853, B>20	BSX 62...64, 2N4238...39, 2SC696, 2SC2214
10975	2N2857	30V, 0,04A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, BFX 63
10976	2N2858	100V, 3A, 0,6W	BSX 64, 2N4239, 2SC696(A), 2SC2214
10977	2N2859	2N2858, 120V	2SC696A
10978	2N2860	18V, 0,15A, 0,15W, >250MHz	2N2635, 2N2955...57
10979	2N2861	B>50	BC 214, BC 259, BC 309, BC 559

10980	2N2862	2N2861, >45MHz, B>25	BC 214, BC 259, BC 309, BC 559
10981	2N2863	60V, 1A, 0,8W, 250MHz	BFS 23, 2SC2419
10982	2N2864	60V, 1A, 0,8W, 250MHz	BFS 23, 2SC2419
10983	2N2865	25V, 0,05A, >600MHz	BFR 37, BFW 30, BFX 59, BFX 73
10984	2N2866	120V, 2A, 40W, B>20	2N5284...85
10985	2N2867	2N2866, B>40	2N5284...85
10986	2N2868	60V, 1A, 0,8W, >50MHz	BC 140...141, BC 300...302, 2N1990
10987	2N2869	60V, 10A, 30W	AL 100...101, AUY 21, 2N2292...93
10988	2N2870	2N2869, 80V	AL 100...101, AUY 37, 2N2292...93
10989	2N2873	35V, 10mA, 0,115W, >300MHz	AF 109R, AF 139, AF 239(S)
10990	2N2874	75V, 2A, 15W, >140MHz	BD 139, BD 230, BD 519, BD 527
10991	2N2875	60V, 2A, 20W, >25MHz	2N5003, 2N5005, 2N5286...87
10992	2N2876	80V, 2,5A, PQ>3W(150MHz)	BLY 35, 2N3632
10993	2N2877	30W(Tc100°),>30MHz,B>20	2N5002, 2N5004, 2N5284...85
10994	2N2878	2N2877, >50MHz, B>40	2N5002, 2N5004, 2N5284...85
10995	2N2879	2N2877, 100V	2N5002, 2N5004, 2N5284...85
10996	2N2880	2N2877, 100V, >50MHz, B>40	2N5002, 2N5004, 2N5284...85
10997	2N2881	60V, 2A, 8,5W(Tc25°)	BSS 17...18, 2N4235...36, 2N5322...23
10998	2N2882	2N2881, 100V	BSS 17...18, 2N4235...36, 2N5322...23
10999	2N2883	40V,0,3A,PQ>0,5W(500MHz)	BFS 50, MRF 515, MRF 629, 2N3948
11000	2N2884	2N2883, PQ>0,75W(500MHz)	BFS 50, MRF 515, MRF 629, 2N3948
11001	2N2885	40V, 0,15W, >300MHz, <40/-ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11002	2N2886	50V, 0,5A, 0,8W	BC 140...141, BC 300...302, 2N3053
11003	2N2887	100V, 1,2A, 25W, >140MHz	-
11004	2N2888	200V, 16A(Tc65°), Igt/<40mA	2N685, T 12N200, MCR 3935-4, C 35B
11005	2N2889	2N2888, 250V	2N686, T 12N300, MCR 3935-5, C 35H
11006	2N2890	B>30	BSX 64, 2N4239, 2SC696(A), 2SC2214
11007	2N2891	2N2890, B>50	BSX 64, 2N4239, 2SC696(A), 2SC2214
11008	2N2892	100V, 5A, 30W, >30MHz, B>30	2N5002, 2N5004, 2N5284...85
11009	2N2893	2N2892, B>50	2N5002, 2N5004, 2N5284...85
11010	2N2894(A)	12V, 0,2A, 0,36W, 23/34ns	BFX 36
11011	2N2895	120V, 1A, 0,5W, >120MHz	BCX 22, 2N3700...01, 2SC2235, 2SD667
11012	2N2896	140V, 1A, 0,5W, >120MHz	2N3700...01, 2SC2383, 2SC3228
11013	2N2897	60V, 1A, 0,5W, >120MHz	BC 337A, BC 637, BC 639, 2SD667
11014	2N2898	2N2895	2N2895
11015	2N2899	2N2896	2N2896
11016	2N29	35V, 0,1A, 0,12W	AC 127, ASY 28
11017	2N290	70V, 12A, 55W	2N1981...82, 2N2079...80, 2N2490
11018	2N2900	2N2897	2N2897
11019	2N2904(S)	B>40	BSW 40, 2N4030...33, 2N4036...37
11020	2N2904A(AS)	2N2904, 60/60V	BSW 40, 2N4030...33, 2N4036...37
11021	2N2905(A,S)	2N2904, B>100	BSW 40, 2N4030...33, 2N4036...37
11022	2N2906(A)	2N2904, 0,4W	2N4026...29
11023	2N2907(A)	2N2904, 0,4W, B>100	2N4026...29
11024	2N2909	60V, 1A, 0,4W, >50MHz	BC 337A, BC 637, BC 639, 2SD667

11025	2N291	25V, 0,2A, 0,18W	AC 125...126, AC 151, 2SB54, 2SB56
11026	2N2911	150V, 3A, 5W(Tc25°)	BUX 49, BUY 41
11027	2N2912	15V, 25A, 75W(Tc35°)	-
11028	2N292	15V, 0,02A, 0,065W, 5MHz	-
11029	2N2921	$\beta > 35$	BC 168, BC 183, BC 238, BC 548
11030	2N2922	2N2921, $\beta > 55$	BC 168, BC 183, BC 238, BC 548
11031	2N2923	2N2921, $\beta > 90$	BC 168, BC 183, BC 238, BC 548
11032	2N2924	2N2921, $\beta > 150$	BC 168, BC 183, BC 238, BC 548
11033	2N2925	2N2921, $\beta > 235$	BC 168, BC 183, BC 238, BC 548
11034	2N2926	2N2921, $\beta > 35$	BC 168, BC 183, BC 238, BC 548
11035	2N2927	25V, 0,5A, 0,8W, $< 75/170\text{ns}$	2N3467...68, 2SA717, 2SA742
11036	2N2928	15V, 0,1A, 0,15W, $> 400\text{MHz}$	2N3283...86, AF 139, AF 239(S)
11037	2N2929	25V, 0,1A, 0,3W, 1100MHz	-
11038	2N292A	2N292, 0,1W	-
11039	2N293	15V, 0,02A, 0,065W, 8MHz	-
11040	2N2930	30V, 0,5A, 0,25W, $> 4\text{MHz}$	ASY 76...77
11041	2N2931	0,05W, $> 20\text{MHz}$ , $\beta > 30$	BC 121...123
11042	2N2932	2N2931, $\beta > 70$	BC 121...123
11043	2N2933	2N2931, $\beta > 45$	BC 121...123
11044	2N2934	2N2931, 45V	BC 123
11045	2N2935	2N2931, 45V, $\beta > 70$	BC 123
11046	2N2938	$< 30/30\text{ns}$	BSS 10, BSX 26, BSX 28, BSX 39, 2N3261
11047	2N2939	75V, 1A, 0,8W, $> 150\text{MHz}$	BC 140...141, BSX 45...47, 2N1990
11048	2N2940	2N2939, 120V	BSS, 42, BSW 67, BSX 47, 2N2405
11049	2N2941	2N2939, 150V	BSS 43, BSW 68
11050	2N2942	50V, 0,1A, 0,15W, $> 150\text{MHz}$	-
11051	2N2943	2N2942, 30V, $> 120\text{MHz}$	2N2635, 2N2955...57
11052	2N2944(A)	15V, 0,1A, 0,4W, 15MHz	2N5229
11053	2N2945(A)	25V, 0,1A, 0,4W, 13MHz	2N5230
11054	2N2946(A)	25V, 0,1A, 0,4W, 12MHz	2N5231
11055	2N2947	60V, 1,5A, PQ15W(50MHz)	-
11056	2N2948	40V, 1,5A, PQ15W(30MHz)	-
11057	2N2949	60V, 0,7A, PQ3,5W(50MHz)	-
11058	2N2950	60V, 0,7A, PQ3,5W(50MHz)	-
11059	2N2951(S)	60V, 0,25A, PQ0,6W(50MHz)	BFX 55, MRF 229...230
11060	2N2952	60V, 0,25A, PQ0,6W(50MHz)	BFX 55, MRF 229...230
11061	2N2953	30V, 0,15A, 0,12W, 10MHz	AC 125...126, AC 151, ASY 26, ASY 76...77
11062	2N2955	40V, 0,1A, 0,15W, 32/53ns	-
11063	2N2956	40V, 0,1A, 0,15W, 25/55ns	-
11064	2N2957	40V, 0,1A, 0,15W, 22/50ns	-
11065	2N2958(S)	$B > 40$	BSW 27...28, BSW 51...54, 2N2218...19(A)
11066	2N2959(S)	2N2958, $B > 100$	BSW 27...28, BSW 51...54, 2N2218...19(A)
11067	2N296	-/60V, 2A, 20W	AL 102...103, AUY 19...20, 2N2145...46
11068	2N2960	60V, 0,6A, 0,6W, $< 95/500\text{ns}$	BSW 27...28, BSW 51...54, 2N2218...19(A)
11069	2N2961	60V, 0,6A, 0,6W, $< 95/500\text{ns}$	BSW 27...28, BSW 51...54, 2N2218...19(A)

11070	2N2962	40V, 0,3A, 0,35W, >560MHz	-
11071	2N2963	40V, 0,3A, 0,35W, >560MHz	-
11072	2N2964	30V, 0,3A, 0,35W, >560MHz	-
11073	2N2965	30V, 0,3A, 0,35W, >560MHz	-
11074	2N2967	12V, 0,3W, <15/15ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
11075	2N2968	30V, 0,05A, 0,15W, >10MHz	2N2946
11076	2N2969	30V, 0,05A, 0,15W, >10MHz	2N2946
11077	2N297(A)	60V, 4A, 85W	AL 102...103, AUY 21...22, 2N1545...48
11078	2N2970	20V, 0,05A, 0,15W, >8MHz	2N2946
11079	2N2971	20V, 0,05A, 0,15W, >8MHz	2N2946
11080	2N2983	155V, 3A, 1W, 60MHz, B>20	BUX 49...53, BUY 41, 2SD625
11081	2N2984	2N2983, 185V	BUX 50...53, 2SD625
11082	2N2985	2N2983, B>40	BUX 49...53, BUY 41, 2SD625
11083	2N2986	2N2983, 185V, B>40	BUX 50...53, 2SD625
11084	2N2987	95V, 1A, 15W(Tc100°), B>25	BUX 49...53, BUY 41, 2SD625
11085	2N2988	2N2987, 155V	BUX 49...53, 2SD625
11086	2N2989	2N2987, B>60	BUX 49...53, BUY 41, 2SD625
11087	2N299	5V, 5mA, 0,02W, 110MHz	AF 106, AF 109R, AF 124...125, AF 200
11088	2N2990	2N2987, 155V, B>60	BUX 49...53, 2SD625
11089	2N2991	2N2987	2SC2275A, 2SC2528...29, 2SD608
11090	2N2992	2N2988	2SC2275A, 2SC2529, 2SD608, 2SD759
11091	2N2993	2N2989	2SC2275A, 2SC2528...29, 2SD608
11092	2N2994	2N2990	2SC2275A, 2SC2529, 2SD608, 2SD759
11093	2N2995	120V, 1A, >10MHz	2SC2275A, 2SC2528...29, 2SD608
11094	2N2996	15V, 0,05A, 0,075W, >400MHz	AF 139, AF 239(S), 2N3283...86
11095	2N2997	30V, 0,05A, 0,075W, >400MHz	AF 139, AF 239(S), 2N3283...86
11096	2N2998	15V, 0,05A, 0,075W, >600MHz	AF 139, AF 239(S), 2N3283...86
11097	2N2999	>1400MHz	-
11098	2N300	5V, 5mA, 0,02W, 95MHz	AF 106, AF 109R, AF 124...125, AF 200
11099	2N3000	45V, 0,4A, 0,15W	ASY 76...77
11100	2N3001	Igt/Ih<0,2/<3mA	2N2323A
11101	2N3002	2N3001, 60V	2N2324A
11102	2N3003	2N3001, 100V	2N2324A
11103	2N3004	2N3001, 200V	2N2326A
11104	2N3005	2N3001, Igt/Ih<0,2/<5mA	2N6605, TAG 06Y, 2N2323, TAG 615-100
11105	2N3006	2N3002, Igt/Ih<0,2/<5mA	2N6606, TAG 06YY, 2N2324, TAG 615-100
11106	2N3007	2N3003, Igt/Ih<0,2/<5mA	2N6607, TAG 06A, 2N2324, TAG 615-100
11107	2N3008	2N3004, Igt/Ih<0,2/<5mA	2N6608, TAG 06B, 2N2326, TAG 615-200
11108	2N3009	40V, 0,2A, 0,36W, <15/25ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11109	2N301	40V, 3A, 50W	AD 149, AUY 19...20, 2N2143...46
11110	2N3010	15V, 0,05A, 0,3W, <12/12ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
11111	2N3011		BSS 11...12, BSX 19...20, 2N2368...69(A)
11112	2N3012		
11113	2N3013(R)		BSS 10...11, BSX 19...20, 2N2368...69(A)
11114	2N3014	40V, 0,2A, 0,36W, <16/25ns	BSS 10...11, BSX 19...20, 2N2368...69(A)

11115	2N3015	60V, 1A, 0,8W, <40/60ns	BSS 27, BSV 77, BSV 95, 2N5189
11116	2N3016	100V, 2,5A, 3,3W(Tc25°)	BSX 64, 2N4239, 2SC696(A), 2SC2214
11117	2N3017	2N3016, 5A	BD 243C, BD 539C, BD 953, 2SD613
11118	2N3018	2N3016, 10A, 25W(Tc25°)	2N5288...89, 2N5542
11119	2N3019(S)	B>100	BSS 43, BSW 68, 2SC1860
11120	2N301A	2N301, 60V	AL 102...103, AUY 19...20, 2N2144...46
11121	2N302	30V, 0,2A, 0,15W, >7MHz	ASY 26, 2N3323...25
11122	2N3020(S)	2N3019, B>40	BSS 43, BSW 68, 2SC1860
11123	2N3021	30V, 3A, 25W, >60MHz, B>20	2SA1141, 2SA1146, 2SA1186, 2SA1292
11124	2N3022	2N3021, 45V	2SA1141, 2SA1146, 2SA1186, 2SA1292
11125	2N3023	2N3021, 60V	2SA1141, 2SA1146, 2SA1186, 2SA1292
11126	2N3024	2N3021, B>50	2SA1141, 2SA1146, 2SA1186, 2SA1292
11127	2N3025	2N3021, 45V, B>50	2SA1141, 2SA1146, 2SA1186, 2SA1292
11128	2N3026	2N3021, 60V, B>50	2SA1141, 2SA1146, 2SA1186, 2SA1292
11129	2N3027	30V, 0,5A(Tc100°), Igt<0,2mA	TAG64Y, BRX44, BR103, TAG60Y, TAG62Y
11130	2N3028	2N3027, 60V	TAG64F, BRX46, BRX51, TAG60F, TAG62F
11131	2N3029	2N3027, 100V	TAG64A, BRX46, BRX51, TAG60A, TAG62A
11132	2N303	2N302, >14MHz	ASY 26, 2N3323...25
11133	2N3030	2N3027, Igt<0,02mA	-
11134	2N3031	2N3028, Igt<0,02mA	-
11135	2N3032	2N3029, Igt<0,02mA	-
11136	2N3033	160V, 0,02A, 0,3W, <5/-ns	-
11137	2N3034	2N3033, 120V	-
11138	2N3035	2N3033, 90V	-
11139	2N3036	120V, 1,2A, 0,8W, 89/575ns	2N2102, 2N2405, 2N3019...20
11140	2N3037	120V, 0,5A, 0,36W, >50MHz	BCX 22, 2N3700...01, 2SD2235, 2SD667
11141	2N3038	2N3037, 100V	BC 639, BCX 24, 2N3700...01, 2SD667
11142	2N3039	50V, 0,5A, 0,36W, >50MHz	BC 327, BC 638, BC 640, 2SB647
11143	2N3040	2N3039, 40V	BC 327, BC 636, BC 638, BC 640
11144	2N3053(S)	60V, 0,7A, 1W, >100MHz	BC 140...141, BC 300...302, 2N2218...19
11145	2N3053A	2N3053, 80V	BC 140...141, BC 300...302, 2N2218...19A
11146	2N3054(S)		BD 243B, BD 539C, 2N3767, 2SD712
11147	2N3054A	2N3054, 75W, >3MHz	BD 243B, BD 539C, 2N3767, 2SD712
11148	2N3055(E,H,S,U)	100V, 15A, 115W, >2,5MHz	BD 317, BD 745C, BDW 51C, 2N5629...31
11149	2N3055A	<4,5/9µs	
11150	2N3055C,V	2N3055, 80V	BD 315, BD 745B, BDW 51B, 2N5629...31
11151	2N3056	B>40	BC 639, BCX 24, 2N3700...01, 2SD667
11152	2N3056A	2N3056, 140V	2N3700...01, 2SC2383, 2SC3228
11153	2N3057	2N3056, B>100	BC 639, BCX 24, 2N3700...01, 2SD667
11154	2N3057A	2N3056, 140V, B>100	2N3700...01, 2SC2383, 2SC3228
11155	2N3058	6/6/6V, 0,1A, 0,4W	-
11156	2N3059	10/10/10V, 0,1A, 0,4W	-
11157	2N306	20V, 2mA, 0,05W	AC 127, ASY 28...29
11158	2N3060	70/60/30V, 0,1A, 0,4W	-
11159	2N3061	70/60/30V, 0,1A, 0,4W	-

11160	2N3062	90/80/40V, 0,1A, 0,4W	-
11161	2N3063	90/80/40V, 0,1A, 0,4W	-
11162	2N3064	110/100/50V, 0,1A, 0,4W	-
11163	2N3065	110/100/50V, 0,1A, 0,4W	-
11164	2N3066(A)	50V, Idss>0,8mA, Up<9,5V	-
11165	2N3067(A)	50V, Idss>0,2mA, Up<4,5V	-
11166	2N3068(A)	50V, Idss>0,05mA, Up<2,2V	-
11167	2N3069(A)	50V, Idss>2mA, Up<10V	-
11168	2N307(A,B)	35V, 5A, 106W	AL 102...103, AUY 21...22, 2N3611...18
11169	2N3070(A)	50V, Idss>0,5mA, Up<5V	-
11170	2N3071	50V, Idss>0,1mA, Up<2,5V	-
11171	2N3072	<40/100ns	BSW 23, 2N2904...05(A), 2N3468, 2SA742
11172	2N3073	2N3072, 0,36W	BSW 24, 2N2906...07(A), 2N4026...29
11173	2N3074	30V, 0,02A, 0,14W	AF 139, AF 239(S), 2N3283...86
11174	2N3075	35V, 0,02A, 0,14W	AF 139, AF 239(S), 2N3283...86
11175	2N3077	0	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
11176	2N3078	2N3077, B>25	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
11177	2N3079	200/200V, 5A, 150W, >2MHz	-
11178	2N308	20V, 5mA, 0,03W	AF 124...127, AF 200
11179	2N3080	2N3079, 300/300V	-
11180	2N3081	<60/175ns	BSW 40, 2N4031, 2N4033, 2N4036
11181	2N3084	30V, Idss>0,8mA, Up<10V	-
11182	2N3085	30V, Idss>0,8mA, Up<10V	-
11183	2N3086	40V, Idss>0,8mA, Up<10V	-
11184	2N3087	30V, Idss>0,8mA, Up<10V	-
11185	2N3088(A)	15V, Idss>0,5mA, Up<5V	-
11186	2N3089(A)	15V, Idss>0,5mA, Up<5V	-
11187	2N309	20V, 5mA, 0,03W	AF 124...127, AF 200
11188	2N310	30V, 5mA, 0,03W	AF 124...127, AF 200
11189	2N3107	B>100	BC 141, BSW 66, BSX 46...47, 2N1990
11190	2N3108	2N3107, B>40	BC 141, BSW 66, BSX 46...47, 2N1990
11191	2N3109	2N3107, 80V	BC 140, BSW 65, BSX 45...47, 2N1990
11192	2N311	15V, 0,075W	ASY 26...27, ASY 76...77
11193	2N3110(S)	2N3107, 80V, B>40	BC 140, BSW 65, BSX 45...47, 2N1990
11194	2N3112	20V, Idss>0,035mA, Up<4V	2N5797
11195	2N3113	2N3112	2N5797
11196	2N3114(S)	150V, 0,2A, 0,8W, >40MHz	BF 257...259, BF 657...659, BFR 57...59
11197	2N3115	2N2958, 0,4W	BSS 26, BSV 59, BSX 49, 2N2221...22(A)
11198	2N3116	2N2959, 0,4W	BSS 26, BSV 59, BSX 49, 2N2221...22(A)
11199	2N3117	60V, 0,05A, 0,36W, >60MHz	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
11200	2N3118	85V,0,5A,PQ>0,4W(150MHz)	BFW 47, 2N3553, 2SC2852
11201	2N3119	<40/700ns	BSW 39, 2N3723
11202	2N312	15V, 0,2A, 0,075W	ASY 28...29, ASY 73...75
11203	2N3120	<40/100ns	2N3468, 2SA717, 2SA742
11204	2N3121	2N3120, 0,36W	BSW 24, BSX 36



11205	2N3122	50V, 0,5A, 0,8W, >60MHz	BC 140...141, BC 300...302, 2N3053
11206	2N3123	60V, 0,5A, 0,8W, >400MHz	BFW 47, BSV 77, BSV 95, 2N3553
11207	2N3124	40V, 15A, 90W	AUY 29, 2N1549...60
11208	2N3125	80V, 3,3A, 90W	AL 102...103, AUY 20, 2N2141, 2N2146
11209	2N3126	100V, 15A, 90W	2N1552, 2N1556, 2N1560
11210	2N3127	25V, 0,05A, 0,1W, >400MHz	AF 139, AF 239(S), 2N3283...86
11211	2N3128	20V, 0,1A, 0,15W, >60MHz	BC 122...123, BC 146
11212	2N3129	45V, 0,1A, 0,15W, >60MHz	BC 123
11213	2N313	15V, 0,02A, 0,065W, 5MHz	-
11214	2N3130	60V, 0,1A, 0,15W, >60MHz	-
11215	2N3131	40V, 0,1A, 0,15W, >250MHz	-
11216	2N3132	100V, 5A, 90W	AL 102...103, 2N1542...43, 2N1547...48
11217	2N3133(S)	50V, 0,6A, 0,6W, 26/70ns, B>40	2N3468, 2SA717, 2SA742
11218	2N3134(S)	2N3133, B>100	2N3468, 2SA717, 2SA742
11219	2N3135	2N3133, 0,4W	BSW 24, BSX 36
11220	2N3136	2N3133, 0,4W, B>100	BSW 24, BSX 36
11221	2N3137	40V,0,15A,PQ0,6W(250MHz)	BFW 16...17, BFS 50, BFR 36, 2SC2852
11222	2N3137T	2N3137, 0,5A	BFS 50, MRF 629, 2N3948, 2SC2852
11223	2N3138	65V, 2A, 20W	2N5002, 2N5004, 2N5284...85
11224	2N3139	140V, 2A, 20W	-
11225	2N314	2N313, 8MHz	-
11226	2N3140	65V, 2A, 20W	2N5002, 2N5004, 2N5284...85
11227	2N3141	140V, 2A, 20W	-
11228	2N3142	65V, 2A, 20W	2N5002, 2N5004, 2N5284...85
11229	2N3143	140V, 2A, 20W	-
11230	2N3144	65V, 2A, 20W	2N5002, 2N5004, 2N5284...85
11231	2N3145	140V, 2A, 20W	-
11232	2N3146	150V, 15A, 150W	-
11233	2N3147	2N3146, 180V	-
11234	2N3148	11V, 0,05A, 0,025W, >25MHz	ASZ 21, 2N705, 2N960...967, 2N2955...57
11235	2N3149	80/80V, 70A, 300W	2N9309...11
11236	2N315	20V, 0,2A, 0,1W	2N1305
11237	2N3150	2N3149, 100/100V	2N9309...11
11238	2N3151	2N3149, 150/150V	-
11239	2N3152	>200MHz	-
11240	2N3153	>30MHz	-
11241	2N315A,B	2N315, 30V, 0,15W	2N1305
11242	2N316	20V, 0,2A, 0,1W	2N1307
11243	2N3162	45V, 0,3W, B>50	-
11244	2N3163	40V, 3A, 85W	2N5003, 2N5005, 2N5286...87
11245	2N3164	2N3163, 60V	2N5003, 2N5005, 2N5286...87
11246	2N3165	2N3163, 80V	2N5003, 2N5005, 2N5286...87
11247	2N3166	2N3163, 100V	2N5003, 2N5005, 2N5286...87
11248	2N316A	2N316, 30V, 0,15A	2N1307
11249	2N317	20V, 0,2A, 0,1W	2N1309



11250	2N3171	2N3163, 75W	BD 246, BDV 92, BDX 92, 2SA980
11251	2N3172	2N3163, 60V, 75W	BD 246A, BDV 92, BDX 92, 2SA980
11252	2N3173	2N3163, 80V, 75W	BD 246B, BDV 94, BDX 94, 2SA980
11253	2N3174	2N3163, 100V, 75W	BD 246C, BDV 96, BDX 96, 2SA980
11254	2N3175	40V, 5A, 85W	2N5003, 2N5005, 2N5286...87
11255	2N3176	2N3175, 60V	2N5003, 2N5005, 2N5286...87
11256	2N3177	2N3175, 80V	2N5003, 2N5005, 2N5286...87
11257	2N3178	2N3175, 100V	2N5003, 2N5005, 2N5286...87
11258	2N317A	2N317, 25V, 0,15W	2N1309
11259	2N3183	2N3175, 75W	BD 246, BDV 92, BDX 92, 2SA980
11260	2N3184	2N3175, 60V, 75W	BD 246A, BDV 92, BDX 92, 2SA980
11261	2N3185	2N3175, 80V, 75W	BD 246B, BDV 94, BDX 94, 2SA980
11262	2N3186	2N3175, 100V, 75W	BD 246C, BDV 96, BDX 96, 2SA980
11263	2N3187	40V, 5A, 85W	2N5003, 2N5005, 2B5286...87
11264	2N3188	2N3187, 60V	2N5003, 2N5005, 2B5286...87
11265	2N3189	2N3187, 80V	2N5003, 2N5005, 2B5286...87
11266	2N319	25V, 0,5A, 0,225W, B>25	AC 128, AC 153, AC 188
11267	2N3190	2N3187, 100V	2N5003, 2N5005, 2B5286...87
11268	2N3195	2N3187, 75W	BD 246, BDV 92, BDX 92, 2SA980
11269	2N3196	2N3187, 60V, 75W	BD 246A, BDV 92, BDX 92, 2SA980
11270	2N3197	2N3187, 80V, 75W	BD 246B, BDV 94, BDX 94, 2SA980
11271	2N3198	2N3187, 100V, 75W	BD 246C, BDV 96, BDX 96, 2SA980
11272	2N3199	40V, 3A, 40W	2N5003, 2N5005, 2N5286...87
11273	2N32(A)	40V, 8mA, 0,05W	AC 125...126, AC 151, ASY 48
11274	2N320	2N319, B>34	AC 128, AC 153, AC 188
11275	2N3200	2N3199, 60V	2N5003, 2N5005, 2N5286...87
11276	2N3201	2N3199, 80V	2N5003, 2N5005, 2N5286...87
11277	2N3202	2N3199, 8,7W(Tc25°)	BSS 46, BUY 90, 2N6190...93
11278	2N3203	2N3199, 60V, 8,7W(Tc25°)	BSS 46, BUY 90, 2N6190...93
11279	2N3204	2N3199, 80V, 8,7W(Tc25°)	BSS 46, BUY 90, 2N6190...93
11280	2N3205	40V, 2A, 40W	2N5003, 2N5005, 2N5286...87
11281	2N3206	2N3205, 60V	2N5003, 2N5005, 2N5286...87
11282	2N3207	2N3205, 100V	2N5003, 2N5005, 2N5286...87
11283	2N3208	40V, 2A, 8,7W(Tc25°)	BSS 46, BUY 90, 2N6190...93
11284	2N3209	20V, 0,2A, 0,36W, <60/90ns	BSW 24, BSX 36, 2N4125...26
11285	2N321	2N319, B>53	AC 128, AC 153, AC 188
11286	2N3210	40V, 0,5A, 0,36W, <40/40ns	BSS 10, BSX 26, BSX 39, 2N3261
11287	2N3211	40V, 0,5A, 0,36W, <40/40ns	BSS 10, BSX 26, BSX 39, 2N3261
11288	2N3212	100V, 5A, 14W	-
11289	2N3213	2N3212, 80V	-
11290	2N3214	2N3212, 60V	-
11291	2N3215	2N3212, 40V	-
11292	2N3216	>9MHz	ASY 76...77, 2N1189...90
11293	2N3217	15/10/15V, 0,1A, 0,4W	2N2944
11294	2N3218	25/20/25V, 0,1A, 0,4W	2N2945

11295	2N3219	40/35/40V, 0,1A, 0,4W	2N2946
11296	2N322	18V, 0,5A, 0,225W, $\beta > 34$	AC 128, AC 153, AC 188
11297	2N3220	100V, 2A, $> 10\text{MHz}$ , $\beta > 20$	2N5002, 2N5004, 2N5284...85
11298	2N3221	2N3220, $\beta > 40$	2N5002, 2N5004, 2N5284...85
11299	2N3222	2N3220, 80V	2N5002, 2N5004, 2N5284...85
11300	2N3223	2N3220, 80V, $\beta > 40$	2N5002, 2N5004, 2N5284...85
11301	2N3224	100V, 0,7W, $> 60\text{MHz}$ , $\beta > 20$	BSW 40, 2N3634...37, 2SA606, 2SA712
11302	2N3225	2N3224, $> 80\text{MHz}$ , $\beta > 40$	BSW 40, 2N3634...37, 2SA606, 2SA712
11303	2N3226	35V, 5A, 75W	BD 245, BDV 91, BDX 91, 2N4914...15
11304	2N3227	40V, 0,5A, 0,36W, $< 23/28\text{ns}$	BSS 10, BSX 26, BSX 39, 2N3261
11305	2N3228	Igt/Ih $< 15/ < 20\text{mA}$	2N3525, 2N4101, BStC0513L, TAG 671-200
11306	2N3229	105V, 2,5A, PQ $> 15\text{W}(150\text{MHz})$	-
11307	2N323	2N322, $\beta > 53$	AC 128, AC 153, AC 188
11308	2N3232	60V, 7,5A, 117W	BD 245A, BD 311, BDV 91, BDX 91
11309	2N3233	2N3232, 100V	BD 245C, BDV 95, BDX 95, 2N5632...34
11310	2N3234	2N3232, 160V	BD 245D, BDX 11, 2N3442, 2SC2260...62
11311	2N3235	55V, 15A, 117W	BD 315, BD 545A, BD 745A, 2N3055
11312	2N3236	90V, 15A, 150W	BD 317, BD 745C, 2N3772, 2N5629...31
11313	2N3237	90V, 20A, 200W	BDY 29, MJ 802, 2N3772, 2SD797
11314	2N3238	80V, 15A, 150W	BD 315, BD 545B, BD 745B, 2N3772
11315	2N3239	80V, 15A, 150W	BD 315, BD 545B, BD 745B, 2N3772
11316	2N324	2N322, $\beta > 72$	AC 128, AC 153, AC 188
11317	2N3240	160V, 15A, 150W	BD 745F, BDW 12, 2N3773, 2SD752
11318	2N3241	$\beta > 70$	BC 168, BC 183, BC 238, BC 548
11319	2N3241A	2N3241, 0,2A, $\beta > 100$	BC 168, BC 183, BC 238, BC 548
11320	2N3242	$\beta > 100$	BC 168, BC 183, BC 238, BC 548
11321	2N3242A	2N3242, 40V, 0,3A, $\beta > 125$	BC 167, BC 182, BC 237, BC 547
11322	2N3244(S)	40V, 1A, 1W, $< 50/185\text{ns}$	2N3467...68, 2SA717, 2SA799
11323	2N3245(S)	50V, 1A, 1W, $< 55/165\text{ns}$	2N3468, 2SA717, 2SA799
11324	2N3246	60V, 0,05A, 0,35W, $> 60\text{MHz}$	BC 174, BC 182, BC 190, BC 546
11325	2N3247	2N3246, 0,15W	-
11326	2N3248	$< 20/80\text{ns}$	BSX 36
11327	2N3249	2N3248, $> 300\text{MHz}$	BSX 36
11328	2N325	35V, 2A, 12W	AD 149, AUY 19...20, 2N2137...46
11329	2N3250		BSW 24, 2N2906...07(A)
11330	2N3250A	2N3250, 60V	BSW 24, 2N2906...07(A)
11331	2N3251		BSW 24, 2N2906...07(A)
11332	2N3251A	2N3251, 60V	BSW 24, 2N2906...07(A)
11333	2N3252(S)		BSS 27, BSV 77, BSV 95, 2N5189
11334	2N3253(S)	75V, 1A, 1W, $< 50/70\text{ns}$	BSV 95, 2N3735, 2SC1069
11335	2N3254	Igt/Ih $< 0,02/ < 2\text{mA}$	2N2322A
11336	2N3255	2N3254, 30V	2N2323A
11337	2N3256	2N3254, 60V	2N2324A
11338	2N3257	2N3254, Igt/Ih $< 0,2/ < 3\text{mA}$	BRY58/30, TAG06Y, 2N6605, 2N2322
11339	2N3258	2N3255, Igt/Ih $< 0,2/ < 3\text{mA}$	BRY58/30, TAG06Y, 2N6605, 2N2323

11340	2N3259	2N3256, Igt/Ih<0,2/<3mA	BRY 58/60, TAG 06YY, 2N66065
11341	2N326	35V, 2A, 7W	2N1218
11342	2N3260	200/200V, 30A, 200W	2N6324...25
11343	2N3261	40V, 0,5A, 0,3W, <13/16ns	BSS 10, BSX 26, BSX 39
11344	2N3262	100V, 1,5A, 1W, <40/750ns	2SD854
11345	2N3265	2N3263, 125W	2N2817...18, 2N2821...22
11346	2N3266	2N3263, 120V, 125W	2N2817...18, 2N2821...22, 2N5539
11347	2N3267	15V, 0,02A, 0,075W, >900MHz	AF 139, AF 239(S), 2N3283...86
11348	2N3268	45V, 0,025A, 0,15W, >2,5MHz	BC 167, BC 182, BC 237, BC 547
11349	2N327(A,B)	40..50V, 0,05..0,1A, 0,33..0,4W	BC 212, BC 257, BC 307, BC 557
11350	2N3273	Igt/Ih<0,2/<2mA	TAG 106A, C 106A1, X 0403A, TAG 108A
11351	2N3274	2N3273, 200V	TAG 106B, C 106B1, X 0403B, TAG 108B
11352	2N3275	2N3273, 300V	TAG 106C, C 106C1, X 0403C, TAG 108C
11353	2N3276	2N3273, 400V	TAG 106D, C 106D1, X 0403D, TAG 108D
11354	2N3277	25V, Idss>0,15mA, Up<5V	2N5473...74, 2N5797
11355	2N3278	25V, Idss>0,4mA, Up<8V	BF 320A, 2N3809, 2N3820, 2N5475
11356	2N3279	30V, 0,05A, 500MHz	AF 139, AF 239(S)
11357	2N328(A,B)	30..50V, 0,05..0,1A, 0,33..0,4W	BC 212, BC 257, BC 307, BC 557
11358	2N3280	30V, 0,05A, 500MHz	AF 139, AF 239(S)
11359	2N3281	30V, 0,05A, 400MHz	AF 139, AF 239(S)
11360	2N3282	30V, 0,05A, 400MHz	AF 139, AF 239(S)
11361	2N3283	25V, 0,05A, 400MHz	AF 139, AF 239(S)
11362	2N3284	25V, 0,05A, 400MHz	AF 139, AF 239(S)
11363	2N3285	20V, 0,05A, 400MHz	AF 139, AF 239(S)
11364	2N3286	20V, 0,05A, 400MHz	AF 139, AF 239(S)
11365	2N3287	40V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11366	2N3288	40V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11367	2N3289	30V, 0,05A, 500MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11368	2N329(A,B)	20..50V, 0,05..0,1A, 0,33..0,4W	BC 212, BC 257, BC 307, BC 557
11369	2N3290	30V, 0,05A, 500MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11370	2N3291	25V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11371	2N3292	25V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11372	2N3293	20V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11373	2N3294	20V, 0,05A, 600MHz	BF 310, BF 314, BF 502, BF 505, BF 507
11374	2N3295(S)	60V, 0,25A, PEP0,3W(30MHz)	MRF 402, MRF 8003
11375	2N3296	60V, 0,7A, PEP3W(30MHz)	-
11376	2N3297	60V, 1,5A, PEP12W(30MHz)	-
11377	2N3298	25V, 0,1A, PQ>0,06W(80MHz)	BFX 59
11378	2N3299(S)	B>40	BSS 27, BSV 77, BSV 95, 2N5189
11379	2N33	8,5V, 7mA, 0,03W	AF 124...127, AF 200
11380	2N330(A)	20..50V, 0,05A, 0,33..0,38W	BC 212, BC 257, BC 307, BC 557
11381	2N3300(S)	2N3299, B>100	BSS 27, BSV 77, BSV 95, 2N5189
11382	2N3301	2N3299, 0,36W	BSS 26, BSV 59, BSX 49, 2N4014
11383	2N3302	2N3299, 0,36W, B>100	BSS 26, BSV 59, BSX 49, 2N4014
11384	2N3303	<15/25ns	BSS 28...29, BSV 69, 2N3724A, 2N5189

11385	2N3304	<60/60ns	BSX 36
11386	2N3305	50V, 0,6W, >20MHz, B>40	BC 161, BC 303...304, BSW 23, 2N2303
11387	2N3306	2N3305, B>100	BC 161, BC 303...304, BSW 23, 2N2303
11388	2N3307	40V, 0,05A, 0,2W, >300MHz	BF 324, BF 414, BF 506, BF 914, BF 936
11389	2N3308	30V, 0,05A, 0,2W, >300MHz	BF 324, BF 414, BF 506, BF 914, BF 936
11390	2N3309	50V, 0,5A, PQ>2W(250MHz)	BFS 23, BLY 34, 2SC2419
11391	2N3309A	PQ>2,2W(250MHz)	BFS 23, BLY 34, 2SC2419
11392	2N331	30V, 0,2W	AC 125...126, AC 151, 2SB54, 2SB56
11393	2N3310	35V, 0,2A, 0,3W, >300MHz	BFR 36, BFR 98, BFX 55, MRF 607
11394	2N3311	30V, 5A, 170W, B>60	2N1980...82, 2N2075...82, 2N2491...93
11395	2N3312	2N3311, 45V	2N1980...82, 2N2075...82, 2N2491...93
11396	2N3313	2N3311, 60V	2N1981...82, 2N2079...80, 2N2491...93
11397	2N3314	2N3311, B>100	2N1980...82, 2N2075...82, 2N2491...93
11398	2N3315	2N3311, 45V, B>100	2N1980...82, 2N2075...82, 2N2491...93
11399	2N3316	2N3311, 60V, B>100	2N1981...82, 2N2079...80, 2N2491...93
11400	2N3317	30/30/30V, 0,05A, 0,15W	2N2946
11401	2N3318	15/15/15V, 0,05A, 0,15W	2N2945
11402	2N3319	10/6/10V, 0,05A, 0,15W	2N2944
11403	2N332(A)	45V, 0,025A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11404	2N3320	15V, 0,1A, 0,06W, <20/35ns	2N705, 2N960...67, 2N2955...57
11405	2N3321	12V, 0,1A, 0,06W, <20/40ns	2N705, 2N960...67, 2N2955...57
11406	2N3322	12V, 0,1A, 0,06W, <20/45ns	2N705, 2N960...67, 2N2955...57
11407	2N3323	35V, 0,1A, 0,15W, >200MHz	AF 109R, AF 139, AF 239(S), 2N3283...86
11408	2N3324	35V, 0,1A, 0,15W, >200MHz	AF 109R, AF 139, AF 239(S), 2N3283...86
11409	2N3325	35V, 0,1A, 0,15W, >200MHz	AF 109R, AF 139, AF 239(S), 2N3283...86
11410	2N3326	60V, 0,8A, 0,8W, >250MHz	BSW 51...54, BSX 32, 2N2218...19(A)
11411	2N3327	65V, 2A, 20W, >100MHz	BLY 59, 2N3375
11412	2N3328	20V, Idss<1mA, Up<6V	-
11413	2N3329	2N2497	2N2497
11414	2N333(A)	45V, 0,025A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11415	2N3330	2N2498	2N2498
11416	2N3331	2N2499	2N2499
11417	2N3332	2N2500	2N2500
11418	2N3337	40V, 0,05A, 0,3W, >400MHz	BF 198...199, BF 224...225, BF 596...597
11419	2N3338	40V, 0,05A, 0,3W, >400MHz	BF 198...199, BF 224...225, BF 596...597
11420	2N3339	40V, 0,05A, 0,3W, >400MHz	BF 198...199, BF 224...225, BF 596...597
11421	2N334(A,B)	45..60V, 0,025A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11422	2N3340	30V, 0,03A, 0,4W, >70MHz	BC 168, BC 183, BC 238, BC 548
11423	2N3341	30V, 0,03A, 0,4W, >50MHz	BC 213, BC 258, BC 308, BC 558
11424	2N3342	20/8/20V, 0,05A, 0,25W	2N2944
11425	2N3343	25/8/25V, 0,05A, 0,25W	2N2944
11426	2N3344	30/30/30, 0,05A, 0,25W	2N2946
11427	2N3345	50/50/50, 0,05A, 0,25W	2N2946
11428	2N3346	50/50/50, 0,05A, 0,25W	2N2946
11429	2N335(A,B)	45..60V, 0,025A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547

11430	2N336(A)	45V, 0,025A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11431	2N3365	40V, Idss>0,8mA, Up<12V	-
11432	2N3366	40V, Idss>0,2mA, Up<7V	2N4119
11433	2N3367	40V, Idss>0,05mA, Up<2,5V	2N4118
11434	2N3368	40V, Idss>2mA, Up<12V	2SK113
11435	2N3369	40V, Idss>0,5mA, Up<12V	-
11436	2N337(A)	45V, 0,02A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11437	2N3370	40V, Idss>0,1mA, Up<3,2V	2N4118
11438	2N3371	25V, 0,1A, 0,15W, >400MHz	AF 139, AF 239(S), 2N3283...86
11439	2N3374	80V, 0,5A, PQ2,8W(130MHz)	BFS 23, BLY 34, 2SC2419
11440	2N3375	65V, 1,5A, PQ>3W(400MHz)	-
11441	2N3376	30V, Idss>0,6mA, Up<5V	-
11442	2N3377	2N3376	-
11443	2N3378	30V, Idss>3mA, Up<5V	-
11444	2N3379	2N3378	-
11445	2N338(A)	45V, 0,02A, 0,1..0,5W	BC 167, BC 182, BC 237, BC 547
11446	2N3380	30V, Idss>3mA, Up<9,5V	-
11447	2N3381	2N3380	-
11448	2N3382	30V, Idss>3mA, Up<5V	-
11449	2N3383	2N3382	-
11450	2N3384	30V, Idss>15mA, Up<5V	-
11451	2N3385	2N3384	-
11452	2N3386	30V, Idss>15mA, Up<9,5V	-
11453	2N3387	2N3386	-
11454	2N3388	125V, 2,5mA, 0,6W, >36MHz	BF 257...259, BF 657...659, 2N5058...59
11455	2N3389	195V, 7mA, 0,6W, >36MHz	BF 258...259, BF 658...659, 2N5058...59
11456	2N339(A)	55..60V, 0,06A..0,15A	BC 174, BC 190, BC 546, 2SC3245(A)
11457	2N3390	B>400	BC 168, BC 183, BC 238, BC 548
11458	2N3391(A)	2N3390, 160MHz, B>250	BC 168, BC 183, BC 238, BC 548
11459	2N3392	2N3390, >120MHz, B>150	BC 168, BC 183, BC 238, BC 548
11460	2N3393	2N3390, >120MHz, B>90	BC 168, BC 183, BC 238, BC 548
11461	2N3394	2N3390, >120MHz, B>55	BC 168, BC 183, BC 238, BC 548
11462	2N3395	2N3390, B>150	BC 168, BC 183, BC 238, BC 548
11463	2N3396	2N3390, B>90	BC 168, BC 183, BC 238, BC 548
11464	2N3397	2N3390, B>55	BC 168, BC 183, BC 238, BC 548
11465	2N3398	2N3390, B>55	BC 168, BC 183, BC 238, BC 548
11466	2N3399	20V, 7mA, 0,08W, >400MHz	AF 139, AF 239(S), 2N3283...86
11467	2N34(A)	25V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
11468	2N34/5	40V, 0,1A, 0,15W	AC 125...126, AC 151, ASY 48
11469	2N340(A)	85V, 0,06A..0,15A	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
11470	2N3400	20V, 0,1A, 0,15W, <90/260ns	2N2635, 2N2955...57
11471	2N3401	25/25/25V, 0,1A, 0,25W	2N2945
11472	2N3402	25V, 0,5A, 0,56W, B>75	BC 337...338, BC 635, BC 637, BC 639
11473	2N3403	2N3402, B>180	BC 337...338, BC 635, BC 637, BC 639
11474	2N3404	2N3402, 50V	BC 337, BC 637, BC 639, 2SD667

11475	2N3405	2N3402, 50V, B>180	BC 337, BC 637, BC 639, 2SD667
11476	2N3406	Iv>8mA	-
11477	2N3407	35V, 0,1A, 0,2W, >300MHz	BF 198...199, BF 224...225, BF 596...597
11478	2N3408	40V, 0,5A, 4W, >200MHz	-
11479	2N341(A)	125V, 0,06A..0,15A	BF 257, 2SC2240, 2SC2459, 2SC3245(A)
11480	2N3412	20V, 0,1A, 0,06W, >100MHz	2N3283...86, (AF 106, AF 109R, AF 306)
11481	2N3413	150/150/150V, 0,2A	-
11482	2N3414	2N3402, 0,36W	2N3402
11483	2N3415	2N3403, 0,36W	2N3403
11484	2N3416	2N3404, 0,36W	2N3404
11485	2N3417	2N3405, 0,36W	2N3405
11486	2N3418	85V, 5A, 15W(Tc100°), B>20	BUX 34, BUY 80, 2N5336...39
11487	2N3419	2N3418, 125V	BUX 34, BUY 80, 2N4895...97
11488	2N342(A,B)	60..85V, 0,06A..0,15A	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
11489	2N3420	2N3418, B>40	BUX 34, BUY 80, 2N5336...39
11490	2N3421	2N3418, 125V, B>40	BUX 34, BUY 80, 2N4895...97
11491	2N3426	<15/25ns	BSS 28...29, BSV 69, BSX 12, 2N3724A
11492	2N3427	45V, 0,5A, 0,2W, B>100	ASY 76...77, 2N1189...90
11493	2N3428	2N3427, B>150	ASY 76...77, 2N1189...90
11494	2N3429	50V, 5A, 150W	2N5387...89
11495	2N343(A,B)	60..65V, 0,06A..0,15A	BC 174, BC 190, BC 546, 2SC3245(A)
11496	2N3430	2N3429, 100V	2N5387...89
11497	2N3431	2N3429, 150V	2N5387...89
11498	2N3432	2N3429, 200V	2N5387...89
11499	2N3433	2N3429, 250V	2N5388...89
11500	2N3434	2N3429, 300V	2N5389
11501	2N3435	80V, 0,25A, 1W, >140MHz	BC 140...141, BC 300...301, 2N2218...19A
11502	2N3436	50V, Idss>3mA, Up<10	2N3368, 2SK113
11503	2N3437	50V, Idss>0,8mA, Up<5	2N5359
11504	2N3438	50V, Idss>0,2mA, Up<2,5	-
11505	2N3439(L,S)	450/350V, 1A, 1W	BUX 55, BUY 59...60, 2N5095
11506	2N344	5V, 5mA, 0,02W, 50MHz	AF 124...127, AF 200
11507	2N3440(L,S)	2N3439, 300/250V	BSS 48...49, BUX 55, BUY 59...60, 2N5092
11508	2N3441	160V, 3A, 25W, >0,8MHz	BD 241D, BD 243D, 2SD386(A)
11509	2N3441X	2N3441, -/80V	BD 241B, BD 537, BD 539B, BD 951
11510	2N3441Y	2N3441, -/100V	BD 241C, BD 539C, BD 953, 2SD712
11511	2N3442	160V, 10A, 117W, >0,8MHz	BD 245D, BDX 11, 2N3773, 2SD1047
11512	2N3443	20V, 0,1A, 0,3W, >75MHz	2N3323...25
11513	2N3444(S)	<50/70ns	
11514	2N3445	80V, 7,5A, 115W, 16MHz, B>20	BD 245B, BDV 93, BDX 93, 2N5874
11515	2N3446	2N3445, 100V	BD 245C, BDV 95, BDX 95, 2N5632...33
11516	2N3447	2N3445, B>40	BD 245B, BDV 93, BDX 93, 2N5874
11517	2N3448	2N3445, 100V, B>40	BD 245C, BDV 95, BDX 95, 2N5632...33
11518	2N3449	15V, 0,1A, 0,15W, >300MHz	2N705A, 2N964(A), 2N2635, 2N2955...57
11519	2N345	5V, 5mA, 0,02W, 50MHz	AF 124...127, AF 200



11520	2N3450	120V, 0,8A, 0,6W, <100/235ns	2N2102, 2N2405, 2N3019...20, 2SC2108
11521	2N3451	6V, 0,3W, >300MHz, <35/32ns	BSX 36
11522	2N3452	50V, Idss>0,8mA, Up<9,8	2N3365
11523	2N3453	50V, Idss>0,2mA, Up<4,8	2SK40, 2SK46, 2SK59
11524	2N3454	50V, Idss>0,05mA, Up<2,3	2N3367, 2N3370, 2N4118
11525	2N3455	50V, Idss>0,8mA, Up<9,8	2N3365
11526	2N3456	50V, Idss>0,2mA, Up<4,8	2SK40, 2SK46, 2SK59
11527	2N3457	50V, Idss>0,05mA, Up<2,3	2N3367, 2N3370, 2N4118
11528	2N3458	50V, Idss>3mA, Up<8	BF 244A, BF 245A, 2N3819, 2N3823
11529	2N3459	50V, Idss>0,8mA, Up<4	2N5359
11530	2N346	5V, 5mA, 0,02W, 75MHz	AF 124...125, AF 200
11531	2N3460	50V, Idss>0,2mA, Up<2	2N3367, 2N3370, 2N4118
11532	2N3461	60V, 3A, 5W(Tc25°)	2N1039...41, 2N2565...67
11533	2N3462	50V, 0,03A, 0,3W, >10MHz	BC 167, BC 182, BC 237, BC 547
11534	2N3463	60V, 0,03A, 0,3W, >45MHz	BC 174, BC 182, BC 190, BC 546
11535	2N3464	60V, 5A, 5W(Tc25°), >30MHz	BFT 32...34, BSS 45, 2N5336...39
11536	2N3465	40V, Idss>1mA, Up<10	-
11537	2N3466	40V, Idss>1mA, Up<10	-
11538	2N3467(S)	40V, 1A, 1W, >175MHz, B>40	2SA717, 2SA799
11539	2N3468(S)	2N3467, 50V, >150MHz, B>25	2SA717, 2SA799
11540	2N3469	35V, 5A, 1,2W, >20MHz	BFT 32...34, BSS 45, 2N5336...39
11541	2N347(A)	60V, 0,06A, 0,75W, 3MHz	BD 517, BD 519, BD 525, BD 527
11542	2N3470	50V, 10A, 150W, B>100	-
11543	2N3471	2N3470, 100V	-
11544	2N3472	2N3470, 150V	-
11545	2N3473	2N3470, 200V	-
11546	2N3474	50V, 10A, 150W, B>350	-
11547	2N3475	2N3474, 100V	-
11548	2N3476	2N3474, 150V	-
11549	2N3477	2N3474, 200V	-
11550	2N3478	30V, 0,2W, 900MHz	BF 377...378, BF 689, BF 763, 2N2857
11551	2N3479...3481	Ip<20μA, Iv>4mA	-
11552	2N348(A)	90V, 0,05A, 0,75W, 3MHz	BD 139, BD 389, BD 529, BD 829
11553	2N3482	2N3479, Ip<2μA	2N4852, 2N4892
11554	2N3483	2N3479, Ip<5μA	2N2646, 2N4871
11555	2N3484	2N3479, Ip<5μA	2N2646, 2N4871
11556	2N3485(A)	2N2906(A), 0,4W	2N2906(A)
11557	2N3486(A)	2N2907(A), 0,4W	2N2907(A)
11558	2N3487	80V, 7,5A, 117W, B>20	2N5288...89
11559	2N3488	2N3488, 100V	2N5288...89
11560	2N3489	2N3488, 120V, B>15	2N5288...89
11561	2N349(A)	125V, 0,05A, 0,75W, 3MHz	BD 424, BF 457, BF 857, 2SC2384
11562	2N3490	80V, 7,5A, 117W, B>40	2N5288...89
11563	2N3491	2N3490, 100V	2N5288...89
11564	2N3492	2N3490, 120V, B>30	2N5288...89



11565	2N3493	12V, 0,025A, 0,15W, >400MHz	BF 377...378, BF 689, BF 763, 2N2857
11566	2N3494(S)	80V, 0,1A, 0,6W, >200MHz	BC 303, BSV 17, 2SA606
11567	2N3495(S)	2N3494, 120V, >150MHz	2N3634...37, 2SA712
11568	2N3496	2N3494, 0,4W	BC 556, 2SA970, 2SA1049, 2SA1285(A)
11569	2N3497	2N3495, 0,4W	BF 398, 2SA970, 2SA1049, 2SA1285(A)
11570	2N3498(S)	B>40	BC 141, BC 300, BSW 39, 2N1990
11571	2N3499(S)	2N3498, B>100	BC 141, BC 300, BSW 39, 2N1990
11572	2N35	25V, 8mA, 0,05W	AC 127, ASY 28...29
11573	2N35/5	40V, 0,1A, 0,15W	AC 127, ASY 28
11574	2N350	40V, 3A, 10W(Tc75°)	AD 149, AUY 19...20, 2N2143...46
11575	2N3500(S)	2N3498, 150V, 0,3A	BSS 43, BSW 68, 2SC1860
11576	2N3501(S)	2N3498, 150V, 0,3A, B>100	BSS 43, BSW 68, 2SC1860
11577	2N3502	45V, 0,6A, 0,7W, <60/120ns	BC 161, BC 303...304, 2N3468, 2SA717
11578	2N3503	2N3502, 60V	BC 161, BC 303...304, 2SA717, 2SA742
11579	2N3504	2N3502, 0,4W	BC 416, BC 560, BSW 24, 2N2906...07(A)
11580	2N3505	2N3502, 60V, 0,4W	BC 416, BC 560, BSW 24, 2N2906...07(A)
11581	2N3506(S)	60V, 3A, 1W, <45/90ns	-
11582	2N3507(S)	2N3506, 80V	-
11583	2N3508	B>40	BSS 10, BSX 26, BSX 39, 2N3261
11584	2N3509	2N3508, B>100	BSS 10, BSX 26, BSX 39, 2N3261
11585	2N350A	2N350, 50V, 5A, 90W	AL 102...103, AUY 21...22, 2N1545...48
11586	2N351	40V, 3A, 10W(Tc75°)	AD 149, AUY 19...20, 2N2143...46
11587	2N3510	40V, 0,5A, 0,36W, <20/25ns	BSS 10, BSX 26, BSX 39, 2N3261
11588	2N3511	40V, 0,5A, 0,36W, <16/18ns	BSS 10, BSX 26, BSX 39, 2N3261
11589	2N3512	60V, 1A, 0,8W, <30/45ns	BSS 27, BSV 77, BSV 95, 2N5189
11590	2N351A	2N351, 50V, 5A, 90W	AL 102...103, AUY 21...22, 2N1545...48
11591	2N352	-/40V, 2A, 25W	AD 149, AUY 19...20, 2N2143...46
11592	2N3525	2N3228, 400V	400
11593	2N3526	130V, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...59
11594	2N3527	30V, 0,1A, 0,4W, >5MHz	BC 213, BC 258, BC 308, BC 558
11595	2N353	-/40V, 2A, 30W	AD 149, AUY 19...20, 2N2143...46
11596	2N354	25V, 0,05A, 0,15W	BC 213, BC 258, BC 308, BC 558
11597	2N3543	65V, 5A, PQ20W(50MHz)	-
11598	2N3544	25V, 0,1A, PQ16mW(1GHz)	BFX 59
11599	2N3545	20V, 0,2A, 0,36W, <60/90ns	BC 308, BC 558, BSW 24, 2N2906...07(A)
11600	2N3546	15V, 0,2A, 0,36W, <25/35ns	BSX 36
11601	2N3547	60V, 0,1A, 0,4W, >45MHz	BC 212, BC 256, BC 266, BC 556
11602	2N3548	60V, 0,1A, 0,4W, >60MHz	BC 212, BC 256, BC 266, BC 556
11603	2N3549	60V, 0,1A, 0,4W, >60MHz	BC 212, BC 256, BC 266, BC 556
11604	2N355	10V, 0,05A, 0,15W	BC 213, BC 258, BC 308, BC 558
11605	2N3550	60V, 0,1A, 0,4W, >60MHz	BC 212, BC 256, BC 266, BC 556
11606	2N3553	65V, 1A, PQ2,5W(175MHz)	BFW 47, BFS 23, BLY 34, 2SC2419
11607	2N3554	60V, 1,2A, 0,8W, <50/105ns	BSS 14, 2N3734...35, 2N5262
11608	2N3555	Igt/Ih<0,02/<3mA	2N2323A
11609	2N3556	2N3555, 60V	2N2324A

11610	2N3557	2N3555, 100V	2N2324A
11611	2N3558	2N3555, 200V	2N2326A
11612	2N3559	2N3555, Igt/Ih<0,2/<5mA	2N2323, 2N6333, TAG 615-100, MCR 606-2
11613	2N356(A)	20..30V, 0,5A, 0,1..0,15W	ASY 28...29, ASY 73...75
11614	2N3560	2N3556, Igt/Ih<0,2/<5mA	2N2324, 2N6334, TAG 615-100, MCR 606-3
11615	2N3561	2N3557, Igt/Ih<0,2/<5mA	2N2324, 2N6334, TAG 615-100, MCR 606-3
11616	2N3562	2N3558, Igt/Ih<0,2/<5mA	2N2326, 2N6335, TAG 615-200, MCR 606-4
11617	2N3563	30V, 0,05A, 0,2W, >600MHz	BF 377...378, BF 689, BF 763, 2N2857
11618	2N3564	30V, 0,05A, 0,2W, >600MHz	BF 370, BF 920...921(S), BF 959
11619	2N3565	30V, 0,05A, 0,2W, >40MHz	BC 168, BC 183, BC 238, BC 548
11620	2N3566	40V, 0,2A, 0,3W, >40MHz	BC 167, BC 182, BC 237, BC 547
11621	2N3567	B>40	BC 639, BCX 24, 2N3700...01, 2SD667
11622	2N3568	2N3567, 80/60V	BC 639, BCX 24, 2N3700...01, 2SD667
11623	2N3569	2N3567, B>100	BC 639, BCX 24, 2N3700...01, 2SD667
11624	2N357(A)	20..30V, 0,5A, 0,1..0,15W	ASY 28...29, ASY 73...75
11625	2N3570	30V, 0,05A, 1700MHz	BFR 37, BFW 30, BFX 59, BFX 73
11626	2N3571	30V, 0,05A, 1400MHz	BFR 37, BFW 30, BFX 59, BFX 73
11627	2N3572	30V, 0,05A, 1200MHz	BFR 37, BFW 30, BFX 59, BFX 73
11628	2N3573	25V, Idss>0,02mA, Up<2V	2N5471
11629	2N3574	25V, Idss>0,075mA, Up<2V	2N2841...42, 2N5472
11630	2N3575	25V, Idss>0,2mA, Up<4V	2N2843
11631	2N3576	20V, 0,2A, 0,36W, <30/50ns	BSX 36
11632	2N3578	20V, Idss>0,9mA, Up<4V	2N2608, 2N5266
11633	2N3579	B>30	BC 212, BC 256, BC 266, BC 556
11634	2N358(A)	20..30V, 0,5A, 0,1..0,15W	ASY 28...29, ASY 73...75
11635	2N3580	2N3579, B>60	BC 212, BC 256, BC 266, BC 556
11636	2N3581	B>50	BC 212, BC 257, BC 307, BC 557
11637	2N3582	2N3581, B>100	BC 212, BC 257, BC 307, BC 557
11638	2N3583	250/175V, 2A, 35W, >10MHz	BUX 84, TIP 75(A...C), 2N4240, 2SC3169
11639	2N3584	2N3583, 375/250V	BUX 84, TIP 75A...C, 2N4240, 2SC3169
11640	2N3585	2N3583, 500/300V	BUX 84, TIP 75C, 2N4240, 2SC3169
11641	2N3588	25V, 10mA, 0,1W, >200MHz	AF 106, AF 109R, AF 306, 2N3323...25
11642	2N3589	200V, 0,5A, >15MHz, B>30	BF 466...468, BF 757...759, MJE 340
11643	2N359	25V, 0,4A, 0,17W	AC 128, AC 152...153, AC 188
11644	2N3590	2N3589, B>75	BF 466...468, BF 757...759, MJE 340
11645	2N3591	2N3589	BF 466...468, BF 757...759, MJE 340
11646	2N3592	2N3589, B>75	BF 466...468, BF 757...759, MJE 340
11647	2N3593	2N3589	BF 466...468, BF 757...759, MJE 340
11648	2N3594	2N3589, B>75	BF 466...468, BF 757...759, MJE 340
11649	2N3595	2N3589	BF 466...468, BF 757...759, MJE 340
11650	2N3596	2N3589, B>75	BF 466...468, BF 757...759, MJE 340
11651	2N3597	60/40V, 20A, 100W(Tc100°)	2N2815...22, 2N5539
11652	2N3598	2N3597, 80/60V	2N2815...22, 2N5539
11653	2N3599	2N3597, 100/80V	2N2816...18, 2N2820...22, 2N5539
11654	2N36	20V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27

11655	2N360	32V, 0,4A, 0,17W	AC 128, AC 152...153
11656	2N3600	30V, 0,05A, 0,2W, >850MHz	BF 377...378, BF 689, BF 763, 2N2857
11657	2N3601	100V, 3,5A, 0,5W, >20MHz	-
11658	2N3602	100V, 3,5A, 0,75W, >20MHz	-
11659	2N3603	130V, 3,5A, 0,5W, >20MHz	-
11660	2N3604	130V, 3,5A, 0,75W, >20MHz	-
11661	2N3605	<35/45ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11662	2N3605A	2N3605, 40V	BSS 10...11, BSX 19...20, 2N2368...69(A)
11663	2N3606	2N3605, <40/60ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11664	2N3606A	2N3605, 40V, <40/60ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11665	2N3607	2N3605, <45/70ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11666	2N3608	25V, Idss<7mA, Up<6V	-
11667	2N361	32V, 0,4A, 0,17W	AC 128, AC 152...153
11668	2N3610	20V, Idss<0,6mA, Up<7V	-
11669	2N3611	40V, 7A, 77W, B>35	AL 102...103, AUY 22, 2N2288...93
11670	2N3612	2N3611, 60V	AL 102...103, AUY 22, 2N2292...93
11671	2N3613	2N3611, B>60	AL 102...103, AUY 22, 2N2288...93
11672	2N3614	2N3611, 60V, B>60	AL 102...103, AUY 22, 2N2292...93
11673	2N3615	80V, 7A, 77W, B>30	AL 102...103, AUY 22, 2N2292...93
11674	2N3616	2N3615, 100V	AL 102...103, 2N2290, 2N2293
11675	2N3617	2N3615, B>45	AL 102...103, AUY 22, 2N2292...93
11676	2N3618	2N3615, 100V, B>45	AL 102...103, 2N2290, 2N2293
11677	2N3619	>200MHz	BSS 15, BSV 84, BSX 64, 2N5320
11678	2N362	25V, 0,2A, 0,17W	AC 128, AC 152...153, AC 188
11679	2N3620	75V, 5A, 7,5W, >200MHz	-
11680	2N3621	75V, 10A, 30W, >200MHz	-
11681	2N3622	75V, 10A, 30W, >200MHz	-
11682	2N3623	>200MHz	BSS 15, BSV 84, BSX 64, 2N5320
11683	2N3624	75V, 5A, 7,5W, >200MHz	-
11684	2N3625	75V, 10A, 30W, >200MHz	-
11685	2N3626	75V, 10A, 30W, >200MHz	-
11686	2N3627	>200MHz	BSS 15, BSV 84, BSX 64, 2N5320
11687	2N3628	100V, 5A, 7,5W, >200MHz	-
11688	2N3629	100V, 10A, 30W, >200MHz	-
11689	2N363	32V, 0,2A, 0,17W	AC 128, AC 152...153
11690	2N3630	100V, 10A, 30W, >200MHz	-
11691	2N3631	20V, Idss>2mA, Up<6V	2N3797
11692	2N3632	65V, 3A, PQ13,5W(175MHz)	-
11693	2N3633	15V, 0,05A, 0,3W, <9/9ns	BSV 89...92, BSX 27, BSX 44, 2N2475
11694	2N3634(S)	140V, 1A, 1W, >150MHz, B>50	BFT 19A,B, BFT 28(A...C), 2N5415
11695	2N3635(S)	2N3634, B>100	BFT 19A,B, BFT 28(A...C), 2N5415
11696	2N3636(S)	2N3634, 175V	BFT 19A,B, BFT 28A...C, 2N5415
11697	2N3637(S)	2N3634, 175V, B>100	BFT 19A,B, BFT 28A...C, 2N5415
11698	2N3638(A)	25V, 0,5A, 0,3W, <90/170ns	BC 160...161, BC 303...304, 2N3072...73
11699	2N3639	6V, 0,08A, 0,2W, <30/32ns	BSX 36

11700	2N364	30V, 0,05A, 0,15W, 2,5MHz	AC 127, ASY 28, ASY 73...75
11701	2N3640	2N3639, 12V	BSX 36
11702	2N3641	0,35W,>250MHz,B>40	BC 337A, BC 637, BC 639, 2N3299...3300
11703	2N3642	2N3641, 60/45V	BC 337A, BC 637, BC 639, 2N3299...3300
11704	2N3643	2N3641, B>100	BC 337A, BC 637, BC 639, 2N3299...3300
11705	2N3644	45V, 0,5A, 0,3W, >200MHz	BC 327, BC 638, BC 640, 2N3072...73
11706	2N3645	2N3644, 60V	BC 327A, BC 638, BC 640, 2N3072...73
11707	2N3646	40V, 0,2A, 0,2W, <25/35ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11708	2N3647	2N3510, 0,4W	2N3510
11709	2N3648	2N3511, 0,4W	2N3511
11710	2N3649	mA,<15µs	BTW 28/500R, CS 15,9-04
11711	2N365	30V, 0,05A, 0,15W, 3MHz	AC 127, ASY 28, ASY 73...75
11712	2N3650	2N3649, 100V	BTW 28/500R, CS 15,9-04
11713	2N3651	2N3649, 200V	BTW 28/500R, CS 15,9-04
11714	2N3652	2N3649, 300V	BTW 28/500R, CS 15,9-04
11715	2N3653	2N3649, 400V	BTW 28/500R, CS 15,9-04
11716	2N3654	2N3649, <10µs	BTW 28/500R, CS 15,9-04
11717	2N3655	2N3650, <10µs	BTW 28/500R, CS 15,9-04
11718	2N3656	2N3651, <10µs	BTW 28/500R, CS 15,9-04
11719	2N3657	2N3652, <10µs	BTW 28/500R, CS 15,9-04
11720	2N3658	2N3653, <10µs	BTW 28/500R, CS 15,9-04
11721	2N3659	>50MHz	BSS 48...40, 2N3440, 2SD576
11722	2N366	30V, 0,05A, 0,15W, 3,5MHz	AC 127, ASY 28, ASY 73...75
11723	2N3660	40V, 1,5A, 5W(Tc25°), >25MHz	BC 461, BCX 60, BSV 17, 2N5322...23
11724	2N3661	2N3660, 60V	BC 461, BCX 60, BSV 17, 2N5322...23
11725	2N3662	18V, 0,025A, 0,2W, 1000MHz	BF 225, BF 314, BF 502, BF 505, BF 507
11726	2N3663	30V, 0,025A, 0,2W, 1000MHz	BF 225, BF 314, BF 502, BF 505, BF 507
11727	2N3664	60V, 0,5A, PQ>2,2W(250MHz)	-
11728	2N3665	B>40	BSS 42...43, 2N2102, 2N2405, 2N3019...20
11729	2N3666	2N3665, B>100	BSS 42...43, 2N2102, 2N2405, 2N3019...20
11730	2N3667	50V, 15A, 117W, >0,5MHz	BD 315, BD 745, BDX 13, 2N3055
11731	2N3668	Igt/Ih<40/<50mA	2N2575
11732	2N3669	2N3668, 200V	2N2576
11733	2N367	30V, 0,05A, 0,1W	AC 125...126, AC 151, ASY 26
11734	2N3670	2N3668, 400V	2N2578
11735	2N3671	60V, 0,6A, 0,6W, 35/80ns	2SA717, 2SA742
11736	2N3672	2N3671, 0,4W	BSW 24, 2N2906...07(A)
11737	2N3673	2N3671, 0,35W	BSW 24, 2N2906...07(A)
11738	2N3675	>1MHz	BSX 64, BUY 41, 2N4239, 2SC2214
11739	2N3676	2N3675, 90/90V	BSX 64, BUY 41, 2N4239, 2SC2214
11740	2N3677	30/20/30V, 0,1A, 0,4W, >5MHz	2N2946
11741	2N3678	75V, 0,8A, 0,8W, <40/250ns	BSW 39, BSW 53...54, 2N2218...19A, 2N3444
11742	2N3679	Iv>4,2mA	-
11743	2N368	30V, 0,05A, 0,1W	AC 125...126, AC 151, ASY 26
11744	2N3681	10V, 0,025A, 0,2W, >1000MHz	BF 377...378, BF 689, BF 763, 2N2857

11745	2N3682	40V, 0,2A, 0,36W, <12/-ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11746	2N3683	30V, 0,03A, 0,2W, >1000MHz	BF 377...378, BF 689, BF 763, 2N2857
11747	2N3684(A)	50V, Idss>2,5mA, Up<5V	BF 256A, BFS 71, 2N3822, 2N4221
11748	2N3685(A)	50V, Idss>1mA, Up<3,5V	BFW 12, 2N4340, 2N5484
11749	2N3686(A)	50V, Idss>0,4mA, Up<2V	2N4339, 2N5358, 2SK83, 2SK193, 2SK195
11750	2N3687(A)	50V, Idss>0,1mA, Up<1,2V	2N4117, 2SK92...93, 2SK103
11751	2N3688	40V, 0,03A, 0,2W, >400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
11752	2N3689	40V, 0,03A, 0,2W, >400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
11753	2N369	30V, 0,05A, 0,1W	AC 125...126, AC 151, ASY 26
11754	2N3690	40V, 0,03A, 0,2W, >400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
11755	2N3691	35V, 0,05A, 0,2W, 260MHz	BF 240...241, BF 254...255, BF 594...595
11756	2N3692	35V, 0,05A, 0,2W, 260MHz	BF 240...241, BF 254...255, BF 594...595
11757	2N3693	45V, 0,05A, 0,2W, 400MHz	BF 240...241, BF 254...255, BF 594...595
11758	2N3694	45V, 0,05A, 0,2W, 400MHz	BF 240...241, BF 254...255, BF 594...595
11759	2N3695	30V, Idss>1,75mA, Up<4,5V	2N2609
11760	2N3696	30V, Idss>0,5mA, Up<3,2V	-
11761	2N3697	30V, Idss>0,2mA, Up<1,8V	2N2843
11762	2N3698	30V, Idss>0,05mA, Up<1,1V	-
11763	2N37	20V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
11764	2N370	24V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
11765	2N370/33	2N370	AF 124...127, AF 200
11766	2N3700	B>100	BSS 59, 2SC2383, 2SC3228
11767	2N3701	2N3700, B>40	BSS 59, 2SC2383, 2SC3228
11768	2N3702	B>60	BC 212, BC 257, BC 307, BC 557
11769	2N3703	2N3702, 45V, B>30	BC 212, BC 257, BC 307, BC 557
11770	2N3704	B>100	BC 337, BC 637, BC 639, 2SD667
11771	2N3705	2N3704, B>50	BC 337, BC 637, BC 639, 2SD667
11772	2N3706	2N3704, 40V, B>30	BC 337, BC 635, BC 637, BC 639
11773	2N3707	30V, 0,03A, 0,36W, 80MHz	BC 169, BC 184, BC 239, BC 549
11774	2N3708	80MHz, B45..660	BC 168, BC 183, BC 238, BC 548
11775	2N3709	2N3708, B45..165	BC 168, BC 183, BC 238, BC 548
11776	2N371	24V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
11777	2N371/33	2N371	AF 124...127, AF 200
11778	2N3710	2N3708, B90..330	BC 168, BC 183, BC 238, BC 548
11779	2N3711	2N3708, B180..600	BC 168, BC 183, BC 238, BC 548
11780	2N3712(S)	150V, 0,2A, 1W, >40MHz	BF 257...259, BF 657...759, 2N5058...59
11781	2N3713		BD 545B, BD 315, 2N3772, 2N5632...34
11782	2N3714	2N3713, 100V	BD 545C, BD 317, 2N3772, 2N5632...34
11783	2N3715	2N3713, B>50	BD 545B, BD 315, 2N3772, 2N5632...34
11784	2N3716	2N3713, 100V, B>50	BD 545C, BD 317, 2N3772, 2N5632...34
11785	2N3717	60V, 1A, 7,5W(Tc25°), 250MHz	2N3553, 2SC2419
11786	2N3718	60V, 1A, 10W(Tc25°), 250MHz	BLY 60
11787	2N3719	<100/400ns	2N3867...68, 2N6303
11788	2N372	24V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
11789	2N372/33	2N372	AF 124...127, AF 200



11790	2N3720	2N3719, 60V	2N3868, 2N6303
11791	2N3721	18V, 0,1A, 0,36W, 120MHz	BC 168, BC 183, BC 238, BC 548
11792	2N3722	<62/130ns	BSV 95, 2N3725, 2SC1069
11793	2N3723	2N3722, 100V, <85/160ns	BSW 39, 2SC1069
11794	2N3724	20/55ns	BSV 77, BSV 95, 2N3722...23, 2N5189
11795	2N3724A	2N3724, 1,2A	BSS 14, 2N3734...35, 2N5262
11796	2N3725	2N3724, 80V	BSV 95, 2N3722...23, 2SC1069
11797	2N3725A	2N3725, 1,2A	BSS 14, 2N3735, 2N5262
11798	2N373	24V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
11799	2N373/33	2N373	AF 124...127, AF 200
11800	2N3730	200V, 3A, 10W(Tc55°)	AU 107, AU 113, AU 213, 2N5324
11801	2N3731	320V, 10A, 5W(Tc55°)	AU 106, AU 109, AU 111...112, 2N5325
11802	2N3732	100V, 3A, 3W(Tc55°)	AU 108, AU 110, AU 210
11803	2N3733	65V, 3A, PQ>10W(400MHz)	-
11804	2N3734(S)	<48/60ns	BSS 14, 2N5262
11805	2N3735(S)	2N3734, 75V	BSS 14, 2N5262
11806	2N3736	2N3734, 0,5W	-
11807	2N3737	2N3734, 75V, 0,5W	-
11808	2N3738	250/225V, 1A, 20W, >10MHz	BUW 40(A,B), BUX 84, 2N4296...97
11809	2N3739	2N3738, 325/300V	BUW 40(A,B), BUX 84, 2N4296...97
11810	2N374	24V, 10mA, 0,08W, 30MHz	AF 124...127, AF 200
11811	2N3740(A)		BD 244A, BD 540A, BDX 14, 2N6313...14
11812	2N3741(A)	2N3740, 80V	BD 244B, BD 540B, BDX 14, 2N6314
11813	2N3742(S)		
11814	2N3743(S)		
11815	2N3744	>30MHz	-
11816	2N3745	2N3744, 80V	-
11817	2N3746	2N3744, 100V	-
11818	2N3747	>40MHz	-
11819	2N3748	2N3747, 80V	-
11820	2N3749	2N3747, 100V	-
11821	2N375	80V, 3A, 106W	2N1536...48, 2N1541...43, 2N3615...18
11822	2N3750	>50MHz	-
11823	2N3751	2N3750, 80V	-
11824	2N3752	2N3750, 100V	-
11825	2N376	40V, 3A, 90W	2N1529...48, 2N2138...41, 2N2143...46
11826	2N3762(S)	>180MHz,<43/115ns	BSV 82, 2SA799
11827	2N3763(S)	2N3762, 60V	BSV 82, 2SA799
11828	2N3764(A)	2N3762, 0,5W	-
11829	2N3765	2N3762, 60V, 0,5W	-
11830	2N3766		BD 243B, BD 539B, BD 951, 2N3054
11831	2N3767	2N3766, 100V	BD 243C, BD 539C, BD 953, 2N3054
11832	2N376A	2N376, 50V, 5A	2N1535...38, 2N1545...48, 2N3615...18
11833	2N377	25V, 0,2A, 0,15W	ASY 28...29, ASY 73...75
11834	2N3770	10V, 0,05A, 0,05W, >100MHz	AF 106, AF 109R, AF 306, 2N3323...25

11835	2N3771	50V, 30A, 150W, >0,2MHz	BDX 41, BDY 29, MJ 802, 2SD630...631
11836	2N3772	100V, 20A, 150W, >0,2MHz	BDX 40, BDY 29, MJ 802, 2SD797
11837	2N3773	160V, 16A, 150W, >0,2MHz	BDW 32...36, BDX 50, MJ 15015, 2SC2608
11838	2N3774	5W(Tc100°),>1MHz,B>20	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11839	2N3775	2N3774, 60V	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11840	2N3776	2N3774, 80V	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11841	2N3777	2N3774, 100V	BSS 17, BSW 40, 2N5322
11842	2N3778	2N3774, B>10	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11843	2N3779	2N3774, 60V, B>10	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11844	2N377A	2N377, 40V	-
11845	2N378	40V, 5A, 106W	2N1529...38, 2N1539...48, 2N3611...18
11846	2N3780	2N3774, 80V, B>10	BSS 17...18, BSW 40, BSV 82, 2N5322...23
11847	2N3781	2N3774, 100V, B>10	BSS 17, BSW 40, 2N5322
11848	2N3782	2N3774, 3A, B>10	2N3719...20, 2N3867...68, 2N4234...36
11849	2N3783	30V, 0,02A, 0,15W, >800MHz	AF 139, AF 239(S), 2N3279...86
11850	2N3784	30V, 0,02A, 0,15W, >700MHz	AF 139, AF 239(S), 2N3279...86
11851	2N3785	15V, 0,02A, 0,15W, >700MHz	AF 139, AF 239(S), 2N3279...86
11852	2N3788	400/325V, 2A, 100W	BU 104, BU 606, BU 608
11853	2N3789		BD546A, BD316, 2N6029...31, 2N6229...31
11854	2N379	2N378, 80V	2N1536...38, 2N1546...48, 2N3615...18
11855	2N3790	2N3789, 80V	BD546B, BD318, 2N6029...31, 2N6229...31
11856	2N3791	2N3789, B>50	BD546A, BD316, 2N6029...31, 2N6229...31
11857	2N3792	2N3789, 80V, B>50	BD546B, BD318, 2N6029...31, 2N6229...31
11858	2N3793	B>20	BC 337, BC 635, BC 637, BC 639
11859	2N3794	2N3793, 100MHz, B>100	BC 337, BC 635, BC 637, BC 639
11860	2N3795	120V, 1A, 5W(Tc25°), >0,5MHz	2N3634...37, 2N5415
11861	2N3796	30V, Idss>0,5mA, Up<4V	-
11862	2N3797	30V, Idss>2mA, Up<7V	-
11863	2N3798	60V, 0,05A, 0,36W, B>150	2SA872(A), 2SA941...942, 2SA970
11864	2N3798A	2N3798, 90V	2SA872(A), 2SA941...942, 2SA970
11865	2N3799	2N3798, B>300	2SA872(A), 2SA941...942, 2SA970
11866	2N3799A	2N3798, 90V, B>300	2SA872(A), 2SA941...942, 2SA970
11867	2N38(A)	20V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
11868	2N380	2N378, 60V	2N1535...38, 2N1545...48, 2N3615...18
11869	2N381	50V, 0,4A, 0,225W, 3MHz	ASY 77, 2N1189...90
11870	2N3818	60V, 2A, PQ15W(100MHz)	BLY 35, 2N3632
11871	2N3819	25V, Idss>2mA, Up<8V	BF 244...245, BFS 72, 2N3823
11872	2N382	2N381, 4MHz	ASY 77, 2N1189...90
11873	2N3820	20V, Idss>0,3mA, Up<8V	BF 320A, 2N3909
11874	2N3821	50V, Idss>0,5mA, Up<4V	BFS 70, 2N4220, 2SK104, 2SK301
11875	2N3822	50V, Idss>2mA, Up<6V	BFS 71, BFS 80, BFW 11, 2N4416
11876	2N3823	30V, Idss>4mA, Up<8V	BF 244...245, BFS 72
11877	2N3824	Idss>12mA	BFS 73
11878	2N3825	30V, 0,1A, 0,25W, >200MHz	BC 168, BC 183, BC 238, BC 548
11879	2N3826	300MHz, B>40	BF 240...241, BF 254...255, BF 594...595



11880	2N3827	2N3826, B>100	BF 240...241, BF 254...255, BF 594...595
11881	2N3828	40V, 0,1A, 0,3W, >360MHz	BF 198...199, BF 224...225, BF 596...597
11882	2N3829	35V, 0,2A, 0,36W, <25/65ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
11883	2N383	2N381, 5MHz	ASY 77, 2N1189...90
11884	2N3830	80V, 1,2A, 1W, <60/70ns	BSS 14, BSV 95, 2N3735, 2N5262
11885	2N3831	2N3830, 70V	BSS 14, BSV 95, 2N3735, 2N5262
11886	2N3832	15V, 0,035A, 0,2W, <35/30ns	BSS 10...12, BSY 17...18, 2N3011
11887	2N3833	25V, 0,1A, >1GHz	BFT 12, 2SC3288, 2SC3368...69
11888	2N3834	25V, 0,1A, >1GHz	BFT 12, 2SC3288, 2SC3368...69
11889	2N3835	25V, 0,1A, >1GHz	BFT 12, 2SC3288, 2SC3368...69
11890	2N3839	30V, 0,04A, 0,2W, >1GHz	BF 357, BF 377...378, 2SC2498, 2SC3037
11891	2N384	70MHz	AF 106, AF 124...125, AF 200
11892	2N384/33	2N384	AF 106, AF 124...125, AF 200
11893	2N3840	50/50/50V, 0,1A, 0,4W	2N2946
11894	2N3841	100/100/80V, 0,1A, 0,3W	-
11895	2N3842	120/120/120V, 0,1A, 0,3W	-
11896	2N3843(A)	30V, 0,1A, 0,2W, >60MHz	BF 240...241, BF 254...255, BF 594...595
11897	2N3844(A)	30V, 0,1A, 0,2W, >90MHz	BF 240...241, BF 254...255, BF 594...595
11898	2N3845(A)	30V, 0,1A, 0,2W, >120MHz	BF 240...241, BF 254...255, BF 594...595
11899	2N3846	300/200V, 20A, 150W(Tc100°)	2N6324...25
11900	2N3847	2N3846, 400/300V	2N6325
11901	2N3848	300/200V, 20A, 150W(Tc100°)	2N6324...25
11902	2N3849	2N3848, 400/300V	2N6325
11903	2N385	25V, 0,2A, 0,15W, 6MHz	ASY 28...29, ASY 73...75
11904	2N3850	B>50	2N5002, 2N5004, 2N5284...85
11905	2N3851	2N3850, B>30	2N5002, 2N5004, 2N5284...85
11906	2N3852	2N3850, 60V	2N5002, 2N5004, 2N5284...85
11907	2N3853	2N3850, 60V, B>30	2N5002, 2N5004, 2N5284...85
11908	2N3854	B>35	BC 168, BC 183, BC 238, BC 548
11909	2N3854A	2N3854, 30V	BC 168, BC 183, BC 238, BC 548
11910	2N3855	2N3854, >130MHz, B>60	BC 168, BC 183, BC 238, BC 548
11911	2N3855A	2N3855, 30V	BC 168, BC 183, BC 238, BC 548
11912	2N3856	2N3854, >140MHz, B>100	BC 168, BC 183, BC 238, BC 548
11913	2N3856A	2N3856, 30V	BC 168, BC 183, BC 238, BC 548
11914	2N3857	45V, 0,5A, 0,6W, >20MHz	BC 160...161, BC 303...304, BC 638
11915	2N3858	B>60	BC 168, BC 183, BC 238, BC 548
11916	2N3858A	2N3858, 60V	BC 174, BC 182, BC 190, BC 546
11917	2N3859	2N3858, 140MHz, B>100	BC 168, BC 183, BC 238, BC 548
11918	2N3859A	2N3859, 60V	BC 174, BC 182, BC 190, BC 546
11919	2N385A	2N385, 40V, 8MHz	-
11920	2N386	60V, 3A, 12,5W(Tc75°)	AL 102...103, AUY 19...20, 2N2144...46
11921	2N3860	2N3858, 170MHz, B>150	BC 168, BC 183, BC 238, BC 548
11922	2N3860A	2N3860, 60V	BC 174, BC 182, BC 190, BC 546
11923	2N3861	530/530V, 0,025A, >50MHz	BD 232, BD 410, BUX 86...87, 2SC2899
11924	2N3862	50V, 0,2A, 0,36W, <78/50ns	BSX 39, 2N4014...14, 2SC1834

11925	2N3863	70V, 7,5A, 117W, >0,5MHz	BD 313, BD 545B, 2N3055, 2N5632...34
11926	2N3864	2N3863, 110V	BD 313, BD 545D, 2N3055, 2N5632...34
11927	2N3865	2N3863, 160V	BDX 11, BDY 54, 2N3442, 2SD733
11928	2N3866(A)	55V, 0,4A, PQ>1W(400MHz)	BFR 97
11929	2N3867	<100/400ns	2N3719...20
11930	2N3868	2N3867, 60V	2N3720
11931	2N3869	40V, 0,5A, >400MHz	BFS 51, BFR 98, BLW 16, 2SC2852
11932	2N387	80V, 3A, 12,5W(Tc75°)	AL 102...103, AUY 20, 2N2141, 2N2146
11933	2N3870	Igt/Ih<40/<70mA	MCR 3835-3, BStE4026M, MCR 63-3
11934	2N3871	2N3870, 200V	MCR 3835-4, BStE4026M, MCR 63-4
11935	2N3872	2N3870, 400V	MCR 3835-6, BStE4026M, MCR 63-6
11936	2N3873	2N3870, 600V	MCR 3835-8, BStE4040M, MCR 63-8
11937	2N3877	70V, 0,05A, 0,2W, 160MHz	BC 546, BSS 38, BSX 21, 2SC1890(A)
11938	2N3877A	2N3877, 85V	BC 546, BSS 38, BSX 21, 2SC1890(A)
11939	2N3878	120V, 4A, 35W, >40MHz	BDV 10...12, BDY 79, 2SD722(A,B)
11940	2N3879	120V, 7A, 35W, >40MHz	MJE 15030
11941	2N388	25V, 0,2A, 0,15W, 17MHz	ASY 28...29, ASY 73...75
11942	2N3880	30V, 0,2W, >1200MHz	BF 357, BF 377...378, BFR 37, BFW 99
11943	2N3881	60V, 1A, 0,6W, >70MHz	BC 140...141, 2N1990, 2N2102, 2N2405
11944	2N3882	30V, Idss>0,25mA, Up<3V	-
11945	2N3883	36/68ns	-
11946	2N388A	2N388, 40V	-
11947	2N3896	Igt/Ih<40/<70mA	MCR70-3, C228A, MCR3935-3, BStE4126M
11948	2N3897	2N3896, 200V	C228B, MCR3935-4, BStE4126M, C35B
11949	2N3898	2N3896, 400V	C228D, MCR3935-6, BStE4126M, C35D
11950	2N3899	2N3896, 600V	C228M, MCR3935-8, BStE4140M, C35M
11951	2N39	30V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
11952	2N3900(A)	18V, 0,1A, 0,36W, 160MHz	BC 169, BC 184, BC 239, BC 549
11953	2N3901	18V, 0,1A, 0,36W, 200MHz	BC 168, BC 183, BC 238, BC 548
11954	2N3902	700/325V, 2,5A, 100W(Tc75°)	BUS 11(A), BUX 46(A), 2SC3091, 2SC3155
11955	2N3903	B>50	BC 174, BC 182, BC 190, BC 546
11956	2N3904	2N3903, B>100	BC 174, BC 182, BC 190, BC 546
11957	2N3905	B<50	BC 212, BC 257, BC 307, BC 557
11958	2N3906	2N3905, B>100	BC 212, BC 257, BC 307, BC 557
11959	2N3909(A)	20V, Idss>0,3mA, Up<8V	BF 320, 2N3820, 2N5800
11960	2N3910	60/50/50V, 0,2A, 0,5W	-
11961	2N3911	60/40/40V, 0,2A, 0,5W	-
11962	2N3912	60/30/30V, 0,2A, 0,5W	-
11963	2N3913	2N3910, 0,4W	-
11964	2N3914	2N3911, 0,4W	-
11965	2N3915	2N3912, 0,4W	-
11966	2N3916	150/150V, 0,15A, 5W, >50MHz	BF 380, BF 415, MJE 340, 2SC2376
11967	2N3917	>80MHz, B>30	2SC1195
11968	2N3918	2N3917, B>100	2SC1195
11969	2N3919	,B>40	BUW 70, BUY 55, 2SC2769

11970	2N392	60V, 5A	2N1535...38, 2N1545...48, 2N3615...18
11971	2N3920	2N3919, B>100	BUW 70, BUY 55, 2SC2769
11972	2N3923	150V, 0,05A, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...59
11973	2N3924		
11974	2N3925	36V, 1A, PQ5W(175MHz)	BLY 55, BLY 57, BLY 78
11975	2N3926	36V, 1,5A, PQ7W(175MHz)	BLW 35, BLY 58
11976	2N3927	36V, 3A, PQ12W(175MHz)	BLY 58
11977	2N3928	80V, 3A, 5W(Tc25°), <35/75ns	2N3507
11978	2N3929	2N3928, 20W	-
11979	2N393	6/6/6V, 0,05A, 50MHz	-
11980	2N3930	180V, 0,05A, 0,4W, >40MHz	BF 436...437, BF 491...493, 2SA1370...71
11981	2N3931	2N3930, 0,7W	BFQ 36...37, BFT 44...45, 2SB606
11982	2N3932	30V, 0,2W, >750MHz	BF 377...378, BF 689, BF 763, 2N2857
11983	2N3933	40V, 0,2W, >750MHz	BF 377...378, BF 689, BF 763, 2N2857
11984	2N3936	Igt/Ih<60/<110mA	BTW 42/600R, TAG 9N400, TAG 15-100
11985	2N3937	2N3936, 200V	BTW 42/600R, TAG 9N400, TAG 15-200
11986	2N3938	2N3936, 300V	BTW 42/600R, TAG 9N400, TAG 15-300
11987	2N3939	2N3936, 400V	BTW 42/600R, TAG 9N400, TAG 15-400
11988	2N394	10/10/10V, 0,2A, 0,15W	ASY 26...27, ASY 48, ASY 76...77
11989	2N3940	2N3936, 500V	BTW 42/600R, TAG 9N600, TAG 15-500
11990	2N3945	70V, 1A, 5W(Tc25°), >60MHz	BC 140...141, 2N1990, 2N2102, 2N2405
11991	2N3946	<70/375ns,B>50	BC 182, BC 546, 2N2221...22(A)
11992	2N3947	2N3946, B>100	BC 182, BC 546, 2N2221...22(A)
11993	2N3948	36V, 0,4A, PQ>1W(400MHz)	BFS 50, MRF 629, 2SC2762, 2SC3185
11994	2N394A	2N394, 30/15/20V	ASY 26, ASY 48, ASY 76...77
11995	2N395	30V, 0,2A, 0,15W, 5MHz	ASY 26, ASY 48, ASY 76...77
11996	2N3950	65V, 3,3A, PQ50W(50MHz)	-
11997	2N3953	15V, 0,03A, 0,2W, >1300MHz	BF 377...378, BF 698, BF 763, 2N2857
11998	2N3959	20V, 0,03A, 0,4W, 5,4/4,9ns	-
11999	2N396(A)	30V, 0,2A, 0,15..0,2W, 9MHz	ASY 26, ASY 48, ASY 76...77
12000	2N3960	20V, 0,03A, 0,4W, 5,4/4,9ns	-
12001	2N3961	65V, 1A, PQ4W(175MHz)	BLY 60
12002	2N3962	60V, 0,2A, 0,36W, >40MHz	2SA970, 2SA1049, 2SA1136...37
12003	2N3963	80V, 0,2A, 0,36W, >40MHz	2SA970, 2SA1049, 2SA1136...37
12004	2N3964	45V, 0,2A, 0,36W, >50MHz	BC 416, BC 560, 2SA970, 2SA1136...37
12005	2N3965	60V, 0,2A, 0,36W, >50MHz	2SA970, 2SA1049, 2SA1136...37
12006	2N3966	<120/100ns	BFS 76, BFS 79
12007	2N3967(A)	30V, Idss>2,5mA, Up<6V	BF 256A, BFS 71, 2N3822, 2N4221
12008	2N3968(A)	30V, Idss>1mA, Up<3V	BFW 12, 2N4340, 2N5484
12009	2N3969(A)	30V, Idss>0,4mA, Up<1,7V	2N4339, 2N5358, 2SK83, 2SK195, 2SK238
12010	2N397	30V, 0,2A, 0,15W, 13MHz	ASY 26, ASY 48, ASY 76...77
12011	2N3970	40V, Idss>50mA, Up<10V	BFS 74, BFS 77...78, 2N4391, 2N4856
12012	2N3971	40V, Idss>25mA, Up<5V	2N4392, 2N5434
12013	2N3972	40V, Idss>5mA, Up<3V	2N4393
12014	2N3973	60V, 0,4A, 0,36W, <60/110ns	BSV 59, BSX 49, 2N2221...22(A), 2N4014

12015	2N3974	60V, 0,4A, 0,36W, <60/110ns	BSV 59, BSX 49, 2N2221...22(A), 2N4014
12016	2N3975	60V, 0,4A, 0,36W, <60/200ns	BSV 59, BSX 49, 2N2221...22(A), 2N4014
12017	2N3976	60V, 0,4A, 0,36W, <60/200ns	BSV 59, BSX 49, 2N2221...22(A), 2N4014
12018	2N3977	15/10/15V, 0,1A, 0,4W	2N2944
12019	2N3978	25/20/25V, 0,1A, 0,4W	2N2945
12020	2N3979	40/35/40V, 0,1A, 0,4W	2N2946
12021	2N398	105V, 0,1A, 0,05W	ACY 39, 2N2042...43
12022	2N3980	Ip<2μA, Iv>1mA	-
12023	2N3981	60V, 1A, 0,8W, <35/40ns	BSS 27, BSV 77, BSV 95, 2N5189
12024	2N3982	2N3981, 50V	BSS 27, BSV 77, BSV 95, 2N5189
12025	2N3983	30V, 0,03A, 0,2W, >500MHz	BF 225, BF 310, BF 314, BF 502, BF 505
12026	2N3984	30V, 0,03A, 0,2W, >400MHz	BF 225, BF 310, BF 314, BF 502, BF 505
12027	2N3985	30V, 0,03A, 0,2W, >300MHz	BF 225, BF 310, BF 314, BF 502, BF 505
12028	2N398A	2N398, 0,2A, 0,15W	ACY 39, 2N2042...43
12029	2N398B	2N398, 0,25W	ACY 39, 2N2042...43
12030	2N399	-/40V, 3A, 45W(Tc45°)	AD 149, AUY 19...20, 2N2143...46
12031	2N3993(A)	25V, Idss>10mA, Up<9,5V	MPF 970
12032	2N3994(A)	25V, Idss>2mA, Up<5,5V	MPF 971
12033	2N3995	20V, 0,1A, 0,3W, >600MHz	2N2929
12034	2N3996	>40MHz	2N5002, 2N5004, 2N5284...85
12035	2N3997	>40MHz	2N5002, 2N5004, 2N5284...85
12036	2N3998	>40MHz	2N5002, 2N5004, 2N5284...85
12037	2N3999	>40MHz	2N5002, 2N5004, 2N5284...85
12038	2N40	30V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
12039	2N400	50/40V, 3A, 45W(Tc45°)	AD 149, AUY 19...20, 2N2143...46
12040	2N4000	>40MHz	BUX 49, BUY 41
12041	2N4001	2N4000, 120V	BUX 49, BUY 41
12042	2N4002	>30MHz	2N2824...25
12043	2N4003	2N4002, 120V	2N2825
12044	2N4006	10/6/10V, 0,1A, 0,4W	2N2944
12045	2N4007	20/15/20V, 0,1A, 0,4W	2N2945
12046	2N4008	35/30/35V, 0,1A, 0,4W	2N2946
12047	2N4009	2N4006	2N2944
12048	2N401	-/40V, 3A, 45W(Tc45°)	AD 149, AUY 19...20, 2N2143...46
12049	2N4010	2N4007	2N2945
12050	2N4011	2N4008	2N2946
12051	2N4012	65V, 1,5A, PQ3W(800MHz)	-
12052	2N4013	50V, 1A, 0,36W, 20/55ns	2N3736...37
12053	2N4014	2N4013, 80V, 20/50ns	2N3737
12054	2N402	25V, 0,15A, 0,18W, B25	AC 125...126, AC 151, 2SB54, 2SB56
12055	2N4026	B>40	BC 327A, BC 638, BC 640, 2N2906...07(A)
12056	2N4027	2N4026, 80V	BC 640, BCX 39, 2SB647, 2N2906...07A
12057	2N4028	2N4026, B>100	BC 327A, BC 638, BC 640, 2N2906...07(A)
12058	2N4029	2N4026, 80V, B>100	BC 640, BCX 39, 2SB647, 2N2906...07A
12059	2N403	2N402, B33	AC 125...126, AC 151, 2SB54, 2SB56

12060	2N4030	2N4026, 0,8W	BC 161, BCX 60, BSW 40, 2N2904...05(A)
12061	2N4031	2N4027, 0,8W	BCX 60, BSW 40, 2N2904...05A, 2N4036
12062	2N4032	2N4028, 0,8W	BC 161, BCX 60, BSW 40, 2N2904...05(A)
12063	2N4033	2N4029, 0,8W	BCX 60, BSW 40, 2N2904...05A, 2N4036
12064	2N4034	<40/150ns,B>70	BFX 48, BSW 24, BSX 36, 2N3250...51(A)
12065	2N4035	2N4034, B>150	BFX 48, BSW 24, BSX 36, 2N3250...51(A)
12066	2N4036	90V, 1A, 1W, <110/700ns	BCX 60, BFR 23, BSW 40
12067	2N4037	60V, 1A, 1W, >60MHz	BC 161, BCX 60, BFR 24, BSW 40
12068	2N4038	50V, Idss<0,1mA, Up<2V	-
12069	2N4039	50V, Idss>0,1mA, Up<6V	-
12070	2N404	25V, 0,15A, 0,15W	ASY 26...27, ASY 48, ASY 76...77
12071	2N4040	65V, 3A, PQ>8W(400MHz)	BLW 94, BLX 94...95, MRF 323, 2SC1118
12072	2N4041	65V, 1A, PQ>3,3W(400MHz)	BLW 93, BLX 93, MRF 321, 2SC1040
12073	2N4046	50V, 0,5A, 0,8W, <45/75ns	BSS 27...29, BSV 77, 2N3724, 2SC1385
12074	2N4047	2N4046, 80V, 45/100ns	BSV 95, 2N3722...23, 2N3725, 2SC1069
12075	2N4048	45V, 60A, 170W, B>60	MP 500, MP 504
12076	2N4049	2N4048, 60V	MP 501, MP 505
12077	2N404A	2N404, 40V	-
12078	2N405	20V, 35mA, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
12079	2N4050	2N4048, 75V	MP 502, MP 506
12080	2N4051	2N4048, B>120	MP 500, MP 504
12081	2N4052	2N4048, 60V, B>120	MP 501, MP 505
12082	2N4053	2N4048, 75V, B>120	MP 502, MP 506
12083	2N4054	>15MHz	BF 617, BF 758...759, BF 859
12084	2N4055	2N4054, 250V	BF 615, BF 617, BF 757...759, BF 858...859
12085	2N4056	2N4054, 200V	BF 615, BF 617, BF 757...759, BF 858...859
12086	2N4057	2N4054, 150V	BF 615, BF 617, BF 757...759, BF 858...859
12087	2N4058	30V, 0,03A, 0,36W	BC 214, BC 259, BC 309, BC 559
12088	2N4059	30V, 0,03A, 0,36W, B>45	BC 213, BC 258, BC 308, BC 558
12089	2N406	2N405	AC 125...126, AC 151, 2SB54, 2SB56
12090	2N4061	2N4060, B>90	BC 213, BC 258, BC 308, BC 558
12091	2N4062	2N4060, B>180	BC 213, BC 258, BC 308, BC 558
12092	2N4063	2N3439, 10W	BD 410, 2SC3051, 2SC3425
12093	2N4064	2N3440, 10W	BD 410, BF 468, BF 668, 2SC3051
12094	2N4065	30V, Idss<12mA, Up<6V	-
12095	2N4068	150V, 0,2A, 0,5W, >50MHz	BF 257...259, BF 657...659, 2N5058...59
12096	2N4069	2N4068, 1W	BF 257...259, BF 657...659, 2N5058...59
12097	2N407	20V, 70mA, 0,15W, 6,8MHz	ASY 26...27
12098	2N4070	120/100V, 10A, 115W, >20MHz	BUW 70, BUY 55...56, BUX 17
12099	2N4071	2N4070, 200V	BUW 70, BUY 55...56, BUX 17
12100	2N4072	40V, 0,1A, PQ>0,25W(175MHz)	BFX 59, 2SC2053
12101	2N4073	40V, 0,15A, PQ>0,5W(175MHz)	BFR 36, BFW 16, MRF 207, MRF 607
12102	2N4074	40V, 0,3A, 0,4W, >50MHz	BC 337, BC 635, BC 637, BC 639
12103	2N4075	100V, 2A, 30W, >30MHz, B>30	2N5002, 2N5004, 2N5284...85
12104	2N4076	2N4076, B>50	2N5002, 2N5004, 2N5284...85



12105	2N4077	32V, 1A, 7,5W(Tc50°)	AD 161
12106	2N4078	32V, 1A, 7,5W(Tc50°)	AD 162
12107	2N4079	2N4077+4078	AD 161162
12108	2N408	2N407	ASY 26...27
12109	2N4080	20V, 0,05A, 0,3W, >1GHz	BF 316, BF 439, BF 516, BF 606
12110	2N4081	40V, 0,2W, >600MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12111	2N4086	12V, 0,1A, 0,2W, B>150	BC 168, BC 183, BC 238, BC 548
12112	2N4087(A)	2N4086, B>250	BC 168, BC 183, BC 238, BC 548
12113	2N4088	30V, Idss>5mA, Up<8V	BF 320B, 2N5462, 2N5465
12114	2N4089	30V, Idss>2mA, Up<5V	2SJ104, 2SJ107, 2SJ108
12115	2N409	13V, 15mA, 0,08W, 6,8MHz	AF 124...127, AF 200
12116	2N4090	30V, Idss>0,4mA, Up<3V	2N2844
12117	2N4091(A)	40..50V, Idss>30mA, Up<10V	BFS 74, BFS 77, 2N4856, 2N4859, 2N4391
12118	2N4092(A)	40..50V, Idss>15mA, Up<7V	BFS 75, BFS 77, 2N4857, 2N4860, 2N4392
12119	2N4093(A)	40..50V, Idss>8mA, Up<5V	BFS 75, BFS 77, 2N4857, 2N4860, 2N4392
12120	2N4094	40V, Idss>75mA, 25/40ns	2N5433
12121	2N4095	40V, Idss>20mA, 35/60ns	BFS 75, BFS 78, BSV 79, 2N4857, 2N4860
12122	2N4096	Igt/Ih<0,2/<2mA	BRY 58/60, 2N2323, 2N6333, TAG 615-100
12123	2N4097	2N4096, 100V	BRY 58/100, 2N2324, 2N6334, TAG 615-100
12124	2N4098	2N4096, 200V	BRY 58/200, 2N2326, 2N6335, TAG 615-200
12125	2N410	2N409	AF 124...127, AF 200
12126	2N4101	2N3228, 600V	BStC0540L, TAG 671-600, TAG 676-600
12127	2N4102	Igt/Ih<15/<20mA	TAG 612-600, TAG 613-600, TAG 606-600
12128	2N4103	2N3668, 600V	2N2579
12129	2N4104	60V, 0,05A, 0,3W, >60MHz	2N2483...84, 2N3117, 2SC2240, 2SC2459
12130	2N4105	25V, 1A	AC 176, AC 187
12131	2N4106	25V, 1A	AC 128, AC 153, AC 188
12132	2N4107	25V, 1A	AC 153176, AC 187188
12133	2N4108	2N4096	2N4096
12134	2N4109	2N4096	2N4096
12135	2N411	13V, 15mA, 0,08W, 16MHz	AF 124...127, AF 200
12136	2N4110	2N4096	2N4096
12137	2N4111	30W(Tc50°),>50MHz,B>40	BDY 90...91
12138	2N4112	2N4111, B>100	BDY 90...91
12139	2N4113	2N4111, 120V	BDY 90
12140	2N4114	2N4111, 120V, B>100	BDY 90
12141	2N4115	>50MHz	2N5284...85
12142	2N4116	>70MHz	2N5284...85
12143	2N4117(A)	40V, Idss>0,02mA, Up<1,8V	2SK92...93, 2SK103
12144	2N4118(A)	40V, Idss>0,08mA, Up<3V	2N3367, 2N3370
12145	2N4119(A)	40V, Idss>0,2mA, Up<6V	2N3366
12146	2N412	2N411	AF 124...127, AF 200
12147	2N4120	30V, Idss>0,5nA, Up<6V	-
12148	2N4121	B>70	BFX 48, BSW 24, BSX 36, 2N3905...06
12149	2N4122	2N4122, B>150	

12150	2N4123		BC 237, BC 547, BSW 41, 2N2221...22(A)
12151	2N4124	30V, 0,2A, 0,625W, 37/136ns	BC 238, BC 548, BSW 41, 2N2221...22(A)
12152	2N4125		BC 308, BC 558, BSW 24, 2N2906...07(A)
12153	2N4126	25V, 0,2A, 0,625W, 43/155ns	BC 308, BC 558, BSW 24, 2N2906...07(A)
12154	2N4127	60V, 2A, PQ>13,5W(175MHz)	BLW 24, BLY 92...93, 2SC2887
12155	2N4128	60V, 4A, PQ>24W(175MHz)	MRF 314A, 2SC2888
12156	2N413(A)	30V, 0,4A, 0,2W	ASY 76...77
12157	2N4130	80V, 10A, PQ50W(70MHz)	-
12158	2N4131	90V, 5A, 60W, >150MHz	-
12159	2N4132	90V, 0,6A, 7,5W, >200MHz	-
12160	2N4133	90V, 0,6A, >200MHz	-
12161	2N4134	30V, 0,03A, 0,2W, >350MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12162	2N4135	30V, 0,03A, 0,2W, >425MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12163	2N4137	40V, 0,2A, 0,36W, <15/20ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12164	2N4138	30V, 0,1A, 0,3W, >20MHz	2N2432
12165	2N4139	50V, Idss>8mA, Up<8V	BFW 10, 2N5363
12166	2N414(A,B,C)	30V, 0,4A, 0,2W	ASY 76...77
12167	2N4140	B>40	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12168	2N4141	2N4140, B>100	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12169	2N4142	B>40	BC 327A, BC 638, BSW 24, 2N2906...07(A)
12170	2N4143	2N4142, B>100	BC 327A, BC 638, BSW 24, 2N2906...07(A)
12171	2N4144	Igt/Ih<1/<5mA	2N1595A, TAG 2-50, MCR 1906-3
12172	2N4145	2N4144, 30V	2N1595A, TAG 2-50, MCR 1906-3
12173	2N4146	2N4144, 60V	2N1596A, TAG 2-100, MCR 1906-3
12174	2N4147	2N4144, 100V	2N1596A, TAG 2-100, MCR 1906-3
12175	2N4148	2N4144, 150V	2N1597A, TAG 2-200, MCR 1906-4
12176	2N4149	2N4144, 200V	2N1597A, TAG 2-200, MCR 1906-4
12177	2N415(A)	30V, 0,4A, 0,2W	ASY 76...77
12178	2N4150	>15MHz	BFT 33...34, BUX 34, BUY 80, 2N5338...39
12179	2N416	30V, 0,4A, 0,2W	ASY 76...77
12180	2N417	30V, 0,4A, 0,2W	ASY 76...77
12181	2N418	100V, 5A, 25W(Tc45°)	AL 102...103, AUY 28, 2N1542...43
12182	2N419	55V, 3A, 25W(Tc45°)	AD 149, AUY 19...20, 2N2144...46
12183	2N4199	Igt/Ih<50/3mA, <20µs	T6F300C, TAG15S-400, C234D, MCR1718-5
12184	2N42	30V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
12185	2N420	65V, 5A, 25W(Tc45°)	AL 102...103, AUY 28, 2N1546...48
12186	2N4200	2N4199, 400V	T6F400C, TAG15S-400, C234D, MCR1718-6
12187	2N4201	2N4199, 500V	T6F500C, TAG15S-500, C234E, MCR1718-7
12188	2N4202	2N4199, 600V	T6F600C, TAG15S-600, C234M, MCR1718-8
12189	2N4203	2N4199, 700V	T6F700C, TAG15S-700, T12F700, 2N691S
12190	2N4204	2N4199, 800V	T6F800C, TAG15S-800, T12F800, 2N692S
12191	2N4205	2N4199, 900V	TAG 15S-900, T 12F900, TAG 35S-900
12192	2N4206	2N4199, 1000V	TAG 15S-1000, T 12F1000, TAG 35S-1000
12193	2N4207	6V, 0,05A, 0,35W, <25/25ns	BSX 36
12194	2N4208	12V, 0,05A, 0,35W, <25/30ns	BSX 36



12195	2N4209	15V, 0,05A, 0,35W, <25/30ns	BSX 36
12196	2N420A	2N420, 90V	AL 102...103, AUY 28, 2N1547...48
12197	2N4210	>10MHz	2N2815...22
12198	2N4211	2N4210, 100/80V	2N2815...18, 2N2820...22
12199	2N4212	25V, 1,6A, Igt/Ih<0,1/3mA	2N2322, 2N6332, TAG 615-100
12200	2N4213	2N4212, 50V	2N2323, 2N6333, TAG 615-100
12201	2N4214	2N4212, 100V	2N2324, 2N6334, TAG 615-100
12202	2N4215	2N4212, 150V	2N2325, 2N6335, TAG 615-200
12203	2N4216	2N4212, 200V	2N2326, 2N6335, TAG 615-200
12204	2N4217	2N4212, 250V	2N2327, 2N6336, TAG 615-300
12205	2N4218	2N4212, 300V	2N2328, 2N6336, TAG 615-300
12206	2N4219	2N4212, 400V	2N2329, 2N6337, TAG 615-400
12207	2N422	35V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
12208	2N4220(A)	30V, Idss>0,5mA, Up<4V	BFS 70, 2N3821, 2SK104, 2SK301
12209	2N4221(A)	30V, Idss>2mA, Up<6V	BFS 71, 2N3822, 2N4341, 2N5361, 2N5458
12210	2N4222(A)	30V, Idss>5mA, Up<8V	BF 244...245, BFS 72, 2N3823, 2N5459
12211	2N4223	30V, Idss>3mA, Up<8V	BF 244...245
12212	2N4224	30V, Idss>2mA, Up<8V	BF 244...245
12213	2N4225	80V, 3A, 5W(Tc25°), <35/75ns	2N3507
12214	2N4226	2N4225, 100V	-
12215	2N4227	60V, 0,2A, 0,3W, <50/310ns	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12216	2N4228	60V, 0,2A, 0,3W, <50/110ns	BC 327A, BC 638, BSW 24, 2N2906...07(A)
12217	2N422A	2N422, 0,2A, 0,185W	AC 125...126, AC 151, 2SB54, 2SB56
12218	2N4231	50V, 3A, 35W, >4MHz	BD 241, BD 535, BD 539A, 2N3054
12219	2N4231A	2N4231, 5A, 75W	BD 243, BD 949, BD 539A, 2N3054
12220	2N4232	2N4231, 70V	BD 241A, BD 537, BD 539B, 2N3054
12221	2N4232A	2N4231, 5A, 75W	BD 243A, BD 951, BD 539B, 2N3054
12222	2N4233	2N4231, 90V	BD 241B, BD 937, BD 539C, 2N3054
12223	2N4233A	2N4231, 90V	BD 243B, BD 953, BD 539C, 2N3054
12224	2N4234		BFT 35...37, BSS 46, 2N6190...93
12225	2N4235	2N4234, 60V	BFT 35...37, BSS 46, 2N6190...93
12226	2N4236	2N4234, 80V	BFT 35...37, BSS 46, 2N6190...93
12227	2N4237	50V, 3A, 1W, >2MHz	BFT 32...34, BSS 63...64, 2N5336...39
12228	2N4238	2N4237, 80V	BFT 32...34, BSX 63...64, 2N5336...39
12229	2N4239	2N4238, 100V	BFT 33...34, BSX 64, 2N5338...39, 2SC2214
12230	2N4240		BUW 40A,B, BUX 84, 2N3585, 2SC3169
12231	2N4241(MP)	32, 5A, 37W	AL 102...103, AUY 28, 2N3611...18
12232	2N4242	80, 10A, 106W, B>40	2N1559...60, 2N2289...90, 2N2292...93
12233	2N4243	2N4242, 60V	2N1558...60, 2N2289...90, 2N2292...93
12234	2N4244	2N4242, 40V	2N1557...60, 2N2288...90, 2N2291...93
12235	2N4245	2N4242, B>60	2N1559...60, 2N2289...90, 2N2292...93
12236	2N4246	2N4242, 60V, B>60	2N1558...60, 2N2289...90, 2N2292...93
12237	2N4247	2N4242, 40V, B>60	2N1557...60, 2N2288...90, 2N2291...93
12238	2N4248	40V, 0,1A, 0,2W, B>50	BC 415...416, BC 560, 2SA970, 2SA1137
12239	2N4249	2N4248, 60V, B>100	2SA970, 2SA1049, 2SA1136...37

12240	2N425	30V, 0,4A, 0,15W, B>20	ASY 76...77
12241	2N4250	2N4248, B>250	BC 415...416, BC 560, 2SA970, 2SA1137
12242	2N4250A	2N4248, 60V, B>250	2SA970, 2SA1049, 2SA1136...37
12243	2N4251	15V, 0,1A, 0,25W, <20/60ns	-
12244	2N4252	30V, 0,05A, >600MHz, B>50	BF 240...241, BF 254...255, BF 594...595
12245	2N4253	2N4252, B>30	BF 240...241, BF 254...255, BF 594...595
12246	2N4254	2N4252, 0,25W	BF 240...241, BF 254...255, BF 594...595
12247	2N4255	2N4252, 0,25W, B>30	BF 240...241, BF 254...255, BF 594...595
12248	2N4256	4/40ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
12249	2N4257(A)	6V, 0,05A, 0,2W, >500MHz	BSX 36
12250	2N4258(A)	12V, 0,05A, 0,2W, >700MHz	BSX 36
12251	2N4259	40V, 0,175W, 1GHz	BF 377...378, BF 689, BF 763, 2N2857
12252	2N426	2N425, B>30	ASY 76...77
12253	2N4260	1,5/2ns	-
12254	2N4262	25V, 0,2A, >900MHz	-
12255	2N4263	2N4262	-
12256	2N4264	B>40	BSS 10...11, BSX 19...20, 2N2368...69(A)
12257	2N4265	2N4264, B>100	BSS 10...11, BSX 19...20, 2N2368...69(A)
12258	2N4266	2N4264, B40..400	BSS 10...11, BSX 19...20, 2N2368...69(A)
12259	2N4267	30V, Idss<1nA, Up<6V	-
12260	2N4268	30V, Idss<1nA, Up<6V	-
12261	2N4269	200V, 0,03A, 0,36W	BF 298...299, BF 422, 2SC3467
12262	2N427	2N425, B>40	ASY 76...77
12263	2N4270	2N4269, 0,2W	BF 258...259, BF 658...659, 2N5058...59
12264	2N4271	>20MHz	BSS 48...49, BUX 50...52, 2N3439...40
12265	2N4272	>10MHz	BUX 50...52, 2SC1861...62, 2SD625
12266	2N4273	175V, 2,5A, 25W, >10MHz	BD 241F, BUX 67, 2SD386(A), 2SD1138
12267	2N4274	<12/12ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
12268	2N4275	2N4274, 40V	BSV 91...92, BSX 92...93, 2N2368...69(A)
12269	2N4276	30V, 60A, 170W, B>60	2N5435...40
12270	2N4277	2N4276, B>120	2N5435...40
12271	2N4278	2N4276, 45V	2N5435...40
12272	2N4279	2N4276, 45V, B>120	2N5435...40
12273	2N428	2N425, B>60	ASY 76...77
12274	2N4280	2N4276, 60V	2N5435...40
12275	2N4281	2N4276, 60V, B>120	2N5435...40
12276	2N4282	2N4276, 75V	2N5435...40
12277	2N4283	2N4276, 75V, B>120	2N5435...40
12278	2N4284	25/25/25V, 0,05A, 0,25W	-
12279	2N4285	2N4284, 35/35/35V	-
12280	2N4286	30V, 0,05A, 0,25W	BC 168, BC 183, BC 238, BC 548
12281	2N4287	2N4286, 45V	BC 167, BC 182, BC 237, BC 547
12282	2N4288	30V, 0,05A, 0,25W, 150MHz	BC 214, BC 259, BC 309, BC 559
12283	2N4289	2N4288, 60V	2SA872(A), 2SA970, 2SA1049, 2SA1137
12284	2N428A	2N425, B>80	ASY 76...77

12285	2N4290	30V, 0,2A, 0,25W, 150MHz	BC 214, BC 259, BC 309, BC 559
12286	2N4291	2N4290, 40V	BC 415...416, BC 560, 2SA872(A), 2SA970
12287	2N4292	30V, 0,06A, 0,2W, 730MHz	BF 225, BF 314, BF 502, BF 505, BF 507
12288	2N4293	30V, 0,06A, 0,2W, 730MHz	BF 225, BF 314, BF 502, BF 505, BF 507
12289	2N4294	30V, 0,2A, 0,2W, <21/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12290	2N4295	40V, 0,2A, 0,2W, <24/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12291	2N4296	B>50	BUW 40(A,B), TIP 47...50, 2N4240
12292	2N4297	2N4296, B>75	BUW 40(A,B), TIP 47...50, 2N4240
12293	2N4298	2N4296, 500/350V, B>25	BUW 40A,B, BUX 84, TIP 50, 2N4240
12294	2N4299	2N4296, 500/350V, B>50	BUW 40A,B, BUX 84, TIP 50, 2N4240
12295	2N43(A)	45V, 0,3A, 0,15W	ASY 48, ASY 76...77, 2N1189...1190
12296	2N4300	>30MHz	BUX 49, BUY 41, 2SC1860
12297	2N4301	50W(Tc100°),>40MHz	2N5288...89, 2N5542
12298	2N4302	30V, Idss>0,5mA, Up<4V	BFS 70, 2N3821, 2N4220, 2SK104, 2SK301
12299	2N4303	30V, Idss>4mA, Up<6V	BFS 80, BFW 11, 2N4416, 2N5362, 2N5245
12300	2N4304	30V, Idss>0,5mA, Up<10V	2N3365
12301	2N4305	B>50	BFT 34, BUX 34, BUY 80, 2N4895...97
12302	2N4306	2N4305, 30W	-
12303	2N4307	2N4305, 100V	BFT 33, BUX 34, BUY 80, 2N4895...97
12304	2N4308	2N4307, 30W	-
12305	2N4309	2N4305, B>40	BFT 34, BUX 34, BUY 80, 2N4895...97
12306	2N4310	2N4309, 30W	-
12307	2N4311	2N4305, 100V, B>40	BFT 33, BUX 34, BUY 80, 2N4895...97
12308	2N4312	2N4311, 30W	-
12309	2N4313	12V, 0,1A, 0,2W, <25/35ns	BSX 36
12310	2N4314	90V, 1A, 1W, >60MHz	BCX 60, BSS 17, BSV 17, 2N3634...37
12311	2N4316	Igt/Ih<15/<25mA	BStC0506, TAG 671-100, TAG 676-100
12312	2N4317	2N4316, 200V	BStC0513, TAG 671-200, TAG 676-200
12313	2N4318	2N4316, 300V	BStC0526, TAG 671-300, TAG 676-300
12314	2N4319	2N4316, 400V	BStC0526, TAG 671-400, TAG 676-400
12315	2N432	30V, 0,1A, 0,15W, >10MHz	-
12316	2N433	30V, 0,1A, 0,15W, >10MHz	-
12317	2N4338	50V, Idss>0,2mA, Up<1V	BFW 13
12318	2N4339	50V, Idss>0,5mA, Up<1,8V	2N5358, 2SK83, 2SK193, 2SK195, 2SK238
12319	2N4340	50V, Idss>1,2mA, Up<3V	BFW 12, 2N5484
12320	2N4341	50V, Idss>3mA, Up<6V	BF 256, BFS 71, 3N3822, 2N4221, 2N5361
12321	2N4342	25V, Idss>4mA, Up<5,5V	2N5116
12322	2N4343	25V, Idss>10mA, Up<10	BFT 11
12323	2N4346	320/60V, 10A, 5W(Tc80°)	AU 106, AU 109, AU 111...112, 2N5325
12324	2N4347	140V, 5A, 100W, >0,2Mhz	BDX 12, 2N5760, 2SD732...733, 2SD551
12325	2N4348	140V, 10A, 120W, >0,2MHz	BDX 51, 2N5634, 2SD732...733, 2SD551
12326	2N4349	65V, 2A, 7W(Tc25°), <55/165ns	BSS 14, 2N5262
12327	2N4350	>300MHz	BSS 27, BSV 95, 2N3722...23, 2SC1386
12328	2N4351	30V, Idss<10nA, Up<5V	-
12329	2N4352	30V, Idss<10nA, Up<5V	-

12330	2N4353	30V, Idss<5nA, Up<5V	-
12331	2N4354	60V, 0,5A, 0,35W, <100/400ns	BC 327A, BC 638, BSW 24, 2N2906...07(A)
12332	2N4355	60V, 0,5A, 0,35W, <100/400ns	BC 327A, BC 638, BSW 24, 2N2906...07(A)
12333	2N4356	80V, 0,5A, 0,35W, <100/400ns	BC 640, BCX 39, 2SB647, 2N4029
12334	2N4357	240V, 0,05A, 0,4W, >40MHz	BF 436...437, BF 492...493, 2SA1371
12335	2N4358	2N4357, 0,7W	BFQ 36...37, BFT 44...45, 2SB606
12336	2N4359	45V, 0,05A, 0,36W, >20MHz	BC 212, BC 257, BC 307, BC 557
12337	2N4360	20V, Idss>3mA, Up<10V	-
12338	2N438(A)	>2,5MHz	ASY 73...75
12339	2N4381	25V, Idss>3mA, Up<5V	2N5461, 2N5464
12340	2N4382	25V, Idss>10mA, Up<9V	BFT 11, 2N4343
12341	2N4383	40V, 0,8A, 0,8W, >120MHz	BC 140...141, BC 300...302, 2N3053
12342	2N4384	2N4383, 0,5W	BC 337, BC 635, BC 637, BC 639
12343	2N4385	40V, 0,8A, 0,8W, >120MHz	BC 140...141, BC 300...302, 2N3053
12344	2N4386	2N4385, 0,5W	BC 337, BC 635, BC 637, BC 639
12345	2N4387	40V, 2A, 20W	BD 240, BD 242, BD 934, 2N3740...41
12346	2N4388	2N4387, 60V	BD 240A, BD 242A, BD 936, 2N3740...41
12347	2N4389	12V, 0,1A, 0,2W, <25/105ns	BSX 36, 2N4313
12348	2N439(A)	30V, 0,4A, 0,1..0,15W, >5MHz	ASY 73...75
12349	2N4390	120V, 0,5W, >50MHz	BF 297...299, BSS 38, BSX 21, 2SC3467
12350	2N4391	40V, Idss>50mA, Up<10V	BFS 74, BFS 77, BSV 78, 2N3970, 2N4859
12351	2N4392	40V, Idss>25mA, Up<5V	2N3971, 2N5434
12352	2N4393	40V, Idss>5mA, Up<3V	2N3972
12353	2N4395	60V, 5A, 62W, >4MHz	BD 245A, BDV 91, BDX 91, 2N4914...15
12354	2N4396	2N4395, 80V	BD 245B, BDV 93, BDX 93, 2N5758...60
12355	2N4397	40V, 0,2W, >600MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12356	2N4398		
12357	2N4399	2N4398, 60V	MJ 4502
12358	2N44(A)	45V, 0,3A, 0,15W	ASY 48, ASY 76...77, 2N1189...1190
12359	2N440(A)	30V, 0,4A, 0,1..0,15W, >10MHz	ASY 73...75
12360	2N4400		BC 337A, BC 637, BC 639, 2N2221...22(A)
12361	2N4401	2N4400, B>100	BC 337A, BC 637, BC 639, 2N2221...22(A)
12362	2N4402		BC 327, BC 638, BC 640, 2N2906...07(A)
12363	2N4403	2N4402, B>100	BC 327, BC 638, BC 640, 2N2906...09(A)
12364	2N4404	B>40	BSV 82, BSW 40, 2N4031, 2N4033, 2N4036
12365	2N4405	2N4404, B>100	BSV 82, BSW 40, 2N4031, 2N4033, 2N4036
12366	2N4406	B>25	BSV 82, 2N6303
12367	2N4407	2N4406, B>75	BSV 82, 2N6303
12368	2N4409	80V, 0,25A, 0,625W, >60MHz	BF 391, BFP 22, MPSA 43, 2SC1670
12369	2N441	40V, 15A, 150W	2N1980...82, 2N2077...78, 2N2491
12370	2N4410	2N4409, 120V	BF 391, BFP 22, MPSA 43, 2SC1670
12371	2N4412	B>100	BC 160...161, BC 303...304, 2N2904...05
12372	2N4412A	2N4412, 60V	BC 161, BC 303...304, 2N2904...05A
12373	2N4413(A)	2N4412(A), 0,4W	BC 327A, BC 638, BC 640, 2N2906...07A
12374	2N4414	2N4412, B>40	BC 160...161, BC 303...304, 2N2904...05

12375	2N4414A	2N4412, 60V, B>40	BC 161, BC 303...304, 2N2904...05A
12376	2N4415(A)	2N4414(A), 0,4W	BC 327A, BC 638, BC 640, 2N2906...07A
12377	2N4416	30V, Idss>5mA, Up<6V	BF 256, BFS 80, BFW 11, 2N5245, 2N5398
12378	2N4416A	2N4416, 35V	BF 256, BFS 80, BFW 11, 2N5245, 2N5398
12379	2N4417(A)	2N4416(A)	BF 256, BFS 80, BFW 11, 2N5245, 2N5398
12380	2N4418	<22/26ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12381	2N4419	<24/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12382	2N442	2N441, 50V	2N1980...82, 2N2077, 2N2081, 2N2491
12383	2N4420	<13/25ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12384	2N4421	<22/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12385	2N4422	<25/35ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12386	2N4423	<45/55ns	BSX 36, 2N4313
12387	2N4424	60V, 0,5A, 0,36W	BC 337A, BC 637, BC 640, 2SD667
12388	2N4425	2N4424, 0,56W	BC 337A, BC 637, BC 640, 2SD667
12389	2N4427	0,4A,1W,PQ0,4W(400MHz)	BFR 98, BFS 50, MRF 515, MRF 629, 2N3948
12390	2N4428	55V, 0,4A, PQ0,75W(500MHz)	BFR 97, 2N3866
12391	2N4429	55V, 0,425A, PQ>1W(1GHz)	BLX 91
12392	2N443	2N441, 60V	2N1981...82, 2N2075...76, 2N2491
12393	2N4430	55V, 1A, PQ>2,5W(1GHz)	BLW 98, BLX 98
12394	2N4431	55V, 2A, PQ>5W(1GHz)	2SC3141
12395	2N4432(A)	50V, 0,2A, 0,6W, 250MHz	BC 140...141, BC 300...302, 2N2218...19
12396	2N4433	50V, 0,03A, 0,145W, 200MHz	BF 240...241, BF 254...255, BF 594...595
12397	2N4434	30V, 0,03A, 0,145W, 300MHz	BF 240...241, BF 254...255, BF 594...595
12398	2N4435	30V, 0,03A, 0,145W, 220MHz	BF 240...241, BF 254...255, BF 594...595
12399	2N4436	B>40	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12400	2N4437	2N4436, B>100	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12401	2N4438	B>40	BF 259, BF 659, BFR 59, BFS 89, 2N5058
12402	2N4439	2N4438, B>100	BF 259, BF 659, BFR 59, BFS 89, 2N5058
12403	2N444	15V, 0,025mA, 0,1W, >0,5MHz	ASY 28...29, ASY 73...75
12404	2N4440		
12405	2N4441	Igt/Ih<30/<40mA	-
12406	2N4442	2N4441, 200V	-
12407	2N4443	2N4441, 400V	-
12408	2N4444	2N4441, 600V	-
12409	2N4445	25V, 0,4A, Up<10V	-
12410	2N4445A	2N4445, 35V	-
12411	2N4446	25V, 0,4A, Up<5V	-
12412	2N4446A	2N4446, 35V	-
12413	2N4447	20V, 0,4A, Up<5V	-
12414	2N4447A	2N4447, 25V	-
12415	2N4448	20V, 0,4A, Up<5V	-
12416	2N4448A	2N4448, 25V	-
12417	2N4449	-/15V, 0,2A, 0,3W, <69/20ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
12418	2N444A	2N444, 40V, 0,15W	-
12419	2N445	15V, 0,05A, 0,1W, >2MHz	ASY 28...29, ASY 73...75

12420	2N4450	60V, 0,5A, 0,36W, 50/125ns	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12421	2N4451	-/12V, 0,1A, 0,3W, <65/95ns	BSX 36, 2N4313, 2N3209, 2N4125...26
12422	2N4452	45V, 0,6A, 0,35W, <95/210ns	BC 327, BC 638, BSW 24, 2N2906...07(A)
12423	2N4453	25V, 0,2A, 0,3W, 30/60ns	BC 308, BC 558, BSW 24, 2N3250...51(A)
12424	2N445A	2N445, 30V, 0,15W	ASY 28, ASY 73...75
12425	2N446	15V, 0,025A, 0,1W, >5MHz	ASY 28...29, ASY 73...75
12426	2N446A	2N446, 30V, 0,05A, 0,15W	ASY 28, ASY 73...75
12427	2N447	15V, 0,05A, 0,1A, >9MHz	ASY 28...29, ASY 73...75
12428	2N447A	2N447, 30V, 0,15W	ASY 28, ASY 73...75
12429	2N447B	2N447, 25V, 0,15W	ASY 28...29, ASY 73...75
12430	2N448	15V, 0,02A, 0,065W, 5MHz	-
12431	2N449	15V, 0,02A, 0,065W, 5MHz	-
12432	2N45(A)	45V, 0,01A, 0,15W	ASY 48, 2SB56A
12433	2N450	20V, 0,125A, 0,15W, 10MHz	ASY 26...27, ASY 76...77
12434	2N456	40V, 5A, 50W	AL 102...103, AUY 21...22, 2N1529...48
12435	2N456A,B	2N456, 7A, 85..150W	2N2288...93, 2N3611...18
12436	2N457	60V, 5A, 50W	AL 102...103, AUY 21...22, 2N1545...48
12437	2N457A,B	2N457, 7A, 85..150W	2N2292...93, 2N3615...18
12438	2N458	80V, 5A, 50W	AL 102...103, AUY 21...22, 2N1546...48
12439	2N458A,B	2N458, 7A, 85..150W	2N2292...93, 2N3615...18
12440	2N459(A)	105V, 5A, 106W	2N1537...38, 2N1547...48, 2N3616, 2N3618
12441	2N460	45V, 0,4A, 0,225W, 1,2MHz	2N1189...90, 2SB405ST
12442	2N461	45V, 0,4A, 0,225W, 4MHz	2N1189...90, 2SB405ST
12443	2N462	40V, 0,2A, 0,15W	2N1191...94, 2SB56A
12444	2N464	45V, 0,5A, 0,2W	2N1189...90, 2SB405ST
12445	2N465	45V, 0,5A, 0,2W	2N1189...90, 2SB405ST
12446	2N466	35V, 0,5A, 0,2W	AC 128, AC 153, 2N1189...90, 2SB405ST
12447	2N467	35V, 0,5A, 0,2W	AC 128, AC 153, 2N1189...90, 2SB405ST
12448	2N47	35V, 0,02A, 0,05W	AC 125...126, AC 151, ASY 26...27
12449	2N470(A)	15V, 0,025A, 0,2W, >8MHz	BC 168, BC 183, BC 238, BC 548
12450	2N471(A)	2N470, 30V	BC 168, BC 183, BC 238, BC 548
12451	2N472(A)	2N470, 45V	BC 167, BC 182, BC 237, BC 547
12452	2N473(A)	15V, 0,025A, 0,2W, >8MHz	BC 168, BC 183, BC 238, BC 548
12453	2N474(A)	2N473, 30V	BC 168, BC 183, BC 238, BC 548
12454	2N475(A)	2N473, 45V	BC 167, BC 182, BC 237, BC 547
12455	2N476(A)	15V, 0,025A, 0,2W, >12MHz	BC 168, BC 183, BC 238, BC 548
12456	2N477(A)	2N476, 30V	BC 168, BC 183, BC 238, BC 548
12457	2N478(A)	15V, 0,025A, 0,2W, >20MHz	BC 168, BC 183, BC 238, BC 548
12458	2N479(A)	2N478, 30V	BC 168, BC 183, BC 238, BC 548
12459	2N48	35V, 0,02A, 0,05W	AC 125...126, AC 151, ASY 26...27
12460	2N480(A)	2N478, 45V	BC 167, BC 182, BC 237, BC 547
12461	2N481	12V, 0,02A, 0,15W, 3MHz	AF 124...127, AF 200
12462	2N482	12V, 0,02A, 0,15W, 3,5MHz	AF 124...127, AF 200
12463	2N483	12V, 0,02A, 0,15W, 5,5MHz	AF 124...127, AF 200
12464	2N484	12V, 0,02A, 0,15W, 10MHz	AF 124...127, AF 200



12465	2N485	12V, 0,01A, 0,15W, 7,5MHz	AF 124...127, AF 200
12466	2N4851	$I_p < 2\mu A$ , $I_v > 2mA$	2N4947, 2N4948, 2N4893
12467	2N4852	2N4851, $I_v > 4mA$	2N4892
12468	2N4853	2N4851, $I_p < 0,4\mu A$ , $I_v > 6mA$	-
12469	2N4856(A)	40V, $I_{dss} > 50mA$ , $U_p < 10V$	BFS 74, BFS 77, BSV 78, 2N3970, 2N4391
12470	2N4857(A)	40V, $I_{dss} > 20mA$ , $U_p < 6V$	BFS 75, BFS 78, BSV 79
12471	2N4858(A)	40V, $I_{dss} > 8mA$ , $U_p < 4V$	BFS 76, BFS 79, BSV 80, 2N4093
12472	2N4859(A)	30V, $I_{dss} > 50mA$ , $U_p < 10V$	BFS 74, BFS 77, BSV 78, 2N3970, 2N4391
12473	2N486	12V, 0,01A, 0,15W, 12MHz	AF 124...127, AF 200
12474	2N4860(A)	30V, $I_{dss} > 20mA$ , $U_p < 6V$	BFS 75, BFS 78, BSV 79
12475	2N4861(A)	30V, $I_{dss} > 8mA$ , $U_p < 4V$	BFS 76, BFS 79, BSV 80, 2N4093
12476	2N4862	$> 50MHz$	BUX 49, BUY 41, 2SC1860
12477	2N4863	140V, 2A, 7W( $T_c 25^\circ$ ), $> 50MHz$	BUX 49, BUY 41, 2SC1860
12478	2N4864	140V, 2A, 29W, $> 50MHz$	2SC2529, 2SC2660, 2SD759...760
12479	2N4865	100/80V, 90A, 350W, $> 10MHz$	2N6309...11
12480	2N4866	2N4865, 140/120V	2N6309...11
12481	2N4867(A)	40V, $I_{dss} > 0,4mA$ , $U_p < 2V$	2N4339, 2N5358, 2SK83, 2SK193, 2SK195
12482	2N4868(A)	40V, $I_{dss} > 3mA$ , $U_p < 3V$	BC 264, BF 410, 2SK192, 2SK370
12483	2N4869(A)	40V, $I_{dss} > 2,5mA$ , $U_p < 6V$	BF 256, BFS 71, 2N3822, 2N4221
12484	2N487	18V, 0,025A, 0,1W, $> 10MHz$	AF 124...127, AF 200
12485	2N4870	$I_p < 5\mu A$ , $I_v > 2mA$	2N4891
12486	2N4870	$I_p < 5\mu A$ , $I_v > 2mA$	2N4891
12487	2N4871	2N4870, $I_v > 4mA$	2N2646
12488	2N4871	2N4870, $I_v > 4mA$	2N2646
12489	2N4872	12V, 0,05A, 0,3W, $< 25/30ns$	-
12490	2N4873	40V, 0,2A, 0,36W, $< 20/30ns$	-
12491	2N4874	30V, 0,2A, 0,72W, $> 900MHz$	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
12492	2N4875	40V, 0,2A, 0,72W, $> 800MHz$	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
12493	2N4876	40V, 0,2A, 0,72W, $> 650MHz$	BFR 36, 2SC1199, 2SC1252, 2SC1365...66
12494	2N4877	70V, 4A, 10W( $T_c 25^\circ$ ), $> 30MHz$	BUX 34, BUY 80, 2N5336...39
12495	2N4881	300V, $I_{dss} > 0,4mA$ , $U_p < 15V$	2N5543
12496	2N4882	300V, $I_{dss} > 1,5mA$ , $U_p < 15V$	2N5543
12497	2N4883	200V, $I_{dss} > 0,4mA$ , $U_p < 15V$	2N5542...43
12498	2N4884	200V, $I_{dss} > 1,5mA$ , $U_p < 15V$	2N5542...43
12499	2N4885	125V, $I_{dss} > 0,4mA$ , $U_p < 15V$	2N5542...43
12500	2N4886	125V, $I_{dss} > 1,5mA$ , $U_p < 15V$	2N5542...43
12501	2N4888	150V, 0,05A, 0,3W, $> 30MHz$	BF 398, BF 423, BF 435...437, 2SC1370
12502	2N4889	2N4888, $> 40MHz$	BF 398, BF 423, BF 435...437, 2SC1370
12503	2N489...494(A)	$I_p < 12\mu A$ , $I_v > 8mA$	-
12504	2N489...494(A)	$I_p < 12\mu A$ , $I_v > 8mA$	-
12505	2N4890(S)	60V, 0,5A, 1W, 35/130ns	BC 161, BC 303...304, 2N2904...05(A)
12506	2N4891(L)	$I_p < 5\mu A$ , $I_v > 2mA$	2N4870
12507	2N4891(L)	$I_p < 5\mu A$ , $I_v > 2mA$	2N4870
12508	2N4892(L)	2N4891, $I_p < 2\mu A$ , $I_v > 4mA$	2N4852
12509	2N4892(L)	2N4891, $I_p < 2\mu A$ , $I_v > 4mA$	2N4852



12510	2N4893(L)	2N4891, Ip<2μA, Iv>2mA	2N4851, 2N4947, 2N4948
12511	2N4893(L)	2N4891, Ip<2μA, Iv>2mA	2N4851, 2N4947, 2N4948
12512	2N4894(L)	2N4891, Ip<1μA, Iv>2mA	2N4949
12513	2N4894(L)	2N4891, Ip<1μA, Iv>2mA	2N4949
12514	2N4895	120V, 5A, 1W, >50MHz, B>40	BFT 34, BUX 34, BUY 80
12515	2N4896	2N4895, >80Mhz, B>100	BFT 34, BUX 34, BUY 80
12516	2N4897	2N4895, 150V	BUY 80
12517	2N4898		BD 240, BD 242, BDX 14, 2N3740...41
12518	2N4899	2N4898, 60V	BD 240A, BD 242A, BDX 14, 2N3740...41
12519	2N489B...494B	2N489..494, Ip<6μA	-
12520	2N489B...494B	2N489..494, Ip<6μA	-
12521	2N489C...494C	2N489..494, Ip<2μA	2N2647
12522	2N489C...494C	2N489..494, Ip<2μA	2N2647
12523	2N49	35V, 0,02A, 0,05W	AC 125...126, AC 151, ASY 26...27
12524	2N4900	2N4898, 80V	BD 240B, BD 242B, BDX 14, 2N3741
12525	2N4901		BD 246, BDV 92, BDX 92, 2N5871...72
12526	2N4902	2N4901, 60V	BD 246A, BDV 92, BDX 92, 2N5871...72
12527	2N4903	2N4901, 80V	BD 246B, BDV 94, BDX 94, 2N5872
12528	2N4904	2N4901, B>25	BD 246, BDV 92, BDX 92, 2N5871...72
12529	2N4905	2N4901, 60V, B>25	BD 246A, BDV 92, BDX 92, 2N5871...72
12530	2N4906	2N4901, 80V, B>25	BD 246B, BDV 94, BDX 94, 2N5872
12531	2N4907	40V, 10A, 150W, 4MHz	BD 312, BD 546, BDW 22, 2N5875...76
12532	2N4908	2N4907, 60V	BD 312, BD 546A, BDW 22A, 2N5875...76
12533	2N4909	2N4907, 80V	BD 314, BD 546B, BDW 22B, 2N5876
12534	2N4910		BD 239, BD 241, BDY 78, 2N4231...33
12535	2N4911	2N4910, 60V	BD 239A, BD 241A, BDY 78, 2N4232...33
12536	2N4912	2N4910, 80V	BD 239B, BD 241B, BDY 78, 2N4233
12537	2N4913		BD 245, BDV 91, BDX 91, 2N5873...74
12538	2N4914	2N4913, 60V	BD 245A, BDV 91, BDX 91, 2N5873...74
12539	2N4915	2N4913, 80V	BD 245B, BDV 93, BDX 93, 2N5874
12540	2N4916	0,2W, >400MHz, <55/180ns	BSW 24, BSX 36, 2N2906...07(A), 2N4125
12541	2N4917	2N4916, >450MHz	BSW 24, BSX 36, 2N2906...07(A), 2N4125
12542	2N4918	40V, 1A, 30W, >3MHz	BD 136, BD 166, BD 176, BD 234
12543	2N4919	2N4918, 60V	BD 138, BD 168, BD 178, BD 236
12544	2N4920	2N4918, 80V	BD 140, BD 170, BD 180, BD 238
12545	2N4921	40V, 1A, 30W, >3MHz	BD 135, BD 165, BD 175, BD 233
12546	2N4922	2N4921, 60V	BD 137, BD 167, BD 177, BD 235
12547	2N4923	2N4921, 80V	BD 139, BD 169, BD 179, BD 237
12548	2N4924(S)	100V, 0,2A, 1W, >100MHz	BC 141, BC 300, 2N1889...90, 2N1893
12549	2N4925(S)	2N4924, 150V	BSS 48...49, 2N3439...40, 2N5010
12550	2N4926	200V, 0,05A, 1W, >30MHz	BF 258...259, BF 658...659, 2N5058...59
12551	2N4927	2N4926, 250V	BF 258...259, BF 658...659, 2N5058...59
12552	2N4928(S)	100V, 0,1A, 0,6W, >100MHz	BFT 44...45, 2N3634...35, 2SB606
12553	2N4929(S)	150V, 0,5A, 1W, >100MHz	BFT 44...45, 2N3636...37, 2SB606
12554	2N4930(S)	200V, 0,5A, 1W, >20MHz	BFT 44...45, 2N5415...16, 2SB606

12555	2N4931(S)	250V, 0,5A, 1W, >20MHz	BFT 44...45, MJ 5415...16, 2N5416, 2SB606
12556	2N4932	50V, 3,3A, PQ>12W(88MHz)	BLW 36
12557	2N4933	70V, 3,3A, PQ>20W(88MHz)	2SC1037
12558	2N4943	120V, 1A, 0,8W, >150MHz	BSS 42...43, BSW 67...68, BSX 47, 2N2102
12559	2N4944	B>40	BC 639, BCX 24, 2N3700...01, 2SD667
12560	2N4945	2N4944, 80/60V	BC 639, BCX 24, 2N3700...01, 2SD667
12561	2N4946	2N4944, B>100	BC 639, BCX 24, 2N3700...01, 2SD667
12562	2N4947	Ip<2μA, Iv>2mA	2N4851, 2N4948, 2N4893
12563	2N4948	2N4947	2N4851, 2N4947, 2N4893
12564	2N4949	2N4947, Ip<1μA	2N4894
12565	2N495	25V, 0,05A, 0,15W, >8MHz	BC 213, BC 258, BC 308, BC 558
12566	2N4950	80/60V, 70A, 200W	2N6309...11
12567	2N4951	B>60	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12568	2N4952	2N4951, B>100	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12569	2N4953	2N4951, B>200	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12570	2N4954	2N4951, 40V	BC 337, BC 635, BSV 59, 2N2221...22(A)
12571	2N4957	30V, 0,03A, 0,2W, 1600MHz	BF 439, BF 516, BF 606, BFR 38, BFR 99
12572	2N4958	30V, 0,03A, 0,2W, 1500MHz	BF 439, BF 516, BF 606, BFR 38, BFR 99
12573	2N4959	30V, 0,03A, 0,2W, 1500MHz	BF 439, BF 516, BF 606, BFR 38, BFR 99
12574	2N496	10V, 0,05A, 0,15W, >7,2MHz	BC 213, BC 258, BC 308, BC 558
12575	2N4960	60V, 1A, 0,8W, >250MHz	BC 140...141, BSW 65...68, BSX 45...47
12576	2N4961	2N4960, 80V	BC 140...141, BSW 65...68, BSX 45...47
12577	2N4962	2N4960, 0,5W	BC 637, BSS 40...41, BSX 33, 2SD774
12578	2N4963	2N4960, 80V, 0,5W	BC 639, BSS 59, BSX 33, 2SD774
12579	2N4964	B>30	BC 212, BC 257, BC 307, BC 557
12580	2N4965	2N4964, B>80	BC 212, BC 257, BC 307, BC 557
12581	2N4966	B>40	BC 167, BC 182, BC 237, BC 547
12582	2N4967	2N4966, B>100	BC 167, BC 182, BC 237, BC 547
12583	2N4968	2N4966, 30V	BC 168, BC 183, BC 238, BC 548
12584	2N4969	B>40	BC 337, BC 637, BSV 59, 2N2221...22(A)
12585	2N497(A)	60V, 0,5A, 0,8..1W, 50MHz	BC 140...141, BC 300...302, 2N3053
12586	2N4970	2N4969, B>100	BC 337, BC 637, BSV 59, 2N2221...22(A)
12587	2N4971	B>40	BC 327, BC 638, BSW 24, 2N2906...07(A)
12588	2N4972	2N4971, B>100	BC 327, BC 638, BSW 24, 2N2906...07(A)
12589	2N4973	20V, 0,03A, 0,2W, >800MHz	BF 316, BF 439, BF 516, BF 606, BFR 38
12590	2N4974	40V, 1A, 0,8W, β>25000	-
12591	2N4975	2N4974, β>15000	-
12592	2N4976	55V, 0,4A, 5W, >1GHz	BLW 90, MRF 5174
12593	2N4977	30V, Idss>50mA, Up<10V	BFS 74, BFS 77, BSV 78, 2N3970, 2N4391
12594	2N4978	30V, Idss>15mA, Up<8V	BFS 75, BFS 78, BSV 79, 2N4857, 2N4092
12595	2N4979	30V, Idss>7,5mA, Up<5V	BFS 76, BFS 79, BSV 80, 2N4858, 2N4093
12596	2N498(A)	2N497, 100V	BC 141, BC 300, 2N1889...90, 2N1990
12597	2N4980	30/30/30V, 0,1A, 0,4W	2N2946
12598	2N4981	50/50/50V, 0,1A, 0,4W	-
12599	2N4982	70/70/70V, 0,1A, 0,4W	-

12600	2N4983	Ub6..10V, Is<0,5mA, Itsm5A	-
12601	2N4983	Ub6..10V, Is<0,5mA, Itsm5A	-
12602	2N4984	Ub7,5..9V, Is<0,15mA, Itsm5A	-
12603	2N4984	Ub7,5..9V, Is<0,15mA, Itsm5A	-
12604	2N4985	Ub7,5..8,2V, Is<0,3mA, Itsm5A	-
12605	2N4985	Ub7,5..8,2V, Is<0,3mA, Itsm5A	-
12606	2N4986	Ub7..9V, Is<0,2mA, Itsm5A	-
12607	2N4986	Ub7..9V, Is<0,2mA, Itsm5A	-
12608	2N4987	2N4983	-
12609	2N4987	2N4983	-
12610	2N4988	2N4984	-
12611	2N4988	2N4984	-
12612	2N4989	2N4985	-
12613	2N4989	2N4985	-
12614	2N499(A)	30V, 0,05A, >120MHz	AF 106, AF 109R, AF 306
12615	2N4990	2N4986	-
12616	2N4990	2N4986	-
12617	2N4991	Ub6..10V, Is<0,5mA, Itsm5A	-
12618	2N4992	Ub7,5..9V, Is<0,12mA, Itsm5A	BS 08A
12619	2N4993	Ub6..10V, Is<0,5mA, Itsm5A	-
12620	2N4994	B>40	BF 240.. 241, BF 254...255, BF 594...595
12621	2N4995	2N4994, B>100	BF 240...241, BF 254...255, BF 594...595
12622	2N4996	B>50	BF 314, BF 502, BF 505, BF 507, BF 562
12623	2N4997	2N4996, B>30	BF 314, BF 502, BF 505, BF 507, BF 562
12624	2N4998	100V, 2A, 30W, >50MHz, B>30	2N5002, 2N5004, 2N5284...85
12625	2N4999	100V, 2A, 30W, >50MHz, B>30	2N5003, 2N5005, 2N5286...87
12626	2N500	20V, 0,05W	AF 109R, AF 139, AF 239(S)
12627	2N5000	2N4998, >60MHz, B>70	2N5002, 2N5004, 2N5284...85
12628	2N5001	2N4999, >60MHz, B>70	2N5003, 2N5005, 2N5286...87
12629	2N5002	100V, 5A, 50W(Tc50°), B>30	2N5284...85
12630	2N5003	100V, 5A, 50W(Tc50°), B>30	2N5286...87
12631	2N5004	2N5002, B>70	2N5284...85
12632	2N5005	2N5003, B>70	2N5286...87
12633	2N5006	100V, 10A, 67W(Tc60°), B>30	2N5288...89
12634	2N5007	100V, 10A, 67W(Tc100°), B>30	2N5290...91
12635	2N5008	2N5006, B>70	2N5288...89
12636	2N5009	2N5007, B>70	2N5290...91
12637	2N501(A,/18)	/22ns	ASZ 21, 2N705(A), 2N2635, 2N2955...57
12638	2N5010	500V, 0,5A, 4W(Tc25°), 15MHz	BUY 59...60, 2N3439, 2N5059, 2SD793...794
12639	2N5011	2N5010, 600V	BUY 60, 2N5097...99, 2SC1762, 2SD594
12640	2N5012	2N5010, 700V	2N5098...99, 2SC1762, 2SD594
12641	2N5013	2N5010, 800V	2N5099, 2SD594
12642	2N5014	2N5010, 900V	-
12643	2N5015	2N5010, 1000V	-
12644	2N5016		

12645	2N5018	30V, Idss>10mA, Up<10V	2N3993
12646	2N5019	30V, Idss>5mA, Up<5V	2N5116
12647	2N502(A,B)	20..30V, 0,05A, 220MHz	AF 106, AF 109R, AF 306
12648	2N5020	25V, Idss>0,3mA, Up<1,5V	2N2844
12649	2N5021	25V, Idss>1mA, Up<2,5V	2SJ74
12650	2N5022		
12651	2N5023	30V, 0,5A, 1W, <45/95ns	2N3467...68, 2SA717, 2SA742
12652	2N5024	20V, 15mA, 0,2W, >1300MHz	BF 377...378, BF 630, BFR 15, BFW 99
12653	2N5025	75V, 5A, PQ>20W(50MHz)	-
12654	2N5026	90V, 5A, PQ>25W(50MHz)	-
12655	2N5027	-/30V, 0,35A, 0,32W, <35/60ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12656	2N5028	-/30V, 0,35A, 0,32W, <45/70ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12657	2N5029	-/15V, 0,2A, 0,32W, <22/26ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12658	2N503	20V, 0,05A, 0,025W, >168MHz	AF 109R, AF 139, AF 239(S)
12659	2N5030	-/12V, 0,2A, 0,32W, <24/30ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12660	2N5031	15V, 0,02A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, 2N2857
12661	2N5032	15V, 0,02A, 0,2W, >1GHz	BF 377...378, BF 689, BF 763, 2N2857
12662	2N5033	20V, Idss>0,3mA, Up<2,5V	2N2607
12663	2N5038(-1)	150V, 20A, 140W, >60MHz	BUV 10, BUW 57, BUX 10, BUX 40
12664	2N5039(-1)	2N5038, 120V	BUV 10, BUW 57, BUX 10, BUX 40
12665	2N504	35V, 0,05A, 0,03W, >50MHz	AF 124...126, AF 200
12666	2N5040	25V, 1A, 0,3W, >80MHz	BC 160...161, BC 327...328, BC 636
12667	2N5041	40V, 1A, 0,3W, >100MHz	BC 160...161, BC 327...328, BC 636
12668	2N5042	40V, 1A, 0,8W, >100MHz	BC 160...161, BCX 60, 2N2904...05(A)
12669	2N5043	15V, 0,03A, >1500MHz	AF 239(S)
12670	2N5044	15V, 0,03A, >1000MHz	AF 239(S)
12671	2N5048	>10MHz	2N5288...89, 2N5542
12672	2N5049	2N5048, 60V	2N5288...89, 2N5542
12673	2N505	40V, 0,25A, 0,125W, 8MHz	ASY 48, ASY 76...77
12674	2N5050	125V, 2A, 40W, >10MHz	BD 241D, BUX 67(A...C), 2N3441, 2SD1138
12675	2N5051	2N5050, 150V	BD 241D, BUX 67(A...C), 2N3441, 2SD1138
12676	2N5052	2N5050, 200V	BD 241F, BUX 67(A...C), 2N3583, 2SD1138
12677	2N5053	30V, 0,025A, 0,2W, >1300MHz	BF 377...378, BF 630, BFR 15, BFW 99
12678	2N5054	30V, 0,025A, 0,2W, >1500MHz	BF 377...378, BF 630, BFR 15, BFW 99
12679	2N5055	12V, 0,1A, 0,2W, <25/35ns	BSX 36, 2N4313
12680	2N5056	15V, 0,1A, 0,36W, <25/45ns	BSX 36, 2N4313
12681	2N5057	15V, 0,1A, 0,36W, <25/45ns	BSX 36, 2N4313
12682	2N5058(S)	300V, 0,15A, 1W, >30MHz	BF 259, BF 659, BFS 89, BFR 59
12683	2N5059(S)	2N5058, 250V	BF 258...259, BF 658...659, BFS 89
12684	2N506	40V, 0,1A, 0,05W	2N1191...94, 2SB56A
12685	2N5060	Igt/Ih<0,2/<5mA	2N6564, TIC 60, MCR 100-3, BRY 55/30
12686	2N5061	2N5060, 60V	2N6564, TIC 61, MCR 100-3, BRY 55/60
12687	2N5062	2N5060, 100V	2N6564, TIC 62, MCR 100-3, BRY 55/100
12688	2N5063	2N5060, 150V	2N6564, TIC 63, MCR 100-4, BRY 55/200
12689	2N5064	2N5060, 200V	2N6564, TIC 64, MCR 100-4, BRY 55/200

12690	2N5065	25V, 0,5A, 0,6W, <19/40ns	-
12691	2N5066	30/20/30V, 0,1A, 0,4W	-
12692	2N5067	40V, 5A, 87,5W, >4MHz	BD 245, BDV 91, BDX 91, 2N4914...15
12693	2N5068	2N5067, 60V	BD 245A, BDV 91, BDX 91, 2N4914...15
12694	2N5069	2N5057, 80V	BD 245B, BDV 93, BDX 93, 2N5758...60
12695	2N507	40V, 0,1A, 0,05W	-
12696	2N5070		
12697	2N5071	65V, 3,3A, PQ>24W(76MHz)	2N5026
12698	2N5073	180V, 0,4A, 0,6W, >40MHz	BFW 36, BSS 48, 2SD413, 2SD576, 2SD624
12699	2N5074	B>30	-
12700	2N5075	2N5074, B>90	-
12701	2N5076	2N5074, 250/250V	-
12702	2N5077	2N5074, 250/250V, B>90	-
12703	2N5078	30V, Idss>4mA, Up<8V	BF 244B...245B, BFS 72, 2N3823, 2N5398
12704	2N5079	60V, 1A, 0,36W, >400MHz	BFX 94...95, 2N3737, 2N4014
12705	2N508	18V, 0,5A, 0,225W	AC 128, AC 152...153, AC 188
12706	2N5080	60V, 1A, 0,36W, >500MHz	BFX 94...95, 2N3737, 2N4014
12707	2N5081	70V, 0,36W, >600MHz	-
12708	2N5082	60V, 0,36W, >600MHz	-
12709	2N5083	120V, 10A, 25W(Tc100°), B>40	2N5288...89, 2N5542
12710	2N5084	2N5083, B>100	2N5288...89, 2N5542
12711	2N5085	2N5083, 150V	2N5542
12712	2N5086		BC 214, BC 416, BC 560, 2SA872(A)
12713	2N5087	2N5086, B>250	BC 214, BC 416, BC 560, 2SA872(A)
12714	2N5088		BC 169, BC 184, BC 239, BC 549
12715	2N5089	2N5088, 30V, B>400	BC 169, BC 184, BC 239, BC 549
12716	2N508A	2N508, 30V, 0,2A, 0,2W	AC 128, AC 152...153, AC 188
12717	2N509	30V, 0,04A, 750MHz	AF 139, AF 239(S)
12718	2N5090		
12719	2N5091	350/300V, 1A, 4W(Tc25°)	MJ 5416, 2N5416
12720	2N5092	400/350V, 1A, 4W(Tc25°)	BSS 49, BUX 55, BUY 59...60, 2N3439
12721	2N5093	400/350V, 1A, 4W(Tc25°)	MJ 5416
12722	2N5094	450/400V, 1A, 4W(Tc25°)	MJ 5416
12723	2N5095	500/400V, 1A, 4W(Tc25°)	BUX 55, BUY 59...60, 2N3439
12724	2N5096	500/450V, 1A, 4W(Tc25°)	MJ 5416
12725	2N5097	600/450V, 1A, 4W(Tc25°)	BUY 60
12726	2N5098	700/500V, 1A, 4W(Tc25°)	-
12727	2N5099	800/550V, 1A, 4W(Tc25°)	-
12728	2N5100	450/400V, 1A, 10W, >20MHz	-
12729	2N5101	500/400V, 1A, 10W, >50MHz	BD 410, BUV 63, BUV 93...95, BUW 40A,B
12730	2N5102	100V, 3,3A, PQ15W(136MHz)	BLY 35, 2N3632
12731	2N5103	25V, Idss>1mA, Up<4V	2N5246, 2N5360, 2SK161
12732	2N5104	25V, Idss>2mA, Up<4V	2N5246, 2N5360, 2SK107
12733	2N5105	25V, Idss>5mA, Up<4V	BF 256, BFS 80, BFW 11, 2N5485
12734	2N5106	60V, 0,6A, 0,8W, >250MHz	-

12735	2N5107	2N5106, 0,36W,	-
12736	2N5108(A)	55V, 0,4A, PQ>1W(1GHz)	-
12737	2N5109	40V, 0,4A, >1200MHz	BFS 50, MRF 515, MRF 629, 2N3948
12738	2N511	40V, 25A, 150W	2N1651...53, 2N2285...87
12739	2N5110	40V, 1A, 0,5W, >1MHz	BC 160...161, BCX 60, BSV 15...17
12740	2N5111	2N5110, 80V	BC 161, BCX 60, BSS 18, BSV 16...17
12741	2N5112	2N5110, 34W	-
12742	2N5113	2N5110, 80V, 34W	-
12743	2N5114	16/21ns	-
12744	2N5115	30/38ns	-
12745	2N5116	42/60ns	-
12746	2N511A	2N511, 60V	2N1651...53, 2N2285...87
12747	2N511B	2N511, 80V	2N1652...53, 2N2286...87
12748	2N512	40V, 25A, 150W	2N1651...53, 2N2285...87
12749	2N5126	20V, 0,03A, 0,2W, >300MHz	BF 240...241, BF 254...255, BF 594...595
12750	2N5127	20V, 0,1A, 0,2W, >150MHz	BF 240...241, BF 254...255, BF 594...595
12751	2N5128	15V, 0,5A, 0,3W, >200MHz	BC 337...338, BC 635, 2N2221...22(A)
12752	2N5129	2N5128, 0,2W	BC 337...338, BC 635, 2N2221...22(A)
12753	2N512A	2N512, 60V	2N1651...53, 2N2285...87
12754	2N512B	2N512, 80V	2N1652...53, 2N2286...87
12755	2N513	40V, 25A, 150W	2N1651...53, 2N2285...87
12756	2N5130	30V, 0,05A, 0,2W, >450MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12757	2N5131	20V, 0,2A, 0,2W, >100MHz	BC 168, BC 183, BC 238, BC 548
12758	2N5132	20V, 0,05A, 0,2W, >200MHz	BF 240...241, BF 254...255, BF 594...595
12759	2N5133	20V, 0,05A, 0,2W, >40MHz	BC 168, BC 183, BC 238, BC 548
12760	2N5134	20V, 0,1A, 0,2W, <26/26ns	BSS 11...12, BSV 89...92, 2N2368...69(A)
12761	2N5135	30V, 0,2A, 0,3W, >40MHz	BC 168, BC 183, BC 238, BC 548
12762	2N5136	30V, 0,5A, 0,3W, >40MHz	BC 337...338, BC 635, BC 637, BC 639
12763	2N5137	2N5136, 0,22W	BC 337...338, BC 635, BC 637, BC 639
12764	2N5138	50V, 0,05A, 0,2W, >30MHz	BC 212, BC 257, BC 307, BC 557
12765	2N5139	20V, 0,1A, 0,2W, <65/230ns	BSW 24, 2N3209, 2N4034...35, 2N4125...26
12766	2N513A	2N513, 60V	2N1651...53, 2N2285...87
12767	2N513B	2N513, 80V	2N1652...53, 2N2286...87
12768	2N514	40V, 25A, 150W	2N1651...53, 2N2285...87
12769	2N5140	5V, 0,05A, 0,2W, <35/35ns	BSX 36, 2N4258, 2N4313, 2N5056...57
12770	2N5141	6V, 0,1A, 0,2W, <115/170ns	BSW 24, 2N3209, 2N4034...35, 2N4125...26
12771	2N5142	20V, 0,5A, 0,3W, <120/225ns	BC 327...328, BC 636, 2N2906...07(A)
12772	2N5143	2N5142, 0,2W	BC 327...328, BC 636, 2N2906...07(A)
12773	2N5144	50V, 0,5A, 0,36W, <45/65ns	-
12774	2N5145	2N5144, 0,8W,	-
12775	2N5147	2N4999, 1W	BSS 17, 2N5322
12776	2N5148	2N4998, 1W	BSS 15, 2N5320
12777	2N5149	2N5001, 1W	BSS 17, 2N5322
12778	2N514A	2N514, 60V	2N1651...53, 2N2285...87
12779	2N514B	2N514, 80V	2N1652...53, 2N2286...87



12780	2N515	18V, 0,01A, 0,05W, 3MHz	ASY 28...29
12781	2N5150	2N5000, 1W	BSS 15, 2N5320
12782	2N5151	2N5003, 1W	BUY 90, 2N6192...93
12783	2N5152	2N5002, 1W	BUX 34, BUY 80, 2N5338...39
12784	2N5153	2N5005, 1W	BUY 90, 2N6192...93
12785	2N5154	2N5004, 1W	BUX 34, BUY 80, 2N5338...39
12786	2N5155	140V, 15A, 106W	-
12787	2N5156	100V, 10A, 93W	AL 100...101, AUY 37, 2N2290, 2N2293
12788	2N5157	700/400V, 3,5A, 100W(Tc75°)	BUS 11(A), BUX 46(A), 2SC3091, 2SC3155
12789	2N5158	40V, Idss<100mA, Up<8V	BFS 74, BFS 77, BSV 78, 2N3970
12790	2N5159	40V, Idss<100mA, Up<10V	BFS 74, BFS 77, BSV 78, 2N3970
12791	2N516	18V, 0,01A, 0,05W, 3MHz	ASY 28...29
12792	2N5160	60V, 0,4A,PQ1,2W(400MHz)	-
12793	2N5161	60V, 1,5A, PQ8,5W(175MHz)	-
12794	2N5162	60V, 5A, PQ35W(175MHz)	-
12795	2N5163	25V, Idss>1mA, Up<8V	BF 244...245, BFS 72, BFW 10, 2N3823
12796	2N5164	Igt/Ih<40/<50mA	MCR 3818-2, 2N3870, MCR 3835-2, MCR 63-2
12797	2N5164...5167R	2N5164..5167	2N5164...5167
12798	2N5165	2N5164, 200V	MCR 3818-4, 2N3871, MCR 3835-4, MCR 63-4
12799	2N5166	2N5164, 400V	MCR 3818-6, 2N3872, MCR 3835-6, MCR 63-6
12800	2N5167	2N5164, 600V	MCR 3818-8, 2N3873, MCR 3835-8, MCR 63-8
12801	2N5168	2N5164	MCR3918-2, T12N100, MCR3935-2, MCR64-2
12802	2N5168...5171R	2N5168..5171	2N5168...5171
12803	2N5169	2N5165	MCR3918-4, T12N200, MCR3935-4, MCR64-4
12804	2N517	18V, 0,01A, 0,05W, 3MHz	ASY 28...29
12805	2N5170	2N5165	MCR3918-6, T12N400, MCR3935-6, MCR64-6
12806	2N5171	2N5166	MCR3918-8, T12N600, MCR3935-8, MCR64-8
12807	2N5172	25V, 0,1A, 0,36W, 200MHz	BC 168, BC 183, BC 238, BC 548
12808	2N5174	90V, 0,025A, 0,36W	BSS 38, BSX 21, 2SC1890(A), 2SC2240
12809	2N5175	130V, 0,025A, 0,2W	BSS 38, BSX 21, 2SC1890A, 2SC2240
12810	2N5176	130V, 0,025A, 0,36W	BSS 38, BSX 21, 2SC1890A, 2SC2240
12811	2N5177	55V, 4A, 40W, >200MHz	-
12812	2N5178	55V, 8A, 70W, >200MHz	-
12813	2N5179		BF 377...378, BF 689, BF 763, 2N2857
12814	2N518	45V, 0,125A, 0,15W, 11MHz	ASY 48, ASY 76...77
12815	2N5180	30V, 0,18W, 900MHz	BF 314, BF 502, BF 505, BF 507, BF 562
12816	2N5181	45V, 0,05A, 0,18W, 700MHz	BF 198...199, BF 224...225, BF 310...311
12817	2N5182	45V, 4mA, 0,18W, 700MHz	BF 198...199, BF 224...225, BF 310...311
12818	2N5183	18V, 1A, 0,5W, <75/575ns	BC 337...338, BC 635, 2N2221...22(A)
12819	2N5184	-/120V, 0,05A, 0,5W, 100MHz	BF 297...299, BFT 57...59, 2SC3467
12820	2N5185	2N5184, 1W	BF 297...299, BFT 57...59, 2SC3467
12821	2N5186	<25/25ns	BSS 10...12, BSX 19...20, 2N3261
12822	2N5187	<12/14ns	BSS 10, BSX 26, BSX 39, 2N3261
12823	2N5188	<35/50ns	BSS 27, BSV 77, BSV 95, 2SC1635
12824	2N5189	<40/70ns	BSS 27, BSV 77, BSV 95, 2SC1635



12825	2N519(A)	15..25V, 0,1..0,15W, >0,5MHz	ASY 26...27, ASY 76...77
12826	2N5190	40V, 4A, 40W, >2MHz	BD 185, BD 437, BD 785, MJE 240...244
12827	2N5191	2N5190, 60V	BD 187, BD 439, BD 787, MJE 240...244
12828	2N5192	2N5190, 80V	BD 189, BD 441, BD 789, MJE 240...244
12829	2N5193	40V, 4A, 40W, >2MHz	BD 186, BD 438, BD 786, MJE 250...254
12830	2N5194	2N5193, 60V	BD 188, BD 440, BD 788, MJE 250...254
12831	2N5195	2N5193, 80V	BD 190, BD 442, BD 788, MJE 250...254
12832	2N520(A)	15..25V, 0,1..0,15W, >3MHz	ASY 26...27, ASY 76...77
12833	2N5200	20V, 0,1A, 0,3W, >900MHz	-
12834	2N5201	20V, 0,1A, 0,3W, >1100MHz	-
12835	2N5202	100V, 4A, 35W, >60MHz	BDV 10...12, 2SD772
12836	2N5203	BFW 35	BFW 35
12837	2N5204	Igt/Ih<40/<100mA	C 228M, 2N3899, MCR 3935-8, C 35M
12838	2N5205	2N5204, 800V	MCR 3935-10, C 35N, MCR 64-10, TAG 35-800
12839	2N5206	2N5204, 1000V	C 35P, MCR 64-10, TAG 35-1000
12840	2N5207	2N5204, 1200V	-
12841	2N5208	30V, 0,05A, 0,35W, >300MHz	BF 324, BF 414, BF 506, BF 914, BF 936
12842	2N5209		BC 184, BC 413...414, BC 550, 2SC2240
12843	2N521(A)	15..25V, 0,1..0,15W, >8MHz	ASY 26...27
12844	2N5210	50V, 0,05A, 0,625W, 80MHz	BC 184, BC 413...414, BC 550, 2SC2240
12845	2N5211	80V, 0,6A, 0,8W, >200MHz	BFS 23, BLY 34
12846	2N5212	80V, 0,6A, 7,5W, >200MHz	-
12847	2N5213	70V, 0,5A, PQ3W(200MHz)	-
12848	2N5215	70V, 1A, PQ10W(200MHz)	BLY 60, 2N3632
12849	2N5218	220/200V, 10A, 50W(Tc100°)	2N5540
12850	2N5219	20V, 0,1A, 0,35W, >150MHz	BC 168, BC 183, BC 238, BC 548
12851	2N522(A)	15..25V, 0,1..0,15W, >15MHz	ASY 26...27
12852	2N5220	15V, 0,5A, 0,625W, >100MHz	BC 337...338, BC 635, BC 637, BC 639
12853	2N5221	15V, 0,5A, 0,35W, >100MHz	BC 327...328, BC 636, BC 638, BC 640
12854	2N5222	20V, 0,05A, >450MHz	BF 198...199, BF 224...225, BF 310...311
12855	2N5223	25V, 0,1A, 0,625W, >150MHz	BC 168, BC 183, BC 238, BC 548
12856	2N5224	25V, 0,2A, 0,625W, <45/60ns	BSS 10...12, BSX 19...20, 2N2368...69(A)
12857	2N5225	25V, 0,5A, 0,625W, >50MHz	BC 337...338, BC 635, BC 637, BC 639
12858	2N5226	25V, 0,5A, 0,625W, >50MHz	BC 327...328, BC 636, BC 638, BC 640
12859	2N5227	30V, 0,05A, 0,625W, >100MHz	BC 213, BC 258, BC 308, BC 558
12860	2N5228	5V, 0,05A, 0,625W, <75/140ns	BSW 24, BSX 36, 2N4258, 2N4313
12861	2N5229	15/10/15V, 0,05A, 0,5W	2N2944
12862	2N523(A)	15..20V, 0,1..0,15W, >21MHz	ASY 26...27
12863	2N5230	30/20/30V, 0,05A, 0,5W	2N2945
12864	2N5231	50/30/50V, 0,05A, 0,5W	2N2946
12865	2N5232(A)	70V, 0,1A, 0,36W, >250MHz	2SC1775(A), 2SC2240, 2SC2389, 2SC2459
12866	2N5232(A)	70V, 0,1A, 0,36W, >250MHz	2SC1775(A), 2SC2240, 2SC2389, 2SC2459
12867	2N5233	80V, 0,1A, 0,33W, B>100	BC 546, 2SC1890(A), 2SD755...756(A)
12868	2N5234	2N5233, B>250	BC 546, 2SC1890(A), 2SD755...756(A)
12869	2N5235	2N5233, B>400	BC 546, 2SC1890(A), 2SD755...756(A)

12870	2N5236	40V, 0,15A, 0,6W, >500MHz	-
12871	2N5237	25MHz	BUY 80, 2N4879
12872	2N5238	2N5237, 200V	BUY 48...49
12873	2N5239	300/225V, 5A, 100W, >2MHz	BU 606...608, BUX 16A...C, 2SC2624
12874	2N524(A)	45V, 0,5A, 0,225W, 1,5MHz	ASY 76...77
12875	2N5240	2N5239, 375/300V	BU 606...608, BUX 16B...C, 2SC2624
12876	2N5241	400/400V, 5A, 125W(Tc62°)	BUX 16C, BUX 18C, BUX 45, 2SD640
12877	2N5242	<45/95ns	2N3467...68, 2N5022...23, 2SA742
12878	2N5243	2N5242, 30V	2N3467...68, 2N5022...23, 2SA742
12879	2N5244	40V, 0,1A, 0,36W, <55/150ns	-
12880	2N5245		BF 244...245, BFS 80, BFW 11, 2N4416
12881	2N5246	30V, Idss>1,5mA, Up<4V	2SK107, 2SK161
12882	2N5247	30V, Idss>8mA, Up<8V	BF 244...245, BFW 10
12883	2N5248	30V, Idss>4mA, Up<8V	BF 244...245, BFS 72, 2N3823
12884	2N5249(A)	70V, 0,1A, 0,36W	2SC1775(A), 2SC2240, 2SC2389, 2SC2459
12885	2N525(A)	45V, 0,5A, 0,225W, 2MHz	ASY 76...77
12886	2N5250	125/100V, 90A, 350W, >10MHz	2N6309...11
12887	2N5251	2N5250, 180/150V	2N6309...11
12888	2N5252	B>40	BFQ 38...40, BSS 48...49, 2N3439...40
12889	2N5253	2N5252, B>80	BFQ 38...40, BSS 48...49, 2N3439...40
12890	2N526(A)	45V, 0,5A, 0,225W, 2,5MHz	ASY 76...77
12891	2N5262	75V, 2A, 1W, 350MHz, 18/35ns	BSS 14, 2N3507
12892	2N5264	400/180V, 7A, 87W, >50MHz	BU 606...608, BUX 18B...C, 2SC2656
12893	2N5265	60V, Idss>0,5mA, Up<3V	-
12894	2N5266	60V, Idss>0,8mA, Up<3V	-
12895	2N5267	60V, Idss>1,5mA, Up<6V	2N5463...64
12896	2N5268	60V, Idss>2,5mA, Up<6V	2N5463...64
12897	2N5269	60V, Idss>4mA, Up<8V	2N5465
12898	2N527(A)	45V, 0,5A, 0,225W, 3,5MHz	ASY 76...77
12899	2N5270	60V, Idss>7mA, Up<8V	-
12900	2N5271	280V, 5A, 0,6W	-
12901	2N5272	<23/28ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
12902	2N5273	200V, 25A, Igt/Ih<150/<100mA	2N5806, BTX 94/200
12903	2N5274	2N5273, 400V	2N5807, BTX 94/400
12904	2N5275	2N5273, 600V	2N5809, BTX 94/600
12905	2N5276	25V, 0,36W, >600MHz	-
12906	2N5277	150V, Idss>2,5mA, Up<7V	-
12907	2N5278	150V, Idss>10mA, Up<10V	-
12908	2N5279	400/300V, 1A, 1W, >15MHz	BFQ 40, BSS 49, 2N3439
12909	2N528	40V, 1A, 2,5W, >4MHz	2SB493
12910	2N5280	2N5279, 15W	BD 410, BUW 40(A,B), TIP 49...50
12911	2N5281	>20MHz	BFT 19(A,B), BFT 28A...C, 2N5415...16
12912	2N5282	2N5281, 325/300V	BFT 19B, 2N5416, MJ 5416
12913	2N5284	>60MHz	-
12914	2N5285	>70MHz	-

12915	2N5286	>60MHz	-
12916	2N5287	>70MHz	-
12917	2N5288	10A,100W(Tc50°),>30MHz	2N5542
12918	2N5289	10A,100W(Tc50°),>40MHz	2N5542
12919	2N529	15V, 0,025A, $\beta > 15$	AC 127AC 128, AC 127AC 152
12920	2N5290	10A,100W(Tc50°),>30MHz	-
12921	2N5291	10A,100W(Tc50°),>40MHz	-
12922	2N5292	12V, 0,1A, 0,36W, >800MHz	-
12923	2N5293		BD 243B, BD 537, BD 539B, BD 951
12924	2N5294	80V, 4A, 36W, >0,8MHz	BD 243B, BD 537, BD 539B, BD 951
12925	2N5295	60V, 4A, 36W, >0,8MHz	BD 243A, BD 535, BD 539A, BD 949
12926	2N5296	60V, 4A, 36W, >0,8MHz	BD 243A, BD 535, BD 539A, BD 949
12927	2N5297	80V, 4A, 36W, >0,8MHz	BD 243B, BD 537, BD 539B, BD 951
12928	2N5298	80V, 4A, 36W, >0,8MHz	BD 243B, BD 537, BD 539B, BD 951
12929	2N530	2N529, $\beta > 20$	AC 127AC 128, AC 127AC 152
12930	2N5301		
12931	2N5302	2N5301, 60V	BDY 29, MJ 802, 2SD797
12932	2N5303	2N5301, 80V	BDY 29, MJ 802, 2SD797
12933	2N5304	>100MHz	-
12934	2N5305	>60MHz	BC 517, BC 617, MPSA 13...14, 2SD892
12935	2N5306	2N5305, B>7000	BC 517, BC 617, MPSA 13...14, 2SD892
12936	2N5306A	2N5305, B>7000	-
12937	2N5307	>60MHz	BC 517, BC 617, MPSA 25...29, 2SD892A
12938	2N5308	2N5307, B>7000	BC 517, BC 617, MPSA 25...29, 2SD892A
12939	2N5308A	2N5307, B>7000	-
12940	2N5309	70V, 0,1A, 0,36W, B>60	BC 174, BC 182, BC 190, BC 546
12941	2N531	2N529, $\beta > 25$	AC 127AC 128, AC 127AC 152
12942	2N5310	2N5309, B>100	BC 174, BC 182, BC 190, BC 546
12943	2N5311	2N5309, B>250	BC 174, BC 182, BC 190, BC 546
12944	2N5312	>30MHz	2N5290...91
12945	2N5313	>30MHz	2N5288...89
12946	2N5314	2N5312, 100V	2N5290...91
12947	2N5315	2N5313, 100V	2N5288...89
12948	2N5316	2N5312	2N5290...91
12949	2N5317	2N5313	2N5288...89
12950	2N5318	2N5312, , 100V	2N5290...91
12951	2N5319	2N5313, , 100V	2N5288...89
12952	2N532	2N529, $\beta > 30$	AC 127AC 128, AC 127AC 152
12953	2N5320	<80/800ns	
12954	2N5321	2N5320, 75V	BSS 15, BSV 84, 2N4238...39, 2SD854
12955	2N5322	2A,10W(Tc25°),<100/1000ns	
12956	2N5323	2N5322, 75V	BSS 17...18, 2N4236
12957	2N5324	250V, 10A, 56W	AU 113, AU 213
12958	2N5325	2N5324, 325V	AU 106, AU 109, AU 111...112
12959	2N5326	>80MHz	2N5002, 2N5004, 2N5284...85

12960	2N5327	>100MHz	BUY 82
12961	2N5328	>100MHz	2N5348...49
12962	2N5329	>80MHz	-
12963	2N533	2N529, B>35	AC 127AC 128, AC 127AC 152
12964	2N5330	>80MHz	-
12965	2N5331	>80MHz	2N2825
12966	2N5332	20V, 0,1A, 0,36W, >800MHz	-
12967	2N5333	100V, 2A, 1W, 150/450ns	BSS 17, 2N5322
12968	2N5334	<100/1050ns	BSX 62...64, 2N4237...39, 2SC2214
12969	2N5335	2N5334, 80V	BSX 63...64, 2N4238...39, 2SC2214
12970	2N5336	80V, 5A, 6W(Tc25°), B>30	BFT 32...34, BUX 34, BUY 80, 2N4895...97
12971	2N5337	2N5336, B>60	BFT 32...34, BUX 34, BUY 80, 2N4895...97
12972	2N5338	2N5336, 100V	BFT 33...34, BUX 34, BUY 80, 2N4895...97
12973	2N5339	2N5336, 100V, B>60	BFT 33...34, BUX 34, BUY 80, 2N4895...97
12974	2N534	50V, 0,025A, 0,025W	ASY 48, ASY 77
12975	2N5344	250/250V, 1A, 40W, >60MHz	BUX 66A...C, 2N6421, 2SA1009(A), 2SA1397
12976	2N5345	2N5344, 300/300V	BUX 66A...C, 2N6421, 2SA1009(A), 2SA1397
12977	2N5346	2N5336, 7A, 60W	-
12978	2N5347	2N5337, 7A, 60W	-
12979	2N5348	2N5338, 7A, 60W	-
12980	2N5349	2N5339, 7A, 60W	-
12981	2N535(A,B)	2MHz	ASY 26...27
12982	2N5354	B>40	BC 327...328, BC 636, BC 638, BC 640
12983	2N5355	2N5354, B>100	BC 327...328, BC 636, BC 638, BC 640
12984	2N5356	2N5354, B>250	BC 327...328, BC 636, BC 638, BC 640
12985	2N5357	>50MHz	2SA1009(A), 2SA1236, 2SA1397
12986	2N5358	40V, Idss>0,5mA, Up<3V	2N4339, 2SK83, 2SK193, 2SK195
12987	2N5359	40V, Idss>0,8mA, Up<4V	-
12988	2N536	2MHz	ASY 26...27
12989	2N5360	40V, Idss>1,5mA, Up<4V	2N5246
12990	2N5361	40V, Idss>2,5mA, Up<6V	BF 256A, BFS 71, 2N3822, 2N4221, 2N5458
12991	2N5362	40V, Idss>4mA, Up<7V	BF 256A, BFS 80, BFW 11, 2N4416
12992	2N5363	40V, Idss>7mA, Up<8V	BFW 10
12993	2N5364	40V, Idss>9mA, Up<8V	BF 244C...245C, BFW 10
12994	2N5365	2N5354, 40V	BC 327, BC 636, BC 638, BC 640
12995	2N5366	2N5355, 40V	BC 327, BC 636, BC 638, BC 640
12996	2N5367	2N5356, 40V	BC 327, BC 636, BC 638, BC 640
12997	2N5368		BC 337A, BC 637, BSV 59, 2N2221...22(A)
12998	2N5369	60V, 0,5A, 0,36W, <40/350ns	BC 337A, BC 637, BSV 59, 2N2221...22(A)
12999	2N537	30V, 0,1A, 600MHz	AF 139, AF 239(S)
13000	2N5370	60V, 0,5A, 0,36W, <40/400ns	BC 337A, BC 637, BSV 59, 2N2221...22(A)
13001	2N5371	40V, 0,5A, 0,36W, <40/400ns	BC 337, BC 637, BSV 59, 2N2221...22(A)
13002	2N5372		BC 327A, BC 638, BSW 24, 2N2906...07(A)
13003	2N5373	60V, 0,5A, 0,36W, <50/150ns	BC 327A, BC 638, BSW 24, 2N2906...07(A)
13004	2N5374	60V, 0,5A, 0,36W, <50/175ns	BC 327A, BC 638, BSW 24, 2N2906...07(A)

13005	2N5375	40V, 0,5A, 0,36W, <50/175ns	BC 327, BC 638, BSW 24, 2N2906...07(A)
13006	2N5376	B>120	BC 337A, BC 637, BSV 59, 2N2221...22(A)
13007	2N5377	B>100	BC 337A, BC 637, BSV 59, 2N2221...22(A)
13008	2N5378	B>120	BC 327A, BC 638, BSW 24, 2N2906...07(A)
13009	2N5379	B>100	BC 327A, BC 638, BSW 24, 2N2906...07(A)
13010	2N538(A,M)	80V, 3,5A, 34W, B>20	-
13011	2N5380	60V, 0,2A, 0,36W, <70/225ns	BC 546, BSV 59, BSX 49, 2N2221...22(A)
13012	2N5381	60V, 0,2A, 0,36W, <70/250ns	BC 546, BSV 59, BSX 49, 2N2221...22(A)
13013	2N5382	40V, 0,2A, 0,36W, <70/260ns	BC 307, BC 556, BSW 24, 2N2906...07(A)
13014	2N5383	40V, 0,2A, 0,36W, <70/300ns	BC 307, BC 556, BSW 24, 2N2906...07(A)
13015	2N5384	100/80V, 5A, 30W(Tc100°)	2N5003, 2N5005, 2N5286...87
13016	2N5385	2N5384	2N5003, 2N5005, 2N5286...87
13017	2N5386	100/80V, 12A, 50W(Tc100°)	2N5290...91
13018	2N5387	200/200V, 7,5A, 100W(Tc100°)	2N5540
13019	2N5388	2N5387, 250/250V	2N5540
13020	2N5389	2N5387, 300/300V	2N5540
13021	2N539(A)	2N538, B>30	-
13022	2N5390	120V, 2A, 1W, B>2000	-
13023	2N5391	70V, Idss>0,5mA, Up<2V	-
13024	2N5392	70V, Idss>1mA, Up<2,5V	-
13025	2N5393	70V, Idss>2,5mA, Up<3V	-
13026	2N5394	70V, Idss>4mA, Up<4V	-
13027	2N5395	70V, Idss>5,5mA, Up<4V	-
13028	2N5396	70V, Idss>7,5mA, Up<5V	-
13029	2N5397	25V, Idss>10mA, Up<6V	BF 256C, 2N5486
13030	2N5398	25V, Idss>5mA, Up<6V	BF 256A,B, 2N5486
13031	2N5399	25V, 0,1A, 0,36W, >600MHz	-
13032	2N54	45V, 10m, 0,2W	ASY 48, 2SB56A
13033	2N540(A)	2N538, B>45	-
13034	2N5400	130V, 0,6A, 0,625W, >100MHz	BF 491, 2SA840, 2SA1221...22, 2SA1319
13035	2N5401	2N5400, 160V	BF 491...493, 2SA1221...22, 2SA1319
13036	2N5404	80V, 5A, 1W, >40MHz, B>20	BFT 35...37, BSS 46, 2N6190...93
13037	2N5405	2N5404, 100V	BFT 36...37, 2N6192...93
13038	2N5406	2N5404, B>40	BFT 35...37, BSS 46, 2N6190...93
13039	2N5407	2N5404, 100V, B>40	BFT 36...37, 2N6192...93
13040	2N5408	80V, 5A, 30W(Tc100°), B>20	2N5003, 2N5005, 2N5286...87
13041	2N5409	2N5408, 100V	2N5003, 2N5005, 2N5286...87
13042	2N541(A)	15V, 0,025A, 0,2W, >10MHz	BC 168, BC 183, BC 238, BC 548
13043	2N5410	2N5408, B>40	2N5003, 2N5005, 2N5286...87
13044	2N5411	2N5408, 100V, B>40	2N5003, 2N5005, 2N5286...87
13045	2N5412	80V, 15A, 100W, >60MHz	2N2815...16, 2N2819...20
13046	2N5413	<42/85ns	BSS 14, 2N5262
13047	2N5414	2N5413, 80V	BSS 14, 2N5262
13048	2N5415(S)	>15MHz	BFT 19(A,B), BFT 28A...C), MJ 5415...16
13049	2N5416	>50MHz	BFT 19B, M 5416

13050	2N5417	40V, 0,5A, 0,5W, >250MHz	-
13051	2N5418	B>40	BC 337...338, BC 635, BC 637, BC 639
13052	2N5419	2N5418, B>100	BC 337...338, BC 635, BC 637, BC 639
13053	2N542(A)	2N541, 30V	BC 168, BC 183, BC 238, BC 548
13054	2N5420	2N5418, B>250	BC 337...338, BC 635, BC 637, BC 639
13055	2N5421	36V, 0,5A, PQ1W(175MHz)	BFQ 42, BFR 98, BLW 16, BLY 61
13056	2N5422	36V, 1A, PQ2W(175MHz)	BFQ 43, 2N6255
13057	2N5423	36V, 2A, PQ5W(175MHz)	BLW 35, BLY 79
13058	2N5424(A)	36V, 4A, PQ13W(175MHz)	BLW 36
13059	2N5425	60V, 5A, 32,5W(Tc70°), B>500	-
13060	2N5426	2N5425, B>1000	-
13061	2N5427	2N5336, 7A, 40W	MJE 15028, 2N6316, 2N6372, 2SC3254
13062	2N5428	2N5337, 7A, 40W	MJE 15028, 2N6316, 2N6372, 2SC3254
13063	2N5429	2N5338, 7A, 40W	MJE 15028
13064	2N543(A)	2N541, 50V	BC 167, BC 182, BC 237, BC 547
13065	2N5430	2N5339, 7A, 40W	MJE 15028
13066	2N5431	Ip<0,4µA, Iv>2mA	-
13067	2N5432	Up<10V	-
13068	2N5433	25V, 0,4A, Idss>100mA, Up<9V	-
13069	2N5434	25V, 0,4A, Idss>30mA, Up<4V	-
13070	2N5435	80V, 60A, 120W, B>20	MP 5435
13071	2N5436	2N5435, 110V	MP 5436
13072	2N5437	2N5435, 140V	MP 5437
13073	2N5438	2N5435, B>40	MP 5438
13074	2N5439	2N5435, 110V, B>40	MP 5439
13075	2N544	18V, 0,01A, 0,08W, 30MHz	AF 124...126, AF 200
13076	2N544/12,/33	2N544, 24V	AF 124...126, AF 200
13077	2N5440	2N5435, 140V, B>40	MP 5440
13078	2N5441	200V, 40A, Igt/Ih<100/<60mA	T 6400B
13079	2N5442	2N5441, 400V	T 6400D
13080	2N5443	2N5441, 600V	T 6400M
13081	2N5444	2N5441	T 6401B
13082	2N5445	2N5442	T 6401D
13083	2N5446	2N5443	T 6401M
13084	2N5447	40V, 0,2A, 0,3W, >100MHz	BC 327, BC 636, BC 638, BC 640
13085	2N5448	50V, 0,2A, 0,3W, >100MHz	BC 327, BC 636, BC 638, BC 640
13086	2N5449	50V, 0,8A, 0,36W, >100MHz	BC 337, BC 635, BC 637, BC 639
13087	2N545	60V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13088	2N5450	50V, 0,8A, 0,36W, >100MHz	BC 337, BC 635, BC 637, BC 639
13089	2N5451	40V, 0,8A, 0,36W, >100MHz	BC 337, BC 635, BC 637, BC 639
13090	2N5455	15V, 0,3A, 0,34W, <30/40ns	BSX 36
13091	2N5456	25V, 0,3A, 0,34W, <30/40ns	BSX 36
13092	2N5457		
13093	2N5458	25V, Idss>2mA, Up<7V	BFS 71, 2N3822, 2N4221, 2N5361
13094	2N5459	25V, Idss>4mA, Up<8V	BF 244B...245B, BFS 72, 2N3823, 2N4222



13095	2N546	30V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13096	2N5460		
13097	2N5461	40V, Idss>2mA, Up<7,5V	BF 320B
13098	2N5462	40V, Idss>4mA, Up<9	2N4360
13099	2N5463	2N5460, 60V	-
13100	2N5464	2N5461, 60V	-
13101	2N5465	2N5462, 60V	-
13102	2N5466	500/400V, 3A, 140W, >2,5MHz	BUX 15, BUX 45, 2SC3041, 2SD640
13103	2N5467	2N5466, 700/400V	BUS 11(A), BUX 47(A), BUX 82...83
13104	2N5468	2N5466, 70W	BUT 93, BUY 63...64, MJ 4380...81
13105	2N5469	2N5466, 700/400V, 70W	BUT 11(A), BUY 46(A), MJ 4381, 3SC3490
13106	2N547	60V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13107	2N5471	40V, Idss>0,02mA, Up<4V	2N5797
13108	2N5472	40V, Idss>0,05mA, Up<4V	2N5797
13109	2N5473	40V, Idss>0,1mA, Up<6V	2N5798
13110	2N5474	40V, Idss>0,2mA, Up<7V	2N5798
13111	2N5475	40V, Idss>0,4mA, Up<8V	BF 320A, 2N3909, 2N3820, 2N5799
13112	2N5476	40V, Idss>0,8mA, Up<9V	2N5800
13113	2N5477	2N5336, 7A, 60W	2N3487...92
13114	2N5478	2N5337, 7A, 60W	2N3487...92
13115	2N5479	2N5338, 7A, 60W	2N3488...89, 2N3491...92
13116	2N548	30V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13117	2N5480	2N5339, 7A, 60W	2N3488...89, 2N3491...92
13118	2N5481	50V, 0,2A, 5W, 3GHz	BFQ 68
13119	2N5482	50V, 0,35A, 10W, 3GHz	BFQ 68, BFQ 136, BFT 99
13120	2N5483	45V, 0,7A, 20W, 3GHz	BFQ 136
13121	2N5484	25V, Idss>1mA, Up<3V	BF 410A,B
13122	2N5485	25V, Idss>4mA, Up<4V	BF 256A,B
13123	2N5486	25V, Idss>8mA, Up<6V	BF 256B,C, 2N5397
13124	2N5487	<125/450ns	BUX 34, BUY 80, 2N4895...97
13125	2N5487-1	120V, 5A, 1,2W, <125/450ns	BUX 34, BUY 80, 2N4895...97
13126	2N5487-3	120V, 5A, 1,5W, <125/450ns	BUX 34, BUY 80, 2N4895...97
13127	2N5488	<125/550n	BUY 80, 2N4897
13128	2N5488-1	150V, 5A, 1,2W, <125/550n	BUY 80, 2N4897
13129	2N5488-3	150V, 5A, 1,5W, <125/550n	BUY 80, 2N4897
13130	2N5489	>0,5MHz	2N6309...11
13131	2N549	60V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13132	2N5490	60V, 7A, 50W, >0,8MHz	BD 243A, BD 543A, BD 797, BD 807
13133	2N5491	2N5490	BD 243A, BD 543A, BD 797, BD 807
13134	2N5492	75V, 7A, 50W, >0,8MHz	BD 243B, BD 543B, BD 799, BD 809
13135	2N5493	2N5492	BD 243B, BD 543B, BD 799, BD 809
13136	2N5494	60W, 7A, 50W, >0,8MHz	BD 243A, BD 543A, BD 797, BD 807
13137	2N5495	2N5495	BD 243A, BD 543A, BD 797, BD 807
13138	2N5496	90V, 7A, 50W, >0,8MHz	BD 243B, BD 543C, BD 801, 2SD550
13139	2N5497	2N5498	BD 243B, BD 543C, BD 801, 2SD550



13140	2N5498	150/130V, 15A, 200W, >1MHz	BDX 50, BUW 57...58, BUX 40, 2N3773
13141	2N55	45V, 10m, 0,2W	ASY 48, 2SB56A
13142	2N550	30V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13143	2N551	60V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13144	2N552	30V, 0,8A, 0,6W, >4MHz	BC 140...141, BC 300...302, 2N3053
13145	2N5525	40V, 0,2A, 0,36W, B>5000	BC 517, BC 617, BC 875, MPSA 25...26
13146	2N5526	2N5525, B>1000	BC 517, BC 617, BC 875, MPSA 25...26
13147	2N5527	60V, 5A, 5W(Tc25°),>200MHz	-
13148	2N5528	2N5527, 10A, 35W	-
13149	2N5529	2N5527, 10A, 35W	-
13150	2N553	80V, 4A, 35W	AL 102...103, AUY 21...22, 2N1546...48
13151	2N5530	2N5527, 10A, 35W	-
13152	2N5531	90V, 5A, 5W(Tc25°), >200MHz	-
13153	2N5532	2N5531, 10A, 35W	-
13154	2N5533	2N5531, 10A, 35W	-
13155	2N5534	2N5531, 10A, 35W	-
13156	2N5535	60V, 20A, 50W, >150MHz	-
13157	2N5536	2N5535	-
13158	2N5537	2N5535, 90V	-
13159	2N5538	2N5535, 90V	-
13160	2N5539	>20MHz	2N2818, 2N2822
13161	2N554	15V, 3A, 40W	AD 149, AUY 19...20, 2N2137...46
13162	2N5540	>20MHz	-
13163	2N5541	>20MHz	BUY 48...49
13164	2N5542	>20MHz	-
13165	2N5543	300V, Idss>2mA, Up<15V	2N4882
13166	2N5544	200V, Idss>2mA, Up<15V	2N4883
13167	2N5548	25V, Idss<10nA, Up<5V	-
13168	2N5548	25V, Idss<10nA, Up<5V	-
13169	2N5549	40V, Idss>10mA, Up<6V	BF 256C, BF 348, BFT 10, 2N5397, 2N5486
13170	2N555	2N554, 30V	AD 149, AUY 19...20, 2N2137...46
13171	2N5550	160V, 0,6A, 0,625W, >100MHz	BF 391...393, BFP 22, MPSA 42...43
13172	2N5551	2N5550, 180V	BF 391...393, BFP 22, MPSA 42...43
13173	2N5552	>30MHz	BUY 82, 2SC2527
13174	2N5552-1	2N5552	BUY 82, 2SC2527
13175	2N5552-2(-4)	2N5552	BUY 82, 2SC2527
13176	2N5555	25V, Idss>15mA, Up<5V	2N4092
13177	2N5556	30V, Idss>0,5mA, Up<4V	BFS 70, 2N3821, 2N4220, 2SK104, 2SK301
13178	2N5557	30V, Idss>2mA, Up<5V	2SK107
13179	2N5558	30V, Idss>4mA, Up<6V	BFS 80, BFW 11, 2N4416, 2N5362
13180	2N5559	>0,8MHz	BD 745E, BDX 11, 2N3442, 2SD1047
13181	2N556	25V, 0,2A, 0,1W	AC 127, ASY 28...29, ASY 73...75
13182	2N5560	175/120V, 30A, 150W, >40MHz	2N6324...25
13183	2N5567	200V, 10A, Igt/Ih<40/<30mA	T 4101B
13184	2N5568	2N5567, 400V	T 4101D

13185	2N5569	2N5567	T 4111B
13186	2N557	20V, 0,2A, 0,1W	AC 127, ASY 28...29, ASY 73...75
13187	2N5570	2N5568	T 4111D
13188	2N5571	200V, 15A, Igt/Ih<80/<75mA	2N6157, T 6400B, 2N5441
13189	2N5572	2N5571, 400V	2N6158, T 6400D, 2N5442
13190	2N5573	2N5571	T 6411B, 2N6160, T 6410B, 2N5444
13191	2N5574	2N5572	T 6411D, 2N6161, T 6410D, 2N5445
13192	2N5575	70/50V, 80A, 300W, >0,4MHz	-
13193	2N5576	70/50V, 80A, 300W, >0,4MHz	-
13194	2N5577	70/50V, 80A, 300W, >0,4MHz	-
13195	2N5578	90/70V, 60A, 300W, >0,4MHz	-
13196	2N5579	90/70V, 60A, 300W, >0,4MHz	-
13197	2N558	15V, 0,2A, 0,1W	AC 127, ASY 28...29, ASY 73...75
13198	2N5580	90/70V, 60A, 300W, >0,4MHz	-
13199	2N5581	2N2221A, 0,5W	2N2221A
13200	2N5582	2N2222A, 0,5W	2N2222A
13201	2N5583	30V, 0,5A, 1W, >1300MHz	-
13202	2N5584	70MHz	2N6324...25
13203	2N5587	>0,5MHz	2N6309...11
13204	2N5588	2N5587, 160/160V	-
13205	2N5589	36V, 0,6A, PQ3W(175MHz)	BLY 85, 2N6080
13206	2N559	15V, 0,05A, 0,15W, 100/37ns	ASZ 21, 2N705(A), 2N2635, 2N2955...57
13207	2N5590	36V, 2A, PQ10W(175MHz)	BLW 19, BLW 37, MRF 208, MRF 212
13208	2N5591	36V, 4A, PQ25W(175MHz)	BLY 89, MRF 209, MRF 238, 2N6082...83
13209	2N5592	50V, Idss>1mA, Up<5V	2N5360, 2N5246, 2SK107, 2SK161
13210	2N5593	50V, Idss>1mA, Up<5V	2N5360, 2N5246, 2SK107, 2SK161
13211	2N5594	50V, Idss>1mA, Up<5V	2N5360, 2N5246, 2SK107, 2SK161
13212	2N5595	55V, 1,2A, 30W, >1500MHz	-
13213	2N5596	55V, 2,5A, 45W, >1500MHz	-
13214	2N5597	80V, 2A, 20W, >60MHz	2SA1078...1079, 2SA1288
13215	2N5598	80V, 2A, 20W, >60MHz	2SC2528...2529, 2SC3252
13216	2N5599	100V, 2A, 20W, >50MHz	2SA1078...1079
13217	2N56	45V, 0,2W	ASY 48, 2SB56A
13218	2N560	60V, 0,1A, 0,5W, <60/50ns	2N3722...23, 2N3725, 2SC1385
13219	2N5600	100V, 2A, 20W, >50MHz	2SC2528...2529
13220	2N5601	100V, 2A, 20W, >60MHz	2SA1078...1079
13221	2N5602	100V, 2A, 20W, >60MHz	2SC2528...2529
13222	2N5603	120V, 2A, 20W, >50MHz	2SA1078...1079
13223	2N5604	120V, 2A, 20W, >50MHz	2SC2528...2529
13224	2N5605	80V, 5A, 25W, >70MHz	MJE 15029, MJE 15031, 2SA1289
13225	2N5606	80V, 5A, 25W, >70MHz	MJE 15028, ME 15030, 2SC3253
13226	2N5607	100V, 5A, 25W, >60MHz	MJE 15029, MJE 15031
13227	2N5608	100V, 5A, 25W, >60MHz	MJE 15028, ME 15030
13228	2N5609	100V, 5A, 25W, >70MHz	MJE 15029, MJE 15031
13229	2N561	80V, 5A, 50W	AL 102...103, AUY 21...22, 2N1546...48

13230	2N5610	100V, 5A, 25W, >70MHz	MJE 15028, ME 15030
13231	2N5611	120V, 5A, 25W, >60MHz	MJE 15029, MJE 15031
13232	2N5612	120V, 5A, 25W, >60MHz	MJE 15028, ME 15030
13233	2N5613	80V, 5A, 50W, >70MHz	2N5621, 2SA1141, 2SA1146, 2SA1186
13234	2N5614	80V, 5A, 50W, >70MHz	2N5622, 2SC2681, 2SC2706, 2SC2837
13235	2N5615	100V, 5A, 50W, >60MHz	2N5623, 2SA1141, 2SA1146, 2SA1186
13236	2N5616	100V, 5A, 50W, >60MHz	2N5624, 2SC2681, 2SC2706, 2SC2837
13237	2N5617	100V, 5A, 50W, >70MHz	2N5625, 2SA1141, 2SA1146, 2SA1186
13238	2N5618	100V, 5A, 50W, >70MHz	2N5626, 2SC2681, 2SC2706, 2SC2837
13239	2N5619	120V, 5A, 50W, >60MHz	2N5627, 2SA1141, 2SA1146, 2SA1186
13240	2N5620	120V, 5A, 50W, >60MHz	2N5628, 2SC2681, 2SC2706, 2SC2837
13241	2N5621	80V, 10A, 100W, >40MHz	2SA1146, 2SA1186, 2SA1227, 2SSA1386
13242	2N5622	80V, 10A, 100W, >40MHz	2SC2681, 2SC2706, 2SC2837, 2SSC2987
13243	2N5623	100V, 10A, 100W, >30MHz	2SA1146, 2SA1186, 2SA1227, 2SSA1386
13244	2N5624	100V, 10A, 100W, >30MHz	2SC2681, 2SC2706, 2SC2837, 2SSC2987
13245	2N5625	100V, 10A, 100W, >40MHz	2SA1146, 2SA1186, 2SA1227, 2SSA1386
13246	2N5626	100V, 10A, 100W, >40MHz	2SC2681, 2SC2706, 2SC2837, 2SSC2987
13247	2N5627	120V, 10A, 100W, >30MHz	2SA1146, 2SA1186, 2SA1227, 2SSA1386
13248	2N5628	120V, 10A, 100W, >30MHz	2SC2681, 2SC2706, 2SC2837, 2SSC2987
13249	2N5629		
13250	2N563	30V, 0,3A, 0,15W, B25	AC 128, AC 152...153, AC 188
13251	2N5630	2N5629, 120V	BDX 50, 2N3773, MJ 15015, 2SC2608
13252	2N5631	2N5629, 140V	BDX 50, 2N3773, MJ 15015, 2SC2608
13253	2N5632		
13254	2N5633	2N5632, 120V	BDX 50, 2N3773, MJ 15015, 2SC2608
13255	2N5634	2N5632, 140V	BDX 50, MJ 15015, 2N3773, 2SC2608
13256	2N5635	60V, 1A, PQ3,2W(400MHz)	BLW 93
13257	2N5636	60V, 1,5A, PQ8,4W(400MHz)	BLW 91, 2SC2893
13258	2N5637	60V, 3A, PQ22W(400MHz)	BLX 95, 2SC2894
13259	2N5638	30V, Idss>50mA, <9/15ns	BFS 74, BFS 77, BSV 78, 2N4856, 2N4859
13260	2N5639	30V, Idss>25mA, <14/30ns	BFS 75, BFS 78, BSV 79, 2N4857, 2N4860
13261	2N564	2N563, 0,12W	AC 128, AC 152...153, AC 188
13262	2N5640	30V, Idss>5mA, <18/45ns	BFS 76, BFS 79, BSV 80, 2N4858, 2N4861
13263	2N5641	65V, 1A, PQ7W(175MHz)	BLY 98
13264	2N5642	65V, 3A, PQ20W(175MHz)	2SC2888
13265	2N5643	65V, 5A, PQ40W(175MHz)	BLW 25, 2SC2889
13266	2N5644	36V, 0,25A, PQ1W(470MHz)	2N5944
13267	2N5645	36V, 1A, PQ4W(470MHz)	BLW 43, BLW 80
13268	2N5646	36V, 2A, PQ12W(470MHz)	BLW 44, 2N5946
13269	2N5647	50V, Idss>0,3mA, Up<1,8V	2N4338, 2SK118
13270	2N5648	50V, Idss>0,5mA, Up<2,4V	2N4339, 2N5358, 2SK83, 2SK193...195
13271	2N5649	50V, Idss>0,8mA, Up<3V	2N4339, 2N5358, 2SK83, 2SK193...195
13272	2N565	30V, 0,3A, 0,15W, B55	AC 128, AC 152...153, AC 188
13273	2N5650	20V, 0,03A, 0,15W, >2GHz	BFR 15, BFS 55, BFT 66...67
13274	2N5651	20V, 0,03A, 0,15W, >2GHz	BFR 15, BFS 55, BFT 66...67

13275	2N5652	20V, 0,03A, 0,15W, >2GHz	BFR 15, BFS 55, BFT 66...67
13276	2N5653	Idss>40mA, <9/15ns	BFS 74, BFS 77, BSV 78, 2N4856, 2N4859
13277	2N5654	Idss>15mA, <14/30ns	BFS 75, BFS 78, BSV 79, 2N4857, 2N4860
13278	2N5655	275V, 0,5A, 20W, >10MHz	BF 668, BF 758...759, BF 461...462
13279	2N5656	2N5655, 325V	BF 759, (BF 462)
13280	2N5657	2N5655, 375V	BD 410, 2SC2899, 2SC3051, 2SC3425
13281	2N5658	120/80V, 10A, 30W, >30MHz	2N5288...89, 2N5542
13282	2N5659	2N5659	2N5288...89, 2N5542
13283	2N566	2N565, 0,12W	AC 128, AC 152...153, AC 188
13284	2N5660	250/200V, 1A, 35W, >20MHz	BUW 40(A,B), TIP 47...50, 2N3738...39
13285	2N5661	2N5660, 400/300V	BUW 40(A,B), TIP 47...50, 2N4298...99
13286	2N5662	2N5660, 15W(Tc100°)	BSS 48...49, BUX 51...54, 2N3439...40
13287	2N5663	15W(Tc100°)	BSS 49, BUX 54, 2N3439
13288	2N5664	250/200V, 3A, 52,5W, >20MHz	BUY 63...64, TIP 75(A...C), 2SC2929
13289	2N5665	2N5664, 400/300V	BUY 63...64, TIP 75A...C, 2SC2929
13290	2N5666	2N5664, 15W(Tc100°)	BUX 51...54, 2SD625
13291	2N5667	15W(Tc100°)	BUX 54
13292	2N5668	25V, Idss>1mA, Up<4V	2N5246, 2SK107, 2SK161
13293	2N5669	25V, Idss>4mA, Up<6V	BFS 80, BFW 11, 2N4416, 2N5245, 2N5398
13294	2N567	30V, 0,3A, 0,15W, B100	AC 128, AC 152...153, AC 188
13295	2N5670	25V, Idss>8mA, Up<8V	BF 244C...245C, BFW 10
13296	2N5671	120/90V, 30A, 140W, >50MHz	BDW 30, BDW 32, BDY 58
13297	2N5672	2N5671, 150/120V	BDW 32, BDY 58
13298	2N5675	125/100V, 2A, 1W, >50MHz	-
13299	2N5676	2N5675	2SA1078...79, 2SA1133, 2SB719...720
13300	2N5677	125/100V, 10A, 50W(Tc100°)	2N5290...91
13301	2N5678	125/100V, 20A, 100W(Tc100°)	-
13302	2N5679		BCX 60, BSS 17, 2N3634...35, 2N5322
13303	2N568	2N567, 0,12W	AC 128, AC 152...153, AC 188
13304	2N5680	2N5679, 120V	2N3634...35
13305	2N5681		BCX 40, 2N3019...20, 2N4300, 2SC1860
13306	2N5682	2N5681, 120V	2N3019...20, 2SC1860
13307	2N5683	60V, 50A, 300W, >2MHz	2N6377...79
13308	2N5684	2N5683, 80V	2N6377...79
13309	2N5685	60V, 50A, 300W, >2MHz	2N5575...80
13310	2N5686	2N5685, 80V	2N5578...80
13311	2N5687	40V, 0,5A, 5W(Tc25°)	-
13312	2N5688	40V, 0,5A, 10W	-
13313	2N5689	60V, 3A, 25W	-
13314	2N569	30V, 0,3A, 0,15W, B150	AC 128, AC 152...153, AC 188
13315	2N5690	50V, 5A, 50W	-
13316	2N5691	50V, 8A, 88W	-
13317	2N5692	50V, 40A, 120W	2N2357...59, 2N5435...40
13318	2N5693	2N5692, 80V	2N2358...59, 2N5435...40
13319	2N5694	2N5692, 100V	2N2358...59, 2N5436...37, 2N5439...40

13320	2N5695	2N5692, 120V	2N2359, 2N5437, 2N5440
13321	2N5696	2N5692, 140V	2N5437, 2N5440
13322	2N5697	40V, 0,5A, 3,5W(Tc25°)	-
13323	2N5698	40V, 0,5A, 5W	-
13324	2N5699	40V, 1A, 10W	-
13325	2N570	2N569, 0,12W	AC 128, AC 152...153, AC 188
13326	2N5700	40V, 3A, 35W	-
13327	2N5701	40V, 3A, 35W	-
13328	2N5702	36V, 0,5A, 0,88W	-
13329	2N5703	36V, 0,75A, 10W	-
13330	2N5704	36V, 2A, 25W	-
13331	2N5705	36V, 4A, 44W	-
13332	2N5706	36V, 7A, 80W	-
13333	2N5707	70V, 4A, PQ>20W(30MHz)	MRF 401, MRF 449A
13334	2N5708	70V, 6A, PQ>20W(28MHz)	MRF 449A
13335	2N5709	70V, 12A, PQ>40W(28MHz)	2SC1764
13336	2N571	30V, 0,3A, 0,15W, B200	AC 128, AC 152...153, AC 188
13337	2N5710	40V, 0,5A, 3,5W(Tc25°)	-
13338	2N5711	60V, 0,75A, 10W	-
13339	2N5712	60V, 2A, 25W	-
13340	2N5713	60V, 5A, 45W	-
13341	2N5714	60V, 8A, 70W	-
13342	2N5715	50V,0,2A,6W(Tc25°),>3,5GHz	-
13343	2N5716	40V, Idss>0,05mA, Up<3V	2N3367, 2N3370, 2N4118
13344	2N5717	40V, Idss>0,2mA, Up<5V	2N3366, 2N4119
13345	2N5718	40V, Idss>0,8mA, Up<8V	2N3365
13346	2N5719	Igt/Ih<0,02/<2mA	2N2324A
13347	2N572	2N571, 0,12W	AC 128, AC 152...153, AC 188
13348	2N5720	2N5719, 100V	2N2324A
13349	2N5721	2N5719, 200V	2N2326A
13350	2N5722	2N5719, 300V	2N2328A
13351	2N5723	2N5719, 400V	2N2329A
13352	2N5724	2N5719, 0,39A(Tc90°)	2N2324A
13353	2N5725	2N5720, 0,39A(Tc90°)	2N2324A
13354	2N5726	2N5721, 0,39A(Tc90°)	2N2326A
13355	2N5727	2N5722, 0,39A(Tc90°)	2N2328A
13356	2N5728	2N5723, 0,39A(Tc90°)	2N2329A
13357	2N5729	11,7W(Tc25°),>30MHz	2N4895...97, 2N5338...39, BUX 34, BUY 80
13358	2N573	40V, 0,25A, 0,2W	2N1191...94, 2SB56A
13359	2N5730	100/80V, 10A, 45W, >30MHz	2N5288...89
13360	2N5731	100/80V, 20A, 75W, >30MHz	-
13361	2N5732	100/80V, 20A, 87,5W, >30MHz	BDX 40, BDY 57, 2N3772
13362	2N5733	100/80V, 30A, 150W, >30MHz	-
13363	2N5734	100/80V, 30A, 125W, >30MHz	BDY 29, MJ 802, 2SD797
13364	2N5737	>10MHz	BD 312, BD 546A, BDW 22A, 2N5875...76

13365	2N5738	2N5737, 100V	BD 318, BD 546C, BDW 22C, 2N6229...31
13366	2N5739	2N5737, 20W(Tc100°)	BD 708, BD 744A, BD 808, BDT 82
13367	2N574	60V, 10A, 187W	-
13368	2N5740	2N5737, 100V, 20W(Tc100°)	BD 712, BD 744C, BDT 86
13369	2N5741	>10MHz	BD 250A, BD 367, BD 746A, 2N5883...84
13370	2N5742	2N5741, 100V	BD 250C, BD 746C, MJ 4502
13371	2N5743	2N5741, 25W(Tc100°)	-
13372	2N5744	2N5741, 100V, 25W(Tc100°)	-
13373	2N5745	80V, 20A, 200W, >2MHz	BD 369, MJ 4502, 2N5884
13374	2N574A	2N574, 80V	-
13375	2N575	60V, 25A, 187W	-
13376	2N5754	T 2303A	T 2303A
13377	2N5755	T 2303B	T 2303B
13378	2N5756	T 2303D	T 2303D
13379	2N5757	T 2303M	T 2303M
13380	2N5758	100V, 6A, 150W, >1MHz	BD 245C, BDV 95, BDX 95, 2N5632...33
13381	2N5759	2N5758, 120V	BD 245D, 2N4348, 2N5634, 2SC2607...08
13382	2N575A	2N575, 80V	-
13383	2N576	20V, 0,4A, 0,2W, 5MHz	-
13384	2N5760	2N5758, 140V	BD 245D, 2N4348, 2N5634, 2SC2607...08
13385	2N5761	20V, 0,03A, 0,25W, >3,7GHz	BFQ 60, BFQ 71, 2SC1119, 2SC1336
13386	2N5762	20V, 0,04A, 0,3W, >3,3GHz	BFQ 60, BFQ 71, 2SC1119, 2SC1336
13387	2N5763	65V, 0,6A, 0,4W, <50/250ns	-
13388	2N5764	55V, 0,75A, 10W	-
13389	2N5765	55V, 1,5A, 19W	-
13390	2N5766	55V, 0,2A, 5W	-
13391	2N5767	55V, 0,35A, 10W	-
13392	2N5768	55V, 0,7A, 20W	-
13393	2N5769	>500MHz, <12/18ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
13394	2N576A	2N576, 40V, 8MHz	-
13395	2N5770	30V, 0,05A, 0,7W, >900MHz	BF 377...378, BF 689, BF 763, 2N2857
13396	2N5771	0,625W, >850MHz, <15/20ns	BSX 36, 2N4313, 2N5056...57
13397	2N5772	0,625W, >350MHz, <25/35ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
13398	2N5773	65V, 0,5A, 5W	-
13399	2N5774	65V, 1,5A, 18W	-
13400	2N5775	65V, 3A, 40W	-
13401	2N5776	65V, 6A, 70W	-
13402	2N578	20V, 0,4A, 0,12W, 5MHz	ASY 76...77
13403	2N5781	80V, 3,5A, 1W, <500/2500ns	2N4236, 2N6303
13404	2N5782	2N5781, 65V	2N3720, 2N3868, 2N4235...36, 2N6303
13405	2N5783	2N5781, 45V	2N3720, 2N3868, 2N4235...36, 2N6303
13406	2N5784	80V, 3,5A, 1W, <5/15µs	BSX 63...64, 2N4238...39, 2SC2214
13407	2N5785	2N5784, 65V	BSX 62...64, 2N4238...39, 2SC2214
13408	2N5786	2N5784, 45V	BSX 62...64, 2N4237...39, 2SC2214
13409	2N5787	30V, 0,24A, Igt/Ih<0,35/<10mA	2N2323, 2N6332, TAG 615-100, TIC 44,



13410	2N5788	2N5787, 60V	2N2324, 2N6334, TAG 615-100, TIC 46,
13411	2N5789	2N5787, 100V	2N2324, 2N6334, TAG 615-100, TIC 46,
13412	2N579	2N578, 8MHz	ASY 76...77
13413	2N5790	2N5787, 200V	2N2326, 2N6335, TAG 615-200, TIC 47,
13414	2N5791	2N5787, 300V	2N2328, 2N6336, TAG 615-300, TAG 06C,
13415	2N5792	2N5787, 400V	2N2329, 2N6337, TAG 615-400, TAG 06D,
13416	2N5792	2N5787, 400V	2N2329, 2N6337, TAG 615-400, TAG 06D,
13417	2N5797	40V, Idss>0,02mA, Up<4V	2N2606
13418	2N5798	40V, Idss>0,08mA, Up<6V	-
13419	2N5799	40V, Idss>0,25mA, Up<8V	-
13420	2N580	2N578, 15MHz	ASY 76...77
13421	2N5800	40V, Idss>0,7mA, Up<9V	-
13422	2N5801	40V, Idss>2mA, Up<4V	2N5360, 2N5246, 2SK107
13423	2N5802	40V, Idss>10mA, Up<6V	BF 256C, BF 348, BFT 10, 2N5397, 2N5486
13424	2N5803	40V, Idss>30mA, Up<8V	BFT 10C, 2SK125
13425	2N5804	300/225, 5A, 110W, >15MHz	BUW 71, BUX 16A...C, BUX 18(A...C)
13426	2N5805	2N5804, 375/300V	BUW 71, BUX 16B...C, BUX 18B...C
13427	2N5806	200V, 25A, Igt/Ih<150/<75mA	BTX 94/200
13428	2N5807	2N5806, 400V	BTX 94/400
13429	2N5808	2N5806, 500V	BTX 94/500
13430	2N5809	2N5806, 600V	BTX 94/600
13431	2N581	18V, 0,1A, 0,08W, 8MHz	ASY 26...27, ASY 76...77
13432	2N5810		BC 337...338, BC 635, BC 637, BC 639
13433	2N5811		BC 327...328, BC 636, BC 638, BC 640
13434	2N5812	2N5810, >135MHz, B>150	BC 337...338, BC 635, BC 637, BC 639
13435	2N5813	2N5811, >135MHz, B>150	BC 327...328, BC 636, BC 638, BC 640
13436	2N5814	2N5810, 50V	BC 337, BC 635, BC 637, BC 639
13437	2N5815	2N5811, 50V	BC 327, BC 636, BC 638, BC 640
13438	2N5816	2N5810, 50V, >120MHz, B>100	BC 337, BC 635, BC 637, BC 639
13439	2N5817	2N5811, 50V, >120MHz, B>100	BC 327, BC 636, BC 638, BC 640
13440	2N5818	2N5810, 50V, >135MHz, B>150	BC 337, BC 635, BC 637, BC 639
13441	2N5819	2N5811, 50V, >135MHz, B>150	BC 327, BC 636, BC 638, BC 640
13442	2N582	25V, 0,1A, 0,12W, 18MHz	ASY 26...27, ASY 76...77
13443	2N5820	2N5810, 70V	BC 639, 2SD667, 2SD1226, 2SD1768
13444	2N5821	2N5811, 70V	BC 640, 2B647, 2SB910, 2SB1041
13445	2N5822	2N5810, 70V, >120MHz, B>100	BC 639, 2SD667, 2SD1226, 2SD1768
13446	2N5823	2N5811, 70V, >120MHz, B>100	BC 640, 2B647, 2SB910, 2SB1041
13447	2N5824	B>60	BC 167, BC 182, BC 237, BC 547
13448	2N5825	2N5824, B>100	BC 167, BC 182, BC 237, BC 547
13449	2N5826	2N5824, B>150	BC 167, BC 182, BC 237, BC 547
13450	2N5827	2N5824, B>250	BC 167, BC 182, BC 237, BC 547
13451	2N5827A	2N5827	BC 414, BC 550, 2SC1775(A), 2SC2390
13452	2N5828	2N5824, B>400	BC 167, BC 182, BC 237, BC 547
13453	2N5828A	2N5828	BC 414, BC 550, 2SC1775(A), 2SC2390
13454	2N5829	30V, 0,03A, 0,2W, 1,5GHz	BF 316, BF 439, BF 516, BF 606, BFR 38



13455	2N583	18V, 0,1A, 0,08W, 8MHz	ASY 26...27, ASY 76...77
13456	2N5830	120V, 0,6A, 0,625W, >100MHz	BF 391...393, BFP 22, MPSA 42...43
13457	2N5831	2N5830, 160V	BF 391...393, BFP 22, MPSA 42...43
13458	2N5832	2N5830, 160V	BF 391...393, BFP 22, MPSA 42...43
13459	2N5833	2N5830, 200V	BF 391...393, BFP 22, MPSA 42...43
13460	2N5835	15V, 15mA, 0,2W, >2,5GHz	BFR 15, BFW 99, BFT 66...67
13461	2N5836	15V, 0,2A, >2GHz	BFR 95
13462	2N5837	10V, 0,3A, >1,7GHz	2SC1253, 2SC1366, 2SC1952
13463	2N5838	275/250V, 3A, 100W, >5MHz	BU 606...608, BUX 16A...C, BUW 71
13464	2N5839	2N5838, 300/275V	BU 606...608, BUX 16B...C, BUW 71
13465	2N584	25V, 0,1A, 0,12W, 18MHz	ASY 26...27, ASY 76...77
13466	2N5840	2N5838, 375/350V	BU 606...608, BUX 16B...C, BUW 71
13467	2N5841	20V, 0,1A, 0,35W, >2,7GHz	2SC3337, BFR 95
13468	2N5842	20V, 0,1A, 0,35W, >2GHz	2SC3337, BFR 95
13469	2N5845	50V, 1A, 0,625W, <45/70ns	2N3736...37, 2N4013...14
13470	2N5845A	2N5845, <40/65ns	2N3736...37, 2N4013...14
13471	2N5846	36V, 1A, PQ>3,5W(50MHz)	-
13472	2N5847	36V, 2A, PQ>8W(50MHz)	-
13473	2N5848	48V, 3,5A, PQ>20W(50MHz)	MRF 234
13474	2N5849	48V, 7A, PQ>40W(50MHz)	-
13475	2N585	25V, 0,2A, 0,12W, 5MHz	ASY 28...29, ASY 73...75
13476	2N5851	30V, 0,1A, 0,5W, 1,6/1,6ns	-
13477	2N5852	30V, 0,1A, 0,5W, 1,6/1,6ns	-
13478	2N5853	>15MHz	2N5290...91
13479	2N5854	>20MHz	2N5288...89
13480	2N5855	60V, 1A, 0,75W, >100MHz	BC 327A, BC 638, BC 640, 2SB647
13481	2N5856	60V, 1A, 0,75W, >100MHz	BC 337A, BC 637, BC 639, 2SB647
13482	2N5857	2N5855, 80V	BC 640, 2SB647, 2SB910, 2SB1041
13483	2N5858	2N5856, 80V	BC 639, 2SD667, 2SD1226, 2SD1768
13484	2N5859	<36/70ns	BSS 14, 2N5262
13485	2N586	45V, 0,25A, 0,25W	ASY 76...77, 2N1191...94
13486	2N5860	<26/70ns	-
13487	2N5861	<26/70ns	-
13488	2N5862	65V, 8A, PQ90W(150MHz)	-
13489	2N5864	90V, 1,5A, 1,25W, <130/750ns	BCX 60, BSS 17, BSV 17, 2N5322
13490	2N5865	70V, 1A, 1,25W, <120/500ns	BCX 60, BSS 17, BSX 59...61, 2N3444
13491	2N5867	60V, 5A, 87,5W, >4MHz	BD 246A, BDV 92, BDX 92, 2N5871...72
13492	2N5868	2N5867, 80V	BD 246B, BDV 94, BDX 94, 2N5872
13493	2N5869	60V, 5A, 87,5W, >4MHz	BD 245A, BDV 91, BDX 91, 2N5873...74
13494	2N587	40/20/40V, 0,2A, 0,15W	-
13495	2N5870	2N5869, 80V	BD 245B, BDV 93, BDX 93, 2N5874
13496	2N5871		BD 312, BD 546A, BDW 22A, 2N5875...76
13497	2N5872	2N5871, 80V	BD 314, BD 546B, BDW 22B, 2N5876
13498	2N5873		BD 545A, BD 311, BDW 21A, 2N5877...78
13499	2N5874	2N5873, 80V	BD 545A, BD 313, BDW 21B, 2N5878

13500	2N5875		BD 312, BD 546A, BDW 22A, 2N5879...80
13501	2N5876	2N5875, 80V	BD 314, BD 546B, BDW 22B, 2N5880
13502	2N5877		BD 311, BD 545A, BDW 21A, 2N5881...82
13503	2N5878	2N5877, 80V	BD 313, BD 545B, BDW 21B, 2N5882
13504	2N5879		BD 316, BD 746A, BDW 52A, 2N6029...31
13505	2N588(A)	15V, 0,05A, 250MHz	AF 106, AF 109R, AF 306
13506	2N5880	2N5879, 80V	BD 316, BD 746B, BDW 52B, 2N6029...31
13507	2N5881		BD 315, BD 745A, BDW 51A, 2N5620...31
13508	2N5882	2N5881, 80V	BD 315, BD 745B, BDW 51B, 2N5620...31
13509	2N5883		
13510	2N5884	2N5883, 80V	BD 369, MJ 4502
13511	2N5885		BD 366, BD 368, BDY 29, MJ 802
13512	2N5886	2N5885, 80V	BD 368, BDY 29, MJ 802, 2SD797
13513	2N5887	20V, 7A, 57W, B>15	-
13514	2N5888	2N5887, 30V	-
13515	2N5889	2N5887, 30V, B>30	-
13516	2N589	100V, 3A, 90W	AL 102...103, AUY 34, 2N1547...48
13517	2N5890	2N5887, 45V, B>30	-
13518	2N5891	2N5887, 60V, B>30	-
13519	2N5892	2N5887, 75V, B>30	-
13520	2N5893	2N5887, 30V, B>60	-
13521	2N5894	2N5887, 45V, B>60	-
13522	2N5895	2N5887, 60V, B>60	-
13523	2N5897	2N5887, 30V, B>100	-
13524	2N5898	2N5887, 45V, B>100	-
13525	2N5899	2N5887, 60V, B>100	-
13526	2N59	25V, 0,2A, 0,18W, B90	AC 125...126, AC 151, ASY 26...27
13527	2N5900	2N5887, 75V, B>100	-
13528	2N5901	2N5887, 30V, B>175	-
13529	2N591(5)	32V, 0,04A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
13530	2N5910	20V, 0,05A, 0,31W, <25/30ns	BSX 36
13531	2N5913	36V, 0,33A, PQ2W(470MHz)	BLX 65, MRF 629, 2SC2762, 2SC3185
13532	2N5914	36V, 0,5A, PQ2,3W(470MHz)	BLW 79, BLX 67, BLY 38, 2N5945
13533	2N5915	36V, 1,5A, PQ6,5W(470MHz)	BLU 97, BLX 68, BLY 53, 2SC2105
13534	2N5916	55V, 0,2A, PQ>2W(400MHz)	BFT 91, BLW 89, BLY 76
13535	2N5917	55V, 0,2A, PQ>2W(400MHz)	-
13536	2N5918	60V, 0,75A, PQ>10W(400MHz)	MRF 321, MRF 331
13537	2N5919(A)	65V, 4,5A, PQ>16W(400MHz)	BLX 95, 2N6105, 2SC2894
13538	2N592	20V, 0,125W, >0,4MHz	-
13539	2N5922	55V, 0,425A, PQ1W(1GHz)	BLX 97
13540	2N5923	55V, 0,75A, PQ2,5W(1GHz)	2N4430
13541	2N5924	55V, 1,5A, PQ5W(1GHz)	-
13542	2N5925	50V, 2,5A, PQ10W(1GHz)	-
13543	2N5926	150V, 50A, 350W, >5MHz	2N6278...81
13544	2N5927	150/120V, 100A, 350W, >5MHz	2N6309...11

13545	2N5928	120/120V, 100A, 350W, >5MHz	2N6309...11
13546	2N5929	90/80V, 30A, 175W, >30MHz	BDW 30, BDY 29, MJ 802, 2SD797
13547	2N593	40V, 0,125W, >0,6MHz	-
13548	2N5930	2N5929, 130/120V	BDW 30, BDY 58, 2N5672
13549	2N5931	2N5929, 170/160V	BDW 34, BDW 36
13550	2N5932	70/60V, 30A, 175W, >30MHz	BDW 30, BDY 29, MJ 802, 2SD797
13551	2N5933	2N5931, 110/100V	BDW 30, BDY 58, 2N5672
13552	2N5934	2N5931, 150/140V	BDW 32, BDY 58, 2N5672
13553	2N5935	90/80V, 30A, 175W, >30MHz	BDW 30, BDY 29, MJ 802, 2SD797
13554	2N5936	2N5935, 130/120V	BDW 30, BDY 58, 2N5672
13555	2N5937	2N5935, 170/160V	BDW 34, BDW 36
13556	2N5938	>150MHz	-
13557	2N5939	40W(Tc100°),>120MHz	-
13558	2N594	40V, 0,1W, >1,5MHz	-
13559	2N5940	2N5939, 70V	-
13560	2N5941(T)	65V, 6A, PEP40W(30MHz)	-
13561	2N5942	65V, 12A, PEP80W(30MHz)	MRF 463...464
13562	2N5943	40V, 0,4A, 1W, 1550MHz	BFS 50, MRF 629, 2N3948, 2SC2852
13563	2N5944	36V, 0,4A, PQ2W(470MHz)	BLW 79
13564	2N5945	36V, 0,8A, PQ4W(470MHz)	BLU 97, BLW 43, BLW 80
13565	2N5946	36V, 2A, PQ10W(470MHz)	BLW 81, 2SC2106
13566	2N5947	40V, 0,4A, 5W, 1,5GHz	BFT 91, BLW 89, MRF 313
13567	2N5949	30V, Idss>12mA, Up<7V	BF 244C...245C, BF 256C, BFT 10A
13568	2N5949	30V, Idss>12mA, Up<7V	BF 244C...245C, BF 256C, BFT 10A
13569	2N595	15V, 0,1W, >3MHz	-
13570	2N5950	30V, Idss>10mA, Up<6V	BF 256C, BF 348, BFT 10A, 2N5397, 2N5486
13571	2N5950	30V, Idss>10mA, Up<6V	BF 256C, BF 348, BFT 10A, 2N5397, 2N5486
13572	2N5951	30V, Idss>7mA, Up<5V	BF 256B
13573	2N5951	30V, Idss>7mA, Up<5V	BF 256B
13574	2N5952	30V, Idss>4mA, Up<3,5V	BC 264, BF 410C, 2N5485, 2SK147, 2SK168
13575	2N5952	30V, Idss>4mA, Up<3,5V	BC 264, BF 410C, 2N5485, 2SK147, 2SK168
13576	2N5953	30V, Idss>2,5mA, Up<3V	BC 264, BF 410B, 2SK192, 2SK370
13577	2N5953	30V, Idss>2,5mA, Up<3V	BC 264, BF 410B, 2SK192, 2SK370
13578	2N5954	90V, 6A, 40W, >5MHz	BD 244C, BD 544C, BD 802, 2N6318
13579	2N5955	2N5954, 70V	BD 244B, BD 544B, BD 800, 2N6318
13580	2N5956	2N5954, 50V	BD 244A, BD 544A, BD 798, 2N6317
13581	2N5957	100V, 20A, 150W, >10MHz	-
13582	2N5958	100V, 20A, 150W, >10MHz	-
13583	2N5959	2N5957	-
13584	2N596	10V, 0,1W, >5MHz	-
13585	2N5960	2N5958	-
13586	2N5961	60V, 0,05A, 0,625W, B>150	BC 174, BC 182, BC 190, BC 546
13587	2N5962	2N5961, 45V, B>600	2SC3495
13588	2N5963	2N5961, 30V, B>1200	2SC3495
13589	2N5964	160V, 0,6A, 0,7W, >100MHz	BF 391...393, BFP 22, MPSA 43, 2SD624

13590	2N5965	2N5964, 200V	BF 391...393, BFP 22, MPSA 43, 2SD624
13591	2N5966	100/100V, 30A, 187W, >10MHz	2N2824...25
13592	2N5967	100/100V, 30A, 187W, >10MHz	-
13593	2N5968	2N5966	-
13594	2N5969	2N5967	-
13595	2N597	>3MHz	ASY 76...77
13596	2N5970	B>20	BD 315, BD 545B, 2N3772, 2N5629...31
13597	2N5971	2N5970, B>50	BD 315, BD 545B, 2N3772, 2N5629...31
13598	2N5972	2N5970, 100/80V	BD 317, BD 545C, 2N3772, 2N5629...31
13599	2N5973	2N5970, 120/100V	BDX 50, BD 545D, 2N3773, 2N5630...31
13600	2N5974	60V, 5A, 75W, >2MHz	BD 200, 2N5980, 2SB579
13601	2N5975	2N5974, 80V	2N5981, 2SB580
13602	2N5976	2N5974, 100V	2N5982, 2SB581
13603	2N5977	60V, 5A, 75W, >2MHz	BD 199, 2N5983, 2SD493
13604	2N5978	2N5977, 80V	2N5984, 2SD494
13605	2N5979	2N5977, 100V	2N5985, 2SD495
13606	2N598	>5,6MHz	ASY 76...77
13607	2N5980	60V, 8A, 90W, >2MHz	BD 208, MJE 2955, 2N5986, 2SB578
13608	2N5981	2N5980, 80V	2N5987
13609	2N5982	2N5980, 100V	2N5988
13610	2N5983	60V, 8A, 90W, >2MHz	BD 207, MJE 3055, 2N5989, 2SD491
13611	2N5984	2N5983, 80V	2N5990
13612	2N5985	2N5983, 100V	2N5991
13613	2N5986	60V, 12A, 100W, >2MHz	-
13614	2N5987	2N5986, 80V	-
13615	2N5988	2N5986, 100V	-
13616	2N5989	60V, 12A, 100W, >2MHz	-
13617	2N599	>10MHz	ASY 76...77
13618	2N5990	2N5989, 80V	-
13619	2N5991	2N5989, 100V	-
13620	2N5992	65V, 5A, PQ>7W(88MHz)	-
13621	2N5993	36V, 5A, PQ20W(88MHz)	-
13622	2N5994	65V, 5A, PQ35W(175MHz)	BLW 25, 2N5643, 2SC2889
13623	2N5995	36V, 1,5A, PQ>7W(175MHz)	2SC2281
13624	2N5996	36V, 5A, PQ>15W(175MHz)	BLW 20, BLW 31, 2N6084
13625	2N5998	35V, 0,5A, 0,4W, 300MHz	BC 184, BC 239, BC 337...338, BC 549
13626	2N5999	35V, 0,5A, 0,4W, 300MHz	BC 214, BC 309, BC 327...328, BC 559
13627	2N59A	2N59, 40V	ASY 48, ASY 76...77
13628	2N59B	2N59, 50V	ASY 48, ASY 77
13629	2N59C	2N59, 60V	ASY 48, ASY 77
13630	2N600	35V, 0,5A, 0,75W, 10MHz	AC 128K, AC 153K, ASY 76...77
13631	2N6000	35V, 0,5A, 0,4W, B>100	BC 184, BC 239, BC 337...338, BC 549
13632	2N6001	35V, 0,5A, 0,4W, B>100	BC 214, BC 309, BC 327...328, BC 559
13633	2N6002	2N6000, B>250	BC 184, BC 239, BC 337...338, BC 549
13634	2N6003	2N6001, B>250	BC 214, BC 309, BC 327...328, BC 559

13635	2N6004	50V, 0,5A, 0,4W, B>100	BC 337, BC 414, BC 550, BC 637
13636	2N6005	50V, 0,5A, 0,4W, B>100	BC 327, BC 416, BC 560, BC 638
13637	2N6006	2N6004, B>250	BC 337, BC 414, BC 550, BC 637
13638	2N6007	2N6005, B>250	BC 327, BC 416, BC 560, BC 638
13639	2N6008	35V, 0,5A, 0,4W, 300MHz	BC 184, BC 239, BC 337...338, BC 549
13640	2N6009	35V, 0,5A, 0,4W, 300MHz	BC 214, BC 309, BC 327...328, BC 559
13641	2N601	30V, 0,5A, 0,75W, 18MHz	AC 128K, AC 153K, ASY 76...77
13642	2N6010	50V, 0,8A, 0,5W, B>100	BC 337, BC 637, BSV 59, 2N2221...22(A)
13643	2N6011	50V, 0,8A, 0,5W, B>100	BC 327, BC 638, BSW 24, 2N2906...07(A)
13644	2N6012	2N6010, B>250	BC 337, BC 637, BSV 59, 2N2221...22(A)
13645	2N6013	2N6011, B<250	BC 327, BC 638, BSW 24, 2N2906...07(A)
13646	2N6014	70V, 0,8A, 0,5W, B>100	BC 639, BSV 59, 2N2221...22A, 2SD667
13647	2N6015	70V, 0,8A, 0,5W, B>100	BC 640, BSW 24, 2N2906...07A, 2SB647
13648	2N6016	2N6014, B>250	BC 639, BSV 59, 2N2221...22A, 2SD667
13649	2N6017	2N6015, B>250	BC 640, BSW 24, 2N2906...07A, 2SB647
13650	2N602(A)	20..35V, 0,12W, 20MHz	AF 124...126, AF 200
13651	2N6021	80/70V, 4A, 36W, >0,8MHz	BD 244B, BD 538, BD 540B, BD 952
13652	2N6022	2N6021	BD 244B, BD 538, BD 540B, BD 952
13653	2N6023	2N6021, 60/40V	BD 244A, BD 536, BD 540A, BD 950
13654	2N6024	2N6021, 60/40V	BD 244A, BD 536, BD 540A, BD 950
13655	2N6025	2N6021, 80/60V	BD 244B, BD 538, BD 540B, BD 952
13656	2N6026	2N6021, 80/60V	BD 244B, BD 538, BD 540B, BD 952
13657	2N6027	Ip<5μA, Iv>70μA	2N6116, 2N6119, MPU131, MPU 231
13658	2N6027	Ip<5μA, Iv>70μA	2N6116, 2N6119, MPU131, MPU 231
13659	2N6028	2N6027, Ip<1μA, Iv>25μA	2N6120
13660	2N6028	2N6027, Ip<1μA, Iv>25μA	2N6120
13661	2N6029		
13662	2N603(A)	30V, 0,12W, 40MHz	AF 124...126, AF 200
13663	2N6030	2N6029, 120V	MJ 15016, 2N6609, 2SA1117
13664	2N6031	2N6029, 140V	MJ 15016, 2N6609, 2SA1117
13665	2N6032	120/90V, 50A, 140W, >50MHz	2N6275...77
13666	2N6033	150/120V, 40A, 140W, >50MHz	2N6275...77
13667	2N6034	40V, 4A, 40W, B>750	BD 676, BD 776
13668	2N6035	2N6034, 60V	BD 678, BD 778
13669	2N6036	2N6034, 80V	BD 680, BD 780
13670	2N6037	40V, 4A, 40W, B>750	BD 675, BD 775
13671	2N6038	2N6037, 60V	BD 677, BD 777
13672	2N6039	2N6037, 80V	BD 679, BD 779
13673	2N604(A)	30V, 0,12W, 60MHz	AF 124...126, AF 200
13674	2N6040		BD 646, BD 898, BDW 74A, BDX 54A
13675	2N6041	2N6040, 80V	BD 648, BD 900, BDW 74B, BDX 54B
13676	2N6042	2N6040, 100V	BD 650, BD 902, BDW 74C, BDX 54C
13677	2N6043		BD 645, BD 897, BDW 73A, BDX 53A
13678	2N6044	2N6043, 80V	BD 647, BD 899, BDW 73B, BDX 53B
13679	2N6045	2N6043, 100V	BD 649, BD 901, BDW 73C, BDX 53C

13680	2N6046	>30MHz	2N2815...18, 2N2819...22
13681	2N6047	2N6046, 110V	2N2817...18, 2N2821...22
13682	2N6048	2N6046, 150V	2N2817...18, 2N2821...22
13683	2N6049	90V, 4A, 75W, >3MHz	BD 244C, BD 540C, BD 954, BDX 14
13684	2N605	15V, 0,12W, 15MHz	AF 124...127, AF 200
13685	2N6050		BDV 66, BDW 84A, BDX 64, BDX 88A
13686	2N6051	2N6050, 80V	BDV 66A, BDW 84B, BDX 64A, BDX 88B
13687	2N6052	2N6050, 100V	BDV 66A, BDW 84C, BDX 64B, BDX 88C
13688	2N6053		BDV 64, BDX 62, MJ 900, TIP 145
13689	2N6054	2N6053, 80V	BDV 64A, BDX 62A, MJ 901, TIP 146
13690	2N6055		BDV 65, BDX 63, MJ 1000, TIP 140
13691	2N6056	2N6055, 80V	BDV 65A, BDX 63A, MJ 1001, TIP 141
13692	2N6057		BDV 67, BDW 83A, BDX 65, BDX 87A
13693	2N6058	26057, 80V	BDV 67A, BDW 83B, BDX 65A, BDX 87B
13694	2N6059	2N6057, 100V	BDV 65A, BDW 83C, BDX 65B, BDX 87C
13695	2N606	15V, 0,12W, 20MHz	AF 124...127, AF 200
13696	2N6060	100/100V, 50A, 225W, >10MHz	2N6278...81
13697	2N6061	100/100V, 50A, 225W, >10MHz	2N6380...82
13698	2N6062	2N6060	-
13699	2N6063	2N6061	-
13700	2N6064	80V, 10A, 56W	-
13701	2N6065	2N6064, 120V	-
13702	2N6066	2N6064, 160V	-
13703	2N6067	50V, 1A, 0,625W, <45/95ns	2N4026...29
13704	2N6068	Igt/Ih<30/<30mA	TAG96A, TAG136A, Z0410A, TAG231-200
13705	2N6068...6075A	2N6068..6075, Igt/Ih<10/<15mA	TAG97..., TAG137..., Z0409..., TAG 232...
13706	2N6068...6075B	2N6068..6075, Igt/Ih<5/<15mA	TAG98..., TAG138..., Z0405..., TAG233...
13707	2N6069	2N6068, 50V	TAG96A, TAG136A, Z0410A, TAG231-200
13708	2N607	15V, 0,12W, 25MHz	AF 124...126, AF 200
13709	2N6070	2N6068, 100V	TAG96A, TAG136A, Z0410A, TAG231-200
13710	2N6071	2N6068, 200V	TAG96B, TAG136B, Z0410B, TAG231-200
13711	2N6072	2N6068, 300V	TAG96C, TAG136C, Z0410C, TAG231-400
13712	2N6073	2N6068, 400V	TAG96D, TAG136D, Z0410D, TAG231-400
13713	2N6074	2N6068, 500V	TAG96E, TAG136E, Z0410E, TAG231-600
13714	2N6075	2N6068, 600V	TAG96M, TAG136M, Z0410M, TAG231-600
13715	2N6076	25V, 0,1A, 0,36W, 200MHz	BC 213, BC 258, BC 308, BC 558
13716	2N6077	300/275V, 7A, 45W, 7MHz	BU 406...408, BUT 56(A), 2SC1865
13717	2N6078	275/250V, 7A, 45W, 7MHz	BU 406...408, BUT 56(A), 2SC1865
13718	2N6079	375/350V, 7A, 45W, 7MHz	BU 406, BU 408, BUT 56(A), 2SC1865
13719	2N608	15V, 0,12W, 35MHz	AF 124...126, AF 200
13720	2N6080		
13721	2N6081	36V, 2,5A, PQ15W(175MHz)	BLW 29, BLY 84, BLY 88, MRF 226
13722	2N6082	36V, 5A, PQ25W(175MHz)	BLY 89, MRF 209, 2N5591
13723	2N6083	36V, 5A, PQ30W(175MHz)	MRF 238
13724	2N6084	36V, 7A, PQ40W(175MHz)	BLW 60



13725	2N609	25V, 0,2A, 0,18W, B100	AC 125...126, AC 151, 2SB54, 2SB56
13726	2N6094	36V, 1A, PQ4W(175MHz)	-
13727	2N6095	36V, 2,5A, PQ15W(175MHz)	-
13728	2N6096	36V, 4A, PQ30W(175MHz)	-
13729	2N6097	36V, 4A, PQ40W(175MHz)	-
13730	2N6098	70V, 10A, 75W, >0,8MHz	BD 709, BD 743A, BD 807, BD 909
13731	2N6099	2N6098	BD 709, BD 743A, BD 807, BD 909
13732	2N60A..C	2N59A..C, B65	2N59A...C
13733	2N610	2N609, B80	AC 125...126, AC 151, 2SB54, 2SB56
13734	2N6100	2N6098, 80V	BD 709, BD 743B, BD 809, BD 909
13735	2N6101	2N6098, 80V	BD 709, BD 743B, BD 809, BD 909
13736	2N6102	2N6098, 45V, 16A	BD 743, BD 905, BDT 81
13737	2N6103	2N6098, 45V, 16A	BD 743, BD 905, BDT 81
13738	2N6104	65V, 4,5A, PQ>30W(400MHz)	-
13739	2N6105	65V, 4,5A, PQ>30W(400MHz)	-
13740	2N6106		BD 244B, BD 544B, BD 800, BD 810
13741	2N6107	2N6106	BD 244B, BD 544B, BD 800, BD 810
13742	2N6108	2N6106, 60V	BD 244A, BD 544A, BD 798, BD 808
13743	2N6109	2N6106, 60V	BD 244A, BD 544A, BD 798, BD 808
13744	2N611	2N609, B60	AC 125...126, AC 151, 2SB54, 2SB56
13745	2N6110	2N6106, 40V	BD 244, BD 544, BD 796, BD 806
13746	2N6111	2N6106, 40V	BD 244, BD 544, BD 796, BD 806
13747	2N6112	50V, 0,36W, >160MHz	BC 167, BC 182, BC 237, BC 547
13748	2N6114	Ip<5μA, Iv>1mA	-
13749	2N6115	2N6114, Ip<15μA	-
13750	2N6116	Ip<5μA, Iv>70μA	2N6027, 2N6119, MPU131, MPU231
13751	2N6117	2N6116, Ip<2μA, Iv>50μA	MPU132, MPU232
13752	2N6118	2N6116, Ip<1μA, Iv>50μA	MPU133, MPU233
13753	2N6119	Ip<5μA, Iv>70μA	2N6027, 2N6116, MPU131, MPU231
13754	2N612	2N609, B25	AC 125...126, AC 151, 2SB54, 2SB56
13755	2N6120	2N6119, Ip<1μA, Iv>25μA	2N6028
13756	2N6121		BD 243, BD 533, BD 539, BD 947
13757	2N6122	2N6121, 60V	BD 243A, BD 535, BD 539A, BD 949
13758	2N6123	2N6121, 80V	BD 243B, BD 537, BD 539B, BD 951
13759	2N6124	45V, 4A, 40W, >2,5W	BD 244, BD 534, BD 540, BD 948
13760	2N6125	2N6124, 60V	BD 244A, BD 536, BD 540A, BD 950
13761	2N6126	2N6124, 80V	BD 244B, BD 538, BD 540B, BD 952
13762	2N6127	>40MHz	2N5290...91
13763	2N6128	>50MHz	2N5288...89
13764	2N6129		BD 543, BD 705, BD 795, BD 805
13765	2N613	2N609, B33	AC 125...126, AC 151, 2SB54, 2SB56
13766	2N6130	2N6129, 60V	BD 543A, BD 707, BD 797, BD 807
13767	2N6131	2N6129, 80V	BD 543B, BD 709, BD 799, BD 809
13768	2N6132	40V, 7A, 50W, >2,5MHz	BD 544, BD 706, BD 796, BD 806
13769	2N6133	2N6132, 60V	BD 544A, BD 708, BD 798, BD 808



13770	2N6134	2N6132, 80V	BD 544B, BD 710, BD 800, BD 810
13771	2N6136	36V, 6A, PQ25W(470MHz)	2SC1339, 2SC2173
13772	2N6137	Iv>70μA	-
13773	2N6138	2N6138	-
13774	2N6139	Igt/Ih<75/<40mA	T4110E, 2N5573, T6411B, 2N6160, T6410B
13775	2N614	20V, 0,15A, 0,125W, 3MHz	ASY 26...27, ASY 76...77
13776	2N6140	2N6139, 400V	T4110E, 2N5574, T6411D, 2N6161, T6410D
13777	2N6141	2N6139, 600V	T4110M, T6411M, 2N6162, T6410M, 2N5446
13778	2N6142	2N6139	2N6139
13779	2N6143	2N6140	2N6140
13780	2N6144	2N6141	2N6141
13781	2N6145	2N5571	T 6421B, 2N6163, T6420B
13782	2N6146	2N5572	T6421D, 2N6164, T6420D
13783	2N6147	T 4100M	T6421M, 2N6165, T6420M
13784	2N615	20V, 0,15A, 0,125W, 5MHz	ASY 26...27, ASY 76...77
13785	2N6151	2N6139	-
13786	2N6152	2N6140	-
13787	2N6153	2N6141	-
13788	2N6154	200V, 10A, Igt<50mA	-
13789	2N6155	2N6154, 400V	-
13790	2N6156	2N6154, 600V	-
13791	2N6157	Igt/Ih<100/<80mA	T6401B, T6400B, 2N5441
13792	2N6158	2N6157, 400V	T6401D, T6400D, 2N5442
13793	2N6159	2N6157, 600V	T6401M, T6400M, 2N5443
13794	2N616	15V, 0,15A, 0,125W, 9MHz	ASY 26...27, ASY 76...77
13795	2N6160	2N6157	T6411B, T6410B, 2N5444
13796	2N6161	2N6158	T6411D, T6410D, 2N5445
13797	2N6162	2N6159	T6411M, T6410M, 2N5446
13798	2N6163	2N6157	T6421B, T6420B
13799	2N6164	2N6158	T6421D, T6420D
13800	2N6165	2N6159	T6421M, T6420M
13801	2N6166	65V, 9A, PQ100W(150MHz)	BLW 78
13802	2N6167	Igt/Ih<40/50mA	2N6171, MCR 65-3
13803	2N6168	2N6167, 200V	2N6172, MCR 65-4
13804	2N6169	2N6167, 400V	2N6173, MCR 65-6
13805	2N617	15V, 0,15A, 0,125W, 7,5MHz	ASY 26...27, ASY 76...77
13806	2N6170	2N6167, 600V	2N6174, MCR 65-8
13807	2N6171	2N3870	MCR 65-3
13808	2N6172	2N3871	MCR 65-4
13809	2N6173	2N3872	MCR 65-6
13810	2N6174	2N3873	MCR 65-8
13811	2N6175	300V, 1A, 20W, >21MHz	BD 410, BUV 63, 2SC3051, 2SC3425
13812	2N6175	300V, 1A, 20W, >21MHz	BD 410, BUV 63, 2SC3051, 2SC3425
13813	2N6176	2N6175, 350V	BD 410, BUV 63, 2SC3051, 2SC3425
13814	2N6176	2N6175, 350V	BD 410, BUV 63, 2SC3051, 2SC3425

13815	2N6177	2N6175, 450V	BD 410, BUV 63, 2SC3051, 2SC3425
13816	2N6177	2N6175, 450V	BD 410, BUV 63, 2SC3051, 2SC3425
13817	2N6178	100V, 2A, 25W, >50MHz	BD 139, BD 230, BD 379, BD 529
13818	2N6178	100V, 2A, 25W, >50MHz	BD 139, BD 230, BD 379, BD 529
13819	2N6179	2N6178, 75V	BD 139, BD 230, BD 377, BD 527
13820	2N6179	2N6178, 75V	BD 139, BD 230, BD 377, BD 527
13821	2N618	80V, 3A, 106W	2N1541...43, 2N1546...48, 2N3615...18
13822	2N6180	100V, 2A, 25W, >50MHz	BD 140, BD 231, BD 380, BD 530
13823	2N6180	100V, 2A, 25W, >50MHz	BD 140, BD 231, BD 380, BD 530
13824	2N6181	2N6182, 75V	BD 140, BD 231, BD 378, BD 528
13825	2N6181	2N6182, 75V	BD 140, BD 231, BD 378, BD 528
13826	2N6182	B>30	2N5290...91
13827	2N6183	2N6182, B>60	2N5290...91
13828	2N6184	2N6182, 100V	2N5290...91
13829	2N6185	2N6182, 100V, B>60	2N5290...91
13830	2N6186	2N6182	2N5290...91
13831	2N6187	2N6183	2N5290...91
13832	2N6188	2N6184	2N5290...91
13833	2N6189	2N6185	2N5290...91
13834	2N619	50V, 0,05A, 0,25W, B>9	BC 167, BC 182, BC 237, BC 547
13835	2N6190	>30MHz, B>30	BFT 35...37, BUY 90
13836	2N6191	2N6190, B>60	BFT 35...37, BUY 90
13837	2N6192	2N6190, 100V	BFT 36...37, BUY 90
13838	2N6193	2N6190, 100V, B>60	BFT 36...37, BUY 90
13839	2N6194	50V, 5W	-
13840	2N6195	50V, 10W	-
13841	2N6196	50V, 20W	-
13842	2N6197	60V, 1A, 10W	-
13843	2N6198	60V, 2,5A, 25W	-
13844	2N6199	60V, 5A, 50W	-
13845	2N61A..C	2N59A..C, B45	2N59A...C
13846	2N62	35V, 0,02A, 0,05W	AC 125...126, AC 151
13847	2N620	2N619, B>18	BC 167, BC 182, BC 237, BC 547
13848	2N6200	60V, 8,5A, 85W	-
13849	2N6201	60V, 12A, 140W	-
13850	2N6202	60V, 0,5A, 10W	-
13851	2N6203	60V, 1A, 20W	-
13852	2N6204	60V, 2A, 40W	-
13853	2N6205	60V, 4A, 80W	-
13854	2N6206	50V, 0,5A, 10W	-
13855	2N6207	50V, 1A, 20W	-
13856	2N6208	50V, 2A, 40W	-
13857	2N621	2N619, B>36	BC 167, BC 182, BC 237, BC 547
13858	2N6211	275/225V, 2A, 35W, >20MHz	2SA1397
13859	2N6212	2N6211, 350/300V	2SA1397

13860	2N6213	2N6211, 400/350V	BUX 66C, 2SA1009A, 2SA1236, 2SA1397
13861	2N6214	2N6211, 450/400V	2N6422...23
13862	2N6215	>20MHz	2N6060, 2N6278...81
13863	2N6216	>20MHz	BUX 17(A...C), BUX 42...43, BUY 18
13864	2N6217	2N6216, 180V	BUX 17(A...C), BUX 42...43, BUY 18
13865	2N6218	300V, 0,05A, 0,5W, >50MHz	BF 299, BF 420, BF 483, 2SC3468
13866	2N6219	2N6218, 250V	BF 298...299, BF 420, BF 483, 2SC3468
13867	2N622	50V, 0,05A, 0,386W	BC 167, BC 182, BC 237, BC 547
13868	2N6220	2N6218, 200V	BF 298...299, BF 422, BF 483, 2SC3468
13869	2N6221	2N6218, 150V	BF 297...299, BF 422, BF 483, 2SC3468
13870	2N6222	60V, 0,1A, 0,36, B>75	BC 174, BC 182, BC 190, BC 546
13871	2N6223	60V, 0,1A, 0,36W, B>75	BC 212, BC 256, BC 266, BC 556
13872	2N6224	2N6222, B>150	BC 174, BC 182, BC 190, BC 546
13873	2N6225	2N6223, B>150	BC 212, BC 256, BC 266, BC 556
13874	2N6226	100V, 6A, 150W, >1MHz	BD 246C, BDV 96, BDX 96, 2N6229...31
13875	2N6227	2N6226, 120V	BD 246D, 2N6230...31, 2SA1116...17
13876	2N6228	2N6226, 140V	BD 246D, 2N6231, 2SA1116...17, 2SB555
13877	2N6229	100V, 10A, 150W, >1MHz	BD 318, 2N6029...31, 2SA1116...17
13878	2N6230	2N6229, 120V	MJ 15016, 2N6030...31, 2SA1116...17
13879	2N6231	2N6229, 140V	MJ 15016, 2N6031, 2SA1116...17, 2SB555
13880	2N6232	>30MHz	BUY 82
13881	2N6232-4	>30MHz	BUY 82
13882	2N6233	250/225V, 5A, 50W, >20MHz	BUT 56(A), BUX 63, 2SC2907, 2SC3035
13883	2N6234	2N6233, 300/275V	BUT 56(A), BUX 63, 2SC2907, 2SC3035
13884	2N6235	2N6233, 350/325V	BUT 56(A), BUX 63, 2SC2907, 2SC3035
13885	2N6236	Igt/Ih<0,2/<5mA	MCR106-1, C108Y, TAG108Y, S2060Y
13886	2N6237	2N6236, 50V	MCR106-2, C108F, TAG108F, S2060F
13887	2N6238	2N6236, 100V	MCR106-3, C108A, TAG108A, S2060A
13888	2N6239	2N6236, 200V	MCR106-4, C108B, TAG108B, S2060B
13889	2N624	30V, 10mA, 0,1W, >12MHz	AF 124...127, AF 200
13890	2N6240	2N6236, 400V	MCR106-6, C108D, TAG108D, S2060D
13891	2N6241	2N6236, 600V	MCR106-8, C108M, TAG108M, S2060M
13892	2N6246	70V, 15A, 125W, >6MHz	BD 316, BD 546B, MJ 2955, 2N6029...31
13893	2N6247	2N6246, 90V	BD 318, BD 546C, MJ 2955, 2N6029...31
13894	2N6248	2N6246, 110V	BD 318, BD 546D, MJ 2955, 2N6030...31
13895	2N6249		BUX 17A...C, BUW 24...25, BUW 72
13896	2N625	40V, 1A	-
13897	2N6250	2N6249, 375/275V	BUX 17B,C, BUW 24...25, BUW 34, BUW 72
13898	2N6251	2N6249, 450/350V	BUX 17C, BUW 24...25, BUW 34, BUW 72
13899	2N6253	55V, 15A, 115W, >0,8MHz	BD 315, BD 545A, 2N3055, 2N5881...82
13900	2N6254	100V, 15A, 150W, >0,8MHz	BD 317, BD 545C, 2N3772, 2N5629...31
13901	2N6255	36V, 1A, PQ3W(175MHz)	BFQ 43, BFS 22, BFW 46, 2N3924
13902	2N6256	36V, 0,4A, PQ0,5W(470MHz)	BLU 98, MRF 627...628
13903	2N6257	50V, 20A, 150W, >0,8MHz	BD 364, BDX 40...41, 2N3771...72
13904	2N6258	100V, 30A, 250W, >0,8MHz	BDY 29, MJ 802, 2SD797

13905	2N6259	170V, 16A, 250W, >0,2MHz	BDW 14, BDY 56, 2SC2607...08, 2SD753
13906	2N6260	50V, 3A, 29W, >0,8MHz	BD 241, BD 535, BD 935, 2N4231...33
13907	2N6261	90V, 4A, 50W, >0,8MHz	BD 243B, BD 539C, BD 953, 2N3054
13908	2N6262	170V, 10A, 150W, >0,8MHz	BD 745F, BDY 54, 2SC2607...08, 2SD753
13909	2N6263	140V, 3A, 20W, >0,2MHz	BD 241D, BD 243D, 2N3441, 2SD608
13910	2N6264	170V, 3A, 50W, >0,2MHz	BD 241E, BD 243E, 2SD386(A)
13911	2N6265	50V, 0,275A, PQ>2W(2GHz)	-
13912	2N6266	50V, 1A, PQ>5W(2GHz)	-
13913	2N6267	50V, 1,5A, PQ>10W(2GHz)	-
13914	2N6268	45V, 0,35A, PQ>2W(2,3GHz)	-
13915	2N6269	45V, 1,5A, PQ>6,5W(2,3GHz)	-
13916	2N627	40V, 10A, 94W	AL 100...101, AUY 21, 2N2288...93
13917	2N6270	>75MHz	2N5671
13918	2N6271	2N6270, 120V	2N5671
13919	2N6272	2N6270	2N2824...25
13920	2N6273	2N6270, 120V	2N2825
13921	2N6274		2N6032...33
13922	2N6275	2N6274, 140V	2N6033
13923	2N6276	2N6274, 160V	-
13924	2N6277	2N6274, 180V	-
13925	2N6278	2N6274	-
13926	2N6279	2N6274, 140V	-
13927	2N628	2N627, 60V	AL 100...101, AUY 21, 2N2292...93
13928	2N6280	2N6274, 160V	-
13929	2N6281	2N6274, 180V	-
13930	2N6282		BDX 69(A...C), MJ 11012, 2SD730, 2SD1460
13931	2N6283	2N6282, 80V	BDX 69A...C, MJ 11014, 2SD730, 2SD1460
13932	2N6284	2N6282, 100V	BDX 69B...C, MJ 11016, 2SD730, 2SD1460
13933	2N6285		BDX 68(A...C), MJ 11011, 2SB694
13934	2N6286	2N6285, 80V	BDX 68A...C, MJ 11013, 2SB694
13935	2N6287	2N6285, 100V	BDX 68B...C, MJ 11015, 2SB694
13936	2N6288		BD 243, BD 543, BD 795, BD 805
13937	2N6289	2N6288	BD 243, BD 543, BD 795, BD 805
13938	2N629	2N627, 80V	AL 100...101, AUY 37, 2N2292...93
13939	2N6290	2N6288, 60V	BD 243A, BD 543A, BD 797, BD 807
13940	2N6291	2N6288, 60V	BD 243A, BD 543A, BD 797, BD 807
13941	2N6292	2N6288, 80V	BD 243B, BD 543B, BD 799, BD 809
13942	2N6293	2N6288, 80V	BD 243B, BD 543B, BD 799, BD 809
13943	2N6294	60V, 4A, 50W, B>750	BD 645, BD 897, BDW 23A, BDW 63A
13944	2N6295	2N6294, 80V	BD 647, BD 899, BDW 23B, BDW 63B
13945	2N6296	60V, 4A, 50W, B>750	BD 646, BD 898, BDW 24A, BDW 64A
13946	2N6297	2N6296, 80V	BD 648, BD 900, BDW 24B, BDW 64B
13947	2N6298	2N6053, 75W	BD 646, BD 898, BDW 74A, BDX 54A
13948	2N6299	2N6054, 75W	BD 648, BD 900, BDW 74B, BDX 54B
13949	2N63	25V, 0,02A, 0,1W	AC 125...126, AC 151

13950	2N630	2N627, 100V	AL 100...101, AUY 37, 2N2290, 2N2293
13951	2N6300	2N6055, 75W	BD 645, BD 897, BDW 73A, BDX 53A
13952	2N6301	2N6056, 75W	BD 647, BD 899, BDW 73B, BDX 53B
13953	2N6302	140V, 16A, 150W, >0,2MHz	BD 745E, BDX 50, 2N3773, 2SC2608
13954	2N6303	<100/400ns	-
13955	2N6304	30V, 0,05A, 0,2W, >1400MHz	BFS 55, BFR 37, BFW 30, BFX 73
13956	2N6305	30V, 0,05A, 0,2W, >1200MHz	BFS 55, BFR 37, BFW 30, BFX 73
13957	2N6306		BUS 12(A), BUW 25...26, BUW 34...36
13958	2N6307	2N6306, 600/300V	BUS 12(A), BUW 25...26, BUW 35...36
13959	2N6308	2N6306, 700/350V	BUS 12(A), BUW 26, BUW 35...36
13960	2N6309	120V, 90A, 400W, >30MHz	-
13961	2N631	25V, 0,05A, 0,167W	AC 125...126, AC 151, 2SB54, 2SB56
13962	2N6310	2N6309, 140V	-
13963	2N6311	2N6309, 160V	-
13964	2N6312	40V, 5A, 75W, >4MHz	BD 244, BD 540, BD 948, 2SB550
13965	2N6313	2N6312, 60V	BD 244A, BD 540A, BD 950, 2SB550
13966	2N6314	2N6312, 80V	BD 244B, BD 540B, BD 952, 2SB550
13967	2N6315	2N5873, 90W	BD 543A, BD 797, BD 807, 2N5428...30
13968	2N6316	2N5874, 90W	BD 543B, BD 799, BD 809, 2N5428...30
13969	2N6317	2N5871, 90W	BD 544A, BD 798, BD 808, 2N5954...55
13970	2N6318	2N5872, 90W	BD 544B, BD 800, BD 810, 2N5954
13971	2N632	30V, 0,05A, 0,167W	AC 125...126, AC 151, 2SB54, 2SB56
13972	2N6322	300/200V, 30A, 350W, >10MHz	BUR 21...22, BUV 22...23, BUX 22...23
13973	2N6323	2N6322, 400/300V	BUV 23, BUX 23
13974	2N6324	2N6322	-
13975	2N6325	2N6322, 400/300V	-
13976	2N6326	60V, 30A, 200W, >3MHz	BDY 29, MJ 802, 2N6270...72, 2SD797
13977	2N6327	2N6326, 80V	BDY 29, MJ 802, 2N6270...72, 2SD797
13978	2N6328	2N6326, 100V	BDY 29, MJ 802, 2N6270...72, 2SD797
13979	2N6329	60V, 30A, 200W, >3MHz	MJ 4502
13980	2N633	35V, 0,05A, 0,167W	AC 125...126, AC 151, 2SB54, 2SB56
13981	2N6330	2N6329, 80V	MJ 4502
13982	2N6331	2N6329, 100V	MJ 4502
13983	2N6332	Igt/Ih<0,2/<5mA	TAG 615-100, C 106Y, TAG 106Y
13984	2N6333	2N6332, 50V	TAG 615-100, C 106F, TAG 106F
13985	2N6334	2N6332, 100V	TAG 615-100, C 106A, TAG 106A
13986	2N6335	2N6332, 200V	TAG 615-200, C 106B, TAG 106B
13987	2N6336	2N6332, 300V	TAG 615-400, C 106C, TAG 106C
13988	2N6337	2N6332, 400V	TAG 615-400, C 106D, TAG 106D
13989	2N6338	120V, 25A, 200W, >40MHz	BDW 30, 2N5671...72, 2N6272, 2N6274...77
13990	2N6339	2N6338, 140V	BDW 30, BDY 58, 2N5672, 2N6275...77
13991	2N634(A)	20..25V, 0,3A, 0,15W, 8MHz	ASY 28...29, ASY 73...75
13992	2N6340	2N6338, 160V	BDW 32, BDY 58, 2N6276...77
13993	2N6341	2N6338, 180V	BDW 34, 2N6277
13994	2N6342	Igt/Ih<50/<40mA	T2802B, MAC222-4, TIC226B, TXD10K40

13995	2N6342A	2N6342, 12A(Tc80°)	TIC236B, TW11N400, TXD10K40P, MAC15-4
13996	2N6343	2N6342, 400V	T2802D, MAC222-6, TIC226D, TXD10K40
13997	2N6343A	2N6343, 12A(Tc80°)	TIC236D, TW11N400, TXD10K40P, MAC15-6
13998	2N6344	2N6342, 600V	T2802M, MAC222-8, TIC226M, TXD10K60
13999	2N6344A	2N6344, 12A(Tc80°)	8
14000	2N6345	2N6342, 800V	T2802N, MAC222-10, TIC226N, TXD10K80
14001	2N6345A	2N6345, 12A(Tc80°)	10
14002	2N6346	Igt/Ih<75/<40mA	TAG224-200, MAC222A-4, BT137/500
14003	2N6346A	2N6346, 12A(Tc80°)	BT138/500, TAG255-200, TXD10H40P
14004	2N6347	2N6346, 400V	TAG224-400, MAC222A-6, BT137/500
14005	2N6347A	2N6347, 12A(Tc80°)	BT138/500, TAG255-400, TXD10H40P
14006	2N6348	2N6346, 600V	TAG224-600, MAC222A-8, BT137/600
14007	2N6348A	2N6348, 12A(Tc80°)	BT138/600, TAG255-600, TXD10H60P
14008	2N6349	2N6346, 800V	TAG224-800, MAC222A-10, BT137/800
14009	2N6349A	2N6349, 12A(Tc80°)	BT138/800, TAG255-800, TXD10H80P
14010	2N635(A)	20..25V, 0,3A, 0,15W, 12MHz	ASY 28...29, ASY 73...75
14011	2N6350	80V, 5A, 5W(Tc50°), B>2000	-
14012	2N6351	150V, 5A, 5W(Tc50°), B>1000	-
14013	2N6354	150/120V, 10A, 140W, >80MHz	-
14014	2N6355	50V, 20A, 150W, B>500	BDX 69(A...C), 2N6282...84, MJ 11012
14015	2N6356	2N6355, B>1500	BDX 69(A...C), 2N6282...84, MJ 11012
14016	2N6357	2N6355, 80V	BDX 69A...C, 2N6283...84, MJ 11014
14017	2N6358	2N6355, 80V, B>1500	BDX 69A...C, 2N6283...84, MJ 11014
14018	2N6359	100V, 16A, 150W, >0,2MHz	BD 317, BDX 40, 2N3772, 2N5629...31
14019	2N636(A)	20..25V, 0,3A, 0,15W, 17MHz	ASY 28...29, ASY 73...75
14020	2N6360	2N6359, 120V	BDX 50, 2N3773, 2N5630...31, 2SC2608
14021	2N6361	60V, 4A, 50W	-
14022	2N6362	60V, 6A, 110W	-
14023	2N6363	50V, 10A, 175W	-
14024	2N6364	50V, 10A, 175W	-
14025	2N6365(A)	30V, 0,1A, 0,15W, 500MHz	-
14026	2N6366	36V, 1A, PEP2,5W(30MHz)	MRF 476
14027	2N6367	36V, 2A, PEP9W(30MHz)	MRF 433
14028	2N6368	40V, 8A, PEP40W(30MHz)	MRF 460
14029	2N6369	60V, 15A, 220W	-
14030	2N637	-/40V, 5A, 60W	AL 102...103, AUY 28, 2N1545...48
14031	2N6370	65V, 1,5A, PEP10W(30MHz)	MRF 433
14032	2N6371	50V, 5A, 150W, >0,8MHz	BD 315, BDX 40, 2N3772, 2N5629...31
14033	2N6372	90V, 6A, 40W, >4MHz	BD 243C, BD 543C, BD 801, 2N5429...30
14034	2N6373	2N6372, 70V	BD 243B, BD 543B, BD 799, 2N5427...30
14035	2N6374	2N6372, 50V	BD 243A, BD 543A, BD 797, 2N5427...30
14036	2N6375	75V, 1,5A, 0,58W, <16/45ns	2N3737
14037	2N6376	2N6375, 1W	BSS 14, 2N3735, 2N5262, 2N5859...61
14038	2N6377	100V, 50A, 250W, >30MHz	-
14039	2N6378	2N6377, 120V	-



14040	2N6379	2N6377, 140V	-
14041	2N637A	2N637, -/70V	AL 102...103, AUY 28, 2N1546...48
14042	2N637B	2N637, -/80V	AL 102...103, AUY 28, 2N1547...48
14043	2N638	-/40V, 5A, 60W	AL 102...103, AUY 28, 2N1545...48
14044	2N6380	2N6377	-
14045	2N6381	2N6377, 120V	-
14046	2N6382	2N6377, 140V	-
14047	2N6383		BDV 67, BDW 83, BDX 83, BDX 85
14048	2N6384	2N6383, 60V	BDV 67, BDW 83A, BDX 83A, BDX 85A
14049	2N6385	2N6383, 80V	BDV 67A, BDW 83B, BDX 83B, BDX 85B
14050	2N6386		BD 643, BD 895, BDW 73, BDX 53
14051	2N6387	2N6386, 60V, 10A	BD 645, BD 897, BDW 73A, BDX 53A
14052	2N6388	2N6386, 80V, 10A	BD 647, BD 899, BDW 73B, BDX 53B
14053	2N6389	20V, 0,04A, 0,2W, >1GHz	BF 377...378, BFR 37, BFW 30, BFX 73
14054	2N638A	2N638, -/70V	AL 102...103, AUY 28, 2N1546...48
14055	2N638B	2N638, -/80V	AL 102...103, AUY 28, 2N1547...48
14056	2N639	-/40V, 5A, 60W	AL 102...103, AUY 28, 2N1545...48
14057	2N6390	50V, 1A, 8,3W	-
14058	2N6391	50V, 2,5A, 16W	-
14059	2N6392	50V, 3,5A, 21W	-
14060	2N6393	45V, 3,5A, 21W	-
14061	2N6394	Igt/Ih<30/<40mA	TAG665-100, TIC126F, T7,5N400, 2N6400
14062	2N6395	2N6394, 100V	TAG665-100, TIC126A, T7,5N400, 2N6401
14063	2N6396	2N6394, 200V	TAG665-200, TIC126B, T7,5N400, 2N6402
14064	2N6397	2N6394, 400V	TAG665-400, TIC126D, T7,5N400, 2N6403
14065	2N6398	2N6394, 600V	TAG665-600, TIC126M, T7,5N600, 2N6404
14066	2N6399	2N6394, 800V	TAG665-800, TIC126N, T7,5N800, 2N6405
14067	2N639A	2N639, -/70V	AL 102...103, AUY 28, 2N1546...48
14068	2N639B	2N639, -/80V	AL 102...103, AUY 28, 2N1547...48
14069	2N64	25V, 0,02A, 0,1W	AC 125...126, AC 151
14070	2N640	34V, 10mA, 0,08W, 42MHz	AF 124...126, AF 200
14071	2N6400	Igt/Ih<30/<40mA	TAG680-100, TAG681-100, T9,5N400
14072	2N6401	2N6400, 100V	TAG680-100, TAG681-100, T9,5N400
14073	2N6402	2N6400, 200V	TAG680-200, TAG681-200, T9,5N400
14074	2N6403	2N6400, 400V	TAG680-400, TAG681-400, T9,5N400
14075	2N6404	2N6400, 600V	TAG680-600, TAG681-600, T9,5N600
14076	2N6405	2N6400, 800V	TAG680-800, TAG681-800, T9,5N800
14077	2N6406	80V, 2A, 12,5W, >50MHz	BD 378, BD 788, BD 790, 2SB874...875
14078	2N6407	2N6407, 100V	BD 380, BD 792, 2SB874...875
14079	2N6408	80V, 2A, 12,5W, >50MHz	BD 377, BD 787, BD 789, 2SD1177...78
14080	2N6409	2N6408, 100V	BD 379, BD 791, 2SD1177...1178
14081	2N641	34V, 10mA, 0,08W, 42MHz	AF 124...126, AF 200
14082	2N6410	40V, 4A, 15W, >50MHz	BD 785, MJE 240...244, 2SD1348
14083	2N6411	40V, 4A, 15W, >50MHz	BD 786, MJE 250...254, 2SB986
14084	2N6412	60V, 4A, 15W, >50MHz	BD 785, MJE 240...244, 2SD1348



14085	2N6413	2N6412, 80V	BD 787, BD 789, MJE 240...244
14086	2N6414	60V, 4A, 15W, >50MHz	BD 786, MJE 250...254, 2SB986
14087	2N6415	2N6414, 80V	BD 788, BD 790, MJE 250...254
14088	2N6416	80V, 3A, 15W, >40MHz	BD 787, BD 789, MJE 240...244
14089	2N6417	2N6416, 100V	BD 791, BDX 35...37, MJE 243...244
14090	2N6418	80V, 3A, 15W, >40MHz	BD 788, BD 790, MJE 250...254
14091	2N6419	2N6418, 100V	BD 792, MJE 253...254
14092	2N642	34V, 10mA, 0,08W, 42MHz	AF 124...126, AF 200
14093	2N6420	250/175V, 1A, 35W, >10MHz	BUX 66A...C, 2N5344...45, 2SA1009(A)
14094	2N6421	375/250V, 1A, 35W, >10MHz	BUX 66C, 2N6213...14, 2SA1009A
14095	2N6422	500/300V, 2A, 35W, >10MHz	-
14096	2N6423	500/300V, 2A, 35W, >15MHz	-
14097	2N6424	250/225V, 1A, 20W, >10MHz	BUX 66A...C, 2N5344...45, 2SA1009(A)
14098	2N6425	325/300V, 1A, 20W, >10MHz	BUX 66B...C, 2N6212...14, 2SA1009(A)
14099	2N6426	40V, 0,5A, 0,625W, B>20000	BC 517, BC 617, MPSA 25...29, 2SD892A
14100	2N6427	40V, 0,5A, 0,625W, B>10000	BC 517, BC 617, MPSA 25...29, 2SD892A
14101	2N6428(A)	60V, 0,2A, 0,625W, >100MHz	BC 414, BC 550, 2SC1775(A), 2SC2390
14102	2N6429(A)	55V, 0,2A, 0,625W, >700MHz	BC 414, BC 550, 2SC1775(A), 2SC2390
14103	2N643	30V, 0,1A, 0,12W, 30MHz	2N2955...57
14104	2N6430	200V, 0,5A, 0,5W, >50MHz	BF 391...393, BFP 22, MPSA 42...43
14105	2N6431	2N6430, 300V	BF 393, BFP 25, MPSA 42, 2SD1350
14106	2N6432	200V, 0,5A, 0,5W, >50MHz	BF 491...493, BFP 23, MPSA 92...93
14107	2N6433	2N6432, 300V	BF 493, BFP 26, MPSA 92, 2SB1074
14108	2N6436	100V, 25A, 200W, >40MHz	2N6377...79
14109	2N6437	2N6436, 120V	2N6378...79
14110	2N6438	2N6436, 140V	2N6379
14111	2N6439	60V, PQ60W(400MHz)	MRF 327, 2SC2186, 2SC2796
14112	2N644	30V, 0,1A, 0,12W, 50MHz	2N2955...57
14113	2N6449	300V, Idss>2mA, Up<15V	-
14114	2N645	30V, 0,1A, 0,12W, 75MHz	2N2955...57
14115	2N6450	200V, Idss>2mA, Up<15V	-
14116	2N6451	20V, Idss>5mA, Up<3,5V	BC 264, BF 410C, 2SK147, 2SK168
14117	2N6452	25V, Idss>5mA, Up<3,5V	BC 264, BF 410C, 2SK147, 2SK168
14118	2N6453	20V, Idss>15mA, Up<5V	BF 256B, BF 348, BFT 10A,B, 2N5397
14119	2N6454	25V, Idss>15mA, Up<5V	BF 256B, BF 348, BFT 10A,B, 2N5397
14120	2N6455	45V, 7A, 60W, >75MHz	-
14121	2N6456	45V, 12A, 75W, >60MHz	-
14122	2N6457	45V, 20A, 140W, >50MHz	-
14123	2N6458	45V, 7A, 75W, >75MHz	-
14124	2N6459	45V, 12A, 120W, >60MHz	-
14125	2N646	25V, 0,05A, 0,1W	AC 127, ASY 28...29
14126	2N6460	45V, 20A, 140W, >50MHz	-
14127	2N6461	B>30	BF 259, BF 659, BFS 89, 3N5058
14128	2N6462	2N6461, B>100	BF 259, BF 659, BFS 89, 3N5058
14129	2N6463	2N6461, 250V	BF 258...259, BF 658...659, 2N5058...59

14130	2N6464	2N6461, 250V, B>100	BF 258...259, BF 658...659, 2N5058...59
14131	2N6465	110V, 4A, 40W, >5MHz	BD 243C, BD 539D, BD 955, 2SD961
14132	2N6466	2N6465, 130V	BD 243D, 2SC2516, 2SD961
14133	2N6467	110V, 4A, 40W, >5MHz	BD 244C, BD 540D, BD 956, 2SB869
14134	2N6468	2N6467, 130V	BD 244D, 2SB869
14135	2N6469	50V, 15A, 125W, >10MHz	BD 316, BD 546A, MJ 2955, 2N5879...80
14136	2N647(/22)	25V, 0,05A, 0,1..0,18W	AC 127, ASY 28...29
14137	2N6470	50V, 15A, 125W, >5MHz	BD 315, BD 545A, 2N3055, 2N5881...82
14138	2N6471	2N6470, 70V	BD 315, BD 545B, 2N3055, 2N5881...82
14139	2N6472	2N6470, 90V	BD 317, BD 545C, 2N3055, 2N5882
14140	2N6473	2N6465	2N6465
14141	2N6474	2N6466	2N6466
14142	2N6475	2N6467	2N6467
14143	2N6476	2N6468	2N6468
14144	2N6477	140V, 2,5A, 50W, >0,2MHz	BD 241D, BD 941, 2SC2516
14145	2N6478(A)	2N6477, 160V	BD 241D
14146	2N6486		
14147	2N6487	2N6486, 70V	BD 743B, BD 909, BDT 83
14148	2N6488	2N6486, 90V	BD 743C, BD 911, BDT 85
14149	2N6489	50V, 15A, 75W, >5MHz	BD 744A, BD 908, BDT 82
14150	2N649(/5,22)	20V, 0,05A, 0,1..0,18W	AC 127, ASY 28...29
14151	2N6490	2N6489, 70V	BD 744B, BD 910, BDT 84
14152	2N6491	2N6489, 90V	BD 744C, BD 912, BDT 86
14153	2N6492	55V, 15A, 100W, B>500	BDV 67, BDW 83A, BDX 67, MJ 4033
14154	2N6493	100V, 15A, 100W, B>500	BDV 67A, BDW 83C, BDX 67B, MJ 4035
14155	2N6494	100V, 15A, 100W, B>500	BDV 67A, BDW 83C, BDX 67B, MJ 4035
14156	2N6495	150V, 10A, 70W, >25MHz	BUS 36...37, BUV 27(A), 2SC2867
14157	2N6496		BUW 57...58, BUX 41, 2SD552, 2SD583
14158	2N6497	350/250V, 5A, 80W, >5MHz	BUT 56(A), MJE 51T...53T, 2SC2907
14159	2N6498	2N6497, 400/300V	BUT 56(A), MJE 52T...53T, 2SC2907
14160	2N6499	2N6497, 450/350V	BUT 56(A), MJE 53T, 2SC3056
14161	2N65	25V, 0,02A, 0,125W	AC 125...126, AC 151
14162	2N650(A)	45V, 0,5A, 0,2W, B>33	2N1189...90, 2SB405ST
14163	2N6500	120V, 4A, 35W, >60MHz	BDV 10...12, BUX 77, 2SC2767, 2SD772
14164	2N6504	50V, 25A, Igt/Ih<40/<40mA	MCR 69-2
14165	2N6505	2N6504, 100V	MCR 69-3
14166	2N6506	2N6504, 200V	-
14167	2N6507	2N6504, 400V	-
14168	2N6508	2N6504, 600V	-
14169	2N6509	2N6504, 800V	-
14170	2N651(A)	2N650, B>45	2N1189...90, 2SB405ST
14171	2N6510	250/200V, 7A, 120W, >3MHz	BUX 18(A...C), BUX 43...44, 2SC3041
14172	2N6511	2N6510, 300/250V	BUX 18(A...C), BUX 43...44, 2SC3041
14173	2N6512	2N6510, 350/300V	BUX 18A...C, BUX 43...44, 2SC3041
14174	2N6513	2N6510, 400/350V	BUX 18B...C, BUX 43...44, 2SC3041

14175	2N6514	2N6510, 350/300V	BUX 18A...C, BUX 43...44, 2SC3041
14176	2N6515	250V, 0,5A, 0,625W, >40MHz	BF 392...393, BFP 25, MPSA 42, 2SD1350
14177	2N6516	2N6515, 300V	BF 393, BFP 25, MPSA 42, 2SD1350
14178	2N6517	2N6515, 350V	2SD1350
14179	2N6518	250V, 0,5A, 0,625W, >40MHz	BF 492...493, BFP 26, MPSA 92, 2SB1074
14180	2N6519	2N6518, 300V	BF 493, BFP 26, MPSA 92, 2SB1074
14181	2N652(A)	2N650, B>80	2N1189...90, 2SB405ST
14182	2N6520	2N6518, 350V	BF 493S, 2SB1074
14183	2N6521	60V, 1A, 0,7W, B>10000	-
14184	2N6522	2N6521, B>20000	-
14185	2N6523	40V, 0,6A, 5W	-
14186	2N6524	40V, 1,2A, 10W	-
14187	2N6525	40V, 2,5A, 20W	-
14188	2N6526	50V, 0,5A, 3,9W	-
14189	2N6527	50V, 1A, 5W	-
14190	2N6528	50V, 1,2A, 10W	-
14191	2N6529	50V, 2,5A, 20W	-
14192	2N653	30V, 0,25A, 0,2W, B>30	AC 125...126, AC 151
14193	2N6530	80V, 8A, 65W, B>1000	BD 647, BD 899, BDX 53B, BDX 73B
14194	2N6531	100V, 8A, 65W, B>500	BD 649, BD 901, BDX 53C, BDX 73C
14195	2N6532	100V, 8A, 65W, B>1000	BD 649, BD 901, BDX 53C, BDX 73C
14196	2N6533	120V, 8A, 65W, B>1000	BD 651, BDT 21, BDX 53D, BDX 73D
14197	2N6534	2N6530, 36W	2N6530
14198	2N6535	2N6531, 36W	2N6531
14199	2N6536	2N6532, 36W	2N6532
14200	2N6537	2N6533, 36W	2N6532
14201	2N6538	60V, 0,2A, 0,625W, >200MHz	BC 414, BC 550, 2SC2240, 2SC2459
14202	2N6539	60V, 0,2A, 0,625W, >200MHz	BC 414, BC 550, 2SC2240, 2SC2459
14203	2N654	2N653, B>50	AC 125...126, AC 151
14204	2N6540	80V, 0,2A, 0,625W, >200MHz	2SC1775(A), 2SC2240, 2SC2459, 2SC2390
14205	2N6541	80V, 0,2A, 0,625W, >200MHz	2SC1775(A), 2SC2240, 2SC2459, 2SC2390
14206	2N6542		BUS 11(A), BUX 82...83, 2SC3048
14207	2N6543	2N6542, 850/400V	BUS 11(A), BUX 82...83, 2SC3048
14208	2N6544	650/300V, 8A, 125W, >6MHz	BUS 12(A), BUX 47(A), 2SC3092, 2SD811
14209	2N6545	2N6544, 850/400V	BUS 12(A), BUX 47(A), 2SC3092, 2SD811
14210	2N6546	650/300V, 15A, 175W, >6MHz	BUS 13(A), BUS 97(A), BUX 47(A...C)
14211	2N6547	2N6546, 850/400V	BUS 13(A), BUS 97(A), BUX 47(A...C)
14212	2N6548	50V, 2A, 10W, B>25000	BD 411...412, MPSU 45
14213	2N6549	2N6548, B>15000	BD 411...412, MPSU 45
14214	2N655	2N653, B>100	AC 125...126, AC 151
14215	2N6550	20V, Idss10..250mA, Up<3V	-
14216	2N6551	60V, 1A, 10W, >75MHz	BC 366, BD 415, BD 517, BD 525
14217	2N6552	2N6551, 80V	BC 367, BD 417, BD 519, BD 527
14218	2N6553	2N6551, 100V	BD 419, BD 529
14219	2N6554	60V, 1A, 10W, >75MHz	BC 363, BD 416, BD 518, BD 526

14220	2N6555	2N6554, 80V	BC 364, BD 418, BD 520, BD 528
14221	2N6556	2N6554, 100V	BD 420, BD 530
14222	2N6557	250V, 0,5A, 10W, >45MHz	BF 381...382, BF 460...462, MPSU 10
14223	2N6558	2N6557, 300V	BF 382, BF 461...462, BF 468, MPSU 10
14224	2N6559	2N6557, 350V	BF 462
14225	2N656(A,S)	60V, 0,5A, 1W	BC 140...141, BC 300...302, 2N3053
14226	2N6560	450/450V, 10A, 220W, >10MHz	-
14227	2N6561	2N6560, 300/300V	-
14228	2N6562	2N6560, 175W	2N6689...93
14229	2N6563	2N6560, 300/300V, 175W	2N6689...93
14230	2N6564	Igt/Ih<0,2/<5mA	2N5064, TAG 72D, TAG 59D, 2N6683
14231	2N6565	2N6564, 400V	TAG 72D, TAG 59D, 2N6683
14232	2N6566	30/30/30V, 0,1A, 0,4W	-
14233	2N6567	30/30/30V, 0,1A, 0,4W	-
14234	2N6568	30V, Idss>500mA, Up<10V	-
14235	2N6569		BD 315, BD 545A, BDW 51, 2N5881...82
14236	2N657(A,S)	2N656, 100V	BC 141, BC 300, 2N1889...90, 2N1990
14237	2N6570	100V, 40A, 250W, >1MHz	2N6032...33, 2N6274...77
14238	2N6571	2N6570, 115V	2N6032...33, 2N6274...77
14239	2N6572	60V, 12A, 250W	-
14240	2N6573	500/250V, 10A, 125W, 15MHz	BUW 25...26, BUW 34...36, 2SC3046
14241	2N6574	2N6573, 600/275V	BUW 25...26, BUW 35...36, 2SC3046
14242	2N6575	2N6573, 700/300V	BUS 12(A), BUW 26, BUW 35...36, 2SC3046
14243	2N6576	60V, 15A, 120W, B>500	BDV 67, BDW 83A, BDX 67, MJ 4033
14244	2N6577	2N6576, 90V	BDV 67A, BDW 83C, BDX 67B, MJ 4035
14245	2N6578	2N6576, 120V	BDV 67B, BDW 83D, BDX 67C
14246	2N6579	450/350V, 10A, 125W, >25MHz	BUW 24...26, BUW 34...36, 2SC3046
14247	2N658	25/16V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB405
14248	2N6580	500/400V, 10A, 125W, >25MHz	BUW 25...26, BUW 34...36, 2SC3046
14249	2N6581	550/450V, 10A, 125W, >25MHz	BUW 25...26, BUW 35...36, 2SC3046
14250	2N6582	450/350V, 10A, 125W, >25MHz	BUW 24...26, BUW 34...36, 2SC3046
14251	2N6583	500/400V, 10A, 125W, >25MHz	BUW 25...26, BUW 34...36, 2SC3046
14252	2N6584	550/450V, 10A, 125W, >25MHz	BUW 25...26, BUW 35...36, 2SC3046
14253	2N6585	2N6579	2N6689...93
14254	2N6586	2N6580	2N6690, 2N6692...93
14255	2N6587	2N6581	2N6690, 2N6692...93
14256	2N6588	2N6582	2N6689...93
14257	2N6589	2N6583	2N6690, 2N6692...93
14258	2N659	25/14V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB405
14259	2N6590	2N6584	2N6690, 2N6692...93
14260	2N6591	150V, 0,5A, 10W, >35MHz	BF 380...382, BF 460...462, MPSU 10
14261	2N6592	2N6591, 200V	BF 381...382, BF 460...462, MPSU 10
14262	2N6593	2N6591, 250V	BF 381...382, BF 460...462, MPSU 10
14263	2N6594	45V, 12A, 100W, >2,5MHz	BD 316, BD 546A, BDW 52, 2N5879...80
14264	2N6595	20V, 25mA, 0,2W, >3,5GHz	BFQ 22, BFQ 53, BFT 66...67

14265	2N6596	15V, 25mA, 0,2W, >3,5GHz	BFQ 22, BFQ 53, BFT 66...67
14266	2N6597	20V, 25mA, 0,2W, >4GHz	BFQ 22, BFQ 53, BFT 66...67
14267	2N6598	15V, 25mA, 0,2W, >4GHz	BFQ 22, BFQ 53, BFT 66...67
14268	2N6599	20V, 75mA, 0,5W, >3GHz	BFQ 63, 2SC2570, 2SC3037, 2SC3337
14269	2N660	25/11V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB405
14270	2N6601	20V, 50mA, 0,25W, >1GHz	BFQ 63, BFS 55, 2SC2498
14271	2N6602	-/15V, 25mA, >3,5GHz	BFQ 59...60, BFQ 72, BFT 65, 2SC2844
14272	2N6603	25V, 30mA, >3,5GHz	BFQ 59...60, BFQ 72, BFT 65, 2SC2844
14273	2N6604	25V, 50mA, >3,5GHz	BFQ 72, BFT 65, 2SC2844
14274	2N6605	Igt/Ih<0,2/<5mA	TAG 06Y, TIC 44, TIC 60, MCR 100-3
14275	2N6606	2N6605, 60V	TAG 06YY, TIC 46, TIC 62, MCR 100-3
14276	2N6607	2N6605, 100V	TAG 06A, TIC 46, TIC 62, MCR 100-3
14277	2N6608	2N6605, 200V	TAG 06B, TIC 47, TIC 64, MCR 100-4
14278	2N6609	160/140V, 16A, 150W, >2MHz	BD 746F, MJ 15016, 2SA1117
14279	2N661	25/9V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB405
14280	2N6617	-/16V, 10mA, 0,15W, 8GHz	BFQ 33, BFQ 77, 2SC1948
14281	2N6618	8GHz	BFQ 33, BFQ 77, 2SC1948
14282	2N662	25/10V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB405
14283	2N6622	>4MHz	BUS 12(A), BUW 26, BUW 35...36, BUX 81
14284	2N663	50V, 4A, 35W	AD 149, AUY 19...20, 2N1529...48
14285	2N6648	40V, 10A, 100W, B>1000	BDV 64, BDX 84, BDX 86, MJ 2500
14286	2N6649	2N6648, 60V	BDV 64, BDX 84A, BDX 86A, MJ 2500
14287	2N665	80V, 3A, 35W	AL 102...103, AUY 20, 2N2141, 2N2146
14288	2N6650	2N6648, 80V	BDV 64A, BDX 84B, BDX 86B, MJ 2501
14289	2N6653	350/300V, 20A, 150W, >25MHz	BUV 24, BUX 24, 2SC3085
14290	2N6654	2N6653, 400/350V	BUV 24, BUX 24, 2SC3085
14291	2N6655	2N6653, 450/400V	BUV 24, BUX 24, 2SC3085
14292	2N6656	<10/10ns	BUZ 63, 2SK259...260
14293	2N6657	<10/10ns	BUZ 62, 2SK259...260
14294	2N6658	<10/10ns	BUZ 63, 2SK259...260
14295	2N6659	<1,8Ohm(1A)	
14296	2N6660	<3Ohm(1A)	-
14297	2N6661	<4Ohm(1A)	-
14298	2N6665	20V, 0,125A, 0,45W, 2GHz	2SC2408, BFR 95
14299	2N6666	40V, 8A, 65W, B>1000	BD 644, BD 896, BDW 74, BDX 54
14300	2N6667	2N6666, 60V	BD 646, BD 898, BDW 74A, BDX 54A
14301	2N6668	2N6666, 80V	BD 648, BD 900, BDW 74B, BDX 54B
14302	2N6669	40V, 10A, 40W, >10MHz	BD 705, BD 743, BD 805, BD 905
14303	2N6670	80V, 1,5A, PQ5W(40MHz)	-
14304	2N6671	450/300V, 5A, 150W, >15MHz	BUW 24...26, BUW 34...36, BUW 72
14305	2N6672	2N6671, 550/350V	BUW 25...26, BUW 35...36, BUX 80
14306	2N6673	2N6671, 650/400V	BUW 26, BUW 35...36, BUX 80...81
14307	2N6674	450/300V, 10A, 175W, >15MHz	BUV 25, BUW 44, BUW 75, BUX 25
14308	2N6675	2N6674, 650/400V	BUS 13(A), BUW 44...46, BUX 48(A...C)
14309	2N6676	450/300V, 15A, 175W, >15MHz	BUV 25, BUW 44...46, BUX 25, BUX 48



14310	2N6677	2N6676, 550/350V	BUS 13(A), BUW 45...46, BUX 48A...C)
14311	2N6678	2N6676, 650/400V	BUS 13(A), BUW 45...46, BUX 48A...C)
14312	2N6679	30V, 70mA, >4GHz	BFQ 82, BFQ 196, 2SC3603
14313	2N6681	100V, 1A, Igt/Ih<0,2/<5mA	TAG 59A, BT 149A, MCR 606-3
14314	2N6682	2N6681, 200V	TAG 59B, BT 149B, MCR 606-4
14315	2N6683	2N6681, 400V	TAG 59D, BT 149D, MCR 606-6
14316	2N6684	2N6681, 600V	TAG 59M, BT 149M, MCR 606-8
14317	2N6685	2N6681, 800V	TAG 615-800
14318	2N6686	260/160V, 25A, 200W, >20MHz	BUV 12, BUW 73, BUX 12
14319	2N6687	2N6686, 280/180V	BUV 12, BUW 73, BUX 12
14320	2N6688	2N6686, 300/200V, 20A	BUV 12, BUW 73, BUX 12
14321	2N6689	450/300V, 15A, 175W, >15MHz	-
14322	2N669	40V, 3A, 90W	2N1529...1548, 2N3611...18
14323	2N6690	2N6689, 650/400V	-
14324	2N6691	450/300V, 15A, 175W, >15MHz	-
14325	2N6692	2N6691, 550/350V	-
14326	2N6693	2N6691, 650/400V	-
14327	2N670	40/40/40V, 2A, 0,3W	-
14328	2N6702	140/90V, 7A, 50W, >50MHz	BU 409, BUW 64A...C, TIP 150...152
14329	2N6703	2N6702, 160/110V	BU 409, BUW 64C, TIP 150...152
14330	2N6704	2N6702, 180/130V	BU 409, BUW 64C, TIP 150...152
14331	2N6705	60V, 1A, 1,2W, >50MHz	2SD1281...82, BD 517, BD 525
14332	2N6706	2N6705, 80V	2SD1281...82, BD 519, BD 527
14333	2N6707	2N6705, 100V	2SD1281...82, BD 529
14334	2N6708	60V, 1A, 1,2W, >50MHz	2SB957...958, BD 518, BD 526
14335	2N6709	2N6708, 80V	2SB957...958, BD 520, BD 528
14336	2N671	2N670, 1W	-
14337	2N6710	2N6708, 100V	2SB957...958, BD 530
14338	2N6711	160V, 0,1A, 1,2W, 50MHz	BF 380...382, BF 460...462, BF 757...759
14339	2N6712	2N6711, 250V	BF 381...382, BF 460...462, BF 757...759
14340	2N6713	2N6711, 300V	BF 382, BF 461...462, BF 758...759
14341	2N6714	40V, 2A, 1,2W, >50MHz	2SD1078...79, BD 509, BD 517
14342	2N6715	2N6714, 50V	2SD1078...79, BD 509, BD 517
14343	2N6716	60V, 2A, 1,2W, >50MHz	2SD1281...82, BD 517, BD 525
14344	2N6717	2N6716, 80V	2SD1281...82, BD 519, BD 527
14345	2N6718	2N6716, 100V	2SD1281...82, BD 529
14346	2N6719	300V, 0,1A, 1,2W, >30MHz	2SC2870, 2SC2924, 2SC3408, BF617
14347	2N672	25/25/25V, 2A, 0,3W	-
14348	2N6720	175V, 1A, 2W, >30MHz	2SC2885, 2SC2946, BF 466...468
14349	2N6721	2N6721, 225V	2SC2885, 2SC2946, BF 467...468
14350	2N6722	2N6721, 275V	2SC2885, 2SC2946, BF 468, BF 668
14351	2N6723	2N6721, 325V	2SC2885, 2SC2946, BF 468, BF 668
14352	2N6724	50V, 2A, 1W, B>15000	2SD1222, 2SD1759, BD 411...412
14353	2N6725	2N6724, 60V	2SD1222, 2SD1759
14354	2N6726	40V, 2A, 1,2W, >50MHz	2SB838...839, BD 518, BD 526

14355	2N6727	2N6726, 50V	2SB838...839, BD 518, BD 526
14356	2N6728	60V, 2A, 1,2W, >50MHz	2SB957...958, BD 518, BD 526
14357	2N6729	2N6728, 80V	2SB957...958, BD 520, BD 528
14358	2N673	2N672, 1W	-
14359	2N6730	2N6728, 100V	2SB957...958, BD 530
14360	2N6731	100V, 1A, 2W, >50MHz	2SD1281...84, BD529
14361	2N6732	100V, 1A, 2W, >50MHz	2SB957...960, BD530
14362	2N6733	160V, 0,1A, 1,2W, >50MHz	2SC2870, 2SC2924, 2SC3408, BF 617
14363	2N6734	2N6733, 250V	2SC2870, 2SC2924, 2SC3408, BF 617
14364	2N6735	2N6733, 300V	2SC2870, 2SC2924, 2SC3408, BF 617
14365	2N6737	80V, >300MHz, <-/60ns	-
14366	2N6738	450/300V, 8A, 100W, >15MHz	BUT 54, BUT 56(A), 2SC3039, 2SC4106
14367	2N6739	2N6738, 550/350V	BUT 54, BUT 56(A), 2SC3039, 2SC4106
14368	2N674	75/75/70V, 2A, 0,3W	-
14369	2N6740	2N6738, 650/400V	BUT 54, BUT 56(A), MJE 13006...07
14370	2N675	2N674, 1W	-
14371	2N6751	800/400V, 10A, 150W, >15MHz	BUS 12(A), BUW 35...36, BUX 80...81
14372	2N6752	2N6751, 850/450V	BUS 12(A), BUW 36, BUX 81, MJ 8504
14373	2N6753	2N6751, 900/500V	BUS 12A, BUW 36, BUX 81, MJ 8504
14374	2N6754	2N6751, 1000/500V	BUS 12A, BUX 81, MJ 8504, 2SC3215
14375	2N6755	<0,25Ohm(8A)	2SK398...399, 2SK500, 2SK633
14376	2N6756	<0,18Ohm(9A)	BUZ 36, BUZ 350, 2SK622
14377	2N6757	<0,6Ohm(5A)	2SK399, 2SK401, 2SK631, 2SK633
14378	2N6758	200V, 9A, 75W, <0,4Ohm(6A)	2SK412, 2SK633
14379	2N6759	350V, 4,5A, 75W, <1,5Ohm(3A)	BUZ 63, 2SK259...260
14380	2N6760	400V, 5,5A, 75W, <1Ohm(3,5A)	BUZ 63, 2SK260, 2SK298
14381	2N6761	<2Ohm(2,5A)	BUZ 84, 2SK351
14382	2N6762	500V, 4,5A, 75W, <1,5Ohm(3A)	BUZ 84, 2SK351
14383	2N6763	<0,08Ohm(20A)	BUZ 24, BUZ 349, 2SK561, 2SK906
14384	2N6764	100V, 38A, 150W, <0,055Ohm	BUZ 345, 2SK850
14385	2N6765	<0,12Ohm(16A)	BUZ 36, BUZ 350, 2SK622
14386	2N6766	200V, 30A, 150W, <0,085Ohm	-
14387	2N6767	<0,4Ohm(7,75A)	BUZ 64, BUZ 325, 2SK312, 2SK351
14388	2N6768	<0,3Ohm(9A)	BUZ 323, BUZ 338, 2SK788, 2SK899
14389	2N6769	<0,5Ohm(7A)	BUZ 45, BUZ 339, BUZ 384, 2SK512
14390	2N677	50V, 15A, 90W	AUY 29, 2N1550...2, 2N1554...6, 2N1559...0
14391	2N6770	<0,4Ohm(7A)	BUZ 45, BUZ 339, BUZ 384, 2SK512
14392	2N6771	450/300V, 1A, 40W, >10MHz	BUW 40(A,B), BUX 84...85, TIP 49...50
14393	2N6772	2N6771, 550/350V	BUW 40A,B, BUX 84...85, 2SC3352
14394	2N6773	2N6771, 650/400V	BUW 40B, BUX 84...85, 2SC3352
14395	2N6774	450/300V, 15A, 175W, >15MHz	-
14396	2N6775	2N6774, 550/350V	-
14397	2N6776	2N6774, 650/400V	-
14398	2N677A	2N677, 60V	2N1550...52, 2N1554...56, 2N1559...60
14399	2N677B	2N677, 90V	2N1552, 2N1556, 2N1560



14400	2N677C	2N677, 100V	2N1552, 2N1556, 2N1560
14401	2N678	50V, 15A, 90W	AUY 29, 2N1550...2, 2N1554...6, 2N1559...0
14402	2N6782	100V, 3,5A, 15W, <0,6Ohm(2A)	2SK429...430
14403	2N6784	15W,<1,5Ohm(1,5A)	BST 95
14404	2N6786	15W,<3,6Ohm(0,8A)	2SK535, 2SK579...580
14405	2N6788	100V, 6A, 20W,<0,3Ohm(3,5A)	-
14406	2N678A	2N678, 60V	2N1550...52, 2N1554...56, 2N1559...60
14407	2N678B	2N678, 90V	2N1552, 2N1556, 2N1560
14408	2N678C	2N678, 100V	2N1552, 2N1556, 2N1560
14409	2N679	25V, 0,15W, 3MHz	AC 127, ASY 28...29
14410	2N6790	<0,8Ohm(2,2A)	-
14411	2N6792	<1,8Ohm(1,25A)	-
14412	2N6794	500V, 1,5A, 20W, <3Ohm(3A)	-
14413	2N6796	100V, 8A, 25W, <0,18Ohm(5A)	-
14414	2N6798	<0,4Ohm(3,5A)	-
14415	2N68(/13)	30V, 1,5A	-
14416	2N680	20V, 0,15A, 0,15W, 3MHz	AC 125...126, AC 151, 2SB54, 2SB56
14417	2N6800	<1Ohm(2A),<65/90ns	-
14418	2N6802	<1,5Ohm(1,5A)	-
14419	2N6804	<0,3Ohm(6,5A)	2SJ112...113
14420	2N6806	200V, 6,5A, 75W, <0,8Ohm(4A)	2SJ56, 2SJ114
14421	2N681(A)	Igt/ih<40/<50mA	T 12N100, MCR 70-1, C 228U, 2N3896
14422	2N681(A)S	2N681, <12μs	T 12F100, C 234U, MCR 1718-5
14423	2N682(A)	2N681, 50V	T 12N100, MCR 70-2, C 228F, 2N3896
14424	2N682(A)S	2N682, <12μs	T 12F100, C 234F, MCR 1718-5
14425	2N6823	600V, 3A, 100W, <2,8Ohm(3A)	BUZ 307, BUZ 360...361, 2SK415, 2SK954
14426	2N6826	600V, 6A, 150W, <1,6Ohm(6A)	BUZ 94, BUZ 332A, 2SK684, 2SK1032
14427	2N683(A)	2N681, 100V	T 12N100, MCR 70-3, C 228A, 2N3896
14428	2N683(A)S	2N683, <12μs	T 12F100, C 234A, MCR 1718-5
14429	2N6833	850/450V, 5A, 80W, >15MHz	BUT11(A), BUT46(A), BUV46(A), 2SC3047
14430	2N6834	2N6833, 125W	BU426(A), BU526(A), BUS11(A), BUW11(A)
14431	2N6835	850/450V, 8A, 150W, >10MHz	BU426(A), BU526(A), BUS12(A), BUW12(A)
14432	2N6836	850/450V, 15A, 175W, >10MHz	BUS 13(A), BUW 46, BUX 48(A...C)
14433	2N6837	850/450V, 20A, 250W, >10MHz	BUS 14(A), BUS 98(A), BUX 348(A)
14434	2N684(A)	2N681, 150V	T 12N200, C 228B, 2N3897,MCR 3935-4
14435	2N684(A)S	2N684, <12μs	T 12F200, C 234B, MCR 1718-5
14436	2N6845	<0,6Ohm(2,25A)	-
14437	2N6847	<1,5Ohm(2,25A)	-
14438	2N6849	<0,3Ohm(4,1A)	-
14439	2N685(A)	2N681, 200V	T 12N200, C 228B, 2N3897,MCR 3935-4
14440	2N685(A)S	2N685, <12μs	T 12F200, C 234B, MCR 1718-5
14441	2N6851	200V, 4A, 25W, <0,8Ohm(2,4A)	-
14442	2N686(A)	2N681, 250V	T 12N300, C 228C, 2N3898,MCR 3935-5
14443	2N686(A)S	2N686, <12μs	T 12F300, C 234C, MCR 1718-5
14444	2N687(A)	2N681, 300V	T 12N300, C 228C, 2N3898,MCR 3935-5

14445	2N687(A)S	2N687, <12μs	T 12F300, C 234C, MCR 1718-5
14446	2N688(A)	2N681, 400V	T 12N400, C 228D, 2N3898,MCR 3935-6
14447	2N688(A)S	2N688, <12μs	T 12F400, C 234D, MCR 1718-6
14448	2N689(A)	2N681, 500V	T 12N500, C 228E, 2N3899,MCR 3935-7
14449	2N689(A)S	2N689, <12μs	T 12F500, C 234E, MCR 1718-7
14450	2N6895	100V, 1,16A, 8,33W, <3,65Ohm	-
14451	2N6896	100V, 6A, 60W, <0,6Ohm(3,8A)	2SJ55...56, 2SJ115, 2SJ118...119
14452	2N6897	<0,3Ohm(7,6A)	2SJ112...113, 2SJ127, 2SJ131
14453	2N6898	<0,2Ohm(15,8A)	-
14454	2N690(A)	2N681, 600V	T 12N600, C 228M, 2N3899,MCR 3935-8
14455	2N690(A)S	2N690, <12μs	T 12F600, C 234M, MCR 1718-8
14456	2N6901	100V, 1,69A, <1,4Ohm(1A)	-
14457	2N6902	100V, 12A, 75W, <0,2Ohm	2N6765
14458	2N6903	200V, 0,98A, 8,33W,<3,65Ohm	-
14459	2N6904	200V, 8A, 75W, <0,6Ohm	-
14460	2N6908	30V, Up<-1,8V	-
14461	2N6909	30V, Up<-2,3V	-
14462	2N691(A)	2N681, 700V	T 12N700, MCR 3935-9, BStE4146N
14463	2N691(A)S	2N691, <12μs	T 12F700, TAG 35S-700
14464	2N6910	30V, Up<-3,5V	-
14465	2N692(A)	2N681, 800V	T 12N800, MCR 3935-10, BStE4153N
14466	2N692(A)S	2N692, <12μs	T 12F800, TAG 35S-800
14467	2N6928	<500/2900ns	MJE 13006...07, BUT 12(A), BUT 56(A)
14468	2N6929	2N6928, 550/350V	MJE 13006...07, BUT 12(A), BUT 56(A)
14469	2N6930	2N6928, 650/400V	MJE 13006...07, BUT 12(A), BUT 56(A)
14470	2N6931	450/300V, 10A, 150W, <0,8/3μs	BUV47(A), BUW12(A), BUW13(A), 2SC4157
14471	2N6932	2N3932, 650/400V	BUV47(A), BUW12(A), BUW13(A), 2SC4157
14472	2N6933	450/300V, 15A, 175W, <0,8/3μs	BUP 23(A...C), BUV48(A), BUW13(A)
14473	2N6934	2N6933, 550/350V	BUP 23(A...C), BUV48(A), BUW13(A)
14474	2N6935	2N6933, 650/400V	BUP 23(A...C), BUV48(A), BUW13(A)
14475	2N694	30V, 0,05A, 0,1W, 500MHz	AF 139, AF 239(S)
14476	2N695	15V, 0,05A, 0,075W, 250MHz	AF 106, AF 109R, AF 306
14477	2N696(A,S)	60V, 1A, 0,6..0,8W, >40MHz	BC 140...141, BC 300...302, 2N3053
14478	2N697(A,S)	60V, 1A, 0,6..0,8W, >50MHz	BC 140...141, BC 300...302, 2N3053
14479	2N6975	400V, 5A, 100W, <100/1400ns	-
14480	2N6976	2N6975, 500V	-
14481	2N6977	2N6975, <100/900ns	-
14482	2N6978	2N6975, 500V, <100/900ns	-
14483	2N698	120V, 1A, 0,8W, 70MHz	BSS 42...43, BSW 67...68, BSX 47, 2N2405
14484	2N699(A,B)	120V, 1A, 0,6..0,78W, 100MHz	BSS 42...43, BSW 67...68, BSX 47, 2N2405
14485	2N700(A,/18)	25V, 0,05A, 0,075W, 800MHz	AF 106, AF 109R, AF 139, AF 239(S)
14486	2N7000	<10/10ns	
14487	2N7001	240V, 50mA, <45Ohm, <30/-ns	-
14488	2N7002	60V, +-0,115A, <7,5Ohm(0,5A)	
14489	2N7007	<30/-ns	-

14490	2N7008	<20/-ns	-
14491	2N701	30V, 0,075W, 200MHz	AF 106, AF 109R, AF 306
14492	2N7010	60V, 1,3A, on0,35Ohm	-
14493	2N702	B>20	BC 168, BC 183, BC 238, BC 548
14494	2N703	2N702, B>40	BC 168, BC 183, BC 238, BC 548
14495	2N705(A)	55/135ns	ASZ 21, 2N964A, 2N2635, 2N2955...57
14496	2N7051	100V, B>20k, >100MHz	-
14497	2N7052	>200MHz	2SD1660, 2SD1978, 2SD1981, 2SD2067
14498	2N7053	>200MHz	2SD1660, 2SD1978, 2SD1981, 2SD2067
14499	2N7056	on<0,1Ohm(16A)	-
14500	2N7059	on<0,45Ohm(7A)	-
14501	2N706(A..C)	25..40V, 0,2A, 0,3W, 30/50ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
14502	2N707	56V, 0,1A, 0,3W, 350MHz	BFX 94...95
14503	2N7071	<0,1Ohm(15A)	BUK 426-100, 2SK622, 2SK629
14504	2N7071	<0,1Ohm(15A)	BUK 426-100, 2SK622, 2SK629
14505	2N7072	<0,2Ohm(10A)	BUZ 350
14506	2N7072	<0,2Ohm(10A)	BUZ 350
14507	2N7073	<0,55Ohm(5,5A)	2SK1225, 2SK1328, BUZ 330...331, BUZ 501
14508	2N7073	<0,55Ohm(5,5A)	2SK1225, 2SK1328, BUZ 330...331, BUZ 501
14509	2N7074	<0,85Ohm(4,5A)	2SK1206, BUZ 330...331, BUZ 332A
14510	2N7074	<0,85Ohm(4,5A)	2SK1206, BUZ 330...331, BUZ 332A
14511	2N7075	<65mOhm(24A)	BUZ 349, 2SK906
14512	2N7075	<65mOhm(24A)	BUZ 349, 2SK906
14513	2N7076	<0,1Ohm(18A)	BUZ 341, 2SK851
14514	2N7076	<0,1Ohm(18A)	BUZ 341, 2SK851
14515	2N7077	<0,3Ohm(9,5A)	2SK1268...1269, BUZ 323, 2SK788, 2SK899
14516	2N7077	<0,3Ohm(9,5A)	2SK1268...1269, BUZ 323, 2SK788, 2SK899
14517	2N7078	<0,4Ohm(8A)	2SK1269, 2SK725, 2SK788, 2SK899
14518	2N7078	<0,4Ohm(8A)	2SK1269, 2SK725, 2SK788, 2SK899
14519	2N7079	<0,21Ohm(8A)	2SJ222
14520	2N7079	<0,21Ohm(8A)	2SJ222
14521	2N707A	2N707, 70V	-
14522	2N708	40V, 0,2A, 0,36W, <40/70ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
14523	2N7080	<0,5Ohm(6,1A)	2SJ114
14524	2N7080	<0,5Ohm(6,1A)	2SJ114
14525	2N7081	<0,15Ohm(7,7A)	BUK 545-100, 2SK1230, 2SK1305
14526	2N7082	200V, 9A, 50W, <0,3Ohm(5,5A)	BUK 545-200, BUZ 30, BUZ 73
14527	2N7085	<75mOhm(12A)	2SK1307, 2SK1318, BUZ 21...22
14528	2N7086	<0,16Ohm(8,5A)	BUZ 30A
14529	2N7089	<0,3Ohm(6,7A)	BUK 545-100, 2SK1230, 2SK1305, BUZ 72
14530	2N708A	2N708, 50V	BSS 10...11, BSX 19...20, 2N2368...69(A)
14531	2N709(A)	15V, 0,3..0,36W, <15/15ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
14532	2N7090	<0,8Ohm(3,6A)	BUK 444-200, BUZ 73(A)F, 2SK924
14533	2N7091	<0,2Ohm(8,7A)	BUK 445-100, 2SK1306, 2SK919, 2SK922
14534	2N7092	200V, 8A, 70W, <0,5Ohm(5,1A)	BUK 545-200, BUZ 30, BUZ 73

14535	2N710(A)	15V, 0,05A, 0,15W, <75/125ns	ASZ 21, 2N705(A), 2N2635, 2N2955...57
14536	2N7104	30V, on<70Ohm, <2/-ns	-
14537	2N7105	30V, on<70Ohm, <2/-ns	-
14538	2N7106	10V, on<70Ohm, <2/-ns	-
14539	2N7107	10V, on<70Ohm, <2/-ns	-
14540	2N7108	20V, on<70Ohm, <2/-ns	-
14541	2N7109	20V, on<70Ohm, <2/-ns	-
14542	2N711(A,B)	<100/150ns	ASZ 21, 2N705(A), 2N2635, 2N2955...57
14543	2N715	50V, 0,1A, 0,5W, >70MHz	BFX 94...95
14544	2N716	2N715, 70V	-
14545	2N717	B>20	BC 337A, BC 637, BC 639, BCX 24
14546	2N717A	2N717, 75V	BC 639, BCX 24, 2SD667, 2SD1226
14547	2N718	2N717, B>40	BC 337A, BC 637, BC 639, BCX 24
14548	2N718A	2N717, 75V, B>40	BC 639, BCX 24, 2SD667, 2SD1226
14549	2N719(A)	B>20	BCX 22, 2N3700...01, 2SD667, 2SD774
14550	2N720(A)	2N719, >50MHz, B>40	BCX 22, 2N3700...01, 2SD667, 2SD774
14551	2N721(A)	B>20	BC 337, BC 637, BC 639, BCX 24
14552	2N722(A)	2N721, >60MHz, B>30	BC 337, BC 637, BC 639, BCX 24
14553	2N7224	<0,081Ohm(24A)	2SK1149, 2SK1435...1436
14554	2N7224	<0,081Ohm(24A)	2SK1149, 2SK1435...1436
14555	2N7225	<0,105Ohm(27A)	2SK1670
14556	2N7225	<0,105Ohm(27A)	2SK1670
14557	2N7227	<0,415Ohm(14A)	2SK1268...1269, 2SK1453
14558	2N7227	<0,415Ohm(14A)	2SK1268...1269, 2SK1453
14559	2N7228	<0,515Ohm(12A)	2SK1269, 2SK1331, 2SK1524
14560	2N7228	<0,515Ohm(12A)	2SK1269, 2SK1331, 2SK1524
14561	2N725	15V, 0,05A, 0,15W, <70/100ns	ASZ 21, 2N705(A), 2N2635, 2N2955...57
14562	2N726	B>15	BC 213, BC 258, BC 308, BC 558
14563	2N727	2N726, B>30	BC 213, BC 258, BC 308, BC 558
14564	2N728	15V, 0,1A, 0,3W, 18/-ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
14565	2N729	2N728, 30V	BSS 11...12, BSX 19...20, 2N2368...69(A)
14566	2N730	60V, 1A, 0,5W, >25MHz, B>20	BC 337A, BC 637, BC 639, BCX 24
14567	2N731	2N730, B>40	BC 337A, BC 637, BC 639, BCX 24
14568	2N734(A)	B>20	BC 546, 2SC1890(A), 2SC2240, 2SC2459
14569	2N735(A)	2N734, 180MHz, B>40	BC 546, 2SC1890(A), 2SC2240, 2SC2459
14570	2N736(A,B)	2N734, 180MHz, B>80	BC 546, 2SC1890(A), 2SC2240, 2SC2459
14571	2N738(A)	B>20	2SC1890A, 2SC2240, 2SC2459, 2SC3245
14572	2N739(A)	2N738, 180MHz, B>30	2SC1890A, 2SC2240, 2SC2459, 2SC3245
14573	2N740(A)	2N738, 180MHz, B>80	2SC1890A, 2SC2240, 2SC2459, 2SC3245
14574	2N741(A)	15..20V, 0,1A, 360MHz	AF 139, AF 239(S), AFY 18
14575	2N742(A)	60V, 0,1A, 0,5W, >60MHz	BC 174, BC 182, BC 190, BC 546
14576	2N743	20V, 0,2A, 0,3W, <16/24ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
14577	2N743A	2N743, 40V, <12/30ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
14578	2N744	20V, 0,2A, 0,3W, <16/24ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
14579	2N744A	2N744, 40V, <12/30ns	BSS 11...12, BSY 19...20, 2N2368...69(A)

14580	2N745	45V, 0,02A, 0,15W, 30MHz	BC 167, BC 182, BC 237, BC 547
14581	2N746	45V, 0,02A, 0,15W, 45MHz	BC 167, BC 182, BC 237, BC 547
14582	2N747	25V, 0,05A, 0,2W, 60MHz	BC 168, BC 183, BC 238, BC 548
14583	2N748	30V, 0,05A, 0,2W, 50MHz	BC 168, BC 183, BC 238, BC 548
14584	2N749	45V, 0,05A, 0,2W, 75MHz	BC 167, BC 182, BC 237, BC 547
14585	2N750	50V, 0,05A, 0,2W, 40MHz	BC 167, BC 182, BC 237, BC 547
14586	2N751	20V, 0,05A, 0,2W, 30MHz	BC 168, BC 182, BC 238, BC 548
14587	2N752	85V, 0,1A, 0,5W, >200MHz	BC 546, 2SC2240, 2SC2459, 2SC3245
14588	2N753	25V, 0,05A, 0,3W, 30/60ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
14589	2N754	60V, 0,05A, 0,3A, >30MHz	BC 174, BC 182, BC 190, BC 546
14590	2N755	2N754, 100V	2SC1890(A), 2SC2240, 2SC2459, 2SC3245
14591	2N756	$\beta > 12$	BC 167, BC 182, BC 237, BC 547
14592	2N756A	2N756, 60V	BC 174, BC 182, BC 190, BC 546
14593	2N757	$\beta > 18$	BC 167, BC 182, BC 237, BC 547
14594	2N757A	2N757, 60V	BC 174, BC 182, BC 190, BC 546
14595	2N758	$\beta > 18$	BC 167, BC 182, BC 237, BC 547
14596	2N758A,B	2N758, 60V	BC 174, BC 182, BC 190, BC 546
14597	2N759	$\beta > 36$	BC 167, BC 182, BC 237, BC 547
14598	2N759A,B	2N759, 60V	BC 174, BC 182, BC 190, BC 546
14599	2N76	20V, 0,01A, 0,05W	AC 125...126, AC 151, ASY 26...27
14600	2N760	$\beta > 76$	BC 167, BC 182, BC 237, BC 547
14601	2N760A,B	2N760, 60V	BC 174, BC 182, BC 190, BC 546
14602	2N761	$\beta > 19$	BC 167, BC 182, BC 237, BC 547
14603	2N762	2N761, $\beta > 39$	BC 167, BC 182, BC 237, BC 547
14604	2N764	30V, 0,2A, $I_{gt}/I_h < 1 / < 5mA$	-
14605	2N765	2N764, 60V	-
14606	2N766	2N764, 100V	-
14607	2N767	2N764, 200V	-
14608	2N768	12V, 0,1A, 0,035W, >125MHz	ASZ 21, 2N960...967, 2N2635, 2N2955...57
14609	2N769	12V, 0,1A, 0,035W, >100MHz	ASZ 21, 2N960...967, 2N2635, 2N2955...57
14610	2N77	25V, 0,015A, 0,035W	AC 125...126, AC 151, ASY 26...27
14611	2N770	20V, 0,1A, 0,15W, 125MHz	BC 238, BC 548, BSW 41, 2N706A
14612	2N771	20V, 0,1A, 0,15W, 200MHz	BC 238, BC 548, BSW 41, 2N706A
14613	2N772	25V, 0,1A, 0,15W, 110MHz	BC 238, BC 548, BSW 41, 2N706A
14614	2N773	20V, 0,1A, 0,15W, 70MHz	BC 238, BC 548, BSW 41, 2N706A
14615	2N774	20V, 0,1A, 0,15W, 90MHz	BC 238, BC 548, BSW 41, 2N706A
14616	2N775	20V, 0,1A, 0,15W, 160MHz	BC 238, BC 548, BSW 41, 2N706A
14617	2N776	20V, 0,1A, 0,15W, 120MHz	BC 238, BC 548, BSW 41, 2N706A
14618	2N777	20V, 0,1A, 0,15W, 160MHz	BC 238, BC 548, BSW 41, 2N706A
14619	2N778	20V, 0,1A, 0,15W, 180MHz	BC 238, BC 548, BSW 41, 2N706A
14620	2N779(A,B)	>320MHz	ASZ 21, 2N964A, 2N2635, 2N2955...57
14621	2N78	15V, 0,02A, 0,065W	ASY 28...29
14622	2N780	45V, 0,05A, 0,3W, >60MHz	BC 167, BC 182, BC 237, BC 547
14623	2N781	15V, 0,2A, 0,15W, <60/70ns	2N705, 2N960...967
14624	2N782	12V, 0,2A, 0,15W, <75/75ns	2N705, 2N960...967



14625	2N783	40V, 0,2A, 0,3W, <18/30ns	BSS 10...11, BSX 19...20
14626	2N784	30V, 0,2A, 0,3W, <20/40ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
14627	2N784A	2N784, 40V	BSS 10...11, BSX 19...20, 2N2368...69(A)
14628	2N789	45V, 0,025A, 0,15W, >1MHz	BC 167, BC 182, BC 237, BC 547
14629	2N78A	2N78, 20V	ASY 28...29
14630	2N79	30V, 0,05A, 0,035W	AC 125...126, AC 151, ASY 26
14631	2N790	45V, 0,025A, 0,15W, >2MHz	BC 167, BC 182, BC 237, BC 547
14632	2N791	45V, 0,025A, 0,15W, >8MHz	BC 167, BC 182, BC 237, BC 547
14633	2N792	45V, 0,025A, 0,15W, >2MHz	BC 167, BC 182, BC 237, BC 547
14634	2N793	45V, 0,025A, 0,15W, >2MHz	BC 167, BC 182, BC 237, BC 547
14635	2N794	13V, 0,1A, 0,12W, 300/-ns	ASZ 21, 2N705, 2N960...967
14636	2N795	13V, 0,1A, 0,12W, 150/-ns	ASZ 21, 2N705, 2N960...967
14637	2N796	12V, 0,1A, 0,12W, 130/-ns	ASZ 21, 2N705, 2N960...967
14638	2N797	20V, 0,15A, 0,15W, 1000MHz	-
14639	2N799	25V, 0,1A, 0,075W, >4MHz	ASY 26...27, ASY 76...77
14640	2N80	25V, 8mA, 0,05W	AC 125...126, AC 151, ASY 26...27
14641	2N801	30V, 0,4A, 0,075W, >3MHz	ASY 76...77
14642	2N803	30V, 0,4A, 0,075W, >5MHz	ASY 76...77
14643	2N805	30V, 0,4A, 0,075W, >10MHz	ASY 76...77
14644	2N807	25V, 0,1A, 0,075W, 18MHz	ASY 26...27, ASY 76...77
14645	2N809	30V, 0,2A, 0,075W, >3MHz	ASY 26...27, ASY 76...77
14646	2N81	20V, 15mA, 0,05W	AC 125...126, AC 151, ASY 26...27
14647	2N811	30V, 0,2A, 0,075W, >5MHz	ASY 26...27, ASY 76...77
14648	2N813	30V, 0,2A, 0,075W, >15MHz	ASY 26...27, ASY 76...77
14649	2N815	25V, 0,2A, 0,075W, 8MHz	ASY 28...29, ASY 73...75
14650	2N817	30V, 0,4A, 0,075W, >2,5MHz	ASY 73...75
14651	2N819	30V, 0,4A, 0,075W, >5MHz	ASY 73...75
14652	2N82	20V, 15mA, 0,035W	AC 125...126, AC 151, ASY 26...27
14653	2N821	30V, 0,4A, 0,075W, >10MHz	ASY 73...75
14654	2N823	25V, 0,1A, 0,075W, >4MHz	ASY 28...29, ASY 73...75
14655	2N825	30V, 0,4A, 0,07W, 8MHz	ASY 76...77
14656	2N827	20V, 0,1A, 0,15W, 25/30ns	2N960...967
14657	2N828(A)	15V, 0,1A, 0,15W, <70/100ns	2N960...967
14658	2N829	15V, 0,1A, 0,15W, 35/60ns	2N960...967
14659	2N83(A)	66V, 2..3A, 10W	-
14660	2N834	40V, 0,2A, 0,3W, <33/75ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
14661	2N834A	2N834, <16/24ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
14662	2N835	25V, 0,2A, 0,3W, <20/35ns	BSS 10...11, BSX 19...20, 2N2368...69(A)
14663	2N837	12V, 0,1A, 0,15W, <30/90ns	ASZ 21, 2N705, 2N960...967
14664	2N838	30V, 0,1A, 0,15W, 17/20ns	2N960...967
14665	2N839	B>15	BC 167, BC 182, BC 237, BC 547
14666	2N84(A)	50V, 2..3A, 10W	-
14667	2N840	2N839, B>30	BC 167, BC 182, BC 237, BC 547
14668	2N841	2N839, >40MHz, B>60	BC 167, BC 182, BC 237, BC 547
14669	2N842	B>20	BC 167, BC 182, BC 237, BC 547

14670	2N843	2N842, >40MHz, B>45	BC 167, BC 182, BC 237, BC 547
14671	2N844	60V, 0,05A, 0,3W, >50MHz	BC 174, BC 182, BC 190, BC 546
14672	2N845	2N844, 100V	2SC1890A, 2SC2240, 2SC2459, 2SD755
14673	2N846	15V, 0,05A, 0,06W, >320MHz	ASZ 21, 2N705, 2N960...967
14674	2N846A,B	2N846, 0,1A, 0,15W	ASZ 21, 2N705, 2N960...967
14675	2N847	40V, 0,05A, 0,2W, <32/58ns	BSS 10...11, BSV 91...92, 2N2368...69(A)
14676	2N848	2N847, 20V	BSS 10...11, BSV 91...92, 2N2368...69(A)
14677	2N849	25V, 0,05A, 0,3W, <40/25ns	BSS 11...12, BSV 91...92, 2N2368...69(A)
14678	2N85	20V, 0,1A, 0,2W	AC 125...126, AC 151, 2SB56
14679	2N850	25V, 0,05A, 0,3W, <40/35ns	BSS 11...12, BSV 91...92, 2N2368...69(A)
14680	2N851	20V, 0,2A, 0,3W, <16/24ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
14681	2N852	20V, 0,2A, 0,3W, <16/24ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
14682	2N858	40V, 0,05A, 0,15W, >5MHz	BC 212, BC 257, BC 307, BC 557
14683	2N859	40V, 0,05A, 0,15W, >6MHz	BC 212, BC 257, BC 307, BC 557
14684	2N86	45V, 0,1A, 0,2W	2SB56A
14685	2N860	25V, 0,05A, 0,15W, >6,5MHz	BC 213, BC 258, BC 308, BC 558
14686	2N861	25V, 0,05A, 0,15W, >7,5MHz	BC 213, BC 258, BC 308, BC 558
14687	2N862	15V, 0,05A, 0,15W, >8MHz	BC 213, BC 258, BC 308, BC 558
14688	2N863	15V, 0,05A, 0,15W, >10MHz	BC 213, BC 258, BC 308, BC 558
14689	2N864	6V, 0,05A, 0,15W, >16MHz	BC 213, BC 258, BC 308, BC 558
14690	2N864A	2N864, 0,1A	BC 213, BC 258, BC 308, BC 558
14691	2N865A	2N865, 0,1A	BC 213, BC 258, BC 308, BC 558
14692	2N866	30V, 0,6A, 0,5W, >40MHz	BC 337...338, BC 635, BC 637, BC 639
14693	2N867	30V, 0,6A, 0,5W, >50MHz	BC 337...338, BC 635, BC 637, BC 639
14694	2N869	25V, 0,2A, 0,36W, 300MHz	BSW 24, 2N3905...06, 2N4125...26
14695	2N869A	2N869, >400MHz	BSW 24, 2N3905...06, 2N4125...26
14696	2N87	25V, 0,1A, 0,2W	AC 125...126, AC 151, 2SB56
14697	2N870	100V, 0,5W, >50MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14698	2N871	2N870, >60MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14699	2N876	Igt/Ih<0,2/<5mA	TAG06Y, 2N2322, 2N6332, TAG615-100
14700	2N877	2N876, 30V	TAG06Y, 2N2323, 2N6332, TAG615-100
14701	2N878	2N876, 60V	TAG06YY, 2N2324, 2N6334, TAG615-100
14702	2N879	2N876, 100V	TAG06A, 2N2324, 2N6334, TAG 615-100
14703	2N88	0,025W	-
14704	2N880	2N876, 150V	TAG06B, 2N2325, 2N6335, TAG615-200
14705	2N881	2N876, 200V	TAG06B, 2N2326, 2N6335, TAG615-200
14706	2N882	2N876, 300V	TAG06C, 2N2328, 2N6336, TAG615-300
14707	2N883	2N876, 400V	TAG06D, 2N2329, 2N6337, TAG615-400
14708	2N884	Igt/Ih<0,02/<3mA	2N2322A
14709	2N885	2N884, 30V	2N2323A
14710	2N886	2N884, 60V	2N2324A
14711	2N887	2N884, 100V	2N2324A
14712	2N888	2N884, 150V	2N2325A
14713	2N889	2N884, 200V	2N2326A
14714	2N89	0,025W	-



14715	2N890	2N884, 300V	2N2328A
14716	2N891	2N884, 400V	2N2329A
14717	2N892	Igt/Ih<0,05/<1mA	-
14718	2N893	2N892	-
14719	2N894	2N892, 30V	-
14720	2N895	2N892, 30V	-
14721	2N896	2N892, 60V	-
14722	2N897	2N892, 60V	-
14723	2N898	2N892, 100V	-
14724	2N899	2N892, 100V	-
14725	2N90	0,025W	-
14726	2N900	2N892, 200V	-
14727	2N909	60V, 1A, 0,5W, >50MHz	BC 337A, BC 637, BC 639, BCX 24
14728	2N91	15V, 0,5A, 0,125W	AC 128, AC 152...153, AC 188, 2SB405
14729	2N910	100V, 1A, 0,5W, >60MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14730	2N911	100V, 1A, 0,5W, >50MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14731	2N912	100V, 1A, 0,5W, >40MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14732	2N913	25V, 0,36W, 350MHz	BF 224...225, BF 314, BF 502...503
14733	2N914(A)	40V, 0,5A, 0,36W, <40/40ns	BSS 10, BSX 26, BSX 39, 2N3261
14734	2N915	70V, 0,36W, >250MHz	BSW 63...64, 2N2221...22(A)
14735	2N915A	2N915, >500MHz	BSW 63...64, 2N2221...22(A)
14736	2N916(A)	45V, 0,05A, 0,36W, >300MHz	BF 224...225, BSW 63...64, 2N2221...22(A)
14737	2N916B	2N916, 60V, >500MHz	BF224...225, BSW63...64, 2N2221...22(A)
14738	2N917(A)	30V, 0,05A, 0,2W, 900MHz	BF 377...378, BF 689, BF 763, 2N2857
14739	2N918	30V, 0,05A, 0,2W, >600MHz	BF 377...378, BF 689, BF 763, 2N2857
14740	2N919	B>20	BC 168, BC 183, BC 238, BC 548
14741	2N92	25V, 0,2A, 0,125W	AC 125...126, AC 151, ASY 26...27
14742	2N920	2N919, B>40	BC 168, BC 183, BC 238, BC 548
14743	2N921	B>20	BC 167, BC 182, BC 237, BC 547
14744	2N922	2N921, B>40	BC 167, BC 182, BC 237, BC 547
14745	2N923	40V, 0,05A, 0,15W, β>12	BC 212, BC 257, BC 307, BC 557
14746	2N924	40V, 0,05A, 0,15W, β>24	BC 212, BC 257, BC 307, BC 557
14747	2N925	50V, 0,05A, 0,15W, β>10	BC 212, BC 257, BC 307, BC 557
14748	2N926	50V, 0,05A, 0,15W, β>20	BC 212, BC 257, BC 307, BC 557
14749	2N927	70V, 0,05A, 0,15W, β>8	BC 212, BC 256, BC 266, BC 556
14750	2N928	70V, 0,05A, 0,15W, β>18	BC 212, BC 256, BC 266, BC 556
14751	2N929	45V, 0,03A, 0,5W, >30MHz	BC 414, BC 550, 2N2483...84, 2N3117
14752	2N929A	2N929, 60V	BC 414, BC 550, 2N2483...84, 2N3117
14753	2N930	45V, 0,03A, 0,5W, >30MHz	BC 414, BC 550, 2N2483...84, 2N3117
14754	2N930A,B	2N929, 60V	BC 414, BC 550, 2N2483...84, 2N3117
14755	2N934	13V, 0,2A, 0,15W, >35MHz	2N705, 2N960...967
14756	2N935	50V, 0,05A, 0,25W, β>9	BC 212, BC 257, BC 307, BC 557
14757	2N935	50V, 0,05A, 0,25W, β>9	BC 212, BC 257, BC 307, BC 557
14758	2N936	50V, 0,05A, 0,25W, β>18	BC 212, BC 257, BC 307, BC 557
14759	2N936	50V, 0,05A, 0,25W, β>18	BC 212, BC 257, BC 307, BC 557

14760	2N937	50V, 0,05A, 0,25W, $\beta > 36$	BC 212, BC 257, BC 307, BC 557
14761	2N937	50V, 0,05A, 0,25W, $\beta > 36$	BC 212, BC 257, BC 307, BC 557
14762	2N938	40V, 0,1A, 0,25W, $\beta > 9$	BC 212, BC 257, BC 307, BC 557
14763	2N938	40V, 0,1A, 0,25W, $\beta > 9$	BC 212, BC 257, BC 307, BC 557
14764	2N939	40V, 0,1A, 0,25W, $\beta > 18$	BC 212, BC 257, BC 307, BC 557
14765	2N939	40V, 0,1A, 0,25W, $\beta > 18$	BC 212, BC 257, BC 307, BC 557
14766	2N94(A)	20V, 0,1A, 0,15W	ASY 28...29, ASY 73...75
14767	2N940	40V, 0,1A, 0,25W, $\beta > 36$	BC 212, BC 257, BC 307, BC 557
14768	2N941	25/8/25V, 0,05A, 0,25W	-
14769	2N942	25/8/25V, 0,05A, 0,25W	-
14770	2N942	25/8/25V, 0,05A, 0,25W	-
14771	2N943	40/18/40V, 0,05A, 0,25W	-
14772	2N944	40/18/40V, 0,05A, 0,25W	-
14773	2N945	50/50/50V, 0,05A, 0,25W	-
14774	2N946	50/50/50V, 0,05A, 0,25W	-
14775	2N947	20V, 0,1A, 0,26W, $> 200\text{MHz}$	BC 238, BC 548, BSY 62...63, 2N706A
14776	2N948	$I_{gt}/I_h < 0,02 / < 1\text{mA}$	2N2322A
14777	2N949	2N948, 60V	2N2324A
14778	2N95(/13)	30V, 1,5A, 2,5W	-
14779	2N950	2N948, 100V	2N2324A
14780	2N951	2N948, 200V	2N2326A
14781	2N955	12V, 0,1A, 0,15W, 1GHz	-
14782	2N955A	2N955, 0,5A	-
14783	2N956	75V, 0,5W, 300MHz	BC 639, BCX 24, 2N3700...01, 2SD667
14784	2N957	40V, 0,25W, $> 200\text{MHz}$	BC 167, BC 182, BC 237, BC 547
14785	2N958	$B > 20$	BC 168, BC 183, BC 238, BC 548
14786	2N959	2N958, $B > 40$	BC 168, BC 183, BC 238, BC 548
14787	2N96	30V, 0,02A, 0,05W	AC 125...126, AC 151, ASY 26
14788	2N960	15V, 0,1A, 0,15W, $< 50/85\text{ns}$	ASZ 21, 2N705
14789	2N961	12V, 0,1A, 0,15W, $< 50/85\text{ns}$	ASZ 21, 2N705(A)
14790	2N962	12V, 0,1A, 0,15W, $< 50/100\text{ns}$	ASZ 21, 2N705(A)
14791	2N963	12V, 0,1A, 0,15W, $< 50/120\text{ns}$	ASZ 21, 2N705(A)
14792	2N964(A)	15V, 0,1A, 0,15W, $< 50/85\text{ns}$	ASZ 21, 2N705(A)
14793	2N965	12V, 0,1A, 0,15W, $< 50/85\text{ns}$	ASZ 21, 2N705(A)
14794	2N966	12V, 0,1A, 0,15W, $< 50/85\text{ns}$	ASZ 21, 2N705(A)
14795	2N967	12V, 0,1A, 0,15W, $< 60/120\text{ns}$	ASZ 21, 2N705(A)
14796	2N968	15V, 0,2A, 0,15W, 50/70ns	2N705, 2N960...967
14797	2N969	12V, 0,2A, 0,15W, 50/70ns	2N705, 2N960...967
14798	2N97(A)	30..40V, 0,01A, 0,05W	AC 127, 2SD39
14799	2N970	12V, 0,2A, 0,15W, 65/100ns	2N705, 2N960...967
14800	2N971	7V, 0,2A, 0,15W, 65/100ns	2N705, 2N960...967
14801	2N972	15V, 0,2A, 0,15W, 50/75ns	2N705, 2N960...967
14802	2N973	12V, 0,2A, 0,15W, 50/75ns	2N705, 2N960...967
14803	2N974	12V, 0,2A, 0,15W, 65/100ns	2N705, 2N960...967
14804	2N975	7V, 0,2A, 0,15W, 65/100ns	2N705, 2N960...967

14805	2N976	15V, 0,1A, 0,1W, >250MHz	2N705, 2N960...967
14806	2N977	15V, 0,2A, 0,15W, >400MHz	2N705, 2N960...967
14807	2N978	30V, 0,6A, 0,33W, >40MHz	BC 327...328, BC 636, BC 638, BC 640
14808	2N979	20/15V, 0,1A, 0,06W, >100MHz	ASZ 21, 2N705, 2N960...967
14809	2N98(A)	40V, 0,01A, 0,05W	AC 127, 2SD39
14810	2N980	2N979, 20/12V	ASZ 21, 2N705, 2N960...967
14811	2N981	80V, 0,1A, 0,5W, >50MHz	BC 546, 2SC1890(A), 2SC2240, 2SC2459
14812	2N982	20V, 0,1A, 0,06W, 450MHz	ASZ 21, 2N705, 2N960...967
14813	2N983	2N982, 15V	ASZ 21, 2N705, 2N960...967
14814	2N984	2N982, 15V	ASZ 21, 2N705, 2N960...967
14815	2N985	15V, 0,2A, 0,15W, <35/80ns	2N705, 2N960...967
14816	2N987	40V, 10mA, 0,1W, >40MHz	AF 124...126, AF 200
14817	2N988	20V, 0,22A, 0,3W, >300MHz	BC 168, BC 183, BC 238, BC 548
14818	2N989	20V, 0,22A, 0,3W, >300MHz	BC 168, BC 183, BC 238, BC 548
14819	2N99	40V, 0,01A, 0,05W	AC 127, 2SD39
14820	2N990	20V, 10mA, 0,067W, >44MHz	AF 124...126, AF 200
14821	2N991	20V, 10mA, 0,067W, >44MHz	AF 124...126, AF 200
14822	2N992	20V, 10mA, 0,067W, >44MHz	AF 124...126, AF 200
14823	2N993	20V, 10mA, 0,067W, >44MHz	AF 124...126, AF 200
14824	2N994	15V, 0,15A, 0,2W, <35/45ns	2N705, 2N960...967
14825	2N995(A)	20V, 0,36W, 300MHz	BC 308, BC 558, 2N3209, 2N4125...26
14826	2N996	15V, 0,2A, 0,36W, >100MHz	BC 213, BC 258, BC 308, BC 558
14827	2N997	75V, 0,3A, 0,5W, B>4000	BFX 66
14828	2N998	100V, 0,5A, 0,5W, B>1600	BFX 66
14829	2N999	60V, 0,5A, 0,5W, B>4000	BFX 67
14830	2NP	2SD2434-P	2SD2434
14831	2NP	2SD1478-P	2SD1478
14832	2NQ	2SD2434-Q	2SD2434
14833	2NQ	2SD1478-Q	2SD1478
14834	2NR	2SD2434-R	2SD2434
14835	2NR	2SD1478-R	2SD1478
14836	2OP	2SD1478A-P	2SD1478A
14837	2OQ	2SD1478A-Q	2SD1478A
14838	2OR	2SD1478A-R	2SD1478A
14839	2P	FMMT 2222R	FMMT 2222R
14840	2P	MMBT 5086	MMBT 5086
14841	2P	KST 5086	KST 5086
14842	2P	SXT2222A	SXT 2222A
14843	2P05M	Igt/Ih<0,2/<3mA	C 106F1, TAG 106F, C 108F, TAG 108F
14844	2P1M	2P05M, 100V	C 106A1, TAG 106A, C 108A, TAG 108A
14845	2P2M	2P05M, 200V	C 106B1, TAG 106B, C 108B, TAG 108B
14846	2P4M	2P05M, 400V	C 106D1, TAG 106D, C 108D, TAG 108D
14847	2P5M	2P05M, 500V	C 106E1, TAG 106E, C 108E, TAG 108E
14848	2P6M	2P05M, 600V	C 106M1, TAG 106M, C 108M, TAG 108M
14849	2PA1015(L)	2SA1015(L), 0,5W	2SA1015(L)

14850	2PA733	2SA733, 0,5W	2SA733
14851	2PB709(A)	2SB709(A)	2SB709(A)
14852	2PC1815(L)	2SC1815(L), 0,5W	2SC1815(L)
14853	2PC945	2SC945, 0,5W	2SC945
14854	2PD601(A)	2SD601(A)	2SD601(A)
14855	2Q	MMBT 5087	MMBT 5087
14856	2Q	KST 5087	KST 5087
14857	2R	MMBT 4260	MMBT 4260
14858	2S	MMBT 4261	MMBT 4261
14859	2S014[Texas]	40V, 20mA, >10MHz	BC 167, BC 183, BC 237, BC 547
14860	2S017[Texas]	60V, 0,4A, >2,5MHz	BC 140...141, BC 300...302, 2N3053
14861	2S018[Texas]	100V, 0,4A, >2,5MHz	BC 141, BC 300, 2N1889...90, 2N1990
14862	2S019[Texas]	60V, 0,4A, >2,5MHz	BC 140...141, BC 300...302, 2N3053
14863	2S020[Texas]	100V, 0,4A, >2,5MHz	BC 141, BC 300, 2N1889...90, 2N1990
14864	2S033(A)[Texas]	100V, 3A, 40W, 25MHz, B>30	BD 245C, BDX 95, 2N5758...60, 2SD895
14865	2S034[Texas]	2S033, B>60	BD 245C, BDX 95, 2N5758...60, 2SD896
14866	2S035[Texas]	2S033, 150V	BD 245D, 2SD731...732, 2SC2260...62
14867	2S036[Texas]	2S033, 150V, B>60	BD 245D, 2SD731...732, 2SC2260...62
14868	2S102[Texas]	B>20	BC 182, BC 190, BC 546, 2N3903...04
14869	2S103[Texas]	2S102, B>40	BC 182, BC 190, BC 546, 2N3903...04
14870	2S104[Texas]	2S102, B>80	BC 182, BC 190, BC 546, 2N3903...04
14871	2S131[Texas]	15V, 0,2A, 0,3W, >220MHz	BSS 11...12, BSY 17...18, 2N2368...69(A)
14872	2S2M	Igt/Ih<0,3/<10mA	-
14873	2S301	80V, 0,1A, 0,3W	BC 303, BC 556, 2SA970, 2SA1285(A)
14874	2S3010	40V, 0,15A, 0,3W	BC 303...304, BC 307, BC 557, 2N2303
14875	2S302	2S301, 40V	BC 303...304, BC 307, BC 557, 2N2303
14876	2S3020	40V, 0,15A, 0,3W	BC 303...304, BC 307, BC 557, 2N2303
14877	2S3021	15V, 0,15A, 0,3W	BC 303...304, BC 308, BC 558, 2N2303
14878	2S302A	2S301, 25V	BC 303...304, BC 308, BC 558, 2N2303
14879	2S303	2S301, 25V	BC 303...304, BC 308, BC 558, 2N2303
14880	2S3030	25V, 0,15A, 0,3W	BC 303...304, BC 308, BC 558, 2N2303
14881	2S304	2S301, 15V	BC 303...304, BC 308, BC 558, 2N2303
14882	2S3040	15V, 0,15A, 0,3W	BC 303...304, BC 308, BC 558, 2N2303
14883	2S305	2S301, 125V	BF 398, 2SA970, 2SA1049, 2SA1285(A)
14884	2S306	6/6/6V, 10mA, 0,05W	-
14885	2S307	2S306, 15/15/15V	-
14886	2S321	2S301	2S301
14887	2S322(A)	2S302(A)	2S302(A)
14888	2S3220	2S3020	2S3020
14889	2S3221	2S3021	2S3021
14890	2S323	2S303	2S303
14891	2S3230	2S3030	2S3030
14892	2S324	2S304	2S304
14893	2S3240	2S3040	2S3040
14894	2S325	2S305	2S305

14895	2S326	2S306	-
14896	2S327	2S307	-
14897	2S3M	2S 3M, 300V	-
14898	2S4M	2S 2M, 400V	-
14899	2S501	B>40	BC 168, BC 183, BC 238, BC 548
14900	2S502	2S501, B>100	BC 168, BC 183, BC 238, BC 548
14901	2S503	2S501, B>180	BC 168, BC 183, BC 238, BC 548
14902	2S512	25V, 0,2A, 0,3W, >250MHz	BSS 11...12, BSX 19...20, 2N2368...69(A)
14903	2S95A[Texas]	25V, 0,2A, 0,3W, >300MHz	BSS 11...12, BSX 19...20, 2N2368...69(A)
14904	2SA100	40V, 10mA, 20MHz	AF 124...127, AF 200, 2SA218...227
14905	2SA1001	130V, 8A, 80W, 40MHz	2SA908, 2SA1386(A), 2SB555, 2SB681
14906	2SA1002	120V, 12A, 120W, 40MHz	2SA908, 2SA1386(A), 2SB555, 2SB681
14907	2SA1003	2SA1002, 150V	2SA908, 2SA1386(A), 2SB697, 2SB681
14908	2SA1004	40V, 0,1A, 0,31W, 200MHz	BC 213, BC 257, BC 307, BC 557
14909	2SA1005	40V,,0,03A, 0,25W, 400MHz	BF 324, BF 414, BF 936, BF 939, BF 509
14910	2SA1006	180V, 1,5A, 25W, 80MHz	2SA968A,B, 2SA1009(A), 2SA1133, 2SB628A
14911	2SA1006A	2SA1006, 200V	2SA968B, 2SA1009(A), 2SA1133
14912	2SA1006B	2SA1006, 250V	2SA1009(A), 2SA1236, 2SA1397
14913	2SA1007(A)	150V, 10A, 100W, 50MHz	BDX 20, 2SA1386(A), 2SB681, 2SB697
14914	2SA1008	100V, 2A, 15W, <0,5/2µs	2SA1078...1079, 2SB719...720, 2SB861
14915	2SA1009	350/350V, 2A, 15W, <1/3,5µs	2SA1236, 2SA1397
14916	2SA1009A	2SA1009, 400/400V	2SA1236, 2SA1397
14917	2SA101	40V, 10mA, 15MHz	AF 124...127, AF 200, 2SA218...227
14918	2SA1010	100V, 7A, 40W, <0,5/2µs	BD 244C, BD 544C, MJE 15029, 2SA1077
14919	2SA1011	180V, 1,5A, 25W, 100MHz	2SA968A,B, 2SA1112, 2SA1133, 2SB628A
14920	2SA1012	60V, 5A, 25W, 60MHz	2SA1289...1291, 2SA1293, 2SB919
14921	2SA1013	160V, 1A, 0,9W, >15MHz	2SA1275, 2SB1212
14922	2SA1014	2SA1013, 10W	2SA913A, 2SA1112, 2SB630, 2SB861
14923	2SA1015	50V, 0,15A, 0,4W, >80MHz	BC 212, BC 257, BC 307, BC 557
14924	2SA1016	120V, 0,05A, 0,4W, 110MHz	2SA941, 2SA970, 2SA992, 2SA1038
14925	2SA1016K	2SA1016, 150V	2SA1123...24
14926	2SA1017	120V, 0,05A, 0,5W, 110MHz	2SA893A, 2SA1019, 2SA1285, 2SB716(A)
14927	2SA1018	>50MHz	BF 423, BF 436...437, 2SA1371...1372
14928	2SA1019	150V, 0,05A, 0,9W, 110MHz	2SA1124, 2SA1281, 2SA1285A, 2SB1348
14929	2SA102	40V, 10mA, 25MHz	AF 124...127, AF 200, 2SA218...227
14930	2SA1020	50V, 2A, 0,9W, 100MHz	2SA1382, 2SA1315, 2SB892, 2SB1312
14931	2SA1021	150V, 1,5A, 20W, >15MHz	2SA1249, 2SB649
14932	2SA1022	30V, 0,03A, >150MHz	BC 859...860, BCF 30, BCF 70, BF 550
14933	2SA1023	70V, 0,1A, 0,25W, 180MHz	BC 556, 2SA970, 2SA1049, 2SA1285(A)
14934	2SA1024	400V, 0,1A, 0,4W, 15MHz	2SA1251, 2SA1372, 2SB1074
14935	2SA1025	60V, 0,1A, 0,4W, 90MHz	BC 212, BC 256, BC 266, BC 556
14936	2SA1026	50V, 0,2A, 0,25W, 100MHz	BC 212, BC 256, BC 266, BC 556
14937	2SA1027	50V, 0,2A, 0,25W, 100MHz	BC 214, BC 416, BC 560, 2SA1136...1137
14938	2SA1028	100V, 10A, 95W, 60MHz	2SA1141, 2SA1146, 2SA1186
14939	2SA1029	30V, 0,1A, 0,2W, 280MHz	BC 213, BC 258, BC 308, BC 558

14940	2SA103	40V, 10mA, 35MHz	AF 124...127, AF 200, 2SA218...227
14941	2SA1030	2SA1029, 55V	BC 212, BC 257, BC 307, BC 557
14942	2SA1031	2SA1029	BC 214, BC 259, BC 309, BC 559, 2SA1137
14943	2SA1032	2SA1029, 55V,	BC 214, BC 416, BC 560, 2SA1136...1137
14944	2SA1033	30V, 0,1A, 0,31W, 280MHz	BC 213, BC 258, BC 308, BC 558
14945	2SA1034	35V, 0,05A, 200MHz	BC 859...860, BCF 29...30, BCF 70, 2SA1312
14946	2SA1035	2SA1034, 55V	BC 860, BCF 70, 2SA1312
14947	2SA1036(K)	40V, 0,5A, 200MHz	BC 807, BCW 67...68, BCX 17, 2SA1313
14948	N)	50V, 0,1A, 140MHz	BC 860, BCF 70
14949	2SA1038	120V, 0,05A, 0,3W, 140MHz	2SA941, 2SA970, 2SA992, 2SA1136
14950	2SA1039	2SA1038, 80V	2SA942, 2SA970, 2SA992, 2SA1136...37
14951	2SA104	40V, 10mA, 50MHz	AF 124...127, AF 200, 2SA218...227
14952	2SA1040	120V, 10A, 100W, 60MHz	BUW 96, 2SA1146, 2SA1186, 2SB552
14953	2SA1041	120V, 15A, 100W, 60MHz	BUW 96, 2SA908...909, 2SA1147, 2SB552
14954	2SA1042	70V, 15A, 100W, 60MHz	BUW 96, 2SA907...909, 2SA1147, 2SB552
14955	2SA1043	120V, 30A, 150W, 60MHz	-
14956	2SA1046	2SA1045, 15A	BDX 66B, MJ 4032, 2SB693
14957	2SA1047	160V, 0,08A, 130MHz	BF 416, BF 418, BF 470, BF 472, 2SB1109
14958	2SA1048	50V, 0,15A, 0,2W, >80MHz	BC 214, BC 416, BC 560, 2SA1136...1137
14959	2SA1049	120V, 0,1A, 0,2W, 100MHz	2SA970, 2SA992, 2SA1136, 2SA1285
14960	2SA105	6V, 10mA, 75MHz	AF 124...126, AF 200, 2SA218...227
14961	2SA1050	140V, 12A, 100W, 70MHz	2SA1227, 2SA1386, 2SB555, 2SB681
14962	2SA1050A	2SA1050, 120W	2SA1227, 2SA1386, 2SB555, 2SB681
14963	2SA1051	150V, 15A, 150W, 60MHz	MJ 15016, 2SA908...09, 2SA1117, 2SA1147
14964	2SA1051A	2SA1051, 160V	MJ 15016, 2SA909, 2SA1116...17, 2SA1147
14965	2SA1052	30V, 0,1A, 280MHz	BC 856...858, BCW 29...30, BCW 69...70
14966	2SA1053	40V, 0,2A, 0,6W, <70/300ns	BSW 24, 2N3250...51(A), 2N3905...06
14967	2SA1054	60V, 0,6A, 0,6W, <35/225ns	BSW 24, 2N2906...07(A), 2N4026...29
14968	2SA1055	25V, 0,2A, 0,6W, <70/300ns	BSW 24, 2N3905...06, 2N4125...26
14969	2SA1056	40V, 0,6A, 0,6W, <35/225ns	BSW 24, 2N2906...07(A), 2N4026...29
14970	2SA1057	20V, 0,05A, 4GHz	BFQ 32, 2SA801, 2SA1223
14971	2SA1058	20V, 0,05A, 2,5GHz	BFQ 32, BFQ 78, 2SA801, 2SA1223
14972	2SA106	6V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
14973	2SA1060	80V, 5A, 60W, 15MHz	BD 246B, 2SB688, 2SB776, 2SB816
14974	2SA1061	100V, 6A, 70W, 15MHz	BD 246C, 2SB688, 2SB776, 2SB816
14975	2SA1062	120V, 7A, 80W, 15MHz	BD 246C, 2SB688, 2SB776, 2SB816
14976	2SA1063	150V, 6A, 80W, 50MHz	2SA1186, 2SB681, 2SB696...697, 2SB816
14977	2SA1064	150V, 8A, 100W, 50MHz	2SA1186, 2SB681, 2SB697, 2SB817
14978	2SA1065	150V, 10A, 120W, 50MHz	2SA1186, 2SB681, 2SB697, 2SB817
14979	2SA1066	70V, 0,2A, 0,5W, 120MHz	BC 556, 2SA970, 2SA941...942, 2SA1285
14980	2SA1067	120V, 10A, 100W, 50MHz	2SA1186, 2SB681, 2SB697, 2SB817
14981	2SA1068	2SA1067, 150V	2SA1186, 2SB681, 2SB697, 2SB817
14982	2SA1069(A)	80V, 5A, 30W, <0,5/3μs	BD 244B, BD 540B, BD 952, 2SA1289...90
14983	2SA107	9V, 10mA, 40MHz	AF 124...127, AF 200, 2SA218...227
14984	2SA1072	120V, 12A, 120W, 60MHz	2SA1227, 2SA1386, 2SB555, 2SB681



14985	2SA1072A	2SA1072, 150V	2SA1227A, 2SA1386, 2SB697, 2SB681
14986	2SA1073	2SA1072, 160V	2SA1227A, 2SA1386, 2SB697, 2SB681
14987	2SA1074	160V, 15A, 150W	MJ 15016, 2SA908...09, 2SA1117, 2SA1147
14988	2SA1075	2SA1072	2SA1094...1095, 2SA1166, 2SA1187
14989	2SA1076	2SA1073	2SA1095, 2SA1166, 2SA1215, 2SA1389
14990	2SA1077	120V, 10A, 60W, 60MHz	-
14991	2SA1078	120V, 2A, 25W, 140MHz	2SA1133, 2SB719...720
14992	2SA1079	2SA1078, 160V	2SA1133, 2SB719...720
14993	2SA108	20V, 10mA, 50MHz	AF 124...126, AF 200, 2SA218...227
14994	2SA1080	40V, 0,5A, 20W, 30MHz	BD 240, 2SA748
14995	2SA1081	90V, 0,1A, 0,4W, 90MHz	2SA970, 2SA1049, 2SA1136, 2SA1285(A)
14996	2SA1082	2SA1081, 120V	2SA970, 2SA1049, 2SA1136, 2SA1285(A)
14997	2SA1083	2SA1081, 60V	BC 416, BC 560, 2SA970, 2SA1049
14998	2SA1084	2SA1081, 90V	2SA970, 2SA1049, 2SA1136
14999	2SA1085	2SA1081, 120V	2SA970, 2SA1049, 2SA1136
15000	2SA109	20V, 10mA, 45MHz	AF 124...126, AF 200, 2SA218...227
15001	2SA1090	60V, 0,2A, 0,3W, 250MHz	BC 212, BC 556, 2N2906...2907(A)
15002	2SA1091	300V, 0,1A, 0,4W, 60MHz	BF 437, BF 421A, 2SA1371...1372
15003	2SA1092	60V, 0,05A, 0,25W, 220MHz	BC 416, BC 560, 2SA970, 2SA1136...1137
15004	2SA1093	120V, 8A, 80W, 90MHz	2SA1141, 2SA1146, 2SA1186
15005	2SA1094	140V, 12A, 120W, 70MHz	2SA1076, 2SA1166, 2SA1187, 2SA1389
15006	2SA1095	60MHz	2SA1076, 2SA1166(A), 2SA1215, 2SA1389
15007	2SA1096(A)	70V, 2A, 5W, 150MHz	BD 378, BD 380, 2SB744(A), 2SB874...75
15008	2SA110	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
15009	2SA1100	50V, 0,2A, 0,3W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...1137
15010	2SA1100	50V, 0,2A, 0,3W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...1137
15011	2SA1102	80V, 6A, 60W, 20MHz	BD 246B, BDV 94, 2SA1141, 2SA1227(A)
15012	2SA1103	100V, 7A, 70W, 20MHz	BD 246C, BDV 96, 2SA1141, 2SA1227(A)
15013	2SA1104	120V, 8A, 80W, 20MHz	BD 246C, 2SA1141, 2SA1186, 2SA1227(A)
15014	2SA1105	120V, 9A, 90W, 20MHz	BD 246C, 2SA1141, 2SA1186, 2SA1227(A)
15015	2SA1106	140V, 10A, 100W, 20MHz	2SA1186, 2SA1227A, 2SA1386(A), 2SB817
15016	2SA1107(A)	150V, 10A, 120W, 50MHz	2SA1076, 2SA1095, 2SA1166(A), 2SA1389
15017	2SA1108	130V, 12A, 120W, 60MHz	2SA1076, 2SA1095, 2SA1166(A), 2SA1389
15018	2SA1108A	2SA1108, 150V	2SA1076, 2SA1095, 2SA1166(A), 2SA1389
15019	2SA1109	180V, 10A, 200W, 60MHz	MJ 15016, 2SA909, 2SA1147, 2SA1116...17
15020	2SA111	20V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
15021	2SA1110	120V, 0,5A, 5W, 200MHz	2SA1178, 2SA1184, 2SA1220(A), 2SA1358
15022	2SA1111	150V, 1A, 20W, 200MHz	2SA913(A), 2SA968(A,B), 2SA1011
15023	2SA1112	2SA1111, 180V	2SA913A, 2SA968A,B, 2SA1011, 2SA1133
15024	2SA1114	70V, 0,2A, 0,5W, 150MHz	2SA970, 2SA1049, 2SA1136...1137
15025	2SA1114	70V, 0,2A, 0,5W, 150MHz	2SA970, 2SA1049, 2SA1136...1137
15026	2SA1115	50V, 0,2A, 0,3W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...1137
15027	2SA1116	200V, 15A, 150W, 20MHz	MJ 15016, 2SA909, 2SB552, 2SB645
15028	2SA1117	200V, 17A, 200W, 20MHz	-
15029	2SA112	20V, 10mA, 20MHz	AF 124...126, AF 200, 2SA218...227



15030	2SA1120	35V, 5A, 10W, 170MHz	2SA1357
15031	2SA1121	35V, 0,5A, 50MHz	BC 807, BCW 67, BCX 17, 2SA1326
15032	2SA1122	55V, 0,1A	BC 856...857, BCW 69...70, BCW 89
15033	2SA1123	150V, 0,05A, 0,75W, 200MHz	2SA1016K, 2SA1482
15034	2SA1124	2SA1123, 1W	2SA1482, 2SA1016K
15035	2SA1125	2SA1123, 1,5W	-
15036	2SA1126	650V, 0,1A, 0,75W, 15MHz	2SA911
15037	2SA1127	60V, 0,1A, 0,4W, 200MHz	BC 560, 2SA1049, 2SA1136...37, 2SA1335
15038	2SA1128	25V, 0,5A, 0,6W, 150MHz	BC 327...328, BC 636, 2SA1515, 2SB910
15039	2SA1129	30V, 7A, 40W, <1/3,5µs	BD 244, BD 544, BD 796, BD 806, 2SB919
15040	2SA113	34V, 10mA, 20MHz	AF 124...126, AF 200, 2SA218...227
15041	2SA1133(A)	200V, 2A, 30W, 40MHz	BD 240F, 2SB720, 2SB861
15042	2SA1135	80V, 4A, 55W, 10MHz	BD 246B, BDV 96, 2SA1141, 2SA1186
15043	2SA1136	120V, 0,1A, 0,3W, 90MHz	2SA941, 2SA970, 2SA992, 2SA1049
15044	2SA1137	2SA1136, 80V	2SA941...942, 2SA970, 2SA992, 2SA1049
15045	2SA1138(1)	80V, 0,01A, 0,6W, 180MHz	2SA941...942, 2SA970, 2SA992, 2SA1049
15046	2SA114	34V, 10mA, 20MHz	AF 124...127, AF 200, 2SA218...227
15047	2SA1141	115V, 10A, 100W, 90MHz	2SA1146, 2SA1186
15048	2SA1142	180V, 0,1A, 8W, 180MHz	BF 416, BF 418, BF 470, BF 472, 2SA1352
15049	2SA1143	20V, 0,05A, 0,2W, 100MHz	BC 213, BC 258, BC 308, BC 558
15050	2SA1143	20V, 0,05A, 0,2W, 100MHz	BC 213, BC 258, BC 308, BC 558
15051	2SA1144	150V, 0,05A, 10W, 200MHz	BF 416, BF 418, BF 470, BF 472, 2SA1352
15052	2SA1145	2SA1144, 0,8W	2SA1124, 2SA1281, 2SA1285A, 2SA1482
15053	2SA1146	140V, 10A, 100W, 70MHz	2SA1186
15054	2SA1147	180V, 15A, 150W, 60MHz	MJ 15016, 2SA909, 2SA1116...17, 2SB645
15055	2SA115	34V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
15056	2SA1150	35V, 0,8A, 0,3W, 120MHz	BC 327...328, BC 636, BC 638, BC 640
15057	2SA1151	60V, 0,1A, 0,25W, 180MHz	BC 212, BC 256, BC 266, BC 556
15058	2SA1152	80V, 0,3A, 0,6W, 50/450ns	BC 640, 2N4027, 2N4029, 2N5400...01
15059	2SA1153	60V, 0,5A, 0,6W, <35/255ns	BSW 24, 2N2906...07(A), 2N4026...29
15060	2SA1154	60V, 0,7A, 1W, 120MHz	BC 638, BC 640, 2N2906...2907(A)
15061	2SA1156	400/400V, 0,5A, 10W, <1/5µs	2SA1775, 2SA1400
15062	2SA1158	80V, 0,1A, 0,4W, >80MHz	BC 556, 2SA970, 2SA1049, 2SA1285
15063	2SA116	30V, 10mA, 120MHz	AF 124...125, AF 200, 2SA340...342
15064	2SA1160	20V, 2A, 0,9W, 140MHz	2SA1382, 2SB927, 2SB892, 2SB985
15065	2SA1161	15V, 0,03A, 0,2W, 3,5GHz	BFQ 32, 2SA1057, 2SA1223, 2SA1228
15066	2SA1162	50V, 0,15A, >80MHz	BC 856...857, BCW 69...70, BCW 89, 2SA1311
15067	2SA1163	120V, 0,1A, 100MHz	2SA1312, 2SA1566
15068	2SA1164	35V, 0,1A, 0,2W, 30/320ns	2N3250...51(A), 2N3905...06, 2N4034...35
15069	2SA1166	160V, 15A, 150W, 60MHz	2SA1076, 2SA1095, 2SA1215, 2SA1389
15070	2SA1166A	2SA1166, 180V	2SA1169...1170, 2SA1216, 2SA1333
15071	2SA1169	200V, 15A, 150W, 20MHz	2SA1295, 2SA1333, 2SB756
15072	2SA117	30V, 10mA, 110MHz	AF 124...125, AF 200, 2SA340...342
15073	2SA1170	200V, 17A, 200W, 20MHz	2SA1295
15074	2SA1171	90V, 0,05A, 200MHz	2SA1312, 2SA1466

15075	2SA1173	140V, 0,05A, 80MHz	2SA1200, 2SB807, 2SB1046...1047
15076	2SA1174	120V, 0,05A, 0,3W, 100MHz	2SA1016(K), 2SA1038, 2SA1123...24
15077	2SA1175	60V, 0,1A, 0,25W, 180MHz	BC 212, BC 256, BC 266, BC 556
15078	2SA1177	230MHz	BF 324, BF 440...441, BF 450...451
15079	2SA1178	150V, 1A, 20W, 200MHz	2SA1220A, 2SB649, 2SB1086A
15080	2SA1179	55V, 0,15A, 180MHz	BC 856...857, BCW 69...70, BCW 89, 2SA1312
15081	2SA118	30V, 10mA, 100MHz	AF 124...125, AF 200, 2SA340...342
15082	2SA1180	180V, 10A, 100W	MJ 15016, BUW 96, 2SA909, 2SA1116...17
15083	2SA1180A	2SA1180, 200V	MJ 15016, BUW 96, 2SA909, 2SA1116...17
15084	2SA1182	35V, 0,5A, 200MHz	BC 807, BCW 68, BCX 17, 2SA1313
15085	2SA1183	120V, 7A, 70W, B15000	BDV 64C
15086	2SA1184	120V, 1A, 15W, 120MHz	2SA1178, 2SA1220(A), 2SA1358, 2SB1086
15087	2SA1185	50V, 7A, 60W, 100MHz	2SA1141, 2SA1146, 2SA1186
15088	2SA1186	150V, 10A, 100W, 60MHz	2SA1227A, 2SA1386(A)
15089	2SA1187	2SA1186, 12A, 120W	2SA1076, 2SA1095, 2SA1215, 2SA1166(A)
15090	2SA1188	90V, 0,1A, 0,4W, 130MHz	2SA970, 2SA1049, 2SA1136, 2SA1285(A)
15091	2SA1189	2SA1188, 120V	2SA970, 2SA1049, 2SA1136, 2SA1285(A)
15092	2SA119	40V, 0,3A, 0,65W, 200MHz	BC 303...304, BSW 23, 2N2904...2905(A)
15093	2SA1190	2SA1188	2SA872, 2SA970, 2SA1049, 2SA1136
15094	2SA1191	2SA1188, 120V	2SA872A, 2SA970, 2SA1049, 2SA1136
15095	2SA1193(K)	60V, 0,5A, 0,9W, B>2000	BC876, BC878, BC880, BSR60...62, 2SB1405
15096	2SA1194(K)	60V, 1A, 8W, B>1000	BD 678, BD 778, BD 876, BDX 45...47
15097	2SA1195	160V, 1,5A, 15W, 50MHz	2SA968(A,B), 2SA1011, 2SA1332
15098	2SA1196	400V, 0,1A, 10W	2SA1700, BF 891, 2SA1354, 2SB1011
15099	2SA1197	2SA1194	2SB963...964
15100	2SA1198(S)	80V, 0,05A, 0,4W, 140MHz	BC 556, 2SA872(A), 2SA970, 2SA1285
15101	2SA1198(S)	80V, 0,05A, 0,4W, 140MHz	BC 556, 2SA872(A), 2SA970, 2SA1285
15102	2SA1199(S)	50V, 0,7A, 0,4W, 100MHz	BC327, BC638, 2SB647, 2SB910, 2SB1116
15103	2SA1199(S)	50V, 0,7A, 0,4W, 100MHz	BC327, BC638, 2SB647, 2SB910, 2SB1116
15104	2SA12	16V, Ueb0,5V, 15mA, 8MHz	AF 124...127, AF 200, 2SA201...202
15105	2SA120	25V, 0,3A, 0,65W, 200MHz	BC 303...304, BSW 23, 2N2904...2905(A)
15106	2SA1200	150V, 0,05A, 120MHz	2SB807, 2SB1046...1047
15107	2SA1201	120V, 0,8A, 120MHz	2SB806, 2SB1025
15108	2SA1202	80V, 0,4A, 120MHz	2SA1368, 2SB767, 2SB789(A)
15109	2SA1203	30V, 1,5A, 120MHz	2SA1213, 2SA1663, 2SB1123, 2SB1313
15110	2SA1204	35V, 0,8A, 120MHz	BCX 51...53, 2SA1364, 2SB1734, 2SB804
15111	2SA1205	70V, 12A, 100W, 20MHz	BD 246A, BD 746A, BDV 94, 2SA1292
15112	2SA1206	15V, 0,05A, 0,6W, <20/40ns	BSX 36, 2N4313, 2N5056...57
15113	2SA1207	180V, 0,07A, 0,6W, 150MHz	BF 436...437, BF 423A, 2SA1281
15114	2SA1208	180V, 0,07A, 0,9W, 150MHz	BF 436, BF 423A, 2SA1281, 2SA1370...71
15115	2SA1209	180V, 0,14A, 10W, 150MHz	BF 416, BF 418, 2SA1352, 2SA1407
15116	2SA120A	2SA120, 40V	BC 303...304, BSW 23, 2N2904...2905(A)
15117	2SA121	15V, 2mA, 100MHz	AF 124...125, AF 106, AF 306, 2SA340...342
15118	2SA1210	200V, 0,14A, 10W	BF 416, BF 418, 2SA1352, 2SA1407
15119	2SA1211	35V, 0,1A, 0,2W, 400MHz	BC 213, BC 308, BC 558, 2N2906...07

15120	2SA1213	50V, 2A, 120MHz	2SA1417, 2SB1029, 2SB1123, 2SB1313
15121	2SA1214	60V, 2A, 25W, 35MHz	BD 178, BD 236, BD 440, 2SB1217
15122	2SA1215	160V, 15A, 150W, 50MHz	2SA1076, 2SA1095, 2SA1166(A), 2SA1389
15123	2SA1216	180V, 17A, 200W, 40MHz	2SA1170, 2SA1295
15124	2SA1217	40V, 3A, 10W, 100MHz	BD 786, 2SB744(A), 2SB986
15125	2SA1218	60V, 0,6A, 0,36W, <45/300ns	BSW 24, 2N2906...07(A), 2N4026...29
15126	2SA1219	60V, 0,1A, 0,25W, 180MHz	BC 212, BC 256, BC 266, BC 556
15127	2SA122	15V, 2mA, 100MHz	AF 124...125, AF 106, AF 306, 2SA340...342
15128	2SA1220	120V, 1,2A, 20W, 175MHz	2SA1249, 2SB649
15129	2SA1220A	2SA1220, 160V	2SA1249, 2SB649
15130	2SA1221	160/140V, 0,5A, 1W, 45MHz	2N5401, 2SA1013, 2SA1319
15131	2SA1222	2SA1221, 160/160V	2N5401, 2SA1013, 2SA1319
15132	2SA1223	20V, 0,05A, 4GHz	BFQ 32, BFQ 79, 2SA801, 2SA1057
15133	2SA1225	160V, 1,5A, 15W, 100MHz	2SA1552, 2SB840...842, 2SB1275
15134	2SA1226	40V, 30mA, 400MHz	BF 536, BF 550, BF 568...569, BF 660
15135	2SA1227	140/140V, 12A, 120W, 60MHz	2SA1386(A), 2SB817
15136	2SA1227A	2SA1227, 160/160V	2SA1386(A), 2SB817
15137	2SA1228	20V, 0,05A, 4GHz	BFQ 24
15138	2SA123	15V, 2mA, 100MHz	AF 124...125, AF 106, AF 306, 2SA340...342
15139	2SA1230	15V, 0,05A, 8GHz	-
15140	2SA1232	130V, 10A, 100W, 60MHz	2SA1146, 2SA1186, 2SA1227(A), 2SA1386(A)
15141	2SA1233	400V, 0,1A, 10W	2SA1700, 2SA1354, 2SB1011
15142	2SA1234	20V, 0,05A	-
15143	2SA1235	50V, 0,2A, 200MHz	BC 856...857, BCW 69...70, BCW 89
15144	2SA1236	400V, 2A, 15W	2SA1009A, 2SA1397
15145	2SA124	15V, 2mA, 120MHz	AF 124...125, AF 106, AF 306, 2SA340...342
15146	2SA1241	50V, 2A, 10W, 100MHz	2SB1201...02, 2SB1215...16
15147	2SA1242	35V, 5A, 10W, 170MHz	2SA1244, 2SA1401, 2SB1203...1204
15148	2SA1243	30V, 3A, 15W, 100MHz	2SB906, 2SB962, 2SB1184, 2SB1202...03
15149	2SA1244	60V, 5A, 20W, 60MHz	2SA1385, 2SA1795, 2SB1203...04
15150	2SA1245	15V, 0,03A, 4GHz	BFT 92...93
15151	2SA1246	60V, 0,15A, 0,4W, 100MHz	2SA1253, BC 212, BC 256, BC 266, BC 556
15152	2SA1247	120V, 0,05A, 100MHz	2SA1312, 2SA1566
15153	2SA1248	180/160V, 0,7A, 10W, 120MHz	2SA1249, 2SB649
15154	2SA1249	180/160V, 1,5A, 10W, 120MHz	2SB649
15155	2SA125	15V, 2mA, 120MHz	AF 124...125, AF 106, AF 306, 2SA340...342
15156	2SA1250	200V, 8A, 30W	-
15157	2SA1250	200V, 8A, 30W	-
15158	2SA1251	<300/2300ns	2SA1625, 2SB1074, 2SB1488
15159	2SA1252	60V, 0,15A, 100MHz	2SA1434, BC 856, BCW 89, 2SA1312
15160	2SA1253	60V, 0,2A, 0,25W, 100MHz	2SA1246, BC 212, BC 256, BC 266, BC 556
15161	2SA1254	30V, 0,03A, 0,4W, 300MHz	BC 308, BC 558, BF 324, BF 414, BF 939
15162	2SA1255	200V, 0,05A, 100MHz	BF 821, BF 823, BFN 23, 2SA1330
15163	2SA1256	30V, 30mA, 230MHz	BF 536, BF 550, BF 568, BF 660
15164	2SA1257	180V, 0,08A, 130MHz	BFN 25, BFN 27, 2SA1330

15165	2SA1258	70V, 3A, 20W, 200MHz, B5000	BDT 60A...C, BDW 64B...D, 2SB751A...B
15166	2SA1259	70V, 5A, 30W, 200MHz, B5000	BDW 24B...C, BDW 64B...D, 2SB1339
15167	2SA126	12V, 0,05A, 50/110ns	ASZ 21, 2N2955...2957
15168	2SA1260	70V, 7A, 40W, B5000	BDT 62A...C, BDX 34B...D
15169	2SA1261	100V, 10A, 60W, <0,5/2 $\mu$ s	BD 712, BD 744C, BD 912
15170	2SA1261	100V, 10A, 60W, <0,5/2 $\mu$ s	BD 712, BD 744C, BD 912
15171	2SA1262	60V, 4A, 30W, 15MHz	2SB920L, BD 536, BD 540A, BD 950
15172	2SA1263	80V, 6A, 60W, 30MHz	BD 246B, BDV 94, 2SA1146, 2SA1186
15173	2SA1264	2SA1263, 120V, 8A, 80W	BD 246C, 2SA1141, 2SA1186, 2SA1227(A)
15174	2SA1265	2SA1263, 140V, 10A, 100W	BD 246D, 2SA1146, 2SA1186, 2SA1227(A)
15175	2SA1266	50V, 0,15A, 0,4W, 130MHz	BC 416, BC 560, 2SA970, 2SA1136...1137
15176	2SA1267	2SA1266, 0,2W	BC 416, BC 560, 2SA970, 2SA1136...1137
15177	2SA1268	120V, 0,1A, 0,3W, 100MHz	2SA970, 2SA1049, 2SA1038, 2SA1136
15178	2SA1269	2SA1268, 0,2W	2SA970, 2SA1049, 2SA1038, 2SA1136
15179	2SA127	70V, 50mA, 25MHz	AF 118, SFT 162, 2SA358
15180	2SA1270	35V, 0,5A, 0,5W, 200MHz	BC 327, BC 636, 2SA1515, 2SB910
15181	2SA1271	35V, 0,8A, 0,6W, 120MHz	BC 327, BC 636, 2SB909...910, 2SB734
15182	2SA1272	2SA1271, 0,3W	BC 327, BC 636, 2SB909...910, 2SB734
15183	2SA1273	30V, 2A, 1W, 120MHz	2SB892, 2SB927, 2SB1312, 2SA1382
15184	2SA1274	80V, 0,4A, 0,8W, 100MHz	BC 640, 2N5400...5401, 2SA965, 2SA1533
15185	2SA1275	160V, 1A, 0,9W, 50MHz	2SA1013, 2SB1212
15186	2SA1276	30V, 3A, 10W, 100MHz	2SA473, 2SA1012, 2SA1288...1289
15187	2SA1277	30V, 3A, 20W, 100MHz	2SA473, 2SA1012, 2SA1288...1289
15188	2SA1278	160V, 1,5A, 25W, 100MHz	2SA968(A...B), 2SA1011, 2SA1079, 2SA1332
15189	2SA1279	60V, 5A, 25W, 60MHz	2SA1012, 2SA1289...91, 2SA1293
15190	2SA128	$\beta > 15$	ASY 76...77
15191	2SA1280	150V, 1,5A, 25W, 4MHz	2SB608, 2SB628(A), 2SB861, 2SB991
15192	2SA1281	180V, 0,1A, 0,9W, 130MHz	BF 436, BF 423A, 2SA1370
15193	2SA1282(A)	20V, 2A, 0,9W, 80MHz	2SA1382, 2SB738...739, 2SB892, 2SB1312
15194	2SA1283	60V, 1A, 0,9W, 85MHz	2SA1315, 2SB647, 2SB892, 2SB1041
15195	2SA1284	100V, 0,5A, 0,9W, 130MHz	BC 640, 2N5400...5401, 2SA695, 2SB1297
15196	2SA1285	120V, 0,1A, 0,9W, 200MHz	2SA1281, 2SA1124, 2SA1482
15197	2SA1285A	2SA1285, 150V	2SA1124, 2SA1281, 2SA1482
15198	2SA1286	30V, 1,5A, 0,9W, B>400	2SB892, 2SB927
15199	2SA1287	50V, 1A, 0,9W, 90MHz, B>400	2SA1315, 2SB892, 2SB1229
15200	2SA1288	80V, 3A, 30W, 100MHz	MJE 15029, 2SA1293
15201	2SA1289	80V, 5A, 30W, 100MHz	2SA1293
15202	2SA129	2SA128, $\beta > 35$	ASY 76...77
15203	2SA1290	80V, 7A, 35W, 100MHz	2SA1329
15204	2SA1291	80V, 10A, 40W, 100MHz	2SA1329
15205	2SA1292	80V, 15A, 70W, 100MHz	2SB922L
15206	2SA1293	100V, 5A, 30W, 60MHz	-
15207	2SA1294	230V, 15A, 130W, 35MHz	-
15208	2SA1295	230V, 17A, 200W, 35MHz	-
15209	2SA1296	20V, 2A, 0,75W, 120MHz	2SA1315, 2SA1382, 2SB985, 2SB911

15210	2SA1297	2SA1296, 0,4W	2SA1315, 2SA1382, 2SB985, 2SB911
15211	2SA1298	30V, 0,8A, 120MHz	BCW 67...68, 2SA1621
15212	2SA1299	50V, 0,2A, 0,3W, 200MHz	BC 416, BC 560, 2SA970, 2SA1136...1137
15213	2SA12H	2SA12, Ueb12V	-
15214	2SA13	12V, 15mA, 8MHz	AF 124...127, AF 200, 2SA201...202
15215	2SA130	9V, 10mA, 65MHz	AF 124...126, AF 200, 2SA218...227
15216	2SA1300	20V, 2A, 0,75W, 140MHz	2SB926...927, 2SB892, 2SB1229
15217	2SA1301	160V, 12A, 120W, 30MHz	2SA1553, 2SB1153, 2SB1162...63, 2SB1347
15218	2SA1302	200V, 15A, 150W, 30MHz	2SA1553
15219	2SA1303	150V, 14A, 125W, 50MHz	2SA1227A, 2SA1386(A), 2SB817
15220	2SA1304	150V, 1,5A, 20W, 4MHz	2SA1306, 2SA1332, 2SA1606, 2SB1338
15221	2SA1305	30V, 3A, 15W, 100MHz	2SA1307, 2SB1185, 2SB1274
15222	2SA1306	160V, 1,5A, 20W, 100MHz	2SA1332, 2SA1606, 2SB1186A
15223	2SA1306A	2SA1306, 180V	2SA1606
15224	2SA1306B	2SA1306, 200V	-
15225	2SA1307	60V, 5A, 20W, 60MHz	2SA1388, 2SA1469...70, 2SA1441
15226	2SA1308	100V, 5A, 30W, 60MHz	2SA1293
15227	2SA1309	30V, 0,1A, 0,3W, 80MHz	BC 213, BC 258, BC 308, BC 558
15228	2SA1309A	2SA1309, 60V	BC 212, BC 257, BC 307, BC 557
15229	2SA131	9V, 10mA, 45MHz	AF 124...126, AF 200, 2SA218...227
15230	2SA1310	60V, 0,1A, 0,3W, 200MHz	BC 416, BC 560, 2SA970, 2SA1136...1137
15231	2SA1311	60V, 0,15A, 150MHz	2SA1312
15232	2SA1312	120V, 0,1A, 100MHz	2SB792
15233	2SA1313	50V, 0,5A, 200MHz	BC 807, BCX 17, 2SA1366
15234	2SA1314	20V, 2A, 140MHz	2SB1121...23
15235	2SA1315	80V, 2A, 0,9W, 80MHz	2SB1459
15236	2SA1316	80V, 0,1A, 0,4W, 50MHz	2SA970, 2SA1038, 2SA1049, 2SA1136...37
15237	2SA1317	60V, 0,2A, 0,3W, 200MHz	BC 212, BC 256, BC 266, BC 556
15238	2SA1318	2SA1317, 0,5W	BC 212, BC 256, BC 266, BC 556
15239	2SA1319	180V, 0,7A, 0,7W, 120MHz	2SA1768
15240	2SA132	9V, 10mA, 50MHz	AF 124...126, AF 200, 2SA218...227
15241	2SA1320	250V, 0,05A, 0,6W, 80MHz	BF 423, BF 436...437, 2SA1371...1372
15242	2SA1321	2SA1320, 0,9W	BF 423, BF 436...437, 2SA1371...1372
15243	2SA1322	2SA1320, 5W	BF 416, BF 418, BF 470, BF 472
15244	2SA1323	30V, 0,03A, 0,3W, 300MHz	BC 308, BC 558, BF 324, BF 414, BF 939
15245	2SA1324	50V, 0,15A, >80MHz	BC 856R...857R, BCW 69...70R, BCW 89R
15246	2SA1325	120V, 0,1A, 100MHz	2SA1312
15247	2SA1326	35V, 0,5A, 200MHz	BC 807R, BCW 68R, BCX 17R, 2SA1313
15248	2SA1327	50V, 10A, 20W, 50MHz	2SA1471, 2SA1567...68
15249	2SA1328	60V, 12A, 40W, 70MHz	2SB903
15250	2SA1329	2SA1328, 80V, 50MHz	2SA1329
15251	2SA133	9V, 10mA, 40MHz	AF 124...127, AF 200, 2SA218...227
15252	2SA1330	150/1500ns	BFN 25, BFN 27
15253	2SA1331	60V, 0,15A, 100MHz, 160/390ns	BC 856, BCW 89, BSR 15...16, 2SA1338
15254	2SA1332	160V, 1,5A, 20W, 200MHz	2SA1306(A,B), 2SA1606



15255	2SA1333	200V, 15A, 150W, 30MHz	2SA1169...1170, 2SA1295, 2SB756
15256	2SA1334	30V, 0,8A, 0,6W, 120MHz	BC 327...328, BC 636, 2SB909...910
15257	2SA1335	120V, 0,1A, 0,2W, 100MHz	2SA970, 2SA1038, 2SA1049, 2SA1136...37
15258	2SA1336	20V, 2A, 0,7W, 80MHz	MPS 750, 2SA1382, 2SB738...739, 2SB892
15259	2SA1337	55V, 0,1A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 557
15260	2SA1338	2SA1339, SMD	BSR 15...16, BSS 80, BSS 82
15261	2SA1339	70/450ns	BSW 24, 2N2906...07(A), 2N4026...29
15262	2SA134	20V, 10mA, 140MHz	AF 124...125, AF 106, AF 306, 2SA213...216
15263	2SA1340	55V, 0,1A, 0,4W, 200MHz	BC 212, BC 257, BC 307, BC 557
15264	2SA1341	2SA1345, SMD	DTA 144EK, FN 1L4M, RN 2404, UN 2113
15265	2SA1342	2SA1346, SMD	DAT 144EK, FN 1F4M, RN2403, UN 2112
15266	2SA1343	2SA1347, SMD	DTA 144WK, FN 1L4L, RN 2409, UN 211E
15267	2SA1344	2SA1348, SMD	DTA 114EK, FN 1A4M, RN 2402, UN 2111
15268	2SA1345	200MHz	AN 1L4M, DTA 144ES, RN 2004, UN 4113
15269	2SA1346	200MHz	AN 1F4M, DTA 124ES, RN 2003, UN 4112
15270	2SA1347	0,1A, 200MHz	AN 1L4L, DTA 144WS, RN 2009, UN 411E
15271	2SA1348	200MHz	AN 1A4M, DTA 114ES, RN 2002, UN 4111
15272	2SA135	20V, 10mA, 150MHz	AF 124...125, AF 106, AF 306, 2SA213...216
15273	2SA1350	40V, 0,1A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 557
15274	2SA1351	2SA1350, 0,4W	BC 212, BC 257, BC 307, BC 557
15275	2SA1352	200V, 0,1A, 5W, 70MHz	2SA1380...81, 2SA1406...07
15276	2SA1353	2SA1352, 300V	2SA1381, BF 418
15277	2SA1354	2SA1352, 400V	2SB1011
15278	2SA1355	70V, 4A, 30W, 40MHz	BD 244A, BD 538, BD 540B, 2SA1289
15279	2SA1356	40V, 0,8A, 5W, 100MHz	2SB1144, BD 136, BD 227, BD 376
15280	2SA1357	35V, 5A, 10W, 170MHz	2SA1120
15281	2SA1358	120V, 1A, 10W, 120MHz	2SB1144, 2SA1178, 2SA1184, 2SA1220(A)
15282	2SA1359	40V, 3A, 10W, 100MHz	2SB1143, BD 786, MJE 250...252, 2SA1217
15283	2SA136	6V, 10mA, 10MHz	AF 124...126, AF 200, 2SA218...227
15284	2SA1360	150V, 0,05A, 5W, 200MHz	2SA1477...78, 2SA1540, BF 418, BF 470
15285	2SA1361	250V, 0,05A, 80MHz	2SA1479...80, BF 416, BF 418, BF 470
15286	2SA1362	15V, 0,8A, 120MHz	BCW 67...68, 2SA1298
15287	2SA1363	20V, 2A, 80MHz	2SA1314, 2SA1369, 2SB1121
15288	2SA1364	60V, 1A, 85MHz	2SA1681, 2SB1115, 2SB1122...1123
15289	2SA1365	25V, 0,7A, 180MHz	BCW 67...68, 2SA1298, 2SA1621
15290	2SA1366	55V, 0,4A, 150MHz	BCW 68, BCX 42, 2SB1198
15291	2SA1367	50V, 0,1A, 0,3W, 100MHz	BC 212, BC 257, BC 307, BC 557
15292	2SA1368	100V, 0,5A, 130MHz	2SA1201, 2SB789(A), 2SB805...806
15293	2SA1369	30V, 1,5A, 90MHz, B>400	2SA1314, 2SB1121
15294	2SA137	6V, 10mA, 5MHz	AF 124...127, AF 200, 2SA218...227
15295	2SA1370	200V, 0,1A, 1W, 150MHz	BF 423A, BF 436...437, 2SA1024, 2SA1251
15296	2SA1371	2SA1370, 300V	BF 421A, BF 437, 2SA1024, 2SA1251
15297	2SA1372	2SA1370, 400V	2SA1251, 2SA1584, 2SA1760
15298	2SA1373	60V, 0,2A, 0,4W, 250MHz	BC 212, BC 256, BC 266, BC 556
15299	2SA1373	60V, 0,2A, 0,4W, 250MHz	BC 212, BC 256, BC 266, BC 556

15300	2SA1374	55V, 0,1A, 0,3W, 250MHz	BC 212, BC 256, BC 266, BC 556
15301	2SA1375	250V, 0,07A, 10W, 80MHz	2SA1700, BF 416, BF 616, BF 848...849
15302	2SA1376(A)	200V, 0,1A, 0,75W, 120MHz	BF 423, BF 436...437, 2SA1370...1372
15303	2SA1377	55V, 0,1A, 0,3W, 150MHz	BC 212, BC 256, BC 266, BC 556
15304	2SA1378	35V, 0,5A, 0,3W, 200MHz	BC 327...328, BC 636, 2SA1515, 2SB910
15305	2SA1379	600V, 0,8A, 10W	2SA1413, 2SA1807
15306	2SA138	15MHz	ASY 26...27, ASY 48
15307	2SA1380	200V, 0,1A, 7W, 150MHz	2SC1352...53, 2SA1406...07
15308	2SA1381	2SA1380, 300V	2SA1353...54
15309	2SA1382	50V, 2A, 0,9W, 110MHz	2SA1315, 2SB892, 2SB1312
15310	2SA1383	180V, 0,1A, 10W, 180MHz	2SA1476, BF 616, BF 848...849, BF 760
15311	2SA1384	300V, 0,1A, 70MHz	BFN 19
15312	2SA1385	60V, 5A, 10W	2SA1244, 2SA1401, 2SB1203...04
15313	2SA1386	160V, 15A, 130W, 40MHz	2SA1294
15314	2SA1386A	2SA1386, 180V	2SA1294
15315	2SA1387	60V, 5A, 20W, 80MHz	2SA1307, 2SA1469, 2SA1293
15316	2SA1388	100V, 5A, 25W, 60MHz	2SA1741...42, 2SA1293
15317	2SA1389	160V, 12A, 120W, 30MHz	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
15318	2SA139	8MHz	ASY 26...27, ASY 48
15319	2SA1390	35V, 0,5A, 0,3W, 120MHz	BC 327...328, BC 636, 2SA1515, 2SB910
15320	2SA1391	2SA1392	BC 416, BC 560, 2SA970, 2SA1136...1137
15321	2SA1392	60V, 0,2A, 0,4W, 200MHz	BC 212, BC 256, BC 266, BC 556
15322	2SA1393	120V, 1,5A, 20W, 180MHz	2SA1306(A,B), 2SA1332, 2SA1606
15323	2SA1394	80V, 5A, 25W	2SA1469, 2SB1016, 2SB1294
15324	2SA1395	100V, 2A, 15W	2SA1440, 2SB1095, 2SB1338
15325	2SA1396	100V, 10A, 30W	2SA1443, 2SA1652, BD 712, BD 744C
15326	2SA1397	400V, 2A, 15W	2SA1501, 2SA1009A, 2SA1236
15327	2SA1398	25V, 0,7A, 0,9W, 180MHz	2SA966, 2SA1382, 2SB978, 2SB1041
15328	2SA1399	55V, 0,4A, 0,9W, 150MHz	BC 638, 2N5400...01, 2SA965, 2SA1533
15329	2SA14	16V, 15mA, 4MHz	AF 124...127, AF 200, 2SA201...203
15330	2SA1400	400V, 0,5A, 10W, <1/6µs	2SA1379, 2SA1413
15331	2SA1401	60V, 5A, 10W	2SA1385, 2SB1203...04, 2SB1244, BD244A
15332	2SA1402	80V, 0,3A, 8W, 700MHz	2SA1405
15333	2SA1403	80V, 0,5A, 10W, 800MHz	-
15334	2SA1404	120V, 0,2A, 8W, 500MHz	2SA1405
15335	2SA1405	120V, 0,3A, 8W, 500MHz	-
15336	2SA1406	200V, 0,1A, 7W, 400MHz	2SA1352, 2SA1407
15337	2SA1407	200V, 0,15A, 7W, 400MHz	-
15338	2SA1408	150V, 1,5A, 10W, 50MHz	2SA1507, 2SA1249, 2SB649
15339	2SA1409	25V, 0,15A, 0,25W, B1000	2SA1436, BC 213, BC 308, BC 558
15340	2SA141	15V, 15mA, 4MHz	AF 124...127, AF 200, 2SA201...203
15341	2SA1410	2SA1409	2SA1436, BC 213, BC 308, BC 558
15342	2SA1411	2SA1409, SMD	BC 856...858, BCW 29...30, BCW 69...70
15343	2SA1412	400/400V, 2A, 10W, 40MHz	2SA1773
15344	2SA1413	600/600V, 1A, 10W, 28MHz	2SA1379, 2SA1807



15345	2SA1415	180V, 0,14A, 150MHz	BFN 17, BFN 19
15346	2SA1416	120V, 1A, 120MHz	2SA1419, 2SB1025...1028
15347	2SA1417	120V, 2A, 120MHz	2SA1419, 2SB1027...28
15348	2SA1418	180V, 0,7A, 120MHz	2SA1419, 2SB1027...1028
15349	2SA1419	180V, 1,5A, 120MHz	2SB1027...28
15350	2SA142	15V, 15mA, 8MHz	AF 124...126, AF 200, 2SA201...203
15351	2SA1420	2SA1345, 0,4W	2SA1345
15352	2SA1421	2SA1346, 0,4W	2SA1346
15353	2SA1422	2SA1347, 0,4W	2SA1347
15354	2SA1423	2SA1348, 0,4W	2SA1348
15355	2SA1424	20V, 0,05A, 4GHz	BFT 93
15356	2SA1425	120V, 0,8A, 1W, 120MHz	2SA965, 2SA1013, 2SA1319, 2SA1768
15357	2SA1426	35V, 0,8A, 1W, 120MHz	BC 327, BC 636, 2SB909...910
15358	2SA1427	30V, 1,5A, 1W, 120MHz	MPS750, 2SA966, 2SB819, 2SB892, 2SB978
15359	2SA1428	50V, 2A, 1W, 100MHz	MPS 750...751, 2SB892, 2SB1433...34
15360	2SA1429	80V, 2A, 1W, 80MHz	MPS 751, 2SA1315, 2SB1459
15361	2SA142A	2SA142, 40V	2SA102...104
15362	2SA143	15V, 15mA, 15MHz	AF 124...126, AF 200, 2SA202
15363	2SA1430	20V, 2A, 1W, 140MHz	MPS 750, 2SB733, 2SB738...739, 2SB892
15364	2SA1431	35V, 5A, 1W, 170MHz	2SB1446
15365	2SA1432	300V, 0,1A, 1W, 60MHz	BF 421A, BF 437, BF 493, 2SA1624
15366	2SA1433	70V, 0,05A, 0,9W, 700MHz	-
15367	2SA1434	60V, 0,1A, B>500	-
15368	2SA1435	30V, 0,3A, B>500	-
15369	2SA1436	60V, 0,2A, B>500	-
15370	2SA1437	120V, 0,05A,85MHz,B>400	-
15371	2SA1438	30V, 1,2A, B>500	-
15372	2SA144	15V, Ueb10V, 10mA, 15MHz	AF 124...126, AF 200, 2SA202
15373	2SA1440	100V, 3A, 15W, <300/1800ns	2SA1388, 2SA1441, 2SA1741
15374	2SA1441	100V, 5A, 25W, <300/1800ns	2SA1388, 2SA1442, 2SA1741
15375	2SA1442	100V, 7A, 30W, <300/1800ns	2SA1443, 2SA1742
15376	2SA1443	100V, 10A, 30W, <300/1800ns	2SA1444, 2SA1743
15377	2SA1444	100V, 15A, 30W, <300/1800ns	2SA1744
15378	2SA145	15V, Ueb10V, 10mA, 6MHz	AF 124...126, AF 200, 2SA201...203
15379	2SA1450	100V, 0,5A, 0,6W, 120MHz	BC 640, 2SA965, 2SB647, 2SA1683
15380	2SA1451	300/1200ns	2SA1568, 2SA1771
15381	2SA1452	300/1500ns	2SA1771
15382	2SA1453	50V, 0,1A, 0,2W, 200MHz	BC 212, BC 257, BC 307, BC 557
15383	2SA1455K	120V, 0,05A, 140MHz	2SA1312, 2SA1587
15384	2SA1458	40V, 0,2A, 0,25W, <70/300ns	2N3250...51, 2N3905...06
15385	2SA1459	15V, 0,05A, 0,25W, <20/40ns	2N4258, 2N4313, 2N5056...57
15386	2SA146	20V, 10mA, 20MHz	AF 124...127, AF 200, 2SA218...227
15387	2SA1460	60V, 1A, 1W, <40/100ns	-
15388	2SA1461	2SA1458, SMD	-
15389	2SA1462	2SA1459, SMD	-

15390	2SA1463	2SA1460, SMD	-
15391	2SA1464	60V, 0,5A, <35/225ns	-
15392	2SA1465	30V, 1A, 0,75W, <1/2µs	-
15393	2SA1466	2SA1465, 0,35W	-
15394	2SA1467	2SA1465, SMD	-
15395	2SA1468	180V, 0,1A, 200MHz	BFN 25, 2SA1257, 2SA1330
15396	2SA1469	80V, 5A, 20W, 100/600ns	2SA1388, 2SA1441, 2SA1741
15397	2SA147	20V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
15398	2SA1470	80V, 7A, 25W, 100/600ns	2SA1452, 2SA1442, 2SA1742
15399	2SA1471	80V, 10A, 30W, <100/900n	2SA1443, 2SA1743
15400	2SA1474	80V, 0,8A, 15W, 800MHz	-
15401	2SA1475	120V, 0,4A, 15W, 500MHz	-
15402	2SA1476	200V, 0,2A, 15W, 400MHz	-
15403	2SA1477	180V, 0,14A, 10W, 150MHz	2SA1541, 2SA1801, BF 416, BF 418
15404	2SA1478	200V, 0,1A, 5W, 150MHz	2SA1540...41, 2SA1380...81, 2SA1406...07
15405	2SA1479	300V, 0,1A, 7W, 70MHz	2SA1353, 2SA1381
15406	2SA148	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
15407	2SA1480	300V, 0,1A, 7W, 150MHz	2SA1353, 2SA1381
15408	2SA1481	<360/1170ns	BC 212, BC 256, BC 556, 2N2906...07
15409	2SA1482	150V, 0,05A, 0,85W	2SA1016K, 2SA1124
15410	2SA1483	60V, 0,2A, 200MHz	-
15411	2SA1484	90V, 0,1A, 130MHz	2SA1312
15412	2SA1485	200V, 0,1A, 0,2W, 160MHz	BF 421A, BF 436...437, 2SB1349
15413	2SA1486	<500/5500ns	2SA1379, 2SA1413
15414	2SA1487	85V, 0,05A, 1W, 500MHz	-
15415	2SA1488A	2SA1488, 80V	2SA1469, 2SB1018
15416	2SA1489	80V, 6A, 60W, 20MHz	BD 246C, BD 546C, 2SB688, 2SB776
15417	2SA149	20V, 10mA, 50MHz	AF 124...126, AF 200, 2SA218...227
15418	2SA1490	120V, 8A, 80W, 20MHz	BD 246D, BD 546D, 2SB688, 2SB816
15419	2SA1491	140V, 10A, 100W, 20MHz	BD 246D, 2SA1386(A), 2SA1294, 2SB817
15420	2SA1492	180V, 15A, 130W, 20MHz	BD 250E, 2SA1386A, 2SA1294
15421	2SA1493	200V, 15A, 150W, 20MHz	2SA1169...1170, 2SA1333, 2SB756
15422	2SA1494	200V, 17A, 200W, 20MHz	2SA1170, 2SA1295
15423	2SA1495	400/400V, 0,6A, 15W, 15MHz	2SA1400
15424	2SA1496	2SA1497, SMD	FN 1A4Z, DTA 124TK, KSR 2110, UN 2117
15425	2SA1497	Rb10kOhm	AN 1A4Z, DTA 114TS, RN 2011, UN 4115
15426	2SA1498	2SA1495, 25W	-
15427	2SA1499	2SA1495, 25W	2SA1397, 2SA1614
15428	2SA15	16V, Ueb0,5V, 15mA, 12MHz	AF 124...126, AF 200, 2SA202
15429	2SA1500	400/400V, 5A, 40W, 15MHz	MJE 5851...5852
15430	2SA1501	2SA1500	-
15431	2SA1502	2SA1503, SMD	DTA 123YK, UN211H
15432	2SA1503	200MHz	DTA 123YS, UN 411H
15433	2SA1504	50V, 0,15A, 130MHz	-
15434	2SA1505	35V, 0,5A, 200MHz	-

15435	2SA1506	120V, 0,1A, 100MHz	-
15436	2SA1507	180/160V, 1,5A, 10W, 120MHz	2SA1249, 2SB649
15437	2SA1508	2SA1509, SMD	DTA 144TK, FN 1L4Z, KSR 2112, UN 2110
15438	2SA1509	Rb47kOhm	AN 1L4Z, DTA 144TS, KSR 2012, UN4110
15439	2SA151	9V, 15mA, 6MHz	AF 124...127, AF 200, 2SA201...203
15440	2SA1510	2SA1511, SMD	DTA 143TK, FN 1L3Z, RN 2410, UN 2116
15441	2SA1511	Rb4,7kOhm	AN 1L3Z, DTA 143TS, RN 2010, UN 4116
15442	2SA1512	2SA1128, 0,3W	2SA1128
15443	2SA1513	100V, 15A, 60W, <300/1800ns	-
15444	2SA1514	120V, 0,05A, 140MHz	2SA1325
15445	2SA1514K	2SA1514	2SA1312, 2SA1566
15446	2SA1515(S)	40V, 1A, 0,5(S0,3)W, 150MHz	BC 636, 2SB734, 2SB909, 2SB1116
15447	2SA1515(S)	40V, 1A, 0,5(S0,3)W, 150MHz	BC 636, 2SB734, 2SB909, 2SB1116
15448	2SA1516	180V, 12A, 130W, 25MHz	2SA1294, 2SA1386A, 2SA1492
15449	2SA1517	120V, 0,1A, 100MHz	-
15450	2SA1518	2SA1522, SMD	DTB 114EK, UN 2123
15451	2SA1519	2SA1523, SMD	DTB 143EK, UN 2122
15452	2SA152	9V, 15mA, 10MHz	AF 124...126, AF 200, 2SA201...202
15453	2SA1520	2SA1524, SMD	DTB 123YK, UN 2124
15454	2SA1521	2SA1525, SMD	DTB 123EK, UN 2121
15455	2SA1522	0,3W, 200MHz	DTB 114ES, RN 2224, UN 4123, 2SA1526
15456	2SA1523	0,3W, 200MHz	DTB 143ES, RN 2223, UN 4122, 2SA1527
15457	2SA1524	200MHz	DTB 123YS, RN 2227, UN 4124, 2SA1528
15458	2SA1525	0,3W, 200MHz	DTB 123ES, RN 2222, UN 4121, 2SA1529
15459	2SA1526	2SA1522, 0,6W	2SA1522
15460	2SA1527	2SA1523, 0,6W	2SA1523
15461	2SA1528	2SA1524, 0,6W	2SA1524
15462	2SA1529	2SA1525, 0,6W	2SA1525
15463	2SA153	15V, 4mA, 60MHz	AF 124...126, AF 200, 2SA218...227
15464	2SA1530	50V, 0,1A, 200MHz	BC 856...857, BCW 69...70, BCW 89
15465	2SA1531	2SA1034	2SA1603, 2SA1611, 2SA1576
15466	2SA1531A	2SA1035	2SA1603, 2SA1611, 2SA1576
15467	2SA1532	2SA1022	BC 859W...860W
15468	2SA1533	80V, 0,5A, 1W, 85MHz	2SA965, 2SB987, 2SB1041, 2SB1297
15469	2SA1534	30V, 1A, 1W, 200MHz	2SA966, 2SB764, 2SB892, 2SB978
15470	2SA1534A	2SA1534, 60V	2SA1315, 2SB647, 2SB764, 2SB1041
15471	2SA1535	150V, 1A, 15W, 200MHz	2SA1306(A,B), 2SA1606, 2SA1332
15472	2SA1535A	2SA1535, 180V	2SA1306, 2SA1606, 2SA1859A
15473	2SA1536	80V, 0,3A, 8W, 600MHz	2SA1402
15474	2SA1537	80V, 0,5A, 10W, 700MHz	2SA1403
15475	2SA1538	120V, 0,2A, 8W, 400MHz	2SA1404
15476	2SA1539	120V, 0,3A, 8W, 400MHz	2SA1405
15477	2SA154	15V, 4mA, 50MHz	AF 124...127, AF 200, 2SA218...227
15478	2SA1540	200V, 0,1A, 7W, 300MHz	2SA1478, 2SA1352, 2SA1406
15479	2SA1541	200V, 0,2A, 7W, 300MHz	2SA1407

15480	2SA1542	60V, 0,15A, 0,3W, 140MHz	BC 212, BC 256, BC 556, 2SB725
15481	2SA1543	2SA1542	BC 212, BC 256, BC 556, 2SB725
15482	2SA1544	250V, 0,1A, 0,75W, 300MHz	BF 421A, BF 436...437, BF 492...493
15483	2SA1545	2SA1544, 1W	BF 421A, BF 436...437, BF 492...493
15484	2SA1546	2SA1544, 7W	BF 418, 2SA1353, 2SC1381
15485	2SA1547	2SA933	2SA933
15486	2SA1548	2SA854, 0,3W	2SA854
15487	2SA1549	2SA790M	2SA790
15488	2SA155	15V, 4mA, 55MHz	AF 124...127, AF 200, 2SA218...227
15489	2SA1550	400/400V, 0,5A, 15W, 20MHz,	2SA1400, 2SA1498
15490	2SA1552	180V, 1,5A, 15W, 120MHz	2SB768, 2SB840...842
15491	2SA1553	230/230V, 15A, 150W, 25MHz	-
15492	2SA1554	2SA785	2SA785
15493	2SA1555	2SA790	2SA790
15494	2SA1556	2SA802	2SA802
15495	2SA1557	2SA805	2SA805
15496	2SA1558	2SA806	2SA806
15497	2SA1559	2SA854, 0,3W	2SA854
15498	2SA156	15V, 4mA, 55MHz	AF 124...127, AF 200, 2SA218...227
15499	2SA1560	2SA881	2SA881
15500	2SA1561	2SA933	2SA933
15501	2SA1562	30V, 1,2A, B>500	-
15502	2SA1563	2SA1564, SMD	DTA 114YK, FN 1A4P, RN 2407, UN 2114
15503	2SA1564	Rbe47kOhm	AN 1A4P, DTA 114YS, RN 2007, UN 4114
15504	2SA1565	2SA1564	2SA1564
15505	2SA1566	120V, 0,1A, 130MHz	2SA1312, 2SA1566
15506	2SA1567	50V, 12A, 35W, 40MHz	2SA1451...52, 2SA1444, 2SA1600...01
15507	2SA1568	2SA1567, 60V, +-12A	2SA1451...52, 2SA1444, 2SA1600...01
15508	2SA157	15V, 4mA, 65MHz	AF 124...126, AF 200, 2SA218...227
15509	2SA1571	2SA1572, SMD	DTA 144GK
15510	2SA1572	50V, 0,1A, 0,3W, Rbe47kOhm	DTA 144GS
15511	2SA1573	2SA1574, SMD	DTA 124GK
15512	2SA1574	50V, 0,1A, 0,3W, Rbe22kOhm	DTA 124GS
15513	2SA1575	200V, 0,1A, 400MHz	BFN 17, BFN 19
15514	2SA1576	2SA1037	2SA1586, 2SA1603, 2SA1622
15515	2SA1577	2SA1036	BCX 51
15516	2SA1578	120V, 0,05A, 140MHz	2SA1587
15517	2SA1579	2SA1514	2SA1609, 2SA1612, 2SB1220
15518	2SA1580	70V, 0,05A, 700MHz	-
15519	2SA1581	2SA1582, SMD	-
15520	2SA1582	Rb2,2kOhm	-
15521	2SA1583	600/550V, 0,1A, <1/4,5µs	-
15522	2SA1584	400/400V, 0,1A, 0,9W, <1/4µs	2SA1372, 2SA1584, 2SA1760, 2SB1363
15523	2SA1585(S)	20V, 2A, 0,4W, 240MHz	2SB738...739, 2SB822, 2SB892, 2SB911
15524	2SA1586	50V, 0,15A, 150MHz	-

15525	2SA1587	120V, 0,1A, 100MHz	2SA1578
15526	2SA1588	35V, 0,5A, 200MHz	2SA1577
15527	2SA1589	2SA1590, SMD	FN 1F4Z, DTA 124TK, KSR 2111, UN 2117
15528	2SA159	15V, 4mA, 55MHz	AF 124...126, AF 200, 2SA218...227
15529	2SA1590	Rb22kOhm	AN 1F4Z, DTA 124TS, KSR 2011, UN 4117
15530	2SA1591	Rbe47kOhm	DTA 143ZS, KSR 2014, RN 2006, 2SA1616
15531	2SA1592	120V, 1A, 10W, 120MHz	2SA1592, 2SB844...845, 2SB959...960
15532	2SA1593	120V, 2A, 15W, 120MHz	2SB1215...16
15533	2SA1594	50V, 0,1A, 140MHz	BC 856W...857W, 2SA1576, 2SA1586
15534	2SA1595	50V, 0,1A, 140MHz	BC 856...857, BCW 69...70, 2SA1311
15535	2SA1596	80V, 2A, 1,2W, <1/4μs	2SA1315, 2SA1429, 2SB1459
15536	2SA1597	2SA1591, SMD	DTA 143ZK, KSR 2114, RN 2406
15537	2SA1598	60V, 7A, 25W, <300/2000ns	2SA1442, 2SA1470, 2SA1742
15538	2SA1598	60V, 7A, 25W, <300/2000ns	2SA1442, 2SA1470, 2SA1742
15539	2SA1599	60V, 10A, 25W, <300/2000ns	2SA1443, 2SA1471, 2SA1743
15540	2SA1599	60V, 10A, 25W, <300/2000ns	2SA1443, 2SA1471, 2SA1743
15541	2SA15H	2SA15, Ueb12V	-
15542	2SA16	12V, 15mA, 12MHz	AF 124...126, AF 200, 2SA202
15543	2SA160	15V, 4mA, 55MHz	AF 124...126, AF 200, 2SA218...227
15544	2SA1600	60V, 12A, 30W, <300/2000ns	2SA1451...52, 2SA1568
15545	2SA1600	60V, 12A, 30W, <300/2000ns	2SA1451...52, 2SA1568
15546	2SA1601	60V, 15A, 45W, <300/2000ns	2SA1444, 2SA1744
15547	2SA1601	60V, 15A, 45W, <300/2000ns	2SA1444, 2SA1744
15548	2SA1602	2SA1235	2SA1586, 2SA1622
15549	2SA1603	2SA1530	2SA1576, 2SA1586, 2SA1611
15550	2SA1605	>50MHz	BF 616, BF 618, BF 760...762, BF 848
15551	2SA1606	180/160V, 1,5A, 15W, 100MHz	2SA1306A,B, 2SA1859A
15552	2SA1607	40V, 0,15A, <40/205ns	-
15553	2SA1608	60V, 0,5A, <35/225ns	-
15554	2SA1609	160V, 0,05A, 80MHz	-
15555	2SA161	20V, 15mA, 500MHz	AF 139, AF 239(S)
15556	2SA1610	15V, 0,05A, <20/40ns	2SA1763
15557	2SA1611	60V, 0,1A, 180MHz	2SB1218A
15558	2SA1612	120V, 0,05A, >50MHz	2SA1578...79, 2SB1220
15559	2SA1613	25V, 0,15A, 200MHz, B>500	-
15560	2SA1614	400/400V, 0,5A, 25W, 20MHz	2SA1397, 2SA1499
15561	2SA1615(Z)	80/520ns	2SA1834
15562	2SA1616	2SA1591	DTA 143ZS, KSR 2014, RN 2006, 2SA1591
15563	2SA1617	55V, 0,1A, 280MHz	BC 856...857, BCW 69...70, 2SA1311
15564	2SA1618	50V, 0,15A, >80MHz	-
15565	2SA1619	30V, 0,5A, 1W, 200MHz	BC 636, 2SA1382, 2SB910, 2SB987
15566	2SA1619A	2SA1619, 60V	BC 638, 2SA1382, 2SA1705, 2SB910
15567	2SA162	20V, 15mA, 500MHz	AF 139, AF 239(S)
15568	2SA1620	80V, 0,3A, 100MHz	2SB1198
15569	2SA1621	35V, 0,8A, 120MHz	BCW 67...68, 2SB1197

15570	2SA1622	55V, 0,15A, 180MHz	2SA1586, 2SA1602, 2SA1611
15571	2SA1623	2SA1511	AN 1L3Z, DTA 143TS, RN 2010, UN 4116
15572	2SA1624	300/300V, 0,1A, 0,5W, 70MHz	BF 421A, BF 436...437, 2SA1371...72
15573	2SA1625	400/400V, 0,5A, 0,75W, <1/6µs	2SB1074, 2SB1488
15574	2SA1626	400/400V, 2A, 1W, <0,5/2,7µs	2SA1786, 2SA1412
15575	2SA1627	600/600V, 1A, 1W, <0,5/5,5µs	2SA1379, 2SA1413
15576	2SA1628	30V, 0,1A, 280MHz	BC 856W...858W, 2SC1603, 2SB1218(A)
15577	2SA1629	55V, 0,1A, 230MHz	BC 856W...857W, 2SC1603, 2SB1218A
15578	2SA163	20V, 15mA, 500MHz	AF 139, AF 239(S)
15579	2SA1630	2SA1530, 0,3W	BC 212, BC 257, BC 307, BC 557
15580	2SA1633	150V, 10A, 100W, 20MHz	BD 246D, 2SA1186, 2SA1386, 2SB817
15581	2SA1634	80V, 4A, 40W, 12MHz	BD 244B, BD 538, BD 540B, BD 952
15582	2SA1635	2SA1634, 30W	2SA1394, 2SA1441, 2SB1095, BD 244B
15583	2SA164	20V, 15mA, 500MHz	AF 139, AF 239(S)
15584	2SA1640	30V, 7A, 40W, <1/3,5µs	2SA1290...91, 2SB896(A), 2SB919
15585	2SA1640	30V, 7A, 40W, <1/3,5µs	2SA1290...91, 2SB896(A), 2SB919
15586	2SA1641	25V, 8A, 15W, <300/950ns	2SA1615, 2SA1834
15587	2SA1643	50V, 7A, 25W, 75MHz	2SA1327, 2SA1470...1471
15588	2SA1644	150V, 5A, 30W, <300/1900ns	2SA1645, 2SA1646
15589	2SA1644Z	2SA1644	-
15590	2SA1645	150V, 7A, 35W, <300/1900ns	2SA1646
15591	2SA1645Z	2SA1645	-
15592	2SA1646	150V, 10A, 40W, <300/1900ns	-
15593	2SA1646Z	2SA1646	-
15594	2SA1647	150V, 5A, 18W, <300/1900ns	-
15595	2SA1648	100V, 5A, 18W, <300/1800ns	-
15596	2SA1649(Z)	40V, 10A, 15W, <300/1800ns	2SB935(A), 2SB 936(A)
15597	2SA165	20V, 15mA, 500MHz	AF 139, AF 239(S)
15598	2SA1650	2SA1644, , 25W	2SA1651, 2SA1652
15599	2SA1651	2SA1645, , 25W	2SA1652
15600	2SA1652	2SA1646, , 30W	-
15601	2SA1653	2SA1654, SMD	FN 1L3N, DTA 143XK, KSR 2105, UN 211F
15602	2SA1654	Rbe10kOhm	AN 1L3N, DTA 143XS, KSR 2005, UN 411F
15603	2SA1655	2SA1656, SMD	FN 1L3M, DTA 143EK, RN 2401, UN 211L
15604	2SA1656	RbRbe4,7kOhm	AN 1L3M, DTA 143ES, RN 2001, UN 411L
15605	2SA1657	150V, 1,5A, 20W, 4MHz	2SA1304, 2SA1306, 2SA1606, 2SB1096
15606	2SA1658	30V, 3A, 15W, 100MHz	2SA1305, 2SA1307, 2SA1440, 2SB1274
15607	2SA1659	160V, 1,5A, 20W, 100MHz	2SA1306A,B, 2SA1332, 2SA1606
15608	2SA166	20V, 15mA, 500MHz	AF 139, AF 239(S)
15609	2SA1660	150V, 0,05A, 120MHz	2SA1200, 2SB807
15610	2SA1661	120V, 0,8A, 120MHz	2SA1201, 2SB806, 2SB1025...26
15611	2SA1662	80V, 0,4A, 120MHz	2SA1202, 2SB767
15612	2SA1663	30V, 1,5A, 120MHz	2SA1314, 2SB1121, 2SB1313
15613	2SA1664	35V, 0,8A, 120MHz	BCX 51...53, 2SA1204, 2SA1364, 2SA1734
15614	2SA1666	20V, 0,2A, 35/70ns	-



15615	2SA1667	150/150V, 2A, 25W, 20MHz	2SA1304, 2SA1306, 2SA1606, 2SB1338
15616	2SA1668	2SA1667, 200/200V	2SA1306B, 2SB1096, 2SB1530
15617	2SA1669	20V, 50mA, 3000MHz	BFR 194, 2SA1424
15618	2SA167	9MHz	ASY 26...27, ASY 48
15619	2SA1670	80/80V, 6A, 60W, 20MHz	2SA1803, 2SA1907
15620	2SA1671	120/120V, 8A, 75W, 20MHz	2SA1804, 2SA1908
15621	2SA1672	140/140V, 10A, 80W, 20MHz	2SA1805, 2SA1909
15622	2SA1673	180/180V, 15A, 85W, 20MHz	2SA1294, 2SA1386A, 2SA1492, 2SA1516
15623	2SA1674	80V, 1A, 1W, 120MHz	BC 640, 2SB1130, 2SB1236, 2SB1437
15624	2SA1676	RbRbe47kOhm	DTA 144EU
15625	2SA1677	RbRbe22kOhm	DTA 142EU
15626	2SA1678	RbRbe10kOhm	DTA 114EU
15627	2SA1679	60V, 5A, 10W, <300/2000ns	2SA1307, 2SA1469, 2SA1741
15628	2SA1679	60V, 5A, 10W, <300/2000ns	2SA1307, 2SA1469, 2SA1741
15629	2SA168(A)	2SA167, 0,175W	ASY 26...27, ASY 48
15630	2SA1680	60V, 2A, 0,9W, 100/400ns	2SA1315, 2SA1382, 2SB892, 2SB1312
15631	2SA1681	2SA1680, SMD	2SB1123...1124, 2SB1520
15632	2SA1682	300V, 0,05A, 70MHz	BF 821, BFN 27, 2SA1721
15633	2SA1683	0ns	2SA1683, 2SA1708
15634	2SA1684	120/120V, 1,5A, 20W, 150MHz	2SA1306(A,B), 2SA1393, 2SA1332, 2SB1186
15635	2SA1685	20V, 0,15A, 400MHz	2SA1610, 2SA1763
15636	2SA1687	60V, 0,15A, 130MHz	2SA1252
15637	2SA1688	2SA1256	-
15638	2SA1689	300V, 0,05A, 0,5W, 70MHz	BF 421(A), BF 437, 2SA1371, 2SA1624
15639	2SA169	15MHz	ASY 26...27, ASY 48
15640	2SA1690	-/400V, 0,1A	2SA1740
15641	2SA1692	30V, 2A, 110MHz	-
15642	2SA1693	80/80V, 6A, 60W, 20MHz	BD 246B...F, 2SA1264, 2SB775...776
15643	2SA1694	120/120V, 8A, 80W, 20MHz	2SA1146, 2SA1186, 2SA1264, 2SB688
15644	2SA1695	140/140V, 10A,100W, 20MHz	BD 246D...F, 2SA1265, 2SA1645, 2SB817
15645	2SA1696	120V, 0,4A, 400MHz	2SA1475
15646	2SA1697	200/200V, 0,2A, 300MHz	2SA1476
15647	2SA1698	>50MHz	BF 418, BF 472, 2SA1353, 2SA1381
15648	2SA1699	400/400V, 0,2A, 0,6W, 70MHz	2SA1251, 2SA1625, 2SB1074, 2SB1488
15649	2SA17	12V, Ueb0,5V, 15mA, 19MHz	AF 124...127, AF 200, 2SA100, 2SA102
15650	2SA170	2SA169, 0,175W	ASY 26...27, ASY 48
15651	2SA1700	2SA1699, 10W	2SA1196, 2SA1233, 2SA1498
15652	2SA1701	15V, 1,5A, 0,9W, 300MHz	2SA966, 2SA1286, 2SA1703
15653	2SA1702	40/210ns	2SA1431, 2SB1288, 2SB1305...07, 2SB1319
15654	2SA1703	30V, 1,5A, 1W, 180MHz	2SB926...927, 2SB892, 2SB1229
15655	2SA1704	30V, 2,5A, 1W, 150MHz	2SB892, 2SB985, 2SB1433...34
15656	2SA1705	60V, 1A, 0,9W, 150MHz	2SA1708, 2SB1116, 2SB1437
15657	2SA1706	60V, 2A, 1W, 150MHz	2SA1315, 2SB892, 2SB1229
15658	2SA1707	60V, 3A, 1W, 150MHz	2SB985
15659	2SA1708	120V, 1A, 1W, 120MHz	2SB1456



15660	2SA1709	120V, 2A, 1W, 120MHz	-
15661	2SA171	8MHz	ASY 26...27, ASY 48
15662	2SA1710	300/300V, 0,1A, 1W, 70MHz	2SA1371
15663	2SA1711	20V, 0,03A, 0,2W, 15/110ns	2N4313, 2N5056...57
15664	2SA1712	2SA1711, SMD	BSR 12, 2SA1764
15665	2SA1714	100/100V, +-3A, 12W, B>2000	BD 680, BD 682, 2N6036
15666	2SA1715	B>2000	2SB1339
15667	2SA1715	B>2000	2SB1339
15668	2SA1716	B>4000	2SB1343
15669	2SA1716	B>4000	2SB1343
15670	2SA1717	B>4000	-
15671	2SA1717	B>4000	-
15672	2SA1718	2SA1715, , 20W	2SB1098, 2SB1430
15673	2SA1719	2SA1716, , 25W	2SB1099, 2SB1431
15674	2SA172	2SA171, 0,2A, 0,175W	ASY 26...27, ASY 48
15675	2SA1720	2SA1717, , 25W	2SB1432
15676	2SA1721	300V, 0,1A, 55MHz	BFN 27
15677	2SA1722	Rbe10kOhm	DTA 123YU
15678	2SA1723	30/20V, 0,3A, 1500MHz	-
15679	2SA1724	30V, 0,3A, 1500MHz	-
15680	2SA1725	2SA1726, , 30W	2SA1442, 2SA1470, 2SB1097, 2SB1290
15681	2SA1726	80V, 6A, 50W, 20MHz	BD 244B...F, BD 544B...C, BD 800, BD 810
15682	2SA1727(F5)	400/400V, 0,5A, 10W, 12MHz	2SA1400
15683	2SA1728	50V, 0,5A, 350MHz, 60/170ns	BSR 15...16, 2SA1338
15684	2SA1729	50V, 1,5A, 50/150ns	-
15685	2SA173	4MHz	ASY 26...27, ASY 48
15686	2SA1730	50V, 3A, 300MHz, 50/150ns	-
15687	2SA1731	50/150ns	-
15688	2SA1732	50/150ns	-
15689	2SA1733K	30V, 0,03A, >200MHz	BC 856...860, BF 550, 2SA1256
15690	2SA1734	40V, 1,2A, 100/300ns	2SA1681, 2SB1123
15691	2SA1735	60V, 1A, 100/350ns	2SA1681, 2SB1122...1123
15692	2SA1736	60V, 3A, 100/300ns	2SB1124
15693	2SA1737	2SA1487, SMD	-
15694	2SA1738	15V, 0,05A, 1500MHz, 12/20ns	BSR 12, 2SA1764
15695	2SA1739	2SA1738	2SA1610, 2SA1763
15696	2SA174	2SA173, 0,175W	ASY 26...27, ASY 48
15697	2SA1740	2SA1699, SMD	2SA1812
15698	2SA1741	2SA1441	2SA1441
15699	2SA1742	2SA1442	2SA1442
15700	2SA1743	2SA1443	2SA1443
15701	2SA1744	2SA1444	2SA1444
15702	2SA1745	20V, 0,5A, 400MHz	-
15703	2SA1746	70V, 12A, 60W, 25MHz	2SB1508...1509
15704	2SA1747	50V, 0,05A, 250MHz	BC 856...857, BF 550, 2SA1256

15705	2SA1748	2SA1747	BC 856W...857W, 2SA1603, 2SA1611
15706	2SA1749	200V, 0,3A, 10W, 400MHz	2SA1777
15707	2SA175	18V, 5mA, 85MHz	AF 124...126, AF 200, 2SA218...227
15708	2SA1750	140V, 0,5A, 10W, 500MHz	-
15709	2SA1751	2SA1749, 20W	-
15710	2SA1752	2SA1750, 20W	-
15711	2SA1753	2SA1745	2SA1298, 2SA1621
15712	2SA1755	<60/400ns	2SA965, 2SA1013, 2SA1275
15713	2SA1757	100V, 5A, 25W, 80MHz	2SA1388, 2SA1441, 2SA1741
15714	2SA1758	100V, 12A, 30W, 80MHz	2SA1444, 2SA1744
15715	2SA1759	2SA1760, SMD	2SA1740
15716	2SA176	18V, 5mA, 85MHz	AF 124...126, AF 200, 2SA218...227
15717	2SA1760	400/400V, 0,1A, 0,9W, 12MHz	2SA1372, 2SA1584, 2SB1363
15718	2SA1761	60V, 3A, 0,9W, 100MHz	2SA1707, 2SB985, 2SB1066
15719	2SA1762	2SA777	2SA777
15720	2SA1763	2SA1764	-
15721	2SA1764	15V, 0,2A, 1GHz, 11/21ns	-
15722	2SA1765	<25/60ns	-
15723	2SA1766	lo-sat, 30V, 0,3A	-
15724	2SA1767	300V, 0,07A, 0,75W, >50MHz	BF 421(A), BF 437, BF 486, 2SA1371
15725	2SA1768	180/160V, 0,7A, 1W, 60/960ns	2SA1319, 2SA1770
15726	2SA1769	2SA1768, 10W	2SA1507, 2SA1248...49
15727	2SA1770	180/160V, 1,5A, 1W, 40/740ns	2SB1212
15728	2SA1771	80V, 12A, 30W, 50MHz	-
15729	2SA1772	400/400V, 1A, 15W, 50MHz	2SA1379, 2SA1413, 2SA1807
15730	2SA1773	400/400V, 2A, 15W, 40MHz	2SA1412
15731	2SA1774	2SA1037	2SB1462
15732	2SA1774	2SA1037	2SB1462
15733	2SA1775	400/400V, 0,5A, 10W, 12MHz	2SA1156
15734	2SA1776	2SA1775	2SA1625, 2SB1074, 2SB1488
15735	2SA1777	250V, 0,3A, 10W, 400MHz	-
15736	2SA1778	15V, 50mA, 600MHz	BF 569, BF 579, BF 767
15737	2SA1779	50V, 0,1A, 0,4W, >200MHz	BC 556...557, 2N2906...07, 2SA1015
15738	2SA178	18V, 5mA	AF 124...126, AF 200, 2SA218...227
15739	2SA1780	2SA1775	2SA1625, 2SB1074, 2SB1488
15740	2SA1781	2SA1782, SMD	BC 856, BCW 89, 2SA1311
15741	2SA1782	55V, 0,15A, 0,3W, 180MHz	BC 212, BC 256, BC 556, 2SA1285(A)
15742	2SA1783	2SA1782, 0,5W	BC 212, BC 256, BC 556, 2SA1285(A)
15743	2SA1784	2SA1699, 1W	2SA1699
15744	2SA1785	400/400V, 1A, 1W, 50MHz	2SA1626
15745	2SA1786	400/400V, 2A, 1W, 40MHz	2SA1626
15746	2SA1787	200/200V, 0,1A, 1W, 150MH	2SA1370...71
15747	2SA1788	-/120V, 8A, 80W	2SA1672, 2SA1805, 2SA1909
15748	2SA1789	-/60V, 12A, 80W	2SA1909
15749	2SA1790	2SA1022	2SA1791

15750	2SA1790	2SA1022	2SA1791
15751	2SA1791	2SA1747	-
15752	2SA1791	2SA1747	-
15753	2SA1792	50V, 10A, 15W, 45MHz	-
15754	2SA1793	100/1100ns	2SA1244, 2SA1795, 2SB1203
15755	2SA1794	60MHz,200/1100ns	2SA1648
15756	2SA1795	60V, 5A, 10W, <300/2000ns	2SA1244, 2SA1385, 2SA1401, 2SB1203
15757	2SA1796	60V, 7A, 10W, <300/2000ns	2SB1204
15758	2SA1797	50/50V, 2A	2SA1681, 2SA1736, 2SB1123...24
15759	2SA1798	25V, 8A, 10W, 200MHz	-
15760	2SA1799	180V, 0,3A, 20W, 400MHz	S 3746
15761	2SA17H	2SA17, 16V, Ueb12V	-
15762	2SA18	21V, Ueb0,5V, 15mA, 19MHz	AF 124...127, AF 200, 2SA100, 2SA102
15763	2SA180	15V, Ueb15V, 10mA, 10MHz	AF 124...127, AF 200, 2SA202
15764	2SA1800	250V, 0,15A, 10W, 240MHz	S 3751
15765	2SA1801	2SA1799, 8W	2SA1749
15766	2SA1802	30V, 3A, 10W, 180MHz	2SB962, 2SB1202
15767	2SA1803	80V, 6A, 55W, 30MHz	2SA1670, 2SA1907, BD 246A...F
15768	2SA1804	120V, 8A, 70W, 30MHz	2SA1671, 2SA1908, BD 246C...F
15769	2SA1805	140V, 10A, 80W, 30MHz	2SA1672, 2SA1909, BD 246D...F
15770	2SA1806	2SA1738	-
15771	2SA1806	2SA1738	-
15772	2SA1807(F5)	600/600V, 1A, 10W, 200/2200ns	2SA1379, 2SA1413
15773	2SA1808	2SA1733K	BC 856W...860W, 2SB1218
15774	2SA1809	600/3700ns	2SA1400, 2SA1727
15775	2SA181	15V, Ueb15V, 10mA, 5MHz	AF 124...127, AF 200, 2SA201...203
15776	2SA1810	200/200V, 0,2A, 10W, 300MHz	2SA1407
15777	2SA1811	35V, 0,5A, 0,8W, 200MHz	2SA1533, 2SA1683, 2SB987, 2SB1297
15778	2SA1812	2SA1775, SMD	-
15779	2SA1813	2SA1814	-
15780	2SA1814	30V, 0,15A, 210MHz, B>500	-
15781	2SA1815	15V, 50mA, 750MHz	BF 569, BF579, BF 767
15782	2SA1816	150V, 0,05A, 0,3W, 200MHz	2SA1016K, 2SA1123...1124, 2SA1482
15783	2SA1818	-/32V, 1A, 0,9W	2SA1315, 2SB764, 2SB892, 2SB1041
15784	2SA1819	-/150V, 0,05A, 0,8W	BF 436, BF 423A, 2SA1281, 2SA1370
15785	2SA182	15V, Ueb15V, 10mA, 5MHz	AF 124...127, AF 200, 2SA201...203
15786	2SA1820	-/50V, 2A, 0,9W	2SA1315, 2SB892, 2SB1459
15787	2SA1821	-/20V, 50mA, 400MHz	-
15788	2SA1821	-/20V, 50mA, 400MHz	-
15789	2SA1822	400/400V, 1A, 25W, <1/6µs	2SA1397
15790	2SA1823	25V, 8A, 200MHz, 30/215ns	-
15791	2SA1824	60V, 5A, 130MHz, 50/470ns	-
15792	2SA1825	60V, 8A, 130MHz, 50/470ns	-
15793	2SA1826	120V, 3A, 130MHz, 100/850ns	-
15794	2SA1827	120V, 4A, 130MHz, 100/850ns	-

15795	2SA1828	2SA1352, 1,3W, 150MHz	2SA1380...81
15796	2SA1829	2SA1353, 1,5W, 150MHz	2SA1381
15797	2SA183	15V, Ueb15V, 10mA, 16MHz	AF 124...127, AF 200, 2SA202
15798	2SA1830	400/400V, 2A, 1,5W, 40MHz	-
15799	2SA1831	800/800V, 20mA, 25W, 10MHz	-
15800	2SA1832	50V, 0,15A, >80MHz	2SB1462
15801	2SA1832	50V, 0,15A, >80MHz	2SB1462
15802	2SA1833	B>4000	2SB1283...84
15803	2SA1834(F5)	30V, 10A, 10W, 150MHz	2SA1615
15804	2SA1835S	-/40V, 0,2A, 0,25W	BSW 24, 2N2906...07(A), 2SA1339
15805	2SA1836	60V, 0,1A, 0,2W, >50MHz	2SB1462
15806	2SA1836	60V, 0,1A, 0,2W, >50MHz	2SB1462
15807	2SA1837	230/230V, 1A, 20W, 70MHz	-
15808	2SA1838	2SA1839	-
15809	2SA1839	15V, 0,1A, 600MHz, Ron3Ohm	-
15810	2SA184	15V, Ueb15V, 10mA, 3MHz	AF 124...127, AF 200, 2SA201
15811	2SA1840	100/100V, +-5A, 1,8W, B>2000	2SA1715
15812	2SA1841	100/100V, 8A, 1,8W, B>4000	2SA1716
15813	2SA1842	B>4000	2SA1717
15814	2SA1843	100/60V, 5A, 1,8W, 80MHz	2SA1441
15815	2SA1844	100/60V, 7A, 1,8W, 40MHz	2SA1442
15816	2SA1845	150/100V, 5A, 1,8W, 150MHz	2SA1644
15817	2SA1846	150/100V, 7A, 1,8W, 150MHz	2SA1645
15818	2SA1847	150/100V, 10A, 1,8W, 150MHz	2SA1646
15819	2SA1848	2SA1536, 1,3W	2SA1536
15820	2SA1849	2SA1537, 1,3W	2SA1537
15821	2SA1850	2SA1538, 1,3W	2SA1538
15822	2SA1851	2SA1539, 1,3W	2SA1539
15823	2SA1852	2SA1540, 1,3W	2SA1540
15824	2SA1853	2SA1541, 1,3W	2SA1541
15825	2SA1854	40/210ns	-
15826	2SA1855	70/480ns	-
15827	2SA1856	<700/2000ns	2SA1501
15828	2SA1857	2SA1815	-
15829	2SA1858	2SA1767, 1W	2SA1371...72, 2SA1584, 2SA1760, 2SB1363
15830	2SA1859	150/150V, 2A, 20W, 60MHz	2SA1306, 2SA1332, 2SA1606, 2SB1186A
15831	2SA1859A	2SA1859, 180/180V	2SA1306A...B, 2SA1606
15832	2SA1860	150/150V, 14A, 80W, 50MHz	2SA1673
15833	2SA1861	2SA1862, 1,2W	2SA1862
15834	2SA1862(F5)	200/2200ns	2SA1412, 2SA1773
15835	2SA1863	2SA1815	-
15836	2SA1863	2SA1815	-
15837	2SA1864	15V, 0,1A, 600MHz, Ron5Ohm	-
15838	2SA1864	15V, 0,1A, 600MHz, Ron5Ohm	-
15839	2SA1865	15V, 0,1A, 600MHz, Ron6Ohm	-

15840	2SA1865	15V, 0,1A, 600MHz, Ron6Ohm	-
15841	2SA1866	Ron10Ohm	-
15842	2SA1866	Ron10Ohm	-
15843	2SA1867		-
15844	2SA1868	400/400V, 0,6A, 10W, 180MHz	2SA1727, 2SA1400
15845	2SA1869	50V, 3A, 10W, 100MHz	2SA1307, 2SA1440, 2SA1469, 2SB1185
15846	2SA1870	100V, 12A, 35W, 80MHz	-
15847	2SA1871	<0,5/5,5µs	-
15848	2SA1873	2SA1618	-
15849	2SA1875	2SA1749, 12W	2SA1749
15850	2SA1876	80V, 3A, 10W, 50MHz	2SB1215...1216
15851	2SA1877	80V, 5A, 10W, 50MHz	2SA1648
15852	2SA1878	80V, 5A, 25W, 50MHz	2SA1469, 2SA1388, 2SA1741
15853	2SA1878	80V, 5A, 25W, 50MHz	2SA1469, 2SA1388, 2SA1741
15854	2SA1879	80V, 7A, 25W, 50MHz	2SA1470, 2SA1742
15855	2SA1879	80V, 7A, 25W, 50MHz	2SA1470, 2SA1742
15856	2SA188	12V, 15mA, 10MHz	AF 124...127, AF 200, 2SA201...202
15857	2SA1880	80V, 10A, 25W, 50MHz	2SA1471, 2SA1743
15858	2SA1880	80V, 10A, 25W, 50MHz	2SA1471, 2SA1743
15859	2SA1881	15V, 1A, 300MHz	-
15860	2SA1882	15V, 1,5A, 300MHz	2SA1314, 2SA1363, 2SA1369, 2SA1663
15861	2SA1883	15V, 0,2A, 1000MHz, 11/19ns	-
15862	2SA1883	15V, 0,2A, 1000MHz, 11/19ns	-
15863	2SA1884	-/400V, 0,5A, 0,9W	2SA1625, 2SB1074, 2SB1488
15864	2SA1885	-/10V, 0,1A, 650MHz	-
15865	2SA1886	2SA1885	-
15866	2SA1886	2SA1885	-
15867	2SA1887	80V, 10A, 45MHz	2SA1443, 2SA1471, 2SA1743
15868	2SA1888	30V, 30mA, 300MHz	BF 550, 2SA1256
15869	2SA1889	2SA1810, , 8W	2SA1749, 2SA1777
15870	2SA189	12V, 15mA, 6MHz	AF 124...127, AF 200, 2SA201...203
15871	2SA1890	80V, 1A, 120MHz	2SB1115A, 2SB1520
15872	2SA1891	60V, 2A, 1,3W, 100MHz	2SB1142
15873	2SA1892	50V, 3A, 1,3W, 100MHz	-
15874	2SA1893	35V, 5A, 1,3W, 170MHz	2SA1357, 2SB1436
15875	2SA1896	25V, 2,5A, 400MHz	2SA1736, 2SB1124, 2SB1518
15876	2SA1897	400/360ns	2SA1431, 2SB1050, 2SB1319, 2SB1398
15877	2SA1898	15V, 3A, 30/120ns	2SB1301, 2SB1518, 2SB1628
15878	2SA1899	120V, 0,8A, 1W, 120MHz	2SA965, 2SA1013, 2SA1319, 2SA1768
15879	2SA18H	2SA18, Ueb12V	-
15880	2SA19	12V, 2mA, 50MHz	AF 124...126, AF 200, 2SA104
15881	2SA190	20V, 15mA, 40MHz	AF 124...126, AF 200, 2SA218...227
15882	2SA1900	60V, 1A, 150MHz	2SA1364, 2SB1115(A), 2SB1122...23
15883	2SA1902	-/80V, 0,7A, 0,9W	2SA1013, 2SA1275, 2SB647, 2SB1212
15884	2SA1903	-/20V, 3A, 0,9W	2SB985, 2SB1505

15885	2SA1905	60V, 5A, 1,3W, 60MHz	2SB1267
15886	2SA1907	80V, 6A, 60W, 20MHz	2SA1670, 2SA1803, BD 246A...F
15887	2SA1908	120V, 8A, 75W, 20MHz	2SA1671, 2SA1804, BD 246C...F
15888	2SA1909	140V, 10A, 80W, 20MHz	2SA1672, 2SA1805, BD 246D...F
15889	2SA191	20V, 15mA, 20MHz	AF 124...126, AF 200, 2SA218...227
15890	2SA192	20V, 15mA, 13MHz	AF 124...127, AF 200, 2SA218...227
15891	2SA1920	-/600V, 0,1A, 1W	-
15892	2SA1923	200/2200ns	2SA1772
15893	2SA1924	2SA1924	2SA1156, 2SA1775
15894	2SA1925	2SA1924, 1,5W(Ta25°)	2SA1156, 2SA1775
15895	2SA1926	80V, 3A, 1W, 80MHz	-
15896	2SA193	15V, Ueb12V, 15mA, 13MHz	AF 124...126, AF 200, 2SA202
15897	2SA1930	180/180V, 2A, 20W, 200MHz	2SA1306A, 2SA1606, 2SA1859A
15898	2SA1932	230/230V, 1A, 1,8W, 70MHz	2SA1837
15899	2SA1932	230/230V, 1A, 1,8W, 70MHz	2SA1837
15900	2SA1933	60V, 5A, 1,8W, 60MHz	2SA1388, 2SA1469...70, 2SA1441
15901	2SA1933	60V, 5A, 1,8W, 60MHz	2SA1388, 2SA1469...70, 2SA1441
15902	2SA1934	100V, 5A, 1,8W, 60MHz	2SA1388, 2SA1441, 2SA1741
15903	2SA1934	100V, 5A, 1,8W, 60MHz	2SA1388, 2SA1441, 2SA1741
15904	2SA1935	15V, 1,5A, 300MHz, 30/120ns	2SA1314, 2SA1363, 2SA1369, 2SA1663
15905	2SA1936	15V, 5A, 300MHz, 30/120ns	2SB1302, 2SB1308, 2SB1386
15906	2SA1937	600/600V, 0,5A, 10W, 35MHz	2SA1379, 2SA1413, 2SA1807
15907	2SA1939	80/80V, 6A, 60W, 30MHz	BD 246C, BDV 94, 2SA1693, 2SB775
15908	2SA194	15V, Ueb12V, 15mA, 7MHz	AF 124...127, AF 200, 2SA201
15909	2SA1940	120/120V, 8A, 80W, 30MHz	BD 246C, BD 546D, 2SA1694, 2SB688
15910	2SA1941	140/140V, 10A, 100W, 30MHz	BD 246D, 2SA1146, 2SA1186, 2SA1491
15911	2SA1942	180/180V, 12A, 120W, 30MHz	2SA1302, 2SB1317, 2SB1429
15912	2SA1943	230/230V, 15A, 150W, 25MHz	2SA1553
15913	2SA1944	50V, 1A, 90MHz, B400..1200	2SA1681, 2SB1115, 2SB1122...1123
15914	2SA1945	55V, 0,4A, 150MHz	2SA1202, 2SA1662, 2SB1122...1123
15915	2SA1946	25V, 0,7A, 180MHz	BCX 51...53, 2SA1364, 2SB1734, 2SB804
15916	2SA1947	30V, 1A, 100MHz	BCX 51...53, 2SA1681, 2SB1122...1123
15917	2SA1948	120V, 0,1A, 200MHz	2SA1173, 2SA1200, 2SB1045...1047
15918	2SA1949	490/490V, 0,5A, 10W, 70MHz	2SA1379, 2SA1413, 2SA1807
15919	2SA195	15V, Ueb12V, 15mA, 4MHz	AF 124...127, AF 200, 2SA203
15920	2SA1950	500/500V, 1A, 10W	2SA1379, 2SA1413, 2SA1807
15921	2SA1951	500/500V, 2A, 10W	-
15922	2SA1958	150/150V, 0,2A, 8W, 500MHz	2SA1749, 2SA1777
15923	2SA196	15V, Ueb12V, 15mA, 2,5MHz	AF 124...127, AF 200, 2SA203
15924	2SA1960	80/80V, 0,3A, 0,625W, 1,3GHz	-
15925	2SA1962	2SA1943, 130W	2SA1294
15926	2SA1963	12V, 50mA, 5GHz	BFT 93
15927	2SA1965	15V, 0,1A, Ron1,2Ohm	-
15928	2SA1965	15V, 0,1A, Ron1,2Ohm	-
15929	2SA1966	500/500V, 0,1A, 10W, 30MHz	-



15930	2SA1967	900/900V, 10mA, 6MHz	-
15931	2SA1968(LS)	2SA1967	-
15932	2SA1969	10/10V, 0,4A, 1,7GHz	-
15933	2SA197	15V, Ueb15V, 10mA	AF 124...127, AF 200, 2SA202
15934	2SA1971	400/400V, 0,5A, 35MHz	-
15935	2SA1974	40V, 0,5A, 0,5W, 200MHz	BC 327, BC 636, 2SB734, 2SB909...910
15936	2SA1975	50V, 0,15A, 0,4W, 80MHz	BC 212, BC 307, BC 556...557, 2SB725
15937	2SA1976	35V, 0,8A, 0,625W, 130MHz	BC 327, BC 636, 2SB734, 2SB909...910
15938	2SA198	15V, 15mA	AF 124...127, AF 200, 2SA201...203
15939	2SA199	15V, 5mA	AF 124...126, AF 200, 2SA201...203
15940	2SA20	12V, 2mA, 55MHz	AF 124...126, AF 200, 2SA104
15941	2SA200	15V, 5mA	AF 124...126, AF 200, 2SA201...203
15942	2SA201	15V, 15mA, 8MHz	AF 124...126, AF 200, 2SA101...104
15943	2SA202	15V, 15mA, 12MHz	AF 124...127, AF 200, 2SA101...104
15944	2SA203	15V, 15mA, 5MHz	AF 124...127, AF 200, 2SA101...104
15945	2SA204	6MHz	ASY 26...27, ASY 48
15946	2SA205	5MHz	ASY 26...37, ASY 48
15947	2SA206	7MHz	ASY 26...27, ASY 48
15948	2SA207	12MHz	ASY 26...27, ASY 48
15949	2SA208	>3MHz	ASY 76...77
15950	2SA209	>5MHz	ASY 76...77
15951	2SA21	12V, 2mA, 55MHz	AF 124...126, AF 200, 2SA104
15952	2SA210	>10MHz	ASY 76...77
15953	2SA211(H)	>4MHz	ASY 26...27, ASY 48
15954	2SA212(H)	2SA211, 25V, Ueb12V	ASY 26...27, ASY 48
15955	2SA213	15V, 2mA, 140MHz	AF 124...125, AF 106, AF 306, 2SA342
15956	2SA214	15V, 2mA, 140MHz	AF 124...126, AF 106, AF 306, 2SA342
15957	2SA215	15V, 2mA, 120MHz	AF 124...126, AF 106, AF 306, 2SA340...342
15958	2SA216	15V, 2mA, 120MHz	AF 124...126, AF 106, AF 306, 2SA340...342
15959	2SA217(H)	14MHz	ASY 26...27, ASY 48
15960	2SA218	20V, 10mA, 55MHz	AF 124...126, AF 200, 2SA102...104
15961	2SA219	20V, 15mA, 55MHz	AF 124...126, AF 200, 2SA103...104
15962	2SA22	20V, 20mA, 12MHz	AF 124...127, AF 200, 2SA201...202
15963	2SA220	20V, 15mA, 60MHz	AF 124...126, AF 200, 2SA104
15964	2SA221	20V, 15mA, 55MHz	AF 124...126, AF 200, 2SA104
15965	2SA222	20V, 15mA, 60MHz	AF 124...126, AF 200, 2SA104
15966	2SA223	20V, 15mA, 65MHz	AF 124...126, AF 200, 2SA104
15967	2SA224	20V, 10mA, 90MHz	AF 124...126, AF 200, 2SA104
15968	2SA225	20V, 15mA, 55MHz	AF 124...126, AF 200, 2SA103...104
15969	2SA226	15V, 10mA, 95MHz	AF 124...126, AF 200, 2SA104
15970	2SA227	20V, 10mA, 90MHz	AF 124...126, AF 200, 2SA104
15971	2SA228	80V, 0,05A, 0,17W, 35MHz	AF 118, SFT 162, 2SA358
15972	2SA229	20V, 5mA, 400MHz	AF 139, AF 239(S)
15973	2SA23	20V, 15mA, 8MHz	AF 124...127, AF 200, 2SA201...203
15974	2SA230	20V, 5mA, 400MHz	AF 139, AF 239(S)



15975	2SA231	40V, 0,4A, 3W(Tc25°), 2,5MHz	AD 162
15976	2SA232	30V, 0,4A, 3W(Tc25°), 4MHz	AD 162
15977	2SA233	20V, 10mA, 100MHz	AF 124...127, AF 200, 2SA342
15978	2SA234(H)	20V, 10mA, 120MHz	AF 124...127, AF 200, 2SA342
15979	2SA235(H)	20V, 10mA, 135MHz	AF 124...125, AF 200, AF 106, AF 306
15980	2SA236	18V, 5mA, 35MHz	AF 124...126, AF 200, 2SA101...104
15981	2SA237	18V, 5mA, 35MHz	AF 124...126, AF 200, 2SA101...104
15982	2SA238	25V, 30mA, 700MHz	AF 139, AF 239(S)
15983	2SA239	20V, 5mA, 200MHz	AF 106, AF 109R, AF 139, AF 239(S)
15984	2SA24	30V, 10mA, 100MHz	AF 124...126, AF 200, AF 239, 2SA104
15985	2SA240	20V, 5mA, 200MHz	AF 106, AF 109R, AF 139, AF 239(S)
15986	2SA241	20V, 5mA, 200MHz	AF 106, AF 109R, AF 139, AF 239(S)
15987	2SA242	20V, 5mA, 250MHz	AF 106, AF 109(R), AF 139, AF 239(S)
15988	2SA243(A)	20V, 5mA, 300MHz	AF 109R, AF 139, AF 239(S)
15989	2SA244(A)	25V, 30mA, 600MHz	AF 109R, AF 139, AF 239(S)
15990	2SA245	25V, 30mA, 700MHz	AF 109(R), AF 139, AF 239(S)
15991	2SA246(H)	30V, 30mA, 160MHz	AF 106, AF 109R, AF 139, AF 239(S)
15992	2SA247	10V, 0,03A, 0,1W, 200MHz	ASZ 21, 2N2955...2957
15993	2SA248	/250ns	ASZ 21, 2N2955...2957
15994	2SA249	β60	AF 118, SFT 162, 2SA358
15995	2SA25	30V, 15mA, 100MHz	AF 124...126, AF 200, AF 239, 2SA104
15996	2SA250	2SA249, β100	AF 118, SFT 162, 2SA358
15997	2SA252	15V, 0,05A, 0,05W, 80MHz	ASZ 21, 2N2955...2957
15998	2SA253	20V, 30mA, 450MHz	AFY 18, AF 139, AF 239(S)
15999	2SA254	12V, 10mA, 10MHz	AF 124...126, AF 200, 2SA201...202
16000	2SA255	12V, 10mA, 5MHz	AF 124...126, AF 200, 2SA201...203
16001	2SA256	20V, 10mA, 60MHz	AF 124...126, AF 200, 2SA104
16002	2SA257	20V, 10mA, 50MHz	AF 124...126, AF 200, 2SA104
16003	2SA258	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16004	2SA259	20V, 10mA, 30MHz	AF 124...126, AF 200, 2SA103...104
16005	2SA26	20V, Ueb15V, 50mA, 6MHz	AF 121S, AF 202(S), AFY 18
16006	2SA260	20V, 10mA, 300MHz	AF 109R, AF 139, AF 239(S)
16007	2SA261	20V, 10mA, 300MHz	AF 109R, AF 139, AF 239(S)
16008	2SA262	20V, 10mA, 450MHz	AF 139, AF 239(S)
16009	2SA263	20V, 10mA, 500MHz	AF 139, AF 239(S)
16010	2SA264	20V, 10mA, 450MHz	AF 139, AF 239(S)
16011	2SA265	20V, 10mA, 300MHz	AF 109R, AF 139, AF 239(S)
16012	2SA266	20V, 10mA, 60MHz	AF 124...126, AF 200, 2SA104
16013	2SA267	20V, 10mA, 50MHz	AF 124...126, AF 200, 2SA104
16014	2SA268	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16015	2SA269	20V, 10mA, 30MHz	AF 124...126, AF 200, 2SA102...104
16016	2SA27	18V, 5mA, 50MHz	AF 124...126, AF 200, AF 239, 2SA104
16017	2SA270	9V, 10mA, 50MHz	AF 124...126, AF 200, 2SA103...104
16018	2SA271	9V, 10mA, 30MHz	AF 124...126, AF 200, 2SA103...104
16019	2SA272	9V, 10mA, 20MHz	AF 124...127, AF 200, 2SA102...104

16020	2SA273	34V, 10mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16021	2SA274	34V, 10mA, 30MHz	AF 124...127, AF 200, 2SA102...104
16022	2SA275	34V, 10mA, 45MHz	AF 124...126, AF 200, 2SA103...104
16023	2SA276	/3,2ns	ASZ 21, 2N2955...2957
16024	2SA277	/450ns	ASY 26...27, ASY 48
16025	2SA278	/400ns	ASY 26...27, ASY 48
16026	2SA279	30V, 30mA, 150MHz	AF 124...126, AF 200, AF 106, AF 109R
16027	2SA28	18V, 5mA, >60MHz	AF 124...126, AF 200, AF 239, 2SA104
16028	2SA280	30V, 30mA, 70MHz	AF 124...126, AF 200, AF 106, AF 109R
16029	2SA281	30V, 30mA, 100MHz	AF 124...126, AF 200, AF 106, AF 109R
16030	2SA282	6MHz	ASY 26...27, ASY 48
16031	2SA283	10MHz	ASY 26...27, ASY 48
16032	2SA284	14MHz	ASY 26...27, ASY 48
16033	2SA285	18V, 5mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16034	2SA286	18V, 5mA, 50MHz	AF 124...126, AF 200, 2SA103...104
16035	2SA287	18V, 5mA, 60MHz	AF 124...126, AF 200, 2SA103...104
16036	2SA288	20V, 10mA, 330MHz	AF 109R, AF 139, AF 239(S)
16037	2SA289	20V, 10mA, 350MHz	AF 109R, AF 139, AF 239(S)
16038	2SA29	18V, 5mA, 35MHz	AF 124...126, AF 200, AF 239, 2SA104
16039	2SA290	20V, 10mA, 370MHz	AF 109R, AF 139, AF 239(S)
16040	2SA291	20V, 50mA, 100MHz	AF 106, AF 109R, AF 139, AF 239(S)
16041	2SA292	15V, 50mA, 200MHz	AF 106, AF 109R, AF 139, AF 239(S)
16042	2SA293	15V, 50mA, 300MHz	AF 109R, AF 139, AF 239(S)
16043	2SA294	15V, 50mA, 400MHz	AF 109R, AF 139, AF 239(S)
16044	2SA295	15V, 50mA	AF 109R, AF 139, AF 239(S)
16045	2SA296	15V, 15mA, 5MHz	AF 124...127, AF 200, 2SA101...104
16046	2SA297	16V, 15mA, 10MHz	AF 124...127, AF 200, 2SA101...104
16047	2SA298	40V, 10mA, 35MHz	AF 124...127, AF 200, 2SA101...104
16048	2SA299	15V, 10mA	AF 124...127, AF 200, 2SA102...104
16049	2SA30	12V, 10mA, 10MHz	AF 124...127, AF 200, 2SA201...202
16050	2SA300	15V, 10mA	AF 124...127, AF 200, 2SA102...104
16051	2SA301	30V, 30mA, 100MHz	AF 121(S), AF 202(S)
16052	2SA304	18V, Ueb12V, 40MHz, 4,5MHz	AF 124...127, AF 200, 2SA102...104
16053	2SA305	18V, Ueb12V, 40mA, 10MHz	AF 124...126, AF 200, 2SA102...104
16054	2SA306	40V, 10mA, 55MHz	AF 124...126, AF 200, 2SA103...104
16055	2SA307	40V, 10mA, 75MHz	AF 124...126, AF 200, 2SA103...104
16056	2SA308	20V, 5mA, 450MHz	AF 139, AF 239(S)
16057	2SA309	20V, 5mA, 600MHz	AF 139, AF 239(S)
16058	2SA31	12V, 10mA, 5MHz	AF 124...127, AF 200, 2SA201...203
16059	2SA310	32V, 25mA, 650MHz	AF 139, AF 239(S)
16060	2SA311	/330ns	ASY 76...77
16061	2SA312	/320ns	ASY 48, ASY 76...77
16062	2SA313	18V, 20mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16063	2SA32	20V, Ueb10V, 50mA, 10MHz	AF 121S, AF 202(S), AFY 18
16064	2SA321	20V, 15mA, 30MHz	AF 124...126, AF 200, 2SA103...104

16065	2SA322	20V, 15mA, 35MHz	AF 124...126, AF 200, 2SA103...104
16066	2SA323	20V, 15mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16067	2SA324	20V, 15mA, 55MHz	AF 124...126, AF 200, 2SA103...104
16068	2SA325	5MHz	ASY 26...27, ASY 48
16069	2SA325	5MHz	ASY 26...27, ASY 48
16070	2SA326	10MHz	ASY 26...27, ASY 48
16071	2SA327	/1600ns	ASY 48, 2N2955...2957
16072	2SA328	20V, 10mA	AF 124...127, AF 200, 2SA101...104
16073	2SA329	20V, 10mA, 5.5MHz	AF 124...127, AF 200, 2SA102...104
16074	2SA33	20V, Ueb10V, 25mA, 6MHz	AF 121S, AF 202(S), AFY 18
16075	2SA330	20V, 10mA	AF 124...127, AF 200, 2SA102...104
16076	2SA331	40V, 50mA, >40MHz	AF 124...127, AF 200, 2SA103...104
16077	2SA332	20V, 10mA, 60MHz	AF 124...126, AF 200, 2SA104
16078	2SA333	20V, 10mA, 55MHz	AF 124...126, AF 200, 2SA104
16079	2SA334	20V, 10mA, 65MHz	AF 124...126, AF 200, 2SA104
16080	2SA336	9V, 10mA, 30MHz	AF 124...127, AF 200, 2SA102...104
16081	2SA337	9V, 10mA, 35MHz	AF 124...126, AF 200, 2SA102...104
16082	2SA338	20V, 5mA, 15MHz	AF 124...127, AF 200, 2SA101...104
16083	2SA339	20V, 5mA, 30MHz	AF 124...127, AF 200, 2SA101...104
16084	2SA340	20V, 10mA, 70MHz	AF 124...125, AF 200, 2SA260...265
16085	2SA341	20V, 10mA, 70MHz	AF 124...125, AF 200, 2SA260...265
16086	2SA342	20V, 10mA, 100MHz	AF 124...125, AF 200, 2SA260...265
16087	2SA343	20V, 5mA, 100MHz	AF 106, AF 109R, AF 139, AF 239(S)
16088	2SA344	30V, 30mA, 100MHz	AF 124...125, AF 106, AF 109R, 2SA342
16089	2SA345	20V, 10mA, >250MHz	AF 109R, AF 139, AF 239(S), 2SA260...265
16090	2SA346	20V, 10mA, >250MHz	AF 109R, AF 139, AF 239(S), 2SA260...265
16091	2SA347	20V, 10mA, >250MHz	AF 109R, AF 139, AF 239(S), 2SA260...265
16092	2SA348	20V, 10mA, >200MHz	AF 106, AF 109R, AF 139, AF 239(S)
16093	2SA349	20V, 10mA, >100MHz	AF 106, AF 109R, AF 139, AF 239(S)
16094	2SA35	16V, 15mA, 10MHz	AF 124...127, AF 200, 2SA201...202
16095	2SA350(A,H)	20(H30)V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16096	2SA351(A,B)	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16097	2SA352(A,B)	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16098	2SA353(A)	25(A50)V, 10mA, 30MHz	AF 124...127, AF 200, 2SA218...227
16099	2SA354(A)	25(A50)V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
16100	2SA355(A)	25(A50)V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
16101	2SA356	9V, 10mA, 25MHz	AF 124...127, AF 200, 2SA218...227
16102	2SA357	9V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
16103	2SA358	75V, 50mA, 40MHz	AF 118, SFT 162
16104	2SA359	20V, 20mA, 300MHz	AF 109R, AF 139, AF 239(S)
16105	2SA36	16V, 15mA, 5MHz	AF 124...127, AF 200, 2SA201...203
16106	2SA360	20V, 10mA, 110MHz	AF 124...125, AF 200, 2SA342
16107	2SA361	20V, 10mA, 125MHz	AF 124...125, AF 200, 2SA342
16108	2SA362	30V, 30mA, 150MHz	AF 124...125, AF 200, AF 106, AF 109R
16109	2SA363	/400ns	ASZ 21, 2N2955...2957

16110	2SA364	9V, 10mA, 45MHz	AF 124...126, AF 200, 2SA218...227
16111	2SA365	9V, 10mA, 50MHz	AF 124...126, AF 200, 2SA218...227
16112	2SA366	9V, 10mA, 75MHz	AF 124...126, AF 200, 2SA218...227
16113	2SA367	20V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
16114	2SA368	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16115	2SA369	20V, 10mA, 50MHz	AF 124...126, AF 200, 2SA218...227
16116	2SA37	18V, Ueb12V, 5mA, 7MHz	AF 124...127, AF 200
16117	2SA370	75V, 50mA, 40MHz	AF 118, SFT 162, 2SA358
16118	2SA371	10,5MHz	ASY 26...27, ASY 48
16119	2SA372	6/45ns	-
16120	2SA373(A)	25V, 0,15A, 0,25W, 400MHz	-
16121	2SA374	34V, 0,3A, 300MHz	-
16122	2SA375	30V, 0,1A, 0,08W, 40MHz	ASY 26...27, ASY 48
16123	2SA376	22V, 10mA	AF 124...125, AF 106, AF 109R, 2SA342
16124	2SA377	20V, 5mA, 200MHz	AF 109R, AF 139, AF 239(S)
16125	2SA378	20V, 5mA, 250MHz	AF 109R, AF 139, AF 239(S)
16126	2SA379	20V, 5mA, 300MHz	AF 109R, AF 139, AF 239(S)
16127	2SA38	18V, Ueb12V, 5mA, 10MHz	AF 124...127, AF 200
16128	2SA380	25V, 10mA, 60MHz	AF 124...126, AF 200, 2SA218...227
16129	2SA381	25V, 10mA, 35MHz	AF 124...126, AF 200, 2SA218...227
16130	2SA382	25V, 10mA, 30MHz	AF 124...126, AF 200, 2SA218...227
16131	2SA383	25V, 10mA, 25MHz	AF 124...126, AF 200, 2SA218...227
16132	2SA384	25V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16133	2SA385	16V, Ueb10V, 10mA, 10MHz	ASY 26...27, AF 124...127, AF 200
16134	2SA386	32V, 0,3A, 350MHz	-
16135	2SA387	10V, 15mA	AF 124...127, AF 200, 2SA218...227
16136	2SA389	20V, 10mA, 600MHz	AF 139, AF 239(S)
16137	2SA39	18V, Ueb12V, 5mA, 5,5MHz	AF 124...127, AF 200
16138	2SA390	20V, 10mA, 700MHz	AF 139, AF 239(S)
16139	2SA391	7MHz	ASY 26...27
16140	2SA392	11MHz	ASY 26...27
16141	2SA393	16MHz	ASY 26...27
16142	2SA393A	2SA393, 30V	ASY 26
16143	2SA394	22MHz	ASY 26...27
16144	2SA395	29MHz	ASY 26...27
16145	2SA396	6MHz	ASY 26...27
16146	2SA397	8MHz	ASY 26...27
16147	2SA398	10MHz	ASY 26
16148	2SA399	12MHz	ASY 26
16149	2SA40	25V, Ueb12V, 0,05A, 5MHz	ASY 26...27, ASY 48
16150	2SA400	20V, 10mA, 70MHz	AF 124...126, AF 200, 2SA218...227
16151	2SA401	30V, 40mA, 230MHz	AF 121(S), AF 202(S)
16152	2SA402	35V, 0,1A, 0,25W, 200MHz	BC 213, BC 258, BC 308, BC 558
16153	2SA403	20V, 5mA, 280MHz	AF 109R, AF 139, AF 239(S)
16154	2SA404	20V, 5mA, 400MHz	AF 109R, AF 139, AF 239(S)

16155	2SA405	15V, 0,05A, 0,15W, 50/110ns	ASZ 21, 2N2955...2957
16156	2SA406	9MHz	ASY 26, ASY 48
16157	2SA407	14MHz	ASY 26, ASY 48
16158	2SA408	50MHz	ASZ 21, 2N2955...2957
16159	2SA409	80MHz	ASZ 21, 2N2955...2957
16160	2SA41(H)	35V, Ueb20V, 40mA, 6MHz	ASY 26...27, ASY 48
16161	2SA410	12V, 0,15A, 0,15W, 25/90ns	ASZ 21, 2N2955...2957
16162	2SA411	15V, 0,15A, 0,15W, 25/75ns	ASZ 21, 2N2955...2957
16163	2SA412	13V, 0,1A, 0,15W, 40MHz	AFY 18, 2N3323...3325
16164	2SA413	20V, 0,03A, 0,1W, 50/80ns	ASZ 21, 2N2635, 2N2955...2957
16165	2SA414	0,15W,320/1300ns	ASY 26, ASY 48
16166	2SA415	0,15W,265/1300ns	ASY 26...27, ASY 48
16167	2SA416	70V, 0,7A, 6W, 350/800MHz	AUY 10
16168	2SA417	15V, 0,2A, 0,15W, <70/100ns	2N2955...2957
16169	2SA419	20V, 5mA, >350MHz	AF 139, AF 239(S)
16170	2SA42(H)	45V, Ueb20V, 40mA, 6MHz	ASY 26...27, ASY 48
16171	2SA420	20V, 5mA, >300MHz	AF 139, AF 239(S)
16172	2SA421	20V, 5mA, 680MHz	AF 139, AF 239(S)
16173	2SA422	20V, 5mA, 880MHz	AF 139, AF 239(S)
16174	2SA423	20V, 5mA	AF 139, AF 239(S)
16175	2SA423	20V, 5mA	AF 139, AF 239(S)
16176	2SA424	20V, 5mA	AF 139, AF 239(S)
16177	2SA425	30V, 30mA, 350MHz	AF 139, AF 239(S)
16178	2SA426	30V, 30mA, 500MHz	AF 139, AF 239(S)
16179	2SA427	20V, 15mA, 45MHz	AF 124...126, AF 200, 2SA340...342
16180	2SA428	20V, 15mA, 50MHz	AF 124...126, AF 200, 2SA340...342
16181	2SA429(G,GTM)	150V, 0,03A, 100MHz	BF 398, BF 421, BF 423, BF 435...437
16182	2SA43	35V, 10mA, 40MHz	AF 124...126, AF 200, 2SA103...104
16183	2SA430	20V, 5mA, >450MHz	AF 139, AF 239(S)
16184	2SA431(A)	20V, 5mA, 500MHz	AF 139, AF 239(S)
16185	2SA432(A)	20V, 5mA, 450MHz	AF 139, AF 239(S)
16186	2SA433	18V, 5mA, 34MHz	AF 124...126, AF 200, 2SA218...227
16187	2SA434	20V, 10mA, 880MHz	AF 109R, AF 139, AF 239(S)
16188	2SA435	20V, 10mA, 330MHz	AF 109R, AF 139, AF 239(S)
16189	2SA436	20V, 10mA, 400MHz	AF 109R, AF 139, AF 239(S)
16190	2SA437	20V, 10mA, 400MHz	AF 109R, AF 139, AF 239(S)
16191	2SA438	20V, 10mA, 520MHz	AF 109R, AF 139, AF 239(S)
16192	2SA44	15V, Ueb10V, 10mA, 15MHz	AF 124...127, AF 200, 2SA201...202
16193	2SA440(A)	20V, 5mA, 350MHz	AF 109R, AF 139, AF 239(S)
16194	2SA441	20V, 10mA, 500MHz	AF 109R, AF 139, AF 239(S)
16195	2SA446	15V, 0,2A, 0,2W, 20/145ns	2N2955...2957
16196	2SA447	25V, 15mA, 650MHz	AF 139, AF 239(S)
16197	2SA448	15V, 5mA, 1700MHz	2N5043, AF 239S
16198	2SA449	10V, 0,1A, 0,15W, <80/120ns	ASZ 21, 2N2955...2957
16199	2SA45	18V, Ueb12V, 5mA	AF 124...127, AF 200, 2SA201...203

16200	2SA450(H)	12V, 0,1A, 0,15W, <60/95ns	ASZ 21, 2N2955...2957
16201	2SA451(H)	12V, 0,1A, 0,15W, <60/110ns	ASZ 21, 2N2955...2957
16202	2SA452(H)	12V, 0,1A, 0,15W, <60/120ns	ASZ 21, 2N2955...2957
16203	2SA453	22V, 10mA, 630MHz	AF 109R, AF 139, AF 239(S)
16204	2SA454	22V, 10mA, 630MHz	AF 109R, AF 139, AF 239(S)
16205	2SA455	22V, 10mA, 630MHz	AF 109R, AF 139, AF 239(S)
16206	2SA456	22V, 10mA, 630MHz	AF 109R, AF 139, AF 239(S)
16207	2SA457	18V, 20mA, 45MHz	AF 124...126, AF 200, 2SA218...227
16208	2SA458	B60	ASY 26...27, ASY 48
16209	2SA459	2SA458, B120	ASY 26...27, ASY 48
16210	2SA46	12V, 25mA, 10MHz	AF 124...127, AF 200, 2SA201...202
16211	2SA460	20V, 10mA, 400MHz	AF 109R, AF 139, AF 239(S)
16212	2SA461	20V, 10mA, 400MHz	AF 109R, AF 139, AF 239(S)
16213	2SA462	20V, 10mA, 400MHz	AF 109R, AF 139, AF 239(S)
16214	2SA463	20V, 10mA, 300MHz	AF 109R, AF 139, AF 239(S)
16215	2SA464	15V, 10mA, 850MHz	AF 139, AF 239(S)
16216	2SA465	20V, 5mA, 600MHz	AF 139, AF 239(S)
16217	2SA466	18V, 10mA, 15MHz	AF 124...127, AF 200, 2SA218...227
16218	2SA467(G,GTM)	40V, 0,4A, 0,3W, 200MHz	BC 327, BC 636, BC 638, BC 640
16219	2SA468	18V, 10mA, 45MHz	AF 124...126, AF 200, 2SA220...227
16220	2SA469	18V, 10mA, 30MHz	AF 124...126, AF 200, 2SA220...227
16221	2SA47	12V, 25mA, 6MHz	AF 124...127, AF 200, 2SA201...203
16222	2SA470	18V, 10mA, 35MHz	AF 124...126, AF 200, 2SA220...227
16223	2SA471	18V, 10mA, 35MHz	AF 124...126, AF 200, 2SA220...227
16224	2SA472	18V, 10mA, 35MHz	AF 124...126, AF 200, 2SA220...227
16225	2SA473	30V, 3A, 10W, 100MHz	2SA1012, 2SB1273, 2SA1288...1289
16226	2SA474	50V, 0,05A, 0,12W, 70MHz	AF 121(S), AF 202(S)
16227	2SA475	20V, 0,05A, 0,12W, 30MHz	AF 121(S), AF 202(S)
16228	2SA476	18V, 10mA, 130MHz	AF 106, AF 109R, 2SA345...349
16229	2SA477	18V, 10mA, 45MHz	AF 124...126, AF 200, 2SA218...227
16230	2SA478	/335ns	2N705, 2N960...967, 2N2955...2957
16231	2SA479	<370ns	2N705, 2N960...967, 2N2955...2957
16232	2SA48	18V, Ueb12V, 5mA	AF 124...127, AF 200, 2SA201...203
16233	2SA480	30V, 100mA, 70MHz	BF 324, BF 440...441, BF 450...451
16234	2SA482	40V, 0,6A, 0,6W, 70MHz	BC 160...161, BC 303...304, 2N2904...05
16235	2SA483	150V, 1,5A, 20W, 10MHz	2SA839, 2SA940, 2SB628(A), 2SB861
16236	2SA484	110V, 1,5A, 0,8W, 20MHz	BCX 60, 2N3634...3637
16237	2SA485	2SA484, 80V	BCX 60, BSV 17, BSS 17...18, 2N5322...23
16238	2SA486	2SA484, 50V	BCX 60, BSV 16...17, 2N5322...5323
16239	2SA489	70V, 4A, 30W, >3MHz	BD 244A, BD 538, BD 540B, BD 952
16240	2SA49	18V, Ueb12V, 5mA, 9MHz	AF 124...127, AF 200, 2SA201...203
16241	2SA490	50V, 3A, 25W, >3MHz	BD 242, BD 244, BD 536, BD 936
16242	2SA493(GTM)	50V, 0,05A, 0,2W, 80MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16243	2SA494	35V, 0,03A, 0,2W, 200MHz	BC 214, BC 259, BC 309, BC 559, 2SA1137
16244	2SA495(GTM)	35V, 0,1A, 0,2W, 200MHz	BC 213, BC 257, BC 307, BC 557, 2SB725



16245	2SA496	40V, 1A, 5W, 100MHz	BD 136, BD 227, BD 376, 2SB1009
16246	2SA497	80V, 0,8A, 0,6W, 70MHz	BC 303, BCX 60, BSV 17, 2N3634...35
16247	2SA498	2SA497, 50V	BC 161, BC 303...304, BCX 60, BSV 16
16248	2SA499(M)	50V, 0,1A, 0,25W, 250MHz	BC 212, BC 257, BC 307, BC 557
16249	2SA50	18V, Ueb12V, 24mA, 14MHz	ASY 26...27, ASY 48
16250	2SA500(M)	2SA499, 30V	BC 213, BC 258, BC 308, BC 558, 2N3906
16251	2SA500D	2SA499, 35V	BC 213, BC 258, BC 308, BC 558
16252	2SA501	40V, 0,2A, 0,75W, 200MHz	BC 160...161, BC 303...304, 2N2303
16253	2SA502	90V, 0,1A, 0,3W, >50MHz	BF 397...398, BSS 68, 2SA970, 2SA1285
16254	2SA503(M)	100V, 0,6A, 0,8W, 60/530ns	BCX 60, BSW 40
16255	2SA504(M)	2SA503, 80V	BC 303, BCX 60, BSW 40, 2N4036
16256	2SA505	60V, 1A, 5W, 100MHz	BD 138, BD 229, BD 378, 2SB744(A)
16257	2SA506	20V, 5mA, 300MHz	AF 109R, AF 139, AF 239(S)
16258	2SA507	20V, 5mA, 250MHz	AF 109R, AF 139, AF 239(S)
16259	2SA508	20V, 5mA, 200MHz	AF 109R, AF 139, AF 239(S)
16260	2SA509	35V, 0,5A, 0,6W, 140MHz	BC 327, BC 636, BC 638, 2SA1515
16261	2SA509GTM	2SA509	2SA509
16262	2SA51	18V, Ueb12V, 5mA, 14MHz	AF 124...127, AF 200, 2SA202
16263	2SA510(M)	120V, 1,5A, 0,8W, 60MHz	2N3634...3637
16264	2SA511	2SA510, 90V	BCX 60, BSS 17, BSV 17, 2N5322
16265	2SA512(M)	2SA510, 80V	BCX 60, BSS 17...18, 2N5322...5323
16266	2SA513	2SA510, 60V	BC 161, BCX 60, BSV 16, 2N5322...23
16267	2SA516(N)	80V, 1,5A, 0,8W, 50MHz	BCX 60, BSS 17...18, 2N5322...5323
16268	2SA516A	2SA516, 120V	2N3634...3637
16269	2SA517	18V, 10mA, 60MHz	AF 124...126, AF 200, 2SA218...227
16270	2SA518	18V, 10mA, 45MHz	AF 124...126, AF 200, 2SA218...227
16271	2SA52	18V, Ueb12V, 5mA, 9MHz	AF 124...127, AF 200, 2SA201...202
16272	2SA522(N)	25V, 0,1A, 0,25W, 200MHz	BC 213, BC 258, BC 308, BC 558
16273	2SA522A	2SA522, 50V	BC 212, BC 257, BC 307, BC 557
16274	2SA523(N)	40V, 0,3A, 0,65W, 200MHz	BC 160...161, BC 303...304, 2N2904...05
16275	2SA523A	2SA523, 60V	BC 161, BC 303...304, 2N2904...2905
16276	2SA524	25V, 0,1A, 0,35W, 250MHz	BC 213, BC 258, BC 308, BC 558
16277	2SA525	20V, 5mA, 250MHz	AF 109R, AF 139, AF 239(S)
16278	2SA526	50V, 1A, 0,5W	BC 161, BSV 16...17, 2N2904...2905
16279	2SA527	50V, 2A, 5W, 80MHz	BD 510, BD 518, BD 526, BD 376
16280	2SA528	50V, 2A, 5W, 80MHz	BD 510, BD 518, BD 526, BD 376
16281	2SA529	50V, 1A, 5W(Tc25°)	BC 161, BSV 16...17, 2N2904...2905
16282	2SA53	18V, Ueb12V, 5mA, 7MHz	AF 124...127, AF 200, 2SA201...202
16283	2SA530(H)	50V, 0,1A, 0,2W, 90/160ns	BC 557, BSW 24, 2N2906...07, 2N3250...51
16284	2SA532	50V, 0,2A, 0,5W, 90MHz	BC 161, BSV 16...17, 2N2904...2905
16285	2SA532-3	2SA532, 75V	BC 161, BSV 16...17, 2N2904...2905
16286	2SA532-4	2SA532, 50V	BC 161, BSV 16...17, 2N2904...2905
16287	2SA535	75V, 0,7A, 0,5W, 80MHz	BC 303, BSV 17, BSW 40, 2N3634...37
16288	2SA536	2SA535, 50V	BC 161, BC 303...304, 2N2904...2905
16289	2SA537(H)	<50/350ns	BSW 40, 2N4030...4033, 2N4036...4037



16290	2SA537A	2SA536, 100V	BSW 40
16291	2SA538	8MHz	ASY 26...27, ASY 48
16292	2SA539(S)	60V, 0,2A, 0,25W, 160MHz	BC 212, BC 256, BC 266, BC 556
16293	2SA54	20V, 5mA, 400MHz	AF 109R, AF 139, AF 239(S)
16294	2SA542	30V, 0,05A, 0,15W, >30MHz	BC 213, BC 258, BC 308, BC 558
16295	2SA543	2SA542	BC 214, BC 259, BC 309, BC 559
16296	2SA544	60V, 0,2A, 0,75W, <50/250ns	BC 161, BC 303...304, 2N2904...2905
16297	2SA545	70V, 0,2A, 0,4W, 180MHz	BC 640, 2SB647, 2SB910, 2SB1041
16298	2SA546(Z)	70V, 1A, 0,75W, 80MHz	BCX 60, BSS 17...18, 2N5322...5323
16299	2SA546A	2SA546, 90V	BCX 60, BSS 17, 2N5322
16300	2SA547(Z)	2SA546, 10W	BD 520, BD 528, BD 530, BD 378
16301	2SA547A	2SA546, 90V, 10W	BD 530, BD 380
16302	2SA548(H)	50V, 0,1A, 0,2W, 90/160ns	BC 557, BSW 24, 2N2906...07, 2N3250...51
16303	2SA549(H)	70V, 0,1A, 0,2W, >40MHz	BC 556, BF 397...398, BSS 68, 2SA970
16304	2SA549A	2SA549, 150V, 0,05A	BF 398, BF 435, 2SA1019, 2SA1285A
16305	2SA55	15V, Ueb10V, 10mA, 6MHz	AF 124...127, AF 200, 2SA201...203
16306	2SA550(Z)	25V, 0,1A, 0,3W, 120MHz	BC 213, BC 258, BC 308, BC 558, 2SA1137
16307	2SA550A	2SA550, 45V	BC 212, BC 257, BC 307, BC 557, 2SA1137
16308	2SA552	60V, 0,2A, 0,75W, <100/300ns	BSW 23, 2N2904...2905, 2N3072...3073
16309	2SA553	40V, 0,3A, 0,25W, 200MHz	BC 213, BC 257, BC 307, BC 557
16310	2SA554	25V, 0,3A, 0,25W, 200MHz	BC 213, BC 258, BC 308, BC 558
16311	2SA554A	2SA554, 40V	BC 213, BC 257, BC 307, BC 557
16312	2SA555	/195ns	BC 213, BC 257, BC 307, BC 557
16313	2SA557	20V, 0,25A, 0,3W, 200MHz	BC 213, BC 258, BC 308, BC 558
16314	2SA558	/115ns	BSW 24, 2N2906...2907, 2N3905...3906
16315	2SA559	/115ns	BSW 24, 2N2906...2907, 2N3905...3906
16316	2SA559A	2SA559, 40V	BSW 24, 2N2906...2907, 2N3905...3906
16317	2SA56	15V, 50mA, 300MHz, 50/110ns	ASZ 21, 2N2635, 2N2955...2957
16318	2SA560(N)	80V, 0,8A, 0,8W, 150MHz	BC 303, BCX 60, BSV 17, 2N3634...37
16319	2SA561	50V, 0,15A, 0,3W, 70MHz	BC 327, BC 638, BC 640, 2N2906...2907
16320	2SA562(TM)	30V, 0,4A, 0,3W, 70MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16321	2SA564(Z)	25V, 0,1A, 0,4W, 200MHz	BC 213, BC 258, BC 308, BC 558
16322	2SA564A(Z)	2SA564, 45V	BC 212, BC 257, BC 307, BC 557
16323	2SA565(K)	50V, 0,5A, 0,3W, 60MHz	BC 327, BC 638, BC 640, 2N2906...2907
16324	2SA566(H)	100V, 0,7A, 10W, 100MHz	2N5344, 2SA913(A), 2SA985(A), 2SA1111
16325	2SA567	30V, 0,1A, 0,2W, 70MHz	BC 213, BC 258, BC 308, BC 558
16326	2SA568	35V, 0,25A, 0,2W, 150MHz	BC 327, BC 636, 2SA953, 2SA1515
16327	2SA568	35V, 0,25A, 0,2W, 150MHz	BC 327, BC 636, 2SA953, 2SA1515
16328	2SA569	2SA568, 50V	BC 638, BC 640, 2SB647, 2SB910, 2SB1041
16329	2SA569	2SA568, 50V	BC 638, BC 640, 2SB647, 2SB910, 2SB1041
16330	2SA57	18V, 5mA, 85MHz	AF 124...126, AF 200, 2SA218...227
16331	2SA570	2SA568, 65V	BC 638, BC 640, 2SB647, 2SB910, 2B1041
16332	2SA570	2SA568, 65V	BC 638, BC 640, 2SB647, 2SB910, 2B1041
16333	2SA571	25/110ns	BSW 40, 2N2904...2905, 2N4030...4033
16334	2SA573	30V, 0,1A, 0,3W, 150MHz	BC 213, BC 258, BC 308, BC 558

16335	2SA574	2SA573, 60V	BC 212, BC 256, BC 266, BC 556
16336	2SA575	2SA573, 90V	2SA970, 2SA1049, 2SA1285(A), 2SA1136
16337	2SA576	30V, 0,2A, 0,6W, 200MHz	BC 327...328, BC 636, 2SA953, 2SA1515
16338	2SA577	60V, 0,4A, 0,6W, 200MHz	BC 327A, BC 638, BC 640, 2N2906...07
16339	2SA578	50V, 0,03A, 0,3W, 180MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16340	2SA579	2SA578	2SA578
16341	2SA58	18V, 5mA, 75MHz	AF 124...126, AF 200, 2SA218...227
16342	2SA580	60V, 0,6A, 0,8W, 100MHz	BC 161, BC 303...304, 2N2904...2905
16343	2SA581	2SA580, 100V	BC 303, BCX 60, BSW 40, 2N3634...3637
16344	2SA59	18V, 5mA, 65MHz	AF 124...126, AF 200, 2SA218...227
16345	2SA594(M,N)	60V, 0,2A, 0,75W, 200MHz	BSW 23, 2N3072...3073, 2N2904...2905
16346	2SA597(N)	50V, 1A, 400MHz	BSW 40, 2N2904...2905, 2N4030...4033
16347	2SA60	18V, 5mA, 55MHz	AF 124...126, AF 200, 2SA218...227
16348	2SA603	60V, 0,2A, 0,3W, 250MHz	BC 212, BC 556, BSW 24, 2N2906...2907
16349	2SA604	120V, 0,03A, 0,3W, 170MHz	BF 398, BF 423, BF 435...437, 2SA1370...72
16350	2SA605	180V, 0,05A, 0,3W, 100MHz	BF 435...437, 2SA1370...1372
16351	2SA606(S)	100V, 0,7A, 0,7W, 100MHz	BCX 60, BSW 40, 2N3634...3637
16352	2SA607(S)	2SA606	BD 380, BD 530, 2SA1014, 2SB874...875
16353	2SA608	30V, 0,1A, 0,1W, 180MHz	BC 213, BC 258, BC 308, BC 558
16354	2SA608K,KNP	2SA608, 55V, 0,25W	BC 212, BC 257, BC 307, BC 557
16355	2SA608NP	2SA608, 40V, 0,25W	BC 212, BC 257, BC 307, BC 557
16356	2SA608SP	2SA608, 40V, 0,2W	BC 212, BC 257, BC 307, BC 557
16357	2SA609	30V, 0,1A, 0,1W, 80MHz	BC 213, BC 258, BC 308, BC 558
16358	2SA609NP	2SA609, 0,25W	BC 213, BC 258, BC 308, BC 558
16359	2SA609SP	2SA609, 0,2W	BC 213, BC 258, BC 308, BC 558
16360	2SA61	20V, 10mA, 70MHz	AF 124...127, AF 200, 2SA218...227
16361	2SA610	30V, 0,1A, 0,15W, 170MHz	BC 213, BC 258, BC 308, BC 558
16362	2SA611	2SA610, 60V	BC 212, BC 256, BC 266, BC 556
16363	2SA612	90V, 0,05A, 0,2W, 150MHz	BF 397...398, 2SA893, 2SA970, 2SB715
16364	2SA613	60V, 1A, 15W, 30MHz	BD 240A, 2SA748, 2SA1111...1112
16365	2SA614	80V, 1A, 15W, 30MHz	BD 240B, 2SA913, 2SA1111...1112
16366	2SA615	70V, 3A, 25W	BD 242A, BD 538, BD 938, BDX 14
16367	2SA616	80V, 3A, 25W, 15MHz	BD 242B, BD 538, BD 938, BDX 14
16368	2SA617(K)	150V, 0,05A, 0,2W, 60MHz	BF 398, BF 423, BF 435...437, 2SA1370
16369	2SA618(K)	2SA617, 180V	BF 423, BF 435...437, 2SA1370...1372
16370	2SA620	30V, 0,05A, 0,2W, 120MHz	BC 214, BC 259, BC 309, BC 559
16371	2SA621	60V, 0,2A, 0,4W, 200MHz	BC 161, BC 303...304, BSW 23, 2SA606
16372	2SA622	30V, 0,3A, 0,15W, B40000	BC 516, BC 876, BSR 60...62, MPSA 75
16373	2SA623	35V, 1,5A, 7W, 70MHz	BD 508, BD 518, BD 526, BD 840
16374	2SA624	2SA 623, 50V	BD 510, BD 518, BD 526, BD 842
16375	2SA625	100V, 0,5A, 0,7W, 100MHz	BC 461, BCX 60, 2SA606
16376	2SA626	80V, 5A, 60W, 15MHz	BD 246B, BD 314, 2N6226, 2SB775...776
16377	2SA627	2SA626, 100V	BD 246C, BD 318, 2N6226, 2SB775...776
16378	2SA628	30V, 0,1A, 0,15W, 100MHz	BC 213, BC 258, BC 308, BC 558
16379	2SA628	30V, 0,1A, 0,15W, 100MHz	BC 213, BC 258, BC 308, BC 558

16380	2SA628A	2SA 628, 60V	BC 212, BC 256, BC 266, BC 556
16381	2SA628A	2SA 628, 60V	BC 212, BC 256, BC 266, BC 556
16382	2SA629	30V, 0,03A, 0,15W, 100MHz	BC 213, BC 259, BC 309, BC 559
16383	2SA629	30V, 0,03A, 0,15W, 100MHz	BC 213, BC 259, BC 309, BC 559
16384	2SA631	40V, 0,05A, >40MHz	AF 121(S); AF 202(S), AFY 18
16385	2SA633	30V, 2A, 10W, 60MHz	2SA699, BD 430, BD 614, BD 814
16386	2SA634	40V, 3A, 10W, 55MHz	BD 616, BD 618, BD 620
16387	2SA635	60V, 1A, 10W, 50MHz	2SA887, BD 386, BD 416, BD 828
16388	2SA636	70/45V, 3A, 10W, 45MHz	BD 620
16389	2SA636A	2SA636, 70/60V	BD 620
16390	2SA637	150V, 0,05A, 0,3W, 150MHz	BF 398, BF 423, BF 435...437, 2SA1370
16391	2SA638(S)	150V, 0,05A, 0,25W, 130MHz	BF 398, BF 423, BF 435...437, 2SA1370
16392	2SA639(S)	2SA638, 180V	BF 423, BF 435...437, 2SA1370...1372
16393	2SA64	16V, 0,04A, 15MHz, -/1850ns	ASY 26...27, ASY 48
16394	2SA640	50V, 0,03A, 0,25W, 100MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16395	2SA641	50V, 0,03A, 0,25W, 100MHz	BC 212, BC 256, BC 266, BC 556
16396	2SA642	30V, 0,2A, 0,25W, 200MHz	BC 327...328, BC 636, BC 638, BC 640
16397	2SA643	40V, 0,5A, 0,5W, 180MHz	BC 327, BC 636, BC 638, BC 640
16398	2SA645	70, 0,8A, 7W, >35MHz	BD 388, BD 418, BD 528, BD 830
16399	2SA646	2SA645, 90V	BD 390, BD 420, BD 530, BD 830
16400	2SA647	2SA645, 110V	BD 390, BD 420, BD 530, BD 830
16401	2SA648	120V, 7A, 60W, 10MHz	BD246D, 2SB681, 2SB695, 2SB696, 2SB816
16402	2SA649	2SA648, 150V	BD246D, 2SB681, 2SB695, 2SB696, 2SB816
16403	2SA65	/240ns	ASY 26...27, ASY 48, ASY 76...77
16404	2SA650	150V, 10A, 100W, 10MHz	BD246D,2SA1386, 2SB681, 2SB817, 2SB908
16405	2SA651	200V, 10A, 100W, 10MHz	BD246F,2SA1116, 2SA1294, 2SB600, 2SB645
16406	2SA652	150/100V, 1A, 15W, 15MHz	BD240D,2SB608, 2SB628(A), 2SB861, 2SB991
16407	2SA653	2SA652, 150/120V	BD240D,2SB608, 2SB628(A), 2SB861, 2SB991
16408	2SA653A	2SA652, 150/140V	BD240E,2SB608, 2SB628(A), 2SB861, 2SB991
16409	2SA656(A)	130V, 7A, 50W, 5MHz	BD246D, 2N6231, 2SB555, 2SB681, 2SB816
16410	2SA657(A)	2SA656, 100V	BD 318, BD 246C, 2SB688, 2SB681
16411	2SA658(A)	2SA656, 70V	BD 316, BD 246B, 2SB688, 2SB681
16412	2SA659(NP)	50V, 0,2A, 0,3W, 90MHz	BC 212, BC 257, BC 307, BC 557
16413	2SA66	/225ns	ASY 26...27, ASY 48, ASY 76...77
16414	2SA661	70V, 0,2A, 0,6W, 100MHz	BC 212, BC 256, BC 266, BC 556
16415	2SA663	100V, 7A, 60W, 6MHz	BD 318, BD 246C, 2N6229, 2SB775...776
16416	2SA666	25V, 0,05A, 0,25W, 130MHz	BC 214, BC 259, BC 309, BC 559
16417	2SA666A	2SA666, 45V	BC 214, BC 416, BC 560, 2SA1136...37
16418	2SA668	100V, 0,1A, 0,15W, 100MHz	BF 398, BF 435...437, BSS68, 2SA1370
16419	2SA668	100V, 0,1A, 0,15W, 100MHz	BF 398, BF 435...437, BSS68, 2SA1370
16420	2SA669	160V, 0,1A, 0,15W, 100MHz	BF 398, BF 435...437, 2SA1370...1372
16421	2SA669	160V, 0,1A, 0,15W, 100MHz	BF 398, BF 435...437, 2SA1370...1372
16422	2SA67	18V, Ueb12V, 0,2A, 14MHz	ASY 26...27, ASY 48, ASY 76...77
16423	2SA670	50V, 3A, 25W, 32MHz	BD 242, BD 536, BD 936, 2SA1288
16424	2SA671(K)	50V, 3A, 25W, 32MHz	BD 242, BD 536, BD 936, 2SA1288

16425	2SA672	50V, 0,2A, 0,2W, 80MHz	BC 214, BC 416, BC 560, 2SA1136...37
16426	2SA673	35V, 0,5A, 0,4W, 50MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16427	2SA673	35V, 0,5A, 0,4W, 50MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16428	2SA673A(AK)	2SA673, 50V	BC 327, BC 636, 2SA1683, 2SB910
16429	2SA673A(AK)	2SA673, 50V	BC 327, BC 636, 2SA1683, 2SB910
16430	2SA675	80V, 0,1A, 0,25W, 170MHz	BC 556, 2SA970, 2SA1049, 2SA1136
16431	2SA677	25V, 0,2A, 0,32W, 140MHz	BC 213, BC 258, BC 308, BC 558
16432	2SA678	2SA677, 50V	BC 212, BC 257, BC 307, BC 557
16433	2SA679	120V, 12A, 100W, 6MHz	BD 746D, 2N6030...6031, 2SB555...556
16434	2SA68	20V, 10mA, 70MHz	AF 124...125, AF 200, 2SA218...227
16435	2SA680	2SA679, 100V	BD 746C, 2N6029...6031, 2SB555...556
16436	2SA681	100V, 1A, 50MHz	BD 140, BD 231, BD 380, 2SB874...875
16437	2SA682	80V, 0,75A, 5W, 100MHz	BD 140, BD 231, BD 380, 2SA1184
16438	2SA683(NC)	30V, 1A, 1W, 200MHz	2SA966, 2SB978, 2SB927, 2SB1312
16439	2SA684(NC)	2SA683, 60V	2SA1315, 2SB764, 2SB892, 2SB1041
16440	2SA685	150V, 0,05A, 0,3W, 100MHz	BF 398, BF 423, BF 435...437, 2SA1370
16441	2SA69	20V, 10mA, 70MHz	AF 124...125, AF 200, 2SA218...227
16442	2SA695	25V, 0,7A, 0,5W, 150MHz	BC 327...328, BC 636, BC 638, 2SB910
16443	2SA695	25V, 0,7A, 0,5W, 150MHz	BC 327...328, BC 636, BC 638, 2SB910
16444	2SA696	45V, 0,3A, 0,5W, 130MHz	BC 327, BC 636, BC 638, 2SB910
16445	2SA696	45V, 0,3A, 0,5W, 130MHz	BC 327, BC 636, BC 638, 2SB910
16446	2SA697	2SA696, 65V	BC 327A, BC 638, BC 640, 2SB647
16447	2SA697	2SA696, 65V	BC 327A, BC 638, BC 640, 2SB647
16448	2SA698	130V, 0,8A, 7W, <200/800ns	2SA1195
16449	2SA699	40V, 2A, 10W, 150MHz	2SA887, BD 508, BD 516, BD 526
16450	2SA699A	2SA699, 50/40V	2SA887, BD 516, BD 526
16451	2SA70	20V, 10mA, 70MHz	AF 124, AF 200, AF 106, AF 306
16452	2SA700	35V, 1,5A, 8W, 11MHz	BD 240, BD 242, BD 536, BD 936
16453	2SA701(NP)	30V, 0,05A, 0,1W, 80MHz	BC 213, BC 258, BC 308, BC 558
16454	2SA702(NP)	2SA701, 50V	BC 212, BC 257, BC 307, BC 557
16455	2SA703	25V, 1,5A, 7W, 70MHz	BD 430, BD 506, BD 516, BD 840
16456	2SA704	25V, 0,2A, 0,32W, 140MHz	BC 213, BC 258, BC 308, BC 558
16457	2SA705	2SA704, 50V	BC 212, BC 257, BC 307, BC 557
16458	2SA706	40V, 1A, 7,9W, 120MHz	BD 416, BD 508, BD 516, BD 526
16459	2SA706-2	2SA706, 60V	BD 416, BD 518, BD 526, BD 530
16460	2SA706-3	2SA706, 80V	BD 418, BD 520, BD 528, BD 530
16461	2SA706-4	2SA706, 100V	BD 420, BD 530
16462	2SA707	40V, 0,5A, 0,75W, 180MHz	BC 327, BC 636, 2SA1515, 2SB910
16463	2SA708	80V, 0,7A, 0,8W, 100MHz	BC 303, BCX 60, 2N3634...37, 2SA606
16464	2SA708A	2SA 708, 100V, 95MHz	BCX 60, BSS 17, 2N3634...37, 2SA606
16465	2SA709	60V, 0,2A, 0,3W, 280MHz	BC 212, BC 256, BC 266, BC 556
16466	2SA71	20V, 10mA, 100MHz	AF 124, AF 200, AF 106, AF 306
16467	2SA710	50V, 0,1A, 600MHz, <80/180ns	BF 516, BF 606, BSW 24, 2N3250A...51A
16468	2SA711	2SA710, 1000MHz, <70/170ns	BF 516, BF 606, BSW 24, 2N3250A...51A
16469	2SA712	150V, 0,5A, 0,75W, 110/350ns	BFT 19, BFT 28, 2N3636...3637, 2N5415

16470	2SA713(S)	B20000	BC 516, BC 876, 2SA790, 2SA830
16471	2SA713A(AS)	2SA713, 40V, B30000	BC 516, BC 876, 2SA790, 2SA830
16472	2SA714	150V, 7A, 60W, 8MHz	BD246D, 2SB681, 2SB695, 2SB696, 2SB816
16473	2SA714L	2SA714, 100V	BD246C, 2SB681, 2SB695, 2SB696, 2SB816
16474	2SA715	35V, 2,5A, 10W, 160MHz	BD 376, 2SA1217, 2SB1009, 2SB1217
16475	2SA717	60V, 1A, 0,8W, <60/160ns	2N4030...4033, 2N4036...4037
16476	2SA718	60V, 0,2A, 0,3W, 250MHz	BC 212, BC 556, BSW 24, 2N2906...2907
16477	2SA719(NC)	30V, 0,5A, 0,625W, 200MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16478	2SA72	18V, 5mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16479	2SA720(NC)	2SA719, 60V	BC 327(A), BC 638, 2SB647, 2SB910
16480	2SA720A	2SA719, 80V, 120MHz	BC 640, 2N5400, 2SA695, 2SB647
16481	2SA721	35V, 0,05A, 0,15W, 250MHz	BC 214, BC 259, BC 309, BC 559
16482	2SA722	2SA721, 55V	BC 214, BC 416, BC 560, 2SA1136...37
16483	2SA723	40V, 0,5A, 0,25W, 180MHz	BC 327, BC 636, 2SA1515, 2SB910
16484	2SA724	35V, 0,05A, 0,25W, 300MHz	BC 213, BC 258, BC 308, BC 558
16485	2SA725	35V, 0,1A, 0,2W, 100MHz	BC 214, BC 259, BC 309, BC 559
16486	2SA725	35V, 0,1A, 0,2W, 100MHz	BC 214, BC 259, BC 309, BC 559
16487	2SA726	2SA725, 50V	BC 214, BC 416, BC 560, 2SA1136...37
16488	2SA726	2SA725, 50V	BC 214, BC 416, BC 560, 2SA1136...37
16489	2SA728	30V, 0,1A, 0,1W, 100MHz	BC 213, BC 258, BC 308, BC 558
16490	2SA728A	2SA728, 60V, 130/700ns	BC 212, BC 556, BSW 24, 2N2906...2907
16491	2SA73	18V, 5mA, 35MHz	AF 124...126, AF 200, 2SA218...227
16492	2SA730	2SA719, 0,6W	2SA719
16493	2SA731	2SA720, 0,6W	2SA720
16494	2SA732	40V, 0,3A, 0,65W, 200MHz	BC 160...161, BC 303...304, 2N2303
16495	2SA733	60V, 0,1A, 0,25W, 180MHz	BC 212, BC 257, BC 307, BC 557
16496	2SA738	25V, 1,5A, 8W, 160MHz	BD 136, BD 227, BD 376, 2SB1009
16497	2SA739	400/400V, 3A, 50W	BUW 22...23, BUW 32
16498	2SA74	50V, 50mA, 70MHz	AF 121(S), AF 202(S), AFY 18
16499	2SA740(A)	150V, 1,5A, 25W, 8MHz	BD 240D, 2SA940, 2SB628(A), 2SB861
16500	2SA741(N)	20V, 0,1A, 0,36W, <70/120ns	BSW 24, 2N3209, 2N4034...35, 2N4125...26
16501	2SA742(N)	60V, 0,5A, 0,7W, <40/100ns	2SA717
16502	2SA743	50V, 1A, 8W, 120MHz	BD 138, BD 229, BD 376, 2SB1007
16503	2SA743A	2SA743, 80V	BD 140, BD 231, BD 380, 2SB1007
16504	2SA744	80V, 8A, 70W, 15MHz	BD 246B, BD 314, 2N5872, 2SB681
16505	2SA745	2SA744, 100V	BD 246C, BD 318, 2N6229, 2SB681
16506	2SA745A	2SA745, 120V	BD 246C, 2N6230...31, 2SB681, 2SB696
16507	2SA746	80V, 10A, 100W, 15MHz	BD 246B, BD 314, 2N5876, 2SB681
16508	2SA747	2SA746, 120V	BD 246C, 2N6230...31, 2SB681, 2SB696
16509	2SA747A	2SA747, 140V	BD246D, 2N6231, 2SA908, 2SB681, 2SB696
16510	2SA748	70V, 2A, 15W, 120MHz	2SA1078, 2SA1288
16511	2SA749	100V, 0,05A, 0,25A, >40MHz	BF 398, BF 423, 2SA1017, 2SB715...716
16512	2SA749A	2SA749, 130V	BF 398, BF 423, 2SA1019, 2SB716A
16513	2SA75	20V, 50mA, 30MHz	AF 121(S), AF 202(S), AFY 18
16514	2SA750	50V, 0,05A, 0,25W, 100MHz	BC 214, BC 416, BC 560, 2SA1136...37



16515	2SA751	30V, 1A, 1W, 200MHz	BC 327...328, BC 636, 2SB809, 2SB1116
16516	2SA752	2SA751, 60V	BC 327A, BC 638, 2SB647, 2SB734
16517	2SA753	140V, 10A, 100W, 20MHz	BDX 20, 2SB681, 2SB697, 2SB817
16518	2SA754	50V, 2A, 20W, 50MHz	BD 240, 2SA748, 2SA1078, 2SA1288
16519	2SA755	2SA754	BD 240, 2SA748, 2SA1078, 2SA1288
16520	2SA756	100V, 6A, 50W, 20MHz	BD 246C, BDX 96, 2N6229...31, 2SB681
16521	2SA757	120V, 7A, 60W, 24MHz	BD 246C, BDX 20, 2N6230...31, 2SB681
16522	2SA758	130V, 7A, 80W, 20MHz	BDX 20, 2N6231, 2SA982, 2SB681
16523	2SA759	60V, 0,2A, 200MHz	BC 856, BCW 68, BCW 89, 2SA1620
16524	2SA76	18V, 5mA, 130MHz	AF 124...125, AF 106, AF 306, 2SA340...342
16525	2SA760	50V, 0,03A, 100MHz	BC 856...857, BCW 69...70, BCW 89
16526	2SA761(S)-1	110V, 2A, 6,3W(Tc25°), 80MHz	BCX 60, BSS 17, 2N5322
16527	2SA761(S)-2	2SA761-1, 140V	BUY 90
16528	2SA762-1	2SA761-1, 23W	2SA1078...1079
16529	2SA762-2	2SA761-1, 140V, 23W	2SA1079
16530	2SA763	30V, 0,05A, 0,2W, 120MHz	BC 214, BC 259, BC 309, BC 559
16531	2SA764	60V, 6A, 40W, 10MHz	BD 244A, BD 544A, BD 798, 2N6317...18
16532	2SA765	2SA764, 80V	BD 244B, BD 544B, BD 800, 2N6318
16533	2SA766(S)	15MHz	2SA839, 2SA940, 2SB628(A), 2SB861
16534	2SA767	55V, 0,1A, 0,2W, 150MHz	BC 212, BC 257, BC 307, BC 557
16535	2SA768	60V, 4A, 30W, 10MHz	BD 244A, BD 536, 2SB682, 2SB690
16536	2SA769	2SA768, 80V	BD 244B, BD 538, 2SB682, 2SB690
16537	2SA77	18V, 5mA, 110MHz	AF 124...125, AF 106, AF 306, 2SA340...342
16538	2SA770	60V, 6A, 40W, 20MHz	BD 244A, BD 798, BD 808, 2SB633
16539	2SA771	2SA770, 80V	BD 244B, BD 800, BD 810, 2SB633
16540	2SA772(-1,-2)	20V, 2A, 0,75W, 80MHz	2SA1382, 2SB738...739, 2SB892, 2SB1312
16541	2SA773(-1,-2)	60..70V, 1A, 0,75W, 65MHz	2SA1382, 2SB892, 2SA1315, 2SB647
16542	2SA774	35V, 0,05A, 0,15W, 120MHz	BC 213, BC 258, BC 308, BC 558
16543	2SA774A	2SA774, 55V	BC 212, BC 257, BC 307, BC 557
16544	2SA775	100V, 0,7A, 12,5W, 30MHz	2SA985(A), 2SA1078, 2SB861
16545	2SA775A	2SA775, 120V	2SA985(A), 2SA1078, 2SB861
16546	2SA776(A)	55V, 0,05A, 0,2W, 180MHz	BC 214, BC 416, BC 560, 2SA1136...37
16547	2SA777(NC)	80V, 0,5A, 1W, 120MHz	2SA1533, 2SB987, 2SB1041, 2SB1297
16548	2SA778	150V, 0,05A, 0,2W, 60MHz	BF 398, BF 423, BF 435...437, 2SA1370
16549	2SA778	150V, 0,05A, 0,2W, 60MHz	BF 398, BF 423, BF 435...437, 2SA1370
16550	2SA778A(AK)	2SA778, 180V	BF 423, BF 435...437, 2SA1370
16551	2SA778A(AK)	2SA778, 180V	BF 423, BF 435...437, 2SA1370
16552	2SA779(K)	35V, 1,5A, 10W, 110MHz	2SA699, 2SA748, 2SA887, 2SA1288
16553	2SA78	40V, 0,4A, 40MHz, -/335ns	ASY 76...77
16554	2SA780(K)	50V, 1A, 10W, 120MHz	2SA748, 2SA887, 2SA1078, 2SA1288
16555	2SA780A	2SA780, 80V	2SA985(A), 2SA1078, 2SA1195, 2SA1288
16556	2SA781	20V, 0,2A, 0,2W, <80/160ns	BSW 24, 2N3209, 2N3250...51, 2SA1458
16557	2SA781K	2SA781, 550MHz, <70/120ns	BSW 24, 2N3209, 2N3250...51, 2SA1458
16558	2SA782	80V, 0,03A, 0,15W, 200MHz	BC 556, 2SA893(A), 2SB715...716(A)
16559	2SA783	2SA782, 50V	BC 212, BC 257, BC 307, BC 557

16560	2SA784	2SA782, 25V	BC 213, BC 258, BC 308, BC 558
16561	2SA785	80V, 0,05A, 0,15W, 180MHz	BC 556, 2SA893(A), 2SB715...716(A)
16562	2SA786	2SA785, 50V	BC 212, BC 257, BC 307, BC 557
16563	2SA787	2SA785, 25V	BC 213, BC 258, BC 308, BC 558
16564	2SA788	50V, 0,03A, 0,15W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...37
16565	2SA789	2SA788, 25V	BC 214, BC 259, BC 309, BC 559
16566	2SA79	20V, Ueb12V, 0,2A, >4MHz	ASY 26...27, ASY 48, ASY 76...77
16567	2SA790(M)	40V, 0,3A, 0,3W, B>1000	BC 516, MPSA 75...77, 2SA1555, 2SB1076
16568	2SA791	2SA790, 25V	BC 516, BC 876, MPSA 75...77, 2SB1076
16569	2SA793	80V, 0,6A, 0,8W, 100MHz	BC 303, BSV 17, 2N3634...37, 2SA606
16570	2SA794	100V, 0,5A, 5W, 120MHz	BD 140, BD 231, BD 380, 2SB874...875
16571	2SA794A	2SA794, 120V	2SA1178, 2SA1184, 2SA1220(A), 2SA1358
16572	2SA795	150V, 0,25A, 10W, 120MHz	2SA1178, 2SA1220A
16573	2SA795A	2SA795, 180V, 1A	2SA1249, 2SB649
16574	2SA796	30V, 0,3A, 0,3W, B40000	BC 516, BC 876, MPSA 75...77, 2SB1076
16575	2SA797	90V, 0,05A, 0,15W, 100MHz	BF 397...398, BF 423, BSS 68, 2SA893
16576	2SA799(F)	60V, 1,5A, 1W, <45/110ns	2N3720
16577	2SA80	20V, 10mA, 60MHz	AF 124...126, AF 200, 2SA218...227
16578	2SA800	20V, 0,03A, 2,5GHz	BFQ 78, BFR 99, 2SA967, 2SA1058
16579	2SA801	20V, 0,05A, 4GHz	BFQ 32, 2SA1057, 2SA1223
16580	2SA802	130V, 0,03A, 0,15W, 50MHz	BF 398, BF 423, BF 435...437, 2SA1370
16581	2SA803	2SA802, 200MHz	BF 398, BF 423, BF 435...437, 2SA1370
16582	2SA804	2SA802, 180MHz	BF 398, BF 423, BF 435...437, 2SA1370
16583	2SA805	2SA802, 180V	BF 423, BF 436...437, 2SA1370...1371
16584	2SA806	2SA802, 210V	BF 423, BF 436...437, 2SA1370...1371
16585	2SA807	60V, 6A, 50W, 10MHz	BD 246A, BD 312, BDX 92, 2N5871...72
16586	2SA808	2SA807, 80V	BD 246B, BD 314, BDX 94, 2N5872
16587	2SA808A	2SA808, 100V	BD 246C, BD 318, BDX 96, 2N6229...30
16588	2SA809	100MHz	BF 470, BF 818, BF 870, 2SA1406...07
16589	2SA81	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16590	2SA810	2SA809, 150/150V	BF 470, BF 818, BF 870, 2SA1406...07
16591	2SA811	50V, 0,03A, 100MHz	BC 856...857, BCW 69...70, BCW 89
16592	2SA811A	2SA811, 120V, 90MHz	2SA1312, 2SA1566
16593	2SA812	60V, 0,1A, 180MHz	BC 856, BCW 89, 2SA1311
16594	2SA813	60V, 0,2A, 200MHz	BCW 68, 2SA1620
16595	2SA814	120V, 1A, 15W, 30MHz	BD 942, 2SA839, 2SA940, 2SB536...537
16596	2SA816	80V, 0,75A, 10W, 100MHz	BD 240B, BD 242B, BD 938, 2SB536...537
16597	2SA817	80V, 0,3A, 0,6W, 100MHz	BC 640, 2N5400...01, 2SA1683, 2SB910
16598	2SA817A	2SA817, 0,4A, 0,8W	BC 640, 2N5400...01, 2SA965, 2SA1533
16599	2SA818	180V, 0,05A, 120MHz	BF 463...465, MPSU 60, 2SA964(A)
16600	2SA819	40V, 0,3A, 0,3W, 240MHz	BC 327, BC 636, 2SA1515, 2SA1683
16601	2SA82	20V, 10mA, 40MHz	AF 124...126, AF 200, 2SA218...227
16602	2SA820	2SA805	2SA805
16603	2SA821	2SA806	2SA806
16604	2SA822	80V, 0,03A, 0,25W, 200MHz	BC 556, 2SA893(A), 2SB715...716(A)



16605	2SA823	2SA822, 50V	BC 212, BC 257, BC 307, BC 557
16606	2SA824	2SA822, 30V	BC 213, BC 258, BC 308, BC 558
16607	2SA825(S)	2SA785, S, Fig.41c	2SA785
16608	2SA825(S)	2SA785, S, Fig.41c	2SA785
16609	2SA826	2SA786	2SA786
16610	2SA827	25V, 0,05A, 0,25W, 180MHz	BC 213, BC 258, BC 308, BC 558
16611	2SA828	50V, 0,03A, 0,25W, 180MHz	BC 214, BC 416, BC 560, 2SA1136...37
16612	2SA829	2SA828, 25V	BC 214, BC 259, BC 309, BC 559, 2SA1137
16613	2SA83	25V, 10mA, 30MHz	AF 124...127, AF 200, 2SA218...227
16614	2SA830(S)	2SA790, S, Fig.41c	2SA790
16615	2SA830(S)	2SA790, S, Fig.41c	2SA790
16616	2SA831	2SA791	2SA791
16617	2SA832	2SA802	2SA802
16618	2SA833	130V, 0,03A, 0,25W, 200MHz	BF 398, BF 423, 2SA1019, 2SB716A
16619	2SA834	2SA833, 0,05A	BF 398, BF 423, 2SA1019, 2SB716A
16620	2SA835	140V, 0,5A, 7,9W	BF 463...465, MPSU 60, 2SA964(A)
16621	2SA836	55V, 0,1A, 0,2W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...37
16622	2SA836	55V, 0,1A, 0,2W, 200MHz	BC 214, BC 416, BC 560, 2SA1136...37
16623	2SA837	90V, 4A, 50W(Tc75°), 10MHz	BD 246C, BD 314, BDX 96, 2N6226...27
16624	2SA838	30V, 0,03A, 0,25W, 300MHz	BC 308, BC 558, BF 324, BF 450...451
16625	2SA839	150V, 1,5A, 25W, 6MHz	2SB861
16626	2SA84	25V, 10mA, 35MHz	AF 124...126, AF 200, 2SA218...227
16627	2SA840	140V, 0,5A, 0,75W, 45MHz	BF 491...493, BF 423A, MPSA 92...93
16628	2SA841	60V, 0,05A, 0,2W, 140MHz	BC 214, BC 416, BC 560, 2SA1136...37
16629	2SA842	2SA841, 40V	BC 214, BC 416, BC 560, 2SA1136...37
16630	2SA843	200V, 0,5A, 20W, 35MHz	BD 240F, 2SA968B, 2SA1133, 2SB861
16631	2SA844	55V, 0,1A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 556
16632	2SA844	55V, 0,1A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 556
16633	2SA845	150V, 0,05A, 0,2W, >40MHz	BF 398, BF 423, BF 435...437, 2SA1370
16634	2SA845A	2SA845, 180V	BF 423, BF 436...437, 2SA1370...71
16635	2SA847	90V, 0,05A, 0,2W, 150MHz	2SA872(A), 2SA941...942, 2SA970
16636	2SA847	90V, 0,05A, 0,2W, 150MHz	2SA872(A), 2SA941...942, 2SA970
16637	2SA847A	2SA847, 120V	2SA872A, 2SA941, 2SA970, 2SA1016
16638	2SA847A	2SA847, 120V	2SA872A, 2SA941, 2SA970, 2SA1016
16639	2SA848	150/120V, 0,05A, 1W, 100MHz	2SA1123...24, 2SA1281, 2SA1285A, 2SA1370
16640	2SA849	2SA848, 150/150V	2SA1123...24, 2SA1281, 2SA1285A, 2SA1370
16641	2SA85	25V, 10mA, 55MHz	AF 124...126, AF 200, 2SA218...227
16642	2SA850	100V, 0,5A, 0,8W, 130MHz	BC 640, 2SA1708, 2SB647, 2SB984
16643	2SA850	100V, 0,5A, 0,8W, 130MHz	BC 640, 2SA1708, 2SB647, 2SB984
16644	2SA851	50V, 0,1A, 0,3W, 150MHz	BC 212, BC 257, BC 307, BC 557
16645	2SA852	2SA852, 35V	BC 213, BC 258, BC 308, BC 558
16646	2SA853	2SA852, 35V,	BC 214, BC 259, BC 309, BC 559, 2SA970
16647	2SA854(S)	40V, 0,5A, 0,4W, 200MHz	BC 327, BC 636, BC 638, 2SA1515
16648	2SA854(S)	40V, 0,5A, 0,4W, 200MHz	BC 327, BC 636, BC 638, 2SA1515
16649	2SA855	60V, 0,05A, 0,15W, 140MHz	BC 212, BC 256, BC 266, BC 556

16650	2SA856(A)	2SA855, 50V,	BC 214, BC 416, BC 560, 2SA1136...37
16651	2SA857	100MHz	BF 398, BF 423, BF 435...437, 2SA1370
16652	2SA858	2SA857, 150/150V	BF 398, BF 423, BF 435...437, 2SA1370
16653	2SA859	MPSA 92	MPSA 92
16654	2SA86	45V, 50mA, 35MHz	AF 121(S), AF 202(S), AFY 18
16655	2SA860	MPSA 93	MPSA 93
16656	2SA861	20V, 2A, 80MHz	2SA473, 2SA699, 2SA748, 2SA887
16657	2SA866	30V, 0,1A, 0,3W, 150MHz	BC 213, BC 258, BC 308, BC 558
16658	2SA867	2SA866, 60V	BC 212, BC 256, BC 266, BC 556
16659	2SA868	2SA866, 90V	2SA970, 2SA1136...1137, 2SA1285(A)
16660	2SA869	30V, 0,4A, 0,5W, 150MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16661	2SA87	30V, 10mA, 100MHz	AF 124, AF 106, AF 306, 2SA340...342
16662	2SA870	2SA869, 60V	BC 327, BC 638, 2SA1683, 2SB910
16663	2SA871	30V, 0,05A, 0,2W, 120MHz	BC 214, BC 259, BC 309, BC 559, 2SA970
16664	2SA872	90V, 0,05A, 0,3W, 120MHz	2SA941...942, 2SA970, 2SA1016, 2SA1038
16665	2SA872A	2SA872, 120V	2SA941, 2SA970, 2SA1016, 2SA1038
16666	2SA873	60V, 0,2A, 0,3W, 220MHz	BC 212, BC 256, BC 266, BC 556
16667	2SA874(M)	2SA854, 0,3W	2SA854
16668	2SA876(H)	70V, 0,5A, 0,35W, 200MHz	BC 640, BCX 39, 2N5400...01, 2SB649
16669	2SA877	80V, 10A, 100W, 15MHz	BD 246B, BD 314, 2N5876, 2SB555...556
16670	2SA878	2SA877, 120V	BD246C, 2N6230...31, 2SB555...56, 2SB681
16671	2SA879	250/200V, 0,07A, 1W, 80MHz	BF 436...437, BF 423A, 2SA1371
16672	2SA88	30V, 10mA, 100MHz	AF 124...125, AF 106, AF 306, 2SA340...342
16673	2SA880	35V, 0,05A, 0,15W, 120MHz	BC 214, BC 259, BC 309, BC 559, 2SA970
16674	2SA881	40V, 1A, 0,6W, 150MHz	BC 636, BC 638, 2SA647, 2SB1116
16675	2SA882	130V, 7A, 100W, 7MHz	BD246D, 2SA982, 2SB681, 2SB695, 2SB696
16676	2SA883	60V, 0,2A, 0,3W, 280MHz	BC 212, BC 256, BC 266, BC 556
16677	2SA885	45V, 1A, 5W, 200MHz	BD 136, BD 227, BD 376, 2SB1007
16678	2SA886	50V, 1,5A, 5W, 150MHz	BD 138, BD 229, BD 376, 2SB744(A)
16679	2SA887	70V, 2A, 10W, 150MHz	2SA748, 2SA1078, 2SA1288
16680	2SA888	25V, 0,05A, 0,35W, 100MHz	BC 213, BC 258, BC 308, BC 558
16681	2SA889	2SA888, 45V	BC 212, BC 257, BC 307, BC 557
16682	2SA89	30V, 10mA, 80MHz	AF 124...125, AF 106, AF 306, 2SA340...342
16683	2SA890	30V, 0,5A, 0,625W, 200MHz	BC 327...328, BC 636, 2SA1515, 2SB910
16684	2SA891	2SA890, 60V	BC 327A, BC 638, BC 640, 2SB647
16685	2SA892	40V, 6A, 40W, B>300	BD 644, BD 896, BDW 24, BDW 64, 2SB1339
16686	2SA893	90V, 0,05A, 0,3W, 120MHz	2SA941...942, 2SA970, 2SA1016, 2SA1038
16687	2SA893A	2SA893, 120V	2SA941, 2SA970, 2SA1016, 2SA1038
16688	2SA894	30V, 1A, 0,6W, 150MHz	BC 636, BC 638, 2SB647, 2SB909
16689	2SA895	30V, 30mA, 500MHz	BF 324, BF 414, BF 506, BF 914, BF 936
16690	2SA896(-1,-2)	200V, 0,1A, 0,75W, 70MHz	BF 436...437, BF 423A, 2SA1370...71
16691	2SA897	60V, 2A, 0,95W, 55MHz	2SA748, 2SA887, 2SA1078, 2SA1288
16692	2SA898	150/120V, 0,05A, 100MHz	BF 470, BF 472, BF 416, BF 418
16693	2SA899	2SA898, 150/150V	BF 470, BF 472, BF 416, BF 418
16694	2SA90	30V, 20mA, >60MHz	AF 124...126, AF 106, AF 306, 2SA340...342

16695	2SA900	20V, 1A, 4W, 200MHz	BD 136, BD 227, BD 376, 2SB1009
16696	2SA901	40V, 0,1A, 0,2W, 100MHz	BC 213, BC 257, BC 307, BC 557
16697	2SA901	40V, 0,1A, 0,2W, 100MHz	BC 213, BC 257, BC 307, BC 557
16698	2SA902	2SA903	BC 214, BC 416, BC 560, 2SA1136...37
16699	2SA903	50V, 0,1A, 0,2W, 150MHz	BC 212, BC 257, BC 307, BC 557
16700	2SA904	90V, 0,05A, 0,2W, 150MHz	2SA893(A), 2SA970, 2SB715...716(A)
16701	2SA904	90V, 0,05A, 0,2W, 150MHz	2SA893(A), 2SA970, 2SB715...716(A)
16702	2SA904A	2SA904, 120V	2SA893A, 2SA970, 2SA1017, 2SB716(A)
16703	2SA904A	2SA904, 120V	2SA893A, 2SA970, 2SA1017, 2SB716(A)
16704	2SA905	120V, 0,05A, 0,8W, 200MHz	BF 398, 2SA893A, 2SA970, 2SA1017
16705	2SA905	120V, 0,05A, 0,8W, 200MHz	BF 398, 2SA893A, 2SA970, 2SA1017
16706	2SA906	40V, 0,1A, 0,2W, 100MHz	BC 214, BC 416, BC 560, 2SA1136...37
16707	2SA906	40V, 0,1A, 0,2W, 100MHz	BC 214, BC 416, BC 560, 2SA1136...37
16708	2SA907	100V, 15A, 150W, 10MHz	BD 318, MJ 2955, 2N6029...6031
16709	2SA908	2SA907, 150V	MJ 15016, 2N6609, 2SA1147, 2SB645
16710	2SA909	2SA907, 200V	MJ 15016, 2SA1116...1117, 2SB552, 2SB645
16711	2SA911	850/550V, 0,1A, 0,47W, 9MHz	-
16712	2SA912(NC)	150V, 0,05A, 0,75W, 200MHz	2SA1016K, 2SA1123...1124, 2SA1482
16713	2SA913	150V, 1A, 15W, 120MHz	2SA968(A,B), 2SA1111...1112, 2SB628(A)
16714	2SA913A	2SA913, 180V	2SA968A,B, 2SA1011, 2SA1112, 2SB628A
16715	2SA914	150V, 0,05A, 200MHz	BF 470, BF 472, BF 416, BF 418
16716	2SA915	120V, 0,05A, 1W, 80MHz	2SA1016...17, 2SA1123...24, 2SB1348
16717	2SA916	2SA915, 160V	2SA1123...24, 2SA1281, 2SB1348
16718	2SA917	120V, 0,1A, 0,75W 70MHz	BF 398, 2SA970, 2SA1136, 2SA1285(A)
16719	2SA918	40V, 0,3A, 0,3W, 200MHz	BC 327, BC 636, 2SA1515, 2SA1683
16720	2SA919	850V, 0,1A, 0,95W, 9MHz	-
16721	2SA92	18V, 5mA, 50MHz	AF 124...126, AF 200, 2SA218...227
16722	2SA920	200V, 0,5A, 7,9W, 40MHz	BF 463...464, MPSU 60
16723	2SA921	120V, 0,02A, 0,25W, 200MHz	2SA941, 2SA970, 2SA1016, 2SA1038
16724	2SA922(-1,-2)	80..100V, 1A, 0,625W, 120MHz	BCX 60, BSS 17, BSW 40, 2N3634...37
16725	2SA923(-1,-2)	200V, 0,2A, 0,625W, 70MHz	BFQ 36...37, BF 616, BF 618, MPSU 60
16726	2SA924	30V, 0,1A, 0,5W, 120MHz	BC 213, BC 258, BC 308, BC 558
16727	2SA925(-1,-2)	30..45V, 30mA, 0,25W, 500MHz	BF 324, BF 414, BF 506, BF 914, BF 936
16728	2SA927	60V, 0,25A, 0,5W, 290MHz	BC 212, BC 256, BC 266, BC 556
16729	2SA928	20V, 1A, 0,25W	-
16730	2SA929	55V, 0,05A, 0,2W, 80MHz	BC 416, BC 560, 2SA970, 2SA1136...37
16731	2SA93	18V, 5mA, 45MHz	AF 124...126, AF 200, 2SA218...227
16732	2SA930	2SA929, 40V	BC 214, BC 416, BC 560, 2SA1136...37
16733	2SA931	>70MHz	BF 398, BF 423, BF 435...437, 2SA1370
16734	2SA932	2SA931, 150/150V	BF 398, BF 423, BF 435...437, 2SA1370
16735	2SA933(A,S,AS)	50(A60)V, 0,1A, 0,3W, 140MHz	BC 212, BC 256, BC 307, BC 557
16736	2SA933(A,S,AS)	50(A60)V, 0,1A, 0,3W, 140MHz	BC 212, BC 256, BC 307, BC 557
16737	2SA933(S)LN	2SA933	BC 416, BC 560, 2SA1039, 2SA1137
16738	2SA933(S)LN	2SA933	BC 416, BC 560, 2SA1039, 2SA1137
16739	2SA934	40V, 1A, 0,75W, 150MHz	BC 327, 2SA1287, 2SB978, 2SB1041

16740	2SA935	2SA934, 80V, 0,7A	BC 640, 2SA965, 2SB647, 2SB1041
16741	2SA936	40V, 0,3A, 0,3W, B>10000	BC 516, BC 876, MPSA 75...77, 2SB1076
16742	2SA937(M)	2SA933	2SA933
16743	2SA937LN,MLN	2SA933	2SA933LN
16744	2SA938	50V, 0,5A, 0,5W	BC 327, BC 638, 2SA1683, 2SB647
16745	2SA939	250V, 0,05A, 130MHz	BF 470, BF 472, BF 416, BF 418
16746	2SA94	9V, 10mA, 45MHz	AF 124...127, AF 200, 2SA218...227
16747	2SA940	150V, 1,5A, 25W, 4MHz	2SA839, 2SB608, 2SB628(A), 2SB861
16748	2SA941	120V, 0,05A, 0,3W, 150MHz	2SA872A, 2SA992, 2SA1016, 2SA1038
16749	2SA942	2SA941, 90V	2SA872(A), 2SA992, 2SA1016, 2SA1038
16750	2SA949	150V, 0,05A, 0,8W, 120MHz	2SA1019, 2SA1124, 2SA1285A, 2SA1482
16751	2SA95	20V, 10mA, 50MHz	AF 124...127, AF 200, 2SA218...227
16752	2SA950	35V, 0,8A, 0,6W, 120MHz	BC 327...328, BC 636, BC 638, 2SB647
16753	2SA951	140V, 0,5A, 45MHz	2SA913(A), 2SA1111...1112, 2SA1195
16754	2SA952	30V, 0,7A, 0,6W, 160MHz	BC 327...328, BC 636, 2SB909...910
16755	2SA953	60V, 0,3A, 0,6W, 100MHz	BC 327A, BC 638, 2SA1683, 2SB647
16756	2SA954	2SA953, 80V	BC 640, BCX 39, 2N5400...01, 2SB647
16757	2SA956	60V, 0,1A, 280MHz	BC 856, BCW 89, 2SA1311...12
16758	2SA957	150V, 2A, 30W, 20MHz	2SA1079, 2SA1133, 2SB628, 2SB861
16759	2SA958	2SA957, 200V	2SA1133, 2SB861
16760	2SA959	100V, 10A, 100W	BUW 96, MJ 15016, 2SA1116...17, 2SA1147
16761	2SA96	20V, 10mA, 45MHz	AF 124...127, AF 200, 2SA218...227
16762	2SA962	60V, 1,5A, 100MHz	BD 518, BD 520, BD 526, BD 528, BD 530
16763	2SA962A	2SA962	BD 816, BD 818, BD 842, BD 844, 2SA887
16764	2SA963	50V, 1,5A, 10W, 150MHz	BD 138, BD 229, BD 376, 2SB874...875
16765	2SA964	200V, 0,2A, 10W, 100MHz	BF 463...465, MPSU 60
16766	2SA964A	2SA964, 250V	BF 463...465, MPSU 60
16767	2SA965	120V, 0,8A, 0,9W, 120MHz	2SA1013, 2SA1275, 2SB647, 2SB1212
16768	2SA966	30V, 1,5A, 0,9W, 120MHz	2SA1382, 2SB978, 2SB892, 2SB1312
16769	2SA967	15V, 0,03A, 4GHz	BFQ 23, BFQ 56, BFQ 75...76
16770	2SA968	160/160V, 1,5A, 25W, 100MHz	2SA1011, 2SA1133, 2SA1112, 2SA1332
16771	2SA968A	2SA968, 180/180V	2SA1011, 2SA1133, 2SA1112, 2SB628A
16772	2SA968B	2SA968, 200/200V	2SA1133, 2SB861
16773	2SA969	2SA968	2SA1011, 2SA1133, 2SA1112, 2SA1332
16774	2SA97	20V, 10mA, 40MHz	AF 124...127, AF 200, 2SA218...227
16775	2SA970	120V, 0,1A, 0,3W, 100MHz	2SA1038, 2SA1049, 2SA1123, 2SA1136
16776	2SA971	150V, 15A, 150W, 10MHz	MJ 15016, 2SA908...909, 2SA1116...17
16777	2SA972	30V, 0,1A, 0,25W, 150MHz	BC 213, BC 257, BC 308, BC 558
16778	2SA973	60V, 0,05A, 0,25W	BC 214, BC 416, BC 560, 2SA1136...1137
16779	2SA977	180V, 0,05A, 80MHz	BF 470, BF 472, 2SA1352...53, 2SA1361
16780	2SA977A	2SA977, 220V	BF 470, BF 472, 2SA1353, 2SA1361
16781	2SA978	40V, 0,1A, 0,2W, 125MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16782	2SA978	40V, 0,1A, 0,2W, 125MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16783	2SA98	20V, 10mA, 30MHz	AF 124...127, AF 200, 2SA218...227
16784	2SA980	100V, 8A, 80W, 20MHz	BD 246C, BDW 52C, 2SB555...556, 2SB681

16785	2SA981	2SA980, 120V	BD246D, 2N6230...31, 2SB555...56, 2SB681
16786	2SA982	2SA980, 140V	BD246D, 2N6231, 2SB555, 2SB681, 2SB697
16787	2SA983	30V, 20mA, 1GHz	BF 479...480, BF 679...680, BF 967...970
16788	2SA984	60V, 0,5A, 0,6W, 120MHz	BC 638, 2N5400...01, 2SB647, 2SB1116
16789	2SA984K	2SA984, 100V	BC 640, 2N5400...01, 2SA840, 2SB647
16790	2SA985	120V, 1,5A, 25W, 180MHz	2SA968, 2SA1078...1079, 2SB628(A)
16791	2SA985A	2SA985, 150V	2SA968, 2SA1079, 2SA1133, 2SB628(A)
16792	2SA986	130V, 7A, 80W, 60MHz	2SB618, 2SB758A
16793	2SA987	40V, 0,1A, 0,5W, 90MHz	BC 213, BC 257, BC 307, BC 557
16794	2SA988	120V, 0,05A, 0,5W, 100MHz	BF 423, 2SA893A, 2SA970, 2SB717(A)
16795	2SA989	60V, 0,1A, 0,25W, 180MHz	BC 212, BC 256, BC 266, BC 556
16796	2SA99	20V, 10mA, 20MHz	AF 124...127, AF 200, 2SA218...227
16797	2SA990	60V, 0,1A, 0,25W, 180MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16798	2SA991	60V, 0,1A, 0,5W, 90MHz	BC 214, BC 416, BC 560, 2SA1136...1137
16799	2SA992	120V, 0,05A, 0,5W, 100MHz	2SA872A, 2SA941, 2SA970, 2SA1136
16800	2SA993	50V, 0,5A, 0,625W, 120MHz	BC 327, BC 638, 2SA1683, 2SB1116
16801	2SA994	40V, 0,3A, 0,5W, 120MHz	BC 327, BC 638, 2SA1683, 2SB1116
16802	2SA994	40V, 0,3A, 0,5W, 120MHz	BC 327, BC 638, 2SA1683, 2SB1116
16803	2SA997	20V, 1A, 0,5W, 150MHz	BC 636, BC 638, 2SB647, 2SB909...910
16804	2SA998	2SA997, 50V	BC 636, BC 638, 2SB647, 2SB910
16805	2SA999	50V, 0,2A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 557
16806	2SA999L	2SA999	BC 416, BC 560, 2SA970, 2SA1136...1137
16807	2SB100	30V, 0,05A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
16808	2SB1000	25V, 1A, 200MHz	BC 869, BCX 51...53, BCX 69, 2SA1364
16809	2SB1000A	2SB1000, 30V	BCX 51...53, 2SA1213, 2SA1364, 2SB766A
16810	2SB1001	20V, 2A, 150MHz	2SA1314, 2SA1363, 2SB1121, 2SB1313
16811	2SB1002	70V, 1A, 150MHz	BCX 53, 2SB803...804, 2SB1025...26
16812	2SB1003	60V, 3A, 25W, B5000	BD 716, BDW 24A, BDW 54A, 2SB751
16813	2SB1003	60V, 3A, 25W, B5000	BD 716, BDW 24A, BDW 54A, 2SB751
16814	2SB1004	100V, 4A, 30W, B4000	BDW 24C, BDW 54C, BDW 64C, 2SB751B
16815	2SB1004	100V, 4A, 30W, B4000	BDW 24C, BDW 54C, BDW 64C, 2SB751B
16816	2SB1005	50V, 4A, 30W, B3000	BD 716, BDW 24A, BDW 54A, 2SB751
16817	2SB1007	80V, 0,7A, 10W, 100MHz	BD 140, BD 231, 2SA1184, 2SA1220
16818	2SB1008	B>1000	BD 776, BD 778, BD 780, 2SB794...795
16819	2SB1009	40V, 2A, 10W, 100MHz	BD 376, 2SB1009, 2SA1217, 2SB1217
16820	2SB101	30V, 0,05A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
16821	2SB1010	2SB1009, 0,75W	2SA1315, 2SA1382, 2SB892, 2SB1312
16822	2SB1011	400/400V, 0,1A, 70MHz	2SA1156, 2SA1354
16823	2SB1012	120V, 1,5A, 20W, B>2000	BD 684
16824	2SB1013	20V, 2A, 0,7W	MPS750...751, 2SB733, 2SB738...739, 2SB911
16825	2SB1014	60V, 1A, 0,7W	BC 638, BC 640, 2SB647, 2SB910, 2SB1041
16826	2SB1015	60V, 3A, 25W, 9MHz	2SA1440, 2SB1015, 2SB1094, 2SB1274
16827	2SB1016	100V, 5A, 30W, 5MHz	2SA1441, 2SB1016, 2SB1294
16828	2SB1017	80V, 4A, 25W, 9MHz	2SA1441, 2SA1635, 2SB1017, 2SB1335
16829	2SB1018	100V, 7A, 30W, 10MHz	BDX 78F, 2SA1442



16830	2SB1019	70V, 7A, 30W, 10MHz	BDX 78F, 2SA1470, 2SB1097, 2SB1290
16831	2SB102	30V, 0,05A, 0,18W	AC 128K, AC 153K, AC 188K, 2N1191...94
16832	2SB1020	100V, 7A, 30W, B2k..15k	2SB1099, 2SB1228, 2SB1283
16833	2SB1021	2SB1020, 80V	2SB1099, 2SB1228, 2SB1283
16834	2SB1022	2SB1020, 60V	2SB1099, 2SB1224, 2SB1228, 2SB1283
16835	2SB1023	60V, 3A, 20W, B5000	2SB1223, 2SB1226, 2SB1257, 2SB1342
16836	2SB1024	100V, 4A, 30W, B4000	2SB1098, 2SB1227, 2SB1282
16837	2SB1025	120/80V, 1A, 140MHz	2SB1027...1028
16838	2SB1026	2SB1025, 120/100V	2SB1027...1028
16839	2SB1027	180/120V, 1,5A	-
16840	2SB1028	2SB1027, 180/160V	-
16841	2SB1029	100V, 2A	2SA1417, 2SB1027...1028
16842	2SB103	30V, 0,1A, 0,125W	AC 128, AC 153, AC 188, 2N1191...94
16843	2SB1030	2SB643, 0,3W	2SB643
16844	2SB1030A	2SB644, 0,3W	2SB643
16845	2SB1031	100V, 15A, 100W, B>1000	BDV 66A, BDW 84C, 2SB969
16846	2SB1032(K)	120V, 10A, 80W, B>1000	BDV 64C, BDV 66B, BDW 84D
16847	2SB1033	60V, 3A, 40W	BD 242B, BD 538, BD 952, 2SA1262
16848	2SB1034	80V, 2A, 15W, 50MHz, B5000	BD 680, BD 780, 2N6036, 2SB795
16849	2SB1035	30V, 1A, 0,9W, 100MHz	2SA966, 2SB764, 2SB978, 2SB1041
16850	2SB1036	2SB788, 0,3W, 200MHz	2SB788
16851	2SB1037	150V, 1,5A, 30W, 15MHz	BD 240D, 2SB861, 2SA940, 2SB628(A)
16852	2SB1038	60V, 3A, 30W, 20MHz	BD 242A, BD 536, BD 936, 2SA1266
16853	2SB1038	60V, 3A, 30W, 20MHz	BD 242A, BD 536, BD 936, 2SA1266
16854	2SB1039	100V, 4A, 40W, 20MHz	BD 244C, BD 540C, BD 954, 2SB682
16855	2SB1039	100V, 4A, 40W, 20MHz	BD 244C, BD 540C, BD 954, 2SB682
16856	2SB104	30V, 0,1A, 0,18W	AC 128K, AC 153K, AC 188K, 2N1191...94
16857	2SB1040	20V, 2A	2SA1241, 2SA1243, 2SB962, 2SB1182
16858	2SB1041	80V, 1A, 0,9W	2SA1013, 2SA1275, 2SB647, 2SB1041
16859	2SB1042(M)	2SB1041, 1W	2SA1013, 2SA1275, 2SB647, 2SB1041
16860	2SB1043	2SB1041, 50V	2SB647, 2SB764, 2SB892, 2SB1041
16861	2SB1044(M)	2SB1041, 50V, 1W	2SB647, 2SB764, 2SB892, 2SB1041
16862	2SB1045	120V, 0,05A, 140MHz	2SA1173, 2SA1200, 2SB1046...1047
16863	2SB1046	180V, 0,05A, 140MHz	2SB1047
16864	2SB1047	180V, 0,05A, 140MHz	2SB1046
16865	2SB1048	60V, 1A, B>2000	BST 60...62, 2SB1126
16866	2SB1049	30V, 0,1A, 0,4W	BC 213, BC 258, BC 308, BC 558
16867	2SB105	30V, 0,5A, 0,5W	2SB493, AD 162
16868	2SB1050	2SB873	2SD873
16869	2SB1051	40V, 0,3A	BC 807R, BCX 17R, BCW 67R...68R
16870	2SB1051K	2SB1051, 1A	-
16871	2SB1052	60V, 2A, 25W, 25MHz	BD 936F, 2SB1187, 2SB1314, 2SB1375
16872	2SB1053	40V, 0,1A	BC 856...857, BCW 69...70, BCW 89
16873	2SB1054	100V, 5A, 60W, 20MHz	2SB1371...72, BD 246C, BDV 96, 2SB688
16874	2SB1055	2SB1054, 120V, 6A, 70W	2SB1361, 2SB1372, BD 246C, 2SA1141



16875	2SB1056	2SB1054, 140V, 7A, 80W	2SB1361, 2SB1372, BD 246D, 2SA1186
16876	2SB1057	2SB1054, 150V, 9A, 100W	2SB1860, BD 246D, 2SA1227A, 2SA1386
16877	2SB1058	20V, 2A, 0,75W, 80MHz	MPS 750, 2SB733, 2SB738...739, 2SB892
16878	2SB1059	70V, 1A, 0,75W, 65MHz	BC 640, 2SB647, 2SB910, 2SB984, 2SB1041
16879	2SB106	2SB106, 3W	2SB493, AD 162
16880	2SB1060	70V, 1A, 1W	BC 640, 2SB647, 2SB910, 2SB984, 2SB1041
16881	2SB1061	B5000	2SB1401, 2SB1465
16882	2SB1062	15V, 0,5A, 0,6W, 130MHz	BC 327...328, BC 636, 2SA1515, 2SB909
16883	2SB1063	2SB1054	BD 954AF, BDT 42AF, 2SB1016, 2SB1294
16884	2SB1064	60V, 3A, 30W, 70MHz	BD 242A, BD 536, BD 936, 2SA1288
16885	2SB1065	2SB1064, 10W	BD 178, BD 190, BD 786, 2SB744(A)
16886	2SB1066(M)	2SB1064, 1W	2SA1707, 2SA1761, 2SB985, 2SB1066
16887	2SB1067	80V, 2A, 10W, B5000	BD 680, BD 780, 2N6036, 2SB795
16888	2SB1068	20V, 2A, 0,75W, 180MHz	MPS 750, 2SB733, 2SB738...739, 2SB892
16889	2SB1069	40V, 4A, 25W, 150MHz	2SA1012, 2SA1289, 2SB919
16890	2SB1069A	2SB1069, 50V	2SA1012, 2SA1289, 2SB919
16891	2SB107	30V, 2A, 10W	AD 149, 2N2137, 2N2142, 2SB449
16892	2SB1070(A)	2SB1069(A)	2SB1267, 2SA1012, 2SA1289, 2SB919
16893	2SB1071(A)	2SB1069(A)	2SA1307, 2SA1469, 2SB953(A)
16894	2SB1072L,S	100V, 4A, 20W, B>1000	2SB908, BDW 24C, BDW54C, 2SB751B
16895	2SB1073	30V, 4A, 120MHz	2SB1308, 2SB1386
16896	2SB1074	400/400V, 0,5A, 1W	2SA1625, 2SB1488
16897	2SB1075	50V, 2A, 150MHz	BD 376, 2SB1065, 2SB1217
16898	2SB1076(M)	40V, 2A, 1W, 150MHz, B20000	2SB1129, 2SB865
16899	2SB1077	60V, 4A, 40W, B>1000	BD 716, BDW 24A, BDW 54A, 2SB751
16900	2SB1078	120V, 8A, 40W, B>1000	BD 652, BDT 20, BDW 74D, BDX 54D
16901	2SB1079	100V, 20A, 100W, B>1000	2SB1383
16902	2SB107A	2SB107, 60V	AD 166, 2N2137, 2N2142
16903	2SB108	40V, 0,5A, 0,5W	2SB493, AD 162
16904	2SB1080	35V, 2A, 10W	BD 508, BD 516, BD 526, BD 814
16905	2SB1085	120V, 1,5A, 20W, 50MHz	BD 940, 2SA985(A), 2SA1078, 2SA1393
16906	2SB1085A	2SB1085, 160V	2SA968(A,B), 2SB628(A), 2SA1011, 2SA1332
16907	2SB1086	2SB1085, 10W	2SA1021, 2SA1249, 2SB649
16908	2SB1086A	2SB1086, 160V	2SA1249, 2SB649
16909	2SB1087	100V, 5A, 30W, B8000	BD 650, BD 902, BDW 24C, BDW 64C
16910	2SB1088	100V, +-10A, 60W, B6000	BDT 62B
16911	2SB1088	100V, +-10A, 60W, B6000	BDT 62B
16912	2SB1089	60V, 3A, 30W, 20MHz	BD 242A, BD 536, BD 936, 2SA1288
16913	2SB108A	2SB108, 60V	-
16914	2SB108B	2SB108, 80V	-
16915	2SB109	2SB108, 3W	2SB493, AD 162
16916	2SB1090	100V, 4A, 40W, 20MHz	BD 244A, BD 536, BD 950, 2SA1293
16917	2SB1091	60V, 8A, 40W, B>1000	BD 646, BD 898, BDW 74A, BDX 54A
16918	2SB1092	80V, 1,5A, 8W, B10000	BD 680, BD 780, 2N6036, 2SB795, 2SB1012
16919	2SB1093	80V, +-1,5A, 1W, B>2000	2SB678, 2SB865, 2SB1129, 2SB1406

16920	2SB1094	2SB1089, , 15W	2SA1394, 2SA1488, 2SB1015, 2SB1274
16921	2SB1095	2SB1090, , 20W	2SA1441, 2SB1016, 2SB1294, BD 240C
16922	2SB1096	200V, 2A, 25W, 5MHz	BD240F,2SA1133,2SB630,2SB720,2SB861
16923	2SB1097	80V, 7A, 30W	2SA1396, 2SA1442, 2SA1470, 2SB1290
16924	2SB1098	B8000	2SB1258, 2SB1340
16925	2SB1099	100V, 8A, 25W, 80MHz, B6000	2SB1100, 2SB1284
16926	2SB109A	2SB108, 60V, 3W	-
16927	2SB109B	2SB108, 80V, 3W	-
16928	2SB110	25V, 0,05A, 0,1W, $\beta > 18$	AC 125...126, AC 151, 2SB54, 2SB56
16929	2SB1100	B6000	2SB1284
16930	2SB1101	60V, 4A, 40W, $B > 1000$	BD 716, BD 718, BDW 54A...D, BDW 64B...D
16931	2SB1102	2SB1101, 80V	BD 718, BDW 54B, BDW 64B, 2SB885
16932	2SB1103	60V, 8A, 40W, $B > 1000$	BD 646, BD 898, BDW 74A, BDX 54A
16933	2SB1104	2SB1103, 80V	BD 648, BD 900, BDW 74B, BDX 54B
16934	2SB1105	120V, 3A, 30W, $B > 1000$	BDT 60C, BDW 54D, 2SB1339
16935	2SB1106	120V, 6A, 40W, $B > 1000$	BD 652, BDT 20, BDW 64D, 2SB1339
16936	2SB1107	120V, 10A, 40W, B5000	BDT 62C, BDX 34D
16937	2SB1108	$B > 1000$	BD 652F, BDT 62CF, 2SB1259, 2SB1107
16938	2SB1109	160V, 0,1A, 140MHz	BF 416, BF 418, 2SA1352...1353, 2SA1380
16939	2SB111	2SB110, $\beta > 30$	AC 125...126, AC 151, 2SB54, 2SB56
16940	2SB1110	2SB1109, 200/200V	BF 416, BF 418, 2SA1352...1353, 2SA1380
16941	2SB1111	60V, +-2A, 10W, $B > 2000$	2SB794...795, 2SB1012
16942	2SB1112	120V, 6A, 40W, B5000	BDT 20, BD 652, BDW 64D, 2SB1339
16943	2SB1112	120V, 6A, 40W, B5000	BDT 20, BD 652, BDW 64D, 2SB1339
16944	2SB1113	120V, 8A, 40W, B5000	BDT 20, BD 652, BDW 74D, 2SB1107
16945	2SB1113	120V, 8A, 40W, B5000	BDT 20, BD 652, BDW 74D, 2SB1107
16946	2SB1114	20V, 2A, 180MHz	2SA1203, 2SA1213, 2SA1314, 2SA1369
16947	2SB1115	60V, 1A, $> 80$ MHz	2SA1364, 2SB1122...23, 2SB1520
16948	2SB1115A	2SB1115, 80V	2SB1520
16949	2SB1116	60V, 1A, 0,75W, 120MHz	2SA1315, 2SA1706, 2SB892, 2SB1229
16950	2SB1116A	2SB1116, 80V	2SA1315, 2SA1708...09, 2SB1459
16951	2SB1117	30V, 3A, 1W, 280MHz	2SB985, 2SB1505
16952	2SB1118	20V, 0,7A, 250MHz	2SA1734, BC 869, BCX 51...53, BCX 69
16953	2SB1119	25V, 1A, 180MHz	BC 869, BCX 51...53, BCX 69, 2SA1314
16954	2SB112	2SB110, $\beta > 43$	AC 125...126, AC 151, 2SB54, 2SB56
16955	2SB1120	20V, 2,5A, 250MHz	2SB1301, 2SB1518
16956	2SB1121	30V, 2A, 150MHz	2SA1681, 2SB1313...14, 2SB1518
16957	2SB1122	60V, 1A, 150MHz	2SA1364, 2SB1115(A), BCX 52...53
16958	2SB1123	60V, 2A, 150MHz	2SA1681, 2SB1520, 2SA1417, 2SB1029
16959	2SB1124	60V, 3A, 150MHz	2SA1736, 2SB1572
16960	2SB1125	80V, 0,7A, 170MHz, $B > 5000$	BST 61...62
16961	2SB1126	80V, 1,5A, 120MHz, $B > 4000$	-
16962	2SB1127	25V, 5A, 10W, 320MHz	2SA1120, 2SA1357
16963	2SB1128	50V, 2A, 10W, B5000	-
16964	2SB1129	80V, +-1,5A, 1W, B10000	2SB865

16965	2SB113	2SB110, B>61	AC 125...126, AC 151, 2SB54, 2SB56
16966	2SB1130(M)	120V, 1,5A, 1W, 50MHz	2SB1212, 2SB1236
16967	2SB1130A(M)	2SB1130, 160V	2SA1770, 2SB1212, 2SB1236A
16968	2SB1131	2SB1127, 1W	2SB1288, 2SB1306
16969	2SB1132	40V, 1A, 150MHz	BCX 51...53, 2SA1364, 2SB766A, 2SB1123
16970	2SB1133	60V, 3A, 25W, 40MHz	2SA1635, 2SA1488, 2SB1094, 2SB1274
16971	2SB1134	60V, 5A, 25W, 30MHz	2SA1307, 2SA1441, 2SA1469, 2SB1019
16972	2SB1135	60V, 7A, 30W, 10MHz	2SA1442, 2SA1470, 2SB1018...19
16973	2SB1136	60V, 12A, 30W, 10MHz	2SA1451...52, 2SA1568, 2SB1468
16974	2SB1137	100V, 10A, 65W, B6000	2SB1388
16975	2SB114	25V, 0,05A, 0,1W, B>45	AC 125...126, AC 151, 2SB54, 2SB56
16976	2SB1140	2SB1127	2SA1357
16977	2SB1141	20V, 1,2A, 10W, 150MHz	2SA1359, 2SB891, BD 136, BD 166, BD 227
16978	2SB1142	60V, 2,5A, 10W, 140MHz	BD 178, BD 188, BD 440, 2N5194
16979	2SB1143	60V, 4A, 10W, 150MHz	BD 188, BD 440, BD 786, 2SB986
16980	2SB1144	120V, 1,5A, 40W, 100MHz	2SA1408, 2SA1507, 2SA1021, 2SA1249
16981	2SB1145	120V, 3A, 20W, B5000	BDT 60CF, 2SB1340
16982	2SB1145	120V, 3A, 20W, B5000	BDT 60CF, 2SB1340
16983	2SB1146	120V, 6A, 25W, B5000	BD 652F, 2SB1340, 2SB1259
16984	2SB1146	120V, 6A, 25W, B5000	BD 652F, 2SB1340, 2SB1259
16985	2SB1147	120V, 8A, 25W, B5000	BD 652F, 2SB1259
16986	2SB1147	120V, 8A, 25W, B5000	BD 652F, 2SB1259
16987	2SB1148(A)	2SB936(A), 15W	-
16988	2SB1149	100V, +-3A, 15W, B10000	-
16989	2SB115	2SB114, B>60	AC 125...126, AC 151, 2SB54, 2SB56
16990	2SB1150	60V, 3A, 15W, B10000	-
16991	2SB1151	60V, 5A, 20W, <1/3,5µs	-
16992	2SB1152	160V, 12A, 120W	BD 746F, 2SA1386(A), 2SA1516, 2SB817
16993	2SB1153	170V, 15A, 150W	2SA1302, 2SA1553, 2SB1163
16994	2SB1154	130V, 10A, 70W, 30MHz	2SA1672, 2SA1805, BD 246D, 2SA1146
16995	2SB1155	130V, 15A, 80W, 25MHz	2SB1860, BD 746D, 2SA1227, 2SA1386
16996	2SB1156	130V, 20A, 100W, 25MHz	BD 250D, BD 746D
16997	2SB1157	100V, 5A, 60W, 20MHz	2SB1371...72, BD246C, BDV96, 2SA1141
16998	2SB1158	120V, 6A, 70W, 20MHz	2SB1371...72, BD 246D, 2SA1146, 2SA1186
16999	2SB1159	140V, 7A, 100W, 20MHz	2SB1361, BD 246D, 2SA1146, 2SA1186
17000	2SB116	2SB114, B>80	AC 125...126, AC 151, 2SB54, 2SB56
17001	2SB1160	150V, 9A, 100W, 20MHz	BD 246D, 2SA1186, 2SA1227, 2SA1386
17002	2SB1161	160V, 12A, 120W, 20MHz	2SA1673, BD 746F, 2SA1386, 2SB817
17003	2SB1162	2SB1161	2SA1301...1302, 2SB1153, 2SB1347
17004	2SB1163	180V, 15A, 150W, 20MHz	2SA1302, 2SA1553, 2SB1429
17005	2SB1164	60V, 2A, 1W	MPS 750...751, 2SA1315, 2SA1429, 2SB892
17006	2SB1165	60V, 5A, 20W, 130MHz	-
17007	2SB1166	60V, 8A, 20W, 130MHz	-
17008	2SB1167	120V, 3A, 20W, 130MHz	-
17009	2SB1168	120V, 4A, 20W, 130MHz	-

17010	2SB1169(A)	2SB954(A), 15W	2SB839, 2SB957...958, 2SB1201
17011	2SB117	2SB114, B>105	AC 125...126, AC 151, 2SB54, 2SB56
17012	2SB1170	2SB1052, 15W	2SB839, 2SB957...958, 2SB1201
17013	2SB1171(A)	2SB928(A), 15W	2SB768, 2SB928(A)
17014	2SB1172(A)	2SB929(A), 15W	2SB906, 2SB1184, 2SB1202
17015	2SB1173(A)	2SB930(A), 15W	2SA1395, 2SA1401, 2SB1203, 2SB1244
17016	2SB1174	2SB931, 15W	-
17017	2SB1175	2SB932, 15W	-
17018	2SB1176	2SB933, 15W	-
17019	2SB1177	2SB934, 15W	-
17020	2SB1178(A)	2SB937(A), 15W	2SB907, 2SB1214
17021	2SB1179(A)	2SB938(A), 15W	-
17022	2SB118	15V, 1,5A, 50W	AD 149, 2N2137, 2N2142, 2SB449
17023	2SB1180(A)	2SB939(A), 15W	-
17024	2SB1181(F5)	80V, 1A, 10W, 100MHz	2SB839, 2SB957...958
17025	2SB1182(F5)	40V, 2A, 10W, 100MHz	2SA1241, 2SB838, 2SB1201
17026	2SB1183(F5)	40V, 2A, 10W, B>1000	2SB907, 2SB1214
17027	2SB1184(F5)	60V, 3A, 15W, 70Mhz	2SA1876, 2SB906, 2SB1202
17028	2SB1185	2SB1184, 25W	2SA1307, 2SA1440, 2SA1469, 2SB1274
17029	2SB1186	120V, 1,5A, 20W, 50MHz	2SA1306, 2SA1332, 2SA1393, 2SA1606
17030	2SB1186A	2SB1186, 160V	2SA1306(A,B), 2SA1332, 2SA1606
17031	2SB1187	60V, 3A, 30W, 12MHz	2SA1440, 2SA1469, 2SB1015, 2SB1094
17032	2SB1188	40V, 2A, 100MHz	2SA1213, 2SB1123
17033	2SB1189	80V, 0,7A, 100MHz	BCX 53, 2SB803...805, 2SB1025...1026
17034	2SB119	2SB118, 32V	AD 149, 2N2137, 2N2142, 2SB449
17035	2SB1190	200/150V, 1A, 25W, 20MHz	BD 240F, 2SB630, 2SA968B, 2SB861
17036	2SB1190	200/150V, 1A, 25W, 20MHz	
17037	2SB1190A	2SB1190, 200/180V	BD 240F, 2SB630, 2SA968B, 2SB861
17038	2SB1191(A)	2SB1190(A)	2SB928, 2SB630, 2SA968B, 2SB861
17039	2SB1192(A)	2SB1190(A)	2SA1306B, 2SA1668, 2SB1096, 2SB1530
17040	2SB1193	B>1000	BD 652F, BDT 62CF, 2SB1259
17041	2SB1194	B>1500	2SB1098, 2SB1227, 2SB1258, 2SB1340
17042	2SB1195	100V, 8A, 50W, B5000	2SB1099...1100, 2SB1284
17043	2SB1196	70V, 4A, 25W	2SA1394, 2SA1469, 2SB1019, 2SB1095
17044	2SB1196	70V, 4A, 25W	2SA1394, 2SA1469, 2SB1019, 2SB1095
17045	2SB1197K	40V, 0,8A, 200MHz	BCW 67...68
17046	2SB1198K	80V, 0,5A, 180MHz	BCX 42
17047	2SB1199	15V, 1A, 0,3W	BC 327...328, 2SA1515
17048	2SB119A	2SB118, 60V	AD 166...167, 2N2139, 2N2144
17049	2SB12	30V, 0,05A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
17050	2SB120	32V, 0,02A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17051	2SB1201	60V, 2A, 15W, 150MHz	-
17052	2SB1202	60V, 3A, 15W, 150MHz	2SA1244
17053	2SB1203	60V, 5A, 20W, 130MHz	2SA1244
17054	2SB1204	60V, 8A, 20W, 130MHz	-

17055	2SB1205	25V, 5A, 10W, 320MHz	-
17056	2SB1206	2SB774, 0,3W	2SB774
17057	2SB1207	15V, 0,5A, 0,3W, 130MHz	BC 327...328, BC 636, 2SA1515, 2SB909
17058	2SB1208	120MHz	2SA1213, 2SA1314, 2SA1363, 2SB1121
17059	2SB1209	400/400V, 0,1A, 1W, 70MHz	2SA1363, 2SA1372, 2SA1584, 2SA1760
17060	2SB121	105V, 0,1A, 0,05W	ACY 39, 2N4042...4043
17061	2SB1210	20V, 2A, 0,5W, 80MHz	MPS 750, 2SB733, 2SB738...739, 2SB892
17062	2SB1211	2SB1210, SMD	2SA1213, 2SA1314, 2SA1363, 2SB1121
17063	2SB1212	160V, 1,5A, 0,9W, 50MHz	2SA1770, 2SB1130A, 2SB1236A
17064	2SB1213	120V, 10A, 30W, B5000	BDT 62CF, 2SB1259
17065	2SB1213	120V, 10A, 30W, B5000	BDT 62CF, 2SB1259
17066	2SB1214	80V, 3A, 15W, B5000	2SB908, 2SB1072, 2SB1303
17067	2SB1215	120V, 3A, 20W, 130MHz	2SA1647
17068	2SB1216	120V, 4A, 20W, 130MHz	2SA1647
17069	2SB1217	60V, 3A, 10W, 50MHz	2SB986
17070	2SB1218	2SB709	2SA1576, 2SA1586, 2SA1603, 2SA1622
17071	2SB1218A	2SB709A	2SA1576, 2SA1586, 2SA1603, 2SA1622
17072	2SB1219	2SB710	2SA1577, 2SA1588
17073	2SB1219A	2SB710A	-
17074	2SB122	80V, 1,5A, 20W	AD 167, 2N2141, 2N2146
17075	2SB1220	2SB792	2SA1609
17076	2SB1221	250/200V, 0,07A, 1W, 80MHz	BF 423A, BF 436, BF 492, 2SA1371...72
17077	2SB1222	40V, 0,2A, -/<300ns	BSR 15...16, BSR 18, 2SA1338
17078	2SB1223	70V, 4A, 20W, 20MHz, B5000	2SB1024, 2SB1098, 2SB1282, 2SB1342
17079	2SB1224	70V, 7A, 25W, 20MHz, B5000	2SB1021, 2SB1099, 2SB1228, 2SB1283
17080	2SB1225	70V, 10A, 30W, 20MHz, B5000	2SB1100, 2SB1259, 2SB1284
17081	2SB1226	110V, 3A, 20W, 20MHz, B4000	BDT 60CF, 2SB1340
17082	2SB1227	110V, 5A, 25W, 20MHz, B4000	2SB1340, 2SB1344
17083	2SB1228	110V, 8A, 30W, 20MHz, B4000	2SB1193, 2SB1259, 2SB1344
17084	2SB1229	60V, 2A, 0,75W, 150MHz	2SA1706, 2SB892, 2SB1312, 2SB1433
17085	2SB123	40V, 5A, 20W	AD 166...167, 2N1529...38, 2N1539...48
17086	2SB1230	110V, 15A, 100W	-
17087	2SB1231	110V, 25A, 120W	-
17088	2SB1232	110V, 40A, 150W	-
17089	2SB1233(A)	2SB1192(A), 15W	2SB768, 2SB842, 2SB928(A)
17090	2SB1234	2SB1235, SMD	BCV 46
17091	2SB1235	80V, 0,2A, B>5000	-
17092	2SB1236	2SB1130,A(M,AM)	2SB1130...
17093	2SB1237	2SB909	2SB909
17094	2SB1238	2SB910	2SB910
17095	2SB1239	2SB1076(M)	2SB1076
17096	2SB1240	2SB911	2SB911
17097	2SB1241	80V, 1A, 1W	BC 640, BCX 23, BCX 39, 2SB647
17098	2SB1242	50V, 1A, 1W	BC 327, BC 638, BC 640, 2SB647
17099	2SB1243	2SB1066	2SB1066

17100	2SB1244	160/160V, 0,1A, 0,9W, 140MHz	BF 423A, BF 435, BF 491, 2SA1370...72
17101	2SB1245	2SB1244, 200/200V	BF 423A, BF 436, BF 491, 2SA1370...73
17102	2SB1246	40V, 2A, 10W	2SA1241, 2SB838, 2SB1182, 2SB1201
17103	2SB1247	60V, 1,5A, 10W	2SB839, 2SB957...960, 2SB1201...02
17104	2SB1248	110V, 0,8A, 10W	2SA1592, 2SB844...845, 2SB959...960
17105	2SB1249	130V, 0,8A, 10W	2SA1225, 2SB840...842, 2SB905, 2SB1275
17106	2SB1250	B>5000	2SB1098, 2SB1251...52, 2SB1430
17107	2SB1251	B>5000	2SB1098, 2SB1252, 2SB1430
17108	2SB1252	B>5000	-
17109	2SB1253	B>5000	2SB1254...55, 2SB1587...88
17110	2SB1254	B>5000	2SB1255, 2SB1587...88
17111	2SB1255	B>5000	2SB1588
17112	2SB1256	100V, 2A, 1,2W, B2000	2SB1387, 2SB1318
17113	2SB1257	B>2000	2SB1282, 2SB1098, 2SB1223, 2SB1342
17114	2SB1258	B>1000	2SB1283, 2SB1099, 2SB1228, 2SB1340
17115	2SB1259	120V, 10A, 30W, B>2000	BDT 62CF, BDT 64CF
17116	2SB126	32V, 3,5A, 30W	AD 149, AD 166...167, AL 102...103
17117	2SB1260	80V, 1A, 100MHz	BCX 53, 2SB803...804, 2SB1025...1026
17118	2SB1261(Z)	50MHz, <0,5/2,5µs	2SB906, 2SB1184, 2SB1202
17119	2SB1262	60V, 4A, 25W, B5000	2SB1257, 2SB1223, 2SB1342
17120	2SB1262	60V, 4A, 25W, B5000	2SB1257, 2SB1223, 2SB1342
17121	2SB1263	60V, 8A, 25W, B5000	2SB1020...21, 2SB1099, 2SB1224
17122	2SB1263	60V, 8A, 25W, B5000	2SB1020...21, 2SB1099, 2SB1224
17123	2SB1264	2SB1221, 0,6W	BF 423A, BF 436...437, 2SA1371
17124	2SB1265	400/400V, 0,1A, 1W	2SA1024, 2SA1372, 2SA1251, 2SB1209
17125	2SB1266	60V, 3A, 30W, 8MHz	2SB929...930(A), BD 936, BD 540A
17126	2SB1267	60V, 8A, 30W, 120MHz	-
17127	2SB1268	60V, 5A, 30W, 30MHz	2SB1270, 2SB1449, 2SB1451
17128	2SB1269	60V, 7A, 40W, 10MHz	2SB1271, 2SB1450, 2SB1452
17129	2SB126A	2SB126, 60V	AD 166...167, AL 102...103, 2SB231
17130	2SB127	32V, 3,5A, 30W	AD 149, AD 166...167, AL 102...103
17131	2SB1270	90V, 5A, 30W, 20MHz	2SB1451...52
17132	2SB1271	90V, 7A, 40W, 20MHz	2SB1452
17133	2SB1272	100V, 2A, 10W, B>1000	BD 682, 2SB1012
17134	2SB1273	60V, 3A, 30W, 100MHz	2SA1012, 2SA1288, 2SA1293, 2SB1064
17135	2SB1274	2SB1273, , 20W	2SA1307, 2SA1440, 2SA1469, 2SB1185
17136	2SB1275(F5)	160V, 1,5A, 10W, 50MHz	2SA1225, 2SA1552, 2SB840...842
17137	2SB1276	2SB737	2SB737
17138	2SB1277	2SB822	2SB822
17139	2SB1278	2SB851	2SB851
17140	2SB1279	15V, 0,2A, 0,3W	BC 213, BC 258, BC 308, BC 558, 2SA1515
17141	2SB127A	2SB127, 60V	AD 166...167, AL 102...103, 2SB231
17142	2SB128	80V, 6A, 30W	AL 102...103, 2N3615...3618
17143	2SB1280	120V, 3A, 25W, B5000	2SB1252, 2SB1340
17144	2SB1280	120V, 3A, 25W, B5000	2SB1252, 2SB1340



17145	2SB1281	120V, 6A, 25W, B5000	2SB1193, 2SB1340
17146	2SB1281	120V, 6A, 25W, B5000	2SB1193, 2SB1340
17147	2SB1282	B>1500	BDT 60BF, 2SB1024, 2SB1194, 2SB1381
17148	2SB1282	B>1500	BDT 60BF, 2SB1024, 2SB1194, 2SB1381
17149	2SB1283	B>1500	BD 650F, 2SB1020, 2SB1099, 2SB1431
17150	2SB1283	B>1500	BD 650F, 2SB1020, 2SB1099, 2SB1431
17151	2SB1284	B>1500	2SB1100, 2SB1259, 2SB1432
17152	2SB1284	B>1500	2SB1100, 2SB1259, 2SB1432
17153	2SB1285	50MHz,B>1500	BDV 66A...D, BDW 84C...D
17154	2SB1286	100V, 2A, 25W, B>1000	BDW 24C, BDW 54C, BDW 64C, 2SB751B
17155	2SB1287	2SB1286, , 20W	2SB1024, 2SB1098, 2SB1282
17156	2SB1288	30V, 5A, 1W, 120MHz	2SB1306, 2SB1319, 2SB1398
17157	2SB1289	80V, 7A, 40W, 12MHz	BD 544C, BD 712, BD 802, 2SB870
17158	2SB128A	2SB128, 120V	AL 100, AL 102, 2N2290, 2N2293
17159	2SB129	80V, 6A, 30W	AL 102...103, 2N3615...3618
17160	2SB1290	2SB1289, , 30W	2SA1396, 2SA1442, 2SA1651, 2SB1018
17161	2SB1291	60V, 5A, 40W, 12MHz	BD 244B, BD 544B, BD 952, 2SA1012
17162	2SB1292	2SB1291, , 30W	BD 950F, 2SA1394, 2SA1469, 2SB1097
17163	2SB1293	2SB1291, 100V	BD 244C, BD 544C, BD 954, 2SB633
17164	2SB1294	2SB1291, , 100V, 30W	BD954F, 2SA1388, 2SA1441, 2SB1016
17165	2SB1295	2SB1296, SMD	BCW 67...68, 2SA1621, 2SB1197
17166	2SB1296	15V, 0,8A, 0,3W, 300MHz	2SA1705, 2SB1116, BC 327...328
17167	2SB1297	120V, 0,5A, 1W, 250MHz	2SA840, 2SA965, 2SB647, 2SB987
17168	2SB1298	40V, 2A, 1,2W	2SA1315, 2SA1382, 2SB892, 2SB1312
17169	2SB1299	80V, 3A, 40W, 30MHz, B>300	-
17170	2SB129A	2SB129, 120V	AL 100, AL 102, 2N2290, 2N2293
17171	2SB13	30V, 0,05A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
17172	2SB130	32V, 1,5A, 6,5W	AD 162, 2SB474
17173	2SB1300	20V, 3A, 0,75W, 140MHz	2SB893, 2SB985, 2SB1117, 2SB1505
17174	2SB1301	2SB1300, SMD	2SA1736, 2SB1124, 2SB1518
17175	2SB1302	25V, 5A, 320MHz	2SB1073
17176	2SB1303	B>1500	2SB908, 2SB1072
17177	2SB1304	100V, 4A, 20W	2SA1441, 2SB1016, 2SB1095, 2SB1294
17178	2SB1304	100V, 4A, 20W	2SA1441, 2SB1016, 2SB1095, 2SB1294
17179	2SB1305	30V, 5A, 0,75W, 120MHz	2SB1050, 2SB1288, 2SB1326, 2SB1398
17180	2SB1306	2SB1305, 1,2W	2SB1288, 2SB1446
17181	2SB1307(M)	2SB1305, 0,3W	2SB1050, 2SB1288, 2SB1326, 2SB1398
17182	2SB1308	2SB1305, SMD	2SB1073
17183	2SB1309	80V, 0,7A, 5W, 100MHz	2SB889, 2SB1142, BD 170, BD 238
17184	2SB131	40V, 1,5A, 65W	AD 149, 2N2138, 2N2143
17185	2SB1310	40V, 2A, 5W, B>1000	BD 676, BD 776, 2SB794...795, 2SB1008
17186	2SB1311	40V, 2A, 5W	2SA1359, 2SB891, 2SB1142
17187	2SB1312	50V, 2A, 1,2W	2SA1315, 2SA1382, 2SB892, 2SB1312
17188	2SB1313	2SB1312, SMD	2SA1213, 2SB1123...1124
17189	2SB1314	60V, 3A, 15W, 100MHz	-

17190	2SB1315	120V, 8A, 65W, 65MHz	2SA1671...72, 2SA1804...05, 2SA1908...09
17191	2SB1316(F5)	100V, 2A, 10W, B3000	2SB908, 2SB1072, 2SB1303
17192	2SB1317	180V, 15A, 150W, 20MHz	2SA1302, 2SA1553
17193	2SB1318	100V, +-3A, 1W, B>2000	2SB1484
17194	2SB1319	2SB1288	2SB1288
17195	2SB131A	2SB131, 8A	AL 100...101, 2N2288, 2N2291
17196	2SB132	2SB131, 60V	AD 166...167, 2N2139, 2N2144
17197	2SB1320	2SB641	2SB641
17198	2SB1320A	2SB642	2SB642
17199	2SB1321	2SB643	2SB643
17200	2SB1321A	2SB644	2SB644
17201	2SB1322(A)	2SB793(A)	2SB792(A)
17202	2SB1323	Rbe800Ohm	-
17203	2SB1324	Rbe800Ohm	-
17204	2SB1325	Rbe1,5kOhm	-
17205	2SB1326	2SB1307	2SB1307
17206	2SB1327	100V, 5A, 58,3W	-
17207	2SB1328	160/160V, 1,5A, 1,2W, 50MHz	2SA1225, 2SA1552, 2SB1275, 2SB1409
17208	2SB1329	40V, 1A, 1,2W, 150MHz	2SA1241, 2SB1201
17209	2SB132A	2SB131, 60V, 8A	AL 100...101, 2N2289, 2N2292
17210	2SB1330	80V, 0,7A, 1,2W, 100MHz	-
17211	2SB1331	40V, 2A, 1,2W, 100MHz	2SA1241, 2SB1201
17212	2SB1332	80V, 1A, 1,2W, 100MHz	2SA1593
17213	2SB1333	2SB1256	2SB908, 2SB1072, 2SB1303
17214	2SB1334(A)	80V, 4A, 40W, 12MHz	BD 244B, BD 538, BD 952, 2SB920L
17215	2SB1335(A)	2SB1334, , 30W	2SA1394, 2SA1635, 2SB1095, 2SB1292
17216	2SB1337	150V, 2A, 40W	BD 242D, 2SA940, 2SB861, 2SB991
17217	2SB1338	2SB1337, , 30W	2SA1332, 2SB1096, 2SB1530
17218	2SB1339	B10000	-
17219	2SB134	30V, 0,1A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
17220	2SB1340	2SB1339, , 30W	-
17221	2SB1341	80V, 4A, 40W, 12MHz, B3000	BD 718, BDW 24B, BDW 54B, BDW 64B
17222	2SB1342	2SB1341, , 30W	2SB1024, 2SB1098, 2SB1227, 2SB1282
17223	2SB1343	B10000	BD 652, BD 9022, BDW 47C, BDX 54C
17224	2SB1344	2SB1343, , 30W	BD 650F, 2SB1020, 2SB1099, 2SB1283
17225	2SB1345	100V, 7A, 80W, 12MHz	BD 246C, BDV 96, 2SA1141, 2SA1186
17226	2SB1346	60V, 3A, 30W, 40MHz	BD 242A, BD 536, BD 936, 2SA1262
17227	2SB1347	160V, 12A, 120W, 15MHz	2SA1301...02, 2SB1153, 2SB1162...63
17228	2SB1348	160/160V, 0,1A, 0,4W, 140MHz	BF 423A, BF 435...437, 2SA1281
17229	2SB1349	2SB1348, 200/200V	BF 423A, BF 435...437, 2SA1370
17230	2SB135	30V, 0,1A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
17231	2SB1351	60V, 12A, 30W, B>2000	BDT 64(A...C)F, BDW 45, BDW 94A
17232	2SB1352	2SB1351, 60W	BDV 64F, BDV 66F, BDW 84A
17233	2SB1353	120V, 1,5A, 1,8W, 50MHz	2SB1086, 2SB1144, 2SB1220(A)
17234	2SB1353A	2SB1353, 160V	2SA1249, 2SB649, 2SB1086A

17235	2SB1354	60V, 3A, 1,8W	BD 178, BD 440, 2N5194, 2SB1217
17236	2SB1355	80V, 4A, 1,8W, 12MHz	BD 788, BD 790, MJE 250...252, 2N5195
17237	2SB1356	80V, 7A, 1,8W, 12MHz	-
17238	2SB1357	60V, 3A, 1,8W, 70MHz	2SB1065, 2SB1217
17239	2SB1358	60V, 5A, 1,8W, 12MHz	2SB1151
17240	2SB1359	100V, 2A, 1,8W, B>1000	-
17241	2SB135A	2SB135, 110V	ACY 39, 2N2042...2043
17242	2SB136	25V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17243	2SB1360	100V, 5A, 1,8W, 12MHz	-
17244	2SB1361	150V, 9A, 100W, 15MHz	2SA1673, BD 246D, 2SA1186, 2SA1386(A)
17245	2SB1362	2SB1361	BD 246D, 2SA1186, 2SA1386(A), 2SB817
17246	2SB1363	400/360V, 0,1A, 0,9W	2SA1024, 2SA1372, 2SA1584, 2SA1760
17247	2SB1364	30V, 1A	BCX 51...53, 2SA1364, 2SB766A, 2SB1260
17248	2SB1365	20V, 2A	2SA1363, 2SA1663, 2SB1121, 2SB1301
17249	2SB1366	60V, 3A, 25W, 9MHz	2SA1440, 2SA1488, 2SA1635, 2SB1335
17250	2SB1367	100V, 5A, 30W, 5MHz	BD 954F, 2SA1441, 2SB1016, 2SB1294
17251	2SB1368	80V, 4A, 25W, 9MHz	2SA1441, 2SA1635, 2SA1394, 2SB1335
17252	2SB1369	60V, 3A, 40W, 15MHz	BD 242, BD 536, BD 936, 2SA1262
17253	2SB136A	2SB136, 60V	ACY 24, ASY 48, ASY 77, 2SB55
17254	2SB137	30V, 5A, 30W	AD 166...167, AL 102...103, 2SB231
17255	2SB1370	2SB1369, , 30W	2SA1488, 2SA1635, 2SB1094, 2SB1335
17256	2SB1371	120V, 6A, 70W, 15MHz	2SA1671, BD 246D, 2SA1146, 2SA1186
17257	2SB1372	140V, 7A, 80W, 15MHz	2SA1672, BD 246D, 2SA1146, 2SA1186
17258	2SB1373	160V, 12A, 120W, 15MHz	BD 746F, 2SA1386(A), 2SA1492, 2SA1516
17259	2SB1374	50V, 2A, 1W, 200MHz	2SA1315, 2SA1706, 2SB892, 2SB1434
17260	2SB1375	B100..320	BD 936F, 2SB1015, 2SB1094, 2SB1274
17261	2SB1376	50V, 0,1A, 1W, 80MHz	BC 212, BC 257, BC 307, BC 557
17262	2SB1377	50V, 0,5A, 1W, 200MHz	BC 327, BC 638, BC 640, 2SA1705
17263	2SB1378	25V, 0,5A, 0,6W, 150MHz	BC 327...328, BC 636, BC 638, 2SA1515
17264	2SB138	2SB137, 60V	AD 166...167, AL 102...103, 2SB231
17265	2SB1381	100V, 5A, 30W, B1,5k..15k	2SB1098, 2SB1227...28, 2SB1258, 2SB1340
17266	2SB1382	120/120V, 16A, 75W, B>2000	BDV 66CF...DF
17267	2SB1383	120/120V, 25A, 120W, B>2000	2SB1494
17268	2SB1386	2SB1305, SMD	2SB1308
17269	2SB1387	B>2000	2SB1256
17270	2SB1388	B4000	BDV 64CF, BDV 66BF...DF, BDW 84D
17271	2SB1389	2SB1101, , 25W	BDT 60F, 2SB1223, 2SB1257, 2SB1342
17272	2SB138A,B	2SB137, 80V	AD 167, AL 102...103, 2SB231
17273	2SB1390	2SB1103, , 25W	BD 646F, BDT 62F, 2SB1021...22, 2SB1224
17274	2SB1391	2SB791, , 25W	BD 652F, BDT 62CF, 2SB1259
17275	2SB1392	70V, 4A, 25W	BD 952F, 2SA1635, 2SB1017, 2SB1335
17276	2SB1393(A)	2SB929(A), 25W	BD 936F, 2SB1015, 2SB1094, 2SB1375
17277	2SB1394	40V, A, Rb900Ohm, Rbe800Ohm	-
17278	2SB1395	15V, 3A, 0,75W	2SB893, 2SB985, 2SB1117, 2SB1300
17279	2SB1396	2SB1395, SMD	2SB1124, 2SB1301, 2SB1518

17280	2SB1397	25V, 2A, Rb0, Rbe1,6kOhm	-
17281	2SB1398	2SB12882SB1319	2SB1288
17282	2SB1399	2SB955, , 30W	BDT 62CF, 2SB1259
17283	2SB14	30V, 0,05A, 0,05W	AC 125...126, AC 151r, ACY 32, 2SB173
17284	2SB140	40V, 1,5A, 12W	AD 149, 2N2138, 2N2143, 2SB449
17285	2SB1400	2SB727, , 25W	BD 652F, 2SB1193, 2SB1340
17286	2SB1401	300V, 0,3A, 15W, B>1000	2SB1465, 2SB1061
17287	2SB1402	2SB1105, , 25W	BDT 60CF, 2SB1252, 2SB1340
17288	2SB1403	2SB1106, , 25W	BD 652F, 2SB1193, 2SB1340
17289	2SB1404	2SB765, , 25W	BDT 60CF, 2SB1252, 2SB1340
17290	2SB1405	80V, 0,7A, 1W, B>5000	2SB865, 2SB888, 2SB1129
17291	2SB1406	80V, 1,5A, 1W, B>4000	2SB865, 2SB1129
17292	2SB1407L,S	35V, 2,5A, 18W	2SB906, 2SB962, 2SB1184, 2SB1202
17293	2SB1409L,S	180/160V, 1,5A, 18W, 240MHz	2SA1552
17294	2SB141	2SB140, 60V	AD 166...167, 2N2139, 2N2144
17295	2SB1411	100V, 2A, 20W, B1,5k..15k	BDT 60BF, 2SB1024, 2SB1226, 2SB1282
17296	2SB1412(F5)	30V, 5A, 120MHz	2SA1242, 2SA1795, 2SB967, 2SB1203
17297	2SB1413	45V, 1A, 1,5W, 200MHz	2SB1142, BD 136, BD 138, BD 140
17298	2SB1414	180/180V, 1A, 1,5W, 200MHz	2SA1249, 2SA1507, 2SB649
17299	2SB1415	60V, 1A, 150MHz, B>4000	-
17300	2SB1416	60V, 3A, 1,5W, 500/1500ns	2SB1143, BD 178, BD 180, BD 190
17301	2SB1417	60V, 3A, 15W, 30MHz	BD 936F, 2SA1488, 2SB1274, 2SB1375
17302	2SB1417A	2SB1417, 80V	2SA1488A, 2SB1017, 2SB1335
17303	2SB1418	60V, 2A, 15W, 20MHz, B>1000	BDT 60F, 2SB1223, 2SB1342, 2SB1411
17304	2SB1418A	2SB1418, 80V	BDT 60AF, 2SB1282, 2SB1342, 2SB1411
17305	2SB1419	160/160V, 12A, 120W	2SA1301...1302, 2SB1162, 2SB1347
17306	2SB142	30V, 1A, 10W, B>12	AD 149, 2N2137, 2N2142, 2SB449
17307	2SB1420	B>2000	BDV 66B...D, BDW 84D
17308	2SB1421	140/140V, 7A, 80W, 15MHz	2SA1146, 2SA1186, 2SA1265, 2SA1491
17309	2SB1422	60V, 1A, 5W, B>4000	BD 680, 2SB1034
17310	2SB1423	2SB1412	2SA1120
17311	2SB1424	2SB1426, SMD	2SA1730, 2SB1518
17312	2SB1425	20V, 2A, 1W, 90MHz	2SA1315, 2SB733, 2SB892, 2SB1434
17313	2SB1426	20V, 3A, 0,75W, 240MHz	2SB1117, 2SB1505
17314	2SB1427	-/20V, 2/3A, B270..1200	2SA1369
17315	2SB1428	2SB1426, 0,6W	2SB1117, 2SB1505
17316	2SB1429	180V, 15A, 150W, 10MHz	2SA1302, 2SA1553
17317	2SB143(P)	2SB142, B>23	AD 149, 2N2137, 2N2142, 2SB449
17318	2SB1430	100/100V, 5A, 20W, B>2000	2SB1089, 2SB1227, 2SB1258, 2SB1340
17319	2SB1431	100/100V, 8A, 25W, B>2000	2SB1099, 2SB1228, 2SB1283, 2SB1344
17320	2SB1432	100/100V, 10A, 30W, B>1000	BDT 62BF...CF, 2SB110, 2SB1259, 2SB1284
17321	2SB1433	50V, 2A, 0,9W	2SA1315, 2SB892, 2SB985
17322	2SB1434	50V, 2A, 1W, 110MHz	2SA1706, 2SB892, 2SB1229
17323	2SB1435	2SB1434, 1,5W, 80MHz	2SB986, 2SB1142
17324	2SB1436	2SB1412	2SA1357

17325	2SB1437	100V, 1A, 1W, 120MHz	2SA1708, BC 640, 2SB647, 2SB984
17326	2SB1438	100V, 2A, 1W, 90MHz	2SA1709
17327	2SB1439	2SB1438, 1,5W, 200MHz	-
17328	2SB144(P)	2SB142, B>45	AD 149, 2N2137, 2N2142, 2SB449
17329	2SB1440	2SB1434, SMD	2SA1681, 2SB1123, 2SB1520
17330	2SB1443	2SB1374	2SB1374
17331	2SB1446	50V, 5A, 1W, 70MHz	2SB1483
17332	2SB1447	50V, 3A, 1,5W, 250MHz	2SB1143, 2SB986, 2SB1217
17333	2SB1448	2SB1285, , 65W	BDV 66AF, BDW 84C, 2SB1285
17334	2SB1449	60V, 5A, 30W, 100/900ns	2SB1268, 2SB1270, 2SB1451
17335	2SB145	2SB142, , B37	AD 149, 2N2137, 2N2142, 2SB449
17336	2SB1450	60V, 7A, 40W, 200/800ns	2SB1269, 2SB1271, 2SB1452
17337	2SB1451	90V, 5A, 30W, 200/900ns	2SB1270...71, 2SB1452
17338	2SB1452	90V, 7A, 40W, 200/900ns	2SB1271
17339	2SB1453	60V, 3A, 5MHz, 400/2200ns	BD 936F, 2SB1015, 2SB1094, 2SB1375
17340	2SB1454	90V, 5A, 25W, 20MHz	2SA1388, 2SA1441, 2SA1741, 2SB1018
17341	2SB1455	90V, 7A, 30W, 20MHz	2SA1442, 2SA1742, 2SB1018
17342	2SB1456	150V, 1A, 1W, 120MHz	-
17343	2SB1457	100V, 2A, 0,9W, B>2000	2SB1256, 2SB1387, 2SB1318
17344	2SB1459	2SB1433, 80V	2SA1315, 2SB1438
17345	2SB146	2SB142, , B75	AD 149, 2N2137, 2N2142, 2SB449
17346	2SB1460	2SB1425	2SB1425
17347	2SB1461	-/20V, 2/3A, B270..1200	-
17348	2SB1462	60V, 0,1A, 80MHz	2SA1832
17349	2SB1462	60V, 0,1A, 80MHz	2SA1832
17350	2SB1463	150V, 0,05A, 200MHz	-
17351	2SB1463	150V, 0,05A, 200MHz	-
17352	2SB1464	60V, 8A, 25W, 20MHz, B>2000	2SB1021...22, 2SB1224...25
17353	2SB1465	25MHz, B>1500	2SB1401
17354	2SB1466	100/100V, 15A, 100W, B>1000	BDV 66A...D, BDW 84C...D, 2SB969
17355	2SB1467	100/230ns	2SA1442, 2SA1470, 2SA1742
17356	2SB1468	100/330ns	2SA1451...52, 2SA1568, 2SA1771
17357	2SB1469	B~5000	2SB1493
17358	2SB147	60V, 1,5A, 12W	AD 166...167, 2N2139, 2N2144
17359	2SB1470	B>5000	2SB1490, 2SD1503
17360	2SB1471	B>2000	BDW 24B...C, BDW 64B...D, 2SB1342
17361	2SB1472	B>2000	BD 648, BD 900, BDW 74B...D, 2SB1020
17362	2SB1473	2SB987	2SB987
17363	2SB1474(F5)	80V, 4A, 10W, 12MHz, B>1000	2SB908, 2SB1072
17364	2SB1475	25V, 0,5A, 50MHz	BC 807W...808W, 2SB1219(A)
17365	2SB1476	120/120V, 6A, 60W, B>2000	2SA1183, 2SB1557
17366	2SB1477	-/100V, 5A, 60W	2SA1671, BD 246D, 2SA1146, 2SA1186
17367	2SB1478	-/100V, 8A, 60W, B>2000	BDV 64C, BDV 66B, BDW 84D
17368	2SB1481	B>2k	BDT 60BF, 2SB1020, 2SB1024, 2SB1282
17369	2SB1482	-/20V, 5A, 1,2W	2SA1242, 2SB1288, 2SB1306, 2SB1446

17370	2SB1483	60/60V, 5A, 1W	-
17371	2SB1484	100/100V, +-3A, 1W, B2k..20k	2SB1318
17372	2SB1485M	2SB1374	2SB1374
17373	2SB1488	400/400V, 0,5A, 1W, 25MHz	2SA1625, 2SB1074
17374	2SB1489	400/400V, 0,6A, 1,5W, 100MHz	2SA1156, 2SA1498
17375	2SB1490	B>5000	2SB1470, 2SB1503
17376	2SB1492	B>5000	2SB1470, 2SB1490, 2SB1503
17377	2SB1493	B>5000	2SB1469, 2SB1560
17378	2SB1494	120/120V, 25A, 120W, B>2000	2SB1383
17379	2SB1495	B>2k	BDT 60BF, 2SB1226, 2SB1250, 2SB1282
17380	2SB1496	60V, 3A, 1,8W, 15MHz	BD 178, BD 190, 2SB1184, 2SB1202
17381	2SB1497	150/600ns	2SA1066, 2SA1707, 2SA1761
17382	2SB1498	600/600V, 0,3A, 15W, <1/4μ	-
17383	2SB1499	200/700ns	2SA1388, 2SA1469...70, 2SA1441
17384	2SB1499A	2SA1499, 80V	2SA1388, 2SA1469...70, 2SA1441
17385	2SB15	60V, 0,05A, 0,05W	ACY 24, ASY 48, 2SB55
17386	2SB150	105V, 0,04A, 0,05W	ACY 39, 2N2042...2043
17387	2SB1500	B>5000	2SB1492
17388	2SB1501	B>5000	2SB1492
17389	2SB1502	B>5000	2SB1492, 2SB1555...56
17390	2SB1503	B>5000	2SB1470, 2SB1490
17391	2SB1504	500/3000ns, B>1000	BD 646, BD 898, BDW 74A...D, 2SB1464
17392	2SB1505	30V, 3A, 0,9W	2SB985, 2SB1117, 2SB1592
17393	2SB1507	200/800ns	2SA1670, 2SB1371, BD 246A...F
17394	2SB1508	100/500ns	BD 546A...D, 2SA1292, 2SB828...829
17395	2SB1509	200/600ns	BD 546A...D, 2SA1292, 2SB828...829
17396	2SB151	80V, 5A, 50W	AL 102...103, 2N3615, 2N3617, 2SB231
17397	2SB1510	80V, 3A, B>2000, 1,5W	BUT 60AF, 2SB1282, 2SB1342, 2SB1568
17398	2SB1511	300/320ns	2SB904
17399	2SB1512	-/80V, 4A, 1,8W, B>1000	2SB908, 2SB1072
17400	2SB1513	-/120V, 6A, 1,8W, B>2000	-
17401	2SB1514	-/100V, 8A, 1,8W, B>1000	-
17402	2SB1515	80V, 4A, 1,2W, 12MHz, B5000	2SB908, 2SB1072
17403	2SB1516(F5)	80V, 3A, 10W, 18MHz	2SB1215...16, BD 190, BD 442
17404	2SB1517	-/50V, 3A, 1,2W	2SA1761, 2SB906, 2SB965, 2SB1184
17405	2SB1518	2SB1505, SMD	2SA1736, 2SB1124
17406	2SB1519	2SB1433, SMD	2SA1681, 2SB1123...24, 2SB1313
17407	2SB152(A)	2SB151, 100V	AL 102...103, 2N3616, 2N3618, 2SB231
17408	2SB1520	2SB1459, SMD	2SB1572
17409	2SB1522K	15V, 1A, 200MHz	-
17410	2SB1526	B>1000	BD 778, BD 780, 2SB794...95, 2SB1067
17411	2SB1527	Rbe1kOhm, 20V, 0,8A, 250MHz	-
17412	2SB1529	180/180V, 15A, 150W, 45MHz	2SA1302, 2SB1163, 2SB1317, 2SB1429
17413	2SB153	12V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17414	2SB1530	200/150V, 2A, 20W	2SA1306B, 2SA1668, 2SB1096



17415	2SB1531	130/110V, 6A, 50W, 20MHz	2SB1469, 2SB1493, 2SB1557...58
17416	2SB1532	40V, 10A, 40W	2SA1327, 2SA1567, 2SA1599, 2SB948(A)
17417	2SB1535(F5)	100/100V, 6A, 10W, 18MHz	BD 244C...F, BD 540C...D, BD 954, 2SB633
17418	2SB1536	30V, 5A, 1,2W, 120MHz	2SA1307, 2SA1469, 2SA1643
17419	2SB1537	10V, 1A, 120MHz	2SA1314, 2SA1734, 2SB1121
17420	2SB1539	20V, 1A, 120MHz	2SA1314, 2SA1734, 2SB1121
17421	2SB154	12V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17422	2SB1541	60V, 1A, 1,2W, 150MHz	BD 518, BD 526, 2SA962, 2SB1201
17423	2SB1542	50V, 2A, 1,2W, 140MHz	BD 510, BD 516, 2SA1241, 2SB1201
17424	2SB1543	60V, 3A, 1,2W, 30MHz	2SA1876, 2SB906, 2SB1184, 2SB1202
17425	2SB1544	80V, 1A, 1,2W, 130MHz	BD 520, BD 528, BD 530, 2SA1593
17426	2SB1545	150V, 1A, 1,2W, 110MHz	2SA1014, 2SA1225, 2SB905, 2SB1275
17427	2SB1546	400/400V, 0,5A, 1,2W, 25MHz	2SA1156, 2SA1498, 2SA1727 2SA1772
17428	2SB1548	80V, 3A, 25W, 30MHz	BDT 32(A...C)F, 2SA1338, 2SA1441, 2SA1469
17429	2SB1549	80V, 10A, 1,8W, 12MHz, B7000	-
17430	2SB155	16V, 0,3A, 0,15W	AC 128, AC 153, AC 188, 2SB405, 2SB475
17431	2SB1550	2SB1549, 40W	-
17432	2SB1551	2SB1549, 30W	-
17433	2SB1553	80V, 3A, 15W, 30MHz	2SB1299, 2SB1314
17434	2SB1554	60V, 4A, 15W, 25MHz	-
17435	2SB1555	140/140V, 7A, 100W, B>5000	2SB1470, 2SB1490, 2SB1503
17436	2SB1556	140/140V, 8A, 120W, B>5000	2SB1470, 2SB1490, 2SB1503
17437	2SB1557	2SB1555, 70W	2SB1469, 2SB1493
17438	2SB1558	2SB1556, 80W	2SB1560
17439	2SB1559	B>5k	BDV 66D
17440	2SB156(H)	16V, 0,3A, 0,15W	AC 128, AC 153, AC 188, 2SB405, 2SB475
17441	2SB1560	B>5k	BDV 66D
17442	2SB1561	60V, 2A, 150MHz	2SA16891 2SB1123
17443	2SB1562	60V, 3A, 25W, B300..1000	2SB1299, 2SB1314
17444	2SB1565	80V, 3A, 25W, 15MHz	BD 938F, BDT 32...F, 2SA1488A, 2SA1635
17445	2SB1566	60V, 3A, 25W, 60MHz	BD 936F, BDT 32...F, 2SB1187, 2SB1375
17446	2SB1567	100V, 2A, 20W, B1k..10k	2SB1226, 2SB1250, 2SB1411, 2SB1495
17447	2SB1568	B1k..10k	BDT 60...F, 2SB1024, 2SB1282, 2SB1342
17448	2SB1569	120V, 1,5A, 20W, 50MHz	2SA1332, 2SA1393, 2SB1186(A), 2SA1859(A)
17449	2SB1569A	2SB1569, 160V	2SA1332, 2SB1186A, 2SA1606, 2SA1859A
17450	2SB156A(AH)	2SB156, 20V	AC 128, AC 153, AC 188, 2SB405, 2SB475
17451	2SB157	7V, 5mA, 0,01W, B35	OC 57
17452	2SB1570	B>5k	-
17453	2SB1571	50V, 5A, 150MHz, 265/400ns	2SB1578
17454	2SB1572	80V, 3A, 160MHz, 155/545ns	-
17455	2SB1573	60V, 3A, 10W, 270MHz	2SB906, 2SB1184, 2SB1202, 2SA1876
17456	2SB1574	50V, 2A, 10W, 150MHz	2SB838, 2SB1184, 2SB1201, 2SB1241
17457	2SB1575	50V, 5A, 10W, 70MHz	2SA1732, 2SB1204, 2SA1796, 2SA1877
17458	2SB1578	60V, 5A, 600/600ns	2SB1571
17459	2SB158	2SB157, B55	OC 58

17460	2SB1582	30V, 0,5A, 200MHz	BC 807R...808R, BCX 17R...18R, 2SA1326
17461	2SB1583	185V, 0,05A, 200MHz	-
17462	2SB1584	25V, 0,5A, 150MHz	2SA1298
17463	2SB1585	15V, 0,5A, 130MHz	2SA1298
17464	2SB1586	B>2k	2SB1253...1255, 2SB1469, 2SB1493
17465	2SB1587	B>5k	2SB1254...1255, 2SB1469, 2SB1493
17466	2SB1588	B>5k	2SB1255, 2SB1560
17467	2SB1589	10V, 1A, 190MHz	BC 869, BCX 69, 2SA1734
17468	2SB159	2SB157, B80	OC 59
17469	2SB1592	30V, 3A, 150MHz	2SA1707, 2SB985, 2SB1117, 2SB1505
17470	2SB1593	29V, 3A, 200MHz	2SA1359, 2SB1143
17471	2SB1594	B>3000	-
17472	2SB1595	-/32V, 2A, 0,9W	2SA1315, 2SB892, 2SB1459
17473	2SB1596	-/160V, 1,5A, 0,9W	2SA1770, 2SB1130A, 2SB1212, 2SB1236A
17474	2SB16	16V, 0,6A, 1,8W	AD 162, 2SB493
17475	2SB160	2SB157, NF-E, B75	OC 60
17476	2SB1602	60V, 3A, 1,3W, B>800	-
17477	2SB1603	40V, 4A, 25W, 150MHz	2SA1388, 2SA1469...70, 2SA1441
17478	2SB1603A	2SB1603, 50V	2SA1388, 2SA1469...70, 2SA1441
17479	2SB1604	40V, 10A, 40W, 100MHz	2SA1327, 2SA1567, 2SB948(A)
17480	2SB1604A	2SB1604, 50V	2SA1327, 2SA1567, 2SB948A
17481	2SB1605	500/1500ns	2SB1185, 2SB1274, 2SB1314
17482	2SB1605A	2SA1605, 80V	2SA1440
17483	2SB1606	130V, 5A, 40W, 30MHz	2SA1650, 2SB945
17484	2SB1607	130V, 7A, 40W, 30MHz	2SA1651, 2SB946
17485	2SB161	30V, 0,1A, 0,125W, B50	AC 125...126, AC 151...152, 2SB475
17486	2SB1610	10V, 0,5A, 120MHz	2SA1298, 2SA1753, 2SB1584...85
17487	2SB1611	20V, 0,5A, 100MHz	2SA1298, 2SA1753, 2SB1584
17488	2SB1612	10V, 2A, 60MHz	2SA1363, 2SA1314, 2SB1121
17489	2SB1614	20V, 2A, 60MHz	2SA1363, 2SA1314, 2SB1121
17490	2SB1616	-/80V, 4A, 30W, B>1000	2SB1098, 2SB1227, 2SB1282
17491	2SB1617	B>2000	2SB1316
17492	2SB1618	2SB1610	BC 808W, 2SA1745, 2SB1219
17493	2SB1619	2SB1611	BC 808W, 2SA1745, 2SB1219
17494	2SB162	2SB161, 0,18W	AC 125...126, AC 151...152, 2SB475
17495	2SB1620	B>5000	-
17496	2SB1621	2SB1620, 17A, 200W	-
17497	2SB1622	2SB1620, , 85W	-
17498	2SB1624	B>5000	2SB1469, 2SB1493, 2SB1557
17499	2SB1625	2SB1624	2SB1253...54, 2SD1587
17500	2SB1626	2SB1624, , 30W	-
17501	2SB1627	45V, 0,1A, 80MHz	BC 856, BC 860, BCW 69...70
17502	2SB1628	20V, 3A, 320MHz, 70/150ns	2SB1301, 2SC1518
17503	2SB1629	60V, 3A, 40W, B300..700	2SB1299, 2SB1314, 2SB1562
17504	2SB163	2SB161, B75	AC 125...126, AC 151...152, 2SB475

17505	2SB1631	2SB1629, 15W	2SB1299, 2SB1314, 2SB1562
17506	2SB1638	40V, 7A, 15W, 150MHz	-
17507	2SB1638A	2SB1638, 50V	-
17508	2SB164	2SB163, 0,18W	AC 125...126, AC 151...152, 2SB475
17509	2SB1640	60V, 3A, 1,8W, 9MHz	BD 786, 2SB986, 2SB1065, 2SB1217
17510	2SB1640	60V, 3A, 1,8W, 9MHz	BD 786, 2SB986, 2SB1065, 2SB1217
17511	2SB1641	100V, 5A, 1,8W, B1,5k..15k	-
17512	2SB1641	100V, 5A, 1,8W, B1,5k..15k	-
17513	2SB1642	60V, 4A, 25W, 9MHz	2SA1307, 2SA1469, 2SB1134...1135
17514	2SB1643	60V, 3A, 40W, B300..700	-
17515	2SB1647	45MHz	-
17516	2SB1648	2SB 1647, 17A	-
17517	2SB1649	2SB 1647	-
17518	2SB165	2SB161, B100	AC 125...126, AC 151...152, 2SB475
17519	2SB166	2SB165, 0,18W	AC 125...126, AC 151...152, 2SB475
17520	2SB167	20V, 0,5A, 0,2W	AC 128, AC 153, AC 188, 2SB405, 2SB415
17521	2SB168	9V, 0,1A, 0,15W, B60	AC 125...126, AC 151, 2SB54, 2SB56
17522	2SB169	2SB168, B85	AC 125...126, AC 151, 2SB54, 2SB56
17523	2SB16A	2SB16, 20V	AD 162, 2SB493
17524	2SB17	32V, 0,6A, 1,8W	AD 162, 2SB493
17525	2SB170	30V, 0,1A, 0,125W, $\beta > 20$	AC 125...126, AC 151, 2SB54, 2SB56
17526	2SB171	2SB170, $\beta > 40$	AC 125...126, AC 151, 2SB54, 2SB56
17527	2SB172	32V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
17528	2SB173	30V, 0,1A, 0,125W	AC 125...126, AC 151r, ACY 32, 2SB175
17529	2SB174	20V, 0,3A, 0,225W	AC 128, AC 152...153, AC 188, 2SB405
17530	2SB175	30V, 0,1A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
17531	2SB176	32V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
17532	2SB177	60V, 0,125A, 0,125W	ACY 24, ASY 48, 2SB55
17533	2SB178(Q)	20V, 0,3A, 0,225W	AC 128, AC 152...153, AC 188, 2SB405
17534	2SB178A	2SB178, 40V	2N1189...90, 2SB405ST
17535	2SB178B	2SB178, 60V	-
17536	2SB179	25V, 0,05A, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
17537	2SB17A	2SB17, 40V	2SB493
17538	2SB18	60V, 0,6A, 1,8W	-
17539	2SB180	40V, 0,5A, 5,5W	2SB493, AD 162
17540	2SB180A	2SB180, 12W	-
17541	2SB181	2SB180, 60V	-
17542	2SB181A	2SB180, 60V, 12W	-
17543	2SB183	12V, 0,02A, 0,05W, B55	AC 125...126, AC 151, 2SB54, 2SB56
17544	2SB184	2SB183, B100	AC 125...126, AC 151, 2SB54, 2SB56
17545	2SB185	25V, 0,15A, 0,2W, $\beta > 30$	AC 125...126, AC 151, 2SB54, 2SB56
17546	2SB186(A,B)	2SB185, $\beta > 100$	AC 126, AC 151, 2SB54, 2SB56
17547	2SB187	25V, 0,15A, 0,2W	AC 125...126, AC 151, 2SB54, 2SB56
17548	2SB188	25V, 0,15A, 0,2W	AC 125...126, AC 151, 2SB54, 2SB56
17549	2SB189	25V, 0,25A, 0,25W	AC 128K, AC 153K, AC 188K, 2SB475

17550	2SB18A	2SB18, 80V	-
17551	2SB190	25V, 0,05A, 0,09W, B150	AC 125...126, AC 151, 2SB54, 2SB56
17552	2SB191	2SB190, B70	AC 125...126, AC 151, 2SB54, 2SB56
17553	2SB192	2SB190, B35	AC 125...126, AC 151, 2SB54, 2SB56
17554	2SB193	2SB190, 0,1A	AC 125...126, AC 151, 2SB54, 2SB56
17555	2SB194	2SB190, 0,1A, B70	AC 125...126, AC 151, 2SB54, 2SB56
17556	2SB195	2SB190, 0,1A, B35	AC 125...126, AC 151, 2SB54, 2SB56
17557	2SB196	30V, 0,5A, 0,5W	2SB493, AD 162
17558	2SB197	2SB196, 50V	-
17559	2SB198	2SB196, 70V	-
17560	2SB199	12V, 0,3A, 0,25W	AC 128, AC 152...153, AC 188, 2SB475
17561	2SB200	32V, 0,4A, 0,25W	AC 128, AC 153, AC 188, 2SB415
17562	2SB200A	2SB200, 45V	2SB405ST
17563	2SB201	35V, 0,4A, 0,3W, B>37	AC 128, AC 153, AC 188, 2SB415
17564	2SB202	2SB201, B>70	AC 128, AC 153, AC 188, 2SB415
17565	2SB203	40V, 20A, 80W	-
17566	2SB204	40V, 30A, 80W	-
17567	2SB205	80V, 20A, 80W	-
17568	2SB206	80V, 30A, 80W	-
17569	2SB207	100V, 20A, 80W	-
17570	2SB207A	2SB207, 140V	-
17571	2SB208	100V, 30A, 80W	-
17572	2SB208A	2SB208, 140V	-
17573	2SB209	40V, 20A, 80W	-
17574	2SB210	40V, 30A, 80W	-
17575	2SB211	80V, 20A, 80W	-
17576	2SB212	80V, 30A, 80W	-
17577	2SB213	100V, 20A, 80W	-
17578	2SB213A	2SB213, 140V	-
17579	2SB214	100V, 30A, 80W	-
17580	2SB214A	2SB214, 140V	-
17581	2SB215	100V, 3A, 24W	AL 102...103, 2N1542, 2N1547, 2SB231
17582	2SB216(A)	2SB215, 60V	AD 149, 2N1540, 2N1545, 2SB449
17583	2SB217	2SB215, 25V	AD 149, 2N1539, 2N1544, 2SB449
17584	2SB218	80V, 0,1A, 0,225W	ACY 39, 2N2042...43
17585	2SB219	30V, 0,2A, 0,225W, B>19	AC 125...126, AC 151, 2SB54, 2SB56
17586	2SB219A	2SB219, 0,5A	AC 128, AC 152...153, AC 188, 2SB415
17587	2SB22	25V, 0,2A, 0,3W	AC128(K), AC151...153, AC188(K), 2SB405
17588	2SB220	2SB219, B>34	AC 125...126, AC 151, 2SB54, 2SB56
17589	2SB220A	2SB219, 0,5A, B>34	AC 128, AC 152...153, AC 188, 2SB415
17590	2SB221	2SB219, B>53	AC 125...126, AC 151, 2SB54, 2SB56
17591	2SB221A	2SB219, 0,5A, B>53	AC 128, AC 152...153, AC 188, 2SB415
17592	2SB222	2SB219, B>72	AC 125...126, AC 151, 2SB54, 2SB56
17593	2SB222A	2SB219, 0,5A, B>72	AC 128, AC 152...153, AC 188, 2SB415
17594	2SB223	2SB219, B>99	AC 125...126, AC 151, 2SB54, 2SB56

17595	2SB223A	2SB219, 0,5A, B>99	AC 128, AC 152...153, AC 188, 2SB415
17596	2SB224	45V, 0,5A, 0,225W, B>19	2N1189...1190, 2SB405ST
17597	2SB225	2SB224, B>34	2N1189...1190, 2SB405ST
17598	2SB226	2SB224, B>53	2N1189...1190, 2SB405ST
17599	2SB227	2SB224, B>72	2N1189...1190, 2SB405ST
17600	2SB228	80V, 5A, 50W	AL 102...103, 2N1541, 2N1546, 2SB231
17601	2SB229	2SB228, 100V	AL 102...103, 2N1542, 2N1547, 2SB231
17602	2SB23	15V, 0,01A, 0,04W	AC 125...126, AC 151, 2SB54, 2SB56
17603	2SB230	2SB228, 120V	AL 102, 2N1543, 2N1548, 2SB231
17604	2SB231	120V, 6A, 25W	AL 102, AU 110, AU 210, 2N5324
17605	2SB232	130V, 6A, 54W, B>20	AL 102, AU 110, AU 210, 2N5324, 2SB231
17606	2SB233	2SB232, B>100	AL 102, AU 110, AU 210, 2N5324, 2SB231
17607	2SB234	2SB232, 180V, B>15	AU 107, AU 113, AU 213, 2N5324
17608	2SB235	80V, 15A, 60W	2N1982, 2N2075, 2N2079, 2N2492...93
17609	2SB236	2SB235, 60V	2N1981, 2N2076, 2N2080, 2N2490...91
17610	2SB237	2SB235, 36V	2N1980, 2N2077, 2N2081, 2N2490...91
17611	2SB238	40V, 1A, 13W	2SB493, AD 162
17612	2SB239	2B238, 80V	-
17613	2SB239A	2B238, 100V	-
17614	2SB24	15V, 0,015A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
17615	2SB240	40V, 1A, 13W	2SB493, AD 162
17616	2SB240A	2B240, 60V	-
17617	2SB241(N)	2SB240, 80V	-
17618	2SB241A(AN)	2B241, 100V	-
17619	2SB242	30V, 1A, 13W	2SB493, AD 162
17620	2SB242A	2B242, 60V	-
17621	2SB243	30V, 1A, 13W	2SB493, AD 162
17622	2SB243A	2SB243, 60V	-
17623	2SB244	80V, 1A, 13W	-
17624	2SB245	80V, 1A, 13W	-
17625	2SB246	40V, 5A, 54W	AL 102...103, 2N1539, 2N1544, 2SB231
17626	2SB247	2SB246, 60V	AL 102...103, 2N1540, 2N1545, 2SB231
17627	2SB248	40V, 5A, 54W	AL 102...103, 2N1539, 2N1544, 2SB231
17628	2SB248A	2SB 248, 60V	AL 102...103, 2N1540, 2N1545, 2SB231
17629	2SB249	80V, 5A, 54W	AL 102...103, 2N1541, 2N1546, 2SB231
17630	2SB25(N)	60V, 1,5A, 20W	AD 166, AUY 19, 2N2139, 2N2144
17631	2SB250	30V, 5A, 54W	AL 102...103, 2N1539, 2N1544, 2SB231
17632	2SB250A	2SB 250, 60V	AL 102...103, 2N1540, 2N1545, 2SB231
17633	2SB251	30V, 5A, 54W	AL 102...103, 2N1539, 2N1544, 2SB231
17634	2SB251A	2SB 251, 60V	AL 102...103, 2N1540, 2N1545, 2SB231
17635	2SB252	80V, 5A, 54W	AL 102...103, 2N1541, 2N1546, 2SB231
17636	2SB252A	2SB 252, 120V	AL 102, 2N1543, 2N1548, 2SB231
17637	2SB253	80V, 5A, 54W	AL 102...103, 2N1541, 2N1546, 2SB231
17638	2SB253A	2SB 253, 120V	AL 102, 2N1543, 2N1548, 2SB231
17639	2SB254	35V, 1A, 12W	AD 162, 2SB474, 2SB481

17640	2SB255	35V, 1A, 12W	AD 162, 2SB474, 2SB481
17641	2SB256	25V, 1A, 12W	AD 162, 2SB474, 2SB481
17642	2SB257	18V, 0,04A, 0,06W	AC 125...126, AC 151r, ACY 32, 2SB173
17643	2SB258	120V, 15A, 60W	-
17644	2SB259	2SB258, 80V	2N1982, 2N2075, 2N2079, 2N2492
17645	2SB26	32V, 1,5A, 20W	AD 149, AUY 19, 2N2137, 2N2142
17646	2SB260	2SB258, 50V	2N1980, 2N2077, 2N2081, 2N2491
17647	2SB261	20V, 0,03A, 0,065W, B45	AC 125...126, AC 151, 2SB54, 2SB56
17648	2SB262	2SB261, B90	AC 125...126, AC 151, 2SB54, 2SB56
17649	2SB263	20V, 0,15A, 0,2W	AC 125...126, AC 151, 2SB54, 2SB56
17650	2SB264	30V, 0,05A, 0,07W	AC 125...126, AC 151r, ACY 32, 2SB173
17651	2SB265	40V, 0,1A, 0,17W	AC 125...126, AC 151, 2SB54, 2SB56
17652	2SB266	25V, 0,15A, 0,15W, B67	AC 125...126, AC 151, 2SB54, 2SB56
17653	2SB267	2SB266, B70	AC 125...126, AC 151, 2SB54, 2SB56
17654	2SB268	30V, 0,15A, 0,25W	AC 128, AC 152...153, AC 188, 2SB475
17655	2SB269	25V, 0,15A, 0,15W	AC 125...126, AC 151r, ACY 32, 2SB173
17656	2SB26A	2SB26, 60V	AD 166, AUY 19, 2N2139, 2N2144
17657	2SB27	15V, 0,5A, 5W, B>18	AD 149, AUY 19, 2N2137, 2N2142, 2SB449
17658	2SB270	12V, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17659	2SB271	25V, 0,5A, 0,72W, B80	AC 128, AC 153, AC 188, 2SB405, 2SB415
17660	2SB272	2SB271, B100	AC 128, AC 153, AC 188, 2SB405, 2SB415
17661	2SB273	2SB271, 35V, B100	AC 128, AC 153, AC 188, 2SB405, 2SB415
17662	2SB274	80V, 6A, 50W	AL 102...103, 2N3615, 2N3617, 2N2526
17663	2SB275	2SB274, 120V	AL 102, 2N2290, 2N2293, 2N2527
17664	2SB276	2SB274, 120V, 10A	AL 100, 2N2290, 2N2293, 2N2527
17665	2SB277	15V, 5mA, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
17666	2SB278	25V, 0,05A, 0,25W, B28	2SA1252, 2SB902, BC 558
17667	2SB279	2SB278, B50	2SA1252, 2SB902, BC 558
17668	2SB28	2B27, B>35	AD 149, AUY 19, 2N2137, 2N2142, 2SB449
17669	2SB280	32V, 0,25A, 0,3W	BC 213, BC 258, BC 308, BC 558, 2SA953
17670	2SB281	2SB280, 60V	BC 212, BC 256, BC 266, BC 556, 2SA953
17671	2SB282	80V, 6A, 30W, B>15	AL 102...103, AUY 22, 2N3615, 2N3617
17672	2SB283	2SB282, 60V, B>35	AL 102...103, AUY 21, 2N3612, 2N3614
17673	2SB284	2SB282, 60V, B>20	AL 102...103, AUY 21, 2N3612, 2N3614
17674	2SB285	2SB282, B>20	AL 102...103, AUY 22, 2N3615, 2N3617
17675	2SB286	80V, 6A, 43W, B17	AL 102...103, AUY 22, 2N3615, 2N3617
17676	2SB287	2SB286, B36	AL 102...103, AUY 22, 2N3615, 2N3617
17677	2SB288	32V, 0,125A, 0,125W	AC 125...126, AC 151...152, 2SB475
17678	2SB289	2SB288, 60V	ACY 24, ASY 48, ASY 77, 2SB55
17679	2SB29	2B27, B>72	AD 149, AUY 19, 2N2137, 2N2142, 2SB449
17680	2SB290	18V, 0,04A, 0,065W	AC 125...126, AC 151r, ACY 32, 2SB173
17681	2SB291	30V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17682	2SB292	30V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17683	2SB292A	2SB292, 60V	ACY 24, ASY 48, ASY 77, 2SB55
17684	2SB293	18, 0,25A, 0,15W, B70	AC 128, AC 152...153, AC 188, 2SB475



17685	2SB294	2SB293, B36	AC 128, AC 152...153, AC 188, 2SB475
17686	2SB295	100V, 5A, 40W	AL 102...103, 2N3616, 2N3618, 2N2527
17687	2SB296	130V, 10A, 35W	AU 110, AU 210
17688	2SB299	30V, Ueb25V, 0,15A, 0,15W	AC 125...126, AC 151, ASY 26, ASY 76...77
17689	2SB30	2B27, ., B68	AD 149, AUY 19, 2N2137, 2N2142, 2SB449
17690	2SB300	100V, 10A, 35W	AL 100...101, 2N2290, 2N2293, 2N2527
17691	2SB301	2SB300, 60V	AL 100...101, 2N2289, 2N2292, 2N2526
17692	2SB302	10V, 2mA, 0,04A	AC 125...126, AC 151r, ACY 32, 2SB173
17693	2SB303	25V, 0,02A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
17694	2SB304	30V, 0,5A, 0,225W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17695	2SB304A	2SB304, 45V	ACY 24, ASY 48, ASY 76...77, 2N1189...90
17696	2SB306	105V, 0,02A, 0,075W	ACY 39, 2N2042...2043
17697	2SB309(A)	75V, 8A, 43W	AL 100...101, 2N2289, 2N2292, 2N2526
17698	2SB31	2B27, ., B115	AD 149, AUY 19, 2N2137, 2N2142, 2SB449
17699	2SB310	2SB309, 140V	AU 110, AU 210, 2N2528
17700	2SB311	2SB309, 180V, 10A	AU 107, AU 113, AU 213, 2N5324
17701	2SB312	2SB309, 140V	AU 110, AU 210, 2N2528
17702	2SB313	2SB309, 180V, 10A	AU 107, AU 113, AU 213, 2N5324
17703	2SB314	30V, 0,5A, 3W	2SB493, AD 162
17704	2SB315	16V, 0,3A, 0,15W, B50	AC 128, AC 152...153, AC 188, 2SB475
17705	2SB316	2SB315, B60	AC 128, AC 152...153, AC 188, 2SB475
17706	2SB317	2SB315, 0,25W, B60	AC 128, AC 152...153, AC 188, 2SB475
17707	2SB318	60V, 5A, 50W	AL 102...103, 2N1540, 2N1545, 2N2526
17708	2SB319	2SB318, 100V	AL 102...103, 2N1542, 2N1547, 2N2527
17709	2SB32	20V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17710	2SB320	2SB318, 100V, 10A	AL 100...101, 2N2290, 2N2293, 2N2527
17711	2SB321	2SB322, B100	AC 125...126, AC 151r, ACY 32, 2SB173
17712	2SB322	12V, 0,05A, 0,04W, B50	AC 125...126, AC 151, 2SB54, 2SB56
17713	2SB323	2SB322, B100	AC 125...126, AC 151, 2SB54, 2SB56
17714	2SB324	32V, 1A, 0,22W	AC 128, AC 153, AC 188, 2SB415
17715	2SB325	120V, 0,6A, 1,8W	-
17716	2SB326	B>45	AC 128, AC 153, AC 188, ASY 76...77
17717	2SB327	2SB326, B>70	AC 128, AC 153, AC 188, ASY 76...77
17718	2SB328	25V, 0,2A, 0,15W, B>40	AC 125...126, AC 151...152, ASY 26...27
17719	2SB329	2SB328, B>85	AC 125...126, AC 151...152, ASY 26...27
17720	2SB33	20V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17721	2SB330	110V, 0,15A, 0,225W	ACY 39, 2N2042...2043
17722	2SB331(H)	40V, 15A, 80W	2N1980, 2N2078, 2N2082, 2N2491
17723	2SB332(H)	2SB331, 60V	2N1981, 2N2076, 2N2080, 2N2491
17724	2SB333(H)	2SB331, 80V	2N1982, 2N2075, 2N2079, 2N2492
17725	2SB334(H)	2SB331, 100V	2N2493
17726	2SB335	20V, 0,06A, 0,083W, B60	AC 125...126, AC 151, 2SB54, 2SB56
17727	2SB336	2SB335, B120	AC 125...126, AC 151, 2SB54, 2SB56
17728	2SB337(H)	40V, 7A, 30W	AL 102...103, AUY 22, 2N3611, 2N3613
17729	2SB338(H)	2SB337, 60V	AL 102...103, AUY 22, 2N3612, 2N3614

17730	2SB339(H)	80V, 10A, 44W	AL 100...101, 2N2289, 2N2292, 2N2526
17731	2SB34	20V, 0,15A, 0,25W	AC 125...126, AC 151, 2SB54, 2SB56
17732	2SB340(H)	2SB339, 100V	AL 100...101, 2N2290, 2N2293, 2N2527
17733	2SB341(H)	2SB339, 120V	AL 100...101, 2N2290, 2N2293, 2N2527
17734	2SB342	120V, 6A, 30W	AU 110, AU 210, 2N2527...2528
17735	2SB343	2SB342, 150V	AU 107, AU 110, 2N2528
17736	2SB345	32V, 0,1A, 0,165W, $\beta > 65$	AC 125...126, AC 151, 2SB54, 2SB56
17737	2SB346	2SB345, $\beta > 80$	AC 125...126, AC 151, 2SB54, 2SB56
17738	2SB347	2SB345	AC 125...126, AC 151r, ACY 32, 2SB173
17739	2SB348	2SB345, $\beta > 80$	AC 125...126, AC 151r, ACY 32, 2SB173
17740	2SB349	20V, 0,01A, 0,05W	AC 125...126, AC 151, 2SB54, 2SB56
17741	2SB350	25V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17742	2SB351	40V, 15A, 70W	2N1980, 2N2078, 2N2082, 2N2491
17743	2SB352	2SB351, 60V	2N1981, 2N2076, 2N2080, 2N2492
17744	2SB353	2SB351, 80V	2N1982, 2N2075, 2N2079, 2N2492
17745	2SB354	2SB351, 100V	2N2493
17746	2SB355	25V, 1A, 15W	AD 162, 2SB474, 2SB481
17747	2SB356	2SB355, 80V	-
17748	2SB357	2SB355, 100V	-
17749	2SB358	80V, 6A, 50W	AL 102...103, 2N3615, 2N3617, 2N2526
17750	2SB359	2SB358, 120V, 10A	AL 100, 2N2290, 2N2293, 2N2527
17751	2SB360	2SB358, 180V, 10A	AU 107, AU 113, AU 213, 2N5324
17752	2SB361(H)	80V, 5A, 40W	AL 102...103, AUY 22, 2N1541, 2N1546
17753	2SB362(H)	100V, 7A, 50W	AL 102...103, 2N3616, 2N3618, 2N2527
17754	2SB363	140V, 8A, 43W	AU 107, AU 110, AU 210, 2N2528
17755	2SB364	20V, 0,4A, 0,15W, $B > 60$	AC 128, AC 153, AC 188, 2SB475
17756	2SB365	2SB364, $B > 35$	AC 128, AC 153, AC 188, 2SB475
17757	2SB366	140V, 8A, 43W	AU 107, AU 110, AU 210, 2N2528
17758	2SB367(H)	25V, 1A, 6,6W	AD 162, 2SB474, 2SB481
17759	2SB368(H)	2SB367, 45V	-
17760	2SB37	30V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17761	2SB370(H)	25V, 0,5A, 0,2W	AC 128, AC 153, AC 188, 2SB405, 2SB475
17762	2SB370A(AH)	2SB370, 32V	AC 128, AC 153, 2SB415, 2SB475
17763	2SB371	32V, 0,2A, 0,165W	AC 125...126, AC 151...152, 2SB475
17764	2SB372	25V, 1A, 1,5W, B70	AC 128, AC 153, AC 188, 2SB405, 2SB415
17765	2SB373	2SB372, B150	AC 128, AC 153, AC 188, 2SB405, 2SB415
17766	2SB374	2SB372, 60V, B150	2N1039, 2N2565
17767	2SB375(A)	150V, 9A, 30W	AU 107, AU 110, AU 113, AU 213, 2N5324
17768	2SB376	20V, 0,3A, 0,225W	AC 128, AC 152...153, AC 188, 2SB475
17769	2SB377	32V, 0,15A, 0,27W	AC 125...126, AC 151r, ACY 32, 2SB173
17770	2SB378	18V, 0,15A, 0,18W	AC 128, AC 152...153, AC 188, 2SB475
17771	2SB378A,B	2SB378, 23V, 0,3..0,5A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17772	2SB379	18V, 0,15A, 0,18W	AC 128, AC 152...153, AC 188, 2SB475
17773	2SB379A,B	2SB379, 23V, 0,3..0,5A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17774	2SB38	30V, 0,15A, 0,25W	AC 125...126, AC 151, 2SB54, 2SB56

17775	2SB380	18V, 0,15A, 0,18W	AC 128, AC 152...153, AC 188, 2SB475
17776	2SB380A,B	2SB380, 23V, 0,3..0,5A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17777	2SB381	32V, 0,3A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17778	2SB382	32V, 0,3A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17779	2SB383	32V, 0,5A, 0,27W	AC 128, AC 152...153, AC 188, 2SB475
17780	2SB384	20V, 0,03A, 0,08W, B60	AC 125...126, AC 151, 2SB54, 2SB56
17781	2SB385	2SB384, B50	AC 125...126, AC 151, 2SB54, 2SB56
17782	2SB386	30V, 0,3A, 0,15W	AC 128, AC 152...153, AC 188, ASY 26
17783	2SB387	12V, 0,02A, 0,03W	AC 125...126, AC 151, 2SB54, 2SB56
17784	2SB389	12V, 0,01A, 0,08W	AC 125...126, AC 151r, ACY 32, 2SB173
17785	2SB39	10V, 2mA, 0,05W	AC 125...126, AC 151r, ACY 32, 2SB173
17786	2SB390	80V, 6A, 30W	AL 102...103, AUY 22, 2N3615, 2N3617
17787	2SB391	2SB390, 50V	AL 102...103, AUY 22, 2N3612, 2N3614
17788	2SB392	20V, 0,2A, 0,2W	AC 125...126, AC 151...152, ASY 26...27
17789	2SB393	28V, 0,2A, 0,2W	AC 125...126, AC 151...152, ASY 26...27
17790	2SB394	28V, 0,2A, 0,2W	AC 125...126, AC 151...152, ASY 26...27
17791	2SB395	28V, 0,2A, 0,2W	AC 125...126, AC 151...152, ASY 26...27
17792	2SB396	40V, 0,2A, 0,15W	ASY 48, ASY 76...77, 2N1191...94
17793	2SB397	48V, 0,08A, 0,2W	ASY 48, ASY 77, 2N1191...94
17794	2SB398	110V, 0,08A, 0,2W	ACY 39, 2N2042...2043
17795	2SB399	110V, 0,08A, 0,2W	ACY 39, 2N2042...2043
17796	2SB40	40V, 0,1A, 0,08W	ASY 48, ASY 76...77, 2SB177
17797	2SB400	20V, 0,04A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
17798	2SB401	40V, 0,3A, 0,24W	ACY 24, ASY 48, ASY 76...77
17799	2SB402	2SB401, 60V	ACY 24, ASY 48, ASY 77
17800	2SB403	40V, 0,3A, 0,24W	ACY 24, ASY 48, ASY 76...77
17801	2SB404	100V, 0,1A, 0,1W	ACY 39, 2N2042...43
17802	2SB405	25V, 1A, 0,21W	AC 128, AC 153, AC 188, 2SB415
17803	2SB405K	2SB405	AC 128K, AC 153K, AC 188K
17804	2SB405ST	2SB405, 40V	-
17805	2SB406	200/100V, 10A, 37,5W	AU 107, AU 113, AU 213, 2N5324
17806	2SB407	30V, 7A, 30W	AL 102...AL 103, AUY 22, 2N3611, 2N3613
17807	2SB41	40V, 1,2A, 44W	AD 149, AUY 19, 2N2138, 2N2143, 2SB449
17808	2SB410	135V, 15A, 40W	AU 107, AU 110, AU 210
17809	2SB411	200V, 11A, 40W	AU 107, AU 113, AU 213, 2N5324
17810	2SB412	300V, 11A, 40W	AU 106, AU 109, AU 111, AU 112, 2N5325
17811	2SB413	60V, 1,5A, 12,5W	-
17812	2SB414	2SB413, 32V	AD 162, 2SB474, 2SB481
17813	2SB415	32V, 1A, 0,2W	AC 128, AC 153, AC 188, 2SB324
17814	2SB416	25V, 0,08A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17815	2SB417	2SB416, 45V	ACY 24, ASY 48, ASY 77, 2N1191...91
17816	2SB418	2SB416, 70V	ACY 24, ASY 48, ASY 77, 2N2042...43
17817	2SB419(H)	45V, 1,5A, 6W	-
17818	2SB42	2SB41, 60V	AD 166, AUY 19, 2N2139, 2N2144
17819	2SB420	120V, 1,5A, 6W	-

17820	2SB421	80V, 0,6A, 0,3W	ACY 39, 2N2042...2043
17821	2SB422	18V, 0,04A, 0,06W	AC 125...126, AC 151, 2SB54, 2SB56
17822	2SB423	30V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17823	2SB424	80V, 3A, 30W	AUY 20, 2N1541, 2N1546, 2N2141, 2N2146
17824	2SB425	2SB424, 60V	AUY 19, 2N1540, 2N1545, 2N2139, 2N2144
17825	2SB426	32V, 3A, 30W	AUY 19, 2N1539, 2N1544, 2N2137, 2N2142
17826	2SB426A	2SB426, 45V	AUY 19, 2N1539, 2N1544, 2N2138, 2N2143
17827	2SB427	45V, 0,5A, 0,225A, B60	2N1189...90, 2SB405ST
17828	2SB428	2SB427, B90	2N1189...90, 2SB405ST
17829	2SB429	30V, 0,05A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
17830	2SB43	25V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
17831	2SB430	70V, 20A, 80W	2N1519, 2N1521, 2N1523
17832	2SB431	32V, 0,5A, 0,2W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17833	2SB432	150V, 5A, 50W	AU 107, AU 110, 2N2528
17834	2SB433(F)	70V, 15A, 56W	2N1981, 2N2076, 2N2080, 2N2490
17835	2SB434	50V, 3A, 25W, 10MHz	BD 242, BD 540A, BD 536, BD 936
17836	2SB435	2SB434, 40V	BD 242, BD 540, BD 534, BD 934
17837	2SB436	25V, 0,12A, 0,12W	AC 125...126, AC 151, 2SB54, 2SB56
17838	2SB437	2SB436, 45V	ACY 24, ASY 48, ASY 76...77, 2N1191...94
17839	2SB438	2SB436, 70V	ACY 24, ASY 48, ASY 76...77
17840	2SB439	30V, 0,15A, 0,15W	AC 125...126, AC 151r, ACY 32, 2SB173
17841	2SB43A	2SA43, 45V, 0,15A	ACY 24, ASY 48, 2SB55, 2SB56A
17842	2SB44	30V, 0,05A, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
17843	2SB440	30V, 0,15A, 0,15W	AC 125...126, AC 151r, ACY 32, 2SB173
17844	2SB441	160/45V, 6A, 40W	AU 107, AU 110, 2N2528
17845	2SB442(H)	160/60(H/80)V, 6A, 40W	AU 107, AU 110, 2N2528
17846	2SB443	18V, 0,01A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
17847	2SB444	18V, 0,01A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173
17848	2SB445	40V, 1,5A, 10W	AD 162, 2SB474, 2SB481
17849	2SB446	2SB445, 60V	-
17850	2SB447	220V, 6A, 45W	AU 113, AU 213, 2N5324
17851	2SB448	32V, 1A, 13W	AD 162, 2SB474, 2SB481
17852	2SB449	50V, 3,5A, 22,5W(Tc50°)	AD 149, AD 166...167, AUY 28, 2N1540
17853	2SB450	25V, 0,5A, 0,2W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17854	2SB450A	2SB450, 32V	AC 128, AC 153, 2SB324, 2SB415
17855	2SB451	25V, 1A, 0,3W, B80	AC 128, AC 153, AC 188, 2SB324, 2SB415
17856	2SB452	2SB451, B150	AC 128, AC 153, AC 188, 2SB324, 2SB415
17857	2SB452A	2SB451, 32V	AC 128, AC 153, 2SB324, 2SB415
17858	2SB453	30V, 0,3A, 0,25W	AC 128, AC 153, AC 188, ASY 48, 2SB475
17859	2SB454	2SB453, 80V	ACY 39, 2N2042...2043
17860	2SB455	2SB453, 105V	ACY 39, 2N2042...2043
17861	2SB456	80V, 1A, 13W	-
17862	2SB457	20V, 0,5A, 0,15W	AC 128, AC 153, AC 188, 2SB415, 2SB475
17863	2SB457A	2SB457, 32V	AC 128, AC 153, 2SB324, 2SB415
17864	2SB458	25V, 1A, 4W	AD 162, 2SB474, 2SB481

17865	2SB458A	2SB458, 45V	-
17866	2SB458B	2SB458, 100V	-
17867	2SB459	30V, 0,05A, 0,12W	AC 125...126, AC 151r, ACY 32, 2SB173
17868	2SB46	25V, 0,05A, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
17869	2SB460	2SB459, 40V	AC 125...126, AC 151r, ACY 32, 2SB173
17870	2SB461	35V, 1A, 0,25W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17871	2SB462	60V, 2A, 6W	-
17872	2SB463	2SB462, 32V	AD 162, 2SB474, 2SB481
17873	2SB464	100V, 6A, 30W	AL 102...103, 2N3616, 2N3618, 2N2527
17874	2SB465	2SB465, 60V	AL 102...103, 2N3612, 2N3614, 2N2527
17875	2SB466	40V, 0,5A, 12W	AD 162, 2SB474, 2SB481
17876	2SB467	2SB466, 60V	-
17877	2SB468	220/90V, 10A, 32W	AU 113, AU 213, 2N4324
17878	2SB468A	2SB468, 270/90V	AU 106, AU 109, AU 111, AU 112, 2N5325
17879	2SB47	25V, 0,05A, 0,08W	AC 125...126, AC 151r, ACY 32, 2SB173
17880	2SB470	25V, 0,05A, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
17881	2SB471	60V, 10A, 30W	AL 100...101, 2N2289, 2N2292, 2N2527
17882	2SB472	2SB471, 80V	AL 100...101, 2N2289, 2N2292, 2N2527
17883	2SB473	32V, 1A, 4,3W	AD 162, 2SB474, 2SB481
17884	2SB474	35V, 2A, 12W	AD 162, 2SB481
17885	2SB475	20V, 0,3A, 0,15W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17886	2SB476	20V, 2A, 6W(Tc25°)	AC153, AC 128, AC 188
17887	2SB477	30V, 30A, 80W	2N2152...2159
17888	2SB478	2SB477, 60V	2N2153...2155, 2N2157...2159
17889	2SB479	2SB477, 80V	2N2155, 2N2159
17890	2SB48	15V, 0,1A, 0,14W, B43	AC 125...126, AC 151, 2SB54, 2SB56
17891	2SB480	2SB477, 100V	2N2155, 2N2159
17892	2SB481	32V, 1A, 6W	AD 162, 2SB474
17893	2SB482	35V, 0,05A, 0,12W	AC 125...126, AC 151, 2SB54, 2SB56
17894	2SB483	80V, 15A, 60W	2N1551, 2N1555, 2N1559, 2N1652
17895	2SB484	2SB483, 100V	2N1552, 2N1556, 2N1560, 2N1652
17896	2SB485	2SB483, 140V	-
17897	2SB486	2SB482, 25V	AC 125...126, AC 151r, ACY 32, 2SB173
17898	2SB487	30V, 0,5A, 5W	AD 162, 2SB474, 2SB481
17899	2SB488	2SB487, 60V	-
17900	2SB49	2SB48, B83	AC 125...126, AC 151, 2SB54, 2SB56
17901	2SB492	25V, 2A, 6W(Tc25°)	AC153, (AC 128, AC 188)
17902	2SB492ST	2SB492, 50V	-
17903	2SB493	40V, 1A, 9W	AD 162, 2SB474, 2SB481
17904	2SB494	25V, 1A, 0,2W, B>38	AC 128, AC 153, AC 188, 2SB324, 2SB415
17905	2SB495	2SB494, B>57	AC 128, AC 153, AC 188, 2SB324, 2SB415
17906	2SB495A	2SB495, 32V	AC 128, AC 153, 2SB324, 2SB415
17907	2SB496	25V, 0,25A, 0,3W	AC 128, AC 152...153, AC 188, 2SB475
17908	2SB497	20V, 0,03A, 0,065W	AC 125...126, AC 151r, ACY 32, 2SB173
17909	2SB498	25V, 0,05A, 0,1W	AC 125...126, AC 151r, ACY 32, 2SB173

17910	2SB50	2SB48, B131	AC 125...126, AC 151, 2SB54, 2SB56
17911	2SB502	110V, 3A, 25W, 1MHz	BD 242C, BD 244C, BD 940, 2SB867
17912	2SB502A	2SB502, 5MHz, 1/4μs	BD 242C, BD 244C, BD 940, 2SB867
17913	2SB503	2SB502, 70V	BD 242A, BD 244A, BD 938, 2SB682
17914	2SB503A	2SB502, 80V	BD 242B, BD 244B, BD 938, 2SB682
17915	2SB504	80V, 2A, 1W, 35MHz	BCX 60, BSS 17...18, 2N5322...5323
17916	2SB504A	2SB504, 100V	BCX 60, BSS 17, 2N5322
17917	2SB505	2SB504, 15W	BD 520, BD 528, BD 530, BD 818
17918	2SB506(A)	150V, 5A, 60W, 10MHz	BD 246D, 2SB695...696, 2SB713, 2SB816
17919	2SB507	60V, 3A, 30W, 8MHz	BD 242A, BD 536, BD 936, 2SB1064
17920	2SB508	2SB507	BD 242A, BD 536, BD 936, 2SB1064
17921	2SB509	2SB507, 4A, 35W	BD 244A, BD 536, 2N3740...41, 2SA1262
17922	2SB51	30V, 0,2A, 0,2W	AC 128, AC 152...153, AC 188, 2SB324
17923	2SB510	80V, 1A, 0,8W, 50MHz	BC 161, BSV 16...17, 2N4030...33
17924	2SB511	35V, 1,5A, 10W, 8MHz	BD 240, BD 242, BD 534, 2SA748
17925	2SB511	35V, 1,5A, 10W, 8MHz	BD 240, BD 242, BD 534, 2SA748
17926	2SB512	60V, 3A, 25W, >3MHz	BD 242A, BD 536, BD 936, 2SB1064
17927	2SB512A	2SB512, 80V	BD 242B, BD 538, BD 938, 2SA1288
17928	2SB513(A)	2SB512(A)	2SB512(A)
17929	2SB514	50V, 2A, 20W, 8MHz	BD 240, BD 242, BD 536, BD 936
17930	2SB515	2SB514	2SB514
17931	2SB516	20V, 0,1A, 0,15W	AC 125...126, AC 151...152, 2SB54, 2SB56
17932	2SB518(-1,-2)	-170V, -290V, 7A, 60W, >3MHz	BD 246B, BDV 96, BDX 96, 2SA980...982
17933	2SB519(-1,-2)	10A,80W,>3MHz	BD 246C, BDW 22C, 2N6229...31, 2SA1141
17934	2SB52	30V, 0,2A, 0,2W	AC 128, AC 152...153, AC 188, 2SB324
17935	2SB520(-1,-2)	100W,>3MHz	BD246F, 2SA908, 2SB555, 2SB681, 2SB817
17936	2SB521(-1,-2)	-160V, -285V, 5A, 43W, 7MHz	BD 244B, BD 544B, BD 952, 2SA1012
17937	2SB522(-1,-2)	2SB521	2SB521
17938	2SB523	40V, 2A, 10W, 70MHz	2SA748, 2SA1288
17939	2SB524	2SB523, 60V, 1,5A	2SA748, 2SA1288
17940	2SB525	30V, 1A, 0,8W, 100MHz	BC 327...328, BC 636, BC 638, 2SB809
17941	2SB525	30V, 1A, 0,8W, 100MHz	BC 327...328, BC 636, BC 638, 2SB809
17942	2SB526	90V, 0,8A, 10W, 70MHz	2SA913(A), 2SA985(A), 2SA1111...1112
17943	2SB527	2SB526, 110V	2SA913(A), 2SA985(A), 2SA1111...1112
17944	2SB528	2SA526, 130V	2SA913(A), 2SA985A, 2SA1111...1112
17945	2SB529	40V, 2A, 10W, 70MHz	2SA748, 2SA1288
17946	2SB53	30V, 0,25A, 0,2W	AC 128, AC 152...153, AC 188, 2SB324
17947	2SB530	110V, 6A, 80W	BD 246C, 2SB688, 2SB776, 2SA981...982
17948	2SB531	90V, 6A, 50W, 8MHz	BD 246B, BD 314, BDV 94, BDX 94
17949	2SB532	80V, 5A, 60W, 10MHz	BD 246B, BD 314, BDV 94, BDX 94
17950	2SB533	20V, 2A, 6W(Tc25°)	2N1038, 2N2564
17951	2SB534	20V, 0,5A, 0,2W	AC 128, AC 153, AC 188, 2SB324, 2SB415
17952	2SB535	35V, 1A, 0,25W, 6W(Tc25°)	2N1038, 2N2564, AC 128, AC 153
17953	2SB536	130V, 1,5A, 20W, 40MHz	2SA968(A,B), 2SA985A, 2SB628(A)
17954	2SB537	2SB536	2SB536



17955	2SB538	65V, 15A, 75W	2N1551...52, 2N1555...56, 2N1559...60
17956	2SB539(A)	130V, 10A, 100W, 8MHz	BD 246D, 2SA1146, 2SB555, 2SB681
17957	2SB539B	2SB539(A), 150V	BD 246D, 2SA1386(A), 2SB681, 2SB697
17958	2SB539C	2SB539(A), 160V	BD 246D, 2SA1147, 2SB697, 2SB817
17959	2SB54	30V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB56, 2SB175
17960	2SB540	50V, 2A, 6W(Tc25°)	2N1039, 2N2565
17961	2SB541	110V, 8A, 80W, 9MHz	BD 246C, 2SA981...982, 2SA1141, 2SB681
17962	2SB542	20V, 0,5A, 0,3W, 150MHz	BC 327...328, BC 636, 2SA1515, 2SB910
17963	2SB542	20V, 0,5A, 0,3W, 150MHz	BC 327...328, BC 636, 2SA1515, 2SB910
17964	)	25V, 1A, 0,9W, 180MHz	2SA966, 2SA1382, 2SB892, 2SB927
17965	2SB546(A)	200V, 2A, 20W, 5MHz	BD 240F, 2SA 1133, 2SB630, 2SB861
17966	2SB547(A)	2SB546(A)	2SB546(A)
17967	2SB548	100/80V, 0,8A, 10W, 70MHz	BD 140, BD 231, 2SA1184, 2SA1220(A)
17968	2SB549	2SB548, 120/100V	2SA1178, 2SA1184, 2SA1220(A), 2SA1358
17969	2SB55	60V, 0,15A, 0,15W	ACY 24, ASY 48, 2N2042...43
17970	2SB550	100V, 5A, 25W, 20MHz	BD 244C, BD 540C, BD 954, 2SB633
17971	2SB551	50V, 3A, 25W, 32MHz	BD 242, BD 536, BD 936, BDX 14, 2SB1064
17972	2SB552	220V, 15A, 150W, 3,5MHz	BUW 96, 2SA1117, 2SA1294, 2SB613
17973	2SB553	70V, 7A, 40W, 10MHz	2SA1290, 2SB921L
17974	2SB554	180V, 15A, 150W, 6MHz	2SA908...09, 2SA1116...17, 2SA1147
17975	2SB555	2SB554, 140V, 12A, 100W	2SA908...909, 2SB681, 2SB697, 2SB817
17976	2SB556	2SB554, 120V, 12A, 100W	2SA908...909, 2SB681, 2SB697, 2SB817
17977	2SB557(S)	2SB554, 120V, 8A, 80..100W	BD 246D, 2SA981...982, 2SB688, 2SB696
17978	2SB558	2SB554, 100V, 7A, 60W	BD 246C, BDV 96, BDX 96, 2SA980...982
17979	2SB559	20V, 1,2A, 8W, 150MHz	BD 136, BD 227, BD 376, 2SB1009
17980	2SB56	30V, 0,15A, 0,15W	AC 128, AC 151...153, AC 188, 2SB324
17981	2SB560(MP)	100V, 0,7A, 0,9W, 100MHz	2SA965, 2SB647, 2SA1013, 2SA1275
17982	2SB561	25V, 0,7A, 0,5W, 350MHz	BC 327...328, BC 636, 2SA1705
17983	2SB562	2SB561, 1A, 0,9W	2SA966, 2SA1382, 2SB978, 2SB892
17984	2SB563	80V, 3A, 25W	BD 242B, BD 538, BDX 14, 2SA1288
17985	2SB564	30V, 1A, 1W, 110MHz	BC 327...328, BC 636, 2SB909, 2SB1116
17986	2SB565(A)	70V, 4A, 40W, 15MHz	BD 244B, BD 538, BD 952, 2SB633
17987	2SB566(A)	2SB565	2SB565
17988	2SB567	200V, 2A, 30W	BD 240F, 2SA1133, 2SB630, 2SB861
17989	2SB568	2SB567	2SB567
17990	2SB569	40V, 4A, 40W, B6000	BD 676, BD 776, 2N6034...6036
17991	2SB56A	2SB56, 45V	ACY 24, ASY 48, ASY 76...77, 2N1189...90
17992	2SB57	30V, 0,1A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
17993	2SB570	2SB569, 60V	BD 678, BD 778, 2N6035...6036
17994	2SB571	2SB569, 80V	BD 680, BD 780, 2N6036
17995	2SB572	40V, 3A, 30W	BD 176, BD 186, BD 438, 2N5193...95
17996	2SB573	2SB572, 60V	BD 178, BD 190, BD 440, 2N5194...95
17997	2SB574	2SB572, 80V	BD 180, BD 442, 2N5195
17998	2SB575	40V, 4A, 40W	BD 186, BD 438, 2N5193...5195
17999	2SB576	2SB575, 60V	BD 190, BD 440, 2N5194...5195

18000	2SB577	2SB575, 80V	BD 442, 2N5195
18001	2SB578	70V, 10A, 90W	BD 208, MJE 2955
18002	2SB579	60V, 5A, 75W	BD 200, 2N5974...5976
18003	2SB57A	45V, 0,5A, 0,225W	ASY 76...77, 2N1189...90
18004	2SB58	12V, 0,05A, 0,1W	AC 125...126, AC 151, 2SB54, 2SB56
18005	2SB580	2SB579, 80V	2N5975...5976
18006	2SB581	2SB579, 100V	2N5976
18007	2SB582	60V, 8A, 75W, B3000	BDV 64(A...C), TIP 145...147
18008	2SB583	2SB582, 80V	BDV 64A...C, TIP 146...147
18009	2SB584	2SB582, 100V	BDV 64B...C, TIP 147
18010	2SB585	60V, 8A, 100W, B3000	BDV 64(A...C), BDX 84A...C, BDX 86A...C
18011	2SB586	2SB585, 80V	BDV 64A...C, BDX 84B...C, BDX 86B...C
18012	2SB587	60V, 12A, 150W, B3000	BDV 64(A...C), BDW 84A...D, BDX 88A...C
18013	2SB588	2SB587, 80V	BDV 64A...C, BDW 84B...D, BDX 88B...C
18014	2SB589	2SB587, 100V	BDV 64B...C, BDW 84C...D, BDX 88C
18015	2SB59	30V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18016	2SB595	100V, 5A, 40W, 5MHz	BD 244C, BD 544C, BD 954, 2SB633
18017	2SB596	80V, 4A, 30W, >3MHz	BD 244B, BD 538, BD 952, 2SB920
18018	2SB598	25V, 1A, 0,5W, 180MHz	2SB892, 2SB926...927, 2SB1229
18019	2SB599	200V, 2A, 30W	BD 240F, 2SA1133, 2SB630, 2SB861
18020	2SB60(A)	20V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18021	2SB600	200V, 10A, 200W, 14MHz	MJ 15016, 2SA1116...17, 2SB613, 2SB645
18022	2SB601	100V, 5A, 30W, B>2000	BD 650, BD 902, BDW 24C, BDW 64C...D
18023	2SB603	500V, 0,5A, 0,8W	2N5096
18024	2SB604	70V, 4A, 30W, 10MHz	BD 244A, BD 538, BD 952, 2SB920
18025	2SB605	60V, 0,7A, 1W, 120MHz	BC 638, BC 640, 2SB647, 2SB910, 2SB1116
18026	2SB606	250V, 0,5A, 0,8W, 200/2000ns	BFT 44...45, MJ 5415...16, 2N5416
18027	2SB607	30V, 1A, 3W(Tc25°)	AC 128, AC 153, AC 188, 2N1038, 2N2564
18028	2SB608(A)	180V, 2A, 30W	2SB991
18029	2SB609	100V, 4A, 40W	BD 244C, BD 540C, BD954, 2SB550
18030	2SB61	30V, 0,05A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18031	2SB611(A)	150V, 7A, 60W	BD 246D, 2SB696, 2SB713, 2SB816
18032	2SB612(A)	180V, 12A, 100W	MJ 15016, BD 746F, 2SA1147, 2SB645
18033	2SB613	250V, 15A, 150W	BUW 42, MJ 15023, MJ 15025
18034	2SB615	110V, 7A, 80W, B>1100	BDV 64C, BDX 62C, BDX 64C, 2SA1183
18035	2SB616(A)	100V, 5A, 60W, 22MHz	2SA986, 2SB758(A), 2SB773(A)
18036	2SB617(A)	14MHz	2SA986, 2SB758(A), 2SB773A
18037	2SB618(A)	14MHz	-
18038	2SB619	32V, 1,3A, 0,3W	AC 153, 2N1038, 2N2564, AC 128
18039	2SB62	60V, 0,5A, 4W	-
18040	2SB620	25V, 0,05A, 0,25W, 100MHz	BC 213, BC 258, BC 308, BC 558
18041	2SB621(NC)	30V, 1A, 0,75W, 200MHz	BC 327...328, BC 636, BC 638, 2SB809
18042	2SB621A	2SB621, 60V	BC 638, BC 640, 2SA1705, 2SB647
18043	2SB621A	2SB621, 60V	BC 638, BC 640, 2SA1705, 2SB647
18044	2SB622	400V, 0,3A, 0,8W, 10MHz	2N5093...96, 2SB603

18045	2SB624	30V, 0,7A, 160MHz	BCW 67...68, 2SA1621
18046	2SB624R	2SB624	BCW 67R...68R
18047	2SB625	100V, 7A, 60W, 7MHz	BD 246C, BDV 96, BDX 96, 2SA980...982
18048	2SB626	2SB625, 120V, 8A, 80W, 6MHz	BD 246C, 2SA980...982, 2SA1141
18049	2SB627	40V, 10A, 13W	AD 136, AUY 35...36
18050	2SB628	160V, 1,5A, 20W, 40MHz	2SA913A, 2SA1112, 2SB608, 2SB861
18051	2SB628A	2SB628, 180V	2SA913A, 2SA1112, 2SB608, 2SB861
18052	2SB63	2SB62, 32V	AD 162, 2SB474
18053	2SB630	200V, 2A, 25W, 4MHz	BD 240F, 2SA1133, 2SB861
18054	2SB631	100V, 1A, 8W, 110MHz	BD 140, BD 231, BD 380, 2SA1184
18055	2SB631K	2SB631, 120V	2SA1178, 2SA1184, 2SA1220(A), 2SA1358
18056	2SB632	25V, 2A, 10W, 100MHz	BD 330, BD 376, 2SB1009
18057	2SB632K	2SB632, 35V	BD 376, 2SB744(A), 2SB1009
18058	2SB633	100V, 6A, 40W, 15MHz	BD 244C, BD 544C, BD 802
18059	2SB633P	2SB633, 50W	2SB617...618, 2SB773(A), 2SB758(A)
18060	2SB634	120V, 7A, 60W, 15MHz	BD 246C, 2SA1141, 2SB981...982
18061	2SB635	32V, 0,15A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18062	2SB636	32V, 0,15A, 0,15W	AC 125...126, AC 151r, ACY 32, 2SB173
18063	2SB637(K)	50V, 0,1A, 0,3W, 200MHz	BC 212, BC 257, BC 307, BC 557
18064	2SB638(H)	100V, 10A, 80W, B>1000	BDV 64B, BDX 84C, BDX 86C, 2N6052
18065	2SB639(H)	2SB638, 100W	BDV 64B, BDX 84C, BDX 86C, 2N6052
18066	2SB64	100V, 6A, 25W	AL 102...103, 2N3616, 2N3618, 2SB231
18067	2SB640	25V, 0,3A, 0,15W	AC 128, AC 152...153, AC 188, 2SB475
18068	2SB641	30V, 0,1A, 0,4W, 80MHz	BC 213, BC 258, BC 308, BC 558
18069	2SB642	2SB641, 60V	BC 212, BC 256, BC 266, BC 556
18070	2SB643	30V, 0,5A, 0,6W, 200MHz	BC 327...328, BC 636, BC 638, 2SA1515
18071	2SB644	2SB643, 60V	BC 638, BC 640, 2N5400...01, 2SA965
18072	2SB645	200V, 15A, 150W, 12MHz	MJ 15016, 2SA909, 2SA1116...17, 2SB613
18073	2SB646(A)	120V, 0,05A, 0,9W, 140MHz	2SA1124, 2SA1281, 2SA1285(A), 2SA1482
18074	2SB647(A)	120V, 1A, 0,9W, 140MHz	2SA1013, 2SA1275, 2SB1212
18075	2SB648(A)	180V, 0,05A, 140MHz	BF 470, BF 472, BF 416, BF 418, 2SA1352
18076	2SB649(A)	180V, 1,5A, 140MHz	2SA1249
18077	2SB65	30V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18078	2SB650(H)	100V, 15A, 100W, B>1000	BDV 66A, BDW 84C, BDX 66B, MJ 4032
18079	2SB653(A)	120V, 7A, 60W, 20MHz	BD 246C, 2SA1141, 2SA981...982
18080	2SB654(A)	2SB653(A), 80W	BD 246C, 2SA1141, 2SA981...982
18081	2SB655(A)	160V, 12A, 100W, 20MHz	2SA1227A, 2SA1386, 2SB554, 2SB697
18082	2SB656(A)	2SB655(A), 125W	MJ 15016, 2SA909, 2SA1116...17, 2SB554
18083	2SB66(H)	30V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18084	2SB668	60V, 3A, 25W, B>1000	BD 716, BDW 24A, BDW 54A, 2SB751
18085	2SB668A	2SB668, 80V	BD 718, BDW 24B, BDW 54B, 2SB751A
18086	2SB669	70V, 4A, 40W, B>1000	BD 718, BDW 24B, BDW 54B, BDW 64B
18087	2SB669A	2SB669, 90V	BD 902, BDW 24C, BDW 54C, BDW 64C
18088	2SB67(H)	30V, 0,15A, 0,35W	AC 125...126, AC 151, 2SB54, 2SB56
18089	2SB670	90V, 5A, 60W, B>1000	BDV 64B, BDX62B, TIP 147, 2SA1183

18090	2SB670A	2SB670, 110V	BDV 64C, BDX62C, TIP 147, 2SA1183
18091	2SB671	100V, 7A, 80W, B>1000	BDV 64B, BDX62B, BDX 84C, TIP 147
18092	2SB671A	2SB671, 120V	BDV 64C, BDW 84D, BDX62C, BDX 64C
18093	2SB672	120V, 8A, 110W, B>1000	BDV 64C, BDV 66B, BDW 84D, BDX 64C
18094	2SB672A	2SB672, 140V	BDV 66C
18095	2SB673	100V, 7A, 40W, B>2000	BD 650, BD 902, BDW 74C, BDX 54C
18096	2SB674	2SB673, 80V	BD 648, BD 900, BDW 74B, BDX 54B
18097	2SB675	2SB673, 60V	BD 646, BD 898, BDW 74A, BDX 54A
18098	2SB676	100V, 4A, 30W, B>2000	BD 902, BDW 24C, BDW 54C, BDW 64C
18099	2SB677	2SB676, 60V	BD 898, BDW 24A, BDW 54A, BDW 64A
18100	2SB678	B>2000	BD 682
18101	2SB679	2SB678, 10W	BDW 54C, 2SB751B
18102	2SB67A(AH)	2SB67, 60V	ACY 24, ASY 48, ASY 77, 2SB55
18103	2SB68(H)	105V, 0,1A, 0,05W	ACY 39, 2N2042...2043
18104	2SB681	150V, 12A, 100W, 13MHz	BD 746E, 2SA908, 2SA1227A, 2SB697
18105	2SB682	100V, 4A, 30W, 8MHz	BD 244C, BD 540C, BD 954, 2SB633
18106	2SB683	100V, 5A, 40W, 8MHz	BD 244C, BD 540C, BD 954, 2SB633
18107	2SB685	B>2000	BDV 64C, BDW 84D, 2SA1183
18108	2SB686	100V, 6A, 60W, 10MHz	BD 246C, BDV 96, 2SA1141, 2SB775...76
18109	2SB688	120V, 8A, 80W, 10MHz	BD 246C, 2SA1141, 2SA1146, 2SA1186
18110	2SB689	100V, 4A, 40W	BD 244C, BD 540C, BD 954, 2SB633
18111	2SB69	60V, 6A, 25W	AL 102...103, 2N3612, 2N3614, 2SB231
18112	2SB690	100V, 4A, 40W, 20MHz	BD 244C, BD 540C, BD 954, 2SB633
18113	2SB691	130V, 5A, 60W, 7MHz	BD246D, 2SA1146, 2SB695, 2SB713, 2SB816
18114	2SB692	150V, 6A, 70W, 7MHz	2SB713
18115	2SB693(H)	100V, 20A, 125W, B>1000	BDX 68B, MJ 11013, 2N6287
18116	2SB694(H)	2SB693, 25A	BDX 68B, MJ 11013, MJ 11015
18117	2SB695	170V, 7A, 80W, 7MHz	BD 246E, 2SA1294, 2SA1386A, 2SB713
18118	2SB696(K)	150V, 8A, 80W, 15MHz	BD 246D, 2SA1186, 2SB681, 2SB697
18119	2SB697	160V, 12A, 100W, 15MHz	BD 746F, 2SA1147, 2SB554, 2SB645
18120	2SB697K	2SB697, 180V	MJ 15016, BD 746F, 2SA1147, 2SB645
18121	2SB698	25V, 0,7A, 0,6W, 250MHz	2SA1703, 2SB892, 2SB926...927
18122	2SB699	160/120V, 12A, 100W	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
18123	2SB70	30V, 0,01, 0,125W, B30	AC 125...126, AC 151, 2SB54, 2SB56
18124	2SB700(A)	2SB699, 160/140V	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
18125	2SB701	160V, 12A, 120W	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
18126	2SB702(A)	160V, 12A, 125W	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
18127	2SB703(A)	100V, 4A, 40W, 18MHz	BD 244C, BD 540C, BD954, 2SB682
18128	2SB705	140V, 10A, 120W, 17MHz	2SA1094...1095, 2SA1187, 2SB755
18129	2SB705A	2SB705, 150V	2SA1076, 2SA1095, 2SA1187, 2SB755
18130	2SB705B	2SB705, 160V	2SA1076, 2SA1095, 2SA1166(A), 2SA1215
18131	2SB707	80V, 7A, 40W	BD 244B, BD 544B, BD 800, BD 810
18132	2SB708	80V, 7A, 40W	BD 244B, BD 544B, BD 800, BD 810
18133	2SB709	25V, 0,1A, 80MHz	BC 856...858, BCW 29...30, BCW 69...70
18134	2SB709A	2SB709, 45V	BC 856...857, BCW 69...70, BCW 89

18135	2SB71	2SB70, B50	AC 125...126, AC 151, 2SB54, 2SB56
18136	2SB710	30V, 0,5A, 200MHz	BC 807...808, BCW 67...68, BCX 17...18
18137	2SB710A	2SB710, 60V	BCW 68, 2SA1366
18138	2SB711	80V, 6A, 50W, B1000	BD 648, BD 900, BDW 24B, BDW 74B
18139	2SB712	2SB711, 100V	BD 650, BD 902, BDW 24C, BDW 74C
18140	2SB713	200V, 9A, 100W, 7MHz	BD 246F, 2SA1294
18141	2SB714	20V, 2A, 6W(Tc25°)	AC 153, 2N1038, 2N2564
18142	2SB715	100V, 0,05A, 0,75W, 150MHz	2SA1124, 2SA1281, 2SA1285(A), 2SA1482
18143	2SB716	2SB715, 120V	2SA1124, 2SA1281, 2SA1285(A), 2SA1482
18144	2SB716A	2SB715, 140V	2SA1124, 2SA1281, 2SA1285A, 2SA1482
18145	2SB717	160V, 0,05A, 140MHz	2SA1383, BF416, BF418, BF470, BF472
18146	2SB718	2SB717, 200V	BF 416, BF 418, BF 470, BF 472
18147	2SB719	160V, 2A, 25W, 100MHz	2SA1079, 2SA1133
18148	2SB720	2SB719, 200V	2SA1133
18149	2SB721	25V, 0,7A, 0,625W, 350MHz	BC 327...328, BC 636, 2SB909...910
18150	2SB722	160V, 15A, 150W	MJ 15016, 2N6609, 2SA1116...17, 2SB554
18151	2SB723	2SB722, 200V	MJ 15016, 2SA909, 2SA1116...17, 2SB645
18152	2SB724	60V, 3A, 25W	BD 242A, BD 536, BD 936, 2SB1064
18153	2SB725	60V, 0,1A, 0,45W, 80MHz	BC 212, BC 256, BC 266, BC 556
18154	2SB726	80V, 0,1A, 0,25W, 150MHz	BC 556, 2SA970, 2SA1136...1137, 2SA1285
18155	2SB727(K)	120V, 6A, 50W, B>1000	BD 652, BDT 20, BDW 64D, BDW 74D
18156	2SB73	10V, 2mA, 0,02W	AC 125...126, AC 151r, ACY 32, 2SB173
18157	2SB731	60V, 1A, 10W, 75MHz	BD 138, BD 229, BD 378, 2SB874...875
18158	2SB733	20V, 2A, 1W, >50MHz	2SA1704, 2SB892, 2SB926...927, 2SB1433
18159	2SB734	60V, 1A, 1W, 80MHz	2SA1315, 2SA1429, 2SB1116, 2SB1229
18160	2SB736	60V, 0,3A, 100MHz	BCW 68, 2SA1366, 2SB1198
18161	2SB736A	2SB736, 80V	BCX 42, 2SB1198
18162	2SB736AR	2SB736, 80V	BCX 42R
18163	2SB736R	2SB736	BCW 68R
18164	2SB737	50V, 0,3A, 0,25W, 100MHz	BC 416, BC 560, 2SA970, 2SA1136...1137
18165	2SB738	20/16V, 2A, 0,9W, 150MHz	2SA1382, 2SB892, 2SB927, 2SB1312
18166	2SB739	2SB738, 20/20V	2SA1382, 2SB892, 2SB927, 2SB1312
18167	2SB73N	2SB73, 18V, 40mA, 0,065W	AC 125...126, AC 151r, ACY 32, 2SB173
18168	2SB74	16V, 15mA, 0,08W	AC 125...126, AC 151, 2SB54, 2SB56
18169	2SB740	70/50V, 1A, 0,9W	2SA1013, 2SA1315, 2SB647, 2SB1212
18170	2SB741	2SB740, 70/70V	2SA1013, 2SA1315, 2SB647, 2SB1212
18171	2SB742	20V, 2A, 10W	BD 176, BD 234, BD 330, BD 376
18172	2SB743	40V, 3A, 10W, 55MHz	BD 786, MJE 250...254, 2SB986
18173	2SB744(A)	70V, 3A, 10W, 45MHz	BD 788, BD 790, MJE 250...254
18174	2SB745	35V, 0,05A, 0,4W, 150MHz	BC 214, BC 259, BC 309, BC 559, 2SA1137
18175	2SB745A	2SB745, 55V	BC 416, BC 560, 2SA970, 2SA1136...1137
18176	2SB746	25V, 0,5A, 0,4W, 260MHz	BC 327...328, BC 636, BC 638, 2SB909
18177	2SB747	80V, 5A, 55W, 7MHz	BD 244 B, BD 544B, BD 952, 2SB920L
18178	2SB748(A)	120V, 6A, 60W, 20MHz	2SA1075...1076, 2SA1094, 2SB705(A,B)
18179	2SB749(A)	120V, 7A, 80W, 20MHz	2SA1075...1076, 2SA1094, 2SB705(A,B)



18180	2SB75(H)	25V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18181	2SB750	60V, 2A, 35W, B>1000	BD 716, BDW 24A, BDW 54A, BDW 64A
18182	2SB750A	2SB750, 80V	BD 718, BDW 24B, BDW 54B, BDW 64B
18183	2SB750B	2SB750, 100V	BDW 24C, BDW 54C, BDW 64C
18184	2SB751	60V, 4A, 40W, B>1000	BD 646, BD 898, BDW 24A, BDW 64A
18185	2SB751A	2SB751, 80V	BD 648, BD 900, BDW 24B, BDW 64B
18186	2SB751B	2SB751, 100V	BD 650, BD 902, BDW 24C, BDW 64C
18187	2SB753	100V, 7A, 40W, 10MHz	2SA1293
18188	2SB754	50V, 7A, 60W, 10MHz	2SB827
18189	2SB755	150V, 12A, 120W, 20MHz	2SA1076, 2SA1166(A), 2SA1187, 2SA1095
18190	2SB756	200V, 15A, 150W, 20MHz	2SA1169...1170, 2SA1295, 2SA1333
18191	2SB757	40V, 15A, 80W	BD 250, BD 546, BD 746, 2SA1292
18192	2SB758	120V, 7A, 80W	2SA986, 2SB618
18193	2SB758A	2SB758, 130V	2SA986, 2SB618
18194	2SB759	25V, 0,05A, 0,25W, 200MHz	BC 213, BC 258, BC 308, BC 558
18195	2SB759A	2SB759, 45V	BC 212, BC 257, BC 307, BC 557
18196	2SB75A(AH)	2SB75, 45V	ACY 24, ASY 48, 2SB55
18197	2SB76	12V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18198	2SB760	60V, 1A, 30W	BD 240A, BD 242A, 2SA748, 2SA1288
18199	2SB760A	2SB760, 80V	BD 240B, BD 242B, 2SA985(A), 2SA1288
18200	2SB760B	2SB760, 100V	BD 240C, BD 242C, 2SA985(A), 2SA1393
18201	2SB761	60V, 3A, 35W	BD 242A, BD 536, BD 936, 2SA1262
18202	2SB761A	2SB761, 80V	BD 242B, BD 538, BD 938, 2SB682
18203	2SB761B	2SB761, 100V	BD 242C, BD 938, 2SB633, 2SB682
18204	2SB762	60V, 4A, 40W	BD 244A, BD 536, BD 950, 2SA1262
18205	2SB762A	2SB762, 80V	BD 244B, BD 538, BD 952, 2SB920L
18206	2SB762B	2SB762, 100V	BD 244C, BD 540C, BD 954, 2SB633
18207	2SB763	60V, 5A, 60W	BD 246A, BDV 92, 2SB775, 2SB688
18208	2SB763A	2SB763, 80V	BD 246B, BDV 94, 2SB775, 2SB688
18209	2SB763B	2SB763, 100V	BD 246C, BDV 96, 2SB775, 2SB688
18210	2SB764	60V, 1A, 0,9W, 150MHz	2SA1315, 2SB647, 2SB892, 2SB1041
18211	2SB765(K)	120V, 3A, 30W, B>1000	BDT 20, BDW 54D, BDW 64D
18212	2SB766	30V, 1A, 200MHz	BC 869, BCX 69, 2SA1203, 2SA1314
18213	2SB766A	2SB766, 60V	BCX 52...53, 2SA1364, 2SB804, 2SB1025
18214	2SB767	80V, 0,5A, 120MHz	2SA1368, 2SB789(A), 2SB805...806
18215	2SB768	200V, 2A, 20W, 10MHz	2SB928(A), 2SB630, 2SB861
18216	2SB77(H,N)	25V, 0,1A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18217	2SB772	40V, 3A, 10W, 80MHz	BD 786, MJE 250...254, 2SB744(A)
18218	2SB773	100V, 6A, 70W	2SA986, 2SB617, 2SB618, 2SB758(A)
18219	2SB773A	2SB773, 120V	2SA986, 2SB617, 2SB618, 2SB758(A)
18220	2SB774	30V, 0,1A, 0,4W, 150MHz	2SB894, 2SB1206, BC 308, BC 558
18221	2SB775	100V, 6A, 60W, 18MHz	BD 246C, BDV 96, 2SA1141, 2SB688
18222	2SB776	120V, 7A, 70W, 15MHz	BD 246C, 2SA1146, 2SA1186, 2SB688
18223	2SB777	80V, 10A, 80W, <1/3µs	BD 246B, BDV 94, 2SA1141, 2SA1146
18224	2SB778	2SB777, 120V	BD 246C, 2SA1141, 2SA1146, 2SB817



18225	2SB779	25V, 0,5A, 150MHz	2SA1298, BC 807...808, BCX 17...18
18226	2SB77A(AH,AN)	2SB77, 45V	ACY 24, ASY 48, 2SB55
18227	2SB78	12V, 0,07A, 0,15W	AC 125...126, AC 151, 2SB54, 2SB56
18228	2SB780	30V, 0,5A, 0,4W, 200MHz	BC 327...328, BC 636, BC 638, 2SB909
18229	2SB781	50V, 4A, 30W	BD 244, BD 536, BD 950, 2SA1262
18230	2SB782	2SB781, 60V	BD 244A, BD 536, BD 950, 2SA1262
18231	2SB783	2SB781, 80V	BD 244B, BD 538, BD 952, 2SB920L
18232	2SB786	40V, 2A, 5W, 150MHz, B10000	2SB794...795, 2SB1008
18233	2SB786	2SB786	2SB1310
18234	2SB787	120V, 0,05A, 0,625W	2SA872A, 2SA970, 2SA1285(A), 2SB716(A)
18235	2SB788	120V, 0,02A, 0,4W, 150MHz	2SA872A, 2SA970, 2SA1038, 2SA1136
18236	2SB789	100V, 0,5A, 120MHz	BCX 53, 2SA1201, 2SA1368, 2SB804...806
18237	2SB789A	2SB789, 120V	2SA1201, 2SB806, 2SB1025
18238	2SB79	25V, 0,15A, 0,25W	AC 125...126, AC 151, 2SB54, 2SB56
18239	2SB790	25V, 0,5A, 0,6W, 150MHz	2SB892, 2SB926...927, BC 327...328
18240	2SB791(K)	120V, 8A, 40W, B>1000	BD 652, BDT 20, BDW 74D, BDX 54D
18241	2SB792	150V, 0,05A, 200MHz	-
18242	2SB792A	2SB792, 185V	-
18243	2SB793	30V, 1A, 1W, 200MHz	BC 327...328, BC 636, BC 638, 2SB909
18244	2SB793A	2SB793, 60V	BC 327A, BC 636, BC 638, 2SB1116
18245	2SB794	60V, +-1,5A, 10W, B2k...30k	BD 678, BD 778, 2N6035...6036
18246	2SB795	2SB794, 80V	BD 680, BD 780, 2N6036
18247	2SB796	200V, 10A, 200W, 14MHz	MJ 15016, 2SA909, 2SA1116...17, 2SB723
18248	2SB798	30V, 1A, 110MHz	BC 869, BCX 51, BCX 69, 2SA1203
18249	2SB799	60V, 0,7A, 120MHz	BCX 53, 2SA1201, 2SB804...806, 2SB1025
18250	2SB80(H)	25V, 1A, 4W	AD 162, 2SB474
18251	2SB800	80V, 0,3A, 100MHz	2SA1202, 2SA1368, 2SB767, 2SB789(A)
18252	2SB801	45V, 1A, 80MHz	BCX 51...53, 2SA1364, 2SB766A, 2SB1025
18253	2SB802	2SB801, 60V	BCX 52...53, 2SA1364, 2SB766A, 2SB1025
18254	2SB803	2SB801, 100V	BCX 53, 2SB804, 2SB1025
18255	2SB804	100V, 1A, 80MHz	BCX 53, 2SB803, 2SB1025
18256	2SB805	100V, 0,7A, 75MHz	BCX 53, 2SA1201, 2SB803...804, 2SB1025
18257	2SB806	2SB805, 120V	2SA1201, 2SB806, 2SB1025
18258	2SB807	150V, 0,1A, 200MHz	-
18259	2SB808	20V, 0,7A, 0,25W, 250MHz	2SA1705, 2SB1116, BC 327...328, BC 636
18260	2SB81(H)	80V, 0,5A, 2W	-
18261	2SB810	30V, 0,7A, 0,35W, 160MHz	2SA1703, 2SB892, 2SB926...927, 2SB1433
18262	2SB811	30V, 1A, 0,35W, 110MHz	BC 327...328, BC 636, 2SB909, 2SB1116
18263	2SB812	60V, 4A, 60W	BD 246A, BDV 92, 2SA1141, 2SB775...776
18264	2SB812A	2SB812, 80V	BD 246B, BDV 94, 2SA1141, 2SB775...776
18265	2SB813	60V, 4A, 40W, 20MHz	BD 244A, BD 536, BD 950, 2SA1262
18266	2SB813K	2SB813, 100V	BD 244C, BD 954, 2SB633, 2SB682
18267	2SB814	120V, 0,02A	2SA1312, 2SB792
18268	2SB815	2SB808, SMD	2SA1298
18269	2SB816	150V, 8A, 80W, 15MHz	BD 246D, 2SA1186, 2SA1227A, 2SB713

18270	2SB817	160V, 12A, 100W, 15MHz	BD 746F, 2SA1294, 2SA1386(A)
18271	2SB818(K)	100V, 10A, 80W, B>1000	2SB853
18272	2SB819	50V, 1,5A, 1W, 150MHz	MPS 750...751, 2SA1315, 2SA1382, 2SB892
18273	2SB82(H)	2SB81, 100V	-
18274	2SB820	350V, 1A, 15W	2SA1412, 2SA1009(A), 2SA1236, 2SA1397
18275	2SB821	2SB737	2SB737
18276	2SB822	40V, 2A, 0,75W, 100MHz	MPS 750, 2SA1315, 2SA1382, 2SB911
18277	2SB823	100V, 6A, 40W	BD 244C, BD 544C, BD 802, 2SB633
18278	2SB824	60V, 5A, 30W, 30MHz	2SA1012, 2SA1289, 2SB920L
18279	2SB825	60V, 7A, 40W, 10MHz	2SA1290, 2SB919, 2SB921L
18280	2SB826	60V, 12A, 40W, 10MHz	2SA1328, 2SB903
18281	2SB827	60V, 7A, 60W, 10MHz	2SA1292, 2SB922L
18282	2SB828	60V, 12A, 80W, 10MHz	2SA1292, 2SB922L
18283	2SB829	60V, 15A, 90W, 20MHz	2SB1230
18284	2SB83(H)	40V, 3A, 44W	AD 149, 2N2138, 2N2143, 2SB449
18285	2SB830	20V, 2A, 0,9W	2SA1382, 2SB738...739, 2SB892, 2SB1312
18286	2SB831	25V, 0,7A, 65MHz	BCW 67...68, 2SA1298, 2SA1621
18287	2SB832	1000V, 10mA, 25W, 4,5MHz	-
18288	2SB833	80V, 30A, 150W, B4000	BDX 68A...C, MJ 11013, MJ 11015, 2SB694
18289	2SB834	60V, 3A, 30W, 9MHz	BD 242A, BD 536, BD 936, 2SA1288
18290	2SB835	20V, 1A, 0,1W, 200MHz	BC 327...328, BC 636, BC 638, 2SB909
18291	2SB836	25V, 2,5A, 20W	2SA1243, 2SB906, 2SB962, 2SB1184
18292	2SB836L	2SB836	BD 330, 2SB744(A)
18293	2SB837	2SB836, 35V	2SA1243, 2SB906, 2SB962, 2SB1184
18294	2SB837L	2SB837	BD 330, 2SB744(A)
18295	2SB838	50V, 2A, 20W, 130MHz	2SA1241, 2SB839, 2SB957...958, 2SB1201
18296	2SB838L	2SB838	BD 376, 2SB744(A), 2SB874...875
18297	2SB839	2SB838, 80V	2SA1593, 2SB957...958, 2SB1215...16
18298	2SB839L	2SB839	BD 378, 2SB874...875
18299	2SB84(N)	2SB83, 60V	AD 166...167, 2N2139, 2N2144
18300	2SB840	180/120V, 1,5A, 20W, 140MHz	2SA1552, 2SB768
18301	2SB840L	2SB840	2SA1249, 2SB649
18302	2SB841	2SB840, 180/160V	2SA1552, 2SB768
18303	2SB841L	2SB841	2SA1249, 2SB649
18304	2SB842	2SB840, 200V	2SB768, 2SB928(A), 2SA968B, 2SA1133
18305	2SB842L	2SB841	-
18306	2SB843	50V, 5A, 10W	2SB1151
18307	2SB844	120V, 1A, 10W, B160	2SA1592, 2SA1225, 2SB959...960, 2SB905
18308	2SB845	2SB944, B100	2SA1592, 2SA1225, 2SB959...960, 2SB905
18309	2SB846	25V, 1A, 10W	2SA1241, 2SB838, 2SB1182, 2SA748
18310	2SB848	100V, 6A, 70W	BD 246C, BDV 96, 2SA1141, 2SA1186
18311	2SB849	120V, 7A, 80W, 14MHz	BD 246C, 2SA1141, 2SA1146, 2SA1186
18312	2SB849A	2SB849, 130V	BD 246D, 2SA1186, 2SB816, 2SB695
18313	2SB85	40V, 10A, 50W	AL 100...101, 2N2288, 2N2291
18314	2SB850	40V, 10A, 50W	BD 706, BD 806, BD 906

18315	2SB850A	2SB850, 80V	BD 710, BD 810, BD 910
18316	2SB851	80V, 0,7A, 0,75W, 100MHz	BC 640, 2SA965, 2SB647, 2SB910
18317	2SB852	40V, 0,3A, 200MHz, B>1000	-
18318	2SB852K	2SB852	BCV 26, BCV 46
18319	2SB853	100V, 15A, 100W, B>1000	-
18320	2SB854	2SB853, 20A, 125W	-
18321	2SB855	50V, 2A, 20W, 35MHz	BD 240A, BD 242A, 2SA748, 2SA1288
18322	2SB856	2SB855, 3A	BD 242A, 2SA748, 2SA1012, 2SA1288
18323	2SB857	70/50V, 4A, 40W, 15MHz	BD 244A, BD 536, BD 950, 2SB690
18324	2SB858	2SB857, 70/60V	BD 244A, BD 538, BD 952, 2SB690
18325	2SB859	100V, 4A, 40W, 20MHz	BD 244C, BD 540C, BD 954, 2SB682
18326	2SB86	2SB85, 60V	AL 100...101, 2N2289, 2N2292
18327	2SB860	100V, 4A, 40W	BD 244C, BD 540C, BD 954, 2SB682
18328	2SB861	200/150V, 2A, 30W	BD 240F, 2SA1133, 2SB630, 2SB720
18329	2SB862	120V, 5A, 30W, 68MHz, B5000	BD 652, BDT 20, BDW 64D, BDX 54D
18330	2SB863	140V, 10A, 100W, 15MHz	BD 246D, 2SA1186, 2SA1227A, 2SB817
18331	2SB864	55V, 0,1A, 0,3W	BC 212, BC 257, BC 307, BC 557
18332	2SB865	80V, 1,5A, 0,9W, B>4000	BC 878, BSR 61...62, 2SB1129, 2SB1406
18333	2SB867	130V, 3A, 30W, 30MHz	2SA1644
18334	2SB868	2SB867, 4A, 35W	2SA1644
18335	2SB869	2SB867, 5A, 40W	2SA1644
18336	2SB87	2SB85, 80V	AL 100...101, 2N2289, 2N2292
18337	2SB870	2SB867, 7A, 40W	-
18338	2SB871	40V, 10A, 40W, 100MHz	2SA1291, 2SA1328...29, 2SB903
18339	2SB871A	2SB870, 50V	2SA1291, 2SA1328...29, 2SB903
18340	2SB872	60V, 8A, 45W, B>1000	BD 646, BD 898, BDW 74A, BDX 54A
18341	2SB872A	2SB871, 80V	BD 648, BD 900, BDW 74B, BDX 54B
18342	2SB872A	2SB871, 80V	BD 648, BD 900, BDW 74B, BDX 54B
18343	2SB873	30V, 5A, 1W, 120MHz	2SB1288, 2SB1306
18344	2SB874	100V, 2A, 20W, 250MHz	BD 380, BD 792, MJE 253...254
18345	2SB875	100V, 2A, 20W, 250MHz	BD 380, BD 792, MJE 253...254
18346	2SB876	120/100V, 1,5A, 20W	2SA1021, 2SA1249, 2SB649
18347	2SB877	2SB876, 120/110V	2SA1021, 2SA1249, 2SB649
18348	2SB878	180V, 1,5A, 10W	BD 240E, 2SA1011, 2SB628A, 2SB861
18349	2SB879	180V, 1,5A, 10W	BD 240E, 2SA1011, 2SB628A, 2SB861
18350	2SB88	2SB85, 100V	AL 100...101, 2N2290, 2N2293
18351	2SB880	70V, 4A, 30W, B5000	BD 718, BDW 24B, BDW 54B, 2SB751A
18352	2SB881	2SB880, 7A, 35W	BD 648, BD 900, BDW 74B, BDX 54B
18353	2SB882	2SB880, 10A, 40W	BDT 62A, BDT 64A, BDW 94B, BDX 34B
18354	2SB883	2SB880, 15A, 70W	BDV 66(A...D), BDW 84(B...D)
18355	2SB884	110V, 3A, 30W, B4000	BDW 24C, BDW 54D, BDW 64D, 2SB751B
18356	2SB885	2SB884, 5A, 35W	BD 652, BD 902, BDW 24C, BDW 64D
18357	2SB886	2SB884, 8A, 40W	BD 652, BD 902, BDW 74D, BDX 54D
18358	2SB887	2SB884, 10A, 70W	BDV 64C, BDW 84D, 2SB913
18359	2SB888	80V, 0,7A, 0,6W, B25000	BC 878, BC 880, BSR 61...62, 2SB865

18360	2SB889(F)	80V, 0,7A, 5W, 100MHz	BD 140, BD 231, 2SA1220A, 2SB1007
18361	2SB89(H)	25V, 0,15A, 0,25W	AC 128, AC 151...153, AC 188, 2SB475
18362	2SB890	50V, 0,5A, 0,4W	BC 327(A), BC 638, BC 640, 2SB910
18363	2SB891(F)	40V, 2A, 5W, 100MHz	2SA1359, 2SB1142...1143
18364	2SB892	60V, 2A, 1W, 150MHz	2SA1315, 2SA1706, 2SB1459
18365	2SB893	20V, 2,5A, 0,75W, 250MHz	2SB985, 2SB1117, 2SB1300, 2SB1505
18366	2SB894	30V, 0,1A, 0,45W, 150MHz	2SB774, 2SB1206, BC 308, BC 558
18367	2SB895	30V, 1A, B8000	BD 466A...B, BD 876, BDX 45, 2SB1008
18368	2SB895A	2SB895, 60V	BD 876, BDX 45...47, 2SB794...795
18369	2SB896	40V, 10A, 35W, 150MHz	2SA1077, 2SA1291
18370	2SB896A	2SB896, 50V	2SA1077, 2SA1291
18371	2SB897	100V, +-10A, 80W, B>1000	BDV 64B, BDV 66A, BDW 84C, TIP 147
18372	2SB898	50V, 3A, 25W	BD 242, BD 536, BD 936, 2SA1288
18373	2SB899	50V, 3A, 25W	BD 242, BD 536, BD 936, 2SA1288
18374	2SB89A(AH	2SB89, 45V	ACY 24, ASY 48, 2SB55
18375	2SB90	18V, 5mA, 0,04W	AC 125...126, AC 151, 2SB54, 2SB56
18376	2SB900	50V, 4A, 40W	BD 536, BD 540A, BD 950, 2SA1289
18377	2SB901	2SB900, 60V	BD 536, BD 540A, BD 950, 2SA1289
18378	2SB902	30V, 0,1A, 150MHz	2SA1252, BC 856...858, BCW 69...70
18379	2SB903	60V, 12A, 35W, 120MHz	2SA1328...29, 2SB826
18380	2SB904	60V, 20A, 60W, 120MHz	2SB1231
18381	2SB905	150V, 1,5A, 10W, 50MHz	2SA1225, 2SB768, 2SB840...842
18382	2SB906	60V, 3A, 20W, 9MHz	2SA1184, 2SA1244, 2SB1202...03
18383	2SB907	60V, 3A, 15W, B5000	2SB1072, 2SB1214, 2SB1303
18384	2SB908	100V, 4A, 15W, B5000	2SB1072, BD 902, BDW 24C, BDW 54C
18385	2SB909(M)	40V, 1A, 1W, 150MHz	BC 636, BC 638, BC 640, 2SB1116(A)
18386	2SB91	18V, 30mA, 0,04W	AC 125...126, AC 151, 2SB54, 2SB56
18387	2SB910(M)	80V, 0,7A, 1W, 100MHz	BC 640, 2SA965, 2SB647, 2SB1116(A)
18388	2SB911(M)	40V, 2A, 1W, 100MHz	MPS 750...751, 2SA1315, 2SA1382, 2SB892
18389	2SB912	70V, 10A, 60W, B5000	BDV 64A, BDV 66A, BDW 84B, TIP 146
18390	2SB913	110V, 8A, 60W, B4000	BDV 64C, BDV 66B, BDW 84D, 2SB897
18391	2SB914	70V, 10A, 70W, B5000	BDV 64A, BDW 84B, BDX 86B, MJ 2501
18392	2SB915	70V, 15A, 80W, B5000	BDV 66A, BDW 84B, BDX 66A, MJ 4031
18393	2SB916	110V, 8A, 70W, B4000	BDV 64C, BDW 84D, BDX 62C, BDX 64C
18394	2SB917	110V, 10A, 80W, B4000	BDV 64C, BDW 84D, BDX 64C, BDX 66C
18395	2SB918	250V, 0,5A, 0,5W	BF 492...493, BF 423A, BFP 26, MPSA 92
18396	2SB919	60V, 8A, 30W, 120MHz	2SA1290...91, 2SB903
18397	2SB92	32V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
18398	2SB920	2SB920L, 120V	2SB869
18399	2SB920L	90V, 5A, 30W, 20MHz	2SA1293
18400	2SB921	2SB921L, 120V	2SB870
18401	2SB921L	90V, 7A, 40W, 20MHz	2SB870
18402	2SB922	2SB922L, 120V	2SB1230
18403	2SB922L	90V, 12A, 80W, 20MHz	2SB1230
18404	2SB923	120V, 20A, 100W	BD 250C, BD 746D

18405	2SB924	120V, 25A, 120W	BD 250C
18406	2SB925	100/600ns	2SA1290...1291, 2SB919
18407	2SB925A	2SB925, 50V	2SA1290...1291, 2SB919
18408	2SB926	30V, 2A, 0,75W	2SB892, 2SB1229, 2SB1433...34
18409	2SB927	2SB926, 2,5A, 1W	2SA1382, 2SB892, 2SB985, 2SB1312
18410	2SB928(A)	200V, 2A, 30W, 30MHz	2SA1133, 2SB720, 2SB861
18411	2SB929	60V, 3A, 35W, 30MHz	2SB1266, 2SB1268, 2SB1270, 2SB1449
18412	2SB929A	2SB929, 80V	2SB1270, 2SB1451
18413	2SB93	30V, 10mA, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
18414	2SB930	60V, 4A, 40W, 20MHz	2SB1268, 2SB1270, 2SB1449, 2SB1451
18415	2SB930A	2SB930, 80V	2SB1270, 2SB1451
18416	2SB931	130V, 3A, 30W, 30MHz	-
18417	2SB932	130V, 4A, 35W, 30MHz	-
18418	2SB933	130V, 5A, 40W, 30MHz	-
18419	2SB934	130V, 7A, 40W, 30MHz	-
18420	2SB935	40V, 10A, 35W, 150MHz	-
18421	2SB935A	2SB935, 50V	-
18422	2SB936	40V, 10A, 40W, 100MHz	-
18423	2SB936A	2SB936, 50V	-
18424	2SB937	60V, 2A, 35W, 20MHz, B>1000	BD 716, BDW 24A, BDW 54A, 2SB751
18425	2SB937A	2SB937, 80V	BD 718, BDW 24B, BDW 54B, 2SB751A
18426	2SB938	60V, 4A, 40W, 15MHz, B>1000	BD 716, BDW 24A, BDW 54A, 2SB751
18427	2SB938A	2SB938, 80V	BD 718, BDW 24B, BDW 54B, 2SB751A
18428	2SB939	60V, 8A, 45W, 15MHz, B>1000	BD 646, BD 898, BDW 74A, BDX 54A
18429	2SB939A	2SB939, 80V	BD 650, BD 900, BDW 74B, BDX 54B
18430	2SB94	25V, 0,15A, 0,15W, B>45	AC 125...126, AC 151, 2SB54, 2SB56
18431	2SB940(A)	2SB928(A), 30W	2SA1306B, 2SA1668, 2SB1096, 2SB1530
18432	2SB941(A)	2SB929(A)	BDT 32F, 2SA1635, 2SB1017, 2SB1335
18433	2SB942	2SB930(A)	BD 952F, 2SA1635, 2SB1017, 2SB1335
18434	2SB943	2SB931	2SA1650
18435	2SB944	2SB932	2SA1650
18436	2SB945	2SB933	2SA1650
18437	2SB946	2SB934	2SA1651
18438	2SB947	2SB935	2SA1327, 2SA1567
18439	2SB947A	2SB935A	2SA1327, 2SA1567
18440	2SB948	2SB936	2SA1327, 2SA1567
18441	2SB948A	2SB936A	2SA1327, 2SA1567
18442	2SB949	2SB937	BDT 60F, 2SB1223, 2SB1342
18443	2SB949A	2SB937A	BDT 60AF, 2SB1024, 2SB1342
18444	2SB95	2SB94, B60	AC 125...126, AC 151, 2SB54, 2SB56
18445	2SB950	2SB938	BDT 60F, 2SB1223, 2SB1342
18446	2SB950A	2SB938A	BDT 60AF, 2SB1024, 2SB1342
18447	2SB951	2SB939	BD 646F, BDT 62F, 2SB1021, 2SB1224...25
18448	2SB951A	2SB939A	BD 948F, BDT 62AF, 2SB1020...21, 2SB1100
18449	2SB952	100/600ns	2SB935...36, 2SB1267, 2SB919



18450	2SB952A	2SB952, 50V	2SB935A...36A, 2SB1267, 2SA1290...1291
18451	2SB953	2SB952	2SA1470...71, 2SA1643
18452	2SB953A	2SB953, 50V	2SA1470...71, 2SA1643
18453	2SB954	60V, 1A, 30W, 500/1500ns	BD 936F, 2SB1015, 2SB1094, 2SB1375
18454	2SB954A	2SB954, 80V	BD 938F, BDT 32AF, 2SA1095, 2SA1395
18455	2SB955	120V, 10A, 50W, B4000	BDT 62C, BDT 64C, BDX 34D
18456	2SB956	20V, 1A, 200MHz	BC 869, BCX 51...53, BCX 69, 2SA1364
18457	2SB957	100V, 2A, 20W, 250MHz	2SA1593, 2SB768, 2SB928(A)
18458	2SB958	100V, 2A, 20W, 250MHz	2SA1593, 2SB768, 2SB928(A)
18459	2SB959	120V, 1,5A, 20W	2SA1593, 2SB768, 2SB928(A)
18460	2SB96	32V, 0,125A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
18461	2SB960	120V, 1,5A, 20W	2SA1593, 2SB768, 2SB928(A)
18462	2SB962(Z)	40V, 3A, 10W, 80MHz	2SB1202...03, 2SB906, 2SB1184
18463	2SB963(Z)	60V, +-1A, 8W, B2k..30k	2SB907, 964, 2SB1214, 2SB1316
18464	2SB964	60V, 1,5A, 10W, B8000	2SB907, 2SB1214, 2SB1316
18465	2SB965	120V, 7A, 70W, 75MHz	BD 246C, 2SA1141, 2SA1186, 2SB688
18466	2SB966	120V, 8A, 80W, 65MHz	BD 246C, 2SA1141, 2SA1186, 2SB688
18467	2SB967	27V, 5A, 20W, 120MHz	2SA1242, 2SA1244, 2SA1385, 2SB1203
18468	2SB968	50V, 1,5A, 20W, 150MHz	2SB838, 2SB957...960, 2SB1201, 2SB1241
18469	2SB969	100V, 15A, 100W, B5000	BDV 66A, BDW 84C, 2SB1079
18470	2SB97	18V, 5mA, 0,04W	AC 125...126, AC 151r, ACY 32, 2SB173
18471	2SB970	15V, 0,5A, 130MHz	BC 807...808, BCX 17...18, 2SA1326
18472	2SB971	20V, 1A, 1W	2SA966, 2SB738...739, 2SB978, 2SB927
18473	2SB972	7V, 0,5A	BC 807...808, BCX 17...18, 2SA1326
18474	2SB973	10V, 0,7A, 280MHz	BCW 67...68, 2SA1298, 2SA1621
18475	2SB974	100V, 5A, 30W, B6000	BD 650, BD 902, BDW 24C, BDW 64C
18476	2SB974	100V, 5A, 30W, B6000	BD 650, BD 902, BDW 24C, BDW 64C
18477	2SB975	100V, 8A, 40W, B6000	BD 650, BD 902, BDW 74C, BDX 54C
18478	2SB975	100V, 8A, 40W, B6000	BD 650, BD 902, BDW 74C, BDX 54C
18479	2SB976	27V, 5A, 0,75W, 120MHz	2SA1431, 2SB1050, 2SB1288, 2SB1305...07
18480	2SB977	30V, 1A, 0,75W, B>2000	BC 876, BC 878, BSR 60...62, 2SB865
18481	2SB977A	2SB977, 60V	BC 876, BC 878, BSR 60...62, 2SB865
18482	2SB978	40V, 1,5A, 0,9W	2SA1315, 2SA1382, 2SB892, 2SB1312
18483	2SB979	100V, 5A, 60W, 20MHz	BD 246C, 2SB688, 2SB775...776, 2SB695
18484	2SB98	30V, 0,05A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
18485	2SB980	120V, 6A, 70W	BD 246C, 2SB688, 2SB776, 2SB695
18486	2SB981	140V, 7A, 80W	BD 246D, 2SA1186, 2SB816...817, 2SB695
18487	2SB982	150V, 9A, 100W	BD 246D, 2SA1227(A), 2SA1386(A), 2SB817
18488	2SB983	200/800ns	BD 244A, BD 544A, BD 798, 2SA1290
18489	2SB984	120V, 1A, 1W, 100MHz	2SA1013, 2SB647, 2SB1130, 2SB1236
18490	2SB985	60V, 3A, 1W, 150MHz	2SA1066, 2SA1707
18491	2SB986	2SB985, 4A, 10W	-
18492	2SB987	120V, 0,5A, 1W, 250MHz	2SA965, 2SA840, 2SB647, 2SB1297
18493	2SB988	60V, 3A, 30W, <400/2200ns	BD 242A, BD 536, BD 936, 2SA1262
18494	2SB989	80V, 4A, 30W, >3MHz	BD 244A, BD 536, BD 936, 2SB920L



18495	2SB99	30V, 0,05A, 0,125W	AC 125...126, AC 151, 2SB54, 2SB56
18496	2SB991	180V, 1,5A, 20W, 8MHz	BD 240E, 2SB608, 2SB628A, 2SB630, 2SB861
18497	2SB992	100V, 7A, 40W, 10MHz	-
18498	2SB992	100V, 7A, 40W, 10MHz	-
18499	2SB993	70V, 7A, 40W, 10MHz	2SA1290, 2SB921L
18500	2SB993	70V, 7A, 40W, 10MHz	2SA1290, 2SB921L
18501	2SB994	60V, 3A, 30W, 3MHz	BD 242A, BD 536, BD 936, 2SA1262
18502	2SB994	60V, 3A, 30W, 3MHz	BD 242A, BD 536, BD 936, 2SA1262
18503	2SB995	100V, 5A, 40W, 5MHz	BD 244C, BD 544C, BD 954, 2SB633
18504	2SB995	100V, 5A, 40W, 5MHz	BD 244C, BD 544C, BD 954, 2SB633
18505	2SB996	80V, 3A, 30W, 9MHz	BD 242B, BD 538, BD 540B, 2SB682
18506	2SB996	80V, 3A, 30W, 9MHz	BD 242B, BD 538, BD 540B, 2SB682
18507	2SB997	100V, 7A, 40W, B6000	BD 650, BD 902, BDW 74C, BDX 54C
18508	2SB997	100V, 7A, 40W, B6000	BD 650, BD 902, BDW 74C, BDX 54C
18509	2SB998	80V, 7A, 40W, B6000	BD 648, BD 900, BDW 74B, BDX 54B
18510	2SB998	80V, 7A, 40W, B6000	BD 648, BD 900, BDW 74B, BDX 54B
18511	2SB999	60V, 7A, 40W, B6000	BD 646, BD 898, BDW 74A, BDX 54A
18512	2SB999	60V, 7A, 40W, B6000	BD 646, BD 898, BDW 74A, BDX 54A
18513	2SC100	40V, 0,2A, 0,15W, <40/70ns	BSS 11, BSX 19...20, 2N2368...69(A)
18514	2SC1000(G)	55V, 0,1A, 0,2W, 80MHz	BC 414, BC 550, 2SC2240, 2SC2459
18515	2SC1000(G)	55V, 0,1A, 0,2W, 80MHz	BC 414, BC 550, 2SC2240, 2SC2459
18516	2SC1000GTM	2SC1000, 60V, 0,4W	2SC2240, 2SC2459, 2SC2675, 2SC3378
18517	2SC1000GTM	2SC1000, 60V, 0,4W	2SC2240, 2SC2459, 2SC2675, 2SC3378
18518	2SC1001	40V, 0,5A, PQ>1,2W(470MHz)	BFS 50, MRF 629, 2N3948, 2SC2852
18519	2SC1002	36V, 1A, PQ3W(470MHz)	-
18520	2SC1003	36V, 2A, PQ6W(470MHz)	-
18521	2SC1004	1100/700V, 0,5A, 50W	BU 204...206, 2SC1167, 2SD1095
18522	2SC1004A	2SC1004, 1500/800V	BU 205...206, 2SD575, 2SD818
18523	2SC1005	1100/600V, 5A, 50W, 3MHz	BU 207...209, 2SC1413, 2SD380(A)
18524	2SC1005A	2SC1005, 1400/600V	BU 208...209, 2SD380(A), 2SD792, 2SD954
18525	2SC1006	50V, 0,03A, 0,3W, 90MHz	BC 184, BC 414, BC 550, 2SC2240
18526	2SC1006	50V, 0,03A, 0,3W, 90MHz	BC 184, BC 414, BC 550, 2SC2240
18527	2SC1007	95/240ns	BC 174, BC 182, BC 190, BC 546, 2N3904
18528	2SC1008	120/300ns	BC 140...141, BC 300...301, 2N1889...90
18529	2SC1008A	2SC1008, 100V	BC 141, BC 300, 2N1889...90, 2N2102
18530	2SC1009(A)	50V, 0,05A, 250MHz	BC 846...847, BCW 71...72, BCW 81
18531	2SC101	60V, 2A, 60W, 16MHz	BD 239A, BD 241A, BD 935, 2SC1398
18532	2SC1010	50V, 0,03A, 0,3W, 90MHz	BC 184, BC 414, BC 550, 2SC2240
18533	2SC1011	40V, 0,75A, PQ3W(150MHz)	BLW 17, 2SC1405
18534	2SC1012(Z)	165V, 0,06A, 0,75W, >80MHz	BF 257...259, BF 657...659, 2N5058...59
18535	2SC1012A(AZ)	2SC1012, 250V	BF 258...259, BF 658...659, 2N5058...59
18536	2SC1013	35V, 1,5A, 7W, 70MHz	BD 507, BD 517, BD 525, BD 839
18537	2SC1014	2SC1013, 50V	BD 509, BD 519, BD 527, BD 841
18538	2SC1015	40V, 3A, PQ14W(450MHz)	BLW 15, BLX 69
18539	2SC1016	35V, 0,5A, PQ1,3W(500MHz)	BLW 12, BLX 66

18540	2SC1017	75V, 1A, PQ0,06W(27MHz)	-
18541	2SC1018	75V, 1A, PQ1,4W(27MHz)	-
18542	2SC1019	60V, 4A, PQ28W(500MHz)	2N6104
18543	2SC101A	2SC100, 70V, 5A, 35W, 20MHz	BD 243A, BD 539B, BD 951, 2SC3253
18544	2SC102	50V, 7A, 100W, 20MHz	BD 245, BDV 91, 2SC3256, 2SD895...896
18545	2SC1020	60V, 8A, PQ45W(500MHz)	-
18546	2SC1021	60V, 6A, PQ45W(90MHz)	BLX 15
18547	2SC1022	60V, 6A, PQ45W(150MHz)	-
18548	2SC1023	25V, 25mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
18549	2SC1023	25V, 25mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
18550	2SC1024	60V, 3A, 25W, 8MHz	BD 241A, BD 935, 2N4232, 2SC3252
18551	2SC1025	200V, 3A, 25W, 8MHz	BU 406...408, 2SC1025, 2SD1136, 2SD1159
18552	2SC1026	25V, 25mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
18553	2SC1026	25V, 25mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
18554	2SC1027	250/80V, 6A, 50W	BU 606...608, BUX 18(A...C), 2SC2769
18555	2SC103(A)	>200MHz	BC 168, BC 183, BC 238, BC 548, 2N2221
18556	2SC1030	150/80V, 6A, 50W, 10MHz	BD 245D, 2N3442, 2SD551, 2SD1046
18557	2SC1031	<5/15µs	BUX 67A...C, 2N3584, 2SC1504, 2SC2023
18558	2SC1032	25V, 25mA, 0,15W, 200MHz	BF 240...241, BF 254...255, BF 594...595
18559	2SC1032	25V, 25mA, 0,15W, 200MHz	BF 240...241, BF 254...255, BF 594...595
18560	2SC1033	150MHz	BF 298, 299, BF 420, BF 422, BF 483
18561	2SC1033A	2SC1033, 250/200V	BF 298...299, BF 420, BF 422, BF 483
18562	2SC1034	1100V, 1A, 25W, 5MHz	BU 505, 2SD470, 2SD948, 2SD1492
18563	2SC1035	30V, 0,02A, 700MHz	BF 377...378, BF 689, BF 763, 2N2857
18564	2SC1036	30V, 0,02A, 700MHz	BF 377...378, BF 689, BF 763, 2N2857
18565	2SC1037	60V, 4A, PQ33W(160MHz)	-
18566	2SC1038	40V, 0,15A, PQ0,8W(2,3GHz)	BFQ 34, BFR 94, BFT 98, 2SC1041
18567	2SC1039	40V, 0,25A, PQ1,4W(2,3GHz)	BFQ 68, BFT 98, 2SC1042
18568	2SC104(A)	250MHz	BC 168, BC 183, BC 238, BC 548, 2N2221
18569	2SC1040	40V, 1,2A, PQ>8W(500MHz)	BLW 91, MRF 321, MRF 331
18570	2SC1041	40V, 0,15A, PQ0,9W(2GHz)	BFQ 34, BFR 94, BFT 98, 2SC1038
18571	2SC1042	40V, 0,25A, PQ1,6W(2GHz)	BFQ 68, BFT 98, 2SC1039
18572	2SC1043	45V, 0,3A, 2,2GHz	BFQ 68
18573	2SC1044	1000MHz	BF 377...378, BF 689, BF 763, 2N2857
18574	2SC1045	1000/550V, 1A, 25W	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18575	2SC1046	1000/400V, 3A, 25W	BU 207...209, 2SC1875, 2SD819, 2SD1098
18576	2SC1046N	2SC1046, 1200/400V	BU 207...209, 2SC1875, 2SD819, 2SD1098
18577	2SC1047	30V, 20mA, 650MHz	BF 225, BF 310, BF 314, BF 502, 2SC829
18578	2SC1047	30V, 20mA, 650MHz	BF 225, BF 310, BF 314, BF 502, 2SC829
18579	2SC1048	200V, 0,05A, 0,6W, 120MHz	BF 258...259, BF 658...659, 2N5058...59
18580	2SC105	30V, 0,08A, 0,25W, 250MHz	BC 168, BC 183, BC 238, BC 548, 2N2221
18581	2SC1050	300/300V, 1A, 40W, 5MHz	BU 104, BU 606...608, 2SD916, 2SD1154
18582	2SC1051	150/100V, 7A, 60W, 8MHz	BD 245D, 2N3442, 2SD551, 2SD1046
18583	2SC1051L	2SC1051, 100/80V	BD 245C, BDV 95, 2SC3181, 2SD1187
18584	2SC1052	75V, 1A, 0,8W, <50/70ns	BSS 14, BSV 95, 2N3735, 2N5262

18585	2SC1053	75V, 0,7A, 0,8W, <40/60ns	BSS 14, BSV 95, 2N3735, 2N5262
18586	2SC1054	35V, 0,05A, 700MHz	BF 377...378, BF 689, BF 763, 2N2857
18587	2SC1055(H)	25(H14)MHz	BU 406...408, MJE 15030, 2SD866
18588	2SC1056	180MHz	BF 258...259, BF 658...659, 2N5058...59
18589	2SC1057	50V, 1A, PQ6,5W(700MHz)	-
18590	2SC1058	50V, 2A, PQ11,5W(700MHz)	-
18591	2SC1059	300/300V, 0,15A, 8W(Tc70°)	2SC1505...1507, 2SC1755...1757, 2SC1905
18592	2SC106	60V, 2A, 15W, 100MHz, -/230ns	BD 137, BD 228, BD 377, 2SD794A
18593	2SC1060	50V, 3A, 25W, 8MHz	BD 241, BD 535, BD 935, 2SC3252
18594	2SC1061(K)	50V, 3A, 25W, 8MHz	BD 241, BD 535, BD 935, 2SC3252
18595	2SC1062	200/200V, 0,1A, 0,7W, 35MHz	BF 258...259, BF 658...659, 2N5058...59
18596	2SC1063	10V, 1A, 0,75W, <60/100ns	BSS 28...29, BSX 12, 2N3426, 2N3724A
18597	2SC1064	60V, 1A, 0,8W	BSS 13, BSS 27, BSV 77, 2N3735
18598	2SC1065	90V, 1A, 0,8W, 400MHz	BSV 95, 2N3735
18599	2SC1066	20V, 25mA, 800MHz	BF 377...278, BF 689, BF 763, 2N2857
18600	2SC1067	35V, 0,05A, 500MHz	BF 225, BF 310, BF 314, BF 502, 2SC1856
18601	2SC1068	25V, 0,15A, 0,5W, 2000MHz	BFR 36, BFW 16, 2SC2852
18602	2SC1069	100V, 1A, 0,8W, <60/120ns	-
18603	2SC107	2SC106, 1,5A	BD 137, BD 228, BD 377, 2SD794A
18604	2SC1070	30V, 0,02A, 900MHz	2SC2144, 2SC2353, 2SC2464, 2SC2466
18605	2SC1071	30V, 0,2A, 0,3W, <45/42ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
18606	2SC1072(A)	60V, 0,7A, 0,8W, <40/60ns	BSS 13, BSS 27, BSV 77, 2N5189
18607	2SC1073(Z)	36V, 0,5A, PQ1,8W(500MHz)	BLW 42, BLW 79, BLX 67, BLY 38, 2N5945
18608	2SC1074(Z)	36V, 1A, PQ4W(500MHz)	BLW 43, BLW 80
18609	2SC1075(Z)	36V, 2A, PQ8W(500MHz)	BLW 14, BLW 44, 2N5946
18610	2SC1076(Z)	36V, 3A, PQ15W(500MHz)	BLW 15, BLX 69
18611	2SC1077(A)	65V, 5..6A, PQ42W(175MHz)	BLW 25, BLY 94, 2N5643
18612	2SC1078	700/500V, 0,5A, 20W, 2MHz	MJ 4361, 2SC1810, 2SC1828, 2SC3352
18613	2SC1079	150/150V, 12A, 100W, 4MHz	BDW 12, 2SC1584, 2SD551, 2SD733
18614	2SC108	90V, 0,6A, 0,6W, >100MHz	BC 300...301, BC 141, BSW 39, 2N1990
18615	2SC1080	2SC1079, 110/100V	BD 545D, BDW 10, 2SD551, 2SD1105
18616	2SC1081	40V, 2,5A, PQ14W(500MHz)	BLW 15, BLX 69
18617	2SC1082	50V, 0,5A, PQ3W(700MHz)	2N4430
18618	2SC1083(F)	40V, 0,5A, 1600MHz	BFS 50, MRF 629, 2N3948
18619	2SC1084	35V, 0,05A, 0,25W, 300MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
18620	2SC1085	30V, 0,1A, 0,2W, 230MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
18621	2SC1086	1000V, 4A, 125W, 5MHz	BU 207...209, 2SC1348-1...-3, 2SC1413
18622	2SC1087	45V, 3A, PQ16W(700MHz)	-
18623	2SC1088	12,5W,>30MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
18624	2SC1089	2SC1088, 300/300V	2SC1505...1507, 2SC1755...1757, 2SC1819
18625	2SC108A	2SC108, 0,8A, 0,8W	BC 300...301, BC 141, BSW 39, 2N1990
18626	2SC109	50V, 0,6A, 0,6W, >70MHz	BC 140...141, BC 300...302, BSW 39
18627	2SC1090	20V, 0,05A, 0,3W, 3GHz	BFQ 72
18628	2SC1092	150/120V, 0,7A, 0,8W	BSS 43, BSW 68, 2SC1860
18629	2SC1095	30V, 2A, 10W, 60MHz	2SC1226, 2SC1848, BD 505, BD 507

18630	2SC1096(L,Z)	40V, 3A, 10W, 60MHz	2SC1226, BD 429, BD 613, BD 813
18631	2SC1097	60V, 1A, 10W, 60MHz	2SC1848, BD 385, BD 415, BD 827
18632	2SC1098(A)(L,Z)	70V, 3A, 10W, 60MHz	BD 619
18633	2SC1099	1200/400V, 3A, 50W	BU 207...209, 2SC1413, 2SD1098, 2SD1102
18634	2SC109A	2SC109, 70V	BC 140...141, BC 300...302, BSW 39
18635	2SC11	18V, 24mA, 0,055W, 60/140ns	ASY 28...29
18636	2SC110	40V, 0,2A, 0,75W, 160MHz	BC 140...141, BSV 69, 2N3723...3725
18637	2SC1100	2SC1099, 1100/400V	BU 207...209, 2SC1413, 2SD1098, 2SD1102
18638	2SC1101	1100/500V, 1A, 50W	BU 204...206, 2SC1132, 2SC1167, 2SD1095
18639	2SC1102	>60MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
18640	2SC1103(A)	250/250V, 0,1A, 0,8W, 80MHz	BF 258...259, BF 658...659, 2N5058...59
18641	2SC1104	300/300V, 0,7A, 20W	TIP 47...50, 2N3739, 2SC782, 2SC1929
18642	2SC1105	300V, 0,1A, 15W, 20MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
18643	2SC1106	350/250V, 2A, 80W	BU 126, 2SC1295
18644	2SC1107	80V, 4A, 25W, 10MHz	BD 243B, BD 537, BD 951, 2SC3179
18645	2SC1108	2SC1107, 100V	BD 243C, BD 539C, BD 953, 2SD613
18646	2SC1109	2SC1107	2SC1107
18647	2SC111	50V, 0,2A, 0,75W, 160MHz	BC 140...141, BSV 77, 2N3723...3725
18648	2SC1110	2SC1108	2SC1108
18649	2SC1111	140/80V, 6A, 50W, 10MHz	BD 245D, 2N3442, 2SD551, 2SD1046
18650	2SC1112	2SC1111, 160/100V	BD 245D, 2N3442, 2SD551, 2SD1046
18651	2SC1113	120/100V, 6A, 40W, 10MHz	BD 243C, BD 543D, MJE 15028, 2SD866
18652	2SC1114	300/325V, 4A, 100W, 10MHz	BU 606...608, BUW 71, BUX 16A...C
18653	2SC1115	140/80V, 10A, 100W, 10MHz	BD 245D, 2N3442, 2SD551, 2SD1047
18654	2SC1116	2SC1115, 180/120V	BD 245E, BDW 14, BDY 54, 2SC3263
18655	2SC1116A	2SC1115, 200/140V	MJ 15015, BD 245F, 2SC1585, 2SC2608
18656	2SC1117(H)	20V, 0,02A, 850MHz	BF 377...378, BF 689, BF 763, 2N2857
18657	2SC1118	45V, 2A, PQ14,5W(500MHz)	BLW 94, BLX 94, MRF 323
18658	2SC1119	20V, 0,03A, 0,25W, 4,5GHz	BFQ 71, BFQ 85, BFR 14, BFR 91
18659	2SC112	/127ns	BC 140...141, BSV 69, 2N3723...3725
18660	2SC1120	35V, 1,5A, PQ4W(470MHz)	BLW 13...14, BLW 43, BLX 68, BLY 53
18661	2SC1121	35V, 3A, PQ8,5W(470MHz)	BLW 15, BLW 81, BLX 69
18662	2SC1122(A)	35V, 4,5A, PQ14W(470MHz)	BLW 15, BLX 69
18663	2SC1123	35V, 0,1A, 550MHz	BF 225, BF 310, BF 314, BF 502, 2SC1393
18664	2SC1124	140/140V, 1A, 7,9W, 120MHz	2SC2384, 2SC1913, 2SC2481, 2SC2483
18665	2SC1126	550MHz	BF 225, BF 310, BF 314, BF 502, 2SC1393
18666	2SC1127-1,-2	180..210V, 0,1A, 7,9W	BF 460...462, MPSU 10, 2SC2224(A)
18667	2SC1128	35V, 0,1A, 550MHz	BF 370, BF 921S, BF 959
18668	2SC1129	35V, 0,03A, 400MHz	BF 370, BF 921S, BF 959
18669	2SC113	/127ns	BC 140...141, BSV 77, 2N3723...3725
18670	2SC1130	<1/2μs	BU 326(A), BU 426(A), BUS 11, BUX 46
18671	2SC1131	2SC1130, 600/300V	BU 326(A), BU 426(A), BUS 11, BUX 46
18672	2SC1132	1200/500V, 2,5A, 30W	BU 204...206, 2SC1875, 2SD1097...1098
18673	2SC1133	1200/500V, 5A, 80W, 4MHz	BU 207...209, 2SC1413, 2SD1103...1104
18674	2SC1136	200/150V, 30A, 200W, 9MHz	2SC2128, 2SC2940, 2SC3224, 2SD540...541

18675	2SC1138	800/400V, 30A, 200W, 9MHz	2SC2204, 2SC2977, 2SD295
18676	2SC1139	2SC1138, 600/300V	2SC2204, 2SC2442, 2SC2977, 2SD644
18677	2SC114	/135ns	BC 140...141, BSV 77, 2N3723...3725
18678	2SC1140	800/400V, 15A, 150W, 10MHz	BUS 13(A), BUW 45...46, BUX 48(A...C)
18679	2SC1141	2SC1140, 600/300V	BUS 13(A), BUW 45...46, BUX 48(A...C)
18680	2SC1142	800/400V, 10A, 125W, 4MHz	BUS 12(A), BUW 26, BUW 35...36, BUX 80
18681	2SC1143	2SC1142, 600/300V	BUS 12(A), BUW 25...26, BUW 35, BUX 80
18682	2SC1144	400/250V, 30A, 200W, 9MHz	2SC1302, 2SC1401, 2SD542...543
18683	2SC1145	700/400V, 20A, 175W, 9MHz	2SC2204, 2SC2977, 2SD295
18684	2SC115	30V, 0,05A, 0,75W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2N2218
18685	2SC1150	60V, 1A, 0,8W, <35/55ns	BSS 13, BSS 27, BSV 77, 2N5189
18686	2SC1151	900/450V, 1A, 50W, 5MHz	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18687	2SC1151A	2SC1150, 1000/580V	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18688	2SC1152	300/300V, 2,5A, 50W, 5MHz	BU 126
18689	2SC1153	1200/500V, 2,5A, 50W	BU 204...206, 2SC1132, 2SD1097...1098
18690	2SC1153A	2SC1153, 1400/500V	BU 205...206, 2SC1922, 2SD575, 2SD818
18691	2SC1154	2SC1153, 3,5A	BU 207...209, 2SC1875, 2SD517, 2SD819
18692	2SC1155	70V, 0,8A, 7W, 70MHz	BD 417, BD 519, BD 527, BD 529
18693	2SC1156	2SC1155, 90V	BD 419, BD 529, BD 829, BD 843
18694	2SC1157	2SC1155, 110V	BD 419, BD 529, BD 829, BD 843
18695	2SC1158	35V, 0,02A, >850MHz	BF 362...363
18696	2SC1159	2SC1158, >600MHz	BF 362...363
18697	2SC116(H)	50V, 0,2A, 0,75W, 120MHz	BC 140...141, BC 300...302, 2N3053
18698	2SC1160	200/100V, 1A, 15W, 20MHz	BD 239F, 2SC783, 2SC2238B, 2SD1138
18699	2SC1161(A)	2SC1160, 200/120(A200/140)V	BD 239F, 2SC783, 2SC2238B, 2SD1138
18700	2SC1162(WT)	35V, 2,5A, 10W, 180MHz	BD 375, 2SC2877, 2SD1380, 2SD1818
18701	2SC1163	300V, 0,1A, 20,8W, 55MHz	BF 459, MJE 340, MJE 3440, 2SC2376
18702	2SC1164	50V, 0,3A, 0,6W, 1400MHz	BFR 36, 2SC2852
18703	2SC1165	40V, 0,5A, PQ1W(470MHz)	BFS 50, MRF 629, 2N3948
18704	2SC1166	60V, 0,2A, 0,6W, 120MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
18705	2SC1167	1200V, 1,5A, 50W, 3MHz	BU 204...206, 2SC1132, 2SD1095, 2SD1097
18706	2SC1168	100MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
18707	2SC1169	40V, 1A, PQ>2,5W(175MHz)	2SC2989
18708	2SC116T	2SC116, 75V	BC 140...141, BC 300...301, 2N1613
18709	2SC117(H,T)	75V, 0,6A, 13W, 112MHz	BD 139, BD 230, 2SD1200, 2SD1378
18710	2SC1170	1200/500V, 3,5A, 50W, 4MHz	BU 207...209, 2SC1413, 2SC1875, 2SD1098
18711	2SC1170A	2SC1170, 1400/500V	BU 208...209, 2SC1875, 2SD849...850
18712	2SC1170B	2SC1170, 1500/500V	BU 208...209, 2SD783, 2SD849...850
18713	2SC1171	1100V/800V, 1A, 50W, 2MHz	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18714	2SC1172	1500/600V, 5A, 50W, 3MHz	BU 208(A), 2SC2928, 2SD792, 2SD820
18715	2SC1172A	2SC1172, 6A	BU 508(A), 2SC3025...26, 2SD649, 2SD821
18716	2SC1172B	2SC1172, 7A	BU 508(A), 2SC3027...28, 2SD822, 2SD1016
18717	2SC1173	30V, 3A, 10W, 100MHz	2SC2562, 2SC3252...3253, 2SD1505
18718	2SC1174	1200/500V, 3,5A, 50W, 4MHz	BU 207...209, 2SC1413, 2SC1875, 2SD1098
18719	2SC1175(NP)	170MHz	BC 167, BC 182, BC 237, BC 547, 2SC3377



18720	2SC1175(NP)	170MHz	BC 167, BC 182, BC 237, BC 547, 2SC3377
18721	2SC1176	40V, 1A, PQ7,5W(175MHz)	BLW 18, BLW 37,BLY 62, BLY 87
18722	2SC1177	40V, 2,5A, PQ16W(175MHz)	BLW 29, BLY 84, BLY 88, MRF 226, 2N6081
18723	2SC1178(A)	40V, 5A, PQ23W(175MHz)	BLW 20, BLW 31
18724	2SC118(H)	80V, 0,6A, 13W, 120MHz	BD 139, BD 230, 2SD1200, 2SD1378
18725	2SC1180	30V, 0,02A, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
18726	2SC1184	900/500V, 1A, 50W	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18727	2SC1185	300/250V, 0,7A, 50W	2SC1106, 2SC2809
18728	2SC1187	40V, 25mA, 700MHz	BF 198, BF 225, BF 310, 2SC1855...56
18729	2SC1188	40V, 0,03A, 850MHz	BF 199, BF 224, BF 311, 2SC1855...56
18730	2SC1189	50V, 25mA, 850MHz	BF 199, BF 224, BF 311, 2SC1855...56
18731	2SC119(H)	75V, 0,6A, 13W, 130MHz	BD 139, BD 230, 2SD1200, 2SD1378
18732	2SC1190(Z)	36V, 2,5A, PQ16W(175MHz)	BLW 29, BLY 84, BLY 88, MRF 226, 2N6081
18733	2SC1191(Z)	36V, 3,5A, PQ27W(175MHz)	-
18734	2SC1192(Z)	36V, 5A, PQ37W(175MHz)	-
18735	2SC1193	20V, 0,03A, 0,2W, 4,5GHz	BFQ 71, BFQ 85, BFR 14, BFR 91
18736	2SC1195	200V, 2,5A, 100W	TIP 51...54, 2SD632
18737	2SC1196	60V, 0,75A, PQ>3W(700MHz)	2N4430, 2SC1082
18738	2SC1196A	PQ>4W(700MHz)	-
18739	2SC1197	60V, 2A, PQ>9W(700MHz)	-
18740	2SC1197A	PQ>12W(700MHz)	-
18741	2SC1198	45V, 3,5A, PQ>18W(700MHz)	-
18742	2SC1199	50V, 0,3A, 0,6W, 1400MHz	BFS 50, MRF 515, 2SC2852
18743	2SC12	60V, 0,25A, 0,18W, 13MHz	BC 140...141, BC 300...302, 2N3053
18744	2SC120	B>20	BC 167, BC 182, BC 237, BC 547, 2N2218
18745	2SC1204	30V, 0,1A, 0,31W, 230MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
18746	2SC1205	30V, 0,1A, 230MHz	BF 240...241, BF 254...255, BF 594...595
18747	2SC1206(A,B)	PQ10..12W(770MHz)	-
18748	2SC1207(A,B)	45V, 3A, PQ16..21W(770MHz)	-
18749	2SC1208(A)	36V, 10A, PQ37..39W(175MHz)	BLW 60, BLY 90
18750	2SC1209	25V, 0,7A, 0,5W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1578
18751	2SC1209	25V, 0,7A, 0,5W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1578
18752	2SC121	2SC120, 130MHz, B20..75	BC 167, BC 182, BC 237, BC 547, 2N2218
18753	2SC1210	2SC1209, 45V, 0,3A	BC 337, BC 635, BC 637, 2SC3377
18754	2SC1210	2SC1209, 45V, 0,3A	BC 337, BC 635, BC 637, 2SC3377
18755	2SC1211	2SC1209, 65V, 0,3A	BC 337A, BC 637, BC 639, 2SC4412
18756	2SC1211	2SC1209, 65V, 0,3A	BC 337A, BC 637, BC 639, 2SC4412
18757	2SC1212	50V, 1A, 8W, 160MHz	BD 137, BD 228, BD 375, 2SD1177...1178
18758	2SC1212A	2SC1212, 80V	BD 139, BD 230, BD 379, 2SD1177...1178
18759	2SC1213	35V, 0,5A, 0,4W, 120MHz	BC 337...338, BC 635, BC 637, 2SC3377
18760	2SC1213	35V, 0,5A, 0,4W, 120MHz	BC 337...338, BC 635, BC 637, 2SC3377
18761	2SC1213A(AK)	2SC1213, 50V	BC 337, BC 635, BC 637, 2SC4414
18762	2SC1213A(AK)	2SC1213, 50V	BC 337, BC 635, BC 637, 2SC4414
18763	2SC1214	50V, 0,5A, 0,6W, 50MHz	BC 337, BC 635, BC 637, 2SC4414
18764	2SC1214	50V, 0,5A, 0,6W, 50MHz	BC 337, BC 635, BC 637, 2SC4414



18765	2SC1215(S,T)	T,>9MHz)	BF 377...378, BF 689K, BF 763, 2SC3037
18766	2SC1215(S,T)	T,>9MHz)	BF 377...378, BF 689K, BF 763, 2SC3037
18767	2SC1216	40V, 0,2A, 0,3W, <20/40ns	BSS 11, BSX 19...20, 2N2368...69(A)
18768	2SC1217	150V, 0,3A, 0,75W, 250MHz	BSS 43, BSW 68, 2SD413, 2SD576, 2SD624
18769	2SC1218	80V, 0,5A, 0,75W, 370MHz	BSW 39, 2N3444, 2N3723, 2SC1069
18770	2SC1219	30V, 0,5A, 0,2W, 60MHz	BC 337...338, BC 635, BC 637, 2SC3377
18771	2SC1219	30V, 0,5A, 0,2W, 60MHz	BC 337...338, BC 635, BC 637, 2SC3377
18772	2SC122	2SC120, 160MHz, B50..150	BC 167, BC 182, BC 237, BC 547, 2N2219
18773	2SC1220(F)	2SC1219, 50V	BC 337A, BC 637, 2SC3939, 2SD1226
18774	2SC1220(F)	2SC1219, 50V	BC 337A, BC 637, 2SC3939, 2SD1226
18775	2SC1222	50V, 0,02A, 0,25W, >30MHz	BC 184, BC 414, BC 550, 2SC2390
18776	2SC1222	50V, 0,02A, 0,25W, >30MHz	BC 184, BC 414, BC 550, 2SC2390
18777	2SC1223	30V, 0,5A, 0,8W, 1300MHz	BFS 50, MRF 515, 2N3948, 2SC2852
18778	2SC1224	130V, 0,8A, 7W, <200/1200ns	2SC2483
18779	2SC1226(A)	40(A50)V, 2A, 10W, 150MHz	2SC1848, BD 507, 2SD1206, 2SD1818
18780	2SC1227(F)	300/200V, 10A, 100W, 27MHz	BUW 24, BUW 72, BUX 17A...C, 2SC2537
18781	2SC1228(F)	500/400V, 10A, 100W, 15MHz	BUW 25, BUW 34, BUW 75, 2SC3043
18782	2SC1229	2SC 1227, 250/200V	BUW 24, BUW 72, BUX 17(A...C), 2SC2537
18783	2SC123	2SC120, 180MHz, B80..200	BC 167, BC 182, BC 237, BC 547, 2N2219
18784	2SC1230	2SC 1228, 450/400V	BUW 24...25, BUW 72, BUW 75, 2SC3043
18785	2SC1231	20V, 0,2A, 0,3W, <-/27ns	BSS 11...12, BSY 17...18, 2N3011
18786	2SC1232	45V, 1A, PQ6W(770MHz)	-
18787	2SC1233	45V, 2A, PQ11W(770MHz)	-
18788	2SC1235	300V, 0,1A, 6,5W(Tc70°)	2SC1505...1507, 2SC1755...1757, 2SC1819
18789	2SC1236	20V, 0,03A, 0,2W, 6,5GHz	BFQ 57...58, BFQ 74, 2SC1923
18790	2SC1237	85V, 2A, PQ3,5W(27MHz)	2SC1306, 2SC1678...1679, 2SC1909
18791	2SC1238	35V, 0,15A, 5W, 1700MHz	BLV 90, MRF 838A
18792	2SC1239	80V, 4A, PQ3,4W(27MHz)	2SC1306, 2SC1909, 2SC2078, 2SC2092
18793	2SC124	2SC120, 200MHz, B>20	BC 167, BC 182, BC 237, BC 547, 2N2218
18794	2SC1240	40V, 0,05A, 0,35W, 600MHz	BF 198...199, BF 224...225, BF 310...311
18795	2SC1240	40V, 0,05A, 0,35W, 600MHz	BF 198...199, BF 224...225, BF 310...311
18796	2SC1241	40V, 1,5A, PQ>6W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
18797	2SC1241A	PQ>8W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
18798	2SC1242	40V, 3A, PQ>13W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
18799	2SC1242A	2SC1242, 35V, 4,5A	BLY 89, MRF 209, 2N5591, 2N6082
18800	2SC1243	25V, 1,5A, 7W, 70MHz	BD 429, BD 505, BD 515, BD 839
18801	2SC1244	30V, 0,05A, 0,2W	BC 168, BC 183, BC 238, BC 548, 2SC1890
18802	2SC1244	30V, 0,05A, 0,2W	BC 168, BC 183, BC 238, BC 548, 2SC1890
18803	2SC1246(A,F,AF)	30V, 0,5A, 0,4(A0,5)W, 60MHz	BC 337...338, BC 635, BC 637, 2SC3377
18804	2SC1246(A,F,AF)	30V, 0,5A, 0,4(A0,5)W, 60MHz	BC 337...338, BC 635, BC 637, 2SC3377
18805	2SC1247(A,F,AF)	2SC1246, 50V	BC 337, BC 637, BC 639, 2SD1226
18806	2SC1247(A,F,AF)	2SC1246, 50V	BC 337, BC 637, BC 639, 2SD1226
18807	2SC1248(R)	20V, 0,03A, 2,5GHz	BFQ 59, BFQ 70, BFR 34, BFT 97, 2SC2143
18808	2SC1249(R)	45V, 0,3A, 1,7GHz	BFQ 68, 2SC1043, 2SC1251
18809	2SC125[Hitachi]	20V, 10mA, 700MHz	-

18810	2SC125[Sony]	100V, 0,05A, 0,75W, 200MHz	BF 257...259, 2SC1890A, 2SC3245, 2SD755
18811	2SC1250(R)	2SC1249, 1,9GHz	BFQ 68, 2SC1043, 2SC1251
18812	2SC1251	45V, 0,3A, 7W, 2,2GHz	BFQ 68, 2SC1043, 2SC1250
18813	2SC1252	45V, 0,3A, 0,8W, 1,7GHz	2SC1199, 2SC2852
18814	2SC1253	45V, 0,3A, 0,8W, 2GHz	2SC1199, 2SC2852
18815	2SC1254	45V, 0,03A, 1000MHz	BF 377...378, BF 689, BF 763, 2N2857
18816	2SC1255	30V, 0,1A, 3,5W, 2,7GHz	BFQ 34, BFR 94, 2SC1592
18817	2SC1256	36V, 0,8A, PQ3W(175MHz)	BFQ 43, BFS 22, BLY 33, MRF 237
18818	2SC1257	36V, 1,5A, PQ8W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
18819	2SC1258	36V, 3A, PQ14W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
18820	2SC1259	36V, 6A, PQ30W(175MHz)	BLW 20, BLW 31, 2N6084
18821	2SC126	2SC125[Sony], 140V	BF257...259, 2SC2375, 2SC3245A, 2SD756A
18822	2SC1260	45V, 0,03A, 0,25W, 2GHz	BFR 37, BFW 30, BFX 73, 2SC2570
18823	2SC1261(F,S)	20V, 0,03A, 0,3W, 2,5GHz	BFQ 59, BFR 34, BFT 97, 2SC2672
18824	2SC1262(F,S)	45V, 0,3A, 1,7GHz	BFQ 68, 2SC1043, 2SC1249...1251
18825	2SC1263(F,S)	2SC1262, 1,9GHz	BFQ 68, 2SC1043, 2SC1250...1251
18826	2SC1264(F)	30V, 0,1A, 0,4W, 2GHz	BFG 34, BFT 12
18827	2SC1266	<63/210ns	BD 139, BD 529, BD 843, 2SC2275
18828	2SC1267	45V, 0,3A, 7W, 2,2GHz	BFQ 68, 2SC1043, 2SC1250...1251
18829	2SC1268	20V, 0,03A, 0,2W, 6GHz	BFG 91, BFQ 57...58, BFQ 74, 2SC3276
18830	2SC1269	20V, 0,03A, 0,2W, 6GHz	BFG 91, BFQ 57...58, BFQ 74, 2SC3276
18831	2SC127	20V, 25mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
18832	2SC1270	20V, 0,03A, 0,2W, 6GHz	BFG 91, BFQ 57...58, BFQ 74, 2SC3276
18833	2SC1271(A)	20V, 0,03A, 0,2W, 6GHz	BFG 91, BFQ 57...58, BFQ 74, 2SC3276
18834	2SC1272	20V, 0,1A, 4GHz	BFG 96, BFP 96, BFQ 73, BFR 96
18835	2SC1273	20V, 0,1A, 4GHz	BFG 96, BFP 96, BFQ 73, BFR 96
18836	2SC1274	40V, 0,3A, 0,3W, <80/86ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18837	2SC1275	30V, 25mA, 2GHz	BF 630, BFR 15, BFS 55, BFW 99
18838	2SC1276	40V, 0,1A, 0,2W, <20/40ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
18839	2SC1276	40V, 0,1A, 0,2W, <20/40ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
18840	2SC1277	60V, 0,5A, 0,25W, 60MHz	BC 337A, BC 637, 2SC3939, 2SD1226
18841	2SC1277	60V, 0,5A, 0,25W, 60MHz	BC 337A, BC 637, 2SC3939, 2SD1226
18842	2SC1278	150V, 0,05A, 0,25W, 150MHz	BF 297...299, BF 422, 2SC2375, 2SD2030
18843	2SC1278	150V, 0,05A, 0,25W, 150MHz	BF 297...299, BF 422, 2SC2375, 2SD2030
18844	2SC1279(S)	2SC1278, 180V	BF 297...299, BF 422, 2SC3248, 2SD2031
18845	2SC1279(S)	2SC1278, 180V	BF 297...299, BF 422, 2SC3248, 2SD2031
18846	2SC128	<320/1300ns	ASY 28...29, ASY 73...75
18847	2SC1280(S)	15V, 0,3A, 0,25W, B>5000	BC 517, BC 617, MPSA 13...14, 2SC4009
18848	2SC1280(S)	15V, 0,3A, 0,25W, B>5000	BC 517, BC 617, MPSA 13...14, 2SC4009
18849	2SC1280A(AS)	2SC1280, 40V, B>12000	BC 517, BC 617, MPSA 25...26, 2SC4009
18850	2SC1280A(AS)	2SC1280, 40V, B>12000	BC 517, BC 617, MPSA 25...26, 2SC4009
18851	2SC1281	20V, 0,02A, 0,3W, 120MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
18852	2SC1282	2SC1282, 70V	BC 174, BC 546, 2SC1890(A), 2SC2240
18853	2SC1283	2SC1281, 110V	2SC1775A, 2SC1890A, 2SC2240, 2SC2363
18854	2SC1284	30V, 0,05A, 700MHz	BF 377...378, BF 689K, BF 763, 2N2857

18855	2SC1284	30V, 0,05A, 700MHz	BF 377...378, BF 689K, BF 763, 2N2857
18856	2SC1285	40V, 0,1A, 0,2W, 140MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
18857	2SC1285	40V, 0,1A, 0,2W, 140MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
18858	2SC1286	25V, 0,05A, 400MHz	BF 198...199, BF 224...225, BF 310...311
18859	2SC1286	25V, 0,05A, 400MHz	BF 198...199, BF 224...225, BF 310...311
18860	2SC1288	7V, 0,06A, 0,2W, 4,5GHz	-
18861	2SC129	10MHz,<265/1300ns	ASY 28...29, ASY 73...75
18862	2SC1290	40V, 0,2A, 0,75W, 1,5GHz	BFR 36, 2SC1199, 2SC1252
18863	2SC1292	300/300V, 2,5A, 80W	BU 126, BUW 71, TIP 51...54, 2SD632
18864	2SC1293	25V, 0,05A, 400MHz	BF 198...199, BF 224...225, BF 310...311
18865	2SC1293	25V, 0,05A, 400MHz	BF 198...199, BF 224...225, BF 310...311
18866	2SC1295	1000/350V, 2A, 40W	BU 204...206, 2SC1132, 2SD1097...1098
18867	2SC1296	1300/400V, 5A, 50W	BU 207...209, 2SC2928, 2SD350, 2SD820
18868	2SC1297	50V, 3,5A, PQ26W(175MHz)	MRF 314A...315A, 2SC2888
18869	2SC1298	50V, 5A, PQ37W(175MHz)	BLW 25, BLY 94, 2N5643, 2SC2889
18870	2SC1299(F)	300/200V, 30A, 200W, 25MHz	2SC1401, 2SC1873, 2SD542...543, 2SD643
18871	2SC13	18V, 0,04A, 0,065W, >3,5MHz	AC 127, ASY 28...29
18872	2SC130	60V, 1A, 20W, 160MHz	BD 137, BD 228, 2SC1398, 2SC3252
18873	2SC1300(F)	500V, 30A, 200W, 20MHz	2SC1874, 2SC2220, 2SC2442, 2SC2444
18874	2SC1301	2SC1301, 250/200V	2SC1873, 2SC2249, 2SC2445, 2SD643
18875	2SC1302	2SC1301, 400/400V	2SC1401, 2SC1470, 2SC2250, 2SD542...43
18876	2SC1304	300/300V, 0,5A, 20W, 7MHz	2N3739, 2SC782, 2SC1929, 2SC2354
18877	2SC1306	65V, 3A, PQ5,5W(50MHz)	-
18878	2SC1307	70V, 8A, PQ15W(50MHz)	-
18879	2SC1308	1500/400V, 7A, 50W	BU 508(A), 2SC3027...28, 2SD822, 2SD1016
18880	2SC1309	1200/500V, 5A, 80W	2SC1413, 2SD1099, 2SD1103
18881	2SC131	/40ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18882	2SC1310	50V, 0,2A, 0,3W, 200MHz	BC 414, BC 550, 2SC2240, 2SC2674...75
18883	2SC1311	2SC1310, AM/FM	BF 240...241, BF 254...255, BF 594...595
18884	2SC1312	35V, 0,1A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC1890
18885	2SC1312	35V, 0,1A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC1890
18886	2SC1313	2SC1312, 50V	BC 184, BC 414, BC 550, 2SC2240
18887	2SC1313	2SC1312, 50V	BC 184, BC 414, BC 550, 2SC2240
18888	2SC1314(A)	40V, 5A, PQ34W(175MHz)	BLW 20, BLW 31, 2N6084
18889	2SC1315	35V, 0,5A, PQ0,5W(150MHz)	BFR 98, BLW 16, BLY 61, MRF 225
18890	2SC1316	750/750V, 2A, 23W, 8,5MHz	BUV 36(A), BUX 84...85, 2SC3149, 2SC3352
18891	2SC1317	30V, 0,5A, 0,625W, 200MHz	BC 337...338, BC 635, BC 637, 2SC3377
18892	2SC1317	30V, 0,5A, 0,625W, 200MHz	BC 337...338, BC 635, BC 637, 2SC3377
18893	2SC1318	2SC1317, 60V	BC 337A, BC 637, BC 639, 2SD667
18894	2SC1318	2SC1317, 60V	BC 337A, BC 637, BC 639, 2SD667
18895	2SC1318A	2SC1351, 80V	BC 639, 2SD667, 2SD1226, 2SD1768
18896	2SC1318A	2SC1351, 80V	BC 639, 2SD667, 2SD1226, 2SD1768
18897	2SC1319	40V, 25mA, 600MHz	BF 198, BF 225, BF 310, BF 596, 2SC2215
18898	2SC1319	40V, 25mA, 600MHz	BF 198, BF 225, BF 310, BF 596, 2SC2215
18899	2SC132	/40ns	BSS 10, BSX 19...20, BSX 26, 2N3261

18900	2SC1320	50V, 30mA, 850MHz	BF 199, BF 224, BF 311, 2SC1855...56
18901	2SC1320	50V, 30mA, 850MHz	BF 199, BF 224, BF 311, 2SC1855...56
18902	2SC1321	30V, 10mA, 900MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
18903	2SC1322	250/200V, 15A, 100W, 27MHz	BUX 13, BUX 41, 2SD552, 2SD583, 2SD3263
18904	2SC1323	30V, 0,5A, 5W, 1300MHz	BLX 66, MRF 627...628, 2N6256
18905	2SC1324	35V, 0,15A, 0,8W, 1,7GHz	BFR 36, BFW 16, 2SC1068
18906	2SC1325(A)	1500/600V, 6A, 80W	BU 208(A), BU 508(A), 2SC2928, 2SD954
18907	2SC1326(Z)	55V, 0,4A, PQ>1W(400MHz)	BFS 23, BFW 47, BLY 34, 2N3553, 2N5160
18908	2SC1327	35V, 0,05A, 0,15W, 250MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
18909	2SC1327	35V, 0,05A, 0,15W, 250MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
18910	2SC1328	2SC1327, 55V	BC 414, BC 550, 2SC2240, 2SC2390
18911	2SC1328	2SC1327, 55V	BC 414, BC 550, 2SC2240, 2SC2390
18912	2SC1329	50V, 8A, PQ32W(70MHz)	2SC2313
18913	2SC133	/40ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18914	2SC1330	50V, 0,1A, 0,4W, 250MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
18915	2SC1331	20V, 0,02A, 750MHz	BF 377...378, BF 689, BF 763, 2N2857
18916	2SC1333	45V, 1A, 10W, 1200MHz	BLW 33...34, 2N4430, 2SC3140
18917	2SC1334	50V, 1A, 11,6W, 1200MHz	BLW 98, BLX 98, 2N4431, 2SC3141
18918	2SC1335	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
18919	2SC1336	20V, 0,03A, 0,25W, 4,5GHz	BFQ 71, BFQ 85, BFR 14, 2SC1119
18920	2SC1337(A)	35V, 2A, PQ8,5W(485MHz)	BLW 14, BLW 44, 2N5946
18921	2SC1338(A)	35V, 3A, PQ16W(485MHz)	BLW 15, BLX 69
18922	2SC1339	35V, 5A, PQ28W(485MHz)	BLW 15, BLX 69
18923	2SC134	/125ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18924	2SC1340	35V, 1A, 5W, 1GHz	BLU 97, BLW 43, BLW 80, BLX 68, BLY 53
18925	2SC1342	320MHz	BF 240...241, BF 254...255, BF 594...595
18926	2SC1342	320MHz	BF 240...241, BF 254...255, BF 594...595
18927	2SC1343(H)	150V, 10A, 100W, 14MHz	BD 245D, 2SD551, 2SD733, 2SD1047
18928	2SC1344	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
18929	2SC1344	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
18930	2SC1345(K)	2SC1344, 55V	BC 414, BC 550, 2SC2240, 2SC2459
18931	2SC1345(K)	2SC1344, 55V	BC 414, BC 550, 2SC2240, 2SC2459
18932	2SC1346	2SC1317, 0,6W	2SC1317
18933	2SC1347	2SC1318, 0,6W	2SC1318
18934	2SC1348(-1...-3)	1000..1200V, 4A, 125W, 5MHz	BU 207...209, BU 508, 2SC2928, 2SD954
18935	2SC1349(F)	20V, 0,2A, 0,2W, -/15ns	BSS 11, BSX 19...20, 2N2369...69(A)
18936	2SC135	/125ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18937	2SC1350	25V, 0,3A, 0,3W, <-/60ns	BSS 11, BSX 19...20, 2N2369...69(A)
18938	2SC1351	80V, 1A, 0,8W, <50/85ns	BSV 95, 2N3735, 2SC1069
18939	2SC1352	25V, 0,8A, 0,6W, <15/20ns	BSS 28...29, BSV 69, BSX 12, 2N3426
18940	2SC1353	90V, 0,7A, 0,65W, 45/95ns	BSW 39, 2SC1069
18941	2SC1354(Z)	55V, 5A, PQ37W(175MHz)	-
18942	2SC1355(F)	40V, 0,7A, PQ2W(700MHz)	BLU 99
18943	2SC1356(F)	40V, 1A, PQ6W(700MHz)	-
18944	2SC1358(A)	1400/500V, 4,5A, 50W	BU 208...209, BU 508(A), 2SD783, 2SD954

18945	2SC1359	30V, 0,03A, 0,4W, 250MHz	BC237, BC548, BF240...241, BF254...255
18946	2SC136	/125ns	2N4014
18947	2SC1360(A)	>300MHz	BF 370, BF 920...921(S), BF 959
18948	2SC1361	25V, 0,2A, 0,25W, 140MHz	BC 169, BC 184, BC 239, BC 549, 2SC2275
18949	2SC1362	2SC1361, 50V	BC 414, BC 550, 2SC2240, 2SC2459
18950	2SC1363	25V, 0,2A, 0,25W, 140MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
18951	2SC1364	2SC1363, 50V	BC 167, BC 182, BC 237, BC 547, 2SD767
18952	2SC1365	45V, 0,3A, 0,8W, 1,7GHz	2SC1199, 2SC1252...1253, 2SC2852
18953	2SC1366	2SC1365, 2GHz	2SC1253, 2SC2852
18954	2SC1367(A)	1000V, 1A, 50W, 6MHz	BU 204...206, 2SC1101, 2SC1167, 2SD1095
18955	2SC1368	25V, 1,5A, 8W, 180MHz	BD 135, BD 226, BD 375, 2SD1380
18956	2SC137	/40ns	BSS 10, BSX 19...20, BSX 26, 2N3261
18957	2SC1373	25V, 0,1A, 0,3W, <100/325ns	BC 238, BC 548, BSY 62...63, 2N706A
18958	2SC1374(H)	25V, 0,1A, 0,3W, <13/16ns	BSV 89...92, BSX 92...93, 2N2368...69(A)
18959	2SC1375(H)	25V, 0,1A, 0,3W, <45/60ns	BSV 89...92, BSX 92...93, 2N2368...69(A)
18960	2SC1376(H)	40V, 0,5A, 0,3W, <25/40ns	BSS 10, BSX 26, BSX 39, 2N3261
18961	2SC1377	90V, 6A, PQ>8W(27MHz)	2SC1307, 2SC1944, 2SC1969, 2SC2098
18962	2SC1378	40V, 4A, PQ25W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
18963	2SC1379	40V, 7A, PQ40W(175MHz)	-
18964	2SC138(A)	60V, 0,5A, 0,8W, 400MHz	BFS 23, BFX 55, BLY 34, 2SC2852
18965	2SC1380	55V, 0,1A, 0,2W, 80MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
18966	2SC1380A	2SC1380	BC 414, BC 550, 2SC2240, 2SC2459
18967	2SC1381	100V, 1A, 5W, 50MHz	BD 139, BD 230, BD 379, 2SC2690
18968	2SC1382	80V, 0,75A, 5W, 100MHz	BD 139, BD 230, BD 379, 2SC2690
18969	2SC1383(NC)	30V, 1A, 1W, 200MHz	2SC2236, 2SD863, 2SD1207, 2SD1331
18970	2SC1384(NC)	2SC1383, 60V	2SC3328, 2SC4145, 2SD863, 2SD1207
18971	2SC1385(H)	60V, 0,5A, 0,8W, <40/60ns	BSS 27, BSV 77, 2N5189, 2SC1072
18972	2SC1386(H)	70V, 1A, 0,8W, <30/55ns	BSS 27, BSV 95, 2N3735, 2SC1069
18973	2SC1387	25V, 0,15A, 0,5W, 1,6GHz	BFR 36, BFW 16, 2SC1068, 2SC1324
18974	2SC1388(F)	100V, 1A, 0,8W, <50/110ns	2SC1069
18975	2SC139	2SC138	BFS 23, BFX 55, BLY 34, 2SC2852
18976	2SC1390	20V, 0,05A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2390
18977	2SC1391	300V, 0,1A, 6,5W, 25MHz	2SC1505...1507, 2SC1749, 2SC1819
18978	2SC1393	30V, 0,02A, 700MHz	BF 225, BF 310, BF 314, 2SC1856
18979	2SC1394	30V, 0,02A, 700MHz	BF 224, BF 310, BF 314, 2SC3136
18980	2SC1395	30V, 0,02A, >600MHz	BF 377...378, BF 689K, BF 763, 2N2857
18981	2SC1396	2SC1395, >800MHz	BF 377...378, BF 689K, BF 763, 2N2857
18982	2SC1398(A)	70V, 2A, 15W, 120MHz	2SC2528, 2SC3252
18983	2SC1399	100V, 0,05A, 0,25W, 100MHz	2SC1890A, 2SC2363, 2SC3245, 2SD756(A)
18984	2SC14	2SC13, >11MHz	AC 127, ASY 28...29
18985	2SC140	60V, 1A, 1,7W, 150MHz	BC 140...141, BCX 40, 2N1990, 2N2102
18986	2SC1400	2SC1399	2SC1775A, 2SC2088, 2SC2240, 2SC2459
18987	2SC1401	400/350V, 30A, 200W, 20MHz	2SC1302, 2SC1470, 2SC2250, 2SD542...543
18988	2SC1402	140V, 8A, 70W, 10MHz	BD 245D, 2N3442, 2SD551, 2SD1047
18989	2SC1403	2SC1402, 160V	BD 245D, 2N3442, 2SD551, 2SD1047



18990	2SC1403A	2SC1402, 180V	BD 245E, BDW 16, 2SC2261...62, 2SD751
18991	2SC1404	36V, 3,5A, PQ18W(470MHz)	BLX 69, 2SC1338
18992	2SC1405(Z)	36V, 0,75A, PQ3,5W(175MHz)	BLW 17, 2SC1011
18993	2SC1406	30V, 1A, 1W, 200MHz	BC 337...338, BC 635, BC 637, 2SD1225
18994	2SC1407	2SC1406, 60V	BC 337A, BC 637, BC 639, 2SD667
18995	2SC1409(A)	20MHz	BD 239F, 2SC2660, 2SD760, 2SD1138
18996	2SC141	20V, 0,2A, 0,36W, 450MHz	BSS 11, 2N2368...69(A), 2SC2901, 2SC3732
18997	2SC1410(A)	200V, 2A, 12,5W, 20MHz	BD 239F, 2SC2660, 2SD760, 2SD1138
18998	2SC1411	6V, 0,05A, 0,2W	-
18999	2SC1412	45V, 0,15A, 0,6W, 1,5GHz	BFR 36, BFW 16, 2SC1068, 2SC1324
19000	2SC1413(H)	1200/500V, 5A, 50W, 4MHz	BU 207...209, BU 508, 2SD1099, 2SD1103
19001	2SC1413A(AH)	2SC1413, 1500/500V	BU 208...209, BU 508, 2SC2928, 2SD954
19002	2SC1414(F)	40V, 2A, PQ10W(700MHz)	2SC1087
19003	2SC1415(F)	40V, 3A, PQ16W(700MHz)	2SC1087
19004	2SC1416(A)	55V, 0,05A, 0,2W, 100MHz	BC 414, BC 550, 2SC2240, 2SC2390
19005	2SC1417	20V, 0,03A, 300MHz	BF 240...241, BF 254...255, BF 594...595
19006	2SC1418	50V, 2A, 20W, 5MHz	BD 239, 2SC1398, 2SC2528, 2SC3252
19007	2SC1419	2SC1418	BD 239, 2SC1398, 2SC2528, 2SC3252
19008	2SC142	30V, 0,2A, 0,36W, 28/42ns	BSS 11, 2N2368...69(A), 2SC2901, 2SC3732
19009	2SC1420	15V, 0,07A, 0,3W, 6GHz	2SC2876, 2SC3603
19010	2SC1421	15V, 0,03A, 0,25W, 5,5GHz	BFG 91, BFP 91, BFQ 57...58, BFQ 74
19011	2SC1422(F)	15V, 0,04A, 0,25W, 5,5GHz	BFG 91, BFP 91, BFQ 57...58, BFQ 74
19012	2SC1423	15V, 0,03A, 0,25W, 7GHz	BFG 65, BFQ 66, 2SC3062, 2SC3276
19013	2SC1424	2GHz	BF 377...378, BFR 37, BFS 55, BFW 30
19014	2SC1425	45V, 1A, PQ3W(1GHz)	2N4430
19015	2SC1426	35V, 0,2A, 2,7GHz	-
19016	2SC1427	30V, 10mA, 1GHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
19017	2SC1428	50V, 0,05A, 250MHz	BC 846...847, BCW 71...72, BCW 81, 2SC3323
19018	2SC1429-...	12..16V, 2A, 80MHz	BC 365, BD 505, BD 515, 2SD1177...78
19019	2SC143	40V, 0,2A, 0,36W, 28/42ns	BSS 11, 2N2368...69(A), 2SC2901, 2SC3732
19020	2SC1430-1	110/110V, 1,5A, 0,5W, 50MHz	BCX 40, BSS 42...43, BSW 67...68, BSX 47
19021	2SC1430-2	2SC1430-1, 140/140V	BSS 43, BSW 68, 2SC1860
19022	2SC1431-1	110/110V, 2A, 23W, 80MHz	2SC2528...2529, 2SD759
19023	2SC1431-2	2SC1431-1, 140/140V	2SC2529, 2SD759
19024	2SC1432	30V, 0,3A, 0,3W, B40000	BC 517, MPSA 13...14, 2SC4009, 2SC40174
19025	2SC1433	600/400V, 5A, 50W, 2/11,5µs	BUW 25, BUX 82, 2SC2962, 2SD640
19026	2SC1434	600/440V, 15A, 150W, 2/17,5µs	BUS 13, BUW 45...46, BUX 48, 2SD641
19027	2SC1435	11/11,5µs	2SD642
19028	2SC1436	230/230V, 15A, 100W, 10MHz	BUW 50...52, BUX 41, BUX 70, 2SD583
19029	2SC1437	2SC1436, 50A, 200W	2SC2147, 2SC2159, 2SC2942
19030	2SC1438	130MHz	BF 297...299, BF 422, 2SC2375, 2SD2030
19031	2SC1439	2SC1438, 150/150V	BF 297...299, BF 422, 2SC2363, 2SD2030
19032	2SC144(A)	50(A60)V, 0,2A, 0,36W, 28/47ns	2SC1834
19033	2SC1440	150/150V, 15A, 100W, 10MHz	BD 745E, BUX 41, 2SC1584, 2SD552
19034	2SC1441	2SC1440, 200V	BDW 16, BUX 41, 2SC1585, 2SD552



19035	2SC1442	2SC1440, 50A, 200W	2SC1437, 2SC2147, 2SC2159, 2SC2942
19036	2SC1443	2SC1440, 200V, 50A, 200W	2SC1437, 2SC2147, 2SC2159, 2SC2942
19037	2SC1444	80V, 6A, 40W, 10MHz	BD 243B, BD 543B, BD 799, 2N5427...28
19038	2SC1445	2SC1444, 100V	BD 243C, BD 543C, BD 801, 2N5429...30
19039	2SC1446	300V, 0,1A, 10W(Tc70°)	2SC1505...1507, 2SC1755...1757, 2SC1905
19040	2SC1447	300/300V, 0,15A, 20W, 80MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19041	2SC1448(A)	5(A7)MHz	BD 239D, 2SC2073, 2SD608(A), 2SD1138
19042	2SC1449	40V, 2A, 5W, 60MHz	BD 375, 2SD1380, 2SD882, 2SD1818
19043	2SC145	30V, 0,2A, 0,36W, 500MHz	BSS 11, 2N2368...69(A), 2SC2901, 2SC3732
19044	2SC1450(S)	150/150V, 0,4A, 20W(Tc80°)	BD 239D, 2SC2073, 2SD608, 2SD1138
19045	2SC1451	130MHz	BF 257...258, 2N5058...59, 2SC3467...68
19046	2SC1452	2SC1451, 150/150V	BF 257...258, 2N5058...59, 2SC3467...68
19047	2SC1453	55V, 0,1A, 0,2W, 150MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19048	2SC1454	/7,2μs	BU 606...608, BUW 71, 2SC2624, 2SD632
19049	2SC1456	300/300V, 0,2A, 15W, 80MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19050	2SC1457	35V, 0,15A, 0,8W, 2,7GHz	BFR 95
19051	2SC1458	20V, 0,05A, 0,3W, 3GHz	BFQ 72, 2SC2844, 2SC3302
19052	2SC1459	2SC1420	2SC1420
19053	2SC146(A)	500MHz	2SC1834
19054	2SC1460	2SC1421	2SC1421
19055	2SC1461	2SC1422	2SC1422
19056	2SC1462	2SC1423	2SC1423
19057	2SC1463	/ $<8\mu s$	BUW 71, BUX 45, 2SC2624, 2SC3083
19058	2SC1464	50V, 0,5A, PQ1,2W(175MHz)	BFR 98, BFS 23, BLW 16, BLY 34, BLY 61
19059	2SC1465	50V, 0,5A, PQ1,8W(700MHz)	-
19060	2SC1466	450/360V, 3A, 30W, 10MHz	BUT 93, BUY 63...64, TIP 75B, 2SC2929
19061	2SC1467	2SC1466, 500/400V	BUT 93, BUY 63...64, TIP 75C, 2SC2826
19062	2SC1468	450/360V, 10A, 100W, 10MHz	BUW 24...26, BUW 34...36, 2SC4138
19063	2SC1469(A)	2SC1468, 500/400V	BUW 25...26, BUW 34...36, 2SC4138
19064	2SC147	30V, 1A, 0,75W, 120MHz	BC 140...141, BCX 40, 2N1990, 2N2102
19065	2SC1470	450/360V, 30A, 200W, 10MHz	2SC1300, 2SC1874, 2SC2220, 2SC2444
19066	2SC1471(A)	2SC1470, 500/400V	2SC1300, 2SC1874, 2SC2220, 2SC2444
19067	2SC1472(K)	B>2000	BC 517, BC 617, BC 875, MPSA 25...29
19068	2SC1472(K)	B>2000	BC 517, BC 617, BC 875, MPSA 25...29
19069	2SC1473(NC)	80MHz	BF 298...299, BF 422, 2SC3468...69
19070	2SC1473A	2SC1473, 300/300V	BF 299, BF 420, BFR 89, 2SC3468
19071	2SC1474-..	20V, 2A, 0,75W, 80MHz	2SD787...788, 2SD1100, 2SD1146, 2SD1207
19072	2SC1475-..	100V, 1A, 0,75W, 80MHz	2SC3228, 2SD667, 2SD1292, 2SD1812
19073	2SC1476	38V, 5A, PQ28W(470MHz)	2SC1339
19074	2SC1477	230V, 9A, 80W, 10MHz	BUX 17(A...C), BUY 18, TIP 160...162
19075	2SC1478	35V, 0,05A, 0,15W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
19076	2SC1478A	2SC1478, 55V	BC 167, BC 182, BC 237, BC 547, 2SC1890
19077	2SC1479	36V, 0,5A, PQ1,2W(175MHz)	BFR 98, BFS 51, BFQ 42, BLW 16, BLY 61
19078	2SC1480	36V, 0,5A, PQ2,4W(470MHz)	BLW 79, BLX 67, BLY 38, 2N5945
19079	2SC1481	36V, 1A, PQ5W(470MHz)	BLW 43, BLW 80

19080	2SC1482	36V, 2A, PQ8,5W(470MHz)	BLW 44, 2N5946, 2SC1337
19081	2SC1482A	PQ15W(470MHz)	BLW 15, BLX 69, 2SC1338
19082	2SC1483(F)	20V, 0,04A, 3GHz	BFQ 59, BFQ 70, BFR 34, BFT 97
19083	2SC1484	45V, 0,3A, 5W, 2GHz	BFR 65, 2SC1043, 2SC1250...1251
19084	2SC1485	250/250V, 0,125A, 0,35W	BF 298...299, BF 422A, 2SC3468...69
19085	2SC149	120V, 0,3A, 0,8W, 160MHz	BC 300, 2N1893(A), 2SD413, 2SD624
19086	2SC1498	36V, 2,5A, 45W	BLU 20/12, MRF 641
19087	2SC1499	36V, 6A, 115W	BLU 30/12, MRF 644
19088	2SC15-0	30V, 0,05A, 0,75W, 150MHz	BC 183, BC 238, BC 548, 2N2218...19
19089	2SC15-1	2SC15-0, 60V	BC 182, BC 190, BC 546, 2N2218...19
19090	2SC15-2	2SC15-0, 90V	2SC1890(A), 2SC2240, 2SD755...756(A)
19091	2SC15-3	2SC15-0, 120V	2SC1890A, 2SC2240, 2SD756(A)
19092	2SC150(H)	20V, 0,1A, 0,75W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2N2218
19093	2SC1500	36V, 8A, 115W	BLU 45/12, BLW 82, MRF 646
19094	2SC1501	300V, 0,1A, 10W, 55MHz	BF 417, BF 459, 2SC3417, 2SC3503
19095	2SC1503	50V, 3A, PQ13W(260MHz)	BLW 94, BLX 94, MRF 323, 2SC1118
19096	2SC1504	400/300V, 2A, 40W, 10MHz	BUX 67C, 2N3585, 2N4240, 2SC3055
19097	2SC1505	300V, 0,2A, 15W, 80MHz	2SC1755...1757, 2SC1905, 2SC4714
19098	2SC1506	2SC1505	2SC1755...1757, 2SC1905, 2SC4714
19099	2SC1507	2SC1505	2SC1755...1757, 2SC1905, 2SC4714
19100	2SC1509(NC,Z)	80V, 0,5A, 1W, 120MHz	2SC3939, 2SC3328, 2SD667, 2SD1812
19101	2SC150T	2SC150, 50V	BC 167, BC 182, BC 237, BC 547, 2N2218
19102	2SC151(H)	40V, 0,2A, 0,75W, 130MHz	BC 167, BC 182, BC 237, BC 547, 2N2218
19103	2SC1510	47V, 1A, PQ4,5W(770MHz)	BLW 98, BLX 98, 2N4431
19104	2SC1511	50V, 3A, PQ25W(275MHz)	MRF 325...326
19105	2SC1512	50V, 5A, PQ37W(275MHz)	2N6439, 2SC2796, 2SC2895
19106	2SC1513	40V, 0,3A, 1,8GHz	2SC1199, 2SC1252, 2SC1365...1366
19107	2SC1514	300/300V, 0,1A, 80MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19108	2SC1515(K)	110MHz	BF 298...299, BF 422, 2SC3468...69
19109	2SC1515(K)	110MHz	BF 298...299, BF 422, 2SC3468...69
19110	2SC1516(K)	35V, 1,5A, 10W, 110MHz	2SC1398, 2SC2275, 2SC2528, 2SC3252
19111	2SC1517	50V, 1A, 10W, 150MHz	2SC1398, 2SC2275, 2SC2528, 2SC3252
19112	2SC1517A	2SC1517, 80V	2SC1398, 2SC2275, 2SC2528, 2SC3252
19113	2SC1518(NC)	25V, 1A, 1W, 150MHz	2SC2236, 2SD863, 2SD1207, 2SD1331
19114	2SC1519	250/250V, 0,2A, 10W, 80MHz	BF 615, BF 617, BF 858...859, 2SC1758
19115	2SC152(H)	60V, 0,2A, 0,75W, 160MHz	BC 174, BC 182, BC 190, BC 546, 2N2218
19116	2SC1520-..	250..300V, 0,2A, 12,5W, 80MHz	BF 617, BF 859, BF 758, MPSU 10
19117	2SC1521	2SC1520	2SC1520
19118	2SC1522	2SC1519	2SC1519
19119	2SC1523	40V, 0,3A, 2GHz	BFQ 41, MRF 626, 2N5944
19120	2SC1524	50V, 1A, PQ8W(700MHz)	-
19121	2SC1525	50V, 2A, PQ13W(700MHz)	2SC1087
19122	2SC1526	50V, 3A, PQ22W(700MHz)	-
19123	2SC1528	40V, 2,5A, PQ16W(175MHz)	-
19124	2SC1529	30V, 0,02A	BF 689, BFX 62, BFX 89, BFR 37, BFW 30

19125	2SC153	120V, 0,2A, 0,75W, 140MHz	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
19126	2SC1530	50V, 0,35A, PQ1,5W(1GHz)	BFT 99, 2SC2956
19127	2SC1532	300/200V, 30A, 200W, >5MHz	2SC1299, 2SC1302, 2SC1873, 2SD643
19128	2SC1533	45V, 0,5A, PQ2,2W(700MHz)	2SC1082
19129	2SC1534	45V, 1A, PQ7W(700MHz)	-
19130	2SC1535	45V, 2A, PQ12W(700MHz)	2SC1087
19131	2SC1536	45V, 4A, PQ24W(700MHz)	-
19132	2SC1537	50V, 0,03A, 0,15W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SC1890
19133	2SC1538	2SC1537	BC 184, BC 414, BC 550, 2SC1775(A)
19134	2SC1539	25V, 0,03A, 0,15W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
19135	2SC154(A..C,H)	150MHz	BF 258...259, BF 658...659, 2N5058...59
19136	2SC1540	2SC1539	BC 169, BC 184, BC 239, BC 549, 2SC1775
19137	2SC1541	40V, 0,15A, 0,3W, 250MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19138	2SC1542	2SC1541, 25V	BC 168, BC 183, BC 238, BC 548, 2SD767
19139	2SC1543	40V, 0,02A, 0,15W, <200/300ns	BC 167, BC 182, BC 237, BC 547, 2N3904
19140	2SC1544	2SC1543, 25V	BC 168, BC 183, BC 238, BC 548, 2N3904
19141	2SC1545(M)	B10000	BC 517, BC 617, BC 875, MPSA 25...29
19142	2SC1546	2SC1545, 25V	BC 517, BC 617, BC 875, MPSA 13...14
19143	2SC1547	30V, 0,02A, 900MHz	BF 377...378, BF 689, BF 763, 2N2857
19144	2SC1548	50V, 5A, PQ23W(260MHz)	BLX 95, 2N6105
19145	2SC1549	150V, 0,05A, 0,75W, 130MHz	BF 297.. 299, BF 422, 2SC3245A, 2SC3248
19146	2SC155	20V, 25mA, 200MHz, B35	BC 122...123, BC 146, BF 254...255
19147	2SC1550	250/250V, 0,1A, 10W, 100MHz	BF 415, BF 417, BF 458...459, 2SC3417
19148	2SC1551	20V, 0,03A, 0,2W, 6,5GHz	BFQ 57...58, BFQ 74, 2SC3276
19149	2SC1552	20V, 0,03A, 0,25W, 4,5GHz	BFQ 71, BFQ 85, BFR 14, BFR 91
19150	2SC1553(A)	20V, 0,03A, 0,175W, 4,5GHz	BFQ 22, BFT 66...67
19151	2SC1554	30V, 0,12A, 0,6W, 4GHz	BFG 34, BFG 96
19152	2SC1555	2SC1554, 1,2W	BFQ 34
19153	2SC1556	PQ>0,13W(500MHz)	BFR 95
19154	2SC1557	40V, 0,18W, PQ>1W(1GHz)	-
19155	2SC1558	15V, 0,08A, 0,25W, 7GHz	2SC2876, 2SC3358, 2SC3603
19156	2SC1559	15V, 0,08A, 0,4W, 7GHz	2SC2876, 2SC3358, 2SC3603
19157	2SC156	2SC155, B50	BC 122...123, BC 146, BF 254...255
19158	2SC1560	25V, 0,07A, 0,58W, 4,5GHz	BFP 96, BFR 96, BFQ 73, 2SC2844
19159	2SC1561	55V, 0,5A, PQ3W(700MHz)	2N4430
19160	2SC1562	55V, 1A, PQ9W(700MHz)	-
19161	2SC1563	55V, 2A, PQ15W(700MHz)	-
19162	2SC1564	55V, 4A, PQ30W(700MHz)	-
19163	2SC1565	150/150V, 0,25A, 10W, 150MHz	BD 524, 2SC2803, 2SC3116
19164	2SC1566	250/250V, 0,1A, 4W, 100MHz	BF 415, BF 417, BF 458...459, 2SC3417
19165	2SC1567	100/100V, 0,5A, 5W, 120MHz	BD 139, BD 230, BD 379, 2SD1177...1178
19166	2SC1567A	2SC1567, 120/120V	2SC2690(A), 2SD1382, 2SD1563
19167	2SC1568	18V, 1A, 4W, 150MHz	BD 135, BD 226, BD 375, 2SD1380
19168	2SC1569	300V, 0,15A, 12,5W, 100MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19169	2SC157	20V, 0,02A, 0,125W, B30	BC 168, BC 183, BC 238, BC 548, 2SD767

19170	2SC1570(NP)	55V, 0,1A, 0,2W, 100MHz	BC 414, BC 550, 2SC2240, 2SC2459
19171	2SC1571(NP)(L)	2SC1570, 40V, L, Ur<65mV	BC 184, BC 413...414, BC 550, 2SC2240
19172	2SC1572	90V, 0,05A, 0,15W, 100MHz	BF 422, BSS 38, BSW 32, BSX 21, 2SC1890
19173	2SC1573(NC)	250/200V, 0,07A, 1W, 80MHz	BF 422A, BF 392...393, 2SC3468...69
19174	2SC1573A	2SC1573, 300/300V	BF 420A, BF 393, 2SC3468...69, 2SC4166
19175	2SC1573B	2SC1573, 400/400V	BF 487, 2SC2267, 2SC3469, 2SC4166
19176	2SC1574	20V, 0,03A, 0,4W, 4,5GHz	BFQ 63
19177	2SC1576	450/330V, 8A, 100W, 10MHz	BUW 24...26, BUX 44, 2SC2625, 2SC4138
19178	2SC1577	500/400V, 8A, 80W, 7MHz	BUW25...26, BUW34...36, 2SC3046, 2SC4138
19179	2SC1578	2SC1577, 600/500V	BUW25...26, BUW35...36, 2SC3046, 2SC4157
19180	2SC1579	500/400V, 15A, 150W, 5MHz	BUW 44...46, BUV 25, BUX 25, 2SD641
19181	2SC158	2SC157, B40	BC 168, BC 183, BC 238, BC 548, 2SD767
19182	2SC1580	2SC1579, 600/500V	BUW 45...46, BUS 13, BUX 48, 2SD641
19183	2SC1581	65V, 7A, PQ50W(30MHz)	-
19184	2SC1582	65V, 13A, PQ100W(30MHz)	-
19185	2SC1584	150/100V, 15A, 150W, 10MHz	MJ 15015, 2N3773, 2SC2607...08, 2SC3264
19186	2SC1585	2SC1584, 200/150V	MJ 15015, 2SC2607...08, 2SC3264, 2SD753
19187	2SC1586	2SC1584, 250/200V	MJ 15022, 2SC3263, 2SD583
19188	2SC1587	45V, 3A, PQ30W(295MHz)	BLX 95, 2N6105
19189	2SC1589	36V, 0,7A, PQ1,5W(225MHz)	-
19190	2SC159	2SC157, B50	BC 168, BC 183, BC 238, BC 548, 2SD767
19191	2SC1590	36V, 1,2A, PQ7W(225MHz)	-
19192	2SC1591	36V, 2,5A, PQ15W(225MHz)	-
19193	2SC1592	30V, 0,1A, 3,5W, 2,7GHz	BFQ 34, BFR 94, 2SC1255
19194	2SC1593	40V, 0,15A, 4,4W, 2GHz	BFQ 34, BFR 94, 2SC1038, 2SC1041
19195	2SC1594	35V, 0,2A, 7W, 2,5GHz	BFT 98, 2SC1039, 2SC1042
19196	2SC1595	35V, 0,3A, 7W, 2,5GHz	BFQ 68, 2SC1043, 2SC1250...1251
19197	2SC1596	130MHz	BF 297...299, BF 422, 2SC3245A, 2SC3248
19198	2SC1597	150V, 0,05A, 0,45W, 130MHz	BF 297...299, BF 422, 2SC3245A, 2SC3248
19199	2SC1598	50V, 0,3A, 6W, >2000GHz	BFQ 68
19200	2SC1599	50V, 0,3A, 6W, >2000GHz	-
19201	2SC16(A)	25V, 0,03A, 0,25W, >100MHz	BC 168, BC 183, BC 238, BC 548
19202	2SC160	2SC157, B60	BC 168, BC 183, BC 238, BC 548, 2SD767
19203	2SC1600	40V, 0,25A, PQ0,7W(1,7GHz)	2SC1253, 2SC1366
19204	2SC1601	35V, 0,1A, 0,2W, 200MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
19205	2SC1602	35V, 0,1A, 0,15W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19206	2SC1603	18V, 0,6A, PQ1,5W(485MHz)	BLW 42, BLW 79, BLX 66, BLY 38
19207	2SC1604	18V, 0,3A, PQ0,35W(485MHz)	BLU 98, MRF 628, 2N6256, 2SC3019
19208	2SC1605(A)	35V, 3,5A, PQ16W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
19209	2SC1606	40V, 0,6A, PQ3W(175MHz)	BLW 17, 2SC1011, 2SC1405
19210	2SC1607	40V, 0,1A, 0,18W	BFX 59
19211	2SC1608	40V, 0,5A, PQ1,6W(470MHz)	BLX 66
19212	2SC1609	<500/2000ns	BD 249D, BUV 10, BUW 57, BUX 10, BUX 40
19213	2SC161	60V, 4A, 50W, 25MHz	BD 245A, BDV 91, 2N4914...15, 2SD895
19214	2SC1610	<500/2000ns	BD 245D, BDX 11, BUW 70, 2N3442

19215	2SC1613(A)	Ara	BF 297...299, BF 422, 2SC3467...68
19216	2SC1614	2SC1613, 180/180V	BF 298...299, BF 422, 2SC3248, 2SC3467
19217	2SC1615	2SC1613, 210/210V	BF 298...299, BF 422, 2SC3467...68
19218	2SC1617	300/100V, 7A, 50W	BU 104, BU 606...608, 2SD1154
19219	2SC1618	80V, 6A, 50W, 10MHz	BD 245B, BD 313, BDX 93, 2N5874, 2SD895
19220	2SC1619	2SC1618, 100V	BD 245C, BDW 21C, BDX 95, 2N5632...34
19221	2SC1619A	2SC1619, 120V	BD 245C, BDX 12, 2N4348, 2N5633...34
19222	2SC162	30V, 0,25A, 0,5W, 500MHz	BFW 16...17, BFX 55, 2N3866
19223	2SC1620(Z)	36V, 0,6A, PQ2,6W(500MHz)	BLX 66
19224	2SC1621	25V, 0,2A, <20/40ns	BSV 52, 2SC3578, 2SC4699K
19225	2SC1622	40V, 0,1A, 110MHz	BC 846...847, BCW 71...72, BCW 81
19226	2SC1622A	2SC1622, 120V	2SC3324, 2SC4050
19227	2SC1623	60V, 0,1A, 250MHz	BC 846, BCV 71...72, 2SC3323
19228	2SC1624	120V, 1A, 15W, 30MHz	BD 941, 2SC2275, 2SD1516, 2SD1562
19229	2SC1625	2SC1624, 100V	BD 239C, BD 939, 2SC2275, 2SD1562
19230	2SC1626	2SC1624, 80V, 0,75A, 100MHz	2SC2275, 2SD1561, BD 239B, BD 937
19231	2SC1627	80V, 0,3A, 0,6W, 100MHz	BC 639, 2SC3665, 2SC4414, 2SD1226
19232	2SC1627A	2SC1627, 0,4A, 0,8W	2SC2235, 2SC3939, 2SD667, 2SD1211
19233	2SC1628	180/150V, 0,05A, 120MHz	BF 460...462, MPSU 10, 2SC2224(A)
19234	2SC1629	90V, 8A, 50W, B>500	2SC1831, 2SC2199, 2SD1831
19235	2SC163	2SC162, 50V	BFW 16...17, BFX 55, 2N3866
19236	2SC1630	100MHz	BF 258...259, 2N5058...59, 2SC3467...68
19237	2SC1631	25V, 0,2A, 0,25W, 140MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
19238	2SC1632	2SC1631, 50V	BC 184, BC 414, BC 550, 2SC2240
19239	2SC1633	25V, 0,2A, 0,25W, 140MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19240	2SC1634	2SC1633, 50V	BC 167, BC 182, BC 237, BC 547, 2SD767
19241	2SC1635(F)	70V, 1A, 0,8W, <35/55ns	BSS 27, BSV 95, 2N3735, 2SC1386
19242	2SC1636	50V, 0,02A, 30MHz	2SC3069, 2SC3615, 2SC3820, 2SD1915
19243	2SC1637	50V, 0,02A, 0,25W, 20MHz	2SC2878, 2SC3114, 2SC3135, (BC 547)
19244	2SC1638	40V, 0,3A, 0,6W, 1,4GHz	2SC1199, 2SC1252, 2SC1365...1366
19245	2SC1639	25V, 0,03A, 0,25W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
19246	2SC164	2SC162, 60V	BFW 16...17, BFX 55, 2N3866
19247	2SC1640	25V, 0,03A, 0,25W, 200MHz	BC 169, BC 184, BC 239, BC 549, 2SC2390
19248	2SC1641	40V, 0,15A, 0,3W, 250MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19249	2SC1642	2SC1641, 25V	BC 168, BC 183, BC 238, BC 548, 2SD767
19250	2SC1643	40V, 0,03A, 0,25W, <200/300ns	BC 237, BC 547, BSW 41, BSY 63, 2N708
19251	2SC1644	2SC1643, 25V	BC 238, BC 548, BSY 62...63, 2N706A
19252	2SC1645(S)	2SC1545	2SC1545
19253	2SC1645(S)	2SC1545	2SC1545
19254	2SC1646	2SC1546	2SC1546
19255	2SC1647	50V, 0,03A, 0,25W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SC1890
19256	2SC1648	2SC1647	BC 414, BC 550, 2SC2240, 2SC2459
19257	2SC1649	2SC1613, 0,25W	2SC1613
19258	2SC165	2SC162, 60V	BFW 16...17, BFX 55, 2N3866
19259	2SC1650	2SC1614, 0,25W	2SC1614



19260	2SC1651(S)	2SC1615, 0,25W	2SC1615
19261	2SC1651(S)	2SC1615, 0,25W	2SC1615
19262	2SC1652(M)	40V, 0,5A, 0,3W, 250MHz	BC 337, BC 635, BC 637, 2SC3377
19263	2SC1653	150/130V, 0,05A, 120MHz	BF 822, BFN 24, 2SC3143, 2SC3360
19264	2SC1654	2SC1653, 180/160V	BF 822, BFN 24, 2SC3143, 2SC3360
19265	2SC1655(A)	16V, 0,03A, 0,15W, 8GHz	BFG 65, BFQ 66, 2SC3267, 2SC3586...87
19266	2SC1656	10V, 0,03A, 0,15W, 7GHz	BFG 65, BFQ 66, 2SC3267, 2SC3586...87
19267	2SC1659	20V, 0,08A, 0,5W, 7GHz	2SC2876, 2SC3358, 2SC3603
19268	2SC166	30V, 0,03A, 0,2W	BC 168, BC 183, BC 238, BC 548
19269	2SC1660	20V, 0,08A, 0,5W, 7GHz	2SC2876, 2SC3358, 2SC3603
19270	2SC1663	140/140V, 0,5A, 7,9W, 50MHz	BF 460...462, MPSU 10, 2SC2224(A)
19271	2SC1664	70V, 6A, 40W, B>500	2SC2315...16, 2SC2491, 2SD1158
19272	2SC1664A	2SC1664, 100V	2SC2198, 2SC2491, 2SC2316
19273	2SC1665	25V, 0,02A, 0,2W, 1,4GHz	BF 689, BFX 62, BFX 89, 2N2857
19274	2SC1666	40V, 0,3A, 0,6W, 700MHz	BFX 55, 2SC1199, 2SC1252, 2SC1365...66
19275	2SC1667	90V, 4A, 50W(Tc75°), 10MHz	BD 245C, BD 313, BDX 95, 2N5758...59
19276	2SC1668	35V, 6A, 40W, 400MHz	BLW 20, BLW 31, 2N6084
19277	2SC1669	150/150V, 1,5A, 25W, 6MHz	2SC2073, 2SD578, 2SD608(A), 2SD1138
19278	2SC167	2SC166, 55V	BC 167, BC 182, BC 237, BC 547
19279	2SC1670	140/140V, 0,5A, 0,75W, 50MHz	2SC2383, 2SC3228, 2SD1812
19280	2SC1672	<500/1000ns	BD 249D, BDW 32, BUW 39, BUW 49
19281	2SC1673	35V, 0,3A, 7W, 2,5GHz	BFQ 68, BFT 99
19282	2SC1674	30V, 20mA, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19283	2SC1675	50V, 30mA, 250MHz	BF 240...241, BF 254...255, BF 594...595
19284	2SC1676	50V, 3A, PQ>10W(270MHz)	BLX 95, 2N6105, 2SC2894
19285	2SC1677	50V, 5A, PQ>19W(270MHz)	-
19286	2SC1678	65V, 3A, PQ>3W(27MHz)	2SC1306, 2SC1909, 2SC1964, 2SC2078
19287	2SC1679	65V, 3A	2SC1306, 2SC1909, 2SC1964, 2SC2078
19288	2SC168	20V, 0,2A, 0,25W, <50/60ns	BSS 11...12, BSY 17...18, 2N2369...69(A)
19289	2SC1680	35V, 2A, PQ8W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
19290	2SC1681	60V, 0,05A, 0,2W, 130MHz	2SC1775(A), 2SC2089, 2SC2240, 2SC2390
19291	2SC1682	2SC1681, 40V	BC 184, BC 414, BC 550, 2SC2390
19292	2SC1683(A)	200V, 0,5A, 30W, 6MHz	BD 239F, 2SC2238B, 2SC2660, 2SD1138
19293	2SC1684(NC)	150MHz	BC 168, BC 183, BC 238, BC 548, 2SC2675
19294	2SC1685(NC)	2SC1684, 60V	BC 174, BC 182, BC 190, BC 546, 2SC2675
19295	2SC1686	40V, 25mA, 0,25W, 330MHz	BF 198...199, BF 224...225, BF 596...597
19296	2SC1687	40V, 30mA, 0,4W, 550MHz	BF 198...199, BF 224...225, BF 596...597
19297	2SC1688	2SC1687, 50V	BF 198...199, BF 224...225, BF 596...597
19298	2SC1689	55V, 3A, PQ26W(220MHz)	BLX 95, 2N6105
19299	2SC169	2SC168, 40V, <40/44ns	BSS 11, BSX 19...20, 2N2369...69(A)
19300	2SC1698	210V, 10A, 125W, B>1000	BUW 28, BUW 67, 2SD1027, 2SD1515
19301	2SC17(A)	25V, 0,05A, 0,25W, 150MHz	BC 168, BC 183, BC 238, BC 548
19302	2SC170	25V, 0,05A, 0,11W, 250MHz	BF 240...241, BF 254...255, BF 594...595
19303	2SC1703	600V, 15A, 150W, B>100	BUT 51, MJ 10008...9, 2SD 683, 2SD606
19304	2SC1706(H)	200V, 0,05A, 0,2W, 60MHz	BF 298...299, BF 422, 2SC3467...68



19305	2SC1707(H)	40V, 0,1A, 0,2W, >100MHz	BC 167, BC 183, BC 238, BC 548, 2SD767
19306	2SC1707A(AH)	2SC1707, 70V	BC 174, BC 182, BC 190, BC 546, 2SC2240
19307	2SC1708	90V, 0,05A, 0,2W, 150MHz	2SC1775(A), 2SC1845, 2SC2240, 2SC2459
19308	2SC1708	90V, 0,05A, 0,2W, 150MHz	2SC1775(A), 2SC1845, 2SC2240, 2SC2459
19309	2SC1708A	2SC1708, 120V	2SC1775A, 2SC1845, 2SC2240, 2SC2459
19310	2SC1708A	2SC1708, 120V	2SC1775A, 2SC1845, 2SC2240, 2SC2459
19311	2SC1709	30V, 0,3A, 0,3W, -/125ns	BSW 41, BSX 48, BSY 63, 2N708, 2N914
19312	2SC171	2SC170, 0,2W	BF 240...241, BF 254...255, BF 594...595
19313	2SC1710	15V, 0,13A, 1W, 7GHz	-
19314	2SC1711(A)	20V, 0,03A, 0,2W, 7,5GHz	BFG 65, BFQ 66, 2SC1655...56, 2SC3276
19315	2SC1712	16V, 0,03A, 0,2W, 8GHz	BFG 65, BFQ 66, 2SC1655...56, 2SC3276
19316	2SC1717	40V, 1A, PQ2,2W(220MHz)	-
19317	2SC1718	35V, 4,5A, PQ14W(220MHz)	MRF 209
19318	2SC1719	150/120V, 0,05A, 1W, 130MHz	2SC2631...32, 2SC3245A, 2SC3248, 2SC3467
19319	2SC172(A)	350MHz	BF 198...199, BF 224...225, BF 505
19320	2SC1720	2SC1719, 150/150V	2SC2631...32, 2SC3245A, 2SC3248, 2SC3467
19321	2SC1721	80V, 1A, 0,5W, >100MHz	BC 639, 2SD667, 2SD1226, 2SD1768
19322	2SC1722	300V, 0,2A, 12,5W, 80MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19323	2SC1723	2SC1722, 15W, 60MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19324	2SC1724	35V, 0,8A, PQ4W(470MHz)	BLW 43, BLW 80, 2N5945
19325	2SC1725	35V, 1,4A, PQ7W(470MHz)	BLU 97, BLW 14, BLX 68, BLY 53
19326	2SC1726	35V, 2,8A, PQ13W(470MHz)	BLW 15, BLX 69, 2SC1338, 2SC1404
19327	2SC1727	700MHz	BF 314, BF 502, BF 505, BF 507, BF 959
19328	2SC1728	100V, 1A, 7,9W, 80MHz	BD 419, BD 529, 2SC2384
19329	2SC1729	35, 3,5A, PQ16W(175MHz)	-
19330	2SC173	15V, 5mA, 0,03W, 20MHz	-
19331	2SC1730	30V, 0,05A, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
19332	2SC1734(H)	40V, 0,03A, 0,1W, 300MHz	BC 184, BC 414, BC 550, 2SC2390
19333	2SC1735	100V, 0,5A, 0,8W, 130MHz	BC 639, 2SC3665, 2SD667(A), 2SD1616A
19334	2SC1735	100V, 0,5A, 0,8W, 130MHz	BC 639, 2SC3665, 2SD667(A), 2SD1616A
19335	2SC1736	50V, 0,1A, 0,3W, 300MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19336	2SC1737	2SC1736, 35V	BC 168, BC 183, BC 238, BC 548, 2SD767
19337	2SC1738	2SC1636, 35V	BC 169, BC 184, BC 239, BC 549, 2SC2675
19338	2SC1739	20V, 32mA, 0,25W, 300MHz	BC 183, BC 238, BC 548, BF 254...255
19339	2SC174	30V, 25mA, 0,2W, 170MHz	BF 240...241, BF 254...255, BF 594...595
19340	2SC1740(S)	50V, 0,1A, 0,3W, 180MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19341	2SC1740(S)	50V, 0,1A, 0,3W, 180MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19342	2SC1740LN(SLN)	2SC1740	BC 184, BC 414, BC 550, 2SC2677...75
19343	2SC1741(S)	2SC1652	2SC1652
19344	2SC1741(S)	2SC1652	2SC1652
19345	2SC1741A(AS)	2SC1652, 50V, 0,4W	2SC1652
19346	2SC1741A(AS)	2SC1652, 50V, 0,4W	2SC1652
19347	2SC1742	20V, 0,03A, 0,15W, 6,5GHz	BFQ 57...58, BFQ 74, 2SC1655...1656
19348	2SC1743	20V, 0,03A, 0,175W, 4,5GHz	BFQ 71, BFT 75, 2SC1119, 2SC1336
19349	2SC1744	35V, 10A, PQ44W(175MHz)	-

19350	2SC1745	60V, 0,05A, 0,15W, 140MHz	2SC1775(A), 2SC2088...2089, 2SC2240
19351	2SC1746(A)	2SC1745, 50V	BC 414, BC 550, 2SC2088...89, 2SC2240
19352	2SC1747	40V, 0,1A, 0,3W, >1400MHz	BFX 59
19353	2SC1748	300/300V, 0,1A, 0,8W, 50MHz	BF 259, BFR 59, BFS 89, 2N5058, 2SC3468
19354	2SC1749	300/220V, 0,1A, 10W, 90MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19355	2SC174A	2SC174, 60V	BF 240...241, BF 254...255, BF 594...595
19356	2SC175	15V, 5mA, 0,03W, 10MHz	-
19357	2SC1752	MPSA 42	MPSA 42
19358	2SC1753	MPSA 43	MPSA 43
19359	2SC1754	2N6426	2N6426
19360	2SC1755	300/300V, 0,2A, >50MHz	2SC1505...1507, 2SC1905
19361	2SC1756	2SC1755	2SC1505...1507, 2SC1905
19362	2SC1757	2SC1755	2SC1505...1507, 2SC1905
19363	2SC1758	300/300V, 0,1A, 10W, 80MHz	BF 382, MPSU 10, BF 617, BF 859
19364	2SC176	15V, 5mA, 0,03W, 10MHz	-
19365	2SC1760	100V, 1A, 7,9W, 80MHz	2SC2275(A), 2SC2483, BD 419, BD 529
19366	2SC1761	20V, 2A, 80MHz	2SC1173, 2SC1226, 2SC1398, 2SC1848
19367	2SC1762-1	700/400V, 0,3A, 0,47W, 13MHz	2N5012...5015, 2SD594
19368	2SC1762-2	2SC1762-1, 800/450V	2N5012...5015, 2SD594
19369	2SC1763	65V, 7A, PEP40W(30MHz)	-
19370	2SC1764	65V, 12A, PEP80W(28MHz)	MRF 463...464
19371	2SC1765	35V, 0,8A, PQ3,2W(470MHz)	-
19372	2SC1766	30V, 0,1A, 0,31W, 230MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19373	2SC1768	200V, 5A, 50W, B>400	2SC1829, 2SD1090
19374	2SC1769	30V, 0,05A, 0,2W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
19375	2SC177	15V, 5mA, 0,03W, 10MHz	-
19376	2SC1770	30V, 0,2A, 0,3W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19377	2SC1771	60V, 0,2A, 0,3W, 100MHz	BC 174, BC 182, BC 190, BC 546, 2SC1815
19378	2SC1772	95V, 0,05A, 0,3W, 40MHz	2SC1890(A), 2SC2240, 2SC2363, 2SC2674
19379	2SC1773	30V, 0,4A, 0,5W, 100MHz	BC 337...338, BC 635, BC 637, 2SC3377
19380	2SC1774	2SC1773, 60V	BC 337A, BC 637, BC 639, 2SD1226
19381	2SC1775	90V, 0,05A, 0,3W, 200MHz	2SC2088...89, 2SC2240, 2SC2362, 2SC2389
19382	2SC1775A	2SC1775, 120V	2SC2088, 2SC2240, 2SC2362, 2SC2389
19383	2SC1776	60V, 0,25A, 0,3W, 220MHz	BC 174, BC 182, BC 190, BC 546, 2N3904
19384	2SC1777	70V, 6A, 50W, 10MHz	BD 245A, BDV 93, BDX 93, 2N5874
19385	2SC1778	25V, 15mA, 650MHz	BF 377...378, BF 689K, BF 763, 2N2857
19386	2SC1779(A,B)	30V, 20mA, 675MHz	BF 377...378, BF 689K, BF 763, 2N2857
19387	2SC178	15V, 5mA, 0,03W, 20MHz	-
19388	2SC1780	25V, 15mA, 0,15W, 3GHz	BFR 15, BFS 55, BFT 66...67, BFW 99
19389	2SC1781(H)	70V, 0,5A, 0,35W, 150MHz	BC 639, 2N2221A...22A, 2SC4414, 2SD1226
19390	2SC1782	140/80V, 10A, 100W, 10MHz	BD 245D, BDX 11, 2N3442, 2SC2706
19391	2SC1783	2SC1782, 180/120V	BD 245E, BDW 14, 2SC3263, 2SD555
19392	2SC1784	150/150V, 15A, 100W, -/3,1μs	BDW 12, BUX 41, 2SD552, 2SD1047
19393	2SC1785	2SC1784, 200/200V	BDW 16, BUX 41, 2SC3263...64, 2SD552
19394	2SC1786	2SC1784, 230/230V	BUX 41, 2SC1586, 2SC3263...64, 2SD583

19395	2SC1787	35V, 0,03A, 0,15W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2390
19396	2SC1788(A)	25V, 0,5A, 0,6W, 150MHz	BC 337...338, BC 635, BC 637, BC 639
19397	2SC1789	25V, 50mA, 0,4W, >600MHz	BF 377...378, BF 689K, BF 763, 2N2857
19398	2SC179	25V, 0,4A, 0,12W, 3MHz	ASY 73...75
19399	2SC1790	25V, 15mA, 0,15W, 3GHz	BFR 15, BFS 55, BFT 66...67, BFW 99
19400	2SC1791	45V, 1A, PQ6W(1GHz)	-
19401	2SC1792	45V, 2A, PQ10W(1GHz)	-
19402	2SC1793	45V, 4A, 42W, >300MHz	BLW 75, MRF 314A, 2N5642
19403	2SC1797	50V, 0,3A, PQ1,6W(2GHz)	-
19404	2SC1798	50V, 1A, PQ3,1W(2GHz)	-
19405	2SC1799	50V, 2A, PQ6,3W(2GHz)	-
19406	2SC18	25V, 0,03A, 0,25W	BC 168, BC 183, BC 238, BC 548
19407	2SC180	2SC179, 5MHz	ASY 73...75
19408	2SC1800	50V, 3A, PQ>10W(2GHz)	-
19409	2SC1801	30V, 0,03A, 1300MHz	BF 377...378, BF 689K, BF 763, 2N2857
19410	2SC1802	30V, 0,02A, 700MHz	BF 377...378, BF 689K, BF 763, 2N2857
19411	2SC1803	30V, 0,13A, 0,58W, 2,7GHz	BFG 34
19412	2SC1804	47V, 1A, PQ4,5W(770MHz)	-
19413	2SC1805	45V, 2A, PQ12W(700MHz)	-
19414	2SC1806	45V, 4A, PQ26W(700MHz)	-
19415	2SC1807(TX)	18V, 0,1A, PQ25mW(485MHz)	BFX 59
19416	2SC1808	35V, 1A, PQ3,5W(485MHz)	BLW 43, BLW 80
19417	2SC1809(S)	25V, 20mA, 500MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19418	2SC1809(S)	25V, 20mA, 500MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19419	2SC181	2SC179, 10MHz	ASY 73...75
19420	2SC1810	700/300V, 0,3A, 7,9W	2SC3184, 2SD1527
19421	2SC1811(-1,-2)	140MHz	BF 298...299, BF 422(A), 2SC3468
19422	2SC1812	22V, 0,02A, 1100MHz	2SC2144, 2SC2353, 2SC2464, 2SC2466
19423	2SC1813	50V, 0,5A, 0,5W, 100MHz	BC 337, BC 635, BC 637, 2SC4414
19424	2SC1815	60V, 0,15A, 0,4W, >80MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
19425	2SC1815L	2SC1815	BC 550, 2SC2240, 2SC2674...75, 2SC3378
19426	2SC1816	100V, 4A, PQ6W(27MHz)	2SC1306, 2SC1909, 2SC2043, 2SC2092
19427	2SC1816H	2SC1816, hi-rel, 200V	-
19428	2SC1817	45V, 5A, PQ21W(27MHz)	-
19429	2SC1818	130V, 7A, 100W, 7MHz	2SC2260...2262, 2SD551, 2SD731...732
19430	2SC1819	300/300V, 0,1A, 15W, 100MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19431	2SC182	25V, 0,15A, 0,15W, 90MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19432	2SC1820	55V, 0,5A, PQ1,6W(175MHz)	BFS 23, BFW 47, BLY 34, 2N3553, 2N5160
19433	2SC1821	55V, 0,5A, PQ4W(470MHz)	BLW 90, 2SC2892
19434	2SC1822	55V, 1A, PQ7,5W(470MHz)	BLX 93, 2SC1040, 2SC2700
19435	2SC1823	55V, 2A, PQ15W(470MHz)	BLW 94, BLX 94, MRF 323, 2SC1118
19436	2SC1824	55V, 4A, PQ30W(470MHz)	BLX 95, 2N6105
19437	2SC1825	55V, 8A, PQ55W(470MHz)	2N6439, 2SC2796
19438	2SC1826	80V, 4A, 30W, 10MHz	BD 243B, BD 537, BD 539B, BD 951
19439	2SC1827	2SC1826, 100V	BD 243C, BD 539C, BD 953, 2SD712

19440	2SC1828	800/400V, 1A, 40W, 7MHz	BUV 36, BUX 84...85, 2SC3149, 2SC3352
19441	2SC1829	200/150V, 5A, 100W, B>400	2SD1090
19442	2SC183(A)	150MHz	BF 240...241, BF 254...255, BF 594...595
19443	2SC1830	140/140V, 15A, 150W, B>500	2SD710
19444	2SC1831	90V, 8A, 100W, B>500	2SD1831
19445	2SC1832	500/400V, 15A, 150W, B>100	BU 932, 2SD711(A), 2SD572...573, 2SD683
19446	2SC1833	60V, 0,2A, 0,3W, 300MHz	BC 182, BC 546, BSV 59, 2N2221...22(A)
19447	2SC1834	60V, 0,2A, 0,3W, <20/40ns	-
19448	2SC1836	25V, 5A, 30W, 500MHz	BLW 20, BLW 31, 2N6084
19449	2SC1837(Z)	35V, 0,6A, PQ1W(2GHz)	-
19450	2SC1838(Z)	35V, 1,5A, PQ3W(2GHz)	-
19451	2SC184	20V, 0,03A, 0,1W, 200MHz	BF 240...241, BF 254...255, BF 594...595
19452	2SC1840	40V, 0,1A, 0,5W, 100MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19453	2SC1841	110MHz	2SC1890A, 2SC2363, 2SC2240, 2SC2459
19454	2SC1842	40V, 0,1A, 0,25W, 250MHz	BC 184, BC 413...414, BC 550, 2SC2240
19455	2SC1843	2SC1842, 60V, 100MHz	BC 414, BC 550, 2SC2240, 2SC2459
19456	2SC1844	60V, 0,1A, 0,5W, 100MHz	BC 414, BC 550, 2SC2240, 2SC2459
19457	2SC1845	120V, 0,05A, 0,5W, 110MHz	2SC1775A, 2SC1845, 2SC2240, 2SC2459
19458	2SC1846	45V, 1A, 5W, 200MHz	BD 135, BD 226, BD 375, 2SD1378
19459	2SC1847	50V, 1,5A, 5W, 150MHz	BD 137, BD 228, BD 377, 2SD794(A)
19460	2SC1848	70V, 2A, 10W, 150MHz	2SC1398, 2SC2528, 2SC3252
19461	2SC1849	30V, 0,1A, 0,35W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19462	2SC185	2SC184, 250MHz	BF 240...241, BF 254...255, BF 594...595
19463	2SC1850	2SC1849, 60V	BC 174, BC 182, BC 190, BC 546, 2SD767
19464	2SC1851	30V, 0,5A, 0,625W, 200MHz	BC 337...338, BC 635, BC 637, 2SC3377
19465	2SC1852	2SC1851, 60V	BC 337A, BC 637, BC 639, 2SD1226
19466	2SC1853	30V, 0,03A, 230MHz	BF 240...241, BF 254...255, BF 594...595
19467	2SC1854	30V, 0,05A, 0,25W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
19468	2SC1855	20V, 0,02A, 550MHz	BF 198, BF 225, BF 310, BF 367, BF 596
19469	2SC1856	20V, 0,02A, 550MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19470	2SC1857	300/300V, 0,1A, 0,8W, 80MHz	BF 259, BFR 59, BFS 89, 2N5058, 2SC3468
19471	2SC1859(-1,-2)	25V, 1,5A, 0,5W, 140MHz	2SC2236, 2SD773, 2SD787...788, 2SD1051
19472	2SC186	B40	BF 240...241, BF 254...255, BF 594...595
19473	2SC1860	150/100V, 2A, 12,5W(Tc25°)	BUX 49...54, BUY 41
19474	2SC1861	2SC1860, 300/250V	BUX 52...54, BUY 61...62
19475	2SC1862	2SC1860, 450/400V	BUX 54, BUY 61...62
19476	2SC1863	<1000/3000ns	BUX 60...61, MJE 15030, 2SC4329
19477	2SC1864(A)	2SC1863, 300V	TIP 150, 2SC2200, 2SC3039, 2SC4106
19478	2SC1865	2SC1863, 450/400V	MJE 13006, 2SC2200, 2SC3039, 2SC4106
19479	2SC1866	<1000/3000ns	BUX 18(A...C), TIP 55A...58A, 2SC3041
19480	2SC1867(A)	2SC1866, 300/250(A300/300)V	BUX 18A...C, TIP 55A...58A, 2SC3041
19481	2SC1868	2SC1866, 450/400V	BUX 18C, TIP 57A...58A, 2SC3040...41
19482	2SC1869	<1000/3000ns	BUW 24...26, BUX 17(A...C), 2SC3520
19483	2SC187	2SC186, B50	BF 240...241, BF 254...255, BF 594...595
19484	2SC1870	2SC1869, 300/250V	BUW 24...26, BUX 17A...C, 2SC3520

19485	2SC1871	2SC1869, 450/400V, >10MHz	BUW 24...26, BUX 17C, 2SC3520, 2SC4140
19486	2SC1871A	2SC1869, 500/400V	BUW 24...26, BUX 17C, 2SC3520, 2SC4140
19487	2SC1872	<1000/3000ns	2SC2128, 2SC2940, 2SC3224, 2SD540...541
19488	2SC1873	2SC1872, 300/250V	2SC1299, 2SC1302, 2SC1401, 2SD643
19489	2SC1874	2SC1872, 450/400V	2SC1300, 2SC1470, 2SC2250, 2SD644
19490	2SC1875	1500/500V, 3,5A, 50W	BU 208...209, BU 706, 2SD819, 2SD850
19491	2SC1876(H)	100V, 0,5A, 0,8W, B>2000	BSS 52, 2SD406, 2SD688
19492	2SC1879(H)	120/120V, 2A, 0,8W, B>1000	2SD615
19493	2SC188	40V, 0,5A, 0,6W, 150MHz	BC 140...141, BC 300...302, 2N2218...19
19494	2SC1880(K)	2SC1879, 15W	BDW 53D, BDW 63D, 2SD1147
19495	2SC1881(K)	60V, 3A, 30W, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
19496	2SC1882(H)	120/120V, 5A, 0,8W, B5000	2SC2165
19497	2SC1883(K)	120/120V, 5A, 30W, B>1000	BD 651, BDW 63D, BDW 73D, 2SD1147
19498	2SC1884(H)	120/120V, 8A, 40W, B>1000	BD 651, BDT 63C, BDW 73D, BDX 33D
19499	2SC1885(NC)	150V, 0,05A, 0,75W, 200MHz	2SC2362K, 2SC2631...2632, 2SC3800
19500	2SC1886	30V, 0,05A, 1000MHz	BF 377...378, BF 689K, BF 763, 2N2857
19501	2SC1887	2SC1886, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
19502	2SC1888	80V, 3A, 0,8W, B1000	2SC1983, 2SC3852, 2SD1157, 2SD1943
19503	2SC1889	2SC1888, 100V	2SD1259A, 2SD1273A, 2SD2092, 2SD2156A
19504	2SC189	60V, 0,5A, 0,6W, 150MHz	BC 140...141, BC 300...302, 2N2218...19
19505	2SC1890	90V, 0,05A, 0,3W, 200MHz	2SC2088...89, 2SC2240, 2SC2362, 2SC2389
19506	2SC1890A	2SC1890, 120V	2SC2088, 2SC2240, 2SC2362, 2SC2389
19507	2SC1891	1200/400V, 1,5A, 50W, 3MHz	BU 204...206, BU 705, 2SC1922, 2SD818
19508	2SC1892	1500/500V, 2,5A, 50W, 3MHz	BU 205...206, BU 705, 2SC1922, 2SD818
19509	2SC1893	1500/500V, 3,5A, 50W, 3MHz	BU 208...209, BU 706, 2SD819, 2SD850
19510	2SC1894	1500/600V, 5A, 50W, 3MHz	BU 208(A), BU 508A, 2SC2928, 2SD820
19511	2SC1895	1500/600V, 6A, 50W, 2MHz	BU 508A, 2SC3486, 2SD649, 2SD821
19512	2SC1896	1500/600V, 7A, 50W, 2MHz	BU 508A, 2SC3686, 2SD822, 2SD1016
19513	2SC1897	30V, 1A, 0,6W, 200MHz	BC 337...337, BC 635, BC 637, 2SD1225
19514	2SC1898	30V, 0,03A, 500MHz	BF 198...199, BF 224...225, BF 596...597
19515	2SC1899	30V, 0,02A, 500MHz	BF 198...199, BF 224...225, BF 596...597
19516	2SC19	40V, 0,4A, 0,6W, >70MHz	BC 140...141, BC 300...302, 2N3053
19517	2SC190	60V, 0,5A, 0,6W, 180MHz	BC 140...141, BC 300...302, 2N2218...19
19518	2SC1900	120/120V, 0,05A, 0,3W, 90MHz	BF 297...299, BSS 38, 2SC2240, 2SD756
19519	2SC1901	25V, 0,02A, 0,6W, 1,4GHz	BFR 37, BFW 30, BFX 73, BFX 89
19520	2SC1902	40V, 0,3A, 0,6W, 650MHz	BFX 55, 2SC1199, 2SC1252, 2SC1365...66
19521	2SC1903	150/120V, 0,05A, 130MHz	BF 415, BF 457, BF 469, 2SD1609
19522	2SC1904	2SC1903, 150/150V	BF 415, BF 457, BF 469, 2SD1609
19523	2SC1905	350/300V, 0,2A, 15W	2SC1929, 2SC4714
19524	2SC1906	30V, 50mA, 1000MHz	BF 377...378, BF 689K, BF 763, 2N2857
19525	2SC1907	30V, 50mA, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
19526	2SC1908	30V, 0,03A, 200MHz	BF 240...241, BF 254...255, BF 594...595
19527	2SC1909	75V, 3A, PQ5,5W(27MHz)	2SC1306, 2SC1816, 2SC2092
19528	2SC191	60V, 0,01A, 0,25W, 50MHz	BF 240...241, BF 254...255, BF 594...595
19529	2SC1913	150/150V, 1A, 15W, 120MHz	2SC2238(A), 2SC2344, 2SC2592, 2SD608(A)



19530	2SC1913A	2SC1913, 180/180V	2SC2238A,B, 2SC2344, 2SC2592, 2SD608A
19531	2SC1914	90/90V, 0,05A, 0,2W, 150MHz	2SC1890(A), 2SC2240, 2SC2363, 2SD756
19532	2SC1914	90/90V, 0,05A, 0,2W, 150MHz	2SC1890(A), 2SC2240, 2SC2363, 2SD756
19533	2SC1914A	2SC1914, 120/120V	2SC1890A, 2SC2240, 2SC2363, 2SD756(A)
19534	2SC1914A	2SC1914, 120/120V	2SC1890A, 2SC2240, 2SC2363, 2SD756(A)
19535	2SC1915	200MHz	BSS 38, 2SC1890A, 2SC2240, 2SC2363
19536	2SC1915	200MHz	BSS 38, 2SC1890A, 2SC2240, 2SC2363
19537	2SC1916	50V, 0,1A, 0,2W, 150MHz	BC 184, BC 414, BC 550, 2SC2240
19538	2SC1916	50V, 0,1A, 0,2W, 150MHz	BC 184, BC 414, BC 550, 2SC2240
19539	2SC1917	2SC1916, 35V	BC 169, BC 184, BC 239, BC 549, 2SC2390
19540	2SC1917	2SC1916, 35V	BC 169, BC 184, BC 239, BC 549, 2SC2390
19541	2SC1918	35V, 0,1A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19542	2SC1918	35V, 0,1A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19543	2SC1919	50V, 0,03A, 0,2W, 150MHz	BC 184, BC 414, BC 550, 2SC2240
19544	2SC1919	50V, 0,03A, 0,2W, 150MHz	BC 184, BC 414, BC 550, 2SC2240
19545	2SC192	2SC191, 10MHz	BF 240...241, BF 254...255, BF 594...595
19546	2SC1921	130MHz	BF 298...299, BF 422(A), 2SC3468
19547	2SC1922	1500/800V, 2,5A, 50W, 5MHz	BU 205...206, BU 705, 2SC3483, 2SD818
19548	2SC1923	550MHz	BF 241, BF 255, BF 314, BF 502, BF 505
19549	2SC1928	50V, 0,05A, 0,315W, 140MHz	BC 167, BC 182, BC 237, BC 547, 2SC1890
19550	2SC1929	300/300V, 0,4A, 25W, 80MHz	BU W 40(A,B), 2SC1263(A), 2SC2022
19551	2SC193	2SC191, 30MHz	BF 240...241, BF 254...255, BF 594...595
19552	2SC1930(A,F,AF)	16V, 0,03A, 0,15W, 8GHz	2SC1655...56, 2SC3276, 2SC3586...87
19553	2SC1935(F)	15V, 0,03A, 0,25W, 6GHz	BFQ 57...58, BFQ 74
19554	2SC1935(F)	15V, 0,03A, 0,25W, 6GHz	BFQ 57...58, BFQ 74
19555	2SC1937(F)	15V, 0,07A, 0,3W, 6GHz	BFQ 82, 2SC2876
19556	2SC194	2SC191	BF 240...241, BF 254...255, BF 594...595
19557	2SC1940	120/120V, 0,05A, 1W, 120MHz	2SC2362...63, 2SC2631...32, 2SD2030
19558	2SC1941	2SC1940, 160/160V	2SC2631...32, 2SC3248, 2SD2030...31
19559	2SC1942	1500/800V, 3A, 50W, 5MHz	BU 208...209, BU 705(A), 2SD819, 2SD850
19560	2SC1943	35V, 0,4A, PQ0,4W(470MHz)	BLU 98, MRF 627...628, 2N6256, 2SC3019
19561	2SC1944	80V, 6A, PQ16W(27MHz)	2SC1817, 2SC1969, 2SC2050, 2SC2098
19562	2SC1945	2SC1944	2SC3133
19563	2SC1946	35V, 7A, PQ32W(175MHz)	-
19564	2SC1946A	2SC1946, PQ35W(175MHz)	-
19565	2SC1947	35V, 1A, PQ4W(175MHz)	BFS 22, BFW 46, MRF 237, 2N3924
19566	2SC1948	15V, 0,02A, 0,15W, 8GHz	BFQ 77, 2SC1655...56, 2SC1923, 2SC3276
19567	2SC1949	30V, 0,13A, 0,58W, 2,7GHz	BFG 34, BFG 96
19568	2SC195	2SC191, 30V, 10MHz	BF 240...241, BF 254...255, BF 594...595
19569	2SC1951	140MHz	BSS 38, 2SC2240, 2SC2459, 2SC3245(A)
19570	2SC1952	45V, 0,3A, 0,8W, 2GHz	2SC1253, 2SC1366
19571	2SC1953	150/150V, 0,05A, 200MHz	BF 415, BF 457, BF 469, 2SD1609
19572	2SC1954	25V, 0,15A, 0,45W, 1,5GHz	2SC2408, 2SC4693
19573	2SC1955	35V, 0,8A, PQ3,2W(175MHz)	BFS 22, BFW 46, MRF 237, 2N3924
19574	2SC1956	35V, 3,5A, PQ17W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082



19575	2SC1957	75V, 1A, PQ1,8W(27MHz)	2SSC2091, 2SC2314
19576	2SC1959	35V, 0,5A, 0,5W, 300MHz	BC 337...338, BC 635, BC 637, 2SC3377
19577	2SC196	2SC191, 30V, 30MHz	BF 240...241, BF 254...255, BF 594...595
19578	2SC1960	20V, 0,2A, 0,3W, -/15ns	BSS 11...12, BSY 17...18, 2N2368...69(A)
19579	2SC1961	35V, 25mA	BF 240...241, BF 254...255, BF 594...595
19580	2SC1962	200/200V, 0,5A, 45MHz	BF 381...382, BF 460...462, MPSU 10
19581	2SC1964	80V, 3,5A, PQ3,4W(27MHz)	2SC1678...79, 2SC2075, 2SC2078
19582	2SC1965(A)	PQ6,5W(175MHz)	-
19583	2SC1966	35V, 1A, PQ3,5W(470MHz)	2SC3020
19584	2SC1967	35V, 2A, PQ8W(470MHz)	2SC2992, 2SC3021
19585	2SC1968(A)	35V, 5A, PQ16W(470MHz)	2SC3022
19586	2SC1969	60V, 6A, PQ16W(27MHz)	2SC1944, 2SC2050, 2SC2098
19587	2SC197	2SC191, 30V	BF 240...241, BF 254...255, BF 594...595
19588	2SC1970	40V, 0,6A, PQ1,3W(175MHz)	-
19589	2SC1971	35V, 2A, PQ7W(175MHz)	-
19590	2SC1972	35V, 3,5A, PQ15W(175MHz)	-
19591	2SC1973	50V, 0,5A, PQ1W(50MHz)	MRF 229...239
19592	2SC1974	80V, 2A, PQ5W(50MHz)	-
19593	2SC1975	120V, 2A, PQ3,8W(50MHz)	-
19594	2SC1976	36V, 0,5A, PQ>0,6W(175MHz)	BRF 98, MRF 207, MRF 225, MRF 607
19595	2SC1977	36V, 1A, PQ>2W(175MHz)	-
19596	2SC1978	36V, 1,5A, PQ>7W(175MHz)	-
19597	2SC198(A)	50V, 0,5A, 0,8W, 350MHz	BFS 23, BFX 55, BLY 34, 2SC2852
19598	2SC1980	120V, 0,02A, 0,25W, 200MHz	2SC2088, 2SC2240, 2SC2362, 2SC2389
19599	2SC1981	50V, 0,1A, 0,3W, 30MHz	2SC3069, 2SC3615, 2SC3820, 2SC3836
19600	2SC1982(S)	140/140V, 1A, 0,625W, 120MHz	BSS 43, BSW 68, 2N3019...20, 2SC1860
19601	2SC1983	80V, 3A, 30W, B700	2SD1157, 2SD1943
19602	2SC1984	2SC1983, 100V	2SC2316, 2SC2491
19603	2SC1985	80V, 6A, 40W, 10MHz	BD 243B, BD 543B, BD 809, 2SC3254
19604	2SC1986	2SC1985, 100V	BD 243C, BD 543C, BD 801, 2SD613
19605	2SC1987	300/90V, 6A, 50W, 12MHz	BU 406...408, 2SD884...885, 2SD1163
19606	2SC1988	25V, 0,07A, 0,35W, 4,5GHz	BFQ 63, 2SC2570, 2SC3037
19607	2SC1989	30V, 0,03A, 300MHz	BF 240...241, BF 254...255, BF 594...595
19608	2SC199	80V, 0,05A, 0,6W, 130MHz	BC 140...141, BC 300...301, BSW 39
19609	2SC1990	30V, 15mA, 650MHz	BF 198...199, BF 224...225, BF 596...597
19610	2SC1991	60V, 0,1A, 0,625W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
19611	2SC1992	50V, 0,1A, 0,3W, 300MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19612	2SC1993	30V, 0,1A, 0,3W, 300MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
19613	2SC1994	45V, 0,1A, 0,3W, 300MHz	BC 184, BC 413...414, BC 550, 2SC2240
19614	2SC1995	2SC1994, 50V	BC 414, BC 550, 2SC2240, 2SC2390
19615	2SC1996	50V, 0,8A, 0,625, 100MHz	BC 337, BC 637, BC 639, 2SD667, 2SD1226
19616	2SC1997	2SC1997, 30V	BC 337...338, BC 635, BC 637, 2SD1225
19617	2SC1998	80V, 0,1A, 0,5W, 300MHz	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
19618	2SC1999	2SC1998, 50V	BC 167, BC 182, BC 237, BC 547, 2SD767
19619	2SC20	40V, 0,4A, 0,6W, 90MHz	BC 140...141, BC 300...302, 2N3053

19620	2SC200	40V, 0,3A, 0,65W, 350MHz	BFS 23, BFX 55, BLY 34, 2SC2852
19621	2SC2000	60V, 0,2A, 0,6W, 70MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
19622	2SC2001	30V, 0,7A, 0,6W, 170MHz	BC 337...338, BC 635, BC 637, 2SD1225
19623	2SC2002	60V, 0,3A, 0,6W, 140MHz	BC 337A, 2SC1627, 2SC3939, 2SC4414
19624	2SC2003	2SC2002, 80V	BC 639, 2SC1627, 2SC3939, 2SC4414
19625	2SC2008	35V, 0,1A, 560MHz	BF 370, BF 920...921S, BF 959
19626	2SC2009	35V, 0,1A, 550MHz	BF 370, BF 920...921S, BF 959
19627	2SC201	2SC200, 20V	BFS 23, BFX 55, BLY 34, 2SC2852
19628	2SC2010	35V, 0,03A, 400MHz	BF 198...199, BF 224...225, BF 596...597
19629	2SC2011	30V, 0,05A, 630MHz	BF 198, BF 225, BF 310, BF 314, BF 505
19630	2SC2012	30V, 0,03A, 0,5W, 200MHz	BF 240...241, BF 254...255, BF 594...595
19631	2SC2013	35V, 25mA, 700MHz	BF 225, BF 314, BF 502, BF 505, BF 507
19632	2SC2014	100V, 0,2A, 0,5W, 100MHz	2SC2240, 2SC2459, 2SC2345(A), 2SC3248
19633	2SC2017	450/400V, 10A, 100W, >10MHz	BUW 24...26, BUW 72, BUX 14, 2SC3520
19634	2SC2018	300/300V, 15A, 100W, >10MHz	BUX 13, BUY 50, MJ15024, 2SC2307
19635	2SC2019	200/200V, 15A, 100W, >10MHz	BUX 41, 2SC2944, 2SD552, 2SD583
19636	2SC202	2SC200, 80V	-
19637	2SC2020	45V, 2A, PQ7W(27MHz)	2SC1816, 2SC2029, 2SC2043
19638	2SC2021(M,LN)	2SC1740(LN)	2SC1740(LN)
19639	2SC2022	300/300V, 1A, 30W, 10MHz	TIP 47...50, 2SC2023, 2SD860(A,B)
19640	2SC2023	300/300V, 2A, 40W, 10MHz	TIP 75(A...C), 2SC2738, 2SC3055
19641	2SC2024	80V, 1A, 150MHz	BD 139, BD 230, BD 379, 2SD1177...1178
19642	2SC2025	35V, 0,05A, 0,35W, 2,2GHz	BFR 37, BFS 55, BFW 30, BFX 73
19643	2SC2026	30V, 0,05A, 0,25W, 2,2GHz	BF 357, 2SC2570(A), 2SC3037, 2SC3777
19644	2SC2027	1500/800V, 5A, 50W, 8MHz	BU 208A, BU 508A, 2SC2928, 2SD820
19645	2SC2028	80V, 1,5A, PQ0,7W(27MHz)	2SC1957, 2SC2091, 2SC2314
19646	2SC2029	80V, 2A, PQ6W(27MHz)	2SC1816, 2SC2020
19647	2SC203	40V, 0,2A, 0,35W, 350MHz	BSW 41, BSY 63, 2N708, 2N914, 2N4123
19648	2SC2031	45V, 0,5A, PQ2,5W(470MHz)	BLW 90, BLX 92, 2SC2892
19649	2SC2032	45V, 1A, PQ5,5W(470MHz)	BLW 93, BLX 93, 2SC1040, 2SC2700
19650	2SC2033	45V, 3A, PQ18W(470MHz)	BLW 94, BLX 94, 2SC2894
19651	2SC2034	120V, 2A, PQ3,8W(50MHz)	-
19652	2SC2035	50V, 0,3A, 0,3W, 350MHz	2SC2053, BC 337, 2SC1627, 2SC2002...03
19653	2SC2037	30V, 0,05A, 0,25W, 2GHz	BF 357, 2SC2570(A), 2SC3037, 2SC3777
19654	2SC2039	70V, 8A, PQ50W(30MHz)	-
19655	2SC204(F)	2SC203, 30V, 250MHz	BSW 41, BSY 63, 2N708, 2N914, 2N4123
19656	2SC2040	40V, 0,5A, 5W, 1,8GHz	-
19657	2SC2043	70V, 4A, PQ16W(27MHz)	2SC1817, 2SC1944, 2SC1969, 2SC2098
19658	2SC2044	55V, 6A, PQ42W(770MHz)	-
19659	2SC205	2SC203, 80V	BSW 63...64, 2N2221A...2222A
19660	2SC2050	60V, 6A, PQ>13W(50MHz)	2SC1307
19661	2SC2051	60V, 0,25A, 0,5W, 300MHz	BC 337A, 2SC1627, 2SC2002...03, 2SC4414
19662	2SC2053	40V, 0,3A, PQ0,2W(175MHz)	2SC2851
19663	2SC2053	40V, 0,3A, PQ0,2W(175MHz)	2SC2851
19664	2SC2055	18V, 0,3A, PQ0,25W(175MHz)	2SC2851

19665	2SC2055	18V, 0,3A, PQ0,25W(175MHz)	2SC2851
19666	2SC2056	18V, 0,6A, PQ2W(175MHz)	BFQ 42, BFS 22, BLY 33, MRF 237, 2SC2852
19667	2SC2057	30V, 0,02A, 500MHz	BF 198, BF 225, BF 310, BF 314, BF 502
19668	2SC2058(S)	40V, 0,05A, 0,25W, 300MHz	BF 240...241, BF 254...255, BF 594...595
19669	2SC2058(S)	40V, 0,05A, 0,25W, 300MHz	BF 240...241, BF 254...255, BF 594...595
19670	2SC2059	25V, 0,02A, 500MHz	-
19671	2SC2059K	2SC2059	BF 599, BF 799, 2SC3015, 2SC3374
19672	2SC206	20V, 25mA, 0,2W, 200MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19673	2SC2060	40V, 1A, 0,75W, 150MHz	2SD667, 2SD863, 2SD1331, 2SD1207
19674	2SC2061	80V, 0,7A, 0,75W, 120MHz	2SC3228, 2SD667, 2SD1292, 2SD1812
19675	2SC2062(S)	B>5000	BC 517, BC 617, BC 875, MPSA 25...29
19676	2SC2063(M)	2SC2058	2SC2058
19677	2SC2065	35V, 0,25A, 6W, 3,2GHz	BFQ 68
19678	2SC2066	35V, 0,45A, 7W, 2GHz	BFT 99
19679	2SC2067	35V, 1A, 0,5W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1225
19680	2SC2068	300V, 0,05A, 95MHz	BF 461...462, BF 758...759, MPSU 10
19681	2SC2069	20V, 0,3A, 0,35W, -/100ns	BSW 41, BSX 87...88, BSY 62...63, 2N706A
19682	2SC207	2SC206, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
19683	2SC2070	40V, 0,3A, 0,3W, <160/172ns	BSW 41, BSX 87...88, BSY 63, 2N914
19684	2SC2071	250/220V, 0,05A, 130MHz	BF 415, BF 457, BF 469, 2SC4147
19685	2SC2073	150V, 1,5A, 25W, 4MHz	BD 239D, 2SC1669, 2SD608(A), 2SD1138
19686	2SC2075	80V, 4A, PQ>3,5W(27MHz)	2SC1306, 2SC1816, 2SC1909, 2SC2092
19687	2SC2076	35V, 0,02A, 150MHz	BF 240...241, BF 254...255, BF 594...595
19688	2SC2078	80V, 3A, PQ>4W(27MHz)	2SC1306, 2SC1816, 2SC1909, 2SC2092
19689	2SC2079	100V, 0,7A, 1W, 100MHz	BC 639, 2SC2235, 2SD667, 2SD1292
19690	2SC208	2SC206, 550MHz	BF 377...378, BF 689, BF 763, 2N2857
19691	2SC2080	60V, 1A, 35/105ns	BD 137, BD 228, BD 377, 2SD1378
19692	2SC2081	38V, 0,75A, PQ>2,8W(500MHz)	BLW 43, BLW 80, 2N5945
19693	2SC2082	38V, 2,2A, PQ>7,9W(500MHz)	BLW 44, 2N5946
19694	2SC2083	38V, 3A, PQ14W(500MHz)	BLW 15, BLX 69, 2SC1338
19695	2SC2085	300V, 0,1A, 10W, 55MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19696	2SC2086	75V, 1A, PQ0,45W(27MHz)	-
19697	2SC2086	75V, 1A, PQ0,45W(27MHz)	-
19698	2SC2087	300V, 5mA, 0,1W, 80MHz	BF 299, BF 420, BF 483, 2SC4218
19699	2SC2088	120V, 0,05A, 0,3W, 150MHz	2SC1775A, 2SC1845, 2SC2240, 2SC2459
19700	2SC2089	120V, 0,05A, 0,3W, 150MHz	2SC1775A, 2SC1845, 2SC2240, 2SC2459
19701	2SC209	2SC206, 450MHz	BF 377...378, BF 689, BF 763, 2N2857
19702	2SC2091	75V, 1A, PQ1,8W(27MHz)	2SC1957, 2SC2314
19703	2SC2092	75V, 3A, PQ5W(27MHz)	2SC1306, 2SC1816, 2SC1909
19704	2SC2094	40V, 3,5A, PQ>17,5W(175MHz)	-
19705	2SC2097	50V, 15A, PQ85W(30MHz)	-
19706	2SC2098	70V, 6A, PQ15W(28MHz)	2SC1944, 2SC1969, 2SC2050, 2SC1817
19707	2SC2099	40V, 6A, PEP20W(28MHz)	-
19708	2SC21	60V, 2A, 60W, 6MHz	BD 245A, BD 311, BD 313, 2N4914...15
19709	2SC210	50V, 0,5A, 0,65W, 150MHz	BC 140...141, BC 300...302, 2N3053

19710	2SC2100	40V, 15A, PEP60W(28MHz)	MRF 421, 2SC2290
19711	2SC2101	35V, 2A, PQ>6W(175MHz)	BLW 19, MRF 208, MRF 212, 2N5590
19712	2SC2102	35V, 3,5A, PQ>15W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
19713	2SC2103(A)	40V, 6A, PQ>24W(175MHz)	BLW 20, BLW 31, 2N6084
19714	2SC2104	35V, 0,8A, PQ>3W(470MHz)	2N5945
19715	2SC2105	35V, 1,4A, PQ>6W(470MHz)	BLW 14, BLW 44, 2N5946
19716	2SC2106	35V, 2,8A, PQ>12W(470MHz)	BLW 15, BLX 69, 2SC1338
19717	2SC2107	60V, 0,1A, 300MHz	BC 846, BCV 71...72, BSR 17, 2SC3361
19718	2SC2108	120V, 0,7A, 0,8W, 250MHz	2N2102, 2N2405, 2SC959
19719	2SC2109	45/400ns	BC 174, BC 182, BC 546, 2N3903...04
19720	2SC211	2SC210, 25V	BC 140...141, BC 300...302, 2N3053
19721	2SC2111	<20/40ns	BSS 11, BSX 19...20, 2N2368...69(A)
19722	2SC2113	40V, 1A, 4W, 100MHz	BD 135, BD 226, BD 375, 2SC3419
19723	2SC2114	15V, 0,08A, 0,225W, 7GHz	2SC2876, 2SC3062
19724	2SC2115	20V, 0,03A, 0,15W, 6,5GHz	BFQ 57...58, BFQ 74, 2SC1655...1656
19725	2SC2116	30V, 0,05A, 0,225W, 3GHz	BFQ 72, BFT 65
19726	2SC2117	35V, 0,8A, PQ3,2W(175MHz)	-
19727	2SC2118	35V, 1,4A, PQ6W(175MHz)	-
19728	2SC2119	80V, 4A, PQ>6W(28MHz)	2SC1816, 2SC2043
19729	2SC212	2SC210, 80V	BC 140...141, BC 300...301, 2N1990
19730	2SC2120	30V, 0,8A, 0,6W, 120MHz	BC 337...338, BC 635, BC 637, 2SD1225
19731	2SC2121	750/300V, 3A, 50W, 8MHz	BU 126, BU 326(A), BU 426(A), 2SD1183
19732	2SC2122	800/325V, 10A, 50W, 6MHz	BU 626A, 2SC2123, 2SD1094, 2SD1279
19733	2SC2122A	2SC2122, 1000/400V	BU 626A, 2SC2123, 2SD1094, 2SD1279
19734	2SC2123	1000/400V, 12A, 50W, 6MHz	2SC3644, BU 626A, 2SD1094, 2SD1279
19735	2SC2124	2200/800V, 2A, 5W(Tc90°)	BU 225, BUY 71, 2SD621, 2SD838
19736	2SC2125	2200/800V, 5A, 50W, 5MHz	-
19737	2SC2126(A)	200/200V, 3A, 30W, <1/2,5µs	TIP 75(A...C), 2SD422...423
19738	2SC2127(A)	200/200V, 10A, 100W, <1/3µs	BUX 17(A...C), BUY 18, TIP 160...162
19739	2SC2128(A)	200/200V, 30A, 200W, <1/3µs	2SC1301, 2SC2249, 2SC2445, 2SC2940
19740	2SC2129	2SC2130	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
19741	2SC2129	2SC2130	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
19742	2SC213	2SC210, 1,5W	BD 137, BD 228, 2SD1200, 2SD1378
19743	2SC2130	70V, 0,1A, 0,2W, 100MHz	BC 174, BC 190, BC 546, 2SD2030...31
19744	2SC2130	70V, 0,1A, 0,2W, 100MHz	BC 174, BC 190, BC 546, 2SD2030...31
19745	2SC2131	40V, 0,6A, PQ1,6W(500MHz)	BLX 65, MRF 629, 2SC2762, 2SC3185
19746	2SC2132	35V, 9A, PQ30W(470MHz)	BLU 45/12, MRF 648
19747	2SC2133	55V, 5A, PQ34W(220MHz)	-
19748	2SC2134	55V, 10A, PQ70W(220MHz)	MRF 327
19749	2SC2135	4V, 0,05A, 0,14W, B>500	-
19750	2SC2137	/<3µs	BUW 34...36, BUX 15, TIP 58A, 2SC3041
19751	2SC2138	2SC2137, 400/300V	BUW 34...36, BUX 15, TIP 56A, 2SC3041
19752	2SC2139(A)	500/400V, 10A, 100W, -/<3µs	BUW 24...26, BUW 34...36, 2SC3046
19753	2SC214	2SC210, 25V, 1,5W	BD 135, BD 226, 2SD1200, 2SD1378
19754	2SC2140	2SC2139, 500/350V	BUW 24...26, BUW 34...36, 2SC3046

19755	2SC2141	140/140V, 0,5A, 50MHz	2SC1913(A), 2SC2483, 2SC2591...2592
19756	2SC2142	15V, 0,03A, 0,165W, 4,5GHz	BFQ 22, BFQ 63, 2SC3037
19757	2SC2143	15V, 0,03A, 0,21W, 4,5GHz	BFQ 71, BFQ 85, BFR 14
19758	2SC2144	15V, 0,02A, 0,21W, 1,4GHz	2SC2144, 2SC2464, 2SC2466, 2SC2726
19759	2SC2145	35V, 2A, PQ3,5W(175MHz)	BFQ 43
19760	2SC2147	400/400V, 50A, 200W, 5MHz	2SC2159
19761	2SC2148	30V, 0,05A, 0,25W, 3GHz	BFQ 72, 2SC2844
19762	2SC2149	25V, 0,07A, 0,29W, 5GHz	BFQ 73, 2SC3302
19763	2SC215	2SC210, 80V, 1,5W	BD 139, BD 230, 2SD1200, 2SD1378
19764	2SC2150	20V, 0,03A, 0,25W, 6GHz	BFG 91, BFP 91, BFQ 57...58, BFQ 74
19765	2SC2151	600/400V, 15A, 150W, 15MHz	BUS 13(A), BUW 45...46, 2SD396, 2SD641
19766	2SC2152	36V, 2A, PQ>7W(500MHz)	-
19767	2SC2153	30V, 0,02A, >450MHz	BF 225, BF 314, BF 502, BF 505, BF 507
19768	2SC2159	400/400V, 50A, 200W, 5MHz	2SC2147
19769	2SC216	50V, 0,3A, 0,65W, >100MHz	BC 140...141, BC 300...302, 2N3053
19770	2SC2160	38V, 1A, PQ1,3W(470MHz)	BLX 65
19771	2SC2161	38V, 1A, PQ2,5W(470MHz)	BLW 43, BLW 80
19772	2SC2162	38V, 2A, PQ5W(470MHz)	BLW 14, BLW 44, 2N5946
19773	2SC2163	45V, 5A, PQ15W(470MHz)	BLW 15, BLX 69, 2SC1338...1339,
19774	2SC2164	45V, 10A, PQ30W(470MHz)	BLU 45/12, MRF 646, 2SC2783
19775	2SC2165(H)	120V, 5A, 0,8W, B>1000	2SC1882
19776	2SC2166	75V, 4A, PQ>6W(27MHz)	2SC1944, 2SC1969, 2SC2043, 2SC2119
19777	2SC2167	150V, 2A, 30W, 20MHz	BD 239D, 2SC2529, 2SC2660, 2SD1138
19778	2SC2168	2SC2167, 200V	BD 239F, 2SC2660, 2SD760, 2SD1138
19779	2SC2169	36V, 4A, 25W, PQ9W(175MHz)	-
19780	2SC217	2SC216, 25V	BC 140...141, BC 300...302, 2N3053
19781	2SC2172	60V, 0,2A	BCW 65...66, 2SC2882, 2SC4209
19782	2SC2173	35V, 6A, PQ28W(470MHz)	-
19783	2SC2174	25V, 0,07A, 0,35W, 4,5GHz	BFP 96, 2SC2844, 2SC3302
19784	2SC2175	350/350V, 10A, 100W	BUW 24...26, TIP 162, 2SC2625...26
19785	2SC2176	50V, 3A, PQ12W(270MHz)	BLX 95, 2SC2894
19786	2SC2177	50V, 5A, PQ22W(270MHz)	2N6105
19787	2SC2178	35V, 3,5A, PQ>15W(175MHz)	MRF 222...223
19788	2SC2179	55V, 6A, PQ40W(770MHz)	-
19789	2SC218	2SC216, 80V	BC 140...141, BC 300...301, 2N1990
19790	2SC2180	35V, 6A, PQ27W(175MHz)	BLW 20, BLW 31, 2N6084
19791	2SC2181	35V, 10A, PQ>40W(175MHz)	BLW 85
19792	2SC2182	65V, 6A, PQ50W(175MHz)	BLY 94
19793	2SC2183	35V, 4,5A, PQ16W(470MHz)	BLW 15, BLX 69, 2SC1404, 2SC1338
19794	2SC2184	60V, 3A, PQ5W(27MHz)	2SC1306, 2SC1816, 2SC1909, 2SC2092
19795	2SC2185	50V, 6A, PQ30W(275MHz)	2SC2796, 2SC2895
19796	2SC2186	50V, 9A, PQ60W(275MHz)	MRF 327
19797	2SC2188	45V, 50mA, 0,6W, 500MHz	BF 225, BF 310, BF 314, BF 502...503
19798	2SC2189	150V, 10A, 80W, <1/4μs	BD 245D, BDX 11, 2N3442, 2SD551, 2SC2769
19799	2SC219	20V, 25mA, 600MHz	BF 377...378, BF 689, BF 763, 2N2857



19800	2SC2190	450V, 5A, 100W, <1,5/5,3μs	BUW 71, BUX 45, TIP 57A...58A, 2SC3083
19801	2SC2191	450V, 10A, 100W, <2/5,2μs	BUW 72, BUW 75, BUX 14, 2SC3520
19802	2SC2192	36V, 5A, PQ>15W(175MHz)	-
19803	2SC2193	150V, 0,3A, 0,6W, 150MHz	2SD413, 2SD624, BF 380, MPSU 10
19804	2SC2194(A)	60V, 1,5A, 100MHz	BD 517, BD 525, BD 137, BD 228
19805	2SC2196	40V, 2A, PQ4,8W(175MHz)	2SC2145
19806	2SC2197	50V, 6A, PQ30W(160MHz)	BLW 20, BLW 31, 2N6084
19807	2SC2198	100V, 6A, 40W, B>300	2SC2316, 2SC2491
19808	2SC2199	150V, 8A, 60W, B>300	-
19809	2SC22	75V, 0,6A, 13W, 110MHz	BD 139, BD 230, BD 237, BD 830
19810	2SC220	2SC210, 0,7A	2SC210
19811	2SC2200	500/400V, 7A, 40W	BUT 56(A), 2SC2335, 2SC2427, 2SC3039
19812	2SC2204	800/400V, 30A, 250W, <1,5/5μs	2SC2977, 2SD295
19813	2SC2206	30V, 0,03A, 0,4W, 300MHz	BC 238, BC 548, BF 240...41, BF 254...55
19814	2SC2207	80V, 8A, PQ14W(27MHz)	2SC1307
19815	2SC2208(H)	120V, 5A, 0,8W, B>1000	-
19816	2SC2209	50V, 1,5A, 10W, 150MHz	BD 137, BD 228, BD 375, 2SD1177...78
19817	2SC221	2SC211, 0,7A	2SC211
19818	2SC2210	90MHz	BF 240...241, BF 254...255, BF 594...595
19819	2SC2212	1400MHz	BF 377...378, BF 689K, BF 763, 2N2857
19820	2SC2213	30V, 0,05A, 0,25W, 2,5GHz	2SC2570(A), 2SC3037, 2SC3337
19821	2SC2214	75/610ns	BFT 33...34, 2N4239, 2N5338...39, 2SC696(A)
19822	2SC2215	40V, 0,05A, >400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
19823	2SC2216	50V, 0,05A, >300MHz	BF 199, BF 224, BF 311, BF 373, BF 959
19824	2SC2217	20V, 0,08A, 0,58W, 8GHz	2SC2876, 2SC3062, 2SC3358, 2SC3603
19825	2SC2218	20V, 0,08A, 0,35W, 8GHz	2SC2876, 2SC3062, 2SC3358, 2SC3603
19826	2SC222	2SC212, 0,7A	2SC212
19827	2SC2220	500/300V, 30A, 250W, <1,5/5μs	2SC1300, 2SC1471, 2SC1874, 2SC2444
19828	2SC2221	25V, 0,75A, PQ>1,6W(175MHz)	BFQ 42, BFR 98, BLW 16, BLY 61
19829	2SC2222	25V, 1,5A, PQ>5W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
19830	2SC2223	30V, 0,02A, 600MHz	BF 599, BF 799, BFS 20, 2SC3015
19831	2SC2224	200V, 0,2A, 10W, 100MHz	BF 381...382, BF 615, BF 617, MPSU 10
19832	2SC2224A	2SC2224, 250V	BF 381...382, BF 615, BF 617, MPSU 10
19833	2SC2227	35V, 0,2A, 2,4GHz	2SC1253, 2SC1366, 2SC1952
19834	2SC2228(Y)	>50MHz	BF 297...299, BF 422A, 2SC3467...69
19835	2SC2228A	2SC2228, 200/200V	BF 298...299, BF 422A, 2SC3467...69
19836	2SC2229	200V, 0,05A, 0,8W, 120MHz	BF 298...299, BF 422A, 2SC3467...69
19837	2SC223	2SC213, 1A	2SC213
19838	2SC2230(A)	200V, 0,1A, 0,8W, >50MHz	BF 298...299, BF 422A, 2SC3467...69
19839	2SC2231(A)	200V, 0,2A, 12W, >50MHz	BF 615, BF 617, BF 757...759, MPSU 10
19840	2SC2233	200/60V, 4A, 40W, 8MHz	BU 406...408, 2SD823, 2SD1136, 2SD1159
19841	2SC2234	35V, 10A, PQ>40W(175MHz)	-
19842	2SC2235	120/120V, 0,8A, 0,9W, 120MHz	2SC2383, 2SC3228, 2SD667, 2SD1812
19843	2SC2236	30V, 1,5A, 0,9W, 120MHz	2SC3328, 2SD1146, 2SD1207, 2SD2069
19844	2SC2237	35V, 2A, PQ>7,5W(175MHz)	-



19845	2SC2238	160/160V, 1,5A, 25W, 100MHz	2SC2592, 2SC2660, 2SC2529, 2SD1138
19846	2SC2238A	2SC2238, 180/180V	2SC2592, 2SC2660, 2SC2344, 2SD1138
19847	2SC2238B	2SC2238, 200/200V	2SC2660, 2SD760, 2SD1138
19848	2SC2239	2SC2238	2SC783, 2SC2529, 2SC2592, 2SD1138
19849	2SC224	2SC214, 1A	2SC214
19850	2SC2240	120/120V, 0,1A, 0,3W, 100MHz	2SC2362, 2SC2389, 2SC2459, 2SC2631...32
19851	2SC2241	>50MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19852	2SC2242	300/300V, 0,15A, 25W, 50MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
19853	2SC2243	450/400V, 5A, 100W, <1/3μs	BUW 71, BUX 44...45, TIP 57A...58A
19854	2SC2244	2SC2243, 8A	BUW 72, BUX 15, BUX 44, TIP 57A...58A
19855	2SC2245	2SC2243, 10A	BUW 24...26, BUW 34...36, BUW 72, 2SC3520
19856	2SC2246	2SC2243, 15A	BUV 25, BUW 44, BUX 25, 2SC4140
19857	2SC2247	2SC2243, 40W	MJE 53T, 2SC1865, 2SC2200, 2SC3056
19858	2SC2248	2SC2243, 8A, 40W	BUY 65, MJE 13006, 2SC3057, 2SC4107
19859	2SC2249	250/200V, 30A, 200W, <2,5μs	2SC1301, 2SC1873, 2SC2445, 2SD643
19860	2SC225	2SC215, 1A	2SC215
19861	2SC2250	2SC2249, 450/400V	2SC1300, 2SC1470, 2SC1874, 2SC2220
19862	2SC2251	45V, 0,5A, PQ1,8W(900MHz)	BLX 97
19863	2SC2252	45V, 1A, PQ4,5W(900MHz)	-
19864	2SC2253	45V, 2A, PQ9W(900MHz)	-
19865	2SC2254	45V, 4A, PQ12W(900MHz)	-
19866	2SC2255	45V, 6A, PQ22W(900MHz)	2SC2044
19867	2SC2256	200/150V, 15A, 150W, 10MHz	BDW 16, BUW 50, BUX 41, 2SD552, 2SD583
19868	2SC2257	180/180V, 0,05A, 80MHz	BF 415, BF 458, BF 469, 2SC3502
19869	2SC2257A	2SC2257, 220/220V	BF 415, BF 458, BF 469, 2SC3503
19870	2SC2258	250/250V, 0,1A, 4W, 100MHz	BF 415, BF 458, 2SC3417, 2SC3503
19871	2SC2258A	2SC2258, 300/300V	BF 417, BF 459, BF 850, 2SC3417...18
19872	2SC2258B	2SC2258, 400/400V	BF 850, 2SC3418
19873	2SC226	2SC216, 0,7A	2SC216
19874	2SC2260	160/160V, 8A, 80W, 15MHz	BD245D, BDX11, 2N3442, 2SD733, 2SD551
19875	2SC2261	2SC2260, 180/120V	MJ 15015, BD 245E, BDW 14, 2SC2607
19876	2SC2262	2SC2260, 200/140V	MJ 15015, BD 245F, BDW 16, 2SC2607
19877	2SC2263	60V, 0,05A, 0,25W, 70MHz	2SC2390, 2SC1775(A), 2SC2631...32
19878	2SC2264	90V, 1A, 0,75W, 200MHz	2SC3228, 2SD667, 2SD1292, 2SD1812
19879	2SC2265(H)	35V, 0,02A, 550MHz	BF 314, BF 502...503, 2SC1393, 2SC1856
19880	2SC2266	<1,5/3,5μs	BUW 25...26, BUW 34...36, 2SC3043, 2SC3520
19881	2SC2267(H)	400/360V, 0,1A, 0,4W, 70MHz	MPSA 44...45, 2SC3118, 2SC3469, 2SD1350
19882	2SC227	2SC217, 0,7A	2SC217
19883	2SC2270	50V, 5A, 10W, 100MHz	2SC3420, 2SD826, 2SD2147
19884	2SC2271	300/300V, 0,1A, 0,9W, >50MHz	2SC3249, 2SC3468...3469, 2SC4166
19885	2SC2272	20V, 0,035A, 0,44W, 10GHz	2SC3584, 2SC3586...3587
19886	2SC2273	25V, 0,065A, 0,44W, 8,5GHz	BFG 195, 2SC3062
19887	2SC2274	60V, 0,5A, 0,6W, 120MHz	BC 637, BC 639, 2SC4414, 2SD1226
19888	2SC2274K	2SC2274, 100V	BC 639, 2SC3665, 2SC4414, 2SD667
19889	2SC2275	120/120V, 1,5A, 25W, 200MHz	2SC2238, 2SC2344, 2SC2528...29

19890	2SC2275A	2SC2275, 150/150V	2SC2238, 2SC2344, 2SC2529, 2SC2660
19891	2SC2276	130/130V, 7A, 80W, 100MHz	2SD588, 2SD848A
19892	2SC2277	50V, 0,5A, 0,625W, 120MHz	BC 337, BC 637, 2SD1226, 2SD2322S
19893	2SC2278	300/300V, 0,1A, 80MHz	BF 382, BF 461...462, MPSU 10, 2SC1758
19894	2SC2279	300/300V, 0,1A, 10W, 35MHz	BF 382, BF 461...462, MPSU 10, 2SC1758
19895	2SC228	2SC218, 0,7A	2SC218
19896	2SC2280	-/18V, 0,75A, 10W	-
19897	2SC2281	38V, 1,5A, PQ>7,1W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
19898	2SC2282	38V, 3A, PQ>15W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
19899	2SC2283	38V, 0,75A, PQ>2,8W(500MHz)	2SC3020
19900	2SC2284(A)	PQ>7,1W(500MHz)	2SC3021
19901	2SC2285(A)	PQ>14,1W(500MHz)	-
19902	2SC2286	38V, 0,75A, PQ>2,5W(175MHz)	-
19903	2SC2287(K)	38V, 1,5A, PQ>7,1W(175MHz)	-
19904	2SC2287M	2SC2287	-
19905	2SC2288(K)	38V, 3A, PQ>15W(175MHz)	2SC2094
19906	2SC2288M	2SC2288	-
19907	2SC2289(K)	25V, 1,5A, PQ>5W(175MHz)	-
19908	2SC2289M	2SC2289	-
19909	2SC229	80V, 1A	BD 139, BD 230, 2SD1200, 2SD1378
19910	2SC2290	45V, 20A, PEP60W(28MHz)	MRF 421, MRF 454
19911	2SC2292	500/400V, 8A, 80W, 20MHz	BUW 25...26, BUW 34...36, 2SC3046
19912	2SC2293	2SC2292, 10A, 100W	BUW 25...26, BUW 34...36, 2SC3046
19913	2SC2294	30V, 0,03A, 300MHz	BF 225, BF 310, BF 314, BF 502, BF 505
19914	2SC2295	30V, 0,03A, 250MHz	BC 849...850, BF 554, BF 840...841
19915	2SC2296	30V, 0,03A, 0,2W, 230MHz	BC 238, BC 548, BF 240...41, BF 254...55
19916	2SC2297	55V, 8A, PQ>16W(27MHz)	2SC1817
19917	2SC2298(A,B)	30V, 1A, 8W, B>4000	BD 477A,B, BD 875, 2SC4340...41
19918	2SC2299	20V, 1A, 0,5W, 150MHz	BC 337...338, BC 635, BC 637, 2SC3377
19919	2SC23	2SC22, 0,5A	BD 139, BD 230, BD 237, BD 830
19920	2SC230	80V, 0,2A, 0,35W, 350MHz	BSW 63...64, 2N2221A...2222A
19921	2SC2300	2SC2299, 50V	BC 337, BC 635, BC 637, 2SD1226
19922	2SC2302	500/400V, 7A, 40W, 35MHz	2SC2427, 2SC2739, 2SC3039, 2SC4106
19923	2SC2303	500/400V, 10A, 80W, 35MHz	BUW 25...26, BUW 34...36, 2SC3046
19924	2SC2304	500/400V, 12A, 100W, 35MHz	BUW 44, BUW 75...77, BUX 25, 2SC3043
19925	2SC2305	400/400V, 7A, 80W	BU 426(A), BU 926, TIP 57A...58A, 2SC3040
19926	2SC2306	450/400V, 15A, 150W, 7MHz	BUV 25, BUW 44...45, BUX 25, 2SD641
19927	2SC2307	500/400V, 12A, 100W, 18MHz	BUV 48(A...C), BUW 13(A), 2SC3520
19928	2SC2308	B>100	BC 167, BC 182, BC 237, BC 547, 2SD767
19929	2SC2309	2SC2308, B>250	2SC3622...23, BC 182, BC 237, BC 547
19930	2SC231	50V, 0,7A, 0,65W	BC 140...141, BC 300...302, 2N3053
19931	2SC2310	2SC2308	BC 414, BC 550, 2SC2240, 2SC2459
19932	2SC2311	50V, 1A, 45/90ns	BD 137, BD 228, BD 375, 2SD1177...78
19933	2SC2312	60V, 6A, PQ18,5W(27MHz)	2SC1307, 2SC1944, 2SC1969, 2SC1817
19934	2SC2313	40V, 10A, PQ38W(65MHz)	-

19935	2SC2314	75V, 1A, PQ1,8W(27MHz)	-
19936	2SC2315	80V, 6A, 40W, B800	2SC2316, 2SC2491, 2SD1158
19937	2SC2316	2SC2315, 100V	2SC2316, 2SC2491
19938	2SC2317	200V, 1A, 30W, B1000	2SD1272
19939	2SC2318	40V, 0,35A, 2700MHz	2SC1199, 2SC1252, 2SC 1365...66, 2SC2852
19940	2SC2319	40V, 0,35A, 2900MHz	2N5944
19941	2SC232	2SC231, 25V	BC 140...141, BC 300...302, 2N3053
19942	2SC2320	50V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
19943	2SC2320L	2SC2320	BC 414, BC 550, 2SC2240, 2SC2459
19944	2SC2321	130/130V, 8A, 80W, 60MHz	2SC1584, 2SD1047, 2SD425, 2SD551
19945	2SC2322	120/120V, 12A, 120W, 60MHz	2SC1584, 2SD1047, 2SD425, 2SD551
19946	2SC2323	2SC2322, 150/150V	2SC1584, 2SD1047, 2SD733, 2SD551
19947	2SC2324(K)	60V, 1A, 8W, B>2000	BD 677, BD 875, BDX 42...44, 2SD985...86
19948	2SC2325	45V, 0,6A, PQ>1,3W(4,2GHz)	-
19949	2SC2326	45V, 1,2A, PQ>2,5W(4,2GHz)	-
19950	2SC2327	20V, 0,03A, 4,5GHz	BFQ 69, BFR 91
19951	2SC2328	20V, 0,03A, 2,2GHz	BFT 24, BFR 34, BFW 93
19952	2SC2329	38V, 0,75A, PQ>2W(175MHz)	BFS 22, BFW 46, BLY 33, MRF 237, 2N3924
19953	2SC233	2SC231, 80V	BC 140...141, BC 300...301, 2N1990
19954	2SC2330	38V, 6A, PQ>31,6W(175MHz)	-
19955	2SC2331	150/100V, 2A, 15W, <0,5/2μs	BD 239F, 2SC2660, 2SD760, 2SD1138
19956	2SC2333	500/400V, 2A, 15W, <1/3,5μs	BUV 36(A), BUX 84...85, 2SC2534, 2SC2738
19957	2SC2334	150/100V, 7A, 40W, <0,5/2μs	BD 243F, BU 409, BUW 64C, TIP 150...152
19958	2SC2335	500/400V, 7A, 40W, <1/3,5μ	BUT 56(A), 2SC2427, 2SC2739, 2SC3039
19959	2SC2336	180/180V, 1,5A, 25W, 95MHz	2SC2238A,B, 2SC2660, 2SD608A, 2SD760
19960	2SC2336A	2SC2336, 200V	2SC2238B, 2SC2660, 2SD610, 2SD760
19961	2SC2336B	2SC2336, 250V	2SC2023, 2SD610
19962	2SC2337(A)	150V, 10A, 100W, 70MHz	BDX 11, 2SD1047, 2SD551, 2SD733
19963	2SC2338	25V, 0,04A, PQ0,14W(7,5GHz)	2SC3584, 2SC3586...3587
19964	2SC2339	25V, 0,15A, PQ0,2W(6GHz)	-
19965	2SC234	100V, 1,5A, 18W, 140MHz	(BD 139, BD 230, BD 379, 2SD1177...1178
19966	2SC2340	30V, 0,3A, 6W, 6,5GHz	-
19967	2SC2344	180/160V, 1,5A, 25W, 100MHz	2SC2238A,B, 2SC2660, 2SD608A
19968	2SC2345	25V, 0,02A, 980MHz	2SC2464...66, 2SC2360, 2SC2726
19969	2SC2347	30V, 0,05A, >650MHz	BF 377...378, BF 689K, BF 763, 2N2857
19970	2SC2348	30V, 0,02A, >400MHz	BF 314, BF 496, BF 502, BF 505, BF 507
19971	2SC2349	30V, 0,05A, >600MHz	BF 199, BF 224, BF 311, BF 503, BF 505
19972	2SC235	2SC 234, 120MHz	(BD 139, BD 230, BD 379, 2SD1177...1178
19973	2SC2350	30V, 0,05A, 2,8GHz	BFR 53, 2SC3014, 2SC3773
19974	2SC2351	25V, 0,07A, 4,5GHz	BFR 106, 2SC3161, 2SC3774
19975	2SC2352	30V, 0,03A, 850MHz	BF 225, BF 310, BF 314, BF 505, BF 507
19976	2SC2353	30V, 0,05A, 2,3GHz	2SC2466, 2SC2728
19977	2SC2354	300/250V, 1A, 30W, 20MHz	BUX 67A...C, TIP 47...50, 2SC782, 2SD860
19978	2SC2356	500/400V, 10A, 100W, 20MHz	BUW 25...26, BUW 34...36, 2SC3046
19979	2SC2357	1000/700V, 10A, 150W, -/3,3μs	BUS 12A, BUX 81, BUY 69A...70A, MJ 8504

19980	2SC2358	2SC2357, 1000/800V	BUS 12A, BUX 81, BUY 69A...70A, MJ 8504
19981	2SC2359	/1,9µs	BUT 93, BUX 64, MJE 53T, TIP 75B,C
19982	2SC236	2SC 234, 90V, 100MHz	(BD 139, BD 230, BD 379, 2SD1177...1178
19983	2SC2360	30V, 20mA, 0,2W, 1100MHz	2SC2464, 2SC2466, 2SC2353, 2SC2726
19984	2SC2361	70V, 4A, 25W, 70MHz	BDV 10...12, MJE 15028, 2SC3253, 2SD772
19985	2SC2361A	2SC2361, 100V	BDV 10...12, MJE 15028, MJE 15030, 2SD772
19986	2SC2362	120V, 0,05A, 0,4W, 130MHz	2SC1845, 2SC2088, 2SC2240, 2SC2389
19987	2SC2362K	2SC2362, 150/120V	2SC2631...32, 2SC3800
19988	2SC2363	120V, 0,05A, 0,5W, 130MHz	2SC1890A, 2SC2375, 2SC3245, 2SD756A
19989	2SC2364	200/150V, 5A, 80W, B1000	2SD921, 2SD933, 2SD1090, 2SD1122
19990	2SC2365	600/500V, 6A, 50W, 10MHz	BU 326, BU 426, BU 526, BUX 47(A)
19991	2SC2366	500/400V, 40A, 300W, 15MHz	2SC1435, 2SD642
19992	2SC2367	20V, 0,08A, 0,58W, 8GHz	BFQ 82, BFQ 196, 2SC3603
19993	2SC2368	30V, 0,05A, 0,25W, 2,8GHz	2SC2368, 2SC2470, 2SC3368
19994	2SC2369	25V, 0,07A, 0,25W, 4,5GHz	BFP 96, BFQ 73, 2SC2844, 2SC3302
19995	2SC237	25V, 0,3A, 0,35W, 450MHz	2SC2851, BFX 55
19996	2SC2370	35V, 0,8A, PQ4W(470MHz)	-
19997	2SC2371	300V, 0,1A, 10W	BF 417, BF 459, 2SC3417, 2SC3503
19998	2SC2373	200/100V, 7,5A, 40W, 10MHz	BU 406...408, 2SC3189, 2SC3589, 2SD1069
19999	2SC2375	150V, 0,05A, 0,9W, 130MHz	2SC2632, 2SC3245(A), 2SC3248, 2SC3800
20000	2SC2376	300V, 0,15A, 20W	MJE 340, MJE 3439...3440, 2SC2899
20001	2SC2377	30V, 15mA, 0,4W, 650MHz	BF 225, BF 310, BF 314, BF 502, BF 505
20002	2SC2378	70V, 0,1A, 0,25W, 250MHz	BC 174, BC 546, 2SC2240, 2SC2675
20003	2SC2379	35V, 1,4A, PQ>6W(470MHz)	-
20004	2SC238	40V, 0,1A, 0,65W, 350MHz	BFW 16...17, BFX 55, 2N3724, 2SC1385
20005	2SC2380	35V, 2,8A, PQ>12W(470MHz)	-
20006	2SC2381	35V, 6A, PQ>25W(470MHz)	-
20007	2SC2382	40V, 12A, PQ>50W(175MHz)	MRF 243
20008	2SC2383	160/160V, 1A, 0,9W, >20MHz	2SC3228, 2SD1812
20009	2SC2384	2SC2383, 10W	2SC1913, 2SC2592, 2SD387A, 2SD1138
20010	2SC2385	70V, 0,1A, 0,2W, 130MHz	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
20011	2SC2385	70V, 0,1A, 0,2W, 130MHz	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
20012	2SC2386	70V, 0,3A, 0,5W, 125MHz	BC 546, BC 639, 2SC4414, 2SD1226
20013	2SC2386	70V, 0,3A, 0,5W, 125MHz	BC 546, BC 639, 2SC4414, 2SD1226
20014	2SC2387	500V, 8A, 100W, 1/2,1µs	BUW 25...26, BUW 34...36, 2SC3046
20015	2SC2388	/1,9µs	BU 326, BU 426, BUX 45, 2SC3083
20016	2SC2388A	2SC2388, 500/400V, 7A	BU 326, BU 426, BUX 15, 2SC2536
20017	2SC239	/150ns	BSS 10, BSX 19...20, BSX 39, 2N3261
20018	2SC2390	2SC2389, 80V	2SC1845, 2SC2089, 2SC2240, 2SC2459
20019	2SC2391	35V, 0,8A, PQ>3W(470MHz)	-
20020	2SC2392	35V, 2,8A, PQ>15W(470MHz)	-
20021	2SC2393	80V, 4A, PQ>6W(28MHz)	2SC1816, 2SC2119
20022	2SC2394	45V, 6A, PQ16W(50MHz)	2SC2050
20023	2SC2395	40V, 5A, PEP10W(28MHz)	2SC2693
20024	2SC2396	60V, 0,1A, 0,4W, 90MHz	BC 174, BC 182, BC 190, BC 546, 2SD767

20025	2SC2397	60V, 8A, PQ>18W(27MHz)	2SC1817
20026	2SC2398	100V, 10A, 95W, 80MHz	2SC2681, 2SC2706, 2SC2837
20027	2SC2399	30V, 0,02A, 940MHz	BF 377...378, BF 689K, BF 763, 2N2857
20028	2SC24	2SC22, 100V, 0,5A	BD 139, BD 230, BD 237, BD 830
20029	2SC240	100V, 5A, 75W	BD 245C, BDV 95, BDX 95, 2N5758...60
20030	2SC2400	40V, 0,1A, 0,31W, <10/15ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
20031	2SC2401	40V ,0,3A, 0,31W, B10000	BC 517, BC 617, BC 875, MPSA 25...29
20032	2SC2402	300/200V, 15A, 150W, -/2,3µs	BUX 13, BUY 50, MJ 15022, MJ 15024
20033	2SC2403	300/200V, 40A, 300W, -/3µs	2SC2366, 2SC2973, 2SD702
20034	2SC2404	2SC2377, SMD	BF 599, BF 799, BFS 20, 2SC3015
20035	2SC2405	35V, 0,05A, 200MHz	BC 849...850, BCF 32...33, BCF 81, 2SC3323
20036	2SC2406	2SC2405, 55V	BC 850, BCF 81, 2SC3323
20037	2SC2407	35V, 0,15A, PQ0,16W(500MHz)	2SC1954
20038	2SC2408	35V, 0,15A, 0,6W, 3,5GHz	2SC3337
20039	2SC2409	50V, 0,1A, 0,3W, 180MHz	BC 184, BC 414, BC 550, 2SC2240
20040	2SC241	2SC240, 60V	BD 245A, BDV 91, BDX 91, 2N4914...15
20041	2SC2410(S)	40V, 0,1A, 0,25W, 230MHz	BF 240...241, BF 254...255, BF 594...595
20042	2SC2410(S)	40V, 0,1A, 0,25W, 230MHz	BF 240...241, BF 254...255, BF 594...595
20043	2SC2411	40V, 0,5A, 250MHz	-
20044	2SC2411K	2SC2411	BC 817, BCW 65...66, BCX 19, 2SC3325
20045	2SC2412	50V, 0,15A, 180MHz	-
20046	2SC2412K	2SC2412	BC 847, BCW 71...72, BCW 81
20047	2SC2412KLN	2SC2412	BC 850, BCF 81, 2SC3323
20048	2SC2412LN	2SC2412	-
20049	2SC2413	40V, 0,05A, 300MHz	BFS 17...18, BF 554, BF 840...841
20050	2SC2413K	2SC2413	BFS 17...18, BF 554, BF 840...841
20051	2SC2414	500V, 2A, 70W, <1/3,5µs	BU 126, BUX 45...46, TIP 54, 2SC3083
20052	2SC2415	2SC2414, 7A, 90W	BU 326, BU 426, BUX 45, 2SC3041
20053	2SC2416	2SC2414, 10A, 120W	BUW 25...26, BUW 34...36, 2SC3046
20054	2SC2417	-/10V, 0,03A, 0,25W, 6,5GHz	BFQ 57...58, BFQ 65, BFQ 74, 2SC3276
20055	2SC2418	-/8V, 0,08A, 0,33W, 7GHz	2SC2876, 2SC3358, 2SC3603
20056	2SC2419	65V, 1A, PQ>2,5W(175MHz)	BFS 23, BLY 34
20057	2SC242	2SC240	BD 245C, BDV 93, BDX 93, 2N5758...60
20058	2SC2420	40V, 6A, PQ>32W(175MHz)	2N6084
20059	2SC2421	200V, 5A, 100W, 30MHz, B700	2SD776, 2SD920...921, 2SD929, 2SD1090
20060	2SC2422	2SC1421, 150V	2SD776, 2SD920...923, 2SD929, 2SD1090
20061	2SC2423	2SC1421, 40W	2SD930, 2SD1023, 2SD1025
20062	2SC2424	2SC1421, 150V, 40W	2SD930, 2SD1023, 2SD1025, 2SD1128
20063	2SC2425	300/200V, 0,1A, 20MHz	2SC1505,,1507, 2SC1755...1758, 2SC1905
20064	2SC2427	500/400V, 7A, 40W, 20MHz	MJE 13006, 2SC2335, 2SC4055, 2SC4106
20065	2SC2428	180/180V, 12A, 120W, 80MHz	MJ 15015, BDW 14, BDY 56, 2SC2608
20066	2SC2429	450/400V, 15A, 150W, 30MHz	BUV 25, BUW 44, BUX 25, 2SD641
20067	2SC2429A	2SC2429, 600/450V	BUS 13(A), BUW 45...46, 2SD641
20068	2SC243	2SC240, 140V	BD245D,2N4347, 2N5760, 2SD731, 2SD1046
20069	2SC2430	120/120V, 10A, 100W, 80MHz	2SC2706, 2SC2837, 2SC2987



20070	2SC2431	120/120V, 15A, 100W, 80MHz	-
20071	2SC2432	70/70V, 15A, 100W, 80MHz	2SC3256
20072	2SC2433	120/120V, 30A, 150W, 80MHz	BUW 39, BUX 39, 2N5671, 2N6272
20073	2SC2434	2SC2433, 70/70V	BUW 39, BUX 39, 2N6270, 2N6272
20074	2SC2435	100/100V, 10A, 100W, B>2000	BDX 65B, BDX 83C, MJ 4035, 2SD628...29
20075	2SC2436	2SC2435, 15A	BDX 67B, MJ 4035, 2SD729
20076	2SC2437	450/400V, 7A, 100W	BUX 15, BUX 44, TIP57A...58A, 2SC3041
20077	2SC2438	<500/3000ns	BU 406...408, BUW 64A...C, MJE 15030
20078	2SC2439	<500/3000ns	BU 406...408, BUW 64A...C, MJE 15030
20079	2SC244	2SC240, 60V	BD 245A, BDV 91, BDX 91, 2N4914...15
20080	2SC2440	450/400V, 5A, 40W	MJE 53T, 2SC2518, 2SC2542, 2SC3056
20081	2SC2441	180/160V, 0,08A, 150MHz	BF 415, BF 417, BF 469, BF 471, 2SD1610
20082	2SC2442	600V, 30A, 200W, <2/8µs	2SC2204, 2SC2977, 2SD295, 2SD644
20083	2SC2443	600V, 50A, 400W	-
20084	2SC2444	500/400V, 30A, 250W, <1,5/4µs	2SC1300, 2SC1471, 2SC1874, 2SC2220
20085	2SC2445	300/200V, 30A, 250W, <1/3µs	2SC1299, 2SC1873, 2SD542...543, 2SD643
20086	2SC2447	20V, 0,05A, 0,25W, 1600MHz	BFR 37, BFS 55, BFW 30, BFX 73
20087	2SC2448	650/600V, 7A, 80W, <1/4µs	BU 526, BUX 47, 2SC3092, 2SC3449
20088	2SC2449	650/600V, 7A, 80W, <1/2,5µs	BU 526, BUX 47, 2SC3092, 2SC3449
20089	2SC245	2SC240, 120V	BD 245C, 2N5759...60, 2SD718, 2SD896
20090	2SC2450	2SC2448, 750/700V	BU 526, BUX 47, 2SC3092, 2SC3449
20091	2SC2451	2SC2449, 750/700V	BU 526, BUX 47, 2SC3092, 2SC3449
20092	2SC2452	2SC2448, 850/800V	BU 526, BUX 47, 2SD811, 2SC3636
20093	2SC2453	2SC2449, 850/800V	BU 526, BUX 47, 2SD811, 2SC3636
20094	2SC2454	50V, 0,03A, 550MHz	2SC2467, 2SC2727, 2SC2729
20095	2SC2455	30V, 0,02A, >450MHz	2SC2464, 2SC2466, 2SC2726, 2SC2728
20096	2SC2456	300/300V, 0,1A, 10W	BF 417, BF 459, 2SC3417, 2SC3503
20097	2SC2458(L)	50V, 0,15A, 0,2W, >80MHz	BC 184, BC 414, BC 550, 2SC2240
20098	2SC2459	120V, 0,1A, 0,2W, 100MHz	2SC1845, 2SC2240, 2SC2389, 2SC3245(A)
20099	2SC246	2SC240, 180V	BD 245E, BU 608, 2SC2261...2262, 2SD751
20100	2SC2460	140/140V, 12A, 100W, 90MHz	BDW 10, 2SD425, 2SD551, 2SD1047
20101	2SC2460A	2SC2460, 120W	BDW 10, BDW 14, 2SD424...425, 2SD551
20102	2SC2461	150/150V, 15A, 150W	2SC1884...1585, 2SC2608, 2SD424
20103	2SC2461A	2SC2460, 160V	2SC1585...1586, 2SC2608, 2SD424
20104	2SC2462	50V, 0,1A, 230MHz	BC 846...847, BCW 71...72, BCW 81
20105	2SC2463	2SC2462, 55V	BC 846, BCV 71...72, 2SC3323
20106	2SC2464	30V, 20mA, 900MHz	2SC2466, 2SC2144, 2SC2360, 2SC2726
20107	2SC2465	20V, 20mA, 550MHz	2SC2470, 2SC2368
20108	2SC2466	30V, 50mA, 2,2GHz	2SC2353, 2SC2728
20109	2SC2467	30V, 50mA, 900MHz	2SC2454, 2SC2727, 2SC2729
20110	2SC2468	30V, 50mA, 900MHz	BF 362...363, BFW 93
20111	2SC2469	30V, 50mA, >600MHz	BF 362...363, BFW 93
20112	2SC247	100V, 0,1A, 0,6W, 150MHz	BF 257...259, 2SC2240, 2SC3245(A)
20113	2SC2470	30V, 0,05A, 0,2W, 2,2GHz	2SC2465, 2SC2368
20114	2SC2471	30V, 0,05A, 0,31W, 2GHz	BF 357, 2SC2570(A), 2SC3037



20115	2SC2472	30V, 0,05A, 0,3W, 2,2GHz	BF 357, 2SC2570(A), 2SC3037
20116	2SC2473	30V, 0,05A, 0,3W, 2,2GHz	BF 357, 2SC2570(A), 2SC3037
20117	2SC2474	60V, 0,2A, 0,6W, <70/250ns	BSV 59, BSX 49, 2N2221...22, 2N3903...04
20118	2SC2475	60V, 0,6A, 0,6W, <35/285ns	BSV 59, BSX 49, 2N2221...22, 2N3301...02
20119	2SC2476	30V, 0,2A, 0,6W, <70/250ns	BSW 41, BSY 63, 2N708, 2N914, 2N4123
20120	2SC2477	60V, 0,6A, 0,6W, <35/300ns	BSX 48, BSX 87...88, BSX 97, 2N914
20121	2SC248	70V, 0,05A, 0,3W, 170MHz	BC 546, 2SC1775(A), 2SC1890(A), 2SD755
20122	2SC2480	30V, 50mA, 1300MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20123	2SC2481	150V, 1,5A, 20W, >20MHz	2SC2690, 2SC3117, 2SD669
20124	2SC2482	300/300V, 0,1A, 0,9W	2SC3468, 2SC4166, 2SC3805, 2SC4019
20125	2SC2483	160/160V, 1,5A, 15W, 120MHz	2SC2238(A,B), 2SC2344, 2SC2529
20126	2SC2484	80/80V, 5A, 60W, 15MHz	BD 245B, 2SD718, 2SD895, 2SD1046
20127	2SC2485	100/100V, 6A, 70W, 15MHz	BD 245C, 2SD718, 2SD896, 2SD1046
20128	2SC2486	120/120V, 7A, 80W, 15MHz	BD 245C, 2SD718, 2SD896, 2SD1046
20129	2SC2487	150/150V, 6A, 80W, 50MHz	2SC2837, 2SD551, 2SD732...733, 2SD1046
20130	2SC2488	150/150V, 8A, 100W, 50MHz	2SC2837, 2SD551, 2SD733, 2SD1047
20131	2SC2489	150/150V, 10A, 120W, 50MHz	2SC2837, 2SD551, 2SD733, 2SD1047
20132	2SC249	70V, 0,07A, 0,5W, 170MHz	BC 546, 2SC2631...32, 2SC3245(A)
20133	2SC2490	55V, 10A, PQ75W(770MHz)	-
20134	2SC2491	100V, 6A, 50W, B600	2SC2316, 2SD1474
20135	2SC2492	120/120V, 10A, 100W, 70MHz	2SC2837, 2SD551, 2SD733, 2SD1047
20136	2SC2493	2SC2482, 150/150V	2SC2837, 2SD551, 2SD733, 2SD1047
20137	2SC2494(K)	25V, 0,75A, PQ>1,4W(500MHz)	-
20138	2SC2494M	2SC2494	-
20139	2SC2495(K)	25V, 1,5A, PQ>3,2W(500MHz)	-
20140	2SC2495M	2SC2495	-
20141	2SC2496(A)	35V, 10A, PQ37W(500MHz)	BLU 45/12, MRF 646, MRF 648, 2SC2783
20142	2SC2497(A)	70V, 1,5A, 5W, 150MHz	BD 139, BD 377, 2SC2690, 2SD1177...78
20143	2SC2498	30V, 0,05A, 0,3W, 3,5GHz	2SC2570(A), 2SC3037, 2SC3512
20144	2SC2499	20V, 0,03A, 0,3W, 4GHz	2SC2570(A), 2SC3037, 2SC3512
20145	2SC25	60V, 0,06A, 0,5W	BC 174, BC 182, BC 190, BC 546, 2N2218
20146	2SC250	20V, 25mA, 0,06W, 170MHz	BF 240...241, BF 254...255, BF 594...595
20147	2SC2500	30V, 2A, 0,9W, 150MHz	2SC3328, 2SD1146, 2SD1207, 2SD1247
20148	2SC2501	500/400V, 3A, 40W, 20MHz	BUT 93, TIP 75C, 2SC3038, 2SC4105
20149	2SC2502	500/400V, 6A, 50W, 20MHz	MJE 13006, 2SC2335, 2SC3039, 2SC4106
20150	2SC2503	500/400V, 8A, 80W, 20MHz	-
20151	2SC2504	500/400V, 10A, 100W, 20MHz	-
20152	2SC2505	500/400V, 3A, 60W, 20MHz	BUT 93, TIP 75C, 2SC2826, 2SC3038
20153	2SC2506	500/400V, 6A, 60W, 20MHz	MJE 13006, 2SC3039, 2SC3170, 2SC4106
20154	2SC2507	500/400V, 20A, 200W, 20MHz	BUS 14(A), 2SC2930, 2SC3058, 2SC3085
20155	2SC2508	40V, 6A, PQ>27W(175MHz)	MRF 224
20156	2SC2509	40V, 5A, PEP10W(28MHz)	-
20157	2SC251(A)	30V, 30mA, 900MHz	BF 180...183, BF 689, BF 763, 2N2857
20158	2SC2510	55V, 20A, PEP>150W(28MHz)	-
20159	2SC2511	60V, 0,1A, 150MHz	BF 240...241, BF 254...255, BF 959

20160	2SC2512	30V, 50mA, 900MHz	BF 377...378, BF 689K, BF 763, 2N2857
20161	2SC2516(A)	150V, 5A, 30W, <0,5/3μs	BD 243D, 2SD772(A,B)
20162	2SC2517	2SC2516, <500/2500ns	BD 243D, 2SD772(A,B)
20163	2SC2518	<1000/3200ns	MJE 13070, 2SC2535, 2SC2827, 2SC3830
20164	2SC2519	30V, 0,03A, 0,25W, 230MHz	BF 240...241, BF 254...255, BF 594...595
20165	2SC252	30V, 30mA, 900MHz	BF 180...183, BF 689, BF 763, 2N2857
20166	2SC2522	120/120V, 12A, 120W, 80MHz	2SC2987(A), 2SD425, 2SD551, 2SD1047
20167	2SC2522A		2SC2987A, 2SD733, 2SD551, 2SD1047
20168	2SC2523	2SC2522, 160V	2SC2987A, 2SD733, 2SD551, 2SD1047
20169	2SC2524	160/160V, 15A, 150W, 80MHz	MJ 15015, 2SC1585...86, 2SC2608, 2SD424
20170	2SC2525	2SC2522	2SC2564...2565, 2SC2766(A), 2SC2921
20171	2SC2526	2SC2523	2SC2565, 2SC2766(A), 2SC2921...22
20172	2SC2527	120V, 10A, 60W, 80MHz	-
20173	2SC2528	120V, 2A, 25W, 160MHz	2SC2660, 2SD759...760
20174	2SC2529	2SC2528, 160V	2SC2660, 2SD759...760
20175	2SC253	30V, 30mA, 900MHz	BF 180...183, BF 689, BF 763, 2N2857
20176	2SC2530	40V, 0,5A, 20W, 35MHz	BD 239, 2SC1398
20177	2SC2531	25V, 0,03A, 2,5GHz	BFR 34, BFT 97, BFW 93
20178	2SC2532	40V, 0,3A, B>5000	BCV 27, 2SD1383K
20179	2SC2534	500/400V, 2A, 20W, -/<3,5μs	BUV 36, BUX 84...85, 2SC2333, 2SC2738
20180	2SC2535	2SC2534, 5A, 40W	BUT 56(A), TIP 75C, 2SC2827, 2SC3038
20181	2SC2536	2SC2534, 7A, 80W	BU 426(A), BUP 22, TIP 58A, 2SC3040
20182	2SC2537	410V, 10A, 100W, -/3050ns	BUV 47(A), BUW 12(A), 2SC2625, 2SC3042
20183	2SC2538	40V, 0,4A, PQ0,6W(175MHz)	BFS 51, BFX 55, BLW 16, MRF 607
20184	2SC2538	40V, 0,4A, PQ0,6W(175MHz)	BFS 51, BFX 55, BLW 16, MRF 607
20185	2SC2539	35V, 4A, PQ17W(175MHz)	-
20186	2SC254	50V, 0,8A, 0,65W, 250MHz	BC 140...141, BC 300...302, 2N3053
20187	2SC2540	35V, 10A, PQ45W(175MHz)	BLV 45/12
20188	2SC2541	500/450V, 10A, 100W, 16MHz	BUV 47(A), BUW 12(A), 2SC2740, 2SC3042
20189	2SC2542	450V, 5A, 40W, <1/3μs	BUT 56(A), MJE 53T, 2SC2440, 2SC3056
20190	2SC2543	90/90V, 0,1A, 0,4W, 90MHz	2SC2240, 2SC2363, 2SC2459, 2SC3245(A)
20191	2SC2544	2SC2543, 120/120V	2SC2240, 2SC2363, 2SC2459, 2SC3245(A)
20192	2SC2545	2SC2543, 60V	BC 414, BC 550, 2SC2240, 2SC2459
20193	2SC2546	2SC2543	2SC2240, 2SC2363, 2SC2389, 2SC2459
20194	2SC2547	2SC2543, 120/120V	2SC2240, 2SC2363, 2SC2389, 2SC2459
20195	2SC2548	20V, 0,03A, 0,25W, 4GHz	2SC2499, 2SC2570(A), 2SC3037
20196	2SC2549	ra. 15V, 0,03A	BF 630, 2SC2499, 2SC2570(A), 2SC2548
20197	2SC255	2SC254, 80V	BC 140...141, BC 300...301, 2N1990
20198	2SC2550	60V, 0,2A, 0,3W, 250MHz	BC 182, BC 546, 2N2221...2222(A)
20199	2SC2551	300V, 0,1A, 0,4W, 80MHz	BF 299, BF 393, BF 420A, 2SC3468
20200	2SC2552	500/400V, 2A, 20W, -/<3,5μs	BUV 36, BUX 84...85, 2SC2333, 2SC2738
20201	2SC2553	2SC2552, 5A, 40W	MJE 13070, TIP 75C, 2SC2827, 2SC3830
20202	2SC2555	2SC2552, 8A, 80W	BU 426(A), TIP 58A, 2SC3040, 2SC4106
20203	2SC2556	130/40V, 1A, 200MHz	2SC2690A, 2SC3117, 2SD669
20204	2SC2556A	2SC2556, 180/50V	2SC3117, 2SD669

20205	2SC2557	60V, 0,05A, 0,25W, 220MHz	BC 414, BC 550, 2SC2240, 2SC2459
20206	2SC2558	35V, 0,5A, PQ1,3W(860MHz)	-
20207	2SC2559	35V, 1,5A, PQ6W(860MHz)	2SC2685
20208	2SC256	2SC254, 90V	BC 141, BC 300...301, 2N1990, 2N2102
20209	2SC2560	35V, 3A, PQ11W(860MHz)	2SC2850
20210	2SC2561	30V, 0,03A, 0,25W, 250MHz	BF 240...241, BF 254...255, BF 594...595
20211	2SC2562	60V, 5A, 25W, 120MHz	2SC3253...3255, 2SC3258, 2SD1235
20212	2SC2563	120/120V, 8A, 80W, 90MHz	2SC2706, 2SC2837, 2SC2987(A)
20213	2SC2564	140/140V, 12A, 120W, 90MHz	2SC2526, 2SC2766, 2SC2838, 2SC2921
20214	2SC2565	2SC2564, 160/160V, 15A, 150W	2SC2526, 2SC2766(A), 2SC2921...2922
20215	2SC2566	30V, 15mA, 650MHz	BF 314, BF 502, BF 505, BF 507, BF 959
20216	2SC2567	35V, 0,05A, 320MHz	BC 846...848, BCW 31...33, BCW 71...72
20217	2SC2567A	2SC2567, 55V	BC 846...847, BCW 71...72, BCW 81
20218	2SC2568	300/300V, 0,2A, 10W, 80MHz	BF 417, BF 459, 2SC3417, 2SC3503
20219	2SC2569	150/150V, 6A, 40W, <1/3μs	BU 409, BUW 64, MJE 15030, 2SC2334
20220	2SC257	2SC254, 0,8W	2SC254
20221	2SC2570(A)	25V, 0,07A, 5GHz	2SC3037, 2SC3512
20222	2SC2572	60V, 0,2A, 0,36W, <80/420ns	BSV 59, BSX 49, 2N2222(A), 2N3904
20223	2SC2575	50V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
20224	2SC2575	50V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
20225	2SC2575L	2SC2575	BC 414, BC 550, 2SC2240, 2SC2459
20226	2SC2575L	2SC2575	BC 414, BC 550, 2SC2240, 2SC2459
20227	2SC2577	120/80V, 6A, 60W, 20MHz	BD 245C, 2SC2706, 2SC2837, 2SC2987(A)
20228	2SC2578	2SC2577, 140/140V, 7A, 70W	BD 245D, 2SC2706, 2SC2987(A), 2SD1046
20229	2SC2579	/3,1μs	BD 245D, 2SC2987A, 2SC3263, 2SD1047
20230	2SC258	2SC255, 0,8W	2SC255
20231	2SC2580	2SC2577, 180/120V, 9A, 90W	BD 245E, 2SC3263, 2SC3855, 2SD751
20232	2SC2581	100W, -2,8μs	BD 245F, 2SC3263, 2SC3855
20233	2SC2582	45V, 1A, 10W, 200MHz	BD 135, BD 226, BD 375, 2SD1378
20234	2SC2584	45V, 4A, PQ22W(175MHz)	2SC2094
20235	2SC2585	24V, 0,4W, 0,065A, 8,5GHz	BFG 195, BFQ 82, 2SC3358, 2SC3603
20236	2SC2586	35V, 0,4A, PQ1,6W(500MHz)	BFS 50, MRF 629, 2SC2762, 2SC3185
20237	2SC2587(A)	150V, 10A, 120W, 70MHz	2SC2526, 2SC2565, 2SC2838, 2SD745A,B
20238	2SC2588(A)	150V, 12A, 120W, 60MHz	2SC2526, 2SC2564...2565, 2SC2838
20239	2SC2589	180/180V, 10A, 200W, 60MHz	BDW 16, 2SC1585...86, 2SC2607...08
20240	2SC259	2SC256, 0,8W	2SC256
20241	2SC2590	120/120V, 0,5A, 5W, 200MHz	2SC2690(A), 2SD1382, 2SD1563
20242	2SC2591	150/150V, 1A, 20W, 200MHz	2SC1913(A), 2SC2238(A,B), 2SC2344
20243	2SC2592	2SC2591, 180/180V	2SC1913A, 2SC2238A,B, 2SC2344, 2SC2660
20244	2SC2593	20/20/20V, 0,05A, 0,14W	-
20245	2SC2594	40V, 5A, 10W, 150MHz	MJE 200, 2SC3420, 2SD741, 2SD826
20246	2SC2595	36V, 1,2A, PQ0,9W(840MHz)	-
20247	2SC2596	36V, 4A, PQ3,5W(840MHz)	-
20248	2SC2597	36V, 6A, PQ9W(840MHz)	-
20249	2SC2599	20V, 0,02A, 0,2W	BFG 90, BFQ 28, BFQ 60, BFQ 71, BFR 49

20250	2SC26	60V, 0,1A, 0,5W, 150MHz	BC 174, BC 182, BC 190, BC 546, 2N2219
20251	2SC260	30V, 1A, 280MHz	BD 135, BD 226, 2SC3419, 2SD1200
20252	2SC2600	25V, 0,04A, 0,35W, 6GHz	BFQ 57...58, BFQ 74, 2SC1655...1656
20253	2SC2602	70V, 0,2A, 0,5W	2SC2240, 2SC2459, 2SC2674...2675
20254	2SC2602	70V, 0,2A, 0,5W	2SC2240, 2SC2459, 2SC2674...2675
20255	2SC2603	50V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
20256	2SC2604	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2240
20257	2SC2605	2SC2604, 50V	BC 184, BC 413...414, BC 550, 2SC2240
20258	2SC2606	300/300V, 0,05A, 30MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
20259	2SC2607	200/200V, 15A, 150W, 20MHz	MJ 15015, BDW 16, 2SD665, 2SD753
20260	2SC2608	2SC2607, 17A, 200W	BUV 11, BUW 58, BUX 11, 2SC2865(A)
20261	2SC2609	55V, 15A, PQ110W(220MHz)	2SC2897
20262	2SC261	2SC260, 60V	BD 137, BD 228, 2SD1200, 2SD1378
20263	2SC2610	300V, 0,1A, 0,8W, 80MHz	BF 299, BF 393, BF 420A, 2SC3468...69
20264	2SC2611	2SC2610	BF 417, BF 459, 2SC3417, 2SC3503
20265	2SC2612	500/400V, 3A, 30W	BUT 93, TIP 75C, 2SC2826, 2SC3038
20266	2SC2613(K)	2SC2612, 5A, 40W	BUT 56(A), 2SC2535, 2SC2827, 2SC3497
20267	2SC2614	2SC2612, 5A, 60W	-
20268	2SC2615	2SC2612, 8A, 80W	2SC2650, 2SC2818
20269	2SC2616	2SC2612, 10A, 100W	BUW 25...26, BUW 34...36, 2SC3043
20270	2SC2617	2SC2612, 15A, 125W	BUV 25, BUW 44, BUX 25, 2SD641
20271	2SC2618	35V, 0,5A, 50MHz	BC 817, BCX 19, 2SC3325, 2SC3341
20272	2SC2619	30V, 0,1A, 230MHz	BC 846...848, BCW 31...33, BCW 71...72
20273	2SC262	2SC260, 80V	BD 139, BD 230, 2SD1200, 2SD1378
20274	2SC2620	30V, 0,02A, 940MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20275	2SC2621	300/300V, 0,2A, 10W, >50MHz	BF 417, BF 459, MJE 3440, 2SC3503
20276	2SC2623	450/400V, 20A, 100W, <1/4µs	BUV 24, BUX 24, 2SC3085, 2SC3850
20277	2SC2624	450/400V, 5A, 80W, <1/3µs	BU 426(A), TIP 57A...58A, 2SC3083
20278	2SC2625	2SC2624, 10A	2SC2541, 2SC2740, 2SC2789, 2SC4138
20279	2SC2626	<0,8/2,8µs	2SC2307, 2SC3520, 2SC3451, 2SC4139
20280	2SC2627	35V, 2A, PQ6W(175MHz)	BLW 18, BLY 62, 2SC2281
20281	2SC2628	35V, 4A, PQ18W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
20282	2SC2629	35V, 8A, PQ34W(175MHz)	2N6084
20283	2SC263	15V, 0,12A, 0,1W, 200MHz	BSX 27, BSX 92...93, 2N2368...69A
20284	2SC2630	35V, 14A, PQ60W(175MHz)	BLV 75/12, 2SC3147
20285	2SC2631	150V, 0,05A, 0,75W, 160MHz	2SC3800
20286	2SC2632	2SC2631, 1W	2SC3800
20287	2SC2633	2SC2631	2SC3514
20288	2SC2634(NC)	60V, 0,1A, 0,4W, 200MHz	BC 550, 2SC2240, 2SC2389...90, 2SC2459
20289	2SC2635(H)	650/600V, 0,1A, 0,75W, 15MHz	2N5012...15, 2SC1762, 2SD594
20290	2SC2636	30V, 0,05A, 0,4W, 1200MHz	BF 357, BF 377...378, 2SC2570(A), 2SC3037
20291	2SC2637	300/300V, 0,1A, 15W, 100MHz	BF 617, BF 758...759, MPSU 10
20292	2SC2638	35V, 2A, PQ>6W(175MHz)	-
20293	2SC2639	35V, 3,5A, PQ>15W(175MHz)	2SC2094
20294	2SC264	2SC263, 30V, 400MHz, 27/40ns	BSX 92...93, 2N2368...69A, 2N3011

20295	2SC2640	35V, 6A, PQ>28W(175MHz)	-
20296	2SC2641	35V, 1,4A, PQ>6W(470MHz)	MRF 641, 2SC2284
20297	2SC2642	35V, 2,8A, PQ>12W(470MHz)	-
20298	2SC2643	35V, 6A, PQ>25W(470MHz)	-
20299	2SC2644	25V, 0,12A, 0,5W, 4GHz	2SC3337, 2SC3779
20300	2SC2645	30V, 0,05A, 0,2W, 1200MHz	BF 362, BF 363
20301	2SC2646	30V, 0,05A, 0,2W, 1200MHz	BF 377...378, BF 689K, BF 763, 2N2857
20302	2SC2647	30V, 0,03A, 0,4W, 230MHz	BF 240...241, BF 254...255, BF 594...595
20303	2SC2648	35V, 3,5A, PQ17W(470MHz)	BLX 69, 2SC1404
20304	2SC2649	35V, 6A, PQ22W(470MHz)	2SC1339, 2SC2173
20305	2SC265	2SC263, 40V	BSS 11, BSX 92...93, 2N2368...69(A)
20306	2SC2650	500/400V, 10A, 100W, -/<3,5µs	2SC2818
20307	2SC2651	45V, 25A, PEP90W(28MHz)	2SC2879
20308	2SC2652	85V, 20A, PEP220W(28MHz)	-
20309	2SC2653	350V, 0,2A, 15W, >50MHz	BF 759
20310	2SC2653(H)	2SC2653, 400/300V	-
20311	2SC2654	40V, 7A, 40W, <1/3,5µs	BD 243, BD 543, BD 795, 2SD1442
20312	2SC2655	60V, 2A, 0,9W, 100MHz	2SC3328, 2SC3669, 2SD1207, 2SD2177
20313	2SC2656	450/450V, 7A, 80W, <1,5/4,5µs	BUP 22, TIP 57A...58A, 2SC2788, 2SC3040
20314	2SC2657	800/500V, 1,5A, 70W, 2,5MHz	BUX 46(A), 2SC3091, 2SC3151, 2SC3533
20315	2SC2657A	2SC2657, 900/500V	BUX 46A, 2SC3155, 2SC3151, 2SC3533
20316	2SC2658	<1/4µs	BU 426(A), BUW 11(A), BUX 46(A), BUX 82
20317	2SC2658A	2SC2658, 900/500V, <1,2/4,2µs	BU 426A, BUW 11A, BUX 46A, BUX 83
20318	2SC2659	800/500V, 7A, 120W, 3,5MHz	BU 546, BUS 12(A), BUW 35...36, BUX 81
20319	2SC2659A	2SC2659, 900/500V	BU 546, BUS 12A, BUW 36, BUX 81
20320	2SC266	30V, 0,03A, 0,1W, 250MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
20321	2SC2660(A)	200V, 2A, 30W, 30MHz	2SD386...387(A), 2SD760, 2SD772A, 2SD1138
20322	2SC2662	100V, 3A, 8W(Tc25°), 50MHz	BSX 64, 2N4239, 2SC696(A), 2SC2214
20323	2SC2664	100/60V, 3A, 10W, 50MHz	BD 791, BDX 35...37, MJE 243...244
20324	2SC2665	100V, 4A, 55W, 10MHz	BD 245C, BDV 95, 2SD718, 2SD895...896
20325	2SC2666	35V, 3,5A, PQ7W(270MHz)	BLW 15, BLW 81, 2SC2106
20326	2SC2667	35V, 6A, PQ20W(270MHz)	2SC2173
20327	2SC2668	40V, 20mA, 0,1W, 550MHz	BF 255, BF 314, BF 495, BF 502, BF 595
20328	2SC2669	35V, 50mA, 0,2W, >100MHz	BF 240, BF 254, BF 494, BF 594, 2SC829
20329	2SC267	35V, 0,2A, 0,15W, 90MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
20330	2SC2670	35V, 0,1A, 0,2W, >80MHz	BF 240...241, BF 254...255, BF 594...595
20331	2SC2671(F)	15V, 80mA, 5,5GHz	2SC2570(A), 2SC3037, 2SC3337
20332	2SC2671(H)	25V, 70mA, 4,5GHz	2SC2570(A), 2SC3037, 2SC3337
20333	2SC2672	30V, 0,05A, 0,25W, 3GHz	BFQ 72
20334	2SC2673	40V, 1A, 0,6W, 150MHz	BC 337, BC 635, 2SD1225, 2SD1616
20335	2SC2674	2SC2675, 120/120V	2SC2240, 2SC2459, 2SC3245, 2SC3378
20336	2SC2675	80V, 0,1A	2SC2240, 2SC2459, 2SC2602
20337	2SC2676(1)	80V, 0,01A, 0,6W, 200MHz	2SC1775(A), 2SC2240, 2SC2389...2390
20338	2SC2677	30V 0,1A, 0,625W, 230MHz	BC 238, BC 548, BF 240...41, BF 254...55
20339	2SC2678	20V, 0,03A, 0,5W, 300MHz	BC 238, BC 548, BF 240...41, BF 254...55



20340	2SC2679	30V, 0,05A, PQ8mW(930MHz)	BF 357, BF 377...378, 2SC2570(A), 2SC3037
20341	2SC267A	2SC267, 50V	BC 167, BC 182, BC 237, BC 547, 2SD767
20342	2SC268	60V, 0,03A, 0,15W, 150MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
20343	2SC2680	40V, 0,03A, 550MHz	BF 599, BF 799, 2SC3053, 2SC3374
20344	2SC2681	115/115V, 10A, 100W, 80MHz	2SC2706, 2SC2837, 2SC2987, BD 245C
20345	2SC2682	180/180V, 0,1A, 8W, 200MHz	BF 415, BF 458...459, 2SC3416, 2SD1610
20346	2SC2684	36V, 0,6A, PQ0,95W(940MHz)	-
20347	2SC2685	36V, 2A, PQ5,5W(940MHz)	-
20348	2SC2686	36V, 3A, PQ13W(940MHz)	-
20349	2SC2687	300/300V, 0,2A, 0,8W, 80MHz	BF 299, BF 420A, BF 393, 2SC3468
20350	2SC2688	300/300V, 0,2A, 10W, 80MHz	BF 417, BF 459, 2SC3417, 2SC3503
20351	2SC2689	300/300V, 0,2A, 10W, 80MHz	BF 382, BF 617, BF 859, MPSU 10
20352	2SC268A	2SC268, 80V	BC 546, BF 297...299, BF 422, BSS 38
20353	2SC268A	2SC268, 80V	BC 546, BF 297...299, BF 422, BSS 38
20354	2SC268B	2SC268, 150V	BF 297...299, BF 422, BFR 87, 2SC3467
20355	2SC268B	2SC268, 150V	BF 297...299, BF 422, BFR 87, 2SC3467
20356	2SC269	14/25ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
20357	2SC2690	120/120V, 1,2A, 20W, 155MHz	2SC3117, 2SD669, 2SD1563(A)
20358	2SC2690A	2SC2690, 160/160V	2SC3117, 2SD669, 2SD1563A
20359	2SC2691	20V, 0,05A, 0,2W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
20360	2SC2691	20V, 0,05A, 0,2W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
20361	2SC2692	28V, 0,2A, PQ0,45W(2GHz)	BFQ 68, BFT 98
20362	2SC2693	70V, 5A, PEP12W(28MHz)	-
20363	2SC2694	35V, 20A, PQ75W(175MHz)	MRF 244, 2SC2782
20364	2SC2695	35V, 10A, PQ32W(520MHz)	-
20365	2SC27	60V, 0,1A, 0,65W, 350MHz	BFW 16...17, BFX 55, 2N3725, 2SC1385
20366	2SC270	270V, 5A, 50W, 22MHz	BU 606...608, BUX 16A...C, 2SD1154
20367	2SC2700	45V, 1A, PQ6,5W(470MHz)	BLX 93, 2SC1040
20368	2SC2701	35V, 0,3A, PQ1,1W(2,3GHz)	-
20369	2SC2702	35V, 0,5A, PQ2,2W(2,3GHz)	-
20370	2SC2703	30V, 1A, 0,9W, 150MHz	2SC2236, 2SD863, 2SD1207, 2SD1331
20371	2SC2704	150/150V, 0,05A, 10W, 200MHz	BF 415, BF 457...459, 2SC3502, 2SD1609
20372	2SC2705	2SC2704, 0,8W	BF 297...299, BF 422(A), 2SC3467...69
20373	2SC2706	140/140V, 10A, 100W, 90MHz	2SC2837, 2SC2987(A)
20374	2SC2707	180/180V, 15A, 150W, 80MHz	MJ 15015, BDW 16, 2SC2607, 2SD753
20375	2SC271	25V, 20mA, 1100MHz	BF 362...363
20376	2SC2710	35V, 0,8A, 0,3W, 120MHz	BC 337...338, BC 635, BC 637, 2SD1225
20377	2SC2711	35V, 0,8A, PQ6W(175MHz)	-
20378	2SC2712	60V, 0,15A, 150MHz	BC 846, BCV 71...72, 2SC3323, 2SC4076
20379	2SC2713	120V, 0,1A, 100MHz	2SC3324, 2SC3744, 2SC4050
20380	2SC2714	40V, 0,02A, 550MHz	BF 599, BF 799, BFS 20, 2SC3015
20381	2SC2715	35V, 0,05A, >100MHz	BF 554, BFS 18...19, BF 840...841
20382	2SC2716	35V, 0,1A, 120MHz	BC 846...848, BCW 31...33, BF 554
20383	2SC2717	30V, 0,05A, >300MHz	BF 198...199, BF 224...225, BF 596...597
20384	2SC2718	60V, 0,1A, 0,25W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767



20385	2SC2719	80V, 0,3A, 0,6W, 50/560ns	BC 639, BSW 63...64, 2N2221A...2222A
20386	2SC272	25V, 20mA, 1200MHz	BF 362...363
20387	2SC2720	60V, 0,5A, 0,6W, <35/275ns	BSV 59, BSW 62, BSX 49, 2N2222(A)
20388	2SC2721	60V, 0,7A, 1W, 110MHz	BC 637, BC 639, 2N2221...22(A), 2SD1226
20389	2SC2722	100/80V, 15A, 150W, 20MHz	2SC2525...2526, 2SC2564...2565, 2SC2838
20390	2SC2723	450/400V, 15A, 150W, 30MHz	BUP 23, 2SC3520, 2SC4139, 2SC4434
20391	2SC2724	30V, 30mA, 200MHz	BF 240...241, BF 254...255, BF 594...595
20392	2SC2726	15V, 0,02A, 0,2W, 1100MHz	2SC2464, 2SC2466, 2SC2144, 2SC2360
20393	2SC2727	15V, 0,02A, >700MHz	2SC2454, 2SC2465
20394	2SC2728	15V, 0,02A, 0,2W, 2500MHz	2SC2466, 2SC2353
20395	2SC2729	15V, 0,05A, 0,2W, 1300MHz	2SC2368, 2SC2454, 2SC2465
20396	2SC273	120V, 0,05A, 0,5W, 150MHz	BF 257...259, 2SC3245(A), 2SC3248
20397	2SC2730	15V, 0,05A, 0,2W, 1600MHz	BF 362...363
20398	2SC2731	20V, 0,05A, 0,2W, 3500MHz	BFQ 59, BFQ 70, 2SC2143, 2SC2844
20399	2SC2732	30V, 0,02A, 1000MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20400	2SC2733	30V, 0,05A, 1000MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20401	2SC2734	20V, 0,05A, 3500MHz	BFT 75, 2SC3014, 2SC3773
20402	2SC2735	30V, 0,05A, 1200MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20403	2SC2736	30V, 0,05A, 2200MHz	BFR 53, BFT 75, 2SC3014, 2SC3773
20404	2SC2737	20V, 0,08A, 8GHz	-
20405	2SC2738	500/400V, 2A, 25W, 11MHz	BUX 84...85, 2SC2333, 2SC2534, 2SC3169
20406	2SC2739	500/400V, 7A, 40W, 11MHz	BUT 56(A), 2SC2427, 2SC3039, 2SC3170
20407	2SC2740	500/400V, 10A, 100W, 11MHz	BUW 12(A), 2SC2789, 2SC2828, 2SC3042
20408	2SC2743	36V, 5A, PQ15W(175MHz)	-
20409	2SC2745	36V, 4A, PQ9W(470MHz)	-
20410	2SC2746	36V, 5A, PQ15W(470MHz)	-
20411	2SC2749(A)	500V, 10A, 100W, <1/3,2μs	BUW 12(A), 2SC3042, 2SC3435, 2SC4138
20412	2SC2750	150V, 15A, 100W, <1/1,8μs	2SC2944, 2SC2987A, 2SD1047, 2SD1703
20413	2SC2751(A)	500V, 15A, 120W, <1/3,2μs	BUW 13(A), 2SC3435, 2SC3520, 2SC4140
20414	2SC2752	500/400V, 0,5A, 10W, <1/3,5μs	BD 410, BUX 86...87, 2SC2899, 2SC3051
20415	2SC2753	17V, 0,07A, 0,3W, 5GHz	2SC2570(A), 2SC3037
20416	2SC2754	30/470ns	BSW 41, BSY 63, 2N708, 2N4123...24
20417	2SC2755	30V, 0,02A, 600MHz	BF 599, BF 799, BFS 20, 2SC3015
20418	2SC2756	20V, 0,02A, 850MHz	BF 599, BF 799, BFS 20, 2SC3015
20419	2SC2757	30V, 0,05A, 1100MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20420	2SC2758	30V, 0,02A, 1000MHz	BFS 17, 2SC3077, 2SC3161
20421	2SC2759	30V, 0,05A, 2000MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20422	2SC2760	50V, 10A, PQ34W(470MHz)	2N6439, 2SC2796, 2SC2895
20423	2SC2761	450/400V, 30A, 200W	BUS 14(A), BUS 98(A), 2SC2930, 2SC3058
20424	2SC2762	35V, 0,4A, PQ1,4W(500MHz)	BFS 50, MRF 629, 2SC2852, 2SC3185
20425	2SC2763	35V, 4A, PQ16W(500MHz)	2SC1968
20426	2SC2766	160/160V, 15A, 150W, 60MHz	2SC2526, 2SC2565, 2SC2921...2922
20427	2SC2766A	2SC2766, 180/180V	2SC2773...2774, 2SC2922, 2SC3370
20428	2SC2767	250/200V, 5A, 40W, <1/3μs	BU 406...409, MJE 51T...53T, 2SC3056
20429	2SC2768	250/200V, 7A, 40W, <1/3μs	BU 406...409, TIP 150...152, 2SC4106

20430	2SC2768A	2SC2768, 10A	BUV 27(A), 2SC2867
20431	2SC2769	<0,8/2,5µs	TIP160...162, 2SC2537, 2SC2944, 2SC2961
20432	2SC2773	200/200V, 15A, 150W, 20MHz	2SC3370, 2SC3264, 2SC3857, 2SD846
20433	2SC2774	200/200V, 17A, 200W, 20MHz	2SC3264
20434	2SC2775	90V, 0,05A, 200MHz	2SC1622A, 2SC3324, 2SC4050
20435	2SC2776	30V, 0,03, 320MHz	BF 599, BF 799, BFS 20, 2SC3015
20436	2SC2778	30V, 0,03A, 230MHz	BF 554, BF 599, BF 799, BFS 18...20
20437	2SC2780	140V, 0,05A, 120MHz	2SC2880, 2SD1009, 2SD1464
20438	2SC2781	35V, 0,5A, PQ0,9W(2,3GHz)	-
20439	2SC2782	36V, 20A, PQ90W(175MHz)	-
20440	2SC2783	36V, 8A, PQ45W(470MHz)	BLV 45/12
20441	2SC2784	120V, 0,05A, 0,3W, 110MHz	2SC1775(A), 2SC2240, 2SC2459, 2SC3378
20442	2SC2785	60V, 0,1A, 0,25W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
20443	2SC2786	30V, 20mA, 600MHz	BF 225, BF 314, BF 502, BF 505, BF 507
20444	2SC2787	50V, 30mA, 250MHz	BF 240...241, BF 254...255, BF 594...595
20445	2SC2788	500/400V, 8A, 80W, 20MHz	BUP 22, TIP 58A, 2SC2536, 2SC3040
20446	2SC2789	500/400V, 10A, 100W	BUP 23, 2SC2828, 2SC3042, 2SC4138
20447	2SC2790(A)	850/800V, 2A, 80W, <1/5µs	BU 326A, BU 426A, BUW 11(A), BUX 46(A)
20448	2SC2791	900V, 5A, 100W, <1/4,5µs	BU 426A, BUS 11A, BUW 11A, 2SC3796A
20449	2SC2792	850/800V, 2A, 80W, <1/5µs	BU 426A, BUW 11(A), 2SC3151...3152
20450	2SC2793	900/800V, 5A, 100W, <1/4,5µs	2SC2980
20451	2SC2794	60V, 2A, 25W, 40MHz	BD 177, BD 235, BD 377, 2SD794(A)
20452	2SC2796	45V, 6A, PQ44W(470MHz)	2N6439, 2SC2895
20453	2SC2797	45V, 1A, PQ6W(770MHz)	-
20454	2SC2798	45V, 2A, PQ14W(770MHz)	-
20455	2SC2799	45V, 4A, PQ27W(770MHz)	-
20456	2SC28	40V, 0,05A, 0,225W, 100MHz	BC 167, BC 182, BC 237, BC 547, 2N2218
20457	2SC2800	45V, 6A, PQ42W(770MHz)	-
20458	2SC2802	300V, 0,2A, 10W, 80MHz	BF 417, BF 617, BF 758...759, MPSU 10
20459	2SC2803	150/150V, 1A, 20W, 200MHz	2SC2690A, 2SC3117, 2SD669, 2SD1563A
20460	2SC2804	25V, 0,02A, 0,2W, 900MHz	2SC2464, 2SC2466, 2SC2144, 2SC2360
20461	2SC2805	30V, 0,05A, 0,2W, 1500MHz	2SC2464, 2SC2466, 2SC2144, 2SC2360
20462	2SC2806	30V, 0,05A, 0,2W, 1100MHz	2SC2464, 2SC2466, 2SC2144, 2SC2360
20463	2SC2808(S)	160V, 0,05A, 0,5W, 140MHz	BF 297...299, BF 422, 2SC3248, 2SC3467
20464	2SC2808(S)	160V, 0,05A, 0,5W, 140MHz	BF 297...299, BF 422, 2SC3248, 2SC3467
20465	2SC2809	300/300V, 2A, 50W, 20MHz	TIP 51...54, 2SC2624
20466	2SC281(H)	30V, 0,1A, 0,2W, >80MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
20467	2SC2810	500/400V, 7A, 50W, 18MHz	MJE13006, 2SC3170, 2SC4055, 2SC4106
20468	2SC2812	55V, 0,15A, 100MHz	BC 846...847, BCW 71...72, 2SC3323
20469	2SC2813	25V, 0,03A, 600MHz	BF 599, BF 799, BFS 20, 2SC3015
20470	2SC2814	30V, 0,03A, 320MHz	BF 554, BFS 18...20, BF 599, BF 799
20471	2SC2815	300/250V, 5A, 40W, <0,5/2µs	BU 406...408, MJE 51T...53T, 2SC2907
20472	2SC2816	500/400V, 5A, 40W, <0,5/2µs	BUT 52, BUT 56(A), 2SC4106, 2SC3497
20473	2SC2817	300/250V, 10A, 80W, <0,5/2µs	2SC2650
20474	2SC2818(H)	500/400V, 10A, 100W, <0,5/2µs	BUW 25, BUW 34...35, 2SC3046, 2SC4138

20475	2SC2819(H)	500/400V, 15A, 100W, <0,5/2μs	BUV 25, BUW 44, BUX 25, 2SD641
20476	2SC282(H)	2SC281, 0,35W	BC 168, BC 183, BC 238, BC 548, 2SD767
20477	2SC2820	500/400V, 20A, 125W, <1/3,5μs	2SC3085, 2SC3094, 2SC3593, 2SC4110
20478	2SC2821	20V, 0,05A, 230MHz	BC 846...848, BCW 31...33, BCW 71...72
20479	2SC2822	75V, 0,8A, 0,36W, <35/300ns	BSW 63...64, 2N2221A...2222A, 2SC3733
20480	2SC2823	120/120V, 7A, 70W, B15000	BDV 65C, 2SD1123, 2SD1210
20481	2SC2824	120/120V, 1A, 15W, 120MHz	2SC2690(A), 2SC3117, 2SD669, 2SD1563
20482	2SC2825	80V, 6A, 70W, B>500	2SD1831
20483	2SC2826	500/400V, 3A, 40W, 20MHz	BUT 93, TIP 75C, 2SC3038, 2SC4105
20484	2SC2827	500/400V, 6A, 50W, 20MHz	MJE 13006, 2SC3830, 2SC4106
20485	2SC2828	500/400V, 10A, 100W, <1/2,5μs	BUP 23, 2SC2789, 2SC3042, 2SC4138
20486	2SC2829	500/400V, 10A, 100W, <1/2,5μs	BUW 25...26, BUW 34...36, 2SC3046, 2SC4138
20487	2SC283(H)	2SC281, 50V, 0,35W	BC 167, BC 182, BC 237, BC 547, 2SD767
20488	2SC2830	500/400V, 20A, 200W, <1/2,5μs	2SC3085, 2SC3094, 2SC3593, 2SC4110
20489	2SC2831	800/500V, 1,5A, 25W	BUV 36(A), BUX 84...85, 2SC3149, 2SC3352
20490	2SC2831A	2SC2831, 900/500V	BUV 36A, BUX 85, 2SC3149, 2SC3531
20491	2SC2832	800/500V, 5A, 40W	BUT 11(A), BUV 46(A), 2SC3047, 2SC3050
20492	2SC2832A	2SC2832, 900/500V	BUT 11A, BUV 46A, 2SC3050
20493	2SC2833	800/500V, 5A, 100W	BUW 11(A), BUW 131(A), 2SC3153, 2SC3232
20494	2SC2833A	2SC2833, 900/500V	BUW 11A, BUW 131A, 2SC3153, 2SC3232
20495	2SC2834	800/500V, 7A, 100W	BUV 47(A), BUW 12(A), 2SC3450, 2SC3797
20496	2SC2834A	2SC2834, 900/500V	BUV 47A, BUW 12A, 2SC3536, 2SC3636
20497	2SC2837	150/150V, 10A, 100W, 70MHz	2SC2987A, 2SC3907, 2SD1047, 2SD1703
20498	2SC2838	2SC2837, 12A, 120W	2SC2526, 2SC2565, 2SC2766, 2SC2921
20499	2SC2839	30V, 30mA, 320MHz	BF 225, BF 314, BF 502, BF 505, BF 959
20500	2SC284(H)	2SC281, 70V, 0,35W	BC 174, BC 182, BC 190, BC 546, 2SC1890
20501	2SC2840	25V, 30mA, 600MHz	BF 225, BF 314, BF 502, BF 505, BF 507
20502	2SC2841	500/400V, 7A, 70W, <1/4μs	BUP 22, TIP 58A, 2SC2788, 2SC3040
20503	2SC2844	25V, 0,07A, 4,5GHz	BFP 96, BFQ 73, 2SC3302
20504	2SC2845	25V, 0,07A, 4,5GHz	2SC3161, 2SC3774...75
20505	2SC2847	30V, 0,02A, >600MHz	BF 799, 2SC3015, 2SC3374
20506	2SC285	50V, 0,2A, 0,5W, 320MHz	BFW 16...17, BFX 55, 2SC2852
20507	2SC2850	35V, 3A, PQ11W(860MHz)	2SC2559
20508	2SC2851	36V, 0,3A, PQ0,9W(175MHz)	2SC2053
20509	2SC2852	36V, 0,5A, PQ1W(470MHz)	BFS 50, MRF 629, 2N3948, 2SC2762
20510	2SC2853	90V, 0,1A, 0,4W, 310MHz	2SC1775(A), 2SC2240, 2SC2459, 2SC3245
20511	2SC2854	2SC2853, 120/120V	2SC1775(A), 2SC2240, 2SC2459, 2SC3245
20512	2SC2855	2SC2853	2SC1775(A), 2SC2240, 2SC2389, 2SC2459
20513	2SC2856	2SC2853, 120V	2SC1775A, 2SC2240, 2SC2389, 2SC2459
20514	2SC2857	180V, 0,05A, 0,5W, >50MHz	BF 298...299, BF 422, 2SC3467...68
20515	2SC2858	500/400V, 8A, 65W, <1/3,5μs	2SC2650, 2SC2818
20516	2SC2859	35V, 0,5A, 300MHz	BC 817...818, BCX 19...20, 2SC3341
20517	2SC285A	2SC285, 0,3A, 500MHz	BFX 55, 2SC2852
20518	2SC286	20V, 10mA, >600MHz	BF 362...363
20519	2SC2860	30V, 15mA, 650MHz	BF 225, BF 314, BF 502, BF 505, BF 507

20520	2SC2865(A)	250V, 20A, 200W, <0,9/1,9µs	BUV 11...12, BUX 11...12, BUW 58, BUW 73
20521	2SC2867	300/200V, 10A, 50W, <1/1,5µs	BUS 37, BUV 27A...28, 3SC3057, 2SC3562
20522	2SC2868	80V, 0,1A, 0,4W, 200MHz	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
20523	2SC2869	20V, 0,08A, 0,4W, 8GHz	2SC2368, 2SC2876
20524	2SC287(A)	20(A35)V, 10mA, >600MHz	BF 362...363
20525	2SC2870(L)	300/300V, 0,1A, 10W, 80MHz	2SC2924, 2SC3408, 2SC3805, 2SC4019
20526	2SC2871(L,S)	60V, 1A, 8W, B>2000, <0,2/5µs	2SC4500, 2SD1574, 2SD1598, 2SD1800
20527	2SC2872(S)	50V, 0,7A, 0,3..0,4W, 120MHz	BC 337, BC 637, BC 639, 2SD667, 2SD1226
20528	2SC2872(S)	50V, 0,7A, 0,3..0,4W, 120MHz	BC 337, BC 637, BC 639, 2SD667, 2SD1226
20529	2SC2873	50V, 2A, 100MHz, 0,1/1,1µs	2SD1422, 2SD1623
20530	2SC2875	35V, 0,1A, 0,2W, 400MHz	BSW 41, BSY 63, 2N708, 2N4123...24
20531	2SC2876	15V, 0,08A, 0,2W, 7GHz	2SC2876, 2SC3358, 2SC3603
20532	2SC2877	40V, 3A, 10W, 100MHz	BD 785, 2SD1348, 2SD1506, 2SD1818
20533	2SC2878	50V, 0,3A, 0,4W, 30MHz	2SC3615, 2SC3836, 2SD1915
20534	2SC2879	45V, 25A, PEP100W(28MHz)	-
20535	2SC288(A)	30(A35)V, 20mA, >850MHz	BF 362...363
20536	2SC2880	200V, 0,05A, 120MHz	BF 620, BF 622, BFN 20, 2SC3380
20537	2SC2881	120V, 0,8A, 120MHz	2SD1007, 2SD1418...1419
20538	2SC2882	80V, 0,4A, 100MHz	2SC3438, 2SD875, 2SD968(A)
20539	2SC2883	30V, 1,5A, 120MHz	2SC2873, 2SC2982, 2SD1621
20540	2SC2884	35V, 0,8A, 120MHz	BCX 54...56, 2SC3444, 2SC4376, 2SD1662
20541	2SC2885	330V, 2A, 15W, <1/3µs	2SC2946, 2SC3233, 2SC3631, 2SC4616
20542	2SC2886	55V, 0,75A, PQ5W(175MHz)	BLY 91, BLY 97
20543	2SC2887	55V, 1,5A, PQ14W(175MHz)	BLY 92
20544	2SC2888	55V, 3A, PQ28W(175MHz)	-
20545	2SC2889	55V, 6A, PQ40W(175MHz)	BLW 25, 2N5643, 2SC2182
20546	2SC289	25V, 10mA, >900MHz	BF 362...363
20547	2SC2890	55V, 12A, PQ84W(175MHz)	MRF 317
20548	2SC2891	55V, 15A, PQ112W(175MHz)	2SC2609
20549	2SC2892	55V, 0,75A, PQ4W(400MHz)	BLW 90, BLY 37
20550	2SC2893	55V, 1,5A, PQ10,7W(400MHz)	BLW 91
20551	2SC2894	55V, 3A, PQ22,4W(400MHz)	BLX 95, 2N6105
20552	2SC2895	55V, 6A, PQ40W(400MHz)	2SC2796
20553	2SC2896	55V, 12A, PQ63W(400MHz)	2SC2186
20554	2SC2897	55V, 15A, PQ100W(400MHz)	-
20555	2SC2898	500/400V, 8A, 50W	MJE 13006, 2SC3039, 2SC3170, 2SC4106
20556	2SC2899	500/400V, 0,5A, 10W, <1/3µs	BD 410, BUX 86...87, 2SC2752, 2SC3051
20557	2SC29	2SC28, 0,025A, 0,115W	BC 167, BC 182, BC 237, BC 547, 2N2218
20558	2SC290	70V, 2A, PQ6W(100MHz)	-
20559	2SC2900	350/300V, 4A, 90W, 10MHz	TIP 51...54, 2SC2624, 2SC3083
20560	2SC2901	40V, 0,2A, 0,6W, <12/18ns	BSS 11, BSX 19...20, 2N2368...69(A)
20561	2SC2902	<1,5/4,5µs	BUS 13(A), BUW 45...46, BUX 48(A...C)
20562	2SC2903	<1,5/4,5µs	BUS 14(A), BUS 98(A), 2SC3094, 2SC3593
20563	2SC2904	50V, 22A, PQ110W(30MHz)	-
20564	2SC2905	35V, 15A, PQ50W(520MHz)	2SC3102

20565	2SC2906	25V, 2,2A, PQ6,3W(500MHz)	-
20566	2SC2906A	2SC2906, 3A, PQ7W(500MHz)	-
20567	2SC2907	400/350V, 5A, 40W, <2/5,5μs	BU 406, BU 408, MJE 52T...53T, 2SC3056
20568	2SC2908	200/100V, 5A, 50W, <0,5/3μs	2SC2908, 2SC3263, 2SC4799
20569	2SC2909	180V, 0,07A, 0,6W, 150MHz	BF 298...299, BF 422A, 2SC3248, 2SC3467
20570	2SC291	70V, 3A, 1W, 90MHz	2N4238...4239, 2SC2214
20571	2SC2910	180V, 0,07A, 0,9W, 150MHz	BF 422A, 2SC3248...49, 2SC3467...68
20572	2SC2911	180V, 0,14A, 10W, 150MHz	BF 415, 2SC3601, 2SC4704
20573	2SC2912	2SC2911, 200V	BF 415, 2SC3601, 2SC4704
20574	2SC2913	500/400V, 7A, 40W, <1/3,5μs	MJE 13006, 2SC2739, 2SC3039, 2SC4106
20575	2SC2914	500/400V, 10A, 120W, <1/3,5μs	BUW 25...26, BUW 34...36, 2SC3043
20576	2SC2915	PQ66W(500MHz)	-
20577	2SC2917	PQ83W(175MHz)	-
20578	2SC2918	35V, 5A, PQ21W(860MHz)	-
20579	2SC292(S)	2SC291, 100V	2N4239, 2SC2214
20580	2SC2920	450V, 15A, 150W, 30MHz	BUV 25, BUW 44, BUX 25, 2SD641
20581	2SC2921	160/160V, 15A, 150W, 60MHz	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
20582	2SC2922	180/180V, 17A, 200W, 50MHz	2SC2774, 2SC3264, 2SC3858
20583	2SC2923	300/300V, 0,1A, 15W, 140MHz	BF 617, BF 758...759, BF 859
20584	2SC2924	2SC2923	2SC2870, 2SC3408, 2SC3805, 2SC4019
20585	2SC2925	60V, 0,7A, 0,75W,200MHz	2SD1582, 2SD1779
20586	2SC2926(S)	30V, 50mA, 1100MHz	BF 357, BF 377...378, BF 689K, BF 763
20587	2SC2926(S)	30V, 50mA, 1100MHz	BF 357, BF 377...378, BF 689K, BF 763
20588	2SC2927	300/300V, 0,2A, 10W, 80MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
20589	2SC2928	1500/800V, 5A, 50W	BU 208A, BU 508A, 2SD792, 2SD954
20590	2SC2929	450/400V, 3A, 40W, <1,5/2,8μs	BUT 93, TIP 75B,C, 2SC2826, 2SC3038
20591	2SC293(S)	2SC291, 130V	BUX 49...50, BUY 41
20592	2SC2930	500/400V, 30A, 200W, <1/4μs	BUS 14(A), BUS 98(A), 2SC3058
20593	2SC2931	35V, 0,6A, PQ1,7W(900MHz)	-
20594	2SC2932	35V, 2A, PQ7W(900MHz)	-
20595	2SC2933	35V, 4A, PQ16W(900MHz)	-
20596	2SC2934	300/300V, 0,2A, 12,5W, 80MHz	BF 417, BF 459, 2SC2621, 2SC3417
20597	2SC2935	2SC2934, 15W	BF 459
20598	2SC2936	500/400V, 30A, 150W, <1/4μs	BUS 14(A), BUS 98(A), 2SC3058
20599	2SC2937	500/400V, 8A, 80W, <1/3,7μs	BUP 22, TIP 58A, 2SC2788, 2SC3040
20600	2SC2938	500/400V, 10A, 100W, <1/3,7μs	BUP 23, 2SC2789, 2SC3042, 2SC4138
20601	2SC2939	500/400V, 10A, 100W, <1/2,5μs	BUP 23, 2SC2789, 2SC3042, 2SC4138
20602	2SC2940	230/230, 30A, 300W, <0,9/2μs	2SC1301, 2SC2249, 2SC2445, 2SC3224
20603	2SC2942	230/230, 50A, 200W, <1,2/2μs	2SC1437
20604	2SC2943	390/250V, 15A, 80W, 70MHz	BUP 23, 2SC2626, 2SC3520, 2SC4139
20605	2SC2944	<0,8/1,9μs	2SC2307, 2SC2626, 2SC3520, 2SC4139
20606	2SC2946(1)	330/200V, 2A, 15W, <1/3μs	2SC2885, 2SC3233, 2SC3631, BUV 93...95
20607	2SC2947	60V, 0,1A, 0,25W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
20608	2SC2948	500/400V, 50A, 300W, <1/4μs	-
20609	2SC2951	25V, 0,44A, 9,7W, 5,5GHz	-



20610	2SC2952	30V, 0,25A, 2,5GHz	2SC1199, 2SC1252, 2SC1365...66
20611	2SC2953	30V, 0,25A, 5W	BFR 65, 2SC1249...1251
20612	2SC2954	35V, 0,15A, 4000MHz	BFQ 18
20613	2SC2955	15V, 5mA, 0,05W, 4GHz	BFQ 59...60, BFQ 70...71, 2SC2143
20614	2SC2956	45V, 0,6A, PQ1,6W(2,3GHz)	-
20615	2SC2957	45V, 1,2A, PQ2,8W(2,3GHz)	-
20616	2SC2958	160/140V, 0,5A, 1W, 60MHz	2SC2383, 2SC3228, 2SC3332
20617	2SC2959	2SC2958, 160/160V	2SC2383, 2SC3228, 2SC3332
20618	2SC296	20V, 25mA, 0,2W, 180MHz	BF 240...241, BF 254...255, BF 594...595
20619	2SC2960	60V, 0,15A, 0,25W, <190/700ns	BSV 59, BSX 49, 2N3302, 2N3904
20620	2SC2961	<0,4/1,9µs	TIP 162, 2SC2537, 2SC2625, 2SC4768
20621	2SC2962	700/600V, 5A, 80W, <0,5/3µs	BU 426(A), BUW 11(A), 2SC3153, 2SC3796
20622	2SC2963	70V, 3A, 40W, <0,5/4,2µs	2SC3252, BD 241A, BD 537, BD 937
20623	2SC2964	600/400V, 15A, 150W, 28MHz	BUS 13(A), BUW 45...46, BUX 48(A...C)
20624	2SC2965	2SC2964, 600/450V	BUS 13(A), BUW 45...46, BUX 48(A...C)
20625	2SC2966	225/225V, 40A, 200W, <1/2µs	2SC2403, 2SC2366, 2SC2973, 2SD702
20626	2SC2967	30V, 0,02, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
20627	2SC2968	50V, 0,03V, 250MHz	BF 240...241, BF 254...255, BF 594...595
20628	2SC2969	36V, 4A, PQ15W(470MHz)	-
20629	2SC297	2SC291, 10W	BD 787, BD 789, MJE 240...242
20630	2SC2970	300/200V, 5A, 40W, <1,5/4,5µs	BU 406...408, MJE 51T...53T, 2SC2907
20631	2SC2971	<1,5/4,5µs	BUW 72, BUX 17A...C, BUX 43, BUY 18
20632	2SC2972	<1,5/4,5µs	BUX 13, BUY 50, MJ 15022, MJ 15024
20633	2SC2973	<1,5/4,5µs	2SC2366, 2SC2403, 2SD642, 2SD702
20634	2SC2974	<1,5/4,5µs	-
20635	2SC2975	800/400V, 5A, 40W, <1,5/4,5µs	BUT 11(A), BUV 46(A), 2SC3047, 2SC3087
20636	2SC2976	<1,5/4,5µs	BUS 12(A), BUW 26, BUW 35...36, BUX 81
20637	2SC2977	<1,5/4,5µs	2SC2204, 2SD295
20638	2SC2978	<1,5/4,5µs	-
20639	2SC2979	900/800V, 3A, 40W, <1/4µs	BUT 11A, BUT 56A, BUV 46A, 2SC3150
20640	2SC298	2SC292, 10W	BD 791, MJE 243...244
20641	2SC2980	900/800V, 5A, 80W, <1/4µs	-
20642	2SC2981	900/800V, 8A, 100W, <1/4µs	BU 526, BU 536, BUV 47A, BUW 12A
20643	2SC2982	30V, 2A, 150MHz	2SD1621, 2SD1623
20644	2SC2983	160/160V, 1,5A, 15W, 100MHz	2SC4027, 2SD1033, 2SD1080...82, 2SD1918
20645	2SC2984	45V, 6A, PQ25W(890MHz)	-
20646	2SC2985	45V, 2A, PQ7,9W(890MHz)	-
20647	2SC2986	40V, 0,05A, 0,3W, 350MHz	BF 370, BF 920...921S, BF 959
20648	2SC2987	140/140V, 12A, 120W, 50MHz	2SD1047
20649	2SC2987A	2SC2987, 160/160V	2SD1047
20650	2SC2988	36V, 0,5A, PQ2,2W(175MHz)	-
20651	2SC2989	36V, 1A, PQ10,5W(175MHz)	-
20652	2SC299	2SC293, 10W	BDX 36...37
20653	2SC2991	36V, 0,6A, PQ2,3W(470MHz)	-
20654	2SC2992	36V, 1,5A, PQ11W(470MHz)	-



20655	2SC2995	2SC2986, 0,2W	2SC2986
20656	2SC2996	2SC2986, SMD	BF 599, BF 799, BFS 20, 2SC3015
20657	2SC2997	20V, 0,08A, 0,35W, 8GHz	2SC2876, 2SC3062, 2SC3358, 2SC3603
20658	2SC2998	2SC2960, 0,5W	2SC2960
20659	2SC2999	25V, 30mA, 750MHz	BF 225, BF 314, BF 502, BF 505, BF 959
20660	2SC30	60V, 0,08A, 0,5W, 280MHz	BFW 16...17, BFX 55, 2N3725, 2SC1385
20661	2SC300	25V, 0,1A, 0,26W, 400MHz	BSW 41, BSY 62...63, 2N706A, 2N708
20662	2SC3000	2SC2839, 0,25W	2SC2839
20663	2SC3001	20V, 3A, PQ7W(175MHz)	2SC1729
20664	2SC3004	30V, 3A, 10W, B>2000	BD 675, BD 775, 2N6037...6039
20665	2SC3005	15V, 0,05A, 1600MHz	BFS 17, 2SC3005, 2SC3016
20666	2SC3006	35V, 1A, PQ>3W(470MHz)	2SC3020
20667	2SC3007	50V, 2A, 8W(Tc25°), 100MHz	BC 440...441, BSS 15...16, 2N5320...21
20668	2SC3008	35V, 10A, PQ40W(175MHz)	-
20669	2SC3009	25V, 1,5A, PQ3,5W(860MHz)	-
20670	2SC301	2SC300	BSW 41, BSY 62...63, 2N706A, 2N708
20671	2SC3010	25V, 3A, PQ5,5W(860MHz)	-
20672	2SC3011	20V, 0,03A, 6,5GHz	BFR 182, 2SC3583, 2SC3585
20673	2SC3012	130V, 10A, 100W, 60MHz	2SC2706, 2SC2837, 2SC2987(A)
20674	2SC3013	15V, 0,05A, 900MHz	BF 599, BF 799, BFS 20, 2SC3015
20675	2SC3014	15V, 0,05A, 3,4GHz	BFT 75, 2SC3773
20676	2SC3015	15V, 0,05A, 1100MHz	BF 599, BF 799, BFS 20, 2SC3130
20677	2SC3016	10V, 0,05A, 1450MHz	BFS 17, 2SC3005, 2SC3077
20678	2SC3017	20V, 0,6A, PQ1,7W(175MHz)	-
20679	2SC3018	20V, 1,5A, PQ3,5W(175MHz)	-
20680	2SC3019	35V, 0,4A, PQ0,6W(520MHz)	BLW 12
20681	2SC302	2SC300, 50V	BSV 59, BSX 48...49, 2N3903...3904
20682	2SC3020	35V, 1A, PQ3,3W(520MHz)	2SC3006
20683	2SC3021	35V, 2A, PQ8W(520MHz)	2SC1967
20684	2SC3022	35V, 7A, PQ22W(520MHz)	2SC2695
20685	2SC3023	1500V, 3A, 50W, <2/5,5µs	BU208...209A, BU705, 2SD850, 2SD1494
20686	2SC3024	2SC3023, 1700/800V	BU 209A, 2SD784...785, 2SD1434
20687	2SC3025	<1,5/5,5µs	BU 208A, BU 508A, 2SD649, 2SD821
20688	2SC3026	2SC3025, 1700/800V	2SC3028
20689	2SC3027	1500/800V, 8A, 50W, <2/5,5µs	BU 508A, BU 908, BU 2508A, 2SC4801
20690	2SC3028	2SC3027, 1700/800V	-
20691	2SC3029	15V, 5mA, 0,05W, 4GHz	BFG 90...91, BFQ 85
20692	2SC303	50V, 0,5A, 0,8W, 200MHz	BC 140...141, BC 300...302, 2N3053
20693	2SC3030	900/800V, 7A, 80W, B15	-
20694	2SC3031	2SC3030	BUT 16
20695	2SC3032	2SC3030, 900/700V	-
20696	2SC3033	2SC3030, 900/700V	BUT 16
20697	2SC3034	250/200V, 10A, 100W, <1/3µs	BUX 17(A...C), BUX 42...43, BUY 18
20698	2SC3035	300/200V, 5A, 40W, <1,5/4,5µs	BU 406...408, 2N6234...35, 2SC2907
20699	2SC3036	2SC3035, 800/400V	BUT 11(A), BUV 46(A), 2SC3047, 2SC3087

20700	2SC3037	20V, 0,07A, 0,4W, 5GHz	2SC2570(A), 2SC3337, 2SC3606
20701	2SC3038	500/400V, 4A, 40W, <1/3,5μs	BUT 93, 2SC2535, 2SC2827, 2SC4105
20702	2SC3039	500/400V, 7A, 50W, <1/3,5μs	MJE 13006, 2SC2739, 2SC3170, 2SC4106
20703	2SC304	60V, 0,5A, 0,8W, 220MHz	BC 140...141, BC 300...302, 2N3053
20704	2SC3040	500/400V, 8A, 80W, <1/3,5μs	BUP 22, TIP 58A, 2SC2536, 2SC2788
20705	2SC3041	2SC3040	BUW 25, BUW 34, 2SC2536, 2SC2788
20706	2SC3042	500/400V, 12A, 100W, <1/3,5μs	BUP 23, 2SC3520, 2SC4139, 2SC4434
20707	2SC3043	2SC3042, 120W	BUW 75...77, 2SC3411, 2SC3451, 2SD641
20708	2SC3044	450/400V, 6A, 100W, 30MHz	BUP 22, BUX 44, 2SC2656, 2SD640
20709	2SC3044A	2SC3044, 450/450V	BUP 22, BUX 44, 2SC2656, 2SD640
20710	2SC3045	450/400V, 10A, 100W, 32MHz	BUW24...26, BUW34...36, 2SC3520, 2SC4138
20711	2SC3046	600/450V, 10A, 100W, 28MHz	BUW 25...26, BUW 35...36, 2SC3451
20712	2SC3047	850/500V, 6A, 40W, <1/4μs	BUT 11(A), BUT 56(A), BUV 46(A)
20713	2SC3048	2SC3047, 50W	BU 426A, BU 526, BUX 47(A), 2SD811
20714	2SC3049	2SC3047, 10A, 50W	BU 626A, BUS 12(A), BUW 36, 2SD1094
20715	2SC305	80V, 0,5A, 0,8W, 220MHz	BC 140...141, BC 300...301, 2N1990
20716	2SC3050	1200/800V, 5A, 150W, -/<4,5μs	BU 546, BU 903, 2SC3214, 2SC3343
20717	2SC3051	500/400V, 0,8A, 10W, -/4μs	BD 410, 2SC3840
20718	2SC3052	2SC2320, SMD	BC 846...847, BCW 71...72, BCW 81
20719	2SC3053	2SC710, SMD	BF 799, BFS 20, 2SC3015
20720	2SC3054	500/400V, 20A, 100W, <3/4μs	BU 932PFI, BUT 13PFI
20721	2SC3055	450/400V, 2A, 15W, 28MHz	BUX 84...85, 2SC2333, 2SC2534, 2SC2738
20722	2SC3056	450/400V, 6A, 50W, 30MHz	MJE 53T, 2SC2518, 2SC2542, 2SC2827
20723	2SC3056A	2SC3056, 450/450V	MJE 53T, 2SC2518, 2SC2542, 2SC2837
20724	2SC3057	2SC3045, 50W	MJE 13008, 2SC3562, 2SC4107, 2SC4164
20725	2SC3058	600/400V, 30A, 200W, 30MHz	BUS 14(A), BUS 98(A)
20726	2SC3058A	2SC3058, 600/450V	BUS 14(A), BUS 98(A)
20727	2SC3059	1200/850V, 2A, 100W, 15MHz	BU 204...206, MJ 8500, 2SC1132, 2SD1097
20728	2SC306	/450ns	BC 140...141, BC 300...302, 2N3053
20729	2SC3060	1200/850V, 5A, 100W, 15MHz	BU 207...208(A), MJ 8502, 2SD1103
20730	2SC3061	1200/850V, 10A, 200W, 15MHz	BU 137A, MJ 8504...8505, 2SC3215
20731	2SC3062	25V, 0,065A, 0,4W, 8,5GHz	2SC3584
20732	2SC3063	300/300V, 0,1A, 140MHz	BF 417, BF 459, 2SC3417, 2SC3503
20733	2SC3068	30V, 0,3A, B>800	2SC3576, 2SC3836
20734	2SC3069	60V, 0,2A, B>800	2SC2925, 3SC3836, 2SC3071
20735	2SC307	2SC306, 80V	BC 140...141, BC 300...301, 2N1990
20736	2SC3070	30V, 1,2A, B>800	2SC4389, 2SD1581...82, 2SD1779
20737	2SC3071	120V,0,2A, B>500	-
20738	2SC3072	50V, 5A, 10W, 100MHz	2SC3074, 2SC3518, 2SC3592, 2SD1803
20739	2SC3073	30V, 3A, 15W, 100MHz	2SC3386, 2SC4681, 2SD1221, 2SD1802
20740	2SC3074	60V, 5A, 20W, 120MHz	2SC3303, 2SC3518, 2SC3592, 2SD1803
20741	2SC3075	500/400V, 0,8A, 10W, -/<4μs	2SC3363, 2SC3632
20742	2SC3076	50V, 2A, 10W, 80MHz	2SD1801...02, 2SD1078, 2SD1221
20743	2SC3077	30V, 20mA, 1100MHz	BFS 17, 2SC3005, 2SC3016, 2SC3161
20744	2SC3078(M)	40V, 0,1A, 0,25W, 230MHz	BF 240...241, BF 254...255, BF 594...595

20745	2SC3079(M)	25V, 20mA, 0,15W, 500MHz	BF 225, BF 310, BF 314, BF 502...503
20746	2SC308	2SC306, 100V, 90MHz	BC 141, BC 300, 2N1889...90, 2N1893(A)
20747	2SC3080(M)	30V, 50mA, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
20748	2SC3081	30V, 0,05A, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
20749	2SC3082	30V, 50mA, 1100MHz	-
20750	2SC3082K	2SC3082	BF 771, BFR 35, 2SC3014, 2SC3016
20751	2SC3083	500/400V, 6A, 60W, <1/3,5µs	BUP 22, TIP 58A, 2SC2962, 2SC3040
20752	2SC3084	2SC3083, 70W	BUX 15, 2SD640, 2SC2962, 2SC3041
20753	2SC3085	500/400V, 25A, 160W, <1/3,5µs	BUS 14(A), BUS 98(A), 2SC2930, 2SC3058
20754	2SC3086	800/500V, 3A, 40W, <1/4µs	BUT 11(A), BUV 46(A), 2SC3148, 2SD841
20755	2SC3087	800/500V, 5A, 50W, <1/4µs	BUT 11(A), BUV 46(A), 2SC3047, 2SC3353
20756	2SC3088	800/500V, 4A, 60W, <1/4µs	BU 426(A), BUW 11(A), 2SC3448, 2SC3796
20757	2SC3089	800/500V, 7A, 80W, <1/4µs	BU 426(A), BU 926, 2SC3449, 2SC3536
20758	2SC309	2SC306, 120V, 120MHz	BC 300, 2N1893(A), 2N2102, 2N2405
20759	2SC3090	800/500V, 10A, 100W, <1/4µs	BUW 12(A), BUV 47(A), 2SC3450, 2SC3637
20760	2SC3091	800/500V, 4A, 70W	2SC3152, 2SC3155, 2SC3550, 2SD802
20761	2SC3092	800/500V, 7A, 90W	BU 526, BU 926, BUX 47, 2SC3449, 2SD811
20762	2SC3093	800/500V, 10A, 120W	BU 626A, BUS 12A, BUW 35...36, 2SC3637
20763	2SC3094	800/500V, 20A, 140W, <1/3,5µs	BUS 14(A), BUS 98(A), 2SC3593
20764	2SC3095	25V, 0,11A, 2,75W, 6,5GHz	-
20765	2SC3096	25V, 0,22A, 5,5W, 6GHz	-
20766	2SC3098	30V, 0,05A, 3,5GHz	BFT 75, 2SC3014, 2SC3773
20767	2SC3099	20V, 0,03A, 4GHz	BFQ 29, BFQ 81, BFR 93, BFT 75
20768	2SC31(S)	B>20	BC 140...141, BC 300...302, 2N3053
20769	2SC310	2SC306, 140V, 120MHz	BSS 43, BSW 68, 2N1893A, 2N3019...20
20770	2SC3101	35V, 1A, PQ3,5W(520MHz)	-
20771	2SC3102	35V, 18A, PQ65W(520MHz)	-
20772	2SC3103	20V, 1,5A, PQ3,2W(520MHz)	-
20773	2SC3104	20V, 3A, PQ7W(520MHz)	-
20774	2SC3105	35V, 10A, PQ35W(850MHz)	-
20775	2SC3109	36V, 0,3A, PQ0,6W(940MHz)	-
20776	2SC3110	15V, 0,03A, 4,5GHz	BFR 92...93, BFT 75
20777	2SC3111	36V, 0,1A, 2W, 2,5GHz	BFG 34, BFG 96, 2SC3368
20778	2SC3112	50V, 0,15A, 0,4W, B1500	-
20779	2SC3113	2SC3112, 0,2W	-
20780	2SC3114	60V, 0,15A, 0,4W, 100MHz	2SC3071, 2SC3135, (BC 546)
20781	2SC3115	120V, 0,05A, 110MHz	2SC1622A, 2SC3324, 2SC4050
20782	2SC3116	180/160V, 0,7A, 10W, 120MHz	2SC3116...17, 2SD669
20783	2SC3117	180/160V, 1,5A, 10W, 120MHz	2SD669
20784	2SC3118	<300/2300ns	MPSA 45, 2SC2267, 2SC3469, 2SD1385
20785	2SC3119	25V, 20mA,900MHz	BFS 17, 2SC3015, 2SC3161, 2SC3374
20786	2SC3120	30V, 2,4GHz	BFR 53, 2SC3014, 2SC3773
20787	2SC3121	30V, 0,05A, 1,5GHz	BFR 53, 2SC3013...3016, 2SC3773
20788	2SC3122	30V, 20mA,650MHz	BF 799, 2SC3015, 2SC3374
20789	2SC3123	30V, 0,05A, 1,4GHz	BFR 53, 2SC3014, 2SC3016, 2SC3773

20790	2SC3124	30V, 1,1GHz	BFR 53, 2SC3014...3016, 2SC3773
20791	2SC3125	30V, 0,05A, 600MHz	BF 599, BF 799, BFS 20, 2SC3014...3016
20792	2SC3126	20V, 0,05A, 0,2W, 4,5GHz	BFP 91, BFQ 72, 2SC3511
20793	2SC3127	2SC3126, SMD	BFT 75, 2SC2845, 2SC3161, 2SC3774
20794	2SC3128	2SC3126, 0,35W	2SC2570(A), 2SC3037, 3SC3512
20795	2SC3129L,S	500/400V, 0,5A, 10W, <1/3,5µs	2SC3075, 2SC3588, 2SC3632, 2SC4499
20796	2SC313(H)	30V, 50mA, 1000MHz	BF 377...378, BF 689, BF 763, 2N2857
20797	2SC3130	15V, 0,05A, 1900MHz	BFR 53, 2SC3014, 2SC3016
20798	2SC3131	600/400V, 10A, 100W, <1/5µs	2SD1094
20799	2SC3132(L,S)	30V, 3A, 10W, B10000	2SD1222...23, 2SD1520, 2SD1799, 2SD1817
20800	2SC3133	60V, 6A, PQ16W(27MHz)	2SC1945
20801	2SC3134	60V, 0,15A, 100MHz	BC 846, BCV 71...72, 2SC3324
20802	2SC3135	60V, 0,2A, 0,25W, 100MHz	2SC3071, 2SC3114
20803	2SC3136	30V, 0,05A, 1400MHz	BF 377...378, BF 689K, BF 763, 2N2857
20804	2SC3137	30V, 0,05A, 0,2W, 2400MHz	2SC2464, 2SC2466, 2SC2353, 2SC2728
20805	2SC3138	200V, 0,05A, 100MHz	BF 820, BF 822, BFN 22, 2SC3360
20806	2SC3139	50V, 1A, PQ2,4W(900MHz)	BLW 33
20807	2SC314	75V, 1,2A, 20W, 70MHz	BD 139, BD 230, BD 377, 2SD1177...1178
20808	2SC3140	50V, 2A, PQ5,4W(900MHz)	BLW 98
20809	2SC3141	50V, 4A, PQ10,7W(900MHz)	2N4431
20810	2SC3142	25V, 0,03A, 750MHz	BF 599, BF 799, 2SC3015, 2SC3374
20811	2SC3143	180/160V, 0,08A, 150MHz	BFN 24, BFN 26, 2SC3360
20812	2SC3144	70V, 3A, 20W, 200MHz, B5000	BDT 61A...C, BDW 53B...D
20813	2SC3145	70V, 5A, 30W, 200MHz, B5000	BDT 63A...C, BDX 33B...D
20814	2SC3146	70V, 7A, 40W, B5000	BDT 63A...C, BDX 33B...D
20815	2SC3147	36V, 14A, PQ60W(175MHz)	BLV 75/12, MRF 245
20816	2SC3148	900/800V, 3A, 40W	-
20817	2SC3149	900/800V, 1,5A, 40W, 15MHz	BUV 36A, BUX 85, 2SC3491, 2SC3531
20818	2SC315(H)	2SC314, 80MHz	BD 139, BD 230, BD 377, 2SD1177...1178
20819	2SC3150	900/800V, 3A, 40W, 15MHz	BUT 11A, BUV 46A, 2SC3490...3491
20820	2SC3151	900/800V, 1,5A, 60W, 15MHz	BUW 11A, 2SC3285, 2SC3152, 2SC3550
20821	2SC3152	900/800V, 3A, 80W, 15MHz	BUW 11A, 2SC3285, 2SC3152, 2SC3550
20822	2SC3153	900/800V, 6A, 100W, 15MHz	BUW 11A, BUW 131A, 2SC3535, 2SC3796A
20823	2SC3154	2SC3151, 70W	BUS 11A, BUW 11A, BUX 46A, 2SC3285
20824	2SC3155	2SC3152, 90W	BUS 11A, BUW 11A, BUX 46A, 2SC3285
20825	2SC3156	2SC3153, 120W	BUS 11A, BUX 47A, BUX 83, 2SD811
20826	2SC3157	150/100V, 10A, 60W, <0,5/2µs	BD 743E, 2SC4330
20827	2SC3157	150/100V, 10A, 60W, <0,5/2µs	BD 743E, 2SC4330
20828	2SC3158	500/400V, 7A, 60W, <1/3,5µs	MJE 13006, 2SC2335, 2SC3170, 2SC4106
20829	2SC3158	500/400V, 7A, 60W, <1/3,5µs	MJE 13006, 2SC2335, 2SC3170, 2SC4106
20830	2SC3159	500/400V, 10A, 80W, <1/3,2µs	MJE 13008...09, 2SC3562, 2SC4107
20831	2SC3159	500/400V, 10A, 80W, <1/3,2µs	MJE 13008...09, 2SC3562, 2SC4107
20832	2SC316	45V, 0,03A, 0,3W, 50MHz	BC 184, BC 413...414, BC 550, 2SC2240
20833	2SC3160	200/100V, 7,5A, 40W, <2/4µs	BU 406D...408D, 2SC3174, 2SC3176
20834	2SC3160	200/100V, 7,5A, 40W, <2/4µs	BU 406D...408D, 2SC3174, 2SC3176

20835	2SC3161	25V, 0,07A, 5GHz	2SC2845, 2SC3704, 2SC3774
20836	2SC3162	<300/1100ns	BUT 11(A), BUT 93, TIP 75C, 2SC4105
20837	2SC3163	<300/1100ns	MJE 13006, 2SC2827, 2SC4055, 2SC4106
20838	2SC3164	<300/1100ns	BUP 23, 2SC3435, 2SC4138, 2SC4434
20839	2SC3165	<300/1100ns	BUT 93, BUY 63...64, 2SC1467, 2SC2826
20840	2SC3166	<300/1100ns	MJE 13070, 2SC3170, 2SC4055, 2SC4106
20841	2SC3167	<300/1100ns	BUW 25...26, BUW 34...36, 2SC3046
20842	2SC3168	<300/1100ns	2SC3085, 2SC3094, 2SC3593
20843	2SC3169	500/400V, 2A, 25W, <1/4μs	BUX 84F...85F, 2SC4421, 2SC4533
20844	2SC317(H)	70V, 0,1A, 0,35W, <80/200ns	BF 297...299, BFR 86, BSS 38, BSX 21
20845	2SC3170	500/400V, 7A, 40W, <1/4μs	BU 306F, 2SC3571, 2SC4161, 2SC4559
20846	2SC3171	500/400V, 10A, 100W, <1/4μs	BUP 23, 2SC3435, 2SC4434, 2SC4138
20847	2SC3172	30V, 0,05A, 0,2W, 1400MHZ	2SC2465, 2SC2470, 2SC2368
20848	2SC3173	330/150V, 7A, 50W, 40MHZ	BU 406...408, 2SC3590...91, 2SD884...885
20849	2SC3174	2SC3173	BU 104DP, BU 406D...408D
20850	2SC3175	2SC3173, 400/200V	BU 104P, BU 406, BU 408, 2SC3591
20851	2SC3176	2SC3174, 400/200V	BU 104DP, BU 406D, BU 408D
20852	2SC3177	15V, 0,05A, 0,25W, 1900MHZ	BF 357, BF 377...378, 2SC2570(A)
20853	2SC3178	2SC3059, 60W	BU 505, MJE 8500...8501, 2SC4230
20854	2SC3179	80V, 4A, 30W, 15MHZ	2SC3253, 2SD1236L, BD 537, BD 539B
20855	2SC317A	2SC317, 100V, 180MHZ	BF 297, 299, BFR 86, BSS 38, BSX 21
20856	2SC318(A)	50V, 0,1A, 0,3W, 170MHZ	BC 237, BC 547, 2N2221...22, 2N3903...04
20857	2SC3180	80V, 6A, 60W, 30MHZ	BD 245B, BDV 93, 2SC2706, 2SC2837
20858	2SC3181	2SC3180, 120V, 8A, 80W	BD 245C, 2SC2681, 2SC2837, 2SC2987(A)
20859	2SC3182	2SC3180, 140V, 10A, 100W	BD 245D, 2SC2706, 2SC2837, 2SD1047
20860	2SC3183	900/800V, 0,2A, 25W, 15MHZ	2SC3149, 2SC3675...76, 2SD1527
20861	2SC3184	900/800V, 0,5A, 30W, 15MHZ	2SC3149, 2SC3456, 2SC3676, 2SD1527
20862	2SC3185	35V, 0,4A, PQ1,4W(500MHZ)	BFS 50, MRF 629, 2N3948, 2SC2762
20863	2SC3186	B2000	2SD834, 2SD1073, 2SD1085, 2SD1121
20864	2SC3187	140MHZ	BF 299, BF 393, BF 420A, 2SC3468
20865	2SC3189	250/100V, 7,5A, 50W	BU 406...408, 2SC3173, 2SC3175
20866	2SC319	40V, 0,3A, PQ1,2W(200MHZ)	BFR 98, BFX 55, BLW 16, MRF 225
20867	2SC3190	35V, 0,1A, 0,4W, 120MHZ	BC 238, BC 548, BF 920...921(S), BF 959
20868	2SC3191	2SC3190, 0,2W	BC 238, BC 548, BF 920...921(S), BF 959
20869	2SC3192	35V, 0,05A, 175MHZ	BF 240...241, BF 254...255, BF 594...595
20870	2SC3193	2SC3192	BF 240...241, BF 254...255, BF 594...595
20871	2SC3194	40V, 0,02A, 550MHZ	BF 225, BF 241, BF 255, BF 314, BF 502
20872	2SC3195	2SC3194	BF 225, BF 241, BF 255, BF 314, BF 502
20873	2SC3196	40V, 0,05A, 530MHZ	BF 198, BF 225, BF 310, BF 367, BF 596
20874	2SC3197	30V, 0,05A, 660MHZ	BF 198...199, BF 224...225, BF 596...597
20875	2SC3198	60V, 0,15A, 0,4W, 130MHZ	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
20876	2SC3199	2SC3198, 0,2W	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
20877	2SC32(A,AN,M,N)	2SC32, B>40	BC 140...141, BC 300...302, 2N3053
20878	2SC320	40V, 0,5A, PQ2,4W(200MHZ)	BFS 22, BFW 46, BLY 33, MRF 237, 2N3924
20879	2SC3200	120V, 0,1A, 0,3W, 100MHZ	2SC1775A, 2SC2240, 2SC2362, 2SC2459



20880	2SC3201	2SC3200, 0,2W	2SC1775A, 2SC2240, 2SC2362, 2SC2459
20881	2SC3202	35V, 0,5A, 0,3W, 300MHz	BC 337...338, BC 635, BC 637, 2SC3377
20882	2SC3203	35V, 0,8A, 0,6W, 120MHz	BC 337...338, BC 635, BC 637, 2SD2322S
20883	2SC3204	2SC3203, 0,3W	2SC3203
20884	2SC3205	30V, 2A, 1W, 120MHz	2SC3328, 2SD1014, 2SD1146, 2SD1207
20885	2SC3206	200V, 0,05A, 0,8W, 120MHz	BF 422(A), 2SC3467...69, 2SC3249
20886	2SC3207	300V, 0,1A, 0,9W, 70MHz	2SC3468...69, 2SC3249, BF 459, 2SC4019
20887	2SC3208	300/300V, 0,15A, 100MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
20888	2SC3209	300/300V, 0,2A, 1W, 50MHz	BF 299, BF 393, BFR 89, 2SC3468
20889	2SC321	B>30	BSS 11, BSX 19...20, 2N2368...69(A)
20890	2SC3210	500/400V, 10A, 100W, <1/3,5µs	2SC4297, 2SC4423
20891	2SC3212	800/500V, 7A, 100W, <1/3,5µs	BUV 47(A)FI, BUW 12(A)F, 2SC4301
20892	2SC3212A	2SC3212, 900/500V, <1,2/3,7µs	BUV 47AFI, BUW 12AF, 2SC4301
20893	2SC3214	1200/800V, 5A, 80W	MJ 8502...8503, 2SC3060, 2SC3343, 2SC3387
20894	2SC3215	1200/800V, 10A, 125W, <1/5µs	BUV 48B,C, MJ 8504...8505, 2SC3061
20895	2SC3216	1200/800V, 20A, 200W	-
20896	2SC3217	50V, 12A, PQ10W(860MHz)	-
20897	2SC3218	55V, 15A, PQ60W(860MHz)	-
20898	2SC3219	230/230V, 6A, 50W, <300/600ns	BU 409, MJE 51T...53T, 2SC2767
20899	2SC322	2SC321, B40	BSS 11, BSX 19...20, 2N2368...69(A)
20900	2SC3220	<300/600ns	TIP 160...162, 2SC2729, 2SC2944
20901	2SC3221	230/230V, 6A, 80W, <300/600ns	BU 409, TIP 150...152, 2SC1987, 2SC2767
20902	2SC3222	<300/600ns	BUX 17(A...C), BUX 42...43, 2SC2944
20903	2SC3223	<300/600ns	BUV 11...12, BUW 58, BUW 73, BUX 11...12
20904	2SC3224	<300/600ns	2SC1301, 2SC2249, 2SC2445, 2SC2940
20905	2SC3225	40V, 2A, 220MHz, B>500	-
20906	2SC3226	30V, 2A, 0,9W, 150MHz	2SC3328, 2SD1014, 2SD1146, 2SD1207
20907	2SC3227	80V, 0,4A, 0,8W, 100MHz	2SC3939, 2SD667(A), 2SD1937, 2SD1211
20908	2SC3228	160/160V, 1A, 0,9W, 120MHz	2SC2383, 2SD1812
20909	2SC3229	300/300V, 0,05A, 95MHz	BF 583, BF 617, BF 758...759, BF 859
20910	2SC323	40V, 0,1A, 0,25W, 250MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
20911	2SC3230	30V, 3A, 10W, 100MHz	2SC1173, 2SC2562, 2SC3252...3253
20912	2SC3231	<3/9,5µs	BD 243F, 2SC2767, 2SD772A,B
20913	2SC3232	900/400V, 6A, 80W, <0,5/4µs	BU 426A, BUW 11A, 2SC3535, 2SC3796A
20914	2SC3233	500/400V, 2A, 20W, <1/3,5µs	2SC3631, BUV 93...95
20915	2SC3234	150/150V, 1,5A, 25W, 4MHz	2SC1669, 2SC2073, 2SD608(A), 2SD1138
20916	2SC3235	500/400V, 2A, 20W, <1/3,5µs	BUX 84...85, 2SC2333, 2SC2534, 2SC2738
20917	2SC3236	500/400V, 5A, 60W, <1/3,5µs	MJE 13070, 2SC2535, 2SC2827, 2SC3830
20918	2SC3237	30V, 3A, 20W, 100MHz	2SC1173, 2SC2562, 2SC3252...53, 2SD1505
20919	2SC3238	160V, 1,5A, 25W, 100MHz	2SC2238(A,B), 2SC2344, 2SD608(A)
20920	2SC3239	60V, 5A, 25W, 120MHz	2SC2562, 2SC3253...54, 2SC3258
20921	2SC324	20V, 25mA, 0,2W, 180MHz	BF 240...241, BF 254...255, BF 594...595
20922	2SC3240	50V, 25A, PQ110W(30MHz)	2SC2879
20923	2SC3241	50V, 18A, PQ85W(30MHz)	MRF 421, MRF 454
20924	2SC3242(A)	20V, 2A, 0,9W, 80MHz	2SC3226, 2SD787...788, 2SD1146, 2SD1207



20925	2SC3243	60V, 1A, 0,9W, 120MHz	2SD667, 2SD863, 2SD1207, 2SD1292
20926	2SC3244	100V, 0,5A, 0,9W, 130MHz	2SC1670, 2SC2235, 2SD1211, 2SD1937
20927	2SC3245	120/120V, 0,1A, 0,9W, 200MHz	2SC2631...32, 2SC3248, 2SC3800
20928	2SC3245A	2SC3245, 150/150V	2SC2632, 2SC3248, 2SC3800
20929	2SC3246	B>400	2SC3225, 2SC4389
20930	2SC3247	50V, 1A, 0,9W, 130MHz, B>600	2SC3225
20931	2SC3248	180/180V, 0,1A, 0,9W, 130MHz	BF 422A, 2SC3467...69, 2SC3249
20932	2SC3249	300/250V, 0,1A, 0,9W, 80MHz	BF 420A, 2SC3468...69, 2SC4166
20933	2SC325	12V, 0,05A, 0,25W, 1000MHz	BFR 37, BFW 30, BFX 73, 2SC2570(A)
20934	2SC3250	300/300V, 0,1A, 15W, 100MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
20935	2SC3251	55V, 0,4A, 15W, 700MHz	-
20936	2SC3252	80V, 3A, 30W, 100MHz	BDV 10...12, MJE 15028, 2SC3259
20937	2SC3253	80V, 5A, 30W, 100MHz	2SC3258
20938	2SC3254	80V, 7A, 35W, 100MHz	2SC3346
20939	2SC3255	80V, 10A, 40W, 100MHz	2SC3346
20940	2SC3256	80V, 15A, 70W, 100MHz	2SD1238L, 2SD1840
20941	2SC3257	250/200V, 10A, 40W, <1/3,5µs	BUS 36...37, BUV 27(A), 2SC2867
20942	2SC3258	100/80V, 5A, 30W, 120MHz	-
20943	2SC3259	800/800V, 3A, 40W, B10	BUD 46A
20944	2SC326	20V, 0,05A, 0,25W, 1000MHz	BFR 37, BFW 30, BFX 73, 2SC2570(A)
20945	2SC3260	2SC3259, 50W	2SC3472
20946	2SC3261	800/800V, 6A, 80W, B10	2SC3030, 2SC3032
20947	2SC3262	800/800V, 10A, 100W, B10	BUT 51P
20948	2SC3263	230/230V, 15A, 130W, 60MHz	2SC2944
20949	2SC3264	230/230V, 17A, 200W, 60MHz	2SC3436
20950	2SC3265	35V, 0,8A, 120MHz	BCW 65...66
20951	2SC3266	20V, 2A, 0,75W, 120MHz	MPS 650, 2SC3205, 2SC3226, 2SD1207
20952	2SC3267	2SC3266, 0,4W	MPS 650, 2SC3205, 2SC3226, 2SD1207
20953	2SC3268	17V, 0,07A, 0,3W, 5GHz	BFQ 19, 2SC3301
20954	2SC3269	100MHz	BF 420A, 2SC3249, 2SC3468...69, 2SC4166
20955	2SC327	30V, 0,05A, 0,25W, 1000MHz	BFR 37, BFW 30, BFX 73, 2SC2570(A)
20956	2SC3270(M)	2SC3269	2SC3296
20957	2SC3270(M)	2SC3269	2SC3296
20958	2SC3271	2SC3269, 5W	2SC3789...90, 2SC4828
20959	2SC3272	2SC3269, 10W	BF 417, BF 459, 2SC2621, 2SC3417
20960	2SC3273	15V, 0,05A, 0,4W, 2,5GHz	2SC2498, 2SC2570(A), 2SC3037
20961	2SC3274	15V, 0,05A, 0,4W, 1,3GHz	BF 357, 2SC2498, 2SC2570(A), 2SC3037
20962	2SC3275	15V, 0,05A, 0,4W, 1,8GHz	BF 357, 2SC2498, 2SC2570(A), 2SC3037
20963	2SC3276	15V, 0,03A, 0,35W, 7GHz	BFG 65, BFQ 182, 2SC1923, 2SC3062
20964	2SC3277	500/400V, 10A, 90W, 20MHz	BUP 23, 2SC3042, 2SC4138, 2SC4434
20965	2SC3278	2SC3277, 100W	BUS 12(A), BUW 25...26, BUW 34...36
20966	2SC3279	30V, 2A, 0,75W, 150MHz	MPS 650, 2SC3205, 2SC3226, 2SD1207
20967	2SC328	30V, 0,02A, 0,2W, 1500MHz	BFR 37, BFW 30, BFX 73, 2SC2570(A)
20968	2SC3280	160/160V, 12A, 120W, 30MHz	2SC4029, 2SD1704, 2SD1717...18, 2SD2029
20969	2SC3281	200/200V, 15A, 150W, 30MHz	2SC4029

20970	2SC3282(A)	35V, 7,5A, PQ23W(860MHz)	BLV 95, MRF 844
20971	2SC3283(A)	35V, 15A, PQ37W(860MHz)	-
20972	2SC3284	150/150V, 14A, 125W, 60MHz	2SC2987(A), 2SC3907, 2SD1047, 2SD1703
20973	2SC3285	1000/800V, 3A, 70W, <1/3μs	2SC3533...35
20974	2SC3286	55V, 24A, PQ126W(230MHz)	-
20975	2SC3287	36V, 0,1A, PQ80mW(915MHz)	2SC3368
20976	2SC3288	36V, 0,3A, PQ0,35W(915MHz)	2SC3369, 2SC3019
20977	2SC329	30V, 0,02A, 0,2W, 1500MHz	BFR 37, BFW 30, BFX 73, 2SC2570(A)
20978	2SC3292	B4000	-
20979	2SC3293	50V, 2A, 20W, 180MHz, B4000	-
20980	2SC3294	50V, 3A, 25W, 180MHz, B4000	-
20981	2SC3295	50V, 0,15A, 250MHz, B>600	2SC3624
20982	2SC3296	150/150V, 1,5A, 20W, 4MHz	2SC3298(A,B), 2SC3364, 2SC3567, 2SC4159
20983	2SC3297	30V, 3A, 15W, 100MHz	2SC3299, 2SC4369, 2SD1913
20984	2SC3298	160/160V, 1,5A, 20W, 100MHz	2SC3364, 2SC4159, 2SC4370
20985	2SC3298A	2SC3298, 180V	2SC4159, 2SC4883A
20986	2SC3298B	2SC3298, 200V	2SC4793
20987	2SC3299	60V, 5A, 20W, 120MHz	2SC3746...47, 2SC4881
20988	2SC33	45V, 50mA, 250MHz	BF 184...185, BF 240...241, BF254...255
20989	2SC330	20V, 0,02A, 0,2W, 3500MHz	BFR 34, BFT 97, BFQ 59...60, BFQ 70
20990	2SC3300	100V, 15A, 100W	2SD1840
20991	2SC3301	15V, 0,08A, 7GHz	2SC3357, 2SC4988
20992	2SC3302	17V, 0,07A, 7GHz	BFG 195, BFQ 73, 2SC3358, 2SC3603
20993	2SC3303	100V, 5A, 20W, 120MHz	-
20994	2SC3304	250/200V, 10A, 40W, <1/3,5μs	BUS 36...37, BUV 27(A), 2SC2867
20995	2SC3305	900/800V, 3A, 40W, <1/5μs	BUT 11(A), BUV 46(A), 2SC3490...3491
20996	2SC3306	500/400V, 10A, 100W, <1/3,5μs	BUP 23, 2SC3042, 2SC4138, 2SC4434
20997	2SC3307	900/800V, 10A, 150W, <1/4μs	2SC3910, 2SC3982, 2SC3992
20998	2SC3308	100V, 5A, 30W, 120MHz	2SC3258
20999	2SC3309	500/400V, 2A, 20W, -/<3,5μs	BUX 84F...85F, 2SC4421, 2SC4533
21000	2SC331	20V, 0,02A, 0,2W, 3500MHz	BFR 34, BFT 97, BFQ 59...60, BFQ 70
21001	2SC3310	500/400V, 5A, 30W, -/<3,5μs	2SC3497, 2SC4073, 2SC4371, 2SC4418
21002	2SC3311	30V, 0,1A, 0,3W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
21003	2SC3311A	2SC3311, 60V	BC 167, BC 182, BC 237, BC 547, 2SD767
21004	2SC3312	60V, 0,1A, 0,3W, 200MHz	BC 414, BC 550, 2SC1775(A), 2SC2390
21005	2SC3313	30V, 0,03A, 0,3W, 250MHz	BF 240...241, BF 254...255, BF 594...595
21006	2SC3314	30V, 0,03A, 0,3W, 300MHz	BF 198...199, BF 224...225, BF 596...597
21007	2SC3315	30V, 15mA, 0,3W, 650MHz	BF 225, BF 314, BF 502, BF 505, BF 507
21008	2SC3316	<500/1650ns	BUX 84...85, 2SC2333, 2SC2534, 2SC2738
21009	2SC3317	<500/1650ns	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21010	2SC3318	<500/1650ns	BUP 23, 2SC2828, 2SC3042, 2SC4138
21011	2SC3319	<500/1650ns	BUW 25...26, BUW 34...36, 2SC3046
21012	2SC332	30V, 0,2A, 0,15W, 450MHz	BSS 11, BSX 19...20, 2N2368...69(A)
21013	2SC3320	<500/1650ns	BUP 23, 2SC3520, 2SC4139, 2SC4434
21014	2SC3321	<500/1650ns	BUV 25, BUW 44, BUX 25, 2SD641

21015	2SC3322	900/800V, 5A, 80W, <1/4μs	BUW 11A, 2SC3153, 2SC3232, 2SC3535
21016	2SC3323	60V, 0,15A, 150MHz	2SC3323...24
21017	2SC3324	120V, 0,1A, 100MHz	2SD814
21018	2SC3325	50V, 0,5A, 300MHz	BC 817, BCX 19, 2SC3441
21019	2SC3326	50V, 0,3A, 30MHz	2SC3134
21020	2SC3327	2SC3326	2SC2878
21021	2SC3328	80V, 2A, 0,9W, 100MHz	2SC4489, 2SD2182
21022	2SC3329	80V, 0,1A, 0,4W, 42MHz	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
21023	2SC333	2SC322, 40V	BSS 11, BSX 19...20, 2N2368...69(A)
21024	2SC3330	60V, 0,2A, 0,3W, 200MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21025	2SC3331	2SC3330, 0,5W	BC 174, BC 182, BC 190, BC 546, 2SD767
21026	2SC3332	180/160V, 0,7A, 0,7W, 120MHz	2SC4612
21027	2SC3333	250V, 0,05A, 0,6W, 100MHz	BF 298...299, BF 422, 2SC3468
21028	2SC3334	2SC3333, 0,9W	BF 422(A), 2SC3249, 2SC3467...69
21029	2SC3335	2SC3333, 5W	BF 415, BF 417, BF 458...459, BF 469
21030	2SC3336	500/400V, 15A, 100W, <0,5/2μs	BUV 48(A...C), BUW 13(A), 2SC3520
21031	2SC3337	20V, 0,1A, 0,6W, 4,4GHz	2SC2570(A), 2SC3037, 2SC3605
21032	2SC3338	15V, 0,05A, 4,5GHz	BFQ 19, BFQ 193, 2SC3268
21033	2SC3339	60V, 0,15A, >80MHz	BC 846R...847R, BCV 71R...72R
21034	2SC334	2SC322, 60V	2N4014
21035	2SC3340	120/120V, 0,1A, 100MHz	2SC1622A, 2SC3324
21036	2SC3341	35V, 0,5A, 300MHz	BC 817R, BCW 65R, BCX 19R, 2SC3325
21037	2SC3342	1300/500V, 5A, 50W	BU 207...209A, BU 508A, BU 903, MJ 8503
21038	2SC3343	1200/500V, 5A, 50W	BU 207...209A, BU 508A, BU 903, MJ 8503
21039	2SC3344	500/400V, 8A, 60W, -/<3,5μs	MJE 13006, 2SC3562, 2SC4106...07
21040	2SC3345	60V, 12A, 40W,90MHz	2SD1212
21041	2SC3346	2SC3345, 80V, 80MHz	-
21042	2SC3347	45V, 2,4A, PQ5,6W(2,2GHz)	-
21043	2SC3348	45V, 3,6A, PQ11,2W(2,2GHz)	-
21044	2SC3349	45V, 0,6A, PQ1W(2GHz)	-
21045	2SC335	2SC322, 50V, 0,25W	2N4014
21046	2SC3350	45V, 1,2A, PQ3,2W(3GHz)	-
21047	2SC3351	45V, 2,4A, PQ5,4W(3GHz)	-
21048	2SC3352	800/500V, 1,5A, 25W, <1/4μs	BUX 84F...85F, 2SC3352, 2SC3794, 2SD1571
21049	2SC3352A	2SC3352, 900/500V, <1,2/7,2μs	BUX 85F, 2SC3794A, 2SC3978, 2SC4304
21050	2SC3353	800/500V, 5A, 40W, <1/4μs	BUT11(A)F, 2SC3750, 2SC3795, 2SC4518
21051	2SC3353A	2SC3353, 900/500V, <1,2/7,2μs	BUT 11AF, 2SC3795A, 2SC4518, 2SC4898
21052	2SC3354	30V, 0,05A, 0,3W, 1200MHz	BF 377...378, BF 357, 2SC2570, 2SC3037
21053	2SC3355	20V, 0,1A, 0,6W, 6,5GHz	-
21054	2SC3356	20V, 0,1A, 0,2W, 7GHz	-
21055	2SC3357	20V, 0,1A, 6,5GHz	2SC4988
21056	2SC3358	20V, 0,1A, 7GHz	BFG 195
21057	2SC3359(S)	80V, 0,3A, 0,4W, 150MHz	BC 639, 2SC4414, 2SD667, 2SD1226
21058	2SC3359(S)	80V, 0,3A, 0,4W, 150MHz	BC 639, 2SC4414, 2SD667, 2SD1226
21059	2SC336	2SC322, 60V, 0,25W	2N4014

21060	2SC3360	200V, 0,1A, <800/1800ns	BFN 24, BFN 26
21061	2SC3361	60V, 0,15A, 120/390ns	BC 846, BCV 71...72, BSR 17, 2SC3392
21062	2SC3362	500/400V, 1,5A, 10W, <1/3µs	2SC3233, 2SC3631, BUV 63, BUV 93...95
21063	2SC3363	800/500V, 1A, 10W, <1/4µs	BUV 94...95
21064	2SC3364	160/160V, 1,5A, 20W, 200MHz	2SC3298(A,B), 2SC4159, 2SC4370
21065	2SC3365	500/400V, 10A, 80W, <1/3,5µs	BUP 23, 2SC3042, 2SC4138, 2SC4434
21066	2SC3366	150/100V, 5A, 40W, <1/3,5µs	BD 243D, MJE 15030, 2SD772(A,B)
21067	2SC3367	120/80V, 5A, 40W, 300/900ns	BD 243C, BDV 10...12, MJE 15028
21068	2SC3368	36V, 0,1A, 0,5W, 2,5GHz	-
21069	2SC3369	36V, 0,3A, 1W, 3GHz	2SC3288, 2SC3019
21070	2SC337	20V, 0,02A, 0,36W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
21071	2SC3370	200V, 15A, 150W, 30MHz	2SC2773...2774, 2SC3264, 2SD846
21072	2SC3371	800/500V, 10A, 200W, <1/4µs	BUS 13(A), BUW 45...46, BUX 48(A...C)
21073	2SC3372	36V, 3A, PQ8W(915MHz)	-
21074	2SC3373	30V, 0,2A, 0,2W, 1500MHz	BF 363, BFW 92...93
21075	2SC3374	20V, 0,02A, 550MHz	BF 599, BF 799, BFS 20, 2SC3015
21076	2SC3375	30V, 0,8A, 0,6W, 120MHz	BC 337...338, BC 635, BC 637, 2SD2322S
21077	2SC3376	900/800V, 3A, 60W, <-/5µs	BUW 11A, 2SC3152, 2SC3285, 2SC3550
21078	2SC3377	40V, 1A, 0,5W, 150MHz	BC 337, BC 635, BC 637, 2SD1225
21079	2SC3378	120V, 0,1A, 0,2W, 100MHz	2SC1775A, 2SC2240, 2SC2389, 2SC2459
21080	2SC338	2SC337, 70V	BC 174, BC 182, BC 190, BC 546, 2SC1890
21081	2SC3380	300V, 0,1A, 80MHz	BFN 18, 2SC3515, 2SC3554
21082	2SC3382	2SC3383	2SC1775(A), 2SC2240, 2SC2390, 2SC2459
21083	2SC3383	60V, 0,2A, 0,5W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21084	2SC3384	500/400V, 15A, 120W, <-/2µs	BUV 25, BUW 44...46, BUX 25, 2SD641
21085	2SC3385	500/400V, 15A, 120W, <-/1,5µs	BUV 25, BUW 44...46, BUX 25, 2SD641
21086	2SC3386	80/50V, 3A, 10W, <1/3µs	2SC3303, 2SC4332, 2SC4978
21087	2SC3387	1200/500V, 5A, 50W, <1/7µs	BU 706, BU 903, 2SC3642, 2SC4236
21088	2SC3388	1200/500V, 5A, 50W, <1/6µs	BU 207...209, BU 706, 2SD1099, 2SD1103
21089	2SC3389	20V, 2A, 0,7W, 80MHz	2SC3205, 2SC3226, 2SD787...788, 2SD1246
21090	2SC339	2SC337, 110V	2SC1775A, 2SC1845, 2SC2240, 2SC3245
21091	2SC3390		BC 414,
21092	2SC3391	30V, 0,02A, 0,2W, 940MHz	BF 377...378, BF 689, BF 763, 2N2857
21093	2SC3392	2SC3393, SMD	BSR 14, BSS 79, BSS 81
21094	2SC3393	60V, 0,5A, 0,3W, 70/470ns	BSV 59, BSX 49, 2N3301...02, 2N2221...22
21095	2SC3394	55V, 0,1A, 0,5W, 230MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21096	2SC3395	2SC3399, SMD	DTC 144EK, FA 1L4M, RN 1404, UN 2213
21097	2SC3396	2SC3400, SMD	DTC 124EK, FA 1F4M, RN 1403, UN 2212
21098	2SC3397	2SC3401, SMD	DTC 144WK, FA 1L4L, RN 1409, UN 221E
21099	2SC3398	2SC3402, SMD	DTC 114EK, FA 1A4M, RN 1402, UN 2211
21100	2SC3399	250MHz	AA 1L4M, DTC 144ES, RN 1004, UN 4213
21101	2SC34	20V, 0,25A, 0,14W, 6MHz	AC 127, ASY 28...29, ASY 73...75
21102	2SC340	20V, 0,02A, 0,1W, 130MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
21103	2SC3400	250MHz	AA 1F4M, DTC 124ES, RN 1003, UN 4212
21104	2SC3401	0,1A, 250MHz	AA 1L4L, DTC 144WS, RN 1009, UN 421E

21105	2SC3402	250MHz	AA 1A4M, DTC 114ES, RN 1002, UN 4211
21106	2SC3403	500/400V, 2A, 25W, <1/4μs	2SC4219, 2SC4597, 2SC4754
21107	2SC3405	900/800V, 0,8A, 20W, <1/5μs	2SC3489, BUV 95, BUX 85, 2SC3149
21108	2SC3408	300/300V, 0,1A, 10W, 80MHz	2SC2870, 2SC2924, 2SC3805, 2SC4019
21109	2SC3409	900/800V, 2A, 80W, <1/4,8μs	2SC3152, 2SC3376, 2SC3533, 2SC3550
21110	2SC341	2SC340, 70V	BC 174, BC 182, BC 546, 2SC1890
21111	2SC3410	35V, 2A, PQ7,2W(500MHz)	-
21112	2SC3411	800/400V, 10A, 50W, <1/4,5μs	BUS 12(A), BUW 26, BUW 35...36, 2SC3049
21113	2SC3412	1200/500V, 8A, 50W, <1/4,5μs	BU 137A, MJ 8504...05, 2SC3215, 2SC4237
21114	2SC3413	40V, 0,1A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21115	2SC3414	2SC3413, 0,4W	2SC3413
21116	2SC3415	2SC3269, 0,5W	BF 299, BF 393, BF 420A, 2SC4218
21117	2SC3416	200/200V, 0,1A, 5W, 70MHz	2SC3502...03, 2SC3600...01, 2SD2492
21118	2SC3417	2SC3416, 300/300V	2SC3503
21119	2SC3418	2SC3416, 400V, 100MHz	BF 850
21120	2SC3419	40V, 0,8A, 5W, 100MHz	2SD1684, BD 135, BD 226, BD 375
21121	2SC342	2SC340, 110V	2SC1775A, 2SC1845, 2SC2240, 2SC3245
21122	2SC3420	50V, 5A, 10W, 100MHz	2SD1685, 2SC2270, 2SD826
21123	2SC3421	120/120V, 1A, 10W, 120MHz	2SC3621, 2SD1684
21124	2SC3422	40V, 3A, 10W, 100MHz	2SD1683, 2SD1685, BD 785, MJE 240...242
21125	2SC3423	150/150V, 0,05A, 5W, 200MHz	2SC3787...88, 2SC3956, BF 415, BF 469
21126	2SC3424	250/250V, 0,05A, 80MHz	2SC3271, 2SC3789...90, BF 415, BF 469
21127	2SC3425	500/400V, 0,8A, 10W, -/<4μs	BD 410, 2SC3051
21128	2SC3426	15V, 0,8A, 120MHz	BCW 65...66, 2SC3265
21129	2SC3427	50V, 7A, 50W, <200/2300ns	BD 543A, BD 797, BD 805, 2SD1442A
21130	2SC3428	60V, 10A, 50W, <200/2300ns	BD 707, BD 743A, BD 807, 2SD1443A
21131	2SC3429	17V, 0,07A, 5GHz	2SC3161, 2SC3774
21132	2SC343	35V, 0,5A, 0,6W, 430MHz	BSV 69, 2N3722...25, 2SC1072, 2SC1385
21133	2SC3430	500/400V, 2A, 20W, <0,5/1,8μs	BUX 84...85, 2SC2333, 2SC2534, 2SC2738
21134	2SC3430	500/400V, 2A, 20W, <0,5/1,8μs	BUX 84...85, 2SC2333, 2SC2534, 2SC2738
21135	2SC3431	500/400V, 5A, 40W, <0,5/1,8μs	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21136	2SC3431	500/400V, 5A, 40W, <0,5/1,8μs	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21137	2SC3432	500/400V, 7A, 60W, <0,5/1,8μs	MJE 13006, 2SC3039, 2SC3170, 2SC4106
21138	2SC3432	500/400V, 7A, 60W, <0,5/1,8μs	MJE 13006, 2SC3039, 2SC3170, 2SC4106
21139	2SC3433	<0,5/1,8μs	MJE 13008, 2SC3562, 2SC4107, 2SC4164
21140	2SC3433	<0,5/1,8μs	MJE 13008, 2SC3562, 2SC4107, 2SC4164
21141	2SC3434	<0,5/1,8μs	BUP 23, 2SC2828, 2SC3042, 2SC4138
21142	2SC3435	<0,5/1,8μs	BUP 23, 2SC3520, 2SC4139...40, 2SC4434
21143	2SC3436	500/500V, 20A, 200W, <1/1,7μs	-
21144	2SC3437	40V, 0,2A, 70/45ns	BSR 17, 2SC3392
21145	2SC3438	100V, 0,5A, 130MHz	2SC2881, 2SD968(A), 2SD1006...1007
21146	2SC3439	30V, 1,5A, 130MHz, B>400	2SC3727
21147	2SC344	2SC343, 60V	BSV 77, 2N3722...23, 2SC1072, 2SC1385
21148	2SC3440	25V, 0,7A, 180MHz	BCW 65...66, 2SC3265
21149	2SC3441	55V, 0,4A, 150MHz	BCW 65...66, BCX 41, 2SD1782



21150	2SC3442	50V, 0,1A, 0,3W, 100MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21151	2SC3443	20V, 2A, 80MHz	2SC2982, 2SC3439, 2SD1621, 2SD1766
21152	2SC3444	60V, 1A, 80MHz	2SC4409, 2SD1615, 2SD1622...1623
21153	2SC3445	15V, 0,08A, 7GHz	BFR 193, 2SC3356
21154	2SC3446	800/500V, 3A, 50W, <0,5/3,3µs	BUT 11(A), BUV 46(A), 2SC3047, 2SC3087
21155	2SC3447	800/500V, 5A, 50W, <0,5/3,3µs	BUT 11(A), BUV 46(A), 2SC3087, 2SC3353
21156	2SC3448	800/500V, 4A, 60W, <0,5/3,3µs	BUW 11(A), BUW 131(A), 2SC3088, 2SC3796
21157	2SC3449	800/500V, 7A, 80W, <0,5/3,3µs	BU 426(A), BU 926, 2SC3089, 2SC3536
21158	2SC345	2SC343, 80V	BSV 95, 2N3722...23, 2N3725, 2N3735
21159	2SC3450	<0,5/3,3µs	BUV 47(A), BUW 12(A), 2SC3090, 2SC3637
21160	2SC3451	<0,5/3,3µs	BUV 48(A...C), BUW 13(A), 2SC3552
21161	2SC3452	800/500V, 7A, 70W, <0,5/3,3µs	BU 326(A), BU 426(A), BUX 47(A)
21162	2SC3453	<0,5/3,3µs	BUS 12(A), BUW 26, BUW 35...35, 2SC3049
21163	2SC3454	<0,5/3,3µs	BUS 13(A), BUW 45...46, BUX 48(A...C)
21164	2SC3455	<0,5/3,3µs	BUS 14(A), BUS 98(A), 2SC3988
21165	2SC3456	<0,5/3,3µs	MJE 8500...8501, 2SC3178, 2SC4230
21166	2SC3457	<0,5/3,3µs	MJE 8502...8503, 2SC3050
21167	2SC3458	<0,5/3,3µs	2SC3387, 2SC3642, 2SC4236
21168	2SC3459	<0,5/3,3µs	2SC3387, 2SC3642, 2SC4236
21169	2SC346	45V, 0,7A, 0,6W, <80/70ns	BSV 69, 2N3722...25, 2SC1072, 2SC1385
21170	2SC3460	<0,5/3,3µs	BU 902...903, BUV 89, 2SC3643, 2SC3461
21171	2SC3461	<0,5/3,3µs	BU 902, BUV 89, 2SC3643, 2SC3466
21172	2SC3462	<0,5/3,3µs	BU 546, MJ 8502...03, 2SC3343, 2SC4236
21173	2SC3463	<0,5/3,3µs	BU 546, MJ 8502...8503, 3SC3343...3344
21174	2SC3464	<0,5/3,3µs	BU 536, MJ 8504...8505, 2SC3412
21175	2SC3465	<0,5/3,3µs	BUX 48B,C, 2SC3552, 2SC3644
21176	2SC3466	1200/650V, 8A, 120W, <1/4,7µs	BUV 70, 2SC3643, 2SC4237
21177	2SC3467	200/200V, 0,1A, 1W, 150MHz	BF 420 A, 2SC3249
21178	2SC3468	2SC3467, 300/300V	BF 420A, 2SC3249
21179	2SC3469	2SC3467, 400/400V	2SC4166, 2SC2267, 2SD1385
21180	2SC347	2SC346, 60V	BSV 77, 2N3722...23, 2SC1072, 2SC1385
21181	2SC3470	55V, 0,1A, 0,3W, 230MHz	BC 237, BC 547, BF 240...41, BF 254...55
21182	2SC3471	60V, 0,2A, 0,4W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21183	2SC3471	60V, 0,2A, 0,4W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21184	2SC3472	<1/5,5µs	BUT 50P, 2SC3030, 2SC3032
21185	2SC3473	50V, 4A, 40W, 50MHz	2SC2562, 2SC3253, BD 243A, BD 535
21186	2SC3474	80V, 2A, 85MHz, B>500	-
21187	2SC3475	100V, 4A, 20W, 20MHz	2SC3540, 2SD1411
21188	2SC3477	15V, 0,03A, 0,35W, 4,5GHz	BFQ 71...72, 2SC1119, 2SC1336
21189	2SC3478(A)	200V, 0,1A, 0,75W, 160MHz	BF 298...299, BF 422, 2SC3467...3468
21190	2SC3479	1500/800V, 2,5A, 80W	BU 705D, 2SD1290...91, 2SD1728, 2SD1876
21191	2SC348	2SC346, 60V	BSV 77, 2N3722...23, 2SC1072, 2SC1385
21192	2SC3480	2SC3479, 3,5A	BU 706D, 2SD1729, 2SD1877
21193	2SC3481	1500/800V, 5A, 120W	2SC3681, BU 2508D, 2SD1730, 2SD1878
21194	2SC3482	2SC3481, 6A	2SC3681, BU 508D, 2SD1731, 2SD1879



21195	2SC3483	1500V, 2,5A, 80W	BU 705, 2SD1493...1494
21196	2SC3484	2SC3483, 3,5A	BU 706, 2SC3484, 2SD1495
21197	2SC3485	1500/800V, 5A, 120W	2SC3685, BU 2508(A), 2SD1496...97
21198	2SC3486	2SC3485, 6A	2SC3685...86, BU 2508(A), 2SD1496...1497
21199	2SC3487	50V, 0,1A, 0,3W, 150MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21200	2SC3488	35V, 0,5A, 0,3W, 300MHz	BC 337...338, BC 635, BC 637, 2SC3377
21201	2SC3489	900/800V, 0,8A, 10W, <1/1,7µs	2SC3405, BUV 95, BUX 85, 2SC3149
21202	2SC349	2SC346, 90V	BSV 95, 2N3722...23, 2N3625, 2N3735
21203	2SC3490	900/800V, 3A, 40W, <0,5/3µs	BUT 11(A), BUV 46(A), 2SC3148, 2SC3150
21204	2SC3491	1000/400V, 4A, 60W, <0,75µs	BUT 11A, BUV 46A, 2SC3050, 2SC3457
21205	2SC3492	50V, 4A, 40W, 50MHz	2SC2562, 2SC3253, BD 243, BD 535
21206	2SC3493	15V, 20mA, >700MHz	BF 599, BF 799, BFS 17, BFS 20, 2SC3130
21207	2SC3494	30V, 0,1A, 0,3W	BF 240...41, BF 254...55, BF 594...595
21208	2SC3495	120V, 0,05A, B1000	2SC3071
21209	2SC3496(A)	900/800V, 1A, 30W, <1/4µs	2SC4223, 2SC4601, BUV 95, BUX 85
21210	2SC3497	500/400V, 6A, 30W, -/<1,8µs	BUF 306F, 2SC3870, 2SC4130, 2SC4161
21211	2SC3498	500/400V, 30A, 150W, -/<3µs	-
21212	2SC3499	500/450V, 30A, 150W	-
21213	2SC35	20V, 0,4A, 0,14W, 12MHz	AC 127, ASY 73...75
21214	2SC350	30V, 0,1A, 0,2W, 180MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
21215	2SC3500(1)	50V, 4A, PQ4,8W(860MHz)	-
21216	2SC3501	20V, 0,05A, 3,5GHz	BFT 65
21217	2SC3502	200V, 0,1A, 7W, 150MHz	2SC3416...17, 2SC3600...01
21218	2SC3503	2SC3502, 300/300V	2SC3417...18, BF 417, BF 471
21219	2SC3504	70V, 0,05A, 0,9W, 500MHz	2SC3596
21220	2SC3505	900/700V, 6A, 80W, <1/6µs	BUW 11A, 2SC3153, 2SC3232, 2SC3535
21221	2SC3506	1000/800V, 3A, 70W, <1/3µs	BUW 11AF, 2SC4426...27, 2SC4583...84
21222	2SC3507	1000/800V, 5A, 80W, <1/3µs	BUW 11AF, 2SC4427...28, 2SC4584
21223	2SC3508	900/800V, 6A, 80W, B>7	-
21224	2SC3509	900/800V, 10A, 100W, B>7	-
21225	2SC351	40V, 0,02A, 0,2W, 600MHz	BF 198...199, BF 224...225, BF 505
21226	2SC3510	20V, 0,05A, 0,6W, 4,5GHz	2SC2570(A), 2SC3037, 2SC3337, 2SC3512
21227	2SC3511	15V, 0,05A, 0,2W, 6GHz	BFG 65, BFP 91, BFQ 66
21228	2SC3512	15V, 0,1A, 0,6W, 6GHz	2SC3355
21229	2SC3513	2SC3512, SMD	2SC3445
21230	2SC3514	180/180V, 0,1A, 10W, 200MHz	2SC3782, BF 615, BF 858...859, BF 757
21231	2SC3515	300/300V, 0,1A, 80MHz	BFN 18, 2SC3380, 2SC3554, 2SC4189
21232	2SC3516	1200/800V, 30A, 200W	-
21233	2SC3517	1200/800V, 50A, 300W	-
21234	2SC3518(Z)	60V, 5A, 10W, <1/3µs	2SC3074, 2SC3303, 2SC3592, 2SD1803
21235	2SC3519	160V, 15A, 130W, 50MHz	2SC2987A, 2SC3263, 2SD1047, 2SD1703
21236	2SC3519A	2SC3519, 180V	2SC3263, 2SC3907, 2SC3856
21237	2SC352(A)	50V, 0,1A, 0,75W, 140MHz	BSY 58, 2N2218...19(A), 2N3299...3300
21238	2SC3520	<0,7/3,7µs	2SC3850, 2SC4110, 2SC4140
21239	2SC3521	40V, 0,1A, <100/150ns	BSR 17, 2SC3361, 2SC3578

21240	2SC3522	500/400V, 7A, 40W, <1/3,5μs	MJE 13006, 2SC3039, 2SC3170, 2SC4106
21241	2SC3523	100V, 3A, 40W	2SC3258, BD 241C, BD 937, BDV 10...12
21242	2SC3524	150V, 7A, 40W, <0,5/2μs	BD 243D, MJE 15030, 2SC2334, 2SC4329
21243	2SC3525	500/400V, 5A, 100W, <1/3μs	BUP 22, BUX 45, TIP 58A, 2SC3083
21244	2SC3526(H)	110V, 0,15A, 1W, 350MHz	2SC3598...99, 2SC3953...54
21245	2SC3527	500/400V, 15A, 100W, <1/3,5μs	2SC4298, 2SC4424
21246	2SC3528	500/400V, 20A, 125W, <1/3,5μs	2SC4425
21247	2SC3529	500/400V, 5A, 40W, <0,5/1,8μs	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21248	2SC353(A)	2SC352, 100V	BSW 39, 2N3723
21249	2SC3531	1000/800V, 3A, 50W, <1/3,5μs	BUT11A, BUV46A, MJE 8502...03, 2SC3457
21250	2SC3532	1000/800V, 4A, 60W, <1/3,5μs	BUT 11A, BUV 46A, MJE 8502...03, 2SC3491
21251	2SC3532	1000/800V, 4A, 60W, <1/3,5μs	BUT 11A, BUV 46A, MJE 8502...03, 2SC3491
21252	2SC3533	1000/800V, 3A, 70W, <1/3,5μs	BUW 11A, BUW 131A, 2SC3285, 2SC3534
21253	2SC3534	1000/800V, 4A, 80W, <1/3,5μs	BUW 11A, BUW 131A, 2SC3285, 2SC3387
21254	2SC3535	1000/800V, 6A, 100W, <1/3,5μs	BUW 11A, BUW 131A, 2SC3387, 2SC3642
21255	2SC3536	1000/800V, 8A, 120W, <1/3,5μs	BU 902...903, BUV 47A, BUW 12A
21256	2SC3537	50V, 3A, PQ20W(900MHz)	-
21257	2SC3538	50V, 6A, PQ40W(900MHz)	-
21258	2SC3539	50V, 9A, PQ60W(900MHz)	-
21259	2SC354	40V, 1,5A, 7W, 180MHz	BFQ 43, 2N4427
21260	2SC3540	100V, 5A, 25W, 120MHz	2SC3691, 2SC4549, 2SC4596
21261	2SC3541	35V, 2A, PQ5,6W(1300MHz)	-
21262	2SC3542	35V, 6A, PQ15,8W(1300MHz)	-
21263	2SC3544	30V, 0,05A, 0,25W, 2GHz	BF 357, 2SC2498, 2SC2570(A), 2SC3037
21264	2SC3545	2SC3544, SMD	BFR 53, BFT 75, 2SC3014
21265	2SC3546	160/160V, 12A, 120W, 30MHz	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
21266	2SC3547(A,B)	20V, 0,03A, 4GHz	BFQ 29, BFR 93, BFT 75
21267	2SC3548	20V, 0,03A, 4GHz	BFQ 59...60, BFQ 70...71, 2SC2143
21268	2SC3549	900/800V, 3A, 40W, <1/4,8μs	BUT 11A, BUV 46, 2SC3148, 2SC3490
21269	2SC355	75V, 2,5A, PQ3W(150MHz)	BLY 35, BLY 60, 2N3632
21270	2SC3550	900/800V, 3A, 80W, <1/4,8μs	BUW 11A, BUW 131A, 2SC3152, 2SC3376
21271	2SC3551	900/800V, 5A, 80W, <1/4,8μs	BUW 11A, BUW 131A, 2SC3153, 2SC3232
21272	2SC3552	1100/800V, 12A, 150W, 15MHz	BUV 48B,C, BUW 13A, 2SC3644
21273	2SC3553	35V, 0,5A, 0,3W, 120MHz	BC 337...338, BC 635, BC 637, 2SC3377
21274	2SC3554	300/300V, 0,2A, 50MHz	BFN 18, 2SC3515, 2SC3380
21275	2SC3555	900/800V, 0,5A, 20W, <1/5μs	2SC3405, 2SC3489, 2SD1945, BUX 87
21276	2SC3556	80V, 4A, 40W, <0,5/2,5μs	BD 243B, BD 537, BD 539B, BDV 10...12
21277	2SC3557	80V, 4A, 40W, <0,5/2μs	BD 243B, BD 537, BD 539B, BDV 10...12
21278	2SC3558	100/60V, 4A, 40W, <0,5/3μs	BD 243C, BD 539C, BD 953, BDV 10...12
21279	2SC3559	900/800V, 3A, 30W, <1/5μs	BUT 11AF, 2SC3752, 2SC4304, 2SC4234
21280	2SC356	30V, 0,2A, 0,3W, <20/40ns	BSS 11...12, BSW 38, 2N2368...69(A)
21281	2SC3560	500/400V, 2A, 20W, -/1,9μs	BUX84F...85F, 2SC3309, 2SC3569, 2SC4421
21282	2SC3561	500/450V, 2A, 20W	BUX84F...85F, 2SC3309, 2SC3569, 2SC4421
21283	2SC3562	500/400V, 10A, 40W, -/1,8μs	2SC3572, 2SC3575, 2SC4162, 2SD1795
21284	2SC3563	2SC3562, 500/450V	2SC3572, 2SC3575, 2SC4162, 2SD1795

21285	2SC3564	120/120V, 1,5A, 200MHz	2SC3364, 2SC3298(A,B), 2SC4159
21286	2SC3565	300/300V, 0,2A, 15W, 80MHz	2SC4075, 2SC1505...07, 2SC1755...57
21287	2SC3566	150/60V, 5A, 25W, <0,5/3µs	2SC3568, 2SC3696, 2SC4153, 2SC4334...35
21288	2SC3567	150/100V, 3A, 15W, <0,5/2µs	BDT 31DF, 2SC3695
21289	2SC3568	150/100V, 10A, 30W, <0,5/2µs	2SC3698, 2SC4336, BD 743E
21290	2SC3569	500/400V, 2A, 15W, <1/3,5µs	BUX 84F...85F, 2SC3560...61, 2SC4421
21291	2SC3570	500/400V, 5A, 25W, <1/2,7µs	BUT 11(A)F, 2SC3310, 2SC4054, 2SC4371
21292	2SC3571	500/400V, 7A, 30W, <1/3,5µs	2SC3890, 2SC4056, 2SC4130, 2SC4161
21293	2SC3572	500/400V, 10A, 30W, <1/3,2µs	2SC3310, 2SC3562, 2SC4162, 2SD1795
21294	2SC3573	500/400V, 5A, 30W, <0,5/1,8µs	BUT 11(A)F, 2SC3310, 2SC4054, 2SC4371
21295	2SC3574	500/400V, 7A, 30W, <0,5/1,8µs	2SC3890, 2SC4056, 2SC4130, 2SC4161
21296	2SC3575	<0,5/1,8µs	2SC3310, 2SC3562, 2SC4162, 2SD1795
21297	2SC3576	30V, 0,3A, B1500	2SC3068, 2SC3836
21298	2SC3577	850/650V, 5A, 80W, <1/3µs	BUW 11(A)F, 2SC4300, 2SC4457
21299	2SC3578	40V, 0,1A, <40/70ns	2SC3757
21300	2SC3579	800/800V, 6A, 50W, <0,5/3,7µs	BUT 11A, BUV 46A, 2SC3050, 2SC3047
21301	2SC3580	25V, 0,7A, 0,9W, 180MHz	BC 337...338, 2SC2236, 2SD863, 2SD1331
21302	2SC3581	55V, 0,4A, 0,9W, 150MHz	BC 637, 2SC3939, 2SD863, 2SD1937
21303	2SC3582	20V, 0,065A, 0,6W, 8GHz	-
21304	2SC3583	20V, 0,065A, 9GHz	BFR 520
21305	2SC3584	20V, 0,065A, 0,2W, 9GHz	-
21306	2SC3585	20V, 0,035A, 10GHz	2SC5089
21307	2SC3586	20V, 0,035A, 0,25W, 10GHz	BFQ 645
21308	2SC3587	20V, 0,035A, 0,58W, 10GHz	BFQ 645
21309	2SC3588(Z)	500/400V, 0,5A, 10W, <1/3,5µs	2SC3129, 2SC3075, BUX 84...85, 2SC2899
21310	2SC3589	250/100V, 7A, 40W	BU 406...408, 2SC3173, 2SC3175
21311	2SC3590	330/150V, 7A, 50W	BU 406...408, 2SC3173, 2SC3175
21312	2SC3591	2SC3590, 400/200V	BU 406, BU 408, 2SC3175
21313	2SC3592	60V, 5A, 10W, <1/3,5µs	2SC3074, 2SC3518, 2SD1803, 2SD1805
21314	2SC3593	850V, 25A, 150W, <3/2,5µs	BUS 14(A), BUS 98(A)
21315	2SC3594	<500/5,5µs	BU 508A, BUV 71, MJ 8505, 2SC4284...85
21316	2SC3595	30V, 0,5A, 5W, 2GHz	-
21317	2SC3596	80V, 0,3A, 8W, 700MHz	2SC3599, 2SC3951
21318	2SC3597	80V, 0,5A, 10W, 800MHz	2SC3952
21319	2SC3598	120V, 0,2A, 8W, 500MHz	2SC3599, 2SC3953...54
21320	2SC3599	120V, 0,3A, 8W, 500MHz	2SC3954
21321	2SC36	20V, 0,4A, 0,14W, 20MHz	AC 127, ASY 73...75
21322	2SC360	30V, 0,1A, 0,25W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
21323	2SC3600	200V, 0,1A, 7W, 400MHz	2SC3601, 2SC3955
21324	2SC3601	200V, 0,15A, 7W, 400MHz	2SC3956
21325	2SC3602	25V, 0,02A, 0,2W, 1100MHz	2SC2464, 2SC2466, 2SC2144, 2SC2360
21326	2SC3603	20V, 0,1A, 0,58W, 7GHz	BFQ 196, 2SC3358
21327	2SC3604	20V, 0,065A, 0,58W, 8GHz	BFQ 82, 2SC3358
21328	2SC3605	20V, 0,08A, 6,5GHz	2SC2570(A), 2SC3037, 2SC3512, 2SC3355
21329	2SC3606	2SC3605, SMD, 7GHz	2SC3356

21330	2SC3607	2SC3605, SMD	2SC3357
21331	2SC3608	2SC3605, 7GHz	2SC2876
21332	2SC3609	2SC3605, SMD, 7GHz	-
21333	2SC361	25V, 40mA, 150MHz, B80	BF 240...241, BF 254...255, BF 594...595
21334	2SC3610	110V, 0,15A, 10W, 300MHz	2SC3781
21335	2SC3611	2SC3610, 4W	2SC3598...99
21336	2SC3612	180V, 0,3A, 20W, 400MHz	-
21337	2SC3613	20V, 0,5A, 5W,3500MHz	-
21338	2SC3614	20V, 0,1A	2SC3357
21339	2SC3615	50V, 0,3A, B>800,220MHz	2SC3836, 2SD1915
21340	2SC3616	25V, 0,7A, B>800,250MHz	2SC3070, 2SC4204, 2SD1582
21341	2SC3617	2SC3615, SMD	-
21342	2SC3618	2SC3616, SMD	2SC3650
21343	2SC3619	300/300V, 0,1A, >50MHz	2SC3271, 2SC3789...90, 2SC4828
21344	2SC362	2SC361, B140	BF 240...241, BF 254...255, BF 594...595
21345	2SC3620	300/300V, 0,1A, >50MHz	2SC3271, 2SC3789...90, 2SC4828
21346	2SC3621	150V, 1,5A, 10W, 100MHz	2SC3902, 2SC3117, 2SD669, 2SD781
21347	2SC3622(A)	60V, 0,15A, B1800	2SC3069, 2SC3836
21348	2SC3623(A)	2SC3622	2SC3069, 2SC3836
21349	2SC3624(A)	2SC3622, SMD	2SC3689
21350	2SC3625	500/400V, 8A, 60W, <1/3,5μs	MJE 13006, 2SC3170, 2SC3562, 2SC4107
21351	2SC3626	2SC3625, 40W	2SC3574...75, 2SC3890, 2SC4130, 2SC4161
21352	2SC3627	250/200V, 10A, 40W, <1/3,5μs	2SC3572, 2SC3575, 2SC4162, 2SD1795
21353	2SC3628	35V, 2A, PQ6,5W(175MHz)	-
21354	2SC3629	20V, 1A, PQ1,5W(520MHz)	-
21355	2SC363	2SC361, B250	BF 240...241, BF 254...255, BF 594...595
21356	2SC3630	35V, 1A, PQ3,3W(520MHz)	-
21357	2SC3631(Z)	500/400V, 2A, 10W, 50MHz	2SC3233, BUV 93...94
21358	2SC3632(Z)	600/600V, 1A, 10W, 30MHz	2SC3363
21359	2SC3633	2SC3636	2SC3639
21360	2SC3634	2SC3637	2SC3640
21361	2SC3635	2SC3638	2SC3641
21362	2SC3636	900/500V, 7A, 80W	2SC3643
21363	2SC3637	900/500V, 10A, 90W	2SC3644
21364	2SC3638	900/500V, 15A, 100W	-
21365	2SC3639	2SC3642	-
21366	2SC364	2SC361, B400	BF 240...241, BF 254...255, BF 594...595
21367	2SC3640	2SC3643	-
21368	2SC3641	2SC3644	-
21369	2SC3642	1200/800V, 6A, 100W	2SC3686...87
21370	2SC3643	1200/800V, 8A, 140W	2SC3687
21371	2SC3644	1200/800V, 12A, 150W	BU 2525A
21372	2SC3645	180/160V, 0,14A, 150MHz	BFN 16, BFN 18
21373	2SC3646	120V, 1A, 120MHz	2SC3647, 2SC4132, 2SC4373, 2SD1418...19
21374	2SC3647	120V, 2A, 120MHz	2SC4132

21375	2SC3648	180V, 0,7A, 120MHz	2SC3649, 2SD1420...1421
21376	2SC3649	180V, 1,5A, 120MHz	2SD1420...1421
21377	2SC3650	30V, 1,2A, B1500	2SD1950
21378	2SC3651	120V, 0,2A, B>500	-
21379	2SC3652	30V, 0,3A, 5W, 1200MHz	-
21380	2SC3653	2SC3399, 0,4W	2SC3399
21381	2SC3654	2SC3400, 0,4W	2SC3400
21382	2SC3655	2SC3401, 0,4W	2SC3401
21383	2SC3656	2SC3402, 0,4W	2SC3402
21384	2SC3657	900/800V, 4A, 80W, <1/3,5µs	BUW 11A, 2SC3153, 2SC3232, 2SC3535
21385	2SC3658	1500/800V, 5A, 50W	BU 208D, BU 508D, 2SC4291, 2SD1171...75
21386	2SC3659	1700/800V, 5A, 50W	BU 209, 2SC3026, 2SD784...785
21387	2SC366(G,GTM)	50..60V, 0,4A, 0,3W, 120MHz	BC 337(A), BC 637, BC 639, 2SD1226
21388	2SC3661	30V, 0,3A, B1500	2SD1938
21389	2SC3662	25V, 0,02A, 1100MHz	-
21390	2SC3663	15V, 5mA, 4GHz	BFQ 29, BFQ 81, BFR 93, 2SC3099
21391	2SC3664	800/400V, 20A, 150W, B>80	-
21392	2SC3665	120/120V, 0,8A, 1W, 120MHz	2SC2235, 2SC3665, 2SD667, 2SD1616A
21393	2SC3666	30V, 1A, 1W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1225
21394	2SC3667	30V, 1,5A, 1W, 120MHz	MPS650...651, 2SC2236, 2SD1051, 2SD1331
21395	2SC3668	50V, 2A, 1W, 100MHz	MPS650...651, 2SD1014, 2SD1146, 2SD1207
21396	2SC3669	80V, 2A, 1W, 100MHz	MPS 651, 2SC3328, 2SC4145, 2SD1642
21397	2SC367(G,GTM)	40V, 0,4A, 0,3W, 120MHz	BC 337, BC 635, BC 637, 2SD1225...26
21398	2SC3670	30V,2A,1W,150MHz	2SC4484, 2SC4486, 2SD1207, 2SD1246...47
21399	2SC3671	50V, 5A, 1W, 100MHz	2SC4482, 2SD1145, 2SD1961...62, 2SD2179
21400	2SC3672	300/300V, 0,1A, 1W, 80MHz	BF 299, BF 393, BF 420A, 2SC3468
21401	2SC3673	40V, 2A, 1W, 220MHz, B1000	2SC3225, 2SD1779
21402	2SC3674	15V, 0,065A, 0,4W, 8GHz	BFQ 66, BFQ 82, 2SC3603
21403	2SC3675	1500/900V, 0,1A, 10W	-
21404	2SC3676	1500/900V, 0,3A, 20W	-
21405	2SC3677	60V, 3A, 25W, 170MHz, B2000	2SD1273, 2SD1972, 2SD2177
21406	2SC3678	<1/6µs	BUW 11A, 2SC3152, 2SC3285, 2SC3550
21407	2SC3679	<1/6µs	BUW 11A, 2SC3153, 2SC3387, 2SC3466
21408	2SC368	25V, 0,1A, 0,25W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
21409	2SC3680	<1/6µs	BUV 47A, BUW 12A, 2SC3466, 2SC3636
21410	2SC3681	2SC3685	2SC3482, 2SC4292, BU 508D, BU 706D
21411	2SC3682	2SC3686	BU 508D, BU 2808D
21412	2SC3683	2SC3687	BU 2520D
21413	2SC3684	2SC3688	BU 2520D
21414	2SC3685	1500/800V, 6A, 120W	2SC3486, BU 508A, BU 706, BU 908
21415	2SC3686	1500/800V, 7A, 120W	2SC3687, BU 508A, BU 908
21416	2SC3687	1500/800V, 8A, 150W	BU 2520A
21417	2SC3688	1500/800V, 10A, 150W	BU 2520A
21418	2SC3689	60V, 0,1A, B1500	2SC3651, 2SC4413
21419	2SC369(G)	2SC368, 0,2W	BC 169, BC 184, BC 239, BC 549, 2SC2675



21420	2SC3690	100V, 3A, 15W, <300/1800ns	2SC3695
21421	2SC3691	100V, 5A, 25W, <300/1800ns	2SC3696, 2SC4549
21422	2SC3692	100V, 7A, 30W, <300/1800ns	2SC3697, 2SC4550
21423	2SC3693	100V, 10A, 30W, <300/1800ns	2SC3698, 2SC4551
21424	2SC3694	100V, 15A, 30W, <300/1800ns	2SC3699, 2SC4552
21425	2SC3695	<300/1800ns	-
21426	2SC3696	150V, 5A, 20W, <300/1800ns	-
21427	2SC3697	150V, 7A, 25W, <300/1800ns	-
21428	2SC3698	150V, 10A, 30W, <300/1800ns	-
21429	2SC3699	150V, 15A, 30W, <300/1800ns	-
21430	2SC37	40V, 0,1A, 0,2W, 200MHz	BFW 16...17, BFX 55
21431	2SC370(G,T)	B>20	BC 167, BC 183, BC 237, BC 547, 2SD767
21432	2SC3700	55V, 6A, PQ30W(860MHz)	-
21433	2SC3701	55V, 12A, PQ50W(860MHz)	-
21434	2SC3702	55V, 20A, PQ80W(860MHz)	-
21435	2SC3703	230/230V, 30A, 300W, <0,7/2μs	2SC2940, 2SC3224
21436	2SC3704	15V, 0,08A, 6GHz	2SC3356, 2SC3445, 2SC3606
21437	2SC3705	B4000	-
21438	2SC3706	<1,2/2,5μs	2SC1437, 2SC2942
21439	2SC3707	10V, 0,01A, 4GHz	BFR 92, 2SC3099, 2SC3110
21440	2SC3708	100V, 0,5A, 0,6W, 120MHz	BC 639, 2SC2235, 2SD667, 2SD1768
21441	2SC3709	200/1200ns	2SC4065
21442	2SC371(G,T)	2SC370, 30V, B>40	BC 167, BC 183, BC 237, BC 547, 2SD767
21443	2SC3710	2SC3709, 80V, 80MHz	2SC4595
21444	2SC3711	60V, 0,1A, 0,2W, 200MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21445	2SC3712	PQ>50..60W(860MHz)	-
21446	2SC3713	60V, 0,1A, 200MHz	BC 846, BCV 71...72, 2SC3323
21447	2SC3714	<500/2300ns	2SC3498...99
21448	2SC3715	1500/600V, 4A, 50W, <2/5,5μs	BU706DF, 2SC3480, 2SC4293, 2SD1554...55
21449	2SC3716	1500/600V, 5A, 50W, <2/5,5μs	BU 706F, 2SC4142, 2SD1545, 2SD1655
21450	2SC3717	30V, 0,05A, 0,2W, 750MHz	BF 225, BF 255, BF 310, BF 314, BF 496
21451	2SC3718	2SC3717, SMD	BF 599, BF 799, 2SC3015, 2SC3374
21452	2SC3719	1200/800V, 5A, 150W	-
21453	2SC372(G,GTM)	B>70	BC 167, BC 183, BC 237, BC 547, 2SD767
21454	2SC3720	1200/800V, 10A, 200W	-
21455	2SC3721	15V, 0,05A, 0,2W, 7GHz	BFG 65, BFQ 66, 2SC3062, 2SC3584
21456	2SC3722	120V, 0,05A, 140MHz	-
21457	2SC3722K	2SC3722	2SC3324, 2SC4050
21458	2SC3723	450/400V, 5A, 40W, <1/3μs	MJE 53T, 2SC2542, 2SC2827, 2SC3056
21459	2SC3724	450/400V, 10A, 80W, <1/3μs	BUP 23, 2SC2625, 2SC3042, 2SC4138
21460	2SC3725	450/400V, 15A, 80W, <1/3μs	BUP 23, 2SC3520, 2SC3435, 2SC4139
21461	2SC3726	50V, 2A, 0,9W, 150MHz, B1200	2SD1779
21462	2SC3727	2SC3726, SMD	-
21463	2SC3728	20V, 2A, 80MHz	-
21464	2SC3729	1500/800V, 5A, 50W	BU 706, BU 2508A, 2SC3485, 2SC3685



21465	2SC373(G,GTM)	2SC372, B>200	BC 167, BC 183, BC 237, BC 547, 2SD767
21466	2SC3730	15V, 0,05A, 7,5GHz	BFQ 67, BFR 183, 2SC3445, 2SC3583
21467	2SC3731	60V, 0,2A, 0,25W, <70/250ns	2SC1834
21468	2SC3732	40V, 0,2A, 0,25W, <12/18ns	BSS 11, 2N2368...89(A), 2SC2901
21469	2SC3733	80V, 1A, 1W, <40/110ns	-
21470	2SC3734	2SC3731, SMD	-
21471	2SC3735	2SC3732, SMD	-
21472	2SC3736	2SC3733, SMD	-
21473	2SC3737	1200/800V, 5A, 100W, <1/3,8μs	2SC4584, 2SC4882
21474	2SC3738	<1/3,8μs	2SC4096
21475	2SC3739	60V, 0,5A, <35/275ns	BSR 13...14, BSS 79, BSS 81, 2N3302
21476	2SC374	35V, 0,1A, 0,2W, 150MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
21477	2SC3740	30V, 1A, 0,75W, <1/3μs	BC 635, BC 637, 2SD1225, 2SD1051
21478	2SC3741	2SC3740	2SC3739
21479	2SC3742	2SC3740, SMD	-
21480	2SC3743	900/800V, 3A, 40W, <1/5μs	BUT 11AF, 2SC3559, 2SC3752, 2SC4304
21481	2SC3744	180/180V, 0,1A, 100MHz	2SC3143, 2SD1305
21482	2SC3745	20V, 0,03A, 6,5GHz	2SC4095
21483	2SC3746	80V, 5A, 20W, 100/600ns	2SC4540, 2SC3691, 2SC4549, 2SC4596
21484	2SC3747	80V, 7A, 25W, 100/600ns	2SC3692, 2SC4550
21485	2SC3748	80V, 10A, 30W, 100/600ns	2SC3693, 2SC4551
21486	2SC3749	<500/3300ns	2SC3559, 2SC4304, 2SD1571
21487	2SC375	20V, 50mA, 600MHz	BF 198...199, BF 224...225, BF 505
21488	2SC3750	<500/3300ns	BUT 11(A)F, 2SC3353, 2SC3795(A)
21489	2SC3751	<500/3300ns	2SC4231
21490	2SC3752	<500/3300ns	2SC4234
21491	2SC3753	1500/800V, 5A, 60W	BU 706DF, 2SC4293...94, 2SD1651...52
21492	2SC3754	1500/800V, 6A, 60W	BU 2508DF, 2SC4294, 2SC4122, 2SD1652
21493	2SC3755	1500/800V, 5A, 60W	BU 706, 2SC3894, 2SC4142...43, 2SD1545
21494	2SC3756	1500/800V, 6A, 60W	BU 2508AF, 2SC3894, 2SC4143, 2SD1546
21495	2SC3757	40V, 0,1A, 17/17ns	2SC3578, 2SC4168
21496	2SC3758	<300/1800ns	2SC4296, 2SC4423
21497	2SC3759	<500/1800ns	2SC4298, 2SC4424
21498	2SC376	70V, 0,1A, 0,2W, 150MHz	BC 174, BC 182, BC 190, BC 546, 2SC1890
21499	2SC3760	<1000/3200ns	2SC4296, 2SC4423
21500	2SC3761	<1000/3200ns	2SC4298, 2SC4424
21501	2SC3762	<1000/1800ns	2SC4886
21502	2SC3763	<1000/3500ns	2SC4426, 2SC4583
21503	2SC3764	<1000/3500ns	2SC4427, 2SC4882
21504	2SC3765	<1000/3500ns	2SC4428, 2SC4584
21505	2SC3766	<1000/3500ns	2SC4429
21506	2SC3769	<500/5500ns	BU 2508A, BU 908, 2SC3027...3028
21507	2SC377	35V, 0,03A, 0,2W, 150MHz	BF 240...241, BF 254...255, BF 594...595
21508	2SC3770	30V, 0,03A, 1200MHz	BF 517, BFS 17, 2SC3005, 2SC3016
21509	2SC3771	30V, 0,03A, 2200MHz	BFR 35, BFR 53, BFT 25, 2SC3014

21510	2SC3772	25V, 0,07A, 3000MHz	BFR 106, 2SC3161, 2SC3774...75
21511	2SC3773	25V, 0,05A, 3500MHz	BF 770A, BFT 75, 2SC3014
21512	2SC3774	20V, 0,07A, 5000MHz	2SC3161, 2SC3704
21513	2SC3775	20V, 0,1A, 5000MHz	BFR 106, 2SC3356
21514	2SC3776	25V, 0,07A, 3000MHz	2SC2570(A), 2SC3037, 2SC3337
21515	2SC3777	25V, 0,05A, 3500MHz	2SC2498, 2SC2570(A), 2SC3037, 2SC3337
21516	2SC3778	20V, 0,07A, 5000MHz	2SC2570(A), 2SC3037, 2SC3337
21517	2SC3779	20V, 0,1A, 5000MHz	2SC3355
21518	2SC378	35V, 0,03A, 0,2W, 150MHz	BF 240...241, BF 254...255, BF 594...595
21519	2SC3780	80V, 0,8A, 15W, 800MHz	-
21520	2SC3781	120V, 0,4A, 15W, 500MHz	-
21521	2SC3782	200V, 0,2A, 15W, 400MHz	-
21522	2SC3783	900/800V, 5A, 100W, <1/4,5µs	BUW 11A, BUW 131A, BUV 82, 2SC3796A
21523	2SC3784	B4000	-
21524	2SC3785	50V, 2A, 20W, 180MHz, B4000	-
21525	2SC3786	50V, 3A, 20W, 180MHz, B4000	-
21526	2SC3787	180V, 0,14A, 10W, 150MHz	2SC3956, BF 415, BF 417, 2SC3601
21527	2SC3788	200V, 0,1A, 5W, 150MHz	2SC3955...56, 2SC3502...03
21528	2SC3789	300V, 0,1A, 7W, 70MHz	2SC3417, 2SC3503
21529	2SC379	30V, 0,1A, 0,2W, 300MHz	BF 198...199, BF 224...225, BF 505
21530	2SC3790	300V, 0,1A, 7W, 150MHz	2SC3417, 2SC3503
21531	2SC3791	15V, 0,08A, 0,25W, 6GHz	BFQ 82, 2SC3358, 2SC3603
21532	2SC3792	250MHz, B>300	2SC2935, 2SD1582
21533	2SC3793	20V, 0,05A, 2900MHz	BFT 75, 2SC3014, 2SC3773
21534	2SC3794	800/500V, 1,5A, 25W, <1/4µs	BUX 84F...85F, 2SC3352, 2SC3978
21535	2SC3794A	2SC3794, 900/500V, <1,2/4,2µs	BUX 85F, 2SC3751, 2SC3978, 2SC4231
21536	2SC3795	800/500V, 5A, 40W, <1/4µs	BUT 11(A)F, 2SC3353, 2SC3750, 2SC4518
21537	2SC3795A	2SC3795, 900/500V, <1,2/4,2µs	BUT 11AF, BUT 18AF, BUT 21CF, 2SC4518
21538	2SC3796	800/500V, 5A, 70W, <1/4µs	BUW 11(A), BUW 131(A), 2SC3089, 2SC3636
21539	2SC3796A	2SC3796, 900/500V, <1,2/4,2µs	BUW 11A, BUW 131A, 2SC3636, 2SC3642
21540	2SC3797	800/500V, 7A, 100W, <1/4µs	BUV 47(A), BUW 12(A), 2SC3449, 2SC3636
21541	2SC3797A	2SC3797, 900/500V, <1,2/4,2µs	BUV 47A, BUW 12A, 2SC3466, 2SC3636
21542	2SC3798	800/500V, 5A, 70W, <1/4µs	BUW 11(A)F, 2SC4300, 2SC4457
21543	2SC3798A	2SC3798, 900/500V, <1,2/4,2µs	BUW 11AF, 2SC4300, 2SC4427
21544	2SC3799	800/500V, 7A, 100W, <1/4µs	BUV 47(A)FI, BUW 12(A)F, 2SC4301
21545	2SC3799A	2SC3799, 900/500V, <1,2/4,2µs	BUV 47AFI, BUW 12AF, 2SC4301, 2SC4429
21546	2SC38	2SC37, 0,5W	BFW 16...17, BFX 55
21547	2SC380(TM,ATM)	35V, 30mA, 250MHz	BF 240...241, BF 254...255, BF 594...595
21548	2SC3800	150V, 0,05A, 0,8W, 140MHz	2SC2632
21549	2SC3801	30V, 0,03A, 0,25W, 1100MHz	BF 377...378, BF 763, 2SC2570(A)
21550	2SC3802K	2SC3801, SMD	BF 517, BFS 17, 2SC3016, 2SC3161
21551	2SC3803	60V, 0,2A, 200MHz	-
21552	2SC3804	35V, 12A, PQ45W(860MHz)	-
21553	2SC3805	300/300V, 0,1A, 10W, 70MHz	2SC2870, 2SC3408, 2SC2924, 2SC4019
21554	2SC3806	15V, 0,05A, 0,15W, 4500MHz	BFQ 63

21555	2SC3807	30V, 2A, B>800	-
21556	2SC3808	80V, 2A, B>800	-
21557	2SC381	40V, 20mA, >250MHz	BF 240...241, BF 254...255, BF 594...595
21558	2SC3811	17/17ns	BSV 91...92, BSX 92...93, 2N2360(A)
21559	2SC3813	300/100V, 7A, 150W, 10MHz	TIP 55A...58A, 2SC2305, 2SC2656
21560	2SC3817	35V, 0,5A, PQ1W(1550MHz)	-
21561	2SC3818	35V, 2A, PQ4W(1550MHz)	-
21562	2SC3819	35V, 4A, PQ10W(1550MHz)	-
21563	2SC382(TM)	600MHz	BF 198, BF 225, BF 310, BF 367, BF 505
21564	2SC3820	60V, 0,1A, B1500	2SC3069, 2SC3071, 2SC3836, 2SC3622
21565	2SC3821	450/400V, 5A, 40W, <1/3,5µs	2SC3570, 2SC3573, 2SC4073, 2SC4371
21566	2SC3822	450/400V, 5A, 30W, <1/3,5µs	2SC3570, 2SC3573, 2SC4073, 2SC4371
21567	2SC3823	120/80V, 5A, 40W, <1/3,5µs	BDV 10...12, MJE 15028, 2SD772
21568	2SC3824(A)	2SC3496(A), 15W	-
21569	2SC3825	2SC3403, 15W	2SC3233, 2SC3631
21570	2SC3826	<500/2800ns	2SC2767, 2SD772A,B
21571	2SC3827	30V, 0,02A, 1300MHz	BF 517, BFS 17, 2SC3005, 2SC3016
21572	2SC3828	25V, 0,02A, 1100MHz	-
21573	2SC3829	15V, 0,08A, 6000MHz	BFR 193, 2SC3445, 2SC3606, 2SC3704
21574	2SC383	75V, 0,05A, 0,3W, >300MHz	BF 199, BF 224, BF 311, BF 373
21575	2SC3830	600/500V, 6A, 50W, <1/5µs	MJE 13006, MJE 13070, 2SC3087, 2SC4055
21576	2SC3831	600/500V, 10A, 100W, <1/5µs	BUP 23, 2SC3090, 2SC3450, 2SC4058
21577	2SC3832	500/400V, 7A, 50W, <1/3,5µs	MJE 13006, 2SC3039, 2SC3170, 2SC4106
21578	2SC3833	500/400V, 12A, 100W, <1/3,5µs	BUP 23, 2SC3520, 2SC4139, 2SC4434
21579	2SC3834	<500/3500ns	BU 406...409, TIP 150...152, 2SC4848
21580	2SC3835	<500/3500ns	TIP 55A...58A, 2SC2305, 2SC2656
21581	2SC3836	60V, 0,3A, B>800	-
21582	2SC3837K	30V, 0,05A, 1500MHz	BF 517, BF 799, 2SC3015...16, 2SC3161
21583	2SC3838K	20V, 0,05A, 3200MHz	BF 775, 2SC3014, 2SC3098, 2SC3773
21584	2SC3839K	30V, 0,05A, 2000MHz	BFR 53, 2SC3014, 2SC3098, 2SC3773
21585	2SC383TM,ATM	2SC383, 50(ATM30V)	BF 199, BF 224, BF 311, BF 373
21586	2SC384	20V, 0,05A, 0,2W, 500MHz	BF 198...199, BF 224...225, BF 505
21587	2SC3840	600/600V, 1A, 15W, 30MHz	BUX 99, BUV 63, 2SC3632
21588	2SC3841	25V, 0,03A, 4GHz	BFQ 29, BFQ 81, BFR 93, BFT 75
21589	2SC3842	600/400V, 10A, 70W, 32MHz	2SC4459, 2SC4587
21590	2SC3843	600/450V, 10A, 75W 28MHz	2SC4459, 2SC4587
21591	2SC3844	600/450V, 15A, 75W 30MHz	BUP 23BF, BUV 48FI, BUW 13F
21592	2SC3845	1200/800V, 3A, 75W 15MHz	2SC4583, 2SC3387, 2SC3642
21593	2SC3846	1200/800V, 6A, 80W, 15MHz	2SC4584, BUV 89, 2SC3466, 2SC3643
21594	2SC3847	1200/800V, 10A, 85W 15MHz	BU 2520AF, 2SC4199, BUV 70...71
21595	2SC3848	25V, 0,2A, 500MHz	-
21596	2SC385(A)	20V, 0,02A, 0,2W, 600MHz	BF 198...199, BF 224...225, BF 505
21597	2SC3850	500/400V, 20A, 125W, <1/3,5µs	2SC4110
21598	2SC3851	80V, 4A, 25W, 15MHz	2SC3691, 2SC3746, 2SC4549, 2SC4596
21599	2SC3851A	2SC3851, 100V	2SC3540, 2SC3691, 2SC4549, 2SC4596

21600	2SC3852	80V,3A,25W,15MHz,B>500	2SD2092, 2SD1944, 2SD1273A, 2SD2156A
21601	2SC3852A	2SC3852, 100V	2SD2092, 2SD1273A, 2SD2156A
21602	2SC3853	120/80V, 6A, 60W, 20MHz	BD 245D, BD 545D, 2SC4466, 2SD896
21603	2SC3854	160/120V, 8A, 80W, 20MHz	BD 245D, 2SC4467, 2SD751
21604	2SC3855	200/140V, 10A, 100W, 20MHz	BD 245F, 2SC3263, 2SC4468
21605	2SC3856	200/180V, 15A, 130W, 20MHz	BD 249F, 2SC3263
21606	2SC3857	200/200V, 15A, 150W, 20MHz	2SC2773...2774, 2SC3370, 2SD846
21607	2SC3858	200/200V, 17A, 200W, 20MHz	2SC2774, 2SC3264
21608	2SC3859	2SC3860, SMD	DTC 114TK, FA 1A4Z, RN 1411, UN 2215
21609	2SC386(A)	20V, 0,02A, 500(A600)MHz	BF 198...199, BF 224...225, BF 505
21610	2SC3860	Rb10kOhm	AA 1A4Z, DTC 114TS, RN 1011, UN 4215
21611	2SC3861	10V, 0,01A, 0,07W, 4GHz	2SC2499, 2SC2570(A), 2SC3512
21612	2SC3862	30V, 0,05A, 2400MHz	-
21613	2SC3863	2SC3864, SMD	DTC 123YK, UN 221H
21614	2SC3864	250MHz	DTC 123YS, UN 421H
21615	2SC3865	<500/1650ns	2SC3497, 2SC3570, 2SC3573, 2SC4054
21616	2SC3866	<1000/4800ns	2SC3559, 2SC4303 2SC4517, 2SC4908
21617	2SC3867	20V, 0,05A, 3800MHz	-
21618	2SC3868	<700/2300ns	2SC3309, 2SC3560...61, 2SC3569
21619	2SC3869	<700/2300ns	2SC3497, 2SC3570, 2SC3573, 2SC4054
21620	)	20V, 0,05A, 900(A1200)MHz	BF 377...378, BF 689K, BF 763, 2SC2570
21621	2SC3870	<700/2300ns	2SC3571, 2SC3574, 2SC4130, 2SC4161
21622	2SC3871	<700/2300ns	2SC3572, 2SC3575, 2SC4162, 2SD1795
21623	2SC3872	<700/2300ns	2SC4296...97, 2SC4423
21624	2SC3873	<700/2300ns	2SC4297, 2SC4423
21625	2SC3874	<700/2300ns	2SC3714
21626	2SC3875	60V, 0,15A, 130MHz	-
21627	2SC3876	35V, 0,5A, 300MHz	-
21628	2SC3877	120V, 0,1A, 100MHz	-
21629	2SC3878	35V, 0,1A, 120MHz	-
21630	2SC3879	35V, 0,05A, 175MHz	-
21631	2SC388(A,ATM)	20(A25)V, 0,02A, 450MHz	BF 198...199, BF 224...225, BF 505
21632	2SC3880	40V, 0,02A, 550MHz	-
21633	2SC3881	30V, 0,05A, 600MHz	-
21634	2SC3883	1500/800V, 5A, 50W	BU 706D, 2SC3481, 2SC3681, 2SC4291
21635	2SC3884	1400/600V, 6A, 50W	2SC3894, 2SC4757, 2SC4830
21636	2SC3884A	2SC3884, 1500/600V	2SC3894, 2SC4757, 2SC4830
21637	2SC3885	1400/600V, 7A, 50W	2SC3895, 2SC4757
21638	2SC3885A	2SC3885, 1500/600V	2SC3895, 2SC4757
21639	2SC3886	1400/600V, 8A, 50W	2SC3896, 2SC4758
21640	2SC3886A	2SC3886, 1500/600V	2SC3896, 2SC4758
21641	2SC389	20V, 0,02A, 500MHz	BF 199, BF 224, BF 310, BF 314, BF 505
21642	2SC3890	<1000/3500ns	2SC3571, 2SC3574, 2SC4130, 2SC4161
21643	2SC3891	2SC3884	2SC4764
21644	2SC3892	2SC3885	2SC4762, 2SC4916

21645	2SC3892A	2SC3885A	2SC4762, 2SC4916
21646	2SC3893	2SC3886	2SC4763, 2SC5043
21647	2SC3893A	2SC3886A	2SC4763, 2SC5043
21648	2SC3894	1500/800V, 6A, 60W	2SC3884A...85A, 2SC4830
21649	2SC3895	1500/800V, 7A, 60W	2SC3885A, 2SC4757
21650	2SC3896	1500/800V, 8A, 70W	2SC3886A, 2SC4758
21651	2SC3897	1500/800V, 10A, 70W	BU 2520AF, 2SC4542, 2SC4759
21652	2SC3898	2SC3899, SMD	FA 1L4Z, DTC 144TK, RN 1413, UN 2210
21653	2SC3899	Rb47kOhm	AA 1L4Z, DTC 144TS, RN 1013, UN 4210
21654	2SC39(A)	350..500MHz	BF 198...199, BF 224...225, BF 505
21655	2SC390(D)	30V, 0,02A, 1000MHz	BF 377...378, BF 689, BF 763, 2N2857
21656	2SC3900	2SC3901, SMD	FA 1L3Z, DTC 143TK, RN 1410, UN 2216
21657	2SC3901	Rb4,7kOhm	AA 1L3Z, DTC 143TS, RN 1010, UN 4216
21658	2SC3902	180/160V, 1,5A, 10W, 120MHz	2SC3117, 2SD669
21659	2SC3903	15V, 65mA, 0,15W, 8,5GHz	2SC3584
21660	2SC3904	2SC3903, SMD	2SC3583, 2SC4591
21661	2SC3905	100V, 15A, 60W, <300/1800ns	2SC3762, 2SC4131, BD 545C, BD 745C
21662	2SC3906	120/120V, 0,05A, 140MHz	-
21663	2SC3906K	2SC3906	2SC3324, 2SC4050
21664	2SC3907	180V, 12A, 130W, 30MHz	2SC3263, 2SC3856
21665	2SC3908	50V, 25A, PQ120W(30MHz)	-
21666	2SC3909	<1000/4500ns	BUW 11A, BUV 82, 2SC3153, 2SC3232
21667	2SC391	20V, 0,02A, 1200MHz	BF 377...378, BF 689, BF 763, 2N2857
21668	2SC3910	<1000/4000ns	2SC3993, 2SD1313
21669	2SC3912	2SC3916, SMD	DTD 114EK, UN 2223
21670	2SC3913	2SC3917, SMD	DTD 143EK, UN 2222
21671	2SC3914	2SC3918, SMD	DTD 123YK, UN 2224
21672	2SC3915	2SC3919, SMD	DTD 123EK, UN 2221
21673	2SC3916	0,3W, 250MHz	DTD 114ES, RN 1224, UN 4223, 2SC3920
21674	2SC3917	0,3W, 250MHz	DTD 143ES, RN 1223, UN 4222, 2SC3921
21675	2SC3918	250MHz	DTD 123YS, RN 1227, UN 4224, 2SC3922
21676	2SC3919	0,3W, 250MHz	DTD 123ES, RN 1222, UN 4221, 2SC3923
21677	2SC392(A)	30V, 0,02A, 800(A>800)MHz	BF 377...378, BF 689, BF 763, 2N2857
21678	2SC3920	2SC3916, 0,6W	2SC3916
21679	2SC3921	2SC3917, 0,6W	2SC3917
21680	2SC3922	2SC3918, 0,6W	2SC3918
21681	2SC3923	2SC3919, 0,6W	2SC3919
21682	2SC3924	<1000/4000ns	2SC3559, 2SC4304, 2SC4517, 2SC4908
21683	2SC3924	<1000/4000ns	2SC3559, 2SC4304, 2SC4517, 2SC4908
21684	2SC3926	20V, 0,03A, 4GHz	BJQ 29, BFQ 81, BFR 93, BFT 75
21685	2SC3927	<1000/5500ns	BUV 47A, BUW 12A, 2SC3637
21686	2SC3928	50V, 0,1A, 200MHz	BC 846...847, BCW 71...72, BCW 81
21687	2SC3929	2SC2405	2SC4098, 2SC4116
21688	2SC3929A	2SC2405	
21689	2SC393	20V, 0,02A	BF 198...199, BF 224...225, BF 505



21690	2SC3930	2SC2295	2SC3931, 2SC3936, 2SC5020
21691	2SC3931	2SC2404	2SC3932, 2SC3935, 2SC5020
21692	2SC3932	2SC2480	BF 517W, BF 547W, BFS 17W, 2SC4780
21693	2SC3933	2SC3077	BF 517W, BF 547W, BFS 17W, 2SC4780
21694	2SC3934	2SC3110	BFR 93W, 2SC4903, 2SC4905...06, 2SC5107
21695	2SC3935	2SC3130	2SC4780, 2SC5110
21696	2SC3936	2SC2778	2SC3931, 2SC5020
21697	2SC3937	2SC3704	BFS 520
21698	2SC3938	2SC3757	-
21699	2SC3939	80V, 0,5A, 1W, 120MHz	2SC2235, 2SD667, 2SD1211, 2SD1937
21700	2SC394	35V, 0,1A, 200MHz	BF 240...241, BF 254...255, BF 594...595
21701	2SC3940	30V, 1A, 1W, 200MHz	2SC2236, 2SC3226, 2SD1207, 2SD1331
21702	2SC3940A	2SC3940, 60V	2SD863, 2SD1014, 2SD1146, 2SD1207
21703	2SC3941	300/300V, 0,07A, 1W, 80MHz	BF 420A, 2SC3249, 2SC3468...69, 2SC4166
21704	2SC3942	300/300V, 0,1A, 10W, 140MHz	2SC3565, 2SC4075
21705	2SC3943	2SC3610, , 8W	2SC3782
21706	2SC3944	150/150V, 1A, 15W, 200MHz	2SC3298, 2SC3364, 2SC4159, 2SC4370
21707	2SC3944A	2SC3944, 180/180V	2SC3298A,B, 2SC4159, 2SC4883A
21708	2SC3945	300/300V, 0,1A, 10W, 100MHz	2SC3565, 2SC4075, 2SC1505...07
21709	2SC3946	350/300V, 0,2A, 15W, >50MHz	2SC1905
21710	2SC3947	<500/3300ns	BUW 11(A)F, 2SC4300, 2SC4428, 2SC4586
21711	2SC3948	<500/3300ns	2SC4199, BUV 47(A), BUW 12(A), 2SC3637
21712	2SC3949	<500/3300ns	BUP 23CF, BUV 48(A)FI, BUW 13(A)F
21713	2SC395	20/40ns	BSS 11...12, BSY 17...18
21714	2SC3950	30V, 0,5A, 5W, 2000MHz	2SC4821
21715	2SC3951	80V, 0,3A, 8W, 600MHz	2SC3954, 2SC3596
21716	2SC3952	80V, 0,5A, 10W, 700MHz	2SC4479, 2SC3597
21717	2SC3953	120V, 0,2A, 8W, 400MHz	2SC3954, 2SC3598
21718	2SC3954	120V, 0,3A, 8W, 400MHz	2SC4565, 2SC3599
21719	2SC3955	200V, 0,1A, 7W, 300MHz	2SC3788, 2SC3600
21720	2SC3956	200V, 0,2A, 7W, 300MHz	2SC4564, 2SC3601, 2SC5024
21721	2SC3958	150/60V, 5A, 30W, <600/3100ns	BUW 64(A...C), 2SC4328, 2SD772(A,B)
21722	2SC3959	2SC3958, 150/80V	BUW 64(A...C), 2SC4328, 2SD772(A,B)
21723	2SC395A	2SC395, 0,5A, 400MHz	BSS 10, BSX 26, BSX 28, BSX 39, 2N3261
21724	2SC396	40V, 0,2A, 0,3W, 450MHz	BSS 11, BSX 19...20, 2N2368...69(A)
21725	2SC3960	2SC3958, 150/100V	BUW 64(A...C), 2SC4328, 2SD772(A,B)
21726	2SC3961	<1000/3300ns	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21727	2SC3962	<500/1900ns	MJE 13070, 2SC2535, 2SC2827, 2SC3830
21728	2SC3963	200/160V, 0,2A, >50MHz	2SC3956, 2SC4564, 2SC4623, BF 415
21729	2SC3964	40V, 2A, 220MHz, B>500	2SD1694
21730	2SC3965	300/300V, 0,1A, 1W, 140MHz	BF 420A, 2SC3249, 2SC3468...69, 2SC4166
21731	2SC3967	2SC3966, SMD	BF 517, BFS 17, 2SC3016, 2SC3161
21732	2SC3968	<1000/3500ns	TIP 75C, 2SC2333, 2SC2738, 2SC3169
21733	2SC3969	2SC3968	2SC3309, 2SC3560...61, 2SC3868, 2SC4421
21734	2SC397(D)	20V, 0,05A, 800(D>400)MHz	BF 377...378, BF 689, BF 763, 2N2857



21735	2SC3970	800/500V, 1,5A, 25W, <1/3,3μs	BUX 84F...85F, 2SC3352, 2SD1571
21736	2SC3970A	2SC3970, 900/500V	BUX 85F, 2SC3794A, 2SC3978, 2SC4304
21737	2SC3971	800/500V, 3A, 30W, <1/3,3μs	BUT 11(A)F, 2SC3749, 2SC4304, 2SD1571
21738	2SC3971A	2SC3971, 900/500V	BUT 11AF, 2SC3559, 2SC4304, 2SC4517
21739	2SC3972	800/500V, 5A, 40W, <1/3,3μs	BUT 11F, BUT 18F, 2SC3353, 2SC3750
21740	2SC3972A	2SC3972, 900/500V	BUT 11AF, BUT 18AF, 2SC3795A, 2SC4518
21741	2SC3973	800/500V, 7A, 45W, <1/3,3μs	BUT 12F, BUT 22BF, BUT 54, BUT 56(A)
21742	2SC3973A	2SC3973, 900/500V	BUT 12AF, BUT 22CF, BUT 56A
21743	2SC3974	800/500V, 7A, 80W, <1/3,3μs	BUV 47FI, BUW 12F, 2SC4429, 2SC4458
21744	2SC3975	800/500V, 10A, 100W, <1/3,3μs	BUW 13(A)F, 2SC4199, 2SC4459, 2SC4587
21745	2SC3976	800/500V, 12A, 150W, <1/3,3μs	2SC3307, 2SC3910, 2SC3982
21746	2SC3977	<700/2800ns	BUX 85F, 2SC3751, 2SC 3794A, 2SC4231
21747	2SC3977A	2SC3977, 1000/800V	BUX 85F, 2SC3751, 2SC4231, 2SC4234
21748	2SC3978	<700/2800ns	BUX 85F, 2SC3752, 2SC4231, 2SC4234
21749	2SC3978A	2SC3978, 1000/800V	BUX 85F, 2SC3752, 2SC4231, 2SC4234
21750	2SC3979	<700/2800ns	BUT 11AF, 2SC3752, 2SC4234, 2SC4304
21751	2SC3979A	2SC3979, 1000/800V	BUT 11AF, 2SC3752, 2SC4234, 2SC4517A
21752	2SC398	20V, 0,02A, >250MHz	BF 225, BF 310, BF 314, BF 502, BF 507
21753	2SC3980	<700/2800ns	BUW 11AF, 2SC4300, 2SC4427, 2SC4882
21754	2SC3980A	2SC3980, 1000/800V	BUW 11AF, 2SC4427, 2SC4882
21755	2SC3981	<700/2800ns	BUW 11AF, 2SC4300, 2SC4586, 2SC4882
21756	2SC3981A	2SC3981, 1000/800V	BUW 11AF, 2SC4427...28, 2SC4584, 2SC4882
21757	2SC3982	<700/3300ns	2SC3307, 2SC3992
21758	2SC3982	2SC3982, 1000/800V	2SC3738, 2SC3992
21759	2SC3983	60V, 0,15A, 0,3W, 180MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21760	2SC3984	2SC3983	BC 174, BC 182, BC 190, BC 546, 2SD767
21761	2SC3985	50V, 1,2A, 15W, 180MHz, B4k	-
21762	2SC3986	50V, 2A, 15W, 180MHz, B4k	-
21763	2SC3987	50V, 3A, 15W, 180MHz, B4k	-
21764	2SC3988	<500/3300ns	BUX 98P
21765	2SC3989	<500/3300ns	2SD1313
21766	2SC399	20V, 0,02A, >250MHz	BF 224, BF 503, BF 505, BF 507, 2SC3136
21767	2SC3990	<500/3300ns	-
21768	2SC3991	<500/3300ns	-
21769	2SC3992	<500/3300ns	2SC3738, 2SC4096
21770	2SC3993	<500/3300ns	-
21771	2SC3994	<500/3300ns	-
21772	2SC3995	1500/800V, 12A, 180W	2SC4288A
21773	2SC3996	1500/800V, 15A, 180W	2SC4289A
21774	2SC3997	1500/800V, 20A, 250W	2SC4290A, 2SC4897
21775	2SC3998	1500/800V, 25A, 250W	2SC4789
21776	2SC3999	300V, 0,1A, 0,75W, 300MHz	BF 299, BF 393, BF 420A, 2SC3468
21777	2SC40	2SC39, 750MHz	BF 198...199, BF 224...225, BF 505
21778	2SC400(D,M)	300MHz	BC 168, BC 183, BC 238, BC 548, 2N3904
21779	2SC4000	2SC3999, 1W	BF 393, BF 420A, MPSA 42, 2SD1350

21780	2SC4001	2SC3999, 7W	BF 417, BF 459, 2SC3417, 2SC3503
21781	2SC4002	400/400V, 0,2A, 0,6W, 70MHz	MPSA 44...45, 2SD1350
21782	2SC4003	2SC4002, 10W	2SC3129, 2SC3588, 2SC4499
21783	2SC4004	900/800V, 1A, 30W, <1/4μs	BUX 85F, 2SC3751, 2SC3794A, 2SC4231
21784	2SC4005	42V, 2A, 15W, 180MHz, B4000	-
21785	2SC4006	42V, 3A, 20W, 180MHz, B4000	-
21786	2SC4007	100V, 4A, 40W, 10MHz	BD 243C, BD 539C, BD 953, 2SD726
21787	2SC4008	2SC4007, , 30W	2SC3691, 2SD1586, BD 243C, BD 539C
21788	2SC4009	B100000	BC 517, MPSA 25...27
21789	2SC401	/650ns	BC 167, BC 182, BC 237, BC 547, 2SD767
21790	2SC4010	2SC2021M	2SC1740
21791	2SC4011	2SC2063M	2SC2058
21792	2SC4012	2SC3078M	2SC3078
21793	2SC4013	2SC3079M	2SC3079
21794	2SC4014	2SC3080M	2SC3080
21795	2SC4015	2SC3270M	2SC3270
21796	2SC4016	2SC1652,, 0,4W	2SC1652
21797	2SC4017	2SC1545	2SC1545
21798	2SC4018K	50V, 0,1A, 230MHz	BC 846...847, BCW 71...72, BCW 81
21799	2SC4019	300/220V, 0,1A, 10W, 90MHz	2SC2924, 2SC3408, 2SC3805
21800	2SC402(A,B)	140..170MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21801	2SC4020	900/800V, 3A, 50W, <1/6μs	BUT 11A, BUV 46A, 2SC3150, 2SC3490
21802	2SC4021	1500/800V, 3A, 100W, -/4,8μs	2SC4022, 2SD1882
21803	2SC4022	1500/800V, 6A, 120W, -/4,8μs	BU 2508A, BUV 71, 2SC4023
21804	2SC4023	1500/800V, 10A, 130W, -/4,8μs	BU 2520A, BUV 71
21805	2SC4024	100V, 10A, 35W	2SC4554
21806	2SC4026	<700/2300ns	2SC3570, 2SC3573, 2SC4054, 2SC4073
21807	2SC4027	180/160V, 1,5A, 15W, 120MHz	2SD1033, 2SD1080...82, 2SD2122...23
21808	2SC4028	1400/800V, 10A, 100W, <1/5μs	BU 2520A, BUV 71, 2SC4023
21809	2SC4029	230/230V, 15A, 150W, 30MHz	-
21810	2SC402S	2SC402, 80V	BC 546, 2SC1775(A), 2SC2240, 2SC3245
21811	2SC403(A,B,C)	140..170MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
21812	2SC4030	1700/900V, 0,05A, 1,2W, 6MHz	2SC4578
21813	2SC4031	2000/900V, 0,02A, 1,2W, 6MHz	2SC4579
21814	2SC4032	2SC1545	2SC1545
21815	2SC4033	130V, 0,03A, 0,15W, 60MHz	2SC2362K, 2SC2375, 2SC3245A, 2SC3800
21816	2SC4034	80V, 0,05A, 0,15W, 140MHz	BC 546, 2SC1890(A), 2SC2675, 2SD1512
21817	2SC4035	2SC1614	2SC1614
21818	2SC4036	2SC1615	2SC1615
21819	2SC4037	2SC1652	2SC1652
21820	2SC4038	2SC2021	2SC1740
21821	2SC4039	2SC2063	2SC2058
21822	2SC404	50V, 0,05A, 0,1W, 170MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
21823	2SC4040	2SC2673	2SC2673
21824	2SC4041	2SC3080	2SC3080

21825	2SC4042(S)	30V, 0,05A, 0,15W, 1500MHz	BF 377...378, BF 357, BF 630, 2SC2570
21826	2SC4042(S)	30V, 0,05A, 0,15W, 1500MHz	BF 377...378, BF 357, BF 630, 2SC2570
21827	2SC4043(S)	20V, 0,05A, 0,15W, 3200MHz	2SC2498...99, 2SC2570, 2SC3776...77
21828	2SC4043(S)	20V, 0,05A, 0,15W, 3200MHz	2SC2498...99, 2SC2570, 2SC3776...77
21829	2SC4044	30V, 0,05A, 0,15W, 2000MHz	BF630, 2SC2498...99, 2SC2570, 2SC3776...77
21830	2SC4045	20V, 0,05A, 0,15W, 3200MHz	2SC2498...99, 2SC2570, 2SC3776...77
21831	2SC4046	120/120V, 0,2A, 8W, 350MHz	2SC3598...99
21832	2SC4047	2SC4048, SMD	FA 1A4P, DTC 114YK, RN 1407, UN 2214
21833	2SC4048	Rbe47kOhm	AA 1A4P, DTC 114YS, RN 1007, UN 4214
21834	2SC4049	2SC4048	2SC4048
21835	2SC405	25V, 0,2A, 0,15W, B60	ASY 28...29, ASY 73...75
21836	2SC4050	120/120V, 0,1A, 310MHz	2SC1622A, 2SC3324
21837	2SC4051	<500/2200ns	BUT 11, BUT 93, BUV 46A, 2SC3086
21838	2SC4052	2SC4051, , 25W	BUT 11F, 2SC4054, 2SC4304, 2SD1571
21839	2SC4052	2SC4051, , 25W	BUT 11F, 2SC4054, 2SC4304, 2SD1571
21840	2SC4053	<500/2200ns	BUT 11, MJE 13070, 2SC3047, 2SC3087
21841	2SC4054	2SC4053	BUT 11F, 2SC3750, 2SC3795, 2SC4056
21842	2SC4054	2SC4053	BUT 11F, 2SC3750, 2SC3795, 2SC4056
21843	2SC4055	<500/2200ns	BUT 54, BUT 56(A), MJE 13006...07
21844	2SC4056	2SC4055, , 45W	BU 306F, BUT 12F, BUT 22BF, 2SC4546
21845	2SC4056	2SC4055, , 45W	BU 306F, BUT 12F, BUT 22BF, 2SC4546
21846	2SC4057	2SC4055, 80W	BUP 22A, 2SC3831, 2SC4058, 2SC4157
21847	2SC4058	<500/2200ns	BUP 23A, 2SC3450, 2SC3831, 2SC4157
21848	2SC4059	<500/2200ns	BUP 23A, BUW 13(A), 2SC3451, 2SC3638
21849	2SC406	2SC405, B120	ASY 28...29, ASY 73...75
21850	2SC4060	<500/2200ns	BUX 98AP, 2SC3988
21851	2SC4061K	300/300V, 0,1A, 100MHz	BFN 26
21852	2SC4062	B>450	2SC4553
21853	2SC4063	B>450	2SC4554
21854	2SC4064	50V, 12A, 35W, 40MHz	2SC3709...10, 2SD1669, 2SD1062
21855	2SC4065	2SC4064, 60V, +-12A	2SC3709...10, 2SD1669, 2SD1062
21856	2SC4066	2SC4067, SMD	DTC 144GK
21857	2SC4067	Rbe47kOhm	DTC 144GS
21858	2SC4068	2SC3966, SMD	BF 517W, BF 547W, BFS 17W, 2SC4780
21859	2SC4069	2SC4070, SMD	DTC 124GK
21860	2SC407	150/100V, 10A, 100W, B>10	BUW 70, BUX 17(A...C), BUY 18, 2SC2944
21861	2SC4070	Rbe22kOhm	DTC 124GS
21862	2SC4073	500/400V, 5A, 30W, <1/3,5µs	2SC3570, 2SC3573, 2SC4054, 2SC4417
21863	2SC4074	30V, 0,05A, 1500MHz	BFR 53, 2SC3014, 2SC3016, 2SC3773
21864	2SC4075	300/300V,0,2A, 10W, >50MHz	2SC3565, 2SC1505...07, 2SC1755...57
21865	2SC4076	60V, 0,15A, 180MHz	BC 846, BCV 71...72, 2SC3323, 2SC4050
21866	2SC4077	30V, 0,1A, 0,3W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2240
21867	2SC4078	2SC4077	2SC4077
21868	2SC4079	2SC4077, SMD	BC 849...850, BCF 32...33, BCF 81
21869	2SC408	2SC407, B>20	BUW 70, BUX 17(A...C), BUY 18, 2SC2944

21870	2SC4080	200/200V, 0,1A, 400MHz	BFN 16, BFN 18, 2SC3380, 2SC3515
21871	2SC4081	2SC2412K	BC 847W, 2SC4116, 2SC4141, 2SC4177
21872	2SC4082	2SC3837K	BF 517W, BF 547W, BFS 17W, 2SC4780
21873	2SC4083	2SC3838K	2SC4780, 2SC5110
21874	2SC4084	2SC3839K	2SC4780, 2SC5110
21875	2SC4085	30V, 0,02A, 1000MHz	2SC4086...4087
21876	2SC4086	30V, 0,05A, 2000MHz	2SC4087
21877	2SC4087	30V, 0,05A, 2000MHz	2SC4086
21878	2SC4088	15V, 5mA, 4000MHz	2SC4089
21879	2SC4089	25V, 0,03A, 4000MHz	-
21880	2SC409	2SC407, 200/140V	BUX 17(A...C), BUX 42, BUY 18, 2SC2944
21881	2SC4090	30V, 0,05A, 2000MHz	2SC4092
21882	2SC4091	15V, 5mA, 4000MHz	2SC4092
21883	2SC4092	25V, 0,07A, 6000MHz	2SC4093
21884	2SC4093	20V, 0,1A, 6500MHz	-
21885	2SC4094	20V, 0,065A, 9000MHz	-
21886	2SC4095	20V, 0,035A, 10GHz	-
21887	2SC4096	1400/800V, 10A, 150W, 1/3,8μs	2SC3995, 2SC4111
21888	2SC4097	2SC2411K	BC 817W, 2SC4519, 2SD1949
21889	2SC4098	2SC2413K	2SC4081, 2SC4128, 2SC4155
21890	2SC4099	2SC2059K	2SC3931, 2SC3935, 2SC5020
21891	2SC41	150V, 5A, 50W, 20MHz, B>12	BD 245D, 2N3442, 2SC2260...2262, 2SD731
21892	2SC410(A)	B>20	BUX 17(A...C), BUX 42, BUY 18, 2SC2944
21893	2SC4100	2SC3082K	BF 547W, BF 517W, BFS 17, 2SC4780
21894	2SC4101	120V, 0,05A, 140MHz	2SC4117, 2SC4180, 2SD1821
21895	2SC4102	2SC3906K	2SC4117, 2SC4180, 2SD1821
21896	2SC4103	2SC3802K	BF 517W, BF 547W, BFS 17, 2SC4780
21897	2SC4104	70V, 0,05A, 700MHz	-
21898	2SC4105	<500/2800ns	BUT 93, TIP 75C, 2SC3038, 2SC4051
21899	2SC4106	<500/2800ns	MJE 13006, 2SC3170, 2SC4055, 2SC4055
21900	2SC4107	<500/2800ns	BUT 76, MJE 13008, 2SC3562, 2SC4164
21901	2SC4108	<500/2800ns	BUP 23, 2SC3520, 2SC4139, 2SC4434
21902	2SC4109	<500/2800ns	BUX 98(A)P, 2SC3850, 2SC4140
21903	2SC411	2SC407, 300/200V	BUX 17A...C, BUX 42, BUY 18, 2SC2626
21904	2SC4110	<500/2800ns	BUX 98P
21905	2SC4111	<1/12,6μs	2SC3995
21906	2SC4112	2SC4113, SMD	-
21907	2SC4113	Rb2,2kOhm	-
21908	2SC4114	600/550V, 0,1A, <2/5,5μs	-
21909	2SC4115(S)	40V, 2A, 0,4W, 290MHz	2SC3225, 2SD1055, 2SD1227, 2SD2177
21910	2SC4116	60V, 0,15A, >80MHz	BC 846W, 2SC4141, 2SC4177, 2SD1819A
21911	2SC4117	120V, 0,1A, 100MHz	2SC4101...4102, 2SC4180
21912	2SC4118	35V, 0,5A, 300MHz	BC 817W, 2SC4097, 2SD1820A, 2SD1949
21913	2SC4119	1500/800V, 15A, 250W, B>25	-
21914	2SC412	2SC407, 300/200V, B>20	BUX 17A...C, BUX 42, BUY 18, 2SC2626

21915	2SC4120	2SC4121, SMD	FA 1F4Z, DTC 124TK, KSR 1111, UN 2217
21916	2SC4121	Rb22kOhm	AA 1F4Z, DTC 124TS, KSR 1011, UN 4217
21917	2SC4122	1500/800V, 6A, 60W	2SC4294, 2SC4764
21918	2SC4123	1500/800V, 7A, 60W	2SC3892A, 2SC4762, 2SC4916
21919	2SC4124	1500/800V, 8A, 70W	2SC3892, 2SC4763
21920	2SC4125	1500/800V, 10A, 70W	BU 2520DF
21921	2SC4126	15V, 0,05A, 6GHz	2SC4092
21922	2SC4127	15V, 0,05A, 7,5GHz	2SC4094
21923	2SC4128	50V, 0,1A, 230MHz	2SC4081, 2SC4141
21924	2SC4129	400/400V, 5A, 30W, <1/3,5μs	2SC3570, 2SC3573, 2SC4073, 2SC4418
21925	2SC413	60V, 1,5A, 20W, 180MHz	BD 137, BD 228, BD 377, 2SD1177...1178
21926	2SC4130	500/400V, 7A, 30W, <1/2,7μs	2SC3571, 2SC3574, 2SC3890, 2SC4056
21927	2SC4131	100V, 15A, 60W, 0,5/2,4μs	-
21928	2SC4132	120V, 2A, 80MHz	2SC3649, 2SD1420...1421
21929	2SC4133	Rbe47kOhm	DTC 143ZS, KSR 1014, RN 1006, 2SC4195
21930	2SC4134	120V, 1A, 10W, 120MHz	2SD1074...75, 2SD1283...84
21931	2SC4135	120V, 2A, 15W, 120MHz	2SD1815...16
21932	2SC4136	200/120V, 20A, 140W, <0,5/2μs	BUV 11, BUW 58, BUX 11, 2SC2865(A)
21933	2SC4137	25V, 0,1A, 400MHz, B>560	-
21934	2SC4138	500/400V, 10A, 80W, <1/3,5μs	BUP 23, 2SC3042, 2SC4058, 2SC4157
21935	2SC4139	500/400V, 15A, 120W, <1/3,5μs	BUP 23, 2SC3435, 2SC3520, 2SC4434
21936	2SC414	90V, 1,5A, 20W, 180MHz	BD 139, BD 230, BD 379, 2SD1177...1178
21937	2SC4140	500/400V, 18A, 130W, <1/3,5μs	BUX 98AP, 2SC3850, 2SC4060, 2SC4110
21938	2SC4141	60V, 0,1A, 180MHz	BC 846W, 2SC4116, 2SC4177, 2SD1819A
21939	2SC4142	1500/800V, 5A, 50W	BU 706F, 2SD1545...46, 2SD1655...56
21940	2SC4143	1500/800V, 5A, 50W	BU 706F, 2SD1545...46, 2SD1655...56
21941	2SC4144	1300/500V, 8A, 50W	BU 2508AF, BU 908F, 2SC3886, 2SD1548
21942	2SC4145	80V, 2A, 1,2W, <1/4μs	2SC3328, 2SC3669, 2SD1015, 2SD2182
21943	2SC4146	2SC4133, SMD	DTC143ZK, KSR 1114, RN1406
21944	2SC4147	300/300V, 0,1A, 5W, 100MHz	BF 417, BF 459, 2SC3417, 2SC3503
21945	2SC4148	60V, 7A, 25W, <300/2000ns	2SC3747
21946	2SC4148	60V, 7A, 25W, <300/2000ns	2SC3747
21947	2SC4149	60V, 10A, 25W, <300/2000ns	2SC3748
21948	2SC4149	60V, 10A, 25W, <300/2000ns	2SC3748
21949	2SC415	120V, 1,5A, 20W, 180MHz	2SC2690A, 2SC3117, 2SD669
21950	2SC4150	60V, 12A, 25W, <300/2000ns	2SC3709, 2SC4065
21951	2SC4150	60V, 12A, 25W, <300/2000ns	2SC3709, 2SC4065
21952	2SC4151	60V, 15A, 30W, <300/2000ns	2SC3694, 2SC4552
21953	2SC4151	60V, 15A, 30W, <300/2000ns	2SC3694, 2SC4552
21954	2SC4152	1400/700V, 0,3A, 20W, <2/4μs	2SC4631
21955	2SC4153	200/120V, 7A, 30W, <0,5/3,5μs	2SD1792
21956	2SC4154	2SC2320	2SC4116
21957	2SC4155	2SC3928	BC 847W, 2SC4081, 2SC4128, 2SC4141
21958	2SC4157	<0,5/3μs	BUP 23, 2SC3450, 2SC3831, 2SC4058
21959	2SC4158	250/250V, 0,1A, 300MHz, 8W	2SC3565, 2SC4075, 2SC1505...1507



21960	2SC4159	180/160V, 1,5A, 15W, 100MHz	2SC3298A,B, 2SC4883A
21961	2SC416	90V, 1,5A, 20W, 180MHz	BD 139, BD 230, BD 379, 2SD1177...1178
21962	2SC4160	2SC4105, , 25W	2SC3573, 2SC4054, 2SC4073, 2SC4418
21963	2SC4161	2SC4106, , 30W	2SC3571, 2SC3574, 2SC4056, 2SC4130
21964	2SC4162	2SC4107, , 35W	2SC3562, 2SC3572, 2SC3575, 2SD1795
21965	2SC4163	2SC4108, , 40W	-
21966	2SC4164	2SC4108, 70W	BUV 66(A), MJE 13008...13009
21967	2SC4165	300/300V, 0,2A, 130MHz	BF 417, 2SC2621, BF 617, BF 758...759
21968	2SC4166	400/400V, 0,1A, 0,9W, 20MHz	2SC3469
21969	2SC4168	40V, 0,15A, <40/205ns	-
21970	2SC4169	50V, 1,2A, 1W, B4000	2SD1153, 2SD1809, 2SD1929, 2SD2026
21971	2SC4170	50V, 0,2A, 180MHz	-
21972	2SC4171	800/500V, 3A, 40W, <1/4μs	2SC4221, 2SC4599, BUT 11(A), 2SC3086
21973	2SC4172	800/500V, 5A, 50W, <1/4μs	2SC4222, 2SC4600, BUT 11(A), 2SC3047
21974	2SC4173	60V, 0,5A, 30/150ns	2SD1820A
21975	2SC4174	180/160V, 0,05A, 120MHz	BF 820W, BF 822W
21976	2SC4175	40V, 0,2A, <20/40ns	2SC4176
21977	2SC4176	40V, 0,2A, <12/18ns	-
21978	2SC4177	60V, 0,1A, 250MHz	2SC4141
21979	2SC4178	30V, 0,02A, 600MHz	2SC3932, 2SC3935
21980	2SC4179	50V, 0,05A, >150MHz	2SC3931, 2SC3936
21981	2SC4180	120V, 0,05A, >50MHz	2SC4101...4102, 2SC4117
21982	2SC4181(A)	60V, 0,15A, B>1000	-
21983	2SC4182	30V, 0,05A, 900MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
21984	2SC4183	30V, 0,02A, 900MHz	BFS 17W, 2SC3933, 2SC4780
21985	2SC4184	30V, 0,05A, 1500MHz	2SC5110, 2SC4780
21986	2SC4185	30V, 0,05A, 1600MHz	2SC5110, 2SC4780
21987	2SC4186	25V, 0,03A, 2000MHz	BFR 93W, 2SC5110, 2SC4780
21988	2SC4187	15V, 5mA, 3000MHz	BF 775, BFQ 29, BFR 35, 2SC3098
21989	2SC4188	200V, 0,1A, 10W, 150MHz	2SC3782
21990	2SC4189	300/300V, 0,1A, 100MHz	BFN 18, 2SC3380, 2SC3515, 2SC3554
21991	2SC4190	65V, 0,3A, >1500MHz	-
21992	2SC4191	500/400V, 2A, 20W, <1/3,5μs	BUX 84...85, TIP 75C, 2SC2738, 2SC3169
21993	2SC4192	500/400V, 3A, 30W, <1/3,5μs	BUT 93, TIP 75C, 2SC2535, 2SC4105
21994	2SC4193	500/400V, 5A, 40W, <1/3,5μs	MJE 13070, 2SC2535, 2SC2827, 2SCSC3830
21995	2SC4194	500/400V, 7A, 50W, <1/3,5μs	MJE 13006, 2SC3170, 2SC4055, 2SC4106
21996	2SC4195	2SC4133	2SC4133
21997	2SC4196	25V, 0,05A, 2400MHz	BFT 75, 2SC3014, 2SC3772...3773
21998	2SC4197	25V, 0,05A, 3800MHz	BF 770A, BFT 75, 2SC2845, 2SC3774
21999	2SC4198	25V, 0,5A, 200MHz, B820	-
22000	2SC4199	1400/800V, 10A, 100W	BU 2520AF, 2SC3897, 2SC4542, 2SD1548
22001	2SC4199A	2SC4199, 1500/800V	BU 2520AF, 2SC3897, 2SC4542, 2SC5068
22002	2SC42	2SC41, B>4	BD 245D, 2N3442, 2SC2260...2262, 2SD731
22003	2SC4200	20V, 0,6A, 5W, 2500MHz	-
22004	2SC4201	100V, 0,5A, 30W, 1100MHz	2SC4411



22005	2SC4202	2SC4201, 20W	2SC4411
22006	2SC4203(LB)	180V,0,5A,10W,400MHz	-
22007	2SC4204	30V, 0,7A,B>800	2SC3070, 2SC3225, 2SC3673, 2SD1582
22008	2SC4205	400/400V, 5A, 40W, <1/3,5µs	MJE 52T...53T, 2SC2827, 2SC3056
22009	2SC4206	900/600V, 6A, 80W, <1/4µs	BU 903, BU 426A, 2SC3536, 2SC3636
22010	2SC4207	60V, 0,15A, >80MHz	-
22011	2SC4208	30V, 0,5A, 1W, 150MHz	BC 635, 2SC2236, 2SD1146, 2SD1331
22012	2SC4208A	2SC4208, 60V	BC 637, 2SC3328, 2SD1207, 2SD1835
22013	2SC4209	80V, 0,3A, 100MHz	BCW 66, 2SD1782
22014	2SC4210	35V, 0,8A, 120MHz	BCW 65...66, 2SC3265, 2SD1782
22015	2SC4211	55V, 0,15A, 200MHz	BC 848W, 2SC4116, 2SC4141, 2SC4177
22016	2SC4212	2SC3946, 5W	BF 850, 2SC3418
22017	2SC4213	50V, 0,3A, B150	-
22018	2SC4214	25V, 0,02A, 850MHz	-
22019	2SC4215	40V, 0,02A, 550MHz	BF 599, BF 799, BFS 20, 2SC3931...32
22020	2SC4216	2SC3901	2SC3901
22021	2SC4217	300V, 0,2A, 70MHz	2SC3789...90, 2SC3417, 2SC3503
22022	2SC4218	300/300V, 0,1A, 0,5W, 70MHz	BF 299, BF 420A, 2SC3249, 2SC3468
22023	2SC4219	500/400V, 4A, 40W, <0,5/2,8µs	2SC4597
22024	2SC4220	500/400V, 7A, 50W, <0,5/2,8µs	2SC4598
22025	2SC4221	800/500V, 3A, 40W, <0,5/3,3µs	2SC4171, 2SC4599
22026	2SC4222	800/500V, 5A, 50W, <0,5/3,3µs	2SC4172, 2SC4600
22027	2SC4223	<0,5/3,3µs	2SC4601
22028	2SC4224	<0,5/3,3µs	2SC4602
22029	2SC4225	-/12V, 0,07A, 4000MHz	BFR 106, 2SC3161, 2SC3774...75
22030	2SC4226	-/12V, 0,1A, 4500MHz	BFR 106, 2SC3775
22031	2SC4227	-/10V, 65mA, 7000MHz	BFR 193, 2SC3445, 2SC5084
22032	2SC4228	-/10V, 35mA, 8000MHz	BFR 183, 2SC3445, 2SC5064
22033	2SC4229	30V, 0,02A, 1000MHz	BF 517, BFS 17, 2SC3161, 2SC3099
22034	2SC423	40V, 0,3A, 0,5W, 500MHz	BFR 36, BFW 16...17, BFX 55
22035	2SC4230	<0,5/3,8µs	BU 505, MJE 8500, 2SC3178
22036	2SC4231	2SC4230, 30W	BU 505F, 2SC4234, MJE 8500, 2SC3178
22037	2SC4231	2SC4230, 30W	BU 505F, 2SC4234, MJE 8500, 2SC3178
22038	2SC4232	2SC4230, 70W	2SD1543, BU 705, 2SC3483, 2SD1493...94
22039	2SC4233	<0,5/3,8µs	BU 505, MJE 8502, 2SC3050
22040	2SC4234	2SC4233, 45W	BU 505F, MJE 8502, 2SC3050
22041	2SC4234	2SC4233, 45W	BU 505F, MJE 8502, 2SC3050
22042	2SC4235	2SC4233, 80W	BU 706, 2SC3387, 2SC3642
22043	2SC4236	<0,5/3,8µs	BUV 89, 2SC3466, 2SC3643
22044	2SC4237	<0,5/3,8µs	BUV 48B,C, 2SC3644, 2SC4023
22045	2SC4238	30V, 0,05A, 1300MHz	BFR 53, 2SC3014, 2SC3016, 2SC4082
22046	2SC4239	15V, 0,05A, 2000MHz	2SC4780, 2SC5110
22047	2SC424	2SC423, 0,2W	BFR 36, BFW 16...17, BFX 55
22048	2SC4241	20V, 0,08A, 6500MHz	2SC4093
22049	2SC4242	450/400V, 7A, 40W, 1/3µs	MJE 13006, 2SC3170, 2SC4055, 2SC4106

22050	2SC4243	300/300V, 0,1A, 1W, 100MHz	2SC2924, 2SC3408, 2SC3805, 2SC4019
22051	2SC4244	25V, 0,02A, 850MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22052	2SC4245	30V, 0,05A, 2400MHz	2SC4780, 2SC5110
22053	2SC4246	30V, 0,05A, 1500MHz	2SC4780, 2SC5110
22054	2SC4247	20V, 0,03A, 4000MHz	BFR 93W, 2SC4903, 2SC5107
22055	2SC4248	20V, 0,03A, 4000MHz	BFR 93W, 2SC4903, 2SC5107
22056	2SC4249	30V, 0,02A, 650MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22057	2SC425	2SC423, 20V	BFR 36, BFW 16...17, BFX 55
22058	2SC4250	30V, 0,05A, 1400MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22059	2SC4251	30V, 0,05A, 1100MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22060	2SC4252	20V, 0,03A, 2000MHz	BFR 93W, 2SC4903, 2SC5107
22061	2SC4253	30V, 0,05A, 600MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22062	2SC4254	50V, 0,1A, 230MHz	BC 846W, 2SC4081, 2SC4128, 2SC4177
22063	2SC4255	20V, 0,03A, 2000MHz	BF 517, BFR 53, 2SC3099, 2SC3773
22064	2SC4256	1500/1200V, 0,01A, 5W	2SC4257, 2SC4451
22065	2SC4257	1500/1200V, 0,03A, 7W	2SC3675
22066	2SC4258	2SC710	2SC3931, 2SC3936, 2SC5020
22067	2SC4259	2SC4229	BF 517W, BFS 17W, 2SC3933, 2SC4780
22068	2SC426	2SC423, 20V, 0,2W	BFR 36, BFW 16...17, BFX 55
22069	2SC426	2SC423, 20V, 0,2W	BFR 36, BFW 16...17, BFX 55
22070	2SC4260	2SC4197	2SC4780, 2SC5110
22071	2SC4261	2SC4196	2SC4780, 2SC5110
22072	2SC4262	2SC3797	2SC4780, 2SC5110
22073	2SC4263	2SC3493	BF 517W, BFS 17W, 2SC3933, 2SC4780
22074	2SC4264	2SC2734	2SC4780, 2SC5110
22075	2SC4265	2SC2735	BF 517W, BFS 17W, 2SC3933, 2SC4780
22076	2SC4266	2SC3928, 0,3W	BC 167, BC 182, BC 237, BC 547, 2SD767
22077	2SC4267	-/20V, 15mA, >450MHz	BF 554, BFS 18...19, 2SC2404, 2SC2778
22078	2SC4269	30V, 0,05A, 1200MHz	BF 517, BFS 17, 2SC3016, 2SC3161
22079	2SC427	40V, 0,1A, 0,3W, 350MHz	BC 167, BC 182, BC 237, BC 547, 2N3904
22080	2SC4270	25V, 0,05A, 3000MHz	BFT 75, 2SC3014, 2SC3161, 2SC3772...73
22081	2SC4271	30V, 0,3A, 5W, 2200MHz	2SC3595
22082	2SC4272	PQ1,8W(27MHz)	BCX 56, 2SD1005, 2SD1368, 2SD1422
22083	2SC4273	500/400V, 5A, 40W, <1/3μs	BUT 93, 2SC2535, 2SC2827, 2SC3830
22084	2SC4274	500/400V, 10A, 40W, <1/3μs	MJE 13008, 2SC3562, 2SC4107, 2SC4164
22085	2SC4275	500/400V, 10A, 80W, <1/3μs	BUP 23, 2SC2828, 2SC3042, 2SC4138
22086	2SC4276	500/400V, 15A, 80W, <1/3μs	BUP 23, 2SC3435, 2SC3520, 2SC4139
22087	2SC4277	500/400V, 5A, 80W, <1/3μs	TIP 58A, 2SC2962, 2SC3083
22088	2SC4278	150/150V, 10A, 100W, 20MHz	BD 245D, 2SC2837, 2SC2987A, 2SD1703
22089	2SC428	2SC427, 20V	BC 168, BC 183, BC 238, BC 548, 2N3904
22090	2SC4283	<0,5/3,8μs	2SC4583
22091	2SC4284	1400/600V, 8A, 150W, <1/4,3μs	MJ 8505, 2SC3594
22092	2SC4285	<1/4,3μs	BUX 88, MJ 8505
22093	2SC4286	2SC4284, 100W	-
22094	2SC4287	2SC4285, 100W	-

22095	2SC4288	1400/600V, 12A, 200W	2SC3995, 2SC4096, 2SC4111
22096	2SC4288A	2SC4288, 1500/600V	2SC3995, 2SC4111
22097	2SC4289	1400/600V, 16A, 200W	2SC3996
22098	2SC4289A	2SC4288, 1500/600V	2SC3996
22099	2SC429	25V, 0,01A, 380MHz	BF 198...199, BF 224...225, BF 314
22100	2SC4290	1400/600V, 20A, 200W	2SC3997, 2SC4897, 2SD2356
22101	2SC4290A	2SC4288, 1500/600V	2SC3997, 2SC4897, 2SD2356
22102	2SC4291	1500/800V, 5A, 100W	2SC3481...82, 2SC3681, BU 2508D
22103	2SC4292	1500/800V, 6A, 100W	2SC3482, 2SC3681, BU 2508D
22104	2SC4293	2SC4291, , 50W	2SC3892A, 2SC4122, BU 2508DF
22105	2SC4294	2SC4292, , 50W	2SC3892A, 2SC4122, BU 2508DF
22106	2SC4295(M)	400/400V, 0,1A, 1W, 1/7,2μs	BF 487, MPSA 45, 2SC3469, 2SD1385
22107	2SC4296	500/400V, 10A, 75W, <1/3,5μs	2SC4423, 2SC4459, 2SC4138
22108	2SC4297	500/400V, 12A, 75W, <1/3,5μs	BUP 23BF, 2SC4423, 2SC4459, 2SC4139
22109	2SC4298	500/400V, 15A, 80W, <1/3,5μs	BUP 23BF, 2SC4424, 2SC4139
22110	2SC4299	900/800V, 3A, 70W, <1/6μs	BUW 11AF, 2SC4426, 2SC4445
22111	2SC42A	2SC41, 200V	BD 245F, 2SC2262, 2SD555, 2SD751
22112	2SC43	2SC41, 100V, B>4	BD 245C, BDV 95, BDX 95, 2N5758
22113	2SC430	2SC429, 420MHz	BF 198...199, BF 224...225, BF 314
22114	2SC4300	900/800V, 5A, 75W, <1/6μs	BUW 11AF, 2SC4428, 2SC4586
22115	2SC4301	900/800V, 7A, 80W, <1/6μs	BUW 12AF, BUV 47AFI, 2SC4429
22116	2SC4302	900/800V, 5A, 75W, <1/4,5μs	BUW 11AF, 2SC4300, 2SC4428
22117	2SC4303	1400/800V, 6A, 80W, <1/4,3μs	BU 508AF, 2SC4941, 2SD1546, 2SD1656
22118	2SC4303A	2SC4303, 1500/800V	BU 508AF, 2SC4941, 2SD1546, 2SD1656
22119	2SC4304	900/800V, 3A, 35W, <0,7/4,7μs	BUT 11AF, 2SC3559, 2SC4517, 2SC4908
22120	2SC4305	100/40V, 7A, 40W, <1/3,5μs	BD 543C, BD 711, BD 801, MJE 15028
22121	2SC4305	100/40V, 7A, 40W, <1/3,5μs	BD 543C, BD 711, BD 801, MJE 15028
22122	2SC4306	30V, 8A, 15W, <300/1150ns	2SC4668, 2SD1804
22123	2SC4308	30V, 0,3A, 0,6W, 2500MHz	2SC4693
22124	2SC4309	<500/2130ns	2SC3738, 2SC3982A, 2SC3992
22125	2SC431	150/100V, 30A, 200W, B>10	2SC1299, 2SC1301, 2SC1872, 2SC2128
22126	2SC4310	<500/3500ns	BUT 11(A), BUT 18(A), BUT 56(A)
22127	2SC4311	2SC4310, , 40W	BUT 11(A)F, BUT 18(A)F, BUV 46(A)FI
22128	2SC4311	2SC4310, , 40W	BUT 11(A)F, BUT 18(A)F, BUV 46(A)FI
22129	2SC4312	<500/3500ns	BUW 11A, BUW 131A, 2SC3535...36
22130	2SC4313	<500/3500ns	BUV 47A, BUW 12A, 2SC3637...38
22131	2SC4314	<500/3500ns	BUV 48A, BUW 13A, BUW 133A, 2SC3638
22132	2SC4315	20V, 0,08A, 7GHz	-
22133	2SC4316	20V, 40mA, 9000MHz	-
22134	2SC4317	2SC4316, SMD, 10GHz	2SC5089
22135	2SC4318	2SC4316, SMD	-
22136	2SC4319	2SC4316, 10GHz	-
22137	2SC432	2SC431, B>20	2SC1299, 2SC1301, 2SC1872, 2SC2128
22138	2SC4320	2SC4316, SMD, 10GHz	2SC5092
22139	2SC4321	2SC4316, SMD, 10GHz	2SC5090

22140	2SC4322	10V, 25mA, 10GHz	BFR 505, 2SC5094
22141	2SC4323	2SC4322	2SC3586...87
22142	2SC4324	2SC4322	-
22143	2SC4325	2SC4322	2SC3585
22144	2SC4326(LK)	12V, 0,05A, 800MHz	BF 517, BFS 17, 2SC3016, 2SC3161
22145	2SC4327	50V, 7A, 25W, 115MHz	2SC3747...48, 2SC4550, 2SD1444A
22146	2SC4328	150V, 5A, 30W, <300/1900ns	-
22147	2SC4329	150V, 7A, 35W, <300/1900ns	-
22148	2SC433	2SC431, 200/140V	2SC1299, 2SC1301, 2SC1873, 2SC2128
22149	2SC4330	150V, 10A, 40W, <300/1900ns	-
22150	2SC4331(Z)	150/100V, 5A, 15W, 150MHz	2SC4343
22151	2SC4332(Z)	100V, 5A, 15W, <300/1800ns	2SC3303, 2SC4344
22152	2SC4333(Z)	40V, 7A, 15W, <300/1800ns	2SD1804
22153	2SC4334	2SC4328, , 25W	2SC3566, 2SC3696
22154	2SC4335	2SC4329, , 30W	2SC3568, 2SC3697, 2SD1792
22155	2SC4336	2SC4330, , 30W	2SC3568, 2SC3698, 2SD1794
22156	2SC4337(Z)	60V, +-1A, 7W, B10000	2SC2871, 2SD1598, 2SD1800
22157	2SC4338(Z)	80V, +-2A, 8W, B10000	2SD1817, 2SD1980
22158	2SC4339(Z)	150/100V, +-3A, 9W, B10000	-
22159	2SC434(A)	B>20	2SC1299, 2SC1301, 2SC1873, 2SC2128
22160	2SC4340	2SC4337, 8W	BD 875, BD 877, BD 879, BDX 42...44
22161	2SC4341	2SC4338, 10W	BD 679, BD 681, BD 683, BD 779, 2N6039
22162	2SC4342	2SC4339, 12W	-
22163	2SC4343(Z)	150V, 7A, 18W, <300/1900ns	-
22164	2SC4344(Z)	100V, 7A, 18W, <300/1800ns	2SC4979
22165	2SC4345(Z)	100V, 5A, 12W, B10000	-
22166	2SC4346(Z)	<700/2800ns	BUT 11A, BUV 46A, 2SC3497
22167	2SC4347	60V, +-5A, 25W, B10000	-
22168	2SC4347	60V, +-5A, 25W, B10000	-
22169	2SC4348	100V, +-5A, 25W, B10000	-
22170	2SC4348	100V, +-5A, 25W, B10000	-
22171	2SC4349	100V, 8A, 30W, B10000	-
22172	2SC4349	100V, 8A, 30W, B10000	-
22173	2SC435	2SC431, 300/200V	2SC1299, 2SC1302, 2SC1401, 2SC1873
22174	2SC4350	100V, 10A, 40W, B10000	-
22175	2SC4350	100V, 10A, 40W, B10000	-
22176	2SC4351	2SC4347, , 20W	-
22177	2SC4352	2SC4348, , 20W	-
22178	2SC4353	2SC4350, , 25W	-
22179	2SC4354	400/400V, 2A, 15W, <1/3,5µs	BUX 84...85, 2SC2738, 2SC3169
22180	2SC4355	100V, 4A, 10MHz	-
22181	2SC4356	60V, 2A, 0,9W, 80MHz	2SC3328, 2SD1014, 2SD1207, 2SD1146
22182	2SC4357	2SC4356, SMD	2SC3647, 2SC4132, 2SD1623, 2SD1422
22183	2SC4358	35V, 0,3A, 2500MHz	-
22184	2SC4359	<700/2800ns	BUW 11AF, 2SC4299, 2SC4445

22185	2SC436	2SC431, 300/200V, B>20	2SC1299, 2SC1302, 2SC1401, 2SC1873
22186	2SC4360	2SC4361, SMD	FA 1L3N, DTC 143XK, KSR 1105, UN 221F
22187	2SC4361	Rbe10kOhm	AA 1L3N, DTC 143XS, KSR 1005, UN 421F
22188	2SC4362	2SC4363, SMD	FA 1L3M, DTC 143EK, RN 1401, UN 221L
22189	2SC4363	RbRbe4,7kOhm	AA 1L3M, DTC 143ES, RN 1001, UN 421L
22190	2SC4364	25V, 0,03A, 3000MHz	BF 775, BFR 35, 2SC3014, 2SC3098
22191	2SC4365	25V, 0,05A, 3000MHz	BFT 75, 2SC3014, 2SC3772...3773
22192	2SC4366	2SC3836, SMD, 250MHz	-
22193	2SC4367	30V, 0,1A, 0,6W, 1000MHz	-
22194	2SC4368	150/150V, 1,5A, 20W, 4MHz	2SC3298(A,B), 2SC3567, 2SC3695, 2SC4159
22195	2SC4369	30V, 3A, 15W, 100MHz	2SC3297, 2SC3690, 2SC1762, 2SD1913
22196	2SC437	100V, 2A, 13W, 210MHz	BD 379, BD 529, 2SD1177...1178
22197	2SC4370	160/160V, 1,5A, 20W, 100MHz	2SC3298(A,B), 2SC3364, 2SC4159
22198	2SC4371	500/400V, 5A, 30W, <1/3,5µs	2SC3570, 2SC3573, 2SC4073, 2SC4418
22199	2SC4372	200/150V, 0,05A, 120MHz	BF 620, BF 622, 2SC2880, 2SC3380
22200	2SC4373	120/120V, 0,5A, 120MHz	2SC2881, 2SD1007, 2SD1418...19
22201	2SC4374	80V, 0,4A, 100MHz	2SC2882, 2SC3438, 2SD875, 2SD1667
22202	2SC4375	30V, 1,5A, 120MHz	2SC2982, 2SC4377, 2SD1621, 2SD1766
22203	2SC4376	35V, 0,8A, 120MHz	BCX 54...56, 2SC2884, 2SC3444, 2SC4539
22204	2SC4377	30V, 2A, 150MHz	2SD1119, 2SD1620, 2SD1766
22205	2SC4378	300/300V, 0,2A, 10W, 70MHz	BF 417, BF 617, BF 758...759
22206	2SC4379	<500/2100ns	BUP 23, 2SC4139, 2SC4434, 2SC4424
22207	2SC438	2SC437, 75V	BD 377, BD 527, 2SD1177...1178
22208	2SC4381	150/150V, 2A, 25W, 15MHz	BDT 31DF, 2SC3298(A...B), 2SC3567
22209	2SC4382	2SC4381, 200/200V	2SC3298B, 2SD1587
22210	2SC4383	200/180V, 8A, 40W, <2/5µs	2SC4387, 2SC5101, BD 245F, 2SD751
22211	2SC4385	120/80V, 6A, 60W, 20MHz	2SC4689, 2SC5099, 2SD2064
22212	2SC4386	160/120V, 8A, 75W, 20MHz	2SC5100, BD 245D...F, 2SC2837, 2SD1046
22213	2SC4387	200/140V, 10A, 80W, 20MHz	2SC4388, 2SC5101, 2SC3263, 2SC3855
22214	2SC4388	200/180V, 15A, 85W, 20MHz	2SC3263, 2SC3856
22215	2SC4389	30V, 2A, B>800	2SD1581, 2SD1779
22216	2SC439	25V, 0,1A, 0,5W, 420MHz	BFX 55, 2N3299...3300, 2N3724, 2SC1385
22217	2SC4390	20V, 2A, B>800	2SD1950
22218	2SC4391	80V, 1A, 1W, 120MHz	BC 639, MPS 651, 2SC3669, 2SD619
22219	2SC4392	20V, 30mA, 6500MHz	BFR 182W, 2SC5065, 2SC5090, 2SC5190
22220	2SC4393	17V, 70mA, 5000MHz	BFS 520, 2SC3937
22221	2SC4394	20V, 80mA, 7000MHz	BFS 520, 2SC5085
22222	2SC4396	RbRbe47kOhm	DTC 144EU, RN 1304, UN 5213
22223	2SC4397	RbRbe22kOhm	DTC 124EU, RN 1303, UN 5212
22224	2SC4398	RbRbe10kOhm	DTC 114EU, RN 1302, UN 5211
22225	2SC4399	20V, 30mA, 320MHz	2SC3931...32, 2SC3935, 2SC5020
22226	2SC44	2SC41, 50V, B>4	BD 245, BDV 91, BDX 91, 2N4914
22227	2SC440	25V, 0,1A, 0,5W, 420MHz	BFX 55, 2N3299...3300, 2N3724, 2SC1385
22228	2SC4400	40V, 50mA, 750MHz	-
22229	2SC4401	25V, 30mA, 3000MHz	BFR 93W, 2SC4905, 2SC5107



22230	2SC4402	25V, 50mA, 3000MHz	2SC4780, 2SC5110
22231	2SC4403	25V, 70mA, 3000MHz	2SC3937, 2SC5085
22232	2SC4404	20V, 70mA, 5000MHz	BFS 520, 2SC3937, 2SC5085
22233	2SC4405	20V, 100mA, 5000MHz	BFS 540
22234	2SC4406	30V, 50mA, 1200MHz	BF 517W, BFS 17W, 2SC3933, 2SC4780
22235	2SC4407	25V, 50mA, 3000MHz	2SC4780, 2SC5110
22236	2SC4408	80V, 2A, 0,9W, 100/600ns	2SC3328, 2SD2485
22237	2SC4409	2SC4408, SMD	2SC4541
22238	2SC441	25V, 0,1A, 0,5W, 420MHz	BFX 55, 2N3299...3300, 2N3724, 2SC1385
22239	2SC4410	2SC3707	BFR 92W, BFR 181W, BFR 280W
22240	2SC4411	100V, 0,5A, 15W, 1200MHz	2SC4202
22241	2SC4412	-/300V, 0,05A, 70MHz	BF 820, 2SC4061
22242	2SC4413	60V, 0,1A, B>800	-
22243	2SC4414	0ns	-
22244	2SC4415	2SC4229	-
22245	2SC4416	2SC4197	-
22246	2SC4417	2SC4444	2SC4780, 2SC5110
22247	2SC4418	500/400V, 5A, 30W, 20MHz	2SC3573, 2SC4054, 2SC4073, 2SC4371
22248	2SC4419	900/800V, 6A, 100W, <1μ/4,8μs	BUW 11A, BUW 132A, 2SC3536, 2SC3636
22249	2SC442	50V, 0,1A, 0,5W, 420MHz	BFX 55, 2N3299...3300, 2N3724, 2SC1385
22250	2SC4420	<700/2800ns	BUW 11AF, 2SC4299, 2SC4300, 2SC4445
22251	2SC4421	<500/2100ns	2SC3570, 2SC4052, 2SC4160, 2SC4533
22252	2SC4422	2SC3513, 0,4W	2SC3607
22253	2SC4423	500/400V, 12A, 55W, 20MHz	2SC4297, BUW 13(A), BUV 48(A...C)
22254	2SC4424	500/400V, 16A, 60W, 20MHz	2SC4298, BUW 13(A), BUV 48(A...C)
22255	2SC4425	500/400V, 25A, 65W, 20MHz	2SC4461, 2SC3850, 2SC4110
22256	2SC4426	1100/800V, 3A, 45W, 15MHz	2SC4583, 2SC3387, 2SC3460, 2SC3642
22257	2SC4427	1100/800V, 4,5A, 50W, 15MHz	2SC4882, 2SC3387, 2SC3460, 2SC3642
22258	2SC4428	1100/800V, 6A, 55W, 15MHz	2SC4584, BUV 89, 2SC3466, 2SC3643
22259	2SC4429	1100/800V, 8A, 60W, 15MHz	2SC4199, 2SC4585, BUV 89, 2SC3643
22260	2SC443	50V, 0,5A, 0,8W, 200MHz	BFS 23, BFX 55, BLY 34
22261	2SC4430	1100/800V, 12A, 65W, 15MHz	2SC4585, BUV 48B,C, 2SC3552, 2SC3644
22262	2SC4431	120/120V, 1,5A, 20W, 150MHz	2SC3298(A,B), 2SC3564, 2SC4370, 2SD1763
22263	2SC4432	40V, 0,05A, 750MHz	BF 599, BF 799, BFS 20, 2SC3374
22264	2SC4433	40V, 50mA, 0,3W, 750MHz	BF 314, BF 502, BF 505, BF 507, BF 562
22265	2SC4434	<500/2150ns	BUP 23, 2SC3435, 2SC3520, 2SC4139
22266	2SC4435	1500/800V, 5A, 100W	2SC3485...86, 2SC3685, BU 2508A
22267	2SC4436	1500/800V, 6A, 100W	2SC3486, 2SC3685...86, BU 2508A
22268	2SC4437	2SC4435, , 50W	2SC3884A, 2SC3894, BU 2508AF
22269	2SC4438	2SC4436, , 50W	2SC3884A...85A, 2SC3894, BU 2508AF
22270	2SC4439	180V, 0,3A, 8W, 400MHz	S 3936, 2SC4564, 2SC4623
22271	2SC444	60V, 0,5A, 0,8W, 220MHz	BFS 23, BFX 55, BLY 34
22272	2SC4440	600/400V, 7A, 30W	BU 307F
22273	2SC4441	600/400V, 10A, 35W	-
22274	2SC4442	<500/2100ns	2SC4054, 2SC4073, 2SC4160, 2SC4371



22275	2SC4443	20V, 0,15A, 700MHz	-
22276	2SC4444	45V, 0,05A, 500MHz	BF 517, BFS 17, 2SC3016, 2SC3161
22277	2SC4445	<700/4700ns	BUW 11AF, 2SC4299, 2SC4300, 2SC4426
22278	2SC4446	60V, 0,15A, 130MHz	-
22279	2SC4448	250V, 0,15A,10W, 240MHz	S 3540
22280	2SC4449	300/300V, 0,05A, 0,6W, 70MHz	BF 299, BF 420(A), 2SC3468
22281	2SC445	80V, 0,5A, 0,8W, 220MHz	BFS 23, BFX 55, BLY 34
22282	2SC4450	1500/1500V, 5mA, 6MHz	2SC4256
22283	2SC4451	1500/1500V, 15mA, 6MHz	2SC4257
22284	2SC4452	2SC4455, SMD	2SC4175...76
22285	2SC4453	2SC4455, SMD	2SC3735
22286	2SC4454	2SC4455, 0,3W	2SC4455
22287	2SC4455	<12/18ns	BSS 11, 2N2368...69(A), 2SC2901
22288	2SC4457	<500/3300ns	BUW 11(A)F, 2SC4300, 2SC4586
22289	2SC4458	<500/3300ns	BUV 47(A)FI, BUW 12(A)F, 2SC4301
22290	2SC4459	<500/3300ns	BUP 23CF, BUV 48(A)FI, BUW 13(A)F
22291	2SC446	60V, 0,5A, 0,8W, 220MHz	BFS 23, BFX 55, BLY 34
22292	2SC4460	<500/3300ns	BUP 23CF, BUV 48(A)FI, BUW 13(A)F
22293	2SC4461	<500/3300ns	BUX 98(A)PI
22294	2SC4462	2SC2732	BF 517W, BFS 17W, 2SC3933, 2SC4780
22295	2SC4463	2SC2733	2SC3931...32, 2SC3935
22296	2SC4464	15V, 5mA, 4000MHz	BFR 92W, BFR 181W, BFR 280W
22297	2SC4466	120/80V, 6A, 60W, 20MHz	BD 245C...F, 2SC2681, 2SC3181, 2SD896
22298	2SC4467	160/120V, 8A, 80W, 20MHz	BD 245D...F, 2SC2837, 2SC2987A, 2SD1047
22299	2SC4468	200/140V, 10A, 80W, 20MHz	BD 245F, 2SC3855, 2SC3263, 2SC3856
22300	2SC447	75V, 2A, 25W, 210MHz	BLY 35, 2N3632
22301	2SC4470	20V, 0,08A, 7GHz	-
22302	2SC4471	<500/2100ns	BUT 11(A)F, BUT 21CF, 2SC3750, 2SC3795
22303	2SC4471A	2SC4471, 900/500V	BUT 11AF, 2SC3895A, 2SC4518(A)
22304	2SC4473	120/120V, 0,4A, 10W, 400MHz	2SC3781
22305	2SC4474	200/200V, 0,2A, 10W, 300MHz	2SC3565, 2SC4975, 2SC3782
22306	2SC4475	2000/1800V, 3mA	-
22307	2SC4476	2000/1800V, 10mA	2SC4709
22308	2SC4477	330/150V, 7A, 30W, tf<300ns	BU 406F...407F, 2SD1404, 2SC3590...91
22309	2SC4478	2SC4477, 400/200V	BU 406F, 2SC3175, 2SC3591
22310	2SC4479	100V, 0,5A, 10W, 1100MHz	2SC4563
22311	2SC448	100V, 2A, 25W, 190MHz	-
22312	2SC4480	2SC4389	2SC4389
22313	2SC4481	15V, 1,5A, 0,9W, 200MHz	2SC2236, 2SC4483, 2SD1050, 2SD1331
22314	2SC4482	60V, 5A, 1W, 150MHz	2SD1145
22315	2SC4483	30V, 1,5A, 1W, 150MHz	2SD1207, 2SD1246...47, 2SD2177
22316	2SC4484	30V, 2,5A, 1W, 150MHz	2SD879, 2SD1207, 2SD1347
22317	2SC4485	60V, 1A, 0,9W, 150MHz	2SD1207, 2SD1616, 2SD1835
22318	2SC4486	60V, 2A, 1W, 150MHz	2SC3328, 2SD1207, 2SD1835, 2SD2069
22319	2SC4487	60V, 3A, 1W, 150MHz	2SD1347

22320	2SC4488	120V, 1A, 1W, 120MHz	2SD1616A
22321	2SC4489	120V, 2A, 1W, 120MHz	-
22322	2SC449	75V, 2A, 25W, 190MHz	BLY 35, 2N3632
22323	2SC4490	300/300V, 0,1A, 1W, 70MHz	2SC3468
22324	2SC4491	50V, 1,2A, 1W, B>1000	-
22325	2SC4492	600/600V, 0,02A, 40MHz	2SC4257, 2SC4572
22326	2SC4493	800/800V, 0,02A, 40MHz	2SC4257, 2SC4572
22327	2SC4494	B>500	2SC3852, 2SD2127, 2SD2092, 2SD1948
22328	2SC4495	2SC4494, 80V	2SC3852, 2SD1944, 2SD2076
22329	2SC4496	B>2000	2SD2024
22330	2SC4497	300V, 0,1A, 70MHz	BFN 26, 2SC4061
22331	2SC4498	Rbe10kOhm	DTC 123YU, UN 521H
22332	2SC4499L,S	500/400V, 0,5A, 10W, <1/3μs	2SC3075, 2SC3129, 2SC3588
22333	2SC45	45V, 0,1A, 0,5W, 160MHz	BFW 16...17, BFX 55
22334	2SC450	60V, 2A, 25W, 210MHz	BLY 35, 2N3632
22335	2SC4500L,S	100/600ns	2SC2871, 2SD1598, 2SD1800
22336	2SC4501L,S	400/1200ns	2SC3132, 2SD1222, 2SD1799
22337	2SC4502	50V, 0,05A, 1W, 500MHz	BF 370, BF 921, BF 959
22338	2SC4503	100V, 30A, 80W, 20MHz	-
22339	2SC4504	30V, 0,3A, 3GHz	-
22340	2SC4505	400/400V, 0,1A, 20MHz	2SC4548
22341	2SC4506	300/300V, 0,1A, 1,5W, 100MHz	BF 417, BF 459, 2SC3503, 2SC4147
22342	2SC4507	500/400V, 5A, 40W, <1/3μs	2SC4026, 2SC4073, 2SC4371, 2SC4418
22343	2SC4508	500/400V, 10A, 40W, <1/3μs	2SC3575, 2SC3871, 2SC4162, 2SD1795
22344	2SC4509(R)	500/400V, 10A, 80W, <1/3μs	BUW 13(A)F, 2SC4296...97, 2SC4423
22345	2SC451	100V, 1,2A, 25W, 180MHz	-
22346	2SC4510(R)	500/400V, 15A, 80W, <1/3μs	2SC4424
22347	2SC4511	2SC4512, , 30W	BDT 41BF...CF, 2SC4335
22348	2SC4512	120/80V, 6A, 50W, 20MHz	BD 243C...F, BD 543D, 2SC4329, 2SD866
22349	2SC4515	15V, 0,05A, 0,2W, 7GHz	-
22350	2SC4516	15V, 0,08A, 0,2W, 8GHz	-
22351	2SC4517	<700/4500ns	BUT 11AF, 2SC4304, 2SC3559, 2SC3979A
22352	2SC4517A	2SC4517, 1000/550	BUT 11AF, 2SC3752, 2SC3979A
22353	2SC4518	<700/4500ns	BUT 11AF, BUT 18AF, 2SC3795A
22354	2SC4518A	2SC4518, 1000/550V	BUT 11AF, BUT 18AF, 2SC4898
22355	2SC4519	60V, 0,5A, <120/350ns	-
22356	2SC452	100V, 1,2A, 25W, 180MHz	-
22357	2SC4520	60V, 1,5A, 50/180ns	-
22358	2SC4521	60V, 3A, 50/180ns	-
22359	2SC4522	60V, 5A, 15W, 50/180ns	2SC3074, 2SC3518, 2SC3592, 2SD1803
22360	2SC4523	60V, 8A, 15W, 50/180ns	2SC4668, 2SD1804
22361	2SC4527	30V, 0,05A, 1500MHz	-
22362	2SC4528	1500/500V, 10A, 150W	-
22363	2SC4529	30V, 0,3A, 5W, >1500MHz	2SC4272
22364	2SC453	90V, 1,2A, 25W, 170MHz	-

22365	2SC4531	1500/600V, 10A, 50W	BU 2520DF, 2SC4125, 2SC4878, 2SD1881
22366	2SC4532	1700/600V, 10A, 200W	S 3934, 2SC4880
22367	2SC4533	500/400V, 3A, 30W, <1/3,3μ	2SC4052, 2SC4160, 2SC4421
22368	2SC4536	30V, 0,25A	BFQ 64, 2SC4807
22369	2SC4537	2SC3513, SMD	BFS 540
22370	2SC4538(R)	900/800V, 5A, 80W, <1μ/4,8μs	BUW 11(A)F, 2SC4300, 2SC4427, 2SC4586
22371	2SC4539	50V, 1,2A, 100/400ns	2SC4409, 2SD1623
22372	2SC454(L)	30V, 0,1A, 230MHz	BF 240...241, BF 254...255, BF 594...595
22373	2SC454(L)	30V, 0,1A, 230MHz	BF 240...241, BF 254...255, BF 594...595
22374	2SC4540	80V, 1A, 100/500ns	2SC4409
22375	2SC4541	80V, 3A, 100/600ns	-
22376	2SC4542	1500/600V, 10A, 50W	BU 2520AF, 2SC4759
22377	2SC4543	2SC3526(H), SMD	-
22378	2SC4544	300V, 0,1A, 8W, 70MHz	2SC3565, 2SC3942, 2SC3945, 2SC4075
22379	2SC4545	50V, 1,5A, 1,5W, 150MHz	2SD1682
22380	2SC4546	<500/2150ns	BU 306F, BUT 22BF...CF, 2SC4056
22381	2SC4547	B>2000	-
22382	2SC4548	2SC4002, SMD	2SD1473
22383	2SC4549	2SC3691	2SC3691
22384	2SC455	230MHz	BF 240...241, BF 254...255, BF 594...595
22385	2SC4550	2SC3692	2SC3692
22386	2SC4551	2SC3693	2SC3693
22387	2SC4552	2SC3694	2SC3694
22388	2SC4553	100V, 7,5A,30W,100MHz	-
22389	2SC4554	100V, 15A,30W,100MHz	-
22390	2SC4555	20V, 0,5A, 300MHz	2SD2483
22391	2SC4557	900/550V, 10A, 80W, <1/5,5μs	BUP 23CF, BUV 48AFI, BUW 13AF, 2SC4587
22392	2SC4558	100V, 6A, 30W, B>700	2SC4553, 2SD2165
22393	2SC4559	500/400V, 7A, 40W, <1/3,3μs	BU 306F, 2SC4056, 2SC4130, 2SC4161
22394	2SC456	50V, 0,6A, 0,75W, 200MHz	BFS 23, BLY 34
22395	2SC4560	1500/600V, 10A, 80W	BU 2525A, 2SC3688
22396	2SC4561	50V, 0,05A, 250MHz	BC 846...847, BCW 71...72, BCW 81
22397	2SC4562	2SC4561	2SC4081, 2SC4128, 2SC4141, 2SC4155
22398	2SC4563	100V, 0,5A, 10W, 1200MHz	2SC4479
22399	2SC4564	200V, 0,3A, 10W, 400MHz	2SC4623
22400	2SC4565	140V, 0,5A, 10W, 500MHz	-
22401	2SC4566	2SC4564, 20W	-
22402	2SC4567	2SC4565, 20W	-
22403	2SC4568	20V, 30mA, 5GHz	BFR 93, 2SC3011, 2SC5106
22404	2SC4569	20V, 60mA, 5GHz	BFR 193, 2SC3161, 2SC3774...75
22405	2SC4570	2SC4568	BFR 93W, 2SC5107
22406	2SC4571	2SC4569	BFS 520, 2SC3937, 2SC5085
22407	2SC4572	800/800V, 20mA, 40MHz	2SC4257, 2SC4451
22408	2SC4573	60V, 4A, 35W, B>2000, 80MHz	2SD2024, BDW 23A...C, BDW 53A...D
22409	2SC4574	2SC4573, , 30W	2SD1595, 2SD1891

22410	2SC4575	2SC4573	-
22411	2SC4576	1400/700V, 0,3A, 20W, <2/4μs	2SC3676
22412	2SC4577	2SC4555	2SC3265
22413	2SC4578	1700/900V, 50mA, 6MHz	-
22414	2SC4579	2000/900V, 20mA, 6MHz	2SC4913
22415	2SC458(K,L,LG)	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
22416	2SC458(K,L,LG)	30V, 0,1A, 0,2W, 230MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
22417	2SC4580	600/450V, 8A, 50W, 20MHz	BUP 22BF...CF, BUV 47FI,AFI, BUW 12F,AF
22418	2SC4581	600/450V, 10A, 65W, 20MHz	BUP 23BF...CF, BUV 48FI,AFI, BUW 13F,AF
22419	2SC4582	600/450V, 15A, 75W, 20MHz	BUP 23BF...CF, BUV 48FI,AFI, BUW 13F,AF
22420	2SC4583	<500/3800ns	BU 705F, 2SD1543, 2SD1653
22421	2SC4584	<500/3800ns	BU 508AF, 2SC3885, 2SC3895, 2SC4144
22422	2SC4585	<500/3800ns	BUH 715, 2SC3897, 2SD1548
22423	2SC4586	<500/3500ns	BU 426AF, BUV 47AF, BUW 12AF, 2SC4428
22424	2SC4587	<500/3500ns	BUP 23CF, BUV 48AF, BUW 13AF, 2SC4430
22425	2SC4589	1500/800V, 10A, 50W	BU 2520AF, 2SC3897, 2SC4199A, 2SC4542
22426	2SC459	30V, 0,1A, 0,2W, 230MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
22427	2SC4591	15V, 50mA, 9000MHz	2SC3583, 2SC3904, 2SC4591, 2SC5218
22428	2SC4592	2SC4591, 9500MHz	2SC4094, 2SC4127, 2SC4900, 2SC5080
22429	2SC4593	2SC4591	2SC4901, 2SC5051
22430	2SC4594	70V, 0,5A, 0,9W, <45/70ns	2N4014
22431	2SC4595	100/60V, 12A, 30W, 120MHz	2SC4552
22432	2SC4596	100/80V, 5A, 25W, 120MHz	2SC3540, 2SC4549
22433	2SC4597	500/400V, 4A, 40W, 20MHz	2SC4219, BUV 46(A), BUT 11(A), 2SC3497
22434	2SC4598	500/400V, 7A, 50W, 20MHz	2SC4220, BUT 54, BUT 56(A), 2SC4055
22435	2SC4599	800/500V, 3A, 40W, 18MHz	2SC4171, 2SC4221, BUT 11(A)
22436	2SC46	60V, 0,3A, 0,6W, 180MHz	BFX 55, BSW 51...52, 2N2218...19
22437	2SC460	30V, 0,1A, 230MHz	BF 240...241, BF 254...255, BF 594...595
22438	2SC460	30V, 0,1A, 230MHz	BF 240...241, BF 254...255, BF 594...595
22439	2SC4600	800/500V, 5A, 50W, 18MHz	2SC4172, 2SC4222, BUT 11(A)
22440	2SC4601	1100/800V, 1,5A, 40W, 15MHz	2SC4223, 2SC3178, 2SC3456
22441	2SC4602	1100/800V, 3A, 50W, 15MHz	2SC4224, 2SC3050, 2SC3457
22442	2SC4603(R)	900/800V, 3A, 80W, <1μ/4,8μs	BUW 11(A)F, 2SC4300, 2SC4299, 2SC4445
22443	2SC4604	80V, 3A, 0,9W, 100MHz	-
22444	2SC4605	2SC4479	-
22445	2SC4606	2SC1509	2SC1509
22446	2SC4607	B>5	-
22447	2SC4608	1700/600V, 8A, 200W	S 3934...35, 2SC4532
22448	2SC461	30V, 0,1A, 230MHz	BF 241, BF 255, BF 314, BF 502, BF 505
22449	2SC461	30V, 0,1A, 230MHz	BF 241, BF 255, BF 314, BF 502, BF 505
22450	2SC4612	180/160V, 0,7A, 1W, 50/1060ns	2SC3332, 2SC4614
22451	2SC4613	180/160V, 0,7A, 1W, 50/1060ns	2SC3902, 2SC3116...17
22452	2SC4614	180/160V, 1,5A, 1W, 40/1280ns	2SD1812
22453	2SC4615	400/400V, 1A, 15W, 70MHz	2SC3362, 2SC3632, 2SD1053
22454	2SC4616	400/400V, 2A, 15W, 60MHz	2SC3233, 2SC3631

22455	2SC4617	2SC2412	2SD2216
22456	2SC4617	2SC2412	2SD2216
22457	2SC4618	2SC2413K	2SC4915, 2SC5021
22458	2SC4618	2SC2413K	2SC4915, 2SC5021
22459	2SC4619	2SC3082K	2SC4809, 2SC5021
22460	2SC4619	2SC3082K	2SC4809, 2SC5021
22461	2SC462	40V, 0,05A, 600MHz	BF 198...199, BF 224...225, BF 310...311
22462	2SC4620	2SC4295(M)	2SC4295
22463	2SC4621	500/400V, 7A, 70W, 30MHz	BUP 22BF...CF, BUV 47FI,AFI, BUW 12F,AF
22464	2SC4622	500/400V, 7A, 50W, <1/3μs	MJE 13006, 2SC3170, 2SC4106, 2SC4055
22465	2SC4623	250V, 0,3A, 10W, 400MHz	-
22466	2SC4626	2SC2295	2SC4655...56, 2SC4915, 2SC5021
22467	2SC4626	2SC2295	2SC4655...56, 2SC4915, 2SC5021
22468	2SC4627	2SC2377, SMD	2SC4655, 2SC4915, 2SC5021
22469	2SC4627	2SC2377, SMD	2SC4655, 2SC4915, 2SC5021
22470	2SC4628	20V, 20mA, 0,2W, >600MHz	BF 377...78, 2SC2498, 2SC2570(A), 2SC3777
22471	2SC4629	15V, 50mA, 0,6W, 8000MHz	2SC3355, 2SC2590(A), 2SC3512
22472	2SC463(H)	40V, 0,05A, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
22473	2SC4630	2SC3675	-
22474	2SC4631	2SC3676	-
22475	2SC4632	2SC4256	2SC4450
22476	2SC4633	2SC4257	2SC4451
22477	2SC4634	2SC4450, , 10mA	2SC4632
22478	2SC4635	2SC4451, , 20mA	2SC4633
22479	2SC4636	2SC4475, , 10mA	-
22480	2SC4637	2SC4476, , 15mA	-
22481	2SC4638	800/500V, 5A, 40W, <1/4μs	BUT 11(A)F, 2SC3353, 2SC3795(A), 2SC4518
22482	2SC4639	2SC4640, SMD	BC 846, BCV 71...72, 2SC3323, 2SC4076
22483	2SC464	30V, 0,02A, 1100MHz	BF 198...199, BF 224...225, BF 310...311
22484	2SC4640	55V, 0,15A, 0,3W, 200MHz	BC 174, BC 182, BC 546, 2SC3245(A)
22485	2SC4641	2SC4640, 0,5W	BC 174, BC 182, BC 546, 2SC3245(A)
22486	2SC4642K	50V, 0,1A, 180MHz	BC 850, BCW 71...72, 2SC3323, 2SC4076
22487	2SC4643	2SC4629, SMD	2SC3301
22488	2SC4644	2SC4002, 1W	2SC4002
22489	2SC4644	2SC4002, 1W	2SC4002
22490	2SC4645	400/400V, 1A, 1W, 70MHz	-
22491	2SC4646	400/400V, 2A, 1W, 60MHz	-
22492	2SC4647	300/300V, 0,1A, 0,4W, >50MHz	BF 393, BF 420A, 2SC3468, 2SC4218
22493	2SC4648	2SC4594, 0,5W	2N4014
22494	2SC4649	2SC2059K	-
22495	2SC4649	2SC2059K	-
22496	2SC465	30V, 0,02A, 1100MHz	BF 377...378, BF 689, BF 763, 2N2857
22497	2SC4650	200/200V, 0,1A, 1W, 150MHz	2SC3467...68
22498	2SC4652	-/120V, 8A, 80W	2SC4386, 2SC4690, 2SC5100
22499	2SC4653	-/60V, 12A, 80W	2SC3762, 2SC4886

22500	2SC4655	2SC2778	2SC4627, 2SC4915, 2SC5021
22501	2SC4655	2SC2778	2SC4627, 2SC4915, 2SC5021
22502	2SC4656	2SC4561	-
22503	2SC4656	2SC4561	-
22504	2SC4657	100/1100ns	2SC3518, 2SC3592, 2SD1803, 2SD1805
22505	2SC4658	200/1100ns	2SC3303, 2SC4332
22506	2SC4659	500/400V, 5A, 15W, <1/3,5µs	2SC4346
22507	2SC466(H)	30V, 0,02A, 1100(H750)MHz	BF 377...378, BF 689, BF 763, 2N2857
22508	2SC4660	30V, 0,3A, 8W, 2200MHz	2SC3595
22509	2SC4661	15V, 35mA, 5000MHz	BFR 93W, 2SC4903, 2SC5107
22510	2SC4662	500/400V, 5A, 30W, <1/3,5µs	2SC3869, 2SC4026, 2SC4371, 2SC4418
22511	2SC4663	<300/1100ns	2SC4073, 2SC4129, 2SC4371, 2SC4418
22512	2SC4664	<300/1100ns	BU 406F...407F, 2SC4161, 2SC4849
22513	2SC4666	hi-beta,50V,0,15A,250MHz	-
22514	2SC4667	40V, 0,2A, 400MHz, 70/45ns	2SC4175...76
22515	2SC4668	60V, 7A, 10W, <300/2000ns	2SC4523, 2SD1804
22516	2SC4669	60V,10A, 10W, <300/2000ns	-
22517	2SC467	20V, 0,05A, 0,3W	BC 168, BC 183, BC 238, BC 548, 2SC1890
22518	2SC4670	2SC4238	2SC4780
22519	2SC4671	50V, 2A, 1W, B>1000	-
22520	2SC4672	60/50V, 2A, 210MHz	2SC4521, 2SD1623...24, 2SC4409
22521	2SC4674	12V, 8mA, 6000MHz	BFR 181W, BFS 505, 2SC4899
22522	2SC4675	30V, 8A, 10W, 250MHz	-
22523	2SC4678	300V, 0,05A, 10W, 240MHz	-
22524	2SC4679	2SC4678, 8W	2SC3789...90, 2SC3417, 2SC3503, 2SC4828
22525	2SC4680	12V, 50mA	-
22526	2SC4681	30V, 3A, 10W, 150MHz	2SC3074, 2SD1802, 2SD1805
22527	2SC4682	30V, 3A, 0,9W, 150MHz	-
22528	2SC4683	2SC4682, 1W	-
22529	2SC4684	50V, 5A, 10W, 150MHz	2SD1719, 2SD1755
22530	2SC4685	2SC4684	-
22531	2SC4686	1500/1000V, 0,05A, 10W	2SC4630, 2SC4578
22532	2SC4686A	2SC4686, 1500/1200V	2SC4578
22533	2SC4687	500/400V, 7A, 70W, 30MHz	BUP 22, TIP 48A, 2SC3040, 2SC3089
22534	2SC4688	80V, 6A, 55W, 30MHz	2SC4385, 2SC5099, 2SD2064, BD 245A...F
22535	2SC4689	120V, 8A, 70W, 30MHz	2SC4386, 2SC5100, 2SD2052, BD 245C...F
22536	2SC469	20V, 0,03A, 250MHz	BF 240, BF 254, BF 494, BF 594
22537	2SC4690	140V, 10A, 80W, 30MHz	2SC4387, 2SC5101, 2SC4886, BD 245D...F
22538	2SC4691	2SC3757	-
22539	2SC4691	2SC3757	-
22540	2SC4692	1500/800V, 12A, 50W	BU 2525AF, 2SC5105
22541	2SC4693	30V, 0,3A, 0,9W, 2500MHz	2SC4308
22542	2SC4694	2SC4695	BC 817W, 2SD1949, 2SD1820A
22543	2SC4695	50V, 0,5A, 250MHz	BC 817, BCW 65, BCX 19, 2SC3325
22544	2SC4696	80/80V, 0,8A, 1W, B>1000	BC 877, BC 879, BSR 51...52, 2SD1153



22545	2SC4699K	25V, 0,2A, 250MHz, <50/40ns	2SC1621, 2SC4894
22546	2SC47	2SC46, 40V, 0,72A	BFX 55, BSW 51...52, 2N2218...19
22547	2SC470(-3...-6)	90..180V, 0,1A, 0,75W, 150MHz	BF 257...259, BF 657...659, 2N5058...59
22548	2SC4700	2SC4699K	2SC4175...76, 2SC4755
22549	2SC4702	300/300V, 0,05A, 80MHz	BFN 26, 2SC4061, 2SC4497
22550	2SC4703	25V, 0,15A, 6GHz	-
22551	2SC4704	200/200V, 0,2A, 10W, 300MHz	2SC3601
22552	2SC4705	60V, 0,2A, 250MHz, B>800	2SC3651
22553	2SC4706	900/600V, 14A, 130W, 6MHz	BUV 48(A), BUW 13(A), BUW 133(A)
22554	2SC4707	35V, 0,5A, 0,8W, 300MHz	2SC3939, 2SC4414 2SD1211, 2SD1937
22555	2SC4708	100V, 0,2A, 5W, 1,1GHz	2SC3598, 2SC3599
22556	2SC4709	2100/2100V, 10mA	2SC4476
22557	2SC471(H)	30V, 0,1A, 0,2W, 160MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
22558	2SC4710(LS)	2SC4709	2SC4637
22559	2SC4713K	12V, 0,05A, 800MHz, Ron2Ohm	-
22560	2SC4714	300/300V, 0,1A, 15W, 140MHz	2SC1929
22561	2SC4715	150V, 0,05A, 0,3W, 160MHz	2SC2362K, 2SC2631...2632, 2SC3800
22562	2SC4716	30V, 0,05A, 0,3W, >600MHz	BF 314, BF 503, BF 505, 2SC1856, 2SC3354
22563	2SC4719	-/32V, 1A, 0,9W	2SC4145, 2SD1207, 2SD1292, 2SD1616
22564	2SC472(H)	2SC471, 180MHz, <100/500ns	BC 168, BC 183, BC 238, BC 548, 2N3904
22565	2SC4720	-/150V, 0,05A, 0,8W	BF 298, BF 422A, 2SC3248, 2SC3467
22566	2SC4721	-/50V, 2A, 0,9W	2SC4145, 2SD1207, 2SD2485
22567	2SC4722	-/300V, 0,1A, 0,9W	BF 420A, 2SC3468...69, 2SC4166
22568	2SC4723	2SC4642	2SC4081, 2SC4128, 2SC4155, 2SC4177
22569	2SC4724	-/100V, 3A, 1,2W, B>2k	2SC4339
22570	2SC4725	2SC3837K	-
22571	2SC4725	2SC3837K	-
22572	2SC4726	2SC3838K	-
22573	2SC4726	2SC3838K	-
22574	2SC4727	30V, 8A, 250MHz, 30/265ns	-
22575	2SC4728	60V, 5A, 180MHz, 50/520ns	-
22576	2SC4729	60V, 8A, 180MHz, 50/520ns	-
22577	2SC473(H)	<80/200ns	BC 174, BC 182, BC 190, BC 546, 2N2222A
22578	2SC4730	120V, 3A, 180MHz, 100/950ns	-
22579	2SC4731	120V, 4A, 180MHz, 100/950ns	-
22580	2SC4732	2SC3416	2SC3502, 2SC3955, 2SC3600...01, 2SC3788
22581	2SC4733	2SC3417	2SC3417, 2SC3503, 2SC3789...90, 2SC4828
22582	2SC4734	400/400V, 2A, 1,5W, 60MHz	-
22583	2SC4735	75V, 1A, 250MHz	-
22584	2SC4736	80V, 2A, 170MHz, B>800	2SC3474, 2SD1754...55
22585	2SC4737	50V, 2A, 200/4000ns, B>1000	BD 677, BD 679, 2SD1759, 2SD1817
22586	2SC4738	60V, 0,15A, >80MHz	2SD2216
22587	2SC4738	60V, 0,15A, >80MHz	2SD2216
22588	2SC474(H)	2SC471, 70V, <100/500ns	BC 174, BC 182, BC 190, BC 546, 2N2222A
22589	2SC4740	1500/800V, 8A, 50W	BU 508A, BU 2508A, 2SC3027...28, 2SC4801

22590	2SC4741	1500/800V, 10A, 50W	BU 2520A, 2SC3688
22591	2SC4742	1500V, 6A, 50W	BU 2508D, 2SC3482, 2SC3682, 2SC4292
22592	2SC4743	1500/800V, 6A, 50W	BU 2508A, BU 908, 2SC3486, 2SC3686
22593	2SC4744	2SC4742	BU 2508DF, 2SC4294, 2SC4764, 2SD1652
22594	2SC4745	2SC4743	BU 2508AF, 2SC3884A, 2SC3894, 2SC4830
22595	2SC4746(A)	2SC4740	BU 2508AF, 2SC3886A, 2SC3896, 2SC4758
22596	2SC4747	2SC4741	BU 2520AF, 2SC4542, 2SC4589
22597	2SC475	2SC476	BC169, BC184, BC239, BC549, 2SC2675
22598	2SC4754	600/400V, 2A, 20W, <1/3,5μs	2SC4171, 2SC4221, BUT 93, BUX 84
22599	2SC4755	25V, 0,2A, 500MHz, 17/15ns	2SC4175...76, 2SC4452
22600	2SC4757	1500/600V, 7A, 50W	2SC3885A, 2SC3895
22601	2SC4758	1500/600V, 8A, 50W	2SC3886A, 2SC3896
22602	2SC4759	1500/600V, 10A, 50W	BU 2520AF, BUH 715, 2SC4542
22603	2SC476	20V, 0,1A, 0,15W, 100MHz	BC168, BC183, BC238, BC548, 2SD767
22604	2SC4760	2000/800V, 8A, 200W	-
22605	2SC4761	1700/600V, 6A, 50W	BUH 417, BUH 517, 2SC4806
22606	2SC4762	1500/600V, +-7A, 50W	2SC3892A, 2SC4123, 2SC4916
22607	2SC4763	1500/600V, +-8A, 50W	BU 2520DF, 2SC3893A, 2SC4124
22608	2SC4764	1500/600V, +-6A, 50W	2SC3892A, 2SC4294, 2SC4122
22609	2SC4765	1700/600V, +-5A, 50W	BUH 517D, 2SC4962, 2SD2253
22610	2SC4766	1700/600V, +-6A, 50W	BUH 517D, 2SC4962
22611	2SC4767	36V, 0,3A, 1W, >1500MHz	-
22612	2SC4768	450/400V, 10A, 80W, <1/3μs	2SC2625, 2SC2740, 2SC3042, 2SC4138
22613	2SC4769	2SC4770	BU 2508DF, 2SC3892A, 2SC4123, 2SC4916
22614	2SC477	50V, 0,03A, 0,14W, 230MHz	BF 240...241, BF 254...255, BF 594...595
22615	2SC4770	1500/800, 7A, 60W	2SC3885A, 2SC3895, 2SC4757, 2SD2252
22616	2SC4771K	30V, 0,05A, 600MHz	BF 599, BF 799, 2SC3130, 2SC3374
22617	2SC4772	2SC4771K	BF 547W, BFS 17W, 2SC3932, 2SC3935
22618	2SC4773	2SC4326LK	BF 547W, BFS 17W, 2SC3933, 2SC4780
22619	2SC4774	2SC4713K	-
22620	2SC4775	2SC4642, 0,4W	BC 167, BC 182, BC 237, BC 547, 2SD767
22621	2SC4776M	2SC4642, 0,4W	BC 167, BC 182, BC 237, BC 547, 2SD767
22622	2SC4777	2SC4642, 0,4W	BC 167, BC 182, BC 237, BC 547
22623	2SC4778	2SC4642, 0,4W	BC 167, BC 182, BC 237, BC 547, 2SD767
22624	2SC4779S	2SC4642, 0,3W	BC 167, BC 182, BC 237, BC 547, 2SD767
22625	2SC478	50V, 0,12A, 0,3W, 180MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
22626	2SC4780	25V, 50mA, 4500MHz	2SC4571, 2SC4905...06, 2SC5110
22627	2SC4781	30V, 4A, 0,9W, 170MHz	2SC4482, 2SD1145
22628	2SC4782	2SC4755	2SC1621, 2SC4453, 2SC4699K, 2SC4894
22629	2SC4783	60V, 0,1A, 150MHz	2SC4738, 2SC4617
22630	2SC4783	60V, 0,1A, 150MHz	2SC4738, 2SC4617
22631	2SC4784	15V, 20mA, 10GHz	BFS 505, 2SC5095
22632	2SC4786	900/500V, 5A, 40W, >20MHz	BUW 11AF, 2SC3400, 2SC4427, 2SC4586
22633	2SC4787	45V, 50mA, 0,6W, >300MHz	BF 921S, BF 959
22634	2SC4789	1500/800V, 25A, 150W	2SC3998, 2SC4290A

22635	2SC479(H)	60V, 0,6A, 0,65W, 30/55ns	BSS 13, BSV 77, 2N5189, 2SC1072
22636	2SC4791	2SC4784	2SC5097
22637	2SC4792	30V, 50mA, 800MHz	BF 799, 2SC3015, 2SC3374
22638	2SC4793	230/230V, 1A, 20W, 100MHz	-
22639	2SC4795	500/400V, 30A, 120W, <1/3μ	-
22640	2SC4796	1700/900V, 6A, 50W	BUH 417, 2SC4796
22641	2SC4797	1700/900V, 8A, 50W	BUH 517
22642	2SC4799	300/80V, 6A, 50W	TIP 55A...57A, 2SC2305, 2SC3813
22643	2SC48	2SC46, 120V	BSW 67...68, BSY 55...56, 2N1893
22644	2SC480	2SC479, 0,8W, <30/40ns	BSS 13, BSV 77, 2N5189, 2SC1072
22645	2SC4800	1500/800V, 5A, 80W	BU 208A, BU 2508A, 2SD1496, 2SC3685
22646	2SC4801	1500/500V, 8A, 50W	BU 908, BU 2508A, 2SC3687, 2SC3896
22647	2SC4802	1700/800V, 5A, 50W	2SC3026, 2SD784...85, 2SD1434
22648	2SC4803	1500/800V, 5A, 50W	BU 208D, BU 2508D, 2SD1171...75, 2SC3481
22649	2SC4805	15V, 65mA, >7GHz	BFS 520, 2SC4901, 2SC5051
22650	2SC4806	1700/600V, 5A, 50W	BUH 417, BUH 517, 2SC4761
22651	2SC4807	20V, 0,2A, 4,4GHz	-
22652	2SC4808	2SC3829	2SC4839, 2SC5086
22653	2SC4808	2SC3829	2SC4839, 2SC5086
22654	2SC4809	2SC3130	2SC5136
22655	2SC4809	2SC3130	2SC5136
22656	2SC481	60V, 1A, PQ>1W(50MHz)	BFS 23, BLY 34
22657	2SC4810	B>2000	-
22658	2SC4811	B>2000	-
22659	2SC4812	B>2000	-
22660	2SC4813	2SC4553, 1,8W	-
22661	2SC4814	100V, +-2,5A, 500/2500ns	-
22662	2SC4815	100V, 5A, 1,8W, 100/1250ns	-
22663	2SC4816	100V, 7A, 1,8W, 200/1400ns	-
22664	2SC4817	150V, 5A, 1,8W, <300/1900ns	-
22665	2SC4818	150V, 7A, 1,8W, <300/1900ns	-
22666	2SC4819	150V, 10A, 1,8W, <300/1900ns	-
22667	2SC482	40V, 0,6A, 0,6W, >50MHz	BC 140...141, BC 300...302, 2N2218...19
22668	2SC4820	<500/3800ns	BUT 12(A)F, BUT 18(A)F, BUV 46(A)FI
22669	2SC4821	2SC3950, 1,3W	2SC3950
22670	2SC4822	2SC3951, 1,3W	2SC3951
22671	2SC4823	2SC3952, 1,3W	2SC3952
22672	2SC4824	2SC3953, 1,3W	2SC3953
22673	2SC4825	2SC3954, 1,3W	2SC3954
22674	2SC4826	2SC3955, 1,3W	2SC3955
22675	2SC4827	2SC3956, 1,3W	2SC3956
22676	2SC4828	300/300V, 0,1A, 8W, 80MHz	2SC3271, 2SC4217, BF 417, BF 459
22677	2SC4829	100V, 0,2A, 0,9W, 1,1GHz	2SC5225
22678	2SC483	100V, 1A, 15W, 25MHz	BD 239C, BD 241C, 2SC1913, 2SC2275
22679	2SC4830	1500/600V, 6A, 50W	2SC3884A, 2SC3894, 2SC4757

22680	2SC4831	<500/1650ns	2SC4298, 2SC4424
22681	2SC4833	<300/1400ns	BUT 11(A)F, 2SC4054, 2SC4073, 2SC4371
22682	2SC4833	<300/1400ns	BUT 11(A)F, 2SC4054, 2SC4073, 2SC4371
22683	2SC4834	<300/1400ns	BU 306F, BUT 12(A)F, 2SC4130, 2SC4161
22684	2SC4834	<300/1400ns	BU 306F, BUT 12(A)F, 2SC4130, 2SC4161
22685	2SC4835	2SC3829	BFS 520, 2SC3937, 2SC5085
22686	2SC4836	60/20V, 5A, 1,5W, 120MHz	2SD1903
22687	2SC4837	60/50V, 4A, 1,5W, 150MHz	2SD1903
22688	2SC4839	2SC3605, SMD	2SC5086
22689	2SC4839	2SC3605, SMD	2SC5086
22690	2SC484	150V, 1,5A, 0,8W, 20MHz	BSS 43, BSW 68, 2SC1860
22691	2SC4840	2SC4316, SMD	2SC5091
22692	2SC4840	2SC4316, SMD	2SC5091
22693	2SC4841	2SC4322	2SC4840
22694	2SC4841	2SC4322	2SC4840
22695	2SC4842	2SC4315	2SC5088
22696	2SC4843	2SC4316, SMD	2SC5093
22697	2SC4844	2SC4322, SMD	2SC4994, 2SC5098
22698	2SC4845	-/120V, 5A, 40W	2SC4328
22699	2SC4846	2SC4845, , 30W	2SD1270
22700	2SC4847	-/120V, 5A, 60W	2SD2065
22701	2SC4848	250/120V, 7A, 40W, 20MHz	-
22702	2SC4849	2SC4848, , 30W	-
22703	2SC485	2SC484, 100V	BCX 40, BSW 66, BSX 46, 2N3107...08
22704	2SC4850	-/120V, 7A, 60W	2SD2065
22705	2SC4851	2SC4852	-
22706	2SC4852	25V, 0,1A, 240MHz,Ron0,9Ohm	-
22707	2SC4853	12V, 15mA, 5GHz	BFR 92W, BFR 820W
22708	2SC4854	2SC4853	BFR 92, BFR 820
22709	2SC4855	2SC4853	-
22710	2SC4856	2SC4859	2SC3937
22711	2SC4857	2SC4859	2SC3704, 2SC3445
22712	2SC4858	2SC4859	2SC4092
22713	2SC4859	18V, 80mA, 5,5GHz	BFQ 193, 2SC3607
22714	2SC486	2SC484, 70V	BCX 40, BSW 65, BSX 45, 2N3109...10
22715	2SC4860	20V, 30mA, 6,5GHz	2SC3937
22716	2SC4861	2SC4860	2SC3704, 2SC3445
22717	2SC4862	2SC4860	2SC3357, 2SC4092
22718	2SC4863	2SC4866	2SC3937
22719	2SC4864	2SC4866	2SC3704, 2SC3445
22720	2SC4865	2SC4866	2SC4092
22721	2SC4866	18V, 70mA, 6,5GHz	BFQ 193, 2SC3301, 2SC3607
22722	2SC4867	16V, 50mA, 9GHz	2SC4593, 2SC4901
22723	2SC4868	2SC4867	2SC3583, 2SC3904, 2SC4591
22724	2SC4869	2SC4867	2SC4094, 2SC4127, 2SC4900

22725	2SC487	110V, 1,5A, 15W, 20MHz	BD 239C, BD 241C, 2SC2275, 2SC2528
22726	2SC4870	2SC4867, 8GHz	2SC4643
22727	2SC4871	16V, 20mA, 10GHz	BFS 505, 2SC5095
22728	2SC4872	2SC4871	BFR 505, 2SC5094
22729	2SC4873	2SC4871	2SC5097
22730	2SC4874	20V, 50mA, 5,8GHz	2SC3512, 2SC4629
22731	2SC4875	15V, 50mA, 8,5GHz	2SC4629
22732	2SC4876	60V, 30A, 45W, <0,3/2μs	-
22733	2SC4876	60V, 30A, 45W, <0,3/2μs	-
22734	2SC4877	1500V, 8A, 50W	BU 2508DF, 2SC3893A, 2SC4763, 2SD2371
22735	2SC4878	1500V, 10A, 50W	BU 2520DF, 2SC4125, 2SC4531, 2SD1881
22736	2SC4879	1700/900V, 10A, 50W	-
22737	2SC487A	2SC487, 150V	BD 239D, 2SC2275A, 2SC2344, 2SC2529
22738	2SC488	140V, 3A, 16W, 10MHz	BD 241D, BDV 11, 2SC2516, 2SD772
22739	2SC4880	1700/900V, 12A, 100W	2SC4896
22740	2SC4881	60V, 5A, 20W, 100/900ns	2SC3299, 2SC3746, 2SC4549, 2SC4596
22741	2SC4882	1200V, 5A, 60W, <2/4μs	2SC4584
22742	2SC4883	150/150V, 2A, 20W, 120MHz	2SC3298, 2SC3364, 2SC4159, 2SD1763A
22743	2SC4883A	2SC4883, 180/180V	2SC3298A...B, 2SC4159
22744	2SC4884	300/300V, 0,1A, 1,5W, 70MHz	2SC1505...07, 2SC3952, 2SC3945, 2SC4075
22745	2SC4885	25V, 50mA, 2,5GHz	2SC4780, 2SC5110
22746	2SC4886	150/150V, 14A, 80W, 60MHz	2SC4388
22747	2SC4887	2500/1200V, 0,1A	-
22748	2SC4888	2500/1200V, 0,3A	-
22749	2SC489	2SC488, 100V	BD 241C, BD 243C, BD 539C, BD 937
22750	2SC4890	1500/800V, 12A, 75W	BU 2525AF, BU 2527AF, 2SC5105
22751	2SC4891	1500/800V, 15A, 100W	BUH 1015T
22752	2SC4892	<1/4μs	BUX 85F, 2SC3794A, 2SC3978
22753	2SC4894	25V, 0,13A, 500MHz, 17/15ns	2SC1621, 2SC4453
22754	2SC4895	B>2k	2SD1785, 2SD2014...2015
22755	2SC4896	1700/900V, 15A, 100W	-
22756	2SC4897	1500/800V, 20A, 150W	2SC3997, 2SC4290A, 2SD2356
22757	2SC4898	8MHz,<1,5/4μs	2SC4518A
22758	2SC4899	15V, 20mA, 9GHz	BFS 505, 2SC5095
22759	2SC49(M,N)	120V, 0,3A, 0,8W, 160MHz	BSW 67...68, BSY 55...56, 2N1893
22760	2SC490	2SC488, 60V	BD 241A, BD 243A, BD 539A, BD 935
22761	2SC4900	15V, 50mA, 9GHz	2SC4094, 2SC4127
22762	2SC4901	2SC4900	2SC4593
22763	2SC4902	20V, 30mA, 6GHz	BFR 182, 2SC3011, 2SC5106
22764	2SC4903	2SC4902	BFR 182W, 2SC5107
22765	2SC4904	20V, 50mA, 5,8GHz	BF 770A, BFQ 67, BFR 183, 2SC3513
22766	2SC4905	2SC4904	BFR 183W, BFQ 67W
22767	2SC4906	2SC4904	BFR 183W, BFQ 67W
22768	2SC4907	<1/5μs	BU 306F, BUT 22BF...CF, 2SC4056, 2SC4546
22769	2SC4908	<1/6μs	2SC3559, 2SC4304, 2SC4517, 2SC4471A

22770	2SC4909	25V, 0,1A	-
22771	2SC491	50V, 1,5A, 15W, 40MHz	BD 239, BD 241, 2SC1398, 2SC3252
22772	2SC4910	38V, 0,75A, PQ0,9W(175MHz)	-
22773	2SC4911K	20V, 0,2A, 450MHz	2SC3735, 2SC4453
22774	2SC4912	2SC4911K	2SC4175...76, 2SC4452
22775	2SC4913	2000/2000V, 20mA, B>10	-
22776	2SC4915	2SC2714	2SC4655, 2SC5021
22777	2SC4915	2SC2714	2SC4655, 2SC5021
22778	2SC4916	1500/600V,+7A, 50W	2SC3892A, 2SC4762
22779	2SC4917	600/400V, 2A, 10W, <1/3,5µs	2SC3924
22780	2SC4918	40V, 0,05A, 750MHz	2SC4809, 2SC4915, 2SC5021
22781	2SC4918	40V, 0,05A, 750MHz	2SC4809, 2SC4915, 2SC5021
22782	2SC4919	2SC4852	-
22783	2SC4919	2SC4852	-
22784	2SC492	110V, 5A, 50W	BD 245C, BDV 95, 2N5759...60, 2SD718
22785	2SC4920	25V, 0,1A, 240MHz,Ron2,2Ohm	-
22786	2SC4920	25V, 0,1A, 240MHz,Ron2,2Ohm	-
22787	2SC4921	25V, 0,1A, 240MHz,Ron2,8Ohm	-
22788	2SC4921	25V, 0,1A, 240MHz,Ron2,8Ohm	-
22789	2SC4922	25V, 0,1A, 240MHz, Ron4Ohm	-
22790	2SC4922	25V, 0,1A, 240MHz, Ron4Ohm	-
22791	2SC4923	1500/800V, 8A, 70W	BU 2520AF, 2SC3896, 2SC3886A, 2SC4758
22792	2SC4924	1500/800V, 10A, 70W	BU 2520AF, BUH 715, 2SC4542, 2SC4759
22793	2SC4926	15V, 50mA, 11GHz	2SC4094, 2SC4127, 2SC4592
22794	2SC4927	1500V, 8A, 50W	BU 2508DF, 2SC3893A, 2SC4763, 2SD2371
22795	2SC4928	1500/800V, 15A, 150W	2SC3996, 2SC4289A
22796	2SC4929	500/400V, 0,8A, 80MHz	-
22797	2SC493	2SC492, 80V	BD 245B, BDV 93, 2N4915, 2SD985...986
22798	2SC4930	7GHz	-
22799	2SC4930	7GHz	-
22800	2SC4931	16V, 0,05A, 9GHz	2SC5139
22801	2SC4932		-
22802	2SC4933		-
22803	2SC4934	2SC4046	2SC3953, 2SC3598...99, 2SC4046
22804	2SC4935	50V, 3A, 10W, 80MHz	2SC3299, 2SC3690, 2SC3746, 2SD1762
22805	2SC4937	2SC3968, 35W	-
22806	2SC4938	400/400V, 5A, 35W, <1/3,5µs	2SC4220
22807	2SC4939	2SC4595, 35W	-
22808	2SC494	2SC492, 50V	BD 245A, BDV 91, 2N4914...15, 2SD985
22809	2SC4940	<500/3300ns	BU 506F
22810	2SC4940	<500/3300ns	BU 506F
22811	2SC4941	<500/3800ns	BU 508(A)F, 2SC4303A, 2SC4770, 2SD2252
22812	2SC4942	<0,5/5,5µs	-
22813	2SC4943	2SC4572	-
22814	2SC4944	2SC4207	-



22815	2SC495	70V, 1A, 5W, 100MHz	BD 137, BD 228, BD 377, 2SD794(A)
22816	2SC4954	9V, 10mA, 12GHz	2SC5050
22817	2SC4955	9V, 30mA, 12GHz	2SC5050
22818	2SC4956	2SC4954	2SC5078
22819	2SC4957	2SC4955	2SC5080
22820	2SC4958	2SC4954	2SC5051
22821	2SC4959	2SC4955	2SC5051
22822	2SC496	2SC495, 40V	BD 135, BD 226, BD 375, 2SD794(A)
22823	2SC4960	900/800V, 1A, 40W, <1/4μs	2SC3285, 2SC3151...52, 2SC3550
22824	2SC4960A	2SC4960, 900/900V	2SC3285, 2SC3533...34
22825	2SC4961	<700/2300ns	2SC3570, 2SC4026, 2SC4073, 2SC4418
22826	2SC4962	1700V, 6A, 50W	2SC4766, 2SD2253
22827	2SC4963	1700V, 8A, 50W	BUH 517D
22828	2SC4964	12V, 0,1A, Ron2Ohm	-
22829	2SC4965	2SC4964	-
22830	2SC4966	12V, 0,1A, Ron1,2Ohm	-
22831	2SC4967	2SC4966	-
22832	2SC4968	15V, 80mA, 0,6W, 6GHz	2SC3355, 2SC3605
22833	2SC4969	2SC3757	2SC3757
22834	2SC497	100V, 0,8A, 0,6W, 50MHz	BC 141, BC 300, BCX 40, 2N2102, 2N2405
22835	2SC4971	2SC4444	2SC4444
22836	2SC4972	2SC2778	2SC2778
22837	2SC4973	2SC2404	2SC2404
22838	2SC4974	2SC2480	2SC2480
22839	2SC4975	2SC3077	2SC3077
22840	2SC4976	2SC4564, 12W	2SC4564
22841	2SC4978	100V, 3A, 10W, 50MHz	2SD1815...1816
22842	2SC4979	100V, 5A, 10W, 50MHz	-
22843	2SC498	2SC497, 80V	BC 140...141, BC 300...301, BCX 40
22844	2SC4980	100V, 5A, 25W, 50MHz	2SC3540, 2SC4549, 2SC4596
22845	2SC4980	100V, 5A, 25W, 50MHz	2SC3540, 2SC4549, 2SC4596
22846	2SC4981	100V, 7A, 25W, 50MHz	2SC3692
22847	2SC4981	100V, 7A, 25W, 50MHz	2SC3692
22848	2SC4982	100V, 10A, 25W, 50MHz	2SC3693, 2SC4595
22849	2SC4982	100V, 10A, 25W, 50MHz	2SC3693, 2SC4595
22850	2SC4983	15V, 1A, 200MHz	-
22851	2SC4984	15V, 1,5A, 200MHz	2SC2983, 2SC3443, 2SC4377, 2SD1621
22852	2SC4985	900/800V, 1A, 1,5W, <1/4μs	BUV 95
22853	2SC4986	500/400V, 2A, 1,5W, <1/4μs	2SC3233, 2SC3631
22854	2SC4987	40V, 0,2A, 750MHz, 8/12ns	-
22855	2SC4988	15V, 0,1A, 8,5GHz	-
22856	2SC499	100V, 0,02A, 0,3W, 150MHz	BF 422, BSW 32, BSS 38, BSX 21
22857	2SC4990		-
22858	2SC4991	15V, 50mA, 9,5GHz	2SC4094, 2SC4127, 2SC4592
22859	2SC4992	2SC4991	2SC4995

22860	2SC4993	15V, 20mA, 10,5GHz	2SC4095, 2SC5092, 2SC5097
22861	2SC4994	2SC4993	2SC4843...44, 2SC5093, 2SC5098
22862	2SC4995	15V, 50mA, 11GHz	-
22863	2SC4997	-/10V, 0,1A, 240MHz	-
22864	2SC4998	2SC4997	2SC4413
22865	2SC50	20V, 0,2A, 0,1W	ASY 28...29, ASY 73...75
22866	2SC500	120V, 0,02A, 0,6W, 175MHz	BF 257...259, BF 657...659, 2N5058...59
22867	2SC5000	80V, 10A, 25W, 90MHz	2SC3693, 2SC3748, 2SC4551, 2SC3255
22868	2SC5001(F5)	30V, 10A, 10W, 150MHz	2SC4669
22869	2SC5002	1500/800V, 7A, 80W	2SC3885A, 2SC3895, 2SC4757
22870	2SC5003	2SC5002	2SC3892A, 2SC4762, 2SC4916
22871	2SC5004	20V, 0,06A, 3000MHz	2SC4839, 2SC5086
22872	2SC5005	20V, 0,03A, 4000MHz	2SC4839, 2SC5086
22873	2SC5006	20V, 0,1A, 3000MHz	-
22874	2SC5007	20V, 0,065A, 4500MHz	2SC4839, 2SC5086
22875	2SC5008	20V, 0,035A, 5500MHz	2SC5108, 2SC5138
22876	2SC5009	9V, 10mA, 12GHz	2SC5246
22877	2SC501	60V, 0,3A, 0,75W, 200MHz	BC 140...141, BC 300...302, 2N3053
22878	2SC5010	9V, 30mA, 12GHz	2SC5139, 2SC5247
22879	2SC5011	20V, 0,1A, 6,5GHz	-
22880	2SC5012	20V, 65mA, 9GHz	-
22881	2SC5013	20V, 35mA, 10GHz	-
22882	2SC5014	9V, 10mA, 12GHz	-
22883	2SC5015	9V, 30mA, 12GHz	-
22884	2SC5016	15V, 0,05A, 1300MHz	BF 599, BFS 20, 2SC3015, 2SC3374
22885	2SC5018	500/400V, 0,8A, 1W, 20MHz	-
22886	2SC5019	15V, 80mA, 6GHz	BFQ 193, 2SC3301, 2SC3357, 2SC3607
22887	2SC502	60V, 1A, 0,8W, >150MHz	BFS 22, BFS 51, BFQ 42, 2N4427
22888	2SC5020	30V, 15mA, 650MHz	2SC3931
22889	2SC5021	2SC5020	2SC4627, 2SC4655, 2SC4915
22890	2SC5022	1500/1500V, 20mA, B>10	2SC4633, 2SC4635
22891	2SC5023	2SC4708, , 8W, 1GHz	2SC3953, 2SC3598...99
22892	2SC5024	2SC4704, , 8W	2SC3956, 2SC3601, 2SC4704
22893	2SC5025	2SC3652	-
22894	2SC5026	80V, 1A, 120MHz	2SC4409, 2SD1615A
22895	2SC5027	300/300V, 0,1A, 70MHz	2SC3271, 2SC3789...90, 2SC4828
22896	2SC5028	60V, 2A, 1,3W, 100MHz	2SD1682
22897	2SC5029	50V, 3A, 1,3W, 100MHz	2SC3420
22898	2SC503(D,M)	100V, 0,6A, 0,8W, 80MHz	BC 141, BC 300, BCX 40, BSW 39
22899	2SC5030	50V, 5A, 1,3W, 150MHz	-
22900	2SC5032	500/400V, 3A, 30W, <1/3,3μs	2SC4052, 2SC4160, 2SC4421, 2SC4533
22901	2SC5034	500/400V, 7A, 35W, <1/2,3μs	BU 306F, 2SC3571, 2SC4130, 2SC4559
22902	2SC5035	800/500V, 5A, 40W, <1,5/4μs	BUT 11(A)F, 2SC3353, 2SC3750
22903	2SC5036	<700/2800ns	BUX 85F, 2SC3794A, 2SC3978(A)
22904	2SC5036A	2SC5036, 1000/800V	BUX 85F, 2SC3751, 2SC3978(A), 2SC4231

22905	2SC5037	<700/2800ns	2SC3752, 2SC3979(A), 2SC4304, 2SC4517(A)
22906	2SC5037A	2SC5037, 1000/800V	2SC3752, 2SC3979A, 2SC4234, 2SC4517A
22907	2SC5039	30V, 2A, 0,9W, B>1200	2SC3225, 2SC4389
22908	2SC504	2SC503, 80V	BC 140...141, BC 300...301, BSW 39
22909	2SC5041	2SC5042	BUH 517D, 2SC4963
22910	2SC5042	1600/800V, 7A, 60W	BUH 417, BUH 517, 2SC4797
22911	2SC5043	2SC5044	BUH 517D
22912	2SC5044	1600/800V, 10A, 70W	2SC4879
22913	2SC5045	1600/800V, 15A, 75W	-
22914	2SC5046	1600/800V, 15A, 180W	-
22915	2SC5047	1600/800V, 25A, 250W	-
22916	2SC5048	1500/600V, 12A, 50W	BU 2525AF, BU 2527AF
22917	2SC5049	15V, 20mA, 10GHz	BFR 505, 2SC3585, 2SC5094
22918	2SC505	300/300V, 0,2A, 0,6W, 60MHz	BF 259, BF 659, BFR 59, BFS 89, 2N5058
22919	2SC5050	15V, 50mA, 11GHz	-
22920	2SC5051	2SC5050	-
22921	2SC5052	120V, 0,8A, 1W, 120MHz	2SC2235, 2SC2383, 2SC3332, 2SC4612
22922	2SC5053	60V, 1A, 150MHz	2SC3444, 2SD1615, 2SD1622...23
22923	2SC5057	1700/900V, 20A, 200W	-
22924	2SC5058	1700/900V, 12A, 150W	2SC4880, 2SC4896
22925	2SC506	2SC505, 200/200V	BF 258...259, BFR 58...59, 2N5058...59
22926	2SC5060	90V, 1A, 1W, 80MHz, B>1k	-
22927	2SC5061	-/80V, 0,7A, 0,9W	2SC2383, 2SC3228, 2SD1292, 2SD1812
22928	2SC5062	-/20V, 3A, 0,9W	2SC4781, 2SD1347
22929	2SC5063	<700/2300ns	2SC3403, 2SC4754
22930	2SC5064	20V, 30mA, 7GHz	BFQ 67, BFR 182...183, 2SC3585
22931	2SC5065	2SC5064	BFQ 67W, BFR 182W...183W, 2SC5190
22932	2SC5066	2SC5064	2SC4840, 2SC5108
22933	2SC5067	1500/800V, 8A, 50W	BU 2508AF, 2SC3896A, 2SC4757, 2SD2372
22934	2SC5068	1500/800V, 10A, 50W	BU 2520AF, 2SC4199A, 2SC4542, 2SC4759
22935	2SC5068A	2SC5068, 12A	BU 2525AF, 2SC4692, 2SC5105
22936	2SC5069	2SC3807, SMD	-
22937	2SC507	170V, 0,1A, 0,75W, 250MHz	BF 257...259, BF 657...659, 2N5058...59
22938	2SC5070	2SC5069	-
22939	2SC5071	500/400V, 12A, 100W, 10MHz	2SC4297, 2SC4423, BUW 13(A), BUV 48...
22940	2SC5072	2SC4911K	2SC4987
22941	2SC5073	2SC4699K	2SC4987
22942	2SC5075	500/400V, 2A, 1,3W, <1/3,5µs	2SC4917
22943	2SC5076	60V, 5A, 1,3W, 120MHz	2SD1903
22944	2SC5077	800/500V, 7A, 45W, <1/3,3µs	BU 307F, BUT 12AF, BUT 22BF,CF
22945	2SC5078	15V, 20mA, 12GHz	-
22946	2SC5079	2SC5078	2SC4995
22947	2SC508	180/60V, 4A, 20W, 25MHz	BU 406...408, 2SD823, 2SD1136, 2SD1159
22948	2SC5080	15V, 50mA, 13,5GHz	-
22949	2SC5081	2SC5080	-

22950	2SC5082M	-/25V, 50mA, 650MHz	BF 920, BF 921S, BF 959
22951	2SC5083	2SC5082M	2SC5082M
22952	2SC5084	20V, 80mA, 7GHz	BFR 193, BFR 520, 2SC3356, 2SC3445
22953	2SC5085	2SC5084	BFS 520, BFS 540
22954	2SC5086	2SC5084	-
22955	2SC5087	20V, 80mA, 7GHz	-
22956	2SC5088	2SC5087	-
22957	2SC5089	20V, 40mA, 10GHz	2SC3583, 2SC3585, 2SC3904, 2SC4591
22958	2SC509(G)	35V, 0,5A, 0,6W, 100MHz	BC 337, BC 635, BC 637, 2SC3377
22959	2SC5090	2SC5089	2SC4593, 2SC5190
22960	2SC5091	2SC5089	-
22961	2SC5092	20V, 40mA, 10GHz	2SC4094...95, 2SC4127
22962	2SC5093	2SC5092	2SC4843
22963	2SC5094	20V, 15mA, 10GHz	BFR 505, 2SC3585, 2SC5089
22964	2SC5095	2SC5094	BFS 505, 2SC5090, 2SC5190
22965	2SC5096	2SC5094	2SC4840...41, 2SC5091
22966	2SC5097	20V, 15mA, 10GHz	2SC4095, 2SC5092
22967	2SC5098	2SC5097	2SC4843, 2SC5093
22968	2SC5099	120V, 6A, 60W, 20MHz	2SC4385, 2SC4689, 2SD2064, BD 245C...F
22969	2SC509GTM	2SC509, 0,8W	BC 337, BC 635, BC 637, 2SC3377
22970	2SC51	60V, 0,3A, 1W, 180MHz	BFX 55, 2N2218...19, 2N3299...3300
22971	2SC510(M)	140/100V, 1,5A, 0,8W, 60MHz	BSS 43, BSW 68, 2SC1860
22972	2SC5100	160V, 8A, 75W, 20MHz	2SC4386, BD 245D...F
22973	2SC5101	200V, 10A, 80W, 20MHz	2SC4387, BD 245F
22974	2SC5103	100V, 5A, 10W, 120MHz	2SC3303
22975	2SC5104	500/400V, 3A, 30W, <1/3,3µs	BUT 11(A)F, 2SC3570, 2SC4052, 2SC4160
22976	2SC5105	1500/800V, 12A, 50W	BU 2525AF, 2SC4692
22977	2SC5106	20V, 30mA, 6GHz	BFR 182, 2SC3011, 2SC5064
22978	2SC5107	2SC5106	BFR 182W, 2SC5065
22979	2SC5108	2SC5106	2SC5066
22980	2SC5109	20V, 60mA, 5GHz	BF770, BFQ67, BFR183, 2SC3513, 2SC3704
22981	2SC511	2SC510, 120/80V	BSS 42...43, BSW 67...68, BSX 47, BSV 84
22982	2SC5110	2SC5109	BFQ 67W, BFR 183W, 2SC3937
22983	2SC5111	2SC5109	2SC5086
22984	2SC5112	-/500, 5A, 40W	BUT 11, BUT 18, BUV 46, 2SC3047
22985	2SC5113	2SC5112, , 35W	BUT 11F, BUT 18F, BUV 46FI, 2SC3750
22986	2SC5114	-/500, 5A, 80W	BUW 11F, 2SC4300, 2SC4427, 2SC4457
22987	2SC5115	-/500, 5A, 35W	2SC4172, 2SC4222, 2SC4600, BUT 11
22988	2SC5116	-/550, 4A, 40W	BUT 11, BUT 18, BUV 46, 2SC3491
22989	2SC5117	2SC5116, , 35W	BUT 11F, BUT 18F, BUV 46FI, 2SC3750
22990	2SC5118	2SC5116, , 80W	BUW 11F, 2SC4300, 2SC4427, 2SC4457
22991	2SC5119	-/550, 4A, 35W	2SC4172, 2SC4222, 2SC4600, BUT 11
22992	2SC512(M)	2SC510, 100/60V	BCX 40, BSW 67...68, BSX 46...47
22993	2SC5120	150/150V, 0,2A, 8W, 500MHz	2SC3787, 2SC3956
22994	2SC5121	400/400V, 0,07A, >50MHz	BF 850, 2SC3418

22995	2SC5122	400/400V, 0,05A, 0,9W	2SC2267, 2SC3469, 2SC4166, 2SD1385
22996	2SC5124	1500/800V, 10A, 100W	BU 2520AF, 2SC4589, 2SC4759, 2SD2373
22997	2SC5127	800/500V, 1,5A, 25W, <1/3,3μs	BUX 84F...85F, 2SC3352, 2SC3794(A)
22998	2SC5127A	2SC5127, 900/500V	BUX 85F, 2SC3794(A), 2SC3978(A)
22999	2SC5128	800/500V, 5A, 40W, <1/3,3μs	BUT 11(A)F, 2SC3353, 2SC3750, 2SC3795
23000	2SC5129		
23001	2SC513	2SC510, 70/40V	BCX 40, BSW 65...68, BSX 45...47
23002	2SC5130	600/400V, 5A, 30W, 20MHz	BUT 11(A)F, 2SC3750, 2SC3795, 2SC4054
23003	2SC5132	2SC5133	2SC4764, 2SC4122, 2SC4294, 2SD2370
23004	2SC5132A	2SC5133, , 8A	BU 2508DF, 2SC4124, 2SC4763, 2SD2371
23005	2SC5133	1500V, 6A, 50W	BU 2508D, 2SC3482, 2SC4122, 2SC4292
23006	2SC5136	25V, 50mA, 3,8GHz	2SC5111, 2SC5141
23007	2SC5137	15V, 20mA, 10GHz	2SC4841, 2SC5096
23008	2SC5138	20V, 30mA, 6GHz	2SC5066, 2SC5108
23009	2SC5139	15V, 50mA, 11GHz	2SC5247
23010	2SC514	300/300V, 0,1A, 4W, 20MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
23011	2SC5140	15V, 20mA, 9GHz	2SC4841, 2SC5096
23012	2SC5141	20V, 50mA, 5,8GHz	-
23013	2SC5142	1500/600V, 20A, 200W	2SC3994, 2SC4290(A), 2SC4897
23014	2SC5143	1700/700V, 10A, 50W	-
23015	2SC5144	1700/600V, 20A, 200W	2SC5057
23016	2SC5145	800/500V, 5A, 40W, <1/4μs	2SC4172, 2SC4222, 2SC4600, BUT 11(A)
23017	2SC5147	300/300V, 0,1A, 10W, 100MHz	2SC3565, 2SC3942, 2SC3945, 2SC4075
23018	2SC5148	1500/600V, 8A, 50W	BU 2525AF, 2SC3896, 2SC4758
23019	2SC5149	2SC5148	BU 2520DF, 2SC3893A, 2SC4763
23020	2SC515(A)	300/300V, 0,1(A0,15)A, 6W	2SC1505...1507, 2SC1755...1757, 2SC1905
23021	2SC5150	1700/700V, 10A, 50W	-
23022	2SC5154	160/160V, 1,5A, 1,3W, 100MHz	2SC3117, 2SD669, 2SD1563A
23023	2SC5155	50V, 3A, 20W, 260MHz, B>800	2SD1584, 2SD1754(A)
23024	2SC5156	1000/800V, 3A, 70W, <1/3μs	BUW 11AF, 2SC4426, 2SC4583
23025	2SC5158	<700/2300ns	2SC4296, BUV 47(A...C), BUW 12(A)
23026	2SC5159	<700/2800ns	BUW 11AF, 2SC4299, 2SC4445
23027	2SC516	100/80V, 1,5A, 0,8W, 50MHz	BCX 40, BSW 66...68, BSX 46...47
23028	2SC5160	<700/2300ns	2SC4296, BUP 22(A...C), BUW 12(A)
23029	2SC5161(F5)	-/400V, 2A, 10W	-
23030	2SC5162(F5)	-/600V, 1A, 10W	2SC3363
23031	2SC516A	2SC516, 140/100V	BSS 43, BSW 68, 2SC1860
23032	2SC517	60V, 2A, PQ>4W(50MHz)	-
23033	2SC5171	180/180V, 2A, 20W, 200MHz	2SC3298A, 2SC4159, 2SC4883A
23034	2SC5172	<700/3000ns	BUT 11(A)F, 2SC3750, 2SC3795, 2SC4054
23035	2SC5173	300/300V, 0,1A, 70MHz	2SC3565, 2SC3942, 2SC3945, 2SC4075
23036	2SC5173	300/300V, 0,1A, 70MHz	2SC3565, 2SC3942, 2SC3945, 2SC4075
23037	2SC5174	230/230V, 1A, 1,8W, 100MHz	2SC4793
23038	2SC5174	230/230V, 1A, 1,8W, 100MHz	2SC4793
23039	2SC5175	60V, 5A, 1,8W, 100MHz	2SC3540, 2SC3746...47, 2SC3691



23040	2SC5175	60V, 5A, 1,8W, 100MHz	2SC3540, 2SC3746...47, 2SC3691
23041	2SC5176	100V, 5A, 1,8W, 120MHz	2SC3540, 2SC3691, 2SC4549, 2SC4596
23042	2SC5176	100V, 5A, 1,8W, 120MHz	2SC3540, 2SC3691, 2SC4549, 2SC4596
23043	2SC5177	5V, 10mA, 10GHz	BFR 505, 2SC5049, 2SC5094
23044	2SC5178(R)	5V, 10mA, 10,5GHz	2SC4993, 2SC5078, 2SC5097
23045	2SC5179	5V, 10mA, 10GHz	BFS 505, 2SC4899, 2SC5095
23046	2SC518	140V, 5A, 50W	BU 104, BU 606...608, 2SD916, 2SD1154
23047	2SC5180	5V, 10mA, 12GHz	2SC4844, 2SC4994, 2SC5098
23048	2SC5181	5V, 10mA, 10GHz	2SC4841, 2SC5096, 2SC5137, 2SC5140
23049	2SC5182	5V, 30mA, 9GHz	2SC3585, 2SC5089
23050	2SC5183(R)	5V, 30mA, 9,5GHz	2SC4095, 2SC5092
23051	2SC5184	5V, 30mA, 9GHz	2SC5090, 2SC5190
23052	2SC5185	5V, 30mA, 10GHz	2SC4843, 2SC5093
23053	2SC5186	5V, 30mA, 9GHz	2SC4840, 2SC5091
23054	2SC5187	25V, 1,5A, 50/180ns	2SC2982, 2SC4377, 2SD1621, 2SD1766
23055	2SC5188	25V, 3A, 50/120ns	2SD1119, 2SD1620, 2SD2150
23056	2SC5189	25V, 5A, 50/180ns	2SD1963, 2SD2540
23057	2SC518A	2SC518, 180V	BU 104, BU 606...608, 2SD916, 2SD1154
23058	2SC519	110/100V, 7A, 50W, 10MHz	BD 245C, BD 550, 2N4348, 2SD1046
23059	2SC5190	9V, 30mA, 10GHz	2SC4593, 2SC4805
23060	2SC5191	9V, 0,1A, 4000MHz	2SC3356
23061	2SC5192(R)	9V, 0,1A, 4000MHz	-
23062	2SC5193	9V, 0,1A, 4000MHz	-
23063	2SC5194	9V, 0,1A, 4000MHz	-
23064	2SC5195	9V, 0,1A, 4500MHz	-
23065	2SC5196	80/80V, 6A, 60W, 30MHz	BD 245C, BDV 93, 2SC3256, 2SD895
23066	2SC5197	120/120V, 8A, 80W, 30MHz	BD 245C, BD 545D, 2SC3181, 2SD718
23067	2SC5198	140/140V, 10A, 100W, 30MHz	BD 245D, 2SC2837, 2SC2706, 2SC3182
23068	2SC5199	180/180V, 12A, 120W, 30MHz	2SC3281, 2SD1975, 2SD2155
23069	2SC519A(A-M)	2SC519, 130/110V, 0,4/4,9µs	BD 245D, 2N4348, 2SC2706, 2SD1046
23070	2SC52	40V, 0,1A, 0,5W, 350MHz	BFW 16...17, BFX 55
23071	2SC520(A,A-M)	2SC519..., 100/80V	BD 245C, BDV 95, BDX 95, 2SD718
23072	2SC5200	230/230V, 15A, 150W, 30MHz	2SC4029
23073	2SC5201	600/600V, 0,05A, 0,9W, 30MHz	2SD1573
23074	2SC5206	500/400V, 5A, 25W, tf600ns	2SC3570, 2SC4026, 2SC4073, 2SC4418
23075	2SC5207A	1500/800V, 10A, 50W	BU 2520AF, BUH 715, 2SC5129
23076	2SC5209	50V, 1A, 130MHz, B>600	2SC3727
23077	2SC521(A)	2SC519..., 70V	BD 245A, BDV 93, BDX 93, 2SD895
23078	2SC5210	300/300V, 0,1A, 80MHz	BFN18, 2SC3380, 2SC3515, 2SC3554, 2SC4189
23079	2SC5211	55V, 0,4A, 150MHz	BCX 55, 2SC3444, 2SD1006, 2SD1767
23080	2SC5212	25V, 0,7A, 180MHz	BCX 54, 2SC3444, 2SC4376, 2SC4539
23081	2SC5213	120/120V, 0,1A, 200MHz	-
23082	2SC5214	30V, 1A, 100MHz	BCX 54...56, 2SC3444, 2SD1005, 2SD1615
23083	2SC5218	15V, 50mA, 9GHz	2SC3583, 2SC3904, 2SC4591
23084	2SC5219	1700/-V, 8A, 50W	BUH 517D, 2SC5143



23085	2SC522(M)	140/100V, 1,5A, 10W, 60MHz	2SC3117, 2SD669
23086	2SC5221	490/490V, 0,2A, 10W, B>150	-
23087	2SC5222	500/500V, 0,5A, 10W, B>100	-
23088	2SC5223	500/500V, 1A, 10W, B>100	-
23089	2SC5224	500/500V, 2A, 10W, B>100	-
23090	2SC5225	100V, 0,3A, 0,625W, 1,4GHz	-
23091	2SC5226	20V, 70mA, 7GHz	BFS 520, 2SC5085
23092	2SC5227	2SC5226	BFR 193, BFR 520, 2SC3445, 2SC5084
23093	2SC5228	2SC5226	2SC5087
23094	2SC5229	2SC5230, SMD	BFQ 193, 2SC3301, 2SC3607
23095	2SC523	2SC522, 120/80V	2SC3117, 2SD669
23096	2SC5230	20V, 70mA, 0,4W, 6,5GHz	2SC3355, 2SC3507
23097	2SC5231	20V, 70mA, 7GHz	2SC5139
23098	2SC5237	250/250V, 0,15A, 8W, 400MHz	2SC4623
23099	2SC5238	1500/800V, 50A, 160W	-
23100	2SC5239	900/550V, 3A, 50W, 6MHz	BUT 11A, BUV 46A, 2SC3148, 2SC3150
23101	2SC524(M)	2SC522, 100/60V	BD 139, BD 230, BD 379, 2SD1177...1178
23102	2SC5242	2SC5200, 130W	2SC3263
23103	2SC5243	1700V, 15A, 200W	2SC4896
23104	2SC5244	1500V, 30A, 200W	-
23105	2SC5244A	2SC5244, 1600	-
23106	2SC5245	20V, 30mA, 11GHz	-
23107	2SC5246	15V, 20mA, 12GHz	2SC5139
23108	2SC5247	15V, 50mA, 13,5GHz	2SC5139
23109	2SC5249	600/600V, 3A, 35W, 6MHz	BUT 11(A)F, 2SC4054, 2SC4304, 2SD1571
23110	2SC525	2SC522, 70/40V	BD 139, BD 230, BD 377, 2SD1177...1178
23111	2SC5250	1500/-V, 8A, 50W	BU 2520DF, 2SC4763
23112	2SC5251	1500/800, 12A, 50W	BU 2525AF, 2SC4890, 2SC5048
23113	2SC5252	1500/800, 15A, 50W	2SC4891
23114	2SC526(M)	165V, 55mA, 0,75W, 250MHz	BF 257...259, BF 657...659, 2N5058...59
23115	2SC5264	1000/450V, 5A, 30W	-
23116	2SC5265	1200/600V, 4A, 30W	-
23117	2SC5266	600/400V, 5A, <700/3000ns	BUT 11(A)F, 2SC3750, 2SC3795, 2SC4056
23118	2SC5266	600/400V, 5A, <700/3000ns	BUT 11(A)F, 2SC3750, 2SC3795, 2SC4056
23119	2SC527	35V, 10mA, 0,13W, 340MHz	BF 198...199, BF 224...225, BF 505
23120	2SC5271	300/200V, 5A, 30W, 10MHz	2SC3570, 2SC3573, 2SC4073, 2SC4129
23121	2SC5273	1300/1300V, 0,03A, 1,8A	2SC3675
23122	2SC5275	20V, 30mA, 11GHz	2SC5051
23123	2SC5276	2SC5275	2SC5050
23124	2SC5277	2SC5275	2SC5139
23125	2SC5279	600/400V, 2A, <1/3,5µs	BUT 11(A)F, 2SC4052, 2SC4304, 2SD1571
23126	2SC5279	600/400V, 2A, <1/3,5µs	BUT 11(A)F, 2SC4052, 2SC4304, 2SD1571
23127	2SC528	20V, 0,15A, 0,2W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23128	2SC5287	900/550V, 5A, 80W, 6MHz	BUW 11A, BUW 131A, 2SC3636, 2SC3642
23129	2SC5288	9V, 0,15A	-

23130	2SC5289	9V, 0,3A	-
23131	2SC529	30V, 0,1A, 0,1W, 230MHz	BC 183, BC 238, BC 548, BF 254...255
23132	2SC5291	2SC3902, 1,5W	2SC3902
23133	2SC5296	2SC5297	BU 2508DF, 2SC4124, 2SC4763
23134	2SC5297	1500/800, 8A, 60W	BU 2508AF, 2SC3896, 2SC4758
23135	2SC5298	2SC5299	BU 2520DF, 2SC4125, 2SC4878
23136	2SC5299	1500/800, 10A, 70W	BU 2520AF, BUH 715, 2SC4589
23137	2SC53	25V, 0,1A, 0,6W, 300MHz	BFW 16...17, BFX 55
23138	2SC530	30V, 0,1A, 0,1W, 230MHz	BC 183, BC 238, BC 548, BF 254...255
23139	2SC5307	400/400V, 0,05A	2SC4548, 2SD2413
23140	2SC531	30V, 0,1A, 0,1W, 230MHz	BC 183, BC 238, BC 548, BF 254...255
23141	2SC5319	8V, 20mA, 13GHz	-
23142	2SC532	30V, 0,1A, 0,1W, 230MHz	BF 240...241, BF 254...255, BF 594...595
23143	2SC5327	40V, 0,5A, 0,5W, 300MHz	BC 337, BC 635, 2SD863, 2SD1225...26
23144	2SC5328	60V, 0,15A, 0,4W, >80MHz	BC 174, BC 182, BC 546, 2SD767
23145	2SC5329	35V, 0,8A, 0,625W, 130MHz	BC 337, BC 635, 2SD863, 2SD1225...26
23146	2SC533	230MHz	BF 240...241, BF 254...255, BF 594...595
23147	2SC5330	30V, 0,02A, 0,4W, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
23148	2SC5331	1500/600V, 15A, 180W	2SC3996, 2SC4289A
23149	2SC5332	1700/800V, 10A, 200W	2SC4532, 2SC4880
23150	2SC5333	300/300V, 2A, 35W, 10MHz	2SC3309, 2SC3560...61, 2SC3868, 2SC3969
23151	2SC5339	1500/600V, 8A, 50W	BU 2520AF, 2SC3886A, 2SC38896A, 2SC4758
23152	2SC534	30V, 0,1A, 0,1W, 230MHz	BF 240, BF 255, BF 495, BF 595
23153	2SC535	700MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23154	2SC535	700MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23155	2SC536(..P..)	40..55V, 0,1A, 0,2W, 180MHz	BC 183, BC 237, BC 547, BF 254...255
23156	2SC537(FP)	2SC536, 20V	BC 183, BC 238, BC 548, BF 254...255
23157	2SC538(Z)	25V, 0,05A, 0,3W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23158	2SC538A(AZ)	2SC538, 45V	BC 167, BC 182, BC 237, BC 547, 2SC1890
23159	2SC539(Z)	2SC538	BC 169, BC 184, BC 239, BC 549, 2SC2675
23160	2SC54	2SC52, 0,3W	BFX 59, BFW 16...17, BFX 55
23161	2SC540	30V, 0,1A, 0,15W, 100MHz	BC169, BC184, BC239, BC549, 2SC2675
23162	2SC541	50V, 1A, PQ4W(175MHz)	BFS 23
23163	2SC542	65V, 1,5A, PQ6W(175MHz)	BLY 60, 2N3632
23164	2SC543	65V, 3A, PQ14,5W(175MHz)	BLY 35, 2N3632
23165	2SC544	40V, 0,03A, 0,15W, 350MHz	BF 198...199, BF 224...225, BF 505
23166	2SC545	20V, 0,03A, 0,15W, 350MHz	BF 198...199, BF 224...225, BF 505
23167	2SC546	30V, 0,03A, 0,15W, 600MHz	BF 198...199, BF 224...225, BF 505
23168	2SC547(D)	65V, 1A, PQ>2,5W(175MHz)	BFS 23, BLY 34
23169	2SC548	36V, 0,5A, PQ>1W(175MHz)	BFS 22, BFQ 42, BFW 46, MRF237, 2N3924
23170	2SC549	65V, 1,5A, PQ>5W(175MHz)	BLY 35, 2N3632
23171	2SC55	2SC52, 0,36W	BFX 59, BFW 16...17, BFX 55
23172	2SC550	36V, 1,5A, PQ>4W(175MHz)	BLW 35, BLY 58, 2N3927
23173	2SC551	65V, 3A, PQ>13,5W(175MHz)	BLY 35, 2N3632
23174	2SC552	36V, 3A, PQ>12W(175MHz)	BLW 36

23175	2SC553	65V, 3A, PQ>10W(175MHz)	-
23176	2SC554	36V, 0,5A, 400MHz	BLX 65
23177	2SC555	55V, 0,4A, PQ>1W(400MHz)	BFR 97
23178	2SC556	40V, 0,4A, 850MHz	BFR 97, 2N3866
23179	2SC557	40V, 2A, 20W, 350MHz	BLY 36, BLY 79
23180	2SC558	250/80V, 5A, 50W	BU 104, BU 606...608, 2SD916, 2SD1154
23181	2SC559	60V, 0,3A, 0,6W, 230MHz	BC 140...141, BC 300...302, 2N3053
23182	2SC56	20V, 25mA, 0,2W	BC 168, BC 183, BC 238, BC 548, 2SD767
23183	2SC560(N)	80V, 0,8A, 0,8W, 150MHz	BC 140...141, 2N1990, 2N2102, 2N2405
23184	2SC561	20V, 25mA, 0,2W, 200MHz	BF 198...199, BF 224...225, BF 594...595
23185	2SC562(Z)	330MHz	BF 198...199, BF 224...225, BF 505
23186	2SC563(A,AZ)	40V, 25mA, 550MHz	BF 198...199, BF 224...225, BF 505
23187	2SC564	50V, 0,5A, 0,65W, -/85ns	BSS 28...29, BSV 77, 2N3724, 2SC1385
23188	2SC565	50V, 0,2A, 0,35W, -/125ns	BSV 59, BSX 48...49, 2N3903...3904
23189	2SC566	50V, 0,3A, 0,8W, 700MHz	BFX 55, 2SC2852
23190	2SC567	30V, 0,02A, 1300MHz	BF 505, BF 689, BF 763, 2N2857
23191	2SC568	30V, 0,02A, 900MHz	BF 505, BF 689, BF 763, 2N2857
23192	2SC569	40V, 0,15A, 0,15W, <-/35ns	BSS 11, BSX 92...93, 2N2368...69(A)
23193	2SC57	75V, 0,5A, 110MHz	BD 139, BD 230, 2SD1200, 2SD1378
23194	2SC570	2SC569, 0,2A, 0,3W	BSS 11, BSX 19...20, 2N2368...69(A)
23195	2SC571	36V, 0,5A, PQ>1W(175MHz)	BFQ 42, BFR 98, BFS 51, BLW 16, BLY 61
23196	2SC572	36V, 1A, PQ>4W(175MHz)	BLY 55, BLY 57
23197	2SC573	36V, 2A, PQ>12W(175MHz)	BLY 36, BLY 79
23198	2SC574	80V, 1A, 7,5W, 280MHz	BLY 60
23199	2SC575	80V, 1A, 5W, 210MHz	BLY 60
23200	2SC576	40V, 0,5A, 0,36W, <12/15ns	BSS 10, BSX 26, BSX 39, 2N3261, 2SC4648
23201	2SC577	2SC576, <12/18ns	BSS 10, BSX 26, BSX 39, 2N3261, 2SC4648
23202	2SC578	60V, 0,5A, 0,6W, <65/150ns	BSS 13, BSV 77, 2N5189, 2SC1385...1386
23203	2SC579	30V, 0,2A, 0,36W, <75/50ns	BSS 11...12, BSX 19...20, 2N2368...69(A)
23204	2SC58(A)	60..135V, 0,06A, 0,6W, 250MHz	BF 257...259, BF 657...659, 2N5058...59
23205	2SC580	60V, 1A, 0,8W, 250MHz	BC 140...141, 2N1990, 2N2102, 2N2405
23206	2SC581	30V, 0,03A, 0,14W, 230MHz	BF 240...241, BF 254...255, BF 594...595
23207	2SC582	300V, 0,1A, 6,5W(Tc70°)	2SC1505...1507, 2SC1755...1757, 2SC1819
23208	2SC583	30V, 0,02A, 1300MHz	BF 377...378, BF 689, BF 763, 2N2857
23209	2SC584	80V, 2A, 200MHz	BLY 35, 2N3632
23210	2SC585	65V, 3A, PQ>13,5W(175MHz)	2N3632
23211	2SC586	150V, 5A, 50W, 55MHz	BUW 86...87, 2SC2837, 2SD731...732
23212	2SC587(M,N)	45V, 0,03A, 0,3W, 80MHz	BC 167, BC 182, BC 237, BC 547, 2SC1890
23213	2SC587A(M,N)	2SC587	BC 169, BC 184, BC 239, BC 549, 2SC2674
23214	2SC588	30V, 0,1A, 0,6W, 200MHz	BC 140...141, BC 300...302, 2N2218...19
23215	2SC589(N)	200MHz	BF 257...259, BF 657...659, 2N5058...59
23216	2SC59	120V, 0,3A, 0,8W, 150MHz	BC 300, 2N1893(A), 2N2102, 2N2405
23217	2SC590(N)	120/70V, 0,3A, 0,8W, 150MHz	BC 300, 2N1893(A), 2N2102, 2N2405
23218	2SC591(N)	100V, 1,5A, 20W, 150MHz	BD 139, BD 230, BD 379, 2SD1177...1178
23219	2SC592	75V, 2,5A, 13W, 180MHz	BLY 35, 2N3632

23220	2SC593	50V, 0,03A, 0,165W, 230MHz	BF 240...241, BF 254...255, BF 594...595
23221	2SC594(M,N)		BSW 51...52, BSY 58, 2N2218...19(A)
23222	2SC595(N)		BSV 90...92, BSX 92...93, 2N2368...69(A)
23223	2SC596(N)	60V, 0,5A, 0,8W, 400MHz	BFX 55, BFS 23, BLY 34
23224	2SC597(N)	65V, 1A, 400MHz	-
23225	2SC598(N)		
23226	2SC599(N)	60V, 1,5A, 20W, >300MHz	BLW 23...24, BLY 92...93
23227	2SC60	20V, 0,02A, 0,1W	AC 127, ASY 28...28
23228	2SC600(N)		
23229	2SC601(N)	<12/18ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
23230	2SC602(N)	30V, 0,03A, 0,2W, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
23231	2SC604	45V, 0,1A, 0,15W	BC167, BC182, BC237, BC547, 2SD767
23232	2SC605	30V, 0,02A, VHF-M, 480MHz	BF 198...199, BF 224...225, BF 505
23233	2SC606	530MHz	BF 225, BF 310, BF 314, BF 505
23234	2SC607	75V, 0,6A, 1W, 70MHz	BC 140...141, BC 300...302, 2SC959
23235	2SC608(T)	75V, 1,5A, PQ>1,2W(27MHz)	BD 139, BD 230, BD 379, 2SD1177...1178
23236	2SC609(T)	2SC208, PQ>3W(27MHz)	BD 139, BD 230, BD 379, 2SD1177...1178
23237	2SC61	30V, 0,3A, 1,2W, 180MHz	BD 135, BD 226, 2SC3419
23238	2SC610	100V, 10A, PQ32W(40MHz)	-
23239	2SC611(N)		BF 377...378, BF 689, BF 763, 2N2857
23240	2SC612(N)	35V, 0,02A, 1300MHz	BF 377...378, BF 689, BF 763, 2N2858
23241	2SC613	40V, 0,2A, 0,36W, <25/25ns	BSS 11, BSX 19...20, 2N2368...69(A)
23242	2SC614	200MHz	BCX 40, BSS 15...16, BSX 45...47, 2SD854
23243	2SC615	2SC614, 30V	BCX 40, BSS 15...16, BSX 45...47, 2SD854
23244	2SC616	2SC614, 13W	BD 139, BD 230, BD 379, 2SD1177...1178
23245	2SC617	2SC615, 13W	BD 135, BD 226, BD 375, 2SD1177...1178
23246	2SC618(A)	25V, 20mA, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23247	2SC619	30V, 0,2A, 0,25W, 250MHz	BC 183, BC 548, BSV 59, 2N2221...22(A)
23248	2SC619	30V, 0,2A, 0,25W, 250MHz	BC 183, BC 548, BSV 59, 2N2221...22(A)
23249	2SC62	40V, 0,05A, 0,36W, <19/75ns	BSS 11, BSV 91...92, BSX 92...93, 2N2368
23250	2SC620(M)	2SC619, 50V	BC 182, BC 547, BSV 59, 2N2221...22(A)
23251	2SC620(M)	2SC619, 50V	BC 182, BC 547, BSV 59, 2N2221...22(A)
23252	2SC621(A,M)	25..30V, 0,1A, 0,15W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23253	2SC622	2SC621	BC 168, BC 183, BC 238, BC 548, 2SD767
23254	2SC623	40V, 0,15A, 0,15W, <-/90ns	BSS 11, BSX 92...93, 2N2368...69(A)
23255	2SC624	2SC623, 0,2A, 0,3W	BSS 11, BSX 92...93, 2N2368...69(A)
23256	2SC626	50V, 0,2A, 0,75W, 350MHz	BFW 16...17, BFX 55
23257	2SC627(F)	200V, 0,1A, 0,7W, 20MHz	BF 258...259, BF 658...659, 2N5058...59
23258	2SC628	40V, 0,5A, PQ2W(200MHz)	BFW 46, BLY 33, BLX 65, 2N3924
23259	2SC629	18V, 0,03A, 800MHz	BF 377...378, BF 689K, BF 763, 2N2857
23260	2SC63	25V, 0,05A, 0,3W, 400MHz	BSY 62...63, BSW 41, 2N706A, 2N708
23261	2SC631(A,S)	2SC632(A), 25V	BC 169, BC 184, BC 239, BC 549, 2SC2675
23262	2SC632(A)	50V, 0,1..0,2A, 140MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
23263	2SC633(A)	25V, 0,1..0,2A, 140MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23264	2SC634(A)	2SC633(A), 50V	BC 167, BC 182, BC 237, BC 547, 2SD767

23265	2SC635	65V, 1,5A, PQ>4W(175MHz)	BLY 60
23266	2SC636	65V, 3A, PQ>7,5W(260MHz)	BLY 35, 2N3632
23267	2SC637	40V, 1A, PQ6W(175MHz)	BLY 57, 2N3926
23268	2SC638	40V, 2A, PQ13,2W(175MHz)	BLY 58, 2N3927
23269	2SC639	40V, 0,2A, 0,36W, <12/18ns	BSS 11, BSX 19...20, 2N2368...69(A)
23270	2SC64	80V, 0,05A, 0,6W, 100MHz	BF 257...259, BF 657...659, 2N5058...59
23271	2SC640	30V, 0,1A, 0,15W, 100MHz	BC168, BC183, BC238, BC548, 2SD767
23272	2SC641(H,K)	40V, 0,1A, 400MHz, 20/35ns	BFX 59, BSV 91...92, BSX 92...93, 2SC2851
23273	2SC641(H,K)	40V, 0,1A, 400MHz, 20/35ns	BFX 59, BSV 91...92, BSX 92...93, 2SC2851
23274	2SC642	1100/700V, 1A, 50W	BU 204...206, 2SC1922, 2SD575, 2SD818
23275	2SC642A	2SC642, 1500/800V	BU 204...206, 2SC1922, 2SD575, 2SD818
23276	2SC643	1100V, 2,5A, 50W	BU 204...206, 2SC1922, 2SD575, 2SD818
23277	2SC643A	2SC642, 1500V	BU 204...206, 2SC1922, 2SD575, 2SD818
23278	2SC644	30V, 0,05A, 0,25W,160MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23279	2SC645(Z)	30V, 0,03A, 0,14W, 200MHz	BF 240...241, BF 254...255, BF 594...595
23280	2SC646	60V, 4A, 25W, 50MHz	2SC2681, 2SC2706, 2SC2837, 2SC3256
23281	2SC647	80V, 5A, 50W(Tc70°), 43MHz	2SC2681, 2SC2706, 2SC2837, 2SC3256
23282	2SC648(H)	30V, 0,03A, 0,1W, 350MHz	BF 198...199, BF 224...225, BF 505
23283	2SC649	30V, 0,03A, 0,2W, 220MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23284	2SC65(Y)	2SC64, 150V, 200MHz	BF 257...259, BF 657...659, 2N5058...59
23285	2SC650	30V, 0,03A, 0,2W, 220MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23286	2SC651	45V,0,3A,PQ>0,75W(500MHz)	BFS 50, MRF 515, 2N3948, 2SC2852
23287	2SC652(M)	40V, 0,3A, PQ>1W(500MHz)	BFS 50, MRF 515, 2N3948, 2SC2852
23288	2SC653	25V, 0,02A, 1400MHz	BF 377...378, BF 689, BF 763, 2N2857
23289	2SC654	40V, 0,3A, 0,8W, 650MHz	BFR 98, BFX 55, MRF 207, MRF 225
23290	2SC657	18V, 0,03A, 500MHz	BF 198...199, BF 224...225, BF 505
23291	2SC658(M)	25V, 0,02A, 550MHz	BF 198...199, BF 224...225, BF 505
23292	2SC659	2SC658, 400MHz	BF 198...199, BF 224...225, BF 505
23293	2SC66	2SC64, 150V, 130MHz	BF 257...259, BF 657...659, 2N5058...59
23294	2SC660	25V, 0,02A, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23295	2SC661	25V, 0,02A, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23296	2SC662	25V, 0,02A, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
23297	2SC663	25V, 0,02A, 900MHz	BF 377...378, BF 689, BF 763, 2N2857
23298	2SC664	100V, 5A, 50W, 15MHz	BD 245C, BDV 95, BDX 95, 2SC2681
23299	2SC665(H)	2SC664, 125V	BD 245D, 2SC2706, 2SC2837, 2SD551
23300	2SC666	2SC664, 150V	BD 245D, 2SC2837, 2SD551, 2SD1046
23301	2SC667	15V, 0,03A, 0,12W, 600MHz	BF 198...199, BF 224...225, BF 505
23302	2SC668	2SC667,	BF 314, BF 502, BF 505, BF 507
23303	2SC668SP	2SC668, 0,15W	2SC668
23304	2SC669(A)	100V, 3A, 10W(Tc25°), 65MHz	BSX 64, 2N4239, 2SC2214
23305	2SC67	<20/40ns	BSS 11, BSX 19...20, 2N2368...69(A)
23306	2SC674	600MHz	BF 198, BF 225, BF 314, BF 502, BF 505
23307	2SC674SP	2SC674, 0,15W	2SC674
23308	2SC675	250/120V, 7A, 50W, -/<3μs	BD 550B, BU 606...608, BUX 18A...C
23309	2SC676	2SC675, 200/100V	BD 245F, BU 606...608, BUX 18A...C



23310	2SC677	2SC675, 150/80V, $-\lt 4,5\mu\text{s}$	BD 245D, BU 606...608, BUX 18A...C
23311	2SC678	2SC675, 100/60V, $-\lt 4,5\mu\text{s}$	BD 245C, BU 606...608, BUX 18A...C
23312	2SC679	300V, 2A, 30W, 20MHz	BU 406...408, 2SC779, 2SC825, 2SD1150
23313	2SC68(M)	$\lt 20/40\text{ns}$	BSS 11, BSX 19...20, 2N2368...69(A)
23314	2SC680(A)	20MHz	BU 406...408, 2SC779, 2SC825, 2SC1025
23315	2SC681	200/70V, 6A, 50W	BU 104, BU 606...608, 2SD916
23316	2SC681A,ARD	2SC681, 250/80V	BU 104, BU 606...608, 2SD916
23317	2SC681AYL	2SC681, 300/80V	BU 104, BU 606...608, 2SD916
23318	2SC682	20V, 0,02A, 550MHz	BF 198, BF 225, BF 310, BF 367, BF 596
23319	2SC683	20V, 0,02A, 550MHz	BF 198, BF 225, BF 310, BF 367, BF 596
23320	2SC684	30V, 0,05A, 1100MHz	BF 377...378, BF 689K, BF 763, 2N2857
23321	2SC685(A,H)	300/300V, 0,1A, 4W, 25MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
23322	2SC686	180MHz	BF 257...259, BF 657...659, 2N5058...59
23323	2SC687	150V, 5A, 50W, $-\lt 3\mu\text{s}$	BD 245D, BU 606...608, 2SD731...732
23324	2SC688	60V, 1,5A, 20W, 300MHz	BLY 97...98, 2N5641
23325	2SC689(H)	6,5/8ns	BSV 91...92, BSX 92...93, 2N2368...69(A)
23326	2SC69	120V, 0,3A, 0,8W, 160MHz	BC 300, BSY 55...56, 2N1893(A)
23327	2SC690(A,M)	60V, 3(A4)A, PQ25W(150MHz)	BLX 39, MRF 314A, MRF 315A
23328	2SC691(M)	60V, 0,5A, PQ3,5W(150MHz)	BLY 91
23329	2SC692	60V, 1A, PQ9W(150MHz)	BLY 92
23330	2SC693(FP,NP)	40V, 0,05A, 0,1W, 150MHz	BC 184, BC 413...414, BC 550, 2SC2390
23331	2SC694(FP)	40V, 0,05A, 0,1W, 100MHz	BC 184, BC 413...414, BC 550, 2SC2390
23332	2SC695	20V, 0,03A, 0,1W, 150MHz	BC169, BC184, BC239, BC549, 2SC2390
23333	2SC696(Z)	100V, 3A, 0,75W, 100MHz	BSX 64, 2N4239, 2SC2214
23334	2SC696A	2SC696, 130V	BU 125S, BUX 49...50, BUY 41, 2SD625
23335	2SC697	2SC696, 10W	BD 791, BDX 35...37, MJE 243...244
23336	2SC697A	2SC696, 130V, 10W	BDV 11, BDX 36...37, 2SD772
23337	2SC698	100V, 3A, 10W, 90MHz	BD 791, BDX 35...37, MJE 243...244
23338	2SC699	50V, 1A, 10W, 100MHz	BD 137, BD 228, BD 377, 2SD1177...78
23339	2SC70	180V, 0,02A, 0,8W, 130MHz	BF 258...259, BF 658...659, 2N5058...59
23340	2SC700	60V, 0,75A, 300MHz	BFS 23, BLY 34
23341	2SC701	40V, 0,75A, 500MHz	BFS 22, BFW 46, BLY 33, MRF 237, 2N3924
23342	2SC702	40V, 0,75A, PQ3W(175MHz)	BLY 85, 2N5589
23343	2SC703	40V, 2A, PQ12W(175MHz)	BLW 19, MRF 208, MRF 212, 2N5590
23344	2SC704	40V, 4A, PQ17W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
23345	2SC705	15V, 0,03A, 700MHz	BF 225, BF 314, BF 502, BF 505, BF 507
23346	2SC706	2SC705, 800MHz	BF 225, BF 314, BF 502, BF 505, BF 507
23347	2SC707(H)	650MHz	BF 377...378, BF 689, BF 763, 2N2857
23348	2SC708(H)	60V, 1A, 0,75W, 15MHz	BC 140...141, 2N1990, 2N2102, 2N2405
23349	2SC708A	2SC708, 100V	BC 141, 2N1990, 2N2102, 2N2405
23350	2SC709	25V, 0,1A, 0,2W, 180MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23351	2SC709	25V, 0,1A, 0,2W, 180MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23352	2SC71	18V, 0,2A, 0,15W	AC 127, ASY 28...29, ASY 73...75
23353	2SC710	30V, 0,03A, 0,2W, 200MHz	BC 548, BF 240...241, BF 254...255
23354	2SC710	30V, 0,03A, 0,2W, 200MHz	BC 548, BF 240...241, BF 254...255



23355	2SC711	30V, 0,05A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23356	2SC711	30V, 0,05A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23357	2SC711A	2SC711, 50V	BC 167, BC 182, BC 237, BC 547, 2SC1890
23358	2SC711A	2SC711, 50V	BC 167, BC 182, BC 237, BC 547, 2SC1890
23359	2SC712(A)	30V, 0,1A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23360	2SC712(A)	30V, 0,1A, 0,2W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23361	2SC713(M)	30V, 0,1A, 0,2W, <60/150ns	BSW 41, BSY 63, 2N708, 2N4123...24
23362	2SC713(M)	30V, 0,1A, 0,2W, <60/150ns	BSW 41, BSY 63, 2N708, 2N4123...24
23363	2SC714	70V, 0,2A, 0,25W, <40/250ns	BSW 63...64, 2N2221...22(A)
23364	2SC714	70V, 0,2A, 0,25W, <40/250ns	BSW 63...64, 2N2221...22(A)
23365	2SC715	40V, 0,1A, 0,125W, 140MHz	BC 167, BC 183, BC 237, BC 547, 2SC1815
23366	2SC716	2SC715, 20V	BC 168, BC 183, BC 238, BC 548, 2SC1740
23367	2SC717	>600MHz	BF 225, BF 314, BF 502, BF 505, BF 507
23368	2SC718	/15ns	BSS 10...12, BSY 18, 2N2368...69(A)
23369	2SC719	2SC718, 0,2W	BSS 10...12, BSY 18, 2N2368...69(A)
23370	2SC72	18V, 0,2A, 0,15W	AC 127, ASY 28...29, ASY 73...75
23371	2SC720	25V, 0,02A, 500MHz	BF 198, BF 225, BF 310, BF 367, BF 596
23372	2SC721	2SC720	BF 198, BF 225, BF 310, BF 367, BF 596
23373	2SC722	25V, 25mA, 700MHz	BF 377...378, BF 689K, BF 763, 2N2857
23374	2SC723	25V, 25mA, 500MHz	BF 377...378, BF 689K, BF 763, 2N2857
23375	2SC724	/ $<300$ ns	BC 168, BC 183, BC 238, BC 548, 2SC1815
23376	2SC725	2SC724, 60V	BC 174, BC 182, BC 190, BC 546, 2SD767
23377	2SC726	/15ns	BSS 10...12, BSY 18, 2N2368...69(A)
23378	2SC727	100/100V, 0,1A, 0,35W, 20MHz	BF 297...299, BSS 38, BSX 21, 2SC3467
23379	2SC728	2SC727, 200/200V	BF 297...299, BF 391...393, 2SC3467
23380	2SC729	50V, 0,2A, 0,6W, 250MHz	BC 140...141, BC 300...302, 2N3053
23381	2SC73	15V, 5mA, 0,03W, 20MHz	-
23382	2SC730	40V, 0,4A, PQ1,5W(150MHz)	BFR 98, BLW 16, MRF 225, MFR 607
23383	2SC731(Z)	40V, 0,5A, PQ1,2W(500MHz)	BFS 50, MRF 629, 2N3948
23384	2SC732(TM)	35..60V, 0,1A, 0,3W, 80MHz	BC 550, 2SC2240, 2SC2459, 2SC2674...75
23385	2SC733	35V, 0,1A, 0,3W, >80MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23386	2SC734	70V, 0,15A, 0,3W, 150MHz	BC 546, 2SC1627, 2SC2003
23387	2SC735	35V, 0,4A, 0,3W, 300MHz	BC 337...338, BC 635, BC 637, 2SC3377
23388	2SC736	135V, 5A, 50W, <2/4 $\mu$ s	BD 550, BU 606...608, 2SC2706, 2SD1046
23389	2SC737(M)	60V, 1,5A, PQ14W(150MHz)	BLW 24, BLY 92
23390	2SC738	25V, 20mA, 440MHz	BF 198...199, BF 224...225, BF 505
23391	2SC738	25V, 20mA, 440MHz	BF 198...199, BF 224...225, BF 505
23392	2SC739	2SC738, 350MHz	BF 198...199, BF 224...225, BF 505
23393	2SC739	2SC738, 350MHz	BF 198...199, BF 224...225, BF 505
23394	2SC74	50V, 0,1A, 0,6W, 300MHz	BC 300...302, BSY 58, 2N3299...3300
23395	2SC740	2SC738, UHF, 900MHz	BF 377...378, BF 689, BF 763, 2N2857
23396	2SC741	40V, 0,3A, PQ0,3W(150MHz)	BFX 55, 2SC2852
23397	2SC742	65V, 1,5A, 12,5W, 400MHz	BLY 35, BLY 60, 2N3632
23398	2SC743	65V, 3A, 25W, 350MHz	BLY 35, 2N3632
23399	2SC745	50V, 1,5A, 12,5W, 450MHz	BLY 35, BLY 60, 2N3632

23400	2SC746	45V, 3A, 25W, 350MHz	BLY 35, 2N3632
23401	2SC748	36V, 1A, 12,5W, 400MHz	BLY 35, BLY 60, 2N3632
23402	2SC749	36V, 2A, 25W, 350MHz	BLY 35, 2N3632
23403	2SC75	15V, 5mA, 10MHz	-
23404	2SC751	20V, 0,02A, 650MHz	BF 198...199, BF 224...225, BF 505
23405	2SC752(G,GTM)	30V, 0,1A, 0,1W, 300MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23406	2SC753	1100MHz	BF 362...363
23407	2SC754	20V, 0,15A, 0,15W, 90MHz	BC168, BC183, BC238, BC548, 2SD767
23408	2SC755	15V, 0,1A, 0,15W, 100MHz	BC168, BC183, BC238, BC548, 2SD767
23409	2SC756(A-...)	65MHz	BUX 34, BUY 80, 2SD625
23410	2SC757	1100MHz	BF 362...363
23411	2SC758	280/120V, 8A, 60W, 18MHz	BD 550B, BU 606...608, BUX 18A...C
23412	2SC759	2SC758, 180/100V	BD 245E, BU 606...608, BUX 18A...C
23413	2SC76	15V, 5mA, 10MHz	-
23414	2SC760	2SC758, 100/60V	BD 245C, BU 606...608, BUX 18A...C
23415	2SC761(Z)	30V, 0,02A, 675MHz	BF 377...378, BF 689, BF 763, 2N2857
23416	2SC762(Z)	30V, 0,02A, 600MHz	BF 377...378, BF 689, BF 763, 2N2857
23417	2SC763	25V, 20mA, >400MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23418	2SC763	25V, 20mA, >400MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23419	2SC764	40V, 0,2A, 0,36W, <12/18ns	BSS 11, BSX 19...20, 2N2368...69(A)
23420	2SC765	60V, 2A, PQ20W(27MHz)	-
23421	2SC766	120V, 2A, PQ19W(27MHz)	-
23422	2SC767	180V, 2A, PQ19W(27MHz)	-
23423	2SC768	60/40V, 10A, 50W, -/<3µs	BD 245A, BD 311, BDV 91, 2N3055
23424	2SC769	2SC768, 120/80V	BD 245D, BDX 51, 2N5633...34, 2SD551
23425	2SC77	15V, 5mA, 10MHz	-
23426	2SC770	2SC768, 200/100V	BD 245F, BUX 17A...C, 2SC3263, 2SD555
23427	2SC771	2SC768, 250/120V	BUX 17A...C, BUY 18, 2SC3263, 2SD555
23428	2SC772	15V, 0,03A, 0,12W, 300MHz	BF 198...199, BF 224...225, BF 254...255
23429	2SC773	50V, 0,2A, PQ40mW(27MHz)	2SC2086, 2SC2851, BC 237, BC 546
23430	2SC773	50V, 0,2A, PQ40mW(27MHz)	2SC2086, 2SC2851, BC 237, BC 546
23431	2SC774	50V, 0,5A, PQ0,07W(27MHz)	MRF 402, MRF 8003, 2SC781
23432	2SC775	75V, 1A, PQ0,7W(27MHz)	2SC781
23433	2SC776	75V, 1A, PQ1,5W(27MHz)	-
23434	2SC777	75V, 1A, PQ3,5W(27MHz)	2SC1306, 2SC1909, 2SC2020, 2SC2029
23435	2SC778	80V, 2A, PQ4W(27MHz)	2SC1306, 2SC1909, 2SC2020, 2SC2029
23436	2SC779	300/250V, 2A, 25W, 8MHz	2SC825, BU 406...408, 2SD1150, 2SD1163
23437	2SC78	15V, 5mA, 20MHz	-
23438	2SC780(G,GTM)	70/70V, 0,02A, 100MHz	BF 297...299, BF 422, BSW 32, BSS 38
23439	2SC780A(G,GTM)	2SC780, 150/150V	BF 297...299, BF 422, 2SC2375, 2SD2030
23440	2SC781	75V, 1A, PQ0,8W(27MHz)	BFS 23, BLY 34
23441	2SC782(A)	10MHz	2SC779, 2SC825, BUX 84...85, 2SD1150
23442	2SC783	2SC782, 200/200V	2SC779, 2SC825, BU 406...408, 2SD1136
23443	2SC784	40V, 0,02A, 500MHz	BF 241, BF 255, BF 314, BF 495, BF 595
23444	2SC785	40V, 0,02A, 500MHz	BF 240, BF 254, BF 310, BF 494, BF 595

23445	2SC786	20V, 0,02A, >250MHz	BF 225, BF 310, BF 314, 2SC1393...91
23446	2SC787	25V, 0,02A, 1000MHz	BF 377...378, BF 689K, BF 763, 2N2857
23447	2SC788	120MHz	BF 258...259, BF 658...659, 2N5058...59
23448	2SC789	70V, 4A, 30W, >3MHz	BD 243A, BD 537, BD 539B, BD 951
23449	2SC79	15V, 50mA, 500MHz	BF 198...199, BF 224...225, BF 505
23450	2SC790	50V, 3A, 25W, >3MHz	BD 241, BD 243, BD 535, BD 935
23451	2SC791	90/60V, 1,5A, 15W	BD 239B, 2SC779, 2SC782...783, 2SC825
23452	2SC792	400/300V, 1,5A, 50W, 10MHz	BU 126, 2SC1295, 2SD1503
23453	2SC793	100V, 7A, 60W, 9MHz	BD 245C, BDV 95, BDX 95, 2N5632...33
23454	2SC794	2SC793, 70V	BD 245A, BDV 93, BDX 93, 2N5874
23455	2SC795	250/200V, 0,1A, 9W, 180MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
23456	2SC796	40V, 0,5A, 0,5W, 230MHz	BFQ 42, BFR 98, BFS 51, BLW 16
23457	2SC797	60V, 0,5A, PQ1,3W(27MHz)	-
23458	2SC798	60V, 1,5A, PQ3,5W(27MHz)	-
23459	2SC799	80V, 1,5A, PQ3,5W(27MHz)	2SC1306, 2SC1909, 2SC2020, 2SC2029
23460	2SC80	30V, 80mA, 200MHz	BF 198...199, BF 224...225, BF 505
23461	2SC800	30V, 0,01A, 800MHz	BF 362...363
23462	2SC801	75V, 0,5A, 13W, 100MHz	BD 139, BD 230, BD 377, 2SD1200
23463	2SC802	60V, 0,5A, PQ1,3W(27MHz)	MRF 229...230, MRF 402
23464	2SC803	60V, 1,5A, PQ3,5W(27MHz)	-
23465	2SC804	15V, 0,02A, 1200MHz	BF 362...363
23466	2SC805	160MHz	BF 257...259, 2SC3245(A), 2SC3248
23467	2SC805A	2SC805, 240/150V	BF 258...259, BFR 58...59, 2SC3468
23468	2SC806	650V, 10A, 125W, 5,5MHz	BUS 12(A), BUW 26, BUW 35...36, BUX 80
23469	2SC806A	2SC806, 700/200V	BUS 12(A), BUW 26, BUW 35...36, BUX 80
23470	2SC807	500/220V, 10A, 125W, 5,5MHz	BUW 25, BUW 34, BUW 75, 2SC3046
23471	2SC807A	2SC807, 580/200V	BUW 25, BUW 34, BUW 75, 2SC3046
23472	2SC808	300/100V, 5A, 80W, 12MHz	BU 606...608, BUW 71, BUX 16A...C
23473	2SC809	25V, 20mA, 1200MHz	BF 377...378, BF 689, BF 763, 2N2857
23474	2SC810	40V, 0,3A, 0,5W, 750MHz	BFX 55, 2SC2852
23475	2SC811	35V, 0,03A, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
23476	2SC812(F)	20V, 0,1A, 0,25W, <-/27ns	BSS 11...12, BSX 27, BSY 17...18, 2N2475
23477	2SC814	30V, 0,5A, 0,4W, 180MHz	BC 337...337, BC 635, BC 637, 2SC3377
23478	2SC815(S)	60V, 0,2A, 0,25W, 200MHz	BC 174, BC 182, BC 190, BC 546, 2SC2675
23479	2SC816	60V, 1A, 1W, 140MHz	BC 140...141, 2N1990, 2N2102, 2N2405
23480	2SC817	30V, 0,02A, >550MHz	BF 377...378, BF 689, BF 763, 2N2857
23481	2SC818	160/120V, 0,1A, 0,8W, 100MHz	BF 257...259, 2N5058...59, 2SC3248
23482	2SC819	65V, 1A, 6W, 500MHz	BFS 23, BLY 34
23483	2SC820	65V, 1,5A, 10W, 500MHz	BLY 35, BLY 60, 2N3632
23484	2SC821(Z)	40V, 0,3A, PQ>1W(175MHz)	BFX 55, MRF 225, MRF 607, 2SC2852
23485	2SC822(Z)	40V, 0,5A, PQ>1,7W(175MHz)	BFS 22, BFW 46, BLY 33, 2N3924
23486	2SC823	30V, 0,06A, 1500MHz	BFR 95, BFS 50, MRF 515
23487	2SC824	50V, 0,12A, 1300MHz	BFR 95, 2N3866, 2N4428
23488	2SC825	300/300V, 2A, 30W, 15MHz	2SC779, BU 406...408, 2SD1150, 2SD1163
23489	2SC826	100V, 0,3A, 0,7W, 20MHz	BC 141, BC 300, 2N1889...90, 2N1893(A)

23490	2SC827	100V, 0,5A, 0,7W, 20MHz	BC 141, BC 300, 2N1889...90, 2N1893(A)
23491	2SC828(Z)	30V, 0,05A, 0,25W, 220MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23492	2SC828A(Z)	2SC828, 45V	BC 167, BC 182, BC 237, BC 547, 2SC1890
23493	2SC829(Z)	30V, 30mA, 230MHz	BF 240...241, BF 254...255, BF 594...595
23494	2SC830	50V, 3A, 25W, 20MHz	BD 241, BD 535, BD 935, 2N4231...33
23495	2SC830H	2SC830, 100V, 6MHz	BD 241C, BD 937, 2N4233, 2SD712
23496	2SC831	50V, 2A, PQ12W(260MHz)	BLY 35, 2N3632
23497	2SC833(N)	<2/3μs	BUW 40, BUY 63...64, 2N4240, 2N3585
23498	2SC836	30V, 0,02A, 600MHz	BF 225, BF 310, BF 314, BF 502, BF 505
23499	2SC837	30V, 0,02A, 550MHz	BF 198...199, BF 224...225, 2SC2215...16
23500	2SC838	50V, 0,05A, 250MHz	BF 240...241, BF 254...255, 2SC2210
23501	2SC839	2SC838	BF 241, BF 255, BF 495, BF 595, 2SC2210
23502	2SC84	25V, 0,2A, 0,12W, -/700ns	ASY 28...29, ASY 73...75
23503	2SC840	100/60V, 2A, 20W, 50MHz	BD 239C, BDY 72, 2N3441, 2SC2528...2529
23504	2SC840A	2SC840, 150/100V	BDY 72, 2N3441, 2SC2529, 2SD759...760
23505	2SC841(H)	36V, 0,5A, 450MHz	BFQ 42, BFR 98, BFS 51, BLW 16, BLY 61
23506	2SC842	36V, 1A, 10W, 450MHz	BLY 55, BLY 57, BLY 78, 2N3926
23507	2SC843	36V, 2A, 20W, 350MHz	BLY 36, BLY 79
23508	2SC844	40V, 0,4A, PQ1,1W(175MHz)	BFQ 42, BFR 98, BFS 51, BLW 16, BLY 61
23509	2SC845	55V, 0,4A, PQ1,4W(100MHz)	BFS 23, BLY 34
23510	2SC847	30V, 0,2A, 0,35W, 70MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23511	2SC848	2SC847, 60MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23512	2SC849	30V, 0,3A, 0,35W, 60MHz	BC 337...338, 2SC1627, 2SC2002...03
23513	2SC85	25V, 0,4A, 0,12W, -/700ns	ASY 73...75
23514	2SC850	2SC849, 50V, 0,5A, 70MHz	BC 337, 2SC1627, 2SC2002...03, 2SC3377
23515	2SC851	50V, 8A, PQ40W(50MHz)	-
23516	2SC852	45V, 0,08A, 0,5W, 1500MHz	BFR 36, BFW 16, 2SC2852
23517	2SC853	70V, 0,2A, 0,4W, 100MHz	BC 639, 2SC3665, 2SD667, 2SD1226
23518	2SC854	40V, 0,3A, PQ0,75W(175MHz)	BFR 98, BFS 51, BFX 55, BLW 16, BLY 61
23519	2SC855	40V, 0,4A, PQ0,9W(175MHz)	BFR 98, BFS 51, BFX 55, BLW 16, BLY 61
23520	2SC856	150V, 0,05A, 0,3W, 150MHz	BF 297...299, BF 422A, 2SC3467...68
23521	2SC857(H,K)	200V, 0,05A, 0,2W, 100MHz	BF 298...299, BF 422A, 2SC3467...68
23522	2SC858(FP)	20V, 0,05A, 0,1W, 140MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23523	2SC859(FP)	20V, 0,05A, 0,1W, 140MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23524	2SC86	25V, 0,4A, 0,12W, -/600ns	ASY 73...75
23525	2SC860	15V, 0,03A, 700MHz	BF 377...378, BF 689, BF 763, 2N2857
23526	2SC861	450/250V, 1A, 50W, 7MHz	BU 126, BUW 71, BUX 45, 2SC1463
23527	2SC862	650/250V, 5A, 50W, 7MHz	BU 326(A), BU 426(A), BUX 97(A,B)
23528	2SC863	60V, 25mA, 600MHz	BF 198...199, BF 224...225, BF 310...311
23529	2SC864	40V, 25mA, 600MHz	BF 198...199, BF 224...225, BF 310...311
23530	2SC865	60V, 2A, PQ4,5W(50MHz)	-
23531	2SC866	60V, 1,5A, PQ3,5W(27MHz)	2SC1306, 2SC1909, 2SC2078, 2SC2092
23532	2SC867	400/150V, 1A, 23W, 8MHz	BUW 40(A,B), TIP 48, 2SC1316, 2SD860A
23533	2SC867A	2SC867, 520V, 3A, 48W	BUT 93, TIP 75C, 2SC2826, 2SC3038
23534	2SC868	130/40V, 0,03A, 0,2W, 150MHz	BF 297...299, BF 422, 2SC2375, 2SC3467

23535	2SC868	130/40V, 0,03A, 0,2W, 150MHz	BF 297...299, BF 422, 2SC2375, 2SC3467
23536	2SC869	2SC868, 160V	BF 297...299, BF 422, BF 483, 2SC3467
23537	2SC869	2SC868, 160V	BF 297...299, BF 422, BF 483, 2SC3467
23538	2SC87	30V, 0,1A, 0,6W, 250MHz	BFW 16...17, BFX 55
23539	2SC870	30V, 0,03A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23540	2SC870	30V, 0,03A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23541	2SC871	30V, 0,03A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23542	2SC871	30V, 0,03A, 0,2W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23543	2SC872(M)	40V, 0,4A, PQ1,3W(400MHz)	BFS 50, MRF 629, 2N3948, 2SC2852
23544	2SC873	75V, 1A, 0,5W, 200MHz	BC 140...141, BSX 45...47, 2N1990
23545	2SC874	2SC873, 50V	BC 140...141, BSX 45...47, 2N1990
23546	2SC875	75V, 0,2A, 0,5W, 170MHz	BC 140...141, BC 300...301, 2N1711
23547	2SC876	2SC875, 50V	BC 140...141, BC 300...302, 2N3053
23548	2SC877	40V, 0,2A, 0,3W, <20/35ns	BSS 11, BSX 19...20, 2N2368...69(A)
23549	2SC878	2SC877, <12/22ns	BSS 11, BSX 19...20, 2N2368...69(A)
23550	2SC879	60V, 1A, 0,8W, <70/100ns	BSS 13, BSS 27, BSV 77, 2N5189
23551	2SC88	2SC87, 120V	BC 300, BF 257, BSY 56, 2N1893(A)
23552	2SC880	60V, 1A, 0,8W	BSS 13, BSS 27, BSV 77, 2N5189
23553	2SC881	60V, 0,2A, 0,4W, 150MHz	BC 337A, BC 637, 2SC3377, 2SC3939
23554	2SC882	150/100V, 2A, 25W, 30MHz	-
23555	2SC883	90/70V, 2A, 25W, 30MHz	-
23556	2SC884	80V, 2A, 15W, 30MHz	BDV 10...12, 2N4233, 2SC3252
23557	2SC885	330/100V, 7A, 50W, -/<9μs	BU 104, BU 606...608, BUX 18(A...C)
23558	2SC886	2SC885, 270/90V	BU 104, BU 606...608, BUX 18(A...C)
23559	2SC887	2SC885, 210/80V	BU 104, BU 606...608, BUX 18(A...C)
23560	2SC888	2SC885, 150/70V	BU 104, BU 606...608, BUW 86...87
23561	2SC889	2SC885, 90/60V	BU 104, BU 606...608, BUW 86...87
23562	2SC89(H)	25V, 0,4A, 0,12W, -/380ns	ASY 73...75
23563	2SC890	40V, 0,4A, PQ1,3W(500MHz)	BFS 50, MRF 629, 2N3948
23564	2SC891	40V, 0,6A, PQ4W(500MHz)	BLW 43, BLW 80, 2N5945
23565	2SC892	40V, 1,2A, PQ8W(500MHz)	BLU 97, BLX 68, BLY 53
23566	2SC893	100V, 0,5A, 12W, 20MHz	BD 139, BD 230, 2SD1382, 2SD1563
23567	2SC894	25V, 0,1A, 0,1W, 200MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23568	2SC895	150/90V, 2,5A, 23W, 20MHz	BD 241D, 2SD608(A), 2SD772(A,B), 2SD1138
23569	2SC896	55V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
23570	2SC897	150/90V, 7A, 60W, 15MHz	BD 245D, 2N3442, 2SD551, 2SD732, 2SD1046
23571	2SC898	2SC897, 150/110V, 80W	BD 245D, 2N3442, 2SD551, 2SD732, 2SD1046
23572	2SC899	50V, 0,05A, 0,25W, 250MHz	BC 184, BC 414, BC 550, 2SC1775(A)
23573	2SC90(H)	25V, 0,4A, 0,12W, -/380ns	ASY 73...75
23574	2SC900	30V, 0,02A, 0,25W, 100MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
23575	2SC901	200V, 5A, 50W, 50MHz	BU 104, BU 606...608, 2SD1154
23576	2SC901A	2SC901, 250V	BU 104, BU 606...608, 2SD1154
23577	2SC902	150/80V, 10A, 75W, -/<4μs	BDW 12, 2SD551, 2SD733, 2SD1047
23578	2SC903	35V, 0,3A, 0,2W, 150MHz	BC 337, BC 635, 2SC3377, 2SC3939
23579	2SC903	35V, 0,3A, 0,2W, 150MHz	BC 337, BC 635, 2SC3377, 2SC3939



23580	2SC904	2SC903, 50V	BC 637, 2SD667, 2SC3377, 2SC3939
23581	2SC904	2SC903, 50V	BC 637, 2SD667, 2SC3377, 2SC3939
23582	2SC905	2SC903, 65V	BC 637, 2SD667, 2SD1226, 2SD1485
23583	2SC905	2SC903, 65V	BC 637, 2SD667, 2SD1226, 2SD1485
23584	2SC906	50V, 0,5A, 0,6W, 70MHz	BC 337, BC 637, 2SC3377, 2SC3939
23585	2SC907(H)	40V, 0,1A, 0,2W, 240MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
23586	2SC907A(AH)	2SC907, 60(AH70)V	BC 174, BC 182, BC 190, BC 546, 2SC3245
23587	2SC908	40V, 0,5A, PQ1,2W(500MHz)	BFS 50, MRF 629, 2N3948
23588	2SC909	40V, 0,5A, PQ3,5W(500MHz)	BLW 43, BLW 80, 2N5945
23589	2SC91(H)	25V, 0,4A, 0,12W, -/360ns	ASY 73...75
23590	2SC910	40V, 1A	BLU 97, BLX 68, BLY 53
23591	2SC911(A)	40V, 0,5A, PQ1,4W(500MHz)	BLX 66
23592	2SC912(M)	30V, 0,1A, 0,15W, <25/140ns	BSW 41, BSY 63, 2N4123, 2N2221...22
23593	2SC913		BSS 10, BSX 19...20, BSX 26, 2N3261
23594	2SC914(A)	2SC913, <80/86ns	BSS 10, BSX 19...20, BSX 26, 2N3261
23595	2SC915(A)	2SC913, 30V	BSS 10, BSX 19...20, BSX 26, 2N3261
23596	2SC916	100/70V, 1,5A, <63/160ns	BD 139, BD 230, BD 379, 2SD1177...78
23597	2SC917	40V, 0,05A, 550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
23598	2SC918	20V, 0,03A, 400MHz	BF 225, BF 310, BF 314, 2SC1393...94
23599	2SC92	100V, 2A, PQ9W(100MHz)	-
23600	2SC920	50V, 0,03A, 250MHz	BF 240...241, BF 254...255, BC 594...595
23601	2SC921	25V, 0,01A, 650MHz	BF 225, BF 310, BF 314, 2SC1393...94
23602	2SC922	30V, 0,02A, >400MHz	BF 241, BF 255, BF 310, BF 314, 2SC829
23603	2SC923	40V, 0,1A, 0,25W, 100MHz	BC 167, BC 183, BC 237, BC 547, 2SC3112
23604	2SC924	30V, 0,05A, 0,25W, 250MHz	BF 240...241, BF 254...255, BF 594...595
23605	2SC925	30V, 0,05A, 0,25W, 250MHz	BC 168, BC 183, BC 238, BC 548, 2SC2390
23606	2SC926(A-4,A-5)	0,1..0,25W	BF 298...299, BF 422, BF 483, 2SC3468
23607	2SC927	30V, 0,02A, ZF, 500MHz	BF 225, BF 310, BF 314, BF 502, 2SC1856
23608	2SC928	30V, 0,02A, ZF, 500MHz	BF 225, BF 310, BF 314, BF 502, 2SC1856
23609	2SC929(NP,SPA)	15..30V, 0,03A, 300MHz	BF 240, BF 254, BF 494, BF 594, 2SC829
23610	2SC93	2SC92, 80V	-
23611	2SC930(NP,SP)	15..30V, 0,03A, 300MHz	BF 241, BF 255, BF 495, BF 595, 2SC829
23612	2SC933	50V, 0,3A, 0,2W, 500MHz	BSV 59, BSW 41, BSY 63, 2N2221...22
23613	2SC933NP,SPA	2SC933, 0,3W	2SC933
23614	2SC934	2SC933, 20V	BSV 59, BSW 41, BSY 63, 2N2221...22
23615	2SC934NP,SPA	2SC934, 0,3W	2SC934
23616	2SC935	300/300V, 2,5A, 50W, 5MHz	BU 104, BU 126, BU 606...608, 2SD1154
23617	2SC936(A)	7MHz	BU 204...206, 2SC1101, 2SC1167, 2SD1095
23618	2SC937	1200/500V, 2,5A, 22W, 4MHz	BU 204...206, 2SC1132, 2SD1097...1098
23619	2SC938	60V, 0,2A, 0,25W, 100MHz	BC 337A, BC 637, 2SC3939, 2SD1226
23620	2SC939	150V, 5A, 50W, 20MHz	BU 104, BU 606...608, 2SD916
23621	2SC94	2SC92	-
23622	2SC940	2SC939, 200V, 9A	BU 106, BU 109, BU 124(A)
23623	2SC941(TM)	35V, 0,02A, 0,2W, 120MHz	BF 240...241, BF 254...255, BF 594...595
23624	2SC943	60V, 0,2A, 0,3W, 220MHz	BC 174, BC 182, BC 190, BC 546, 2N3904



23625	2SC944(S)	20/300ns	BC 174, BC 182, BC 190, BC 546, 2N3904
23626	2SC944(S)	20/300ns	BC 174, BC 182, BC 190, BC 546, 2N3904
23627	2SC945(T)	60V, 0,1A, 0,25W, 250MHz	BC 174, BC 182, BC 190, BC 546, 2SD767
23628	2SC945L	2SC945	2SC1775(A), 2SC2674...75, 2SC3378
23629	2SC947(Z)	25V, 15mA, 650MHz	BF 377...378, BF 689, BF 763, 2N2857
23630	2SC948(Z)	25V, 15mA, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
23631	2SC949	45V, 0,05A, 0,2W, 200MHz	BC 184, BC 413...414, BC 550, 2SC2390
23632	2SC95	140V, 0,1A, 0,8W, 140MHz	BF 257...259, BF 657...659, 2N5058...59
23633	2SC950	30V, 0,1A, 0,3W, 100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
23634	2SC951	2SC950, 60V	BC 174, BC 182, BC 190, BC 546, 2SD767
23635	2SC952	2SC950, 100V	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
23636	2SC953	30V, 0,2A, 0,6W, 90MHz	BC 337...338, BC 635, BC 637, 2SC3377
23637	2SC954	60V, 0,4A, 0,6W, 90MHz	BC 337A, BC 637, 2SC3939, 2SD1226
23638	2SC955	20V, 0,05A, 0,15W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SC1890
23639	2SC956	50V, 0,05A, 0,15W, 200MHz	BC 167, BC 182, BC 237, BC 547, 2SC1890
23640	2SC957	30V, 0,1A, 0,36W, 700MHz	BF 225, BF 310, BF 311, BF502, 2SC1856
23641	2SC959(S)	120V, 0,7A, 0,7W, 100MHz	BC 300, BSY 55...56, 2N1893(A), 2N2102
23642	2SC960(S)	2SC959	2SC2384, 2SC2690A, 2SD1382
23643	2SC961	120/90V, 7A, 60W, 13MHz	BD 245C, BD 550, 2N5633, 2SD1046
23644	2SC962	2SC961, 100/80V	BD 245C, BDV 95, BDX 95, 2N5632...33
23645	2SC963	B70	BC 168, BC 183, BC 238, BC 548, 2SC1860
23646	2SC964	2SC963, B100	BC 168, BC 183, BC 238, BC 548, 2SC1890
23647	2SC965	2SC963, 45V, -/<300ns	BC 167, BC 182, BC 237, BC 547, 2N3904
23648	2SC966	30V, 0,2A, 0,5W, 70MHz	BC 337...338, BC 635, BC 637, 2SC3377
23649	2SC967	30V, 0,5A, 0,5W, 70MHz	BC 337...338, BC 635, BC 637, 2SC3377
23650	2SC968	50V, 0,5A, 0,5W, 70MHz	BC 337, BC 637, 2SC3939, 2SD1226
23651	2SC969	50V, 0,2A, 0,5W, 60MHz	BC 337, BC 637, 2SC3377, 2SD1226
23652	2SC97	<50/150ns	BSS 13, BSV 77, 2N2218...19, 2N5189
23653	2SC970	50V, 0,5A, 0,5W, 70MHz	BC 337, BC 637, 2SC3939, 2SD1226
23654	2SC971	50V, 0,5A, 1W, 70MHz	BC 337, BC 637, BC 639, 2SD1225...26
23655	2SC972	70V, 0,4A, 0,6W, 80MHz	BC 140...141, BC 300...301, 2N1711
23656	2SC973(A)	40V, 0,5A, PQ4W(500MHz)	BLW 43, BLW 80, 2N5945
23657	2SC974	40V, 1A, PQ6W(500MHz)	BLU 97, BLX 68, BLY 53
23658	2SC975(A)	35V, 1,5A, PQ8W(500MHz)	BLW 44, BLW 81, 2N5946
23659	2SC976	55V, 0,4A, PQ1,1W(1GHz)	BFT 99, BLV 91, MRF 817
23660	2SC977	55V, 0,6A, PQ3W(1GHz)	BLU 99
23661	2SC978	55V, 1,2A, PQ5,5W(1GHz)	-
23662	2SC979	25/430ns	BC 174, BC 182, BC 190, BC 546, 2N2222A
23663	2SC979A	2SC979, 100V	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
23664	2SC97A	2SC97, 80V, <30/90ns	BSV 95, BSW 39, 2N3735
23665	2SC98	B>30	BSV 89...92, BSX 92...93, 2N2368...69(A)
23666	2SC980(G,GTM)	25/630ns	BC 174, BC 182, BC 190, BC 546, 2N2222A
23667	2SC980A(G,GTM)	2SC980, 90V	2SC2240, 2SC2459, 2SC3245(A), 2SC3248
23668	2SC981	100V, 5A, 25W, 10MHz	BD 243C, BD 543C, BD 953, 2SD613
23669	2SC982(TM)	40V, 0,3A, 0,4W, B>5000	BC 517, BC 617, MPSA 25...29

23670	2SC983	120MHz	BF 298...299, BF 422, BF 483, 2SC3468
23671	2SC984	50V, 0,5A, 0,35W, 230MHz	BC 337, BC 637, 2SC3939, 2SD1226
23672	2SC984H	2SC984, 100V	BC 639, BCX 24, 2SC4414, 2SD667, 2SD1226
23673	2SC985(A)	20V, 0,04A, 3,2GHz	BFQ 59...60, BFQ 70...71, BFT 97, 2N5762
23674	2SC986	35V, 0,2A, 2,5GHz	BFT 98, BFQ 68
23675	2SC987(A)	20V, 0,03A, 4,5GHz	BFQ 69, BFQ 71, BFQ 85, BFR 14, BFR 91
23676	2SC988(A,B)	20V, 0,03A, 3GHz	BFR 15, BFT 66...67, BFS 55, 2N5650...52
23677	2SC989	20V, 0,05A, 3GHz	BFT 65, BFQ 72
23678	2SC99	2SC98, B>40	BSV 89...92, BSX 92...93, 2N2368...69(A)
23679	2SC990	50V, 2A, PQ13,4W(400MHz)	BLW 94, BLX 94, MRF 323
23680	2SC991	36V, 0,4A, PQ1,3W(175MHz)	BFQ 42, BFS 51, BFR 98, BLW 16, BLY 61
23681	2SC992	36V, 0,6A, PQ2,5W(175MHz)	BFS 22, BFW 46, BLY 33, MRF 237, 2N3924
23682	2SC993	25V, 0,2A, 0,2W, 400MHz	BSW 41, BSY 62...63, 2N706A, 2N4124
23683	2SC994	36V, 0,1A, PQ>0,95W(175MHz)	BFW 16...17, BFX 55
23684	2SC995	100MHz	BF 259, BF 659, BFR 59, BFS 89, 2N5058
23685	2SC996	2SC995	BF 417, BF 459, BF 617, BF 758
23686	2SC997	40V, 25mA, 600MHz	BF 198...199, BF 224...225, BF 310...311
23687	2SC998	40V, 0,4A, PQ>1W(175MHz)	BFQ 42, BFS 51, BFR 98, BLW 16, BLY 61
23688	2SC999	1500/700V, 1,5A, 50W, 1MHz	BU 204...206, 2SD575, 2SD818
23689	2SC999A	4MHz	BU 204...206, 2SD575, 2SD818
23690	2SD100	32V, 0,4A, 0,25W	AC 127, AC 176, AC 187, 2SD72, 2SD352
23691	2SD1000	60V, 0,7A, 110MHz	BCX 56, 2SC2881, 2SD1005...07, 2SD1418
23692	2SD1001	80V, 0,3A, 140MHz	2SC2882, 2SC3438, 2SD875, 2SD968(A)
23693	2SD1002	45V, 1A, 160MHz	BCX 54...56, 2SC3444, 2SD874A, 2SD1368
23694	2SD1003	2SD1002, 60V	BCX 55...56, 2SC3444, 2SD874A, 2SD1368
23695	2SD1004	2SD1002, 100V	BCX 56, 2SD1005, 2SD1368, 2SD1418...19
23696	2SD1005	100V, 1A, 100MHz	BCX 56, 2SC2881, 2SD1368, 2SD1418...19
23697	2SD1006	100V, 0,7A, 90MHz	BCX 56, 2SC2881, 2SD1368, 2SD1418...19
23698	2SD1007	2SD1006, 120V	2SC2881, 2SC4373, 2SD1418...19
23699	2SD1009	150/150V, 0,05A, 160MHz	-
23700	2SD100A	2SD100, 45V	-
23701	2SD101	80V, 0,6A, 0,25W	-
23702	2SD1010	50V, 0,05A, 200MHz	2SC3495, 2SC3071, 2SD1424, 2SD2073
23703	2SD1011	100V, 0,02A, 200MHz	2SC3495, 2SC3071, 2SD1511
23704	2SD1012	20V, 0,7A, 0,25W, 250MHz	2SD1207, 2SD1616, 2SD1835
23705	2SD1014	50/50/50V, 2A, 0,9W, B>150	-
23706	2SD1015	140/50/50V, 2A, 0,9W, B>150	-
23707	2SD1016	1500/600V, 7A, 50W	BU 2508A, 2SC3027...28, 2SC3686, 2SD822
23708	2SD1017	250/250V, 2A, 50W	TIP 51...55, 2SC2809
23709	2SD1018	2SD1017, 4A, 80W	TIP 51...54, 2SC2624, 2SC3083
23710	2SD102	3/10µs	BD 241C, BD 243C, BD 539D, BD 939
23711	2SD1020	30V, 0,7A, 0,35W, 170MHz	2SC4483, 2SC4485, 2SD1207, 2SD1616
23712	2SD1021	30V, 1A, 0,35W, 100MHz	BC 337...338, BC 635, BC 637, 2SD1225
23713	2SD1022	100/100V, 5A, 30W, B>1500	BD 649, BD 901, BDW 23C, BDW 63C
23714	2SD1023	200/200V, 5A, 30W, B>1500	2SD930, 2SD1025

23715	2SD1024	100/100V, 8A, 50W, B>1500	BD 649, BD 901, BDW 73C, BDX 53C
23716	2SD1025	200/200V, 8A, 50W, B>1500	2SD1141, 2SD1756
23717	2SD1026	100/100V, 15A, 100W, B>1500	BDV 67A, BDW 83C, 2SD1296, 2SD1299
23718	2SD1027	200/200V, 15A, 100W, B>1500	2SD1515
23719	2SD1029	60V, 4A, 40W	BD 243A, BD 535, BD 949, 2SC3179
23720	2SD1029K	2SD1029, 100V	BD 243B, BD 537, BD 951, 2SD1528
23721	2SD103(M)	2SD102, 80/50V	BD 241B, BD 243B, BD 539B, BD 937
23722	2SD1030	2SD1010, SMD	2SC3689
23723	2SD1031	120V, 6A, 50W, B4000	BD 651, BDT 21, BDW 73D, BDX 53D
23724	2SD1032	60V, 4A, 60W, 0,2/1,4µs	BD 245A, BDV 91, 2SC2681, 2SD895...896
23725	2SD1032A	2SD1032, 80V	BD 245B, BDV 93, 2SC2681, 2SD895...896
23726	2SD1032B	2SD1032, 100V	BD 245C, BDV 95, 2SC2681, 2SD895...896
23727	2SD1033	200/150V, 2A, 20W, 10MHz	2SD1557, 2SD610, 2SD1138, 2SD1250(A)
23728	2SD1035	1,5MHz	-
23729	2SD1036	1,5MHz	-
23730	2SD1037	1,5MHz	-
23731	2SD1038	1,5MHz	-
23732	2SD1039	2SD1035	-
23733	2SD104	20V, 0,4A, 0,15W, B>60	AC 127, AC 176, AC 187, 2SD72, 2SD352
23734	2SD1040(A)	2SD1036, 120W	-
23735	2SD1041	2SD1037, 200W	-
23736	2SD1042	2SD1038	-
23737	2SD1042	2SD1038	-
23738	2SD1043	430V, 5A, 80W, B1000	BU 322(A), BU 921...922, 2SD1461
23739	2SD1044	100V, 6A, 60W, B>700	TIP 142, 2SD1170, 2SD1230
23740	2SD1044A	2SD1044, 170V	2SD921, 2SD1090, 2SD1122...1123
23741	2SD1045	30V, 3A, 0,9W, 200MHz	2SD1347, 2SD1507, 2SD1617, 2SD1864
23742	2SD1046	150V, 8A, 80W, 15MHz	BD 245D, 2SC2837, 2SC3263, 2SD751
23743	2SD1047	160V, 12A, 100W, 15MHz	BD 745F, 2SC2987A, 2SC3263
23744	2SD1048	2SD1012, SMD	BCW 65...66, 2SC3265
23745	2SD1049	120V, 25A, 80W	BD 249C
23746	2SD105	2SD104, B>35	AC 127, AC 176, AC 187, 2SD72, 2SD352
23747	2SD1050(K)	100V, 10A, 80W, B>1000	2SD851...852, 2SD1087, 2SD1129
23748	2SD1051	50V, 1,5A, 1W, 150MHz	MPS 650...651, 2SC3328, 2SD619, 2SD1207
23749	2SD1052	50V, 3A, 30W, B>250	2SC1983, 2SD1943
23750	2SD1052A	2SD1052, B>400	2SC1983, 2SD1943
23751	2SD1053	400V, 1A, 15W	2SC3362...3363, 2SC3632, BD 410
23752	2SD1054	300/250V, 3A, 80W	BU 126, TIP51...54, 2SC1463, 2SD632
23753	2SD1055	40V, 2A, 0,75W, 100MHz	MPS 650, 2SC3328, 2SD1207, 2SD1227
23754	2SD1056	600/600V, 50A, 400W, B>100	-
23755	2SD1059	100V, 6A, 40W	BD 243C, BD 543C, BD 801, 2SD550
23756	2SD1060	60V, 5A, 30W, 30MHz	2SC3253, 2SC3258, 2SD1236L
23757	2SD1061	60V, 7A, 40W, 10MHz	2SC3254, 2SD1237L
23758	2SD1062	60V, 12A, 40W, 10MHz	2SC3345, 2SD1212
23759	2SD1063	60V, 7A, 60W, 10MHz	2SD1187

23760	2SD1064	60V, 12A, 80W, 10MHz	2SC3256, 2SD1238L
23761	2SD1065	60V, 15A, 90W, 10MHz	2SC3256, 2SD1840
23762	2SD1067	600/600, 30A, 200W, B200	-
23763	2SD1068	1000V, 10mA, 25W, 8.5MHz	2SC4256, 2SC4451
23764	2SD1069	300/150V, 7A, 40W, 18MHz	BU 406D...408D, 2SC3174, 2SC3176
23765	2SD107	80/60V, 5A, 50W, B>1000	BDX 63A, MJ 1001, 2N6056, 2SD1124
23766	2SD107	80/60V, 5A, 50W, B>1000	BDX 63A, MJ 1001, 2N6056, 2SD1124
23767	2SD1070	100V, 10A, 60W	BD 245C, BD 545C, BDV 95, 2SC2681
23768	2SD1071	450/450V, 6A, 40W, B>500	BU 910...912, 2SD798...99, 2SD1245
23769	2SD1072	450/450V, 5A, 60W, B>500	BU 911...912, 2SD978, 2SD987, 2SD1245
23770	2SD1073	300/250V, 4A, 40W, B>1000	BU 910...912, 2SD816, 2SD978, 2SD987
23771	2SD1074	120V, 1A, 10W, B160	2SC2983, 2SC4134, 2SD1283...84, 2SD1220
23772	2SD1075	2SD1074, B100	2SC2983, 2SC4134, 2SD1283...84, 2SD1220
23773	2SD1076(L,S)	25V, 2.5A, 20W	2SC3073, 2SC3386, 2SD1221, 2SD1802
23774	2SD1077(L,S)	2SD1076, 35V	2SC3073, 2SC3386, 2SD1221, 2SD1802
23775	2SD1078(L,S)	50V, 2A, 20W	2SC3076, 2SD1281...1282, 2SD1801
23776	2SD1079(L,S)	2SD1078, 80V	2SC3386, 2SD1281...82, 2SD1815...16
23777	2SD108	2SD107, 80/40V	BDX 63A, MJ 1001, 2N6056, 2SD1124
23778	2SD108	2SD107, 80/40V	BDX 63A, MJ 1001, 2N6056, 2SD1124
23779	2SD1080(L,S)	180/120V, 1.5A, 20W	2SC4027, 2SD1033, 2SD1557
23780	2SD1081(L,S)	2SD1080, 180/160V	2SC4027, 2SD1033, 2SD1557
23781	2SD1082(L,S)	2SD1080, 200/160V	2SD1033, 2SD1557
23782	2SD1083(L,S)	150V, 2A, 10W, B>150	2SD1033, 2SD1557
23783	2SD1084	500/400V, 50A, 400W, B300	-
23784	2SD1085(K)	300/300V, 3A, 40W, B3000	2SD816, 2SD1073, BU 806...807
23785	2SD1087	100V, 15A, 100W, B3000	2SD829, 2SD852, 2SD1129...1130
23786	2SD1088	300/250V, 6A, 30W, B5000	BU 910...912, 2SD835, 2SD1114, 2SD1307
23787	2SD1089	350/350V, 6A, 30W, B1000	BU 910...912, 2SD835, 2SD1114, 2SD1307
23788	2SD1090	200V, 5A, 80W, B>500	-
23789	2SD1091	170V, 4A, 40W, B5000	2SC3186, 2SD930, 2SD1023, 2SD1121
23790	2SD1092	55V, 4A, 80W, B>500	2SC2825
23791	2SD1093	1000/400V, 7A, 50W, <5/11μs	BU 536, BU 546, BU 902...903
23792	2SD1094	1000/400V, 10A, 50W, <5/21μs	BU 626A
23793	2SD1095	1200V, 1.5A, 50W	BU 204, 2SD1097, 2SC1132, 2SC1167
23794	2SD1096	25V, 1A, 10W	2SD1078...79, 2SD1295, 2SD1801
23795	2SD1097	1200V, 2.5A, 50W	BU 204, 2SC1132, 2SC1922, 2SD818
23796	2SD1098	1200V, 3A, 50W	BU 207, 2SC1875, 2SD850, 2SD1495
23797	2SD1099	1200V, 5A, 50W	BU 207, 2SC2928, 2SD954, 2SD1496
23798	2SD11	25V, 0.3A, 0.15W, 2.5MHz	ASY 73...75
23799	2SD110(M)	3/12μs	BDX 11, 2N3442, 2SD551, 2SD732...733
23800	2SD110(M)	3/12μs	BDX 11, 2N3442, 2SD551, 2SD732...733
23801	2SD1100	20V, 2A, 0.9W, B400	2SC3225, 2SC4389, 2SD1014, 2SD1146
23802	2SD1101	25V, 0.7A	BCW 65...66, 2SC3265
23803	2SD1102	1200V, 4A, 50W	BU 207, 2SC1358, 2SC3642, 2SD1495
23804	2SD1103	1200V, 5A, 50W	BU 207, 2SC2928, 2SD954, 2SD1496

23805	2SD1104	1200V, 6A, 50W	BU 508A, 2SC3025, 2SD821, 2SD1497
23806	2SD1105	120V, 15A, 200W, 1MHz	BDW 10, 2N5630...31, 2SC1584, 2SD752
23807	2SD1106	450/450V, 50A, 400W, B300	-
23808	2SD1107	500/500V, 50A, 400W, B300	-
23809	2SD1109	100/100V, 6A, 70W	BD 245C, BDV 95, 2SC2681, 2SC2837
23810	2SD1109A	2SD1109, 120/120V	BD 245C, 2SC2681, 2SC2706, 2SC2837
23811	2SD111(M)	2SD110, 100V	BD 317, BDW 21C, BDY 53, 2N5632...33
23812	2SD111(M)	2SD110, 100V	BD 317, BDW 21C, BDY 53, 2N5632...33
23813	2SD1110	120/120V, 7A, 80W, 15MHz	BD 245C, 2SC2681, 2SC2706, 2SC2837
23814	2SD1110A	2SD1110, 130/130V	BD 245D, 2SC2706, 2SD731, 2SD1046
23815	2SD1111	80V, 0,7A, 0,6, B25000	BC 618, BC 877, BC 879, BSR51...52
23816	2SD1112	300/300V, 0,2A, 10W, 70MHz	2SC3129, 2SC3588, 2SC3805, 2SC4003
23817	2SD1113(K)	300/300V, 6A, 40W, B>500	2SD971, 2SD991, 2SD1071, 2SD1088...89
23818	2SD1114(K)	400/300V, 6A, 50W, B>500	BU 910...912, 2SD835, 2SD1245
23819	2SD1115(K)	400/300V, 3A, 40W, B>500	2SD977...978, 2SD987, 2SD1072
23820	2SD1116	400/300V, 3A, 40W, B>500	2SD977...978, 2SD987, 2SD1072
23821	2SD1117	40V, 10A, 50W	BD 705, BD 743, BD 805, BD 905, 2SD1062
23822	2SD1117A	2SD1117, 80V	BD 709, BD 743B, BD 809, BD 909
23823	2SD1118	80V, 10A, 50W, B>300, <1/5µs	BDT 63A, BDT 65A, BDX 33B, 2SD2024
23824	2SD1119	40V, 3A, 150MHz	2SC4521, 2SD1624, 2SD2150
23825	2SD1120	200/150V, 2A, 40W, B1000	2SC3186, 2SD930, 2SD1023, 2SD1121
23826	2SD1121	200/200V, 3A, 50W, B1000	2SC3186, 2SD930, 2SD1023, 2SD1025
23827	2SD1122	200/150V, 5A, 80W, B1000	2SD921, 2SD1090, 2SD1123
23828	2SD1123	200/150A, 100W, B1000	-
23829	2SD1124	80V, 8A, 80W, B1000	BDV 65A...C, TIP 141...142
23830	2SD1125	80V, 12A, 100W, B1000	BDV 65A...C, BDV 67A...D, BDW 83B...D
23831	2SD1126(K)	120/120V, 10A, 50W, B>1000	BDT 63C, BDT 65C, BDX 33D, 2SD1607
23832	2SD1127(K)	120V, 10A, 50W, B>1000	BDT 63C, BDT 65C, BDX 33D, 2SD1607
23833	2SD1128	150/100V, 5A, 30W, B5000	BDX 53F, 2SD830, 2SD1169, 2SD1500
23834	2SD1129(K)	100V, 15A, 100W, B>1000	2SD829, 2SD852, 2SD1087
23835	2SD113(M)	3/10µs	BDW 30, BDY 29, MJ 802, 2SD797
23836	2SD113(M)	3/10µs	BDW 30, BDY 29, MJ 802, 2SD797
23837	2SD1130(K)	100V, 20A, 100W, B>1000	-
23838	2SD1131	50V, 4A, 40W, 8MHz	BD 243A, BD 535, BD 949, 2SC3179
23839	2SD1132	2SD1131, 60V	BD 243A, BD 535, BD 949, 2SC3179
23840	2SD1133	70/50V, 4A, 40W, 7MHz	BD 243A, BD 537, BD 951, 2SC3179
23841	2SD1134	2SD1133, 70/60V	BD 243A, BD 537, BD 951, 2SC3179
23842	2SD1135	100V, 4A, 40W, 10MHz	BD 243C, BD 539C, BD 953, 2SD712
23843	2SD1136	200/80V, 4A, 30W	BU 406...408, 2SD823, 2SD1150, 2SD1159
23844	2SD1137	100V, 4A, 40W	BD 243C, BD 539C, BD 953, 2SD712
23845	2SD1138	200/150V, 2A, 30W	BD 239F, 2SC2660, 2SD610, 2SD760
23846	2SD1139	200/150V, 2A, 30W	BD 239F, 2SC2660, 2SD610, 2SD760
23847	2SD114(M)	2SD113, 70V	BDW 30, BDY 29, MJ 802, 2SD797
23848	2SD114(M)	2SD113, 70V	BDW 30, BDY 29, MJ 802, 2SD797
23849	2SD1140	30V, 1,5A, 0,9W, B7000	2SD1536, 2SD1786, 2SD1861, 2SD2046



23850	2SD1141(K)	400/300V, 6A, 40W, B3000	BU 910...912, 2SD835, 2SD1114, 2SD1245
23851	2SD1142	1500V, 3,5A, 50W	BU 208A, BU 706, 2SD849...850, 2SD1495
23852	2SD1143	1500V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD954
23853	2SD1145	60V, 5A, 0,9W, 120MHz	2SC4482, 2SD2243
23854	2SD1146	50V, 2A, 0,9W, B300	2SC3328, 2SC4145, 2SD1207, 2SD2182
23855	2SD1147	120V, 5A, 30W, B5000	BD 651, BDT 21, BDW 63D, BDW 73D
23856	2SD1148	140/140V, 10A, 100W	BD 245D, 2SC2706, 2SC2987(A), 2SD1047
23857	2SD1149	2SD1011, SMD	2SC3651
23858	2SD1150	350/90V, 6A, 40W	BU 406, BU 408, 2SC3175, 2SC3591
23859	2SD1151	1500V, 5A, 95W, B40..150	-
23860	2SD1152	55V, 0,1A, 0,2W	BC 167, BC 182, BC 237, BC 547, 2SD767
23861	2SD1153	80V, 1,5A, 0,9W, B>4000	2SD1579, 2SD1978, 2SD1981, 2SD2067
23862	2SD1154	350/200V, 7A, 50W	BU 104, BU 606, BU 608
23863	2SD1155	400/400V, 50A, 300W, B400	-
23864	2SD1156	100/80V, 5A, 58W	2N5002, 2N5004, 2N5284...5285
23865	2SD1157	80V, 4A, 25W, B400	2SC2315...16, 2SC2491
23866	2SD1158	80V, 8A, 40W, B400	2SC4024, 2SD1947
23867	2SD1159	200/60V, 4,5A, 40W, 10MHz	BU 406...408, 2SC3189, 2SC3589, 2SD1163
23868	2SD116	100/40V, 7A, 75W	BD 245C, BDV 95, BDX 85, 2N5632...33
23869	2SD116	100/40V, 7A, 75W	BD 245C, BDV 95, BDX 85, 2N5632...33
23870	2SD1160	Rbe800Ohm, 50V, 2A, 10W	-
23871	2SD1161	30V, 0,03A	-
23872	2SD1162	500V, 5A, 40W, B>400, 1/18µs	BU 912, 2SD798...799, 2SD987, 2SD1245
23873	2SD1163	300/120V, 7A, 40W	BU 406...408, 2SC3173, 2SC3590
23874	2SD1163A	2SD1163, 350/150V	BU 406...408, 2SC3175, 2SC3591
23875	2SD1164(Z)	150V, +-1,5A, 10W, B>2000	2SC4339, 2SD985...986
23876	2SD1168	1500/800V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD954
23877	2SD1169	150/80V, 5A, 40W, B10000	2SD1128
23878	2SD117	2SD116, 150/80V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
23879	2SD117	2SD116, 150/80V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
23880	2SD1170	120V, 6A, 70W, B4000	2SD921, 2SD923, 2SD1090, 2SD1210
23881	2SD1171	1500V, 5A, 50W	BU 208D, BU 508D, 2SC3481...82, 2SC3681
23882	2SD1172	1500V, 5A, 65W	BU 208D, BU 508D, 2SC3481...82, 2SC3681
23883	2SD1173	1500V, 5A, 70W	BU 508D, 2SC3481...82, 2SC3681, 2SD953
23884	2SD1174	1500V, 5A, 95W	BU 508D, 2SC3481...82, 2SC3681, 2SD953
23885	2SD1175	1500V, 5A, 100W	BU 508D, 2SD953, 2SC3481...82, 2SC3681
23886	2SD1176	60V, 8A, 45W, B4000	BD 645, BD 897, BDW 73A, BDX 53A
23887	2SD1176A	2SD1176, 80V	BD 647, BD 899, BDW 73B, BDX 53B
23888	2SD1177	100/60V, 2A, 20W, 230MHz	BD 379, BD 791, BDX 35, MJE 243...244
23889	2SD1178	2SD1177, 100/80V	BD 379, BD 791, BDX 35, MJE 243...244
23890	2SD1179	120/100V, 1,5A, 20W	2SC2481, 2SC2690(A), 2SC3117, 2SD669
23891	2SD118	130V, 7A, 100W, 2MHz	BD245D, BDX11, 2N3442, 2SD551, 2SD732
23892	2SD118	130V, 7A, 100W, 2MHz	BD245D, BDX11, 2N3442, 2SD551, 2SD732
23893	2SD1180	2SD1179, 120/110V	2SC2481, 2SC2690(A), 2SC3117, 2SD669
23894	2SD1181	180V, 1,5A, 10W	2SC2238A,B, 2SC2344, 2SD608A, 2SD1138



23895	2SD1182	2SD1181, 50W	2SC2660, 2SD760, 2SD772A,B
23896	2SD1183	1200/800V, 3A, 50W, <2/11μs	BU 546, BU 903, 2SC1875, 2SD1098
23897	2SD1184	1500/800V, 3A, 50W, <2/11μs	BU 208A, BU 706, BU 908, 2SC3023
23898	2SD1185	1200/800V, 5A, 50W, <2/11μs	BU 546, BU 706, BU 903, 2SD1099, 2SD1103
23899	2SD1186	1200/800V, 5A, 50W, <2/11μs	BU 208A, BU 706, BU 908, 2SC2928
23900	2SD1187	100/80V, 10A, 80W	2SD1064, 2SD1238L, 2SD1840
23901	2SD1189(F)	40V, 2A, 5W, 100MHz	2SD1682...1683
23902	2SD119	2SD118, 100V	BDW 21C, BDX 95, 2N3055, 2N5632...33
23903	2SD119	2SD118, 100V	BDW 21C, BDX 95, 2N3055, 2N5632...33
23904	2SD1190	70V, 4A, 30W, 20MHz, B5000	BD 717, BDW 23B, BDW 53B, BDW 63B
23905	2SD1191	2SD1190, 7A	BD 647, BD 899, BDW 73B, BDX 53B
23906	2SD1192	2SD1190, 10A	BDT 63A, BDT 65A, BDW 93B, BDX 33B
23907	2SD1193	2SD1190, 15A	BDV 67A, BDW 83B, 2SD1026
23908	2SD1194	110V, 3A, 30W, 20MHz, B4000	BDW 53D, BDW 63D, 2SD1091, 2SD1147
23909	2SD1195	2SD1194, 5A	BD 651, BDT 21, BDW 63D, 2SD1147
23910	2SD1196	2SD1194, 8A	BD 651, BDT 21, BDW 73D, BDX 53D
23911	2SD1197	2SD1194, 10A	BDV 65C, BDV 67B, BDW 83D, 2SD1296
23912	2SD12	75V, 2.5A, 60W	BD 245B, BDV 93, 2N4915, 2SD895...896
23913	2SD120(H)	60V, 1.5A, 1W, 750/470ns	BCX 40, BSX 45...47, 2N5320...21
23914	2SD1200(F)	80V, 0.7A, 5W, 120MHz	2SC3421, BD 139, BD 230, 2SD1378
23915	2SD1201	500/400V, 10A, 100W, B>200	BU 323A, BU 922, BUW 81(A), 2SD685
23916	2SD1202	500/400V, 10A, 100W, B100	BU 323A, BU 922, BUW 81(A), 2SD685
23917	2SD1203	500/400V, 15A, 100W, B>200	BU 932, 2SD572...573, 2SD711(A)
23918	2SD1204	500/400V, 15A, 100W, B100	BU 932, 2SD572...573, 2SD711(A)
23919	2SD1204	500/400V, 15A, 100W, B100	BU 932, 2SD572...573, 2SD711(A)
23920	2SD1205	2SD892	2SD892
23921	2SD1205A	2SD892A	2SD892A
23922	2SD1206	30V, 0.1A, 0.4W, 150MHz	2SD889, 2SD1807
23923	2SD1207	60V, 2A, 1W, 150MHz	2SC3328, 2SC4145, 2SD2069, 2SD2485
23924	2SD1208	45V, 5A, 100W, B2k..20k	BDX 63..., MJ 1000, TIP 142, 2SD629
23925	2SD1209	60V, 1A, 0.9W, B>4000	2SD1153, 2SD1660, 2SD1809, 2SD1981
23926	2SD121(H)	2SD120, 100V	BCX 40, BSS 15, BSX 46...47, 2N5320
23927	2SD1210	150V, +-10A, 80W, B>1000	BDV 67D, 2SD1123, 2SD1296, 2SD1299
23928	2SD1211	120V, 0.5A, 1W, 200MHz	2SC2235, 2SD667(A), 2SD1812, 2SD1937
23929	2SD1212	60V, 12A, 35W, 120MHz	2SC3345...46, 2SD1062
23930	2SD1213	60V, 20A, 50W, 120MHz	2SD1841
23931	2SD1214	25V, 2A, 35W, B5000	BD 713, BDT 61, BDW 53, 2SD837
23932	2SD1215	25V, 4A, 40W, B5000	BD 713, BDT 61, BDW 53, 2SD837
23933	2SD1216	25V, 8A, 45W, B5000	BD 643, BD 895, BDW 73, BDX 53
23934	2SD1217	50V, 2A, 35W, B5000	BD 715, BDT 61, BDW 53A, 2SD837
23935	2SD1218	50V, 4A, 40W, B5000	BD 715, BDT 61, BDW 53A, 2SD837
23936	2SD1219	50V, 8A, 45W, B5000	BD 645, BD 897, BDW 73A, BDX 53A
23937	2SD122(H)	60/40V, 3A, 15W	BD 241A, BD 535, BD 935, 2SD712
23938	2SD1220	150V, 1.5A, 10W, 100MHz	2SC4027, 2SD1033, 2SD1080...82, 2SD1918
23939	2SD1221	60V, 3A, 20W, 3MHz	2SC3386, 2SC3518, 2SC3592, 2SD1802

23940	2SD1222	60V, 3A, 15W, B5000	2SD1520, 2SD1817, 2SD1955
23941	2SD1223	100V, 4A, 15W, B5000	2SC4339, 2SD1520, 2SD1955
23942	2SD1224	30V, 1,5A, 10W, B10000	2SC3132, 2SD1222, 2SD1759, 2SD1799
23943	2SD1225(M)	40V, 1A, 1W, 150MHz	BC 635, BC 637, 2SD667, 2SD1225
23944	2SD1226(M)	80V, 0,7A, 1W, 120MHz	BC 639, 2SC2235, 2SC2383, 2SD667
23945	2SD1227(M)	40V, 2A, 1W, 100MHz	MPS 650...651, 2SC3328, 2SD1146, 2SD1207
23946	2SD1228(M)	50V, 0,5A, 0,6W, 250MHz	BC 337, BC 635, BC 637, 2SC3377
23947	2SD1229	70V, 10A, 60W, B5000	BDV 65A, BDW 83B, TIP 141, 2SD1125
23948	2SD123(H)	2SD122, 100/55V	BD 241C, BD 539C, BD 939, 2SD712
23949	2SD1230	110V, 8A, 60W, B4000	BDV 65C, 2SD1210
23950	2SD1231	70V, 10A, 70W, B5000	BDV 65A, BDX 83B, BDX 85B, MJ 3001
23951	2SD1232	70V, 15A, 80W, B5000	BDV 67A, BDW 83B, BDX 67A, MJ 4034
23952	2SD1233	110V, 8A, 70W, B4000	BDV 65C, BDX 63C, BDX 65C, 2SD922
23953	2SD1234	110V, 10A, 80W, B4000	BDV 65C, BDW 83D, BDX 65C, 2SD922
23954	2SD1235	60V, 8A, 30W, 120MHz	2SC3254...3255
23955	2SD1236	2SD1236L, 120V	2SC4329...30
23956	2SD1236L	90V, 5A, 30W, 20MHz	2SC3258
23957	2SD1237	2SD1237L, 120V	2SC4329
23958	2SD1237L	90V, 7A, 40W	2SC4329
23959	2SD1238	2SD1238L, 120V	-
23960	2SD1238L	90V, 12A, 80W, 20MHz	2SD1840
23961	2SD1239	120V, 20A, 100W	BD 249C, BD 745D, 2SD1049
23962	2SD124(H)	60/40V, 6A, 60W, 1,6/7,2μs	BD 245A, BDV 91, BDX 91, 2N5873...74
23963	2SD124(H)	60/40V, 6A, 60W, 1,6/7,2μs	BD 245A, BDV 91, BDX 91, 2N5873...74
23964	2SD1240	120V, 25A, 120W	BD 249C
23965	2SD1241	60V, 5A, 60W	BD 245A, BDV 91, 2SC2681, 2SD895...896
23966	2SD1241A	2SD1241, 80V	BD 245B, BDV 93, 2SC2681, 2SD895...896
23967	2SD1242	60V, 6A, 70W	BD 245A, BDV 91, 2SC2681, 2SD895...896
23968	2SD1242A	2SD1242, 80V	BD 245B, BDV 93, 2SC2681, 2SD895...896
23969	2SD1243	60V, 10A, 100W	BD 245A, BD 545A, BDV 91, 2SC2681
23970	2SD1243A	2SD1243, 80V	BD 245B, BD 545B, BDV 93, 2SC2681
23971	2SD1244	2SD965, 1W	2SD965
23972	2SD1245	500/400V, 6A, 40W, B>500	BU 810, BU 912, 2SD798...799
23973	2SD1246	30V, 2A, 0,75W	2SC4484, 2SD1207, 2SD2177
23974	2SD1247	2SD1246, 2,5A, 1W	2SC4487, 2SD1347
23975	2SD1248	120V, 8A, 40W, B>1000	BD 651, BDT 21, BDW 73D, BDX 53D
23976	2SD1249	350/250V, 0,75A, 35W, 30MHz	BUW 40(A,B), TIP 47...50, 2SD859(A)
23977	2SD1249A	2SD1249, 400V	BUW 40A,B, TIP 48...50, 2SD859A
23978	2SD124A(AH)	2SD124, 75V, 7A	BD 245B, BDV 93, BDX 93, 2N5874
23979	2SD124A(AH)	2SD124, 75V, 7A	BD 245B, BDV 93, BDX 93, 2N5874
23980	2SD125(H)	100/55V, 6A, 60W, 1,6/7,7μs	BD 245C, BDV 95, BDX 95, 2N5632...33
23981	2SD125(H)	100/55V, 6A, 60W, 1,6/7,7μs	BD 245C, BDV 95, BDX 95, 2N5632...33
23982	2SD1250(A)	200V, 2A, 30W, 20MHz	2SD1033, 2SC2660, 2SD760, 2SD1138
23983	2SD1251	60V, 4A, 30W, 1MHz	2SD1904, 2SD1906, BD 241A, BD 535
23984	2SD1251A	2SD1251, 80V	2SD1906, 2SD2200, BD 241B, BD 537

23985	2SD1252	60V, 3A, 35W, 30MHz	2SD1902, BD 241A, BD 535, BD 935
23986	2SD1252A	2SD1252, 80V	2SD1906, 2SD2200, BD 241B, BD 537
23987	2SD1253	60V, 4A, 40W, 20MHz	2SD1904, 2SD2198, BD 243A, BD 535
23988	2SD1253A	2SD1253, 80V	2SD1906, 2SD2200, BD 243B, BD 537
23989	2SD1254	130V, 3A, 30W, 30MHz	2SD1529
23990	2SD1255	130V, 4A, 35W, 30MHz	-
23991	2SD1256	130V, 5A, 40W, 30MHz	-
23992	2SD1257	130V, 7A, 40W, 30MHz	-
23993	2SD1257A	2SD1257, 150V	-
23994	2SD1258	200V, 1A, 40W, 25MHz, B>500	-
23995	2SD1259	80V, 3A, 40W, 50MHz, B>500	-
23996	2SD1259A	2SD1259, 100V	-
23997	2SD125A(AH)	2SD125, 7A	BD 245C, BDV 95, BDX 95, 2N5632...33
23998	2SD125A(AH)	2SD125, 7A	BD 245C, BDV 95, BDX 95, 2N5632...33
23999	2SD126(H)	150/100V 6A, 60W, 1,6/8,2µs	BD245D, BDX11, 2N3442, 2SD551, 2SD732
24000	2SD126(H)	150/100V 6A, 60W, 1,6/8,2µs	BD245D, BDX11, 2N3442, 2SD551, 2SD732
24001	2SD1260	60V, 2A, 35W, 20MHz, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
24002	2SD1260A	2SD1260, 80V	BD 717, BDW 23B, BDW 53B, 2SD837A
24003	2SD1261	60V, 4A, 40W, 20MHz, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
24004	2SD1261A	2SD1261, 80V	BD 717, BDW 23B, BDW 53B, 2SD837A
24005	2SD1262	60V, 8A, 45W, 20MHz, B>1000	BD 645, BD 897, BDW 73A, BDX 53A
24006	2SD1262A	2SD1262, 80V	BD 647, BD 899, BDW 73B, BDX 53B
24007	2SD1263	350/250V, 0,75A, 35W, 30MHz	2SC3969, BUW 40(A,B), TIP 47...50
24008	2SD1263A	2SD1263, 400/300V	2SC3969, BUW 40(A,B), TIP 48...50
24009	2SD1264(A)	2SD1250(A)	2SC3298B, 2SC4382, 2SD1587, 2SD2337
24010	2SD1265(A)	2SD1251	BD 951F, 2SC3851, 2SD1408, 2SD2000
24011	2SD1266(A)	2SD1252(A)	BDT 31F, 2SC3851, 2SD1408, 2SD2000
24012	2SD1267(A)	2SD1253(A)	BD 951F, 2SC3851, 2SD1408, 2SD2000
24013	2SD1268	2SD1254	-
24014	2SD1269	2SD1255	-
24015	2SD127	23V, 0,5A, 0,25W	AC 127, AC 176, AC 187, 2SD72, 2SD352
24016	2SD1270	2SD1256	-
24017	2SD1271(A)	2SD1257(A)	-
24018	2SD1272	2SD1258	2SC2317
24019	2SD1273	2SD1259	2SD1944, 2SD1943, 2SC1983
24020	2SD1273A	2SD1259A	2SD2092
24021	2SD1274	150/80V, 5A, 40W, 40MHz	2SC3566, 2SC4334
24022	2SD1274A	2SD1274, 200/80V	2SC4153, BD 243F, 2SD772A,B
24023	2SD1274B	2SD1274, 250/80V	2SD772B
24024	2SD1275	2SD1260	BDT 61F, 2SD1796, 2SD1825, 2SD1987
24025	2SD1275A	2SD1260A	BDT 61AF, 2SD1414, 2SD1788, 2SD1933
24026	2SD1276	2SD1261	BDT 61F, 2SD1796, 2SD1825, 2SD1987
24027	2SD1276A	2SD1261A	BDT 61AF, 2SD1414, 2SD1788, 2SD1933
24028	2SD1277	2SD1262	BD 643F, BDT 63F, 2SD1416, 2SD1826...27
24029	2SD1277A	2SD1262A	BD 645F, BDT 63AF, 2SD1415...16

24030	2SD1278	1200/650V, 8A, 100W, <1/5µs	BU 508A, 2SC3412, 2SD905...906, 2SD1498
24031	2SD1279	1400V, 10A, 50W, 3MHz	2SC3688
24032	2SD128	2SD127, 32V	AC 127, AC 176, AC 187, 2SD72, 2SD352
24033	2SD1280	20V, 1A, 150MHz	BC 868, BCX 54...56, BCX 68, 2SC2884
24034	2SD1281	100V, 2A, 20W	2SC4135, 2SD1557, 2SD1815...16
24035	2SD1282	100V, 2A, 20W	2SC4135, 2SD1557, 2SD1815...16
24036	2SD1283	120V, 2A, 20W	2SC4135, 2SD1557, 2SD1815...16
24037	2SD1284	120V, 2A, 20W	2SC4135, 2SD1557, 2SD1815...16
24038	2SD1286(Z)	60V, +-1A, 8W, B2k..30k	2SC2871, 2SD1598, 2SD1800
24039	2SD1287	300/250V, 30A, 150W, B300	BUT 13, MJ 10022...10023
24040	2SD1288	120V, 7A, 70W, 55MHz	BD 245C, BD 545D, 2SD718, 2SD1046
24041	2SD1289	120V, 8A, 80W, 60MHz	BD 245C, BD 545D, 2SD718, 2SD1046
24042	2SD129	90/80V, 3A, 25W, 1MHz	BD 241B, BD 939, 2N4233, 2SD712
24043	2SD1290	1500V, 3A, 50W	BU 706D, 2SC3479, 2SC3481, 2SD1729
24044	2SD1291	1500V, 3A, 50W	BU 706D, 2SC3479, 2SC3481, 2SD1729
24045	2SD1292	120V, 1A, 0.9W, 100MHz	2SC2383, 2SC3228, 2SD667(A), 2SD1812
24046	2SD1293(M)	2SD1292, 1W	2SC2383, 2SC3228, 2N3700...01, 2SD667
24047	2SD1294	60V, 5A, 80W, B2k..20k	BDV 65, TIP 140...142, 2SD1124, 2SD1170
24048	2SD1295	50V, 1.5A, 20W, 150MHz	2SC3076, 2SD1078, 2SD1281...1284
24049	2SD1296	150V, +-15A, 100W, B1k..30k	BDV 67D, 2SD1027, 2SD1299, 2SD1515
24050	2SD1297	150V, 25A, 100W, B1k..30k	-
24051	2SD1298	B200..2000	2SC3262, 2SD979
24052	2SD1299	150V, 15A, 100W, B5000	BDV 67D, 2SD1027, 2SD1297, 2SD1515
24053	2SD13	35V, 10A, 100W	BD 245, BDV 91, 2SC2681
24054	2SD130	2SD129, 60/50V	BD 241A, BD 535, BD 935, 2N4232...33
24055	2SD1300	1500V, 3A, 50W	BU 208A, 2SC3023...24, 2SD849...850
24056	2SD1301	1500V, 2A, 45W	BU 208D, BU 705D, 2SD993, 2SD1728
24057	2SD1302	25V, 0.5A, 0.6W, 200MHz	-
24058	2SD1303	20V, 1A, 1W	2SC2236, 2SD863, 2SD1247, 2SD1331
24059	2SD1304	20V, 0.1A, 150MHz	BC 846...848, BCW 31...33, 2SC1622
24060	2SD1305	185/185V, 0.15A, 120MHz	BFN 24, BFN 26, 2SC3360, 2SC4061
24061	2SD1306	30V, 0.7A, 250MHz	BCW 65...66, 2SD1782
24062	2SD1307	350/300V, 6A, 35W, B2500	BU 910...912, 2SD835, 2SD1089, 2SD1114
24063	2SD1308	100V, +-5A, 30W, B2k..20k	BD 901, BDW 23C, BDW 63C, 2SD1147
24064	2SD1308	100V, +-5A, 30W, B2k..20k	BD 901, BDW 23C, BDW 63C, 2SD1147
24065	2SD1309	150V, +-8A, 40W, B2k..15k	BDX 53F, 2SD1025, 2SD1500
24066	2SD1309	150V, +-8A, 40W, B2k..15k	BDX 53F, 2SD1025, 2SD1500
24067	2SD131	100V, 5A, 50W, 20MHz	BD 245C, BDV 95, BDX 95, 2N5758...60
24068	2SD131	100V, 5A, 50W, 20MHz	BD 245C, BDV 95, BDX 95, 2N5758...60
24069	2SD1310	60V, 3A, 30W, 16MHz	BD 241A, BD 535, BD 935, 2SC3179
24070	2SD1310	60V, 3A, 30W, 16MHz	BD 241A, BD 535, BD 935, 2SC3179
24071	2SD1311	100V, 4A, 40W, 20MHz	BD 241C, BD 539C, BD 937, 2SD712
24072	2SD1311	100V, 4A, 40W, 20MHz	BD 241C, BD 539C, BD 937, 2SD712
24073	2SD1312	120V, 1A, 1W, 120MHz	2N3700...01, 2SC2383, 2SC3228, 2SD667
24074	2SD1313	800/350V, 25A, 200W, 0.8/3.5µs	2SC3989

24075	2SD1314	600/450V, 15A, 150W	-
24076	2SD1315	B>5000	2SD1590, 2SD1169
24077	2SD1316	30V, 2A, 35W, B>1000	BD 713, BDW 23, BDW 53, BDW 63
24078	2SD1317	30V, 4A, 40W, B>1000	BD 713, BDW 23, BDW 53, BDW 63
24079	2SD1318	30V, 8A, 45W, B>1000	BD 643, BD 895, BDW 73, BDX 53
24080	2SD1319	60V, 2A, 35W, B>1000	BD 715, BDW 23A, BDW 53A, BDW 63A
24081	2SD132	100V, 20A, 150W	2SD363, 2SD372
24082	2SD1320	60V, 4A, 40W, B>1000	BD 715, BDW 23A, BDW 53A, BDW 63A
24083	2SD1321	60V, 8A, 45W, B>1000	BD 645, BD 897, BDW 73A, BDX 53A
24084	2SD1322	2SD1316	2SC3986, 2SD1983, 2SD1989, 2SD2051
24085	2SD1323	2SD1317	BDT 61F, 2SD1595, 2SD1796, 2SD2131
24086	2SD1324	2SD1318	BD 643F, 2SD1416...17, 2SD1826
24087	2SD1325	2SD1319	2SD1413, 2SD1983, 2SD2051
24088	2SD1326	2SD1320	BDT 61F, 2SD1595, 2SD1796, 2SD2131
24089	2SD1327	2SD1321	BD 643F, 2SD1416...17, 2SD1826
24090	2SD1328	25V, 0,5A, 200MHz, Ron1Ohm	BC 817...818, BCX 19...20, 2SC3325
24091	2SD1329(K)	50V, 6A, 40W, B>2000	BD 645, BD 897, BDW 23A, BDW 63A
24092	2SD1330	2SD1302	2SD1302
24093	2SD1331	40V, 1,5A, 0,9W	2SC4486, 2SD1051, 2SD1146, 2SD1207
24094	2SD1332	100V, 5A, 60W, 20MHz	BD 245C, 2SD718, 2SD895...896, 2SD731
24095	2SD1333	120V, 6A, 70W	BD 245C, 2SD718, 2SD896, 2SD731
24096	2SD1334	140V, 7A, 80W	BD 245D, 2SD1046...1047, 2SD731
24097	2SD1335	150V, 9A, 100W	BD 245D, 2SC2987(A), 2SC2838, 2SD1047
24098	2SD1336	150/100V, 6A, 35W, B>1500	2SD1590, 2SD1023, 2SD1025, 2SD1113
24099	2SD1336A	2SD1336, 180/120V	2SD1792, 2SD991, 2SD1088, 2SD1113
24100	2SD1337	1500/600V, 2,5A, 50W	BU 205, BU 705, 2SC3023, 2SD627
24101	2SD1338	1500/600V, 2,5A, 50W	BU 208D, BU 705D, 2SD993, 2SD1728
24102	2SD1339	1500/600V, 3,5A, 50W	BU 208A, BU 706, 2SD849...850, 2SD783
24103	2SD134	60V, 5mA, 0,03W	-
24104	2SD1340	1500/600V, 3,5A, 50W	BU 208D, BU 706D, 2SD993, 2SD1729
24105	2SD1341	1500/600V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD954
24106	2SD1342	1500/600V, 5A, 50W	BU 208D, BU 706D, 2SD1171...75, 2SD1730
24107	2SD1343	1500/600V, 6A, 50W	BU 508A, 2SC3025, 2SD821...822, 2SD1497
24108	2SD1344	1500/600V, 6A, 50W	BU 508D, 2SD903...904, 2SD1731
24109	2SD1345	0,2/1,2μs	BD 243A, BD 543A, BD 797, 2SC3254
24110	2SD1346	1400V, 2,5A, 40W	BU 505
24111	2SD1347	60V, 3A, 1W, 150MHz	2SC4487, 2SC4482, 2SD1145
24112	2SD1348	2SD1347, 4A, 10W	2SD1348
24113	2SD1349	500V, 7A, 50W, 11MHz, B>150	BU 810, 2SD1533
24114	2SD1350	400/400V, 0,5A, 1W, 55MHz	2SC4645
24115	2SD1350A	2SD1350, 600/500V	-
24116	2SD1351	60V, 3A, 30W, 3MHz	BD 241A, BD 535, BD 935, 2SC3179
24117	2SD1352	80V, 4A, 30W, 8MHz	BD 243B, BD 537, BD 951, 2SC3179
24118	2SD1353	50V, 3A, 30W, 5MHz, B600	2SD1052, 2SC1983, 2SD1943, 2SD1157
24119	2SD1354	60V, 3A, 30W, 3MHz	BD 241A, BD 535, BD 935, 2SC3179



24120	2SD1355	100V, 5A, 40W, 12MHz	BD 243C, BD 539C, BD 953, 2SD613
24121	2SD1356	80V, 4A, 30W, 8MHz	BD 243B, BD 539B, BD 951, 2SC3179
24122	2SD1357	100V, 7A, 40W, B6000	BD 649, BD 901, BDW 73C, BDX 53C
24123	2SD1358	80V, 7A, 40W, B6000	BD 647, BD 899, BDW 73B, BDX 53B
24124	2SD1359	60V, 7A, 40W, B6000	BD 645, BD 897, BDW 73A, BDX 53A
24125	2SD136	200/200V, 0,1A, 4W, 20MHz	BF 415, BF 458...459, 2SC3502...03
24126	2SD1360	600/400V, 6A, 30W, B1000	BU 810, 2SC3579, 2SD798...799
24127	2SD1361	300/250V, 6A, 30W, B5000	BU 910...912, 2SD1088...89, 2SD1113...14
24128	2SD1362	100V, 7A, 40W, 10MHz	2SD1237L
24129	2SD1363	70V, 7A, 40W, 10MHz	2SC3254, 2SD1237L
24130	2SD1364	300/150V, 7A, 40W	BU 406D...408D, 2SC3174, 2SC3176
24131	2SD1365	800/400V, 3A, 40W, <1/8μs	BUT 11(A), BUV 46(A), 2SC3086, 2SC3490
24132	2SD1366	25V, 1A, 240MHz	BC 868, BCX 54...56, BCX 68, 2SC3444
24133	2SD1366A	2SD1366, 30V	BCX 54...56, 2SC2873, 2SC3444, 2SD874A
24134	2SD1367	20V, 2A, 100MHz	2SC2883, 2SC3443, 2SC3439, 2SC2982
24135	2SD1368	100V, 1A, 100MHz	BCX 56, 2SD1005, 2SD1368, 2SD1418...1419
24136	2SD1369	60V, 3A, 25W, B5000	BD 715, BDW 23A, BDW 53A, BDW 63A
24137	2SD137	2SD136, 300/300V	BF 417, BF 459, 2SC3417, 2SC3503
24138	2SD1370	100V, 4A, 30W, B4000	BDW 23C, BDW 53C, BDW 63C, 2SD837B
24139	2SD1371	300/300V, 2A, 40W, 5MHz	TIP 75(A...C), BUT 93, 2SC2023, 2SC3055
24140	2SD1372	300/300V, 4A, 50W, 5MHz	TIP 75(A...C), BUT 93, 2SC2907, 2SC2440
24141	2SD1373	300/300V, 4A, 50W, 5MHz	TIP 51...54, 2SC2624, 2SC4799
24142	2SD1374	300/300V, 3A, 50W	TIP 51...54, 2SC4799, 2SD632
24143	2SD1375	300/300V, 4A, 90W	TIP 51...54, 2SC4799, 2SD632
24144	2SD1376(K)	120/120V, 1,5A, 20W, B>2000	2SD985...986, 2SD1953, 2SD2019
24145	2SD1377(K)	120/120V, 8A, 40W, B>1000	BD 651, BDT 21, BDW 73D, BDX 53D
24146	2SD1378	80V, 0,7A, 10W, 120MHz	BD 139, BD 230, 2SD1382, 2SD1563
24147	2SD1379	B>4000	BD 775, 2SC4341, 2SD1438, 2SD1953
24148	2SD138	200/200V, 1A, 30W	BUW 40(A,B), TIP 47, 2SC783, 2SD1138
24149	2SD1380	40V, 2A, 10W, 100MHz	BD 375, 2SD1177...78, 2SD1506, 2SD1818
24150	2SD1381	120V, 1A, 5W, 100MHz	2SC3421, 2SD1684
24151	2SD1382	2SD1381, 10W	2SC2690(A), 2SC2803, 2SD781
24152	2SD1383	40V, 0,3A, 250MHz, B>1000	-
24153	2SD1383K	2SD1383	BCV 27, BCV 47, 2SD1478A
24154	2SD1384	40V, 2A, 0,75W, 100MHz	2SC3328, 2SC4145, 2SD1146, 2SD1207
24155	2SD1385	400/400V, 0,1A, 1W, 40MHz	MPSA 45, 2SC2267, 2SC3118, 2SC3469
24156	2SD1386	140V, 8A, 50W, B4000	BDX 33E, BDX 53E,F, 2SD1500, 2SD1756
24157	2SD1387	20V, 2A, 0,7W, B250	2SC3225, 2SC3673, 2SD1207, 2SD1835
24158	2SD1388	60V, 1A, 0,7W, B250	BC 337A, BC 637, 2SC3939, 2SD1616(A)
24159	2SD1389	1200/650V, 6A, 50W	BU 546, BU 903, 2SC3343...44, 2SD1104
24160	2SD139	2SD138, 300/300V	BUW 40(A,B), TIP 47...50, 2SC2022
24161	2SD1390	1500/700V, 1A, 40W	BU 505
24162	2SD1391	1500/700V, 5A, 100W	BU 706, 2SC3485, 2SD954, 2SD1496
24163	2SD1392	60+-10V, 5A, 30W, B>2k	BD 645, BD 897, BDW 23A, BDW 63A
24164	2SD1392	60+-10V, 5A, 30W, B>2k	BD 645, BD 897, BDW 23A, BDW 63A



24165	2SD1393	60+-10V, 2A, 30W, B>1k	BD 715, BDT 61, BDW 53A, 2SD837
24166	2SD1394	60+-10V, 3A, 30W, B>1k	BD 715, BDT 61, BDW 53A, 2SD837
24167	2SD1395	60+-10V, 5A, 40W, B>1k	BD 645, BD 897, BDW 23A, BDW 63A
24168	2SD1396	1500/800V, 2,5A, 80W	BU 705D, 2SC3479, 2SD1290...91, 2SD1728
24169	2SD1397	1500/800V, 3,5A, 80W	BU 706D, 2SC3480, 2SD1729
24170	2SD1398	1500/800V, 5A, 80W	BU 706D, 2SC3481, 2SC3681, 2SD1730
24171	2SD1399	1500/800V, 6A, 80W	BU 508D, 2SC3482, 2SC3681, 2SD1732
24172	2SD14	75V, 10A, 100W	BD 245B, BDV 93, 2SC2681
24173	2SD1400	1500/800, 2,5A, 80W	BU 705, 2SC3483, 2SD1493...94
24174	2SD1401	1500/800V, 3,5A, 80W	BU 706, 2SC3484, 2SD1495
24175	2SD1402	1500/800V, 5A, 120W	BU 706, 2SC3485, 2SC3685, 2SD1496
24176	2SD1403	1500/800V, 6A, 120W	BU 508A, BU 908, 2SC3486, 2SD1497
24177	2SD1404	300/150V, 7/15A, 25W, 18MHz	BU 406D...408D, 2SC3174, 2SC3176
24178	2SD1405	2SD1353, , 25W	2SC3677, 2SC3852, 2SD1948, 2SD1972
24179	2SD1406	2SD1354, , 25W	2SC3299, 2SC3746, 2SD1913, 2SD2012
24180	2SD1407	2SD1355, , 30W	2SC3691, 2SD1411, 2SD1488, 2SD1940
24181	2SD1408	2SD1356, , 25W	2SC3691, 2SC3746, 2SC3851, 2SD2000
24182	2SD1409	2SD1360, , 25W	2SC3579, 2SD798...799
24183	2SD141	20V, 2A, 15W	BD 239, BD 533, BD 933, 2N4231
24184	2SD1410	2SD1361, , 25W	2SD2017, 2SD1088, 2SD1113, 2SD1976
24185	2SD1411	100V, 7A, 30W. 10MHz	2SC3692, 2SC4550
24186	2SD1412	2SD1411, 70V	2SC3747
24187	2SD1413	60V, 3A, 20W, B>2000	BDT 61F, 2SD1796, 2SD1825, 2SD1987
24188	2SD1414	100V, 4A, 20W, B>2000	2SD1589, 2SD1788, 2SD1928, 2SD2014
24189	2SD1415	2SD1357, , 30W	2SD1791, 2SD1830, 2SD2025
24190	2SD1416	2SD1358, , 30W	2SD1791, 2SD1830, 2SD2025
24191	2SD1417	2SD1359, , 30W	2SD1791, 2SD1826, 2SD2025
24192	2SD1418	120/80V, 1A, 140MHz	2SC3646, 2SD1420...1421
24193	2SD1419	2SD1418, 120/100V	2SC3646, 2SD1420...1421
24194	2SD142	2SD141, 40V	BD 239, BD 533, BD 933, 2N4231
24195	2SD1420	180/120V, 1,5A	2SC3649
24196	2SD1421	2SD1420, 180/160V	2SC3649
24197	2SD1422	100V, 2A	2SC3647, 2SC4132, 2SD1420...1421
24198	2SD1423	2SD638, 0,3W	2SD638
24199	2SD1423A	2SD639, 0,3W	2SD639
24200	2SD1424	2SD1010	2SD1010
24201	2SD1425	1500/600V, 2,5A, 80W	BU 705D, 2SC3479, 2SD1290...91, 2SD1728
24202	2SD1425..1432FI	2SD1425..1432	
24203	2SD1426	1500/600V, 3,5A, 80W	BU 706D, 2SC3480, 2SD1729
24204	2SD1427	1500/600V, 5A, 80W	BU 508D, BU 2508D, 2SC3481, 2SD1730
24205	2SD1428	1500/600V, 6A, 80W	BU 508D, BU 2508D, 2SC3482, 2SD1731
24206	2SD1429	1500/600V, 2,5A, 80W	BU 705, 2SC3483, 2SD1493...94
24207	2SD143	80V, 1A, 15W	BD 239B, BD 537, BD 937, 2N4912
24208	2SD1430	1500/600V, 3,5A, 80W	BU 706, 2SC3484, 2SD1495
24209	2SD1431	1500/600V, 5A, 80W	BU 508A, BU 908, 2SC3485, 2SC3685

24210	2SD1432	1500/600V, 6A, 80W	BU 508A, BU 908, 2SC3686, 2SD1497
24211	2SD1433	1500/600V, 7A, 80W	BU 508A, BU 908, BU 2508A, 2SC3686...87
24212	2SD1434	1700/800V, 5A, 80W	-
24213	2SD1435(K)	100V, 15A, 100W, B>1000	BDV 67A, BDW 83C, 2SD1026
24214	2SD1436(K)	120V, 10A, 80W, B>1000	BDV 65C, BDV 67B, BDW 83D, 2SD1210
24215	2SD1437	80V, 3A, 40W, 8MHz	BD 241B, BD 537, BD 937, 2SC3179
24216	2SD1438	80V, 2A, 15W, B5000	BD 679, BD 779, 2N6039, 2SD1376
24217	2SD1439	1500V, 3A, 50W	BU 706D, 2SC3480, 2SD1290...91, 2SD1729
24218	2SD144	2SD143, 100V	BD 239C, BD 937, 2SD712, 2SD1516
24219	2SD1440	1500V, 3A, 50W	BU 706D, 2SC3480, 2SD1290...91, 2SD1729
24220	2SD1441	1500V, 4A, 70W	BU 706D, 2SC3481, 2SC3681, 2SD1730
24221	2SD1442	40V, 7A, 30W, 150MHz	2SC3254, 2SD1235
24222	2SD1442A	2SD1442, 50V	2SC3254, 2SD1235
24223	2SD1443	40V, 10A, 40W, 120MHz	2SC3255, 2SC3345, 2SD1212
24224	2SD1443A	2SD1443, 50V	2SC3255, 2SC3345, 2SD1212
24225	2SD1444(A)	2SD1442	2SC3747, 2SC4327
24226	2SD1445(A)	2SD1443(A)	2SC3709, 2SC4064...65
24227	2SD1446	500/400V, 6A, 40W, B>500	-
24228	2SD1447	30V, 1A, 0,9W, 100MHz	2SC2236, 2SD863, 2SD1146, 2SD1207
24229	2SD1448(Z)	70V, 3A, 10W, 60MHz	2SC3303, 2SC3386, 2SD1815...16
24230	2SD1449	2SD958, 0,3W	2SD958
24231	2SD1450	2SD1302, 0,3W	2SD1302
24232	2SD1451	1500/600V, 1,5A, 50W	BU 705, 2SC3483, 2SD1492...94
24233	2SD1452	1500/600V, 2,5A, 50W	BU 705, 2SC3483, 2SD1493...94
24234	2SD1453	1500/600V, 3A, 50W	BU 706, 2SC3484, 2SD1495
24235	2SD1454	1500/600V, 4A, 50W	BU 706, 2SC3484, 2SC3685, 2SD1495
24236	2SD1455	1500/600V, 5A, 50W	BU 706, 2SC3485, 2SC3685, 2SD1496
24237	2SD1456	1500/600V, 6A, 50W	BU 508A, 2SC3486, 2SC3685, 2SD1497
24238	2SD1457(A)	200V, 6A, 60W, 15MHz, B>700	2SD921, 2SD1090, 2SD1122...23
24239	2SD1458	20V, 0,7A, 1W, 55MHz	2SC3070, 2SC3616, 2SC4204, 2SD1582
24240	2SD1459	150V, 1,5A, 30W, 8MHz	BD 239D, 2SC2073, 2SD608(A), 2SD1138
24241	2SD146(F)	40V, 1A, 20W	BD 239, BD 533, BD 933, 2N4910...11
24242	2SD1460	100V, 30A, 200W, B4000	MJ 11016, 2SD730
24243	2SD1461	400V, 5A, 80W, B>400	BU 826, 2SC3261, 2SD663
24244	2SD1462	20V, 2A, B400	2SD1583...84
24245	2SD1463	120/100V, 0,05A, 140MHz	2SC2780, 2SC2880, 2SC4372, 2SD1464
24246	2SD1464	180/160V, 0,05A, 140MHz	2SC2880, 2SC4372
24247	2SD1465L,S	120V, 1,5A, 20W, B>2000	2SD1164, 2SD985...986, 2SD1376
24248	2SD1466	500/450V, 15A, 100W, B>200	BUT 51P
24249	2SD1468(S)	30V, 1A, 0,3..0,4W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1225
24250	2SD1468(S)	30V, 1A, 0,3..0,4W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1225
24251	2SD1469(M)	2SD1468, 0,6W	BC 337...338, BC 635, BC 637, 2SD1225
24252	2SD147(F)	2SD146, 60V	BD 239A, BD 535, BD 935, 2N4911...12
24253	2SD1470	60V, 1A, B2k..100k	BST 50...52, 2SD1511
24254	2SD1471	40V, 0,3A, B2k..100k	BCV 29, BCV 49

24255	2SD1472	120V, 1,5A, B2k..30k	-
24256	2SD1473	500/400V, 0,5A	2SC4929
24257	2SD1474	100V, 6A, 40W	2SC4553, 2SD1947
24258	2SD1475	2SD1476	2SC3691, 2SC3746, 2SC4549, 2SC4596
24259	2SD1476	80V, 4A, 35W, 50MHz	BD 243B, BD 537, BD 951, 2SC3179
24260	2SD1477	30V, 0,1A, 0,4W, B300	BC 168, BC 183, BC 238, BC 548, 2SD767
24261	2SD1478	2SD892, SMD, 200MHz	BCV 27, 2SD1383K, 2SD2026
24262	2SD1478A	2SD892A, SMD, 200MHz	BCV 47
24263	2SD1479	1500/700V, 2,5A, 80W	BU 705, 2SC3483, 2SD1493...94
24264	2SD148	70V, 2A, 20W, 1,2MHz, -/5,8µs	BD 239A, BD 537, BD 937, 2N4912
24265	2SD1480	60V, 2A, 25W, 20MHz	BD 936F, 2SD1585, 2SD1985, 2SD2012
24266	2SD1481	60+-10V, 2A, 15W, B>2k	BD 715, BDW 23A, BDW 53B, 2SD837
24267	2SD1482	40V, 0,1A	BC 846...847, BCW 71...72, BCW 81
24268	2SD1483	2SD1458, SMD	2SC3618, 2SC3650
24269	2SD1484	50V, 0,5A, 250MHz	-
24270	2SD1484K	2SD1484	BC 817, BCW 65...66, 2SC3325, 2SC3441
24271	2SD1485	2SD1332	2SC4385, 2SD2064, BD 245C, 2SC2837
24272	2SD1486	2SD1333	2SC4385, 2SD2064, BD 245D, 2SC3181
24273	2SD1487	2SD1334	2SC4386, 2SD2052, BD 245D, 2SD1046
24274	2SD1488	2SD1335	2SC4386, 2SD2052, BD 245D, 2SC2837
24275	2SD1489	20V, 2A, 0,75W, 80MHz	2SC3226, 2SD1100, 2SD1146, 2SD1207
24276	2SD149	70V, 1A, 0,8W, 1,2MHz	BC 441, BCX 40, 2N1990, 2N2102, 2N3109
24277	2SD1490	70V, 1A, 0,75W, 80MHz	BC 639, 2SD667, 2SD1616(A), 2SD1768
24278	2SD1491	60+-10V, +-2A, 10W, B>2k	-
24279	2SD1492	1500/600V, 1,5A, 50W	BU 705, 2SC3483
24280	2SD1493	1500/800V, 2,5A, 50W	BU 705, 2SC3483
24281	2SD1494	1500/800V, 3A, 50W	BU 706, 2SC3484
24282	2SD1495	1500/600V, 4A, 50W	BU 508A, BU 2508A, BU 706, 2SC3484
24283	2SD1496	1500/600V, 5A, 50W	BU 508A, BU 908, 2SC3485, 2SC3685
24284	2SD1497	1500/650A, 6A, 50W	BU 508A, BU 908, 2SC3486, 2SC3685
24285	2SD1498	1400/650V, 8A, 50W	BU 508A, BU 908, BU 2508A, 2SC3687
24286	2SD1499	2SD1485, 40W	BD 953F, BDT41AF, 2SD1407, 2SD1940
24287	2SD15	60V, 6A, 80W, <1460/5100ns	BD 245A, BDV 91, 2N4914...4915
24288	2SD150	50V, 1A, 15W, >10MHz	BD 239, 2SC1398, 2SC2591...2592
24289	2SD1500	150V, 10A, 40W, B5000	2SD1756
24290	2SD1501	70V, 1A, 1W, B250	2SD667, 2SD774, 2SD1616(A), 2SD1768
24291	2SD1502	300/300V, 0,3A, 15W, B7000	2SD1798
24292	2SD1503	900/400V, 6A, 50W	BU 508A, BU 908, 2SC3636, 2SC3642
24293	2SD1504	Ron0,5Ohm	BC 337...338, 2SD774, 2SC3377, 2SD1302
24294	2SD1505	60V, 3A, 30W, 90MHz	BD 241A, BD 535, BD 935, 2SC3252
24295	2SD1506	2SD1505, 10W	BD 177, BD 439, BD 785, 2SD1348
24296	2SD1507(M)	2SD1505, 1W	2SC4487, 2SD1145, 2SD1347, 2SD1864
24297	2SD1508	30V, 1,5A, 10W, B7000	2SD947
24298	2SD1509	80V, 2A, 10W, 100MHz, B5000	-
24299	2SD151	100V, 10A, 120W	BDY 53, 2N3055, 2N5632...33, 2SD426

24300	2SD151	100V, 10A, 120W	BDY 53, 2N3055, 2N5632...33, 2SD426
24301	2SD1510	60V, 4A, 35W, B>1000	BDT 61F, 2SD1796, 2SD1825, 2SD1987
24302	2SD1511	100V, 1A, 150MHz, B>4000	BST 52, 2SD1472
24303	2SD1512	2SD1011	2SD1011
24304	2SD1513	20V, 2A, 0,75W, 200MHz	2SC3226, 2SD1100, 2SD1146, 2SD1207
24305	2SD1514	100V, 15A, 100W, B4000	BDV 67A, BDW 83C, 2SD1026
24306	2SD1515	2SD1514, 200V	2SD1027
24307	2SD1516	130V, 2A, 25W, 25MHz	2SD1528
24308	2SD1517	2SD1516	2SD1268
24309	2SD1518	900V, 6A, 50W, 5MHz	BU 426A, BUW 11(A), 2SC3153, 2SD1503
24310	2SD1519	1400/600V, 10A, 80W	BU 2520A, 2SC3688
24311	2SD152	150V, 1A, 15W	BD 239D, 2SC2073, 2SD608(A), 2SD1138
24312	2SD1520L,S	100V, 4A, 20W, B>1000	2SC4345, 2SD1223, BDW 23C, BDW 53C
24313	2SD1521	50V, 1,5A, 10W, B>2000	2SC4341, 2SD1376, 2SD1438
24314	2SD1522	500/450V, 10A, 100W, B500	BUT 51P, 2SC3262, 2SD979, 2SD1298
24315	2SD1523	450/450V, 15A, 100W, B500	BUT 51P, 2SD1466
24316	2SD1524	450/450V, 10A, 100W, B300	BUT 51P, 2SC3262, 2SD979, 2SD1298
24317	2SD1525	100V, 30A, 150W, B4000	-
24318	2SD1526	130V, 1A, 1W, 200MHz	2N3700...01, 2SC2383, 2SC3228, 2SD1812
24319	2SD1527	1000/1000V, 0,5A, 25W, 5MHz	BUV 36A, BUX 85, 2SC3178, 2SC3531
24320	2SD1528	130V, 3A, 30W, 25MHz	2SD959...960
24321	2SD1529	2SD1528	2SD1254...55
24322	2SD153	250/200V, 10A, 120W	2N5540
24323	2SD1530	2SD1528	2SD1268
24324	2SD1531	50V, 2A, 5W, 150MHz	BD 177, BD 235, BD 377, 2SD1177...78
24325	2SD1532	120V, 4A, 30W, B3000	BDT 21, BDW 53D, BDW 63D, 2SD1147
24326	2SD1533	B>500	BU 810
24327	2SD1534	2SD1533	2SC4220, 2SC4598, BU 810
24328	2SD1535	2SD1533	BU 810
24329	2SD1536(M)	40V, 2A, 1W, 150MHz, B>1000	2SD1786, 2SD1861, 2SD1931
24330	2SD1537	40V, 4A, 25W, 120MHz	2SC2562, 2SC3253, 2SD1235
24331	2SD1537A	2SD1537, 50V	2SC2562, 2SC3253, 2SD1235
24332	2SD1538(A)	2SD1537(A)	2SD1903, 2SC2562, 2SC3253, 2SD1235
24333	2SD1539(A)	2SD1537(A)	2SC3299, 2SC4327, 2SD1444(A)
24334	2SD154	80V, 3A, 25W	BD 241B, BD 537, BD 937, 2SD1505
24335	2SD1540	100V, 6A, 60W, B800	BDV 65B, BDX 63B, TIP 142, 2SD1170
24336	2SD1541	1500V, 3A, 50W	BU 706DF, 2SD1554, 2SD1650, 2SD1877
24337	2SD1542	1500/600V, 1,5A, 40W	BU 705F, 2SD1653, 2SD1882
24338	2SD1543	1500/600V, 2,5A, 40W	BU 705F, 2SD1563, 2SD1882
24339	2SD1544	1500/600V, 3,5A, 40W	BU 706F, 2SD1654, 2SD1883, 2SD2381
24340	2SD1545	1500/600V, 5A, 50W	BU 706F, 2SC3894, 2SC4142, 2SD1655
24341	2SD1546	1500/600V, 6A, 50W	BU 2508AF, 2SC4143, 2SD1556, 2SD1885
24342	2SD1547	1500/600V, 7A, 50W	BU 2508AF, 2SC3895, 2SC4757, 2SD2252
24343	2SD1548	1400/600V, 10A, 50W	BU 2520AF, BUH 715, 2SC3897, 2SC4199(A)
24344	2SD1549	1000/800V, 5A, 50W	BU 508AF, BU 706F, 2SC3884, 2SD1885

24345	2SD155	80V, 3A, 25W	BD 241B, BD 537, BD 937, 2SD1505
24346	2SD1550	1000/400V, 10A, 50W	BU 2520AF, 2SC3897, 2SC4542, 2SD1887
24347	2SD1551	1500/600V, 5A, 50W	BU 508AF, 2SC3894, 2SC4142, 2SD1885
24348	2SD1552	1500/600V, 5A, 50W	BU 508AF, 2SC3894, 2SC4142, 2SD1885
24349	2SD1553	1500/600V, 2,5A, 40W	BU 706DF, 2SD1649, 2SD1876, 2SD2367
24350	2SD1554	1500/600V, 3,5A, 40W	BU 706DF, 2SD1650, 2SD1877, 2SD2089
24351	2SD1555	1500/600V, 5A, 50W	BU 508DF, 2SD1651, 2SD2095, 2SD2125
24352	2SD1556	1500/600V, 6A, 50W	BU 508DF, 2SC4294, 2SD1652, 2SD2125
24353	2SD1557	200V, 2A, 20W, 10MHz	2SD1033, 2SD1250(A), 2SD1138
24354	2SD1558	60V, 4A, 40W, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
24355	2SD1559	100V, 20A, 100W, B>1000	2SD1597
24356	2SD156(F)	200V, 0,1A, 4W(Tc70°), 20MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
24357	2SD1562	120/120V, 1,5A, 20W, 80MHz	BD 239D, BD 959, 2SC2275, 2SD1138
24358	2SD1562A	2SD1562, 160/160V	BD239D, 2SC2238A,B, 2SD608(A), 2SD1138
24359	2SD1563	2SD1562, 10W	2SC2690(A), 2SD781
24360	2SD1563A	2SD1563, 160/160V	2SC3117, 2SD669
24361	2SD1564	50V, 5A, 30W, B8000	BDW 23A, BDW 63A
24362	2SD1565	100/100V, 5A, 30W, B8000	BDW 23C, BDW 63C
24363	2SD1566	150V, +-10A, 60W, B9000	BDX 53F, 2SD1500
24364	2SD1566	150V, +-10A, 60W, B9000	BDX 53F, 2SD1500
24365	2SD1567	60V, 3A, 30W, 16MHz	BD 241A, BD 535, BD 935, 2SC3252
24366	2SD1568	100V, 4A, 40W, 20MHz	BD 243C, BD 537, BD 539C, 2SC3253
24367	2SD1569	60V, 3A, 30W, B>800	-
24368	2SD157(F)	2SD156, 300/300V	2SC1505...1507, 2SC1755...1757, 2SC1819
24369	2SD1571	800/400V, 3A, 30W	BUT 11(A)F, 2SC3353, 2SC3749, 2SC4304
24370	2SD1572	60V, 8A, 40W, B>1000	BD 645, BD 897, BDW 73A, BDX 53A
24371	2SD1573	600/600V, 0,1A, 1W	-
24372	2SD1574	100V, 1A, 10W, B>4000	2SD1465, 2SD1980
24373	2SD1575	1500/700V, 2A, 40W	BU 505F
24374	2SD1576	1500/700V, 2A, 80W	BU 705F, 2SD1543, 2SD1653, 2SD1882
24375	2SD1577	1500/700V, 5A, 100W	BU 2508AF, 2SC3884A, 2SC3894, 2SC4142
24376	2SD1577FI	2SD1577	2SD1577
24377	2SD1578	30V, 0,7A, 0,5W, B550	2SC3225, 2SC4204, 2SC4389, 2SD1984
24378	2SD1579	150V, +-1,5A, 1W, B>2000	2SD1659, 2SD2213
24379	2SD158(F)	200/200V, 1A, 30W, 15MHz	BUW 40, TIP 47...50, 2SC782, 2SC2354
24380	2SD1580	100V, 7A, 40W, 5MHz	BD 243C, BD 543C, BD 801, 2SD550
24381	2SD1581	30V, 2A, 1W, 350MHz	2SC4389, 2SD1779
24382	2SD1582	60V, 1A, 1W, 250MHz	2SD1779
24383	2SD1583(Z)	30V, 2A, B>800, 270MHz	2SC3474
24384	2SD1584	60V, 3A, B>800, >50MHz	2SD1755
24385	2SD1585	2SD1567, , 15W	2SC3690, 2SC3851...52, 2SD1913
24386	2SD1586	2SD1568, , 20W	2SC3691, 2SD1407, BD 243C, BD 539C
24387	2SD1587	200/150V, 2A, 25W, 5MHz	2SC4382, BD 239F, 2SC2660, 2SD760
24388	2SD1588	100/60V, 7A, 30W	2SC3568, 2SC3692, 2SC4335, 2SD1411
24389	2SD1589	100V, +-5A, 20W, B8000	BD 647F, 2SD1785, 2SD1829, 2SD1928



24390	2SD159(F)	2SD158, 300/300V	BUW 40, TIP 47...50, 2SC782, 2SC2354
24391	2SD1590	150V, 8A, 25W, B6000	2SD1591, 2SD1792, 2SD1974
24392	2SD1591	150V, 10A, 30W, B6000	2SD1794, 2SD1500
24393	2SD1592	30W, B1000	2SD1409
24394	2SD1593	60V, 3A, 110MHz, B>800	2SD1972, 2SD2127
24395	2SD1594	B>800	2SC4553, 2SD1947
24396	2SD1595	60V, 5A, 20W, B6000	2SD1415...17, 2SD1589, 2SD1826
24397	2SD1597	120V, 30A, 80W, B>1000	-
24398	2SD1598	60V, 1A, 10W, B8000	2SC2871, 2SD1465, 2SD1164, 2SD1800
24399	2SD1599	80V, 4A, 40W, B>1000	BDW 23B, BDW 53B, BDW 63B, 2SD837A
24400	2SD16	2SD15, 100V	BD 245C, BDV 95, 2N5758...5759
24401	2SD160	100V, 1,5A, 25W, -/3,5µs	BD 237, BD 239C, BD 937, 2SC2275A
24402	2SD1600	80V, 8A, 40W, B>1000	BD 647, BD 899, BDW 73B, BDX 53B
24403	2SD1601	60V, 4A, 40W, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
24404	2SD1602	2SD1601, 80V	BD 717, BDW 23B, BDW 53B, 2SD837A
24405	2SD1603	60V, 8A, 40W, B>1000	BD 645, BD 897, BDW 73A, BDX 53A
24406	2SD1604	2SD1604, 80V	BD 647, BD 899, BDW 73B, BDX 53B
24407	2SD1605	120V, 3A, 30W, B>1000	BDW 53D, BDW 63D, 2SD830, 2SD1147
24408	2SD1606	120V, 6A, 40W, B>1000	BDT 21, BDW 63D, 2SD830, 2SD1147
24409	2SD1607	120V, 10A, 40W, B5000	BDT 63C, BDT 65D, BDX 33D, 2SD1126
24410	2SD1608	B>5000	BD 649F, BDT 63CF, 2SD1773, 2SD1590
24411	2SD1609	160/160V, 0,1A, 140MHz	BF 415, BF 457...459, 2SC3416, 2SC3502
24412	2SD161	120V, 10A, 100W, -/5µs	BDX 11, 2N3442, 2SD551, 2SD732...733
24413	2SD1610	2SD1609, 200/200V	BF 415, BF 458...459, 2SC3416, 2SC3502
24414	2SD1611	B>500	-
24415	2SD1612	120V, 6A, 40W, B5000	BDW 63D, BDW 73D, BDX 53D, 2SD1147
24416	2SD1612	120V, 6A, 40W, B5000	BDW 63D, BDW 73D, BDX 53D, 2SD1147
24417	2SD1613	120V, 8A, 40W, B5000	BDW 73D, BDX 33D, BDX 53D, 2SD651
24418	2SD1613	120V, 8A, 40W, B5000	BDW 73D, BDX 33D, BDX 53D, 2SD651
24419	2SD1614	40V, 2A, 200MHz	2SC2873, 2SD1119, 2SD1766
24420	2SD1615	60V, 1A, >80MHz	2SC3444, 2SD1622...23, 2SC4409
24421	2SD1615A	2SD1615, 120V	2SC3646, 2SD1418...19
24422	2SD1616	60V, 1A, 0,75W, 160MHz	2SC4485...86, 2SD1207, 2SD1835
24423	2SD1616A	2SD1616, 120V	2SC4488...89, 2SD1812, 2SD1857
24424	2SD1617	40V, 3A, 1W, 200MHz	2SC4487, 2SD1347
24425	2SD1618	20V, 0,7A, 250MHz	2SC2982, 2SC3443
24426	2SD1619	25V, 1A, 180MHz	BC 868, BCX 68, BCX 54...56, 2SC3444
24427	2SD162	20V, 0,03A, 0,65W	-
24428	2SD1620	30V, 3A, 200MHz	2SC4541, 2SD1624
24429	2SD1621	30V, 2A, 150MHz	2SC2982, 2SD1620
24430	2SD1622	60V, 1A, 150MHz	2SC3444, 2SC1615, 2SC5026
24431	2SD1623	60V, 2A, 150MHz	2SC4409
24432	2SD1624	60V, 3A, 150MHz	2SC4541
24433	2SD1625	80V, 0,7A, B>5000, 200MHz	BST 51...52, 2SD1511
24434	2SD1626	80V, 1,5A, B>4000, 120MHz	2SD1472



24435	2SD1627	30V, 2A, B>4000, 120MHz	2SD1784
24436	2SD1628	60V, 5A, 30/340ns	-
24437	2SD1629	60V, +-1,2A, 10W, B>2000	-
24438	2SD163	60V, 10A, 100W, 1,56/6µs	BD 311, 2N3055, 2N5632...33, 2SD426
24439	2SD1630	60V, +-1A, 10W, B>2000	2SC4340...41
24440	2SD1631	2SD1140, 1W	2SD1536, 2SD1786, 2SD1861, 2SD2046
24441	2SD1632	1500V, 4A, 70W	BU 508DF, 2SD1554, 2SD1650, 2SD2089
24442	2SD1633	B>1500	2SD1589, 2SD1785, 2SD1829, 2SD1928
24443	2SD1634	B>1500	2SD1415, 2SD1590...91, 2SD1791
24444	2SD1635	1500V, 5A, 100W, B100	-
24445	2SD1636	300V, 0,07A, 1W, 80MHz	BF 299, BF 487, BF 420A, 2SC3468
24446	2SD1637	60V, 2A, 15W, B>1000	-
24447	2SD1638	100V, 2A, 15W, B1k..10k	2SD1376, 2SD1953
24448	2SD1639	100V, 2,2A, 10W(Tc25°)	BUY 41, 2N4300, 2SC1680
24449	2SD164	2SD163, 100V	BD 317, 2N3055, 2N5632...33, 2SD426
24450	2SD1640	120V, 2A, 150MHz, B>4000	-
24451	2SD1641	55V, 4A, 80W, 45MHz, B>500	-
24452	2SD1642	100V, 2A, 0,7W	2SC4489, 2SD1015, 2SD2182
24453	2SD1643	80V, 3A, 50W, 50MHz, B>500	-
24454	2SD1643A	2SD1643, 100V	-
24455	2SD1644	95V, 1A, B10000	BST 52, 2SD1511
24456	2SD1645	60V, 1A, 150MHz, B4k..40k	-
24457	2SD1646	2SD1638, 25W	BDT 61B, BDW 53C, 2SD837B
24458	2SD1647	2SD1637, 25W	-
24459	2SD1648	30V, 0,02A	-
24460	2SD1649	1500/800V, 2,5A, 50W	2SD705DF, 2SD1553, 2SD1876, 2SD2367
24461	2SD165	2SD163, 150V	BDX 11, 2N3442, 2SD551, 2SD732...733
24462	2SD1650	1500/800V, 3,5A, 50W	BU 706DF, 2SD1554, 2SD1877, 2SD2089
24463	2SD1650FI	2SD1650	BU 706DF, 2SD1554, 2SD1877, 2SD2089
24464	2SD1651	1500/800V, 5A, 60W	BU 2508DF, 2SD1555, 2SD2095, 2SD2125
24465	2SD1652	1500/800V, 6A, 60W	BU 2508DF, 2SC4293, 2SD1556, 2SD2125
24466	2SD1653	1500/800V, 2,5A, 50W	BU 705F, 2SD1543, 2SD1882, 2SC3483
24467	2SD1654	1500/800V, 3,5A, 50W	BU 706F, 2SD1544, 2SD1883, 2SC3484
24468	2SD1655	1500/800V, 5A, 50W	BU 2508AF, 2SC3894, 2SC4142, 2SD1545
24469	2SD1656	1500/800V, 6A, 50W	BU 2508AF, 2SC3894, 2SC4294, 2SD1546
24470	2SD1657	25V, 0,7A, 0,6W, 150MHz	BC 337...338, BC 635, BC 637, 2SD1578
24471	2SD1658	60V, 2A, 10W, B5000	-
24472	2SD1659	150V, +-1,5A, 1W, B10000	2SD1579, 2SC2213
24473	2SD166	2SD163, 200V	MJ 15015, BDW 16, 2SC1585...86, 2SD665
24474	2SD1660(M)	2SD1638, 1W	2SD1978, 2SD1981, 2SD2067, 2SD2206
24475	2SD1661(M)	2SD1637, 1W	-
24476	2SD1662	100V, 15A, 100W, B5000	BDV 67A, BDW 83C, 2SD1026
24477	2SD1663	1500V, 5A, 80W	BU 706, 2SC3884A, 2SC3894, 2SD1655
24478	2SD1664	40V, 1A, 150MHz	BCX 54...56, 2SC3444, 2SD874A
24479	2SD1665(M)	120/120V, 1,5A, 1W, 80MHz	2SD1015, 2SD1812, 2SD1857

24480	2SD1665A(M)	2SD1665, 160/160V	2SD1812, 2SD1857A, 2SC4614
24481	2SD1666	60V, 3A, 25W, 8MHz	2SC3299, 2SC3852, 2SD1585, 2SD2012
24482	2SD1667	60V, 5A, 25W, 30MHz	2SC3299, 2SC3746, 2SD1411
24483	2SD1668	60V, 7A, 30W, 10MHz	2SC3747, 2SD1412
24484	2SD1669	60V, 12A, 30W, 10MHz	2SC3709, 2SC4065
24485	2SD167	20V, 0,5A, 0,2W	AC 127, AC 176, AC 187, 2SD72, 2SD352
24486	2SD1670	150/100V, +-10A, 65W, B9000	2SD1895
24487	2SD1671	150/100V, +-15A, 70W, B3500	-
24488	2SD1672	150/100V, 25A, 70W, B3500	-
24489	2SD1673	500/400V, 10A, 70W, B600	BU 922, BUW 81, MJ 10003, 2SD685
24490	2SD1676	RbRbe6,8kOhm	DTC 363ES
24491	2SD1677	1500/800V, 5A, 100W	BU 508A, BU 908, 2SC3485, 2SC3685
24492	2SD1678	100V, 15A, 100W, B5000	2SD1087, 2SD1129
24493	2SD1679	18V, 0,5A, 170MHz	-
24494	2SD168	80V, 10A, 50W, B2500	BDV 65A, BDX 83B, BDX 85B, MJ3000...01
24495	2SD1680	330/200V, 7A, 70W, 30MHz	BU 124A, 2SC2305, 2SC2656, 2SD917
24496	2SD1681	20V, 1,2A, 10W, 150MHz	2SC3244, BD 135, BD 226
24497	2SD1682	60V, 2,5A, 10W, 140MHz	BD 785, 2SD1348
24498	2SD1683	60V, 4A, 10W, 150MHz	BD 785, 2SD1348
24499	2SD1684	120V, 1,5A, 10W, 120MHz	2SC3621, 2SC2481, 2SC2690(A)
24500	2SD1685	60V, 5A, 10W, 120MHz	BDX 35...37, 2SD826
24501	2SD1686	120V, 3A, 20W, B5000	2SD1785, 2SD2015, BDW 53D, BDW 63D
24502	2SD1686	120V, 3A, 20W, B5000	2SD1785, 2SD2015, BDW 53D, BDW 63D
24503	2SD1687	60V, 3A, 20W, B5000	BDT 61F, 2SD1413, 2SD1796, 2SD1987
24504	2SD1687	60V, 3A, 20W, B5000	BDT 61F, 2SD1413, 2SD1796, 2SD1987
24505	2SD1688	120V, 8A, 25W, B7000	BD 649F, 2SD1590...91, 2SD1773
24506	2SD1688	120V, 8A, 25W, B7000	BD 649F, 2SD1590...91, 2SD1773
24507	2SD1689	120V, 6A, 25W, B5000	BD 649F, 2SD1336, 2SD1773, 2SD1785
24508	2SD1689	120V, 6A, 25W, B5000	BD 649F, 2SD1336, 2SD1773, 2SD1785
24509	2SD1690	120V, 8A, 25W, B5000	BD 649F, 2SD1590...91, 2SD1773, 2SD1792
24510	2SD1690	120V, 8A, 25W, B5000	BD 649F, 2SD1590...91, 2SD1773, 2SD1792
24511	2SD1691	60V, 5A, 20W, <1/3,5µs	2SD826
24512	2SD1692	150V, 3A, 15W, B>2000	2SC4342
24513	2SD1693	60V, 3A, 15W, B>2000	-
24514	2SD1694	60V, 3A, 20W, B>800	-
24515	2SD1695	31V, +-2A, B>2000	-
24516	2SD1696	+-4A, B10000	-
24517	2SD1697	100V, +-0,8A, 1W, B>4000	2SC1879, 2SD1660, 2SD1978, 2SD1981
24518	2SD1698	2SD1697, 0,75W	2SD1697
24519	2SD1699	2SD1697, SMD	BST 52, 2SD1511
24520	2SD17	2SD15, 150V	BD 245D, BDX 11, 2N3442, 2SD731...732
24521	2SD170	25V, 0,5A, 0,2W	AC 127, AC 176, AC 187, 2SD72, 2SD352
24522	2SD1700	2SD1697	-
24523	2SD1701	2SD1698, 60+-10V	-
24524	2SD1702	2SD1699, 60+-10V	-

24525	2SD1703	160/160V, 12A, 120W	BD 745F, 2SC3907, 2SD1047
24526	2SD1704	170/170V, 15A, 150W	2SC3281, 2SD1718, 2SD1975, 2SD2155
24527	2SD1705	130/80V, 10A, 70W, 20MHz	2SC4690, BD 245D, 2SC2706, 2SC2837
24528	2SD1706	130/80V, 15A, 80W, 20MHz	2SC3762, 2SC4886, (BD 745E, 2SC2987A
24529	2SD1707	130/80V, 20A, 100W, 20MHz	BD 745E, BD 249D
24530	2SD1708	120V, 2A, B6000	2SD1376, 2SD1953
24531	2SD1709	1500/800V, 5A, 100W	BU 508D, 2SC3481, 2SC3681, 2SC4291
24532	2SD170A	2SD170, 32V	AC 127, AC 176, 2SD352
24533	2SD171-1,-2	-1 450V, -2 600V, 3,5A, 125W	BUS 11(A), BUX 47(A), 2SC3156, 2SD640
24534	2SD1710	1500/800V, 5A, 50W	BU 508AF, 2SC3894, 2SC4142, 2SD1655
24535	2SD1711	1500/800V, 5A, 100W	BU 508DF, 2SC4122, 2SC4293, 2SD1555
24536	2SD1712	100V, 5A, 60W, 20MHz	2SC4385, 2SC5099, 2SD2064...65
24537	2SD1713	120V, 6A, 70W, 20MHz	2SC4385, 2SC5099, 2SD2064...65
24538	2SD1714	140V, 7A, 80W, 20MHz	2SD2065, BD 245D, 2SC2837, 2SD1046
24539	2SD1715	150V, 9A, 100W, 20MHz	2SC4386, 2SC5100, 2SD2052
24540	2SD1716	160V, 12A, 120W, 20MHz	2SC3762, 2SC4886, BD 745F, 2SC2987A
24541	2SD1717	160V, 12A, 120W, 20MHz	2SC3280...3281, 2SD1704, 2SD2029
24542	2SD1718	180V, 15A, 150W, 20MHz	2SC3281, 2SD1975, 2SD2155
24543	2SD1719	100V, 6A, 40W	-
24544	2SD172	60V, 10A, 100W	BD 245A, BD 315, 2N3055, 2N5877...78
24545	2SD1720	80V, 5A, 40W, 8MHz	BD 243B, BD 543B, BD 951, 2SD613
24546	2SD1721	60V, 2A, 1W	MPS 650...651, 2SC3328, 2SD1207
24547	2SD1722	60V, 5A, 20W, 180MHz	2SD826, 2SD1685
24548	2SD1723	60V, 8A, 20W, 180MHz	-
24549	2SD1724	120V, 3A, 20W, 180MHz	-
24550	2SD1725	120V, 4A, 20W, 180MHz	-
24551	2SD1726	150/100V, 7A, 25W, B>1500	2SD1590...91
24552	2SD1727	1500/700V, 1,5A, 60W	BU 705D, 2SC3479, 2SD1290...1291
24553	2SD1728	1500/700V, 2,5A, 60W	BU 705D, 2SC3479, 2SD1290...1291
24554	2SD1729	1500/700V, 3,5A, 60W	BU 706D, 2SC3480
24555	2SD173	2SD172, 100V	BD 245C, BD 317, 2N3055, 2N5632...33
24556	2SD1730	1500/700V, 5A, 100W	BU 508D, 2SC3481, 2SC3681, 2SC4291
24557	2SD1731	1500/700V, 6A, 100W	BU 508D, 2SC3482, 2SC3681, 2SC4292
24558	2SD1732	1500/700V, 7A, 120W	BU 508D, BU 2508D, 2SC3682...3683
24559	2SD1733(F5)	120V, 1A, 10W, 100MHz	2SC4134, 2SD1074...75, 2SD1283...1284
24560	2SD1734	1500/700V, 1,5A, 40W	BU 505F, 2SD1575, 2SD1390
24561	2SD1735	1500/700V, 1,5A, 60W	BU 705F, 2SD1542, 2SD1653, 2SD1882
24562	2SD1736	1500/700V, 2,5A, 60W	BU 705F, 2SD1543, 2SD1653, 2SD1882
24563	2SD1737	1500/700V, 3,5A, 60W	BU 706F, 2SD1544, 2SD1654, 2SD1883
24564	2SD1738	1500/700V, 5A, 100W	BU 706F, 2SD1545, 2SD1655, 2SD1884
24565	2SD1739	1500/700V, 6A, 100W	BU 508AF, 2SD1546, 2SD1656, 2SD1885
24566	2SD174(F)	60V, 5A, 50W	BD 245A, BDV 91, BDX 91, 2N5873...74
24567	2SD1740	150/100V, 5A, 30W, B>700	2SD1590, 2SD1315, 2SD1336
24568	2SD1741(A)	2SD1250(A), 15W	2SD1033, 2SD1557
24569	2SD1742	2SD1252(A), 15W	2SC3386, 2SD1221, 2SD1802

24570	2SD1743	2SD1253(A), 15W	2SC3074, 2SC3518, 2SC3592, 2SD1803
24571	2SD1744	2SD1254, 15W	-
24572	2SD1745	2SD1255, 15W	-
24573	2SD1746	2SD1256, 15W	-
24574	2SD1747(A)	2SD1257(A), 15W	-
24575	2SD1748(A)	2SD1260(A), 15W	2SD1222, 2SD1817
24576	2SD1749(A)	2SD1261(A), 15W	2SD1223, 2SD1520
24577	2SD175(F)	2SD174, 100V	BD 245C, BDV 95, BDX 95, 2N5758...59
24578	2SD1750(A)	2SD1262(A), 15W	-
24579	2SD1751	2SD1480, 15W	2SD1079, 2SD1281...1282
24580	2SD1752(A)	2SD1445(A), 15W	-
24581	2SD1753	2SD1258, 15W	-
24582	2SD1754(A)	2SD1259(A), 15W	-
24583	2SD1755	2SD1719, 15W	-
24584	2SD1756	200/200V, 10A, 40W, B>1500	-
24585	2SD1757K	30V, 0,5A, 150MHz	2SC3265, 2SC4519
24586	2SD1758(F5)	40V, 2A, 10W, 100MHz	2SC3076, 2SD1078...79, 2SD1801
24587	2SD1759(F5)	40V, 2A, 10W, B>1000	2SD1222, 2SD1817, BD 411...412, MPSU 45
24588	2SD176	90V, 10A, 100W	BD 245C, BD 317, 2N3055, 2N5632...33
24589	2SD1760(F5)	60V, 3A, 15W, 90MHz	2SC3592, 2SC3386, 2SD1221, 2SD1802
24590	2SD1761	80V, 3A, 30W, 8MHz	2SC3690, 2SC3746, 2SC3851, 2SD1586
24591	2SD1762	60V, 3A, 25W, 70MHz	2SC3299, 2SC3690...91, 2SC3746, 2SD1913
24592	2SD1763	120/120V, 1,5A, 20W, 80MHz	2SC3298(A,B), 2SC3364, 2SC3564, 2SC4370
24593	2SD1763A	2SD1763, 160/160V	2SC3298(A,B), 2SC4159, 2SC4370
24594	2SD1764	60V, 2A, 20W, B>1000	BDT 61F, 2SD1413, 2SD1796, 2SD1825
24595	2SD1765	100V, 2A, 20W, B>1000	2SD1414, 2SD1788, 2SD1828, 2SD2015
24596	2SD1766	40V, 2A, 100MHz	2SC2873, 2SD1623, 2SD1766
24597	2SD1767	80V, 0,7A, 120MHz	BCX 56, 2SD1005, 2SD1368, 2SD1418...19
24598	2SD1768(S)	100V, 1A, 0,3W, 100MHz	BC 639, 2SD667, 2SD774, 2SD1616A
24599	2SD1769	B>2000	BD 651, BDT 21, BDW 73D, BDX 53D
24600	2SD177(M)	2SD176, 120V	BDX 11, 2N3442, 2SD551, 2SD732...733
24601	2SD1770	200/150V, 1A, 25W, 20MHz	BD 239F, 2SC2238B, 2SD387(A), 2SD1138
24602	2SD1770A	2SD1770, 200/180V	BD 239F, 2SC2238B, 2SD387(A), 2SD1138
24603	2SD1771(A)	2SD1770(A)	2SD1250, BD 239F, 2SC2238B, 2SD1138
24604	2SD1772(A)	2SD1770(A)	2SC3298B, 2SC4382, 2SD1587, 2SD2337
24605	2SD1773	50W,20MHz,B>1000	BD 649F, BDT 63CF, 2SD1590...91
24606	2SD1774	80V, 2A, 25W, 40MHz, B>500	2SC3852, 2SD1157, 2SD1943, 2SC1983
24607	2SD1774A	2SD1774, 100V	-
24608	2SD1775(A)	2SD1774(A)	2SD1259(A)
24609	2SD1776(A)	2SD1774(A)	2SD1273(A), 2SD1944, 2SD2092
24610	2SD1777	2SD1676, SMD	-
24611	2SD1778(A)	80V, 4A, 40W, 8MHz	BD 243B, BD 537, BD 951, 2SC3179
24612	2SD1779	60V, 2A, 1W, B>800	-
24613	2SD178	20V, 0,3A, 0,225W	AC 127, AC 176, AC 187, 2SD72, 2SD352
24614	2SD1780	2SD1779	-

24615	2SD1781K	40V, 0,8A, 150MHz	BCW 65...66, BCX 41
24616	2SD1782K	80V, 0,7A, 180MHz	BCW 66, BCX 41
24617	2SD1783	60V, 5A, 30W, B>2000	BD 645, BD 897, BDW 23A, BDW 63A
24618	2SD1784	2SD1140, SMD	2SD1626...1627
24619	2SD1785	B>2000	2SD1336, 2SD1590
24620	2SD1786	40V, 2A, 0,9W, B20000	2SD1153, 2SD1536, 2SD1861, 2SD1929
24621	2SD1787	50V, 0,5A, 0,4W, 250MHz	BC 337, BC 635, BC 637, 2SD1226
24622	2SD1788	50MHz, B>1,5k	2SD1891...92, 2SD2014
24623	2SD1788	50MHz, B>1,5k	2SD1891...92, 2SD2014
24624	2SD1789	2SD1788, 200/200V	-
24625	2SD1789	2SD1788, 200/200V	-
24626	2SD178A	2SD178, 40V	AC 127, AC 176, 2SD352
24627	2SD178B	2SD178, 60V	-
24628	2SD179	300/300V, 40A, 580W	-
24629	2SD1790	2SD1788, 60V	-
24630	2SD1790	2SD1788, 60V	-
24631	2SD1791	B1,5k..30k	2SD1793, 2SD1415, 2SD1830
24632	2SD1791	B1,5k..30k	2SD1793, 2SD1415, 2SD1830
24633	2SD1792	2SD1791, 200/200V	2SD1794
24634	2SD1792	2SD1791, 200/200V	2SD1794
24635	2SD1793	50MHz, B1,5k..30k	2SD1591, 2SD2163
24636	2SD1793	50MHz, B1,5k..30k	2SD1591, 2SD2163
24637	2SD1794	2SD1793, 200V	2SD2101
24638	2SD1794	2SD1793, 200V	2SD2101
24639	2SD1795	B>150	-
24640	2SD1795	B>150	-
24641	2SD1796	60V, 4A, 25W, 60MHz, B>2000	2SD1788, 2SD1987, 2SD1825
24642	2SD1797	60V, 7A, 30W, B>800	BD 645F, 2SD1416...17, 2SD1791, 2SD1826
24643	2SD1798	300/300V, 0,3A, 15W, B5000	2SD1502
24644	2SD1799	B>4000	2SC3132, 2SD1222...1223
24645	2SD18	2SD15, 200/85V	BD 245F, 2SC3263, 2SD555, 2SD751
24646	2SD180	80V, 5A, 50W, 10MHz	BD 245B, BD 313, 2N5758, 2SD895...896
24647	2SD1800	B>4000	2SD1817, 2SD1980, 2SD2410
24648	2SD1801	60V, 2A, 15W, 150MHz	2SC3303, 2SD1815...1816
24649	2SD1802	60V, 3A, 15W, 150MHz	2SC3303, 2SD1815...1816
24650	2SD1803	60V, 5A, 20W, 180MHz	2SC3074, 2SC3303, 2SD1805
24651	2SD1804	60V, 8A, 20W, 180MHz	2SC4668
24652	2SD1805	60V, 5A, 15W, 120MHz	2SC3074, 2SC3303, 2SD1803
24653	2SD1806	Rbe1kOhm	-
24654	2SD1807	2SD889, 0,3W	2SD889
24655	2SD1808(A)	2SD892(A), 0,3W	2SD892(A)
24656	2SD1809	60V, 1A, 0,9W, B>2000	2SD1153, 2SD1660, 2SD1978, 2SD1981
24657	2SD181	150/100V, 15A, 100W, 10MHz	MJ 15015, BD 745E, BDW 12, 2SC2607...08
24658	2SD1810	20V, 2A, 0,5W, 80MHz	2SC3226, 2SD787...88, 2SD1100, 2SD1207
24659	2SD1811	2SD1810, SMD	2SC2883, 2SC2982, 2SC3443, 2SC3439



24660	2SD1812	160V, 1,5A, 0,9W, 80MHz	2SC4614, 2SD1665A, 2SD1857A
24661	2SD1813	70V, 4A, 25W	2SC3691, 2SC3746, 2SC3851, 2SD1586
24662	2SD1813	70V, 4A, 25W	2SC3691, 2SC3746, 2SC3851, 2SD1586
24663	2SD1814	120V, 10A, 30W, B5000	2SD1591, BDT 63C, BDX 33D, 2SD1607
24664	2SD1814	120V, 10A, 30W, B5000	2SD1591, BDT 63C, BDX 33D, 2SD1607
24665	2SD1815	120V, 3A, 20W, 180MHz	-
24666	2SD1816	120V, 4A, 20W, 180MHz	-
24667	2SD1817	80V, 3A, 15W, B>2000	2SD1223, 2SD1520, 2SD1955
24668	2SD1818	60V, 3A, 10W, 120MHz	2SD1348
24669	2SD1819	2SD601	BC 848W, 2SC4081, 2SC4128, 2SC4155
24670	2SD1819A	2SD601A	BC 846W, 2SC4117, 2SC4141, 2SC4177
24671	2SD181A	2SD181, 250/200V, 10A	BUX 17(A...C), BUX 42, 2SC1586, 2SD583
24672	2SD182(F)	40V, 1A, 10W	BD 135, BD 226, BD 507, BD 825
24673	2SD1820	2SD602	BC 818W, 2SC4097, 2SC4118, 2SD1949
24674	2SD1820A	2SD602A	PMST 4401
24675	2SD1821	2SD814	-
24676	2SD1821A	2SD814A	-
24677	2SD1822	25V, 0,5A, 200MHz	2SD1820
24678	2SD1823	2SD1010	2SC4413
24679	2SD1824	2SD1149	-
24680	2SD1825	70V, 4A, 20W, 20MHz, B5000	2SD1589, 2SD1788, 2SD1933, 2SD2014
24681	2SD1826	70V, 7A, 25W, 20MHz, B5000	2SD1415...16, 2SD1791
24682	2SD1827	70V, 10A, 30W, 20MHz, B5000	BDT 63AF, 2SD1591, 2SD1793, 2SD2163
24683	2SD1828	110V, 3A, 20W, 20MHz, B4000	2SD1785, 2SD1891...92, 2SD2014...15
24684	2SD1829	110V, 5A, 25W, 20MHz, B4000	2SD1315, 2SD1336, 2SD1785, 2SD2025
24685	2SD183(F)	2SD182, 100V	BD 139, BD 230, BD 529, BD 829
24686	2SD1830	110V, 8A, 30W, 20MHz, B4000	BD 649F, 2SD1590, 2SD1773, 2SD2025
24687	2SD1831	100V, 12A, 60W, 30MHz	-
24688	2SD1832	80V, 5A, 30W, 8MHz	2SC3691, 2SC3746, 2SD1588, 2SD1940
24689	2SD1833	100V, 7A, 30W, 5MHz	2SC3692, 2SC4550, 2SD1411, 2SD1588
24690	2SD1834	60V, 1A, B>2000	BST 50...52, 2SD1470, 2SD1511
24691	2SD1835	60V, 2A, 150MHz, 60/580ns	2SC3328, 2SD1207, 2SD2182, 2SD2485
24692	2SD1836	60V, 2A, 20W, B4000	2SC3986, 2SD1413, 2SC1983, 2SD2051
24693	2SD1837	50V, 3A, 20W, 20MHz, B4000	2SC3987, 2SD1413, 2SD1825, 2SD1987
24694	2SD1838	50V, 5A, 25W, 20MHz, B4000	2SD1790, 2SD1796, 2SD1825, 2SD1987
24695	2SD1839	365/365V, 5A, 80W, B2000	-
24696	2SD184	60V, 1,5A, 25W, -/3,5µs	BD 165, BD 233, BD 239A, BD 241A
24697	2SD1840	110V, 15A, 100W	-
24698	2SD1841	110V, 25A, 120W	-
24699	2SD1842	110V, 40A, 150W	-
24700	2SD1843	60V, +-1A, 1W, B>2000	-
24701	2SD1843A	2SD1843, 80V	-
24702	2SD1844	1500/700V, 1,5A, 60W	BU 705DF, 2SD1553, 2SD1649, 2SD1727
24703	2SD1845	1500/700V, 2,5A, 60W	BU 705DF, 2SD1553, 2SD1649, 2SD2367
24704	2SD1846	1500/700V, 3,5A, 60W	BU 706DF, 2SD1554, 2SD1650, 2SD2369



24705	2SD1847	1500/700V, 5A, 100W	BU 706DF, 2SC4122, 2SC4293, 2SD1555
24706	2SD1848	1500/700V, 6A, 100W	BU 508DF, 2SC4122, 2SC4294, 2SD1556
24707	2SD1849	1500/700V, 7A, 120W	BU 508DF, 2SC4123, 2SC4769, 2SC4916
24708	2SD185	2SD184, 100V	BD 169, BD 237, BD 239C, BD 241C
24709	2SD1850	1500/700V, 7A, 120W	BU 508AF, 2SC3885A, 2SC3895, 2SD1547
24710	2SD1851	2SD1852, SMD	BCV 47
24711	2SD1852	80V, 0,2A, 0,3W, B>5000	MPSA 28...29
24712	2SD1853	80V, 1,5A, 0,7W, B>2000	2SD1153, 2SD1660
24713	2SD1854	2SD1853, 1W	2SD1153, 2SD1660, 2SD1978, 2SD1981
24714	2SD1855(A)	80V, 4A, 30W, 8MHz	2SC3851, 2SC3691, 2SD1408, 2SD2000
24715	2SD1856	60V, 5A, 25W, B>2000	2SD1417, 2SD1589, 2SD1595, 2SD1826
24716	2SD1857	2SD1665(M)	2SD1665
24717	2SD1858	2SD1225(M)	2SD1225
24718	2SD1859	2SD1226(M)	2SD1226
24719	2SD186	25V, 0,15A, 0,2W	AC 127, AC 176, AC 187, 2SD30, 2SD72
24720	2SD1860	2SD1228(M)	2SD1228
24721	2SD1861	2SD1536(M)	2SD1536
24722	2SD1862	2SD1227(M)	2SD1227
24723	2SD1863	2SD1293(M)	2SD1293
24724	2SD1864	2SD1507(M)	2SD1507
24725	2SD1865	2SD1469M	2SD1469M
24726	2SD1866(M)	2SD1661(M)	2SD1661
24727	2SD1867(M)	2SD1660(M)	2SD1660
24728	2SD1868	160/160V, 0,1A, 0,9W, 140MHz	BF 391...393, 2SC3248, 2SC3467
24729	2SD1869	2SD1868, 200/200V	BF 391...393, 2SC3467...3469
24730	2SD187	25V, 0,15A, 0,2W	AC 127, AC 176, AC 187, 2SD30, 2SD72
24731	2SD1870	30V, 1A, B1k..3k	2SC3727, 2SD1950
24732	2SD1871	40V, 2A, 10W	2SC3076, 2SD1078...79, 2SD1801...02
24733	2SD1872	60V, 1,5A, 10W	2SD1079, 2SD1221, 2SD1801...02, 2SD1282
24734	2SD1873	110V, 0,8A, 10W	2SC4134, 2SD1074...75, 2SD1283...84
24735	2SD1874	130V, 0,8A, 10W	2SC2983, 2SC4027, 2SD1080...82, 2SD1220
24736	2SD1875	50V, 1,5A, 10W, B10000	2SD1509, BD 677, BD 777, 2SD1376
24737	2SD1876	1500/800V, 3A, 50W	BU706DF, 2SD1553...54, 2SD1650, 2SD2089
24738	2SD1877	1500/800V, 4A, 50W	BU 706DF, 2SD1554, 2SD1650, 2SD2089
24739	2SD1878	1500/800V, 5A, 60W	BU 706DF, 2SD1555, 2SD2095, 2SD2125
24740	2SD1879	1500/800V, 6A, 60W	BU 508DF, 2SC4294, 2SD1556, 2SD2125
24741	2SD188(S)	100V, 7A(S5A), 60W, 10MHz	BD 245C, BD 317, 2N5758, 2SD895...896
24742	2SD1880	1500/800V, 8A, 70W	BU 508DF, 2SC3893A, 2SC4124, 2SC4531
24743	2SD1881	1500/800V, 10A, 70W	BU 2520DF, 2SC4125, 2SC4531, 2SC4878
24744	2SD1882	1500/800V, 3A, 50W	BU 706F, 2SD1544, 2SD1654, 2SD2381
24745	2SD1883	1500/800V, 4A, 50W	BU 706F, 2SD1544, 2SD1654, 2SD2381
24746	2SD1884	1500/800V, 5A, 60W	BU 706F, 2SC4142, 2SD1545, 2SD1655
24747	2SD1885	1500/800V, 6A, 60W	BU 508AF, 2SC4143, 2SD1546, 2SD1656
24748	2SD1886	1500/800V, 8A, 70W	BU 508AF, 2SC3886A, 2SC3896, 2SC4758
24749	2SD1887	1500/800V, 10A, 70W	BU 2520AF, 2SC3897, 2SC4542, 2SC4759

24750	2SD1888	120/120V, 6A, 40W, B5000	BD 651, BDT 21, BDW 63D, BDW 73D
24751	2SD1889	2SD1888, , 30W	2SD1785, 2SD2025, 2SD1590
24752	2SD189	80V, 5A, 50W, 12MHz	BD 245B, BDV 93, BDX 93, 2N5632...33
24753	2SD1890	B>5000	2SD1315, 2SD1828, 2SD2129, 2SD2257
24754	2SD1891	B>5000	2SD1315, 2SD1829, 2SD2014
24755	2SD1892	B>5000	2SD1315, 2SD1785
24756	2SD1893	B>5000	2SD2438
24757	2SD1894	B>5000	2SD2438
24758	2SD1895	B>5000	2SD2439
24759	2SD1896	100V, 5A, 40W, 8MHz	BD 243C, BD 539C, BD 953, 2SC3258
24760	2SD1897	2SD1896, , 30W	2SC3691, 2SD1407, 2SD1588, 2SD1940
24761	2SD1898	100V, 1A, 100MHz	BCX 56, 2SD1005, 2SD1386, 2SD1418...19
24762	2SD1899(Z)	60V, 3A, 10W, 120MHz	2SC3386, 2SD1221, 2SD1802, 2SD1815...16
24763	2SD189A	2SD189, 100V	BD 245C, BDV 95, BDX 95, 2N5632...33
24764	2SD19	25V, 0,3A, 0,15W, B31	AC 127, AC 176, AC 187, 2SD72, 2SD352
24765	2SD190	300V, 0,1A, 4W, 25MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
24766	2SD1900	60V, 4A, 25W, B5000	2SD1790, 2SD1796, 2SD1825, 2SD1987
24767	2SD1900	60V, 4A, 25W, B5000	2SD1790, 2SD1796, 2SD1825, 2SD1987
24768	2SD1901	60V, 8A, 25W, B5000	2SD1416...17, 2SD1793, 2SD1826...27
24769	2SD1901	60V, 8A, 25W, B5000	2SD1416...17, 2SD1793, 2SD1826...27
24770	2SD1902	60V, 3A, 30W, 40MHz	2SD1251...52,(BD 241A, BD 535, 2SC3179
24771	2SD1903	60V, 8A, 30W, 120MHz	2SD2199, 2SC3254...55
24772	2SD1904	60V, 5A, 30W, 30MHz	2SD1906, 2SD2198, 2SD2200
24773	2SD1905	60V, 7A, 40W, 10MHz	2SD1907, 2SD2199, 2SD2201
24774	2SD1906	90V, 5A, 30W, 20MHz	2SD1907, 2SD2200...01
24775	2SD1907	90V, 7A, 40W, 20MHz	2SD2201
24776	2SD1908	330/150V, 7A, 50W, 40MHz	BU 406...408, 2SC3173, 2SD884...885
24777	2SD1909	500/300V, 6A, 45W, B>500	2SD1409
24778	2SD191	30V, 0,15A, 0,15W	AC 127, AC 176, 2SD352
24779	2SD1910	1500/600V, 3A, 40W	BU 706DF, 2SD1544, 2SD1650, 2SD2089
24780	2SD1910FI	2SD1910	2SD1910
24781	2SD1911	1500/600V, 5A, 50W	BU 706DF, 2SC4293, 2SC4122, 2SD1651
24782	2SD1912	60V, 3A, 30W, 100MHz	2SC3252, BD 241A, BD 535, BD 539A
24783	2SD1913	2SD1912, , 20W	2SC3299, 2SC3691, 2SC3746
24784	2SD1914	100V, 2A, 10W, B2k..30k	2SD1376, 2SD1953
24785	2SD1915	50V, 0,3A, B>500	2SC3615, 2SC3247, 2SD1582
24786	2SD1916	50V, 2A, 1W, B5000	2SD1153, 2SD1809, 2SD1866, 2SD1853
24787	2SD1917	60V, 1A, B20000	-
24788	2SD1918(F5)	160/160V, 1,5A, 10W, 80MHz	2SC2983, 2SC4027, 2SD1080...82
24789	2SD1919	2SD1055	2SD1055
24790	2SD192	30V, 0,15A, 0,15W	AC 127, AC 176, 2SD352
24791	2SD1920	2SD1469	2SD1469
24792	2SD1921	2SD1787	2SD1787
24793	2SD1922	25V, 0,8A, 0,9W, B600	-
24794	2SD1923	80V, 4A, 25W, B5000	2SD1589, 2SD1928, 2SD1933, 2SD2014

24795	2SD1923	80V, 4A, 25W, B5000	2SD1589, 2SD1928, 2SD1933, 2SD2014
24796	2SD1924	80V, 8A, 25W, B5000	BD 645F, 2SD1415...16, 2SD1793
24797	2SD1924	80V, 8A, 25W, B5000	BD 645F, 2SD1415...16, 2SD1793
24798	2SD1925	120V, 3A, 25W, B5000	BDT 61CF, 2SD1785, 2SD1892, 2SD2014...15
24799	2SD1925	120V, 3A, 25W, B5000	BDT 61CF, 2SD1785, 2SD1892, 2SD2014...15
24800	2SD1926	200/200V, 10A, 30W, B5000	2SD1794, 2SD2101, 2SD1756
24801	2SD1926	200/200V, 10A, 30W, B5000	2SD1794, 2SD2101, 2SD1756
24802	2SD1927	120/120V, 6A, 25W, B5000	BD 649F, 2SD1590, 2SD1773, 2SD1785
24803	2SD1927	120/120V, 6A, 25W, B5000	BD 649F, 2SD1590, 2SD1773, 2SD1785
24804	2SD1927	120/120V, 6A, 25W, B5000	BD 649F, 2SD1590, 2SD1773, 2SD1785
24805	2SD1927	120/120V, 6A, 25W, B5000	BD 649F, 2SD1590, 2SD1773, 2SD1785
24806	2SD1928	100/100V, +-8A, 25W, B>2000	BD 647F, 2SD1415, 2SD1791
24807	2SD1929	60V, 2A, 1,2W, B5000	2SD1854, 2SD1931
24808	2SD193	35V, 0,4A, 0,25W, -/4,7μs	AC 127, AC 176, 2SD352
24809	2SD1930	100V, 2A, 1,2W, B5000	2SD1978, 2SD1981
24810	2SD1931	60V, 2A, 1,2W, B10000	-
24811	2SD1932	80/80V, 4A, 35W, B3000	BD 717, BDW 32B, BDW 53B, BDW 63B
24812	2SD1933	2SD1932, , 30W	BD 647F, 2SD1589, 2SD1788, 2SD1928
24813	2SD1934	2SD965, 1W	2SD966, 2SD1244, 2SD2249, 2SD1961
24814	2SD1935	2SD1936, SMD	2SC3265
24815	2SD1936	15V, 0,8A, 0,3W, 200MHz	2SD1012, 2SD1616, 2SD2322
24816	2SD1937	2SD1211	2SC2235, 2SD667(A), 2SD1616A, 2SD1812
24817	2SD1938	2SD1915, SMD	-
24818	2SD1939	B>2000	2SD1579, 2SD1659, 2SD2213
24819	2SD194	32V, 0,4A, 0,25W	AC 127, AC 176, 2SD352
24820	2SD1940	100V, 6A, 25W, 15MHz	2SC3692, 2SC4550, 2SD1411, 2SD1588
24821	2SD1941	1500/650V, 6A, 50W	BU 508AF, 2SC4143, 2SD1546, 2SD1656
24822	2SD1942	40V, 2A, 1,2W	2SC3328, 2SC4145, 2SD1146, 2SD1207
24823	2SD1943	80V, 3A, 40W, 50MHz, B>400	2SD1157, 2SC1983
24824	2SD1944	2SD1943, , 30W	2SD1273, 2SD2092, 2SD2156, 2SD2375
24825	2SD1945	1000/1000V, 0,5A, 20W	BUX 87
24826	2SD1946	15V, 1A, B800	2SC3439, 2SC4390, 2SD1870
24827	2SD1947	100V, 10A, 70MHz, B>500	2SC4024
24828	2SD1948	60V, 5A, 110MHz, B>500	2SD2075...2076
24829	2SD1949	2SD1484K	PMST 4401
24830	2SD195	20V, 0,05A, 0,15W	AC 127, 2SD30
24831	2SD1950	30V, 2A, B1500	-
24832	2SD1951	20V, 3A, 0,75W, 140MHz	2SC4487, 2SD879, 2SD1617, 2SD1347
24833	2SD1952	2SD1951, SMD	2SD1119, 2SD1620, 2SD1624
24834	2SD1953	120V, 1,5A, 10W, B8000	2SD1376
24835	2SD1955	B>1500	2SC4339
24836	2SD1956	120V, 7A, 40W, 40MHz, B300	-
24837	2SD1957	2SD1956, , 30W	-
24838	2SD1958	200/60V, 4,5A, 30W, 10MHz	2SC4153
24839	2SD1959	1400/650V, 10A, 50W	BU 2520AF, 2SC3897, 2SC4542, 2SD1548

24840	2SD196(A)	100/50V, 10A, 125W(A150W)	BD 249C, BD 745C, 2SD1049
24841	2SD1960	30V, 5A, 0,75W, 170MHz	2SC4482, 2SD1145
24842	2SD1961	50V, 5A, 1,2W, 150MHz	2SC3671, 2SC4482, 2SD1145, 2SD2097
24843	2SD1962(M)	2SD1961, 0,3W, M1W	2SC3671, 2SC4482, 2SD1145, 2SD2097
24844	2SD1963	50V, 3A, 150MHz	2SC4521, 2SD1624
24845	2SD1964	130/80V, 15A, 50W, 20MHz	2SC3699
24846	2SD1965	120V, 1A, 5W	2SD1684
24847	2SD1966	80V, 0,7A, 5W	2SD1200
24848	2SD1967	40V, 2A, 5W, B20000	2SD947
24849	2SD1968	40V, 2A, 5W	2SC3422, 2SD1189, 2SD1682
24850	2SD1969	50V, 2A, 0,5W	-
24851	2SD197(A)	2SD196, 130/70V	2SD1049
24852	2SD1970	24V, 2A, 10W, B>7000	2SD947, 2SD1509
24853	2SD1971	400/400V, 0,5A, 5W, 55MHz	2SC2752, 2SC2899, 2SC3051
24854	2SD1972	60V, 3A, 15W, 100MHz, B>250	2SD2092, 2SD2127, 2SD1948
24855	2SD1973	80V, 2A, B1000	-
24856	2SD1974	2SD1922, SMD	-
24857	2SD1975	180V, 15A, 150W, 20MHz	2SC3281, 2SD1704, 2SD1718, 2SD2155
24858	2SD1976	300/300V, 6A, 40W, B>500	2SD991, 2SD1071, 2SD1088, 2SD1113
24859	2SD1977	120V, 8A, 65W, 60MHz	2SC4386, 2SC4689, BD 245C, BD 545D
24860	2SD1978	120V, 1,5A, 0,9W, B2k..30k	2SD1579, 2SD1659, 2SD2067, 2SD2213
24861	2SD1979	2SD1915, SMD	-
24862	2SD198(Z)	25W(Tc75°),45(Z25)MHz	BU 126, 2SC2809, 2SD632
24863	2SD1980	100V, 2A, 10W, B3000	2SD1223, 2SD1520
24864	2SD1981	100V, 2A, 1W, B7000	2SC1879, 2SD1660, 2SD1867, 2SD1978
24865	2SD1982	300/300V, 6A, 80W, B2000	2SD1461
24866	2SD1983	60V, 1,5A, 20W, B10000	2SD2051
24867	2SD1984	30V, 1A, 0,9W, B1500	2SC3070, 2SC3225, 2SC3726
24868	2SD1985(A)	2SD1252(A), 25W	BD 935F, 2SC3851...52, 2SD1585, 2SD1913
24869	2SD1986	60V, 4A, 35W, B5000	BD 715, BDW 23A, BDW 53A, BDW 63A
24870	2SD1987	2SD1986, , 30W	2SD1595, 2SD1790, 2SD1796, 2SD1933
24871	2SD1988	45V, 2A, 25W, B3000	BD 713, BDW 53, 2SD837
24872	2SD1989	2SD1988, , 20W	BDT 61F, 2SC3986, 2SD1796, 2SD1987
24873	2SD199	7MHz	2SC3151
24874	2SD1990	80V, 4A, 35W, 80MHz	BDV 10...12, 2SC3253, 2SC3258
24875	2SD1991	2SD636	2SD636
24876	2SD1991A	2SD637	2SD637
24877	2SD1992	2SD938	2SD638
24878	2SD1992A	2SD939	2SD639
24879	2SD1993	2SD661A	2SD661A
24880	2SD1994(A)	2SD973(A)	2SD973(A)
24881	2SD1995	2SD1010	2SD1010
24882	2SD1996	2SD1302	2SD1302
24883	2SD1997	Rbe800Ohm	-
24884	2SD1998	40V, 3A, Rb0Ohm, Rbe800Ohm	-

24885	2SD1999	30V, 4A, Rb00hm, Rbe1,5kOhm	-
24886	2SD20	2SD19, B50	AC 127, AC 176, AC 187, 2SD72, 2SD352
24887	2SD200(A)	1500V, 2,5A, 10W(Tc90°)	BU 205...206, 2SC1922, BU 705, 2SD818
24888	2SD2000	2SD1990	2SC3691, 2SC3746, 2SC4549, 2SC4596
24889	2SD2001	1500/700V, 1,5A, 40W	BU 505DF
24890	2SD2002	1500/800V, 5A, 50W	BU 508AF, 2SC3894, 2SC4142, 2SD1884
24891	2SD2004	160/160V, 1,5A, 1,2W, 80MHz	2SC2983, 2SC4027, 2SD1918, 2SA2122...23
24892	2SD2005	40V, 1A, 1,2W, 150MHz	2SC3076, 2SD1801
24893	2SD2006	80V, 0,7A, 1,2W, 120MHz	-
24894	2SD2007	40V, 2A, 1,2W, 100MHz	2SC3076, 2SD1801
24895	2SD2008	120/80V, 1A, 1,2W, 100MHz	2SC4135
24896	2SD2009	60/60V, 1A, 1,2W, B>2000	2SC2871, 2SC4500, 2SD1598, 2SD1800
24897	2SD201	90/60V, 6A, 50W, -/4µs	BD 245C, BDV 95, BDX 95, 2N5632...33
24898	2SD2010	60/60V, 2A, 1,2W, B>1000	-
24899	2SD2011	2SD1638	2SD1955, 2SD1980, 2SD2410
24900	2SD2012	B100..320	BD 935F, 2SD1406, 2SD1585, 2SD1913
24901	2SD2014	75MHz, B>2000	BDT 61CF, 2SD1336, 2SD1785
24902	2SD2015	25W, 40MHz, B>2000	2SD1590, 2SD1789
24903	2SD2016	25W, 90MHz, B>1000	-
24904	2SD2017	300/250V, 6A, 35W, B>2000	2SD1410, 2SD1088, 2SD1113, 2SD1976
24905	2SD2018	60V, 1A, 5W, 150MHz, B>6500	-
24906	2SD2019	150V, 1,5A, 10W, B>5000	2SC4342, 2SD985...986
24907	2SD202	2SD201, 110/80V	BD 245C, 2N5633, 2SC2681, 2SD718
24908	2SD2020	150V, 2A, 40W	BD 239D, 2SC1669, 2SC2073, 2SD1138
24909	2SD2021	2SD2020, , 30W	BDT 31DF, 2SC3567, 2SC3695, 2SD1587
24910	2SD2022	60V, 1,5A, 25W, B3000	BD 715, BDW 23A, BDW 53A, BDW 63A
24911	2SD2023	80V, 3A, 40W, 8MHz	BD 241B, BD 537, BD 951, 2SC3179
24912	2SD2024	100V, 8A, 40W, B10000	-
24913	2SD2025	2SD2024, , 30W	-
24914	2SD2026	30V, 0,3A, 200MHz, B30000	2SD1478
24915	2SD2027	60V, 3A, 30W, 8MHz	BD 241A, BD 535, BD 935, 2SC3179
24916	2SD2028	8V, 0,7A	-
24917	2SD2029	160/160V, 12A, 120W, 20MHz	2SC3280...81, 2SD1717...18, 2SD1975
24918	2SD203	2SD201, 130/100V	BD245D, BDX11, 2N4348, 2N5634, 2SD551
24919	2SD2030	2SD1868, 0,4W	BF 420A, BF 422A, BF 391, 2SC3248
24920	2SD2031	2SD1869, 0,4W	BF 420A, BF 422A, BF 391, 2SC3467
24921	2SD2032	80V, 4A, 20W, B3000	2SD1223, 2SD1520
24922	2SD2033	120V, 1,5A, 1,8W, 80MHz	2SC2690, 2SD1563, 2SD1684
24923	2SD2033A	2SD2033, 160V	2SC2690A, 2SC3117, 2SD1563A
24924	2SD2034	80V, 3A, 25W	BD 441, BD 787, BD 789, MJE 240...242
24925	2SD2035	80V, 4A, 1,8W, 8MHz	BD 441, BD 787, BD 789, MJE 240...242
24926	2SD2036	100V, 7A, 1,8W, 5MHz	-
24927	2SD2037	60V, 3A, 1,8W, 90MHz	BD 787, BD 789, 2SD1506, 2SD1818
24928	2SD2038	80V, 5A, 1,8W, 8MHz	-
24929	2SD2039	100V, 2A, 1,8W, B4000	2SD985...86, 2SD1376, 2SD1953



24930	2SD204	60V, 0,7A, 0,7W, 9W(Tc25°)	BD 137, BD 228, BD 517, BD 525
24931	2SD2040	100V, 5A, 1,8W, 8MHz	-
24932	2SD2041	60V, 2A, B4000	-
24933	2SD2042	60V, 5A, B10000	-
24934	2SD2043	120V, 6A, B10000	-
24935	2SD2044	80V, 3A, B400..2000	-
24936	2SD2045	B>2000	2SD1893, 2SD2437, 2SD1170, 2SD1210
24937	2SD2046	50V, 1,5A, 1W, B2k..10k	2SD1809, 2SD1866, 2SD1929, 2SD1931
24938	2SD2047(R)	1500V, 5A, 80W	BU 2508AF, 2SC3894, 2SD1545, 2SD1655
24939	2SD2048	110V, 3A, 30W, 20MHz, B4000	-
24940	2SD2049	110V, 5A, 35W, 20MHz, B4000	-
24941	2SD205	60V, 0,7A, 9W(Tc25°)	BD 137, BD 228, BD 517, BD 525
24942	2SD2050	110V, 8A, 40W, 20MHz, B4000	-
24943	2SD2051	>200MHz, B>4k	2SD1983
24944	2SD2052	150/150V, 9A, 100W, 20MHz	2SC4386, 2SC5100, BD 245D, 2SD1046
24945	2SD2053	2SD2052	BD 245D, 2SC2837, 2SC3907, 2SD1046
24946	2SD2054	100V, 1A	BCX 56, 2SD1005, 2SD1368, 2SD1418...19
24947	2SD2055	80V, 10A, 40W	BD 709, BD 743B, BD 809, BD 909
24948	2SD2056	2SD2055, , 30W	BDT 95F, 2SC3693...3694
24949	2SD2057	1500/700V, 5A, 100W	BU 508DF, 2SC4122, 2SC4293, 2SD1555
24950	2SD2058	<0,8/2,3µs	2SC3851...52, 2SD1585, 2SD1985, 2SD2012
24951	2SD2059	100V, 5A, 30W, 12MHz	BD 953F, 2SC3540, 2SC3691, 2SD1940
24952	2SD206(A)	50/30V, 10A, 150W	BD 315, 2N5629...31, 2SC2608, 2SD1105
24953	2SD2060	80V, 4A, 25W, 8MHz	BD 951F, 2SC3691, 2SC3851, 2SD2000
24954	2SD2061	2SD2023	2SC3691, 2SC3851, 2SD2000
24955	2SD2062	100/80V, 7A, 80W, 8MHz	2SC4385, 2SD2064, BD 245C, 2SC2681
24956	2SD2063	15V, 1A, 0,9W, B700	2SC3070, 2SC3225, 2SC3726, 2SD1984
24957	2SD2064	120/120V, 6A, 70W, 20MHz	2SC4385, 2SC5099, BD 245D, 2SC4486
24958	2SD2065	140/140V, 7A, 80W, 20MHz	2SC4386, 2SC5100, BD 245D, 2SC4467
24959	2SD2066	160/160V, 12A, 120W, 20MHz	BD 745E, 2SC2987A, 2SC3907, 2SD1047
24960	2SD2067	120/100V, 2A, 1W, B>4k	2SD1579, 2SD1659, 2SD1978
24961	2SD2068	60V, 1A, 1W, B>4k	2SD1809, 2SD1866, 2SD1929, 2SD1931
24962	2SD2069	60V, 2A, 1W, 210MHz	2SC3328, 2SC4486, 2SD1207, 2SD2177
24963	2SD207(A)	2SD206, 100/60V	BD 317, 2N5629...31, 2SC2608, 2SD1105
24964	2SD2070	50V, 0,1A, 1W	BC 174, BC 182, BC 190, BC 546, 2SD767
24965	2SD2071	50V, 0,5A, 1W, 200MHz	BC 337...338, BC 635, BC 637, 2SD1226
24966	2SD2072	2SD661, 1W,	2SD661
24967	2SD2073	2SD1010, 1W	2SD1010
24968	2SD2074	2SD1302, 1W	2SD1302
24969	2SD2075	60V, 10A, 90MHz, B>500	2SD1947
24970	2SD2076	100V, 5A, 90MHz, B>500	2SC4553, 2SD1947
24971	2SD2079	100V, 5A, 30W, B2k..15k	BD 647F, 2SD1589, 2SD1829...30, 2SD1785
24972	2SD208(A)	2SD206, 150/90V	BDW 12, MJ 15015, 2N3773, 2SC2607...08
24973	2SD2081	120/120V, 10A, 30W, B>2000	BDT 63CF, BDT 65CF, 2SD1591
24974	2SD2082	120/120V, 16A, 75W, B>2000	BDV 67BF



24975	2SD2083	120/120V, 25A, 120W, B>2000	2SD1597, 2SD2256
24976	2SD2084	450/450V, 6A, 50W, B>1000	BU 810, BU 911...912, 2SD798...799
24977	2SD2085	80V, 6A, 40W, 50MHz, B>400	2SC2315...16, 2SC2491
24978	2SD2088	B>2000	2SD1153, 2SD1809, 2SD1854, 2SD1929
24979	2SD2089	1500/600V, 3,5A, 40W	BU 2508DF, 2SD1554, 2SD1650, 2SD1877
24980	2SD2090	90V, 2A, 25W, B>1000	-
24981	2SD2091	2SD2090	-
24982	2SD2092	100V, 3A, 140MHz, B>500	2SD2076
24983	2SD2093	B4000	BDV 65CF, BDW 83D, 2SD1230
24984	2SD2094	120/120V, 8A, 25W, B>1000	BD 649F, 2SD1773
24985	2SD2095	1500/600V, 5A, 50W	BU 508DF, 2SD1555, 2SD1651, 2SD2125
24986	2SD2096	2SD2023, 1,8W	BD 441, BD 787, BD 789, MJE 240...241
24987	2SD2097	2SD1961	2SC3671, 2SC4482, 2SD1145
24988	2SD2098	2SD1961, SMD	2SD1628
24989	2SD2099	40V, 3A, Rb90Ohm, Rbe800Ohm	-
24990	2SD21	2SD19, B72	AC 127, AC 176, AC 187, 2SD72, 2SD352
24991	2SD2100	25V, 2A, Rb0, Rbe1,6kOhm	-
24992	2SD2101	200/200V, 10A, 30W, B>1500	2SD1794
24993	2SD2102	60V, 4A, 25W, B>1000	BDT 61(A,B,C)F, 2SD1595, 2SD2131
24994	2SD2103	60V, 8A, 25W, B>1000	BD 643F, 2SD1415...17, 2SD1826...27
24995	2SD2104	120/120V, 8A, 25W, B>1000	BD 649F, BD 651F, 2SD1590, 2SD1773
24996	2SD2105	120/120V, 10A, 30W, B>1000	BDT 63CF, 2SD1591, 2SD2081
24997	2SD2106	120/120V, 6A, 25W, B>1000	BD 649F, BD 651F, 2SD1336, 2SD1590
24998	2SD2107	70V, 4A, 25W	BD 951F, BD 953F, BD 955F, 2SD1407
24999	2SD2108	80V, 8A, 25W, B>1000	BD 645F, BD 647F, 2SD1415...16
25000	2SD2109	300/300V, 0,3A, 15W, B>1000	2SD2217, 2SD1502, 2SD1798
25001	2SD211	60/40V, 10A, 100W, -/4,4μs	BD 311, BDW 21A, 2N3055, 2N5877...78
25002	2SD2110	80V, 4A, 25W, B>1000	BDT 61(A...C)F, 2SD1933, 2SD2014
25003	2SD2111	120/120V, 3A, 25W, B>1000	BDT 61CF, 2SD2014...15
25004	2SD2112	120/120V, 6A, 25W, B>1000	BD 649F, BD 651F, 2SD1336
25005	2SD2113	120/120V, 3A, 25W, B>1000	BDT 61CF, 2SD2014...15
25006	2SD2114K	2SD2132, SMD	-
25007	2SD2115L,S	150/60V, 2A, 18W	2SD1033, 2SD1557
25008	2SD2116	B>5000	BC 618, BC 877, BC 879, 2SD1153
25009	2SD2117	80V, 1,5A, 1W, B>4000	2SD1153, 2SD1660, 2SD1853...54, 2SD1981
25010	2SD2118(F5)	50V, 5A, 1W, 150MHz	2SC3072, 2SC3074, 2SD1803, 2SD1805
25011	2SD2119	90V, 4A, 25W, B>2000	BDT 61BF...CF, 2SD1414, 2SD1788, 2SD2079
25012	2SD212	2SD211, 90/60V	BD 313, BDW 21C, 2N3055, 2N5632...33
25013	2SD2120	100V, 2A, 1W, B2k..30k	2SD1660, 2SD1981
25014	2SD2121L,S	35V, 2,5A, 18W	2SC3386, 2SD1221, 2SD1760, 2SD1802
25015	2SD2122L,S	180/120V, 1,5A, 18W, 180MHz	2SC4027, 2SD1080...82
25016	2SD2123L,S	180/160V, 1,5A, 18W, 180MHz	2SC4027, 2SD1080...82
25017	2SD2124L,S	120/120V, 1,5A, 18W, B>2000	2SD1464...65
25018	2SD2125	1500/600V, 6A, 50W	BU 508DF, 2SC4294, 2SD1556, 2SD1652
25019	2SD2127	60V, 3A, 140MHz, B>500	2SD1948, 2SD1972, 2SD2076

25020	2SD2128	60V, 3A, 25W, B>1000	BDT 61(A...C)F, 2SD1413, 2SD1796
25021	2SD2129	100V, 3A, 20W, B2000..15000	2SD1414, 2SD1788, 2SD1828, 2SD2014
25022	2SD213	2SD211, 110/80V	BDW 21C, 2N3055, 2N5632...33, 2SD551
25023	2SD2130	B2k..15k	2SD1796
25024	2SD2131	60V, 5A, 30W, B2000..15000	2SD1595
25025	2SD2132	25V,Ueb12V, 0,5A,B>560	2SC4204, 2SD2144...45, 2SD2191...92
25026	2SD2133	60V, 1A, 1,5W, 200MHz	BD 137, BD 139, BD 228, BD 377
25027	2SD2134	180/180V, 1A, 1,5W, 200MHz	2SC3117, 2SC3902, 2SD669
25028	2SD2135	60V, 1A, 150MHz, B>6500	-
25029	2SD2136	60V, 3A, 1,5W, 500/2900ns	BD 785, 2SD794A, 2SD1506, 2SD1818
25030	2SD2137	60V, 3A, 15W, 30MHz	2SD1406, 2SD1585, 2SD1985, 2SD1913
25031	2SD2137A	2SD2137, 80V	BDT 31F, 2SC3690, 2SD1761, 2SD2061
25032	2SD2138	60V, 2A, 15W, 20MHz, B>1000	BDT 61(A...C)F, 2SD1413, 2SD1983
25033	2SD2138A	2SD2138, 80V	BDT 61A...CF, 2SC2399, 2SD1414, 2SD1933
25034	2SD2139	80V, 3A, 15W, 50MHz, B>500	2SD1273, 2SD2156, 2SD2375, 2SD2396
25035	2SD214	2SD211, 130/100V	BDX 11, 2N3442, 2SD551, 2SD732...733
25036	2SD2140	140/140V, 7A, 80W, 20MHz	BD 245D, 2SC2706, 2SC2837, 2SC3182
25037	2SD2141	380V, 6A, 35W, B>1500	-
25038	2SD2143	60+-10V, 2A, 10W, B>1k	2SD1222, 2SD1817
25039	2SD2144(S)	2SD2132, 0,3W	2SD2132
25040	2SD2145(M)	2SD2132, 0,4W	2SD2132
25041	2SD2146	60V, 3A, 1,2W, 90MHz	2SC3386, 2SC4522, 2SD1802, 2SD1221
25042	2SD2147	50V, 5A, 150MHz	2SC2270, 2SD826
25043	2SD2148	1500/700V, 8A, 50W	BU 508AF, 2SC3886A, 2SC3896, 2SC4758
25044	2SD2149	100/100V, 15A, 100W, B>1000	BDV 67A...D, BDW 83C...D, 2SD1026
25045	2SD215(F)	40V, 1A, 0,8W	BC 140...141, 2N1990, 2N2102, 2N2405
25046	2SD2150	2SD2152, SMD	2SD1119, 2SD1624
25047	2SD2151	130/80V, 10A, 30W, 20MHz	2SC3568, 2SC3698, 2SC4336
25048	2SD2152	40V, 3A, 0,75W, 290MHz	2SC4487, 2SD1507, 2SD1617, 2SD1864
25049	2SD2153	30/25V, 2/3A, B390..2700	2SC3439, 2SC3727
25050	2SD2154	2SD2152, 0,6W	2SD2152
25051	2SD2155	180V, 15A, 150W, 10MHz	2SC3281, 2SC4029, 2SD1975
25052	2SD2156	80V, 3A, 25W, 50MHz, B>500	2SD1944, 2SD2076, 2SD2092
25053	2SD2156A	2SD2156, 100V	2SD2076, 2SD2092
25054	2SD2157	60V, 4A, 25W, 20MHz, B>1000	BDT 61(A...C)F, 2SD1796, 2SD1825, 2SD1987
25055	2SD2157A	2SD2157, 80V	BDT 61A...CF, 2SD1414, 2SD1788, 2SD1933
25056	2SD2158	80V, 2A, 20W, 40MHz, B>500	2SC3852, 2SD1776(A), 2SD1944, 2SD2092
25057	2SD2158A	2SD2158, 100V	2SD1776A, 2SD2092, 2SD2156A
25058	2SD2159	30V, 2A, 1W, 110MHz	2SC3225, 2SC4389,
25059	2SD216(F)	2SD215, 60V	BC 140...141, 2N1990, 2N2102, 2N2405
25060	2SD2161	2SD1589	2SD1589
25061	2SD2162	2SD1590	2SD1590
25062	2SD2163	2SD1591	2SD1591
25063	2SD2164	2SD1593	2SD1593
25064	2SD2164	2SD2152, 1W	2SD2152

25065	2SD2165	2SD1594	2SD1594
25066	2SD2166	2SD2147	2SC3420, 2SD1685
25067	2SD2167	2SD2169, SMD	-
25068	2SD2168	2SD2169	-
25069	2SD2169	31V, 2A, 0,5W, 100MHz	-
25070	2SD217	120/80V, 7A, 60W, 10MHz	BD 245D, 2N3442, 2SD551, 2SD731...732
25071	2SD2170	90V, 2A, 80MHz, B>1000	-
25072	2SD2171S	30V, 1,5A, 0,3W, 200MHz	2SC3070, 2SD1582
25073	2SD2172	2SD2171S, 1W	2SC4389
25074	2SD2175	-/80V, 0,7A, 0,5W	BC 639, 2SD774, 2SC3665, 2SD1226
25075	2SD2176	50V, 1,2A, B>1000	2SD1626
25076	2SD2177	50V, 2A, 1W, 110MHz	2SC3328, 2SD1207, 2SD1835, 2SD2182
25077	2SD2178	2SD2177, 1,5W	BD 375, 2SD1177...78, 2SD1506, 2SD1682
25078	2SD2179	50V, 5A, 1W, 80MHz	2SD1145, 2SD1961...62, 2SD2097
25079	2SD218(S)	2SD217, 150/100V(S150/120V)	BD 245D, 2N3442, 2SD551, 2SD731...732
25080	2SD2180	50V, 3A, 1,5W, 80MHz	BD 785, 2SD794A, 2SD1506, 2SD1818
25081	2SD2181	100V, 1A, 1W, 100MHz	2SC4488, 2SD1616A
25082	2SD2182	100V, 2A, 1W, 80MHz	2SC4489
25083	2SD2183	2SD2182, 1,5W	-
25084	2SD2184	150/150V, 1A, 1W, 90MHz	2SC4614, 2SD1665A, 2SD1812, 2SD1857A
25085	2SD2185	2SD2177, SMD, 3A	2SC4409, 2SD1623
25086	2SD2188	2SD2085, , 30W	2SC4553, 2SC4558, 2SD1474
25087	2SD219	40V, 1A, 0,5W, 340/5000ns	BC 140...141, 2N1990, 2N2102, 2N2405
25088	2SD2191	2SD2132, 0,4W,	2SD2132
25089	2SD2192	2SD2132, 0,4W,	2SD2132
25090	2SD2193	25V, 0,8A, 0,9W, B>800	-
25091	2SD2195	100/100V, 2A, B1k..10k	2SD1472
25092	2SD2196	2SD1027, , 65W	2SD1515
25093	2SD2197M	2SC2069	2SC2069
25094	2SD2198	60V, 5A, 30W, 100/1600ns	2SD1904, 2SD1906, 2SD2200
25095	2SD2199	60V, 7A, 40W, 200/1200ns	2SD1905, 2SD1907, 2SD2201
25096	2SD219F	2SD222	2SD222
25097	2SD22	2SD19, B97	AC 127, AC 176, AC 187, 2SD72, 2SD352
25098	2SD220	2SD219, 80V	BC 140...141, 2N1990, 2N2102, 2N2405
25099	2SD2200	90V, 5A, 30W, 100/1600ns	2SD1906...07, 2SD2201
25100	2SD2201	90V, 7A, 40W, 100/2000ns	2SD1907
25101	2SD2202	90V, 5A, 25W, 20MHz	2SC3540, 2SC3691, 2SC4549, 2SC4596
25102	2SD2203	90V, 7A, 30W, 20MHz	2SC3692, 2SC4550, 2SD1411
25103	2SD2204	65V, 4A, 25W, B2k..15k	-
25104	2SD2205	2SD1590	2SD1590
25105	2SD2206	B>2000	2SD1978, 2SD1981
25106	2SD2209	100/100V, 4A, 15W, B>1000	2SC4345, 2SD1223, 2SD1520
25107	2SD220F	2SD223	2SD223
25108	2SD221	2SD219, 110V	BC 141, 2N1990, 2N2102, 2N2405
25109	2SD2210	2SD1302, SMD	2SC2982, 2SC3265, 2SD1621

25110	2SD2211	2SD1918, SMD	2SC3649, 2SD1420...21
25111	2SD2212	60V, 2/3A, 80MHz, B>1k	-
25112	2SD2213	150/80V, 1,5A, 0,9W, B>5000	2SD1579, 2SD1659
25113	2SD2214	60V, 8A, 25W, 20MHz, B>2000	BD 643F, 2SD1415...17, 2SD1826
25114	2SD2215(A)	2SD1249(A), 15W	2SC3075
25115	2SD2216	60V, 0,1A, 150MHz	2SC4738
25116	2SD2217	45MHz, B>1500	2SD2109
25117	2SD2218	100/530ns	2SC3692...93, 2SC3747...48, 2SC4550...51
25118	2SD2219	200/530ns	2SC3709...10, 2SC4065
25119	2SD221F	2SD224	2SD224
25120	2SD222	2SD219, 1,5A, 10W	BD 135, BD 226, BD 233, BD 507
25121	2SD2220	150MHz, B>4000	BD 139, BD 230, 2SC2690, 2SD1684
25122	2SD2221	B>5000	2SD2255
25123	2SD2222	B>3500	2SD2250, 2SD2276
25124	2SD2223	B>2000	BDW 23B...C, BDW 63B...D, 2SD1933
25125	2SD2224	B>2000	BD 647, BD 899, BDW 73B, 2SD1415...16
25126	2SD2225	2SD1211	2SC2235, 2SC3665, 2SD667, 2SD1616A
25127	2SD2226K	2SD2227S, SMD	2SD1938
25128	2SD2227S	60V, 0,15A, 250MHz	2SC3069, 2SC3071, 2SC3836
25129	2SD2228	25V, 0,5A, 50MHz	-
25130	2SD2229	16V, 0,5A, 0,25W, >50MHz	2SC3225, 2SC3247, 2SC4483, 2SD1302
25131	2SD223	2SD219, 80V, 1,5A, 10W	BD 139, BD 230, BD 237, BD 527
25132	2SD2230	2SD2229, SMD	2SC3265, 2SC4519
25133	2SD2231	120/120V, 6A, 60W, B>2000	2SD1170
25134	2SD2232	B>3000	2SD1141
25135	2SD2233	B>2700	2SD1410, 2SD2017
25136	2SD2234	1500V, 3A, 40W, <1/4,5µs	BU 505F, 2SD1575
25137	2SD2236	-/100V, 5A, 60W	2SC4385, 2SC4689, 2SC5099, BD 245D
25138	2SD2237	-/100V, 8A, 60W, B>2000	BDV 65CF, 2SD1670, 2SD1895
25139	2SD224	2SD219, 110V, 1,5A, 10W	BD 139, BD 230, BD 237, BD 529
25140	2SD2240(A)	2SD814(A)	-
25141	2SD2241	200/2100ns	BTD 61BF, 2SD1414, 2SD1589, 2SD2079
25142	2SD2242	60V, 4A, 15W, 20MHz, B>1000	BDT 61(A...C)F, 2SD1825, 2SD1987
25143	2SD2242A	2SD2242, 80V	BDT 61AF...CF, 2SD1933, 2SD2478
25144	2SD2243	60/60V, 5A, 1W	2SC4482, 2SD1145
25145	2SD2244	60/60V, 3A, 1W, B>800	-
25146	2SD2245	60V, +-2A, 1W, B>2000	-
25147	2SD2246	0,4/1,9µs	2SD1153, 2SD1809, 2SD1853, 2SD1866
25148	2SD2247	55V, 0,1A, 0,2W, 50MHz	BC 167, BC 237, BC 546...547, 2SD767
25149	2SD2248	B>2000	2SD1981
25150	2SD2249	2SD965, 1W	2SD1244, 2SD1934, 2SD1961...62, 2SD2097
25151	2SD2250	B>5000	2SD2222, 2SD2276
25152	2SD2251	2SD2252	BU 508DF, 2SC3892A, 2SC4123, 2SC4769
25153	2SD2252	1500/800, 7A, 60W	BU 508AF, 2SC3885A, 2SC3895, 2SC4770
25154	2SD2253	1700/600, 6A, 50W	2SC4766

25155	2SD2254	B>5000	2SD2222, 2SD2250, 2SD2276
25156	2SD2255	B>5000	2SD2221
25157	2SD2256	120/120V, 25A, 120W, B>2000	2SD2083
25158	2SD2257	B>2k	BDT 61BF, 2SD1828, 2SD2129, 2SD1788
25159	2SD2258	2SD1198A, 1W,	2SD1198A
25160	2SD2259	2SD1458, 1W,	2SD1458
25161	2SD226(Z)	40V, 3A, 25W	BD 241, BD 533, BD 933, 2N4231...33
25162	2SD2260	2SD662B, 0,6W,	2SD662B
25163	2SD2261	80/60V, 2,5A, B>2000	-
25164	2SD2263	25V, 0,5A, 0,5W	-
25165	2SD2264	2SD2152	2SD2152
25166	2SD2265	B>200	-
25167	2SD2266	80V, 4A, 15W, 80MHz	2SC3540, 2SC3691, 2SC3746, 2SC4549
25168	2SD226A	2SD226, 60V	BD 241A, BD 535, BD 935, 2N4232...33
25169	2SD226B	2SD226, 80V	BD 241B, BD 537, BD 937, 2N4233
25170	2SD227	30V, 0,3A, 0,25W, 120MHz	BC 337...338, BC 635, BC 637, 2SC3377
25171	2SD2271	<1/14µs	-
25172	2SD2273	B>5000	2SD2254
25173	2SD2274	B>5000	2SD2254
25174	2SD2275	B>5000	2SD2254
25175	2SD2276	B>5000	2SD2222, 2SD2250
25176	2SD2279	2SD2069	2SD2069
25177	2SD228	2SD227, 0,4W	BC 337...338, BC 635, BC 637, 2SC3377
25178	2SD2280	200/1200ns	2SC4385, 2SC4688, 2SC5099, 2SD2064
25179	2SD2281	100/1250ns	2SD2282, 2SD2285, BD 545A, 2SC3256
25180	2SD2282	200/1100ns	BD 545A...D, 2SC3256, 2SD1065
25181	2SD2283	2SD2090, 1,8W	-
25182	2SD2284	80V, 3A, B>2000	-
25183	2SD2285	60V, 20A, 40W, 300/620ns	-
25184	2SD2287	1500V, 3A, 50W	BU 706D, 2SC3480, 2SD1441, 2SD1729
25185	2SD2288	1500/800V, 3A, 50W	BU 706, 2SC3484, 2SD1495
25186	2SD2289	1500V, 5A, 50W	BU 706D, 2SC3481, 2SC3681, 2SC4291
25187	2SD2290	1500/800V, 5A, 50W	BU 706, 2SC3485, 2SC3685, 2SD1496
25188	2SD2291	1500V, 6A, 50W	BU 2508D, 2SC3482, 2SC3681, 2SC4192
25189	2SD2292	1500/800V, 6A, 50W	BU 2508A, 2SC3486, 2SC3685, 2SD1497
25190	2SD2293	2SD2287	2SD2287
25191	2SD2294	2SD2288	2SD2288
25192	2SD2295	2SD2289	2SD2289
25193	2SD2296	2SD2290	2SD2290
25194	2SD2297	2SD2291	2SD2291
25195	2SD2298	2SD2292	2SD2292
25196	2SD2299	2SD2287	BU 706DF, 2SD1554, 2SD1650, 2SD2368
25197	2SD23	2SD19, B150	AC 127, AC 176, AC 187, 2SD72, 2SD352
25198	2SD2300	2SD2289	BU 706DF, 2SC4122, 2SC4293, 2SD1555
25199	2SD2301	2SD2292	BU 2508AF, 2SC3486, 2SC3685, 2SC4143

25200	2SD2306	-/60V, 4A, B>1000	BD677, BD777, 2N6038, 2SD1223, 2SD1520
25201	2SD2307	-/100V, 8A, B>1000	-
25202	2SD2308	80V, 4A, 1,2W, 40MHz, B5000	BD679, BD779, 2N6039, 2SD1223, 2SD1520
25203	2SD2309	2SD1986	BD677, BD777, 2N6038, 2SD1223, 2SD1520
25204	2SD231(F)	50/40V, 30A, 125W, -/11µs	BDX 41, 2N3771, 2SD630
25205	2SD2310	1500/700, 1,5A, 40W	BU 505DF, 2SD2001
25206	2SD2311	2SD2290	BU 706F, 2SC3894, 2SC4142, 2SC4830
25207	2SD2312	2SD2227S, 0,4W	2SD2227S
25208	2SD2313M	2SD2227S, 0,4W	2SD2227S
25209	2SD2314	2SD2227S, 0,4W,	2SD2227S
25210	2SD2315	2SD2227S, 0,4W,	2SD2227S
25211	2SD2318(F5)	B>390	2SD1754
25212	2SD232(F)	2SD231, 120/100V, -/13,5µs	BDW 30, 2N6032, 2N6274...6275
25213	2SD2321	40V, 5A, 0,4W, 150MHz	2SD1244, 2SD1934, 2SD2249, 2SD2097
25214	2SD2322S	40V, 0,8A, 0,3W, 150MHz	2SC4485, 2SD1616
25215	2SD2323	300/300V, 6A, 30W, B>500	-
25216	2SD2324	20V, 0,8A, 150MHz, Rbe1kOhm	-
25217	2SD2326	B>6500	-
25218	2SD2328	180/180V, 15A, 150W, 30MHz	2SC3281, 2SD1718, 2SD1975, 2SD2155
25219	2SD2329	1500/600V, 5A, -IBp2,5A, 80W	BU 508A(F), BU 706(F), BU 908(F)
25220	2SD232A	2SD231, 160/140V	BDW 32, BDY 58, 2N6276...6277
25221	2SD2330	1500/600V, 7A, 100W	BU 508A(F), BU 2508A(F), BU 908(F)
25222	2SD2331	1500/600V, 3A, -IBp2A, 60W	BU 706DF, 2SD1554, 2SD1650, 2SD2089
25223	2SD2332	1500/600V, 3A, -IBp2A, 60W	BU 706F, 2SD1544, 2SD1654, 2SD1883
25224	2SD2333	1500/600V, 5A, -IBp2,5A, 80W	BU 706DF, 2SC4293, 2SD1555, 2SD2125
25225	2SD2334	1500/600V, 5A, -IBp2,5A, 80W	BU 706F, 2SC4142, 2SD1655, 2SD1884
25226	2SD2335	1500/600V, 7A, -IBp3A, 100W	BU 2508DF, 2SC4123, 2SC4762, 2SC4769
25227	2SD2336	1500/600V, 7A, -IBp3A, 100W	BU 2508AF, 2SC4770, 2SD1547, 2SD2252
25228	2SD2337	200/150V, 2A, 20W	2SC3298B, 2SC4382, 2SD1587
25229	2SD234(G)	60V, 3A, 25W, 3MHz	BD 241A, BD 535, BD 935, 2SC3179
25230	2SD2340	B>5k	2SD2221, 2SD2255
25231	2SD2341	200/180V, 2A, 1,5W, 150MHz	-
25232	2SD2342	150/80V, 6A, 50W	BD245D...F, 2SC2837, 2SC4467, 2SD1046...47
25233	2SD2343	120V, 1,5A, 5W, 80MHz	2SC3621, 2SD1684, 2SC2690(A), 2SD1563
25234	2SD2344	350/150V, 7A, 20W	BU 306F, BU 406F, 2SC4130, 2SC4160
25235	2SD2345	2SD1010, SMD	-
25236	2SD2348	1500/600V, +-8A, 50W	BU 2508DF, 2SC4124, 2SC4763, 2SD1880
25237	2SD2349	1500/600V, +-10A, 50W	BU 2520DF, 2SC4125, 2SC4531, 2SD1881
25238	2SD235(G)	2SD234, 50V	BD 241, BD 535, BD 935, 2SC3179
25239	2SD2350	300/300V, 6A, 40W, B>500	2SD1071, 2SD1113, 2SD1307, 2SD1976
25240	2SD2351	2SD2227S, SMD	2SC4413
25241	2SD2352	60V, 2A, 25W, 17MHz, B>800	2SC3852, 2SD1776(A), 2SD1944, 2SD2158(A)
25242	2SD2353	60V, 3A, 25W, 18MHz, B>800	2SC3852, 2SD1972, 2SD1944, 2SD2127
25243	2SD2354	1500V, 7A, -IBp3A, 100W	BU 508A(F), BU 908(F), BU 2508A(F)
25244	2SD2355	1500V, 10A, -IBp4A, 100W	BU 2520A(F), BU 2525A(F)



25245	2SD2356	HA(64kHz), 1500V, 20A, 200W	2SC3997, 2SC4290A, 2SC4897
25246	2SD2357	10V, 1A, 120MHz	2SC2982, 2SC3443, 2SD1621
25247	2SD2359	20V, 1A, 100MHz	2SC2982, 2SC3443, 2SD1621
25248	2SD236	40V, 1,5A, 10W	BD 239, BD 241, BD 933, 2N4231...33
25249	2SD2361	60V, 1A, 1,2W, 150MHz	BD 517, BD 525, 2SC2194, 2SD1801
25250	2SD2362	50V, 2A, 1,2W, 130MHz	BD 509, BD 515, 2SC3076, 2SD1801
25251	2SD2363	60V, 3A, 1,2W, 25MHz	2SC3386, 2SD1221, 2SD1802, 2SD1805
25252	2SD2364	80V, 1A, 1,2W, 140MHz	BD 519, BD 527, BD 529, 2SC4135
25253	2SD2365	150V, 1A, 1,2W, 90MHz	2SC2384, 2SC2983, 2SD1220, 2SD1918
25254	2SD2366	400/400V, 0,5A, 1,2W, 30MHz	2SC2752, 2SC3362, 2SC4615 2SD1053
25255	2SD2367	1500V, 3A, -IBp2,5A, 50W	BU 705DF, 2SD1554, 2SD1877, 2SD2089
25256	2SD2368	1500/700V, 3,5A, 60W	BU 706DF, 2SD1554, 2SD1877, 2SD2089
25257	2SD2369	1500V, 4A, -IBp2,5A, 70W	BU 706DF, 2SD1555, 2SD2095, 2SD2125
25258	2SD237	2SD236, 80V	BD 239B, BD 241B, BD 937, 2N4233
25259	2SD2370	1500/700V, 5A, 100W	BU 706DF, 2SD1555, 2SD2095, 2SD2125
25260	2SD2371	1500V, 7A, 100W	BU 2508DF, 2SC3893A, 2SC4124, 2SD1880
25261	2SD2372	1500/600V, 7A, -IBp3A, 100W	BU 2508AF, 2SC3895, 2SC4757, 2SD2252
25262	2SD2373	1500/600V, 10A, -IBp4A, 100W	BUH 715, 2SC3897, 2SC4542, 2SD1887
25263	2SD2374	500/2900ns	2SD1762, 2SD1913, 2SC3690
25264	2SD2375	80V, 3A, 25W, 50MHz, B>500	2SD1273, 2SD1944, 2SD2092, 2SD2156
25265	2SD238	2SD236, 110V	BD 239C, BD 241C, BD 939, 2SD381...382
25266	2SD2381	1500/800V, 3A, 40W	BU 706F, 2SD1544, 2SD1654, 2SD1883
25267	2SD2383	400/300V, 20mA, 90MHz	-
25268	2SD2384	140/140V, 7A, 100W, B>5000	2SD2222, 2SD2250, 2SD2276
25269	2SD2385	140/140V, 8A, 120W, B>5000	2SD2222, 2SD2250, 2SD2276
25270	2SD2386	2SD2384, 70W	2SD2221, 2SD2255
25271	2SD2387	2SD2385, 80W	BDV 67C...D, 2SD1210
25272	2SD2388	2SD2090, 1,2W	-
25273	2SD2389	B>5k	BDV 67D, 2SD1123
25274	2SD2390	B>5k	BDV 67D, 2SD1123, 2SD1027, 2SD1515
25275	2SD2391	60V, 2A, 210MHz	2SC4409
25276	2SD2394	80V, 3A, 25W, 8MHz	BD 937F, BDT 31...F, 2SC3475, 2SC3851
25277	2SD2395	60V, 3A, 25W, 100MHz	BD 935F, BDT 31...F, 2SD1585, 2SD1985
25278	2SD2396	2SD1943, , 30W	2SD1273, 2SD2092, 2SD2156, 2SD2375
25279	2SD2397	2SD1764	2SD1764
25280	2SD2398	100V, 2A, 20W, B1k..10k	2SD1828, 2SD1890, 2SD2129, 2SD2257
25281	2SD2399	B1k..10k	BDT 61...F, 2SD1414, 2SD1788, 2SD1933
25282	2SD24	300V, 0,1A, 6W(Tc70°), 25MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
25283	2SD2400	120V, 1,5A, 20W, 80MHz	2SC3364, 2SC3564, 2SC4883(A), 2SD1763
25284	2SD2400A	2SD2400, 160V	2SC3364, 2SC4159, 2SC4370, 2SC4883A
25285	2SD2401	B>5k	-
25286	2SD2402	50V, 5A, 170MHz, 275/530ns	2SD1628
25287	2SD2403	80V, 3A, 130MHz, 150/665ns	2SC4541
25288	2SD2406	80V, 4A, 25W, 8MHz	2SC3851, 2SC3691, 2SD1408, 2SD2000
25289	2SD2407	500/2900ns	2SC4522, 2SD1221, 2SD1760, 2SD1802

25290	2SD2408	50V, 2A, 10W, 150MHz	2SC3076, 2SD1078...1079, 2SD1801
25291	2SD2409	50V, 5A, 10W, 80MHz	2SC3072, 2SC3518, 2SC3592, 2SD1805
25292	2SD241	60V, 4A, 25W	BD 243A, BD 535, BDW 25, BDX 25
25293	2SD2410	B1k..10k	2SD1980
25294	2SD2411	200V, 2A, 10W, B1k..10k	-
25295	2SD2412	400/300V, 0,75A, 10W, 180MHz	2SC3362, 2SC3632, 2SC4615, 2SD1053
25296	2SD2413	400/400V, 0,1A, 40MHz	2SC4548
25297	2SD2414(SM)	100V, 7A, 40W, 10MHz	2SD1257(A)
25298	2SD2415	25V, 0,5A, 0,5W	-
25299	2SD242	2SD241, 90V	BD 243C, BD 539B, BDW 25, BDX 25
25300	2SD2421	2SD2422, 1,8W	-
25301	2SD2422	B>1000	2SD1791, BD 647F, 2SD1415
25302	2SD2423	50V, 1,5A, B>2000	-
25303	2SD2425	60V, 5A, 600/880ns	2SD2098, 2SD2402
25304	2SD2426	100/80V, 2A, 1,5W, 80MHz	-
25305	2SD2428	1700/600V, 8A, 200W	S 3934...35, 2SC4532, 2SC4608
25306	2SD243	2SD241, 110V	BD 243C, BD 539C, BDW 25, BDX 25
25307	2SD2432	2SD602	2SD602
25308	2SD2433	2SD1030	2SD1030
25309	2SD2434	2SD1478	2SD1478
25310	2SD2436	2SD1328	2SD1328
25311	2SD2437	B>2k	2SD1893...95, 2SD2045
25312	2SD2438	B>5k	2SD1894...95, 2SD2221, 2SD2255
25313	2SD2439	B>5k	2SD1895, 2SD2390
25314	2SD244	2SD241, 130V	BD 243D, BDW 25, BDX 25, 2SD960...961
25315	2SD2440	100V, 6A, 40W, 5MHz	-
25316	2SD2441	10V, 1,5A, 190MHz	2SC2982, 2SC3443, 2SD1621
25317	2SD2443	150MHz	2SC2871, 2SC4500, 2SD1598, 2SD1800
25318	2SD2449	B>3000	-
25319	2SD2450	-/32V, 2A, 0,9W	2SC4145, 2SD1207, 2SD2069
25320	2SD2451	-/160V, 1,5A, 0,9W	2SC4614, 2SD1665A, 2SD1812, 2SD1857A
25321	2SD2452	+/-31V, 2A, 1,2W, B>1000	-
25322	2SD2453	80V, 3A, 10W, 100MHz, B>500	2SD1223, 2SD1520, 2SD1817, 2SD1955
25323	2SD2454	1700/600V, 7A, 50W	BUH 517D, 2SC4963
25324	2SD2457	50V, 1,5A, 150MHz	2SC2873, 2SD1623...24
25325	2SD246	1500V, 4,5A, 16W(Tc90°)	BU 208...209(A), BU 706, 2SC2928
25326	2SD2461	60V, 2A, 1,3W, B>800	2SC3808
25327	2SD2462	60/60V, 3A, 1,3W, B>800	2SD1694
25328	2SD2463	31V, +/-2A, 1W, B>2000	-
25329	2SD2464	B>300	2SC4482, 2SD1145
25330	2SD2465	40V, 4A, 25W, 120MHz	2SC3299, 2SC3746, 2SC4881
25331	2SD2465A	2SD2465, 50V	2SC3299, 2SC3746, 2SC4881
25332	2SD2466	40V, 10A, 40W, 120MHz	2SC3709, 2SC4064...65, 2SD1445(A)
25333	2SD2466A	2SD2466, 50V	2SC3709, 2SC4064...65, 2SD1445A
25334	2SD2467	2SD1254	2SD1268

25335	2SD2468	2SD1255	2SD1269
25336	2SD2469(A)	2SD1257(A)	2SD1271(A)
25337	2SD247	80V, 5A, 50W	BD 245B, BDV 93, BDX 93, 2N5632...33
25338	2SD2470	-/10V, 5A, 0,4W	2SD1244, 2SD1934, 2SD2249, 2SD2497
25339	2SD2472	10V, 0,5A, 120MHz	2SC4577
25340	2SD2473	20V, 0,5A	2SC4519, 2SC4577
25341	2SD2474	10V, 2A, 180MHz	2SC3443, 2SC2982, 2SD1621
25342	2SD2478	B>1000	2SD1788, BDT 61BF, 2SD1414, 2SD1589
25343	2SD2479	B>4000	-
25344	2SD2480	B>2000	2SD1980, 2SD2410
25345	2SD2481	180/900ns	2SD947
25346	2SD2482	2SD2472	2SC4555
25347	2SD2483	2SD2473	2SC4555
25348	2SD2484	50V, 2A, 0,9W	2SC3726, 2SD1207, 2SD2069, 2SD2177
25349	2SD2485	2SD2484, 80V	2SC3328, 2SC4489, 2SD2182
25350	2SD2486	60V, 5A, 70MHz, B>500	2SD1948, 2SD2075...2076
25351	2SD2488	B>5000	-
25352	2SD2489	2SD2488, 17A, 200W	-
25353	2SD249	50V, 30A, 125W, 0,8MHz	BDX 41, 2N3771, 2SD630
25354	2SD2490	2SD2488, , 85W	-
25355	2SD2491	160/160V, 0,1A, 8W, 140MHz	2SC3788, 2SC3955...56
25356	2SD2492	2SD2491, 200/200V	2SC3788, 2SC3955...56
25357	2SD2493	B>5000	2SD2340, 2SD2386
25358	2SD2494	2SD2493	2SD1893...94, 2SD2438
25359	2SD2495	2SD2493, , 30W	2SD2025
25360	2SD2496	2SD601A	2SD601A
25361	2SD2497	40/20V, 5A, 0,75W	2SC4482, 2SD1145, (2SD1244, 2SD2249
25362	2SD2498	1500/600V, 6A, 50W	BU 2508AF, 2SC3884A, 2SC3894, 2SC4830
25363	2SD2499	1500/600V, 6A, 50W	2SC4764
25364	2SD24Y	2SD24, 0,15A, 8MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
25365	2SD25	25V, 0,1A, 0,11W	AC 127, AC 176, AC 187, 2SD30
25366	2SD250	2SD249, 100V, 0,6MHz	BDY 29, MJ 802, 2SD797
25367	2SD2500	1500/600V, 10A, 50W	BU 2520AF, BUH 715, 2SC4542, 2SC4759
25368	2SD2504	B>300	2SC4482, 2SD1145
25369	2SD251	200/200V, 2A, 30W, -/7,5µs	BD 239F, BUX 67, 2SD610, 2SD1138
25370	2SD2510	1500V, 3A, 60W	BU 706F, 2SD1544, 2SD1654, 2SD1883
25371	2SD2511	1500V, 3A, 60W	BU 706F, 2SD1544, 2SD1654, 2SD1883
25372	2SD2512	1500V, 5A, 80W	BU 706F, 2SC4830, 2SD1545, 2SD1655
25373	2SD2513	1500V, 5A, 80W	BU 706F, 2SC4830, 2SD1545, 2SD1655
25374	2SD2514	1500V, 7A, 100W	BU 2508AF, 2SC3895, 2SC4757, 2SD2252
25375	2SD2515	1500V, 7A, 100W	BU 2508AF, 2SC3895, 2SC4757, 2SD2252
25376	2SD2521	1700V, 2,5A, 60W	2SC4761, 2SC4796
25377	2SD2522	1700V, 4A, 80W	2SC4761, 2SC4796
25378	2SD2523	1700V, 6A, 90W	BUH 417, BUH 517, 2SC4797
25379	2SD2524	1700V, 8A, 100W	BUH 517, 2SC4797

25380	2SD2525	60V, 3A, 1,8W, 3MHz	2SD1683, BD 785, 2SD1506, 2SB1818
25381	2SD2525	60V, 3A, 1,8W, 3MHz	2SD1683, BD 785, 2SD1506, 2SB1818
25382	2SD2525	60V, 3A, 1,8W, 3MHz	2SD1683, BD 785, 2SD1506, 2SB1818
25383	2SD2525	60V, 3A, 1,8W, 3MHz	2SD1683, BD 785, 2SD1506, 2SB1818
25384	2SD2526	100V, 5A, 1,8W, B2k..15k	-
25385	2SD2526	100V, 5A, 1,8W, B2k..15k	-
25386	2SD2529	2SD1938	2SD1938
25387	2SD2531	60V, 4A, 25W, 3MHz	BD 949F, 2SC3299, 2SC3746, 2SD1667
25388	2SD2532	2SD2484, SMD	2SC4409, 2SC4541, 2SD1623...24
25389	2SD2533	2SD2485, SMD	2SC4409, 2SC4541
25390	2SD2536	Rb3,6k, R	
25391	2SD2539	1500/600V, 7A, 50W	BU 2508DF, 2SC3892A, 2SC4123, 2SD2251
25392	2SD254	70V, 2A, 20W	BD 241A, BD 937, BDY 78, 2SC1398
25393	2SD2540	2SD2497, SMD	2SD1628
25394	2SD2544	2SD2486, 15W	2SD2486
25395	2SD255	70V, 2A, 20W	BD 241A, BD 937, BDY 78, 2SC1398
25396	2SD2553	1700/600V, 8A, 50W	BUH 517, 2SC4797
25397	2SD2557	200/200V, 5A, 70W, B>1500	-
25398	2SD2558	2SD2557, , 60W	-
25399	2SD256	60/40V, 4A, 25W, 1270/3300ns	BD 243A, BD 535, BDY 79, 2SC3179
25400	2SD2560	150/150V, 15A, 130W, B>5k	BDV 67D
25401	2SD2561	2SD2560, 17A, 200W	-
25402	2SD2562	2SD2560, , 85W	BDV 67DF
25403	2SD257	2SD256, 90/60V	BD 243B, 2SD712, BDY 79, 2SC3258
25404	2SD258	2SD256, 110/80V	BD 243C, BD 539D, BD 955, BDY 79
25405	2SD259	2SD256, 130/100V	BD 243D, BD 941, 2SC2516, 2SD960...961
25406	2SD26	40V, 7A, 50W	BD 245, BDV 91, BDX 91, 2N5873...5874
25407	2SD260	100V, 5A, 50W	BD 245C, BDV 95, BDX 95, 2N5632...33
25408	2SD261	40V, 0,5A, 0,5W, 160MHz	BC 337, BC 535, BC 637, 2SC3377
25409	2SD262	300/140V, 12A, 125W	BUW 74...75, BUX 42, MJ 15022, 2SC3043
25410	2SD265	800/400V, 6A, 100W, B>15	BU 326(A), BU 426(A), BU 526, BUX 47
25411	2SD266	2SD265, B>30	BU 326(A), BU 426(A), BU 526, BUX 47
25412	2SD26A	2SD26, 60V	BD 245A, BDV 91, BDX 91, 2N5873...5874
25413	2SD26B	2SD26, 100V	BD 245C, BDV 95, BDX 95, 2N5632...5633
25414	2SD26C	2SD26, 150V	BD 245D, BDX 11, 2N3442, 2SD731...732
25415	2SD27	32V, 0,5A, 0,28W	AC 127, AC 176, AC 187, 2SD72, 2SD352
25416	2SD271	800/400V, 2A, 30W, B>15	BUV 36(A), BUX 84...85, 2SC3531
25417	2SD272	2SD271, B>30	BUV 36(A), BUX 84...85, 2SC3531
25418	2SD273	800/400V, 5A, 80W, B>15	BUS 11(A), BUW 11(A), 2SC3796(A)
25419	2SD274	2SD273, B>30	BUS 11(A), BUW 11(A), 2SC3796(A)
25420	2SD28	70/40V, 3A, 18W	BD 241A, BD 537, BD 937, 2SD712
25421	2SD280	600/300V, 6A, 100W, B>350	BUW 81, MJ 10013...14, 2SD605, 2SD705
25422	2SD283	120V, 5A, 25W, B>42	BD 243C, BD 539D, BD 955, 2SD961
25423	2SD284	2SD283, 20MHz, B>25	BD 243C, BD 539D, BD 955, 2SD961
25424	2SD285	2SD283, 100V	BD 243C, BD 539C, BD 953, 2SD613

25425	2SD286	180/100V, 10A, 100W	BD 245E, 2SC2607...08, 2SC3263, 2SD665
25426	2SD287(A...C)	200/120V, 10A, 100W, 8MHz	BD 245F, 2SC2607...08, 2SC3263, 2SD665
25427	2SD288	80V, 3A, 20W, 35MHz	2SC3252, BD 241B, BD 537, BD 937
25428	2SD289	2SD288	2SC3252, BD 241B, BD 537, BD 937
25429	2SD29	2SD28, 70/60V	BD 241B, BD 537, BD 937, 2SD712
25430	2SD290	80V, 5A, 23W, 10MHz	BD 243B, BD 539B, BD 951, 2N4233A
25431	2SD291	70/40V, 3A, 18W, 4MHz	BD 241A, BD 537, BD 937, 2N4232...33
25432	2SD292	2SD291, 70/55V	BD 241A, BD 537, BD 937, 2N4232...33
25433	2SD293	800/400V, 10A, 125W, B>14	BUS 12(A), BUW 26, BUW 35...36, BUX 81
25434	2SD294	2SD293, B>28	BUS 12(A), BUW 26, BUW 35...36, BUX 81
25435	2SD295	800/400V, 30A, 200W, B>15	2SC2204, 2SC2977
25436	2SD296	2SD295, B>30	2SC2204, 2SC2977
25437	2SD297	150/80V, 3A, 25W, 40MHz	BD241D, 2N3441, 2SC2516, 2SD772(A,B)
25438	2SD299	1500V, 5A, 16W(Tc90°), B>2	BU 208(A), BU 706, 2SC2928, 2SD820
25439	2SD30	25V, 0,2A, 0,3W	AC 127, AC 176(K), AC 187(K), 2SD72
25440	2SD300	2SD299, B>3	BU 208(A), BU 706, 2SC2928, 2SD820
25441	2SD301(F)	80V, 10A, 50W, B2500	BDV 65A, BDX 83B, BDX 85B, MJ 3001
25442	2SD31	25V, 0,125A, 0,125W, B50	AC 127, AC 176, AC 187, 2SD30, 2SD72
25443	2SD310	800/400V, 15A, 150W, B>15	BUS 13(A), BUW 45...46, BUX 48(A...C)
25444	2SD311	2SD310, B>30	BUS 13(A), BUW 45...46, BUX 48(A...C)
25445	2SD312	800/600V, 0,5A, 25W(Tc100°)	2SC3151
25446	2SD313	60V, 3A, 30W, 8MHz	BD 241A, BD 535, BD 539A, BD 935
25447	2SD314	2SD313	BD 241A, BD 535, BD 539A, BD 935
25448	2SD315	2SD313, 4A, 35W	BD 243A, BD 535, BD 539A, 2N4232...33A
25449	2SD316(-1,-2)	80..100V, 7A, 80W, 12MHz	BD 245C, BDV 95, BDX 95, 2N5632...33
25450	2SD317	60V, 3A, 25W	BD 241A, BD 535, BD 935, 2N4232...33
25451	2SD317A	2SD317, 80V	BD 241B, BD 537, BD 937, 2N4233
25452	2SD318	2SD317	2SD317
25453	2SD318A	2SD318, 80V	2SD317A
25454	2SD319(Z)	110V, 10A, 100W, 1MHz	BD 317, 2N3055, 2N5632...33, 2SD426
25455	2SD32	2SD31, B90	AC 127, AC 176, AC 187, 2SD30, 2SD73
25456	2SD320	300/230V, 2A, 50W	2SC1463, 2SC2809, 2SD632
25457	2SD321	250V, 6A, 60W, 8MHz	BU 606...608, BUX 18(A...C), 2SD1154
25458	2SD322	120/80V, 7A, 80W	BD 245D, 2N3442, 2SD551, 2SD731...733
25459	2SD323	2SD322, 150/100V	BD 245D, 2N3442, 2SD551, 2SD731...733
25460	2SD324	300V, 0,1A, 10W(Tc70°)	2SC1505...1507, 2SC1755...1757, 2SC1819
25461	2SD325	35V, 1,5A, 10W, 8MHz	BD 239, BD 533, BD 933, 2SC1398
25462	2SD326	330/220V, 1A, 23W, 6,5MHz	TIP 47...50, 2SC782, 2SC867, 2SD860
25463	2SD327	40V, 0,5A, 0,25W, 120MHz	BC 337, BC 635, BC 637, 2SC3377
25464	2SD328(S)	100V, 1A, 0,8W, 50MHz	BC 141, 2N1990, 2N2102, 2N2405
25465	2SD329	70V, 1A, 0,8W, 30MHz, -/6,5µs	BC 140...141, 2N1990, 2N2102, 2N2405
25466	2SD33	20V, 0,05A, 0,15W	AC 127, 2SD30
25467	2SD330	50V, 2A, 20W, 8MHz	BD 239, BD 241, BD 535, BD 935
25468	2SD331	2SD330	BD 239, BD 241, BD 535, BD 935
25469	2SD332	130V, 7A, 65W, 30MHz	BD 245D, 2N3442, 2SD551, 2SD731...733



25470	2SD334	110V, 6A, 75W	BD 245C, 2N3442, 2SD551, 2SD731...733
25471	2SD334A	2SD334, 130V	BD 245D, 2N3442, 2SD551, 2SD731...733
25472	2SD335	80V, 3A, 30W	BD 245B, BDV 93, 2N4915, 2SD895...896
25473	2SD336	40V, 0,5A, 0,75W	BC 337, BC 635, BC 637, 2SC3377
25474	2SD338-1,-2	-170V, -290V, 7A, 60W, >3MHz	BD 245C, BDV 95, BDX 95, 2N5632...34
25475	2SD339-1,-2	80W	BD 245C, BDV 95, BDX 95, 2N5632...34
25476	2SD34	20V, 0,15A, 0,25W	AC 127, AC 176, AC 187, 2SD30, 2SD72
25477	2SD340-1,-2)	100W	BD 745E, 2N3442, 2SD551, 2SD733
25478	2SD341(H)	100V, 15A, 115W, >0,8MHz	BD 317, BDW 10, 2N3055, 2SD1105
25479	2SD342	70/40V, 3A, 35W	BD 241A, BD 537, BD 937, 2SC3179
25480	2SD343	2SD342	2SD342
25481	2SD344	2SD342, 70/55V	BD 241A, BD 537, BD 937, 2SC3179
25482	2SD345	2SD342, 70/55V	2SD344
25483	2SD346	60V, 5A, 25W	BD 243A, BD 543A, BD 949, 2SD1505
25484	2SD347	2SD346	2SD346
25485	2SD348	1500/400V, 7A, 50W	BU 2508A, BU 908, 2SC3027...3028
25486	2SD349	30V, 0,05A	BC 846...848, BCW 31...33, 2SC1622
25487	2SD35	20V, 0,06A, 0,083W	AC 127, 2SD72
25488	2SD350(A)	1500/700V, 5A, 22W(Tc90°)	BU 208A, BU 706, 2SC2928, 2SD954
25489	2SD351	650/270V, 5A, 80W, 40MHz	BU 326(A), BU 426(A), 2SC2962, 2SC3092
25490	2SD352	32V, 1A, 0,22W	AC 176
25491	2SD353	150V, 2A, 60W, 8MHz	2SC1195, 2SC2809, 2SD1136, 2SD1159
25492	2SD355	30V, 1A, 0,8W, 100MHz	BC 337...338, BC 635, BC 637, 2SD1225
25493	2SD355	30V, 1A, 0,8W, 100MHz	BC 337...338, BC 635, BC 637, 2SD1225
25494	2SD356	90V, 0,8A, 10W, 70MHz	2SC1913(A), 2SC2275(A), 2SC2591...92
25495	2SD357	2SD356, 110V	2SC1913(A), 2SC2275(A), 2SC2591...92
25496	2SD358	2SD356, 130V	2SC1913(A), 2SC2275(A), 2SC2591...92
25497	2SD359	40V, 2A, 10W, 70MHz	2SC1398, 2SC3252
25498	2SD36	20V, 0,06A, 0,083W	AC 127, 2SD72
25499	2SD360	40V, 2A, 10W, 70MHz	2SC1398, 2SC3252
25500	2SD361	60V, 1,5A, 10W, 70MHz	2SC1398, 2SC3252
25501	2SD362	150/100V, 5A, 40W, 15MHz	BU 406...409, MJE 15030, 2SD772(A,B)
25502	2SD363	<2/10,5µs	2SD374
25503	2SD363A	2SD363, 350/300V	2SD374
25504	2SD364	2SD363, 450/400V	2SD374
25505	2SD365	60V, 3A, 25W, >3MHz	BD 241A, BD 535, BD 935, 2SC3179
25506	2SD365A	2SD365, 80V	BD 241B, BD 537, BD 937, 2SC3179
25507	2SD366(A)	2SD365(A)	2SD365(A)
25508	2SD367	25V, 0,3W, 0,15W	AC 127, AC 176, AC 187, 2SD72, 2SD352
25509	2SD368	1300/400V, 5A, 50W	BU 207...208A, BU 706, BU 903, 2SC2928
25510	2SD369	80V, 10A, 100W, 2MHz	BD 315, BDW 21C, 2N3055, 2N5632...34
25511	2SD37	30V, 0,05A, 0,15W	AC 127, 2SD30
25512	2SD370	110V, 8A, 80W	BD 245C, BD 550, 2N3055, 2N5633...34
25513	2SD371	100V, 6A, 50W, 5MHz	BD 245C, BDV 95, BDX 95, 2SD895...896
25514	2SD372	150/100V, 30A, 200W, 0,3/2µs	2SD363



25515	2SD373	2SD372, 250/200V	2SD363
25516	2SD373A	2SD372, 350/300V	-
25517	2SD374	2SD372, 450/400V	-
25518	2SD375	150/100V, 10A, 100W, 15MHz	BUW 70, BUX 17(A...C), BUX 43, BUY 18
25519	2SD376	2SD375, 250/200V	BUW 72, BUX 17(A...C), BUX 43, BUY 18
25520	2SD376A	2SD375, 350/300V	BUW 72, BUX 14, BUX 17A...C, BUX 43
25521	2SD377	2SD375, 450/400V	BUW 72, BUX 14, BUX 17C, 2SC3046
25522	2SD378	100V, 2A, 1W	BCX 40, BSS 15, BSV 84, 2N5320
25523	2SD379	80V, 5A, 60W, 10MHz	BD 245B, BD 313, BDV 93, BDX 93
25524	2SD38	30V, 0,15A, 0,25W	AC 127, AC 176, AC 187, 2SD30, 2SD72
25525	2SD380(A)	1500/700V, 5A, 50W(Tc75°)	BU 208(A), BU 706, 2SC2928, 2SD954
25526	2SD381	130V, 1,5A, 20W, 45MHz	2SC2238(A), 2SC2275(A), 2SD608(A)
25527	2SD382	2SD381	2SD381
25528	2SD383	300/300V, 5A, 100W	BU 606...608, BUX 16A...C, BUY 35
25529	2SD384	80V, 7A, 30W, B>1500, <3/9µs	BD 647, BD 899, BDW 73B, BDX 53B
25530	2SD385	2SD384, 100V	BD 649, BD 901, BDW 73C, BDX 53C
25531	2SD386(A)	200/120V, 3A, 25W, 8MHz	BD 241F, 2SD772A,B
25532	2SD387(A)	2SD386(A), 2A	BD239F, 2SC2660, 2SD610, 2SD760, 2SD1138
25533	2SD388	150V, 8A, 80W, 9MHz	BD 245D, 2N3442, 2SD551, 2SD732...733
25534	2SD389	60V, 3A, 25W	BD 241A, BD 535, BD 935, 2SC3179
25535	2SD389A	2SD389, 80V	BD 241B, BD 537, BD 937, 2SC3179
25536	2SD390(A)	2SD389(A)	2SD389(A)
25537	2SD392	20V, 0,3A, 0,3W, 150MHz	BC 337...338, BC 635, BC 637, 2SC3377
25538	2SD392	20V, 0,3A, 0,3W, 150MHz	BC 337...338, BC 635, BC 637, 2SC3377
25539	2SD393	500/350V, 6A, 100W	BU 326(A), BU 426(A), BUX 15, 2SC3041
25540	2SD394	700/400V, 6A, 100W	BU 326(A), BU 426(A), BUX 47, 2SC3092
25541	2SD395	700/400V, 8A, 100W	BU 526(A), BUW 26, BUW 35...36, 2SC3049
25542	2SD396	<15/40µs	BUS 13(A), BUW 45...46, BUX 48(A...C)
25543	2SD400(MP)	25V, 1A, 0,9W, 180MHz	2SC4483...85, 2SD1207
25544	2SD400P1,P2	2SD400(MP), 1W	BD 505, BD 515, BD 525, 2SC2194
25545	2SD401(A)	200V, 2A, 20(A25)W, 5MHz	BD 239F, 2SC2660, 2SD610, 2SD1138
25546	2SD402(A)	2SD401(A)	2SD401(A)
25547	2SD404(G)	50V, 6A, 40W	BD 243A, BD 797, BD 805, 2SD1442A
25548	2SD405	70V, 2A, 1W, B>2000, 0,4/3µs	2SC1879, 2SC1888, 2SD614...615, 2SD688
25549	2SD406	2SD405, 100V	2SC1879, 2SD614...615, 2SD688
25550	2SD407	100V, 5A, 25W, B4000, 1,7/6µs	BD 649, BD 901, BDW 23C, BDW 63C
25551	2SD408	2SD407, 150V, hFE3000	2SD830, 2SD1128, 2SD1169, 2SD1590
25552	2SD409	2SD407, 30W	BD 649, BD 901, BDW 23C, BDW 63C
25553	2SD41	80V, 10A, 200W	BD 315, BD 317, 2N3772, 2N5629...31
25554	2SD410	2SD407, 150V, 30W, B3000	2SD830, 2SD1128, 2SD1169, 2SD1590
25555	2SD411	100V, 10A, 80W, B4000, 1/7µs	BDV 65B, BDW 83C, BDX 83C, BDX 85C
25556	2SD412	150/100V, 15A, 100W, B4000	2SD1296, 2SD1299
25557	2SD413	200/200V, 0,5A, 0,8W, 25MHz	2SD576, 2SD624, BF 757...759, MPSU 10
25558	2SD414	120/80V, 0,8A, 10W, 45MHz	2SC2690(A), 2SD1382, 2SD1563(A)
25559	2SD415	2SD414, 120/100V	2SC2690(A), 2SD1382, 2SD1563(A)

25560	2SD416	1500/400V, 7A, 50W	BU 508A, BU 908, 2SC3027...28, 2SC3686
25561	2SD417	250/200V, 7A, 75W, 30MHz	BU 606...608, BUX 18(A...C), 2SD1154
25562	2SD418	1000/500V, 5A, 80W	BU 207...208(A), BU 706, 2SC1413, 2SC3672
25563	2SD419	B2500	BD 649, BD 901, BDW 73C, BDX 53C
25564	2SD420	2SD419, 120/100V	BD 651, BDT 21, BDW 73D, BDX 53E
25565	2SD421	2SD419, 140V	BDX 53E,F, 2SD1386, 2SD1590...1591
25566	2SD422	250/200V, 4A, 30W, 30MHz	BU 406...409, 2N6233...35, 2SC2767
25567	2SD423	250/200V, 4A, 30W, 30MHz	BU 406...409, 2N6233...35, 2SC2767
25568	2SD424	180V, 15A, 150W, 5MHz	BDW 12, MJ15015, 2N3773, 2SC2607...2608
25569	2SD425	140V, 12A, 100W	BDW 12, BDY 54, 2SD551, 2SD1047
25570	2SD426	120V, 12A, 100W, 5MHz	BDW 10, 2SD551, 2SD733, 2SD1105
25571	2SD427(S)	120V, 8A, 80..100W, 5MHz	BD 550, 2N5633...34, 2SD551, 2SD733
25572	2SD428	100V, 7A, 60W, 7MHz	BD 245C, BDV 95, BDX 95, 2N5632...33
25573	2SD429	<20/15µs	BUS 13(A), BUW 45...46, BUX 48(A...C)
25574	2SD43	25V, 0,05A, 0,11W	AC 127, 2SD30
25575	2SD430	120/80V, 5A, 50W, 15MHz	BD 245D, 2N4347, 2N5759, 2SD896
25576	2SD431	120/80V, 7A, 60W, 20MHz	BD 245D, 2N4348, 2N5633...34, 2SD718
25577	2SD432	130/100V, 10A, 100W, 15MHz	BD 245D, 2N3442, 2SD551, 2SD733
25578	2SD433	250V, 10A, 100W, 15MHz	BUX 17(A...C), 2SC1586, 2SD555, 2SD583
25579	2SD434	200/200V, 20A, 200W	BUV 11...12, BUW 58, BUW 73, BUX 11...12
25580	2SD435	2SD434, 300/300V	BUV 12, BUV 24, BUW 73, BUX 12, BUX 24
25581	2SD436	2SD434, 400/400V	BUV 24, BUX 24, 2SC3085
25582	2SD437(W)	600/350V, 10A, 80W, 2,5MHz	BUW 12(A), BUW 25...26, BUX 80, 2SC3046
25583	2SD438(MP)	100V, 0,7A, 0,9W, 100MHz	2SC4488, 2SC4489, 2SD667, 2SD1812
25584	2SD439	20V, 1,2A, 8W, 150MHz	BD 135, BD 226, BD 375, 2SD1380
25585	2SD43A	2SD43, 45V, 0,15A	-
25586	2SD44	30V, 0,05A, 0,08W	AC 127, 2SD30
25587	2SD445	350/300V, 4A, 60W, B>350	BUX 28...29, 2SD650, 2SD706, 2SD1043
25588	2SD45	150/100V, 5A, 50W, 20MHz	BD245D, BDX11, 2N3442, 2SD551, 2SD732
25589	2SD457	250/200V, 55A, 200W	-
25590	2SD458	600/400V, 5A, 80W	BU326(A), BU426(A), BUW 11(A), 2SC2962
25591	2SD459	80V, 7A, 50W, B>1500, 3/9µs	BD 647, BD 899, BDW 73B, BDX 53B
25592	2SD46	2SD45, 150/75V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
25593	2SD460	2SD459, 100V	BD 649, BD 901, BDW 73C, BDX 53C
25594	2SD461	250/250V, 3A, 80W, 1MHz	BU 606...608, BUX 16(A...C), 2SD632
25595	2SD463	80V, 7A, 80W, B3000, <10/16µs	BDX 63A, TIP 141...142, 2SD628...629
25596	2SD464	2SD463, 100V	BDX 63B, TIP 142, 2SD628...629, 2SD1230
25597	2SD465	500/400V, 50A, 400W, B>150	-
25598	2SD466	2SD465, 600/450V	-
25599	2SD467	25V, 0,7A, 0,5W, 280MHz	BC 337...338, BC 635, BC 637, 2SD1225
25600	2SD468	2SD467, 1A, 0,9W, 190MHz	2SC2236, 2SC4483, 2SD1207, 2SD1331
25601	2SD469	0,5/3,5µs	BD 245D, 2N3442, 2SD551, 2SD733
25602	2SD47	2SD45, 100/50V	BD 245C, BDV 95, BDX 95, 2N5632...33
25603	2SD470(-B)	1600/700V, 1A, 15W	BU 505, 2SD948, 2SD1575
25604	2SD471	30V, 1A, 1W, 130MHz	BC 337...338, BC 635, BC 637, 2SD1225

25605	2SD472(H)	150V, 10A, 80W, B>1000, 2/9 $\mu$ s	BDV 67D, 2SD922, 2SD1296, 2SD1299
25606	2SD473(H)	2SD472, 100V, 15A, 100W	BDV 67A, BDW 83C, BDX 67B, MJ 4035
25607	2SD474(K)	30V, 0,1A, 0,05W, >100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
25608	2SD475(A)	70V, 4A, 40W, 7MHz	BD 243B, BD 537, BD 539B, BD 951
25609	2SD476(A)	2SD475(A)	2SD475(A)
25610	2SD477	200/150V, 2A, 30W	BD239F, 2SC2660, 2SD610, 2SD760, 2SD1138
25611	2SD478	2SD477	2SD477
25612	2SD479	40V, 4A, 40W, B6000	BD 675, BD 775, 2N6037...6039
25613	2SD48(N)	100V, 3A, 20W	BD 241C, BD 539C, BD 939, 2SD712
25614	2SD480	2SD479, 60V	BD 677, BD 777, 2N6038...6039
25615	2SD481	2SD479, 80V	BD 679, BD 779, 2N6039
25616	2SD482	275/250V, 0,5A, 20W	MJE 340, 2N5655, 2SC2752, 2SC2899
25617	2SD483	2SD482, 325/300V	MJE 340, 2N5656, 2SC2752, 2SC2899
25618	2SD484	2SD482, 375/350V	BD 410, 2N5657, 2SC2899, 2SC3051
25619	2SD485	40V, 4A, 40W	BD 185, BD 437, BD 785, 2N5190...92
25620	2SD486	2SD485, 60V	BD 187, BD 439, BD 787, 2N5191...92
25621	2SD487	2SD485, 80V	BD 189, BD 441, BD 787, 2N5192
25622	2SD488	40V, 3A, 30W	BD 175, BD 185, BD 437, 2N4921...23
25623	2SD489	2SD488, 60V	BD 177, BD 187, BD 439, 2N4922...23
25624	2SD49	100V, 3A, 18W	BD 241C, BD 539C, BD 939, 2SD877
25625	2SD490	2SD488, 80V	BD 179, BD 189, BD 441, 2N4923
25626	2SD491	70V, 10A, 90W	BD 207, MJE 3055
25627	2SD492	2N3055	2N3055
25628	2SD493	60V, 5A, 75W	BD 199, 2N5977...5979
25629	2SD494	2SD493, 80V	2N5978...5979
25630	2SD495	2SD493, 100V	2N5979
25631	2SD496	60V, 8A, 75W, B3000	BDV 65A...C, TIP 140...142
25632	2SD497	2SD496, 80V	BDV 65A...C, TIP 141...142
25633	2SD498	2SD496, 100V	BDV 65B...C, TIP 142
25634	2SD499	60V, 8A, 90W	BD 207, 2N5983...5985
25635	2SD50(N)	100V, 6A, 50W	BD 245C, BDV 95, BDX 95, 2N5632...33
25636	2SD500	2SD499, 80V	2N5984...5985
25637	2SD501	2SD499, 100V	2N5985
25638	2SD502	60V, 8A, 100W, B3000	BDV 65(A...C), BDX 83A...C, BDX 85A...C
25639	2SD503	2SD502, 80V	BDV 65A...C, BDX 83B...C, BDX 85B...C
25640	2SD504	60V, 12A, 150W, B3000	BDV 65(A...C), BDW 83A...D, BDX 87A...C
25641	2SD505	2SD504, 80V	BDV 65A...C, BDW 83B...D, BDX 87B...C
25642	2SD506	2SD504, 100V	BDV 65B...C, BDW 83C...D, BDX 87C
25643	2SD507	90V, 250A, 625W, <5/10 $\mu$ s	-
25644	2SD508	2SD507, 110V	-
25645	2SD509	2SD507, 130V	-
25646	2SD51(N)	100V, 6A, 50W	BD 245C, BDV 95, BDX 95, 2N5632...33
25647	2SD510	2SD507, 150V	-
25648	2SD511	90V, 250A, 625W, <5/10 $\mu$ s	-
25649	2SD512	2SD511, 110V	-

25650	2SD513	2SD511, 130V	-
25651	2SD514	90V, 250A, 625W, <5/10µs	-
25652	2SD515	2SD514, 110V	-
25653	2SD516	20V, 1,5A, 5W, B100..500	BD 135, BD 165, BD 226, BD 233
25654	2SD517	1500/700V, 3A, 16W(Tc90°)	BU 208A, BU 706, 2SC3023...24, 2SD1495
25655	2SD518	220/200V, 4A, 30W, 30MHz	BU 406...409, 2SC2767, 2SD422...423
25656	2SD519	<3,5/6,5µs	BUW 25...26, BUW 35...36, 2SC3046
25657	2SD51A(AN)	2SD51, 150V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
25658	2SD52(N)	100V, 6A, 80W	BD 245C, BDV 95, BDX 95, 2N5632...33
25659	2SD520	600/400V, 7A, 100W, B>350	BUW 81(A), 2SD528, 2SD605, 2SD705
25660	2SD521	700/450V, 8A, 100W, B>200	BUT 50P, BUW 81A, 2SC3030...3033
25661	2SD522	100V, 10A, 100W	BD 317, BDW 21C, 2N3055, 2N5632...34
25662	2SD523	80V, 7A, 50W, B>2000	BDV 65A, BDX 63A, MJ 1001, 2N6056
25663	2SD524	80V, 15A, 100W, B>2000	BDW 83B, BDX 67A, MJ 4034...4035
25664	2SD525	100V, 5A, 40W, 12MHz	BD 243C, BD 543C, BD 953, 2SD613
25665	2SD526	80V, 4A, 30W, >3MHz	BD 243B, BD 537, BD 951, 2SD1236L
25666	2SD528(H)	600/500V, 8A, 100W, B>350	BUW 81(A), 2SD520...521, 2SD605, 2SD705
25667	2SD529	850/320V, 5A, 85W, 4MHz	BU 326A, BU 426A, BUS 11(A), 2SC3155
25668	2SD52A(AN)	2SD52, 130V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
25669	2SD53(N)	90V, 10A, 100W	BD 245C, BDV 95, BDX 95, 2N5632...33
25670	2SD531(-1,-2)	100V, 5A, 43W, 9MHz	BD 243C, BD 539C, BD 953, 2SD613
25671	2SD532	200/70V, 7A, 70W, 9MHz	BU 606...608, 2SC2262, 2SC2769, 2SD751
25672	2SD533	270/90V, 10A, 100W, 8MHz	BUX 17(A...C), BUX 42...43, 2SC2961
25673	2SD534	110V, 12A, 100W, 5MHz	BD 317, BDW 10, 2N3055, 2N5629...31
25674	2SD535	250/120V, 12A, 150W, 1,5/8µs	BUW 74, BUX 41...42, MJ 15022, 2SD583
25675	2SD536	200/200V, 10A, 100W, -/1,8µs	BUX 17(A...C), BUX 42...43, 2SC2769
25676	2SD537	2SD536, 200/150V	BUX 17(A...C), BUX 42...43, 2SC2769
25677	2SD538(A)	15MHz	BUW25...26, BUW34...36, 2SC3046, 2SC4138
25678	2SD539(A)	2SD538(A), 400/350V	BUW24...26, BUW34...36, 2SC3046, 2SC4138
25679	2SD53A(AN)	2SD53, 130V	BD245D, BDX11, 2N3442, 2SD551, 2SD733
25680	2SD54(N)	100V, 10A, 150W	BD 249C, BD 745C, 2SD1049
25681	2SD540	200/200V, 30A, 200W, 25MHz	2SC2249, 2SC2445, 2SC2940, 2SC3224
25682	2SD541	2SD540, 200/150V	2SC2249, 2SC2445, 2SC2940, 2SC3224
25683	2SD542	400/400V, 30A, 200W, 20MHz	2SC1302, 2SC1401, 2SC1470, 2SC2250
25684	2SD543	2SD542, 400/350V	2SC1302, 2SC1401, 2SC1470, 2SC2250
25685	2SD544(-1,-2)	2SD531-..	2SD531
25686	2SD545(NP)	25V, 1A, 0,5W, 180MHz	2SC4483...85, 2SD1207, 2SD1247
25687	2SD546	800/500V, 1A, 30W, 7MHz	BUV 36(A), BUX 84...85, 2SC1828, 2SC3352
25688	2SD547	600/450V, 50A, 400W, 1/10,5µs	-
25689	2SD549	30V, 1,5A, 15W, B>4000	BD 675, BD 775, 2SD985...986, 2SD1379
25690	2SD55(N)	100V, 20A, 200W	BDW 30, BDY 29, MJ 802, 2N3772, 2SD797
25691	2SD550	120V, 7A, 40W, 10MHz	BD 243C, BD 543D, MJ 15028, 2SD866
25692	2SD551	150V, 12A, 100W, 15MHz	BD 745E, 2SC1584, 2SD733, 2SD1047
25693	2SD552	1/4µs	BUX41, 2SC1586, 2SC2608, 2SC3263, 2SD583
25694	2SD553	70V, 7A, 40W, 10MHz, 0,2/3µs	2SC3254, 2SD1237L

25695	2SD554	250V, 2A, 30W	BUX 67(A...C), 2N3583...85, 2SD610
25696	2SD555	250V, 10A, 200W, 15MHz	BUX 17A...C, BUY 18, 2SC1576, 2SD583
25697	2SD556	110V, 15A, 120W, 8MHz	BD 745C, BDW 10, 2N5630...31, 2SD1105
25698	2SD557	2SD556, 140V	BD 745E, BDW 10, 2N5631, 2SC2607...08
25699	2SD558	90V, 2A, B>2000, 0,4/3μs	2SD1223, 2SD1520, 2SD1980
25700	2SD55A(AN)	2SD55, 130V	BDW 30, BDW 32, BDY 58
25701	2SD56	220V, 3A, 30W	D44Q3, TIP 75(A...C), 2SC867A, 2SC2767
25702	2SD560	150V, 5A, 30W, B2k..15k	2SD830, 2SD1128, 2SD1169, 2SD1590
25703	2SD565	400/400V, 10A, 100W, B>800	BU 920...922, MJ 10002...03, 2SD685
25704	2SD568	100V, 7A, 40W	MJE 15028, BD 543B, BD 799, BD 809
25705	2SD569	100V, 7A, 40W	MJE 15028, BD 543B, BD 799, BD 809
25706	2SD57	30V, 3A, 20W	BD 241, BD 533, BD 933, 2SD877
25707	2SD570	70V, 4A, 30W, >3MHz	BD 243A, BD 537, BD 951, 2SC3179
25708	2SD571	60V, 0,7A, 1W, 110MHz	BC 637, BC 639, 2SD667, 2SD1226
25709	2SD572	500/400V, 15A, 150W, B>80	BU 932, 2SD683, 2SD711(A)
25710	2SD573	2SD572, 600/450V	2SD683, 2SD711A
25711	2SD574(A)	120/120V, 30A, 400W, B>200	-
25712	2SD575	1400/600V, 2,5A, 50W	BU 205...206, 2SC1922, 2SD818...819
25713	2SD575L	2SD575, 1200/600V	BU 204...206, 2SC1922, 2SD818...819
25714	2SD576	250V, 0,5A, 0,8W, 200MHz	BFQ 38...40, 2N5010, BF 757...759
25715	2SD577	1500V, 3A, 16W(Tc90°)	BU 208...209A, BU 706, 2SC3023...24
25716	2SD578	500/140V, 8A, 100W, B>350	BU 922, 2SD528, 2SD605, 2SD796
25717	2SD578(A)	180V, 2A, 30W	BD 239E, 2SC2660, 2SD760, 2SD1138
25718	2SD579	100V, 4A, 40W	BD 243C, BD 539C, BD 953, 2N3767
25719	2SD58	2SD57, 60V	BD 241A, BD 535, BD 935, 2SD877
25720	2SD580	60V, 1A, 20W, 1,2MHz	BD 137, BD 167, BD 228, BD 235
25721	2SD581(A)	150/100(A/120)V, 7A, 60W	BDX 11, 2SD732, 2SD751, 2SD1046
25722	2SD582(A)	180/140(A/160)V, 12A, 100W	BDW 14, MJ 15015, 2SC2607...08, 2SD424
25723	2SD583	250V, 15A, 150W	BUX 41, MJ 15022, MJ 15024, 2SC1586
25724	2SD585	110V, 7A, 80W, B>1100	BDV 65C, BDX 63C, BDX 65C, 2SD1210
25725	2SD586(A)	100V, 5A, 60W, 15MHz	2SC2276, 2SD848(A), 2SD883(A)
25726	2SD587(A)	120V, 6A, 70W, 17MHz	2SC2276, 2SB848(A), 2SB883A
25727	2SD588(A)	150V, 7A, 80W	-
25728	2SD589	1500V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD954
25729	2SD59	100V, 6A, 50W	BD 245C, BDV 95, BDX 95, 2N5632...33
25730	2SD590	100V, 2A, 1W, <150/210ns	2SD854, BD 379, BD 529, 2SD1177...78
25731	2SD591	30V, 0,05A, 0,15W, 150MHz	BC 169, BC 184, BC 239, BC 549, 2SC2390
25732	2SD592(NC)	30V, 1A, 0,75W, 200MHz	BC 337...338, BC 635, BC 637, 2SD1225
25733	2SD592A(ANC)	2SD592, 60V	BC 637, BC 639, 2SD667, 2SD1616
25734	2SD593	500/400V, 0,3A, 0,8W, 15MHz	2N5010...5015, 2SC1762
25735	2SD594	2SD593, 800/700V	2N5013...5015
25736	2SD596	30V, 0,7A, 170MHz	BCW 65...66, 2SD1782
25737	2SD597	100V, 5A, 60W, 7MHz	BD 245C, BDV 95, BDX 95, 2SD731...732
25738	2SD598	2SD597, 120V, 6A, 80W, 6MHz	BD 245C, 2SC2681, 2SC4466, 2SD731...732
25739	2SD599	25V, 1A, 0,35W, 180MHz	BC 337...338, BC 635, BC 637, 2SD1225



25740	2SD60	2SD59, 150/75V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
25741	2SD600	100V, 1A, 8W, 130MHz	BD 139, BD 230, BD 379, 2SD1684
25742	2SD600K	2SD600, 120V	2SC2690(A), 2SD1382, 2SD1563, 2SD1684
25743	2SD601	30V, 0,1A, 150MHz	BC 846...848, BCW 31...33, BCW 71...72
25744	2SD601A	2SD601, 60V	BC 846, BCV 71...72, 2SC3323...3324
25745	2SD602	30V, 0,5A, 200MHz	BC 817...818, BCW 65...66, BCX 19...20
25746	2SD602A	2SD602, 60V	BCW 65...66, 2SC4519
25747	2SD603	30V, 0,1A, 0,25W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
25748	2SD604	180/180V, 5A, 100W, B>400	2SD920...921, 2SD1090, 2SD1122...1123
25749	2SD605(D)	B>200	BUW 81(A), 2SD520...521, 2SD528, 2SD705
25750	2SD606	600/500V, 15A, 100W, B>200	BUT 51P, 2SD573, 2SD683, 2SD711A
25751	2SD608	160/160V, 1,5A, 20W, 45MHz	BD 239D, 2SC2592, 2SC3364, 2SD1562A
25752	2SD608A	2SD608, 180/180V	BD 239E, 2SC2344, 2SD608A
25753	2SD61	30V, 0,1A, 0,12W	AC 127, 2SD30
25754	2SD610	250/200V, 2A, 25W, 5MHz	2SC2023, 2SD772B
25755	2SD611	100V, 7A, 30W	BD 243C, BD 543C, BD 801, 2N5429...30
25756	2SD611A	2SD611, 120V	BD 243C, BD 543D, 2SD550, 2SD866
25757	2SD612	25V, 2A, 10W, 100MHz	BD 329, BD 375, 2SD1380, 2SD1506
25758	2SD612K	2SD612, 35V	BD 375, 2SD794(A), 2SD1380, 2SD1506
25759	2SD613	100V, 6A, 40W, 15MHz	BD 243C, BD 543C, BD 801, 2SD866
25760	2SD613P	2SD613, 50W	2SD587...588, 2SD883(A), 2SD848(A)
25761	2SD614	100/80V, 3A, 0,8W, B3000	2SC2208, BD 681, BDW 53C,D, 2SD1091
25762	2SD615	2SD614, 140/120V	2SD830, 2SD1091, 2SD1128, 2SD1169
25763	2SD616	120V, 7A, 60W, 15MHz	BD 245C, 2SC2681, 2SD731...733, 2SD1046
25764	2SD617	120/100V, 8A, 100W, B2500	BDV 65C, BDX 63C, 2SD922
25765	2SD619	80V, 1,5A, 0,5W, 100MHz	MPS 651, 2SC3328, 2SD1665, 2SD1857
25766	2SD62	30V, 0,1A, 0,12W	AC 127, 2SD30
25767	2SD620	2SD619	BD 139, BD 230, BD 379, 2SD1177...78
25768	2SD621	2500/900V, 3A, 50W	2SD838
25769	2SD622	450/400V, 3A, 30W, 25MHz	BUY63...65, TIP75B,C, 2SC1466, 2SC2929
25770	2SD624	200/150V, 0,5A, 0,8W, 50MHz	2SD413, 2SD576, BF 757...759, MPSU 10
25771	2SD625	250V, 4A, 6,2W(Tc25°), 60MHz	BUY 49, BU 406...409, 2SC2767
25772	2SD626	600V, 6A, 80W, B>300, <1/45µs	BUW 81, 2SD520, 2SD528, 2SD605, 2SD705
25773	2SD627	1500/600V, 3A, 50W	BU 208...209(A), BU 706, 2SC3023...24
25774	2SD628(H)	100V, 10A, 80W, B>1000	BDV 65B, BDX 83C, BDX 85C, 2N6059
25775	2SD629(H)	2SD628, 100W	BDV 65B, BDX 83C, BDX 85C, 2N6059
25776	2SD63	25V, 0,1A, 0,12W	AC 127, 2SD30
25777	2SD630	50V, 30A, 200W, 0,8MHz	BDX 41, BDY 29, MJ 802, 2N3771
25778	2SD631	60V, 40A, 200W	2N6032, 2N6274...6275
25779	2SD632	350/300V, 2,5A, 80W	BUX 16B,C, TIP 51...54, 2SC1463, 2SC2624
25780	2SD633	100V, 7A, 40W, B>2000	BD 649, BD 901, BDW 73C, BDX 53C
25781	2SD634	2SD633, 80V	BD 647, BD 899, BDW 73B, BDX 53B
25782	2SD635	2SD633, 60V	BD 645, BD 897, BDW 73A, BDX 53A
25783	2SD636	30V, 0,1A, 0,4W, 150MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
25784	2SD637	2SD636, 60V	BC 174, BC 182, BC 190, BC 546, 2SD767



25785	2SD638	30V, 0,5A, 0,6W, 200MHz	BC 337...338, BC 635, BC 637, 2SD1578
25786	2SD639	2SD638, 60V	BC 637, BC 639, 2N3700...01, 2SC2235
25787	2SD64	25V, 0,1A, 0,12W	AC 127, 2SD30
25788	2SD640	600/400V, 7A, 100W, 3MHz	BU 526, BU 536, BU 626A, 2SD1094
25789	2SD641	600/400V, 15A, 150W, 4MHz	BUS 13(A), BUW 45...46, BUX 48A...C
25790	2SD642	600/400V, 40A, 300W	2SC1435
25791	2SD643	300/200V, 30A, 300W, B>150	-
25792	2SD644	600/450V, 30A, 300W, B>150	-
25793	2SD645	600/450V, 30A, 350W, B>150	-
25794	2SD646(A)	600/450V, 50A, 400W, B>150	-
25795	2SD649	1500/600V, 6A, 80W	BU 2508A, 2SC3025...26, 2SC3685, 2SD821
25796	2SD65	25V, 0,1A, 0,12W	AC 127, 2SD30
25797	2SD650(H)	400/400V, 6A, 80W, B>500	BU 180A, BU 284, BU 826
25798	2SD651(H)	400/400V, 4A, 30W, B>500	BU 910...912, 2SD977, 2SD1072, 2SD1245
25799	2SD652	500/500V, 6A, 80W, B3000	BU 322(A), BUW 81, 2SD796, 2SD980
25800	2SD654	50V, 0,5A, 0,57W, 190MHz	BC 140...141, BC 300...302, 2N3053
25801	2SD655	30V, 0,7A, 0,5W, 250MHz	BC 337...338, BC 635, BC 637, 2SD1578
25802	2SD656	200/180V, 1,5A, 30W, >2MHz	BD239F, BUX 67(A...C), 2SC783, 2SD1138
25803	2SD657	200/200V, 1,5A, 50W	BD 239F, 2SC1195, 2SC2809, 2SD632
25804	2SD658	1500/600V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD820
25805	2SD66	25V, 0,1A, 0,12W	AC 127, 2SD30
25806	2SD660	90V, 2A, 1W, 150/2100ns	BCX 40, BSS 15, BSV 84, 2N5320
25807	2SD661	35V, 0,1A, 0,4W, 200MHz	BC 169, BC 184, BC 239, BC 549, 2SC2240
25808	2SD661A	2SD661, 55V	BC 414, BC 550, 2SC2675, 2SC2390
25809	2SD662	250/200V, 0,07A, 0,6W, 80MHz	BF 298...299, BF 422A, 2SC3468, 2SC4218
25810	2SD662B	2SD662, 400/400V	2SC2267, 2SC3469, 2SC4166, 2SD1385
25811	2SD663	500/500V, 6A, 80W, B>400	BUW 81, 2SD520, 2SD528, 2SD605, 2SD705
25812	2SD664	80V, 7A, 40W, B>2000	BD 647, BD 899, BDW 73B, BDX 53B
25813	2SD665	200/200V, 15A, 150W, 15MHz	BDW 16, 2SC2607...2608, 2SD552, 2SD583
25814	2SD666(A)	120V, 0,05A, 0,9W, 140MHz	2SC2632, 2SC3245(A), 2SC3248, 2SC3800
25815	2SD667(A)	2SD666(A), 1A	2SC2383, 2SC3228, 2SD1292, 2SD1812
25816	2SD668(A)	180V, 0,05A, 20W, 140MHz	BF 469, BF 471, BF 415, BF 417, 2SC3416
25817	2SD669(A)	2SD668, 1,5A	2SC3117
25818	2SD67	120V, 5A, 50W, 100MHz	2SC2706, 2SC2837, 2SC2987(A), 2SD1047
25819	2SD670(H)	100V, 15A, 100W, B>1000	BDV 67A, BDW 83C, BDX 67B, MJ 4035
25820	2SD671	30V, 0,5A, 0,6W, 150MHz	BC 337...338, BC 635, BC 637, 2SC3377
25821	2SD672	300V, 1A, 40W(Tc45°), 20MHz	2SC1463, 2SC2809, 2SD632
25822	2SD673(A)	120V, 7A, 60W, 8MHz	BD 245C, 2SC2681, 2SC4466, 2SD731...733
25823	2SD674(A)	2SD673, 80W	BD 245C, 2SC2681, 2SC4466, 2SD731...733
25824	2SD675(A)	160V, 12A, 100W, 8MHz	BD 745F, 2SD424, 2SD733, 2SD1047
25825	2SD676(A)	2SD675, 125W	BD 745F, 2SC2607...2608, 2SD753
25826	2SD677	450V, 5A, 100W	BU 426(A), BUW 11(A), BUW 71, BUX 45
25827	2SD678	60V, 3A, 25W, B>1000	BD 715, BDW 23A, BDW 53A, 2SD837
25828	2SD678A	2SD678, 80V	BD 717, BDW 23B, BDW 53B, 2SD837A
25829	2SD679	70V, 4A, 40W, B>1000	BD 717, BDW 23B, BDW 53B, BDW63B

25830	2SD679A	2SD679, 90V	BD 901, BDW 23C, BDW 53C, BDW 63C
25831	2SD68	2SD67, 75V	2SC2681, 2SC2706, 2SC2837, BD 245B
25832	2SD680	90V, 6A, 60W, B>1000	BDV 65B, BDX 63B, TIP 142, 2SD1170
25833	2SD680A	2SD680, 110V	BDV 65C, BDX 63C, TIP 142, 2SD1170
25834	2SD681	100V, 8A, 80W, B>1000	BDV 65B, BDX 63B, BDX 83C, TIP 142
25835	2SD681A	2SD681, 120V	BDV 65C, BDW 84D, BDX 63C, BDX 65C
25836	2SD682	120V, 8A, 110W, B>1000	BDV 65C, BDV 67B, BDW 83D, BDX 65C
25837	2SD682A	2SD682, 140V	BDV 67C, 2SD1296, 2SD1299
25838	2SD683	600/400V, 15A, 150W, B>500	BUT 51, 2SD573, 2SD606, 2SD711A
25839	2SD683A	2SD683, 600/450V	BUT 51, 2SD573, 2SD606, 2SD711A
25840	2SD684	600/300V, 6A, 30W, B>1500	BU 810, 2SC3579, 2SD798...799
25841	2SD684A	600/400V, 6A, 30W, B>600	BU 810, 2SC3579, 2SD799
25842	2SD685	600/400V, 10A, 100W, B>400	BUW 81(A), MJ 10013...14, 2SC3262
25843	2SD686	100V, 4A, 30W, B>2000	BD 901, BDW 23C, BDW 53C, BDW 63C
25844	2SD687	60V, 3A, 25W, B>2000	BD 899, BDW 23A, BDW 53A, BDW 63A
25845	2SD688	B>2000	2SC1879, 2SD406, BD 681
25846	2SD689	2SD688, 10W	BDT 61B, BDW 53C, 2SD837B
25847	2SD69	140V, 3A, 50W, 13MHz	BDX 12, 2N5760, 2SC2706, 2SC2837
25848	2SD690	70V, 7A, 40W, 10MHz	BD 543B, BD 799, BD 809, 2N6372...73
25849	2SD691	100V, 6A, 40W, B>500	BD 649, BD 901, BDW 73C, BDX 53C
25850	2SD692	2SD691, 50W	BDV 65B, BDX 63B, BDX 83C, BDX 85C
25851	2SD693	450/450V, 10A, 80W, B>150	BU 922, BUW 81(A), MJ10003, 2SD685
25852	2SD694	400/350V, 30A, 300W, B>150	-
25853	2SD695	400/350V, 30A, 350W, B>150	-
25854	2SD696(A)	400/350V, 50A, 400W, B>150	-
25855	2SD699	300/200V, 30A, 250W, B>150	-
25856	2SD70	40V, 2A, 15W	BD 239, BD 241, BD 933, 2SC2528
25857	2SD702	400/300V, 40A, 300W	2SC1435, 2SC2366, 2SD642
25858	2SD703	200/150V, 30A, 300W, B>150	-
25859	2SD704	50V, 5A, 40W, 10MHz	BD 245(A...C), BDV 91, BDV 93, BDV 95
25860	2SD705	600V, 8A, 80W, B300	BUW 81(A), 2SD520, 2SD528, 2SD605
25861	2SD706	345V, 6A, 80W, B1000	BU 322(A), BUX 28...29, 2SD720
25862	2SD707	500V, 8A, 100W, B>200	BU 922, BUW 81(A), MJ 10013...14
25863	2SD708	345V, 6A, 30W, B1000	BU 910...912, 2SD835, 2SD1114, 2SD1245
25864	2SD709	250V, 4A, 25W, B>1500	2SD816, 2SD834, 2SD1073
25865	2SD71	100V, 2A, 15W	BD 239C, BD 241C, BD 937, 2SC2528
25866	2SD710	300V, 15A, 150W, B500	BU 930...932, 2SD572...573, 2SD683
25867	2SD711	500/450V, 15A, 100W, B>100	BU 932, 2SD572...573, 2SD606, 2SD683
25868	2SD711A	2SD711, 600/600V, B>200	BUT 51P, 2SD573, 2SD606, 2SD683
25869	2SD712	100V, 4A, 30W, 8MHz	BD 243C, BD 539C, BD 953, 2SD613
25870	2SD712A	2SD712, 280V	TIP 75(A...C), 2SC2826, 2SC2929
25871	2SD713	100V, 5A, 40W, 8MHz	BD 243C, BD 539C, BD 953, 2SD613
25872	2SD715	110V, 7A, 80W, B>2000	BDV 65C, BDW 83D, 2SD1210
25873	2SD716	100V, 6A, 60W, 12MHz	BD 245C, BDV 95, 2SC2681, 2SD895...96
25874	2SD717	70V, 10A, 80W, 10MHz	2SD1187, 2SD1238L

25875	2SD718	120V, 8A, 80W, 12MHz	BD 245C, 2SC2681, 2SC2706, 2SC2837
25876	2SD72	25V, 0,6A, 0,21W	AC 176, AC 187, 2SD352
25877	2SD720	400/400V, 7A, 100W, B>400	BU 322(A), BUX 29, 2SD707, 2SD796
25878	2SD721	100V, 6A, 50W, B1000	BD 649, BD 901, BDW 73C, BDX 53C
25879	2SD722	2SD721, 120V	BD 651, BDT 21, BDW 73D, BDX 53E
25880	2SD723	100V, 4A, 40W	BD 243C, BD 539C, BD 953, 2SD712
25881	2SD724	200V, 4A, 30W	BD 243F, 2SC2767, 2SD772A,B
25882	2SD725	1500/600V, 6A, 50W	2SC2027
25883	2SD726	100V, 4A, 40W, 10MHz	BD 243C, BD 539C, BD 953, 2SD712
25884	2SD727	130V, 5A, 60W, 7MHz	BD 245D, 2SD731, 2SD751, 2SD1046
25885	2SD728	2SD727, 150V, 6A, 70W	BD 245D, 2SC3263, 2SD731, 2SD751
25886	2SD729(H)	100V, 20A, 125W, B>1000	BDX 69B, MJ 11014, 2N6284, 2SD1460
25887	2SD72K	2SD72, 0,72W	AC 176K, AC 187K, 2SD352
25888	2SD73	100V, 5A, 60W, 20MHz	BD 245C, BDV 95, BDX 95, 2N5632...33
25889	2SD730(H)	2SD729, 25A	BDX 69B, MJ 11014, MJ 11016, 2SD1460
25890	2SD731	170V, 7A, 80W, 7MHz	BD 245E, 2SC3263, 2SD751
25891	2SD732(K)	150V, 8A, 80W, 15MHz	BD 245D, 2SC2837, 2SD551, 2SD752
25892	2SD733	160/140V, 12A, 100W, 15MHz	BD 745E, MJ 15015, 2SC2607...08
25893	2SD733K	2SD733, 180/160V	BD 757F, MJ 15015, 2SC2607...08
25894	2SD734	25V, 0,7A, 0,6W, 250MHz	2SC4483, 2SD1207, 2SD1302, 2SD1616
25895	2SD735	160/120V, 12A, 100W	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
25896	2SD736(A)	2SD735, 160/140V	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
25897	2SD737	160V, 12A, 120W	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
25898	2SD738(A)	160V, 12A, 125W	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
25899	2SD74	2SD73, 150/90V	BD 245D, BDX 11, 2N3442, 2SD551, 2SD732
25900	2SD741	40V, 5A, 15W, 200MHz	MJE 200, 2SC2270, 2SC2594
25901	2SD743(A)	100V, 4A, 40W, 17MHz	BD 243C, BD 539C, BD 953, 2SD726
25902	2SD745	140/140V, 10A, 120W, 15MHz	2SC2564...2565, 2SC2838, 2SD845
25903	2SD745A	2SD745, 150/150V	2SC2526, 2SC2565, 2SC2838, 2SD845
25904	2SD745B	2SD745, 160/160V	2SC2526, 2SC2565, 2SC2766(A), 2SC2921
25905	2SD747	50V, 0,5A, <1µs	BSW 61...64, BSX 33, 2N2221...2222(A)
25906	2SD748	250/200V, 3A, 80W	TIP 51...54, 2SC1463, 2SD632, 2SD1018
25907	2SD748A	2SD748, 250/250V	TIP 51...54, 2SC1463, 2SD632, 2SD1018
25908	2SD749	750/300V, 3A, 50W	BUW 11(A), BUX 46(A), 2SC3088, 2SC3448
25909	2SD75(H)	25V, 0,1A, 0,15W	AC 127, AC 176, AC 187, 2SD30
25910	2SD750	110/80V, 15A, 100W, 1MHz	BD 317, BD 745C, 2N3055, 2N5629...31
25911	2SD751	200/140V, 9A, 100W, 7MHz	BD 245F, 2SC3263, 2SC3855
25912	2SD752	160/160V, 15A, 150W	BDW 12, MJ 15015, 2N3773, 2SC2607...08
25913	2SD753	2SD752, 200/200V	BDW 16, MJ 15015, 2SC1585, 2SC2607...08
25914	2SD754	25V, 0,7A, 0,625W, 280MHz	BC 337...338, BC 635, BC 637, 2SD1225
25915	2SD755	100V, 0,05A, 0,75W, 350MHz	2SC2632, 2SC3245(A), 2SC3248, 2SD3800
25916	2SD756	2SD755, 120V	2SC2632, 2SC3245(A), 2SC3248, 2SC3800
25917	2SD756A	2SD755, 140V	2SC2375,2SC2631...32,2SC3248,2SC3245A
25918	2SD757	160/160V, 0,05A, 140MHz	2SC3514, BF415, BF417, BF469, BF471
25919	2SD758	2SD757, 200/200V	2SC1819, BF415, BF417, BF469, BF471

25920	2SD759	160/160V, 2A, 25W, 100MHz	2SC2529, 2SC2660
25921	2SD75A(AH)	2SD75, 45V	-
25922	2SD760	2SD759, 200/200V	2SC2660, 2SD772A...B
25923	2SD761	180/180V, 1,5A, 20W	BD 239E, 2SD608A, 2SD610, 2SD1138
25924	2SD762	60V, 3A, 25W	BD 241A, BD 535, BD 935, 2SC3179
25925	2SD762A	2SD762, 80V, 4A, 30W	BD 243B, BD 537, BD 951, 2SC3179
25926	2SD763	120V, 1A, 0,9W	2SC2383, 2SC3228, 2SD667(A), 2SD1812
25927	2SD764	1500/600V, 1,5A, 50W	BU 205...206, 2SD1492, 2SC1922, 2SD818
25928	2SD765	1500/800V, 3A, 50W	BU 207...209A, BU 706, 2SC3023...24
25929	2SD766	300V, 0,7A, 30W, 45MHz	BUW 40(A,B), TIP 47...50, 2SC782
25930	2SD767	60V, 0,1A, 0,25W, 150MHz	BC 174, BC 182, BC 190, BC 546, 2SC2240
25931	2SD768(K)	120V, 6A, 40W, B>1000	BD 651, BDW 63D, BDW73D, BDT 21
25932	2SD769	20V, 0,5A, 0,4W	BC 337...338, BC 635, BC 637, 2SC3377
25933	2SD77(H)	25V, 0,1A, 0,15W	AC 127, AC 176, AC 187, 2SD30
25934	2SD770	2SD769, 50V	BC 337, BC 635, BC 637, 2SD1226
25935	2SD771	25V, 0,05A, 0,15W	BC 168, BC 183, BC 238, BC 548, 2SD767
25936	2SD772	150/80V, 5A, 40W, 40MHz	MJE 15030, 2SC4328
25937	2SD772A	2SD772, 200/80V	2SC2767
25938	2SD772B	2SD772, 250/80V	2SC2767
25939	2SD773	20V, 2A, 1W, 110MHz	2SC3225, 2SC4484, 2SD1246...47
25940	2SD774	100V, 1A, 1W, 95MHz	2SD1616A, 2SD1665, 2SD1768, 2SD1857
25941	2SD776	200V, 5A, 100W, B>500	2SD1090
25942	2SD777	55V, 4A, 100W, B>500	-
25943	2SD778	30V, 0,1A, 0,4W	BC 168, BC 183, BC 238, BC 548, 2SD767
25944	2SD779	2SD778, 60V	BC 174, BC 182, BC 190, BC 546, 2SD767
25945	2SD77A(AH)	2SD77, 45V	-
25946	2SD78(A)(M)	100/60(A100/80)V, 2A, 1W	BCX 40, BSS 15, 2N5320, BD 529
25947	2SD780	60V, 0,3A, 140MHz	BCW 65...66, 2SD1782
25948	2SD780A	2SD780, 80V	BCW 66, 2SD1782
25949	2SD781	150/60V, 2A	2SD975
25950	2SD782	300/80V, 5A, 30W	BU 406...408, 2SD884...885, 2SD1150
25951	2SD783	1500/600V, 4A, 50W	BU 208A, BU 706, 2SC2928, 2SD1495
25952	2SD784	2SD783, 1700/700V, 5A	BU 209(A), 2SC3026, 2SD1434
25953	2SD785	2SD783, 1900/700V, 5A	2SC2125
25954	2SD786(S)	50V, 0,3A, 0,25W, 100MHz	BC 414, BC 550, 2SC2390, 2SC2674...75
25955	2SD786(S)	50V, 0,3A, 0,25W, 100MHz	BC 414, BC 550, 2SC2390, 2SC2674...75
25956	2SD787	20/16V, 2A, 0,9W, 100MHz	2SD1100, 2SD1014, 2SD1146, 2SD1207
25957	2SD788	2SD787, 20/20V	2SD1100, 2SD1014, 2SD1146, 2SD1207
25958	2SD789	100/50V, 1A, 0,9W, 100MHz	2SC2383, 2SC3228, 2SD667(A), 2SD1812
25959	2SD79	2SD78	BD 237, BD 239C, BD 529, BD 817
25960	2SD790	2SD789, 100/70V	2SC2383, 2SC3228, 2SD667(A), 2SD1812
25961	2SD792	1500/700V, 5A, 35W(Tc=90°)	BU 208A, BU 706, 2SC2928, 2SD954
25962	2SD793	40V, 3A, 10W, 65MHz	BD 785, MJE 240...244, 2SD1348
25963	2SD794(A)	70V, 3A, 10W, 60MHz	BD 787, BD 789, MJE 240...244
25964	2SD795(A)	50V, 3A, 20W, 95MHz	2SC3252

25965	2SD796	<1,4/21µs	BU 922, BUW 81(A), 2SD707, 2SD685
25966	2SD797	1,5/7µs	BDW 30, BDY 29, MJ 802
25967	2SD798	600/300V, 6A, 30W, B>1500	BU 810, 2SC3579
25968	2SD799	600/400V, 6A, 30W, B>600	BU 810, 2SC3579
25969	2SD80	30V, 6A, 50W, 1320/4500ns	BD 245, BDV 91, BDX 91, 2N5873...74
25970	2SD800	750V, 4A, 30W, 8MHz	BUS 11(A), BUW 11(A), BUX 82...83
25971	2SD801	800/375V, 6A, 50W	BU 326(A), BU 426(A), BU 526, 2SD1093
25972	2SD802	2SD801, 900/400V	BU 326A, BU 426A, BU 526, 2SD1093
25973	2SD803	120V, 8A, 100W, B>2000	BDV 65C, BDX 63C, 2SD922, 2SD1210
25974	2SD804	60V, 3A, 25W	BD 241A, BD 535, BD 935, 2SC3179
25975	2SD805	600/600V, 30A, 200W, B>100	-
25976	2SD806	2SD805, 50A, 400W	-
25977	2SD807	1500/800V, 5A, 50W	BU 208A, BU 706, 2SC2928, 2SD954
25978	2SD808	25V, 0,5A, 0,4W, 250MHz	BC 337...338, BC 635, BC 637, 2SD1578
25979	2SD809(1)	100V, 1A, 10W, 85MHz	BD 139, BD 230, BD 379, 2SD1177...78
25980	2SD81	2SD80, 60/40V	BD 245A, BDV 91, BDX 91, 2N5873...74
25981	2SD810	20/20/20V, 4A, 30W, B400	-
25982	2SD811	900/400V, 6A, 50W, 5MHz	BU 526, BU 536, BUW 12A, BUX 47A
25983	2SD812	80V, 5A, 40W, 15MHz	BD 243B, BD 539B, BD 951, 2SD613
25984	2SD813	25V, 0,5A, 150MHz	2SC3265, BC 817...818, BCX 19...20
25985	2SD814	150/150V, 0,05A, 150MHz	-
25986	2SD814A	2SD814, 185/185V	-
25987	2SD815	<3/11µs	-
25988	2SD816	300V, 4A, 30W, B1500, <2/20µs	2SD1073
25989	2SD817	1500/600V, 1,5A, 50W	BU 205, 2SD1492, 2SC1922, 2SC3023...24
25990	2SD818	1500/600V, 2,5A, 50W	BU 205, BU 705, 2SC1922, 2SD849...850
25991	2SD819	2SD818, 3,5A	BU 208A, BU 706, 2SC3023...24, 2SD1495
25992	2SD82	2SD80, 100/60V	BD 245C, BDV 93, BDX 93, 2N5632...33
25993	2SD820	2SD818, 5A	BU 208A, BU 706, 2SC2928, 2SD954
25994	2SD821	2SD818, 6A	BU 2508A, 2SC3025...26, 2SC3685, 2SD649
25995	2SD822	2SD818, 7A	BU 2508A, 2SC3027...28, 2SD1016, 2SC3686
25996	2SD823	200/90V, 6A, 40W	BU 406...409, 2SD884...885, 2SD1150
25997	2SD824(A)	120V, 6A, 60W, 10MHz	2SC2525...26, 2SC2564...65, 2SD745(A,B)
25998	2SD825(A)	120V, 7A, 80W, 10MHz	2SC2525...26, 2SC2564...65, 2SD745(A,B)
25999	2SD826	60V, 5A, 10W, 120MHz	BDX 35...37
26000	2SD827	500/500V, 4A, 50W, B>500	2SD932
26001	2SD828	2SD827, B2000	2SD932
26002	2SD829(K)	150/120V, 15A, 100W, B4000	2SD852
26003	2SD83	2SD80, 150/75V	BD245D, BDX11, 2N3442, 2SD551, 2SD732
26004	2SD830	150/100V, 5A, 30W, B>2000	BDX 53F, 2SD1128, 2SD1169, 2SD1500
26005	2SD831	500/400V, 20A, 150W, B500	BUT 13, MJ 10001, MJ 10005, MJ 10008...09
26006	2SD832	600/400V, 50A, 400W, B200	-
26007	2SD833	60V, 7A, 40W, B>4000	2SD2024
26008	2SD834	250/200V, 4A, 25W, B>1500	2SD816, 2SD1073
26009	2SD835	400/400V, 6A, 40W, B>400	BU 910...912, 2SD1114, 2SD1245



26010	2SD836	60V, 2A, 35W, B>1000	BD 715, BDT 61, BDW 53A, BDW 63A
26011	2SD836A	2SD836, 80V	BD 717, BDT 61A, BDW 53B, BDW 63B
26012	2SD836B	2SD836, 100V	BDT 61B, BDW 53C, BDW 63C
26013	2SD837	60V, 4A, 40W, B>1000	BD 645, BD 897, BDW 23A, BDW 63A
26014	2SD837A	2SD837, 80V	BD 647, BD 899, BDW 23B, BDW 63B
26015	2SD837B	2SD837, 100V	BD 649, BD 901, BDW 23C, BDW 63C
26016	2SD838	2500/900V, 3A, 50W	2SD621
26017	2SD839	35V, 4A, 30W, B>1000	BD 713, BDW 23, BDW 53, BDW 63
26018	2SD84	2SD80, 200/85V	BD 245F, BD 550A,B, 2SC2262, 2SD751
26019	2SD840	70V, 5A, 40W, B>1000	BD 647, BD 899, BDW 23B, BDW 63B
26020	2SD841	800/400V, 3A, 40W, 4MHz	BUT 11(A), BUV 46(A), 2SC3047, 2SC3086
26021	2SD842	80V, 30A, 150W, B4000	BDX 69A...C, MJ 11014, 2SD1460
26022	2SD843	100V, 7A, 40W, 10MHz	2SD866
26023	2SD844	50V, 7A, 60W, 15MHz	2SD1063
26024	2SD845	150V, 12A, 120W, 20MHz	2SC2526, 2SC2766(A), 2SC2838, 2SC2921
26025	2SD846	200V, 15A, 150W, 20MHz	2SC2773...2774, 2SC3264, 2SC3370
26026	2SD847	40V, 15A, 80W	BD 249, BD 545, BD 745, 2SC3256, 2SD1065
26027	2SD848	120V, 7A, 80W	2SC2276, 2SD588
26028	2SD848A	2SD848, 130V	2SC2276, 2SD588
26029	2SD849	1500/600V, 3A, 70W	BU 208A, BU 706, 2SD850, 2SD1495
26030	2SD850	1500/700V, 3A, 65W	BU 208A, BU 706, 2SD849, 2SD1495
26031	2SD851	150V, 10A, 80W, B3000, 1/7µs	2SD829, 2SD2401
26032	2SD852	150V, 15A, 100W, B3000	2SD829
26033	2SD854	<100/500ns	-
26034	2SD855	60V, 1A, 30W, -/1µs	BD 239A, BD 241A, 2SC1398, 2SC3252
26035	2SD855A	2SD855, 80V	BD 239B, BD 241B, 2SC2275(A), 2SC3252
26036	2SD855B	2SD855, 100V	BD 239C, BD 241C, 2SC2275(A), 2SC2528
26037	2SD856	60V, 3A, 35W, -/3µs	BD 241A, BD 535, BD 935, 2SC3179
26038	2SD856A	2SD856, 80V	BD 241B, BD 537, BD 937, 2SC3179
26039	2SD856B	2SD856, 100V	BD 241C, BD 539C, BD 937, 2SD613
26040	2SD857	60V, 4A, 40W, -/1,4µs	BD 243A, BD 535, BD 949, 2SC3179
26041	2SD857A	2SD857, 80V	BD 243B, BD 537, BD 951, 2SC3179
26042	2SD857B	2SD857, 100V	BD 243C, BD 539C, BD 953, 2SD613
26043	2SD858	60V, 5A, 60W, -/1,4µs	BD 245A, BDV 91, 2SD895, 2SD718
26044	2SD858A	2SD858, 80V	BD 245B, BDV 93, 2SD895, 2SD718
26045	2SD858B	2SD858, 100V	BD 245C, BDV 95, 2SD895, 2SD718
26046	2SD859	350/250V, 0,75A, 35W, -/2µs	BUW 40(A,B), TIP 47...50, 2SD1263
26047	2SD859A	2SD859, 400/300V	BUW 40(A,B), TIP 48...50, 2SD1263A
26048	2SD859B	2SD859, 450/350V	BUW 40(A,B), TIP 49...50
26049	2SD860	350/250V, 1A, 40W, -/2µs	BUW 40(A,B), TIP 47...50, 2SC3968
26050	2SD860A	2SD860, 400/300V	BUW 40(A,B), TIP 48...50, 2SC3968
26051	2SD860B	2SD860, 450/350V	BUW 40(A,B), TIP 49...50, 2SC3169
26052	2SD861	350/250V, 1,5A, 45W	BUW 40(A,B), TIP 47...50, 2SC3968
26053	2SD861A	2SD861, 400/300V	BUW 40(A,B), TIP 48...50, 2SC3968
26054	2SD861B	2SD861, 450/350V	BUW 40(A,B), TIP 49...50, 2SC3169



26055	2SD862	20V, 2A, 10W	BD 175, BD 233, BD 329, BD 375, 2SD1380
26056	2SD863	60V, 1A, 0,9W, 150MHz	2SD1014, 2SD1146, 2SD1207, 2SD1292
26057	2SD864(K)	120V, 3A, 30W, B>1000	BDT 61C, BDW 53D, BDW 63D, 2SD1147
26058	2SD865	B1500,<2/20µs	2SD816, 2SD977, 2SD1073
26059	2SD866	130V, 7A, 40W, 30MHz	2SC4329
26060	2SD866A	2SD866, 150V	2SC4329
26061	2SD867	1,5/5,7µs	BD 245D, 2N3442, 2N4348, 2SD551
26062	2SD868	1500/600V, 2,5A, 50W	BU 208D, BU 705D, 2SD1301, 2SD1171...75
26063	2SD869	2SD868, 3,5A	BU 208D, BU 706D, 2SD1171...1175
26064	2SD870	2SD868, 5A	BU 208D, BU 706D, 2SD1171...1175
26065	2SD871	2SD868, 6A	BU 508D, BU 2508D, 2SC3581, 2SD1731
26066	2SD872	500/400V, 5A, 40W, -/3µs	MJE 13070, 2SC2535, 2SC2827, 2SC3830
26067	2SD873	2N3773	2N3773
26068	2SD874	30V, 1A, 200MHz	BC 868, BCX 68, 2SC2883, 2SC2982
26069	2SD874A	2SD874, 60V	BCX 55...56, 2SC3444, 2SD1005, 2SD1418
26070	2SD875	80V, 0,5A, 120MHz	2SC3438, 2SD968(A), 2SD1006...1007
26071	2SD876	200/150V, 1A, 40W, B>500	2SC2317
26072	2SD877	110V, 3A, 25W, 3MHz, 1,5/7µs	BD 241C, BD 939, BDW 25, BDX 25
26073	2SD878	2N3055	2N3055
26074	2SD879	30V, 3A, 0,75W, 200MHz	2SC4781, 2SD1347, 2SD1617
26075	2SD88	300/55V, 5A, 80W	BU 104, BU 606...608, BUX 18(A...C)
26076	2SD88-1	2SD88, 100/60V	BD 245C, BDX 95, 2N5758...60, 2SD895
26077	2SD88-2	2SD88, 150/80V	BD 245D, BDX 11, 2N3442, 2SD1046
26078	2SD88-3	2SD88, 200/100V	BD 245F, DD 550A, 2SC2262, 2SD751
26079	2SD880	60V, 3A, 30W, 3MHz	BD 241A, BD 537, BD 937, 2SD712
26080	2SD882	40V, 3A, 10W, 90MHz	BD 785, MJE 240...244, 2SD794(A)
26081	2SD883	100V, 6A, 70W	2SC2276, 2SD587...588, 2SD848(A)
26082	2SD883A	2SD883, 120V	2SC2276, 2SD587...588, 2SD848(A)
26083	2SD884	330/200V, 7A, 40W, -/<3µs	BU 406...408, 2SC3173, 2SC3590...91
26084	2SD885	2SD884, 330/330V	BU 406...408, 2SC3173, 2SC3590...91
26085	2SD886	80/60V, 3A, 40W, B>500	2SD887...888, 2SD1157, 2SD1943, 2SC1983
26086	2SD886A	2SD886, 100/80V	2SC2316, 2SC2491
26087	2SD887	80V, 4A, 40W, B>500	2SC2315...16, 2SC2491, 2SD1157
26088	2SD888	80V, 6A, 50W, B>500	2SC2315...16, 2SC2491, 2SD1158
26089	2SD889	30V, 0,1A, 150MHz	2SC3114, 2SC3135, 2SD1206, 2SD1807
26090	2SD88A	2SD88, 10A, 120W	BU 109, BUX 17A...C, BUY 18, BUX 43
26091	2SD88A1	2SD88, 100/60V, 10A, 120W	BD 545C, BDW 21C, 2N5632...34, 2SD1187
26092	2SD88A2	2SD88, 150/80V, 10A, 120W	BDX 11, 2N3442, 2SC2837, 2SD1047
26093	2SD88A3	2SD88, 200/100V, 10A, 120W	BDW 16, MJ 15015, 2SD753, 2SC3855
26094	2SD890	100V, 0,02A, 0,25W, 150MHz	2SC3071, 2SC3495, 2SD1011
26095	2SD891	30V, 0,2A, 0,25W, B>2000	BC 517, BC 617, BC 875, MPSA 13...14
26096	2SD891A	2SD891, 60V	BC 875, BSR 50...52, MPSA 27...29
26097	2SD892	B>2000	BC617, BC875, BSR50...52, MPSA 27...29
26098	2SD892A	2SD892, 60V	BC 875, BSR 50...52, MPSA 27...29
26099	2SD893	B>2000	BC617, BC875, BSR50...52, MPSA 27...29

26100	2SD893A	2SD893, 60V	BC 875, BSR 50...52, MPSA 27...29
26101	2SD894	30V, 1,5A, 10W, 120MHz	2SC4341, 2SD985...986, 2SD1379, 2SD1438
26102	2SD895	100V, 6A, 60W, 15MHz	BD 245C, BDV 95, 2SC2681, 2SD718
26103	2SD896	120V, 7A, 70W, 15MHz	BD 245C, 2SC2681, 2SC2837, 2SD718
26104	2SD897(A)	1500V, 1,5A, 50W	BU 208D, BU 705D, 2SD1171...75, 2SD1301
26105	2SD898(A,B)	2SD897, 3..3,5A	BU 208D, BU 706D, 2SD1171...75, 2SD1729
26106	2SD899(A)	2SD897, 4..5A	BU 208D, BU 706D, 2SD1171...75, 2SD1729
26107	2SD90	30V, 3A, 20W, -/3,8μs	BD 241, BD 533, BD 933, 2SD877
26108	2SD900(A,B)	2SD897, 5..6A	BU 208D, BU 508D, 2SD1171...75, 2SD1731
26109	2SD901	200V, 2A, 25W	BD 239F, 2SC2660, 2SD760, 2SD1138
26110	2SD902	350V, 4A, 80W	BUX 16B, 2SC2624, 2SC3083
26111	2SD903	1500/600V, 7A, 50W	BU 508D, 2SD994, 2SC3682, 2SD1732
26112	2SD904	1500/600V, 7A, 50W	BU 508D, 2SD994, 2SC3682, 2SD1732
26113	2SD905	1400/650V, 8A, 50W	BU 508(A), 2SC3027, 2SC4801, 2SD1279
26114	2SD906	1400/650V, 8A, 50W	BU 508(A), 2SC3027, 2SC4801, 2SD1279
26115	2SD907	80V, 10A, 80W, <1/3μs	BD 245B, BD 545B, BDV 93, 2SC3256
26116	2SD908	2SD907, 120V	BD 245C, BD 545D, 2SC2681, 2SD1047
26117	2SD909	80V, 15A, 80W	BD 249B, BD 545B, BD 745B
26118	2SD91	2SD90, 60/40V	BD 241A, BD 535, BD 935, 2SD877
26119	2SD910	2SD909, 120V	BD 249C, BD 545D, BD 745D
26120	2SD911	80V, 15A, 100W	BD 249B, BD 317, BD 545B, BD 745B
26121	2SD912	2SD911, 120V	BD 249C, BD 545D, BD 745D, 2N5630...31
26122	2SD913	200/80V, 25A, 150W, <1/2,9μs	BDW 36, BUV 11...12, BUX 11...12
26123	2SD914	2SD913, 200/120V	BDW 36, BUV 11...12, BUX 11...12
26124	2SD915	600/600V, 30A, 200W, B300	-
26125	2SD916	60V, 7A, 30W, B>800	BD 645, BD 897, BDW 73A, BDX 53A
26126	2SD917	330/200V, 7A, 70W	BU 426A, BU 926
26127	2SD918	250V, 2A, 80W	-
26128	2SD919	30V, 0,5A, 0,4W, 200MHz	BC 337...338, BC 635, BC 637, 2SC3377
26129	2SD92	2SD90, 100/55V	BD 241C, BD 937, 2SD712, 2SD877
26130	2SD920	200/180V, 5A, 100W, B>700	2SD929, 2SD931, 2SD1090, 2SD1122...23
26131	2SD921	2SD920, 80W	2SD1090, 2SD1122...23
26132	2SD922	150V, 10A, 100W, B>700	2SD1123, 2SD1210
26133	2SD923	2SD922, 80W	2SD1123, 2SD1210
26134	2SD926	50V, 4A, 30W	BD 243, BD 535, BD 949, 2SC3179
26135	2SD927	2SD926, 60V	BD 243A, BD 535, BD 949, 2SC3179
26136	2SD928	2SD926, 80V	BD 243B, BD 537, BD 951, 2SC3179
26137	2SD929	200/180V, 5A, 80W, B>700	2SD776, 2SD920...921, 2SD931, 2SD1123
26138	2SD93	2SD90, 150/150V	BD 241D, 2SD772(A,B)
26139	2SD930	200/180V, 5A, 30W, B5000	2SD1023, 2SD1025
26140	2SD931	200/180V, 5A, 50W, B>700	2SD776, 2SD920...921, 2SD929, 2SD1123
26141	2SD932	500/300V, 6A, 80W, B1500	-
26142	2SD933(H)	300/300V, 6A, 80W, B1500	2SD650, 2SD706, 2SD1043, 2SD1461
26143	2SD934(K)	300/300V, 6A, 80W, B1500	2SD932
26144	2SD935	250V, 5A, 60W	TIP 55A...58A, 2SC2305, 2SC2624, 2SD1150

26145	2SD936	300/250V, 30A, 400W, B>150	-
26146	2SD937	2SD936, 400/350V	-
26147	2SD938	2SD936, 600/450V	-
26148	2SD939	300/250V, 40A, 400W, B>150	-
26149	2SD94	2SD90, 200/80V	BD 241F, 2SD772A,B
26150	2SD940	2SD939, 400/350V	-
26151	2SD941	2SD939, 600/450V	-
26152	2SD942	300/250V, 50A, 400W, B>150	-
26153	2SD943	2SD942, 400/350V	-
26154	2SD944	40V, 2A, 5W, 150MHz, B>4000	2SD1379, 2SD1438
26155	2SD946	30V, 1A, 150MHz, B>4000	BD 477A,B, BD 875, BDX 42, 2SD1379
26156	2SD946A	2SD946, 60V	BD 875, BDX 42...44, 2SC4340, 2SD1376
26157	2SD946B	2SD946, 100V	BD 879, BDX 44, 2SD1376, 2SD1953
26158	2SD947(F)	40V, 2A, 5W, 150MHz, B>4000	2SD1509, 2SD1379, 2SD1438
26159	2SD948	1600V, 1A, 25W	BU 505, 2SD470, 2SD1575
26160	2SD949	1500V, 2A, 40W	BU 205...206, BU 705, 2SC1922, 2SD818
26161	2SD950	1500V, 3A, 42W	BU 208D, 2SC3480, 2SD993, 2SD1171...75
26162	2SD951	1500V, 3A, 65W	BU 208D, 2SC3480, 2SD993, 2SD1171...75
26163	2SD952	1500V, 3A, 70W	BU 706D, 2SC3480, 2SD1173...75, 2SD1729
26164	2SD953	1500V, 5A, 95W	BU 2508D, 2SD1174...75, 2SD1730...31
26165	2SD954	1500V, 5A, 95W	BU 508A, BU 2508A
26166	2SD955	120V, 0,05A, 0,625W	2SC1890A, 2SC2240, 2SC2363, 2SC3245(A)
26167	2SD956	1500V, 2,5A, 50W	BU 208D, 2SC3479, 2SD993, 2SD1171...75
26168	2SD957	1500V, 6A, 50W	2SD903...904, 2SD994
26169	2SD957A	2SD957, 7A	2SD903...904, 2SD994
26170	2SD958	120V, 0,02A, 0,4W, 200MHz	2SC1775A, 2SC2240, 2SC2389, 2SC2459
26171	2SD959	130V, 3A, 30W, 30MHz	2SD1528
26172	2SD96	25V, 0,25A, 0,3W	AC 127, AC 176, AC 187, 2SD30, 2SD72
26173	2SD960	2SD959, 4A, 35W	2SD866
26174	2SD961	2SD959, 5A, 40W	2SD866
26175	2SD962	200V, 5A, 80W, B3000	2SD776, 2SD920...921, 2SD929, 2SD931
26176	2SD963	2SD962, 100W	2SD776, 2SD920...921, 2SD929, 2SD931
26177	2SD965	40V, 5A, 0,75W, 150MHz	2SC3671, 2SD1145, 2SD1244, 2SD2249
26178	2SD966	2SD965, 1W	2SD1934, 2SD1961
26179	2SD967	30V, 0,2A, 0,4W, B7000	BC 517, BC 617, BC 875, MPSA 13...13
26180	2SD968	100V, 0,5A, 120MHz	BCX 56, 2SC2881, 2SC3438, 2SD1005...1007
26181	2SD968A	2SD968, 120V	2SC2881, 2SC4373, 2SD1007, 2SD1418...19
26182	2SD969	25V, 0,5A, 0,6W, 150MHz	2SD1012, 2SD1302, 2SD1207, 2SD1246...47
26183	2SD970(K)	120V, 8A, 40W, B>1000	BD 651, BDT 21, BDW 73D, BDX 53D
26184	2SD971	300/300V, 6A, 50W, B2000	BU 910...912, 2SD1088...1089, 2SD1307
26185	2SD972	50V, 4A, 30W, B3000	BD 715, BDW 23A, BDW 53A, BDW 63A
26186	2SD973	30V, 1A, 1W, 200MHz	BC 337...338, BC 635, BC 637, 2SD1225
26187	2SD973A	2SD973, 60V	BC 337A, BC 635, BC 637, 2SD1616
26188	2SD974	120V, 1A, 0,9W	2SC2383, 2SC3228, 2SD667(A), 2SD1812
26189	2SD975	150/60V, 2A	2SD781

26190	2SD976	300/120V, 7A, 50W	BU 406...408, 2SD884...885, 2SD1163
26191	2SD976A	2SD976, 350/150V	BU 406, BU 408, 2SC3175, 2SC3591
26192	2SD977	<1/25 $\mu$ s	BU 911...912, 2SD987, 2SD1072, 2SD1245
26193	2SD978	2SD977, 5A, B>400	BU 911...912, 2SD987, 2SD1072, 2SD1245
26194	2SD979	450/350V, 10A, 100W, B900	BU 921...922, BUW 81(A), 2SD685
26195	2SD980	2SD979, 7A	BU 921...922, BUW 81(A), 2SD707
26196	2SD981	200/180V, 5A, 100W, B3000	2SD776, 2SD920...921, 2SD929, 2SD931
26197	2SD982	2SD981, 40W	2SD930, 2SD1023, 2SD1025, 2SD1756
26198	2SD983	2SD981, 150/100V, 40W	BDX 53F, 2SD830, 2SD1128, 2SD1169
26199	2SD985	150/60V, +-1,5A, 10W, B>2000	2SD2019
26200	2SD986	2SD985, 150/80V	2SD2019
26201	2SD987	500/400V, +-5A, 40W, B>200	BU 912, 2SD798...799, 2SD1245
26202	2SD990(K)	100V, 3A, 30W, B>500	BDW 23C, BDW 53C, BDW 63C, 2SD837B
26203	2SD991(K)	300/300V, 6A, 50W, B>500	2SD971, 2SD1071, 2SD1088...89, 2SD1113
26204	2SD992(Z)	30V, 2A, 10W	2SC3076, 2SD1801...02
26205	2SD993	1500/600V, 3A, 50W	BU 208D, 2SC3480, 2SD1171...75, 2SD1729
26206	2SD994	1500/600V, 8A, 50W	BU 508D, BU 2508D, 2SC3683
26207	2SD995	2500/900V, 3A, 50W	-
26208	2SD997	250/200V, 10A, 200W, 15MHz	BUX 17(A...C), 2SC1586, 2SD555, 2SD583
26209	2SD998	100V, 1,5A, 10W, B7000	BD 681, 2SD1376, 2SD1953
26210	2SD999	30V, 1A, 130MHz	BC 868, BCX 54, BCX 68, 2SC2883
26211	2SF1168(A)	Igt/Ih<25/15mA	MCR 218..., TAG 625-..., TAG 651-...
26212	2SF1188	Igt<30mA	S 3703, TD 3F700H, TD 4F700H
26213	2SF1189	Igt<40mA	S 3702, TD 3F800R, TD 4F800R
26214	2SF1418C..G	<4,3 $\mu$ s	BTW 27S/..., T 3S..., TAG 670...671S-...
26215	2SF1420D..G	3,2A(75°),Igt/Ih<35/<30mA	BTW 27S/..., T 3S..., TAG 670...671S-...
26216	2SH11	35V, 50mA, Ip<12 $\mu$ A, Iv>7mA	-
26217	2SH11	600V, 10A	-
26218	2SH12	2SH11	-
26219	2SH12	600V, 15A	-
26220	2SH13	55V, 50mA, Ip<6 $\mu$ A, Iv>11mA	-
26221	2SH13	600V, 20A	-
26222	2SH14	2SH13, Ip<8 $\mu$ A, Iv>8mA	-
26223	2SH14	600V, 30A	-
26224	2SH15	30V, 50mA, Ip<12 $\mu$ A, Iv>7mA	-
26225	2SH15	600V, 50A	-
26226	2SH16	600V, 75A	-
26227	2SH16(A)	30V, 50mA, Ip<12 $\mu$ A, Iv>4mA	2N2646P
26228	2SH17	2SH16, Ip<4 $\mu$ A, Iv>2mA	-
26229	2SH17	600V, 12A	-
26230	2SH18	2SH16, 0,3W	-
26231	2SH18	600V, 18A	-
26232	2SH19	2SH17, 0,3W	-
26233	2SH19	2SH17, 0,3W	-
26234	2SH19	600V, 24A	-

26235	2SH20	55V, 50mA, Ip<3,5μA, Iv>6mA	-
26236	2SH20	600V, 36A	-
26237	2SH21	2SH20, Ip<4μA, Iv>4mA	-
26238	2SH21	600V, 50A	-
26239	2SH22	25V, 50mA, Ip<4μA, Iv>4mA	2SH21
26240	2SH22	600V, 75A	-
26241	2SH23	25V, 100mA, Ip<4μA, Iv>7mA	2SH20
26242	2SH24	2SH23, Ip<12μA	-
26243	2SH25	2SH23, 75mA, 0,3W	-
26244	2SH25	2SH23, 75mA, 0,3W	-
26245	2SJ100	2SJ99, 160V	2SJ83
26246	2SJ101	60/100ns	BUZ 172, IRF 9521, IRF 9523, 2SJ153
26247	2SJ102	2SJ101, 60V	BUZ 172, IRF 9521, IRF 9523, 2SJ153
26248	2SJ103	50V, Idss>1,2mA, Up<6V	2N5460, 2N5463, 2SJ105
26249	2SJ104	25V, Idss>2,6mA, Up<2V	2SJ107...108
26250	2SJ105	2SJ103	2N5460, 2N5463, 2SJ103
26251	2SJ106	2SJ103, SMD	-
26252	2SJ107	2SJ104	2SJ104, 2SJ108
26253	2SJ108	25V, Idss>1mA, Up<2V	2SJ104, 2SJ107
26254	2SJ11	20V, Idss0,05..0,9mA, Up<5V	2N2606, 2N5797
26255	2SJ110	25V, Idss5..30, Up<2V	2SJ72
26256	2SJ111	25V, Idss5..30, Up<2V	2SJ72
26257	2SJ112	<0,35Ohm(5A)	2SJ131, 2SJ200
26258	2SJ113	2SJ112	2SJ131, 2SJ200
26259	2SJ114	2SJ112, 200V, 8A	-
26260	2SJ115	160V, 8A, 100W, <1,4Ohm	2SJ114, 2SJ119
26261	2SJ116	<2,25Ohm,60/220ns	-
26262	2SJ118	100W,<4Ohm(4A),70/160ns	2SJ114...115
26263	2SJ119	2SJ118, 160V	2SJ114...115
26264	2SJ12	2SJ11, Idss0,09..0,9mA	2N2606, 2N5797
26265	2SJ120(L,S)	<1,5Ohm(1A),35/40ns	2SJ128, 2SJ133, 2SJ191, 2SJ194
26266	2SJ122	80/200ns	IRF 9531, IRF 9533, 2SJ136, 2SJ169
26267	2SJ123	70V, 10A, 30W, <0,4Ohm	2SJ170, 2SJ138
26268	2SJ125	50V, Idss1..12mA, Up<6V	-
26269	2SJ126	60V, 10A, 40W, <0,4Ohm(5A)	2SJ137, 2SJ147, 2SJ175, 2SJ236
26270	2SJ127	0,25Ohm,110/240ns	IRF 9640, IRF 9641
26271	2SJ128(Z)	100V, +-2A, 20W, <1Ohm(1A)	2SJ194
26272	2SJ129	Up<3V	2N5021, 2SJ74
26273	2SJ13	20V, Idss1..12mA, Up<6V	-
26274	2SJ130(L,S)	35/80ns	-
26275	2SJ131	170V, 10A, 100W	2SJ200
26276	2SJ132(Z)	30V, +-2A, 20W, <0,4Ohm(1A)	2SJ120, 2SJ191
26277	2SJ133(Z)	60V, +-2A, 20W, <0,8Ohm(1A)	2SJ191
26278	2SJ134	<0,6Ohm(3,5A)	IRF 9630...9633
26279	2SJ135	2SJ134, , +-5A, 30W	2SJ154

26280	2SJ136	<0,3Ohm(6,5A)	IRF 9541, IRF 9543, 2SJ140, 2SJ173
26281	2SJ137	2SJ136, , +-10A, 30W	2SJ147, 2SJ175
26282	2SJ138	<0,3Ohm(6,5A)	IRF 9540, IRF 9542, 2SJ127
26283	2SJ139	2SJ138, , +-10A, 35W	2SJ274
26284	2SJ140	<0,2Ohm(10A)	2SJ174, 2SJ221
26285	2SJ141	2SJ140, , +-13A, 35W	2SJ176, 2SJ293
26286	2SJ142	<0,2Ohm(10A)	2SJ222
26287	2SJ143	<0,15Ohm(10A)	2SJ176...177, 2SJ240
26288	2SJ144	50V, Idss1,2..14mA, Up<6V	-
26289	2SJ145	2SJ125	-
26290	2SJ146	50V, 0,1A, <40/60ns, <150Ohm	BSS 84, 2SJ185, 2SJ209...210
26291	2SJ147	65/160ns	2SJ141, 2SJ175...176, 2SJ265
26292	2SJ148	<2Ohm(50mA),14/100ns	BST 100
26293	2SJ15	18V, Idss1,5mA, Up<6V	2N5460, 2N5463, 2SJ103, 2SJ105
26294	2SJ151	<1,2Ohm(1,5A)	IRF 9510, IRF 9620...9623
26295	2SJ152	2SJ151, , 30W	2SJ135, 2SJ157
26296	2SJ153	<0,6Ohm(3,5A)	-
26297	2SJ154	2SJ153, , +-5A, 30W	2SJ137, 2SJ147, 2SJ175, 2SJ236, 2SJ390
26298	2SJ155	50V, 3A, 30W, <0,65Ohm(2A)	2SJ152
26299	2SJ156	50V, 5A, 30W, <0,22Ohm(3A)	2SJ135, 2SJ154
26300	2SJ157	100V, 3A, 30W, <1,6Ohm(2A)	2SJ135, 2SJ152
26301	2SJ158	100V, 5A, 30W, <0,55Ohm(3A)	2SJ135, 2SJ154
26302	2SJ159	160V, 3A, 30W, <1Ohm(2A)	2SJ306
26303	2SJ16	18V, Idss1,5mA, Up<6V	2N5460, 2N5463, 2SJ103, 2SJ105
26304	2SJ163	2SJ164, SMD	-
26305	2SJ164	Up<3,5V	2N5020
26306	2SJ165	<50Ohm(20mA)	BSS 110, 2SJ148
26307	2SJ166	2SJ165, SMD	BSS 84, 2SJ185
26308	2SJ167	2SJ148, 0,3W	BST 100
26309	2SJ168	2SJ148, SMD	2SJ209...211
26310	2SJ169	50W,<0,35Ohm(6,5A)	2SJ122...123, 2SJ172
26311	2SJ17	20V, Idss>0,11mA	-
26312	2SJ170	50W,<0,35Ohm(6,5A)	2SJ127, 2SJ138
26313	2SJ171	9,7A,40W,<0,28Ohm(5,6A)	BUZ 171, 2SJ122...123, 2SJ136, 2SJ172
26314	2SJ172	60V, 10A, 40W, <0,18Ohm(5A)	2SJ290, 2SJ302
26315	2SJ173	60V, 15A, 50W, <0,11Ohm(8A)	2SJ221, 2SJ290, 2SJ302
26316	2SJ174	75W,<0,085Ohm(10A)	2SJ221, 2SJ291
26317	2SJ175	2SJ172, , 25W	2SJ236
26318	2SJ176	2SJ173, , 30W	2SJ293, 2SJ321
26319	2SJ177	2SJ174, , 35W	2SJ294, 2SJ322
26320	2SJ178	<1Ohm(0,5A)	2SJ196
26321	2SJ178	<1Ohm(0,5A)	2SJ196
26322	2SJ179	2SJ178, SMD, +-1,5A	2SJ190, 2SJ197, 2SJ238
26323	2SJ18	170V, 5A, 63W, 16Ohm	-
26324	2SJ180	2SJ178, 1W	2SJ196



26325	2SJ181(L,S)	<25Ohm(0,3A)	-
26326	2SJ182(L,S)	60V, 3A, 20W, <0,4Ohm(2A)	2SJ235
26327	2SJ183	60V, 5A, 20W, <0,35Ohm(2,5A)	2SJ192, 2SJ245, 2SK279
26328	2SJ184	<40Ohm(1mA)	BSS 110
26329	2SJ185	2SJ184, SMD	BSS 84
26330	2SJ186	<12Ohm(0,25A),12/32ns	-
26331	2SJ187	30V, 1A, <0,75Ohm(0,5A)	2SJ190, 2SJ278
26332	2SJ188	30V, 2A, 20W, <0,3Ohm(1A)	2SJ191, 2SJ194
26333	2SJ189	30V, 4A, 30W, <0,12Ohm(2A)	2SJ192, 2SJ245, 2SJ279
26334	2SJ19	140V, 0,1A, 0,8W	-
26335	2SJ190	60V, 1A, <1,2Ohm(0,5A)	2SJ278
26336	2SJ191	60V, 2A, 20W, <0,45Ohm(1A)	2SJ235
26337	2SJ192	60V, 4A, 30W, <0,2Ohm(2A)	2SJ245, 2SJ279
26338	2SJ193	100V, 1A, <2,4Ohm(0,5A)	-
26339	2SJ194	100V, 2A, 20W, <0,95Ohm(1A)	2SJ195
26340	2SJ195	100V, 4A, 30W, <0,4Ohm(2A)	-
26341	2SJ196	<1Ohm(0,5A)	-
26342	2SJ196	<1Ohm(0,5A)	-
26343	2SJ197	2SJ196, SMD	2SJ190, 2SJ238
26344	2SJ198	<2Ohm(0,5A)	2SJ231
26345	2SJ198	<2Ohm(0,5A)	2SJ231
26346	2SJ199	2SJ198, SMD	2SJ213
26347	2SJ20	100V, 10A, 100W, 10Ohm	-
26348	2SJ200	180V, 10A, 120W	-
26349	2SJ201	200V, 12A, 150W	-
26350	2SJ202	16V, +-0,1A, <30Ohm(1mA)	-
26351	2SJ203	16V, +-0,2A, <10Ohm(1mA)	BSS 84, 2SJ185
26352	2SJ204	30V, +-0,2A, <8Ohm(10mA)	BSS 84, 2SJ185
26353	2SJ205	16V, +-0,5A, <3Ohm(0,3A)	2SJ212
26354	2SJ206	30V, +-0,5A, <3Ohm(0,3A)	2SJ212
26355	2SJ207	16V, +-1A, <1,5Ohm(0,5A)	2SJ190, 2SJ197, 2SJ238
26356	2SJ208	16V, +-2A, <1Ohm(1A)	-
26357	2SJ209	100V, +-0,1A, <60Ohm(10mA)	-
26358	2SJ21	160V, 15W, Idss30..300	-
26359	2SJ210	60V, +-0,2A, <10Ohm(10mA)	BSS 84, 2SJ185
26360	2SJ211	100V, +-0,2A, <20Ohm(10mA)	-
26361	2SJ212	60V, +-0,5A, <3Ohm(0,5A)	2SJ199, 2SJ213
26362	2SJ213	100V, +-0,5A, <4,2Ohm(0,3A)	2SJ199
26363	2SJ214(L,S)	60V, 10A, 40W, <0,18Ohm(5A)	2SJ219, 2SJ296
26364	2SJ215	60V, 35A, 125W, <0,06Ohm	2SJ217
26365	2SJ216	2SJ215, , 50W	2SJ218
26366	2SJ217	60V, 45A, 150W, <0,042Ohm	-
26367	2SJ218	2SJ217, , 60W	-
26368	2SJ219(L,S)	60V, 15A, 50W, <0,11Ohm(8A)	2SJ268, 2SJ296
26369	2SJ22	80V, Idss0,3..0,7mA	-

26370	2SJ220(L,S)	75W,<0,085Ohm(10A)	2SJ241, 2SJ297, 2SJ409
26371	2SJ221	100V, 20A, 75W	-
26372	2SJ222	2SJ221, , 35W	-
26373	2SJ223(L,S)	60V, 2A, 10W, <0,7Ohm(1A)	2SJ326
26374	2SJ224	60V, 12A, 80W, <0,2Ohm(6A)	2SJ219, 2SJ296
26375	2SJ225	30V, 1A, 1W, <0,75Ohm(0,5A)	2SJ196
26376	2SJ226	30V, 2A, 1,5W, <0,3Ohm(1A)	-
26377	2SJ227	<0,13Ohm(1,5A)	-
26378	2SJ228	60V, 0,8A, 1W, <1,2Ohm(0,4A)	2SJ353
26379	2SJ229	60V, 1,6A, <0,45Ohm(0,8W)	-
26380	2SJ230	60V, 2,5A, <0,21Ohm(1,5A)	-
26381	2SJ231	<2,4Ohm(0,25A)	-
26382	2SJ232	100V, 1,2A, <0,95Ohm(0,6A)	-
26383	2SJ233	100V, 1,8A, <0,4Ohm(1A)	-
26384	2SJ234(L,S)	30V, 2,5A, 10W,<0,4Ohm(1,4A)	2SJ191
26385	2SJ235(L,S)	integr. Rg	
26386	2SJ236	integr. Rg	
26387	2SJ237	integr. Rg	
26388	2SJ238	60V, 1A, <0,85Ohm(0,5A)	2SJ190, 2SJ193, 2SJ278
26389	2SJ239	60V, 5A, 20W, <0,25Ohm(2,5A)	2SJ183, 2SJ192, 2SJ195, 2SJ279
26390	2SJ240	<0,045Ohm(10A)	2SJ177, 2SJ294, 2SJ322, 2SJ330
26391	2SJ241	2SJ240, 100W	2SJ220, 2SJ297, 2SJ409
26392	2SJ243	30V, +-0,1A, <25Ohm(10mA)	-
26393	2SJ244	integr. Rg	
26394	2SJ245(L,S)	60V, 5A, 20W,<0,25Ohm(3A)	2SJ192, 2SJ279
26395	2SJ246(L,S)	30V, 7A, 20W,<0,17Ohm(4A)	2SJ333
26396	2SJ247	100V, 8A, 40W,<0,3Ohm(4A)	-
26397	2SJ248	2SJ247, , 25W	2SJ350
26398	2SJ249	<0,16Ohm(7A)	2SJ142, 2SJ222
26399	2SJ250	60V, 10A, 12W,<0,19Ohm(5A)	-
26400	2SJ251	30V, 10A, 50W, <0,17Ohm(5A)	2SJ172
26401	2SJ252	30V, 12A, 60W, <0,13Ohm(6A)	2SJ173, 2SJ290
26402	2SJ253	<75mOhm(10A)	2SJ174, 2SJ291
26403	2SJ254	30V, 8A, 25W, <0,12Ohm(5A)	2SJ175, 2SJ236
26404	2SJ255	30V, 10A, 25W, <95mOhm(6A)	2SJ175, 2SJ236
26405	2SJ256	<55mOhm(10A)	2SJ177, 2SJ294, 2SJ374
26406	2SJ257	30V, 10A, 50W, <0,12Ohm(5A)	2SJ214
26407	2SJ258	30V, 12A, 60W, <95mOhm(6A)	2SJ214
26408	2SJ259	<55mOhm(10A)	2SJ409
26409	2SJ260	60V, 8A, 50W, <0,27Ohm(4A)	2SJ172
26410	2SJ261	60V, 10A, 60W, <0,2Ohm(5A)	2SJ172
26411	2SJ262	60V, 18A, 70W, <0,11Ohm(9A)	2SJ174, 2SJ291
26412	2SJ263	60V, 6A, 25W, <0,2Ohm(4A)	2SJ175, 2SJ236
26413	2SJ264	60V, 8A, 25W, <0,15Ohm(5A)	2SJ175, 2SJ236
26414	2SJ265	60V, 15A, 30W, <0,11Ohm(9A)	2SJ176, 2SJ293

26415	2SJ266	60V, 8A, 50W, <0,2Ohm(4A)	2SJ214
26416	2SJ267	60V, 10A, 60W, <0,15Ohm(5A)	2SJ214
26417	2SJ268	60V, 18A, 70W, <0,08Ohm(9A)	2SJ409
26418	2SJ269	100V, 6A, 50W, <0,55Ohm(3A)	-
26419	2SJ270	100V, 8A, 60W, <0,4Ohm(4A)	2SJ247
26420	2SJ271	<0,22Ohm(8A)	2SJ221
26421	2SJ272	100V, 4A, 25W, <0,4Ohm(3A)	2SJ248
26422	2SJ273	100V, 6A, 25W, <0,3Ohm(4A)	2SJ248
26423	2SJ274	<0,16Ohm(8A)	2SJ222
26424	2SJ275	100V, 6A, 50W, <0,4Ohm(3A)	-
26425	2SJ276	100V, 8A, 50W, <0,3Ohm(4A)	-
26426	2SJ277	<0,16Ohm(8A)	2SJ409
26427	2SJ278	60V, 1A, <0,83Ohm(0,5A)	2SJ190
26428	2SJ279(L,S)	60V, 5A, 20W, <0,2Ohm(3A)	2SJ245
26429	2SJ280(L,S)	60V, 30A, 75W, <43mOhm(15A)	2SJ402
26430	2SJ281	250V, 3A, 30W, <2,6Ohm	-
26431	2SJ282	250V, 3A, 50W, <2Ohm(1,5A)	-
26432	2SJ283	120V, 5A, 25W, <1,4Ohm	2SJ350
26433	2SJ284	30V, 0,3A, <2,2Ohm(0,15A)	-
26434	2SJ285	60V, 0,25A, <3Ohm(0,15A)	2SJ210...211
26435	2SJ286	100V, 0,15A, <7Ohm(0,1A)	2SJ209, 2SJ211
26436	2SJ287	30V, 0,5A, <2,2Ohm(0,25A)	2SJ190, 2SJ278
26437	2SJ288	60V, 0,5A, <3Ohm(0,25A)	2SJ190, 2SJ278
26438	2SJ289	100V, 0,5A, <7,5Ohm	2SJ193
26439	2SJ29	140V, 10A, 100W, 15Ohm	-
26440	2SJ290	60V, 15A, 50W, <95mOhm(8A)	2SJ173, 2SJ221
26441	2SJ291	<65mOhm(10A)	2SJ174, 2SJ221
26442	2SJ292	2SJ280	-
26443	2SJ293	2SJ290, , 30W	2SJ176, 2SJ321
26444	2SJ294	2SJ291, , 35W	2SJ177, 2SJ322
26445	2SJ295	2SJ280, , 35W	2SJ323
26446	2SJ296(L,S)	2SJ290	2SJ219
26447	2SJ297(L,S)	2SJ291	2SJ220, 2SJ241, 2SJ409
26448	2SJ298	20V, 5A, 12W, <0,12Ohm(3A)	2SJ250
26449	2SJ299	2SJ298	2SJ245, 2SJ279, 2SJ318
26450	2SJ300	20V, 10A, 12W, <0,08Ohm(5A)	2SJ250
26451	2SJ302	60V, 16A, 75W, <0,1Ohm(8A)	2SJ173, 2SJ290, 2SJ328
26452	2SJ302Z	2SJ302	2SJ241, 2SJ268, 2SJ297, 2SJ384
26453	2SJ303	60V, 14A, 35W, <0,1Ohm(7A)	2SJ237, 2SJ275, 2SJ293, 2SJ329
26454	2SJ304	60V, 14A, 40W, <0,12Ohm(7A)	2SJ176, 2SJ265, 2SJ303, 2SJ329
26455	2SJ305	30V, 0,2A, <4Ohm(0,05A)	2SJ210...211
26456	2SJ306	250V, 3A, 25W, <2Ohm(1,5A)	2SJ307
26457	2SJ307	250V, 6A, 30W, <3Ohm(3A)	2SJ308
26458	2SJ308	250V, 9A, 40W, <0,48Ohm(5A)	-
26459	2SJ312	2SJ304	2SJ268

26460	2SJ313	180V, 1A, 25W	-
26461	2SJ314-01(L,S)	60V, 5A, 20W, <0,03Ohm(2,5A)	2SJ192, 2SJ245, 2SJ279, 2SJ327
26462	2SJ315	60V, 5A, 20W, <0,25Ohm(2,5A)	2SJ192, 2SJ245, 2SJ279, 2SJ327
26463	2SJ316	12V, 1A, <0,42Ohm(0,5A)	2SJ190, 2SJ278
26464	2SJ317	integr. Rg	
26465	2SJ318(L,S)	20V, 5A, 20W,<0,13Ohm(3A)	2SJ245, 2SJ279, 2SJ299
26466	2SJ319(L,S)	200V, 3A, 20W, <2,3Ohm(2A)	-
26467	2SJ320	250V, 4A, 25W, <1,3Ohm(2A)	-
26468	2SJ321	60V, 15A, 30W, <95mOhm(8A)	2SJ176, 2SJ293
26469	2SJ322	<65mOhm(10A)	2SJ177, 2SJ294
26470	2SJ323	<43mOhm(15A)	2SJ295
26471	2SJ324(Z)	<0,25Ohm(1A)	2SJ191, 2SJ326
26472	2SJ325(Z)	<0,11Ohm(2A)	2SJ245, 2SJ327, 2SJ327
26473	2SJ326(Z)	<0,37Ohm(1A)	2SJ191, 2SJ194
26474	2SJ327(Z)	<0,17Ohm(2A)	2SJ192, 2SJ195, 2SJ245, 2SJ279
26475	2SJ328	<65mOhm(10A)	2SJ174, 2SJ221
26476	2SJ328Z	2SJ328	2SJ241, 2SJ409
26477	2SJ329	<0,06Ohm(8A)	2SJ176, 2SJ265, 2SJ293
26478	2SJ330	<50mOhm(10A)	2SJ177, 2SJ294, 2SJ322
26479	2SJ331	60V, +-30A, 150W, <0,03Ohm	2SJ217
26480	2SJ332(L,S)	20V, 10A, 20W,<0,08Ohm(5A)	2SJ389
26481	2SJ333(L,S)	30V, 7A, 20W, <0,14Ohm(4A)	2SJ246
26482	2SJ334	<38mOhm(15A)	2SJ295, 2SJ323
26483	2SJ335	12V, 0,5A, <1.4Ohm	2SJ190, 2SJ278
26484	2SJ336	12V, 2A, 20W, <0,35Ohm(1A)	2SJ191
26485	2SJ337	12V, 8A, 30W, <0,09Ohm(4A)	2SJ246, 2SJ333
26486	2SJ338	180V, 1A, 20W, <5Ohm(0,6A)	2SJ130
26487	2SJ339	<55mOhm(15A)	2SJ295, 2SJ323
26488	2SJ340	<40mOhm(15A)	2SJ280
26489	2SJ341	20V, 5A, 12W,<0,12Ohm(3A)	2SJ250, 2SJ300
26490	2SJ342	50V, 0,05A, <50Ohm	-
26491	2SJ343	2SJ342, SMD	-
26492	2SJ344	2SJ342, SMD	-
26493	2SJ345	20V, 0,05A, <40Ohm	-
26494	2SJ346	2SJ345	-
26495	2SJ347	2SJ345	-
26496	2SJ348	<0,04Ohm(15A)	2SJ292
26497	2SJ349	<45mOhm(10A)	2SJ177, 2SJ294, 2SJ322, 2SJ374
26498	2SJ350	120V, 6A, 20W, <0,7Ohm(4A)	-
26499	2SJ351	180V, 8A, 100W, 320/120ns	-
26500	2SJ352	2SJ351, 200V	-
26501	2SJ353	<0,37Ohm(1A)	-
26502	2SJ355	30V, +-2A, <0,35Ohm(1A)	2SJ356
26503	2SJ356	60V, +-2A, <0,5Ohm(1A)	-
26504	2SJ357	30V, +-3A, <0,2Ohm(1,5A)	2SJ358

26505	2SJ358	60V, +-3A, <0,3Ohm(1,5A)	-
26506	2SJ359	60V, 5A, <0,25Ohm(2,5A)	-
26507	2SJ360	60V, 1A, <0,73Ohm(0,5A)	2SJ190, 2SJ238, 2SJ278, 2SJ450
26508	2SJ361	integr. Rg	
26509	2SJ362	60V, 2A, 20W, <0,4Ohm(1A)	2SJ191, 2SJ194
26510	2SJ363	integr. Rg	(2SJ355...356)
26511	2SJ365	60/160ns	2SJ191, 2SJ223
26512	2SJ366	70/270ns	2SJ192, 2SJ245, 2SJ279
26513	2SJ367	70/270ns	2SJ214
26514	2SJ368	2SJ367, 20W	2SJ248
26515	2SJ369	100/320ns	2SJ219, 2SJ296
26516	2SJ370	2SJ369, 25W	2SJ236, 2SJ293, 2SJ321
26517	2SJ371	130/460ns	2SJ219, 2SJ296
26518	2SJ372	2SJ371	2SJ237, 2SJ293, 2SJ321
26519	2SJ373	175/660ns	2SJ220, 2SJ297
26520	2SJ374	2SJ373	2SJ294, 2SJ322, 2SJ374
26521	2SJ375	270/1020ns	-
26522	2SJ376	2SJ375	2SJ295, 2SJ323
26523	2SJ377	60V, 5A, 20W, <0,19Ohm(2,5A)	2SJ192, 2SJ195, 2SJ245, 2SJ327
26524	2SJ378	2SJ377, 1,2W	-
26525	2SJ379	100V, 8A, 15W, <0,21Ohm(4A)	-
26526	2SJ380	<0,21Ohm(6A)	2SJ222
26527	2SJ381	12V, 2A, <0,4Ohm(0,5A)	2SJ355...356
26528	2SJ382	12V, 4A, 20W, <177mOhm(1A)	2SJ192, 2SJ245, 2SJ327
26529	2SJ383	12V, 8A, 30W, <82mOhm(2A)	2SJ389
26530	2SJ384(L,S)	60V, 15A, 50W, <0,1Ohm(8A)	2SJ268
26531	2SJ387(L,S)	20V, 10A, 20W, <70mOhm(5A)	2SJ388...389
26532	2SJ388(L,S)	30V, 10A, 20W, <80mOhm(5A)	2SJ389
26533	2SJ389(L,S)	<135mOhm(5A)	-
26534	2SJ390	60V, 10A, 25W, <0,12Ohm(5A)	2SJ175...176, 2SJ236
26535	2SJ399	integr. Rg	
26536	2SJ40	50V, Idss0,6..12mA, Up<6V	-
26537	2SJ400	30V, 35A, 70W, <35mOhm	2SJ280
26538	2SJ401	<45mOhm(10A)	2SJ220, 2SJ241, 2SJ297, 2SJ409
26539	2SJ402	<38mOhm(15A)	2SJ280
26540	2SJ403	200V, 5A, 25W, <1,1Ohm(2,5A)	2SJ320
26541	2SJ404	200V, 6A, 25W, <0,8Ohm(3A)	-
26542	2SJ405	200V, 8A, 30W, <0,5Ohm(4A)	-
26543	2SJ406	200V, 12A, 40W, <0,23Ohm	-
26544	2SJ407	200V, 5A, 30W, <1Ohm(2,5A)	2SJ320, 2SJ403, 2SJ410
26545	2SJ408(L,S)	100W, <0,02Ohm(25A)	-
26546	2SJ409(L,S)	75W, <0,16Ohm(10A)	-
26547	2SJ410(L,S)	200V, 6A, 30W, <0,85Ohm(3A)	2SJ307, 2SJ405
26548	2SJ411	<0,24Ohm(2,5A)	2SJ183, 2SJ192, 2SJ245, 2SK279, 2SJ327
26549	2SJ412	<0,21Ohm(6A)	-

26550	2SJ413	60V, 50A, 70W, <0,02Ohm	2SJ218
26551	2SJ416	30V, 2A, <0,44Ohm(1A)	2SJ356
26552	2SJ417	30V, 4A, 20W, <0,16Ohm	2SJ192, 2SJ245, 2SJ279
26553	2SJ418	30V, 8A, 30W, <0,08Ohm	-
26554	2SJ424	<0,5Ohm(2,5A)	2SJ135, 2SJ154, 2SJ158, 2SJ272
26555	2SJ425	<0,28Ohm(4A)	2SJ137, 2SJ147, 2SJ175, 2SJ236, 2SJ390
26556	2SJ426	<0,14Ohm(8A)	2SJ141, 2SJ143, 2SJ265, 2SJ321, 2SJ329
26557	2SJ43	50V, Idss0,5..12mA, Up<3V	2SJ129
26558	2SJ438	60V, 5A, 25W, <0,19Ohm(2,5A)	2SJ263, 2SJ272, 2SJ274
26559	2SJ439	16V, 5A, 20W, <0,2Ohm(2,5A)	2SJ183, 2SJ192, 2SJ239
26560	2SJ44	40V, Idss1..18mA, Up<1,5V	2N5021, 2SJ74
26561	2SJ440	180V, 9A, 80W	-
26562	2SJ443	60V, 10A, 25W, <0,18Ohm(5A)	2SJ175...176, 2SJ236, 2SJ390
26563	2SJ448	250V, +-4A, 30W, <2Ohm(2A)	2SJ320
26564	2SJ449	<0,8Ohm(3A)	2SJ307...308
26565	2SJ45	40V, Idss1..18mA, Up<1,5V	2N5021, 2SJ74
26566	2SJ450	60V, 1A, <1,2Ohm(0,5A)	2SJ190, 2SJ278
26567	2SJ451	integr. Rg	
26568	2SJ452	integr. Rg	
26569	2SJ453	250V, 3A, 30W, <2,6Ohm(1,5A)	2SJ281
26570	2SJ457	<15Ohm(0,3A)	-
26571	2SJ458	450V, 2A, 60W, <5,5Ohm(1A)	-
26572	2SJ459	450V, 4A, 70W, <2,8Ohm(2A)	-
26573	2SJ462	12V, +-2,5A, <0,29Ohm	2SJ356, 2SJ358
26574	2SJ463	30V, +-0,1A, <60Ohm(1mA)	-
26575	2SJ464	<0,12Ohm(9A)	-
26576	2SJ465	16V, 2A, <0,71Ohm(1A)	2SJ356
26577	2SJ467	30V, 8A, 30W, <0,1Ohm	-
26578	2SJ47	<1,7Ohm	2SJ55...56, 2SJ160...162
26579	2SJ471	<35mOhm(15A)	2SJ295, 2SJ323
26580	2SJ472-01(L,S)	30V, 5A, 15W, <0,4Ohm	2SJ183, 2SJ192, 2SK239, 2SJ245
26581	2SJ473-01(L,S)	60V, 7A, 20W, <0,2Ohm	-
26582	2SJ474-01(L,S)	60V, 7A, 20W, <0,2Ohm	2SJ266
26583	2SJ475-01	60V, 25A, 50W, <0,6Ohm	2SJ174, 2SJ221, 2SJ291, 2SJ328
26584	2SJ476-01	60V, 25A, 50W, <0,6Ohm	2SJ409
26585	2SJ477-01	60V, 25A, 40W, <0,6Ohm	2SJ174, 2SJ221, 2SJ291, 2SJ328
26586	2SJ478	<45mOhm(10A)	2SJ174, 2SJ221, 2SJ291, 2SJ328
26587	2SJ479	2SJ471, 50W	-
26588	2SJ48	2SJ47, 120V	2SJ55...56, 2SJ160...162
26589	2SJ480	12V, 0,3A, <1,4Ohm	-
26590	2SJ483	30V, 5A, 0,9W,<0,11Ohm(2,5A)	-
26591	2SJ484	30V, 2A, <0,23Ohm(1A)	2SJ356
26592	2SJ486	integr. Rg	
26593	2SJ49	2SJ47, 140V	2SJ55...56, 2SJ161...162
26594	2SJ50	2SJ47, 160V	2SJ55...56, 2SJ162



26595	2SJ51	40V, Idss6..50mA, Up<1,1V	2SJ70
26596	2SJ55	180V, 8A, 125W, <1,7Ohm	-
26597	2SJ56	2SJ55, 200V	-
26598	2SJ68	40V, Idss1,6..12mA, Up<1,5V	2SJ104, 2SJ107...108
26599	2SJ69	40V, Idss2,5..20mA, Up<1,5V	2SJ104, 2SJ107...108
26600	2SJ70	40V, Idss6..50mA, Up<1,5V	2SJ51
26601	2SJ72	25V, Idss5..30mA, Up<2V	2SJ110...111
26602	2SJ74	25V, Idss>1mA, Up<2V	2N5021
26603	2SJ76	10Ohm	-
26604	2SJ77	2SJ76, 160V	-
26605	2SJ78	2SJ76, 180V	-
26606	2SJ79	2SJ76, 200V	-
26607	2SJ81	<1,7Ohm,230/110ns	2SJ99...100
26608	2SJ82	2SJ81, 140V	2SJ99...100
26609	2SJ83	2SJ81, 160V	2SJ100
26610	2SJ84	15V, Idss0,5..12mA, Up<3V	-
26611	2SJ91	140V, 8A, 120W	2SJ114...115, 2SJ118...119, 2SJ55...56
26612	2SJ92	2SJ91, 7A, 100W	2SJ114...115, 2SJ118...119
26613	2SJ96	100/250ns	2SJ81...83, 2SJ99...100
26614	2SJ99	100/90ns	2SJ82...83
26615	2SK1000	Idss>10mA,Up<2,5V	-
26616	2SK1001	2SK1000, SMD	-
26617	2SK1002	20V, Idss0,12..0,5mA, Up<1V	-
26618	2SK1006(-01MR)	450V, 5A, 40W, <1,6Ohm(2,5A)	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
26619	2SK1007(-01)	2SK1006, 60W	BUZ 41A...42, 2SK893, 2SK1156, 2SK1246
26620	2SK1008(-01)	<2,2Ohm(2,5A)	BUZ 41A...42, 2SK893, 2SK1156, 2SK1246
26621	2SK1009(-01)	450V, 7A, 80W, <1,3Ohm(3A)	IRF 840, IRF 842, 2SK894, 2SK1495...96
26622	2SK1010(-01)	<1,6Ohm(3A)	IRF 840, IRF 842, 2SK894, 2SK1496
26623	2SK1011(-01)	450V, 10A, 100W, <0,65Ohm	BUZ 339, 2SK896, 2SK1488, 2SK1785
26624	2SK1012(-01)	2SK1011, 500V, <0,9Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1785
26625	2SK1013(-01)	<0,6Ohm(6A)	2SK899, 2SK1610, 2SK1745, 2SK1757
26626	2SK1014(-01)	<0,74Ohm(6A)	2SK899, 2SK1610, 2SK1745, 2SK1757
26627	2SK1015(-01)	125W, <0,45Ohm(8A)	2SK870, 2SK1517...18, 2SK1499...1500
26628	2SK1016(-01)	<0,55Ohm(8A)	2SK899, 2SK1745, 2SK1678, 2SK1757
26629	2SK1017(-01)	450V, 20A, 150W, <0,35Ohm	2SK870, 2SK1517...18, 2SK1409, 2SK1680
26630	2SK1018	<0,45Ohm(10A)	2SK870, 2SK1518, 2SK1498, 2SK1680
26631	2SK1019	450V, 35A, 300W, <0,2Ohm	2SK1519...20, 2SK1628...29
26632	2SK1020	<0,25Ohm(15A)	2SK1520, 2SK1629
26633	2SK1021	800V, 3A, 60W, <6Ohm(1,5A)	BUZ 81, 2SK1501, 2SK1639, 2SK1643
26634	2SK1022	<7,3Ohm(1,5A)	BUK 456-1000, 2SK791...792, 2SK1793
26635	2SK1023(-01)	800V, 4A, 60W, <4,5Ohm(2A)	BUZ 81, 2SK1501, 2SK1639, 2SK1643
26636	2SK1024(-01)	2SK1023, 900V, 3,5A	2SK1457, 2SK1501, 2SK1639, 2SK1643
26637	2SK1025	<0,08Ohm(10A)	BUK 445-50, BUZ 11F, 2SK1095, 2SK1420
26638	2SK1026	250V, 20A, 150W, <0,26Ohm	2SK901, 2SK944, 2SK1641, 2SK1673...74
26639	2SK1027	<0,29Ohm(10A)	2SK1409, 2SK1674, 2SK1680

26640	2SK1028	100V, 6A, PQ100W(230MHz)	-
26641	2SK1029	500V, +-10A, 200W, <0,5Ohm	2SK694
26642	2SK1030	800V, 3A, 50W, <5Ohm(2A)	2SK1356, 2SK1460
26643	2SK1030A	2SK1030, 900V	2SK1356, 2SK1460
26644	2SK1031	Up<5V	-
26645	2SK1032	800V, 8A, 120W, <1,7Ohm(5A)	2SK684, 2SK1342, 2SK1358, 2SK1502
26646	2SK1032A	2SK1032, 900V	2SK1342, 2SK1358, 2SK1462, 2SK1614
26647	2SK1033	60V, 12A, 45W, <0,1Ohm(6A)	2SK1093, 2SK1256, 2SK1305...06, 2SK1344
26648	2SK1034	100V, 15A, 45W, <0,18Ohm(6A)	2SK1306, 2SK1558
26649	2SK1035	150V, 12A, 45W, <0,35(6A)	-
26650	2SK1036	250V, 10A, 50W, <0,3Ohm(5A)	2SK526
26651	2SK1037	250V, 50W	-
26652	2SK1038	400V, 5A, 50W, <1,8Ohm(3A)	BUK 445-400, 2SK530, 2SK1377, 2SK1990
26653	2SK1039	400V, 8A, 50W, <1,4Ohm(5A)	2SK1566...67, 2SK1609, 2SK2116...17
26654	2SK104	30V, Idss0,5..12mA, Up<4,5V	BFS 70, 2N3821, 2N4220, 2N5359, 2SK104
26655	2SK1040	400V, 10A, 100W, <1Ohm(5A)	BUZ 326, BUZ 351, 2SK556, 2SK634
26656	2SK1043	4V, Idss12..60mA, 12G	-
26657	2SK1044	<1,7Ohm(2,5A)	2SK727, 2SK793, 2SK1461, 2SK1649...50
26658	2SK1045	2SK1044, 900V, <2Ohm(2,5A)	2SK727, 2SK794, 2SK1341, 2SK1649...50
26659	2SK1046	4V, 70mA, 12GHz	-
26660	2SK1047	250V, 20A, 150W, <0,26Ohm	2SK901, 2SK944, 2SK1673...74, 2SK1641
26661	2SK1048	<0,29Ohm(10A)	2SK868(A), 2SK1674
26662	2SK1049	<0,65Ohm(8A)	2SK899, 2SK1610, 2SK1678, 2SK1745
26663	2SK105	2SK104, 50V	-
26664	2SK1050	2SK1049, 500V, <0,78Ohm(8A)	2SK899, 2SK1610, 2SK1678, 2SK1745
26665	2SK1051	<0,03Ohm(20A)	BUZ 347...348, 2SK857, 2SK905, 2SK1124
26666	2SK1052	450V, 0,5A, 30W, <7Ohm(0,3A)	-
26667	2SK1053	450V, 1A, 40W, <4,5Ohm(0,5A)	-
26668	2SK1059(Z)	<0,135Ohm(3A)	2SK1112, 2SK1471, 2SK1719
26669	2SK106	50V, Idss0,5..12mA, Up<1,5V	2SK68, 2SK121, 2SK163, 2SK170, 2SK184
26670	2SK1060(Z)	2SK1059, 100V, <0,27Ohm(3A)	2SK1474, 2SK1804
26671	2SK1061	2SK982, 0,3W	BS 170, BST 170, 2SK422...423
26672	2SK1062	2SK982, SMD	BST 82
26673	2SK1063	2SK559, 125W	2SK788, 2SK899, 2SK1610, 2SK1678
26674	2SK1064	2SK560, 125W	2SK788, 2SK899, 2SK1610, 2SK1678
26675	2SK1065	2SK968	-
26676	2SK1066	2SK436	-
26677	2SK1067	2SK543	-
26678	2SK1068	2SK546, SMD	-
26679	2SK1069	2SK771, SMD	-
26680	2SK107	27V, Idss>2,7mA, Up<3,85V	BF 410B, 2SK192
26681	2SK1070	2SK435, SMD	-
26682	2SK1073	2SK1074, , 45W	2SK1356, 2SK1460
26683	2SK1074	<3,6Ohm(1,5A)	2SK603, 2SK726, 2SK954, 2SK1339
26684	2SK1078	2SK940, SMD	2SK1697, 2SK1727, 2SK2109

26685	2SK1079	2SK941, SMD	2SK1079, 2SK1485, 2SK1728
26686	2SK108	50V, Idss1..12mA, Up<3V	BF 410B, BFW 12, 2N4340, 2N5484
26687	2SK1081(-01)	800V, 7A, 125W, <2,2Ohm(3A)	BUK 638-800, 2SK684, 2SK1032, 2SK1502
26688	2SK1082(-01)	2SK1081, 6A, <2,8Ohm(3A)	BUK 638-800, 2SK684, 2SK1032, 2SK1502
26689	2SK1083(-MR)	60V, 8A, 20W, <0,22Ohm(4A)	
26690	2SK1084	100V, 5A, 20W, <0,5Ohm(2,5A)	BUK 542-100, 2SK1260, 2SK1265
26691	2SK1085(-MR)	150V, 3A, 20W, <0,9Ohm(1,5A)	2SK1264...1265
26692	2SK1086(-MR)	<0,07Ohm(10A)	2SK943, 2SK1214, 2SK1345, 2SK1951
26693	2SK1087(-MR)	<0,17Ohm(6A)	
26694	2SK1088(-MR)	<0,13Ohm(4,5A)	
26695	2SK1089	60V, 35A, 80W, <0,035Ohm	2SK1297, 2SK1514, 2SK1665
26696	2SK1090	<0,08Ohm(10A)	2SK1267
26697	2SK1091	150V, 15A, 80W, <0,15Ohm	2SK1267
26698	2SK1092	2SK666, SMD	-
26699	2SK1093	2SK970, , 20W	2SK1033, 2SK1256, 2SK1305...06, 2SK1344
26700	2SK1094	2SK971, , 25W	2SK1034, 2SK1306, 2SK1345, 2SK1558
26701	2SK1095	2SK972, , 30W	2SK943, 2SK1345...46, 2SK1348...49
26702	2SK1096(-MR)	60V, 13A, 30W, <0,12Ohm(7A)	2SK1034, 2SK1306, 2SK1558
26703	2SK1097	100V, 8A, 30W, <0,28Ohm(4A)	BUK 543-100, 2SK1261, 2SK1556
26704	2SK1098(-MR)	150V, 6A, 30W, <0,5Ohm(3A)	
26705	2SK1099	<0,67Ohm(5A)	2SK1206, 2SK1523, 2SK1696, 2SK1832
26706	2SK111	20V, Idss0,3..6,5mA, Up<6V	BFS 70, 2N3369, 2N3821, 2SK381
26707	2SK110	Up<2V	BC 264A...D, BF 410B...D, 2SK192
26708	2SK1100	4V, 60mA, 12GHz	-
26709	2SK1101(-01MR)	<0,65Ohm(5A)	
26710	2SK1102(-01MR)	2SK1101, 500V, <0,9Ohm(5A)	
26711	2SK1103	2SK1104, SMD	-
26712	2SK1104	Up<3,5V	-
26713	2SK1105(-R)	800V, 3A, 80W, <0,4Ohm(1,5A)	BUK 426-800
26714	2SK1108	20V, 10mA, Idss>0,04mA	-
26715	2SK1109	2SK1108, SMD	-
26716	2SK1112	60V, 5A, 20W, <0,16Ohm	2SK1471, 2SK1719, 2SK1949
26717	2SK1113	120V, 3A, 20W, <0,42Ohm	2SK1474
26718	2SK1114	60V, 12A, 40W, <0,07Ohm(6A)	BUK 552-60, 2SK970...971, 2SK1300
26719	2SK1115	60V, 20A, 60W, <0,055Ohm	2SK942, 2SK972, 2SK1287, 2SK1910
26720	2SK1116	100V, 25A, 100W, <0,058Ohm	BUK 555-100, 2SK1347, 2SK1293, 2SK2050
26721	2SK1117	600V, 6A, 100W,	2SK1643
26722	2SK1118	2SK1117, , 45W	2SK1404, 2SK1637, 2SK2044
26723	2SK1119	SMPS(240V), 1000V, 4A, 100W	-
26724	2SK112	50V, Idss>1,2mA, Up<1,2V	-
26725	2SK1120	SMPS(240V), 1000V, 8A, 150W	2SK1934
26726	2SK1121	<0,03Ohm(13A)	BUK 545-50, 2SK943, 2SK1345
26727	2SK1122	100V, +-40A, 100W, <50mOhm	2SK1263, 2SK1304
26728	2SK1123	60V, +-40A, 100W, <27mOhm	2SK1297, 2SK1514, 2SK1665
26729	2SK1124	<0,03Ohm(25A)	BUK 439-60, 2SK849, 2SK857, 2SK1379

26730	2SK113	50V, Idss5..150mA, Up<10V	-
26731	2SK1131	20V, Idss0,15..0,8mA	-
26732	2SK1132	<50Ohm(20mA)	BSS 100
26733	2SK1133	2SK1132, SMD	BSS 123
26734	2SK1134	50V, 45A, 80W, <0,03Ohm	BUZ 347, 2SK905, 2SK1379, 2SK1514
26735	2SK1135	<0,22Ohm(8A)	2SK1401
26736	2SK1136	50V, 10A, 30W, <0,06Ohm(5A)	BUK 543-50, 2SK1256, 2SK1344
26737	2SK1137	<0,035Ohm(8A)	BUK 545-50, 2SK943, 2SK1214, 2SK1345...46
26738	2SK1138	150V, 7A, 30W, <0,3Ohm(4A)	BUK 545-200
26739	2SK1139	<0,08Ohm(7A)	2SK1266
26740	2SK1142	800V, 2A, 35W, <5Ohm(1A)	BUK 446-800, 2SK1611, 2SK1834, 2SK1459
26741	2SK1143	2SK1142, 900V, <6Ohm(1A)	2SK1459, 2SK1275
26742	2SK1149	<50mOhm(20A)	-
26743	2SK1150	<27mOhm(20A)	2SK1298, 2SK1666
26744	2SK1151(L,S)	450V, 1,5A, 20W, <5,5Ohm(1A)	2SK579...80, 2SK1327, 2SK1672
26745	2SK1152(L,S)	2SK1151, 500V, <6Ohm(1A)	2SK580, 2SK1327, 2SK1672
26746	2SK1153	450V, 3A, 30W, <2,8Ohm(2A)	BUZ 41A...42, 2SK1244, 2SK1493...94
26747	2SK1154	2SK1153, 500V, <3Ohm(2A)	BUZ 41A...42, 2SK1244, 2SK1494
26748	2SK1155	450V, 5A, 50W, <1,4Ohm(2,5A)	BUZ 41A...42, IRF 830, 2SK893, 2SK1246
26749	2SK1156	2SK1155, 500V, <1,5Ohm(2,5A)	BUZ 41A...42, IRF 830, 2SK893, 2SK1246
26750	2SK1157	450V, 7A, 60W, <0,8Ohm(4A)	IRF 840, 2SK894, 2SK1495...96, 2SK1574
26751	2SK1158	2SK1157, 500V, <0,9Ohm(4A)	IRF 840, 2SK894, 2SK1496, 2SK1574
26752	2SK1159	450V, 8A, 60W, <0,7Ohm(4A)	IRF 840, 2SK894, 2SK1495...96, 2SK1574
26753	2SK1160	2SK1159, 500V, <0,8Ohm(4A)	IRF 840, 2SK894, 2SK1496, 2SK1574
26754	2SK1161	<0,8Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1752
26755	2SK1162	2SK1161, 500V, <0,9Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1753
26756	2SK1163	<0,7Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1752
26757	2SK1164	2SK1163, 500V, <0,8Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1753
26758	2SK1165	<0,55Ohm(6A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
26759	2SK1166	2SK1165, 500V, <0,6(6A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
26760	2SK1167	<0,36Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
26761	2SK1168	2SK1167, 500V, <0,4Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
26762	2SK1169	<0,25Ohm(10A)	2SK870, 2SK1409, 2SK1411, 2SK1497...1500
26763	2SK117	50V, Idss>0,6mA, Up<1,5V	2SK68, 2SK106, 2SK121, 2SK163, 2SK184
26764	2SK1170	<0,27Ohm(10A)	2SK870, 2SK1411, 2SK1498, 2SK1500
26765	2SK1171	800V, 4A, 80W, <4,5Ohm(2A)	2SK695, 2SK727, 2SK793...94, 2SK1649...50
26766	2SK1172	<5,5Ohm(2A)	2SK794, 2SK1341, 2SK1649...50, 2SK1760
26767	2SK1174	900V, 2,5A, 40W, <4Ohm	2SK1459
26768	2SK1175	900V, 4,5A, 85W, <2,5Ohm	2SK809A, 2SK1463, 2SK1684
26769	2SK1176	900V, 6,5A, 85W, <1,6Ohm	2SK1464, 2SK1685
26770	2SK1177	<3Ohm(1,4A)	BUK 444-500, 2SK1758, 2SK1833
26771	2SK1178	<1,5Ohm(2A)	2SK1232, 2SK1627, 2SK1993, 2SK2115
26772	2SK1179	<0,85Ohm(4,5A)	2SK1329, 2SK1523, 2SK1696, 2SK1832
26773	2SK118	50V, Idss>0,3mA, Up<1,5V	2SK68, 2SK106, 2SK184
26774	2SK1180	<0,6Ohm(5A)	2SK1329, 2SK1523, 2SK1696, 2SK1832

26775	2SK1181	<0,4Ohm(6,5A)	2SK1269, 2SK1331, 2SK1524
26776	2SK1182	500V, 16A, 90W, <0,27Ohm	2SK1269, 2SK1524
26777	2SK1183	<1,5Ohm(1,5A)	BUZ 73(A)F, 2SK2010, 2SK2108
26778	2SK1184	<0,8Ohm(2,5A)	BUZ 73(A)F, 2SK2010, 2SK2108
26779	2SK1185	<0,54Ohm(2,5A)	BUK 442-100, BUK 542-100, 2SK1260
26780	2SK1186	<0,27Ohm(4,5A)	BUK 443-100, BUK 543-100, 2SK1430
26781	2SK1187	<0,16Ohm(6A)	BUK 545-100, 2SK1430...31, 2SK1558
26782	2SK1188	<0,2Ohm(5A)	BUK 442-60, 2SK1033, 2SK1093, 2SK1974
26783	2SK1189	<0,1Ohm(8A)	BUK 445-60, 2SK1094, 2SK1286, 2SK1419
26784	2SK119	Up<4,5V	BFS 70, 2N3821, 2N4220, 2N5359, 2SK104
26785	2SK1190	<0,05Ohm(12A)	BUK 445-60, 2SK1095, 2SK1420, 2SK1951
26786	2SK1191	<28mOhm(15A)	2SK1257, 2SK1421, 2SK1653, 2SK1952
26787	2SK1192	<28mOhm(20A)	2SK1298, 2SK1424, 2SK1666, 2SK2203
26788	2SK1193	60V, 45A, 95W, <20mOhm	2SK1298, 2SK1424, 2SK1666
26789	2SK1194	230V, 0,5A, 6W, <8Ohm(0,5A)	2SK1838
26790	2SK1195	230V, 1,5A, 10W, <2Ohm(1A)	2SK375, 2SK535, 2SK945, 2SK1838
26791	2SK1196	12GHz	-
26792	2SK1198	<3,2Ohm(1A)	BUK 446-800, 2SK1459, 2SK1611, 2SK1834
26793	2SK1199	70/125ns	BUZ 50, 2SK1324, 2SK1338
26794	2SK12	20V, Idss0,45..5mA, Up<4,5V	BFS 70, 2N3821, 2N4220, 2SK104
26795	2SK120	Up>0,3V	BF 410A...B, 2N5484, 2SK192
26796	2SK1200	900V, 3A, 80W, <7Ohm(1,5A)	2SK726, 2SK794, 2SK1339, 2SK1341
26797	2SK1201	900V, 4A, 80W, <5,5Ohm(2A)	BUZ 357...358, 2SK727, 2SK1341, 2SK1760
26798	2SK1202	900V, 5A, 100W, <4Ohm(3A)	BUZ 357...358, 2SK727, 2SK1341, 2SK1760
26799	2SK1203	900V, 6A, 100W, <3Ohm(3A)	2SK1342, 2SK1358, 2SK1502, 2SK1614
26800	2SK1204	900V, 8A, 100W, <1,6Ohm(4A)	2SK1342, 2SK1358, 2SK1502, 2SK1614.
26801	2SK1205	1000V, 5A, 100W, <2Ohm(3A)	BUZ 357...358, 2SK685, 2SK1359
26802	2SK1206	2SK557, , 60W	2SK1331, 2SK1523...24
26803	2SK121	30V, Idss>0,9mA, Up<1,49V	BF 410A...B, 2N4340, 2SK163, 2SK170
26804	2SK1211	800V, 2,5A, 40W, <7Ohm(1A)	BUK 426-800
26805	2SK1212(-01R)	900V, 5A, 80W, <2,5Ohm(2,5A)	2SK1175...76, 2SK1463, 2SK1684, 2SK2147
26806	2SK1213	<1,25Ohm(3A)	BUZ 332A, 2SK684, 2SK1032, 2SK1925
26807	2SK1214	80V, 20A, 45W, <0,135Ohm	2SK1307, 2SK1348...49, 2SK1432
26808	2SK1215	2SK359, SMD	-
26809	2SK1216	10V, 50mA, Idss>9,2mA	-
26810	2SK1217	900V, 8A, 100W, <2Ohm(4A)	2SK1464, 2SK1685, 2SK1775
26811	2SK1221	250V, 10A, 80W, <0,4Ohm(5A)	2SK925...26, 2SK1393
26812	2SK1222	<0,55Ohm(6A)	2SK725, 2SK788, 2SK899, 2SK1610
26813	2SK1223	130W, <45mOhm(13A)	2SK1380
26814	2SK1224	800V, 4A, 50W, <4,5Ohm(2A)	2SK1501, 2SK1639, 2SK1643
26815	2SK1225	2SK556, , 60W	2SK1268...69, 2SK1328, 2SK1523...24
26816	2SK1227	15V, Zin>200MOhm, Ur<40mV	-
26817	2SK1228	50V, 50mA, <50Ohm(10mA)	BSS 138, BSS 145, BST 82
26818	2SK1229	12GHz	-
26819	2SK123	20V, 2mA, Idss130..375µA	-



26820	2SK1230	2SK551, , 25W	2SK525, 2SK1035
26821	2SK1231	2SK552, , 30W	2SK1351, 2SK1608, 2SK1626...27
26822	2SK1232	2SK553, , 30W	2SK1351, 2SK1608, 2SK1627
26823	2SK1233	4GHz, 6V, 0,1A, Idss20..90mA	-
26824	2SK1234	4GHz, 5V, 0,1A, Idss20..80mA	-
26825	2SK1235	12GHz, 6V, 0,1A, Idss20..90mA	-
26826	2SK1236	12GHz, 6V, 0,1A, Idss20..90mA	-
26827	2SK1237	12GHz, 5V, 0,1A, Idss20..80mA	-
26828	2SK1238	Idss20..60mA	-
26829	2SK1239	2SK1238	-
26830	2SK124	8V, 0,1A, 12GHz	-
26831	2SK1240	0,06A, Idss10..60mA	-
26832	2SK1241	0,06A, Idss10..60mA	-
26833	2SK1242	2SK1240	-
26834	2SK1243	2SK1241	-
26835	2SK1244	45/75ns	2SK1154, 2SK1494
26836	2SK1245	2SK1244	BUK 445-500, 2SK1572, 2SK1767
26837	2SK1245	2SK1244	BUK 445-500, 2SK1572, 2SK1767
26838	2SK1246	50/90ns	BUZ 41A, BUZ 90, 2SK1156, 2SK1751
26839	2SK1247	2SK1246	2SK1232, 2SK1351, 2SK1608, 2SK1627
26840	2SK1247	2SK1246	2SK1232, 2SK1351, 2SK1608, 2SK1627
26841	2SK1248	70/143ns	2SK724, 2SK896, 2SK1488, 2SK1753
26842	2SK1249	130W, <0,45Ohm, 100/200ns	BUZ338, 2SK725, 2SK899, 2SK1610, 2SK1745
26843	2SK125	25V, Idss>30mA, Up<6V	BFT 10C
26844	2SK1250	150W, <0,35Ohm, 130/260ns	2SK1169...70, 2SK1497...1500, 2SK1680
26845	2SK1251	60V, 5A, 10W, <0,24Ohm(2,5A)	-
26846	2SK1252	<0,58Ohm(1,5A)	-
26847	2SK1253	<0,03Ohm(15A)	2SK1262
26848	2SK1254(L,S)	100V, 3A, 20W, <0,4Ohm(2A)	2SK1113, 2SK1284
26849	2SK1255	60V, 5A, 30W, <0,3Ohm(2A)	BUK 541-60, BUK 542-100, 2SK1260
26850	2SK1256	<0,165Ohm(3A)	2SK1033, 2SK1093, 2SK1305, 2SK1344
26851	2SK1257	60V, 40A, 45W, <0,05Ohm(10)	2SK1653, 2SK1952
26852	2SK1258	60V, 50A, 100W, <45mOhm(13)	2SK1379, 2SK1381
26853	2SK1259	<23mOhm(25A)	-
26854	2SK1260	100V, 5A, 30W, <0,6Ohm(2A)	BUK 542-100, 2SK1265
26855	2SK1261	100V, 8A, 40W, <0,3Ohm(3A)	BUK 543-100, 2SK1556
26856	2SK1262	<85mOhm(10A)	-
26857	2SK1263	<75mOhm(13A)	2SK1304, 2SK1381
26858	2SK1264	150V, 3A, 30W, <1,3Ohm(2A)	-
26859	2SK1265	150V, 6A, 40W, <0,6Ohm(3A)	BUK 545-200, 2SK1035
26860	2SK1266	<135mOhm(10A)	-
26861	2SK1267	100W, <0,13Ohm(12A)	-
26862	2SK1268	2SK559, , 60W	2SK1331, 2SK1524
26863	2SK1269	2SK560, , 60W	2SK1331, 2SK1524
26864	2SK127	50V, 20mA, Idss0,5..12mA	-



26865	2SK1270	2SK975, 2A, 10W	2SK1283
26866	2SK1271	<4Ohm(3A)	-
26867	2SK1272	60V, +-1A, <0,65Ohm(0,5A)	2SK1274, 2SK1733
26868	2SK1272	60V, +-1A, <0,65Ohm(0,5A)	2SK1274, 2SK1733
26869	2SK1273	2SK1272, SMD, +-2A	2SK1311, 2SK1470, 2SK1717
26870	2SK1274	2SK1272, +-1,5A, 1W	2SK975, 2SK1733, 2SK1736
26871	2SK1275	2SK1199, , 30W	2SK1143, 2SK1459
26872	2SK1276(A)	<0,2Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK1673...74
26873	2SK1277	150W, <0,12Ohm(15A)	2SK902, 2SK1492, 2SK1671, 2SK1675...76
26874	2SK1278	<1,1Ohm(5A)	BUZ339, 2SK724, 2SK896, 2SK1488, 2SK1753
26875	2SK1279	<0,58Ohm(8A)	BUZ338, 2SK725, 2SK899, 2SK1610, 2SK1678
26876	2SK127A	2SK127, 80V	-
26877	2SK128	Up<1,5V	2SK68, 2SK106, 2SK184
26878	2SK1280	<0,5Ohm(9A)	2SK1409, 2SK1411, 2SK1680
26879	2SK1281	700V, 4A, 120W, <3,2Ohm(2A)	2SK695, 2SK727, 2SK793, 2SK1649...50
26880	2SK1282(Z)	<0,18Ohm(2A)	2SK974
26881	2SK1283	2SK1282	2SK1285
26882	2SK1284(Z)	<0,32Ohm(2A)	2SK1113, 2SK1254, 2SK1299
26883	2SK1285	2SK1284	-
26884	2SK1286	2SK1287, , +-15A, 30W	2SK943, 2SK1214, 2SK1345...46
26885	2SK1287	<0,07Ohm(10A)	2SK972, 2SK942, 2SK1115
26886	2SK1288	2SK1289, , +-15A, 30W	2SK1034, 2SK1306, 2SK1292, 2SK1558
26887	2SK1289	<0,15Ohm(10A)	2SK1116, 2SK1302, 2SK1347
26888	2SK1290	2SK1291, , +-25A, 35W	2SK943, 2SK1214, 2SK1345...46
26889	2SK1291	<45mOhm(15A)	2SK1296, 2SK2411
26890	2SK1292	2SK1293, , +-20A, 35W	2SK1262, 2SK1307, 2SK1348...49
26891	2SK1293	<80mOhm(15A)	2SK2050, 2SK2314
26892	2SK1294	<27mOhm(20A)	2SK1257, 2SK1653, 2SK1952, 2SK2120
26893	2SK1295	<50mOhm(15A)	2SK2050
26894	2SK1296	<28mOhm(15A)	2SK1291
26895	2SK1297	<18mOhm(20A)	2SK1514, 2SK1665
26896	2SK1298	2SK1297, , 50W	2SK1666
26897	2SK1299(L,S)	100V, 3A, 20W, <0,35Ohm(2A)	2SK1113, 2SK1254, 2SK1284
26898	2SK13	12V, Idss0,45..5mA, Up<4,5V	BFS 70, 2N3821, 2N4220, 2SK104
26899	2SK130(A)	Up<1,5V	2N5247, 2SK147, 2SK151, 2SK162, 2SK363
26900	2SK1300	100V, 10A, 40W, <0,25Ohm(5A)	2SK1559, 2SK1561
26901	2SK1301	100V, 15A, 50W, <0,13Ohm(8A)	2SK1559, 2SK1561
26902	2SK1302	50W, <85mOhm(10A)	BUK 555-100, 2SK1116, 2SK1347
26903	2SK1303	100W, <0,06Ohm(15A)	2SK1263
26904	2SK1304	100W, <0,03Ohm(20A)	2SK1263, 2SK1381
26905	2SK1305	2SK1300, , 25W	BUK 545-100, 2SK1035
26906	2SK1306	2SK1301, , 30W	2SK1034, 2SK1558
26907	2SK1307	2SK1302, , 35W	2SK1266, 2SK1292, 2SK1348...49
26908	2SK1308	400V, 5A, 40W, <1,4Ohm(3A)	2SK1691
26909	2SK1308A	2SK1308, 450V	2SK1691

26910	2SK1310	100V, 12A,PQ190W(230MHz)	-
26911	2SK1311	60V, 2A, <0,45Ohm(1A)	2SK1273, 2SK1470, 2SK1717, 2SK2315
26912	2SK1313(L,S)	450V, 5A, 50W, <1,4Ohm(2,5A)	2SK1540...41, 2SK1722
26913	2SK1314(L,S)	2SK1313, 500V, <1,5Ohm(2,5A)	2SK1541, 2SK1722
26914	2SK1315(L,S)	450V, 8A, 60W, <0,7Ohm(4A)	2SK2187
26915	2SK1316(L,S)	2SK1540, 500V, <0,8Ohm(4A)	2SK2187
26916	2SK1317	<12Ohm(2A)	2SK1835
26917	2SK1318	<0,12Ohm(10A)	2SK1266
26918	2SK1319	250V, 8A, 75W, <0,52Ohm(4A)	2SK741, 2SK1320, 2SK1400
26919	2SK1319..1320S	2SK1319..1322	2SK1621
26920	2SK132	18/14ns	2SK175...176, BUZ 33
26921	2SK1320	2SK1319, 300V	2SK1400
26922	2SK1321	450V, 5A, 75W, <1,3Ohm(3A)	BUZ 41A...42, 2SK893, 2SK1246, 2SK1751
26923	2SK1321..1322S	2SK1321..1322	2SK2355Z...56Z
26924	2SK1322	2SK1321, <1,6Ohm(3A)	BUZ 41A...42, 2SK893, 2SK1246, 2SK1751
26925	2SK1323	800V, 2A, 75W, <6,5Ohm(1A)	BUZ 80, 2SK1199, 2SK1338
26926	2SK1323..1324S	2SK1323..1324	2SK1647
26927	2SK1324	2SK1323, 900V	2SK1199, 2SK1338
26928	2SK1325	12GHz	-
26929	2SK1326	10V, 20mA, Idss>6mA	-
26930	2SK1327(L,S)	600V, 1A, 20W, <9Ohm(0,5A)	2SK1533, 2SK1880
26931	2SK1328	<0,55Ohm(6A)	2SK1206, 2SK1225, 2SK1268...69, 2SK1523
26932	2SK1329	2SK1328, 500V, <0,6Ohm(6A)	2SK1206, 2SK1225, 2SK1269, 2SK1523
26933	2SK133	2SK132, 120V	2SK175...176, BUZ 33
26934	2SK1330	800V, 8A, 100W, <1,7Ohm(5A)	2SK1032, 2SK1358, 2SK1502, 2SK1692
26935	2SK1330A	2SK1330, 900V	2SK1358, 2SK1502, 2SK1692, 2SK1795
26936	2SK1331	<0,5Ohm(8A)	2SK1269, 2SK1405, 2SK1524
26937	2SK1331	<0,5Ohm(8A)	2SK1269, 2SK1405, 2SK1524
26938	2SK1333	<0,4Ohm(15A)	2SK678, 2SK1544
26939	2SK1334	13/17ns	-
26940	2SK1335(L,S)	200V, 3A, 20W, <0,8Ohm(2A)	-
26941	2SK1336	0,4W,<1,7Ohm(0,2A)	BST 70, BST 72, 2SK422...423
26942	2SK1337	0,4W,<4,5Ohm(0,2A)	BSS 89, BST 74, BST 76, 2SK423
26943	2SK1338	900V, 2A, 50W, <7Ohm(1A)	2SK1199, 2SK1324
26944	2SK1339	900V, 3A, 80W, <7Ohm(1,5A)	2SK538, 2SK696, 2SK726...727, 2SK794
26945	2SK134	2SK132, 140V	2SK175...176, BUZ 33
26946	2SK1340	900V, 5A, 100W, <4Ohm(3A)	BUZ 357...358, 2SK727, 2SK794, 2SK1760
26947	2SK1341	900V, 6A, 100W, <3Ohm(3A)	2SK1358, 2SK1462, 2SK1502, 2SK1614
26948	2SK1342	900V, 8A, 100W, <1,6Ohm(4A)	2SK1358, 2SK1462, 2SK1502, 2SK1614
26949	2SK1344	60V, 12A, 30W, <0,07Ohm(6A)	2SK1033, 2SK1094, 2SK1256, 2SK1895
26950	2SK1345	40W,<0,055Ohm(10A)	2SK943, 2SK1095, 2SK1214
26951	2SK1346	<0,06Ohm(15A)	2SK943, 2SK1095, 2SK1214, 2SK1420
26952	2SK1347	100V, 20A, 75W, <85mOhm	BUK 555-100, 2SK1302, 2SK1116, 2SK2050
26953	2SK1348	2SK1347, , 40W	2SK1266, 2SK1307, 2SK1292, 2SK1906
26954	2SK1349	100V, 25A, 45W, <58mOhm	2SK1262, 2SK1292, 2SK1906

26955	2SK135	2SK132, 160V	2SK175...176, BUZ 33
26956	2SK1350	<0,18Ohm(10A)	2SK2012
26957	2SK1351	500V, 5A, 40W, <1,5Ohm	2SK1232, 2SK1608, 2SK1627, 2SK1993
26958	2SK1352	500V, 7A, 45W, <0,85Ohm	2SK1567, 2SK1805
26959	2SK1356	900V, 3A, 40W, <4,3Ohm(1,5A)	2SK1460
26960	2SK1357	900V, 5A, 125W, <2,8Ohm(2A)	2SK727, 2SK794, 2SK1341, 2SK1649...50
26961	2SK1358	900V, 9A, 150W, <1,4Ohm(4A)	2SK1342, 2SK1502, 2SK1614, 2SK1796
26962	2SK1359	1000V, 5A, 125W, <3,8(2A)	2SK1205
26963	2SK136	Up<2V	2N4339, 2N5358, 2SK83
26964	2SK1360	900V, 3A, 80W, <4,3Ohm	2SK1463, 2SK1683, 2SK1770
26965	2SK1360	900V, 3A, 80W, <4,3Ohm	2SK1463, 2SK1683, 2SK1770
26966	2SK1362	900V, 5A, 85W, <2,5Ohm(3A)	2SK1463...65, 2SK1684...85, 2SK1859
26967	2SK1362	900V, 5A, 85W, <2,5Ohm(3A)	2SK1463...65, 2SK1684...85, 2SK1859
26968	2SK1363	900V, 8A, 90W, <1,4Ohm(4A)	2SK1464, 2SK1685, 2SK1775
26969	2SK1363	900V, 8A, 90W, <1,4Ohm(4A)	2SK1464, 2SK1685, 2SK1775
26970	2SK1365	1000V, 7A, 90W, <1,8Ohm(4A)	2SK1120, 2SK1934
26971	2SK1365	1000V, 7A, 90W, <1,8Ohm(4A)	2SK1120, 2SK1934
26972	2SK1366	<3,6Ohm(1A)	BUK 444-400, 2SK1833, 2SK1988...89
26973	2SK1367	<1,8Ohm(1,5A)	BUK 445-450, 2SK1862...63, 2SK1444
26974	2SK1368	<1Ohm(2,5A)	BUK 445-400, 2SK1377, 2SK1992...93
26975	2SK1369	<0,55Ohm(5A)	2SK1452, 2SK1328...29, 2SK1523
26976	2SK1370	<0,3Ohm(8A)	2SK1453, 2SK1268...69, 2SK1524
26977	2SK1371	450V, 20A, 125W, <0,25Ohm	2SK1497, 2SK1499, 2SK1517, 2SK1680
26978	2SK1372	2SK1371, 500V	-
26979	2SK1373	550V, 12A, 100W, <0,67Ohm	BUZ 334, 2SK1723
26980	2SK1374	2SK1228	-
26981	2SK1375	2SK596, SMD	-
26982	2SK1377	400V, 5,5A, 40W, <1,2Ohm	2SK1231, 2SK1351, 2SK1608, 2SK1627
26983	2SK1378	400V, 10A, 125W, <0,55Ohm	BUZ 61
26984	2SK1379	60V, 50A, 150W, <0,017Ohm	BUK 539-60, 2SK1258
26985	2SK138	5V, 100mA, 8GHz	-
26986	2SK1380	60V, 60A, 200W, <0,011Ohm	2SK1259
26987	2SK1381	100V, 50A, 150W, <0,032Ohm	-
26988	2SK1382	100V, 60A, 200W, <0,02Ohm	-
26989	2SK1384(-R)	800V, 5A, 80W, <2Ohm(2,5A)	2SK1175...76, 2SK1463, 2SK1684, 2SK2147
26990	2SK1385(-01)	800V, 9A, 100W, <1,5Ohm(4A)	2SK1686, 2SK2148
26991	2SK1386	450V, 7A, 100W, <1,3Ohm(3A)	BUZ 330...331
26992	2SK1387(-MR)	<0,035Ohm(17,5A)	2SK1653, 2SK2120, 2SK2312, 2SK2529
26993	2SK1388	<0,022Ohm(17,5A)	BUK 555-50
26994	2SK1389	<0,025Ohm(25A)	2SK1258, 2SK1379
26995	2SK1390(-R)	2SK1389, 80W	2SK1298, 2SK1424, 2SK1666, 2SK2203
26996	2SK1391	65/80ns	2SK477, 2SK741, 2SK924
26997	2SK1392	2SK1391, , 25W	2SK1478, 2SK1568, 2SK1668
26998	2SK1392	2SK1391, , 25W	2SK1478, 2SK1568, 2SK1668
26999	2SK1393	75/100ns	2SK925...926, 2SK1221, 2SK1393

27000	2SK1394	2SK1393, , 30W	2SK526, 2SK1036, 2SK1762
27001	2SK1394	2SK1393, , 30W	2SK526, 2SK1036, 2SK1762
27002	2SK1395	250V, 20A, 100W, <0,25Ohm	2SK623, 2SK901, 2SK944, 2SK1641, 2SK1673
27003	2SK1396	250V, 30A, 120W, <0,18Ohm	2SK902, 2SK1669, 2SK1671, 2SK1675
27004	2SK1397	250V, 40A, 130W, <0,13Ohm	-
27005	2SK1398	<20Ohm(10mA)	BS 170, BSS 98
27006	2SK1399	2SK1398, SMD	BSS 123, BSS 138, BSS 145
27007	2SK140	5V, 100mA, 12GHz	-
27008	2SK1400	300V, 7A, 50W, <0,7Ohm(4A)	2SK554...555, 2SK1320
27009	2SK1400A	2SK1400, 350V, <0,8Ohm(4A)	2SK554...555, 2SK1495...96
27010	2SK1401	<0,35Ohm(8A)	BUZ 323
27011	2SK1401A	2SK1401, 350V, <0,4Ohm(8A)	BUZ 323
27012	2SK1402	600V, 4A, 50W, <2,4Ohm(2A)	BUZ 90, 2SK1117
27013	2SK1402A	2SK1402, 650V, <2,6Ohm(2A)	-
27014	2SK1403	600V, 8A, 100W, <1,3Ohm(4A)	2SK684, 2SK1032
27015	2SK1403A	2SK1403, 650V, <1,4Ohm(4A)	2SK684, 2SK1032
27016	2SK1404	600V, 5A, 35W, <1,5Ohm(2,5A)	2SK1118, 2SK1637
27017	2SK1405	600V, 15A, 60W, <0,5Ohm(8A)	-
27018	2SK1406	<0,4Ohm(10A)	2SK1525
27019	2SK1406	<0,4Ohm(10A)	2SK1525
27020	2SK1407	4V, 60mA, 12GHz	-
27021	2SK1408	<0,31Ohm(8A)	-
27022	2SK1409	<0,25Ohm(10A)	-
27023	2SK141(A)	Up<4,5V	BFS 70, 2N3821, 2N4220, 2SK104
27024	2SK1410	2SK1408, 500V	-
27025	2SK1411	2SK1409, 500V	-
27026	2SK1412(LS)	<200Ohm(50mA)	-
27027	2SK1413	1500V, 2A, 60W, <11Ohm(1A)	-
27028	2SK1414	<3,5Ohm(3A)	-
27029	2SK1416	<0,08Ohm(10A)	BUK 552-60, 2SK971...72, 2SK1115
27030	2SK1417	<45mOhm(15A)	BUK 555-60, 2SK972, 2SK1115, 2SK1296
27031	2SK1418	<26mOhm(25A)	BUK 556-60, 2SK1542
27032	2SK1419	<0,08Ohm(10A)	2SK943, 2SK1345...46
27033	2SK1420	<45mOhm(15A)	2SK943, 2SK1345...46
27034	2SK1421	<26mOhm(25A)	2SK1257, 2SK1653
27035	2SK1422	<26mOhm(25A)	BUK539-60, 2SK1258, 2SK1379
27036	2SK1423	<16mOhm(50A)	-
27037	2SK1424	<26mOhm(25A)	2SK1298, 2SK1666
27038	2SK1425	<16mOhm(50A)	-
27039	2SK1426	<12mOhm(60A)	2SK1259
27040	2SK1427	<0,16Ohm(6A)	2SK1300
27041	2SK1428	<0,1Ohm(12A)	BUK 555-100, 2SK1302, 2SK1116, 2SK1347
27042	2SK1429	<55mOhm(20A)	BUK 456-100, 2SK1303
27043	2SK1430	<0,16Ohm(6A)	BUK 545-100, 2SK1035, 2SK1305
27044	2SK1431	<0,1Ohm(12A)	BUK 445-100, 2SK1306, 2SK1558

27045	2SK1432	<55mOhm(20A)	2SK1307, 2SK1348...49
27046	2SK1433	<55mOhm(20A)	2SK1303
27047	2SK1434	<35mOhm(40A)	2SK1381
27048	2SK1435	<55mOhm(20A)	2SK1149
27049	2SK1436	<35mOhm(40A)	2SK1149
27050	2SK1437	<26mOhm(45A)	2SK1382
27051	2SK1438	<12Ohm(0,2A)	2SK1052
27052	2SK1439	450V, 3A, 50W, <2,6Ohm(1,5A)	2SK1154, 2SK1244
27053	2SK1440	450V, 5A, 60W, <1,4Ohm(3A)	2SK1246,BUZ41A...42, 2SK552...53, 2SK893
27054	2SK1441	450V, 8A, 70W, <0,8Ohm(4A)	2SK554...55, 2SK636, 2SK894
27055	2SK1442	450V, 12A, 70W, <0,6Ohm(6A)	2SK1503
27056	2SK1443(LS)	450V, 1A, 20W, <4,5Ohm(0,5A)	2SK1833, BUK 444-450, 2SK529, 2SK1833)
27057	2SK1444(LS)	450V, 3A, 25W, <2,6Ohm(1,5A)	BUK 445-450, 2SK1572, 2SK1767
27058	2SK1445(LS)	450V, 5A, 30W, <1,4Ohm(3A)	2SK1351, 2SK1608, 2SK1626, 2SK1990...93
27059	2SK1446(LS)	450V, 7A, 35W, <0,8Ohm(4A)	2SK1352, 2SK1566...67, 2SK1609
27060	2SK1447(LS)	450V, 9A, 40W, <0,6Ohm(6A)	-
27061	2SK1448	450V, 8A, 100W, <0,8Ohm(4A)	2SK1574, BUZ 330...331
27062	2SK1449	<0,6Ohm(6A)	2SK1488, 2SK1610, 2SK1745, 2SK1785
27063	2SK1450	<0,3Ohm(10A)	2SK1169...70, 2SK1497...1500, 2SK1680
27064	2SK1451	450V, 8A, 50W, <0,8Ohm(4A)	2SK1206, 2SK1225, 2SK1328, 2SK1523
27065	2SK1452	450V, 10A, 60W, <0,6Ohm(6A)	2SK1206, 2SK1225, 2SK1328, 2SK1523
27066	2SK1453	<0,3Ohm(10A)	2SK1268...69, 2SK1331, 2SK1524...25
27067	2SK1454	250W,<0,16Ohm(15A)	2SK1628...29
27068	2SK1455	<70Ohm(0,1A)	-
27069	2SK1456	900V, 3A, 60W, <6Ohm(1,5A)	BUK 456-1000, 2SK1601, 2SK1638, 2SK1793
27070	2SK1457	900V, 5A, 70W, <3,6Ohm(2A)	2SK1501, 2SK1639, 2SK1643
27071	2SK1458(LS)	<70Ohm(0,1A)	-
27072	2SK1459(LS)	900V, 2,5A, 30W, <6Ohm(1,5A)	2SK1143, 2SK1275
27073	2SK1460(LS)	900V, 3,5A, 40W, <3,6Ohm(2A)	2SK1356
27074	2SK1461	900V, 5A, 120W, <3,6Ohm(2A)	2SK727, 2SK794, 2SK1649...50, 2SK1760
27075	2SK1462	900V, 8A, 150W, <1,6Ohm(4A)	2SK1358, 2SK1502, 2SK1614, 2SK1795
27076	2SK1463	900V, 4,5A, 60W, <3,6Ohm(2A)	2SK1684, 2SK1859
27077	2SK1464	900V, 8A, 80W, <1,6Ohm(4A)	2SK1685...86, 2SK1775
27078	2SK1465	900V, 8A, 200W, <1,6Ohm(4A)	2SK1489
27079	2SK1466	<0,8Ohm(8A)	-
27080	2SK1467	S, 30V, 2A,<0,3Ohm(1A)	2SK1311, 2SK1470, 2SK1717
27081	2SK1468	30V, 4A, 20W, <0,12Ohm(2A)	2SK1112, 2SK1471, 2SK1719
27082	2SK1469	30V, 8A, 30W, <0,055Ohm(4A)	2SK1472, 2SK1748
27083	2SK147	40V, Idss>5mA, Up<1,2V	2N5247, 2SK130, 2SK151, 2SK162, 2SK363
27084	2SK1470	60V, 2A, <0,45Ohm(1A)	2SK1311, 2SK1717, 2SK1763
27085	2SK1471	60V, 4A, 20W, <0,2Ohm(2A)	2SK1112, 2SK1474, 2SK1719
27086	2SK1472	60V, 8A, 30W, <0,08Ohm(4A)	2SK1475, 2SK1748
27087	2SK1473	100V, 2A, <0,95Ohm(1A)	2SK2055
27088	2SK1474	100V, 4A, 20W,<0,4Ohm(2A)	2SK1804
27089	2SK1475	100V, 8A, 30W,<0,16Ohm(4A)	2SK1557



27090	2SK1476	150W,<0,65Ohm(6A)	2SK896, 2SK1488, 2SK1752, 2SK1785
27091	2SK1477	2SK1476, 500V, <0,78Ohm(6A)	2SK896, 2SK1488, 2SK1753, 2SK1785
27092	2SK1478	250V, 8A, 40W, <0,6Ohm(2A)	2SK526, 2SK1036, 2SK1568...69
27093	2SK1479	25V, 5mA, Idss>0,3mA	-
27094	2SK148	25V, Idss<12mA	-
27095	2SK1480	Up<2V	-
27096	2SK1482	<0,4Ohm(0,5A)	2SK1272, 2SK1733
27097	2SK1482	<0,4Ohm(0,5A)	2SK1272, 2SK1733
27098	2SK1483	2SK1482, SMD, +-2A	2SK1273, 2SK1311, 2SK1470
27099	2SK1484	<0,8Ohm(0,5A)	2SK1729
27100	2SK1484	<0,8Ohm(0,5A)	2SK1729
27101	2SK1485	2SK1484, SMD, +-1A	2SK1728
27102	2SK1486	<0,095Ohm(16A)	2SK1454, 2SK1628, 2SK1681
27103	2SK1487	450V, 10A, 125W, <1Ohm(5A)	2SK896, 2SK1488, 2SK1723, 2SK1752
27104	2SK1488	500V, 10A, 125W, <1Ohm(5A)	2SK896, 2SK1723, 2SK1753, 2SK1785
27105	2SK1489	1000V, 12A, 200W, <1Ohm(6A)	-
27106	2SK149	20V, Idss>8mA, Up<2,2V	-
27107	2SK1491	120W,<0,15Ohm(13A)	2SK901, 2SK944, 2SK1641, 2SK1673...74
27108	2SK1492	140W,<0,1Ohm(18A)	2SK902, 2SK1669, 2SK1671, 2SK1675...76
27109	2SK1493	<2,8Ohm(2A)	2SK1154, 2SK1244, 2SK1439
27110	2SK1493..1494Z	2SK1493..1494	2SK2356Z
27111	2SK1493..1496Z	2SK1493..1496	2SK1540...41
27112	2SK1494	2SK1493, 500V, <3Ohm(2A)	2SK1154, 2SK1244
27113	2SK1495	<0,9Ohm(4A)	IRF 840, IRF 842, 2SK1574
27114	2SK1496	2SK1495, 500V, <1Ohm(4A)	IRF 840, IRF 842, 2SK1574
27115	2SK1497	120W,<0,35Ohm(10A)	2SK1169...70, 2SK1409, 2SK1411, 2SK1680
27116	2SK1498	2SK1497, 500V, <0,4Ohm(10A)	2SK1170, 2SK1411, 2SK1680
27117	2SK1499	160W,<0,25Ohm(13A)	2SK1169...70, 2SK1409, 2SK1411, 2SK1680
27118	2SK15	20V, Idss0,45..5mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK104
27119	2SK1500	<0,27Ohm(13A)	2SK1170, 2SK1411, 2SK1680
27120	2SK1501	900V, +-4A, 70W, <4Ohm(2A)	2SK1119, 2SK1457, 2SK1639, 2SK1643
27121	2SK1501Z	2SK1501	-
27122	2SK1502	900V, +-7A, 120W, <2Ohm(2A)	2SK1358, 2SK1614, 2SK1692, 2SK1795
27123	2SK1503(-01)	500V, 10A, 80W, <0,9Ohm(5A)	2SK2366
27124	2SK1504(-01)L,S	2SK1503	2SK2366Z
27125	2SK1505(-MR)	<0,022Ohm(17,5A)	2SK1653, 2SK2120, 2SK2312, 2SK2529
27126	2SK1506	<0,03Ohm(25A)	-
27127	2SK1507(-01MR)	600V, 9A, 50W, <1Ohm(5A)	-
27128	2SK1508	<35mOhm(17,5A)	BUK 555-60, 2SK1291, 2SK1296
27129	2SK1509	<80mOhm(10A)	BUZ 21, IRF 540, IRF 542, 2SK1116
27130	2SK151	40V, Idss>6mA, Up<1,1V	2N5247
27131	2SK1510(-01)L,S	900V, 3,5A, 60W, <5,5Ohm(2A)	2SK1528, 2SK1659
27132	2SK1511	1000V, 5A, 100W, <3Ohm	BUZ 357...358, 2SK1205, 2SK1359, 2SK1773
27133	2SK1512	900V, 10A, 150W, <1,2Ohm	-
27134	2SK1513	<0,75Ohm(8A)	2SK1029



27135	2SK1514	125W, <0,03Ohm(20A)	2SK1297, 2SK1665
27136	2SK1515	<0,80Ohm(5A)	BUK 637-450, 2SK683
27137	2SK1516	2SK1515, 500V, <0,90Ohm(5A)	BUK 637-500, 2SK683
27138	2SK1517	<0,25Ohm(10A)	-
27139	2SK1518	<0,27Ohm(10A)	-
27140	2SK1519	<0,15Ohm(15A)	-
27141	2SK152	15V, Idss>9,5mA, Up<2V	BF 410D
27142	2SK1520	<0,16Ohm(15A)	-
27143	2SK1521	<0,10Ohm(25A)	-
27144	2SK1522	<0,11Ohm(25A)	-
27145	2SK1523	2SK1248	2SK1206
27146	2SK1524	2SK1249	2SK1269, 2SK1331, 2SK1405
27147	2SK1525	2SK1250	2SK1406
27148	2SK1526	<0,15Ohm(20A)	2SK1521...22
27149	2SK1527	<0,16Ohm(20A)	2SK1522
27150	2SK1528(L,S)	900V, 4A, 60W, <4Ohm(2A)	2SK2006
27151	2SK1529	180V, 10A, 120W	-
27152	2SK1530	200V, 12A, 150W	-
27153	2SK1531	0,45Ohm(7A)	2SK725, 2SK788, 2SK899, 2SK1745, 2SK1678
27154	2SK1532	2SK1031	-
27155	2SK1533	900, 1A, 10W, <15Ohm, 40/85ns	-
27156	2SK1534	900, 3A, 50W, <5Ohm, 45/110ns	2SK791...792, 2SK1456, 2SK1601, 2SK1638
27157	2SK1535	2SK1534, , 30W	2SK1356, 2SK1460
27158	2SK1535	2SK1534, , 30W	2SK1356, 2SK1460
27159	2SK1536	45/110ns	2SK726, 2SK1339
27160	2SK1537	65/145ns	2SK727, 2SK794, 2SK1649...50, 2SK1794
27161	2SK1538	80/200ns	2SK1342, 2SK1358, 2SK1462, 2SK1795
27162	2SK1539	115/290ns	2SK1796
27163	2SK154	20V, Idss<18mA	-
27164	2SK1540(L,S)	450V, 7A, 60W, <0,80Ohm(4A)	2SK1315...16, 2SK2187
27165	2SK1541(L,S)	2SK1540, 500V, <0,90Ohm(4A)	2SK1316, 2SK2187
27166	2SK1542	125W, <0,02Ohm(20A)	BUK 556-60, 2SK1911
27167	2SK1544	<0,20Ohm(13A)	2SK1629, 2SK1971
27168	2SK1545	800V, 3A, 40W, <6Ohm	2SK1356, 2SK1460, 2SK1995
27169	2SK1546	900V, 2,5A, 40W, <7,30Ohm	2SK1174, 2SK1459, 2SK1994
27170	2SK1547(-01MR)	800V, 4A, 40W, <4,5Ohm(2A)	2SK1404, 2SK1637, 2SK2044...45, 2SK2118
27171	2SK1548(-01MR)	900V, 3,5A, 40W, <5,5Ohm(2A)	2SK1356, 2SK1460, 2SK1995
27172	2SK1549(-R)	<0,15Ohm(10A)	2SK822, 2SK2008
27173	2SK155	20V, Idss>0,5mA, Up<1,5V	2SK68, 2SK106, 2SK184
27174	2SK1552(-01)L,S	800V, 4A, 60W, <4,5Ohm(2A)	2SK1528, 2SK2006, 2SK2089
27175	2SK1553	650V, 5A, 40W, <2,5Ohm(2,5A)	2SK1404, 2SK1637, 2SK2118
27176	2SK1554	650V, 3A, 30W, <4,5Ohm	2SK1572, 2SK1767, 2SK1995, 2SK2144
27177	2SK1555	50V, 16A, 75W, <0,05Ohm(8A)	BUK 552-50, 2SK971
27178	2SK1555S	2SK1555	2SK1648, 2SK1898, 2SK2322
27179	2SK1556	100V, 8A, 30W, <0,20Ohm(4A)	BUK 543-100, 2SK1261

27180	2SK1557	2SK1556, 45W	2SK1475
27181	2SK1558	<0,09Ohm(8A)	2SK1034, 2SK1288, 2SK1306
27182	2SK1559	2SK1558, 75W	2SK1301, 2SK1561
27183	2SK1559S	2SK1558	-
27184	2SK156	20V, Idss>0,06mA	-
27185	2SK1560	150V, 7A, 45W, <0,3Ohm(4A)	-
27186	2SK1561	150V, 16A, 75W, <0,12Ohm(8A)	BUK 555-200
27187	2SK1561S	2SK1561	-
27188	2SK1562	150W, <0,65Ohm(6A)	-
27189	2SK1562..1563S	2SK1562..1563	-
27190	2SK1563	2SK1562, 500V, <0,78Ohm(6A)	-
27191	2SK1564	150W, <3,6Ohm(1,5A)	-
27192	2SK1564..1565S	2SK1564..1565	-
27193	2SK1565	2SK1564, 900V, <4Ohm(1,5A)	-
27194	2SK1566	2SK1157, , 35W	2SK1352, 2SK1609, 2SK1805
27195	2SK1567	2SK1158, , 35W	2SK1352, 2SK1609, 2SK1805
27196	2SK1568	250V, 8A, 40W, <0,6Ohm(4A)	2SK1478, 2SK1668
27197	2SK1569	2SK1468, 300V, <0,65Ohm(4A)	-
27198	2SK157	50V, Idss>0,5mA, Up<1,5V	2SK94
27199	2SK1570	150W, <0,78Ohm(6A)	2SK683, 2SK1488, 2SK1516, 2SK1785
27200	2SK1571	2SK1570, 500V, <0,9Ohm(6A)	2SK683, 2SK1488, 2SK1516, 2SK1785
27201	2SK1572	33/95ns	2SK1767, 2SK2144
27202	2SK1573	<0,5Ohm(8A)	2SK1723
27203	2SK1574	<0,85Ohm(4A)	IRF 840, 2SK894, 2SK1496, 2SK2360
27204	2SK1576	30V, Idss2,5..14mA, Up<1,5V	-
27205	2SK1577	35V, Idss>30mA, Up<6V	-
27206	2SK1578	V	-
27207	2SK1579	12V, +-2A, 500/1500ns	-
27208	2SK158	55V, Idss<6,5mA	-
27209	2SK1580	16V, +-0,1A, <10Ohm(1mA)	-
27210	2SK1581	16V, +-0,2A, <3Ohm(1mA)	BSS 123
27211	2SK1582	30V, +-0,2A, <3Ohm(10mA)	BSS 123
27212	2SK1583	16V, +-0,5A, <1,5Ohm(0,3A)	BST 80, 2SK601, 2SK1078, 2SK1592
27213	2SK1584	30V, +-0,5A, <1,5Ohm(0,3A)	BST 80, 2SK601, 2SK1078, 2SK1592
27214	2SK1585	16V, +-1A, <1Ohm(0,5A)	2SK1726
27215	2SK1586	30V, +-1A, <0,6Ohm(0,5A)	2SK1726
27216	2SK1588	16V, +-3A, <0,3Ohm(1A)	2SK2054
27217	2SK1589	100V, +-0,1A, <25Ohm(10mA)	BSS 123
27218	2SK1590	60V, +-0,2A, <3Ohm(10mA)	BST 82
27219	2SK1591	100V, +-0,2A, <6,5Ohm(10mA)	-
27220	2SK1592	60V, +-0,5A, <2Ohm(0,5A)	BST 80, 2SK601, 2SK1078
27221	2SK1593	100V, +-0,5A, <5Ohm(0,5A)	2SK1079, 2SK1728
27222	2SK1594	<45mOhm(10A)	BUK 545-50, 2SK943, 2SK1214, 2SK1345...46
27223	2SK1595	<0,03Ohm(15A)	2SK1262
27224	2SK1596	<0,02Ohm(20A)	2SK1257, 2SK1653, 2SK1952

27225	2SK16	15V, Idss0,5..7mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK104
27226	2SK160	30V, Idss>0,5mA, Up<4,5V	-
27227	2SK1600	800V, 3A, 75W, <5Ohm(1,5A)	BUK 456-800, 2SK1456, 2SK1638
27228	2SK1601	2SK1600, 900V, <6,4Ohm(1,5A)	BUK 456-1000, 2SK1456, 2SK1638
27229	2SK1602	2SK1600, 2,8A, 40W	2SK1356, 2SK1460
27230	2SK1603	2SK1601, 2,5A, 40W	2SK1356, 2SK1460, 2SK1995
27231	2SK1605	450V, 5A, 50W, <1,3Ohm(3A)	2SK1231...32, 2SK1351, 2SK1626...27
27232	2SK1606	450V, 8A, 50W, <0,75Ohm(4A)	2SK1352, 2SK1566...1567
27233	2SK1607	<0,45Ohm(7A)	BUZ 338, 2SK725, 2SK788, 2SK899, 2SK1745
27234	2SK1608	500V, 5A, 50W, <1,7Ohm(3A)	2SK1232, 2SK1351, 2SK1627
27235	2SK1609	500V, 8A, 50W, <1Ohm(4A)	2SK1352, 2SK1567, 2SK2117
27236	2SK160A	2SK160, 50V	-
27237	2SK161	18V, Idss>1mA, Up<4V	2N5246, 2SK107
27238	2SK1610	<0,6Ohm(7A)	BUZ 338, 2SK725, 2SK788, 2SK899, 2SK1757
27239	2SK1611	800V, 3A, 50W, <4Ohm(2A)	2SK1356, 2SK1460
27240	2SK1612	900V, 3A, 50W, <5Ohm(2A)	2SK1356, 2SK1460
27241	2SK1613	900V, 5A, 120W, <2,8Ohm(3A)	BUZ 380...381, 2SK685, 2SK727
27242	2SK1614	900V, 8A, 120W, <1,7Ohm(4A)	2SK1120, 2SK1358, 2SK1502, 2SK1692
27243	2SK1615	12GHz	-
27244	2SK1616	12GHz	-
27245	2SK1617	12GHz	-
27246	2SK1618	600V, 3A, 30W, <5Ohm(1A)	2SK1624
27247	2SK1619	12GHz	-
27248	2SK162	40V, Idss>5mA, Up<1,2V	2SK147, 2SK151
27249	2SK1620(L,S)	<0,15Ohm(5A)	2SK1636, 2SK1741
27250	2SK1621(L,S)	250V, 7A, 50W, <0,55Ohm(4A)	2SK1636
27251	2SK1622(L,S)	<0,04Ohm(15A)	2SK1918, 2SK2311
27252	2SK1623(L,S)	<0,085Ohm(10A)	-
27253	2SK1624(L,S)	600V, 4A, 50W, <2,4Ohm(2A)	-
27254	2SK1625(L,S)	600V, 7A, 75W, <1,3Ohm(4A)	-
27255	2SK1626	2SK1155, , 35W	2SK1231...32, 2SK1351, 2SK1608
27256	2SK1627	2SK1156, , 35W	2SK1232, 2SK1351, 2SK1608
27257	2SK1628	<0,25Ohm(15A)	2SK1454, 2SK1519...20, 2SK1681, 2SK1629
27258	2SK1629	<0,27Ohm(15A)	2SK1520
27259	2SK163	50V, Idss>1mA, Up<1,2V	2SK43, 2SK121, 2SK170, 2SK186...187
27260	2SK1630	700V, 3A, 75W, <4,4Ohm(2A)	2SK1456, 2SK1600...01, 2SK1638, 2SK1793
27261	2SK1631	2SK1630, , 35W	2SK1356, 2SK1460, 2SK1995
27262	2SK1632	700V, 5A, 100W, <2,3Ohm(3A)	2SK1457, 2SK1501, 2SK1639, 2SK1643
27263	2SK1632S	2SK1632	-
27264	2SK1633	2SK1632, , 45W	2SK1808, 2SK1985
27265	2SK1634	2SK1632, 150W	2SK1341, 2SK1461, 2SK1760, 2SK1794
27266	2SK1635	<23mOhm(25A)	2SK1223, 2SK1380
27267	2SK1636(L,S)	<0,27Ohm(8A)	2SK2063, 2SK2133Z, 2SK2254
27268	2SK1637	600V, 4A, 35W, <2,4Ohm(2A)	2SK1118, 2SK1404
27269	2SK1638	900V, 3A, 60W, <5,5Ohm(2A)	BUK 456-1000, 2SK1456, 2SK1601, 2SK1793

27270	2SK1639	900V, 4A, 75W, <40hm(2A)	2SK1119, 2SK1501, 2SK1639, 2SK1643
27271	2SK1641	<0,230hm(10A)	2SK623, 2SK901, 2SK944, 2SK1673...74
27272	2SK1642	400V, 9A, 45W, <0,550hm(5A)	2SK1446...47, 2SK1609, 2SK2116...17
27273	2SK1643	900V, 5A, 125W, <2,80hm(2A)	2SK1639, 2SK1501
27274	2SK1646	6V, 100mA, Idss>15mA, 12GHz	-
27275	2SK1647(L,S)	900V, 2A, 50W, <70hm(1A)	2SK2005
27276	2SK1648(L,S)	<0,0650hm(8A)	2SK1622, 2SK1918, 2SK2284
27277	2SK1649	900V, 6A, 150W, <2,50hm(3A)	2SK1358, 2SK1502, 2SK1614, 2SK1795
27278	2SK165	15V, Idss>8mA, Up<3V	-
27279	2SK1650	<4,30hm(1,5A)	2SK727, 2SK794, 2SK1461, 2SK1760
27280	2SK1651	500V, 8A, 80W, <10hm(5A)	2SK1206, 2SK1329, 2SK1696, 2SK1832
27281	2SK1651	500V, 8A, 80W, <10hm(5A)	2SK1206, 2SK1329, 2SK1696, 2SK1832
27282	2SK1653	<0,020hm(20A)	2SK1257, 2SK1952, 2SK2120, 2SK2312
27283	2SK1654	250V, 16A	-
27284	2SK1655	300V, 16A	-
27285	2SK1656	0,25W,<250hm(10mA)	BS 170, BSS 98
27286	2SK1657	2SK1657, SMD	BSS 123
27287	2SK1658	2SK1657, SMD	-
27288	2SK1659(L,S)	900V, 3A, 80W, <50hm(1,5A)	2SK1528
27289	2SK1660	450V, 10A, 80W, <0,650hm	2SK1452, 2SK1523, 2SK1696, 2SK1831...32
27290	2SK1661	200V, 20A, 80W, <0,170hm	2SK2107
27291	2SK1662	700V, 3A, 40W, <5,50hm	2SK1356, 2SK1460, 2SK1995
27292	2SK1663(L,S)	800V, 3A, 80W, <40hm(1,5A)	2SK1510, 2SK1528
27293	2SK1664	700V, +-2A, 30W, <60hm(1A)	BUK 446-800, 2SK1142, 2SK1611, 2SK1834
27294	2SK1665	<0,020hm(20A)	BUK 539-60, 2SK1379, 2SK1297, 2SK1514
27295	2SK1666	2SK1665, , 60W	2SK1298, 2SK1653
27296	2SK1667	250V, 7A, 50W, <0,550hm(4A)	2SK741, 2SK1319...20, 2SK1400
27297	2SK1668	2SK1667	2SK1478, 2SK1568...69
27298	2SK1669	<0,0950hm(15A)	-
27299	2SK1670	2SK1669, , 60W	-
27300	2SK1671	<0,0950hm(15A)	2SK902, 2SK1675...76
27301	2SK1672	40/65ns	2SK580, 2SK1152, 2SK1327, 2SK2017
27302	2SK1673	200W,<0,170hm(12A)	-
27303	2SK1674	2SK1673, 300V, <0,20hm(12A)	-
27304	2SK1675	250W,<0,130hm(15A)	-
27305	2SK1676	<0,150hm(15A)	-
27306	2SK1677	200W,<0,390hm(8A)	2SK1409, 2SK1411
27307	2SK1678	2SK1677, 500V, <0,470hm(8A)	2SK1411
27308	2SK1679	250W,<0,30hm(10A)	2SK1409, 2SK1411
27309	2SK168	30V, Idss>4mA, Up<3V	BF 410C
27310	2SK1680	<0,350hm(10A)	2SK1411
27311	2SK1681	<0,230hm(15A)	2SK1520, 2SK1629, 2SK1971
27312	2SK1682	30V, Idss1..12mA, Up<4V	2SK374
27313	2SK1683	2SK1536, , 50W	2SK1463
27314	2SK1684	2SK1537, , 55W	2SK1463

27315	2SK1685	2SK1538, , 65W	2SK1464, 2SK1775
27316	2SK1686	2SK1539, , 70W	-
27317	2SK1687	4V, 60mA, 12GHz	-
27318	2SK1688	4V, 60mA, 12GHz	-
27319	2SK1689	6V, 70mA, 12GHz	-
27320	2SK169	15V, 50mA, Idss<50mA	-
27321	2SK1690	450V, 3A, 50W, <2,6Ohm(1,5A)	2SK1691
27322	2SK1691	450V, 5A, 60W, <1,4Ohm(3A)	-
27323	2SK1692	900V, 7A, 150W, <2Ohm(3,5A)	2SK1342, 2SK1358, 2SK1614, 2SK1795
27324	2SK1693	60/120ns	IRF 840, IRF 842, 2SK1496, 2SK1574
27325	2SK1694	2SK1693, , 35W	2SK1352, 2SK1567, 2SK1609, 2SK1805
27326	2SK1694	2SK1693, , 35W	2SK1352, 2SK1567, 2SK1609, 2SK1805
27327	2SK1695	60/120ns	2SK724, 2SK896, 2SK1488, 2SK1753
27328	2SK1696	2SK1695, , 50W	2SK1206, 2SK1329, 2SK1523
27329	2SK1697	60V, 0,5A,<1,7Ohm(0,3A)	2SK1079
27330	2SK1698	100V, 0,3A,<4,5Ohm(0,2A)	2SK1079
27331	2SK1699	450V, 5A, 75W, <1,8Ohm(3A)	BUZ 41A...42, 2SK893, 2SK1246, 2SK1751
27332	2SK1699S	2SK1699	-
27333	2SK17	20V, Idss0,3..6,5mA, Up<6V	BFS 70, 2N3369, 2N3821, 2SK381
27334	2SK170	40V, Idss>1mA, Up<1,5V	2SK43, 2SK121, 2SK163, 2SK186...187
27335	2SK1700	2SK1699, , 35W	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
27336	2SK1701	450V, 8A	-
27337	2SK1702	450V, 8A	2SK1352, 2SK1566...67, 2SK2116...17
27338	2SK1703	500V, 5A, 75W, <2,4Ohm(3A)	BUZ 41A...42, 2SK893, 2SK1246, 2SK1751
27339	2SK1703S	2SK1703	-
27340	2SK1704	2SK1703, , 35W	2SK1232, 2SK1351, 2SK1608, 2SK1627
27341	2SK1705	500V, 8A	-
27342	2SK1706	500V, 8A	2SK1352, 2SK1566...67, 2SK2116...17
27343	2SK1707	600V, 4A	-
27344	2SK1708	600V, 4A	2SK1404, 2SK1637, 2SK2044, 2SK2118
27345	2SK1709	600V, 6A	-
27346	2SK1710	600V, 6A	-
27347	2SK1711	<0,2Ohm(5A)	2SK1033, 2SK1093, 2SK1256, 2SK1895
27348	2SK1712	<0,1Ohm(8A)	2SK1094, 2SK1286, 2SK1419, 2SK1896
27349	2SK1713	<50mOhm(12A)	2SK1095, 2SK1346, 2SK1882, 2SK2346
27350	2SK1714	<28mOhm(15A)	2SK1421, 2SK1653, 2SK2120, 2SK2529
27351	2SK1715	<28mOhm(20A)	2SK1298, 2SK1424, 2SK1660, 2SK2203
27352	2SK1716	60V, 2A, 20W, <0,37Ohm(1A)	BUK 541-100, 2SK1255
27353	2SK1717	2SK1716, SMD	2SK1273, 2SK1311, 2SK1470, 2SK2315
27354	2SK1718	60V, 6A, 25W, <0,11Ohm(3A)	BUK541-60, BUK542-100, 2SK1255, 2SK1260
27355	2SK1719	60V, 5A, 20W,<0,11Ohm(2,5A)	2SK1112, 2SK1804, 2SK1949
27356	2SK1720	<0,03Ohm(25A)	2SK1792, 2SK1919, 2SK2164, 2SK2266
27357	2SK1721	30/80ns	2SK1314, 2SK1541, 2SK2066, 2SK2181
27358	2SK1722	500V, 5A, 60W, <1,5Ohm(2,5A)	2SK1316, 2SK2067, 2SK2184
27359	2SK1723	<0,65Ohm(6A)	2SK1968

27360	2SK1724	2SK1725, SMD	2SK1485, 2SK1726
27361	2SK1725	30V, 1A, 1W, <0,75Ohm(0,5A)	2SK1727, 2SK1733
27362	2SK1726	2SK1727, SMD, 1A	2SK1485, 2SK1728
27363	2SK1727	60V, 0,8A, 1W, <1,2Ohm(0,4A)	2SK1729, 2SK1733
27364	2SK1728	2SK1729, SMD, 1A	2SK1334, 2SKJ1485
27365	2SK1729	100V, 0,5A, <3,5Ohm(0,25A)	2SK2085
27366	2SK173	210V, 10A, 95W	BUZ 35, 2SK401
27367	2SK1730	30V, 1,8A, 1W, <0,3Ohm(1A)	2SK1470, 2SK1717, 2SK1733
27368	2SK1731	30V, 3A, <0,14Ohm(1,5A)	2SK1735
27369	2SK1732	30V, 4,5A, <0,065Ohm(2,5A)	2SK1735
27370	2SK1733	60V, 1,5A, <0,45Ohm(0,75A)	2SK1736
27371	2SK1734	60V, 2,5A, <0,22Ohm(1,5A)	2SK1738
27372	2SK1735	60V, 4A, <0,09Ohm(2A)	-
27373	2SK1736	100V, 1A, <0,95Ohm(0,5A)	2SK2085
27374	2SK1737	100V, 1,8A, <0,4Ohm(1A)	-
27375	2SK1738	100V, 3A, <0,17Ohm(1,5A)	-
27376	2SK1740	Up<5V	-
27377	2SK1741	<0,16Ohm(6A)	2SK1620, 2SK1636
27378	2SK1745	<0,36Ohm(9A)	2SK870, 2SK1170, 2SK1498, 2SK1500
27379	2SK1746	23/80ns	2SK1624, 2SK1980
27380	2SK1748(Z)	<0,11Ohm(4A)	2SK1472, 2SK2415
27381	2SK1749	<18mOhm(25A)	BUK539-60, 2SK1258, 2SK1379, 2SK2121
27382	2SK175	<1,7Ohm	2SK258, BUZ 33
27383	2SK1750	<1,4Ohm(2,5A)	BUZ 41A...42, 2SK552...53, 2SK893, 2SK1246
27384	2SK1750Z..1751Z	2SK1750..51	-
27385	2SK1751	2SK1750, 500V, <1,5Ohm(2,5A)	BUZ 41...42, 2SK553, 2SK893, 2SK1246
27386	2SK1752	<0,9Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1785
27387	2SK1753	2SK1752, 500V, <1Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1785
27388	2SK1754	50V, 10A, 45W, <0,09Ohm(5A)	2SK2414
27389	2SK1756	<0,5Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27390	2SK1757	2SK1756, 500V, <0,6Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27391	2SK1758	<4,2Ohm(1A)	BUK 445-600, 2SK1142, 2SK1834
27392	2SK176	2SK175, 200V	2SK258, BUZ 33
27393	2SK1760	900V, +-5A, 100W, <4Ohm(3A)	2SK727, 2SK1341, 2SK1649...50, 2SK1794
27394	2SK1761	<0,35Ohm(6A)	-
27395	2SK1762	2SK1761, , 35W	-
27396	2SK1763(L,S)	30V, 2,5A, 10W, <0,35Ohm	2SK974, 2SK1282
27397	2SK1764	60V, 2A, <0,45Ohm(1A)	2SK1311, 2SK1470, 2SK1717, 2SK2054
27398	2SK1766	250V, 10A, 40W, <0,6Ohm(5A)	2SK1036, 2SK1762, 2SK2011, 2SK2426
27399	2SK1767	<2,5Ohm(2,5A)	2SK1572, 2SK2144
27400	2SK1768	60V, 12A, 15W, <0,07Ohm(6A)	-
27401	2SK1769	600V, 2A, 15W, <4Ohm(1A)	-
27402	2SK1770	2SK1205, , 60W	-
27403	2SK1771	12,5V, 30mA	-
27404	2SK1772	30V, 1A, <0,6Ohm(0,5A)	2SK1485, 2SK1726, 2SK1728



27405	2SK1773	1000V, 5A, 100W, <2Ohm(3A)	BUZ 357...358, 2SK1120, 2SK1205, 2SK1359
27406	2SK1774	2SK684, , 60W	2SK1464, 2SK1685
27407	2SK1775	2SK1342, , 60W	2SK1464, 2SK1685...86
27408	2SK1776	60V, 10A, 20W, <0,15Ohm(5A)	-
27409	2SK1777	60V, 15A, 25W, <65mOhm(8A)	-
27410	2SK1778	80V, 10A, 25W, <25mOhm(5A)	-
27411	2SK1779	800V, 3A, 80W, <3,5Ohm	2SK1510, 2SK1659
27412	2SK1784	<0,6Ohm(6A)	2SK644, 2SK724, 2SK1488, 2SK1723
27413	2SK1785	2SK1784, 500V, <0,7Ohm(6A)	2SK644, 2SK724, 2SK1488, 2SK1723
27414	2SK1792	<20mOhm(20A)	2SK1919, 2SK2164, 2SK2266, 2SK2376
27415	2SK1793	<7,5Ohm(2A)	BUK 456-1000, 2SK1456, 2SK1601, 2SK1638
27416	2SK1793Z	2SK1793	2SK1510
27417	2SK1794	<2,8Ohm(3A)	2SK1358, 2SK1614, 2SK1502, 2SK1692
27418	2SK1795	<1,6Ohm(4A)	2SK1358, 2SK1614, 2SK1502, 2SK1692
27419	2SK1796	<1,2Ohm(5A)	2SK1933
27420	2SK180	600V, 20A, 300W, 200/250ns	-
27421	2SK1803	900V, 8A, 100W, <1,7Ohm(4A)	2SK1358, 2SK1614, 2SK1502, 2SK1692
27422	2SK1804	20W, <0,28Ohm(2,5A)	2SK1474
27423	2SK1805	500V, 7A, 45W, <0,85Ohm(4A)	2SK1352, 2SK1567, 2SK1609
27424	2SK1807	900V, 4A, 60W, <4Ohm(2A)	2SK1639, 2SK1643, 2SK1501
27425	2SK1808	2SK1807, , 35W	2SK1985
27426	2SK1809	2SK1404, 60W	2SK1117, 2SK1402
27427	2SK181	2SK180, 800V	-
27428	2SK1810	75/100ns	BUZ 61, 2SK1378
27429	2SK1811	100W, <0,35Ohm, 140/160ns	2SK868, 2SK1674
27430	2SK1812	120W, <0,23Ohm, 190/240ns	2SK1676
27431	2SK1813	<0,55Ohm(20A)	-
27432	2SK1814	<70mOhm(10A)	BUK 555-60, 2SK972, 2SK1115, 2SK1296
27433	2SK1815	<35mOhm(17,5A)	2SK1424, 2SK1435...36, 2SK1666
27434	2SK1816	100V, 5A, 20W	-
27435	2SK1817	<80mOhm(10A)	2SK1292, 2SK1307, 2SK1348...49, 2SK1906
27436	2SK1818(-MR)	<0,25Ohm(10A)	-
27437	2SK1819(-MR)	450V, 5A, 35W, <1,5Ohm(2,5A)	2SK1231...32, 2SK1608, 2SK2114...15
27438	2SK1820(-01)L,S	500V, 6A, 80W, <1,6Ohm(3A)	2SK1314, 2SK1703S, 2SK2365Z
27439	2SK1821(-1M)	600V, 2A, 30W, <6,5Ohm(1A)	BUK 445-600, 2SK1142, 2SK1384, 2SK1953
27440	2SK1822(-01MR)	<0,07Ohm(10A)	2SK943, 2SK1214, 2SK1290, 2SK1345...46
27441	2SK1823(-01R)	<17mOhm(25A)	2SK1298, 2SK1653, 2SK1666, 2SK2203
27442	2SK1824	30V, +-0,1A, <8Ohm(10mA)	-
27443	2SK1825	50V, 0,05A, <50Ohm(10mA)	-
27444	2SK1826	2SK1825, SMD	-
27445	2SK1827	2SK1825, SMD	-
27446	2SK1828	20V, 0,05A, <40Ohm(10mA)	-
27447	2SK1829	2SK1828	-
27448	2SK1830	2SK1828	-
27449	2SK1831	2SK1161, , 50W	2SK1225, 2SK1206, 2SK1328...29, 2SK1696

27450	2SK1832	2SK1162, , 50W	2SK1206, 2SK1329, 2SK1523, 2SK1696
27451	2SK1833	500V, 2,5A, 40W, <4Ohm(1,5A)	BUK 444-500, 2SK1758
27452	2SK1834	35/85ns	BUK 446-800, 2SK1142, 2SK1459, 2SK1611
27453	2SK1835	1500V, 4A, 125W, <7Ohm(2A)	-
27454	2SK1836	<0,1Ohm(25A)	2SK1521...22
27455	2SK1837	<0,11Ohm(25A)	2SK1522
27456	2SK1838(L,S)	250V, 1A, 10W, <8Ohm(0,5A)	2SK945, 2SK1195
27457	2SK1839	2SK1841, SMD	-
27458	2SK184	50V, Idss>0,6mA, Up<1,5V	2SK68, 2SK106
27459	2SK1840	2SK1841, SMD	2SK1590
27460	2SK1841	0,2W,<25Ohm(10mA)	2SK1398
27461	2SK1842	40V, Idss>30μA, Up<3V	-
27462	2SK1846	40/140ns	2SK1528, 2SK2005
27463	2SK1847	30V, 0,5A, <0,75Ohm(250mA)	-
27464	2SK1848	60V, 0,4A, <1,2Ohm(0,2A)	-
27465	2SK1849	100V, 0,25A, <3,5Ohm(0,15A)	-
27466	2SK1850	60V, +-10A, <0,07Ohm(5A)	-
27467	2SK1851	60V, +-15A, <45mOhm(8A)	-
27468	2SK1852	100V, +-10A, <0,15Ohm(5A)	-
27469	2SK1853	100V, +-15A, <0,08Ohm(8A)	-
27470	2SK1854	400V, 6A, 40W, <1Ohm(2,5A)	2SK1231, 2SK1351, 2SK1608, 2SK1627
27471	2SK1855	<0,7Ohm(6A)	2SK896, 2SK1488, 2SK1753, 2SK1785
27472	2SK1856	500V, 15A, 150W, <0,5Ohm	2SK899, 2SK1610, 2SK1745, 2SK1757
27473	2SK1858	800V, 3A, 60W, <5Ohm(1,5A)	2SK1510, 2SK1528, 2SK1659, 2SK1858
27474	2SK1859	2SK1341, , 60W	2SK1464, 2SK1684...85, 2SK1775
27475	2SK186	40V, Idss>1,6mA, Up<1,5V	2SK187, 2SK364, 2SK366
27476	2SK1861	150V, 4A, 10W, <0,6Ohm(2A)	-
27477	2SK1862	2SK1153, , 25W	BUK 445-450...-500, 2SK1572, 2SK1767
27478	2SK1863	2SK1154, , 25W	BUK 445-500, 2SK1572, 2SK1767
27479	2SK1864	<0,85Ohm(4A)	2SK1316, 2SK2187, 2SK2360-Z
27480	2SK1865	<0,07Ohm(6A)	2SK2366Z
27481	2SK1867	900V, 2A, 15W, <4,85Ohm(2A)	2SK1143, 2SK1275, 2SK1459
27482	2SK1868	60V, 3A, 15W, <0,2Ohm(3A)	BUK 541-60, 2SK1255
27483	2SK1869(L,S)(A)	2SK1400, 50W	-
27484	2SK187	40V, Idss>2,5mA, Up<1,5V	2SK186, 2SK364, 2SK366
27485	2SK1871	<80mOhm(10A)	2SK1648, 2SK1898, 2SK2322
27486	2SK1872	<40mOhm(12A)	2SK943, 2SK1290, 2SK1420, 2SK1346
27487	2SK1875	2SK709, SMD	-
27488	2SK1876	450V, 10A, 80W, <0,65Ohm	2SK1442, 2SK2365...66
27489	2SK1877	60V, 10A, 12W, <75mOhm(5A)	-
27490	2SK1878	<0,14Ohm(5A)	-
27491	2SK1879	<0,03Ohm(25A)	BUK 439-60, 2SK849, 2SK857, 2SK1379
27492	2SK1880(L,S)	600V, 1,5A, 20W, <8Ohm(1A)	2SK1327
27493	2SK1881(L,S)	<0,07Ohm(10A)	2SK1918
27494	2SK1882	60V, 25A, 40W,<0,05Ohm(12A)	2SK943, 2SK1095, 2SK1214, 2SK1345

27495	2SK1883	<0,055Ohm(9A)	2SK942, 2SK972, 2SK1115, 2SK1910
27496	2SK1884	<0,04Ohm(11A)	2SK942, 2SK972, 2SK1115, 2SK1910
27497	2SK1885	<25mOhm(18A)	2SK1291, 2SK1296
27498	2SK1886	30V, 15A, 25W, <55mOhm(9A)	2SK1094, 2SK1286
27499	2SK1887	<40mOhm(11A)	2SK943, 2SK1290, 2SK1345, 2SK1348...49
27500	2SK1888	<25mOhm(18A)	2SK943, 2SK1290, 2SK1345, 2SK1348...49
27501	2SK1889	30V, 18A, 50W, <55mOhm(9A)	2SK1648, 2SK1898
27502	2SK1890	<40mOhm(11A)	2SK1622
27503	2SK1891	<25mOhm(18A)	2SK1900
27504	2SK1892	60V, 15A, 50W, <80mOhm(8A)	BUK 552-60, 2SK942, 2SK1115...16, 2SK1347
27505	2SK1893	60V, 18A, 60W, <70mOhm(9A)	BUK 552-60, 2SK942, 2SK1115...16, 2SK1347
27506	2SK1894	<40mOhm(15A)	2SK1291, 2SK1296
27507	2SK1895	60V, 12A, 25W, <80mOhm(8A)	2SK1093, 2SK1256, 2SK1305...06, 2SK1344
27508	2SK1896	60V, 15A, 25W, <70mOhm(9A)	2SK943, 2SK1214, 2SK1345
27509	2SK1897	<0,04Ohm(15A)	2SK943, 2SK1095, 2SK1214, 2SK1345
27510	2SK1898	60V, 15A, 50W, <80mOhm(8A)	2SK1648
27511	2SK1899	60V, 18A, 60W, <70mOhm(9A)	2SK1622
27512	2SK19(TM)	18V, Idss3..24mA, Up3V	BFS 71, BFS 80, BFW 11, 2N3822, 2N4416
27513	2SK190	40V, 0,2A, Idss>6mA, Up<1,5V	-
27514	2SK1900	<40mOhm(15A)	-
27515	2SK1901	<0,16Ohm(6A)	2SK1300...01, 2SK1559, 2SK1561
27516	2SK1902	<135mOhm(7A)	2SK1301, 2SK1559, 2SK1561
27517	2SK1903	<80mOhm(12A)	2SK1116, 2SK1302, 2SK1347
27518	2SK1904	<0,16Ohm(6A)	BUK 545-100, 2SK1305, 2SK1035
27519	2SK1905	<135mOhm(7A)	2SK1034, 2SK1288, 2SK1306
27520	2SK1906	30W,<0,08Ohm(12A)	2SK1292, 2SK1307, 2SK1348...49
27521	2SK1907	<0,16Ohm(6A)	2SK1623
27522	2SK1908	<135mOhm(7A)	2SK1623
27523	2SK1909	<80mOhm(12A)	-
27524	2SK191	15V, 0,5A, Idss>10mA, Up<3V	-
27525	2SK1910	<0,04Ohm(15A)	2SK942, 2SK972, 2SK1115
27526	2SK1911	<22mOhm(20A)	BUK 556-60, 2SK1542
27527	2SK1913	600V, 4A, 40W, <1,8Ohm(2,5A)	2SK1118, 2SK1637, 2SK2045, 2SK2097
27528	2SK1914	<6,5Ohm(0,75A)	-
27529	2SK1915	<1,25Ohm(3A)	2SK1624, 2SK2089
27530	2SK1916(-01R)	<0,45Ohm(8A)	2SK1406, 2SK1453, 2SK1525
27531	2SK1917-M(-MR)	250V, 10A, 50W, <0,4Ohm(5A)	2SK526, 2SK1036, 2SK2011, 2SK2436
27532	2SK1918(L,S)	2SK1910	2SK1622, 2SK2311
27533	2SK1919(L,S)	2SK1911	2SK1792, 2SK2164, 2SK2266
27534	2SK192(A)	18V, Idss>3mA, Up<3V	BF 410B...C
27535	2SK1920	250V, 4A, 30W, <0,7Ohm(2A)	-
27536	2SK1921	250V, 4A, 50W, <0,7Ohm(2A)	2SK477, 2SK741, 2SK924, 2SK1391
27537	2SK1922	600V, 2A, 50W, <4,3Ohm(1A)	BUZ 80, 2SK858, 2SK1323...24
27538	2SK1923	600V, 4A, 60W, <1,8Ohm(2A)	2SK1402, 2SK1501, 2SK1639, 2SK1643
27539	2SK1924	600V, 6A, 70W, <1,5Ohm(3A)	2SK1117, 2SK1643

27540	2SK1925	600V, 8A, 120W, <1,2Ohm(4A)	BUZ 332A, 2SK1032
27541	2SK1926	60V, 15A, 50W, <0,1Ohm	2SK943, 2SK1214, 2SK1345
27542	2SK1927	<0,18Ohm(8A)	2SK1623, 2SK1909
27543	2SK1928	<85mOhm(15A)	2SK1813
27544	2SK1929	900V, 5A, 100W, <2,8Ohm(2A)	2SK1528, 2SK2006
27545	2SK193	20V, Idss>0,5mA, Up<2,5V	BF 410A, 2SK195, 2SK212
27546	2SK1930	1000V, 4A, 80W, <3,8Ohm(2A)	2SK2004
27547	2SK1931	<0,65Ohm(2,5A)	2SK1920, 2SK2099
27548	2SK1933	<1,2Ohm(5A)	2SK1796
27549	2SK1934	<1,6Ohm(4A)	2SK1120
27550	2SK1936-01	<0,76Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1785
27551	2SK1937-01	<0,48Ohm(7,5A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27552	2SK1938-01(-01R)	<0,35Ohm(9A)	2SK1406, 2SK1525
27553	2SK1939-01	600V, 8A, 100W, <1,2Ohm(4A)	BUZ 332A, 2SK1032
27554	2SK1940-01	<0,75Ohm(6A)	BUZ 334, 2SK1723
27555	2SK1941-01	<0,55Ohm(8A)	2SK1405
27556	2SK1942-01	900V, 3A, 80W, <4Ohm(1,5A)	2SK696, 2SK726...727, 2SK794, 2SK1341
27557	2SK1943-01	900V, 5A, 80W, <2,8Ohm(2,5A)	2SK1457, 2SK1501, 2SK1639, 2SK1643
27558	2SK1944-01	<2,8Ohm(2,5A)	2SK727, 2SK794, 2SK1341, 2SK1760
27559	2SK1945-01	900V, 5A, 80W, <2,8Ohm(2,5A)	2SK1463, 2SK1684, 2SK1859
27560	01M(MR)	<22mOhm(22,5A)	2SK1257, 2SK1653, 2SK1952, 2SK2120
27561	2SK1947	<60mOhm(25A)	-
27562	2SK1948	<60mOhm(25A)	-
27563	2SK1949(L,S)	60V, 5A, 20W, <0,15Ohm(3A)	2SK1112, 2SK1471, 2SK1719
27564	2SK195	20V, Idss>0,5mA, Up<2,5V	BF 410A, 2SK193, 2SK212, 2SK606
27565	2SK1950(L,S)	60V, 3A, 10W, <0,23Ohm(2A)	2SK974, 2SK1282, 2SK1254, 2SK1299
27566	2SK1951	2SK1910, , 35W	2SK943, 2SK1095, 2SK1345...46, 2SK1307
27567	2SK1952	2SK1911, , 35W	2SK1257, 2SK1653
27568	2SK1953	600V, +-2A, 25W, <5Ohm(1A)	BUK 445-600, 2SK1142, 2SK1834
27569	2SK1954(Z)	<0,65Ohm(2A)	2SK1920
27570	2SK1957	200V, 7A, 30W, <0,45Ohm(4A)	BUK 545-200, 2SK1568...69, 2SK1668
27571	2SK1958	16V, +-0,1A, <12Ohm(10m)	-
27572	2SK1959	16V, +-2A, <0,5Ohm(1A)	2SK1311, 2SK1470, 2SK1717
27573	2SK196	20/30ns	BSS 93
27574	2SK1960	16V, +-3A, <0,2Ohm(1,5A)	2SK2054
27575	2SK1961	15V, Idss40..75mA, Up<4,5V	-
27576	2SK1962	4V, 60mA, Idss>12mA, 12GHz	-
27577	2SK1963	4V, 60mA, Idss>12mA, 12GHz	-
27578	2SK1964	4V, 60mA, Idss>12mA, 12GHz	-
27579	2SK1967	<0,07Ohm(10A)	2SK1622, 2SK1918
27580	2SK1968	<0,88Ohm(6A)	BUZ 334, 2SK1723
27581	2SK1969-01	<17mOhm(25A)	BUK 539-60, 2SK1258, 2SK1379...80
27582	2SK197	18V, Idss>2mA, Up<4V	2SK210, 2SK217
27583	2SK1971	<0,23Ohm(18A)	2SK1520, 2SK1629
27584	2SK1973(F5)	60V, 2A, 20W, <0,35Ohm(1A)	2SK462, 2SK973, 2SK1763

27585	2SK1974	60V, 10A, 30W, <0,35Ohm(1A)	BUK 442-60, 2SK1093, 2SK1256, 2SK1344
27586	2SK1975	<0,35Ohm(1A)	2SK724, 2SK899, 2SK1488, 2SK1757
27587	2SK1976	450V, 5A, 30W, <1,4Ohm(1A)	2SK1231...32, 2SK1608, 2SK1626...27
27588	2SK198	30V, 20mA, Idss>0,5mA	-
27589	2SK1981-01	<0,76Ohm(5A)	2SK1503, 2SK2366
27590	01M(MR)	2SK1981, , 50W	-
27591	2SK1983-01	900V, 3A, 60W, <4Ohm(1,5A)	BUK 456-1000, 2SK1601, 2SK1638, 2SK1793
27592	01M(MR)	2SK1983	2SK1356, 2SK1460, 2SK1995
27593	01M(MR)	900V, 5A, 50W, <2,8Ohm(2,5A)	2SK1808
27594	2SK1986-01	1000V, 4A, 80W, <3,6Ohm(2A)	2SK1119
27595	2SK1987	<0,5Ohm(4A)	2SK1478, 2SK1568...69, 2SK1668
27596	2SK1988	<2,8Ohm(1,5A)	BUK 444-450, 2SK1833
27597	2SK1989	2SK1988, 500V, <3Ohm(1,5A)	BUK 444-500, 2SK1833
27598	2SK199	15V, Idss<12mA	-
27599	2SK1990	<1,4Ohm(2,5A)	2SK1351, 2SK1445, 2SK1608, 2SK1626...27
27600	2SK1991	2SK1990, 500V, <1,5Ohm(2,5A)	2SK1351, 2SK1232, 2SK1608, 2SK1627
27601	2SK1992	<0,9Ohm(3A)	2SK1352, 2SK1566...67, 2SK1609, 2SK1805
27602	2SK1993	2SK1992, 500V, <1Ohm(3A)	2SK1352, 2SK1567, 2SK1609, 2SK1805
27603	2SK1994	<7,5Ohm(1A)	2SK1143, 2SK1174, 2SK1275
27604	2SK1995	900V, +-3A, 35W, <4Ohm(2A)	2SK1356, 2SK1460
27605	2SK1996	12GHz	-
27606	2SK1997	<0,03Ohm(18A)	2SK1257, 2SK1653, 2SK1952, 2SK2120
27607	2SK2000-R	100V, 32A, 80W, <0,06Ohm	2SK1149, 2SK1435...36
27608	01M(MR)	600V, 3A, 30W, <4,5Ohm(1,5A)	2SK1572, 2SK2144
27609	01M(MR)	600V, 4A, 40W, <2,4Ohm(2A)	2SK1118, 2SK2044, 2SK2097, 2SK2118
27610	2SK2004-01L,S	1000V, 4A, 80W, <3,6Ohm(2A)	-
27611	2SK2005	900V, 3A, 50W, <5Ohm(1,5A)	2SK1510, 2SK1659, 2SK2029
27612	2SK2006	900V, 5A, 65W, <3Ohm(2,5A)	2SK1501-Z, 2SK1528
27613	2SK2007	<0,15Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK2058
27614	2SK2008	2SK2007, , 60W	2SK1406, 2SK1525, 2SK1670
27615	2SK2009	30V, 0,2A, <2Ohm(50mA)	-
27616	2SK201	10V, 400mA, 8GHz	-
27617	2SK2010	250V, 4A, 25W, <0,7Ohm(2A)	2SK1478, 2SK1568...69, 2SK1668, 2SK1987
27618	2SK2011	<0,35Ohm(6A)	2SK1036, 2SK1762
27619	2SK2012	<0,16Ohm(12A)	2SK2255
27620	2SK2013	180V, 1A, 25W	2SK528...529, 2SK1443
27621	2SK2014	<0,95Ohm(0,5A)	-
27622	2SK2015	150V, 3A, 10W, <1,1Ohm(2A)	-
27623	2SK2016	100V, 5A, 10W, <0,47Ohm(3A)	2SK1474, 2SK1804
27624	2SK2017	550V, 1A, 10W, <8Ohm(0,6A)	2SK1327, 2SK1880
27625	2SK2018-01(L,S)	60V, 10A, 20W, <0,1Ohm(5A)	2SK2414
27626	2SK2019-01	500V, 3,5A, 40W, <3Ohm(1,5A)	2SK1154, 2SK1244
27627	01M(MR)	2SK2019, , 30W	BUK 445-500, 2SK1572, 2SK1767, 2SK2144
27628	2SK2021-01	500V, 5A, 60W, <1,6Ohm(2,5A)	BUZ 41A...42, 2SK553, 2SK893, 2SK1246
27629	01M(MR)	2SK2021, , 40W	2SK1351, 2SK1608, 2SK1627, 2SK2115



27630	2SK2023-01	600V, 3A, 50W, <4,5Ohm(1,5A)	BUK 456-800, 2SK1600
27631	2SK2024-01	2SK2023	BUZ 307, BUZ 360...361, 2SK603
27632	2SK2025-01	600V, 4A, 60W, <2,4Ohm(2A)	BUZ 90, 2SK1117, 2SK1402, 2SK1809
27633	2SK2026-01	2SK2025	2SK695, 2SK793, 2SK1213, 2SK1403
27634	2SK2027-01	600V, 8A, 80W, <1,2Ohm(4A)	BUK 657-600, BUZ 91, BUZ 305
27635	01M(MR)	2SK2027, , 50W	-
27636	2SK2029-01(L,S)	900V, 3A, 60W, <4Ohm(1,5A)	2SK1510, 2SK1528
27637	2SK203	10V, 180mA, 8GHz	-
27638	2SK2030	60V, 5A, 20W, <0,14Ohm(2,5A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
27639	2SK2032	<0,45Ohm(7A)	2SK899, 2SK1678, 2SK1745, 2SK1757
27640	2SK2033	20V, 0,1A, <12Ohm(10mA)	-
27641	2SK2034	2SK2033	-
27642	2SK2035	2SK2033	-
27643	2SK2036	20V, 0,1A, <6Ohm(10mA)	-
27644	2SK2037	2SK2036	-
27645	2SK2038	800V, 5A, 125W, <2,2Ohm(3A)	2SK727, 2SK1341, 2SK1649...50, 2SK1794
27646	2SK2039	900V, 5A, 150W, <2,5Ohm(3A)	2SK727, 2SK1341, 2SK1649...50, 2SK1794
27647	2SK2040(Z)	900V, +-2A, 20W, <5Ohm(1A)	-
27648	2SK2041	60V, 10A, 60W, <95mOhm(5A)	2SK1907
27649	2SK2042	450V, 5A, 60W, <1,4Ohm(2,5A)	2SK1691
27650	2SK2043(LS)	600V, 2A, 25W, <4,3Ohm(1A)	BUK 445-600, 2SK1142, 2SK1834
27651	2SK2044(LS)	600V, 4A, 30W, <2,4Ohm(2A)	2SK1118, 2SK1404, 2SK1637
27652	2SK2045(LS)	600V, 5,5A, 35W, <1,5Ohm(3A)	2SK1118, 2SK1404
27653	2SK2046	30V, 12A, 30W, <0,05Ohm(4A)	2SK1754, 2SK2018, 2SK2414
27654	2SK2047	550V, 1,2A, 15W, <8Ohm(0,6A)	-
27655	2SK2048(-01)L,S	<22mOhm(17,5A)	2SK1919, 2SK2164, 2SK2266, 2SK2376
27656	2SK2049	<25mOhm(25A)	BUK 556-60, 2SK1542
27657	2SK2050	<55mOhm(15A)	2SK1293, 2SK2314
27658	2SK2051(-01)L,S	250V, 10A, 80W, <0,4Ohm(5A)	2SK1636, 2SK2133-Z, 2SK2254
27659	2SK2052(-R)	500V, 10A, 80W, <1,1Ohm(5A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
27660	2SK2053	16V, +-5A, <0,12Ohm(2,5A)	-
27661	2SK2054	60V, +-3A, <0,2Ohm(1,5A)	-
27662	2SK2055	100V, +-2A, <0,35Ohm(1A)	2SK1473
27663	2SK2056	800V, 4A, 40W, <2,4Ohm(2A)	2SK1808, 2SK1985, 2SK2044, 2SK2118
27664	2SK2057	<0,31Ohm(12A)	2SK1170, 2SK1411, 2SK1500, 2SK1680
27665	2SK2058	120W, <0,16Ohm(12A)	2SK901, 2SK944, 2SK1641, 2SK1673...74
27666	2SK2059(L,S)	600V, 3A, 20W, <5Ohm(2A)	-
27667	2SK2062	250V, 10A, 50W, <0,5Ohm(5A)	2SK1636, 2SA2133-Z, 2SK2254
27668	2SK2063	<0,25Ohm(10A)	2SK2254
27669	2SK2064	300V, 10A, 50W, <0,7Ohm(5A)	-
27670	2SK2065	300V, 20A, 60W, <0,35Ohm	-
27671	2SK2066	45/75ns	2SK1314, 2SK1721
27672	2SK2067	50/90ns	2SK1314, 2SK1541, 2SK1722, 2SK2356Z
27673	2SK2068	60/120ns	2SK1316, 2SK1541, 2SK2187, 2SK2360-Z
27674	2SK2069	70/143ns	2SK2187, 2SK2366Z



27675	2SK2070	100V, +-1,5A, <0,35Ohm(1A)	-
27676	2SK2071-01(L,S)	600V, 2A, 20W, <6,5Ohm(1A)	-
27677	2SK2072-01(L,S)	800V, 6A, 80W, <2,1Ohm(3A)	-
27678	2SK2073	2SK2074, SMD	-
27679	2SK2074	15V, Idss>6mA, Up<1,2V	-
27680	2SK2075	<0,13Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK2007
27681	2SK2077	<1,7Ohm(3,5A)	2SK1342, 2SK1358, 2SK1502, 2SK1795
27682	2SK2078	800V, 9A, 150W, <1,2Ohm(4A)	2SK1796, 2SK1933
27683	2SK208	50V, Idss>0,3mA, Up<5V	-
27684	2SK2080-01(R)	<0,55Ohm(8A)	2SK1269, 2SK1331, 2SK1405, 2SK1524
27685	2SK2081-01	<0,6Ohm(6A)	BUZ 339, 2SK1610, 2SK1745, 2SK1785
27686	2SK2082-01	<1,4Ohm(4,5A)	2SK1358, 2SK1614, 2SK1502, 2SK1692
27687	2SK2083	900V, 5A, 70W, <3,6Ohm(2A)	2SK1528
27688	2SK2084(L,S)	20V, 7A, 20W, <53mOhm(4A)	2SK1472, 2SK1748
27689	2SK2085	100V, 1A, 0,9W, <0,9Ohm(0,5A)	2SK1736
27690	2SK2085	100V, 1A, 0,9W, <0,9Ohm(0,5A)	2SK1736
27691	2SK2088	200V, 10A, 60W, <0,4Ohm(5A)	2SK1636, 2SK2133-Z, 2SK2254
27692	2SK2089	800V, 5A, 100W, <2,4Ohm(3A)	2SK1528
27693	2SK209	50V, Idss>0,6mA, Up<1,5V	2SK94, 2SK425
27694	2SK2090	50V, +-0,1A, <20Ohm(10mA)	-
27695	2SK2091	2SK2076	-
27696	2SK2094(L,S)	60V, 2A, 20W, <0,35Ohm(1A)	2SK973, 2SK1763
27697	2SK2095(N)	60V, 10A, 30W, <95mOhm(5A)	2SK1093, 2SK1256, 2SK1305...06, 2SK1344
27698	2SK2096	100W, <22mOhm(25A)	2SK1297, 2SK1514, 2SK1665
27699	2SK2097	600V, 4A, 35W, <2,4Ohm(2A)	2SK1118, 2SK1404, 2SK1637
27700	01M(MR)	<80mOhm(10A)	2SK1266
27701	2SK2099-01(L,S)	250V, 6A, 20W, <0,85Ohm(3A)	2SK1920
27702	2SK210	18V, Idss>3mA, Up<3V	2SK217
27703	2SK2100(-01MR)	800V, 4A, 40W, <3,3Ohm(2A)	2SK1808, 2SK1985
27704	01M(MR)	800V, 6A, 50W, <2,1Ohm(3A)	-
27705	2SK2103	30V, 2A, <0,4Ohm(1A)	2SK1311, 2SK1470, 2SK1717
27706	2SK2104(F5)	60V, 5A, 20W	2SK1471, 2SK1719, 2SK1949
27707	2SK2106	60V, 5A, 30W	BUK 541-60, 2SK705, 2SK1255, 2SK1260
27708	2SK2107	<0,18Ohm(10A)	-
27709	2SK2108	250V, 6A, 25W, <0,5Ohm(3A)	2SK1478, 2SK1568...69, 2SK1668, 2SK1987
27710	2SK2109	60V, +-0,5A, <0,8Ohm(0,3A)	2SK1079, 2SK1697
27711	2SK211	18V, Idss>1mA, Up<4V	2SK197
27712	2SK2110	100V, +-0,5A, <1,2Ohm(0,3A)	2SK1079, 2SK1728
27713	2SK2111	60V, +-1A, <0,45Ohm(0,5A)	2SK1485, 2SK1726, 2SK1728
27714	2SK2112	100V, +-1A, <0,8Ohm(0,5A)	2SK1485, 2SK1728
27715	2SK2113	3V, Idss12..60mA, Up<2,5V	-
27716	2SK2114	450V, 5A, 35W, <1,4Ohm(2,5A)	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
27717	2SK2115	2SK2114, 500V, <1,5Ohm(2,5A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
27718	2SK2116	450V, 7A, 35W, <0,8Ohm(4A)	2SK1352, 2SK1566...67, 2SK1609, 2SK1805
27719	2SK2117	2SK2116, 500V, <0,9Ohm(4A)	2SK1352, 2SK1567, 2SK1805

27720	2SK2118	600V, 5A, 35W, <1,5Ohm(2,5A)	2SK1118, 2SK1404, 2SK1637, 2SK2097
27721	2SK2119	2SK1910, , 30W	2SK943, 2SK1095, 2SK1345...46, 2SK1307
27722	2SK212	20V, Idss>0,6mA, Up<2,5V	BF 410A, 2N5484
27723	2SK2120	2SK1911, , 35W	2SK1257, 2SK1653
27724	2SK2121	<10mOhm(25A)	BUK 539-60, 2SK1258, 2SK1379
27725	2SK2122	2SK1478	2SK1478
27726	2SK2123	2SK1605	2SK1605
27727	2SK2124	2SK1606	2SK1606
27728	2SK2125	2SK1833	2SK1833
27729	2SK2126	2SK1608	2SK1608
27730	2SK2127	2SK1609	2SK1609
27731	2SK2128	2SK1834	2SK1834
27732	2SK2129	2SK1846	2SK1356, 2SK1460
27733	2SK213	20/30ns	-
27734	2SK2130	2SK1612	2SK1612
27735	2SK2131	<0,12Ohm(8A)	2SK1350
27736	2SK2132	<0,65Ohm(2A)	-
27737	2SK2133	<0,26Ohm(8A)	BUZ 255
27738	2SK2133Z	2SK2133	2SK1636, 2SK1636, 2SK2063
27739	2SK2134	<0,40Ohm(7A)	BUK 456-200, BUZ 255, IRF 640, IRF 642
27740	2SK2134Z	2SK2134	2SK1636
27741	2SK2135	<0,18Ohm(7A)	2SK1350, 2SK2012
27742	2SK2136	<0,18Ohm(10A)	BUZ 30A
27743	2SK2136Z	2SK2136	2SK2107
27744	2SK2137	<2,4Ohm(2A)	2SK1118, 2SK1404, 2SK1637
27745	2SK2138	<2,4Ohm(2,5A)	2SK1117, 2SK1402, 2SK1809
27746	2SK2138Z	2SK2138	2SK2089, 2SK1915
27747	2SK2139	<1,5Ohm(2,5A)	2SK1118, 2SK1404, 2SK1637
27748	2SK214	2SK213, 160V	-
27749	2SK2140	<1,5Ohm(3,5A)	BUK 657-600, BUZ 91, BUZ 305
27750	2SK2140Z	2SK2140	2SK1625
27751	2SK2141	<1,1Ohm(3A)	2SK1404, 2SK2045, 2SK2101, 2SK2118
27752	2SK2142	250V, 12A, 70W, <0,35Ohm	BUZ 255, 2SK2133
27753	2SK2144	2SK2059, , 25W	2SK1572, 2SK1767
27754	2SK2145	50V, Idss1,2..14mA, Up<1,5V	-
27755	2SK2146	250V, 2A, 25W, <2Ohm(1A)	-
27756	2SK2147(-01MR)	900V, 6A, 80W, <2,8Ohm(3A)	2SK1176, 2SK1464, 2SK1685, 2SK1859
27757	2SK2148	<0,75Ohm(6A)	2SK1405, 2SK1686
27758	2SK2149	<0,8Ohm(1A)	2SK724, 2SK1488, 2SK1753, 2SK1785
27759	2SK215	2SK213, 180V	-
27760	2SK2150	<0,4Ohm(7A)	BUZ 338, 2SK899, 2SK1516, 2SK1610
27761	2SK2151	20V, 1A, <0,48Ohm(0,5A)	2SK1485, 2SK1726, 2SK1728
27762	2SK2152	20V, 2A, <0,18Ohm(1A)	2SK1311, 2SK1470, 2SK1717
27763	2SK2153	20V, 4A, 20W, <90mOhm	2SK1059, 2SK1112, 2SK1471, 2SK1719
27764	2SK2154	20V, 12A, 30W, <42mOhm(6A)	-

27765	2SK2156A	<45mOhm(12A)	2SK1346, 2SK1882, 2SK1897, 2SK2232
27766	2SK2157	30V, +-5A, <0,10hm(2,5A)	-
27767	2SK2158	50V, +-0,1A, <15Ohm(10mA)	2SK1590...91
27768	2SK2159	60V, +-2A, <0,3Ohm(1A)	2SK1311, 2SK1470, 2SK1717
27769	2SK216	2SK213, 200V	-
27770	2SK2160	25W,<0,45Ohm(3,5A)	BUK 545-200
27771	2SK2161	25W,<0,35Ohm(4,5A)	-
27772	2SK2162	180V, 1A, 20W	2SK1195, 2SK1838
27773	2SK2163	<20mOhm(22A)	2SK1257, 2SK1653, 2SK1952
27774	2SK2164	<20mOhm(22A)	2SK1919
27775	2SK2165	<0,03Ohm(20A)	BUK 539-60, 2SK1379, 2SK1297, 2SK1514
27776	2SK2166	2SK2165, , 80W	2SK1298, 2SK1666, 2SK2203
27777	2SK2167	250V, 0,4A, <12Ohm(0,2A)	-
27778	2SK2168	250V, 0,8A, <5Ohm(0,4A)	-
27779	2SK2169	250V, 0,4A, <5Ohm(0,2A)	-
27780	2SK217	30V, Idss>2,5mA, Up<2,5V	2SK210, 2SK217
27781	2SK2170	30V, 20mA, Idss1,2..4,5mA	-
27782	2SK2171	40V, 100mA, Idss40..75mA	-
27783	2SK2173	<17mOhm(25A)	BUK 539-60, 2SK1258, 2SK1379, 2SK2121
27784	2SK2174(L,S)	<0,27Ohm(10A)	-
27785	2SK2175	60V, 15A, 30W, <0,13Ohm(8A)	BUK 552-60, 2SK971...72, 2SK1115, 2SK1910
27786	2SK2176	500V, 5A, 30W, <1,5Ohm(2,5A)	2SK1231...32, 2SK1351, 2SK1608
27787	2SK2177	500V, 1A, 10W, <7Ohm(0,5A)	2SK580, 2SK1152, 2SK1672, 2SK2017
27788	2SK2178	40/70ns	-
27789	2SK2179	500V, 3A, 20W, <2,3Ohm(1,5A)	2SK2059
27790	2SK218	15V, 50mA, Idss>5mA	-
27791	2SK2180	500V, 3A, 40W, <2,3Ohm(1,5A)	2SK1154, 2SK1244, 2SK1494
27792	2SK2181	2SK2180	2SK1314, 2SK1721, 2SK2066
27793	2SK2182	2SK2180, , 25W	BUK 445-500, 2SK1863, 2SK1572, 2SK1767
27794	2SK2183	55/100ns	2SK1156,
27795	2SK2184	2SK2183	2SK1314, 2SK1722, 2SK2067, 2SK2356Z
27796	2SK2185	2SK2180, , 30W	2SK1232, 2SK1351, 2SK1608, 2SK2115
27797	2SK2186	70/140ns	2SK1503, 2SK2366
27798	2SK2187	2SK2186	2SK1865, 2SK2069, 2SK2366Z
27799	2SK2188	2SK2186, , 40W	-
27800	2SK2189	2SK2186, 70W	2SK724, 2SK896, 2SK1488, 2SK1753
27801	2SK2190	2SK2186, , 40W	2SK1206, 2SK1329, 2SK1523, 2SK1696
27802	2SK2191	500V, 12A, 60W, <0,7Ohm(6A)	-
27803	2SK2192	2SK2191, 80W	2SK899, 2SK1678, 2SK1745, 2SK1757
27804	2SK2193	2SK2186, , 50W	2SK1269, 2SK1331, 2SK1524
27805	2SK2194	110W,<0,45Ohm,110/270ns	2SK899, 2SK1610, 2SK1678, 2SK1745
27806	2SK2195	2SK2194, , 60W	2SK1269, 2SK1331, 2SK1524
27807	2SK2196	<0,35Ohm(10A)	2SK870, 2SK1170, 2SK1411, 2SK1498
27808	2SK2197	2SK2196, , 70W	2SK1406, 2SK1525
27809	2SK2198	<0,23Ohm(15A)	2SK1520, 2SK1629, 2SK1971

27810	2SK2199	250V, 0,8A, 15W, <5Ohm(0,4A)	2SK1838
27811	2SK220	25/45ns	2SK258, BUZ 33
27812	2SK2200	100V, 3A, 1,2W, <0,35Ohm(2A)	-
27813	2SK2201	2SK2200, 20W	2SK1113, 2SK1254, 2SK1284, 2SK1299
27814	2SK2202	120V, 7A, 20W, <0,4Ohm(4A)	BUK 545-200, 2SK1957
27815	2SK2203	2SK2121, , 60W	2SK1298, 2SK1424, 2SK1666
27816	2SK2204(L,S)	2SK2205	2SK1792, 2SK1919
27817	2SK2205	<15mOhm(25A)	2SK1542, 2SK1911
27818	2SK2206	2SK2205, , 35W	2SK1257, 2SK1653, 2SK1952
27819	2SK2207	<5Ohm(1,5A)	2SK1356, 2SK1460, 2SK1995
27820	2SK2208	<3Ohm(2,5A)	2SK1808, 2SK1985
27821	2SK2209(-01R)	500V, 15A, 80W, <0,48Ohm	2SK1269, 2SK1331, 2SK1405, 2SK1524
27822	2SK221	2SK220, 200V	2SK258, BUZ 33
27823	2SK2210	<2,4Ohm(2A)	2SK1808, 2SK1985
27824	2SK2211	30V, +-1A, <0,75Ohm(0,5A)	2SK1726, 2SK1728, 2SK2111...12
27825	2SK2212	200V, 10A, 30W, <0,3Ohm(5A)	2SK526, 2SK1036, 2SK1762
27826	2SK2213-01(L,S)	<0,76Ohm(5A)	2SK2366Z
27827	2SK2215-01(L,S)	600V, 8A, 80W, <1,2Ohm(4A)	-
27828	2SK2218	15V, 100mA, Idss40..75mA	-
27829	2SK2219	20V, Idss>0,14mA	-
27830	2SK222	40V, Idss>0,6mA, Up0,5V	2SK68, 2SK102, 2SK184
27831	2SK2220	180V, 8A, 100W, 250/90ns	-
27832	2SK2221	2SK2220, 200V	-
27833	2SK2222	800V, 5A, 80W, <2,2Ohm(3A)	2SK1684, 2SK1774...75, 2SK1859, 2SK2147
27834	2SK2222	800V, 5A, 80W, <2,2Ohm(3A)	2SK1684, 2SK1774...75, 2SK1859, 2SK2147
27835	2SK2223-01(R)	<0,76Ohm(5A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
27836	2SK2224-01(R)	900V, 3A, 50W, <4Ohm(1,5A)	2SK1463, 2SK1683, 2SK1859, 2SK2147
27837	2SK2225	1500V, 2A, 50W, <12Ohm(1A)	-
27838	2SK2226(-01)L,S	150V, 20A, 80W, <0,08Ohm	2SK2107, 2SK2136-Z
27839	2SK2227	600V, 4A, 60W, <2,4Ohm	-
27840	2SK2228	60V, 5A, <0,11Ohm(2,5A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
27841	2SK2229	60V, 5A, <0,16Ohm(2,5A)	2SK1112, 2SK1471, 2SK1719
27842	2SK223	80V, Idss>1,2mA, Up0,75V	-
27843	2SK2230	250V, 2A, 1,2W, <2Ohm(1A)	-
27844	2SK2231	60V, 5A, 20W, <0,16Ohm(2,5A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
27845	2SK2232	<46mOhm(12A)	2SK1095, 2SK1214, 2SK1346, 2SK1897
27846	2SK2233	100W, <30mOhm(25A)	2SK1297, 2SK1514, 2SK1665, 2SK2096
27847	2SK2234	<0,6Ohm(4A)	2SK1352, 2SK1567, 2SK1609, 2SK1805
27848	2SK2235	250V, 2A, 20W, <2Ohm(1,5A)	2SK2250
27849	2SK2236	500V, 5A, 40W, <1,6Ohm(2,5A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
27850	2SK2237	500V, 7A, 45W, <0,8Ohm(4A)	2SK1352, 2SK1567, 2SK1805, 2SK2117
27851	2SK2238	<3,5Ohm(0,8A)	BUK 444-450, 2SK1833, 2SK1988...89
27852	2SK2239	450V, 3A, 35W, <2Ohm(1,5A)	BUK 445-450, 2SK1862...63, 2SK2431
27853	2SK2240	450V, 5A, 35W, <1,5(2,5A)	2SK1351, 2SK1445, 2SK1990...91
27854	2SK2241	450V, 7A, 35W, <0,95(3,5A)	2SK1446, 2SK2116...17, 2SK2237

27855	2SK2242	450V, 7A, 70W, <0,95(3,5A)	2SK1451
27856	2SK2243	450V, 10A, 80W, <0,75(5A)	2SK1328...29, 2SK1523, 2SK1831...32
27857	2SK2244	450V, 12A, 85W, <0,55(6A)	2SK1268...69, 2SK1331, 2SK1453, 2SK1524
27858	2SK2245	450V, 15A, 85W, <0,45(7,5A)	2SK1268...69, 2SK1331, 2SK1453, 2SK1524
27859	2SK2247	60V, +-2A, <0,35Ohm(1A)	2SK1311, 2SK1717, 2SK1763, 2SK2315
27860	2SK2248-01L,S	30V, 10A, 20W, <0,06Ohm	2SK2018, 2SK2329, 2SK2414
27861	2SK2249-01L,S	30V, 10A, 35W, <0,06Ohm	2SK2041
27862	2SK225	180/60ns	2SK343...344
27863	2SK2250-01(L,S)	250V, 2A, 10W, <2Ohm(1A)	2SK2235
27864	2SK2251-01	250V, 2A, 20W, <2Ohm(1A)	2SK923
27865	2SK2252-01(L,S)	250V, 8A, 50W, <0,5Ohm(4A)	2SK1621
27866	01M(MR)	250V, 8A, 20W, <0,5Ohm(4A)	2SK1568...69, 2SK1668, 2SK1987, 2SK2425
27867	2SK2254-01(L,S)	<0,18Ohm(9A)	2SK2063, 2SK2133Z
27868	01M(MR)	2SK2254, , 50W	2SK1818, 2SK2012
27869	2SK2256-01	2SK2254	2SK2133
27870	2SK2257-01	<0,4Ohm(9A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27871	2SK2258-01	<3,6Ohm(2A)	BUZ 357...358, 2SK1205, 2SK1359, 2SK1773
27872	01M(MR)	<30mOhm(20A)	2SK1257, 2SK1653, 2SK1952, 2SK2120
27873	2SK226	2SK225, 140V	2SK343...344
27874	2SK2260	220V, 1,2A, <4,5Ohm(0,6A)	2SK1334
27875	2SK2261	60V, 2A, 1,2W	2SK462, 2SK973, 2SK1763, 2SK1973
27876	2SK2262	60V, 2A, 1,2W, <0,35Ohm(1A)	2SK973, 2SK1282, 2SK1763, 2SK1950
27877	2SK2263	500V, 5A, 80W	2SK1206, 2SK1523
27878	2SK2264	350V, 5A, 100W, <3Ohm(3A)	-
27879	2SK2265	2SK2264, 400V	BUZ 330...331, 2SK501
27880	2SK2266	<30mOhm(25A)	2SK1792, 2SK1919, 2SK2164, 2SK2376
27881	2SK2267	<11mOhm(30A)	2SK1223, 2SK1259, 2SK1380
27882	2SK2268	2SK2270, SMD	-
27883	2SK2269	2SK2270, SMD	-
27884	2SK227	2SK225, 160V	2SK344
27885	2SK2270	Idss1,2..12mA	-
27886	2SK2272-01R	900V, 5A, 100W, <2,8Ohm	2SK1176, 2SK1464, 2SK1684, 2SK1859
27887	2SK2273	12V, 0,5A, <0,48Ohm	-
27888	2SK2274	700V, 5A, 45W, <1,7Ohm(2A)	2SK1808, 2SK1985, 2SK2101
27889	2SK2275	<2,8Ohm(2A)	2SK1356, 2SK1460, 2SK1808, 2SK1995
27890	2SK2276	60V, +-3A, 10W, <0,2Ohm(3A)	2SK1282, 2SK1254, 2SK1299, 2SK1950
27891	2SK2277	60V, +-1A, <1Ohm(0,5A)	2SK1485, 2SK1726, 2SK1728, 2SK2111
27892	2SK2278(L,S)	2SK1317	-
27893	2SK2279	60V, 2A, 15W, <0,35Ohm(1A)	2SK973, 2SK1763, 2SK1973
27894	2SK2280	60V, 5A, 20W, <0,16Ohm(2,5A)	2SK1471, 2SK1719, 2SK1949, 2SK2231
27895	2SK2281	60V, 10A, 25W, <0,1Ohm(5A)	2SK2018, 2SK2329, 2SK2414
27896	2SK2282	60V, 10A, 40W, <0,1Ohm(5A)	2SK1907, 2SK2041
27897	2SK2283	2SK2282, , 30W	BUK 442-60, 2SK1033, 2SK1093, 2SK1344
27898	2SK2284	<0,07Ohm(7,5A)	2SK1648, 2SK1898, 2SK1967, 2SK2322
27899	2SK2285	2SK2284, , 35W	2SK1094, 2SK1286, 2SK1419, 2SK1896

27900	2SK2286	<45mOhm(10A)	2SK1622, 2SK1918, 2SK1967, 2SK2311
27901	2SK2287	2SK2286, , 40W	2SK1095, 2SK1345...46, 2SK1420, 2SK1951
27902	2SK2288	<30mOhm(15A)	2SK1792, 2SK1900, 2SK2411-Z
27903	2SK2289	2SK2288, , 50W	2SK1421, 2SK1653, 2SK1952, 2SK2120
27904	2SK2290	<20mOhm(22,5A)	2SK1792, 2SK1919, 2SK2164, 2SK2266
27905	2SK2291	2SK2290, , 55W	2SK1421, 2SK1653, 2SK1952, 2SK2120
27906	2SK2292-01L,S	250V, 4A, 20W, <1,1Ohm	2SK1920, 2SK2099
27907	2SK2293	900V, 3A, 30W	2SK1356, 2SK1460
27908	2SK2294	800V, 3A, 30W, <4Ohm(1,5A)	2SK1356, 2SK1460, 2SK1995
27909	2SK2295	600V, 4A, 30W, <2,4Ohm(2A)	2SK1118, 2SK2044, 2SK2100...01, 2SK2118
27910	2SK2298	500V, 7A, 30W	2SK1352, 2SK1567, 2SK1609, 2SK1805
27911	2SK2299(N)	450V, 7A, 30W, <1,1Ohm(4A)	2SK1352, 2SK1566, 2SK1609, 2SK1805
27912	2SK23(A)-2...9	18..40V, Idss>2,7mA, Up<4,9V	2SK107, 2SK192
27913	2SK2300	60V, 15A, 30W	2SK943, 2SK1286, 2SK1345
27914	2SK2306(F5)	60V, 3A, 20W	2SK1113, 2SK1254, 2SK1282
27915	2SK2307(F5)	100V, 2A, 20W	2SK1113, 2SK1299, 2SK1254, 2SK1284
27916	2SK2309	100V, 10A, 30W	BUK 545-100, 2SK1035, 2SK1305, 2SK1904
27917	2SK2311	<46mOhm(12A)	2SK1622, 2SK1918
27918	2SK2312	<17mOhm(25A)	2SK1257, 2SK1653, 2SK1952, 2SK2120
27919	2SK2313	<11mOhm(30A)	BUK 539-60, 2SK1258, 2SK1379, 2SK2121
27920	2SK2314	<85mOhm(15A)	2SK1293, 2SK2050
27921	2SK2315	60V, +-2A, <0,45Ohm(1A)	2SK1311, 2SK1470, 2SK1717, 2SK2055
27922	2SK2316	20V, 2A, <0,2Ohm(0,5A)	2SK1311, 2SK1470, 2SK1717, 2SK2315
27923	2SK2317	20V, 4A, 20W, <85mOhm	2SK1112, 2SK1471, 2SK1719
27924	2SK2318	20V, 12A, 30W, <38mOhm	2SK2414
27925	2SK2319	800V, 7A, 90W, <1,7Ohm(3,5A)	2SK1464, 2SK1685, 2SK1774...75
27926	2SK2320	800V, 8,5A, 90W, <1,2Ohm(4A)	2SK1464, 2SK1686, 2SK1775, 2SK2148
27927	2SK2321	<0,35Ohm(6A)	2SK1636, 2SK2063
27928	2SK2322(L,S)	60V, 15A, 50W, <50mOhm(8A)	2SK1648
27929	2SK2323	<8,5Ohm(0,5A)	BUK 444-600, 2SK808
27930	2SK2324	600V, +-2A, 40W, <6Ohm(1A)	BUK 445-600, 2SK1758, 2SK1834, 2SK2043
27931	2SK2325	<2,5Ohm(2A)	2SK1572, 2SK1767, 2SK1995, 2SK2144
27932	2SK2326	<1,5Ohm(3A)	2SK2100...01, 2SK2044, 2SK2097, 2SK2118
27933	2SK2327	<0,75Ohm(5A)	2SK1686, 2SK2148
27934	2SK2328	2SK1403A, 7A, 75W	-
27935	2SK2329(L,S)	30V, 10A, 20W, <40mOhm(5A)	2SK2414
27936	2SK2330	2SK1168	-
27937	2SK2331	12GHz	-
27938	2SK2332	12GHz	-
27939	2SK2333	<2Ohm(3A),70/160ns	-
27940	2SK2334(L,S)	<55mOhm(10A)	-
27941	2SK2339	<0,23Ohm	-
27942	2SK2340	<2,8Ohm(3A)	2SK1808, 2SK1985
27943	2SK2341	<0,26Ohm(6A)	2SK1036, 2SK1762, 2SK2011, 2SK2426
27944	2SK2342	30V, +-2A, <0,45Ohm(1A)	2SK973, 2SK1763



27945	2SK2345	350V, 6A, 35W, <0,8Ohm(5A)	BUK 445-400, 2SK1351, 2SK1608, 2SK1627
27946	2SK2346	<50mOhm(10A)	2SK1095, 2SK1214, 2SK1345, 2SK1897
27947	2SK2347	<0,8Ohm(10A)	-
27948	2SK2348	<1,5Ohm(7A)	-
27949	2SK2349	<2,5Ohm(5A)	-
27950	2SK2350	200V, 8,5A, 30W, <0,4Ohm(5A)	BUK 545-200, 2SK1668, 2SK2160...61
27951	2SK2351	<1,25Ohm(3A)	BUZ 91, 2SK1117, 2SK1924
27952	2SK2352	2SK2351	2SK1118, 2SK1404, 2SK2045
27953	2SK2353	2SK2355, , +-4,5A, 30W	2SK1351, 2SK1608, 2SK2114...15, 2SK2236
27954	2SK2354	2SK2356, , +-4,5A, 30W	2SK1351, 2SK1608, 2SK2115, 2SK2236
27955	2SK2355	<1,4Ohm(2,5A)	2SK1156, 2SK1246, 2SK1440, 2SK1751
27956	2SK2355..2356Z	2SK2355..2356	2SK1540...1541
27957	2SK2356	2SK2355, 500V, <1,5Ohm(2,5A)	2SK1156, 2SK1246, 2SK1751
27958	2SK2357	2SK2359, , +-6A, 35W	2SK1352, 2SK1805, 2SK2116...17, 2SK2237
27959	2SK2358	2SK2360, , +-6A, 35W	2SK1352, 2SK1805, 2SK2117, 2SK2237
27960	2SK2359	<0,9Ohm(4A)	2SK1495...96, 2SK1574, IRF 840, IRF 842
27961	2SK2359..2360Z	2SK2359..2360	2SK1315...16, 2SK1540...1541
27962	2SK2360	2SK2359, 500V, 1Ohm(4A)	2SK1496, 2SK1574, IRF 840, IRF 842
27963	2SK2361	<0,9Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1784...85
27964	2SK2362	2SK2361, 500V, <1Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1785
27965	2SK2363	<0,5Ohm(4A)	2SK1352, 2SK1805, 2SK2116...17, 2SK2237
27966	2SK2364	2SK2363, 500V, <0,6Ohm(4A)	2SK1352, 2SK1609, 2SK2117, 2SK2237
27967	2SK2365	<0,5Ohm(5A)	2SK1442, 2SK1503
27968	2SK2365..2366Z	2SK2365..2366	2SK1865
27969	2SK2366	2SK2365, 500V, <0,6Ohm(5A)	2SK1503
27970	2SK2367	<0,5Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27971	2SK2368	2SK2367, 500V, <0,6Ohm(8A)	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
27972	2SK2369	<0,35Ohm(10A)	2SK870, 2SK1409, 2SK1411, 2SK1497...1500
27973	2SK2370	2SK2369, 500V, <0,4Ohm(10A)	2SK870, 2SK1409, 2SK1411, 2SK1498/1500
27974	2SK2371	<0,25Ohm(13A)	2SK1499...1500
27975	2SK2372	<0,27Ohm(13A)	2SK1500
27976	2SK2373	integr. Rg	(2SK1590...91)
27977	2SK2374	<2,8Ohm(3A)	2SK1176, 2SK1464, 2SK1684, 2SK1859
27978	2SK2375	<1,7Ohm(4A)	2SK1365, 2SK1464, 2SK1685, 2SK1775
27979	2SK2376	<17mOhm(25A)	2SK1792, 2SK1919, 2SK2164, 2SK2266
27980	2SK2377	170V, +-20A, 50W, <0,145Ohm	-
27981	2SK2378	<0,21Ohm(7A)	2SK1350
27982	2SK2379	<95mOhm(10A)	2SK1818
27983	2SK238	20V, Idss>0,5mA, Up<2,5V	BF 510
27984	2SK2380	40V, Idss0,05..0,2mA, Up<3V	-
27985	2SK2381	200V, 5A, 25W, <0,8Ohm(2,5A)	BUK 444-200, BUZ 73, 2SK2010, 2SK2108
27986	2SK2382	<0,18Ohm(10A)	2SK1350, 2SK2012
27987	2SK2383	<0,6Ohm(7A)	2SK1269, 2SK1331, 2SK1405, 2SK1524
27988	2SK2385	<30mOhm(18A)	2SK1257, 2SK1952, 2SK2120, 2SK2312
27989	2SK2386	500V, 5A, 75W, <1,6Ohm(2,5A)	BUZ 41...42, 2SK553, 2SK893, 2SK1246

27990	2SK2388	<2,2Ohm(1,8A)	2SK1118, 2SK2044, 2SK2097, 2SK2118
27991	2SK2389	700V, 5A, 125W, <1,7Ohm(2A)	-
27992	2SK2390	60V, 12A, 20W, <90mOhm(6A)	2SK1093, 2SK1256, 2SK1305...06, 2SK1344
27993	2SK2391	<85mOhm(10A)	2SK1266, 2SK1307, 2SK1292, 2SK1906
27994	2SK2393	<2,8Ohm(4A)	-
27995	2SK2394	2SK2395, SMD	BF 513
27996	2SK2395	15V, Idss6..32mA, Up<1,8V	BC 264C...D
27997	2SK2397(-01MR)	800V, 5A, 50W, <2,3Ohm	2SK1808, 2SK1985, 2SK2101
27998	2SK2398	<30mOhm(25A)	2SK1297, 2SK1514, 2SK1665, 2SK2096
27999	2SK2399	20W,<23mOhm(2,5A)	2SK1474, 2SK1804, 2SK2013
28000	2SK24	40V, Idss0,6..24mA, Up<6V	BFS 71, 2N3822, 2N5457, 2SK246, 2SK330
28001	2SK2400	2SK2399, 1,3W	-
28002	2SK2401	<0,18Ohm(10A)	2SK1636, 2SK2063, 2SK2133Z, 2SK2254
28003	2SK2402	<2,2Ohm(1,8A)	BUZ 90, 2SK1117, 2SK1809, 2SK1923
28004	2SK2403	450V, 3A, 50W, <3,2Ohm(1,5A)	-
28005	2SK2404	450V, 5A, 60W, <1,6Ohm(3A)	-
28006	2SK2405	<0,75Ohm(6A)	-
28007	2SK2406	450V, 1A, 30W, <4,5Ohm(5A)	-
28008	2SK2407	<0,75Ohm(6A)	-
28009	2SK2408	500V, 7A, 60W, <0,9Ohm(4A)	2SK1496, 2SK1574, IRF 840, IRF 842
28010	2SK2409	<27mOhm(20A)	2SK1653, 2SK1952, 2SK2120, 2SK2312
28011	2SK241	20V, Idss>1,5mA, Up<2,5V	-
28012	2SK2410	2SK2411, , 35W	2SK1262
28013	2SK2411	<40mOhm(15A)	2SK1291, 2SK1296
28014	2SK2411Z	2SK2411	2SK1900
28015	2SK2412	<70mOhm(10A)	2SK1095, 2SK1214, 2SK1345, 2SK1882
28016	2SK2413	2SK2414, 1,8W	-
28017	2SK2414(Z)	<0,07Ohm(5A)	2SK2018, 2SK2329
28018	2SK2415(Z)	60V, +-8A, 20W, <0,1Ohm(4A)	2SK1472, 2SK1475, 2SK1748
28019	2SK2417	<0,5Ohm(3,5A)	2SK1036, 2SK1762, 2SK2011, 2SK2425...26
28020	2SK2418(L,S)	50V, 7A, 20W, <0,05Ohm(4A)	2SK1472, 2SK1475, 2SK1748
28021	2SK2419	<50mOhm(12A)	2SK1290, 2SK1346, 2SK1882, 2SK1897
28022	2SK242	20V, Idss>0,6mA, Up<2,5V	BF 510, 2SK238
28023	2SK2420	<28mOhm(15A)	2SK1421, 2SK1653, 2SK2120, 2SK2312
28024	2SK2421	<20mOhm(20A)	2SK1421, 2SK1653, 2SK2120, 2SK2312
28025	2SK2422	650V, 4A, 20W, <2,6Ohm(2A)	2SK1637, 2SK1404, 2SK2097, 2SK2118
28026	2SK2423	450V, 7A, 35W, <0,7Ohm(4A)	2SK1352, 2SK1566...67, 2SK1609, 2SK1805
28027	2SK2424	450V, 8A, 35W, <0,55Ohm(4A)	2SK1352, 2SK1566...67, 2SK1609, 2SK1805
28028	2SK2425	250V, 7A, 30W, <0,55Ohm(4A)	2SK1478, 2SK1568...69, 2SK1668
28029	2SK2426	<0,35Ohm(6A)	2SK1036, 2SK1762
28030	2SK2431	450V, 3A, 25W, <2,8Ohm(3A)	BUK 445-450, 2SK1572, 2SK1767
28031	2SK2437	30V, 2A, <0,18Ohm	2SK1311, 2SK1717, 2SK1763
28032	2SK2438	30V, 4A, 20W, <80mOhm	2SK1112, 2SK1471, 2SK1719
28033	2SK2439	30V, 12A, 30W, <40mOhm	2SK2414
28034	2SK2445	<18mOhm(25A)	BUK 539-60, 2SK1258, 2SK1379, 2SK2121

28035	2SK2446(-01)L,S	100V, 30A, 80W, <55mOhm	2SK1813
28036	2SK2459N	<0,65Ohm(2,5A)	BUK 444-200, BUZ 73, 2SK2010, 2SK2108
28037	2SK246	50V, Idss>1,2mA, Up<6V	2N5457, 2SK330
28038	2SK2460N	<0,75Ohm(2,5A)	2SK2010, 2SK2108
28039	2SK2461	<80mOhm(10A)	2SK1292, 2SK1348, 2SK1906, 2SK2098
28040	2SK2462	<14mOhm(8A)	2SK1288, 2SK1306, 2SK1558, 2SK2131
28041	2SK2463	60V, 2A, <0,38Ohm(1A)	2SK1273, 2SK1470, 2SK1717, 2SK2315
28042	2SK2466	<70mOhm(15A)	2SK1262
28043	2SK2467	180V, 9A, 80W	-
28044	2SK2469-01MR	300V, 5A, 30W, <1Ohm(2,5A)	BUK 445-400, 2SK1377, 2SK2345
28045	2SK247	15V, Idss>0,5mA, Up<3V	-
28046	2SK2470-01MR	<0,53Ohm(5A)	-
28047	2SK2471-01	300V, 5A, 80W, <1Ohm(2,5A)	-
28048	2SK2473-01MR	<0,2Ohm(10A)	2SK868, 2SK1674
28049	2SK2474	250V, +-2A, 10W, <2Ohm(1A)	2SK2235, 2SK2250
28050	2SK2475	500V, 12A, 50W, <0,7Ohm(6A)	-
28051	2SK2476	800V, +-3A, 40W, <5Ohm(2A)	2SK1356, 2SK1460, 2SK1995
28052	2SK2477	<1Ohm(5A)	2SK1796, 2SK1933
28053	2SK2478	<7,5Ohm(1A)	2SK1143, 2SK1174, 2SK1459, 2SK1994
28054	2SK2479	<7,5Ohm(2A)	2SK1456, 2SK1601, 2SK1638, 2SK1793
28055	2SK2480	900V, +-3A, 35W, <4Ohm(2A)	2SK1356, 2SK1460, 2SK1995
28056	2SK2481	900V, +-4A, 70W, <4Ohm(2A)	2SK1457, 2SK1639, 2SK1643, 2SK1807
28057	2SK2482	900V, +-5A, 100W, <4Ohm(3A)	2SK727, 2SK1341, 2SK1760, 2SK1794
28058	2SK2483	<2,8Ohm(2A)	2SK1460, 2SK1808, 2SK1985
28059	2SK2484	<2,8Ohm(3A)	2SK1501, 2SK1639, 2SK1643, 2SK1807
28060	2SK2485	<2,8Ohm(3A)	2SK1502, 2SK1614, 2SK1692, 2SK1795
28061	2SK2486	900V, +-7A, 120W, <2Ohm(4A)	2SK1358, 2SK1462, 2SK1692, 2SK1795
28062	2SK2487	<1,6Ohm(4A)	2SK1358, 2SK1462, 2SK1692, 2SK1795
28063	2SK2488	<1,2Ohm(5A)	2SK1796, 2SK1933
28064	2SK2489	<0,25Ohm(5A)	2SK1636, 2SK2088, 2SK2133-Z, 2SK2254
28065	2SK2490	2SK2489, 40W	2SK2011, 2SK2212, 2SK2426
28066	2SK2491	<0,13Ohm(10A)	2SK2107
28067	2SK2492	2SK2491, 70W	2SK1818
28068	2SK2493	16V, 5A, 20W, <0,1Ohm(2,5A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
28069	2SK2494	60V, 2A, 20W, 0,3Ohm	-
28070	2SK2494-01	60V, 45A, 80W, <25mOhm	2SK1418, 2SK1542, 2SK1911
28071	2SK2495	250V, +-2A, 30W, <2Ohm(1A)	-
28072	2SK2498	2SK2499, , 35W	2SK1257, 2SK1653, 2SK2120, 2SK2529
28073	2SK2499	<9mOhm(25A)	BUK 556-60, 2SK2049
28074	2SK2499-Z	2SK2499	2SK2553
28075	2SK25	18V, Idss0,6..24mA, Up<7,2V	BF 244...245, BFS 71, 2N3822...23
28076	2SK2503	60V, 5A, 20W, <0,135Ohm	-
28077	2SK2504	100V, 5A, 20W, <0,22Ohm	-
28078	2SK2507	<46mOhm(12A)	2SK1882, 2SK1897, 2SK2232, 2SK2346
28079	2SK2508	<0,25Ohm(6,5A)	2SK2012

28080	2SK2509	<4Ohm(1,5A)	2SK1690
28081	2SK2510	<20mOhm(20A)	2SK1653, 2SK2120, 2SK2529
28082	2SK2511	<27mOhm(20A)	BUK 539-60, 2SK2121, 2SK2173, 2SK2313
28083	2SK2512	2SK2513, , 35W	2SK1653, 2SK2120, 2SK2529
28084	2SK2513	<15mOhm(23A)	BUK 556-60, 2SK1542, 2SK1911
28085	2SK2513-Z	2SK2513	2SK1919, 2SK2164, 2SK2266, 2SK2376
28086	2SK2514	<15mOhm(25A)	BUK 539-60, 2SK2121, 2SK2173, 2SK2313
28087	2SK2515	<9mOhm(25A)	BUK 539-60, 2SK2121, 2SK2173, 2SK2313
28088	2SK2516-01L,S	30V, 50A, 80W, <13mOhm	2SK2553
28089	2SK2517-01L,S	60V, 50A, 80W, <20mOhm	2SK2553
28090	2SK2518-01MR	<0,13Ohm(10A)	2SK1818
28091	2SK2519-01	200V, 10A, 40W, <0,4Ohm	2SK890, 2SK1221, 2SK1393, 2SK1761
28092	2SK2520-01MR	200V, 10A, 30W, <0,4Ohm	2SK2011, 2SK2212, 2SK2426
28093	2SK2521-01	200V, 18A, 50W, <0,18Ohm	BUZ 30A
28094	2SK2522-01MR	200V, 18A, 40W, <0,18Ohm	2SK1818
28095	2SK2523-01	450V, 9A, 50W, <1Ohm	2SK1442, 2SK1503, 2SK2365...66
28096	2SK2524-01MR	450V, 9A, 40W, <1Ohm	2SK2363...64
28097	2SK2525-01	450V, 9A, 80W, <1Ohm	2SK1488, 2SK1516, 2SK1753, 2SK1785
28098	2SK2526-01	900V, 5A, 60W, <3,6Ohm	2SK1457, 2SK1501, 2SK1643, 2SK1807
28099	2SK2527-01MR	900V, 5A, 40W, <3,6Ohm	2SK1808, 2SK1985
28100	2SK2528-01	900V, 5A, 80W, <3,6Ohm	2SK727, 2SK1461, 2SK1760, 2SK1794
28101	2SK2529	<0,01Ohm(25A)	2SK1653, 2SK2120
28102	2SK2530	250V, 2A, 20W, <2Ohm(1A)	-
28103	2SK2538	250V, +-2A, 30W, <2Ohm(1A)	2SK2146
28104	2SK2539	15V, Idss10..50mA	-
28105	2SK2540	100V, 10A, <0,16Ohm(5A)	2SK1620, 2SK1741, 2SK1907
28106	2SK2541	50V, +-0,1A, <50mOhm(1mA)	BS 170, BSS 98, 2SK1398
28107	2SK2542	500V, 8A, 80W, <0,85Ohm(4A)	IRF 840, 2SK1496, 2SK1574, 2SK2360
28108	2SK2543	2SK2542, , 40W	2SK1352, 2SK1609, 2SK2117, 2SK2237
28109	2SK2544	600V, 6A, 80W, <1,25Ohm(3A)	BUZ 91, 2SK1117, 2SK1924
28110	2SK2545	2SK2544, , 40W	2SK1118, 2SK1637, 2SK2097, 2SK2045
28111	2SK2549	16V, 2A, <0,29Ohm(1A)	-
28112	2SK2550	<30mOhm(25A)	BUZ 348, 2SK1998, 2SK2096, 2SK2233
28113	2SK2551	<11mOhm(25A)	BUZ 346, 2SK1423, 2SK2121, 2SK2173
28114	2SK2552	20V, Idss>40µA	-
28115	2SK2553(L,S)	2SK2529, 75W	2SK2499-Z
28116	2SK2554	<6mOhm(40A)	-
28117	2SK2555	30V, 12A, 30W, <46mOhm	2SK2414
28118	2SK2561-01R	600V, 9A, 80W, <1,2Ohm	2SK2148
28119	2SK2562-01R	800V, 7A, 80W, <2,2Ohm	2SK1464, 2SK1685, 2SK1774...75
28120	2SK2568	<0,6Ohm(6A)	2SK724, 2SK1488, 2SK1723, 2SK1785
28121	2SK2569	integr. Rg	
28122	2SK2570	integr. Rg	
28123	2SK2571	<0,45Ohm(7A)	2SK1268...69, 2SK1331, 2SK1524...25
28124	2SK2572	<0,5Ohm(8A)	2SK1269, 2SK1331, 2SK1524...25

28125	2SK2573	<0,40hm(10A)	2SK1406, 2SK1525
28126	2SK2574	<70mOhm(10A)	2SK1094, 2SK1286, 2SK1896
28127	2SK2575	<135mOhm(8A)	2SK1288, 2SK1306, 2SK1558, 2SK2131
28128	2SK2576	<0,30hm(5A)	2SK1036, 2SK1762, 2SK2011, 2SK2426
28129	2SK2577	<70mOhm(15A)	2SK1262
28130	2SK2578	60V, +-5A, 30W, <0,20hm(3A)	BUK 541-60, 2SK705, 2SK1255
28131	2SK2579	<0,110hm(5A)	2SK1093, 2SK1256, 2SK1344, 2SK1895
28132	2SK258	25/140ns	2SK277...278, 2SK293, 2SK299
28133	2SK2580	<35mOhm(20A)	2SK1882, 2SK1897, 2SK1951, 2SK2232
28134	2SK2581	<0,470hm(3A)	BUK 542-100, 2SK992, 2SK1260, 2SK1265
28135	2SK2582	350V, 13A, 75W, <0,40hm(7A)	-
28136	2SK2586	<10mOhm(30A)	BUK 539-60, 2SK1258, 2SK1379, 2SK2121
28137	2SK2588	<1,10hm(2A)	2SK1264
28138	2SK259	25/140ns	BUZ 44, BUZ 46, BUZ 63
28139	2SK2590	200V, 7A, 50W, <0,450hm(4A)	BUZ 30...32, BUZ 73, 2SK741, 2SK1319
28140	2SK2591	500V, 8A, 35W, <0,60hm(4A)	2SK1532, 2SK1567, 2SK1805, 2SK2117
28141	2SK2592	250V, 13A, 60W, <0,270hm	-
28142	2SK2593	55V, Idss1..20mA, Up<5V	-
28143	2SK2598	<0,250hm(6,5A)	2SK2063, 2SK2133Z, 2SK2254
28144	2SK2599	500V, 2A, 1,3W, <3,20hm(1A)	-
28145	2SK260	25/140ns	BUZ 44, BUZ 46, BUZ 63
28146	2SK2601	500V, 10A, 125W, <10hm(5A)	2SK1488, 2SK1723, 2SK1745, 2SK1757
28147	2SK2602	<1,250hm(3A)	2SK1032, 2SK1358, 2SK1502, 2SK1614
28148	2SK2603	<3,60hm(1,5A)	BUK 456-800, 2SK1456, 2SK1638, 2SK1600
28149	2SK2604	800V, 5A, 125W, <2,20hm(3A)	2SK793...94, 2SK1341, 2SK1650, 2SK1794
28150	2SK2605	800V, 5A, 45W, <2,20hm(3A)	BUZ 81, 2SK1457, 2SK1643, 2SK1807
28151	2SK2607	800V, 9A, 150W, <1,20hm(4A)	2SK1796, 2SK1933
28152	2SK2608	<4,30hm(1,5A)	BUK456-1000, 2SK1456, 2SK1638, 2SK1793
28153	2SK2610	900V, 5A, 125W, <2,50hm(3A)	2SK727, 2SK1341, 2SK1649...50, 2SK1794
28154	2SK2611	900V, 9A, 150W, <1,40hm(4A)	2SK1796, 2SK1933
28155	2SK2614	<46mOhm(10A)	-
28156	2SK2615	60V, 2A, <0,30hm(1A)	2SK1311, 2SK1717, 2SK1763, 2SK2315
28157	2SK2616	500V, 2A, 30W, <40hm	-
28158	2SK2617	500V, 4A, 25W, <1,60hm	2SK1351, 2SK1232, 2SK1608, 2SK1627
28159	2SK2618(LS)	500V, 5A, 30W, <1,250hm	2SK1351, 2SK1232, 2SK1608, 2SK1627
28160	2SK2619	500V, 6A, 70W, <1,250hm	2SK1540...1541
28161	2SK2620	500V, 7A, 35W, <0,80hm	2SK1352, 2SK1567, 2SK1805, 2SK2117
28162	2SK2621	500V, 12A, 120W, <0,60hm	2SK644, 2SK724, 2SK1488, 2SK1723
28163	2SK2622	500V, 14A, 125W, <0,520hm	2SK725, 2SK788, 2SK899, 2SK1610, 2SK1745
28164	2SK2623	600V, 1,5A, 30W, <5,50hm	2SK1533, 2SK1880
28165	2SK2624(LS)	600V, 3A, 25W, <2,60hm	2SK1572, 2SK1767, 2SK2044, 2SK2144
28166	2SK2625(LS)	600V, 4A, 30W, <20hm	2SK1637, 2SK2044, 2SK2097, 2SK2118
28167	2SK2626	600V, 5A, 70W, <20hm	2SK1915, 2SK2089
28168	2SK2628(LS)	600V, 6A, 35W, <1,20hm	2SK1118, 2SK1404, 2SK2045, 2SK2118
28169	2SK2629	600V, 10A, 120W, <10hm	BUZ 334, 2SK1723, 2SK1968



28170	2SK2630	600V, 10A, 120W, <10hm	BUZ 334, 2SK1573, 2SK1723, 2SK1968
28171	2SK2631	800, 1A, 30W, <100hm	2SK1533
28172	2SK2632(LS)	800V, 2,5A, 25W, <4,80hm	BUK 445-600, 2SK1142, 2SK1834, 2SK1953
28173	2SK2633(LS)	800V, 3A, 30W, <3,60hm	2SK1356, 2SK1460, 2SK1808, 2SK1995
28174	2SK2634	800V, 3,5A, 70W, <3,60hm	2SK1510, 2SK1528, 2SK1659, 2SK1858
28175	2SK2635	800V, 5A, 100W, <2,60hm	2SK727, 2SK1341, 2SK1649...50, 2SK1794
28176	2SK2636	800V, 7A, 120W, <1,80hm	2SK1358, 2SK1614, 2SK1502, 2SK1692
28177	2SK2638-01MR	<0,650hm(5A)	-
28178	2SK2639-01	2SK2638, 100W	2SK642, 2SK644, 2SK683, 2SK1753, 2SK1785
28179	2SK2640-01MR	500V, 10A, 50W, <0,90hm(5A)	-
28180	2SK2641-01	2SK2640, 100W	2SK642, 2SK644, 2SK683, 2SK1753, 2SK1785
28181	2SK2643-01	<0,550hm(7,5A)	2SK725, 2SK1610, 2SK1745, 2SK1757
28182	2SK2645-01MR	600V, 9A, 50W, <1,20hm(4,5A)	-
28183	2SK2646-01MR	800V, 4A, 80W, <40hm(2A)	2SK1501, 2SK1639, 2SK1643, 2SK1807
28184	2SK2647-01MR	2SK2646, 40W	2SK1808, 2SK1985, 2SK2100...01
28185	2SK2648-01	<1,50hm(4,5A)	2SK1796, 2SK1933
28186	2SK2649-01R	2SK2648, , 100W	2SK1686
28187	2SK2651-01MR	900V, 6A, 50W, <2,50hm(3A)	2SK1985
28188	2SK2652-01	2SK2651, 125W	2SK1502, 2SK1614, 2SK1692, 2SK1795
28189	2SK2653-01R	2SK2651, 80W	2SK1365, 2SK1464, 2SK1685, 2SK1775
28190	2SK2654-01	900V, 8A, 150W, <20hm(4A)	2SK1502, 2SK1614, 2SK1692, 2SK1795
28191	2SK2655-01R	2SK2654, , 100W	2SK1365, 2SK1464, 2SK1685, 2SK1775
28192	2SK2659	<70m0hm(10A)	2SK1094, 2SK1286, 2SK1419, 2SK1896
28193	2SK2660	<1,10hm(2A)	2SK1920, 2SK2099
28194	2SK2661	500V, 5A, 75W, <1,50hm(2,5A)	BUZ 41A...42, IRF 830, 2SK1751, 2SK2356
28195	2SK2662	2SK2661, , 35W	BUK 445-500, 2SK1993, 2SK2115, 2SK2354
28196	2SK2679	400V, 5,5A, 35W, <1,20hm(3A)	BUK 445-450, 2SK1377, 2SK1445, 2SK1990
28197	2SK2680(LS)	LS, lead s	2SK1568...69, 2SK1668, 2SK1987, 2SK2425
28198	2SK2681(LS)	<0,390hm(5A)	2SK1036, 2SK1762, 2SK2011, 2SK2426
28199	2SK2682(LS)	<0,270hm(6A)	2SK2012
28200	2SK2683	<0,180hm(8A)	2SK1818
28201	2SK2684(L,S)	<28m0hm(15A)	2SK1900, 2SK2411Z
28202	2SK2685	2GHz	-
28203	2SK2687-01	30V, 50A, 60W, <0,010hm	BUK 556-60, 2SK1542, 2SK2049
28204	2SK2688-01L,S	30V, 50A, 60W, <0,010hm	2SK2553
28205	2SK2689-01MR	30V, 50A, 40W, <0,010hm	2SK1653, 2SK2312, 2SK2529
28206	2SK2690-01	60V, 80A, 125W, <0,010hm	2SK1423
28207	2SK2691-01R	60V, 60A, 100W, <0,010hm	-
28208	2SK2695	700V, 5A, 60W, <1,850hm	BUZ 81, 2SK1501, 2SK1643, 2SK1807
28209	2SK2696-01MR	700V, 5A, 50W, <1,850hm	2SK1808, 2SK1985
28210	2SK2698	<0,40hm(7A)	2SK899, 2SK1610, 2SK1745, 2SK1757
28211	2SK2699	<0,650hm(6A)	BUZ 334, 2SK1723, 2SK1968
28212	2SK2700	900V, 3A, 40W, <4,30hm(1,5A)	2SK1356, 2SK1460, 2SK1995
28213	2SK271	140V, 8A, 120W	2SK405, 2SK631, 2SK633
28214	2SK2711	<0,250hm(8A)	2SK2012, 2SK2255



28215	2SK2713	<1,45Ohm(2,5A)	2SK1351, 2SK1608, 2SK2114...15, 2SK2236
28216	2SK2714	<0,95Ohm(5A)	-
28217	2SK2715	500V, 2A, 20W, <40Ohm(1A)	2SK1721
28218	2SK2718	<6,40Ohm(1,5A)	2SK1174, 2SK1275, 2SK1459, 2SK1994
28219	2SK2719	<4,30Ohm(1,5A)	2SK696, 2SK726...727, 2SK1339
28220	2SK272	2SK271, 7A, 100W	2SK405, 2SK413...414, 2SK631, 2SK633
28221	2SK2725	500V, 5A, 30W, <1,60Ohm(3A)	2SK1351, 2SK1608, 2SK1993, 2SK2115
28222	2SK2726	500V, 7A, 30W, <0,95Ohm(4A)	2SK1352, 2SK1609, 2SK1805, 2SK2117
28223	2SK2727	<0,95Ohm(5A)	2SK644, 2SK724, 2SK1488, 2SK1785
28224	2SK2728	<0,45Ohm(9A)	2SK1170, 2SK1411, 2SK1500, 2SK1680
28225	2SK2729	<0,29Ohm(10A)	2SK1170, 2SK1411, 2SK1500, 2SK1680
28226	2SK273	8V, 100mA, 12GHz	-
28227	2SK2730	<0,24Ohm(15A)	2SK1500
28228	2SK2731	30V, 0,2A, <2,80Ohm	BSS 138, BSS 145, BST 82
28229	2SK2733	900V, 1A, 60W, <90Ohm(0,5A)	BUZ 50, 2SK1199, 2SK1324, 2SK1338
28230	2SK2734	30V, 5A, 0,9W, <0,55mOhm	-
28231	2SK2735	<28mOhm(10A)	2SK2334
28232	2SK2736	<85mOhm(15A)	2SK1262
28233	2SK2737	<14mOhm(20A)	2SK1257, 2SK1653, 2SK1952, 2SA2120
28234	2SK2738	<20mOhm(20A)	2SK1257, 2SK1653, 2SK1952, 2SA2120
28235	2SK2739	<0,33Ohm(8A)	-
28236	2SK274	8V, 100mA, 12GHz	-
28237	2SK2740	600V, 7A, 30W, <1,20Ohm(4A)	-
28238	2SK2741	60V, 5A, <0,160Ohm(2,5A)	-
28239	2SK2747	30V, 0,5A, <0,55Ohm	-
28240	2SK275	8V, 100mA, 4GHz	-
28241	2SK2750	<2,20Ohm(1,8A)	2SK1767, 2SK2044, 2SK2118, 2SK2144
28242	2SK2751	40V, Idss1...3.7mA, Up<3,5V	-
28243	2SK2752	6V, 8mA, Up0,2...2V	-
28244	2SK2753-01	120V, 50A, 150W, <32mOhm	-
28245	2SK2754-01L,S	<0,65Ohm(5A)	2SK1865, 2SK2366Z
28246	2SK2755-01	<0,45Ohm(9A)	2SK1488, 2SK1516, 2SK1753, 2SK1785
28247	2SK2756-01R	2SK2755, , 80W	2SK1452, 2SK1523, 2SK1696, 2SK1831...32
28248	2SK2757-01	500V, 10A, 80W, <0,90Ohm(5A)	2SK1503, 2SK2366
28249	2SK2758-01L,S	2SK2757	2SK1865, 2SK2366Z
28250	2SK2759-01R	<0,55Ohm(7,5A)	2SK1331, 2SK1269, 2SK1405, 2SK1524
28251	2SK276	6V, 80mA, 18GHz	-
28252	2SK2760-01R	600V, 9A, 60W, <1,20Ohm(4,5A)	2SK1405, 2SK1686, 2SK2148
28253	2SK2761-01MR	600V, 10A, 50W, <10Ohm(5A)	-
28254	2SK2762-01L,S	800V, 4A, 80W, <40Ohm(2A)	2SK1528, 2SK2089
28255	2SK2763-01	2SK2762, 100W	2SK727, 2SK1341, 2SK1649...50, 2SK1794
28256	2SK2764-01R	2SK2762	2SK1463, 2SK1684, 2SK1859, 2SK2147
28257	2SK2765-01	800V, 7A, 125W, <20Ohm(3,5A)	2SK1032, 2SK1342, 2SK1358, 2SK1502
28258	2SK2766-01R	2SK2765, , 80W	2SK1464, 2SK1685, 2SK1774...75
28259	2SK2767-01	900V, 3,5A, 80W, <5,50Ohm(2A)	2SK1501, 2SK1639, 2SK1643, 2SK1807

28260	2SK2768-01L,S	2SK2767	2SK1528, 2SK2004
28261	2SK2769-01MR	2SK2767, , 40W	2SK1356, 2SK1460, 2SK1995
28262	2SK277	40/60ns	BUZ 330...331, 2SK298, 2SK501
28263	2SK2770-01	2SK2767, 100W	2SK1339, 2SK1341, 2SK1760, 2SK1794
28264	2SK2771-01R	900V, 9A, 125W, <1,4Ohm	2SK1464, 2SK1775
28265	2SK2772	<1,3Ohm(2A)	2SK1920, 2SK2099
28266	2SK2776	500V, 8A, 65W, <0,85Ohm(4A)	2SK1316, 2SK2187, 2SK1864...65
28267	2SK2777	600V, 6A, 65W, <1,25Ohm(3A)	2SK1915, 2SK2089
28268	2SK278	2SK277, 400V	BUZ 330...331, 2SK298, 2SK501
28269	2SK2788	60V, 2A, <0,16Ohm(1A)	2SK1273, 2SK1470, 2SK1717, 2SK2315
28270	2SK2789	<85mOhm(15A)	-
28271	2SK279	5V, 250mA, 8GHz	-
28272	2SK2790	<0,7Ohm(3A)	2SK1308, 2SK1691
28273	2SK2792	600V, 4A, 30W, <2,4Ohm(2A)	2SK1118, 2SK1404, 2SK1637, 2SK2044
28274	2SK2793	500V, 5A, 30W, <1,5Ohm(2,5A)	2SK1351, 2SK1608, 2SK1627, 2SK2236
28275	2SK2796(L,S)	60V, 5A, 20W, <0,16Ohm(3A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
28276	2SK2797	<3,5Ohm(1A)	2SK2235, 2SK2250
28277	2SK280	5V, 100mA, 15GHz	-
28278	2SK2800	<20mOhm(20A)	2SK1418, 2SK1542, 2SK1911
28279	2SK2801	<10mOhm(25A)	BUK 556-60
28280	2SK2802	integr. Rg	
28281	2SK2806-01	30V, 35A, 30W, <0,02Ohm	BUK 556-60, 2SK1542, 2SK1911
28282	2SK2807-01L,S	30V, 35A, 30W, <0,02Ohm	2SK1919, 2SK2164, 2SK2266, 2SK2376
28283	2SK2808-01MR	30V, 35A, 30W, <0,02Ohm	2SK1421, 2SK1653, 2SK2120, 2SK2312
28284	2SK2809-01	60V, 50A, 50W, <0,02Ohm	2SK1653, 2SK2529
28285	2SK281	5V, 120mA, 8GHz	-
28286	2SK2823	20V, 0,1A, <40Ohm(10mA)	BST 82, 2SK1590, 2SK2158
28287	2SK2824	2SK2823	-
28288	2SK2825	2SK2823	-
28289	2SK2829	500V, 15A, <0,55Ohm	2SK1610, 2SK1678, 2SK1745, 2SK1757
28290	2SK283	80V, Idss>1,2mA, Up0,75V	-
28291	2SK2830	500V, 9A, <0,55Ohm	2SK2364
28292	2SK2837	<0,27Ohm(10A)	2SK1411, 2SK1500, 2SK1680, 2SK2057
28293	2SK2838	400V, 5,5A, 40W, <1,2Ohm(3A)	2SK1691, 2SK2355Z...56Z
28294	2SK2847	900V, 8A, 85W, <1,4Ohm(4A)	2SK1464, 2SK1775, 2SK1685...86
28295	2SK286	80/110ns	2SK225...227, 2SK343...344
28296	2SK287	25/350ns	2SK225...227, 2SK343...344
28297	2SK288	2SK287, 80V	2SK225...227, 2SK343...344
28298	2SK2887	200V, 3A, 20W, <0,9Ohm(1,5A)	2SK782
28299	2SK289	80V, 8A, 100W, 25/350ns	2SK175...176, BUZ 33
28300	2SK290	2SK289, 100V	2SK175...176, BUZ 33
28301	2SK291	15V, Idss>5mA, Up<3V	-
28302	2SK292	20V, Idss>0,5mA, Up<2,5V	BF 410A, 2SK193, 2SK195, 2SK212
28303	2SK293(A)	300V, 7A, 100W, <1,3Ohm	2SK277...278, 2SK298, 2SK501
28304	2SK294	80V, 5A, 30W, 0,4Ohm, 40/70ns	IRF 510...513, 2SK357...358, 2SK917

28305	2SK295	2SK294, 100V	IRF 510, IRF 512, 2SK357...358, 2SK917
28306	2SK296	20/70ns	IRF 712
28307	2SK298	50/120ns	BUZ 54, BUZ 94, 2SK512, 2SK724
28308	2SK299	2SK298, 450V	BUZ 54, BUZ 94, 2SK512, 2SK724
28309	2SK30(A,ATM)	50V, Idss>0,3mA, Up<5V	BFS 70, 2N3821, 2SK40, 2SK46, 2SK59
28310	2SK300	15V, Idss>9,5mA, Up<2V	BF 513
28311	2SK301	Up<5V	BFS 70, 2N3821, 2N4220, 2SK104
28312	2SK302	20V, Idss>1,5mA, Up<2,5V	-
28313	2SK303	2SK304, SMD	2SK160
28314	2SK304	30V, Idss>0,6mA, Up<4V	BFS 70, 2N3821, 2N4220, 2SK104, 2SK301
28315	2SK308	60/160ns	BUZ 35, 2SK401, 2SK631, 2SK633
28316	2SK310	25/70ns	BUZ 60, BUZ 76, IRF720, IRF722, 2SK1244
28317	2SK311	2SK310, 450V	BUZ 41A...42, 2SK1244, 2SK1493...1494
28318	2SK312	70/200ns	BUZ 45, BUZ 64, 2SK512, 2SK724
28319	2SK313	2SK312, 450V	BUZ 45, 2SK512, 2SK724
28320	2SK314	40V, 50mA, Idss>5mA, Up<3V	BC 264, BF 410C, 2SK147, 2SK168
28321	2SK315	20V, Idss>2,5mA, Up<3,5V	BF 410B, 2SK192
28322	2SK316	10V, Idss>5mA, Up<3V	2SK321
28323	2SK319	50/120ns	BUZ 41A...42, BUZ 60, 2SK893, 2SK1246
28324	2SK32	35V, 20mA, Idss<10mA, Up<4V	BFS 70, 2N3821, 2SK40, 2SK46, 2SK59
28325	2SK320	2SK319, 450V	BUZ 41A...42, 2SK552, 2SK893, 2SK1246
28326	2SK321	15V, Idss>5mA, Up<3V	-
28327	2SK322	15V, 50mA, Idss>5mA, Up<3V	-
28328	2SK323	40V, Idss>1,6mA, Up<1,5V	-
28329	2SK324	400V, 10A, 120W, <0.6Ohm	BUZ 45, BUZ 64, 2SK312...313
28330	2SK325	2SK324, 450V, <0.7Ohm	BUZ 45, BUZ 339, 2SK313, 2SK724
28331	2SK33	20V, Idss2,5..20mA, Up<8V	BF 244...245, BFS 71, 2N3822...23
28332	2SK330	50V, Idss>1,2mA, Up<0,6V	2N5457, 2SK246
28333	2SK334	2SK331, SMD	-
28334	2SK336	50V, 0,4A, 0,6W, 12Ohm	-
28335	2SK337	<100Ohm(20mA)	-
28336	2SK338	<1,5Ohm(2A)	BUZ 41A...42, BUZ 60, 2SK552, 2SK1246
28337	2SK339	<0,5Ohm(3A)	BUZ 30, BUZ 73, IRF 510, IRF 512, 2SK917
28338	2SK34	30V, Idss>0,3mA, Up<6V	BFS 70, 2N3369, 2N3821, 2SK381
28339	2SK343	100/90ns	2SK226...227
28340	2SK344	2SK343, 160V	2SK227
28341	2SK345	40/70ns	IRF 510...513, 2SK357, 2SK463, 2SK917
28342	2SK346	2SK345, 60V	IRF 510...513, 2SK357, 2SK463, 2SK917
28343	2SK347(L,S)	400V, 1A, 10W	2SK535, 2SK579...580, 2SK945, 2SK1151
28344	2SK349	70/200ns	BUZ 326, BUZ 351, 2SK1752, 2SK1785
28345	2SK35	Up<1,6V	2N5247, 2SK186...187, 2SK363...364
28346	2SK350	2SK349, 450V	BUZ 339, 2SK896, 2SK1752, 2SK1785
28347	2SK351	100/300ns	BUZ 54, BUZ 84, 2SK793, 2SK1213
28348	2SK352	250V, 0,3A, 8W, 30Ohm	BST 78, 2SK511
28349	2SK353	5V, 120mA, 15GHz	-

28350	2SK354(A)	5V, 150mA, 8GHz	-
28351	2SK355	<0,18Ohm(10A)	BUZ 35, 2SK401, 2SK1529
28352	2SK356	<0,25Ohm(10A)	BUZ 64, BUZ 325, 2SK401, 2SK412
28353	2SK357	150V, 5A, 40W, <0,9Ohm(3A)	BUZ 60, 2SK924, 2SK1391
28354	2SK358	250V, 5A, 40W, <1Ohm(3A)	BUZ 60, 2SK924, 2SK1391
28355	2SK359	Up<2V	-
28356	2SK362	50V, Idss>1,2mA, Up<1,5V	2SK163, 2SK365
28357	2SK363	40V, Idss>5mA, Up<1,2V	2N5247, 2SK130, 2SK147, 2SK151, 2SK162
28358	2SK364	40V, Idss>2,6mA, Up<1,5V	2SK187, 2SK366
28359	2SK365	2SK362	2SK163, 2SK362
28360	2SK366	2SK364	2SK187, 2SK364
28361	2SK367	100V, Idss>0,6mA, Up<3,5V	-
28362	2SK368	2SK367, SMD	-
28363	2SK369	2SK363	2SK363
28364	2SK37	20V, Idss0,5..6mA, Up<4,5V	BFS 70, 2N3821, 2SK161
28365	2SK370	2SK364	2SK364
28366	2SK371	2SK363	2SK363
28367	2SK372	2SK363	2SK363
28368	2SK373	2SK367	2SK367
28369	2SK374	55V, 30mA, Idss>1mA, Up<5V	-
28370	2SK375	20/70ns	2SK535, 2SK945, 2SK1151, 2SK1672
28371	2SK376	20V, Idss0,06..0,8mA	-
28372	2SK378	5V, 130mA, Idss>15mA, Up<4V	-
28373	2SK379	400V, 8A, 100W, <1,5Ohm	BUZ 94, 2SK278, 2SK298, 2SK554...555
28374	2SK38	20V, Idss0,4..5mA, Up<9V	BFS 70, 2N3369, 2N3821, 2SK381
28375	2SK380	2SK379, 450V, <2Ohm	BUZ 94, 2SK554...555, 2SK636, 2SK1495
28376	2SK381	50V, Idss>0,3mA, Up<6V	2N3369
28377	2SK382	25/70ns	BUZ 40, BUZ 74, IRF 820...821, 2SK892
28378	2SK383	<0,18Ohm,60/150ns	BUZ 20, BUZ 72, IRF 532, 2SK918, 2SK921
28379	2SK384	20/20ns	-
28380	2SK385	<0,6Ohm(5A)	2SK693...694
28381	2SK386	2SK385, 450V, <0,7Ohm(5A)	2SK693...694
28382	2SK387	150V, 12A, 150W, <0,18Ohm	2SK1530
28383	2SK388	2SK387, 250V, <0,25Ohm(10A)	2SK1530
28384	2SK38A	2SK38, Idss0,7..7mA, Up<5V	BFS 70, 2N3369, 2N3821, 2SK381
28385	2SK39(A)	20V, Idss35..564A	2SK92...93, 2SK103
28386	2SK398	<0,25Ohm(5A)	BUZ 23, 2SK631, 2SK633, 2SK1529
28387	2SK399	2SK398	2SK631, 2SK633, 2SK1529
28388	2SK40	50V, Idss0,3..6,5mA, Up<5V	BFS 70, 2N3369, 2N3821, 2SK46, 2SK59
28389	2SK400	40/110ns	2SK412
28390	2SK401	65/180ns	BUZ 64, 2SK312...313, 2SK573, 2SK1401
28391	2SK402	50/120ns	BUZ 330...331, BUZ 353...354, 2SK501
28392	2SK403	2SK402, 450V	BUZ 330...331, BUZ 353...354, 2SK557
28393	2SK404	20V, Idss>1,2mA, Up<2V	BC 264A, BFW 12, 2N4340, 2N5484
28394	2SK405	160V, 8A, 100W, <1,4Ohm(5A)	2SK1529

28395	2SK406	5V, 120mA, 18GHz	-
28396	2SK407	5V, 120mA, 18GHz	-
28397	2SK408	180V, 2A, PQ>10W(28MHz)	-
28398	2SK409	2SK408	-
28399	2SK41	18V, Idss>0,6mA, Up<5V	BFS 70, 2N3821, 2N5246, 2SK161
28400	2SK411	600V, 5A, 100W	BUZ 54, BUZ 84, 2SK351, 2SK793, 2SK1403
28401	2SK412	65/180ns	BUZ 326, BUZ 351, 2SK573, 2SK1401
28402	2SK413	50/110ns	2SK400, 2SK405, 2SK631, 2SK633
28403	2SK414	2SK413, 160V	2SK400, 2SK405, 2SK633
28404	2SK415	50/120ns	BUZ 307, 2SK603, 2SK954, 2SK1339
28405	2SK416	25/35ns	2SK462, 2SK468, 2SK1282, 2SK1973
28406	2SK417	60V, 10A, 60W, <0,14Ohm	BUZ 20, BUZ 72, 2SK442, 2SK672
28407	2SK418	400V, 2A, 50W, <2,2Ohm	BUZ 40, IRF 710, 2SK382, 2SK892
28408	2SK419	2SK418, 450V, <2,5Ohm	BUZ 40, 2SK382, 2SK892
28409	2SK41NP	2SK41	
28410	2SK42	10V, Idss1..5mA, Up>0,3V	2N5246, 2SK107, 2SK161
28411	2SK420	400V, 5A, 60W, <1,4Ohm	BUZ 41A...42, 2SK552...553, 2SK1440
28412	2SK421	2SK420, 450V, <1,6Ohm	BUZ 41A...42, 2SK552...553, 2SK1440
28413	2SK422	17/12ns	BST 70, 2SK940...941, 2SK975
28414	2SK423	<4,5Ohm,15/20ns	BSS 296, 2SK941
28415	2SK424	600V, 3A, 100W, <1,5Ohm(2A)	BUZ 53, BUZ 83
28416	2SK425	50V, Idss>1mA, Up<1,2V	-
28417	2SK426	2SK425	-
28418	2SK427	15V, Idss>1,2mA, Up<1,5V	2SK186
28419	2SK428	60/120ns	BUZ 20, BUZ 72, IRF 533, 2SK442, 2SK672
28420	2SK429(L,S)	35/50ns	2SK1113, 2SK1299, 2SK1254, 2SK1284
28421	2SK43(S)	30V, Idss>0,9mA, Up<1,49V	2SK121, 2SK163, 2SK170, 2SK186...187
28422	2SK430(L,S)	2SK429, 150V, <1Ohm(2A)	2SK1335
28423	2SK432	250V, +-10A, 120W, <0,4Ohm	BUZ 45, BUZ 64, 2SK401, 2SK512
28424	2SK433	50V, Idss>0,3mA, Up<6V	-
28425	2SK435	22V, 0,1A, Idss>6mA, Up<2,5V	2SK494
28426	2SK436	2SK427, SMD	2SK425
28427	2SK437	12GHz	-
28428	2SK438	12GHz	-
28429	2SK439	20V, 30mA, Idss>4mA, Up<2V	-
28430	2SK44	20V, Idss0,06..0,3mA, Up<4V	-
28431	2SK440	40/110ns	BUZ 30, BUZ 73, 2SK741, 2SK1319...20
28432	2SK441	500V, 0,3A, 0,75W, <50Ohm	2SK384
28433	2SK442	70V, 10A, 30W, <0,4Ohm	BUZ 20, BUZ 72, 2SK740, 2SK918
28434	2SK443	2SK444, SMD	BF 512...513, 2SK322
28435	2SK444	15V, Idss5..38mA, Up<2V	BC 264C...D, BF 410C...D, 2SK147, 2SK168
28436	2SK445	2SK444	BC 264C...D, BF 410C...D, 2SK147, 2SK168
28437	2SK446	20V, +-2A, 20W, <0,5Ohm(3A)	2SK416, 2SK973, 2SK1763
28438	2SK447	<0,24Ohm(15A)	2SK678, 2SK693
28439	2SK448	250V, +-10A, 120W, <0,5Ohm	BUZ 64, 2SK312, 2SK401

28440	2SK449	450V, +-8A, 120W, <1,25Ohm	BUZ 45, 2SK312, 2SK512
28441	2SK44SP	2SK44	-
28442	2SK45	22V, Idss0,5..6mA, Up<4,5V	BFS 70, 2N3369, 2N3821, 2N4220, 2SK104
28443	2SK455	2SK456, SMD	-
28444	2SK457	Up<5V, 3GHz	-
28445	2SK458	<1,5Ohm	-
28446	2SK459	<0,5Ohm(3A)	BUZ 31...32, 2SK890, 2SK925, 2SK1393
28447	2SK46	30V, Idss0,3..3mA, Up<5V	BFS 70, 2N3369, 2N3821, 2N4220, 2SK59
28448	2SK462	60V, +-2A, 20W, <0,5Ohm(1A)	2SK468, 2SK612, 2SK973, 2SK1282
28449	2SK463	60V, +-5A, 40W, <0,3Ohm(3A)	2SK294...295, 2SK346, 2SK357, 2SK917
28450	2SK464	60V, +-8A, 50W, <0,2Ohm(4A)	IRF 521, IRF 523, 2SK470, 2SK993
28451	2SK468	100V, +-2A, 20W	2SK429...430, 2SK612, 2SK1113, 2SK1299
28452	2SK47	20V, Idss0,5..6mA, Up<4,5V	BFS 70, 2N3369, 2N3821, 2N4220, 2SK104
28453	2SK470	<0,3Ohm(4A)	BUZ 30, BUZ 73, IRF 520, IRF 522
28454	2SK477	<0,8Ohm(3A)	2SK1319...20, 2SK1400, 2SK1667
28455	2SK479	250V, +-15A, 100W, <0,4Ohm	2SK559, 2SK573, 2SK1135, 2SK1401
28456	2SK48	20V, Idss0,3..3mA, Up<2,3V	BF 410A, 2N4339, 2N5358, 2SK193
28457	2SK482	450V, +-5A, 50W, <2Ohm(2A)	BUZ 41A...42, IRF 830, 2SK1246, 2SK1440
28458	2SK484	450V, +-8A, 100W, <1Ohm	BUZ 330...331, 2SK559, 2SK634, 2SK1488
28459	2SK49	20V, Idss0,5..6mA, Up<2,5V	BF 410A, 2SK193, 2SK195, 2SK212
28460	2SK490	400V, +-10A, 100W, <0,8Ohm	BUZ 325...326, 2SK559, 2SK634, 2SK1488
28461	2SK492	50V, Idss>1mA, Up<2V	-
28462	2SK493	15V, Idss>5mA, Up<2,2V	BC 264C...D, BF 410C...D, 2SK147, 2SK168
28463	2SK494	2SK435	2SK435
28464	2SK495	30/40ns	2SK346, 2SK463, 2SK917, 2SK920
28465	2SK496	2SK495	BUK 441-60, 2SK499, 2SK705, 2SK1255
28466	2SK497	30/40ns	2SK346, 2SK463, 2SK917, 2SK920
28467	2SK498	2SK497	2SK1059, 2SK1112, 2SK1471, 2SK1719
28468	2SK499	2SK497	BUK 441-60, 2SK496, 2SK705, 2SK1255
28469	2SK50	10V, Idss0,07..1mA	2N3367, 2N4117...18, 2SK92...93, 2SK103
28470	2SK500	60V, 10A, 80W, <0,12Ohm	2SK399, 2SK631
28471	2SK501	55/40ns	BUZ 330...331, BUZ 385
28472	2SK502	35/15ns	BUZ 76, 2SK310...311, 2SK1244
28473	2SK503	2SK502	BUK 445-450, 2SK1444, 2SK1862...63
28474	2SK505	15V, Idss>10mA, Up<3,5V	2SK507
28475	2SK507	2SK505	2SK505
28476	2SK508	2SK505, SMD	-
28477	2SK511	250V, 0,3A, 8W, <50Ohm(0,1A)	-
28478	2SK512	125W, <0,65Ohm, 75/300ns	BUZ 45, 2SK1785
28479	2SK513	50/120ns	BUK 456/800, 2SK1600...1601, 2SK1638
28480	2SK514	Up<4,5V	-
28481	2SK515	2SK514, SMD	-
28482	2SK518	30V, 0,05A, Idss>30mA, Up<9V	BF 244C, BF 245C, 2SK519
28483	2SK519	2SK518	BD 244C, BF 245C, 2SK518
28484	2SK520	2SK518, SMD	BF 545C



28485	2SK521	18V, Idss>2mA, Up<5,5V	2SK107, BFS 71, 2N3822
28486	2SK522	30V, Idss>4mA, Up<3V	BF 410C
28487	2SK523	Up<1,2V	-
28488	2SK525	<0,28Ohm(5A)	2SK1035...1036
28489	2SK526	250V, 10A, 40W, <0,6Ohm(5A)	2SK1036, 2SK1762
28490	2SK527	60V, 10A, 40W, <0,14Ohm(5A)	BUK 442/60, 2SK1033, 2SK1093, 2SK1974
28491	2SK528	400V, 2A, 30W, <2,2Ohm(1A)	BUK 444-400, 2SK1833, 2SK1988...89
28492	2SK529	2SK528, 450V, <2,6Ohm(1A)	BUK 444-450, 2SK1833, 2SK1988...89
28493	2SK530	400V, 5A, 40W, <1,4Ohm(3A)	2SK1231...32, 2SK1608, 2SK1990...91
28494	2SK531	2SK530, 450V, <1,6Ohm(3A)	2SK1231...32, 2SK1608, 2SK1990...91
28495	2SK532	<0,085Ohm(6A)	BUK 445-100, 2SK1094, 2SK1419
28496	2SK533	2SK523, Igss<100pA	-
28497	2SK534	75/220ns	BUZ 355...358, 2SK695, 2SK793, 2SK1341
28498	2SK535(L,S)	20/45ns	2SK579...80, 2SK945, 2SK1151...52, 2SK1672
28499	2SK536	50V, 100mA, 20Ohm	-
28500	2SK537	900V, 1A, 60W, <9Ohm(0,5A)	BUZ 50, 2SK1199, 2SK1338
28501	2SK538	<4,5Ohm(1,5A)	BUZ 357...358, 2SK794, 2SK1339
28502	2SK539	900V, 5A, 150W, <2,5Ohm(3A)	-
28503	2SK541	12V, Idss>14mA, Up<2,5V	-
28504	2SK542	<1,5Ohm(1A)	IRF 612...613, 2SK923
28505	2SK543	2SK544, SMD	-
28506	2SK545	2SK546, SMD	-
28507	2SK546	40V, Idss>0,03mA, Up<4V	-
28508	2SK549	55/100ns	BUZ 20, BUZ 72, IRF 532...33, 2SK1114
28509	2SK550	75W, <0,045Ohm, 115/245ns	BUZ 21, IRF 541, IRF 543, 2SK1115...16
28510	2SK551	55/100ns	BUZ 31...32, 2SK459, 2SK720, 2SK890
28511	2SK552	45/115ns	BUZ 41...42, BUZ 90, IRF 830, 2SK1246
28512	2SK553	2SK552, 500V	BUZ 41...42, BUZ 90, IRF 830, 2SK1246
28513	2SK554	65/155ns	BUK 657-500, IRF 840, 2SK894, 2SK1496
28514	2SK555	2SK554, 500V, <1Ohm(4A)	BUK 657-500, IRF 840, 2SK894, 2SK1496
28515	2SK556	<0,55Ohm(6A)	2SK725, 2SK899, 2SK1610, 2SK1745
28516	2SK557	2SK556, 500V, <0,6Ohm(6A)	2SK725, 2SK899, 2SK1610, 2SK1745
28517	2SK558	500V, 12A, 100W, 85/300ns	2SK557, 2SK560, 2SK1516, 2SK1753
28518	2SK559	<0,36Ohm(8A)	2SK725, 2SK899, 2SK1745, 2SK1757
28519	2SK56	10V, Idss0,7..10mA, Up<4V	BF 410A, BFS 70, 2N3821, 2SK161
28520	2SK560	2SK559, 500V, 0,4Ohm(8A)	2SK725, 2SK899, 2SK1745, 2SK1757
28521	2SK561	100V, 30A, 150W, <0,07Ohm	BUZ 24, 2N6764, 2SK906, 2SK1303
28522	2SK562	50V, 39A, 125W, <0,04Ohm	BUZ 347...348, 2SK857, 2SK905, 2SK1124
28523	2SK564	100V, 32A, 125W, <0,06Ohm	BUZ 349, 2SK906, 2SK1303, 2SK1433
28524	2SK565	500V, 9,6A, 125W, <0,6Ohm	2SK557, 2SK637, 2SK1516, 2SK1753
28525	2SK566	800V, 2,9A, 78W, <4Ohm	2SK415, 2SK538, 2SK603, 2SK762
28526	2SK568	450V, +-8A, 150W, <0,75Ohm	-
28527	2SK569	6V, Idss>15mA, Up<2V	-
28528	2SK57	Up<4V	BF 510, 2SK160
28529	2SK570(S)	6V, Idss>12mA, Up<2V	-

28530	2SK571	5V, Idss30..150mA	-
28531	2SK572	<0,18Ohm(10A)	BUZ 350, 2SK622, 2SK1267, 2SK1491
28532	2SK573	<0,32Ohm(10A)	BUZ 323, 2SK944, 2SK1401, 2SK1641
28533	2SK575	5V, Idss>5, Up<3V, 12GHz	-
28534	2SK578	150V, +-15A, 120W, <0,22Ohm	-
28535	2SK579(L,S)	28/48ns	2SK1151...52, 2SK1672
28536	2SK580(L,S)	2SK579, 500V, <6Ohm(1A)	2SK1152, 2SK1672
28537	2SK581	30V, Idss>0,9mA, Up<1,49V	-
28538	2SK582	500MHz	-
28539	2SK583	50V, 0,2A, 0,6W, 20Ohm	BSS 100, BST 72
28540	2SK585	5V, Idss>20mA, Up<4V, 12GHz	-
28541	2SK586	5V, Idss>2mA, Up<3V, 12GHz	-
28542	2SK587	5V, Idss>2mA, Up<3V, 12GHz	-
28543	2SK59	30V, Idss0,3..1,4mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK46, 2SK104
28544	2SK590	10V, Idss>20mA, Up<4V, 1GHz	-
28545	2SK591	<55mOhm(6A)	2SK1094
28546	2SK593	800MHz	-
28547	2SK595	2SK596, SMD	-
28548	2SK596	20V, Idss>0,1..0,8mA	KSK 596
28549	2SK60	170V, 5A, 63W, 16Ohm	-
28550	2SK600	60V, 25A, 75W, <0,055Ohm	BUZ 21, IRF 540...543, 2SK942, 2SK1115
28551	2SK601	80V, 0,5A, 1W, <4Ohm, 15/20ns	BST 80, 2SK1078...1079
28552	2SK602	800V, 1A, 40W, <8Ohm	BUZ 78, 2SK537
28553	2SK603	800V, 3A, 80W, <5Ohm	BUZ 307, 2SK415, 2SK954
28554	2SK604	800V, 5A, 80W, <3,5Ohm	BUZ 355...357, 2SK534, 2SK695, 2SK793
28555	2SK606	Up<3V	2SK193, 2SK195
28556	2SK607	2SK606	2SK193, 2SK195
28557	2SK608	2SK606, SMD	2SK238
28558	2SK609	6V, Idss>20mA, Up<3,5V	-
28559	2SK61	18V, Idss1..10mA, Up<4V	BF 244A...245A, BFS 71, 2N3822...23
28560	2SK610	400V, 3A, 80W, <4Ohm	BUZ 307, 2SK415, 2SK635, 2SK954
28561	2SK611(Z)	<5Ohm(0,5A)	2SK468
28562	2SK612(Z)	<0,45Ohm(1A)	2SK468, 2SK429...430, 2SK1283
28563	2SK613	15V, Idss>13,4mA, Up<2V	-
28564	2SK614	15/20ns	BST 70, 2SK423, 2SK940...941
28565	2SK615	2SK614, 1W	BST 70, 2SK423, 2SK940...941
28566	2SK616	200V, 22A, 125W, <0,12Ohm	BUZ 350, 2SK1491, 2SK2007, 2SK2058
28567	2SK618	10V, Idss>20mA, Up<4V	-
28568	2SK619	70V, 0,3A, 10W	-
28569	2SK620	50V, 0,1A	-
28570	2SK621	20V, 0,1A	-
28571	2SK622	<75mOhm(10A)	BUZ 350, 2SK1267, 2SK1491, 2SK2007
28572	2SK623	<0,15Ohm(10A)	2SK1491, 2SK2007, 2SK2058, 2SK2075
28573	2SK624	20V, 2mA, Idss95..385µA	-
28574	2SK625	20V, Idss>0,06mA	-

28575	2SK626	30V, 20A, 80W, <0,07Ohm	BUZ 350
28576	2SK627	2SK626, 50V	BUZ 350
28577	2SK628	100V, 5A, 40W, <0,4Ohm	BUK 442-100, BUK 542-100, 2SK992
28578	2SK629	100V, 20A, 80W, <0,1Ohm	2SK622
28579	2SK63	120V, 0,2A, 0,47W, Up<9,5V	-
28580	2SK630	160V, 5A, 40W, <0,5Ohm	-
28581	2SK631	160V, 10A, 80W, <0,2Ohm	2SK633
28582	2SK632	200V, 5A, 40W, <1,2Ohm	-
28583	2SK633	200V, 10A, 80W, <0,25Ohm	2SK412
28584	2SK634	400V, 10A, 80W, <0,7Ohm	BUZ 326, BUZ 351, 2SK559
28585	2SK635	500V, 3A, 40W, <4,5Ohm	BUZ 307, 2SK415, 2SK954
28586	2SK637	500V, 10A, 80W, <1,4Ohm	2SK557, 2SK644, 2SK1488, 2SK1753
28587	2SK638	800V, 3A, 80W, <5Ohm	BUZ 307, 2SK415, 2SK538, 2SK603
28588	2SK641	<0,8Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1752
28589	2SK642	2SK641, 500V, <1Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1753
28590	2SK643	<0,8Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1752
28591	2SK644	2SK643, 500V, <1Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1753
28592	2SK646	80/350ns	-
28593	2SK647	12GHz	-
28594	2SK648	12GHz	-
28595	2SK649	6V, 0,1A, 12GHz	-
28596	2SK65	12V, 2mA, Idss0,04..0,8mA	-
28597	2SK650	4GHz	-
28598	2SK651	4GHz	-
28599	2SK652	2SK301	2SK301
28600	2SK653	5V, 70mA, 800MHz	-
28601	2SK654(Z)	<3Ohm(0,5A)	2SK468, 2SK611...612
28602	2SK655	2SK620	-
28603	2SK656	2SK621	-
28604	2SK657	2SK620	-
28605	2SK658	2SK621	-
28606	2SK659	<75mOhm(6A)	2SK1033, 2SK1093, 2SK1256, 2SK1344
28607	2SK66	55V, Idss>0,3mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK59, 2SK104
28608	2SK660	20V, 10mA	-
28609	2SK662	2SK198	-
28610	2SK663	2SK374	-
28611	2SK664	2SK620	-
28612	2SK665	2SK621	-
28613	2SK666	900MHz	-
28614	2SK667	400V, 8A, 80W, <1,5Ohm	BUZ 330...331, BUZ 353...354, 2SK501
28615	2SK668	2SK457	-
28616	2SK67(A)	20V, Idss0,02..1mA, Up<0,8V	-
28617	2SK671	5,5V, 120mA, 12GHz	-
28618	2SK672	60V, 10A, 40W, <0,2Ohm(5A)	BUZ 20, IRF 532...533, 2SK918, 2SK1114
28619	2SK673	60V, 15A, 75W, <0,11Ohm(8A)	BUZ 21, IRF 530...531, 2SK971, 2SK1416

28620	2SK674	<60mOhm(15A)	BUK 555-60, 2SK1296
28621	2SK676	5V, 70mA, 12GHz	-
28622	2SK677	5V, 100mA, 12GHz	-
28623	2SK679	<1Ohm(0,5A)	BST 70, 2SK422, 2SK940
28624	2SK679	<1Ohm(0,5A)	BST 70, 2SK422, 2SK940
28625	2SK68(A)	50V, Idss0,5..12mA, Up<1,5V	2SK106, 2SK121, 2SK163, 2SK170, 2SK184
28626	2SK680(A)	2SK681, SMD, +-1A	2SK1726
28627	2SK681(A)	2SK679, +-1A, 1W	2SK975, 2SK1272, 2SK1274, 2SK1733
28628	2SK682	<0,55Ohm(6A)	BUK 638-500
28629	2SK683	2SK682, 500V, <0,6Ohm(6A)	BUK 638-500
28630	2SK684	800V, 7A, 100W, <1,5Ohm(4A)	2SK1032, 2SK1358, 2SK1502, 2SK1614
28631	2SK685	1000V, 5A, 100W, <2Ohm(3A)	BUK 638-1000, BUZ 380...381
28632	2SK686	60V, 5A, 40W, <0,3Ohm(2,5A)	2SK294, 2SK346, 2SK463, 2SK917
28633	2SK687	60V, 10A, 60W, <0,18Ohm(5A)	2SK442, 2SK549, 2SK672, 2SK970, 2SK1114
28634	2SK688	60V, 15A, 60W, <0,12Ohm(8A)	BUK 552-60, 2SK673, 2SK971, 2SK1416
28635	2SK689	6V, 70mA, Idss13..70mA, 4GHz	-
28636	2SK69	140V, 0,1A, 0,8W	-
28637	2SK692	20V, Idss>0,06mA	-
28638	2SK693	<0,4Ohm(7A)	2SK678, 2SK1333, 2SK1544
28639	2SK694	<0,5Ohm(7A)	2SK678, 2SK1333, 2SK1544
28640	2SK695	800V, 5A, 100W, <3Ohm(3A)	2SK793...94, 2SK727, 2SK1760, 2SK1794
28641	2SK696	1000V, 3A, 100W, <4Ohm(2A)	2SK727, 2SK794, 2SK1461, 2SK1649...50
28642	2SK697	5V, Idss15..50mA, 50MHz	-
28643	2SK698	450V, +-10A, 120W, <0,6Ohm	2SK556...557, 2SK642, 2SK644, 2SK683
28644	2SK699	<1,2Ohm(1A)	2SK1284
28645	2SK70	100V, 10A, 100W, Idss3..6A	-
28646	2SK700	2SK699, 80V, <0,8Ohm(1A)	2SK1284
28647	2SK701	2SK699, 60V, <0,6Ohm(1A)	2SK1283
28648	2SK702	<0,45Ohm(5A)	2SK991
28649	2SK703	2SK702, , 35W	BUK 542-100, 2SK1260, 2SK1265
28650	2SK704	<0,25Ohm(5A)	2SK702, 2SK991
28651	2SK705	2SK704, , 35W	BUK 541-60, 2SK1260, 2SK1255
28652	2SK707	<0,15Ohm(13A)	2SK623, 2SK901, 2SK944, 2SK1641
28653	2SK708	<0,6Ohm(10A)	2SK678, 2SK693, 2SK694, 2SK1029
28654	2SK709	20V, Idss6..32mA, Up<2,5V	2SK1000
28655	2SK71	160V, 15W, Idss30..300	-
28656	2SK710	2SK709	-
28657	2SK711	2SK709, SMD	-
28658	2SK712	120V, 10A, 25W, <0,2Ohm	2SK1035, 2SK1230, 2SK2212
28659	2SK713	450V, 4A, 25W, <1,4Ohm	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
28660	2SK714	2SK713, 500V	2SK1232, 2SK1351, 2SK1608, 2SK1627
28661	2SK715	15V, Idss5..24mA, Up<1,4V	-
28662	2SK719	900V, +-5A, 120W, <4Ohm(3A)	2SK727, 2SK1205, 2SK1461, 2SK1649...1650
28663	2SK720A	<0,23Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK1673...74
28664	2SK722	170V, 10A, 100W	2SK633

28665	2SK723	500V, 7A, 125W, <1,2Ohm	BUZ 330...331, BUZ 353...354, 2SK1032
28666	2SK724	500V, 10A, 100W, <0,67Ohm	2SK642, 2SK644, 2SK683, 2SK1753, 2SK1785
28667	2SK725	500V, 15A, 125W, <0,38Ohm	BUZ 338, 2SK788, 2SK899, 2SK1610
28668	2SK726	900V, 3A, 100W, <5Ohm(1,5A)	2SK696, 2SK1339
28669	2SK727(-01)	<2,5Ohm(2,5A)	2SK685, 2SK1461, 2SK1760, 2SK1794
28670	2SK73	200V, 0,1A, 5W, Idss<100mA	-
28671	2SK732	<0,78Ohm(5A)	-
28672	2SK733	2SK732, 120W	BUZ 339, 2SK896, 2SK1488, 2SK1785
28673	2SK734	<0,52Ohm(8A)	2SK1610, 2SK1678, 2SK1745, 2SK1757
28674	2SK735	<0,8Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1785
28675	2SK736	<80mOhm(6A)	2SK1034, 2SK1306, 2SK1558
28676	2SK737	35W,<0,15Ohm(6A)	2SK1035, 2SK1305, 2SK1558
28677	2SK738(Z)	<0,17Ohm(1A)	2SK973...74, 2SK1973
28678	2SK739(Z)	2SK738, 60V, <0,25Ohm(1A)	2SK973...74, 2SK1973
28679	2SK740	<0,15Ohm(5A)	BUZ 31...32, 2SK459, 2SK890, 2SK925
28680	2SK741	250V, 7A, 50W, <0,55Ohm(4A)	2SK477, 2SK1319...20, 2SK1400
28681	2SK742	50V, 5A, 30W, <0,22Ohm	BUK 441-60, BUK 541-60, 2SK499, 2SK1255
28682	2SK743	50V, 8A, 40W, <0,15Ohm	BUK 542-50, BUZ 72(A)F, 2SK1261, 2SK1556
28683	2SK744	50V, 10A, 50W, <0,12Ohm	BUZ 71(A)F, BUK 442-50, 2SK1033, 2SK1093
28684	2SK745	50V, 20A, 100W, <0,055Ohm	2SK622, 2SK629, 2SK1267
28685	2SK746	50V, 20A, 100W, <0,055Ohm	2SK622, 2SK629, 2SK1267
28686	2SK747	100V, 5A, 30W, <0,55Ohm	BUK 442-100, BUK 542-100, 2SK1260
28687	2SK748	100V, 8A, 40W, <0,22Ohm	BUK 443-100, BUK 543-100, 2SK1261
28688	2SK749	100V, 10A, 50W, <0,18Ohm	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
28689	2SK750	100V, 20A, 100W, <0,08Ohm	2SK622, 2SK629, 2SK1267
28690	2SK751	100V, 20A, 100W, <0,08Ohm	2SK622, 2SK629, 2SK1267
28691	2SK752	160V, 3A, 30W, <1Ohm	BUZ 73(A)F, BUK 444-200, 2SK1264
28692	2SK753	160V, 5A, 40W, <0,5Ohm	BUZ 73(A)F, BUK 444-200, 2SK1265
28693	2SK754	160V, 10A, 50W, <0,22Ohm	2SK525, 2SK1035
28694	2SK755	200V, 5A, 40W, <0,5Ohm(3A)	BUZ 73(A)F, BUK 444-200, 2SK2010
28695	2SK756	200V, 8A, 40W, <0,53Ohm(3A)	BUK 445-200, BUK 545-200, 2SK1478
28696	2SK757	<0,33Ohm(5A)	2SK526, 2SK1036, 2SK2212
28697	2SK758	250V, 5A, 40W, <0,7Ohm(3A)	2SK2010, 2SK2345
28698	2SK759	250V, 8A, 50W, <0,4Ohm(5A)	2SK1478, 2SK1568...69, 2SK1668
28699	2SK760	250V, 15A, 100W, <0,22Ohm	2SK573, 2SK1135, 2SK1401
28700	2SK761	250V, 15A, 100W, <0,22Ohm	2SK2012
28701	2SK762	400V, 3A, 40W, <3Ohm(2A)	BUK 445-450, 2SK1444, 2SK1862, 2SK2431
28702	2SK763	400V, 5A, 50W, <1,4Ohm(3A)	BUK 445-400, 2SK1231, 2SK1445, 2SK1992
28703	2SK764	400V, 10A, 100W, <0,75Ohm	BUZ 339, 2SK896, 2SK1488, 2SK1753
28704	2SK765	400V, 10A, 100W, <0,75Ohm	2SK1206, 2SK1225, 2SK1328
28705	2SK766	500V, 3A, 40W, <3,6Ohm(2A)	BUK 445-500, 2SK1572, 2SK1767
28706	2SK767	500V, 5A, 50W, <1,8Ohm(3A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
28707	2SK768	500V, 10A, 100W, <1Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1753
28708	2SK769	2SK768	2SK1206, 2SK1523, 2SK1832
28709	2SK770	600V, 2A, 40W, <5Ohm(1A)	BUK 445-600, 2SK1758, 2SK1834, 2SK1953



28710	2SK771	2SK772, SMD	-
28711	2SK772	40V, Idss1,2..12mA, Up<2,5V	-
28712	2SK773	<0,6Ohm(6A)	BUK 637-500, 2SK644, 2SK896, 2SK1488
28713	2SK774	<0,45Ohm(9A)	2SK870, 2SK1170, 2SK1518, 2SK1500
28714	2SK775	450V, 2A, 50W, <3,5Ohm(1A)	BUZ 74, IRF 820, IRF 822, 2SK892
28715	2SK776	450V, 5A, 60W, <1,6Ohm(2A)	BUZ 41A...42, 2SK1246, 2SK1440, 2SK1751
28716	2SK777	<0,65Ohm(5A)	BUZ 339, 2SK644, 2SK683, 2SK1488
28717	2SK778	<9Ohm(0,25A)	2SK296, 2SK1052
28718	2SK779	5V, 0,12A, 20..120mA, 12GHz	-
28719	2SK780	12GHz	-
28720	2SK782	200V, 5A, 40W, <0,5Ohm(3A)	2SK924, 2SK1391
28721	2SK784	<0,35Ohm(10A)	2SK868A, 2SK870, 2SK1517...18, 2SK1680
28722	2SK785	2SK784, 500V, <0,4Ohm(10A)	2SK870, 2SK1500, 2SK1518, 2SK1680
28723	2SK786	<7,5Ohm(1,5A)	BUK 456-1000, 2SK792, 2SK1793
28724	2SK787	<1,6Ohm(4A)	2SK1358, 2SK1502, 2SK1614, 2SK1692
28725	2SK788	<0,5Ohm(7A)	2SK560, 2SK725, 2SK1610, 2SK1745
28726	2SK789	<0,7Ohm(7A)	2SK559...560, 2SK725,, 2SK1610, 2SK1745
28727	2SK79	120V, 0,2A, 0,75W	-
28728	2SK790	<0,4Ohm(7A)	2SK560, 2SK725, 2SK1610, 2SK1745
28729	2SK791	<4,5Ohm(1,5A)	BUK456-1000, 2SK1456, 2SK1601, 2SK1638
28730	2SK792	2SK791, 900V	BUK456-1000, 2SK1456, 2SK1601, 2SK1638
28731	2SK793	850V, 5A, 150W, <2,5Ohm(3A)	2SK727, 2SK1341, 2SK1649...50, 2SK1794
28732	2SK794	2SK793, 900V	2SK727, 2SK1341, 2SK1649...50, 2SK1794
28733	2SK795	2SK770, 15W	-
28734	2SK796	800V, 3A, 90W, <5Ohm(2A)	BUZ 307, 2SK603, 2SK954, 2SK1339
28735	2SK796A	2SK796, 900V	2SK696, 2SK726, 2SK1339
28736	2SK797	<18mOhm(20A)	2SK1297, 2SK1514, 2SK1665
28737	2SK798	2SK797, 100V, <31mOhm(20A)	2SK1263, 2SK1304
28738	2SK799	2SK773, 450V <0,5Ohm(6A)	BUK 637-500, 2SK644, 2SK896, 2SK1488
28739	2SK800	2SK774, 450V, <0,38Ohm(9A)	2SK868A, 2SK870, 2SK1170, 2SK1518
28740	2SK801	<0,35Ohm(1A)	2SK973...974, 2SK1282
28741	2SK802	2SK801, 15W	2SK1283
28742	2SK803	160V, 8A, 40W, <0,38Ohm	BUK 445-200, BUK 545-200, 2SK1478
28743	2SK804	150V, 20A, 100W, <0,12Ohm	2SK822, 2SK1549, 2SK2008
28744	2SK805	200V, 20A, 100W, <0,19Ohm	2SK822, 2SK1549, 2SK2008
28745	2SK806	600V, 3A, 50W, <2,7Ohm(2A)	2SK1572, 2SK1767, 2SK2144
28746	2SK807	600V, 5A, 100W, <1,7Ohm(3A)	BUK 427-600, 2SK1176, 2SK1463, 2SK1859
28747	2SK808	800V, 1A, 45W, <7Ohm(0,7A)	BUK 444-800, 2SK1142, 2SK1611, 2SK1834
28748	2SK808A	2SK808, 900V	BUK 446-1000, 2SK1174, 2SK1459, 2SK1994
28749	2SK809	800V, 5A, 100W, <3Ohm(3A)	2SK1176, 2SK1463, 2SK1684, 2SK1859
28750	2SK809A	2SK809, 900V	2SK1176, 2SK1463, 2SK1684, 2SK1859
28751	2SK810	60W, <0,18Ohm(8A)	2SK1301, 2SK1559, 2SK1561
28752	2SK811	2SK810, , +12A, 35W	BUK 545-100, 2SK1035, 2SK1305
28753	2SK812	<85mOhm(15A)	2SK1291, 2SK1296
28754	2SK813	2SK810, , +21A, 35W	2SK943, 2SK1214, 2SK1345...46



28755	2SK814	<45mOhm(8A)	2SK1034, 2SK1306, 2SK1558
28756	2SK815	<85mOhm(15A)	2SK1266, 2SK1307, 2SK1348...49
28757	2SK817	<55mOhm(15A)	2SK1262
28758	2SK818	800V, 5A, 100W, <3Ohm(3A)	2SK727, 2SK1649...50, 2SK1760, 2SK1794
28759	2SK818A	2SK818, 900V	2SK727, 2SK1649...50, 2SK1760, 2SK1794
28760	2SK819	<1Ohm(5A)	BUZ 339, 2SK896, 2SK1488, 2SK1785
28761	2SK820	<0,23Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK1673
28762	2SK821	<0,23Ohm(10A)	2SK901, 2SK944, 2SK1641, 2SK1673
28763	2SK822	<0,15Ohm(13A)	2SK1670, 2SK944, 2SK1641, 2SK1673
28764	2SK823	<0,15Ohm(13A)	2SK902, 2SK1669, 2SK1671, 2SK1675
28765	2SK824	<0,5Ohm(7,5A)	2SK1268...69, 2SK1524, 2SK1831
28766	2SK825	<0,5Ohm(7,5A)	BUZ 338, 2SK899, 2SK1573, 2SK1610
28767	2SK826	<0,38Ohm(9A)	2SK1268...69, 2SK1331, 2SK1524
28768	2SK827	<0,38Ohm(9A)	BUZ 338, 2SK899, 2SK1610, 2SK1680
28769	2SK828	<0,6Ohm(7,5A)	2SK1269, 2SK1331, 2SK1524
28770	2SK829	<0,6Ohm(7,5A)	BUZ 338, 2SK899, 2SK1610, 2SK1757
28771	2SK83	25V, Idss>0,5mA, Up<2,5V	BF410A, 2SK193, 2SK195, 2SK606
28772	2SK830	<0,45Ohm(9A)	2SK1269, 2SK1331, 2SK1524
28773	2SK831	<0,45Ohm(9A)	BUZ 338, 2SK899, 2SK1500, 2SK1610
28774	2SK832	900V, +-4A, 85W, <4Ohm(3A)	2SK809A, 2SK1463
28775	2SK833	900V, +-5A, 150W, <4Ohm(3A)	2SK727, 2SK794, 2SK1341, 2SK1794
28776	2SK834	<1,6Ohm(4A)	2SK1464, 2SK1685, 2SK1775
28777	2SK84	55V, Idss0,3..6,5mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK59, 2SK104
28778	2SK843	60V, 10A, 40W, <0,1Ohm(5A)	BUK 442-60, 2SK532, 2SK1093, 2SK1974
28779	2SK844	100V, 8A, 40W, <0,15Ohm(4A)	BUK 443-100, BUZ 72(A)F, 2SK1261
28780	2SK845	450V, 5A, 40W, <1,3Ohm(3A)	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
28781	2SK846	900V, 3A, 45W, <4Ohm(1,5A)	2SK1356, 2SK1460
28782	2SK847	2SK846, 120W	2SK726, 2SK1339
28783	2SK848	250V, 0,5A, <9Ohm(0,25A)	-
28784	2SK849	<38mOhm(20A)	2SK1124, 2SK1514, 2SK1665
28785	2SK85	10V, 0,1A, 8GHz	-
28786	2SK850	<60mOhm(20A)	2SK1122, 2SK1263, 2SK1304
28787	2SK851	200V, 30A, 150W, <85mOhm	BUZ 341, 2SK1492, 2SK1669, 2SK1671
28788	2SK852	50V, Idss0,5..12mA, Up<1,5V	-
28789	2SK853(A)	50V, Idss0,5..12mA, Up<4,5V	-
28790	2SK854	<1,4Ohm(2,5A)	BUZ 41A...42, BUZ 90, 2SK893, 2SK1246
28791	2SK855	2SK854, 500V, <1,5Ohm(2,5A)	BUZ 41A...42, BUZ 90, 2SK893, 2SK1246
28792	2SK856	60V, 45A, 125W, <0,03Ohm	PRFZ 42, 2SK1418, 2SK1542, 2SK1911
28793	2SK857	2SK856	2SK1124, 2SK1297, 2SK1665, 2SK2096
28794	2SK858	35/110ns	BUZ 80, 2SK1323...24
28795	2SK859	500V, 9A, 125W, <0,8Ohm(5A)	BUZ 330, BUZ 353, 2SK557, 2SK724
28796	2SK867	400V, 15A, 120W, <0,45Ohm	BUK 637-400, 2SK1610, 2SK1745, 2SK1757
28797	2SK867A	2SK867, 450V	BUK 638-500, 2SK1610, 2SK1745, 2SK1757
28798	2SK868	400V, 20A, 130W, <0,35Ohm	2SK1169...70, 2SK1517...18, 2SK1497...98
28799	2SK868A	2SK868, 450V	2SK1169...70, 2SK1517...18, 2SK1497...98

28800	2SK869	<0,5Ohm(8A)	BUZ 338, 2SK1610, 2SK1745, 2SK1757
28801	2SK87	50V, Idss0,3..6,5mA, Up<5V	BFS 70, 2N3821, 2N4220, 2SK59, 2SK104
28802	2SK870	<0,4Ohm(10A)	2SK1170, 2SK1518, 2SK1498, 2SK1500
28803	2SK871	<5,5Ohm(2A)	2SK727, 2SK1461, 2SK1649...50, 2SK1760
28804	2SK872	<2,5Ohm(3A)	2SK1358, 2SK1614, 2SK1692, 2SK1795...96
28805	2SK873	<1,1Ohm(4A)	BUZ 330...331, BUZ 385, 2SK1488
28806	2SK874	2SK873, 500V, <1,2Ohm(4A)	BUZ 330...331, BUZ 385, 2SK1488
28807	2SK875	<0,6Ohm(6A)	BUZ 339, BUK 637-500, 2SK724, 2SK896
28808	2SK876	2SK875, 500V, <0,7Ohm(6A)	BUZ 339, BUK 637-500, 2SK724, 2SK896
28809	2SK879	50V, Idss0,3..6,5mA, Up<5V	-
28810	2SK880	50V, Idss0,6..14mA, Up<1,5V	-
28811	2SK881	18V, Idss1..10mA, Up<4V	-
28812	2SK882	20V, Idss3..14mA, Up<2,5V	-
28813	2SK888	<0,18Ohm(8A)	IRF640...643, 2SK919, 2SK922, 2SK1301
28814	2SK889	<85mOhm(15A)	BUK 456-100, 2SK1429
28815	2SK890	200V, 10A, 75W, <0,4Ohm(5A)	BUZ 31...32, 2SK925, 2SK1221, 2SK1393
28816	2SK891	<0,18Ohm(10A)	BUK 456-200, BUZ 30A, IRF 640
28817	2SK892	500V, 2,5A, 40W, <3Ohm(1A)	BUZ 74, IRF 820, IRF 822, 2SK858
28818	2SK893	500V, 5A, 75W, <1,5Ohm(2,5A)	BUZ 41A...42, IRF 830, IRF 832, 2SK1246
28819	2SK894	<0,85Ohm(4A)	BUK 657-500, 2SK1496, 2SK1574
28820	2SK895	450/20V, 12A, 125W, <0,6Ohm	BUZ 339, 2SK899, 2SK1515...16, 2SK1610
28821	2SK896	2SK895, 500V	BUZ 339, 2SK899, 2SK1516, 2SK1610
28822	2SK897(-MR)	550V, 4A, 40W, <1,5Ohm(2A)	2SK1404, 2SK1637, 2SK2044, 2SK2118
28823	2SK899	<0,33Ohm(8A)	2SK725, 2SK1170, 2SK1518, 2SK1680
28824	2SK900	250V, 12A, 80W, <0,3Ohm(6A)	2SK925, 2SK1221, 2SK1393
28825	2SK901	250V, 20A, 125W, <0,15Ohm	2SK623, 2SK944, 2SK1641, 2SK1673
28826	2SK902	<0,1Ohm(15A)	2SK1669, 2SK1671, 2SK1675...76
28827	2SK903(-MR)	800V, 3A, 40W, <4Ohm(1,5A)	
28828	2SK904	2SK903, 80W	BUK 456-800, 2SK791...792, 2SK1600...01
28829	2SK905	50V, 45A, 125W, <0,03Ohm	BUZ 347...348, 2SK857, 2SK1124, 2SK1514
28830	2SK906	100V, 32A, 125W, <0,06Ohm	BUZ 341, 2SK850, 2SK1303, 2SK1429
28831	2SK917	100V, 5A, 40W, <0,5Ohm	IRF 510, IRF 512, 2SK357, 2SK628
28832	2SK918	100V, 10A, 50W, <0,3Ohm	BUZ 20, BUZ 72, 2SK740, 2SK1427
28833	2SK919	100V, 15A, 60W, <0,15Ohm	BUZ 21, IRF 530, 2SK888, 2SK1559
28834	2SK92	20V, Idss0,02..1mA, Up<0,8V	2SK93, 2SK103
28835	2SK920	120V, 5A, 40W, <0,6Ohm	IRF 620, 2SK357
28836	2SK921	120V, 10A, 50W, <0,35Ohm	BUZ 31, 2SK740
28837	2SK922	120V, 15A, 60W, <0,2Ohm	IRF 641, IRF 643
28838	2SK923	250V, 3A, 40W, <1,4Ohm	BUZ 76, 2SK310...311
28839	2SK924	250V, 5A, 50W, <0,8Ohm	BUZ 60, 2SK358, 2SK1391
28840	2SK925	250V, 10A, 60W, <0,45Ohm	2SK926, 2SK1221, 2SK1393
28841	2SK926	<0,5Ohm(5A)	2SK925, 2SK1221, 2SK1393
28842	2SK928	<1,4Ohm(2,5A)	2SK1231...32, 2SK1351, 2SK1608, 2SK1626
28843	2SK929	2SK928, 500V, <1,5Ohm(2,5A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
28844	2SK93	20V, Idss18..564μA	2SK92, 2SK103

28845	2SK930	2SK433	-
28846	2SK931	30V, Idss5..30mA, Up<2V	-
28847	2SK932	15V, Idss5..24mA,Up<1,4V	2SK931
28848	2SK933	60V, +-15A, 35W	2SK1094, 2SK1286, 2SK1419
28849	2SK934	250V, 8A, 40W, <0,52Ohm(4A)	2SK1478, 2SK1568...69, 2SK1668
28850	2SK935	2SK934, 300V, <0,6Ohm(4A)	2SK1566, 2SK1569
28851	2SK937	Up<5V	-
28852	2SK94	50V, Idss0,5..12mA, Up<1,5V	2SK209, 2SK425
28853	2SK940	60V, 0,8A, 0,9W, <0,55Ohm	2SK975, 2SK1274
28854	2SK941	100V, 0,6A, 0,9W, <1,3Ohm	2SK1729, 2SK1736
28855	2SK942	<46mOhm(12A)	BUK 555-60, 2SK972, 2SK1115, 2SK1296
28856	2SK943	2SK942, , 40W	2SK1345, 2SK1214, 2SK1348...49, 2SK1897
28857	2SK944	250V, 22A, 150W, <0,15Ohm	2SK901, 2SK1641, 2SK1673
28858	2SK945	400V, 1A, 10W, <5Ohm(0,5A)	2SK535, 2SK579...580, 2SK1151
28859	2SK946	<5,5Ohm(2A)	2SK1356, 2SK1460
28860	2SK947(-MR)	250V, 12A, 40W, <0,3Ohm(6A)	
28861	2SK948	2SK947, 10W	-
28862	2SK949(-MR)	500V, 6A, 40W, <1,2Ohm(3,5A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
28863	2SK950	2SK949, 80W	2SK893, 2SK1156, 2SK1246, 2SK1751
28864	2SK951(-MR)	800V, 2,5A, 40W, <7Ohm(1A)	BUK 446-800, 2SK1142, 2SK1611, 2SK1834
28865	2SK952	800V, 2,5A, 40W, <7Ohm(1A)	BUZ 80, 2SK1323...24, 2SK1456, 2SK1601
28866	2SK953	2SK952, 80W	BUZ 307...308, 2SK954, 2SK1339
28867	2SK954	800V, 3A, 100W, <4Ohm(1,5A)	BUZ 307, 2SK538, 2SK603, 2SK1339
28868	2SK955	800V, 5A, 125W, <2Ohm(2,5A)	2SK534, 2SK604, 2SK695, 2SK727, 2SK793
28869	2SK956	800V, 9A, 150W, <1,5Ohm(4A)	2SK1032, 2SK1796
28870	2SK957(-MR)	900V, 2A, 40W, <8,5Ohm(1A)	
28871	2SK958	2SK957, 45W	2SK1199, 2SK1338, 2SK1324
28872	2SK959	2SK957, 80W	2SK726, 2SK1339
28873	2SK960(-MR)	900V, 3A, 40W, <5Ohm(1,5A)	
28874	2SK961	2SK960, 80W	2SK1601, 2SK1456, 2SK1638, 2SK1793
28875	2SK962(-01)	900V, 8A, 150W, <2Ohm(4A)	2SK1358, 2SK1614, 2SK1502, 2SK1795
28876	2SK963	2SK758, 15W	-
28877	2SK968	20V, Idss0,6..12mA, Up<2,5V	2SK608
28878	2SK969	16V, 20mA, Idss1,2..12mA	-
28879	2SK970	60V, 10A, 30W, <0,15Ohm(5A)	2SK1114, 2SK1300
28880	2SK971	60V, 15A, 40W, <65mOhm(8A)	BUK 552-60, 2SK942, 2SK1115...16, 2SK1347
28881	2SK972	<40mOhm(15A)	BUK 555-60, 2SK942, 2SK1115, 2SK1296
28882	2SK973(L,S)	60V, 2A, 10W, <0,35Ohm(1A)	2SK1763
28883	2SK974(L,S)	60V, 3A, 20W, <0,18Ohm(2A)	2SK1113, 2SK1254, 2SK1282
28884	2SK976	2SK970, , 20W	2SK1093, 2SK1895, 2SK1878
28885	2SK977	2SK971, , 25W	2SK1094, 2SK1286, 2SK1306
28886	2SK978	2SK972, , 30W	2SK1290, 2SK1897, 2SK1951
28887	2SK979	450V, 10A, 120W, 0,5Ohm(5A)	2SK724, 2SK896, 2SK1488, 2SK1752
28888	2SK980	12V, 40mA, Idss>8mA	-
28889	2SK981(A)	2SK762(A), 15W	-

28890	2SK982	<1Ohm(50mA), 14/75ns	BS 170, BST 170, 2SK422...423
28891	2SK984	4V, Idss0,5..2mA	-
28892	2SK987	500V, 5A, 40W, <1,6Ohm(3A)	2SK1232, 2SK1351, 2SK1608, 2SK1627
28893	2SK988	500V, 10A, 45W, <0,9Ohm(5A)	-
28894	2SK989	<0,9Ohm(5A)	2SK896, 2SK1488, 2SK1753, 2SK1785
28895	2SK990	150W, <0,65Ohm(8A)	2SK899, 2SK1610, 2SK1678, 2SK1745
28896	2SK991	<0,5Ohm(2A)	2SK702, 2SK1474
28897	2SK992	2SK991, , 30W	BUK 542-100, 2SK1260, 2SK1265
28898	2SK993	<0,25Ohm(4A)	BUK 552-100
28899	2SK994	2SK993, , +-7A, 30W	BUK 542-60, 2SK1033, 2SK1256, 2SK1344
28900	2SK995	550V, 5A, 60W, <1,8Ohm(3A)	BUK 627-600
28901	2SK996	600V, 4A, 50W, <1,8Ohm(2A)	2SK1118, 2SK1404, 2SK1637, 2SK2044
28902	2SK997	20V, 10mA, Idss>0,1mA	-
28903	2SK998	Up<2,2V	-
28904	2SM148	Igt/Ih<45/10mA	T 2700B, TAG 261-200, TAG 266-200
28905	2SM149	2SM148, 400V	T 2700D, TAG 261-400, TAG 266-400
28906	2SM150	2SM148, 600V	T 2700M, TAG 261-600, TAG 266-600
28907	2SM152	200V, 1A, Igt<15mA	TAG 137..., TAG 138...
28908	2ST1396	2SD1396	2SD1396
28909	2ST1651FI	2SD1651	2SD1651
28910	2ST1877FI	2SD1877	2SD1877
28911	2ST1942	2SC1942	2SC1942
28912	2ST2000	S 2000	S 2000
28913	2ST2000FI	S 2000AF	S 2000AF
28914	2ST3153	2SC3153, 1000V	2SC3153
28915	2ST3412	2SC3412	2SC3412
28916	2ST3460	2SC3460, 1500V	BU 508A, BU 908, BU 2508A
28917	2ST3461	2SC3461, 1500V	BU 508A, BU 908, BU 2508A
28918	2ST3485	2SC3485	2SC3485
28919	2ST3485FI	2SC3485	2SC3884A, 2SC3894
28920	2ST3552	2SC3552, 1200V	2SC3552
28921	2ST3642	2SC3642, 1200V	2SC3642
28922	2ST3679FI	2SC3679, , 1000V	BUW 11AF, 2SC4300, 2SC4427
28923	2T	YTS 4403	YTS 4403
28924	2T	SO 4403	SO 4403
28925	2T	HT 2	HT 2
28926	2T	KST 4403	KST 4403
28927	2T	MMBT 4403	MMBT 4403
28928	2U	D 1FL20U	D 1FL20U
28929	2U	KST 63	KST 63
28930	2U	MMBTA 63	MMBTA 63
28931	2V	MMBTA 64	MMBTA 64
28932	2V	KST 64	KST 64
28933	2W	2SC3937	2SC3937
28934	2W	2SC3704	2SC3704

28935	2W	MMBT 8599	MMBT 8599
28936	2W	FMMT 3905	FMMT 3905
28937	2X	YTS 4401	YTS 4401
28938	2X	KST 4401	KST 4401
28939	2X	2SC3707	2SC3707
28940	2X	SO 4401	SO 4401
28941	2X	2SC4410	2SC4410
28942	2X	MMBT 4401	MMBT 4401
28943	2Y4	BZV 49/C2V4	BZV 49/C2V4
28944	2Y7	BZV 49/C2V7	BZV 49/C2V7
28945	2YQ	2SC4969-Q	2SC4969
28946	2YQ	2SC4691-Q	2SC4691
28947	2YQ	2SC3757-Q	2SC3757
28948	2YQ	2SC3938-Q	2SC3938
28949	2YR	2SC4969-R	2SC4969
28950	2YR	2SC3938-R	2SC3938
28951	2YR	2SC3757-R	2SC3757
28952	2YR	2SC4691-R	2SC4691
28953	2YS	2SC3757-S	2SC3757
28954	2YS	2SC3938-S	2SC3938
28955	2YS	2SC4691-S	2SC4691
28956	2Z	2SC4417	2SC4417
28957	2Z	MMBT 6520	MMBT 6520
28958	2Z12..51	12..51V, 10%, 600W(1ms)	BZW70/..., BZX70/..., BZY93/...
28959	3	HSU276,277	HSU 276, HSU 277
28960	3	HVE 306A	HVE 306A
28961	3	HVC 306A	HVC 306A
28962	3	HVU 306(A)	HVU 306(A)
28963	3.0B	HZF 3.0BP	HZF 3.0BP
28964	3.0C	HZF 3.0CP	HZF 3.0CP
28965	3.3B	HZF 3.3BP	HZF 3.3BP
28966	3.3C	HZF 3.3CP	HZF 3.3CP
28967	3.6B	HZF 3.6BP	HZF 3.6BP
28968	3.6C	HZF 3.6CP	HZF 3.6CP
28969	3.9B	HZF 3.9BP	HZF 3.9BP
28970	3.9C	HZF 3.9CP	HZF 3.9CP
28971	30B	HZF 30BP	HZF 30BP
28972	30C	HZF 30CP	HZF 30CP
28973	30D1..D4	100..400V, 3A	BY 251...255, GP 30A...M, 1N5400...08
28974	30DF1..DF6	100..600V, 3A, 200..400ns	BYW 95A...C, BYW 96D...E, RG 3A...M
28975	30DL1..DL4	100..400V, 2,7A, 800ns	BYW 95A...C, BYW 96D...E, RG 3A...M
28976	30Y	BZV 49/C30	BZV 49/C30
28977	31DF1..DF6	100..600V, 3A, 30ns	BYW 178, EGP 30D...G, FE 3D...H
28978	32	MMBD 1403	MMBD 1403
28979	33	MMBD 1404	MMBD 1404

28980	33B	HZF 33BP	HZF 33BP
28981	33C	HZF 33CP	HZF 33CP
28982	33Y	BZV 49/C33	BZV 49/C33
28983	34	MMBD 1405	MMBD 1405
28984	359V	1N5052, 900V	BY 227, BYX 86, GP 15M, 1N5399
28985	35SP-01..10	50..1000V, 35A	-
28986	36B	HZF 36BP	HZF 36BP
28987	36C	HZF 36CP	HZF 36CP
28988	36Y	BZV 49/C36	BZV 49/C36
28989	37740	BC 214	BC 214
28990	37741	2N5320	2N5320
28991	38387	40361	40361
28992	38388	40362	40362
28993	384P	1N5391, 900V	BY 227, BY 255, BYW 56, GP 15M
28994	384V	1N5391, 1100V	BY 227, BY 255, BYX 87, GH 3E
28995	385A	50V, 1A, 300ns	BY 231/800, BY 245/800, MR 810...818
28996	385B	385A, 100V	BY 231/800, BY 245/800, MR 811...818
28997	385C	385A, 150V	BY 231/800, BY 245/800, MR 812...818
28998	385D	385A, 200V	BY 231/800, BY 245/800, MR 812...818
28999	385F	385A, 300V	BY 231/800, BY 245/800, MR 813...818
29000	385H	385A, 400V	BY 231/800, BY 245/800, MR 814...818
29001	385K	385A, 500V	BY 231/800, BY 245/800, MR 816...818
29002	385M	385A, 600V	BY 231/800, BY 245/800, MR 816...818
29003	38647	2N5320	2N5320
29004	386A	50V, 1A, 200ns	BY 201/2, BYT 52A, BYV 12, RGP 10A
29005	386B	386A, 100V	BY 201/2, BYT 52B, BYV 12, RGP 10B
29006	386C	386A, 150V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29007	386D	386A, 200V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29008	386F	386A, 300V	BY 201/3, BYT 52G, BYV 13, RGP 10G
29009	386H	386A, 400V	BY 201/4, BYT 52G, BYV 13, RGP 10G
29010	386K	386A, 500V	BY 201/5, BYT 52J, BYV 14, RGP 10J
29011	386M	386A, 600V	BY 201/6, BYT 52J, BYV 14, RGP 10J
29012	387A	50V, 1A, 120ns	BY 201/2, BYT 52A, BYV 12, RGP 10A
29013	387B	387A, 100V	BY 201/2, BYT 52B, BYV 12, RGP 10B
29014	387C	387A, 150V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29015	387D	388A, 200V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29016	387F	387A, 300V	BY 201/3, BYT 52G, BYV 13, RGP 10G
29017	387H	387A, 400V	BY 201/4, BYT 52G, BYV 13, RGP 10G
29018	387K	387A, 500V	BY 201/5, BYT 52J, BYV 14, RGP 10J
29019	387M	387A, 600V	BY 201/6, BYT 52J, BYV 14, RGP 10J
29020	388A	50V, 1A, 120ns	BY 201/2, BYT 52A, BYV 12, RGP 10A
29021	388B	388A, 100V	BY 201/2, BYT 52B, BYV 12, RGP 10B
29022	388C	388A, 150V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29023	388D	388A, 200V	BY 201/2, BYT 52D, BYV 13, RGP 10D
29024	388F	388A, 300V	BY 201/3, BYT 52G, BYV 13, RGP 10G



29025	388H	388A, 400V	BY 201/4, BYT 52G, BYV 13, RGP 10G
29026	388K	388A, 500V	BY 201/5, BYT 52J, BYV 14, RGP 10J
29027	388M	388A, 600V	BY 201/6, BYT 52J, BYV 14, RGP 10J
29028	398P	1N5400, 700V	BY 254...255, BYW 17/800, BYW 85
29029	398V	1N5400, 900V	BY 255, BYW 17/1000, BYW 86
29030	39Y	BZV 49/C39	BZV 49/C39
29031	3A	MA 30-A	MA 30-A
29032	3A	BC 856AW	BC 856W
29033	3A	KST 24	KST 24
29034	3A	MMBTH 24	MMBTH 24
29035	3A(p,s)	BC 856A	BC 856
29036	3A16	2N3819	2N3819
29037	3AG	2SA1324-GR	2SA1324
29038	3AO	2SA1324-O	2SA1324
29039	3AR	BC 856AR	BC 856R
29040	3As	BC 856AW	BC 856W
29041	3AY	2SA1324-Y	2SA1324
29042	3B	MA 30-B	MA 30-B
29043	3B	BC 856BW	BC 856W
29044	3B	FMMT 918	FMMT 918
29045	3B	MMBT 918	MMBT 918
29046	3B(p,s)	BC 856B	BC 856
29047	3BG	2SA1325-GR	2SA1325
29048	3BL	2SA1325-BL	2SA1325
29049	3BP	3SK139-P	3SK139
29050	3BQ	3SK139-Q	3SK139
29051	3BR	BC 856BR	BC 856R
29052	3Bs	BC 856BW	BC 856W
29053	3C	MA 30W-A	MA 30W-A
29054	3C	MMBT 5179	MMBT 5179
29055	3C2	2N5245	2N5245
29056	3C2P	2N5245	2N5245
29057	3CO	2SA1326-O	2SA1326
29058	3CY	2SA1326-Y	2SA1326
29059	3D	MA 30W-B	MA 30W-B
29060	3D	BC 856W	BC 856W
29061	3D	MMBTH 81	MMBTH 81
29062	3D(p)	BC 856	BC 856
29063	3DO	3SK143-O	3SK143
29064	3DP	3SK143-P	3SK143
29065	3DQ	3SK143-Q	3SK143
29066	3E	BC 857AW	BC 857W
29067	3E	FMMT-A42	FMMT-A42
29068	3E	MMBTH 10	MMBTH 10
29069	3E	KST 10	KST 10

29070	3E(p,s)	BC 857A	BC 857A
29071	3EM	MMBTH 10	MMBTH 10
29072	3EQ	3SK144-Q	3SK144
29073	3ER	3SK144-R	3SK144
29074	3ER	BC 857AR	BC 857R
29075	3Es	BC 857AW	BC 857W
29076	3EZ3.9..200D..	3,9..200V, +-..%, 3W	BZT03/..., BZV16/..., BZX40/..., BZV48/...
29077	3F	MMBT 6543	MMBT 6543
29078	3F	BC 857BW	BC 857W
29079	3F(p,s)	BC 857B	BC 857
29080	3FP	3SK169-P	3SK169
29081	3FQ	3SK169-Q	3SK169
29082	3FR	BC 857BR	BC 857R
29083	3Fs	BC 857BW	BC 857W
29084	3G	BC 857CW	BC 857W
29085	3G	MMBTH 11	MMBTH 11
29086	3Gs	BC 857CW	BC 857W
29087	3H	BC 857W	BC 857W
29088	3H(p)	BC 857	BC 857
29089	3J	BC 858AW	BC 858W
29090	3J(p,s)	BC 858A	BC 858
29091	3J4	SS 3J4	SS 3J4
29092	3Jp	BCV 62A	BCV 62
29093	3JR	BC 858AR	BC 858R
29094	3Js	BCV 62A	BCV 62
29095	3Js	BC 858AW	BC 858W
29096	3K	BC 858BW	BC 858W
29097	3K(p,s)	BC 858B	BC 858
29098	3Kp	BCV 62B	BCV 62
29099	3KR	BC 858BR	BC 858R
29100	3Ks	BCV 62B	BCV 62
29101	3Ks	BC 858BW	BC 858W
29102	3L	MMBTH 20	MMBTH 20
29103	3L	BC 858CW	BC 858W
29104	3L(p,s)	BC 858C	BC 858
29105	3L2U	DE 3L20U	DE 3L20U
29106	3L4	DE 3L40	DE 3L40
29107	3Lp	BCV 62C	BCV 62
29108	3LP	2SK608-P	2SK608
29109	3LQ	2SK608-Q	2SK608
29110	3LR	BC 858CR	BC 858R
29111	3LR	2SK608-R	2SK608
29112	3Ls	BCV 62C	BCV 62
29113	3LS	2SK608-S	2SK608
29114	3Ls	BC 858CW	BC 858W

29115	3M	FMMT 5087R	FMMT 5087R
29116	3M	2SC3829	2SC3829
29117	3M	BC 858W	BC 858W
29118	3M	2SC4835	2SC4835
29119	3M	2SC4808	2SC4808
29120	3M(p)	BC 858	BC 858
29121	3Mp	BCV 62	BCV 62
29122	3N	2SK620	2SK620
29123	3N	2SK664	2SK664
29124	3N100	20V, 50mA, 0,3W	-
29125	3N101	30V, 50mA, 0,3W	-
29126	3N102	40V, 50mA, 0,3W	-
29127	3N103	50V, 50mA, 0,3W	-
29128	3N104	60V, 50mA, 0,3W	-
29129	3N105	20V, 50mA, 0,3W	-
29130	3N106	40V, 50mA, 0,3W	-
29131	3N107	60V, 50mA, 0,3W	-
29132	3N108	50V, 20mA, 0,3W	-
29133	3N109	50V, 20mA, 0,3W	-
29134	3N110	50V, 20mA, 0,3W	-
29135	3N111	50V, 20mA, 0,3W	-
29136	3N114	30V, 20mA, 0,3W	-
29137	3N115	30V, 20mA, 0,3W	-
29138	3N116	30V, 20mA, 0,3W	-
29139	3N117	50V, 20mA, 0,3W	-
29140	3N118	50V, 20mA, 0,3W	-
29141	3N119	50V, 20mA, 0,3W	-
29142	3N120	30V, 10mA, 0,2W	-
29143	3N121	30V, 10mA, 0,2W	-
29144	3N123	30V, 20mA, 0,1W	-
29145	3N124	50V, Idss>0,2mA, Up<8V	-
29146	3N125	3N124, Idss>1,5mA, Up<14V	-
29147	3N126	3N124, Idss>3mA, Up<26V	-
29148	3N127	30V, 10mA, 0,2W	-
29149	3N128	20V, Idss>5mA, Up<8V	BFR 29, 3N143, 3N152, 3N154
29150	3N129	20V, 20mA, 0,3W	-
29151	3N130	30V, 20mA, 0,3W	-
29152	3N131	40V, 20mA, 0,3W	-
29153	3N132	50V, 20mA, 0,3W	-
29154	3N133	60V, 20mA, 0,3W	-
29155	3N134	20V, 20mA, 0,3W	-
29156	3N135	40V, 20mA, 0,3W	-
29157	3N136	60V, 20mA, 0,3W	-
29158	3N138	45V, 0,05A	-
29159	3N139	42V, Idss>5mA	-

29160	3N140	20V, Idss>5mA	BF 351, 3N201...206, 3N211...213
29161	3N141	20V, Idss>5mA	BF 351, 3N201...206, 3N211...213
29162	3N143	20V, Idss>10mA, Up<8V	BFR 29, 3N142, 3N152, 3N154
29163	3N145	30V, Up<6V	-
29164	3N146	30V, Up<6V	-
29165	3N149	30V, Idss>16mA, Up<6V	-
29166	3N150	30V, Idss>16mA, Up<6V	-
29167	3N152	20V, Idss>10mA, Up<8V	BFR 29, 3N143, 3N154
29168	3N152	20V, Idss>10mA, Up<8V	BFR 29, 3N143, 3N154
29169	3N153	20V, 0,05A	-
29170	3N153	20V, 0,05A	-
29171	3N154	20V, Idss>10mA, Up<8V	BFR 29, 3N143, 3N152
29172	3N154	20V, Idss>10mA, Up<8V	BFR 29, 3N143, 3N152
29173	3N155(A)	35V, 0,03A, Up<3,2V	BFW 27, 3N160...161, 3N163...164
29174	3N156(A)	3N155, Up<5V	BFW 27, 3N160...161, 3N163...164
29175	3N157(A)	35..50V, 0,03A, Up<3,2V	BFW 27, 3N160...161, 3N163...164
29176	3N158(A)	3N157, Up<5V	BFW 27, 3N160...161, 3N163...164
29177	3N159	20V, Idss>5mA, Up<4V	BF 351, 3N201...206, 3N211...213
29178	3N160	25V, 0,125A, Up<5V	-
29179	3N161	25V, 0,125A, Up<5V	-
29180	3N162	25V, 0,25A, Up<5V	-
29181	3N163	40V, 0,05A, Up<5V	-
29182	3N164	30V, 0,05A, Up<5V	-
29183	3N167	30V, 0,5A, Up<6V	-
29184	3N168	25V, 0,5A, Up<6V	-
29185	3N169	35V, 0,03A, Up<1,5V	-
29186	3N170	3N169, Up<2	-
29187	3N171	3N169, Up<3	-
29188	3N172	40V, 0,05A, Up<6V	-
29189	3N173	3N172, 30V	-
29190	3N174	30V, 0,02A, Up<6V	BFW 27, 3N155...158, 3N163...164
29191	3N175	30V, 0,05A, Up<2V	-
29192	3N176	25V, 0,05A, Up<2,5V	-
29193	3N177	20V, 0,05A, Up<3,5V	-
29194	3N178	75V, 0,02A, Up<5,5V	-
29195	3N179	60V, 0,02A, Up<6V	-
29196	3N180	40V, 0,02A, Up<6V	-
29197	3N181	30V, 0,1A, Up<4V	-
29198	3N182	30V, 0,1A, Up<5V	-
29199	3N183	25V, 0,1A, Up<6V	-
29200	3N184	35V, 0,05A, Up<3V	-
29201	3N185	30V, 0,05A, Up<3V	-
29202	3N186	25V, 0,05A, Up<3,5V	-
29203	3N187	20V, Idss>5mA, Up<4V	BF 351, 3N201...206, 3N211...213
29204	3N192	30V, Idss<30mA, Up<4V	-

29205	3N193	3N192, Idss<20mA	-
29206	3N200	20V, Idss>0,5mA	3SK66, 3SK79, 3SK87, 3SK100
29207	3N201	30V, Idss>6mA, Up<5V	BF 351, 3N209...213
29208	3N202	30V, Idss>6mA, Up<5V	BF 351, 2N209...213
29209	3N203(A)	30V, Idss>3mA, Up<5V	BF 351, 3N209...213
29210	3N204	30V, Idss>6mA	3N209...210
29211	3N205	30V, Idss>6mA, Up<5V	BF 351, 3N209...213
29212	3N206	30V, Idss>3mA, Up<5V	BF 351, 3N209...213
29213	3N209	30V, Idss>5mA, Up<4V	BF 900
29214	3N211	35V, Idss>6mA, Up<5V	BF 351, 3N201...206
29215	3N212	3N211, VHF-M, Up<4V	BF 351, 3N201...206
29216	3N213	3N211, TV-ZF, 40V	BF 351, 3N201...206
29217	3N214	20V, Idss>50mA, Up<6V	-
29218	3N215	20V, Idss>50mA, Up<6V	-
29219	3N216	20V, Idss>50mA, Up<6V	-
29220	3N217	20V, Idss>50mA, Up<6V	-
29221	3N218	25V, 0,7A, Up<3,5V	-
29222	3N223	40V, Idss<12mA, Up<2V	BF 352...353, BF 963, 3SK81
29223	3N225(A)	25V, Idss>1mA, Up<4V	3SK70, 3SK80
29224	3N242	30V, 0,03A, Up<2V	-
29225	3N246	50V, 1A	B35C1000, etc.
29226	3N246	50V, 1A	B35C1000, etc.
29227	3N247	3N246, 100V	B70C1000, etc.
29228	3N247	3N246, 100V	B70C1000, etc.
29229	3N248	3N246, 200V	B140C1000, etc.
29230	3N248	3N246, 200V	B140C1000, etc.
29231	3N249	3N246, 400V	B280C1000, etc.
29232	3N249	3N246, 400V	B280C1000, etc.
29233	3N250	3N246, 600V	B420C1000, etc.
29234	3N250	3N246, 600V	B420C1000, etc.
29235	3N251	3N246, 800V	B560C1000, etc.
29236	3N251	3N246, 800V	B560C1000, etc.
29237	3N252	3N246, 1000V	B700C1000, etc.
29238	3N252	3N246, 1000V	B700C1000, etc.
29239	3N253	50V, 2A	B35C2000, etc.
29240	3N253	50V, 2A	B35C2000, etc.
29241	3N254	3N253, 100V	B70C2000, etc.
29242	3N254	3N253, 100V	B70C2000, etc.
29243	3N255	3N253, 200V	B140C2000, etc.
29244	3N255	3N253, 200V	B140C2000, etc.
29245	3N256	3N253, 400V	B280C2000, etc.
29246	3N256	3N253, 400V	B280C2000, etc.
29247	3N257	3N253, 600V	B420C2000, etc.
29248	3N257	3N253, 600V	B420C2000, etc.
29249	3N258	3N253, 800V	B560C2000, etc.

29250	3N258	3N253, 800V	B560C2000, etc.
29251	3N259	3N253, 1000V	B700C2000, etc.
29252	3N259	3N253, 1000V	B700C2000, etc.
29253	3N34	30V, 20mA, 0,125W	-
29254	3N35(A)	30V, 20mA, 0,125W	-
29255	3N36	7V, 20mA, 0,03W	-
29256	3N37	7V, 20mA, 0,03W	-
29257	3N49	3N45, 15A, 94W	-
29258	3N50	3N46, 15A, 94W	-
29259	3N51	3N47, 15A, 94W	-
29260	3N52	3N48, 15A, 94W	-
29261	3N56	18V, 0,03A, 0,15W	-
29262	3N57	18V, 0,03A, 0,15W	-
29263	3N62		-
29264	3N63		-
29265	3N64		-
29266	3N65		-
29267	3N66		-
29268	3N67		-
29269	3N68(A)		-
29270	3N69		-
29271	3N70		-
29272	3N71	15V	-
29273	3N72	15V	-
29274	3N73	15V	-
29275	3N74	50V	-
29276	3N75	50V	-
29277	3N76	50V	-
29278	3N77	40V	-
29279	3N78	40V	-
29280	3N79	40V	-
29281	3N87	20V, 10mA, 0,2W	-
29282	3N88	20V, 10mA, 0,2W	-
29283	3N89	30V, Idss>0,5mA, Up<4V	-
29284	3N90	50V, 20mA, 0,3W	-
29285	3N91	50V, 20mA, 0,3W	-
29286	3N92	50V, 20mA, 0,3W	-
29287	3N93	50V, 20mA, 0,3W	-
29288	3N94	50V, 20mA, 0,3W	-
29289	3N95	50V, 20mA, 0,3W	-
29290	3N98	32V, Idss>3,5mA, Up<6V	-
29291	3N99	32V, Idss>5mA, Up<6V	-
29292	3O	2SC4497-O	2SC4497
29293	3O	2SK621	2SK621
29294	3O	2SK665	2SK665



29295	3P	FMMT 2222AR	FMMT 2222AR
29296	3P1M	<5/5mA	X 0609..., TAG 621-..., TAG 622-...
29297	3P1MH..3P6MH	3 P1M..3P6M, Igt/Ih <0,2/1mA	TAG 108-..., TAG 623-..., TAG 628-...
29298	3P2M	3 P1M, 200V	X 0609..., TAG 621-..., TAG 622-...
29299	3P4J(Z)	<0,1/<5mA	-
29300	3P4M	3 P1M, 400V	X 0609..., TAG 621-..., TAG 622-...
29301	3P5M	3 P1M, 500V	X 0609..., TAG 621-..., TAG 622-...
29302	3P6M	3 P1M, 600V	X 0609..., TAG 621-..., TAG 622-...
29303	3R	MMBT 5771	MMBT 5771
29304	3R	2SC4497-R	2SC4497
29305	3RP	3SK184-P	3SK184
29306	3RQ	3SK184-Q	3SK184
29307	3RR	3SK184-R	3SK184
29308	3RS	3SK184-S	3SK184
29309	3S	2SC3904	2SC3904
29310	3S	MMBT 5551	MMBT 5551
29311	3S	2SC4805	2SC4805
29312	3S4	DE 3S4M	DE 3S4M
29313	3S4M	400V, 3A(Tc70°C), Igt <30mA	TAG 650S-..., TAG 655S-..., CSF 11-...
29314	3S6	DE 3S6M	DE 3S6M
29315	3SJ11	30V, 10mA, Up3..6,5V, <1kOhm	-
29316	3SJ11A	<500Ohm	-
29317	3SK100	15V, Idss>0,5mA, Up<3V	3SK66, 3SK79, 3SK87
29318	3SK101	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29319	3SK102	20V, Idss>3mA, Up<3,5V	BF 900, BF 980
29320	3SK103	15V, Idss<10mA, Up<1V	BF 980
29321	3SK104(V)	15V, Idss<20mA, Up<2V	BF 980
29322	3SK107	20V, Idss>2,5mA, Up<3V	BF 964, 3SK49
29323	3SK108	20V, Idss>3mA, Up<1,5V	-
29324	3SK11	20V, Idss>0,5mA, Up<8V	-
29325	3SK112	10V, Idss>20mA, Up<3,7V	-
29326	3SK113	12V, Idss>10mA, Up<6V	-
29327	3SK114	15V, Idss>0mA, Up<1V	3SK53
29328	3SK115	15V, Idss>0mA, Up<1V	3SK198
29329	3SK116	20V, Idss>2,5mA, Up<3V	BF 989, BF 991, BF 994, BF 996
29330	3SK117	15V, Idss<6mA	-
29331	3SK118	15V, Idss>1mA, Up<1V	-
29332	3SK119	15V, Idss>0,8mA, Up<3V	-
29333	3SK12	20V, Idss>0,5mA, Up<8V	-
29334	3SK120	15V, Idss>2mA	-
29335	3SK121	10V, Idss>20mA, Up<4V	-
29336	3SK122	20V, Idss>7mA	3SK74
29337	3SK123	18V, Idss>0,01mA, Up<2V	3SK88
29338	3SK125	15V, Idss>1mA	BF 960, BF 966
29339	3SK126	15V, Idss>0mA, Up<1V	3SK195

29340	3SK127	15V, Idss>0mA, Up<1V	3SK199
29341	3SK128	15V, Idss>1mA	-
29342	3SK129	13V, Idss>8,5mA, Up<3,5V	-
29343	3SK13	20V, Idss>2mA, Up<8V	-
29344	3SK131	20V, Idss>7mA, Up<2V	-
29345	3SK132(A)	20V, Idss>0,5mA, Up<2V	-
29346	3SK133(A)	20V, Idss>10μA, Up<2V	-
29347	3SK134(A,B)	15(A,B,18)V	-
29348	3SK135(A)	15V, Idss>10μA	3SK133
29349	3SK136	20V, Idss>5mA, Up<3V	-
29350	3SK137	15V, Idss<20mA, Up<2V	-
29351	3SK137V	3SK137, VHF	-
29352	3SK138	15V, Idss<10mA, Up<1V	-
29353	3SK139	3SK125, SMD	-
29354	3SK14	20V, 10mA, Idss1mA, Up<5V	-
29355	3SK140		-
29356	3SK141	3SK129, SMD	-
29357	3SK142	15V, Idss>0,5mA	3SK79, 3SK87, 3SK100
29358	3SK143	3SK142, SMD, Idss>0,2mA	-
29359	3SK144	15V, Idss>0,8mA	-
29360	3SK145	13,5V, Idss0..6mA	-
29361	3SK146	3SK145, SMD	-
29362	3SK15(A)	25V, Idss<10mA, Up<9V	-
29363	3SK150	15V, Idss>3mA	BF 980
29364	3SK151	3SK150, SMD	-
29365	3SK152	13,5V, Idss0..6V	-
29366	3SK153	3SK152, SMD	-
29367	3SK154	3SK96, SMD	-
29368	3SK156	12V, Idss0..12mA	-
29369	3SK159	13,5V, Idss0..6mA	-
29370	3SK16	25V, Idss<10mA, Up<9V	-
29371	3SK160	3SK159, SMD	-
29372	3SK162	12V, Idss0..12mA	-
29373	3SK163	15V, 100mA, Uon<5,5V	-
29374	3SK164	12V, Idss>10mA	-
29375	3SK165	8V, Idss>20mA	-
29376	3SK166	8V, Idss>20mA	-
29377	3SK167	12V, Idss>10mA	-
29378	3SK168	12V, Idss>10mA	-
29379	3SK169	15V, Idss>1,5mA	-
29380	3SK17	25V, Idss<10mA, Up<9V	-
29381	3SK171	3SK113, SMD	-
29382	3SK173	18V, Idss0,5..10mA	-
29383	3SK174	13V, Idss5..40mA	-
29384	3SK176(A)	3SK173, SMD	-

29385	3SK177	3SK174, SMD	-
29386	3SK179	20V, Idss>7mA	-
29387	3SK18	15V, Idss<5mA, Up<6V	-
29388	3SK180	15V, Idss>2,5mA	-
29389	3SK181	15V	-
29390	3SK182	3SK80, SMD	-
29391	3SK183	13V, Idss>8,5mA, Up<6V	-
29392	3SK184	3SK183, SMD	-
29393	3SK186	12V, Idss0..4V	-
29394	3SK187	20V, Idss8,5..130mA	-
29395	3SK188	3SK85, SMD	-
29396	3SK189	13V, Idss>8,5mA	-
29397	3SK19	15V, Idss<5mA, Up<6V	-
29398	3SK190	3SK189	-
29399	3SK191	12V, Idss>10mA	-
29400	3SK192	15V, Idss>1mA	3SK193
29401	3SK193	15V, Idss>1mA	3SK192
29402	3SK194	Idss0..10	-
29403	3SK195	13,5V, Idss>0mA	3SK126
29404	3SK196	12V, 35mA	-
29405	3SK197	12V, 35mA	-
29406	3SK198	13,5V, Idss>0mA	3SK115
29407	3SK199	3SK198, SMD	3SK127
29408	3SK20	20V, Idss>0,5mA, Up<3,5V	3SK66, 3SK79, 3SK87, 3SK100
29409	3SK200	15V, Idss>4mA	-
29410	3SK201	Idss8,5..	-
29411	3SK202	15V, Idss>0,8mA, Up<3V	-
29412	3SK203	10V, Idss8..60mA	-
29413	3SK204	3SK203, SMD	-
29414	3SK205	10V, Idss10..80mA	-
29415	3SK206	3SK205, SMD	-
29416	3SK207	13,5V, Idss>0V	-
29417	3SK21	20V, Idss>3mA	-
29418	3SK212	10V, 15mA	-
29419	3SK215	12V, 1mA, Idss>6mA	-
29420	3SK216	12V, 1mA, Idss>4mA	-
29421	3SK217	3SK186	-
29422	3SK219	15V, 30mA	-
29423	3SK22	18V, Idss>3mA, Up<5V	-
29424	3SK220	15V, 30mA	-
29425	3SK222	18V, 25mA	-
29426	3SK223	18V, 25mA	-
29427	3SK224	18V, 25mA	-
29428	3SK225	13,5V, Idss>0V	-
29429	3SK226	13,5V, Idss>0V	-

29430	3SK227	15V, 30mA	-
29431	3SK228(A)	Idss10..3	-
29432	3SK229	Idss15..4	-
29433	3SK23	15V, Idss>6mA, Up>1,8V	-
29434	3SK230	18V, 25mA	-
29435	3SK231	18V, 25mA	-
29436	3SK232	12,5V, Idss<0,1mA	-
29437	3SK233	Idss0..2m	-
29438	3SK234	Idss0..1m	-
29439	3SK235	Idss0..1m	-
29440	3SK236	3SK234	-
29441	3SK237	3SK235	-
29442	3SK238	3SK233	-
29443	3SK239A	3SK228A	-
29444	3SK24	3SK39	-
29445	3SK240	9V, Idss6..20mA	-
29446	3SK241	13V, 50mA	-
29447	3SK242	20V, 25mA	-
29448	3SK243	18V, 25mA	-
29449	3SK244	18V, 25mA	-
29450	3SK245	18V, 25mA	-
29451	3SK246	18V, 25mA	-
29452	3SK247	15V, Idss0..10mA	-
29453	3SK248	10V, 100mA, Up<1,5V	-
29454	3SK249	3SK232	-
29455	3SK25	3SK39	-
29456	3SK250	6V	-
29457	3SK252	18V, 25mA	-
29458	3SK253	18V, 25mA	-
29459	3SK255	3SK253	-
29460	3SK255	3SK226	-
29461	3SK256	3SK207	-
29462	3SK257	3SK225	-
29463	3SK259	3SK152, SMD	-
29464	3SK260	3SK150, SMD	-
29465	3SK263	15V, 30mA, Idss>2,5mA	-
29466	3SK264	15V, 30mA, Idss>5mA	-
29467	3SK265	15V, 30mA, Idss>5mA	-
29468	3SK266	13,5V, 30mA, Idss>2,5mA	-
29469	3SK268	3SK219	-
29470	3SK269	3SK200	-
29471	3SK270	3SK220	-
29472	3SK271	3SK227	-
29473	3SK272	3SK241	-
29474	3SK273	13V, 50mA	-

29475	3SK274	3SK240	-
29476	3SK275	3SK250	-
29477	3SK276	Idss0,5..	
29478	3SK28	18V, Idss>3,7mA	-
29479	3SK283	Idss4..16	
29480	3SK284	3SK283	-
29481	3SK285	Idss10..2	
29482	3SK286	Idss6..20	
29483	3SK288	Idss1..10	
29484	3SK29	20V, Idss1mA, Up<5V	-
29485	3SK290	Idss0,5..	
29486	3SK291	12,5V, 30mA	-
29487	3SK292	12,5V, 30mA	-
29488	3SK293	3SK291	-
29489	3SK294	3SK292	-
29490	3SK295	12V, 25mA, Up<1V	-
29491	3SK296	3SK295	-
29492	3SK297	12V, 25mA, Up<1V	-
29493	3SK298	3SK297	-
29494	3SK30(A)	15V, Idss>3mA, Up<5V	-
29495	3SK300	Up<1V	
29496	3SK301	Idss5..23	
29497	3SK302	Idss0..10	
29498	3SK303	Idss0..10	
29499	3SK304	15V, 30mA	-
29500	3SK305	3SK301	-
29501	3SK306	3SK302	-
29502	3SK307	3SK303	-
29503	3SK308	3SK304	-
29504	3SK309	Idss25..6	
29505	3SK32	20V, Idss<5mA, Up<2,5V	3SK39, 3SK70, 3SK80
29506	3SK33	25V, Idss>4mA, Up<4V	-
29507	3SK35	20V, Idss>3mA, Up<4V	BF 350, BF 900, 3SK40
29508	3SK37	20V, Idss>4mA, Up<3V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29509	3SK38(A)	10V, Up<3V	-
29510	3SK39	20V, Idss>1mA, Up<3V	3SK70, 3SK80
29511	3SK40	20V, Idss>4mA, Up<4V	BF 350...351, BF 900, 3N201...206
29512	3SK41	20V, Idss>4mA, Up<4V	BF 350...351, BF 900, 3N201...206
29513	3SK44	20V, Idss>3mA, Up<3,3V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29514	3SK45	22V, Idss>4mA, Up<3V	BF 981, 3SK37, 3SK61, 3SK77
29515	3SK47	20V, Idss>4mA, Up<3V	BF 980...982, 3SK37, 3SK45, 3SK61, 3SK77
29516	3SK48	18V, Idss>2mA, Up<3V	BF 960, BF 965...966
29517	3SK49	20V, Idss>2,5mA, Up<3V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29518	3SK51	20V, Idss>8mA, Up<3V	3SK74
29519	3SK53	20V, Idss>0,1mA, Up<1,7V	3SK115

29520	3SK55	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29521	3SK59	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29522	3SK60	15V, Idss<20mA, Up<1,7V	BF 980...982, 3SK47
29523	3SK61	20V, Idss>4mA, Up<3V	BF 981, 3SK37, 3SK45, 3SK77
29524	3SK63	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29525	3SK66	20V, Idss>0,5mA, Up<3V	3SK79, 3SK87, 3SK100
29526	3SK70	20V, Idss>1mA, Up<3V	BF 960, BF 965...966, 3SK48, 3SK80
29527	3SK72	20V, Idss>2,5mA, Up<3V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29528	3SK73	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29529	3SK74	20V, Idss>7mA, Up<3V	3SK51
29530	3SK76	14V, Idss>5mA, Up<1V	-
29531	3SK77	20V, Idss>3mA, Up<2,5V	BF 981, 3SK37, 3SK45, 3SK61
29532	3SK78	20V, Idss>3mA, Up<3,5V	BF 900, 3N209...210
29533	3SK79	20V, Idss>0,5mA, Up<3V	3SK66, 3SK87, 3SK100
29534	3SK80	20V, Idss>1mA, Up<3V	BF 960, BF 965...966, 3SK48, 3SK70
29535	3SK81	20V, Idss>5mA, Up<3V	BF 352...353, BF 963, 3SK51, 3SK74
29536	3SK82	15V, Idss<20mA, Up<1,7V	BF 980
29537	3SK83	15V, Idss<20mA, Up<1,7V	BF 982, 3SK47
29538	3SK85	22V, Idss>4mA, Up<3V	BF 981, 3SK37, 3SK45, 3SK61, 3SK77
29539	3SK87	20V, Idss>0,5mA, Up<2V	3SK66, 3SK79, 3SK100
29540	3SK88	20V, Idss>0,01mA, Up<2V	3SK123
29541	3SK90	20V, Up<3V	-
29542	3SK95	15V, Idss<30mA, Up<2V	BF 980
29543	3SK96	15V, Idss<30mA, Up<2V	BF 352...353, BF 963, 3SK81
29544	3SK97	15,5V, Idss3..80mA	-
29545	3SS	MMBTA 28	MMBTA 28
29546	3SS3M	300V, 3A(Tc70°C), Igt <30mA	TAG 650S-..., TAG 655S-..., CSF 11-...
29547	3SS4M	3 SS3M, 400V	TAG 650S-..., TAG 655S-..., CSF 11-...
29548	3T	HT 3	HT 3
29549	3TE120	90V, 12A, PQ50W(70MHz)	-
29550	3TE130	90V, 5A, PQ30W(70MHz)	-
29551	3TE220	80V, 5A, PQ50W(150MHz)	-
29552	3TE230	80V, 4A, PQ30W(150MHz)	-
29553	3TE240	80V, 3A, >200MHz	-
29554	3TX002	100V, 5A, >150MHz	-
29555	3TX003	100V, 5A, >150MHz	-
29556	3TX004	60V, 5A, >150MHz	-
29557	3U	2SC4068	2SC4068
29558	3U	2SC3967	2SC3967
29559	3W	FMMT-A12	FMMT-A12
29560	3WS	2SD2529-S	2SD2529
29561	3WS	2SD1979-S	2SD1979
29562	3WS	2SD1938-S	2SD1938
29563	3WT	2SD2529-T	2SD2529
29564	3WT	2SD1979-T	2SD1979



29565	3WT	2SD1938-T	2SD1938
29566	3Y	2SC5190	2SC5190
29567	3Y0	BZV 49/C3V0	BZV 49/C3V0
29568	3Y3	BZV 49/C3V3	BZV 49/C3V3
29569	3Y6	BZV 49/C3V6	BZV 49/C3V6
29570	3Y9	BZV 49/C3V9	BZV 49/C3V9
29571	3Z12..390	12..390V, 1,5kW(1ms)	1N5635...5665, 1N6273...6303
29572	3ZP	3SK193-P	3SK193
29573	3ZQ	3SK193-Q	3SK193
29574	4	HVU 350	HVU 350
29575	4.3B	HZF 4.3BP	HZF 4.3BP
29576	4.3C	HZF 4.3CP	HZF 4.3CP
29577	4.7B	HZF 4.7BP	HZF 4.7BP
29578	4.7C	HZF 4.7CP	HZF 4.7CP
29579	40004	40V, 10mA, 30MHz	AF 124...127, AF 200
29580	40005	40V, 10mA, 100MHz	AF 124...125, AF 200
29581	40006	40V, 10mA, 120MHz	AF 124...125, AF 200
29582	40022	32V, 5A, 12,5W(Tc75°)	AL 102...103, AUY 28, 2N1539...48
29583	40050	40V, 5A, 12,5W(Tc75°)	AL 102...103, AUY 28, 2N1539...48
29584	40051	40050, 50V	AL 102...103, AUY 28, 2N1540...43
29585	40053	2N3053	2N3053
29586	40080	PQ>0,1W(27MHz)	MRF 402, MRF 8003
29587	40081	60V, 0,25A, PQ>0,4W(27MHz)	MRF 402, MRF 8003
29588	40082	60V, 1,5A, PQ>3W(27MHz)	-
29589	40084	ns	BSS 26, BSS 40...41, 2N4014
29590	40108R...40116R	40108..40116	BYX 42/...R, BYX 98/...R
29591	40111	40108, 300V	BYX 42/300, BYX 98/300
29592	40112	40108, 400V	BYX 42/600, BYX 98/600
29593	40113	40108, 500V	BYX 42/600, BYX 98/600
29594	40114	40108, 600V	BYX 42/600, BYX 98/600
29595	40115	40108, 800V	BYX 42/900, BYX 98/900
29596	40116	40108, 1000V	BYX 42/1200, BYX 98/1200
29597	40208	50V, 18A(Tc150°)	1N4525...30
29598	40208R...40214R	40208..40214	D 24/...C
29599	40209	40208, 100V	1N4525...30
29600	40210	40208, 200V	1N4525...30
29601	40211	40208, 300V	1N4526...30
29602	40212	40208, 400V	1N4526...30
29603	40213	40208, 500V	1N4527...30
29604	40214	40208, 600V	1N4527...30
29605	40216	S 6431M	S 6431M
29606	40217	25V, 0,3W, >200MHz	BSS 11...12, BSX 19...20, 2N2369(A)
29607	40218	25V, 0,05A, 0,3W, >200MHz	BSS 11...12, BSX 19...20, 2N2369(A)
29608	40219	40V, 0,36W, >300MHz	BSS 11, BSX 19...20, 2N2369(A)
29609	40220	40V, 0,2A, 0,3W, >350MHz	BSS 11, BSX 19...20, 2N2369(A)

29610	40221	40V, 0,36W, >300MHz	BSS 11, BSX 19...20, 2N2369(A)
29611	40222	25V, 0,2A, 0,3W, >200MHz	BSS 11...12, BSX 19...20, 2N2369(A)
29612	40231	18V, 0,1A, 0,5W, 60MHz	BC 169, BC 184, BC 239, BC 549
29613	40232	18V, 0,1A, 0,5W, 60MHz	BC 169, BC 184, BC 239, BC 549
29614	40233	18V, 0,1A, 0,5W, 60MHz	BC 169, BC 184, BC 239, BC 549
29615	40234	18V, 0,1A, 0,5W, 60MHz	BC 169, BC 184, BC 239, BC 549
29616	40235	1000MHz	BF 314, BF 496, BF 502...503, BF 505
29617	40236	1000MHz	BF 314, BF 496, BF 502...503, BF 505
29618	40237	1000MHz	BF 314, BF 496, BF 502...503, BF 505
29619	40238	800MHz	BF 198, BF 225, BF 310, BF 367
29620	40239	800MHz	BF 199, BF 224, BF 311, BF 373
29621	40242	900MHz	BF 241, BF 255, BF 495, BF 595
29622	40243	850MHz	BF 241, BF 255, BF 495, BF 595
29623	40244	800MHz	
29624	40246	800MHz	BF 240, BF 254, BF 494, BF 594
29625	40250	50V, 4A, 29W, 1MHz	BD 243, BD 535, BD 539A, 2N3054
29626	40250V1	40250	40250
29627	40251	50V, 15A, 117W, 0,5MHz	BD 315, BD 545A, BDX 13, 2N3055
29628	40253	25V, 0,5A, 0,125W	AC 128, AC 152...153, AC 188, 2SB405
29629	40254	32V, 5A, 12,5W(Tc75°)	AL 102...103, AUY 28, 2N1539...48
29630	40255	450/350V, 1A, 10W, >20MHz	BD 410, BUW 40(A,B), TIP 49...50
29631	40256	40255, 300/250V	BD 410, BUW 40(A,B), TIP 47...50
29632	40261	40MHz	AF 124...127, AF 200
29633	40262	30MHz	AF 124...127, AF 200
29634	40263	20V, 0,05A, 0,12W	AC 125, AC 126, AC 151
29635	40264	300/300V, 0,1A, 4W, 25MHz	BF 459, BF 859, 2SC1505...1507
29636	40268	25V, 0,1A, 0,1W, >250MHz	AF 139, AF 239(S)
29637	40269	25V, 0,1A, 0,15W, >4MHz	AC 125...126, AC 151, ASY 26...27
29638	40279	2N3375	2N3375
29639	40280	36V, 0,5A, PQ>1W(175MHz)	BFQ 42, BFR 98, BLW 16, BLY 61
29640	40281	36V, 1A, PQ>4W(175MHz)	BLY 57, BLY 78, 2N3926
29641	40282	36V, 2A, PQ>12W(175MHz)	BLY 58, 2N3927
29642	40283	60V, 1A, 0,4W, <30/45ns	2N4014
29643	40290	50V, 0,5A, PQ>2W(135MHz)	BFW 46, BLY 33, 2N3924
29644	40291	50V, 0,5A, PQ>2W(135MHz)	BLY 55
29645	40292	50V, 1,25A, PQ>6W(135MHz)	BLY 57, 2N3926
29646	40294	2N2857	2N2857
29647	40295	2N2708	2N2708
29648	40296	2N3839	2N3839
29649	40305	2N3553	2N3553
29650	40306	2N3375	2N3375
29651	40307	2N3632	2N3632
29652	40309(L,S)	-/18V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N3053
29653	40309V1	40309(L,S)	BD 137, BD 228, BD 517, BD 527
29654	40309V2	40309(L,S)	BD 137, BD 228, BD 517, BD 527

29655	40310	-/35V, 4A, 29W, 0,75MHz	BD 243, BD 533, BD 539, BD 947
29656	40310V1	-/35V, 4A, 29W, 0,75MHz	BD 243, BD 533, BD 539, BD 947
29657	40312(V1)	40310, 60V	BD 243A, BD 535, BD 539A, BD 949
29658	40313	300V, 2A, 35W	BUX 67A...C, TIP 75(A...C), 2SC782
29659	40314(L,S)	-/40V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N3053
29660	40314V1	40314(L,S)	BD 137, BD 228, BD 517, BD 527
29661	40314V2	40314(L,S)	BD 137, BD 228, BD 517, BD 527
29662	40316	40V, 4A, 29W, 0,75MHz	BD 243A, BD 535, BD 539A, BD 949
29663	40318	300V, 2A, 35W	BUX 67A...C, TIP 75(A...C), 2SC782
29664	40319(L,S)	-/40V, 0,7A, 1W, 100MHz	BC 160...161, BC 303...304, 2N2303
29665	40319V1	40319(L,S)	BD 138, BD 229, BD 518, BD 528
29666	40319V2	40319(L,S)	BD 138, BD 229, BD 518, BD 528
29667	40321(L,S)	300V, 1A, 1W	BFQ 38...39, BSS 48...49, 2N3440, 2SC1861
29668	40321V1	40321(L,S)	BD 410, BUW 63, BUW 40, TIP 47...50
29669	40321V2	40321(L,S)	BD 410, BUW 63, BUW 40, TIP 47...50
29670	40322	40318	40318
29671	40324	40310	40310
29672	40325	35V, 15A, 117W	BD 315, BD 545, BD 745, 2N3055
29673	40328	40318	40318
29674	40329	25V, 0,1A, 0,125W	AC 125...126, AC 151, ASY 26...27
29675	40340	60V, 3,3A, PQ>25W(50MHz)	-
29676	40341	70V, 3,3A, PQ>30W(50MHz)	-
29677	40342	65V, 3A, 23W	-
29678	40343	65V, 3A, 23W	-
29679	40346(L,S)	175V, 1A, 1W, >10MHz	BFQ 38...39, BSS 48...49, 2N3440, 2SC1861
29680	40346V1	40346(L,S)	BD 410, BUW 40, 2SC3117, 2SD669
29681	40346V2	40346(L,S)	BD 410, BUW 40, 2SC3117, 2SD669
29682	40347(L,S)	60V, 1,5A	BCX 40, BSS 42...43, BD 139, BD 529
29683	40347V1	40347(L,S)	BD 139, BD 237, BD 529, BD 843
29684	40347V2	40347(L,S)	BD 139, BD 237, BD 529, BD 843
29685	40350		BF 377...378, BF 689, BF 763, 2N2857
29686	40351		BF 377...378, BF 689, BF 763, 2N2857
29687	40352		BF 377...378, BF 689, BF 763, 2N2857
29688	40354	-/150V, 0,05A, 0,5W, 100MHz	BF 297...299, BFR 87...89, 2SC3467
29689	40355	40354, 1W	BF 297...299, BFR 87...89, 2SC3467
29690	40359	20V, 0,05A, 0,12W	AC 125...126, AC 151, ASY 26...27
29691	40360(L,S)	70V, 0,7A, 1W, 100MHz, B>40	BC 140...141, BC 300...301, 2N1990
29692	40360V1	40360(L,S)	BD 139, BD 230, BD 519, BD 529
29693	40360V2	40360(L,S)	BD 139, BD 230, BD 519, BD 529
29694	40362(L,S)	70V, 0,7A, 1W, 100MHz	BC 161, BC 303, BCX 60, 2SA606
29695	40362V1	40362(L,S)	BD 140, BD 231, BD 520, BD 530
29696	40362V2	40362(L,S)	BD 140, BD 231, BD 520, BD 530
29697	40363	70V, 15A, 115W, 0,7MHz	BD 315, BD 545B, BD 745B, 2N3055
29698	40364	60V, 7A, 35W, 15MHz	BD 243A, BD 543A, BD 807, 2N6315...16
29699	40366(L,S)	2N2102	2N2102

29700	40366V1	40366(L,S)	BD 424, 2SC2275, 2SC2384, 2SC2690(A)
29701	40366V2	40366(L,S)	BD 424, 2SC2275, 2SC2384, 2SC2690(A)
29702	40367(L,S)	100V, 1,5A, 1W	BCX 40, BSW 66...68, BSX 46...47
29703	40367V1	40367(L,S)	BD 139, BD 230, BD 529, BD 843
29704	40367V2	40367(L,S)	BD 139, BD 230, BD 529, BD 843
29705	40368	100V, 3A, 25W	BD 241C, BD 539C, BD 939, 2SD712
29706	40369	100V, 6A, 75W	BD 245C, BDV 91, BDX 91, 2N5758...59
29707	40372	2N3054, 5,8W	2N3054
29708	40373		2N3441: 5,8W
29709	40373	2N3441, 5,8W	
29710	40374	2N3583, 5,8W	
29711	40375	2N3878, 5,8W	2N3878
29712	40378	S 2600B	S 2600B
29713	40379	S 2600D	S 2600D
29714	40385(L,S)	2N3439	2N3439
29715	40385V1	2N3439	2N3439
29716	40385V2	2N3439	2N3439
29717	40389	2N3053, 3,5W	2N3053
29718	40390	2N3440, 3,5W	2N3440
29719	40391	2N4037, 3,5W	2N4037
29720	40392	2N3053, 7W(Tc25°)	2N3053
29721	40393	2N3440, 10W(Tc25°)	2N3440
29722	40394	2N4037, 7W(Tc25°)	2N4037
29723	40395	18V, 0,5A, 0,3W	AC 128, AC 152...153, AC 188
29724	40396	18V, 0,5A, 0,3W	AC 127, AC 176, AC 187
29725	40397	$\beta > 165$	BC 168, BC 183, BC 238, BC 548
29726	40398	40397, $\beta > 75$	BC 168, BC 183, BC 238, BC 548
29727	40399	40397, 18V	BC 168, BC 183, BC 238, BC 548
29728	40400	40397, 18V, $\beta > 75$	BC 168, BC 183, BC 238, BC 548
29729	40403	30V, 0,2A, 0,2W, <850/1200ns	AC 125...126, AC 151, ASY 26
29730	40404	40V, 0,5A, PQ>0,05W(86MHz)	MRF 604, 2SC2053
29731	40405	40V, 0,5A, PQ>0,2W(172MHz)	MRF 604, 2SC2053
29732	40406(L,S)	-/50V, 0,7A, 1W, 100MHz	BC 161, BC 303...304, 2SA606
29733	40407(L,S)	-/50V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N3053,
29734	40408(L,S)	-/90V, 0,7A, 1W, 100MHz	BC 141, BC 300...301, 2N1990, 2N2405
29735	40409	90V, 0,7A, 3W	BD 139, BD 230, BD 529, BD 829
29736	40410	90V, 0,7A, 3W	BD 140, BD 231, BD 530, BD 830
29737	40411	90V, 30A, 150W, 0,8MHz	BDW 30, BDY 29, MJ 802, 2SD797
29738	40412(L,S)	>10MHz	BUX 55, BUY 59...60, 2N5092, 2N5095
29739	40412V1	40412, 4W	BD 410, BUW 40A,B, TIP 47...50
29740	40412V2	40412, 4W	BD 410, BUW 40A,B, TIP 47...50
29741	40413	>700MHz	BF 377...378, BF 689, BF 763, 2N2857
29742	40414	>1000MHz	BF 377...378, BF 689, BF 763, 2N2857
29743	40421	75V, 5A, 12,5W(Tc80°)	AL 102...103, AUY 28, 2N1541...43
29744	40422	300V, 0,15A, 8W(Tc75°)	2SC1505...1507, 2SC1755...1757, 2SC1905

29745	40423	40422	2SC1505...1507, 2SC1755...1757, 2SC1905
29746	40424	300V, 0,15A, 8W(Tc75°)	2SC1505...1507, 2SC1755...1757, 2SC1905
29747	40425	40424	2SC1505...1507, 2SC1755...1757, 2SC1905
29748	40426	300V, 0,15A, 8W(Tc75°)	2SC1505...1507, 2SC1755...1757, 2SC1905
29749	40427	40426	2SC1505...1507, 2SC1755...1757, 2SC1905
29750	40428	0,275V(80mA)	-
29751	40429	T 2700B	T 2700B
29752	40430	T 2700D	T 2700D
29753	40431	200V, 6A, Ih<30mA	-
29754	40432	40431, 400V	-
29755	40439	320V, 10A, 5W(Tc55°)	AU 106, AU 109, AU 111...112, 2N5325
29756	40440	200V, 10A, 5W(Tc55°)	AU 107, AU 113, AU 213, 2N5324
29757	40442	200V, 7A	-
29758	40444	PQ>20W(2,5MHz)	-
29759	40446	-/60V, 1,5A, PQ>3W(27MHz)	2SC2020, 2SC2029
29760	40450	2N3241A, 1W	2N3241A
29761	40451	2N3242A, 1W	2N3242A
29762	40452	2N4074, 1W	2N4074
29763	40453	40397, 1W	40397
29764	40454	40398, 1W	40398
29765	40455	40399, 1W	40399
29766	40456	40400, 1W	40400
29767	40457	25V, 1A, 0,5W, >80MHz	BC 337...338, BC 635, BC 637, BC 639
29768	40458	60V, 1A, 0,5W, <75/575ns	BC 637, BC 639, BSS 26, BSS 40...41
29769	40459	40458, 1W	BC 637, BC 639, BSS 26, BSS 40...41
29770	40460	25V, Idss<9mA	-
29771	40461	25V, Idss4..14mA	-
29772	40462	40V, 5A, 12, W(Tc75°)	AL 102...103, AUY 28, 2N1539...48
29773	40464	35V, 5A, 40W, >2MHz	BD 245, BDV 91, BDX 91, 2N4914...15
29774	40465	40464, 40V	BD 245, BDV 91, BDX 91, 2N4914...15
29775	40466	40464, 50V	BD 245, BDV 91, BDX 91, 2N4914...15
29776	40467(A)	20V, Idss>10mA, Up<8V	-
29777	40468(A)	20V, Idss>5mA	-
29778	40469	700MHz	BF 225, BF 314, BF 502, BF 505, BF 506
29779	40470	700MHz	BF 198, BF 225, BF 310, BF 367, BF 596
29780	40471	700MHz	BF 198, BF 225, BF 310, BF 367, BF 596
29781	40472	900MHz	BF 225, BF 314, BF 502, BF 505, BF 507
29782	40473	900MHz	BF 224, BF 314, BF 503, BF 505, BF 507
29783	40474	900MHz	BF 224, BF 314, BF 503, BF 505, BF 507
29784	40475	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
29785	40476	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
29786	40477	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
29787	40478	800MHz	BF 241, BF 255, BF 495, BF 595
29788	40479	800MHz	BF 241, BF 255, BF 495, BF 595
29789	40480	800MHz	BF 240, BF 254, BF 494, BF 594

29790	40481	860MHz	BF 240, BF 254, BF 494, BF 594
29791	40482	860MHz	BF 240, BF 254, BF 494, BF 594
29792	40485	200V, 6A, Igt/Ih<40/<30mA	-
29793	40486	40485, 400V	-
29794	40487	40MHz	AF 124...127, AF 200
29795	40488	30MHz	AF 124...127, AF 200
29796	40489	30MHz	AF 124...127, AF 200
29797	40490	20V, 0,02A, 0,12W	AC 125...126, AC 151
29798	40491	300V, 0,15A, 3,8W, 25MHz	2SC1505...1507, 2SC1755...1757, 2SC1905
29799	40495	400V, 0,5A	BY 126...127, BY 133...134, 1N4004...07
29800	40500	30V, 0,2A, 0,5W, >80MHz	BC 168, BC 183, BC 238, BC 548
29801	40502	T 2710B	T 2710B
29802	40503	T 2710D	T 2710D
29803	40504	S 2710B	S 2710B
29804	40505	S 2710D	S 2710D
29805	40506	S 2710M	S 2710M
29806	40507	S 2600B	S 2600B
29807	40508	S 2600D	S 2600D
29808	40509	40485	40485
29809	40510	40486	40486
29810	40511	40431	40431
29811	40512	40432	40432
29812	40517	1900MHz	BF 377...378, BF 689, BF 763, 2SC2570
29813	40518	40517	BF 377...378, BF 689, BF 763, 2SC2570
29814	40519	40V, 0,5A, PQ0,3W(240MHz)	BFS 50, MRF 515, 2SC2852
29815	40525	T 2300A	T 2300A
29816	40526	T 2300B	T 2300B
29817	40527	T 2300D	T 2300D
29818	40528	T 2302A	T 2302A
29819	40529	T 2302B	T 2302B
29820	40530	T 2302D	T 2302D
29821	40531	T 2310A	T 2310A
29822	40532	T 2310B	T 2310B
29823	40533	T 2310D	T 2310D
29824	40534	T 2312A	T 2312A
29825	40535	T 2312B	T 2312B
29826	40536	T 2312D	T 2312D
29827	40537(L,S)	55V, 0,7A, 1W, 100MHz	BC 161, BC 303...304, 2SA606
29828	40538(L,S)	55V, 0,7A, 1W, 100MHz	BC 161, BC 303...304, 2SA606
29829	40539(L,S)	55V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N1990
29830	40544	50V, 0,7A, 7W, 100MHz	BD 137, BD 228, BD 525, BD 827
29831	40546	250V, 0,15A, 8W(Tc75°), B>50	2SC1505...1507, 2SC1755...1757, 2SC1905
29832	40547	40546, B>20	2SC1505...1507, 2SC1755...1757, 2SC1905
29833	40553	S 3700B	S 3700B
29834	40554	S 3700D	S 3700D



29835	40555	S 3700M	S 3700M
29836	40559(A)	20V, Idss>5mA, Up<6V	-
29837	40561	1N3847	1N3847
29838	40562	1N3848	1N3848
29839	40563	1N3849	1N3849
29840	40564	1N3850	1N3850
29841	40565	1N3851	1N3851
29842	40566	1N3852	1N3852
29843	40567	1N3853	1N3853
29844	40568	1N3854	1N3854
29845	40569	1N3855	1N3855
29846	40570	1N3856	1N3856
29847	40571	1N3857	1N3857
29848	40572	1N3858	1N3858
29849	40573	1N3859	1N3859
29850	40574	1N3860	1N3860
29851	40575	T 4700B	T 4700B
29852	40576	T 4700D	T 4700D
29853	40577	2N3118	2N3118
29854	40578	2N3866	2N3866
29855	40581	60V, 1,5A, PQ>3,5W(27MHz)	2SC2020, 2SC2029
29856	40582	60V, 1,5A, PQ>3,5W(27MHz)	2SC2020, 2SC2029
29857	40583	Ub27..37, Ib<0,05mA, Itsm2A	1N5761, N413M, BR100, D3202Y, DO201YR
29858	40594(L,S)	RCA 1A03	RCA 1A03
29859	40595(L,S)	RCA 1A04	RCA 1A04
29860	40600	20V, Idss18mA, Up2V	BF 351...353, 3N201...206, 3N211...213
29861	40601	20V, Idss18mA, Up2V	BF 351...353, 3N201...206, 3N211...213
29862	40602	20V, Idss18mA, Up2V	BF 351...353, 3N201...206, 3N211...213
29863	40603	20V, Idss18mA, Up2V	BF 351...353, 3N201...206, 3N211...213
29864	40604	20V, Idss18mA, Up2V	BF 351...353, 3N201...206, 3N211...213
29865	40605	65V, 0,33A, PQ>1,5W(500MHz)	BFR 97, 2SC2852
29866	40608	40V, 0,4A, >700MHz	BFS 50, MRF 629, 2N3948, 2SC2852
29867	40611(L,S)	-/25V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N3053
29868	40612	25V, 5A, 12,5W	AL 102...103, AUY 28, 2N1529...48
29869	40613	-/25V, 4A, 36W	BD 243, BD 533, BD 539, BD 947
29870	40616(L,S)	-/32V, 0,7A, 1W, 100MHz	BC 140...141, BC 300...302, 2N3053
29871	40618	-/30V, 4A, 36W, >0,8MHz	BD 243, BD 533, BD 539, BD 947
29872	40621	-/32V, 4A, 36W, >0,8MHz	BD 243, BD 533, BD 539, BD 947
29873	40622	40621, -/40V	BD 243, BD 533, BD 539, BD 947
29874	40623	45V, 5A, 12,5W	AL 102...103, AUY 28, 2N1529...48
29875	40624	-/45V, 6A, 50W	BD 243A, BD 543A, BD 797, BD 807
29876	40625	-/45, 1A, 3,5W	BD 137, BD 228, BD 525, BD 827
29877	40626	55V, 5A, 12,5W	AL 102...103, AUY 28, 2N1540...48
29878	40627	-/55V, 6A, 50W	BD 243B, BD 543B, BD 799, BD 809
29879	40628	-/55V, 1A, 3,5W	BD 139, BD 230, BD 527, BD 829

29880	40629	35V, 4A, 36W	BD 243, BD 533, BD 539, BD 947
29881	40630	40V, 4A, 36W	BD 243, BD 533, BD 539, BD 947
29882	40631	45V, 4A, 36W	BD 243, BD 533, BD 539A, BD 947
29883	40632	60V, 6A, 50W	BD 243A, BD 543A, BD 797, BD 807
29884	40634(L,S)	RCA 1A05	RCA 1A05
29885	40635(L,S)	RCA 1A06	RCA 1A06
29886	40636	RCA 1B01	RCA 1B01
29887	40637	30V, 0,1A, 0,3W, 300MHz	BFX 59
29888	40637A	40637, 36V, 0,2A, 0,75W	2SC2053, 2SC2851, BFR 36
29889	40638	40485	40485
29890	40639	40486	40486
29891	40640	S 3705M	S 3705M
29892	40641	S 3706M	S 3706M
29893	40642	D 2601EF	D 2601EF
29894	40643	D 2601DF	D 2601DF
29895	40644	D 2600EF	D 2600EF
29896	40654	S 2600B	S 2600B
29897	40655	S 2600D	S 2600D
29898	40656	S 2620B	S 2620B
29899	40657	S 2620D	S 2620D
29900	40658	S 2610B	S 2610B
29901	40659	S 2610D	S 2610D
29902	40660	T 6401B	T 6401B
29903	40661	T 6401D	T 6401D
29904	40662	T 6411B	T 6411B
29905	40663	T 6411D	T 6411D
29906	40664	450V,6A,Igt<50mA	-
29907	40665	65V, 1A, PQ>13,5W(175MHz)	BLY 60, 2N3632
29908	40666	65V, 0,5A, PQ>3W(400MHz)	BLY 60, 2N3632
29909	40667	40664	-
29910	40668	T 2800B	T 2800B
29911	40669	T 2800D	T 2800D
29912	40670	T 2800M	T 2800M
29913	40671	T 6401M	T 6401M
29914	40672	T 6411M	T 6411M
29915	40673	20V,Idss>5mA,Up<4V	3N209...210
29916	40680	S 6420A	S 6420A
29917	40681	S 6420B	S 6420B
29918	40682	S 6420D	S 6420D
29919	40683	S 6420M	S 6420M
29920	40684	T 2313A	T 2313A
29921	40685	T 2313B	T 2313B
29922	40686	T 2313D	T 2313D
29923	40687	T 2313M	T 2313M
29924	40688	T 6420B	T 6420B

29925	40689	T 6420D	T 6420D
29926	40690	T 6420M	T 6420M
29927	40691	T 2301B	T 2301B
29928	40692	T 2301D	T 2301D
29929	40693	T 2316A	T 2316A
29930	40694	T 2316B	T 2316B
29931	40695	T 2316D	T 2316D
29932	40696	T 2306A	T 2306A
29933	40697	T 2306B	T 2306B
29934	40698	T 2306D	T 2306D
29935	40699	T 6406B	T 6406B
29936	40700	T 6406D	T 6406D
29937	40701	T 6406M	T 6406M
29938	40702	T 6416B	T 6416B
29939	40703	T 6416D	T 6416D
29940	40704	T 6416M	T 6416M
29941	40705	T 6407B	T 6407B
29942	40706	T 6407D	T 6407D
29943	40707	T 6417B	T 6417B
29944	40708	T 6417D	T 6417D
29945	40709	T 6407M	T 6407M
29946	40710	T 6407M	T 6407M
29947	40711	T 4106B	T 4106B
29948	40712	T 4106D	T 4106D
29949	40713	T 4116B	T 4116B
29950	40714	T 4116D	T 4116D
29951	40715	T 4706B	T 4706B
29952	40716	T 4706D	T 4706D
29953	40717	T 4107B	T 4107B
29954	40718	T 4107D	T 4107D
29955	40719	T 4117B	T 4117B
29956	40720	T 4117D	T 4117D
29957	40721	T 2806B	T 2806B
29958	40722	T 2806D	T 2806D
29959	40723	T 2606DF	T 2606DF
29960	40724	T 2616DF	T 2616DF
29961	40725	T 2606B	T 2606B
29962	40726	T 2606D	T 2606D
29963	40727	T 2706B	T 2706B
29964	40728	T 2706D	T 2706D
29965	40729	T 2716B	T 2716B
29966	40730	T 2716D	T 2716D
29967	40731	40485, Igt/Ih<45/15mA	-
29968	40732	40486, Igt/Ih<45/15mA	-
29969	40733	40485, Igt/Ih<45/15mA	-

29970	40734	40486, Igt/Ih<45/15mA	-
29971	40735	2N3653, 600V, S 7430M	S 7430M, 2N3653
29972	40737	Igt/Ih<15/<20mA	T6N100H, T8N100H, BStD4026, S 6200A
29973	40738	40737, 200V	T6N200H, T8N200H, BStD4026, S 6200B
29974	40739	40737, 400V	T6N400H, T8N400H, BStD4026, S 6200D
29975	40740	40737, 600V	T6N600H, T8N600H, BStD4040, S 6200M
29976	40741	40737	T6N100C, T8N100C, BStD4126, S 6210A
29977	40742	40738	T6N200C, T8N200C, BStD4126, S 6210B
29978	40743	40739	T6N400C, T8N400C, BStD4126, S 6210D
29979	40744	40740	T6N600C, T8N600C, BStD4140, S 6210M
29980	40745	40737	S 6220A, C 230A3
29981	40746	40738	S 6220B, C 230B3
29982	40747	40739	S 6220D, C 230D3
29983	40748	40740	S 6220M, C 230M3
29984	40749	S 6200A	S 6200A
29985	40750	S 6200B	S 6200B
29986	40751	S 6200D	S 6200D
29987	40752	S 6200M	S 6200M
29988	40753	S 6210A	S 6210A
29989	40754	S 6210B	S 6210B
29990	40755	S 6210D	S 6210D
29991	40756	S 6210M	S 6210M
29992	40757	S 6220A	S 6220A
29993	40758	S 6220B	S 6220B
29994	40759	S 6220D	S 6220D
29995	40760	S 6220M	S 6220M
29996	40761	T 2311B	T 2311B
29997	40762	T 2311D	T 2311D
29998	40766	T 2301A	T 2301A
29999	40767	T 2311A	T 2311A
30000	40768	S 3701M	S 3701M
30001	40769	T 2304B	T 2304B
30002	40770	T 2304D	T 2304D
30003	40771	T 2305B	T 2305B
30004	40772	T 2305D	T 2305D
30005	40773	200V, 2,5A, Igt/Ih<40/<30mA	T 2306B, T 2303B, TAG 208-200
30006	40774	40773, 400V	T 2306D, T 2303D, TAG 208-400
30007	40775	T 4105B	T 4105B
30008	40776	T 4105D	T 4105D
30009	40777	T 4115B	T 4115B
30010	40778	T 4115D	T 4115D
30011	40779	T 4104B	T 4104B
30012	40780	T 4104D	T 4104D
30013	40781	T 4114B	T 4114B
30014	40782	T 4114D	T 4114D

30015	40783	T 4103B	T 4103B
30016	40784	T 4103D	T 4103D
30017	40785	T 4113B	T 4113B
30018	40786	T 4113D	T 4113D
30019	40787	T 6405B	T 6405B
30020	40788	T 6405D	T 6405D
30021	40789	T 6415B	T 6415B
30022	40790	T 6415D	T 6415D
30023	40791	T 6404B	T 6404B
30024	40792	T 6404D	T 6404D
30025	40793	T 6414B	T 6414B
30026	40794	T 6414D	T 6414D
30027	40795	T 4101M	T 4101M
30028	40796	T 4111M	T 4111M
30029	40797	T 4100M	T 4100M
30030	40798	T 4110M	T 4110M
30031	40799	T 4121B	T 4121B
30032	40800	T 4121D	T 4121D
30033	40801	T 4121M	T 4121M
30034	40802	T 4120B	T 4120B
30035	40803	T 4120D	T 4120D
30036	40804	T 4120M	T 4120M
30037	40805	T 6421B	T 6421B
30038	40806	T 6421D	T 6421D
30039	40807	T 6421M	T 6421M
30040	40808	600V, 0,5A	BYV 36C, BYV 95C, BYW 95C, 1N4247...49
30041	40809	AC 127+AC 128	AC 127/128
30042	40809	40808, 800V	BYV 36D, BYV 96D, BYW 96D, 1N4248...49
30043	40810	Igt/Ih<15/<20mA	TAG 612-100, TAG 613-100, TAG 606-100
30044	40811	40810, 200V	TAG 612-200, TAG 613-200, TAG 606-200
30045	40812	40810, 400V	TAG 612-400, TAG 613-400, TAG 606-400
30046	40813	40810, 600V	TAG 612-600, TAG 613-600, TAG 606-600
30047	40814	RCA 1A07	RCA 1A07
30048	40815	RCA 1A08	RCA 1A08
30049	40819	25V, Idss>5mA, Up<4V	BF 351, 3N201...206, 3N211...213
30050	40820	20V, Idss>0,5mA, Up<3V	3SK66, 3SK79, 3SK87, 3SK100
30051	40821	20V, Idss>0,5mA, Up<3V	3SK66, 3SK79, 3SK87, 3SK100
30052	40822	20V, Idss>5mA, Up<4V	BF 351, 3N201...206, 3N211...213
30053	40823	20V, Idss>5mA, Up<4V	BF 351, 3N201...206, 3N211...213
30054	40829	2N5954, 5.8W	2N5954
30055	40830	2N5955, 5.8W	2N5955
30056	40831	2N5956, 5.8W	2N5956
30057	40832	40852	40852
30058	40833	S 2600M	S 2600M
30059	40834	S 2620M	S 2620M

30060	40835	S 2610M	S 2610M
30061	40841	24V, Idss10mA, Up2V	BF 351, 3N201...206, 3N211...213
30062	40842	T 2801DF	T 2801DF
30063	40850	2N3585	2N3585
30064	40851	2N6079	2N6079
30065	40852	2N5240	2N5240
30066	40853	2N5805	2N5805
30067	40854	2N6251	2N6251
30068	40867	S 2800A	S 2800A
30069	40868	S 2800B	S 2800B
30070	40869	S 2800D	S 2800D
30071	40871	120V, 7A, 40W, >4MHz	BD 243D, BD 543D, 2SD550, 2SD866
30072	40872	120V, 7A, 40W, >4MHz	BD 244D, BD 544D, 2SB870
30073	40873	80V, 7A, 40W, >4MHz	BD 243B, BD 543B, BD 799, BD 809
30074	40874	80V, 7A, 40W, >4MHz	BD 244D, BD 544D, BD 800, BD 810
30075	40875	60V, 7A, 40W, >4MHz	BD 243A, BD 543A, BD 797, BD 807
30076	40876	60V, 7A, 40W, >4MHz	BD 244A, BD 544A, BD 798, BD 808
30077	40877	-/65V, 10A, 75W, 7MHz	BD 709, BD 743B, BD 809, BD 909
30078	40878	-/65V, 10A, 75W, 10MHz	BD 710, BD 744B, BD 810, BD 910
30079	40879	-/85V, 10A, 75W, 7MHz	BD 711, BD 743C, BD 911
30080	40880	-/85V, 10A, 75W, 10MHz	BD 712, BD 744C, BD 912
30081	40881	-/40V, 10A, 75W, 7MHz	BD 707, BD 743A, BD 807, BD 907
30082	40882	-/40V, 10A, 75W, 10MHz	BD 708, BD 744A, BD 808, BD 908
30083	40885	2N6175	2N6175
30084	40886	2N6176	2N6176
30085	40887	2N6177	2N6177
30086	40888(U)	S 3703SF	S 3703SF
30087	40889(U)	S 3702SF	S 3702SF
30088	40890	D 2103SF	D 2103SF
30089	40891	D 2103S	D 2103S
30090	40892	D 2101S	D 2101S
30091	40893	36V, 3A, PQ>15W(470MHz)	BLW 15, BLX 69, 2SC1338, 2SC1404
30092	40894	1400MHz	BF 225, BF 314, BF 502, BF 505, BF 507
30093	40895	1400MHz	BF 225, BF 314, BF 502, BF 505, BF 507
30094	40896	1400MHz	BF 225, BF 314, BF 502, BF 505, BF 507
30095	40897	1400MHz	BF 225, BF 314, BF 502, BF 505, BF 507
30096	40900	T 2850A	T 2850A
30097	40901	T 2850B	T 2850B
30098	40902	T 2850D	T 2850D
30099	40910	2N6260, 5,8W	2N6260
30100	40911	2N6261, 5,8W	2N6261
30101	40912	2N6263, 5,8W	2N6263
30102	40913	2N6264, 5,8W	2N6264
30103	40915	30V, 0,04A, 2900MHz	BFR 15, BFS 55, 2SC2498, 2SC2570
30104	40925	T 6400N	T 6400N



30105	40926	T 6410N	T 6410N
30106	40927	T 6420N	T 6420N
30107	40934	36V, 0,5A, PQ>2W(470MHz)	BLX 66, 2SC1620
30108	40936	65V, 3,3A, PEP20W(30MHz)	-
30109	40940	65V, 1,5A, PQ>5W(400MHz)	BLW 91, 2SC2893
30110	40941	55V, 0,4A, PQ>1W(400MHz)	MRF 509
30111	40942	S 2400A	S 2400A
30112	40943	S 2400B	S 2400B
30113	40944	S 2400D	S 2400D
30114	40945	S 2400M	S 2400M
30115	40952	2N3873, 800V, S 6420N	2N3873, S 6420N
30116	40953	36V, 0,33A, PQ>2W(156MHz)	BFW 46, BLY 33, MRF 227, 2N3924
30117	40954	36V, 4,5A, PQ>10W(156MHz)	BLW 38, BLY 63, MRF 209, 2N5591
30118	40955	36V, 5A, PQ>25W(156MHz)	BLW 20, BLW 31, 2N6084
30119	40964	36V, 0,2A, PQ0,44W(470MHz)	BFS 50, MRF 515, 2N3948
30120	40965	36V, 0,2A, PQ0,44W(470MHz)	BFS 50, MRF 515, 2N3948
30121	40967	36V, 0,5A, PQ>2W(470MHz)	BLX 67, 2N5945, 2SC2104
30122	40968	36V, 1,5A, PQ>6W(470MHz)	BLW 14, BLW 44, 2N5946, 2SC2105
30123	40970	36V, PQ>30W(470MHz)	BLU 45/12, MRF 646, 2SC2783
30124	40971	36V, PQ>45W(136MHz)	BLV 75/12, 2SC2630, 2SC3147
30125	40972	PQ>1,75W(175MHz)	BFW 46, MRF 227, 2N3924
30126	40973	36V, 4,5A, PQ>10W(175MHz)	BLY 89, MRF 209, 2N5591, 2N6082
30127	40974	36V, 5A, PQ>25W(175MHz)	BLW 20, BLW 31, 2N6084
30128	40975	-/30V, 0,4A	BFR 98, BLW 16, BLY 61, MRF 607
30129	40976	-/30V, 0,5A	BFR 98, BLW 16, BLY 61, MRF 607
30130	40977	-/30V, 5A, PQ>6W(118MHz)	BLW 38, BLY 63
30131	40979	RCA 1C10	RCA 1C10
30132	40980	RCA 1C11	RCA 1C11
30133	40HF-10..100	100..1000V, 40A	BYX 56/..., BYX 97/...
30134	40HF-10R..100R	HF 40..	-
30135	410	200/200V, 7A, 125W, 4MHz	BUW 87, BUX 18(A,B), TIP 160...162
30136	41002	D 2101S	D 2101S
30137	41004	30V, Up<4V	-
30138	41008	36V, PQ>0,5W(470MHz)	-
30139	41008A	41008	-
30140	41009	36V, PQ>2W(470MHz)	-
30141	41009A	41009	-
30142	41010	36V, PQ>5W(470MHz)	-
30143	41012	120/80V, 20A, 175W, >40MHz	BUV 10...12, BUW 57...58, BUX 10...12
30144	41013	41012, 160/125V	BUV 11...12, BUW 58, BUX 11...12
30145	41014	T 2500B	T 2500B
30146	41015	T 2500D	T 2500D
30147	41017	S 3800SF	S 3800SF
30148	41018	S 3800MF	S 3800MF
30149	41019	S 3800E	S 3800E

30150	41020	S 3800S	S 3800S
30151	41021	S 3800M	S 3800M
30152	41022	S 3800EF	S 3800EF
30153	41023	S 3800D	S 3800D
30154	41024	55V, 0,4A, PQ>1W(1GHz)	-
30155	41025	50V, 0,35A, PQ>3W(1GHz)	-
30156	41026	50V, 1,5A, PQ>10W(1GHz)	-
30157	41027	45V, 0,35A, PQ>3W(1GHz)	-
30158	41028	45V, 1,5A, PQ>10W(1GHz)	-
30159	41038	-/21V, PQ>0,75W	-
30160	41039	40V, 0,25A, >2GHz	2SC1253, 2SC1366, 2SC1952
30161	41042	65V, 90W(Tc75°)	-
30162	41044	40V, 5W(Tc100°)	-
30163	411	410, 300/300V	BUX 18A,B, TIP 160...162, 2SC2961
30164	413	410, 400/325V	BUX 18B, TIP 162, 2SC2625, 2SC2961
30165	41420	BSt CC0146R	BSt CC0146R
30166	41500	35V, 7A, 40W, >4MHz	BD 243, BD 543, BD 795, BD 805
30167	41501	35V, 7A, 40W, >4MHz	BD 244, BD 544, BD 796, BD 806
30168	41502	-/30V, 1A, 0,8W	BC 140...141, BCX 40, 2N1990, 2N2102
30169	41504	35V, 4A, 36W, >0,8MHz	BD 243, BD 533, BD 539, BD 947
30170	41505		
30171	41505	-/200V, 1A, 20W, 20MHz	BD 410, BUV 63
30172	41506	200/200V, 3A, 100W	2SD632
30173	41508	-/140V, 30A, 150W	BD 249F, BUW 58, BUW 73, 2SC2865(A)
30174	42	BAT 54AW	BAT 54AW
30175	423	410, 400/325V	BUX 18B, TIP 162, 2SC2625, 2SC2961
30176	43	BAT 54CW	BAT 54CW
30177	43(s)	BAS 40	BAS 40
30178	43(X,Y,Z)	U 02W4.3V	Z 02W 4.3V
30179	431	410, 400/325V	BUX 18B, TIP 162, 2SC2625, 2SC2961
30180	43104	>0,2MHz	BD 745F, BUW 58, BUW 73, 2SC2865(A)
30181	43A	HZM 4.3FA	HZM 4.3FA
30182	43Y	BZV 49/C43	BZV 49/C43
30183	44	BAT 54SW	BAT 54SW
30184	44(s)	BAS 40-04	BAS 40-04
30185	44001	1N4001	1N4001
30186	44002	1N4002	1N4002
30187	44003	1N4003	1N4003
30188	44004	1N4004	1N4004
30189	44005	1N4005	1N4005
30190	44006	1N4006	1N4006
30191	44007	1N4007	1N4007
30192	44933	D 2201F	D 2201F
30193	44934	D 2201A	D 2201A
30194	44935	D 2201B	D 2201B

30195	44936	D 2201D	D 2201D
30196	44937	D 2201M	D 2201M
30197	44938	D 2201N	D 2201N
30198	45(s)	BAS 40-05	BAS 40-05
30199	45190	-/40V, 7A, 40W, >2MHz	BD 243A, BD 543A, BD 797, BD 807
30200	45191	45190, -/60V	BD 243B, BD 543B, BD 799, BD 809
30201	45192	45190, -/80V	BD 243C, BD 543C, BD 801, BD 711
30202	45193	-/40V, 7A, 40W, >2MHz	BD 244A, BD 544A, BD 798, BD 808
30203	45194	45193,-/60V	BD 244B, BD 544B, BD 800, BD 810
30204	45195	45193,-/80V	BD 244C, BD 544C, BD 802, BD 712
30205	46(s)	BAS 40-06	BAS 40-06
30206	47(s)	BAS 40-07	BAS 40-07
30207	47(X,Y,Z)	U 02W4.7V	Z 02W 4.7V
30208	47Y	BZV 49/C47	BZV 49/C47
30209	4A	D 1FS4A	D 1FS4A
30210	4A	MA 72	MA 72
30211	4A	BC 859AW	BC 859W
30212	4A	MMBV 109	MMBV 109
30213	4A(p,s)	BC 859A	BC 859
30214	4AR	BC 859AR	BC 859AR
30215	4As	BC 859AW	BC 859W
30216	4B	MA 77	MA 77
30217	4B	MA 73	MA 73
30218	4B	MMBV 432	MMBV 432
30219	4B	2SC4238	2SC4238
30220	4B	2SC4670	2SC4670
30221	4B	BC 859BW	BC 859W
30222	4B(p,s)	BC 859B	BC 859
30223	4BR	BC 859BR	BC 859BR
30224	4Bs	BC 859BW	BC 859W
30225	4C	3SK269	2SK269
30226	4C	3SK200	3SK200
30227	4C	MA 79	MA 79
30228	4C	BC 859CW	BC 859W
30229	4C	2SC4239	2SC4239
30230	4C	MMBV 3102	MMBV 3102
30231	4C	FMMD 3102	FMMD 3102
30232	4C(p,s)	BC 859C	BC 859
30233	4CR	BC 859CR	BC 859CR
30234	4Cs	BC 859CW	BC 859W
30235	4D	MA 81	MA 81
30236	4D	MMBV 3401	MMBV 3401
30237	4D	BC 859W	BC 859W
30238	4D	HD 3A	HD 3A
30239	4D	2SJ146	2SJ146

30240	4D	HD 3A	HD 3A
30241	4D	MMSV 3401	MMSV 3401
30242	4D(p)	BC 859	BC 859
30243	4E	MMBV 105G	MMBV 105G
30244	4E	BC 860AW	BC 860W
30245	4E	FMMT-A92	FMMT-A92
30246	4E(p,s)	BC 860A	BC 860
30247	4E100-8	4E20-8, Ub90..110V	4E100M
30248	4E100A	4E20A, Ub80..120V	4E100M
30249	4E100M-8	4E20M-8, Ub80..115V	4E100A
30250	4E20-8	Ub16..24V, Is<125μA, Itsm5A	4E20M
30251	4E200-8	4E20-8, Ub180..220V	4E200M
30252	4E200A	4E20A, Ub170..230V	4E200M
30253	4E200M-8	4E20M-8, Ub160..230V	4E200A
30254	4E20A	Ub14..26V, Itsm5A	4E20M
30255	4E20M-8	Ub14..25V, Itsm5A	4E20A
30256	4E30-8	4E20-8, Ub26..34V	4E30M
30257	4E30A	4E20A, Ub24..36V	4E30M
30258	4E30M-8	4E20M-8, Ub23..36V	4E30A
30259	4E40-8	4E20-8, Ub36..44V	4E40M
30260	4E40A	4E20A, Ub34..46V	4E40M
30261	4E40M-8	4E20M-8, Ub32..46V	4E40A
30262	4E50-8	4E20-8, Ub46..54V	4E50M
30263	4E50A	4E20A, Ub44..56V	4E50M
30264	4E50M-8	4E20M-8, Ub41..57V	4E50A
30265	4ER	BC 860AR	BC 860R
30266	4EX580	Ub15..25V, Is<0.25mA, Itsm5A	4E20M
30267	4EX581	4EX580, Ub25..35V	4E30M
30268	4EX582	4EX580, Ub35..50V	4E40M
30269	4F	2SC4971	2SC4971
30270	4F	2SC4444	2SC4444
30271	4F	BC 860BW	BC 860W
30272	4F(p,s)	BC 860B	BC 860
30273	4FR	BC 860BR	BC 860R
30274	4Fs	BC 860BW	BC 860W
30275	4G	BC 860CW	BC 860W
30276	4G	FMMT 2484	FMMT 2484
30277	4G	MMBV 2101	MMBV 2101
30278	4G(p,s)	BC 860C	BC 860
30279	4GR	BC 860CR	BC 860CR
30280	4Gs	BC 860CW	BC 860W
30281	4GZ..R	4GZ..	BZX 98/...R, BZY 93/...R
30282	4GZ10A..82A	10..82V, 10%, 4W(Tc75°)	BZX 98/..., BZY 93/...
30283	4GZ10B..18B	100..180V, 10%, 4W(Tc75°)	BZX 98/...
30284	4H	BC 860W	BC 860W

30285	4H	MMBV 2103	MMBV 2103
30286	4H(p)	BC 860	BC 860
30287	4J	MMBV 2109	MMBV 2109
30288	4J100-5	4J50-5, Ub90..110V	4E100M
30289	4J200-5	4J50-5, Ub180..220V	4E200M
30290	4J50-5	Ub45..55V, Is<0,25mA	4E50M
30291	4K	MMBV 2097	MMBV 2097
30292	4L	MMBV 2098	MMBV 2098
30293	4LO	2SK1103-O	2SK1103
30294	4LP	2SK1103-P	2SK1103
30295	4LQ	2SK1103-Q	2SK1103
30296	4LR	2SK1103-R	2SK1103
30297	4M	MMBD 101	MMBD 101
30298	4MO	2SJ163-O	2SJ163
30299	4MP	2SJ163-P	2SJ163
30300	4MQ	2SJ163-Q	2SJ163
30301	4MR	2SJ163-R	2SJ163
30302	4N	XN 5601	XN 5601
30303	4N	XP 5601	XP 5601
30304	4O	XN 1507	XN 1507
30305	4O	XP 1507	XP 1507
30306	4O	2SA1721-O	2SA1721
30307	4P	XN 1A312	XN 1A312
30308	4Q	XN 1B301	XN 1B301
30309	4Q	XP 1B301	XP 1B301
30310	4R	XP 1C301	XP 1C301
30311	4R	XN 1C301	XN 1C301
30312	4R	MMBV 3700	MMBV 3700
30313	4R	2SA1721-R	2SA1721
30314	4S	XP 611FH	XP 611FH
30315	4S	XN 611FH	XN 611FH
30316	4S	MMBD 201	MMBD 201
30317	4T	MMBD 301	MMBD 301
30318	4T	2SK1216	2SK1216
30319	4U	XP 5553	XP 5553
30320	4U	XN 5553	XN 5553
30321	4U	MMBV 2105	MMBV 2105
30322	4V	2SK1228	2SK1228
30323	4V	MMBV 2106	MMBV 2106
30324	4V	2SK1374	2SK1374
30325	4W	MMBV 2107	MMBV 2107
30326	4X	2SC4515	2SC4515
30327	4X	MMBV 2108	MMBV 2108
30328	4Y	2SC4516	2SC4516
30329	4Y	MMBV 2102	MMBV 2102

30330	4Y3	BZV 49/C4V3	BZV 49/C4V3
30331	4Y7	BZV 49/C4V7	BZV 49/C4V7
30332	4Z	MMBV 2104	MMBV 2104
30333	5	HVR 300	HVR 300
30334	5	1SV202	1SV202
30335	5	HVU 202	HVU 202
30336	5.1(X,Y,Z)	U 02W5.1V	Z 02W5.1V
30337	5.1B	HZF 5.1BP	HZF 5.1BP
30338	5.1C	HZF 5.1CP	HZF 5.1CP
30339	5.6B	HZF 5.6BP	HZF 5.6BP
30340	5.6C	HZF 5.6CP	HZF 5.6CP
30341	504BSY	BSV 78	BSV 78
30342	508BSY	BSV 81	BSV 81
30343	510	F 1C510	F 1C510
30344	512	F 1C512	F 1C512
30345	516	F 1C516	F 1C516
30346	518	F 1C518	F 1C518
30347	51C	F 1C5120	F 1C5120
30348	51Y	BZV 49/C51	BZV 49/C51
30349	5253OA	BU 326A	BU 326A
30350	527	F 1C527	F 1C527
30351	528BSY	2N4351	2N4351
30352	53	BAT 17	BAT 17
30353	54	BAT 17-04	BAT 17-04
30354	540	F 1C540	F 1C540
30355	55	BAT 17-05	BAT 17-05
30356	550	F 1C550	F 1C550
30357	555BRY	BRY61	BRY61
30358	556BCYA	BCX 17	BCX 17
30359	556BCYB	BCX 18	BCX 18
30360	557BCYA	BCX 19	BCX 19
30361	557BCYB	BCX 20	BCX 20
30362	56	BAT 17-06	BAT 17-06
30363	56(X,Y,Z)	U 02W5.6V	Z 02W 5.6V
30364	560	F 1C560	F 1C560
30365	563BSY	BSS 63	BSS 63
30366	564BSY	BSS 64	BSS 64
30367	565BAT	BAT 17	BAT 17
30368	56Y	BZV 49/C56	BZV 49/C56
30369	57	BAT 17-07	BAT 17-07
30370	57	BFQ 57	BFQ 57
30371	57	F 1C57	F 1C57
30372	574BAT	BAT 18	BAT 18
30373	575	F 1C575	F 1C575
30374	58	BFQ 58	BFQ 58



30375	59	BFQ 59	BFQ 59
30376	5A	FMMD 6050	FMMD 6050
30377	5A	PMBD 6050	PMBD 6050
30378	5A	MMBD 6050	MMBD 6050
30379	5A	BC 807-16W	BC 807W
30380	5A(p,s)	BC 807-16	BC 807
30381	5AG	HN3B01F-GR	HN 3B01F
30382	5AM	MMBD 6050	MMBD 6050
30383	5AR	BC 807-16R	BC 807
30384	5AY	HN3B01F-Y	HN 3B01F
30385	5B	MA 733	MA 733
30386	5B	MA 707	MA 707
30387	5B	KST 4123	KST 4123
30388	5B	MMBD 6100	MMBD 6100
30389	5B	PMBD 6100	PMBD 6100
30390	5B	MMBT 4123	MMBT 4123
30391	5B	BC 807-25W	BC 807W
30392	5B(p,s)	BC 807-25	BC 807
30393	5BM	MMBD 6100	MMBD 6100
30394	5BR	BC 807-25R	BC 807
30395	5C	XN 4601	XN 4601
30396	5C	XP 4601	XP 4601
30397	5C	MMBD 7000	MMBD 7000
30398	5C	BC 807-40W	BC 807W
30399	5C	PMBD 7000	PMBD 7000
30400	5C(p,s)	BC 807-40	BC 807
30401	5CR	BC 807-40R	BC 807
30402	5D	BC 807W	BC 807W
30403	5D	PMBD 914	PMBD 914
30404	5D	HD 2A	HS 2A
30405	5D	MMBD 914	MMBD 914
30406	5D	FMMD 914	FMMD 914
30407	5D	MMSD 914	MMSD 914
30408	5D(p)	BC 807	BC 807
30409	5E	XN 4608	XN 4608
30410	5E	YTS 2906	YTS 2906
30411	5E	FMMT-A43R	FMMT-A43R
30412	5E	BC 808-16W	BC 808W
30413	5E(p,s)	BC 808-16	BC 808
30414	5ER	BC 808-16R	BC 808
30415	5EZ3,6..200D..	3,6..200V, 5W, D55%, D1010%	BZV 40/..., BZV 48/..., 1N5334...5388
30416	5F	XN 4609	XN 4609
30417	5F	YTS 2906A	YTS 2906A
30418	5F	MMBD 501	MMBD 501
30419	5F	BC 808-25W	BC 808W

30420	5F(p,s)	BC 808-25	BC 808
30421	5FR	BC 808-25R	BC 808
30422	5G	BC 808-40W	BC 808W
30423	5G	MMBD 352	MMBD 352
30424	5G(p,s)	BC 808-40	BC 808
30425	5GR	BC 808-40R	BC 808
30426	5H	XN 4501	XN 4501
30427	5H	XP 4501	XP 4501
30428	5H	BC 808W	BC 808W
30429	5H	MMBD 4148	MMBD 4148
30430	5H	MMBD 701	MMBD 701
30431	5H(p)	BC 808	BC 808
30432	5I	XN 4601	XN 4601
30433	5I	YTS 4402	YTS 4402
30434	5K	XN 4401	XN 4401
30435	5K	XP 4401	XP 4401
30436	5K	MMBV 809	MMBV 809
30437	5KP5.0..110(A)	5..110V, 5W, Pbr5kW(1ms)	BZW 11/..., 1N5629...58, 1N6267...96
30438	5L	XP 5501	XP 5501
30439	5L	XN 5501	XN 5501
30440	5L	MMBV 609	MMBV 609
30441	5M	XN 5531	XN 5531
30442	5M	IMBT 3905	IMBT 3905
30443	5M	YTS 3905	YTS 3905
30444	5N	XN 6501	XN 6501
30445	5N	XP 6501	XP 6501
30446	5N	IMBT 3906	IMBT 3906
30447	5N	YTS 4126	YTS 4126
30448	5O	XN 6401	XN 6401
30449	5O	XP 6401	XP 6401
30450	5P	MA 344	MA 344
30451	5P	FMMT 2907AR	FMMT 2907AR
30452	5P05M	5P1M, 50V	T 3,5N..., TAG 661-..., TAG 662-...
30453	5P1M	<15/<10mA	T 3,5N..., TAG 661-..., TAG 662-...
30454	5P2M	5P1M, 200V	T 3,5N..., TAG 661-..., TAG 662-...
30455	5P4J(Z)	<0,2/1mA	-
30456	5P4M	5P1M, 400V	T 3,5N..., TAG 661-..., TAG 662-...
30457	5P5M	5P1M, 500V	T 3,5N..., TAG 661-..., TAG 662-...
30458	5P6J(Z)	5 P4J, 600V	-
30459	5P6M	5P1M, 600V	T 3,5N..., TAG 661-..., TAG 662-...
30460	5Q	XN 4502	XN 4502
30461	5R	XN 1501	XN 1501
30462	5R	XP 1501	XP 1501
30463	5R	MMBS 5060	MMBS 5060
30464	5S	XN 1504	XN 1504

30465	5S	XP 1504	XP 1504
30466	5S	MMBS 5061	MMBS 5061
30467	5S4	DE 5S4M	DE 5S4M
30468	5S4M	<50/60mA, <5µs	BT 151/500, TAG 655S-400, TAG 656S-400
30469	5S6	DE 5S6M	DE 5S6M
30470	5T	XN 1871	XN 1871
30471	5T	BCW 66RG	BCW 66RG
30472	5T	MMBS 5062	MMBS 5062
30473	5U	XN 1872	XN 1872
30474	5V	XP 1401	XP 1401
30475	5V	XN 1401	XN 1401
30476	5W	XN 2501	XN 2501
30477	5W	XP 2501	XP 2501
30478	5X	XN 4504	XN 4504
30479	5Y	XN 4503	XN 4503
30480	5Y1	BZV 49/C5V1	BZV 49/C5V1
30481	5Y6	BZV 49/C5V6	BZV 49/C5V6
30482	5Z	XN 6542	XN 6542
30483	5Z	MMBPU 131	MMBPU 131
30484	6	HVU 351	HVU 351
30485	6	HVE 351	HVE 351
30486	6	HVC 351	HVC 351
30487	6.2B	HZF 6.2BP	HZF 6.2BP
30488	6.2C	HZF 6.2CP	HZF 6.2CP
30489	6.8B	HZF 6.8BP	HZF 6.8BP
30490	6.8C	HZF 6.8CP	HZF 6.8CP
30491	60	BAR 60	BAR 60
30492	60	BFQ 60	BFQ 60
30493	60911	S 3703 SF	S 3703 SF
30494	60912	S 3702 S	S 3702 S
30495	60A...Y	TAG 60 A...Y	TAG 60 A...Y
30496	61	BAR 61	BAR 61
30497	61A	MMBF 4117	MMBF 4117
30498	61C	MMBF 4118	MMBF 4118
30499	61E	MMBF 4119	MMBF 4119
30500	61S	MMBF 5458	MMBF 5458
30501	61U	MMBF 5461	MMBF 5461
30502	62	BAT 62	BAT 62
30503	62(X,Y,Z)	U 02W6.2V	Z 02W 6.2V
30504	62P	MMBFJ 201	MMBFJ 201
30505	62Q	MMBFJ 202	MMBFJ 202
30506	62W	MMBFJ 211	MMBFJ 211
30507	62X	MMBFJ 212	MMBFJ 212
30508	62Y	BZV 49/C62	BZV 49/C62
30509	62Z	HZM 6.2ZWA	HZM 6.2ZWA

30510	63(s)	BAT 64	BAT 64
30511	636BC/A	BCX 51	BCX 51
30512	636BC/B	BCX 52	BCX 52
30513	636BC/C	BCX 53	BCX 53
30514	637BC/A	BCX 54	BCX 54
30515	637BC/B	BCX 55	BCX 55
30516	637BC/C	BCX 56	BCX 56
30517	64(s)	BAT 64-04	BAT 64-04
30518	645	BFQ 645	BFQ 645
30519	65(s)	BAT 64-05	BAT 64-05
30520	66(s)	BAT 64-06	BAT 64-06
30521	67	BFP 67	BFP 67
30522	67(s)	BAT 64-07	BAT 67-07
30523	68(X,Y,Z)	U 02W6.8V	Z 02W 6.8V
30524	68A	HZM 6.8FA	HZM 6.8FA
30525	68A	HZM 6.8WA	HZM 6.8WA
30526	68Y	BZV 49/C68	BZV 49/C68
30527	6A	MA 360	MA 360
30528	6A	MA 321	MA 321
30529	6A	MUN 2111	MUN 2111
30530	6A	UN 2111	UN 2111
30531	6A	MUN 5111	MUN 5111
30532	6A	BC 817-16W	BC 817W
30533	6A	UN 5111	UN 5111
30534	6A	UN 9111	UN 9111
30535	6A	MMBF 4416	MMBF 4416
30536	6A(p,s)	BC 817-16	BC 817
30537	6AR	BC 817-16R	BC 817
30538	6B	MA 329	MA 329
30539	6B	MA 361	MA 361
30540	6B	MUN 5112	MUN 5112
30541	6B	MMBF 5484	MMBF 5484
30542	6B	MUN 2112	MUN 2112
30543	6B	UN 2112	UN 2112
30544	6B	BC 817-25W	BC 817W
30545	6B	UN 5112	UN 5112
30546	6B	UN 9112	UN 9112
30547	6B(p,s)	BC 817-25	BC 817
30548	6BR	BC 817-25R	BC 817
30549	6C	MA 333	MA 333
30550	6C	UN 2113	UN 2113
30551	6C	UN 5113	UN 5113
30552	6C	MUN 5113	MUN 5113
30553	6C	BC 817-40W	BC 817W
30554	6C	MUN 2113	MUN 2113

30555	6C	MMBFU 310	MMBFU 310
30556	6C	UN 9113	UN 9113
30557	6C(p,s)	BC 817-40	BC 817
30558	6CR	BC 817-40R	BC 817
30559	6D	MA 334	MA 334
30560	6D	MA 363	MA 363
30561	6D	UN 9114	UN 9114
30562	6D	UN 2114	UN 2114
30563	6D	MUN 2114	MUN 2114
30564	6D	MMBF 5457	MMBF 5457
30565	6D	MUN 5114	MUN 5114
30566	6D	UN 5114	UN 5114
30567	6D(p)	BC 817	BC 817
30568	6E	MA 364	MA 364
30569	6E	MA 335	MA 335
30570	6E	UN 2115	UN 2115
30571	6E	FMMT-A93R	FMMT-A93R
30572	6E	MUN 2115	MUN 2115
30573	6E	MUN 5115	MUN 5115
30574	6E	MMBF 5460	MMBF 5460
30575	6E	UN 5115	UN 5115
30576	6E	BC 818-16W	BC 818W
30577	6E	UN 9115	UN 9115
30578	6E(p,s)	BC 818-16	BC 818
30579	6ER	BC 818-16R	BC 818
30580	6F	MA 365	MA 365
30581	6F	MA 337	MA 337
30582	6F	MMBF 4860	MMBF 4860
30583	6F	MUN 2116	MUN 2116
30584	6F	UN 9116	UN 9116
30585	6F	BC 818-25W	BC 818W
30586	6F	UN 5116	UN 5116
30587	6F	MUN 5116	MUN 5116
30588	6F	UN 2116	UN 2116
30589	6F(p,s)	BC 818-25	BC 818
30590	6FR	BC 818-25R	BC 818
30591	6G	PMBF 4393	PMBF 4393
30592	6G	MUN 2130	MUN 2130
30593	6G	BC 818-40W	BC 818W
30594	6G	MUN 5130	MUN 5130
30595	6G	MMBF 4393	MMBF 4393
30596	6G(p,s)	BC 818-40	BC 818
30597	6GR	BC 818-40R	BC 818
30598	6H	MA 366	MA 366
30599	6H	MA 338	MA 338

30600	6H	MUN 2131	MUN 2131
30601	6H	UN 2117	UN 2117
30602	6H	UN 5117	UN 5117
30603	6H	MUN 5131	MUN 5131
30604	6H	BC 818W	BC 818W
30605	6H	UN 9117	UN 9117
30606	6H	MMBF 5486	MMBF 5486
30607	6H(p)	BC 818	BC 818
30608	6I	UN 5118	UN 5118
30609	6I	UN 9118	UN 9118
30610	6I	UN 2118	UN 2118
30611	6J	PMBF 4391	PMBF 4391
30612	6J	MMBF 4391	MMBF 4391
30613	6J	MUN 2132	MUN 2132
30614	6J	MUN 5132	MUN 5132
30615	6K	MA 341	MA 341
30616	6K	MA 367	MA 367
30617	6K	MMBF 4392	MMBF 4392
30618	6K	PMBF 4392	PMBF 4392
30619	6K	UN 5119	UN 5119
30620	6K	UN 9119	UN 9119
30621	6K	MUN 2133	MUN 2133
30622	6K	MUN 5133	MUN 5133
30623	6K	UN 2119	UN 2119
30624	6L	MA 368	MA 368
30625	6L	UN 2110	UN 2110
30626	6L	MUN 2134	MUN 2134
30627	6L	UN 5110	UN 5110
30628	6L	MUN 5134	MUN 5134
30629	6L	UN 9110	UN 9110
30630	6L	MMBF 5459	MMBF 5459
30631	6M	MMBF 5485	MMBF 5485
30632	6M	UN 211D	UN 211D
30633	6M	UN 911D	UN 911D
30634	6M	UN 511D	UN 511D
30635	6N	MA 372	MA 372
30636	6N	MA 339	MA 339
30637	6N	UN 511E	UN 511E
30638	6N	UN 911E	UN 911E
30639	6N	UN 211E	UN 211E
30640	6O	UN 511F	UN 511F
30641	6O	UN 211F	UN 211F
30642	6O	UN 911F	UN 911F
30643	6P	BCX 71RH	BCX 71RH
30644	6P	UN 911H	UN 911H



30645	6P	UN 511H	UN 511H
30646	6P	MMBFJ 111	MMBFJ 111
30647	6P	UN 211H	UN 211H
30648	6Q	UN 511L	UN 511L
30649	6Q	UN 211L	UN 211L
30650	6Q	UN 911L	UN 911L
30651	6R	XP 4112	XP 4112
30652	6R	XN 4112	XN 4112
30653	6R	MMBFJ 112	MMBFJ 112
30654	6S	XN 4113	XN 4113
30655	6S	XP 4113	XP 4113
30656	6S	MA 371	MA 371
30657	6S	MA 353	MA 353
30658	6S	MMBFJ 113	MMBFJ 113
30659	6S	UN 5101	UN 5101
30660	6T	XP 4115	XP 4115
30661	6T	XN 4115	XN 4115
30662	6T	MA 331	MA 331
30663	6T	MMBFJ 310	MMBFJ 310
30664	6T	BCW 68RG	BCW 68RG
30665	6U	XP 4116	XP 4116
30666	6U	XN 4116	XN 4116
30667	6U	MA 332	MA 332
30668	6U	MMBFJ 309	MMBFJ 309
30669	6V	XP 6112	XP 6112
30670	6V	XN 6112	XN 6112
30671	6W	XN 6113	XN 6113
30672	6W	XP 6113	XP 6113
30673	6W	MMBFJ 175	MMBFJ 175
30674	6X	XP 6115	XP 6115
30675	6X	XN 6115	XN 6115
30676	6X	MMBFJ 176	MMBFJ 176
30677	6Y	XP 6116	XP 6116
30678	6Y	XN 6116	XN 6116
30679	6Y	MA 355	MA 355
30680	6Y	MMBFJ 177	MMBFJ 177
30681	6Y2	BZV 49/C6V2	BZV 49/C6V2
30682	6Y8	BZV 49/C6V8	BZV 49/C6V8
30683	6Z	XP 6111	XP 6111
30684	6Z	XN 6111	XN 6111
30685	6Z	MA 373	MA 373
30686	6Z	MMBF 170	MMBF 170
30687	7	HVU 307	HVU 307
30688	7.5B	HZF 7.5BP	HZF 7.5BP
30689	7.5C	HZF 7.5CP	HZF 7.5CP

30690	70	BFQ 70	BFQ 70
30691	702	2N7002	2N7002
30692	70HF-10..100	100..1000V, 70A	DS 75-...
30693	70HF-10R..100R	HF 70..	-
30694	71	BFQ 71	BFQ 71
30695	71T2	80V, 2A, 15W, 50MHz, B>30	BD 379, 2SC3252, 2SD1177...1178
30696	72	BFQ 72	BFQ 72
30697	72	2N7002	2N7002
30698	72T2	71T2, B>75	BD 379, 2SC3252, 2SD1177...1178
30699	73(s,p)	BAS 70	BAS 70
30700	73S	BFQ 73	BFQ 73
30701	73T2	80V, 1A, 15W, B>30	BD 139, BD 230, BD 379, 2SC3252
30702	74	BFQ 74	BFQ 74
30703	74(s,p)	BAS 70-04	BAS 70-04
30704	74T2	73T2, B>75	BD 139, BD 230, BD 379, 2SC3252
30705	75	BFQ 75	BFQ 75
30706	75(s,p)	BAS 70-05	BAS 70-05
30707	75(X,Y,Z)	U 02W7.5V	Z 02W 7.5V
30708	75Y	BZV 49/C75	BZV 49/C75
30709	76	BFQ 76	BFQ 76
30710	76(s,p)	BAS 70-06	BAS 70-06
30711	77(s)	BAS 70-07	BAS 70-07
30712	779	S 779 T	S 779 T
30713	77B	S 5277B	S 5277B
30714	77D	S 5277D	S 5277D
30715	77G	S 5277G	S 5277G
30716	77J	S 5277J	S 5277J
30717	77L	S 5277L	S 5277L
30718	77N	S 5277N	S 5277N
30719	78	MMBT 4258	MMBT 4258
30720	7A	MA 374	MA 374
30721	7A	MMBR 901	MMBR 901
30722	7A	UN 2121	UN 2121
30723	7AO	KTK 136-O	KTK 136
30724	7AY	KTK 136-Y	KTK 136
30725	7B	UN 2122	UN 2122
30726	7B	MMBR 920	MMBR 920
30727	7BO	KTQ 127-O	KTQ 127-O
30728	7BY	KTQ 127-Y	KTQ 127-Y
30729	7C	MA 376	MA 376
30730	7C	UN 2123	UN 2123
30731	7C	YTS 4123	YTS 4123
30732	7C	MMBR 930	MMBR 930
30733	7D	MA 377	MA 377
30734	7D	HD 4A	HD 4A

30735	7D	UN 2124	UN 2124
30736	7D	MMBR 931	MMBR 931
30737	7E	YTS 2221	YTS 2221
30738	7E	FMMT-A42R	FMMT-A42R
30739	7E	MMBR 2060	MMBR 2060
30740	7F	XN 6534	XN 6534
30741	7F	XP 6534	XP 6534
30742	7F	YTS 2221A	YTS 2221A
30743	7F	MMBR 4957	MMBR 4957
30744	7G	MMBR 5031	MMBR 5031
30745	7H	XN 6537	XN 6537
30746	7H	MMBR 5179	MMBR 5179
30747	7H	KST 5179	KST 5179
30748	7I	UN 212X	UN 212X
30749	7I	YTS 4400	YTS 4400
30750	7K	XN 1112	XN 1112
30751	7K	XP 1112	XP 1112
30752	7K	MA 357	MA 357
30753	7K	MMBR 2857	MMBR 2857
30754	7L	XP 1113	XP 1113
30755	7L	XN 1113	XN 1113
30756	7M	XN 1115	XN 1115
30757	7M	XP 1115	XP 1115
30758	7N	XN 1116	XN 1116
30759	7N	XP 1116	XP 1116
30760	7N	MA 392	MA 392
30761	7O	XP 111F	XP 111F
30762	7O	XN 111F	XN 111F
30763	7O	2SA1621-O	2SA1621
30764	7P	XN 1119	XN 1119
30765	7P	XP 1119	XP 1119
30766	7P	MA 393	MA 393
30767	7P	MMBR 911	MMBR 911
30768	7P	BCW 66RF	BCW 66RF
30769	7Q	XN 1114	XN 1114
30770	7Q	XP 1114	XP 1114
30771	7R	XN 2401	XN 2401
30772	7R	XP 2401	XP 2401
30773	7R	MMBR 536	MMBR 536
30774	7S	XN 1601	XN 1601
30775	7S	XP 1601	XP 1601
30776	7S	MA 391	MA 391
30777	7T	XN 4312	XN 4312
30778	7T	XP 4312	XP 4312
30779	7U	XN 4316	XN 4316

30780	7U	XP 4316	XP 4316
30781	7V	XN 4322	XN 4322
30782	7W	XP 6435	XP 6435
30783	7W	XN 6435	XN 6435
30784	7X	XP 4311	XP 4311
30785	7X	XN 4311	XN 4311
30786	7X	MMBR 571	MMBR 571
30787	7Y	UN 212Y	UN 212Y
30788	7Y	2SA1621-Y	2SA1621
30789	7Y	MMBR 941	MMBR 941
30790	7Y5	BZV 49/C7V5	BZV 49/C7V5
30791	7Z	XP 6211	XP 6211
30792	7Z	XN 6211	XN 6211
30793	8	HVU 308	HVU 308
30794	8.2B	HZF 8.2BP	HZF 8.2BP
30795	8.2C	HZF 8.2CP	HZF 8.2CP
30796	801	FC 801	FC 801
30797	802	FC 802	FC 802
30798	803	FC 803	FC 803
30799	804	FC 804	FC 804
30800	805	FC 805	FC 805
30801	806	FC 806	FC 806
30802	809	FC 809	FC 809
30803	81A	PMBZ 5250B	MMBZ 5250B, PMBZ 5250B
30804	81B	PMBZ 5251B	MMBZ 5251B, PMBZ 5251B
30805	81C	PMBZ 5252B	MMBZ 5252B, PMBZ 5252B
30806	81D	PMBZ 5253B	MMBZ 5253B, PMBZ 5253B
30807	81E	PMBZ 5254B	MMBZ 5254B, PMBZ 5254B
30808	81F	PMBZ 5255B	MMBZ 5255B, PMBZ 5255B
30809	81G	PMBZ 5256B	MMBZ 5256B, PMBZ 5256B
30810	81H	PMBZ 5257B	MMBZ 5257B, PMBZ 5257B
30811	82	BFQ 82	BFQ 82
30812	82(X,Y,Z)	U 02W8.2V	Z 02W 8.2V
30813	83	BAT 68	BAT 68
30814	84	BAT 68-04	BAT 68-04
30815	85	BAT 68-05	BAT 68-05
30816	85	MMBD 1701	MMBD 1701
30817	85A	MMBD 1701A	MMBD 1701A
30818	86	BAT 68-06	BAT 68-06
30819	87	MMBD 1703	MMBD 1703
30820	87(s)	BAT 68-07	BAT 68-07
30821	879	S 879 T	S 879 T
30822	87A	MMBD 1703A	MMBD 1703A
30823	88	MMBD 1704	MMBD 1704
30824	887	S 887	S 887

30825	88A	MMBD 1704A	MMBD 1704A
30826	89	MMBD 1705	MMBD 1705
30827	896	AEG 896	
30828	897	S 897T	S 897T
30829	89A	MMBD 1705A	MMBD 1705A
30830	8A	UN 5211	UN 5211
30831	8A	MMBZ 5226B	MMBZ 5226B
30832	8A	MUN 2211	MUN 2211
30833	8A	PMBZ 5226B	PMBZ 5226B
30834	8A	UN 2211	UN 2211
30835	8A	MUN 5211	MUN 5211
30836	8A	UN 9211	UN 9211
30837	8B	UN 5212	UN 5212
30838	8B	UN 9212	UN 9212
30839	8B	MUN 5212	MUN 5212
30840	8B	MMBZ 5227B	MMBZ 5227B
30841	8B	MUN 2212	MUN 2212
30842	8B	PMBZ 5227B	PMBZ 5227B
30843	8B	UN 2212	UN 2212
30844	8C	PMBZ 5228B	PMBZ 5228B
30845	8C	MUN 2213	MUN 2213
30846	8C	MMBZ 5228B	MMBZ 5228B
30847	8C	UN 2213	UN 2213
30848	8C	UN 5213	UN 5213
30849	8C	MUN 5213	MUN 5213
30850	8C	UN 9213	UN 9213
30851	8D	MUN 2214	MUN 2214
30852	8D	UN 9214	UN 9214
30853	8D	UN 5214	UN 5214
30854	8D	MUN 5214	MUN 5214
30855	8D	MMBZ 5229B	MMBZ 5229B
30856	8D	PMBZ 5229B	PMBZ 5229B
30857	8D	UN 2214	UN 2214
30858	8E	PMBZ 5230B	PMBZ 5230B
30859	8E	UN 5215	UN 5215
30860	8E	MUN 5215	MUN 5215
30861	8E	FMMT-A92R	FMMT-A92R
30862	8E	UN 9215	UN 9215
30863	8E	UN 2215	UN 2215
30864	8E	MUN 2215	MUN 2215
30865	8E	MMBZ 5230B	MMBZ 5230B
30866	8F	MUN 2216	MUN 2216
30867	8F	UN 2216	UN 2216
30868	8F	MMBZ 5231B	MMBZ 5231B
30869	8F	MUN 5216	MUN 5216

30870	8F	UN 5216	UN 5216
30871	8F	PMBZ 5231B	PMBZ 5231B
30872	8F	UN 9216	UN 9216
30873	8G	PMBZ 5232B	PMBZ 5232B
30874	8G	MUN 5230	MUN 5230
30875	8G	MMBZ 5232B	MMBZ 5232B
30876	8G	MUN 2230	MUN 2230
30877	8H	UN 2217	UN 2217
30878	8H	MMBZ 5233B	MMBZ 5233B
30879	8H	UN 9217	UN 9217
30880	8H	MUN 2231	MUN 2231
30881	8H	PMBZ 5233B	PMBZ 5233B
30882	8H	MUN 5231	MUN 5231
30883	8H	UN 5217	UN 5217
30884	8I	UN 9218	UN 9218
30885	8I	UN 2218	UN 2218
30886	8I	UN 5218	UN 5218
30887	8J	MMBZ 5234B	MMBZ 5234B
30888	8J	MUN 2232	MUN 2232
30889	8J	PMBZ 5234B	PMBZ 5234B
30890	8J	MUN 5232	MUN 5232
30891	8K	UN 2219	UN 2219
30892	8K	MMBZ 5235B	MMBZ 5235B
30893	8K	PMBZ 5235B	PMBZ 5235B
30894	8K	MUN 2233	MUN 2233
30895	8K	UN 9219	UN 9219
30896	8K	UN 5219	UN 5219
30897	8K	MUN 5233	MUN 5233
30898	8L	PMBZ 5236B	PMBZ 5236B
30899	8L	UN 2210	UN 2210
30900	8L	MMBZ 5236B	MMBZ 5236B
30901	8L	UN 9210	UN 9210
30902	8L	MUN 2234	MUN 2234
30903	8L	UN 5210	UN 5210
30904	8L	MUN 5234	MUN 5234
30905	8M	UN 921D	UN 921D
30906	8M	PMBZ 5237B	PMBZ 5237B
30907	8M	UN 221D	UN 221D
30908	8M	MMBZ 5237B	MMBZ 5237B
30909	8M	UN 521D	UN 521D
30910	8N	UN 921E	UN 921E
30911	8N	UN 221E	UN 221E
30912	8N	PMBZ 5238B	PMBZ 5238B
30913	8N	MMBZ 5238B	MMBZ 5238B
30914	8N	UN 521E	UN 521E



30915	8O	UN 521F	UN 521F
30916	8O	UN 921F	UN 921F
30917	8O	UN 221F	UN 221F
30918	8P	UN 921K	UN 921K
30919	8P	PMBZ 5239B	PMBZ 5239B
30920	8P	MMBZ 5239B	MMBZ 5239B
30921	8P	UN 221K	UN 221K
30922	8P	UN 521K	UN 521K
30923	8P1M	Igt/Ih<15/<10mA	TIC 122..., TIC 126..., T 7,5N...
30924	8P2M	8 P1M, 200V	TIC 122..., TIC 126..., T 7,5N...
30925	8P4J(Z)	<10/6mA	-
30926	8Q	UN 521L	UN 521L
30927	8Q	PMBZ 5240B	PMBZ 5240B
30928	8Q	UN 221L	UN 221L
30929	8Q	UN 921L	UN 921L
30930	8Q	MMBZ 5240B	MMBZ 5240B
30931	8R	XN 4212	XN 4212
30932	8R	XP 4212	XP 4212
30933	8R	PMBZ 5241B	PMBZ 5241B
30934	8R	MMBZ 5241B	MMBZ 5241B
30935	8S	XN 4213	XN 4213
30936	8S	XP 4213	XP 4213
30937	8S	UN 5201	UN 5201
30938	8S	PMBZ 5242B	PMBZ 5242B
30939	8S	MMBZ 5242B	MMBZ 5242B
30940	8T	XN 4215	XN 4215
30941	8T	XP 4215	XP 4215
30942	8T	PMBZ 5243B	PMBZ 5243B
30943	8T	MMBZ 5243B	MMBZ 5243B
30944	8U	XN 4216	XN 4216
30945	8U	XP 4216	XP 4216
30946	8U	MMBZ 5244B	MMBZ 5244B
30947	8U	PMBZ 5244B	PMBZ 5244B
30948	8V	XP 6212	XP 6212
30949	8V	XN 6212	XN 6212
30950	8V	PMBZ 5245B	PMBZ 52445B
30951	8V	MMBZ 5245B	MMBZ 5245B
30952	8W	XP 6213	XP 6213
30953	8W	XN 6213	XN 6213
30954	8W	PMBZ 5246B	PMBZ 52446B
30955	8W	MMBZ 5246B	MMBZ 5246B
30956	8X	XN 6215	XN 6215
30957	8X	XP 6215	XP 6215
30958	8X	MMBZ 5247B	MMBZ 5247B
30959	8X	PMBZ 5247B	PMBZ 52447B

30960	8Y	XN 6216	XN 6216
30961	8Y	XP 6216	XP 6216
30962	8Y	MMBZ 5248B	MMBZ 5248B
30963	8Y	PMBZ 5248B	PMBZ 52448B
30964	8Y2	BZV 49/C8V2	BZV 49/C8V2
30965	8Z	XN 4210	XN 4210
30966	8Z	XP 4210	XP 4210
30967	8Z	MMBZ 5249B	MMBZ 5249B
30968	8Z	PMBZ 5249B	PMBZ 524489
30969	9	HSU 88	HSU 88
30970	9.1(X,Y,Z)	U 02W9.1V	Z 02W9.1V
30971	9.1B	HZF 9.1BP	HZF 9.1BP
30972	9.1C	HZF 9.1CP	HZF 9.1CP
30973	9.1C	HZF 9.1CP	HZF 9.1CP
30974	9003	CS 9003	
30975	9010	CS 9010	
30976	9011	SS 9011	SS 9011
30977	9012(HH)	SS 9012	SS 9012
30978	9013(HH)	SS 9013	SS 9013
30979	9014	SS 9014	SS 9014
30980	9015	SS 9015	SS 9015
30981	9016	SS 9016	SS 9016
30982	9017	CS 9017	
30983	9018	SS 9018	SS 9018
30984	9020	CS 9020	
30985	9021	CS 9021	
30986	9022	CS 9022	
30987	903	FC 903	FC 903
30988	90T2	2N1990, 0,2W	BC 639, 2N3700...01, 2SD667, 2SD774
30989	91	2SK300-1	2SK300
30990	92	2SK300-2	2SK300
30991	92GE37A...C	2N6705..6707	2N6705...6707
30992	92GE487	2N6711	2N6711
30993	92GE488	2N6712	2N6712
30994	92GE489	2N6713	2N6713
30995	92GE77A...C	2N6708..6710	2N6708...6710
30996	92GU01	2N6714	2N6714
30997	92GU01A	2N6715	2N6715
30998	92GU05	2N6716	2N6716
30999	92GU06	2N6717	2N6717
31000	92GU10	2N6719	2N6719
31001	92GU391	2N6733	2N6733
31002	92GU392	2N6734	2N6734
31003	92GU393	2N6735	2N6735
31004	92GU45	2N6724	2N6724

31005	92GU45A	2N6725	2N6725
31006	92GU51	2N6726	2N6726
31007	92GU51A	2N6727	2N6727
31008	92GU55	2N6728	2N6728
31009	92GU56	2N6729	2N6729
31010	92PE37A	60/45V, 1A, 0,85W, >50MHz	BD 517, BD 525, 2SD1281...1284
31011	92PE37B	92 PE 37A, 80/60V	BD 519, BD 527, 2SD1281...1284
31012	92PE37C	92 PE 37A, 100/80V	BD 519, BD 529, 2SD1281...1284
31013	92PE487	160/160V, 0,03A, 0,85W	BF 615, BF 617, BF 757...759
31014	92PE488	92 PE 487, 250/250V	BF 615, BF 617, BF 757...759
31015	92PE489	92 PE 487, 300/300V	BF 617, BF 758...759, MPSU 10
31016	92PE77A	60/45V, 1A, 0,85W, >50MHz	BD 518, BD 526, 2SB957...960
31017	92PE77B	92 PE 77A, 80/60V	BD 520, BD 528, 2SB957...960
31018	92PE77C	92 PE 77A, 100/80V	BD 520, BD 530, 2SB957...960
31019	92PU01	40/30V, 2A, 0,85W, >100MHz	BD 507, BD 515, BD 525, 2SD1801
31020	92PU01A	92 PU 01, 50/40V	BD 509, BD 515, BD 525, 2SD1801
31021	92PU02	-/40V, 0,8A, 0,85W, >150MHz	BD 515, BD 525, 2SD1074...75, 2SD1733
31022	92PU05	-/60V, 2A, 0,85W, >50MHz	BD 527, BD 529, 2SC4135, 2SD1281...82
31023	92PU06	-/80V, 2A, 0,85W, >50MHz	BD 527, BD 529, 2SC4135, 2SD1281...82
31024	92PU07	-/80V, 2A, 0,85W, >50MHz	BD 527, BD 529, 2SC4135, 2SD1281...82
31025	92PU10	-/300V, 0,5A, 0,85W	BF 462, BF 758...759, MPSU 10
31026	92PU100	100/80V, 1A, 0,85W, >50MHz	BD 529, 2SD1074...75, 2SD1281...84
31027	92PU200	100/80V, 1A, 0,85W, >50MHz	BD 530, 2SB844...845, 2SB957...960
31028	92PU36	175/150V, 0,5A, 0,85W	BF 466...468, BF 666...668, BF 757...759
31029	92PU36A	92 PU 36, 225/200V	BF 467...468, BF 667...668, BF 757...759
31030	92PU36B	92 PU 36, 275/250V	BF 468, BF 668, BF 758...759
31031	92PU36C	92 PU 36, 325/300V	BF 462, BF 759
31032	92PU391	200/200V, 0,85W, >50MHz	BF 615, BF 617, BF 757...759, MPSU 10
31033	92PU392	92 PU 391, 250/250V	BF 615, BF 617, BF 757...759, MPSU 10
31034	92PU393	92 PU 391, 300/300V	BF 617, BF 758...759, MPSU 10
31035	92PU393	92 PU 391, 300/300V	BF 617, BF 758...759, MPSU 10
31036	92PU45	B>25000	-
31037	92PU45A	92 PU 45, 60V	-
31038	92PU51	40/30V, 2A, 0,85W, >50MHz	BD 508, BD 516, BD 526, 2SB1201
31039	92PU51A	92 PU 51, 50/40V	BD 510, BD 516, BD 526, 2SB1201
31040	92PU52	-/40V, 0,8A, 0,85W, >150MHz	BD 516, BD 526, 2SB844...45, 2SB1181
31041	92PU55	-/60V, 2A, 0,85W, >50MHz	BD 528, BD 530, 2SA1593, 2SB957...58
31042	92PU56	92 PU 56, -/80V	BD 528, BD 530, 2SA1593, 2SB957...58
31043	92PU57	92 PU 56, -/100V	BD 530, 2SA1593, 2SB957...58
31044	92PU60	-/300V, 0,5A, 0,85W, >50MHz	BF 465, BF 761...762, MPSU 60
31045	92PU95	B>15000	-
31046	92V	BFP 92A	BFP 92A
31047	93	2SK300-3	2SK300
31048	94	2SK300-4	2SK300
31049	95B	S 5295B	S 5295B

31050	95D	S 5295D	S 5295D
31051	95G	S 5295G	S 5295G
31052	95J	S 5295J	S 5295J
31053	97(p)	BCV 65	BCV 65
31054	972	AEG 972	
31055	98(p)	BCV 65B	BCV 65B
31056	992	AEG 992	
31057	9A	UN 2221	UN 2221
31058	9B	UN 2222	UN 2222
31059	9C	UN 2223	UN 2223
31060	9D	UN 2224	UN 2224
31061	9F	XN 1531	XN 1531
31062	9H	XP 1214	XP 1214
31063	9H	XN 1214	XN 1214
31064	9I	XN 2531	XN 2531
31065	9K	XN 1212	XN 1212
31066	9K	XP 1212	XP 1212
31067	9L	XP 1213	XP 1213
31068	9M	XN 1215	XN 1215
31069	9M	XP 1215	XP 1215
31070	9N	XP 1216	XP 1216
31071	9N	XN 1216	XN 1216
31072	9O	XN 2211	XN 2211
31073	9O	XP 2211	XP 2211
31074	9P	XN 1217	XN 1217
31075	9P	XP 1217	XP 1217
31076	9Q	XP 2210	XP 2210
31077	9Q	XN 2210	XN 2210
31078	9R	XP 2215	XP 2215
31079	9R	XN 2215	XN 2215
31080	9S	XP 1111	XP 1111
31081	9S	XN 1111	XN 1111
31082	9T	XP 1211	XP 1211
31083	9T	XN 1211	XN 1211
31084	9U	XN 4111	XN 4111
31085	9U	XP 4111	XP 4111
31086	9V	XN 4211	XN 4211
31087	9V	XP 4211	XP 4211
31088	9W	XN 7651	XN 7651
31089	9X	XN 111H	XN 111H
31090	9X	XP 111H	XP 111H
31091	9Y	XN 6543	XN 6543
31092	9Y1	BZV 49/C9V1	BZV 49/C9V1
31093	9Z	XP 8081	XP 8081
31094	9Z	XN 8081	XN 8081

31095	A	2SK1619	2SK1619
31096	A	2SK1617	2SK1617
31097	A	HVU 12	HVU 12
31098	A	MA 2S111	MA 2S111
31099	A	2SC2532	2SC2532
31100	A	2SK1066	2SK1066
31101	A	HVS 303	HVS 303
31102	A1	CFY 19-18	CFY 19
31103	A1	1SS308	1SS308
31104	A1	CFY 10	CFY 10
31105	A1	HN 2D01F	HN 2D01F
31106	A1	1SS272	1SS272
31107	A1	2SJ243	2SJ243
31108	A1	BAW 56W	BAW 56W
31109	A1	HSB 124SJ	HSB 124SJ
31110	A1	HSM 124S	HSM 124S
31111	A1	D70G.05T1	D70G.05T1
31112	A1(p,s)	BAW 56	BAW 56
31113	A11	MMBD 1501A	MMBD 1501A
31114	A13	MMBD 1503A	MMBD 1503A
31115	A13	1SS220	1SS220
31116	A14	MMBD 1504A	MMBD 1504A
31117	A14	1SS221	1SS221
31118	A14A...U	25...1000V, 1A	BYW 52...56, 1N4245...4249, 1N5059...5062
31119	A15	MMBD 1505A	MMBD 1505A
31120	A15	1SS222	1SS222
31121	A15A...U	25...800V, 3A	BY 251...255, BYW 17/..., 1N5624...5627
31122	A16	1SS223	1SS223
31123	A16-H010...H012	SSi A16-H010..H012	
31124	A17	2SK436-A17	2SK436
31125	A18	2SK436-A18	2SK436
31126	A19	2SK436-A19	2SK436
31127	A19-H025...H034	SSi A19-H025..H034	
31128	A2	CFY 30	CFY 30
31129	A2	CFY 10-22	CFY 10
31130	A2	1SS309	1SS309
31131	A2	HN 1D01F	HN 1D01F
31132	A2	PMBD 2836	PMBD 2836
31133	A2	HSM 221C	HSM 221C
31134	A2	MMBD 2836	MMBD 2836
31135	A2	BAT 18	BAT 18
31136	A2	ZC 833A	ZC 833A
31137	A20	2SK1066-20	2SK1066
31138	A20	2SK436-A20	2SK436
31139	A21	2SK1066-21	2SK1066

31140	A21	2SK436-A21	2SK436
31141	A22	2SK1066-22	2SK1066
31142	A22	2SK436-A22	2SK436
31143	A3	1SS306	1SS306
31144	A3	HN 1D02F	HN 1D02F
31145	A3	1SS360	1SS360
31146	A3	1SS300	1SS300
31147	A3	PMBD 2835	PMBD 2835
31148	A3	1SS181	1SS181
31149	A3	MMBD 2835	MMBD 2835
31150	A3	BAS 16	BAS 16
31151	A3	1S2835	1S2835
31152	A3	KDS 181	KDS 181
31153	A3(p)	BAT 17	BAT 17
31154	A3T	1PS181	1PS181
31155	A4	1SS319	1SS319
31156	A4	HN 1D03F	HN 1D03F
31157	A4	BAV 70W	BAV 70W
31158	A4	MC 2846	MC 2846
31159	A4	HSB 2836	HSB 2836
31160	A4	1S2836	1S2836
31161	A4	MC 2836	MC 2836
31162	A4	HSM 2836C	HSM 2836C
31163	A4(p,s)	BAV 70	BAV 70
31164	A44	BAV 74	BAV 74
31165	A46	BAR 46A	BAR 46A
31166	A5	HN 2D02FU	HN 2D02FU
31167	A5	HVC 317B	HVC 317B
31168	A5	1S2837	1S2837
31169	A5	PMBD2837	PMBD 2837
31170	A5	MMBD2837	MMBD 2837
31171	A5(p)	BRY 61	BRY 61
31172	A51	BRY 62	BRY 62
31173	A6	BAS 216	BAS 216
31174	A6	MC 2848	MC 2848
31175	A6	HSB 2838	HSB 2838
31176	A6	1S2838	1S2838
31177	A6	PMBD 2838	PMBD 2838
31178	A6	MMBD 2838	MMBD 2838
31179	A6	HSM 2838C	HSM 2838C
31180	A6	MC 2838	MC 2838
31181	A6(p,s)	BAS 16	BAS 16
31182	A61	BAS 28	BAS 28
31183	A6A	MMUN 2111	MMUN 2111
31184	A6B	MMUN 2112	MMUN 2112



31185	A6C	MMUN 2113	MMUN 2113
31186	A6D	MMUN 2114	MMUN 2114
31187	A6E	MMUN 2115	MMUN 2115
31188	A6F	MMUN 2116	MMUN 2116
31189	A6G	MMUN 2130	MMUN 2130
31190	A6H	MMUN 2131	MMUN 2131
31191	A6J	MMUN 2132	MMUN 2132
31192	A6K	MMUN 2133	MMUN 2133
31193	A6L	MMUN 2134	MMUN 2134
31194	A7	MC 2850	MC 2850
31195	A7	BAV 99W	BAV 99W
31196	A7	MC 2840	MC 2840
31197	A7(p,s)	BAV 99	BAV 99
31198	A8	BAS 19	BAS 19
31199	A8	HSM 223C	HSM 223C
31200	A81	BAS 20	BAS 20
31201	A82	BAS 21	BAS 21
31202	A8A	MMUN 2211	MMUN 2211
31203	A8B	MMUN 2212	MMUN 2212
31204	A8C	MMUN 2213	MMUN 2213
31205	A8D	MMUN 2214	MMUN 2214
31206	A8E	MMUN 2215	MMUN 2215
31207	A8F	MMUN 2216	MMUN 2216
31208	A8G	MMUN 2230	MMUN 2230
31209	A8H	MMUN 2231	MMUN 2231
31210	A8J	MMUN 2232	MMUN 2232
31211	A8K	MMUN 2233	MMUN 2233
31212	A8L	MMUN 2234	MMUN 2234
31213	A9	HSB 123	HSB 123
31214	A9	1SS322	1SS322
31215	A9	HSM 123	HSM 123
31216	A9	AAY 60	AAY 60
31217	A9	1SS294	1SS294
31218	A91	BAS 17	BAS 17
31219	A9903	Ub28..36V, Ib0,4<1mA, Itsm1A	D 32
31220	A9L	XN 1213	XN 1213
31221	AA	BCP 51	BCP 51
31222	AA	XN 6214	XN 6214
31223	AA	XP 6214	XP 6214
31224	AA	μPA571T	æPA571T
31225	AA	μPA501T	æPA501T
31226	AA	2SC4213A	2SC4213A
31227	AA	2SA1415	2SA1415
31228	AA	2SD1366-AA	2SD1366
31229	AA	BCX 51	BCX 51

31230	AA(p,s)	BCW 60A	BCW 60A
31231	AA1	2SC4942-AA1	2SC4942
31232	AA103	70V, 10mA	AA 117, AA 118, AA 133, 1N54(A)
31233	AA110	22,5V, 15mA	AA 112, AA 116, AA 119, 1N60
31234	AA111	40V, 10mA	AA 113, AA 119, 1N60
31235	AA112	20V, 30mA	AA 114, AA 116, 1N60
31236	AA113	65V, 25mA	AA 113, 1N60
31237	AA114	30V, 40mA	AA 116, 1N60
31238	AA115	45V, 35mA	AA 113, AA 119, 1N60
31239	AA116	30V, 30mA	AA 114, AA 138, 1N60
31240	AA117	115V, 50mA	AA 118, AA 133
31241	AA118	115V, 50mA	AA 117, AA 133
31242	AA119	45V, 35mA	AA 113, 1N60
31243	AA120	0,26..0,32V/8,5mA	-
31244	AA121	25V, 30mA	AA 114, AA 116, 1N60
31245	AA123	24V, 30mA	AA 114, AA 116, 1N60
31246	AA127	95V, 15mA	AA 117, AA 118, AA 133
31247	AA129	0,23V/5mA	-
31248	AA130	15V, 20mA	AA 112, AA 114, AA 116, AA 138, 1N60
31249	AA131	40V, 20mA	AA 114, AA 116, AA 138, 1N60
31250	AA132	110V, 50mA	AA 133
31251	AA133	AA 132, 140V	1N39
31252	AA134	AA 132, 70V	AA 132, AA 133
31253	AA135	30V, 150mA	AA 136, AA 139
31254	AA136	AA 135, 60V	1N270
31255	AA137	40V, 20mA	AA 114, AA 116, AA 138, 1N60
31256	AA138	25V, 20mA	AA 112, AA 114, AA 116, 1N60
31257	AA139	20V, 200mA	1N270
31258	AA140	32V, 20mA	AA 114, AA 116, AA 138, 1N60
31259	AA142	AA 140	AA 114, AA 116, AA 138, 1N60
31260	AA143(S)	30V, 60mA	AA 114, AA 116, AA 138, 1N60
31261	AA144	100V, 45mA	AA 117, AA 118, AA 133
31262	AA1A3Q	0,25W	DTC 113ZS, UN 4219
31263	AA1A4M	AA 1A3Q, RbRbe10kOhm	DTC 114ES, RN 1002, UN 4211, 2SC3402
31264	AA1A4P	AA 1A3Q, Rb10k, Rbe47kOhm	DTC 114YS, RN 1007, UN 4214, 2SC4048
31265	AA1A4Z	AA 1A3Q, Rb10kOhm, Rbe-	DTC 114TS, RN 1011, UN 4215, 2SC3860
31266	AA1F4M	AA 1A3Q, RbRbe22kOhm	DTC 124ES, RN 1003, UN 4212, 2SC3654
31267	AA1F4N	AA 1A3Q, Rb22k, Rbe47kOhm	DTC 124XS, KSR 1007, RN 1008
31268	AA1F4Z	AA 1A3Q, Rb22k, Rbe-	DTC 124TS, KSR 1011, UN 4217, 2SC4121
31269	AA1L3M	AA 1A3Q, RbRbe4,7kOhm	DTC 143ES, RN 1001, UN 421L, 2SC4363
31270	AA1L3N	AA 1A3Q, Rb4,7k, Rbe10kOhm	DTC 143XS, KSR 1005, UN 421F, 2SC4361
31271	AA1L3Z	AA 1A3Q, Rb4,7k, Rbe-	DTC 143TS, RN 1010, UN 4216, 2SC3901
31272	AA1L4L	AA 1A3Q, Rb47k, Rbe22kOhm	DTC 144WS, RN 1009, UN 421E, 2SC3401
31273	AA1L4M	AA 1A3Q, RbRbe47kOhm	DTC 144ES, RN 1004, UN 4213, 2SC3399
31274	AA1L4Z	AA 1A3Q, Rb47k, Rbe-	DTC 144TS, KSR 1012, UN 4210, 2SC3899

31275	AA2	2SC4942-AA2	2SC4942
31276	AA3	2SC4942-AA3	2SC4942
31277	AAA	MMBF 4856	MMBF 4856
31278	AAQ	2SD1757K-Q	2SD1757K
31279	AAR	2SD1757K-R	2SD1757K
31280	AAS	2SD1757K-S	2SD1757K
31281	AAX	MMBTA42	MMBTA 42
31282	AAY10-120	95V, 3,8A	-
31283	AAY11	90V, 35mA	AAY 49, AAZ 15, AAZ 17
31284	AAY12	100V, 115mA	1N270
31285	AAY13	25V, 50mA, 500ns	AAY 49, AAZ 15, AAZ 17
31286	AAY14	100V, 130mA	1N270
31287	AAY15	30V, 190mA, 25ns	AAZ 18
31288	AAY21	15V, 20mA, <12ns	AAY 48
31289	AAY22	30V, 50mA	AA 114, AA 116, 1N60
31290	AAY27	25V, 75mA, 15ns	-
31291	AAY28	100V, 50mA, 100ns	-
31292	AAY30	50V, 110mA, <150ns	-
31293	AAY32	30V, 110mA, <50ns	AAZ 18
31294	AAY33	15V, 100mA, <12ns	-
31295	AAY41	30V, 300mA, 350ns	AA 139, 1N270
31296	AAY42	70V, 75mA	AA 136
31297	AAY47	50V, 50mA, 200ns	AAZ 15, AAZ 17, 1N276
31298	AAY48	12V, 50mA, <6ns	-
31299	AAY49	40V, 150mA, 250ns	AAZ 15, AAZ 17
31300	AAY60	0,15V/0,05mA	-
31301	AAZ10	30V, 30mA, 500ns	AAY 49, AAZ 15, AAZ 17
31302	AAZ12	30V, 220mA	-
31303	AAZ13	8V, 30mA	-
31304	AAZ15	100V, 140mA, 350ns	-
31305	AAZ17	75V, 140mA, <350ns	AAZ 15
31306	AAZ18	30V, 180mA, <70ns	-
31307	AB	2SC4213B	2SC4213B
31308	AB	2SD1101B	2SD1101B
31309	AB	BCX 51-6	BCX 51
31310	AB	2SD1366-AB	2SD1366
31311	AB	2SA1416	2SA1416
31312	AB(p,s)	BCW 60B	BCW 60B
31313	AB1	2SD2425-AB1	2SD2425
31314	AB1A3M	0,75W	-
31315	AB1A4A	AB 1 A3M, Rb-, Rbe10kOhm	-
31316	AB1A4M	AB 1 A3M, Rb10k, Rbe10kOhm	-
31317	AB1F3P	Rbe10kOhm	-
31318	AB1J3P	Rbe10kOhm	-
31319	AB1L2Q	Rbe4,7kOhm	-

31320	AB1L3N	Rbe10kOhm	-
31321	AB2	2SD2425-AB2	2SD2425
31322	AB3	2SD2425-AB3	2SD2425
31323	ABG	2SA1312-GR	2SA1312
31324	ABL	2SA1312-BL	2SA1312
31325	ABX	MMBTA43	MMBTA 43
31326	AC	BCP 51-10	BCP 51
31327	AC	XN 1210	XN 1210
31328	AC	XP 1210	XP 1210
31329	AC	2SD1101C	2SD1101C
31330	AC	BCX 51-10	BCX 51
31331	AC	2SA1417	2SA1417
31332	AC	RXT 2907A	RXT 2907A
31333	AC	2SD1366A-AC	2SD1366A
31334	AC(p,s)	BCW 60C	BCW 60C
31335	L,R	Igt/Ih<15/5mA	TAG 137-...
31336	AC03DJM(Z)	<12/7mA	-
31337	AC03FJM(Z)	AC 03DJM, 600V	-
31338	L,R	Igt/Ih<15/5mA	TAG 137-...
31339	AC05DJM(Z)	<10/10mA	-
31340	AC05FJM(Z)	AC 05DJM, 600V	-
31341	L,R	8A(Tc86°),Igt/Ih<75/30mA	BT 158/..., MAC 222-..., TIC 225...
31342	R	AC 08BGM..FGM..	-
31343	AC105	40V, 1A, 0,4W, B33	AC 128(K), AC 153(K), AC 188(K)
31344	AC106	AC 105, B50	AC 128(K), AC 153(K), AC 188(K)
31345	AC107	15V, 10mA	AC 125, AC 126, AC 151(r)
31346	AC108	20V, 50mA, B30..60	AC 125, AC 126, AC 151
31347	AC109	AC 108, B50..100	AC 125, AC 126, AC 151
31348	L,R	/30mA	BT 162/..., SC 146..., TIC 236...
31349	R	AC 10BGM..FGM..	-
31350	AC110	AC 108, B75..150	AC 125, AC 126, AC 151
31351	AC113	26V, 50mA	AC 125, AC 126, AC 151
31352	AC114	26V, 200mA	AC 125, AC 126, AC 151
31353	AC115	26V, 50mA	AC 125, AC 126, AC 151
31354	AC116	30V, 0,2A	AC 128K, AC 153K, AC 188K
31355	AC117	32V, 1A, 1,1W	AC 128K, AC 153K, AC 188K
31356	AC119		AC 128, AC 153, AC 188
31357	AC120	20V, 0,3A, 0,6W	AC 128, AC 153, AC 188
31358	AC121	20V, 0,3A, 0,9W	AC 128, AC 153, AC 188
31359	AC122	30V, 0,2A	AC 125, AC 126, AC 151
31360	AC123	45V, 0,2A, 0,225W	AC 128K, AC 153K, ACY 24, ASY 48
31361	AC124	45V, 1A, 1,1W	AC 128K, AC 153K, AC 188K
31362	AC125	32V, 0,2A, B80..170	AC 126, AC 151, ACY 24, ASY 48
31363	AC126	AC 125, B130..300	AC 151, ACY 24, ASY 48
31364	AC127	32V, 0,5A, 0,34W	AC 176, AC 187

31365	AC128	32V, 1A, 1W	AC 153, AC 188
31366	AC128K	AC 128	AC 153K, AC 188K
31367	AC129	9V, 10mA	OC 57...60
31368	L,R	/30mA	BT 162/..., SC 149..., TIC 236...
31369	R	AC 12BGM..FGM..	-
31370	AC130	20V, 0,1A	-
31371	AC131	30V, 1A, 0,75W	AC 128, AC 153, AC 188
31372	AC132	32V, 0,2A, 0,5W	AC 128, AC 151, AC 153, AC 188
31373	AC134	32V, 0,2A, $\beta$ 45	AC 125, AC 126, AC 151
31374	AC135	32V, 0,2A, $\beta$ 110	AC 125, AC 126, AC 151
31375	AC136	40V, 0,2A, $\beta$ 110	AC 125, AC 126, AC 151
31376	AC137	32V, 0,05A, $\beta$ 170	AC 125, AC 126, AC 151
31377	AC138	25V, 1,2A, 1W	AC 128, AC 153, AC 188
31378	AC139	32V, 1A, 1W	AC 128, AC 153, AC 188
31379	AC139K	AC 139	AC 128K, AC 153K, AC 188K
31380	AC141	32V, 1,2A, 1W	AC 176, AC 187
31381	AC141K	AC 141	AC 176K, AC 187K
31382	AC142	32V, 1,2A, 1W	AC 128, AC 153, AC 188
31383	AC142K	AC 142	AC 128K, AC 176K, AC 188K
31384	AC150	30V, 50mA	AC 151r, ACY 32
31385	AC151(r)	32V, 0,2A	AC 122, AC 125, AC 126, ACY 32
31386	AC152	32V, 0,5A, 0,9W	AC 128, AC 153, AC 188
31387	AC153	32V, 2A, 1W	AC 128, AC 188
31388	AC153K	AC 153	AC 128K, AC 188K
31389	AC154	26V, 0,5A, 0,2W	AC 128, AC 153, AC 188
31390	AC155	26V, 50mA, B20..68	AC 125, AC 126, AC 151
31391	AC156	AC 155, B40..114	AC 125, AC 126, AC 151
31392	AC157	26V, 0,5A, 0,2W	AC 127, AC 176, AC 187
31393	AC160	15V, 10mA	AC 151r, ACY 32
31394	AC161	15V, 100mA	AC 151r, ACY 32
31395	AC162	32V, 0,2A, $\beta$ 80..170	AC 125, AC 126, AC 151
31396	AC163	AC 162, $\beta$ 130..300	AC 126, AC 151
31397	AC164	10V, 30mA	AC 125, AC 126, AC 151
31398	AC165	32V, 50mA	AC 125, AC 126, AC 151
31399	AC166	32V, 0,5A, 0,2W, B52..315	AC 128, AC 153, AC 188
31400	AC167	AC 166, B45..250	AC 128, AC 153, AC 188
31401	AC168	32V, 0,5A, 0,2W	AC 127, AC 176, AC 187
31402	AC169	2V, 30mA	-
31403	L,R	/40mA	MAC 15-..., SC 151..., TIC 246...
31404	AC16BIF..FIFL,R	AC 16BGM..FGM..	-
31405	AC170	32V, 0,2A, $\beta$ 80..170	AC 125, AC 126, AC 151
31406	AC171	AC 170, $\beta$ 130..300	AC 126, AC 151
31407	AC172	32V, 10mA	AC 127
31408	AC173	32V, 0,3A, 0,2W	AC 128, AC 151, AC 153, AC 188
31409	AC174	32V, 0,6A, 0,6W	AC 128, AC 153, AC 188

31410	AC175	25V, 1A, 1,1W	AC 176K, AC 187K
31411	AC176	32V, 1A, 1W	AC 187
31412	AC176K	AC 176	AC 187K
31413	AC177	32V, 0,5A, 0,2W	AC 128, AC 153, AC 188
31414	AC178	20V, 0,7A, 1,1W	AC 128K, AC 153K, AC 188K
31415	AC179	20V, 0,7A, 1,1W	AC 176K, AC 187K
31416	AC180	32V, 1,5A, 0,3W	AC 128, AC 153, AC 188
31417	AC180K,L	AC 180, 0,44W	AC 128K, AC 153K, AC 188K
31418	AC181	32V, 1,5A, 0,3W	AC 176, AC 187
31419	AC181K,L	AC 181, 0,44W	AC 176K, AC 187K
31420	AC182	32V, 0,15A	AC 125, AC 126, AC 151
31421	AC183	32V, 0,15A	AC 127, AC 176, AC 187
31422	AC184	32V, 0,5A, 0,16W	AC 128, AC 153, AC 188
31423	AC185	32V, 0,5A, 0,16W	AC 127, AC 176, AC 187
31424	AC186	30V, 0,7A, 0,75W	AC 127, AC 167, AC 187
31425	AC187	25V, 1A, 1W	AC 176
31426	AC187K	AC 187	AC 176K
31427	AC188	25V, 1A, 1W	AC 128, AC 153
31428	AC188K	AC 188	AC 128K, AC 153K
31429	AC191	AC 192	AC 151r, ACY 32
31430	AC192	32V, 0,25A	AC 125, AC 126, AC 151
31431	AC193	32V, 1A, 1W	AC 128, AC 153, AC 188
31432	AC193K	AC 193	AC 128K, AC 153K, AC 188K
31433	AC194	32V, 1A, 1W	AC 176, AC 187
31434	AC194K	AC 194	AC 176K, AC 187K
31435	AC1A3M	RbRbe1kOhm, 20V, 2A, 0,75W	-
31436	AC1A4A	AC 1A3M, Rb-, Rbe10kOhm	-
31437	AC1F2Q	Rbe2,2kOhm	-
31438	AC1F3M	AC 1A3M, RbRbe2,2kOhm	-
31439	AC1F3P	AC 1A3M, Rb2,2k, Rbe10kOhm	-
31440	AC1L2N	AC 1A3M, Rb0,47k, Rbe1kOhm	-
31441	AC1L2Q	Rbe4,7kOhm	-
31442	AC230	24V, 10mA	AC 125, AC 126, AC 151
31443	AC240	24V, 10mA, $\beta$ 30..50	AC 125, AC 126, AC 151
31444	AC241	AC 240, $\beta$ 50..80	AC 125, AC 126, AC 151
31445	AC242	AC 240, $\beta$ 80..150	AC 125, AC 126, AC 151
31446	AC250	32V, 50mA	AC 125, AC 126, AC 151
31447	AC251	32V, 125mA	AC 125, AC 126, AC 151
31448	AC25BIF..FIFL,R	/40mA	MAC 515(A)-...
31449	AC2A4A	140MHz	-
31450	AC330	24V, 10mA	AC 127
31451	AC340	24V, 10mA, $\beta$ 30..50	AC 127
31452	AC341	AC 340, $\beta$ 50..80	AC 127
31453	AC342	AC 340, $\beta$ 80..150	AC 127
31454	AC350	32V, 50mA	AC 127



31455	AC351	32V, 125mA	AC 127
31456	AC402	32V, 1,5A	AC 128, AC 153, AC 188
31457	AC404	45V, 0,5A	AC 128, AC 153, AC 188
31458	AC502	16V, 0,1A, B35..65	AC 125, AC 126, AC 151
31459	AC503	16V, 0,1A, B55..120	AC 125, AC 126, AC 151
31460	AC504	16V, 0,1A, B72..192	AC 125, AC 126, AC 151
31461	AC508	16V, 0,1A, B100..200	AC 126, AC 151
31462	AC509	16V, 0,1A, B100..200	AC 126, AC 151
31463	AC515	16V, 0,1A, B>60	AC 125, AC 126, AC 151
31464	AC516	16V, 0,1A, B>95	AC 125, AC 126, AC 151
31465	AC517	30V, 0,2A, B>45	AC 125, AC 126, AC 151
31466	AC518	30V, 0,2A, B>85	AC 125, AC 126, AC 151
31467	AC519	30V, 0,2A, B25..45	AC 125, AC 126, AC 151
31468	AC520	30V, 0,2A, B35..65	AC 125, AC 126, AC 151
31469	AC521	30V, 0,2A, B55..120	AC 125, AC 126, AC 151
31470	AC524	45V, 0,5A, B20..42	AC 128, AC 153, AC 188
31471	AC525	45V, 0,5A, B35..65	AC 128, AC 153, AC 188
31472	AC526	45V, 0,5A, B55..90	AC 128, AC 153, AC 188
31473	AC527	45V, 0,5A, B70..120	AC 128, AC 153, AC 188
31474	AC530	24V, 10mA, B20..40	AC 125, AC 126, AC 151
31475	AC540	24V, 10mA, B30..50	AC 125, AC 126, AC 151
31476	AC541	AC 540, B50..80	AC 125, AC 126, AC 151
31477	AC542	AC 540, B80..150	AC 125, AC 126, AC 151
31478	AC548	26V, 0,15A	AC 125, AC 126, AC 151
31479	AC549	26V, 0,3A	AC 125, AC 126, AC 151
31480	AC550	32V, 50mA	AC 125, AC 126, AC 151
31481	AC551(R)	32V, 125mA	AC 125, AC 126, AC 151
31482	AC552	60V, 125mA	ACY 24, ASY 48
31483	AC553	20V, 0,3A, 0,12W	AC 128, AC 153, AC 188
31484	AC554	26V, 0,3A, 0,12W	AC 128, AC 153, AC 188
31485	AC555	32V, 0,3A, 0,12W	AC 128, AC 153, AC 188
31486	AC556	25V, 1A, 0,23W	AC 128, AC 153, AC 188
31487	AC556K	AC 556, 0,35W	AC 128K, AC 153K, AC 188K
31488	AC558	25V, 1A, 0,23W	AC 176, AC 187
31489	AC558K	AC 558, 0,35W	AC 176K, AC 187K
31490	AC570	70V, 0,5A, 0,15W, B17..40	ASY 48
31491	AC571	AC 570, B30..60	ASY 48
31492	AC572	AC 570, B45..85	ASY 48
31493	AC573	AC 570, B65..110	ASY 48
31494	AC577	AC 570, B45..110	ASY 48
31495	AC598	105V, 0,2A, 0,1W	-
31496	ACG	KTA1517-G	KTA 1517
31497	ACL	KTA1517-L	KTA 1517
31498	ACL	2SC3837K-L	2SC3837K
31499	ACM	2SC3837K-M	2SC3837K

31500	ACN	2SC3837K-N	2SC3837K
31501	ACO	2SA1313-O	2SA1313
31502	ACP	2SC3837K-P	2SC3837K
31503	ACQ	2SC3837K-Q	2SC3837K
31504	ACY	2SA1313-Y	2SA1313
31505	ACY10	32V, 50mA, B>32	AC 125, AC 126, AC 151
31506	ACY11	32V, 50mA, B>38	AC 125, AC 126, AC 151
31507	ACY12	32V, 50mA, B>38	AC 151r, ACY 32
31508	ACY13	16V, 50mA, B>50	AC 125, AC 126, AC 151
31509	ACY14	32V, 50mA, B>54	AC 125, AC 126, AC 151
31510	ACY15	32V, 50mA, B>54	AC 151r, ACY 32
31511	ACY16	40V, 0,4A, 0,8W	AC 128K, AC 153K, ACY 33
31512	ACY17	70V, 0,5A, 0,26W, B50..150	ASY 77
31513	ACY18	50V, 0,5A, 0,26W, B40..120	ASY 77
31514	ACY19	50V, 0,5A, 0,26W, B80..250	ASY 77
31515	ACY20	40V, 0,5A, 0,26W, B80..145	AC 128, AC 153, ASY 77
31516	ACY21	40V, 0,5A, 0,26W, B90..250	AC 128, AC 153, ASY 77
31517	ACY22	20V, 0,5A, 0,26W, B30..300	AC 128, AC 153, AC 188, ASY 77
31518	ACY23	32V, 0,2A	AC 125, AC 126, AC 151, ACY 32
31519	ACY24	70V, 0,3A, 0,53W	ASY 48
31520	ACY25	32V, 50mA	AC 125, AC 126, AC 151
31521	ACY27	40V, 0,25A, 0,2W, B20..55	AC 125, AC 126, AC 151, ACY 32
31522	ACY28	40V, 0,25A, 0,2W, B45..150	AC 125, AC 126, AC 151, ACY 32
31523	ACY29	40V, 0,25A, B45..145	AC 151r, ACY 32
31524	ACY30	40V, 0,25A, 0,2W, B60..200	AC 126, AC 151, ACY 32
31525	ACY31	50V, 0,25A, 0,2W, B>35	AC 125, AC 126, AC 151, ACY 32
31526	ACY32	ACY 23	AC 151r
31527	ACY33	32V, 1A, 1,1W	AC 128, AC 153, AC 188
31528	ACY34	30V, 50mA, B20..40	AC 125, AC 126, AC 151
31529	ACY35	30V, 50mA, B30..75	AC 125, AC 126, AC 151
31530	ACY36	30V, 250mA, B30..90	AC 125, AC 126, AC 151
31531	ACY38	15V, 0,1A	AC 151r, ACY 32
31532	ACY39	110V, 0,5A, 0,26W	2N2042, 2N2043
31533	ACY40	32V, 0,5A, 0,26W	AC 128, AC 153, ASY 77
31534	ACY41	21V, 0,5A, 0,26W	AC 128, AC 153, AC 188, ASY 77
31535	ACY44	50V, 0,5A, 0,26W	AC 128, AC 153, ASY 77
31536	ACY50	32V, 0,2A, 0,22W, B30..150	AC 125, AC 126, AC 151, ACY 32
31537	ACY51(R)	32V, 0,2A, 0,22W, B30..300	AC 125, AC 126, AC 151(r), ACY 32
31538	ACY52	60V, 0,2A, 0,22W, B50..120	ASY 48
31539	ACY55	32V, 0,3A, 0,22W	AC 128, AC 153, AC 188
31540	ACZ10	70V, 0,3A, 0,4W	ASY 48
31541	AD	BCP 51-16	BCP 51
31542	AD	XP 1110	XP 1110
31543	AD	XN 1110	XN 1110
31544	AD	P4 SMA-6.8	P4 SMA-6.8

31545	AD	BCX 51-16	BCX 51
31546	AD	2SA1418	2SA1418
31547	AD	2SD1366A-AD	2SD1366A
31548	AD	RXT 3906	RXT 3906
31549	AD(p,s)	BCW 60D	BCW 60D
31550	AD1202	45V, 1,5A, 13,5W	AD 149, AL 102, AUY 19, 2N1539...1548
31551	AD1203	AD 1202, 60V	AL 102, AUY 19, 2N1540...34, 2N1545...48
31552	AD130	32V, 3A, 30W	AD 149, AL 102, 2N1539...1548
31553	AD131	AD 130, 64V	AL 102, 2N1540...1541, 2N1545...1546
31554	AD132	AD 130, 80V	AL 102, 2N1541...1542, 2N1546...1547
31555	AD133	50V, 15A, 36W	AUY 29, 2N1549...1560
31556	AD134	65V, 10A, 22,5W	AUY 21, 2N2526, 2N2289, 2N2292
31557	AD135	80V, 8A, 22,5W	AUY 22, 2N2526, 2N2289, 2N2292
31558	AD136	40V, 10A, 11W	AUY 18, AUY 35, AUY 36, 2SB627
31559	AD138(/50)	40(70)V, 8A, 30W	AUY 21, AL 102, 2N2526, 2N2288...2293
31560	AD139	32V, 3,5A, 13W	AD 162
31561	AD140	55V, 3A, 35W	AD 149, AL 102, AUY 19, 2N1540, 2N1545
31562	AD142	80V, 10A, 30W	AUY 22, AL 102, 2N2526, 2N2289, 2N2292
31563	AD143(R)	AD 142, 40(32)V	AUY 21, AL 102, ASZ 16...17, 2N2288/91
31564	AD145	AD 142, 20V	AUY 21, AL 102, ASZ 16...17, 2N2288/91
31565	AD148	32V, 3,5A, 13,5W	AD 162
31566	AD149	50V, 3,5A, 27,5W	AL 102, AUY 19, ASZ 16...17, 2N1539...48
31567	AD150	AD 149, 32V	AUY 21, AL 102, ASZ16...17, 2N1539...48
31568	AD152	45V, 1A, 6W	AD 162
31569	AD153	40V, 3A, 33W	AD 149, AL 102, AUY 19, 2N1539...1548
31570	AD155	25V, 1A, 6W	AD 162
31571	AD156	30V, 3A, 6W	AD 162
31572	AD157	30V, 3A, 6W	AD 161
31573	AD159	40V, 8A, 9W	AUY 18, AUY 35, AUY 36, 2SB627
31574	AD160	AD 159, 30V	AUY 18, AUY 35, AUY 36, 2SB627
31575	AD161	32V, 1A, 4W(Tc70°)	-
31576	AD162	32V, 1A, 6W(Tc63°)	-
31577	AD163	100V, 3A, 30W	AL 102, AUY 34, ASZ 15, ASZ 18
31578	AD164	25V, 1A, 6W	AD 162
31579	AD165	25V, 1A, 5,3W	AD 161
31580	AD166	60V, 5A, 27,5W	AL 102, AUY 21, 2N1540, 2N1545
31581	AD167	AD 166, 75V	AL 102, AUY 22, 2N1541, 2N1546
31582	AD169	45V, 1A, 6W	AD 162
31583	AD1A3M	RbRbe1kOhm, 80V, 1A, 0,75W	-
31584	AD1A4A	Rbe10kOhm	-
31585	AD1A4M	AD 1A3M, RbRbe10kOhm	-
31586	AD1F2Q	Rbe2,2kOhm	-
31587	AD1F3P	Rbe10kOhm	-
31588	AD1L2Q	Rbe4,7kOhm	-
31589	AD1L3N	Rbe10kOhm	-

31590	AD262	35V, 4A, 10W(Tc60°)	AD 162
31591	AD263	AD 262, 60V	-
31592	AD2A3M..L3N	AD 1A3M..L3N, 60V	-
31593	AD301	30V, 3A, 30W	AD 149, AL 102, AUY 19, 2N1539...1548
31594	AD302	40V, 3A, 45W	AD 149, AL 102, AUY 19, 2N1539...1548
31595	AD303	60V, 3A, 45W	AL 102, AUY 19, 2N1540, 2N1545
31596	AD304	80V, 3A, 45W	AL 102, AUY 20, 2N1541, 2N1546
31597	AD312	40V, 6A, 45W	AL 102, AUY 28, 2N3611, 2N3613
31598	AD313	AD 312, 60V	AL 102, AUY 28, 2N3612, 2N3614
31599	AD314	AD 312, 80V	AL 102, AUY 28, 2N3615, 2N3617
31600	AD315	32V, 2,5A, 6W	AD 161
31601	AD325	100V, 10A, 45W	AL 102, AUY AUY 37, 2N2527, 2N2290/93
31602	AD412	24V, 1A	AD 162
31603	AD415	32V, 2,5A, 6W	AD 162
31604	AD430	32V, 1,4A, 6W	AD 149, AL 102, AUY 19, 2N2137, 2N2142
31605	AD431	32V, 2A, 17W	AD 149, AL 102, AUY 19, 2N2137, 2N2142
31606	AD432	32V, 1,5A, 20W	AD 149, AL 102, AUY 19, 2N2137, 2N2142
31607	AD433	AD 432, 45V	AD 149, AL 102, AUY 19, 2N2138, 2N2143
31608	AD434	45V, 3A, 20W	AD 149, AL 102, AUY 19, 2N2138, 2N2143
31609	AD436	40V, 3,5A, 30W	AD 149, AL 102, AUY 19, 2N2138, 2N2143
31610	AD437	64V, 3A, 20W	AL 102, AUY 19, 2N2139, 2N2144
31611	AD438	AD 437, 60V	AL 102, AUY 19, 2N2139, 2N2144
31612	AD439	AD 437, 80V	AL 102, AUY 20, 2N2141, 2N2146
31613	AD450	32V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31614	AD451	32V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31615	AD452	32V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31616	AD453	35V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31617	AD454	35V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31618	AD455	35V, 5A, 30W	AL 102, AUY 28, 2N1539...1548
31619	AD456	50V, 5A, 30W	AL 102, AUY 28, 2N1540...43, 2N1545...48
31620	AD457	50V, 5A, 30W	AL 102, AUY 28, 2N1540...43, 2N1545...48
31621	AD458	80V, 5A, 30W	AL 102, AUY 28, 2N1541...43, 2N1546...48
31622	AD459	80V, 5A, 30W	AL 102, AUY 28, 2N1541...43, 2N1546...48
31623	AD460	32V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31624	AD461	32V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31625	AD462	32V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31626	AD463	35V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31627	AD464	35V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31628	AD465	35V, 6A, 30W	AL 102, AUY 28, 2N1539...43, 2N1544...48
31629	AD466	50V, 6A, 30W	AL 102, AUY 28, 2N1540...43, 2N1545...48
31630	AD467	50V, 6A, 30W	AL 102, AUY 28, 2N1540...43, 2N1545...48
31631	AD468	70V, 6A, 30W	AL 102, AUY 28, 2N1541...43, 2N1546...48
31632	AD469	70V, 6A, 30W	AL 102, AUY 28, 2N1541...43, 2N1546...48
31633	AD541	24V, 8A, 45W	2N2078, 2N2082, 2N1980, 2N2491
31634	AD542	80V, 8A, 45W	2N2075, 2N2079, 2N1982, 2N2492

31635	AD545	80V, 8A, 45W	2N2076, 2N2080, 2N1982, 2N2491
31636	AD701D..J	40..80V, 6A, 45W	AL 102, AUY 28, 2N1539...1548
31637	AD702A..Z	30..100V, 3..10A, 45W	AL 102, AUY 28, 2N1539...1548
31638	ADG	KTC3911-G	KTC 3911
31639	ADL	KTC3911-L	KTC 3911
31640	ADL	2SC3838K-L	2SC3838K
31641	ADM	2SC3838K-M	2SC3838K
31642	ADN	2SC3838K-N	2SC3838K
31643	ADP	2SC3838K-P	2SC3838K
31644	ADQ	2SC3838K-Q	2SC3838K
31645	ADY10	32V, 0,6A, 0,25W	2SB493
31646	ADY11	60V, 0,6A, 0,25W	-
31647	ADY12	32V, 0,6A, 0,25W	2SB493
31648	ADY13	60V, 0,6A, 0,25W	-
31649	ADY18	60V, 15A, 45W	2N1550...52, 2N1554...56, 2N1558...60
31650	ADY19	32V, 0,6A, 0,25W	2SB493
31651	ADY20	60V, 0,6A, 0,25W	-
31652	ADY21	60V, 0,6A, 0,25W	-
31653	ADY22	30V, 10A, 40W	AUY 21, 2N2289, 2N2292, 2N2526
31654	ADY23	ADY 22, 80V	AUY 37, 2N2289, 2N2292, 2N2526
31655	ADY24	ADY 22, 80V	AUY 37, 2N2289, 2N2292, 2N2526
31656	ADY25	ADY 22, 100V	AUY 37, 2N2290, 2N2293, 2N2527
31657	ADY26	80V, 25A, 100W	2N1519, 2N1521, 2N1523
31658	ADY27	32V, 3,5A, 27,5W	AD 149, AL 102, AUY 19, 2N2137, 2N2142
31659	ADY28	80V, 6A, 33W	AL 102, AUY 22, 2N3615, 2N3617
31660	ADY30	45V, 50A, 150W	2N4048...4053
31661	ADY31	60V, 160A, 85W	-
31662	ADY32	80V, 160A, 35W	-
31663	ADZ11	50V, 15A, 45W	2N1980, 2N2077, 2N2081
31664	ADZ12	ADZ 11, 80V	2N1982, 2N2075, 2N2079, 2N2492
31665	AE	BCP 52	BCP 52
31666	AE	3SK268	3SK268
31667	AE	3SK219	3SK219
31668	AE	P4 SMA-6.8A	P4 SMA-6.8A
31669	AE	BCW 60E	BCW 60E
31670	AE	2SA1365-E	2SA1365
31671	AE	2SA1419	2SA1419
31672	AE	BCX 52	BCX 52
31673	AE	2SA1363-E	2SA1363
31674	AEG	2SA1362-GR	2SA1362
31675	AEL	2SC3839K-L	2SC3839K
31676	AEL	2SA1362-BL	2SA1362
31677	AEM	2SC3839K-M	2SC3839K
31678	AEN	2SC3839K-N	2SC3839K
31679	AEO	KTC3883-O	KTC 3883

31680	AEP	2SC3839K-P	2SC3839K
31681	AEP	2SB1424-P	2SB1424
31682	μPA500T	60V, 0,1A, 250MHz	-
31683	μPA501T	60V, 0,1A, 180MHz	-
31684	μPA502T	50V, 0,1A, <25Ohm(10mA)	-
31685	μPA503T	50V, 0,1A, <60Ohm(10mA)	-
31686	μPA504T	60V, 0,1A, 180/250MHz	-
31687	μPA505T	50V, 0,1A, <60/25Ohm	-
31688	μPA570T	μPA 500T	-
31689	μPA571T	μPA 501T	-
31690	μPA572T	30V, +-0,1A, <8Ohm(10mA)	-
31691	μPA573T	30V,+-0,1A, <25Ohm(10mA)	-
31692	μPA574T	μPA 504T	-
31693	μPA600T	μPA 500T	-
31694	μPA601T	μPA 501T	-
31695	μPA602T	μPA 502	-
31696	μPA603T	μPA 503	-
31697	μPA604T	μPA 500T	-
31698	μPA605T	μPA 501T	-
31699	μPA606T	μPA 502	-
31700	μPA607T	μPA 503	-
31701	μPA608T	0,1A	-
31702	μPA609T	60V, 0,5A, 200/150MHz	-
31703	μPA670T	μPA 500T	-
31704	μPA671T	μPA 501T	-
31705	μPA672T	50V, 0,1A, <20Ohm(10mA)	-
31706	μPA673T	40V, 0,2A, 500MHz, 12/25ns	-
31707	μPA674T	0,05A	-
31708	AEQ	2SC3839K-Q	2SC3839K
31709	AEQ	2SB1424-Q	2SB1424
31710	AER	KTC3883-R	KTC 3883
31711	AER	2SB1424-R	2SB1424
31712	AEY	2SA1362-Y	2SA1362
31713	AF	3SK270	3SK270
31714	AF	3SK220	3SK220
31715	AF	P4 SMA-7.5	P4 SMA-7.5
31716	AF	2SA1365-F	2SA1365
31717	AF	2SA1363-F	2SA1363
31718	AF	2SA1575	2SA1575
31719	AF	BCX 52-6	BCX 52
31720	AF(s)	BCW 60FF	BCW 60FF
31721	AF101	10MHz	AF 121, AF 127, AF 200
31722	AF102	180MHz	AF 106, AF 306
31723	AF105	22MHz	AF 121, AF 126, AF 200
31724	AF106	220MHz	AF 121, AF 306



31725	AF107	330MHz	AF 109R
31726	AF108	330MHz	AF 109R
31727	AF109(R)	280MHz	AF 139, AF 239(S)
31728	AF110		AF 121, AF 126, AF 200
31729	AF111	50MHz	AF 127, AF 200
31730	AF112	60MHz	AF 126, AF 200
31731	AF113	80MHz	AF 125, AF 200
31732	AF114	75MHz	AF 124, AF 200
31733	AF115	75MHz	AF 125, AF 200
31734	AF116	75MHz	AF 126, AF 200
31735	AF117	75MHz	AF 127, AF 200
31736	AF118	70V, 175MHz	-
31737	AF121	270MHz	AF 200, AF 201
31738	AF121S	32V, 270MHz	AF 201, AF 202(S,L)
31739	AF122	275MHz	AF 106, AF 109R, AF 306
31740	AF124	75MHz	AF 200, AF 139, AF 239(S)
31741	AF125	75MHz	AF 200, AF 139, AF 239(S)
31742	AF126	75MHz	AF 200, AF 139, AF 239(S)
31743	AF127	75MHz	AF 200, AF 139, AF 239(S)
31744	AF128	6MHz	AF 127, AF 200
31745	AF129	150MHz	AF 121, AF 124, AF 200
31746	AF130	150MHz	AF 124, AF 200
31747	AF131	100MHz	AF 125, AF 200
31748	AF132	90MHz	AF 126, AF 200
31749	AF133	100MHz	AF 127, AF 200
31750	AF134	55MHz	AF 124, AF 200
31751	AF135	50MHz	AF 125, AF 200
31752	AF136	40MHz	AF 126, AF 200
31753	AF137	35MHz	AF 126, AF 200
31754	AF138	40MHz	AF 126, AF 200
31755	AF139	550MHz	AF 239(S)
31756	AF142	150MHz	AF 124, AF 200
31757	AF143	130MHz	AF 125, AF 200
31758	AF144	130MHz	AF 126, AF 200
31759	AF146		AF 125, AF 200
31760	AF147		AF 126, AF 127, AF 200
31761	AF148		AF 126, AF 127, AF 200
31762	AF149		AF 126, AF 200
31763	AF150		AF 126, AF 127, AF 200
31764	AF164	150MHz	AF 124, AF 200
31765	AF165	130MHz	AF 125, AF 200
31766	AF166	130MHz	AF 126, AF 200
31767	AF168		AF 125, AF 200
31768	AF169		AF 126, AF 127, AF 200
31769	AF170	60MHz	AF 126, AF 127, AF 200

31770	AF171		AF 126, AF 200
31771	AF172	60MHz	AF 127, AF 200
31772	AF178	180MHz	AF 106, AF 306
31773	AF179	270MHz	AF 109R
31774	AF180	250MHz	AF 106, AF 109R, AF 306
31775	AF181	170MHz	AF 121, AF 200
31776	AF182	>120MHz	AF 121, AF 200, AF 201
31777	AF185	80MHz	AF 106, AF 121, AF 200, AF 201, AF 306
31778	AF186		AF 139, AF 239(S)
31779	AF187	18V, 0,1A, 7MHz	AC 125, AC 151, AF 127, AF 200
31780	AF188	18V, 0,1A, 13MHz	AC 126, AC 151, AF 127, AF 200
31781	AF189	18V, 0,1A, 7MHz	AC 125, AC 151, AF 127, AF 200
31782	AF190	18V, 0,1A, 13MHz	AC 126, AC 151, AF 127, AF 200
31783	AF192	10V, 0,1A	-
31784	AF193	40MHz	AF 126, AF 200
31785	AF194	110MHz	AF 124, AF 200
31786	AF195	85MHz	AF 125, AF 200
31787	AF196	80MHz	AF 126, AF 200
31788	AF197	>60MHz	AF 127, AF 200
31789	AF198	>60MHz	AF 127, AF 200
31790	AF200(U)		AF 121
31791	AF201(U)		AF 121
31792	AF202(L,S)		AF 121(S)
31793	AF239(S)	700MHz	AF 279, AF 280, AF 379
31794	AF240(S)	500MHz	AF 239(S)
31795	AF250		AF 239(S)
31796	AF251	750MHz	AF 239(S)
31797	AF252	650MHz	AF 239(S), AF 240
31798	AF253	550MHz	AF 109R
31799	AF254		AF 239(S), AF 240
31800	AF256	>170MHz	AF 106, AF 306
31801	AF257	>170MHz	AF 109R
31802	AF260	3MHz	AF 126, AF 200
31803	AF261	3MHz	AF 126, AF 127, AF 200
31804	AF263	550MHz	AF 109R
31805	AF264	>170MHz	AF 106, AF 109R, AF 306
31806	AF265	18V, 0,1A, 6MHz	AC 125, AC 151
31807	AF266	18V, 0,1A, 8MHz	AC 126, AC 151
31808	AF267	780MHz	AF 279, AF 280, AF 379
31809	AF268		AF 279, AF 280, AF 379
31810	AF269	550MHz	AF 279, AF 280, AF 379
31811	AF271	30MHz	AF 125, AF 126, AF 200, AF 201
31812	AF272	40MHz	AF 125, AF 126, AF 200, AF 201
31813	AF273	60MHz	AF 125, AF 126, AF 200, AF 201
31814	AF275	35MHz	AF 125, AF 126, AF 200, AF 201

31815	AF279(S)	780MHz	AF 379
31816	AF280(III..VIII)	40MHz	AF 125, AF 126, AF 200, AF 201
31817	AF280(S)	550MHz	AF 279(S), AF 379
31818	AF282(V..VIII)	80MHz	AF 125, AF 126, AF 200, AF 201
31819	AF284(IV..VIII)	80MHz	AF 125, AF 126, AF 200, AF 201
31820	AF289	950MHz	AF 279, AF 379
31821	AF290	800MHz	AF 279, AF 280, AF 379
31822	AF367	800MHz	AF 279, AF 379
31823	AF369	550MHz	AF 279, AF 280, AF 379
31824	AF379	1250MHz	-
31825	AF439	800MHz	AF 279, AF 280, AF 379
31826	AFP	2SD1781K-P	2SD1781K
31827	AFQ	2SD1781K-Q	2SD1781K
31828	AFR	2SD1781K-R	2SD1781K
31829	AFY10	30V, 70mA, 350MHz	AFY 18, AFY 19
31830	AFY11	AFY 10, 300MHz	AFY 18, AFY 19
31831	AFY12	230MHz	AF 106, AF 109R, AF 306
31832	AFY13	50MHz	AF 125, AF 200, AF 201
31833	AFY14	60MHz	AFY 18, AFY 19
31834	AFY15	16MHz	AFY 18, AFY 19
31835	AFY16	550MHz	AF 139, AF 239(S)
31836	AFY17	>250MHz	AF 139, AF 239(S)
31837	AFY18	30V, 100mA, 600MHz	-
31838	AFY19	32V, 250mA, 350MHz	-
31839	AFY20	20V, 0,1A, >2,5MHz	AFY 18, AFY 19
31840	AFY21	AFY 20, >5MHz	AFY 18, AFY 19
31841	AFY22	AFY 20, >5MHz	AFY 18, AFY 19
31842	AFY23	AFY 20, >10MHz	AFY 18, AFY 19
31843	AFY24	AFY 20, >10MHz	AFY 18, AFY 19
31844	AFY25	1800MHz	-
31845	AFY26	1600MHz	-
31846	AFY29	35MHz	AF 126, AF 200, AF 201
31847	AFY30	30V, 0,1A, >200MHz	AFY 18, AFY 19
31848	AFY31	30V, 0,1A, >200MHz	AFY 18, AFY 19
31849	AFY32	30V, 0,1A, >200MHz	AFY 18, AFY 19
31850	AFY33	20V, 70mA, >200MHz	AFY 18, AFY 19
31851	AFY35	30V, 50mA, >300MHz	AFY 18, AFY 19
31852	AFY36	30V, 50mA, >300MHz	AFY 18, AFY 19
31853	AFY37	32V, 20mA, 600MHz	AF 239(S), AFY 40
31854	AFY38	>190MHz	AF 106, AF 109R, AF 306
31855	AFY40	32V, 20mA, 700MHz	AF 239(S), AFY 37
31856	AFY40R	AFY 40, 20V, 10mA, 600MHz	AF 239(S), AFY 37
31857	AFY41	650MHz	AF 239(S), AFY 37, AFY 40
31858	AFY42(R)	700MHz	AF 239(S), AFY 37, AFY 40
31859	AFY60	4,5MHz	AF 126, AF 127, AF 200, AF 201

31860	AFY61	10MHz	AF 126, AF 127, AF 200, AF 201
31861	AFY66	18V, 0,1A, 8MHz	AFY 18, AFY 19
31862	AFY71	18V, 30MHz	AF 126, AF 127, AF 200, AF 201
31863	AFY75	18V, 35MHz	AF 126, AF 127, AF 200, AF 201
31864	AFY77	18V, 35MHz	AF 126, AF 127, AF 200, AF 201
31865	AFZ10	40V, 35MHz	AFY 18, AFY 19
31866	AFZ11	140MHz	AF 106, AF 109R, AF 306
31867	AFZ12	AFZ 11, 180MHz	AF 106, AF 109R, AF 306
31868	AG	BCP 52-10	BCP 52
31869	AG	P4 SMA-7.5A	P4 SMA-7.5A
31870	AG	2SA1365-G	2SA1365
31871	AG	2SA1729	2SA1729
31872	AG	2SA1363-G	2SA1363
31873	AG	BCX 52-10	BCX 52
31874	AG(p,s)	BCX 70G	BCX 70G
31875	AG01	400V, 0,7A, <100ns	BYV 26B...E, BYV 36B...D, BYX 92/400
31876	AG01A	600V, 0,5A, <100ns	BYV 26C...E, BYV 36C...D
31877	AG01Y	70V, 1A, <100ns	BYV 26B...E, BYV 36A...D, BYX 92/100
31878	AG01Z	200V, 0,7A, <100ns	BYV 26B...E, BYV 36A...D, BYX 92/200
31879	AGP	2SA1797-P	2SA1797
31880	AGQ	2SA1797-Q	2SA1797
31881	AH	BCP 53	BCP 53
31882	AH	XN 1101	XN 1101
31883	AH	XP 1101	XP 1101
31884	AH	P4 SMA-8.2	P4 SMA-8.2
31885	AH	1SS345	1SS345
31886	AH	2SA1730	2SA1730
31887	AH	BCX 53	BCX 53
31888	AH	2SB1000-AH	2SB1000
31889	AH(p,s)	BCX 70H	BCX 70H
31890	AHN	2SA1759-N	2SA1759
31891	AHP	2SB1197K-P	2SB1197K
31892	AHP	2SA1759-P	2SA1759
31893	AHQ	2SB1197K-Q	2SB1197K
31894	AHQ	2SA1759-Q	2SA1759
31895	AHR	2SB1197K-R	2SB1197K
31896	AI	XN 1201	XN 1201
31897	AI	XP 1201	XP 1201
31898	AI	3SK171	3SK171
31899	AIZ	KSC 3125	KSC 3125
31900	AJ	2SB1000-AJ	2SB1000
31901	AJ	BCX 53-6	BCX 53
31902	AJ	2SA1724	2SA1724
31903	AJ(p,s)	BCX 70J	BCX 70J
31904	AJ2	2SK67-AJ2	2SK67

31905	AJ3	2SK67-AJ3	2SK67
31906	AJ4	2SK67-AJ4	2SK67
31907	AJ5	2SK67-AJ5	2SK67
31908	AJ5	2SK443-AJ5	2SK443
31909	AJ6	2SK67-AJ6	2SK67
31910	AJ6	2SK443-AJ6	2SK443
31911	AJ7	2SK67-AJ7	2SK67
31912	AJ7	2SK443-AJ7	2SK443
31913	AJP	2SD1782K-P	2SD1782K
31914	AJQ	2SD1782K-Q	2SD1782K
31915	AJR	2SD1782K-R	2SD1782K
31916	AK	BCP 53-10	BCP 53
31917	AK	P4 SMA-8.2A	P4 SMA-8.2A
31918	AK	2SA1740	2SA1740
31919	AK	BCX 53-10	BCX 53
31920	AK	2SB1000A-AK	2SB1000A
31921	AK(p,s)	BCX 70K	BCX 70K
31922	AK03	30V, 1A, 100ns	BYV 10-30, SB 130...160, 1N5818...19
31923	AK04	40V, 1A, 100ns	BYS 21-45, BYV 10-40, SB140...160, 1N5819
31924	AK06	60V, 0,7A, 100ns	BYS 21-90, BYV 10-60, SB 160, MBR 160
31925	AK06	60V, 0,7A, 100ns	BYS 21-90, BYV 10-60, SB 160, MBR 160
31926	AK09	90V, 0,7A, 100ns	BYS 21-90, HRP 32
31927	AKP	2SB1198K-P	2SB1198K
31928	AKQ	2SA1806-Q	2SA1806
31929	AKQ	2SB1198K-Q	2SB1198K
31930	AKQ	2SA1738-Q	2SA1738
31931	AKR	2SA1806-R	2SA1806
31932	AKR	2SA1738-R	2SA1738
31933	AKR	2SB1198K-R	2SB1198K
31934	AL	BCP 53-16	BCP 53
31935	AL	P4 SMA-9.1	P4 SMA-9.1
31936	AL	BCX 70L	BCX 70L
31937	AL	2SA1338	2SA1338
31938	AL	BCX 53-16	BCX 53
31939	AL	2SA1766	2SA1766
31940	AL	2SB1000A-AL	2SB1000A
31941	AL01Z	200V, 1A, 50ns	BYD 73D...G, EGP 10D, FE 1D
31942	AL100	130V, 10A, 30W	AUY 38, 2N2528
31943	AL101	AL 100, 100V	AUY 38, 2N2527, 2N2290, 2N2293
31944	AL102	130V, 6A, 30W	AL 100, AUY 38, 2N2528
31945	AL103	AL 102, 100V	AL 100...102, AUY 38, 2N2527, 2N2290/93
31946	AL112	130V, 6A, 10W	-
31947	AL113	AL 112, 100V	-
31948	ALG	KTC3875-G	KTC 3875
31949	ALL	KTC3875-L	KTC 3875

31950	ALM	2SC3802K-M	2SC3802K
31951	ALN	2SC3802K-N	2SC3802K
31952	ALO	KTC3875-O	KTC 3875
31953	ALP	2SC3802K-P	2SC3802K
31954	ALP	2SA1900-P	2SA1900
31955	ALQ	2SA1748-Q	2SA1748
31956	ALQ	2SA1791-Q	2SA1791
31957	ALQ	2SA1747-Q	2SA1747
31958	ALQ	2SC3802K-Q	2SC3802K
31959	ALQ	2SA1900-Q	2SA1900
31960	ALR	2SA1748-R	2SA1748
31961	ALR	2SA1791-R	2SA1791
31962	ALR	2SA1747-R	2SA1747
31963	ALR	2SA1900-R	2SA1900
31964	ALs	BFP 405	BFP 405
31965	ALY	KTC3875-Y	KTC 3875
31966	AM	BCP 52-16	BCP 52
31967	AM	P4 SMA-9.1A	P4 SMA-9.1A
31968	AM	BCX 52-16	BCX 52
31969	AM(p,s)	BSS 64	BSS 64
31970	AM01(A,B,Z)	200..800V, 1A	BY 126...127, BY 133...134, 1N4003...07
31971	AMN	2SC4018K-N	2SC4018K
31972	AMP	2SC4018K-P	2SC4018K
31973	AMQ	2SC4562-Q	2SC4562
31974	AMQ	2SC4561-Q	2SC4561
31975	AMQ	2SC4656-Q	2SC4656
31976	AMR	2SC4562-R	2SC4562
31977	AMR	2SC4656-R	2SC4656
31978	AMR	2SC4561-R	2SC4561
31979	AMs	BFP 420	BFP 420
31980	AN	2SC2413-AN	2SC2413
31981	AN	XN 1509	XN 1509
31982	AN	P4 SMA-10	P4 SMA-10
31983	AN	2SC4098-N	2SC4098
31984	AN	2SC2532	2SC2532
31985	AN	2SC2413K-N	2SC1413K
31986	AN(s)	BCW 60FN	BCW 60FN
31987	AN1A3Q	0,25W	DTA 113ZS, UN 4119
31988	AN1A4M	AN 1A3Q, RbRbe10kOhm	DTA 114ES, RN 2002, UN 4111, 2SA1348
31989	AN1A4P	AN 1A3Q, Rb10k, Rbe47kOhm	DTA 114YS, RN 2007, UN 4114, 2SA1564
31990	AN1A4Z	AN 1A3Q, Rb10k, Rbe-	DTA 114TS, RN 2011, UN 4115, 2SA1497
31991	AN1F4M	AN 1A3Q, Rb22k, Rbe22kOhm	DTA 124ES, RN 2003, UN 4112, 2SA1346
31992	AN1F4N	AN 1A3Q, Rb22k, Rbe47kOhm	DTA 124XS, KSR 2007, RN 2008
31993	AN1F4Z	AN 1A3Q, Rb22k, Rbe-	DTA 124TS, KSR 2011, UN 4117, 2SA1590
31994	AN1L3M	AN 1A3Q, Rb4,7k, Rbe4,7kOhm	DTA 143ES, RN 2001, UN 411L, 2SA1656



31995	AN1L3N	AN 1A3Q, Rb4,7k, Rbe10kOhm	DTA 143XS, KSR 2005, UN 411F, 2SA1654
31996	AN1L3Z	AN 1A3Q, Rb4,7k, Rbe-	DTA 143TS, RN 2010, UN 4116, 2SA1511
31997	AN1L4L	AN 1A3Q, Rb47k, Rbe22kOhm	DTA 144WS, RN 2009, UN 411E, 2SA1347
31998	AN1L4M	AN 1A3Q, Rb47k, Rbe47kOhm	DTA 144ES, RN 2004, UN 4113, 2SA1345
31999	AN1L4Z	AN 1A3Q, Rb47k, Rbe-	DTA 144TS, KSR 2012, UN 4110, 2SA1509
32000	ANi		AC 151
32001	ANk		AC 151
32002	ANm		AC 127
32003	ANM	2SC4061K-M	2SC4061K
32004	ANN	2SC4061K-N	2SC4061K
32005	ANP	2SC4061K-P	2SC4061K
32006	AO	XN 4509	XN 4509
32007	AO	2SC4210-O	2SC4210
32008	AO	BCW 60RA	BCW 60RA
32009	AO	KTC4372-O	KTC 4372
32010	AO	2SC2880-O	2SC2880
32011	AP	2SC2413-AP	2SC2413
32012	AP	P4 SMA-10A	P4 SMA-10A
32013	AP	2SC2413K-P	2SC2413K
32014	AP	BCW 60RB	BCW 60RB
32015	AP	2SC4098-P	2SC4098
32016	AP01C	1000V, 0,2A, 200ns	BA 159, BYT 11/1000, BYT 52M, BYV 26E
32017	AP1A3M	0,75W	-
32018	AP1A4A	AP 1A3M, Rb-, Rbe10kOhm	-
32019	AP1A4M	AP 1A3M, Rb10k, Rbe10kOhm	-
32020	AP1F3P	AP 1A3M, Rb2,2k, Rbe10kOhm	-
32021	AP1J3P	AP 1A3M, Rb3,3k, Rbe10kOhm	-
32022	AP1L2Q	Rbe4,7kOhm	-
32023	AP1L3N	AP 1A3M, Rb4,7k, Rbe10kOhm	-
32024	AP647	MR 31	MR 31
32025	APD203	BA 100	BA 100
32026	AQ	2SC2413-AQ	2SC2413
32027	AQ	P4 SMA-11	P4 SMA-11
32028	AQ	2SB1218-Q	2SB1218
32029	AQ	2SC4098-Q	2SC4098
32030	AQ	2SB1462-Q	2SB1462
32031	AQ	2SC2413K-Q	2SC2413K
32032	AQ	2SB709-Q	2SB709
32033	AQ	2PB709Q	2PB709
32034	AQ	2SB766-Q	2SB766
32035	AQ1A3M	RbRbe1kOhm, 20V, 2A, 0,75W	-
32036	AQ1A4A	AQ 1A3M, Rb-, Rbe10kOhm	-
32037	AQ1F2Q	Rbe2,2kOhm	-
32038	AQ1F3M	Rbe2,2kOhm	-
32039	AQ1F3P	AQ 1A3M, Rb2,2k, Rbe10kOhm	-

32040	AQ1L2N	AQ 1A3M, Rb0,47k, Rbe1kOhm	-
32041	AQ1L2Q	Rbe4,7kOhm	-
32042	AQ2A4A	140MHz	-
32043	AQO	KTC3880-O	KTC 3880
32044	AQP	2SB1051K-P	2SB1051K
32045	AQQ	2SB1051K-Q	2SB1051K
32046	AQR	2SB1051K-R	2SB1051K
32047	AQR	KTC3880-R	KTC 3880
32048	AQY	KTC3880-Y	KTC 3880
32049	AR	XN 121F	XN 121F
32050	AR	P4 SMA-11A	P4 SMA-11A
32051	AR	BCW 60RC	BCW 60RC
32052	AR	2PB709R	2PB709
32053	AR	2SB1218-R	2SB1218
32054	AR	2SB1462-R	2SB1462
32055	AR	2SB709-R	2SB709
32056	AR	2SB766-R	2SB766
32057	AR	2SC3338	2SC3338
32058	AR1	BSP 40	BSP 40
32059	AR1	BSR 40	BSR 40
32060	AR1A3M	RbRbe1kOhm, 60V, 1A, 0,75W	-
32061	AR1A4A	AR 1A3M, Rb-, Rbe10kOhm	-
32062	AR1A4M	Rbe10kOhm	-
32063	AR1F2Q	Rbe2,2kOhm	-
32064	AR1F3P	AR 1A3M, Rb2,2k, Rbe10kOhm	-
32065	AR1L2Q	Rbe4,7kOhm	-
32066	AR1L3N	AR 1A3M, Rb4,7k, Rbe10kOhm	-
32067	AR2	BSP 41	BSP 41
32068	AR2	BSR 41	BSR 41
32069	AR3	BSP 42	BSP 42
32070	AR3	BSR 42	BSR 42
32071	AR4	BSP 43	BSP 43
32072	AR4	BSR 43	BSR 43
32073	AS	P4 SMA-12	P4 SMA-12
32074	AS	2SB1462-S	2SB1462
32075	AS	2SB1218-S	2SB1218
32076	AS	2PB709S	2PB709
32077	AS	2SB709-S	2SB709
32078	AS	BAT 18-05	BAT 18-05
32079	AS	BCW 60RD	BCW 60RD
32080	AS	2SA1655	2SA1665
32081	AS	2SB766-S	2SB766
32082	AS	2SC3380	2SC3380
32083	AS01	200..600V, 0,6A, 1,5µs	BY 126...127, BY 133...134, 1N4003...07
32084	AS1	BSP 50	BSP 50

32085	AS1	BST 50	BST 50
32086	AS2	BSP 51	BSP 51
32087	AS2	BST 51	BST 51
32088	AS3	BSP 52	BSP 52
32089	AS3	BST 52	BST 52
32090	ASG	KTA1504-G	KTA 1504
32091	ASO	KTA1504-O	KTA 1504
32092	ASY	KTA1504-Y	KTA 1504
32093	ASY10	32V, 0,3A, B30..50	AC 125, AC 126, AC 151
32094	ASY11	ASY 10, B40..70	AC 125, AC 126, AC 151
32095	ASY12	32V, 0,6A, 0,135W	AC 128, AC 153, ASY 48, ASY 76
32096	ASY13	60V, 0,6A, 0,135W	ASY 48, ASY 76
32097	ASY14	80V, 0,25A, 0,13W	-
32098	ASY23	80V, 0,3A, 0,85W	-
32099	ASY24	50V, 0,25A, 0,1W	ASY 48, ASY 77
32100	ASY24B	ASY 24, 35V	AC 125, AC 126, AC 151, ASY 48, ASY 76
32101	ASY25	32V, 0,3A, 0,15W	AC 128, AC 153
32102	ASY26	30V, 0,2A, 0,15W	ASY 48, ASY 76
32103	ASY27	25V, 0,2A, 0,15W	ASY 48, ASY 76
32104	ASY28	30V, 0,2A, 0,15W	ASY 73...75
32105	ASY29	25V, 0,2A, 0,15W	ASY 73...75
32106	ASY30	50V, 0,25A, 0,2W	ASY 48, ASY 77
32107	ASY31	25V, 0,2A, 0,125W, B30..80	ASY 26, ASY 27, ASY 48, ASY 76
32108	ASY32	ASY 31, B50..150	ASY 26, ASY 27, ASY 48, ASY 76
32109	ASY33	32V, 0,3A, 0,15W	AC 125, AC 126, AC 151, ASY 48, ASY 76
32110	ASY37	64V, 0,3A, 0,15W	ASY 48, ASY 77
32111	ASY48	64V, 0,3A, 0,22W	ASY 77
32112	ASY49	100V, 0,25A, 0,09W	-
32113	ASY50	20V, 0,5A, 0,06W	AC 128, AC 153, AC 188
32114	ASY51	60V, 0,25A, 0,09W	ASY 48, ASY 77
32115	ASY52	60V, 0,25A, 0,09W	ASY 48, ASY 77
32116	ASY53	20V, 0,25A, 0,06W	AC 127, AC 176, AC 187, ASY 29, ASY 73
32117	ASY54	30V, 0,5A, 0,2W	AC 128, AC 153
32118	ASY54N	ASY 54, 0,15W	AC 128, AC 153
32119	ASY55	20V, 0,5A, 0,2W	AC 128, AC 153, AC 188
32120	ASY55N	ASY 55, 0,15W	AC 128, AC 153, AC 188
32121	ASY56	20V, 0,2A, 0,2W, B26..60	AC 125, AC 126, AC 151
32122	ASY56N	ASY 56, 0,15W	AC 125, AC 126, AC 151
32123	ASY57	ASY 56, B30..80	AC 125, AC 126, AC 151
32124	ASY57N	ASY 57, 0,15W	AC 125, AC 126, AC 151
32125	ASY58	ASY 56, B40..100	AC 125, AC 126, AC 151
32126	ASY58N	ASY 58, 0,15W	AC 125, AC 126, AC 151
32127	ASY59	ASY 56, B60..150	AC 125, AC 126, AC 151
32128	ASY59N	ASY 59, 0,15W	AC 125, AC 126, AC 151
32129	ASY60	20V, 0,25A, 0,2W	-

32130	ASY61	30V, 0,25A, 0,1W	AC 127, AC 176, ASY 28, ASY 73...75
32131	ASY62	20V, 0,25A, 0,1W	AC 127, AC 176, AC 187, ASY 29, ASY 73
32132	ASY63	26V, 0,2W	AC 125, AC 126, AC 151
32133	ASY63N	ASY 63, 0,075W	AC 125, AC 126, AC 151
32134	ASY64	30V, 0,2W	AC 125, AC 126, AC 151
32135	ASY66	30V, 0,2W	AC 125, AC 126, AC 151
32136	ASY67	50V, 0,05A, 150MHz	AFY 18, AFY 19
32137	ASY68	12V, 0,1A, 0,075W	ASY 26...27
32138	ASY69	20V, 0,35A, 0,075W	ASY 26...27
32139	ASY70	20V, 0,35A, 0,075W	AC 128, AC 153, ASY 26, ASY 48, ASY 76
32140	ASY71	100V, 0,1A, 0,15W	-
32141	ASY72	20V, 0,25A, 0,1W	AC 127, AC 176, AC 187, ASY 29, ASY 75
32142	ASY73	30V, 0,4A, 0,085W, >4MHz	-
32143	ASY74	ASY 73, >6MHz	-
32144	ASY75	ASY 73, >10MHz	-
32145	ASY76	40V, 0,5A, 0,16W	AC 128, AC 153, ASY 48
32146	ASY77	ASY 76, 60V	ASY 48
32147	ASY78(T)	40V, 0,4A, 0,125W, 40MHz	-
32148	ASY80	40V, 0,5A, 0,16W	AC 128, AC 153, ASY 48, ASY 76
32149	ASY81	60V, 0,5A, 0,15W	ASY 48, ASY 77
32150	ASY82	26V, 0,5A, 0,2W, B30..130	AC 128, AC 153, AC 188
32151	ASY83	ASY 82, B70..320	AC 128, AC 153, AC 188
32152	ASY84	40V, 0,5A, 0,2W, B30..130	AC 128, AC 153
32153	ASY85	ASY 84, B70..320	AC 128, AC 153
32154	ASY86	16V, 0,5A, 0,2W, B25..120	AC 127, AC 176, AC 187
32155	ASY87	ASY 86, B60..295	AC 127, AC 176, AC 187
32156	ASY88	26V, 0,5A, 0,2W, B25..120	AC 127, AC 176, AC 187
32157	ASY89	ASY 88, B60..295	AC 127, AC 176, AC 187
32158	ASY90	40V, 0,25A, 0,185W	AC 125, AC 126, AC 151, ASY 48, ASY 76
32159	ASY91	ASY 90, 25V	AC 125, AC 126, AC 151, ASY 48, ASY 76
32160	ASZ10	50V, 0,25A, 0,15W	ASY 48, ASY 77
32161	ASZ1015	80V, 6A, 22,5W	AUY 37, 2N2527
32162	ASZ1016	60V, 6A, 22,5W	AUY 21, 2N2526
32163	ASZ1017	60V, 6A, 22,5W	AUY 21, 2N2526
32164	ASZ1018	80V, 6A, 22,5W	AUY 37, 2N2527
32165	ASZ11	20V, 0,2A, 0,125W, B>40	AC 125, AC 126, AC 151, ASY 48, ASY 76
32166	ASZ12	ASZ 11, B>60	AC 125, AC 126, AC 151, ASY 48, ASY 76
32167	ASZ15	100V, 8A, 30W	AUY 37, 2N2527
32168	ASZ16	60V, 8A, 30W	AUY 21, 2N2526
32169	ASZ17	60V, 8A, 30W	AUY 21, 2N2526
32170	ASZ18	100V, 8A, 30W	AUY 37, 2N2527
32171	ASZ20	40V, 25mA, 100MHz	AF 202S/L
32172	ASZ21	20V, 30mA, >300MHz, 50/80ns	2N2635, 2N2955...2957
32173	ASZ23	30V, 0,1A, 0,05W	-
32174	ASZ30	50V, 0,25A, 0,03W, 20MHz	ASY 48, ASY 77

32175	AT	P4 SMA-12A	P4 SMA-12A
32176	AT	BCW 60RE	BCW 60RE
32177	AT	BAT 18-06	BAT 18-06
32178	AT	2SC4066	2SC4066
32179	AT	2SD1470	2SD1470
32180	AT1	BSP 19	BSP 19
32181	AT1	BST 39	BST 39
32182	AT2	BSP 20	BSP 20
32183	AT2	BST 40	BST 40
32184	AT200	AU 106	AU 106
32185	AT201	AU 107	AU 107
32186	AT202	100V, 3A, 3W	AUY 34
32187	AT207	60V, 10A, 9W	2N2490...2492, 2N2079...2080, 2N1981
32188	AT208	100V, 10A, 30W	AUY 37, 2N2527
32189	AT209	40V, 0,25A, 0,18W	AC 125, AC 126, AC 151
32190	AT210	30V, 0,25A, 0,18W	AC 125, AC 126, AC 151
32191	AT216	320V, 10A, 5W	AU 106, AU 109, AU 111, AU 112, 2N5325
32192	AT270	ASY 90	ASY 90
32193	AT275	ASY 91	ASY 91
32194	AT450	420V, 10A, 5W	-
32195	AT529	140V, 8A	BUX 59...60, BUW 64A...C, 2SC2334
32196	AT605	BU 126	BU 126
32197	ATN	2SA1812-N	2SA1812
32198	ATP	2SA1812-P	2SA1812
32199	ATQ	2SC4326LK-Q	2SC4326LK
32200	ATQ	2SA1812-Q	2SA1812
32201	ATR	2SC4326LK-R	2SC4326LK
32202	ATS	2SC4326LK-S	2SC4326LK
32203	AU	P4 SMA-13	P4 SMA-13
32204	AU	BCX 70RG	BCX 70RG
32205	AU	BAT 18-04	BAT 18-04
32206	AU	2SB804-AU	2SB804
32207	AU01	200..600V, 0,5A, 400ns	BA 157...159, BY 208/..., BY 407
32208	AU02	200..600V, 0,8A, 400ns	BYD 33J...M, BYT 11/600, BYT 52J...M
32209	AU101	120V, 10A, 10W(Tc75°)	AU 210
32210	AU102	40V, 10A, 10W(Tc75°)	AU 108
32211	AU103	155V, 10A, 10W(Tc60°)	AU 107, AU 110
32212	AU104	185V, 12A, 15W(Tc75°)	AU 107
32213	AU105	130V, 10A, 27,5W	AU 110, AU 210
32214	AU106	320V, 10A, 5W(Tc55°)	AU 109, AU 111, AU 112, 2N5325
32215	AU107	200V, 10A, 30W	AU 113, AU 213, 2N5324
32216	AU108(F)	100V, 10A, 30W	AU 210
32217	AU109	320V, 10A, 15W	AU 106, AU 111, AU 112, 2N5325
32218	AU110	160V, 10A, 30W	AU 107
32219	AU111	320V, 10A, 5W(Tc55°)	AU 106, AU 109, AU 112, 2N5325

32220	AU112	320V, 10A, 5W(Tc55°)	AU 106, AU 109, AU 111, 2N5325
32221	AU113	250V, 10A, 5W(Tc55°)	AU 213, 2N5324
32222	AU206	320V, 10A, 5W(Tc55°)	AU 106, AU 109, AU 111, AU 112, 2N5325
32223	AU210	140V, 10A, 5W(Tc55°)	AU 107, AU 110
32224	AU213	250V, 10A, 5W(Tc55°)	AU 113, 2N5324
32225	AUY10	70V, 0,7A, 6W(Tc50°)	AUY 19, AUY 20
32226	AUY14	65V, 10A, 36,5W	AUY 21, 2N2289, 2N2292
32227	AUY15	65V, 10A, 36,5W	AUY 21, 2N2289, 2N2292
32228	AUY16	80V, 8A, 36,5W	AUY 22, 2N2289, 2N2292
32229	AUY17	80V, 8A, 36,5W	AUY 22, 2N2289, 2N2292
32230	AUY18	64V, 8A, 11W	AUY 35, AUY 36
32231	AUY19	64V, 3A, 30W	AL 102, AUY 20, 2N1531/36, 2N1541/46
32232	AUY20	AUY 19, 80V	AL 102, AUY 28, 2N1531/36, 2N1541/46
32233	AUY21	65V, 10A, 36W	ASZ 16, ASZ 17, 2N2526, 2N2289, 2N2292
32234	AUY22	80V, 8A, 36W	ASZ 15, ASZ 18, 2N2526, 2N2289, 2N2292
32235	AUY24	65V, 3A, 30W	AL 102, AUY 19, 2N1530/35, 2N1540/45
32236	AUY26	80V, 3A, 30W	AL 102, AUY 20, 2N1531/36, 2N1541/46
32237	AUY27	80V, 3A, 30W	AL 102, AUY 20, 2N1531/36, 2N1541/46
32238	AUY28	90V, 6A, 30W	AL 102, ASZ 15, ASZ 18, 2N3616/18
32239	AUY29	50V, 15A, 36W	2N1549...1560
32240	AUY30	100V, 10A, 33W	AUY 37, 2N2527, 2N2290, 2N2293
32241	AUY31	60V, 6A, 33W	AL 102, ASZ 16...17, AUY 21, 2N3612/14
32242	AUY32	80V, 3A, 33W	AL 102, AUY 20, 2N2141/46
32243	AUY33	AUY 33, 60V	AL 102, AUY 19, 2N2139/44
32244	AUY34	100V, 3A, 30W	AL 102, AUY 28, 2N1532/37, 2N1542/47
32245	AUY35	70V, 10A, 15W	AUY 36
32246	AUY36	70V, 10A, 15W	AUY 35
32247	AUY37	100V, 10A, 30W	2N2527, 2N2290, 2N2293
32248	AUY38	130V, 10A, 30W	AL 100, 2N2528
32249	AV	P4 SMA-13A	P4 SMA-13A
32250	AV	2SB804-AV	2SB804
32251	AV03-03...-30	3...30V, +-5%, 10W	BZX 98/..., BZY 93/..., 1N2970...89
32252	AW	P4 SMA-15	P4 SMA-15
32253	AW	BCX 70RH	BCX 70RH
32254	AW	2SB804-AW	2SB804
32255	AW01-06...-33	6...33V, 5%, 1W	BZV 85/..., BZW 22/..., BZX 61/..., ZPY...
32256	AW03-02...-05	1,4...5,4V, 1W	-
32257	AX	XN 2212	XN 2212
32258	AX	P4 SMA-15A	P4 SMA-15A
32259	AX	2SA1739	2SA1739
32260	AX	BCX 70RJ	BCX 70RJ
32261	AXQ	2SA1739-Q	2SA1739
32262	AXR	2SA1739-R	2SA1739
32263	AY	P4 SMA-16	P4 SMA-16
32264	AY	2SC4210-Y	2SC4210



32265	AY	BCX 70RK	BCX 70RK
32266	AY	2SC3392	2SC3392
32267	AY	KTC4372-Y	KTC 4372
32268	AY	2SC2880-Y	2SC2880
32269	AY101	150V, 15A	-
32270	AY102	60/320V, 7A	-
32271	AY106	60/200V, 7A	-
32272	AZ	P4 SMA-16A	P4 SMA-16A
32273	AZ	BCX 70RL	BCX 70RL
32274	AZO	KTA1505-O	KTA 1505
32275	AZY	KTA1505-Y	KTA 1505
32276	B	2SK1616	2SK1616
32277	B	2SK1325	2SK1325
32278	B	MA 2S728	MA 728
32279	B	2SK1068	2SK1068
32280	B	S 5566B	S 5566B
32281	B0	HVC 350B	HVC 350B
32282	B1	HVU 355B	HVU 355B
32283	B1	HVC 355B	HVC 355B
32284	B1	HSM 2692	HSM 2692
32285	B1	2SK1824	2SK1824
32286	B1	D71G.05T1	D71G.05T1
32287	B10	2SK545-B10	2SK545
32288	B10100	MBR 10100	MBR 10100
32289	B1035	MBR 1035	MBR 1035
32290	B1045	MBR 1045	MBR 1045
32291	B1045	MBRF 1045	MBRF 1045
32292	B1060	MBR 1060	MBR 1060
32293	B1070	MBR 1070	MBR 1070
32294	B1080	MBR 1080	MBR 1080
32295	B1085		AU 106, AU 109, AU 111, AU 112, 2N5325
32296	B1090	MBR 1090	MBR 1090
32297	B11	2SK545-B11	2SK545
32298	B110	MBRS 1100	MBRS 1100
32299	B1100	MBR 1100	MBR 1100
32300	B12	2SC3739-B12	2SC3739
32301	B12	2SK545-B12	2SK545
32302	B12	2SC4173-B12	2SC4173
32303	B13	2SC3739-B13	2SC3739
32304	B13	2SC4173-B13	2SC4173
32305	B130	MBRS 130	MBRS 130
32306	B14	2SC3739-B14	2SC3739
32307	B14	2SC4173-B14	2SC4173
32308	B140	MBRS 140	MBRS 140
32309	B15	NTM 2222A	NTM 2222A

32310	B150	MBR 150	MBR 150
32311	B1535	MBR 1535CT	MBR 1535CT
32312	B1545	MBR 1545CT	MBR 1545CT
32313	B1545	MBRF 1545CT	MBRF 1545CT
32314	B1545T	MBRB 1545CT	MBRB 1545CT
32315	B160	MBR 160	MBR 160
32316	B1635	MBR 1635	MBR 1635
32317	B1645	MBR 1645	MBR 1645
32318	B170	MBR 170	MBR 170
32319	B180	MBR 180	MBR 180
32320	B190	MBR 190	MBR 190
32321	B1O	KSC 2715-O	KSC 2715
32322	B1R	KSC 2715-R	KSC 2715
32323	B1Y	KSC 2715-Y	KSC 2715
32324	B2	HVC 358B	HVC 358B
32325	B2	MBR 0520	MBR 0520
32326	B2	2SC1621-B2	2SC1621
32327	B2	2SC4175-B2	2SC4175
32328	B2(p)	BSV 52	BSV 52
32329	B20100	MBRF20100CT	MBRF 20100CT
32330	B20100	MBR 20100CT	MBR 20100CT
32331	B20100T	MBRB20100CT	MBRB 20100CT
32332	B2015	MBR 2015CTL	MBR 2015CTL
32333	B20200	MBR 20200CT	MBR 20200CT
32334	B20200T	MBRB20200CT	MBRB 20200CT
32335	B2060T	MBRB 2060CT	MBRB 2060CT
32336	B22	2SC3734-B22	2SC3734
32337	B23	2SC3734-B23	2SC3734
32338	B24	2SC3734-B24	2SC3734
32339	B25	NTM 3904	NTM 3904
32340	B2515L	MBRB 2515L	MBRB 2515L
32341	B2535L	MBRB2535CTL	MBRB 2535CTL
32342	B2545T	MBRB 2545CT	MBRB 2545CT
32343	B26	BF 570	BF 570
32344	B3	MBR 0530	MBR 0530
32345	B3	HVC 369B	HVC 369B
32346	B3	1SS361	1SS361
32347	B3	HSM 2694	HSM 2694
32348	B3	1SS301	1SS301
32349	B3	2SC4175-B3	2SC4175
32350	B3	KDS 184	KDS 184
32351	B3	2SC1621-B3	2SC1621
32352	B3	1SS184	1SS184
32353	B3030	MBRB 3030CT	MBRB 3030CT
32354	B3035	MBR 3035PT	MBR 3035PT

32355	B3035	MBR 3035WT	MBR 3035WT
32356	B3045	MBR 3045PT	MBR 3045PT
32357	B3045	MBR 3045WT	MBR 3045WT
32358	B320	MBRD 320	MBRD 320
32359	B33	2SC4176-B33	2SC4176
32360	B33	2SC3735-B33	2SC3735
32361	B330	MBRD 330	MBRD 330
32362	B34	2SC4176-B34	2SC4176
32363	B34	2SC3735-B34	2SC3735
32364	B340	MBRD 340	MBRD 340
32365	B35	2SC4176-B35	2SC4176
32366	B35	2SC3735-B35	2SC3735
32367	B350	MBRD 350	MBRD 350
32368	B360	MBRD 360	MBRD 360
32369	B3T	1PS184	1PS184
32370	B4	MBR 0540	MBR 0540
32371	B4	BSV 52R	BSV 52R
32372	B4	2SC4175-B4	2SC4175
32373	B4	HSM 2693A	HSM 2693A
32374	B4	2SC1621-B4	2SC1621
32375	B4015L	MBR 4015LWT	MBR 4015LWT
32376	B4030	MBRB 4030	MBRB 4030
32377	B4045	MBR 4045PT	MBR 4045PT
32378	B4045	MBR 4045WT	MBR 4045WT
32379	B5	HVC 372B	HVC 372B
32380	B5(p)	BSR 12	BSR 12
32381	B5025L	MBR 5025L	MBR 5025L
32382	B51	2SB736A-B51	2SB736A
32383	B52	2SB736A-B52	2SB736A
32384	B53	2SB736A-B53	2SB736A
32385	B54	2SB736A-B54	2SB736A
32386	B55	2SB736A-B55	2SB736A
32387	B6	2SB815-6	2SB815
32388	B6045	MBR 6045PT	MBR 6045PT
32389	B6045	MBR 6045WT	MBR 6045WT
32390	B620T	MBRD 620CT	MBRD 620CT
32391	B630T	MBRD 630CT	MBRD 630CT
32392	B640T	MBRD 640CT	MBRD 640CT
32393	B650T	MBRD 650CT	MBRD 650CT
32394	B660T	MBRD 660CT	MBRD 660CT
32395	B7	2SB815-7	2SB815
32396	B8	BSR 12R	BSR 12R
32397	B81	BSR 12R	BSR 12R
32398	B835L	MBRD 835L	MBRD 835L
32399	B9	1SS311	1SS311

32400	BA	BCP 54	BCP 54
32401	BA	μPA500T	æPA500T
32402	BA	μPA674T	æPA674T
32403	BA	μPA570T	æPA570T
32404	BA	XN 2216	XN 2216
32405	BA	1SS154	1SS154
32406	BA	2SB1118	2SB1118
32407	BA	2SD1367-BA	2SD1367
32408	BA	2SB1132	2SB1132
32409	BA	BCX 54	BCX 54
32410	BA(p,s)	BCW 61A	BCW 61A
32411	BA100	60V, 90mA	BA 128, 1N4148, 1N5194...5196
32412	BA101(A,B,C)		BA 125, BB 119, 1SV114, 1SV125
32413	BA102/A..D		BA 125, BB 119, 1SV114, 1SV125
32414	BA103	6V, 0,2A	BA 127, BA 187...188, BA 215, 1N4148
32415	BA104	100V, 0,19A	BA 188...190, BAY 73, BAY 19...21
32416	BA105	300V, 0,15A	BA 147/300, BAY 21, BAY 46, BAY 88
32417	BA108	50V, 0,19A	BA 127, BA 188...190, BA 215, 1N4148
32418	BA109		BA 125, BB 119, 1SV114, 1SV125
32419	BA110		BA 111, BA 124, 1S2790, 1SV50
32420	BA110G		BB 109, BB 143, MV 109, 1SV50
32421	BA111		BA 125, BB 119, 1SV114, 1SV125
32422	BA112		BA 111, BA 124
32423	BA114	0,58..0,8V/3mA	BA 216, BA 314, BA 315, 1N4148
32424	BA115	150V, 2mA	BA 195, BAY 80, BAV 20, 1N3070
32425	BA117	0,2A, 0,72V/1mA	BA 220, BZV49/C0V8, 1N4148
32426	BA119		BA 111, BA 124, 1S2790, 1SV50
32427	BA120		BA 125, BB 119, 1SV114, 1SV 125
32428	BA121		BB 117, BB 417, 1SV89
32429	BA122	100V, 90mA	BA 147/100, 1N5195, 1N5606
32430	BA123	1600..2400pF/2V	-
32431	BA124/50..65		BA 111, 1S2790, 1SV50
32432	BA125/35..50		BB 119, 1SV114, 1SV125, 1SV 145...146
32433	BA127(D)	60V, 0,2A	BA 188...190, BA 215, BAY 45, 1N4148
32434	BA128	75V, 0,11A	BA 127, BA 147/50, BA 187...190, 1N4148
32435	BA129	200V, 0,225A	BAY 20...21, BAY 46, BAY 88, BAW 52
32436	BA130	30V, 75mA	BA 128, BA 222, 1N4148, 1N5194
32437	BA131	600V, 0,3A	BA 199/550, BA 158...159, BY 204/8...10
32438	BA132	BA 131, 800V	BA 159, BY 204/8...10
32439	BA133(F)	BA 131, 1000V	BA 159, BY 204/10
32440	BA136(A)		BA 243, BA 283, BA 483...484
32441	BA137	150V, 0,1A, <50ns	BA 196...198, BAV 20...21, BAY 80, 1N3070
32442	BA138		BB 109, BB 143, MV 109, 1SV50
32443	BA139		BB 105A/B, BB 205A/B, BB 405A/B
32444	BA140		BB 109, BB 143, MV 109, 1SV50

32445	BA141		BB 105A/B, BB 205A/B, BB 405A/B
32446	BA142		BB 109, BB 143, MV 109, 1SV50
32447	BA143U		BA 244, BA 282, BA 284, BA 482
32448	BA143V		BA 243, BA 283, BA 483...484
32449	BA144	50V, 50mA	-
32450	BA145	350V, 0,3A	BA 157...159, BA 245, BA 248, BY 206...207
32451	BA147/...	25..300V, 0,15A	BAY 17...21, BAY 86...88, BAY 44...46
32452	BA148	350V, 0,3A	BA 157...159, BA 245, BA 248, BY 206...207
32453	BA149/...		BB 105A/B, BB 205A/B, BB 405A/B
32454	BA150/...		BB 110, BB 203, 1SV68, 1SV84
32455	BA151	0,6V/0,05mA	BA 216, BA 314, BA 315, 1N4148
32456	BA152(A,P,PR)		BA 243, BA 283, BA 483...484
32457	BA153	40V, 25mA	-
32458	BA154	50V, 30mA	BA 128, BA 222, BA 147/50, 1N4148
32459	BA155	150V, 0,1A	BA 147/150, BA 189...190, 1N5606...07
32460	BA156	30mA, <0,7V/3mA	BA 216, BA 314, BA 315, 1N4148
32461	BA157(GP)		BY 204/4, BY 206, BY 406, BY 208/600
32462	BA158(GP)	BA 157, 600V	BY 204/8, BY 207, BY 407, BY 208/600
32463	BA159(GP)	BA 157, 1000V	BY 204/10, BY 208/1000, BY 268
32464	BA159SGP	BA 157, 1300V	BY 231/1400, BY 268...269
32465	BA159XGP	BA 157, 1500V	BY 231/1500, BY 269
32466	BA160	BA 157, 1600V	BY 269
32467	BA161		BB 105A/B, BB 205A/B, BB 405A/B
32468	BA162		BB 109, BB 143, MV 109, 1SV50
32469	BA163		BB 112, BB 130, BB 509
32470	BA164	75mA, 0,85V/10mA	BA 216, BA 314, BA 315, 1N4148
32471	BA165(A)		BA 243, BA 283, BA 483, BA 484
32472	BA166	20V, 50mA	BA 128, BA 222, BA 147/50, 1N4148
32473	BA167	25V, 50mA, <200ns	BAX 88, BAX 94, BAY 93, 1N4148
32474	BA168	15V, 50mA, <4ns	BA 217, BA 317, BAY 71, 1N4148
32475	BA169	20V, 75mA	-
32476	BA170	20V, 0,15A, 250ns	BAW 21, BAX 15...17, 1N4148
32477	BA171	BA 170, 30V, 100ns	BAW 21, BAX 15...17, 1N4148
32478	BA172	BA 170, 50V, 100ns	BAW 21, BAX 15...17, 1N4148
32479	BA173	350V, 0,3A, <500ns	BA 157...159, BY 204/4, BY 206, BY 406
32480	BA174	35V, 0,115A, <35ns	BAS 20, BAX 90, BAX 94, 1N4148
32481	BA175	75V, 0,25A, <300ns	BAS 20, BAX 90, BAX 94, 1N4148
32482	BA176		BA 157...159, BA 199/..., BY 208/...
32483	BA177		BA 243, BA 283, BA 483...BA 484
32484	BA178		BA 243, BA 283, BA 483, BA 484
32485	BA179	50V, 25mA	-
32486	BA180(a,b,c)	10V, 50mA	BA 128, BA 222, BA 147/25, 1N4148
32487	BA181(A,B,C)	BA 180, 20V	BA 128, BA 222, BA 147/25, 1N4148
32488	BA182		BA 243, BA 283, BA 483, BA 484
32489	BA184	350V, 0,2A, 700ns	BA 157...159, BY 204/4, BY 206, BY 406

32490	BA185	BA 184, 450V	BA 157...159, BY 204/4, BY 207, BY 407
32491	BA186	BA 184, 500V	BA 159...159, BY 204/8, BY 207, BY 407
32492	BA187	50V, 0,2A	BAY 18, BAY 44, BAY 86, BA 157...159
32493	BA188	BA 187, 100V	BAY 19, BAY 45, BAY 87, BA 157...159
32494	BA189	BA 187, 150V	BAY 20, BAY 45, BAY 88, BA 157...159
32495	BA190	BA 187, 200V	BAY 20, BAY 46, BAY 88, BA 157...159
32496	BA191	25V, 0,1A	BAT 42...43, BAT 47, BAT 85, 1SS293
32497	BA192	50V, 0,4A	BA 157...159, BA 199/250, BY 208/600
32498	BA193	BA 192, 100V	BA 157...159, BA 199/250, BY 208/600
32499	BA194	BA 192, 150V	BA 157...159, BA 199/250, BY 208/600
32500	BA195	200V, 0,15A, <50ns	BA 197, BAV 20, BAW 50, 1N3070, 1SS83
32501	BA196	150V, 0,25A, <50ns	BAV 20...21, BAW 50, 1SS83
32502	BA197	BA 196, 200V	BAV 20...21, BAW 50, 1SS83
32503	BA198	BA 196, 250V	BAV 21, 1SS83
32504	BA199/...	250..550V, 0,4A, <1µs	BA 157...159, BY 204/..., BY 208/...
32505	BA1A3Q..L4Z	AA 1A3Q..L4Z, Fig. ->	-
32506	BA200	45V, 0,15A, 4ns	BA 204, BAT 13, BAY 95, 1N3600, 1N4148
32507	BA201	BA 200, 70V	BAW 46, BAW 62, BAY 61, BAX 95, 1N4148
32508	BA202	BA 200, 100V	BAW 46, BAW 62, BAY 61, BAX 95, 1N4148
32509	BA203	BA 200, 150V	BAV 14
32510	BA204	60V, 0,2A, <10ns	BAT 13, BAW 62, BAY 95, 1N3600, 1N4148
32511	BA206		BA 121, BB 117, BB 417
32512	BA207		BA 121, BB 117, BB 417
32513	BA208		BA 121, BB 117, BB 417
32514	BA209	1N4148	1N4148
32515	BA210	1N4149	1N4149
32516	BA211	1N4446	1N4446
32517	BA212	1N4447	1N4447
32518	BA213	1N4448	1N4448
32519	BA214	1N4449	1N4449
32520	BA215	60V, 0,2A	BA 127, BA 188, BAY 73, 1N4148
32521	BA216	75mA, 0,58..0,8V/3mA, <4ns	BA 217...219, BA 315...317, 1N4148
32522	BA217	30V, 75mA, <4ns	BA 317...318, BAX 13, BAX 91, 1N4148
32523	BA218	50V, 75mA, <4ns	BA 318, BAX 13, BAX 91, BAY 38, 1N4148
32524	BA219	100V, 0,1A, <4ns	BAW 47, BAX 96, 1N4148, 1SS115
32525	BA220	0,2A, 0,64..0,7V/5mA, <4ns	BA 221, BAY 74, 1N4154, 1N4148
32526	BA221	30V, 0,2A, <4ns	BAW 62, BAX 95, BAY 74, 1N4154, 1N4148
32527	BA222	50V, 75mA	BA 128, BA 147/50, 1N4148, 1N5194
32528	BA223		BA 423
32529	BA223-10..-70	1000..7000V, 1A..0,15A	-
32530	BA224/...	150..300V, 0,15A, <40ns	BA 196...198, BAV 20...21
32531	BA225	50V, 50mA, 6ns	-
32532	BA226	BA 225[Fer]	-
32533	BA243(A,S)		BA 182, BA 283, BA 483, BA 484
32534	BA244(A,S)		BA 282, BA 284, BA 482



32535	BA245	350V, 0,4A, <300ns	BA 157...159, BY 204/4, BY 206, BY 406
32536	BA248	350V, 0,4A, <500ns	BA 157...159, BY 204/4, BY 206, BY 406
32537	BA280	4V, 30mA	BA 480...481, BAR 19, BAT 29, 1SS88
32538	BA281	50V, 0,2A	BA 127, BA 187, BA 215, 1N4148
32539	BA282		BA 244, BA 284, BA 482
32540	BA283		BA 243, BA 483, BA 484
32541	BA284		BA 244, BA 282, BA 482
32542	BA2A3Q	Rb1k, Rbe10kOhm, 60V, 0,1A	
32543	BA2A4M	BA 2A3Q, Rb10k, Rbe10kOhm	-
32544	BA2A4P	BA 2A3Q, Rb10k, Rbe47kOhm	-
32545	BA2A4Z	BA 2A3Q, Rb10k, Rbe-	-
32546	BA2F4M	BA 2A3Q, Rb22k, Rbe22kOhm	-
32547	BA2F4N	BA 2A3Q, Rb22k, Rbe47kOhm	-
32548	BA2F4Z	BA 2A3Q, Rb22k, Rbe-	-
32549	BA2L3M	BA 2A3Q, RbRbe4,7kOhm	-
32550	BA2L3N	BA 2A3Q, Rb4,7k, Rbe10kOhm	-
32551	BA2L3Z	BA 2A3Q, Rb4,7k, Rbe-	-
32552	BA2L4L	BA 2A3Q, Rb47k, Rbe22kOhm	-
32553	BA2L4M	BA 2A3Q, Rb47k, Rbe47kOhm	-
32554	BA2L4Z	BA 2A3Q, Rb47k, Rbe-	-
32555	BA314(A)	0,68..0,76V/1mA	BZX 62, BZX 84/C0V8, BZX 97/0V8
32556	BA315	0,1A, 0,71..0,79V/10mA, <4ns	BA 316, BA 220, BAY 94, 1N4148
32557	BA316	10V, 0,1A, <4ns	BA 220, BA 221, BAY 94, 1N4148
32558	BA317	BA 316, 30V	BAY 71, BAY 74, 1N4154, 1N4148
32559	BA318	BA 316, 50V	BAX 80, BAY 38, BAY 95, 1N4148
32560	BA319	75V, 0,25A, <50ns	BA 196, BAV 19, BAY 43, 1N4148
32561	BA320	BA 319, 100V	BA 196, BAV 19, BAW 50
32562	BA379	30V, 20mA	BA 382, MPN 3401, MPN 3402
32563	BA382	40V	MPN 3401, MPN 3402
32564	BA389	1MHz..1GHz, 30V, 50mA	BA 479
32565	BA3L4Z	Rb47kOhm, 30V, 20mA	
32566	BA423	20V, 50mA	BA 223
32567	BA423L	BA 423	-
32568	BA479(A,G,S)	10..1000MHz, 30V, 50mA	BA 389
32569	BA480	4V, 30mA	BAR 19, BAT 29, 1S1925
32570	BA481	4V, 30mA	BAR 19, BAT 29, 1S1925
32571	BA482	35V, 0,1A	BA 243, BA 283, BA 483...484
32572	BA483	35V, 0,1A	BA 243, BA 283, BA 483...484
32573	BA484	35V, 0,1A	BA 243, BA 283, BA 483...484
32574	BA579A	30V, 20mA	-
32575	BA579C(K)	BA 579A	-
32576	BA579S	BA 579A	-
32577	BA579S	BA 579A	-
32578	BA582	-	1SS241
32579	BA585	50V, 1..2000MHz	-

32580	BA586	50V, >1MHz	-
32581	BA592	BA 582	MA 77, 1SS314, 1SS356
32582	BA592	BA 582	MA 77, 1SS314, 1SS356
32583	BA595	BA 585	-
32584	BA595	BA 585	-
32585	BA596	BA 586	-
32586	BA596	BA 586	-
32587	BA604	50V, 0,2A, <20ns	-
32588	BA679(S)	BA 479(A,G,S), SMD	BA 979
32589	BA682	BA 282, SMD	BA 982
32590	BA683	BA 283, SMD	BA 983
32591	BA779(S)	BA 479G(S), SMD	-
32592	BA779-2	BA 479(S), SMD,	-
32593	BA885	BA 585	-
32594	BA886	BA 586	-
32595	BA979(S)	BA 479G(S), SMD	-
32596	BA982	BA 282, SMD	BA 682
32597	BA983	BA 283, SMD	BA 683
32598	BAL74	50V, 0,25A, <4ns	BAR 74
32599	BAL99	70V, 0,25A, <6ns	BAR 99
32600	BAP	2SB1132-P	2SB1132
32601	BAQ	2SB1132-Q	2SB1132
32602	BAQ133	BAQ 33	BAQ 33...35
32603	BAQ134	BAQ 34	BAQ 34...35
32604	BAQ135	BAQ 35	BAQ 35
32605	BAQ33	30V, 0,2A	BAQ 133...135
32606	BAQ34	BAQ 33, 60V	BAQ 134...135
32607	BAQ35	BAQ 33, 125V	BAQ 135
32608	BAR	2SB1132-R	2SB1132
32609	BAR10	20V, 35mA	HSS 101, 1N5712, 1SS108
32610	BAR11	15V, 20mA	HSS 101, 1N5712, 1SS108
32611	BAR12-...	1MHz..3GHz, 100V	-
32612	BAR13-...	BAR 12	-
32613	BAR14-...	BAR 12, SMD,	-
32614	BAR15-...	BAR 12, SMD,	-
32615	BAR16-...	BAR 12, SMD,	-
32616	BAR17-...	BAR 12, SMD	-
32617	BAR18	70V, 30mA	1SS348
32618	BAR19	4V, 30mA	BA 480...481, BAT 19, BAT 29, 1S1925
32619	BAR223-10..-70	1000..7000V, 0,5A..0,075A	-
32620	BAR28	70V, 15mA	HSS 102, 1N5711
32621	BAR35	5V	-
32622	BAR42	30V, 100mA	BAT 54, BAT 64
32623	BAR43	30V, 100mA	BAT 54, BAT 64
32624	BAR43A	BAR 43	BAT 54A, BAT 64-06

32625	BAR43C	BAR 43	BAT 54C, BAT 64-05
32626	BAR43S	BAR 43	BAT 54S, BAT 64-04
32627	BAR46	100V	-
32628	BAR46A	BAR 46	-
32629	BAR60	100V, 0,1A	-
32630	BAR61	100V, 0,1A	-
32631	BAR63	35V, 0,1A	-
32632	BAR64	..3GHz, 200V, 0,1A	-
32633	BAR65-03W	35V, 0,1A	-
32634	BAR65-03W	35V, 0,1A	-
32635	BAR74	BAL 74	BAL 74
32636	BAR79	60V	-
32637	BAR99	BAL 99	BAL 99
32638	BAS11	300V, 0,35A, <1μs	BYD 11G...M, BYX 57/...
32639	BAS116	85V, 0,25A	-
32640	BAS12	BAS 11, 400V	BYD 11G...M, BYX 57/...
32641	BAS125	25V, 0,1A	BAR 42...43
32642	BAS15	50V, 75mA, <4ns	BA 218, BAX 13, BAX 91, 1N4148
32643	BAS16	85V, 0,25A, <6ns	BAS 678, BAL 99, BAR 99
32644	BAS16W	BAS 16	-
32645	BAS17	0,75..0,83V/10mA	BZX 84/COV8
32646	BAS19	120V, 0,2A, <50ns	BAS 20, BAS 21
32647	BAS20	BAS 19, 200V	BAS 21
32648	BAS21	BAS 19, 250V	ISS250
32649	BAS216	BAS 16	-
32650	BAS26-20	20V,	-
32651	BAS27	300V, 0,25A, <1μs	-
32652	BAS28	BAS 16	-
32653	BAS29	90V, 0,25A, <50ns	BAS 19
32654	BAS31	BAS 29	-
32655	BAS32(L)	75V, 0,2A, <4ns	LL 4148
32656	BAS33	30V, 0,2A	BAS 45, BAY 135
32657	BAS34	BAS 33, 60V	BAS 45, BAY 135
32658	BAS35	BAS 29	-
32659	BAS40	40V, 0,12A	-
32660	BAS45	125V, 0,225A	BAY 135
32661	BAS45L	BAS 45, SMD	-
32662	BAS55	60V, 0,25A, <6ns	BAS 16, BAS 678, BAL 99, BAR 99
32663	BAS56	60V, 0,2A, <6ns	-
32664	BAS678	100V, 0,25A, <6ns	-
32665	BAS70	70V, 0,07A	-
32666	BAS78A	50V, 1A, 1μs	-
32667	BAS78B	BAS 78A, 100V	-
32668	BAS78C	BAS 78A, 200V	-
32669	BAS78D	BAS 78D, 400V	-

32670	BAS79A..D	BAS 78A..D	-
32671	BAS81	BAT 81, SMD	-
32672	BAS82	BAT 82, SMD	-
32673	BAS83	BAT 83, SMD	-
32674	BAS85	30V, 0,2A, <5ns	TMMBAT 42...43, TMMBAT 48
32675	BAS86	50V, 0,2A, <4ns	TMMBAT 49
32676	BAT10		-
32677	BAT114-099	4V, 90mA	-
32678	BAT114-099R		-
32679	BAT13	60V, 0,2A, <10ns	BAW 62, BAX 95, BAY 61, 1N4148, 1N4151
32680	BAT16-...	40V, 30mA	-
32681	BAT17	4V, 30mA	1SS350
32682	BAT18(DK)	35V, 0,1A	MA 57, 1SS153
32683	BAT19	10V, 30mA	BAR 10...11, 1N5712, 1SS88, 1SS106
32684	BAT29	5V, 30mA	BA 480...481, BAR 19, 1SS88, 1SS106
32685	BAT34	5V, 0,05A	-
32686	BAT35	4x BAT 34	-
32687	BAT36	5V, 0,1A	-
32688	BAT37	2 x BAT 36	-
32689	BAT41	100V, 0,1A, <5ns	BAT 46
32690	BAT42	30V, 0,2A, <5ns	BAT 48, BAT 85
32691	BAT42W..43W	BAT 42..43, SMD	-
32692	BAT43	30V, 0,2A, <5ns	BAT 48, BAT 85
32693	BAT45	15V, 30mA	BAR 10...11, 1N5712
32694	BAT46	100V, 0,15A	BAT 41
32695	BAT46W	BAT 46, SMD	-
32696	BAT47	20V, 0,35A	BAT 42...43, BAT 85, MBR 030
32697	BAT48	40V, 0,35A	BAT 86, MBR 040
32698	BAT49	80V, 0,5A	BYS 21-90, HRP 32, SB 180
32699	BAT53	10V, 10mA	-
32700	BAT54	30V, 0,2A, <5ns	BAT 64
32701	BAT62	40V, 20mA	-
32702	BAT62W..63W	BAT 62..63, SMD	-
32703	BAT62W..63W	BAT 62..63, SMD	-
32704	BAT63	3V, 0,1A	-
32705	BAT64	30V, 0,2A, <5ns	BAT 54
32706	BAT65	30V, 0,5A	-
32707	BAT66	30V, 2A	-
32708	BAT68	S, 8V, 0,13A	-
32709	BAT69	BAT 66, SMD	-
32710	BAT74	30V, 0,2A,<5ns	-
32711	BAT81	40V, 30mA, <1ns	HSS 100, 1N6263
32712	BAT82	BAT 81, 50V	HSS 100, 1N6263
32713	BAT83	BAT 81, 60V	HSS 100, 1N6263
32714	BAT85	30V, 0,2A, <5ns	BAT 42...43

32715	BAT86	50V, 0,2A, <4ns	BAT 49
32716	BAV10	75V, 0,3A, <6ns	BAV 12, BAW 55, BAW 76, BAX 81
32717	BAV100	60V, 0,25A, <50ns	BAV 200...203
32718	BAV101	BAV 100, 120V	BAV 201...203
32719	BAV102	BAV 100, 200V	BAV 202...203
32720	BAV103	BAV 100, 250V	BAV 203
32721	BAV105	60V, 0,3A, <6ns	-
32722	BAV12	90V, 0,35A, <10ns	BAV 14, BAW 25, BAW 26, BAX 81
32723	BAV13	50V, 0,4A, <10ns	BAV 14, BAW 24, BAW 25, BAW 26
32724	BAV14	120V, 0,5A, <10ns	BAV 15, BAV 16
32725	BAV15	140V, 0,5A, <20ns	BAV 16
32726	BAV16	150V, 0,5A, <15ns	-
32727	BAV17	25V, 0,25A, <50ns	BA 196...198, BAW 48...50
32728	BAV170	BAS 116, , 70V	-
32729	BAV18	BAV 17, 60V	BA 196...198, BAW 49...50
32730	BAV19	BAV 17, 120V	BA 196...198, BAW 50
32731	BAV199	BAS 116, , 70V	-
32732	BAV20	BAV 17, 200V	BA 197...198, BAW 50
32733	BAV200	BAV 100	BAV 100...103
32734	BAV201	BAV 101	BAV 101...103
32735	BAV202	BAV 102	BAV 102...103
32736	BAV203	BAV 103	BAV 103
32737	BAV21	BAV 17, 250V	BA 198
32738	BAV23	250V, 0,2A, <50ns	-
32739	BAV23S	BAV 23	-
32740	BAV24	50V, 0,3A, <8ns	BAV 10, BAW 54, BAW 55, BAW 76, 1N4150
32741	BAV39	40V, 0,1A	-
32742	BAV44	65V, 0,75A, <20ns	-
32743	BAV45	20V, 50mA, Ir<5pA/5V	BAS 33...34
32744	BAV45A	2x BAV 45	-
32745	BAV47	45V, 50mA, Ir<5pA/20V	BAS 33...34
32746	BAV48	BAV 47, Ir<20pA/20V	BAS 33...34
32747	BAV49	BAV 47, 35V, Ir<100pA/20V	BAS 33...34
32748	BAV53	25V, 50mA	BAT 42...43, BAT 85
32749	BAV53A	BAT 53	BAT 42...43, BAT 85
32750	BAV53B	BAT 53	BAT 42...43, BAT 85
32751	BAV54/...	30..100V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148
32752	BAV55	150V, 0,22A, 50ns	BA 196...198, BAV 20...21, BAY 80
32753	BAV65(A)	25V, 0,1A	BAT 42...43, BAT 85
32754	BAV67	80V, 90mA, <6ns	BA 219, BAW 46...47, 1N4148
32755	BAV68	180V, 0,25A, <50ns	BA 197...198, BAV 20...21, BAW 50
32756	BAV69	BAV 68, 240V	BA 198, BAV 21
32757	BAV70	70V, 0,25A, <6ns	-
32758	BAV70W	BAV 70	-
32759	BAV74	50V, 0,25A, <4ns	BAV 70

32760	BAV84	25V, 10mA	-
32761	BAV85	BAV 84	-
32762	BAV90		-
32763	BAV91	2x BAV 90 .	-
32764	BAV99	70V, 0,25A, <6ns	-
32765	BAV99W	BAV 99	-
32766	BAW10	50V, 0,2A	BA 157...159, BA 187...190, BAY 18...21
32767	BAW100	BAW 56	MA 157A
32768	BAW101	300V, 0,2A	-
32769	BAW11	BAW 10, 100V	BA 157...159, BA 188...190, BAY 20...21
32770	BAW12	BAW 10, 150V	BA 157...159, BA 189...190, BAY 20...21
32771	BAW13	BAW 10, 200V	BA 157...159, BA 190, BAY 20...21
32772	BAW14	BAW 10, 300V	BA 157...159, BAY 21, BAY 46
32773	BAW156	BAS 116, , 70V	-
32774	BAW16	150V, 0,2A	BA 157...159, BA 189...190, BAY 20...21
32775	BAW17	200V, 0,2A	BA 157...159, BA 190, BAY 21
32776	BAW18	150V, 0,2A	BA 157...159, BA 189...190, BAY 20...21
32777	BAW21(A,B)	70..90V, 0,4A, <300ns	BYX 57/..., BA 173, BA 157...159
32778	BAW22	50V, 0,1A	-
32779	BAW23	BAW 22, 30V	-
32780	BAW24	50V, 0,6A, <6ns	BAW 25, BAW 26, BAW 27
32781	BAW25	50V, 0,6A, <6ns	BAW 26, BAW 27
32782	BAW26	75V, 0,6A, <6ns	BAW 27
32783	BAW27	75V, 0,6A, <6ns	BAW 26
32784	BAW28	30V, 0,4A, <6ns	BAV 13, BAV 14
32785	BAW29		-
32786	BAW31	50V, 0,1A	-
32787	BAW32A...E	10..200V, 60mA	BA 147/..., BA 187...190, BAY 17...21
32788	BAW33	70V, 0,225A, <25ns	BAV 19...21, BAY 43, BAW 50, 1N4148
32789	BAW36	60V, 0,4A, <6ns	BAV 14, BAW 24...27
32790	BAW43	125V, 0,3A	BA 157...159, BA 194, BA 199/...
32791	BAW45	20V, 0,1A, <6ns	BA 317, BAY 71, BAY 94, 1N4148
32792	BAW46	75V, 0,12A, <6ns	BAW 62, BAW 76, BAX 95, 1N4148
32793	BAW47	100V, 0,115A, <6ns	BA 202, BA 203, BA 219,
32794	BAW48	50V, 0,3A, 35ns	BAX 78, BAW 49, BAW 50, 1N4148
32795	BAW49	100V, 0,35A, <60ns	BAW 50, BAX 12, BAY 72
32796	BAW50	200V, 0,35A, <60ns	BAW 50
32797	BAW51	80V, 0,3A	BA 157...159, BA 193...194, BAW 52
32798	BAW52	200V, 0,3A	BA 157...159, BA 199/..., BAS 11
32799	BAW53	30V, 0,225A, <8ns	BA 204, BA 221, BAY 74, 1N4148
32800	BAW54	50V, 0,3A, <6ns	BAV 10, BAV 24, BAW 55, BAW 76, 1N4150
32801	BAW55	75V, 0,3A, <6ns	BAV 10, BAV 12, BAW 76, BAX 81
32802	BAW56	70V, 0,25A, <6ns	BAW 66, BAW 68
32803	BAW56G	BAW 56	-
32804	BAW56GT	BAW 56	-



32805	BAW56W	BAW 56	-
32806	BAW58	100V, 80mA, <50ns	BAV 19...21, BAY 43, BAY 80, 1N4148
32807	BAW59	40V, 60mA, <6ns	BA 217...218, BA 317, BAX 87, 1N4148
32808	BAW60	15V, 50mA, <0,85ns	-
32809	BAW62	75V, 0,2A, <4ns	BAW 76, BAX 95, 1N4148...4149
32810	BAW63	60V, 0,2A, <4ns	BAS 16
32811	BAW63A	BAS 63, 30V	BAS 16
32812	BAW63B	BAS 63, 15V	BAS 16
32813	BAW64	BAS 63	BAV 70
32814	BAW65	BAS 63A	BAV 70
32815	BAW66	BAS 63A	BAW 56
32816	BAW67	BAS 63B	BAV 70
32817	BAW68	BAS 63B	BAW 56
32818	BAW75	35V, 0,3A, <4ns	BAW 54...55, BAW 76, 1N4148, 1N4150
32819	BAW76	75V, 0,3A, <4ns	BAV 10, BAW 55, BAX 81, 1N4148
32820	BAW77	120V, 0,1A	BA 147/150, BA 157...159, BA 189...190
32821	BAW78A	50V, 1A	-
32822	BAW78B	BAW 78A, 100V	-
32823	BAW78C	BAW 78A, 200V	-
32824	BAW78D	BAW 78A, 400V	-
32825	BAW79A	BAW 78A	-
32826	BAW79B	BAW 78B	-
32827	BAW79C	BAW 78C	-
32828	BAW79D	BAW 78D	-
32829	BAW84	350V, 0,25A, 700ns	BA 157...159, BY 204/..., BY 208/...
32830	BAW85	BAW 84, 450V	BA 157...159, BY 204/..., BY 208/...
32831	BAW86	BAW 84, 500V	BA 158...159, BY 204/..., BY 208/...
32832	BAW90	75V, 0,05A	-
32833	BAW92	BAW 90	-
32834	BAW93	BAW 90, Br	-
32835	BAX12(A)	90V, 0,4A, <60ns	BA 157...159, BAV 15...16
32836	BAX13(A)	50V, 75mA, <6ns	BA 218, BA 318, BAX 91, BAY 38, 1N4148
32837	BAX14	40V, 0,5A, <30ns	BAV 15, BAV 16, BAV 44
32838	BAX14A	BAX 14, <300ns	BA 157...159, BY 204/..., BY 208/...
32839	BAX15	180V, 0,25A, <300ns	BA 157...159, BA 173, BY 204/...
32840	BAX157	400V, 0,5A, 400ns	BY 204/4, BY 206, BY 406, BY 208/600
32841	BAX158	BAX 157, 600V	BY 204/8, BY 207, BY 407, BY 208/600
32842	BAX159	BAX 157, 1000V	BY 204/10, BY 208/1000, BY 268
32843	BAX16(A)	150V, 0,2A, <120ns	BA 157...159, BA 196...198, BAX 17, BAY 80
32844	BAX17(A)	200V, 0,2A, <120ns	BA 157...159, BA 197...198, BAV 20...21
32845	BAX18(A)	75V, 0,5A	BA 157...159, BY 402, BY 295/...
32846	BAX20	35V, 0,115A, <250ns	BAX 15...17, BAX 88, 1N4148
32847	BAX21	BAX 20, 75V	BA 157...159, BAX 15...17, 1N4148
32848	BAX22	BAX 20, 125V	BA 157...159, BA 173, BAX 15...17
32849	BAX25	30V, 0,05A, <0,5ns	-

32850	BAX26	30V, 0,1A,<0,5ns	-
32851	BAX27	30V, 0,5A,<0,5ns	-
32852	BAX28	25V, 0,115A, <4ns	-
32853	BAX280	1000V, 3,5A(Tc80°), 55ns	-
32854	BAX30	25V, 0,115A, <4ns	-
32855	BAX32	250V	-
32856	BAX33	30V, 0,115A, <2ns	-
32857	BAX34	30V, 0,115A, <2ns	-
32858	BAX35	30V, 0,115A, <2ns	-
32859	BAX36	50V, 0,15A, <50ns	-
32860	BAX37	50V, 0,15A, <50ns	-
32861	BAX38	50V, 0,15A, <50ns	-
32862	BAX45	80V, 0,3A, <25ns	-
32863	BAX46	BAX 45	-
32864	BAX47	BAX 45	-
32865	BAX48	BAX 45	-
32866	BAX52	BAX 45	-
32867	BAX53	BAX 45	-
32868	BAX54	BAX 45	-
32869	BAX55	BAX 45	-
32870	BAX56	60V, 0,3A, <4ns	-
32871	BAX57	BAX 56	-
32872	BAX58	BAX 56	-
32873	BAX59	BAX 56	-
32874	BAX60	BAX 56	-
32875	BAX61	BAX 56	-
32876	BAX62	BAX 56	-
32877	BAX63	BAX 56	-
32878	BAX78	55V, 0,3A, <20ns	BA 318, BAY 38, BAY 69, 1N4148
32879	BAX79	50V, 0,4A, <4ns	BAV 13, BAV 14, BAW 24...27
32880	BAX80	50V, 0,15A, <4ns	BAX 80, BAW 62, BAY 95, 1N4148
32881	BAX81	90V, 0,35A, <6ns	BAV 14
32882	BAX82	50V, 0,25A, <6ns	BAV 10, BAW 54...55, BAW 76, 1N4148
32883	BAX83	100V, 75mA, <10ns	BA 202...203, BA 219, BAX 96, 1N4148
32884	BAX84	50V, 75mA, <6ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32885	BAX85	BAX 84, <15ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32886	BAX86A	50V, 75mA, <8ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32887	BAX86B	BAX 86A, <10ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32888	BAX87	40V, 75mA, 6ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32889	BAX88	20V, 75mA, <150ns	BAX 15...17, BAY 92, BAW 21, 1N4148
32890	BAX89A	45V, 75mA, <10ns	BA 218, BA 318, BAX 13, BAY 38, 1N4148
32891	BAX89B	BAX 89A, <20ns	BA 218, BA 318, BAX 13, BAY 38, 1N4148
32892	BAX89C	BAX 89A, 6ns	BA 218, BA 318, BAX 13, BAY 38, 1N4148
32893	BAX90A	45V, 75mA, <50ns	BAX 80, BAX 85, BAX 94, 1N4148
32894	BAX90B	BAX 90A, 50V	BAX 80, BAX 85, BAX 94, 1N4148

32895	BAX90C	BAX 90A, <4ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32896	BAX91(A..C)	50V, 75mA, <4ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32897	BAX92	50V, 75mA, <10ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32898	BAX93	BAX 92, <6ns	BA 218, BA 318, BAX 13, BAX 91, 1N4148
32899	BAX94	50V, 75mA, <50ns	BAX 85, BAX 89, BAX 90, 1N4148
32900	BAX95	75V, 0,2A, <4ns	BAW 62, BAW 76, 1N4148...4149
32901	BAX96(A..C)	100V, 75mA, <4ns	BA 219, 1N4148...4149, 1N4151
32902	BAY135	140V, 0,2	BAS 45
32903	BAY14	500V, 0,2A	BA 158...159, BAY 89, 1N4005...4007
32904	BAY15	BAY 14, 650V	BA 159, BAY 90, 1N4006...4007
32905	BAY16	BAY 14, 800V	BA 159, BAY 90, 1N4006...4007
32906	BAY17	15V, 0,25A, 1μs	BA 157...159, BAY 44...46, BAY 86...89
32907	BAY18	BAY 17, 60V	BA 157...159, BAY 44...46, BAY 86...89
32908	BAY19	BAY 17, 120V	BA 157...159, BAY 45...46, BAY 87...89
32909	BAY20	BAY 17, 180V	BA 157...159, BAY 56, BAY 88...89
32910	BAY21	BAY 17, 350V	BA 157...159, BAY 46, BAY 88...89
32911	BAY23	1000V, 80mA	BAY 90...91, BY 203/12, 1N5181...5184
32912	BAY24	BAY 23, 1500V	BAY 91, BY 203/16, 1N5181...5184
32913	BAY25	BAY 23, 2000V	BAY 91, BY 203/20, 1N5181...5184
32914	BAY26	BAY 23, 3000V	HVG 3, 1N1733, 1N5181...5184
32915	BAY31	15V, 0,1A, 2,3ns	BA 317...318, BAY 38, BAY 71, 1N4148
32916	BAY32	150V, 0,17A, <5μs	BA 157...159, BA 147/150, BA 189...190
32917	BAY33	150V, 0,13A, <500ns	BA 157...159, BAX 15...17, BA 173
32918	BAY35		-
32919	BAY36	30V, 0,1A, <10ns	BA 317...318, BAY 69, BAY 71, 1N4148
32920	BAY38	50V, 0,115A, <4ns	BA 318, BAX 80, BAY 95, 1N4148
32921	BAY39	75V, 0,45A, <160ns	BAV 15, BAV 16, BYX 57/...
32922	BAY41	40V, 0,225A, <15ns	BA 204, BAX 82, BAX 95, BAY 61, 1N4148
32923	BAY42	BAY 41, 60V	BAW 62, BAX 95, BAY 61, 1N4148
32924	BAY43	BAY 41, 80V	BAV 14, 1N4148, 1N4149, 1N4151
32925	BAY44	50V, 0,25A	BA 157...159, BAY 18...21, BAY 86
32926	BAY45(DHD)	BAY 44, 150V	BA 157...159, BAY 20...21, BAY 88
32927	BAY46	BAY 44, 300V	BA 157...159, BAY 21, BAY 88
32928	BAY52	15V, 0,1A, <15ns	BA 317...318, BAY 38, BAY 71, 1N4148
32929	BAY60	25V, 0,115A, 4ns	BA 317...318, BAY 38, BAY 71, 1N4148
32930	BAY61	75V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148
32931	BAY63	50V, 0,2A, 4ns	BAW 62, BAW 76, BAX 95, 1N4148
32932	BAY64	20V, 0,1A	-
32933	BAY67		BA 243...244, BA 282...284, BA 482...484
32934	BAY68	35V, 0,115A, <10ns	BA 318, BAY 38, BAY 71, 1N4148
32935	BAY69	BAY 68, 60V	BA 318, BAX 80, BAY 38, 1N4148
32936	BAY70		BA 182, BA 243, BA 283, BA 483...484
32937	BAY71(DHD)	70V, 0,115A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148
32938	BAY72	125V, 0,375A, <400ns	BA 157...159, BAV 15...16, BAW 50
32939	BAY73	125V, 0,225A, <3μs	BA 157...159, BAY 20...21, BAY 45...46

32940	BAY74	50V, 0,2A, <4ns	BAW 62, BAX 95, BAY 95, 1N4148
32941	BAY77	30V, 0,2A, 2,3ns	BAW 62, BAX 95, BAY 95, 1N4148
32942	BAY80	150V, 0,25A, <50ns	BA 157...159, BA 196...198, BAV 20...21
32943	BAY82	15V, 50mA, <0,75ns	FD 700, 1N4244, 1N4376
32944	BAY84	90V, 0,15A, <50ns	BAS 31
32945	BAY85(S)	300V, 0,15A, <40ns	-
32946	BAY86	60V, 0,25A, <3µs	BA 157...159, BAY 20...21, BAY 45
32947	BAY87	BAY 86, 120V	BA 157...159, BAY 20...21, BAY 45
32948	BAY88	BAY 86, 350V	BA 157...159, BAY 21, BAY 46
32949	BAY89	600V, 0,25A	BA 158...159, BY 133, BY 204/6
32950	BAY90	BAY 89, 1000V	BA 159, BY 133, BY 204/10, BYX 94...95
32951	BAY91	BAY 89, 2000V	BY 203/20, BY 268, DM 516
32952	BAY91A	BAY 89, 1750V	BY 203/20, BY 268, DM 516
32953	BAY92	650V, 0,1A, <500ns	BA 158...159, BY 204/6.../10, BY 405
32954	BAY93	35V, 0,115A, <15ns	BA 317...318, BAY 38, BAY 69, 1N4148
32955	BAY94	35V, 0,115A, <4ns	BA 317...318, BAY 38, BAY 69, 1N4148
32956	BAY95	75V, 0,2A, <4ns	BAW 62, BAX 95, BAY 61, 1N4148
32957	BAY96	120V, 25GHz	-
32958	BAY97	25V, 0,1A, <4ns	BA 317...318, BAY 38, BAY 69, 1N4148
32959	BAY98	150V, 0,2A, 50ns	BA 157...159, BAX 16...17, BAY 80
32960	BAY99	40V, 0,1A, <50ns	BAX 80, BAX 94, BAY 41...43, 1N4148
32961	BB	1SV237	1SV237
32962	BB	1SV128	1SV128
32963	BB	2SB831-B	2SB831
32964	BB	2SD1367-BB	2SD1367
32965	BB	BCX 54-6	BCX 54-6
32966	BB	2SB1119	2SB1119
32967	BB(p,s)	BCW 61B	BCW 61B
32968	BB1...10	250..1200V, 0,3A, 800ns	BAY 89...91, BY 203/..., BY 208/...
32969	BB100		BB 105G, BB 106, BB 205G, BB 405G
32970	BB100G		BB 105G, BB 106, BB 205G, BB 405G
32971	BB101		BB 110, BB 203, MV 310, 1SV68, 1SV84
32972	BB102		BB 105G, BB 106, BB 205G, BB 405G
32973	BB103		BB 110, BB 203, MV 310, 1SV68, 1SV84
32974	BB104		BB 204, BB 304, MV 104, 1SV55, 1SV109
32975	BB105A,B		BB 121...122, BB 205A,B, BB 405A,B
32976	BB105G		BB 106, BB 205G, BB 405G, BB 505G
32977	BB106	-	BB 209, BB 229, BB 309, BB 409
32978	BB107		BB 212, BB 312
32979	BB109		BB 143, MV 109, MV 2101...2115, 1SV50
32980	BB110(B,G)		BB 203, MV 310, 1SV68, 1SV84
32981	BB112		BB 130, BB 509, MV 1401, MV 1403...1405
32982	BB117		BA 121, BB 417, 1SV89
32983	BB119		BA 125, 1SV114, 1SV125
32984	BB11A,B	Iv2mA	-

32985	BB12	Iv1mA	-
32986	BB121A,B		BB 105A,B, BB 205A,B, BB 405A,B
32987	BB122		BB 105A,B, BB 205A,B, BB 405A,B
32988	BB125		BB 105A,B, BB 205A,B, BB 405A,B
32989	BB126		BB 105A,B, BB 205A,B, BB 405A,B
32990	BB130		BB 112, BB 509, MV 1401, MV 1403...1405
32991	BB131		-
32992	BB131		-
32993	BB132		-
32994	BB132		-
32995	BB133	..460MHz	MA 355, MA 365...366
32996	BB133	..460MHz	MA 355, MA 365...366
32997	BB134		BB 535
32998	BB134		BB 535
32999	BB135		BB 535
33000	BB135		BB 535
33001	BB139		BB 106, BB 209, BB 229, BB 309, BB 409
33002	BB14	Iv25mA	-
33003	BB141A,B		BB 105A,B, BB 205A,B, BB 405A,B
33004	BB142		BB 105A,B, BB 205A,B, BB 405A,B
33005	BB143A,B		BB 109, MV 109, MV 2101...2115, 1SV50
33006	BB148	..460MHz	MA 355, MA 365...366
33007	BB148	..460MHz	MA 355, MA 365...366
33008	BB149		BB 535
33009	BB149		BB 535
33010	BB150	..460MHz	MA 355, MA 365...366
33011	BB150	..460MHz	MA 355, MA 365...366
33012	BB18	Iv>2mA	-
33013	BB1A3M..L3N	AB 1A3M..L3N, Fig. ->	-
33014	BB203	BB 103	BB 103
33015	BB204	BB 104	BB 104
33016	BB205A,B,G	BB 105 A,B,G	BB 105A,B,G
33017	BB209(G)		BB 106, BB 229, BB 309, BB 409
33018	BB212(B)		BB 107, BB 312
33019	BB215		BB 621...623
33020	BB219		BB 629, BB 631
33021	BB221	BB 121 A,B	BB 121A,B
33022	BB222	BB 122	BB 122
33023	BB229	BB 209	BB 209
33024	BB240	..400MHz	-
33025	BB241	..160MHz	-
33026	BB249	-	-
33027	BB3	Iv1mA	-
33028	BB304		BB 104, BB 204, MV 104, 1SV55, 1SV109
33029	BB305B		BB 105A,B, BB 205A,B, BB 405A

33030	BB305G		BB 105G, BB 205G, BB 405G, BB 505G
33031	BB309		BB 106, BB 209, BB 229, BB 409
33032	BB312		BB 107, BB 212
33033	BB314		BB 104, BB 204, BB 304, MV 104, 1SV 109
33034	BB319		BB 106, BB 209, BB 229, BB 409
33035	BB329A,B		BB 106, BB 209, BB 229, BB 409
33036	BB404(A..E)		BB 804, BB 814
33037	BB405A,B		BB 105A,B, BB 205A,B, BB 505B
33038	BB405G		BB 105G, BB 205G, BB 505G, BB 609
33039	BB406		BB 106, BB 209, BB 229, BB 609
33040	BB409		BB 106, BB 209, BB 229, BB 609
33041	BB417		BA 121, BB 117, 1SV89
33042	BB419		BB 619...620, MA 329, MA335
33043	BB421		BB 105A,B, BB 205A,B, BB 405A,B
33044	BB422		BB 105G, BB 205G, BB 405G, BB 505G
33045	BB439	BB 419	MA 361, MA 364
33046	BB439	BB 419	MA 361, MA 364
33047	BB4A	Iv1mA	-
33048	BB4B	Iv8mA	-
33049	BB5(A,B,C)	Iv8mA	-
33050	BB501		BA 121, BB 117, BB 417, 1SV89
33051	BB502		BA 125, BB 119, 1SV114, 1SV125
33052	BB503	BB 501, SMD	-
33053	BB503DK	BB 501, SMD,	-
33054	BB504	BB 502, SMD	-
33055	BB505B		BB 105A,B, BB 205A,B, BB 405A,B
33056	BB505G		BB 105G, BB 205G, BB 405G
33057	BB509	4,43MHZ	-
33058	BB512		-
33059	BB515B,G		BB 721
33060	BB521	BB 221	BB 221
33061	BB523		BB 105A,B, BB 205A,B, BB 405A,B, BB 505B
33062	BB525		-
33063	BB529	BB 329	BB 329
33064	BB531		BB 105G, BB 205G, BB 405G, BB 505G
33065	BB535	BB 515	MA 360, MA 372, 1SV214, 1SV223
33066	BB535	BB 515	MA 360, MA 372, 1SV214, 1SV223
33067	BB545	BB 525	-
33068	BB545	BB 525	-
33069	BB601		-
33070	BB609A,B		BB 106, BB 209, BB 229, BB 409
33071	BB610		BB 105G, BB 205G, BB 405G, BB 505G
33072	BB619(A,B)		BB 515B,G, BB 723, BB 729...731
33073	BB620		-
33074	BB621	BB 221, SMD	BB 215, BB 623



33075	BB622	BB 222, SMD	BB 215, BB 623
33076	BB623		BB 215, BB 621...622
33077	BB629	BB 329, SMD	BB 219, BB 631
33078	BB631		BB 219, BB 629
33079	BB639	BB 619	MA 365, MA 374, 1SV231
33080	BB639	BB 619	MA 365, MA 374, 1SV231
33081	BB640	BB 620	-
33082	BB640	BB 620	-
33083	BB709A,B		BB 106, BB 209, BB 229, BB 409
33084	BB721		BB 723
33085	BB723		BB 721
33086	BB729		BB 723, BB 730...731
33087	BB730		BB 723, BB 729, BB 731
33088	BB731		BB 723, BB 729...730
33089	BB801		-
33090	BB804(-0..-4)		BB 404, BB 814
33091	BB809		BB 106, BB 209, BB 229, BB 409
33092	BB811	..2GHz	-
33093	BB813	..2,5GHz	-
33094	BB814(-1,-2)		BB 404, BB 804
33095	BB824		-
33096	BB831	BB 811	-
33097	BB831	BB 811	-
33098	BB833	BB 813	1SV245
33099	BB833	BB 813	1SV245
33100	BB835	..2,8GHz	1SV245
33101	BB835	..2,8GHz	1SV245
33102	BB901		-
33103	BB909A,B		BB 106, BB 209, BB 229, BB 409
33104	BB910	..460MHz	-
33105	BB911(A)	..160MHz	-
33106	BBCC106B	200V, 3,2A, Igt/Ih<0,2/<5mA	TIC 106, TAG 623, TAG 628, S 4060, MCR72
33107	BBCC106B-1	200V, 2A, Igt/Ih<0,25/<2mA	C 106, TAG 106, TAG 108, C 108, XO 403
33108	BBCC106D	400V, 3,2A, Igt/Ih<0,2/<5mA	TIC 106, TAG 623, TAG 628, S 4060, MCR72
33109	BBCC106D-1	400V, 2A, Igt/Ih<0,25/<2mA	C 106, TAG 106, TAG 108, C 108, XO 403
33110	BBCC106E	500V, 3,2A, Igt/Ih<0,2/<5mA	TIC 106, TAG 623, TAG 628, S 4060, MCR72
33111	BBCC106E-1	500V, 2A, Igt/Ih<0,25/<2mA	C 106, TAG 106, TAG 108, C 108, XO 403
33112	BBCC106F	600V, 3,2A, Igt/Ih<0,2/<5mA	TIC 106, TAG 623, TAG 628, S 4060, MCR72
33113	BBCC106F-1	600V, 2A, Igt/Ih<0,25/<2mA	C 106, TAG 106, TAG 108, C 108, XO 403
33114	BBU	2SD2114K-U	2SD2114K
33115	BBV	2SD2114K-V	2SD2114K
33116	BBW	2SD2114K-W	2SD2114K
33117	BBY30		-
33118	BBY31		-
33119	BBY39		-

33120	BBY40		-
33121	BBY51		-
33122	BBY51-03W	BBY 51	-
33123	BBY51-03W	BBY 51	-
33124	BBY52		-
33125	BBY52-03W	BBY 52	-
33126	BBY52-03W	BBY 52	-
33127	BBY62		-
33128	BC	BCP 54-10	BCP 54-10
33129	BC	U 1BC44	U 1BC44
33130	BC	2SB831-C	2SB831
33131	BC	2SD1367-BC	2SD1367
33132	BC	BCX 54-10	BCX 54-10
33133	BC	2SB1120	2SB1120
33134	BC	2SB1188	2SB1188
33135	BC(p,s)	BCW 61C	BCW 61C
33136	BC100	350V, 0,15A, 0,6W	BF 259, BF 659, BFR 59, BFS 89, 2N5058
33137	BC101	40V, 40mA, 0,3W, 30MHz	BC 167, BC 182, BC 237, BC 547
33138	BC107	50V, 0,1A, 0,3W, 300MHz	BC 167, BC 182, BC 237, BC 547
33139	BC107P	BC 107	BC 107
33140	BC108	BC 107, 30V	BC 168, BC 183, BC 238, BC 548
33141	BC108P	BC 108	BC 108
33142	BC109	BC 107, 30V,	BC 169, BC 184, BC 239, BC 549
33143	BC109P	BC 109	BC 109
33144	BC110	80V, 50mA, 0,3W, 100MHz	BC 546, 2SC1890
33145	BC111	20V, 50mA, 0,03W, >50MHz	BC 122...123, BC 146
33146	BC112	20V, 50mA, 0,05W, 150MHz	BC 122...123, BC 146
33147	BC113	30V, 50mA, 0,2W, 100MHz	BC 168, BC 183, BC 238, BC 548
33148	BC113A	BC 113, 40V	BC 167, BC 183, BC 237, BC 547
33149	BC114	BC 133	BC 169, BC 184, BC 239, BC 549
33150	BC114A	BC 113, 40V,	BC 184, BC 550
33151	BC115	40V, 0,2A, 0,3W, 80MHz	BC 167, BC 183, BC 237, BC 547
33152	BC116(A)	45V, 0,5A, 0,3W, 200MHz	BC 327, BC 636, BC 160...161
33153	BC117	120V, 50mA, 0,3W, >60MHz	BF 257, BF 297, 2SC1890A, 2SC2363
33154	BC118	45V, 0,2W, >200MHz	BC 167, BC 183, BC 237, BC 547
33155	BC119	60V, 1A, 0,8W, >40MHz	BC 140...141, 2N1990, 2N2102, 2N2405
33156	BC120	60V, 1A, 0,8W, >40MHz	BC 140...141, 2N1990, 2N2102, 2N2405
33157	BC121	5V, 75mA, 0,25W, 250MHz	BC 122...123, BC 146
33158	BC122	BC 121, 30V	BC 123, BC 146
33159	BC123	BC 121, 45V	-
33160	BC125(A,B)	50..60V, 0,5A, 0,3W, 350MHz	BC 337, BC 637, BC 140...141
33161	BC126(A)	35..40V, 0,6A, 0,3W, 200MHz	BC 327...328, BC 638, BC 160...161
33162	BC127	25V, 0,075W, 30MHz	BC 122...123
33163	BC128	25V, 0,1W, 30MHz	BC 122...123
33164	BC129	50V, 0,1A, 0,135W, 300MHz	BC 167, BC 182, BC 237, BC 547

33165	BC130	BC 129, 30V	BC 168, BC 183, BC 238, BC 548
33166	BC131	BC 129, 30V,	BC 169, BC 184, BC 239, BC 549
33167	BC132(A)	30..40V, 50mA, 0,4W, >40MHz	BC 167, BC 183, BC 237, BC 547
33168	BC134	45V, 0,2W, >400MHz	BC 167, BC 183, BC 237, BC 547
33169	BC135(A)	45V, 0,2W, >200MHz	BC 167, BC 183, BC 237, BC 547
33170	BC136	60V, 0,5A, 0,3W, >60MHz	BC 337, BC 637, BC 140...141
33171	BC137	60V, 0,5A, 0,3W, >60MHz	BC 327, BC 638, BC 161
33172	BC138	60V, 1A, 0,8W, >40MHz	BC 140...141, 2N3019...3020
33173	BC139(A)	40V, 0,5A, 0,7W	BC 160...161, BC 303...304, 2N2303
33174	BC140	80V, 1A, 0,75W, >50MHz	BCX 40, 2N3019...3020, 2N4238...4239
33175	BC141	BC 140, 100V	BCX 40, 2N3019...3020, 2N4239
33176	BC142	80V, 1A, 0,8W, 90MHz	BC 140...141, BCX 40, 2N3019...3020
33177	BC143	60V, 1A, 0,7W, 170MHz	BC 161, BC 461, BCX 60, 2N4236
33178	BC144	70V, 1A, 0,7W	BC 140...141, BCX 40, 2N3019...3020
33179	BC145	120V, 0,1A, 0,3W, 80MHz	BF 257...259, BF 297...299, 2SC1890A
33180	BC146	20V, 50mA, 0,05W, 150MHz	BC 122...123
33181	BC147	BC 237	BC 237
33182	BC148	BC 238	BC 238
33183	BC149	BC 239	BC 239
33184	BC150	18V, 0,1A, 0,2W, 160MHz	BC 168, BC 183, BC 238, BC 548
33185	BC151	25V, 0,1A, 0,2W, 160MHz	BC 168, BC 183, BC 238, BC 548
33186	BC152	35V, 0,5A, 0,36W, 180MHz	BC 337, BC 635, BC 637, BC 639
33187	BC153	40V, 0,1A, 0,2W, 70MHz	BC 214, BC 415...416, BC 560
33188	BC154	40V, 0,1A, 0,2W, 70MHz	BC 214, BC 415...416, BC 560
33189	BC155	5V, 50mA, 0,105W, >50MHz	BC 121...123, BC 146
33190	BC156	BC 155, 0,05W	BC 121...123, BC 146
33191	BC157	BC 307	BC 307
33192	BC158	BC 308	BC 308
33193	BC159	BC 309	BC 309
33194	BC160	40V, 1A, 0,75W, >50MHz	BC 460...461, BCX 60, 2N4234...4236
33195	BC161	BC 160, 60V	BC 461, BCX 60, 2N4235...4236
33196	BC167	BC 237	BC 237
33197	BC168	BC 238	BC 238
33198	BC169	BC 239	BC 239
33199	BC170	20V, 0,1A, 0,3W, 100MHz	BC 168, BC 183, BC 238, BC 548
33200	BC171	50V, 0,1A, 0,3W, 250MHz	BC 167, BC 182, BC 237, BC 547
33201	BC172	BC 171, 30V	BC 168, BC 183, BC 238, BC 548
33202	BC173	BC 171, 30V,	BC 169, BC 184, BC 239, BC 549
33203	BC174	BC 171, 64V	BC 182, BC 190, BC 546
33204	BC174[Mot]	BC 174	
33205	BC175	35V, 0,5A, 0,56W, 180MHz	BC 337...338, BC 635, BC 637, BC 639
33206	BC177	50V, 0,1A, 0,3W, 130MHz	BC 212, BC 257, BC 307, BC 557
33207	BC177P	BC 177	BC 177
33208	BC178	BC 177, 30V	BC 213, BC 258, BC 308, BC 558
33209	BC178P	BC 178	BC 178

33210	BC179	BC 177, 25V,	BC 214, BC 259, BC 309, BC 559
33211	BC179P	BC 179	BC 179
33212	BC180	45V, 0,5A, 0,36W, 180MHz	BC 337, BC 635, BC 637, BC 639
33213	BC181(A)	40V, 0,2A, 0,3W	BC 213, BC 257, BC 307, BC 557
33214	BC182	BC 183, 60V	BC 174, BC 190, BC 546
33215	BC182K	BC 182	BC 182
33216	BC182L	BC 182	BC 182
33217	BC182P	BC 182	BC 182
33218	BC183	45V, 0,2A, 0,3W, 280MHz	BC 167, BC 237, BC 547
33219	BC183K	BC 183	BC 183
33220	BC183L	BC 183	BC 183
33221	BC183P	BC 183	BC 183
33222	BC184	BC 183	BC 413...414, BC 550
33223	BC184K	BC 184	BC 184
33224	BC184L	BC 184	BC 184
33225	BC184P	BC 184	BC 184
33226	BC185	60V, 1A, 0,8W, 300MHz	BC 140...141, BCX 40, 2N3019...3020
33227	BC186	40V, 0,1A, 0,3W, >50MHz	BC 213, BC 257, BC 307, BC 557
33228	BC187	BC 186, 30V	BC 213, BC 258, BC 308, BC 558
33229	BC190	70V, 0,1A, 0,3W, 250MHz	BC 174, BC 546, 2SC1890
33230	BC192	25V, 0,5A, 0,4W, >100MHz	BC 327...328, BC 636, BC 638, BC 640
33231	BC194	40V, 0,8A, >250MHz	BC 337, BC 635, BC 637, BC 639
33232	BC196	30V, 0,1A, 150MHz	BC 200, BC 202...203
33233	BC197	BC 198, 50V	BC 123
33234	BC198	30V, 0,1A, 0,05W, 300MHz	BC 122...123, BC 146
33235	BC199	BC 198	BC 122...123, BC 146
33236	BC200	20V, 50mA, 0,05W, 90MHz	BC 202...203
33237	BC201	5V, 75mA, 0,25W, 80MHz	BC 200
33238	BC202	BC 201, 30V	-
33239	BC203	BC 201, 45V	-
33240	BC204	BC 205, 50V	BC 212, BC 257, BC 307, BC 557
33241	BC205	25V, 0,1A, 0,2W, 200MHz	BC 213, BC 258, BC 308, BC 558
33242	BC206	BC 205	BC 214, BC 259, BC 309, BC 559
33243	BC207	BC 208, 50V	BC 167, BC 182, BC 237, BC 547
33244	BC208	25V, 0,1A, 0,2W, 300MHz	BC 168, BC 183, BC 238, BC 548
33245	BC209	BC 208	BC 169, BC 184, BC 239, BC 549
33246	BC210	50V, 0,7A, 0,45W, >100MHz	BC 337, BC 637, BC 639
33247	BC211	80V, 1A, 0,8W, 300MHz	BC 140...141, BCX 40, 2N3019...3020
33248	BC211A	BC 211, 100V	BC 141, BCX 40, 2N3019...3020
33249	BC212	BC 213, 60V	BC 256, BC 266, BC 556
33250	BC212K	BC 212	BC 212
33251	BC212L	BC 212	BC 212
33252	BC212P	BC 212	BC 212
33253	BC213	45V, 0,2A, 0,3W, 350MHz	BC 257, BC 307, BC 557
33254	BC213K	BC 213	BC 213

33255	BC213L	BC 213	BC 213
33256	BC213P	BC 213	BC 213
33257	BC214	BC 213	BC 415...416, BC 560
33258	BC214K	BC 214	BC 214
33259	BC214L	BC 214	BC 214
33260	BC214P	BC 214	BC 214
33261	BC215	50V, 0,6A, 0,4W, 200MHz	BC 327, BC 638, BC 640
33262	BC216(A)[Riz]	30..40V, 0,6A, 0,3W, 200MHz	BC 327, BC 636, BC 638, BC 640
33263	BC216(A,B)[SGS]	45V, 20mA, 0,85W, 70MHz	BC 167, BC 183, BC 237, BC 547
33264	BC218(A)	30..45V, 0,1A, 0,3W, 350MHz	BC 167, BC 183, BC 237, BC 547
33265	BC219	60V, 0,5A, 0,8W, 40MHz	BC 140...141, BCX 40, 2N3019...3020
33266	BC220	30V, 50mA, 0,2W, 80MHz	BC 168, BC 183, BC 238, BC 548
33267	BC221	30V, 0,5A, 0,3W, 150MHz	BC 327...328, BC 636, BC 638, BC 640
33268	BC222	30V, 0,5A, 0,3W, 250MHz	BC 337...338, BC 635, BC 637, BC 639
33269	BC223	50V, 0,4A, 0,36W	BC 337, BC 637, BC 639
33270	BC224	30V, 30mA, 0,25W	BC 213, BC 258, BC 308, BC 558
33271	BC225	40V, 0,1A, 0,2W, 70MHz	BC 415...416, BC 560
33272	BC226(A)[Riz]	30..40V, 0,6A, 0,3W, 200MHz	BC 327...328, BC 636, BC 638, BC 640
33273	BC226[SGS]	40V, 0,1A, 0,8W, 40MHz	BC 140...141, BC 337, BC 635, BC 637
33274	BC231	40V, 0,4A, 0,625W, 250MHz	BC 327, BC 636, BC 638, BC 640
33275	BC231M	BC 231, 0,8W	BC 160...161, BCX 60, 2N2303, 2SA606
33276	BC232	40V, 0,4A, 0,625W, 300MHz	BC 337, BC 635, BC 637, BC 639
33277	BC232M	BC 232, 0,8W	BC 140...141, BCX 40, 2N3053, 2SC2108
33278	BC234(A)	30..45V, 0,1A, 0,3W, 350MHz	BC 167, BC 183, BC 237, BC 547
33279	BC235(A)	30..45V, 0,1A, 0,3W, 350MHz	BC 167, BC 183, BC 237, BC 547
33280	BC236	120V, 50mA, 0,3W	BF 297...299, BF 422, BSS 38, BSX 21
33281	BC237	BC 238, 50V	BC 167, BC 182, BC 547
33282	BC237P	BC 237	BC 237
33283	BC238	30V, 0,1A, 0,3W, 250MHz	BC 168, BC 183, BC 548
33284	BC238[Riz]	-/28V, 0,5A, 0,7W, 200MHz	BC 160...161, BCX 60, 2N2303, 2SA606
33285	BC238P	BC 238	BC 238
33286	BC239	BC 238	BC 169, BC 184, BC 549
33287	BC239[Riz]	-/40V, 0,5A, 0,7W, 200MHz	BC 160...161, BCX 60, 2N2303, 2SA606
33288	BC239P	BC 239	BC 239
33289	BC250	20V, 0,1A, 0,3W, 180MHz	BC 213, BC 258, BC 308, BC 558
33290	BC251	BC 252, 50V	BC 212, BC 257, BC 307, BC 557
33291	BC252	30V, 0,1A, 0,3W, 130MHz	BC 213, BC 258, BC 308, BC 558
33292	BC253	BC 252	BC 214, BC 259, BC 309, BC 559
33293	BC254(A)[Riz]	18..25V, 0,1A, 0,3W, 120MHz	BC 168, BC 183, BC 238, BC 548
33294	BC254[Texas]	100V, 30mA, 0,25W	BC 546, BF 297...299, BF 422, 2SC1890A
33295	BC255(A)[Riz]	18..25V, 0,1A, 0,3W, 120MHz	BC 168, BC 183, BC 238, BC 548
33296	BC255[Texas]	BC 254[Texas], 0,625W	BC 254
33297	BC256	64V, 0,1A, 0,3W, 130MHz	BC 212, BC 266, BC 556
33298	BC257	BC 307	BC 307
33299	BC258	BC 308	BC 308

33300	BC259	BC 309	BC 309
33301	BC260	20V, 0,1A, 0,3W, 180MHz	BC 213, BC 258, BC 308, BC 558
33302	BC261	BC 262, 50V	BC 212, BC 257, BC 307, BC 557
33303	BC262	30V, 0,1A, 0,3W, 130MHz	BC 213, BC 258, BC 308, BC 558
33304	BC263	BC 262	BC 241, BC 259, BC 309, BC 559
33305	BC264	30V, Idss>2mA, Up<1,6V	BF 244, BF 245, BFS 71, 2N3822
33306	BC264L	BC 264	BC 264
33307	BC266	BC 261, 64V	BC 212, BC 256, BC 556
33308	BC267	BC 268, 50V	BC 337, BC 637, BC 639
33309	BC268	30V, 0,5A, 0,375W, 200MHz	BC 337...338, BC 635, BC 637, BC 639
33310	BC269	BC 268	BC 337...338, BC 635, BC 637, BC 639
33311	BC270	BC 268, 20V	BC 337...338, BC 635, BC 637, BC 639
33312	BC271	25V, 1A, 0,3W, 225MHz	BC 337...338, BC 635, BC 637, BC 639
33313	BC272	45V, 1A, 0,3W, 150MHz	BC 337, BC 635, BC 637, BC 639
33314	BC274	BC 275, 50V	BC 212, BC 257, BC 307, BC 557
33315	BC275	30V, 0,1A, 0,33W, 130MHz	BC 213, BC 258, BC 308, BC 558
33316	BC276	BC 275	BC 214, BC 259, BC 309, BC 559
33317	BC277	BC 278, 45V	BC 167, BC 183, BC 237, BC 547
33318	BC278	20V, 0,1A, 0,3W, 150MHz	BC 168, BC 183, BC 238, BC 548
33319	BC279	BC 278	BC 169, BC 184, BC 239, BC 549
33320	BC280	45V, 0,1A, 0,36W, 130..250MHz	BC 184, BC 413...414, BC 550
33321	BC281	45V, 0,2A, 0,36W, 130..250MHz	BC 214, BC 415...416, BC 560
33322	BC283	30V, 0,6A, 0,4W, 110MHz	BC 327, BC 636, BC 638, BC 640
33323	BC284	40V, 0,2A, 0,5W, 60MHz	BC 167, BC 183, BC 237, BC 547
33324	BC285	120V, 0,1A, 0,36W, 80MHz	BF 297...299, BF 422, 2SC1890A
33325	BC286	70V, 1A, 0,8W, 100MHz	BC 140...141, BCX 40, 2N3019...3020
33326	BC287	60V, 1A, 0,8W, 200MHz	BC 161, BC 461, BCX 60, 2N4235...4236
33327	BC288	80V, 5A, 0,8W, 80MHz	BFT 32...34, BDX 35...37, 2N5336...5339
33328	BC289	45V, 0,1A, 0,36W	BC 167, BC 183, BC 237, BC 547
33329	BC290	BC 289	BC 184, BC 413...414, BC 550
33330	BC291	45V, 0,2A, 0,36W	BC 213, BC 257, BC 307, BC 557
33331	BC292	BC 291	BC 214, BC 415...416, BC 560
33332	BC293	80V, 5A, 0,8W, 80MHz	BFT 32...34, BDX 35...37, 2N5336...5339
33333	BC294	60V, 0,5A, 0,6W	BC 161, BC 303...304, BC 461, BCX 60
33334	BC295	30V, 0,05A, 0,2W, 90MHz	BC 168, BC 183, BC 238, BC 548
33335	BC297	50V, 1A, 0,375W, 250MHz	BC 327, BC 636, BC 638, BC 640
33336	BC298	BC 297, 30V	BC 327...328, BC 636, BC 638, BC 640
33337	BC300	120V, 0,5A, 0,85W, 120MHz	2N1893(A), 2N2102, 2N3019...3020
33338	BC301	BC 300, 90V	BC 141, BCX 40, 2N1990, 2N2102
33339	BC302	BC 300, 60V	BC 140...141, BCX 40, 2N1990, 2N2102
33340	BC303	85V, 0,5A, 0,85W, 75MHz	BC 461, BCX 60, 2N4236
33341	BC304	BC 303, 60V	BC 161, BCX 60, BC 461, 2N4235...4236
33342	BC307	BC 308, 50V	BC 212, BC 257, BC 557
33343	BC307P	BC 307	BC 307
33344	BC308	30V, 0,1A, 0,3W, 130MHz	BC 213, BC 258, BC 558



33345	BC308P	BC 308	BC 308
33346	BC309	BC 308, 25V,	BC 213, BC 259, BC 559
33347	BC309P	BC 309	BC 309
33348	BC310	70V, 1A, 0,8W, 90MHz	BC 140...141, BCX 40, 2N3019...3020
33349	BC311	70V, 1A, 0,8W, 200MHz	BC 161, BC 461, BCX 60, 2N4235...4236
33350	BC312	100V, 0,15A, 0,8W	BC 141, BC 300, BF 257...259
33351	BC313	60V, 1A, 0,8W, 200MHz	BC 161, BC 461, BCX 60, 2N4235...4236
33352	BC313A	BC 313, 80V	BC 461, BCX 60, 2N4236
33353	BC314	120V, 0,05A, 0,18W, >50MHz	BF 297...299, BF 422, 2SC1890A
33354	BC315	45V, 0,1A, 0,3W, >200MHz	BC 212, BC 415...416, BC 560
33355	BC317	BC 318, 50V	BC 167, BC 182, BC 237, BC 547
33356	BC318	40V, 0,15A, 0,35W, 280MHz	BC 167, BC 183, BC 237, BC 547
33357	BC319	BC 318, 30V,	BC 169, BC 184, BC 239, BC 549
33358	BC320	BC 321, 50V	BC 212, BC 257, BC 307, BC 557
33359	BC321	45V, 0,15A, 0,31W, 250MHz	BC 213, BC 257, BC 307, BC 557
33360	BC322	BC 321, 30V,	BC 214, BC 259, BC 309, BC 559
33361	BC323	100V, 5A, 0,8W, 100MHz	BFT 33...34, BDX 35...37, 2N5339...5339
33362	BC324	85V, 1A, 0,8W, 100MHz	BC 140...141, BCX 40, 2N3019...3020
33363	BC325	60V, 50mA, 0,36W, B40..120	BC 214, BC 415...416, BC 560
33364	BC326	BC 325, B100..500	BC 214, BC 415...416, BC 560
33365	BC327	50V, 0,8A, 0,625W, 100MHz	BC 638, BC 640, 2SB647
33366	BC327A	BC 327, 60V	BC 638, BC 640, 2SB647
33367	BC327L	BC 327	BC 327
33368	BC327P	BC 327	BC 327
33369	BC328	BC 327, 30V	BC 636, BC 638, BC 640, 2SB647
33370	BC328L	BC 328	BC 328
33371	BC328P	BC 328	BC 328
33372	BC329	60V, 30mA, 0,25W	BC 184, BC 413...414, BC 550
33373	BC330	BC 329, 45V	BC 184, BC 413...414, BC 550
33374	BC331	60V, 30mA, 0,25W	BC 184, BC 413...414, BC 550
33375	BC332	BC 321, 45V	BC 184, BC 413...414, BC 550
33376	BC333	25V, 50mA, 0,31W, 50MHz	BC 168, BC 183, BC 238, BC 548
33377	BC334	25V, 50mA, 0,31W, 50MHz	BC 213, BC 258, BC 308, BC 558
33378	BC335	BC 333	BC 169, BC 184, BC 239, BC 549
33379	BC336	BC 334	BC 214, BC 259, BC 309, BC 559
33380	BC337	50V, 0,8A, 0,625W, 100MHz	BC 637, BC 639, 2SD667
33381	BC337A	BC 337, 60V	BC 637, BC 639, 2SD667
33382	BC337L	BC 337	BC 337
33383	BC337P	BC 337	BC 337
33384	BC338	BC 337, 30V	BC 635, BC 637, BC 639, 2SD667
33385	BC338L	BC 338	BC 338
33386	BC338P	BC 338	BC 338
33387	BC340	40V, 0,5A, 0,8W, 100MHz	BC 140...141, BC 300...302, 2N1990
33388	BC341	BC 340, 60V	BC 140...141, BC 300...302, 2N1990
33389	BC342	70V, 1A, 0,8W, 100MHz	BC 140...141, BCX 40, 2N3019...3020

33390	BC343	70V, 1A, 0,8W, 100MHz	BC 161, BCX 60, 2N4236
33391	BC344	BC 342, 90V	BC 141, BCX 40, 2N3019...3020
33392	BC345	BC 343, 90V	BC 461, BCX 60
33393	BC347	50V, 0,1A, 0,3W, >125MHz	BC 167, BC 182, BC 237, BC 547
33394	BC348	BC 347, 40V	BC 167, BC 183, BC 237, BC 547
33395	BC349	BC 347, 30V	BC 168, BC 183, BC 238, BC 548
33396	BC350	50V 0,1A, 0,3W, >125MHz	BC 212, BC 257, BC 307, BC 557
33397	BC351	BC 350, 40V	BC 213, BC 257, BC 307, BC 557
33398	BC352	BC 350, 30V	BC 213, BC 258, BC 308, BC 558
33399	BC354	30V, 0,2A, 0,31W, >200MHz	BC 213, BC 258, BC 308, BC 558
33400	BC355	30V, 0,2A, 0,31W, >200MHz	BC 213, BC 258, BC 308, BC 558
33401	BC357	25V, 0,1A, 0,31W, >125MHz	BC 213, BC 258, BC 308, BC 558
33402	BC358	25V, 0,1A, 0,31W, >125MHz	BC 168, BC 183, BC 238, BC 548
33403	BC360	40V, 0,5A, 0,8W, 250MHz	BC 160...161, BC 303...304, BCX 60
33404	BC361	BC 360, 60V	BC 161, BC 303...304, BCX 60
33405	BC362	50V, 2A, 8W, 100MHz	BD 518, BD 520, BD 526, BD 528, BD 530
33406	BC363	BC 362, 60V	BD 518, BD 520, BD 526, BD 528, BD 530
33407	BC364	BC 362, 80V	BD 520, BD 528, BD 530
33408	BC365	50V, 2A, 8W, 150MHz	BD 517, BD 519, BD 525, BD 527, BD 529
33409	BC366	BC 365, 60V	BD 517, BD 519, BD 525, BD 527, BD 529
33410	BC367	BC 365, 80V	BD 519, BD 527, BD 529
33411	BC368	25V, 1A, 0,8W, 65MHz	BC 337...338, BC 635, BC 637, BC 639
33412	BC369	25V, 1A, 0,8W, 65MHz	BC 327...328, BC 636, BC 638, BC 640
33413	BC370	20V, 0,5A, 0,375W, 150MHz	BC 327...328, BC 636, BC 638, BC 640
33414	BC371	60V, 1A, 0,85W	BC 140...141, BCX 40, 2N3019...3020
33415	BC372	B>10000	BC 879, BSR 52, 2SD1660, 2SD2067
33416	BC373	BC 372, 80V	BC 877, BC 879, BSR 51...52, 2SD1853
33417	BC375	30V, 1A, 0,625W, 150MHz	BC 337...338, BC 635, BC 637, BC 639
33418	BC376	30V, 1A, 0,625W, 100MHz	BC 327...328, BC 636, BC 638, BC 640
33419	BC377	50V, 1A, 0,375W, 200MHz	BC 337, BC 637, BC 639
33420	BC378	BC 377, 30V	BC 337...338, BC 635, BC 637, BC 639
33421	BC381	40V, 0,2A, 0,625W	BC 327, BC 636, BC 638, BC 640
33422	BC382	50V, 0,1A, 0,3W, >150MHz	BC 184, BC 413...414, BC 550
33423	BC383	BC 382, 45V	BC 184, BC 413...414, BC 550
33424	BC384	BC 382, 45V, Ur<0,135μ V	BC 184, BC 413...414, BC 550
33425	BC385	45V, 0,1A, 0,3W, >150MHz	BC 167, BC 183, BC 237, BC 547
33426	BC386	45V, 0,1A, 0,3W, >150MHz	BC 167, BC 183, BC 237, BC 547
33427	BC387	35V, 0,6A, 0,31W	BC 337, BC 635, BC 637, BC 639
33428	BC389	B>40	BC 167, BC 183, BC 237, BC 547
33429	BC390	BC 389, -/20V	BC 168, BC 183, BC 238, BC 548
33430	BC391	BC 389, -/20V, B>100	BC 168, BC 183, BC 238, BC 548
33431	BC393	180V, 0,1A, 0,4W, 120MHz	BF 423, BF 436...437, BF 491...493
33432	BC394	180V, 0,1A, 0,4W, 90MHz	BF 298...299, BF 391...393, BF 423
33433	BC395	80V, 0,5A, 0,3W, >60MHz	BC 140...141, BC 300...301, BC 639
33434	BC396	80V, 0,5A, 0,3W	BC 303, BC 640

33435	BC397	50V, 1A, 0,8W	BC 161, BC 460...461, BCX 60
33436	BC398	60V, 1A, 0,8W	BC 140...141, BC 440...441, BCX 40
33437	BC399	30V, 75mA, 75mW	BC 122...123
33438	BC400	90V, 50mA, 0,2W, 150MHz	BC 477, 2SA893(A), 2SA1017, SB715
33439	BC404	80V, 0,15A, 0,36W, 150MHz	BC 477, BC 556, 2SA1136...37, 2SA1335
33440	BC405	BC 404, 60V,	BC 416, BC 560, 2SA1136...1137
33441	BC406	BC 404, 40V,	BC 214, BC 415...416, BC 560
33442	BC407	BC 237	BC 237
33443	BC408	BC 238	BC 238
33444	BC409	BC 239	BC 239
33445	BC410	30V, 50mA, 0,25W	BC 168, BC 183, BC 238, BC 548
33446	BC411	85V, 1A, 0,3W, 80MHz	BC 140...141, BCX 40, BC 639
33447	BC412	75V, 1A, 0,5W, 90MHz	BC 639, 2SD667(A), 2SD774, 2SD1616A
33448	BC413	45V, 0,1A, 0,3W, 250MHz	BC 184, BC 550
33449	BC413P..416P	BC 413..416	BC 413...416
33450	BC414	BC 413, 50V	BC 184, BC 550
33451	BC415	45V, 0,1A, 0,3W, 200MHz	BC 214, BC 560
33452	BC416	BC 415, 50V	BC 214, BC 560
33453	BC417	BC 307	BC 307
33454	BC418	BC 308	BC 308
33455	BC419	BC 309	BC 309
33456	BC420	180V, 0,1A, 0,4W, 150MHz	BF 423, BF 435...437, BF 491...493
33457	BC424	80V, 0,5A, 0,5W, >50MHz	BC 639, 2N3700...3701, 2SD667
33458	BC425	BC 424, 60V	BC 637, BC 639, 2N3700...3701, 2SD667
33459	BC426	80V, 0,5A, 0,5W, >50MHz	BC 640, 2SB647
33460	BC427	BC 426, 60V	BC 638, BC 640, 2SB647
33461	BC429	45V, 1A, 6W, >100MHz	BD 135, BD 137, BD 139, BD 226
33462	BC429A	BC 429, 60V	BD 137, BD 139, BD 228, BD 230
33463	BC430	45V, 1A, 6W, >100MHz	BD 136, BD 138, BD 140, BD 227
33464	BC430A	BC 430, 60V	BD 138, BD 140, BD 229, BD 231
33465	BC431	70V, 0,8A, 0,5W, 100MHz	BC 639, 2SD667, 2N3700...3701
33466	BC432	70V, 0,8A, 0,5W, 100MHz	BC 640, 2SB647
33467	BC437	BC 438, 50V	BC 167, BC 182, BC 237, BC 547
33468	BC438	30V, 0,1A, 0,22W, 300MHz	BC 168, BC 183, BC 238, BC 548
33469	BC439	BC 438	BC 169, BC 184, BC 239, BC 549
33470	BC440	50V, 2A, 1W, >50MHz	BCX 40, 2N4237...4239, 2SC2214
33471	BC441	BC 440, 75V	BCX 40, 2N4238...4239, 2SC2214
33472	BC445	60V, 0,3A, 0,625W, >100MHz	BC 182, BC 546, BC 637, BC 639
33473	BC446	60V, 0,3A, 0,625W, >100MHz	BC 212, BC 556, BC 638, BC 640
33474	BC447	BC 445, 80V	BC 546, BC 639, 2SD667
33475	BC448	BC 446, 80V	BC 556, BC 640, 2SB647
33476	BC449	BC 445, 100V	BC 639, 2SD667, 2SC1670
33477	BC450	BC 446, 100V	BC 640, 2SB647, 2SA840
33478	BC451	50V, 0,1A, 0,3W, >150MHz	BC 167, BC 182, BC 237, BC 547
33479	BC452	BC 451, 30V	BC 168, BC 183, BC 238, BC 548

33480	BC453	BC 451, 30V,	BC 169, BC 184, BC 239, BC 549
33481	BC454	50V, 0,1A, 0,3W, >150MHz	BC 212, BC 257, BC 307, BC 557
33482	BC455	BC 454, 30V	BC 213, BC 258, BC 308, BC 558
33483	BC456	BC 454, 30V,	BC 214, BC 259, BC 309, BC 559
33484	BC460	50V, 2A, 1W, >50MHz	BCX 60, 2N4235...4236
33485	BC461	BC 460, 75V	BCX 60, 2N4236
33486	BC462	35V, 1,5A, 0,88W, 200MHz	BC 636, BC 638, BC 640, 2SA966
33487	BC463	35V, 1,5A, 0,88W, 200MHz	BC 635, BC 637, BC 639, 2SC2236
33488	BC464	BC 462, 25V	BC 636, BC 638, BC 640, 2SA966
33489	BC465	BC 463, 25V	BC 635, BC 637, BC 639, 2SC2236
33490	BC467	BC 468, 50V	BC 167, BC 182, BC 237, BC 547
33491	BC468	30V, 0,1A, 0,22W, 300MHz	BC 168, BC 183, BC 238, BC 548
33492	BC469	BC 468	BC 169, BC 184, BC 239, BC 549
33493	BC477	90V, 0,15A, 0,36W, 150MHz	BC 556
33494	BC478	BC 477, 40V	BC 213, BC 257, BC 307, BC 557
33495	BC479	BC 477, 40V,	BC 214, BC 415...416, BC 560
33496	BC485	45V, 1A, 0,625W, 200MHz	BC 337, BC 635, BC 637, BC 639
33497	BC486	45V, 1A, 0,625W, 200MHz	BC 327, BC 636, BC 638, BC 640
33498	BC487	BC 485, 60V	BC 637, BC 639, 2SD667, 2N3700...3701
33499	BC488	BC 486, 60V	BC 638, BC 640, 2SB647
33500	BC489	BC 485, 80V	BC 639, 2SD667, 2N3700...3701
33501	BC490	BC 486, 80V	BC 640, 2SB647
33502	BC507	BC 508, 70V	BC 174, BC 190, BC 546
33503	BC508	60V, 0,2A, 0,36W, 200MHz	BC 174, BC 182, BC 190, BC 546
33504	BC509	BC 508	BC 414, BC 550, 2SC2240, 2SC2459
33505	BC510	BC 508, 40V,	BC 184, BC 413...414, BC 550
33506	BC512	BC 513, 50V	BC 212, BC 257, BC 307, BC 557
33507	BC513	30V, 0,2A, 0,3W, >200MHz	BC 213, BC 258, BC 308, BC 558
33508	BC514	BC 513	BC 214, BC 259, BC 309, BC 559
33509	BC516(P)	B>30k	MPSA 75, BC 876, BC 878, 2SA1555
33510	BC517(P)	B>30k	MPSA 25, BC 875, BC 877, 2SC4017
33511	BC520	60V, 0,05A, 0,625W, >100MHz	BC 414, BC 550, 2SC2240, 2SC2459
33512	BC521	BC 520, 45V	BC 184, BC 413...414, BC 550
33513	BC522	BC 520, 20V	BC 169, BC 184, BC 239, BC 549
33514	BC523	BC 520, 45V	BC 184, BC 413...414, BC 550
33515	BC524	45V, 0,1A, 0,625W	BC 184, BC 413...414, BC 550
33516	BC525	35V, 0,1A, 0,625W	BC 214, BC 415...416, BC 560
33517	BC526	60V, 0,2A, 0,625W, >100MHz	BC 212, BC 256, BC 266, BC 556
33518	BC527	60V, 1A, 0,625W, >100MHz	BC 638, BC 640, 2SB647
33519	BC527[Ucp]	45V, 0,05A, 0,3W, 150MHz	BC 167, BC 182, BC 237, BC 547
33520	BC528	BC 527, 80V	BC 640, 2SB647
33521	BC528[Ucp]	45V, 0,05A, 0,3W, 150MHz	BC 167, BC 182, BC 237, BC 547
33522	BC529	50V, 0,2A, 0,625W, >100MHz	BC 212, BC 556...557, BC 327
33523	BC530	130V, 0,1A, 0,625W, >50MHz	BF 398, BF 423, BF 435...437, 2SA1370
33524	BC531	BC 530, 160V	BF 423, BF 435...437, 2SA1370

33525	BC532	160V, 0,1A, 0,625W, >50MHz	BF 297...299, BF 422, 2SC3467
33526	BC533	BC 532, 180V	BF 298...299, BF 422, 2SC3467
33527	BC534	80V, 0,5A, 0,625W, >50MHz	BC 640, 2SB647
33528	BC535	80V, 0,5A, 0,625W, >50MHz	BC 639, 2SD667
33529	BC537	60V, 1A, 0,625W, >100MHz	BC 637, BC 639, 2SD667
33530	BC538	BC 537, 80V	BC 639, 2SD667
33531	BC546	BC 547, 80V	2SC2240, 2SC2459, 2SC2674...75, 2SC3378
33532	BC547	50V, 0,1A, 0,5W, 300MHz	BC 167, BC 182, BC 237
33533	BC548	BC 547, 30V	BC 168, BC 183, BC 238
33534	BC549	BC 547, 30V,	BC 169, BC 184, BC 239
33535	BC550	BC 547	BC 184, BC 414, 2SC2240, 2SC2459
33536	BC551	50V, 0,1A, 0,5W	BC 212, BC 257, BC 307, BC 557
33537	BC556	BC 557, 80V	2SA970, 2SA1049, 2SA1136
33538	BC557	50V, 0,1A, 0,5W, 150MHz	BC 212, BC 257, BC 307
33539	BC558	BC 557, 30V	BC 213, BC 258, BC 308
33540	BC559	BC 557, 30V,	BC 214, BC 259, BC 309
33541	BC560	BC 557	BC 214, BC 416, 2SA1136...1137
33542	BC582	BC 583, 50V	BC 167, BC 182, BC 237, BC 547
33543	BC583	30V, 0,2A, 0,3W, >150MHz	BC 168, BC 183, BC 238, BC 548
33544	BC584	BC 583	BC 169, BC 184, BC 239, BC 549
33545	BC585	25V, 0,1A, 0,35W	BC 168, BC 183, BC 238, BC 548
33546	BC586	25V, 0,1A, 0,35W	BC 213, BC 258, BC 308, BC 558
33547	BC587	60V, 1A, 4W(Tc25°)	BC 161, BC 461, BCX 60, 2N4235...4236
33548	BC612	75V, 0,2A, 0,3W, >200MHz	BC 556, 2SA1136...1137
33549	BC612L	BC 612	BC 612
33550	BC617	0,625W,>150MHz,B>10k	BC 875, BC 877, BC 879, BSR 50...52
33551	BC618	BC 617, 80V	BC 877, BC 879, BSR 51...52
33552	BC635	45V, 1A, 0,8W, 130MHz	BC 537...538, 2N3700...3701, 2SD667
33553	BC636	45V, 1A, 0,8W, 50MHz	BC 527...528, 2SB647, 2SA1013
33554	BC637	BC 635, 60V	BC 537...538, 2SD667, 2N3700...3701
33555	BC638	BC 636, 60V	BC 527...528, 2SB 647, 2SA1013
33556	BC639	BC 635, 100V	2SD667, 2N3700...3701, 2SC2383
33557	BC640	BC 636, 100V	2SB647, 2SA1013
33558	BC650(S)	30V, 0,2A, 0,625W, 300MHz	BC 169, BC 184, BC 239, BC 549
33559	BC651(S)	BC 650, 45V	BC 184, BC 413...414, BC 550
33560	BC682	75V, 0,2A, 0,3W, >150MHz	BC 174, BC 190, BC 546
33561	BC682L	BC 682	BC 682
33562	BC714	45V, 0,2A, 0,3W, >200MHz	BC 214, BC 415...416, BC 560
33563	BC727	50V, 1A, 0,625W, >100MHz	BC 638, BC 640, 2SB647
33564	BC728	BC 727, 30V	BC 636, BC 638, BC 640, 2SB647
33565	BC737	50V, 1A, 0,625W, >100MHz	BC 637, BC 639, 2SD667, 2N3700...3701
33566	BC738	BC 737, 30V	BC 635, BC 637, BC 639, 2SD667
33567	BC807	50V, 0,5A, 100MHz	BCX 17, BCW 68
33568	BC807-W	BC 807	2SB1219A
33569	BC807R	BC 807	BCX 17R, BCW 68R

33570	BC808	BC 807, 30V	BCX 17...18, BCW 67...68
33571	BC808-W	BC 808	2SA1588, 2SB1219(A)
33572	BC808R	BC 808	BCX 17R...18R, BCW 67R...68R
33573	BC817	50V, 0,5A, 200MHz	BCX 19, BCW 65...66
33574	BC817-W	BC 817	2SD1820A, 2SD1949
33575	BC817R	BC 817	BCX 19R, BCW 65R...66R
33576	BC818	BC 817, 30V	BCX 19...20, BCW 65...66
33577	BC818-W	BC 818	2SC4097, 2SC4118, 2SD1820(A), 2SD1949
33578	BC818R	BC 818	BCX 19R...20R, BCW 65R...66R
33579	BC827	30V, 0,8A, 0,8W, 100MHz	BC 327...328, BC 636, BC 638, BC 640
33580	BC828	BC 827, 50V	BC 327, BC 638, BC 640, 2SB647
33581	BC837	30V, 0,8A, 0,8W, 100MHz	BC 337...337, BC 635, BC 637, BC 639
33582	BC838	BC 837, 50V	BC 337, BC 637, BC 639, 2SD667
33583	BC846	BC 847, 80V	BCV 71...72
33584	BC846-W..850-W	BC 846..850	2SC4101...02, 2SC4117
33585	BC846R	BC 846	BCV 71R...72R
33586	BC847	50V, 0,1A, 300MHz	BCW 71...72, BCW 81
33587	BC847R	BC 847	BCW 71R...72R, BCW 81R
33588	BC848	BC 847, 30V	BCW 31...33, BCW 71...72, BCW 81
33589	BC848R	BC 848	BCW 31R...33R, BCW 71R...72R, BCW 81R
33590	BC849	BC 847, 30V,	BCF 32...33, BCF 81
33591	BC849R	BC 849	BCF 32R...33R, BCF 81R
33592	BC850	BC 847	BCF 81
33593	BC850R	BC 850	BCF 81R
33594	BC856	BC 857, 80V	BCW 89
33595	BC856-W..860-W	BC 856..860	2SA1587, 2SA1587
33596	BC856R	BC 856	BCW 89R
33597	BC857	50V, 0,1A, 150MHz	BCW 69...70, BCW 89
33598	BC857R	BC 857	BCW 69R...70R, BCW 89R
33599	BC858	BC 857, 30V	BCW 29...30, BCW 69...70, BCW 89
33600	BC858R	BC 858	BCW 29R...30R, BCW 69R...70R, BCW 89R
33601	BC859	BC 857, 30V,	BCF 29...30, BCF 70
33602	BC859R	BC 859	BCF 29R...30R, BCF 70R
33603	BC860	BC 857	BCF 70
33604	BC860R	BC 860	BCF 70R
33605	BC868	25V, 1A, 60MHz	BCX 54...55, BCX 68
33606	BC869	25V, 1A, 60MHz	BCX 51...52, BCX 69
33607	BC875	B>2000	BC 618, BSR 50...52
33608	BC876	B>2000	BSR 60...62
33609	BC877	BC 875, 80V	BC 618, BSR 51...52
33610	BC878	BC 876, 80V	BSR 61...62
33611	BC879	BC 875, 100V	BSR 52
33612	BC880	BC 876, 100V	BSR 62
33613	BCF29	32V, 0,1A, 150MHz	BC 859...860, BCF 70
33614	BCF29R	BCF 29	BC 859R...860R, BCF 70R



33615	BCF30	32V, 0,1A, 150MHz	BC 859...860, BCF 70
33616	BCF30R	BCF 30	BC 859R...860R, BCF 70R
33617	BCF32	32V, 0,1A, 300MHz	BC 849...850, BCF 81
33618	BCF32R	BCF 32	BC 849R...850R, BCF 81R
33619	BCF33	32V, 0,1A, 300MHz	BC 849...850, BCF 81
33620	BCF33R	BCF 33	BC 849R...850R, BCF 81R
33621	BCF70	BCF 30, 50V	BC 860
33622	BCF70R	BCF 70	BC 860R
33623	BCF81	BCF 33, 50V	BC 850
33624	BCF81R	BCF 81	BC 850R
33625	BCP	2SB1188-P	2SB1188
33626	BCP28	BCV 26, 1,5W	-
33627	BCP29	BCV 27, 1,5W	-
33628	BCP48	BCV 46, 1,5W	-
33629	BCP49	BCV 47, 1,5W	-
33630	BCP51	BCX 51, 1,5W	-
33631	BCP52	BCX 52, 1,5W	-
33632	BCP53	BCX 53, 1,5W	-
33633	BCP54	BCX 54, 1,5W	-
33634	BCP55	BCX 55, 1,5W	-
33635	BCP56	BCX 56, 1,5W	-
33636	BCP68	BCX 68, 1,5W	-
33637	BCP69	BCX 69, 1,5W	-
33638	BCQ	2SB1188-Q	2SB1188
33639	BCR	2SB1188-R	2SB1188
33640	BCR108	Rbe47kOhm	-
33641	BCR10A-2	100V, 10A(Tc75°), Igt<50mA	-
33642	BCR10A-4	200V, 10A(Tc75°), Igt<50mA	-
33643	BCR10A-6	300V, 10A(Tc75°), Igt<50mA	-
33644	BCR10A-8	400V, 10A(Tc75°), Igt<50mA	-
33645	BCR10AM-10	500V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33646	BCR10AM-10	500V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33647	BCR10AM-12	600V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33648	BCR10AM-12	600V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33649	BCR10AM-4	200V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33650	BCR10AM-4	200V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33651	BCR10AM-6	300V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33652	BCR10AM-6	300V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33653	BCR10AM-8	400V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33654	BCR10AM-8	400V, 10A(Tc100°), Igt<30mA	TAG 252, TAG 257
33655	BCR10B-2..-8	BCR 10A-2..-8	-
33656	BCR10C-2..-8	BCR 10A-2..-8	SC 245, BS 10-...A, TXD 99, SC 250
33657	BCR10CM-4..-12	BCR 10AM-4..-12, 10A(Tc103°)	TAG 252, TAG 257
33658	BCR10CM-4..-12	BCR 10AM-4..-12, 10A(Tc103°)	TAG 252, TAG 257
33659	BCR10DM-4..-12	BCR 10AM-4..-12, 10A(Tc93°)	TAG 252, TAG 257

33660	BCR10DM-4..-12	BCR 10AM-4..-12, 10A(Tc93°)	TAG 252, TAG 257
33661	BCR10EM-4..-12	BCR 10AM-4..-12, 10A(Tc80°)	TAG 252, TAG 257
33662	BCR10EM-4..-12	BCR 10AM-4..-12, 10A(Tc80°)	TAG 252, TAG 257
33663	BCR112	Rbe4,7kOhm	KSR 1101, 2SC4362
33664	BCR119	50V, 0,1A, Rb4,7kOhm, Rbe0	KSR 1109, 2SC3900
33665	BCR12AM-10	500V, 12A(Tc101°), Igt<30mA	TAG 257
33666	BCR12AM-10	500V, 12A(Tc101°), Igt<30mA	TAG 257
33667	BCR12AM-12	600V, 12A(Tc101°), Igt<30mA	TAG 257
33668	BCR12AM-12	600V, 12A(Tc101°), Igt<30mA	TAG 257
33669	BCR12AM-4	200V, 12A(Tc101°), Igt<30mA	TAG 257
33670	BCR12AM-4	200V, 12A(Tc101°), Igt<30mA	TAG 257
33671	BCR12AM-6	300V, 12A(Tc101°), Igt<30mA	TAG 257
33672	BCR12AM-6	300V, 12A(Tc101°), Igt<30mA	TAG 257
33673	BCR12AM-8	400V, 12A(Tc101°), Igt<30mA	TAG 257
33674	BCR12AM-8	400V, 12A(Tc101°), Igt<30mA	TAG 257
33675	BCR12CM-4..-12	BCR 12AM-4..-12, 12A(Tc98°)	TAG 257
33676	BCR12DM-4..-12	BCR 12AM-4..-12, 12A(Tc84°)	TAG 257
33677	BCR12EM-4..-12	BCR 12AM-4..-12, 12A(Tc77°)	TAG 257
33678	BCR133	Rbe10kOhm	KSR 1102, 2SC3398
33679	BCR135	Rbe47kOhm	KSR 1106, 2SC4047
33680	BCR141	Rbe22kOhm	KSR 1103, 2SC3396
33681	BCR142	Rbe47kOhm	KSR 1107
33682	BCR146	Rbe22kOhm	KSR 1108, 2SC3397
33683	BCR148	Rbe47kOhm	KSR 1104, 2SC3395
33684	BCR16A-10	500V, 16A(Tc99°), Igt<30mA	-
33685	BCR16A-4	200V, 16A(Tc99°), Igt<30mA	-
33686	BCR16A-6	300V, 16A(Tc99°), Igt<30mA	-
33687	BCR16A-8	400V, 16A(Tc99°), Igt<30mA	-
33688	BCR16B-4..-10	BCR 16A-4..-10	-
33689	BCR16C-4..-10	BCR 16A-4..-10	-
33690	BCR16CM-12	BCR 16A-4..-10, 600V	-
33691	BCR16CM-4..-10	BCR 16A-4..-10	-
33692	BCR16DM-12	16A(Tc79°)	-
33693	BCR16DM-4..-10	BCR 16A-4..-10, 16A(Tc79°)	-
33694	BCR16E-4..-10	BCR 16A-4..-10	-
33695	BCR16HM-4..-10	BCR 16A-4..-10, 16A(Tc82°)	-
33696	BCR183	Rbe10kOhm	KSR 2102, 2SA1344
33697	BCR185	Rbe47kOhm	KSR 2106, 2SA1563
33698	BCR191	Rbe22kOhm	KSR 2103, 2SA1342
33699	BCR192	Rbe47kOhm	KSR 2107
33700	BCR198	Rbe47kOhm	KSR 2104, 2SA1341
33701	BCR1AM-10	500V, 1A(Tc56°), Igt<10mA	ZO 104, ZO 101, ZO 106, TAG 204, TAG 205
33702	BCR1AM-12	600V, 1A(Tc56°), Igt<10mA	ZO 104, ZO 101, ZO 106, TAG 204, TAG 205
33703	BCR1AM-4	200V, 1A(Tc56°), Igt<10mA	ZO 104, ZO 101, ZO 106, TAG 204, TAG 205
33704	BCR1AM-6	300V, 1A(Tc56°), Igt<10mA	ZO 104, ZO 101, ZO 106, TAG 204, TAG 205

33705	BCR1AM-8	400V, 1A(Tc56°), Igt<10mA	ZO 104, ZO 101, ZO 106, TAG 204, TAG 205
33706	BCR20A-10	500V, 20A(Tc98°), Igt<30mA	-
33707	BCR20A-4	200V, 20A(Tc98°), Igt<30mA	-
33708	BCR20A-6	300V, 20A(Tc98°), Igt<30mA	-
33709	BCR20A-8	400V, 20A(Tc98°), Igt<30mA	-
33710	BCR20B-4..-10	BCR 20A-4..-10	-
33711	BCR20C-4..-10	BCR 20A-4..-10	-
33712	BCR20E-4..-10	BCR 20A-4..-10	-
33713	BCR25A-10	500V, 25A(Tc92°), Igt<75mA	-
33714	BCR25A-4	200V, 25A(Tc92°), Igt<75mA	-
33715	BCR25A-6	300V, 25A(Tc92°), Igt<75mA	-
33716	BCR25A-8	400V, 25A(Tc92°), Igt<75mA	-
33717	BCR25B-4..-10	BCR 25A-4..-10	-
33718	BCR30GM-10	500V, 30A(Tc60°), Igt<50mA	-
33719	BCR30GM-4	200V, 30A(Tc60°), Igt<50mA	-
33720	BCR30GM-6	300V, 30A(Tc60°), Igt<50mA	-
33721	BCR30GM-8	400V, 30A(Tc60°), Igt<50mA	-
33722	BCR3AM-10	500V, 3A(Tc71°), Igt<30mA	T 2323, ZO 410, T 2322, ZO 409
33723	BCR3AM-12	600V, 3A(Tc71°), Igt<30mA	T 2323, ZO 410, T 2322, ZO 409
33724	BCR3AM-4	200V, 3A(Tc71°), Igt<30mA	T 2323, ZO 410, T 2322, ZO 409
33725	BCR3AM-8	400V, 3A(Tc71°), Igt<30mA	T 2323, ZO 410, T 2322, ZO 409
33726	BCR6AM-10	500V, 6A(Tc103°), Igt<30mA	TAG 220, TAG 225, TAG 252, TAG 250
33727	BCR6AM-12	600V, 6A(Tc103°), Igt<30mA	TAG 220, TAG 225, TAG 252, TAG 250
33728	BCR6AM-4	200V, 6A(Tc103°), Igt<30mA	TAG 220, TAG 225, TAG 252, TAG 250
33729	BCR6AM-6	300V, 6A(Tc103°), Igt<30mA	TAG 220, TAG 225, TAG 252, TAG 250
33730	BCR6AM-8	400V, 6A(Tc103°), Igt<30mA	TAG 220, TAG 225, TAG 252, TAG 250
33731	BCR8A-10	500V, 8A(Tc92°), Igt<50mA	MAC 222, TIC 226, T 2802, BS 9-A
33732	BCR8A-4	200V, 8A(Tc92°), Igt<50mA	MAC 222, TIC 226, T 2802, BS 9-A
33733	BCR8A-6	300V, 8A(Tc92°), Igt<50mA	MAC 222, TIC 226, T 2802, BS 9-A
33734	BCR8A-8	400V, 8A(Tc92°), Igt<50mA	MAC 222, TIC 226, T 2802, BS 9-A
33735	BCR8CM-10	500V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33736	BCR8CM-12	600V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33737	BCR8CM-12	600V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33738	BCR8CM-4	200V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33739	BCR8CM-6	300V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33740	BCR8CM-8	400V, 8A(Tc105°), Igt<30mA	BTA 21, BT 158, T 2806, BT 162
33741	BCR8DM-..	BCR 8CM-.., 8A(Tc94°)	BTA 21, BT 158, T 2806, BT 162
33742	BCV26	40V, 0,5A, 200MHz, B>20000	BCV 46
33743	BCV27	40V, 0,5A, 200MHz, B>20000	BCV 47
33744	BCV28	BCV 26	BST 60...62, 2SB1048
33745	BCV29	BCV 27	BST 50...52, 2SD1470, 2SD1511
33746	BCV46	BCV 26, 80V	-
33747	BCV47	BCV 27, 80V	-
33748	BCV48	BCV 46	BST 61...62
33749	BCV49	BCV 47	BST 51...52

33750	BCV61	50V, 0,1A, 300MHz	-
33751	BCV62	50V, 0,1A, 150MHz	-
33752	BCV63		-
33753	BCV64		-
33754	BCV71	80V, 0,1A, 300MHz, B110..220	BC 846, 2SC3324
33755	BCV71R	BCV 71	BC 846R
33756	BCV72	BCV 71, B200..450	BC 846, 2SC3324
33757	BCV72R	BCV 72	BC 846R
33758	BCW10	25V, 0,5A, 0,3W, >150MHz	BC 337...338, BC 635, BC 637, BC 639
33759	BCW11	25V, 0,5A, 0,3W, >150MHz	BC 327...328, BC 636, BC 638, BC 640
33760	BCW12	BCW 10, 35V	BC 337, BC 635, BC 637, BC 639
33761	BCW13	BCW 11, 35V	BC 327, BC 636, BC 638, BC 640
33762	BCW14	BCW 10, 35V	BC 337, BC 635, BC 637, BC 639
33763	BCW15	BCW 11, 35V	BC 327, BC 636, BC 638, BC 640
33764	BCW16	BCW 10, 45V	BC 337, BC 635, BC 637, BC 639
33765	BCW17	BCW 11, 45V	BC 327, BC 636, BC 638, BC 640
33766	BCW18	BCW 10, 70V	BC 639, 2SD667
33767	BCW19	BCW 11, 70V	BC 640, 2SB647
33768	BCW20	30V, 0,3W, >30MHz	BC 109, BC 184, BC 239, BC 549
33769	BCW21	30V, 0,3W, >30MHz	BC 214, BC 259, BC 309, BC 559
33770	BCW22	BCW 20, 45V	BC 184, BC 413...414, BC 550
33771	BCW23	BCW 20, 45V	BC 214, BC 415...416, BC 560
33772	BCW24	45V, 30mA, 0,3W, >30MHz	BC 184, BC 413...414, BC 550
33773	BCW27	150V, 0,1A, 0,625W	BF 422, BF 398, BF 435...437, 2SA1019
33774	BCW28	100V, 0,1A, 0,625W	BF 422, BF 398, BF 435...437, 2SA1019
33775	BCW29	30V, 0,1A, 150MHz, B>120	BC 856...858, BCW 69...70, BCW 89
33776	BCW29R	BCW 29	BC 856R...858R, BCW 69R...70R, BCW 89R
33777	BCW30	BCW 29, B>215	BC 856...858, BCW 69...70, BCW 89
33778	BCW30R	BCW 30	BC 856R...858R, BCW 69R...70R, BCW 89R
33779	BCW31	30V, 0,1A, 300MHz, B>110	BC 846...848, BCW 71...72, BCW 81
33780	BCW31R	BCW 31	BC 846R...848R, BCW 71R...72R, BCW 81R
33781	BCW32	BCW 31, B>200	BC 846...848, BCW 71...72, BCW 81
33782	BCW32R	BCW 32	BC 846R...848R, BCW 71R...72R, BCW 81R
33783	BCW33	BCW 31, B>420	BC 846...848, BCW 71...72, BCW 81
33784	BCW33R	BCW 33	BC 846R...848R, BCW 71R...72R, BCW 81R
33785	BCW34	60V, 0,6A, 0,36W, >150MHz	BC 637, BC 639, BCX 22, BCX 24
33786	BCW35	60V, 0,6A, 0,36W, >150MHz	BC 638, BC 640, BCX 23, BCX 39
33787	BCW36	BCW 34, 0,3W	BCW 34
33788	BCW37	BCW 35, 0,3W	BCW 35
33789	BCW38	60V, 0,6A, 0,625W, >200MHz	BC 637, BC 639, 2N3700...3701, 2SD667
33790	BCW39	BCW 38, >250MHz	BC 637, BC 639, 2N3700...3701, 2SD667
33791	BCW44	70V, 1A, 0,8W, 80MHz	BC 140...141, BCX 40, 2N1990, 2N2102
33792	BCW45	70V, 1A, 0,8W, 200MHz	BC 161, BCX 60, 2N4235...4236
33793	BCW46	BCW 48, 80V	BC 174, BC 190, BC 546, 2SC1890
33794	BCW47	BCW 48, 50V	BC 167, BC 182, BC 237, BC 547

33795	BCW48	30V, 0,1A, 0,2W, 300MHz	BC 168, BC 183, BC 238, BC 548
33796	BCW49	BCW 48	BC 169, BC 184, BC 239, BC 549
33797	BCW50	120V, 0,5W, >50MHz	BF 297...299, 2SC1890A, 2SC2240
33798	BCW51	50V, 0,2A, 0,3W, >200MHz	BC 167, BC 182, BC 237, BC 547
33799	BCW52	50V, 0,2A, 0,3W, >200MHz	BC 212, BC 257, BC 307, BC 557
33800	BCW54	$\beta > 125$	BC 174, BC 190, BC 546, 2SC1890
33801	BCW55	BCW 54, $\beta > 240$	BC 174, BC 190, BC 546, 2SC1890
33802	BCW56	BCW 58, 80V	BC 556, BC 477, 2SA893, 2SB715
33803	BCW57	BCW 58, 50V	BC 212, BC 257, BC 307, BC 557
33804	BCW58	30V, 0,1A, 0,2W, 150MHz	BC 213, BC 258, BC 308, BC 558
33805	BCW59	BCW 58	BC 214, BC 259, BC 309, BC 559
33806	BCW60	32V, 0,2A, 250MHz	BC 846...848, BCW 31...33, BCX 70
33807	BCW60R	BCW 60	BC 846R...848R, BCW 31R...33R, BCX 70R
33808	BCW61	32V, 0,2A, 180MHz	BC 856...858, BCW 29...30, BCX 71
33809	BCW61R	BCW 61	BC 856R...858R, BCW 29R...30R, BCX 71R
33810	BCW62	BCW 63, 60V	BC 212, BC 256, BC 266, BC 556
33811	BCW63	45V, 0,2A, 0,225W, >200MHz	BC 213, BC 257, BC 307, BC 557
33812	BCW64	BCW 63	BC 214, BC 415...416, BC 560
33813	BCW65	60V, 0,8A, >100MHz	BCX 41
33814	BCW65R	BCW 65	BCX 41R
33815	BCW66	BCW 65, 75V	BCX 41
33816	BCW66R	BCW 66	BCX 41R
33817	BCW67	45V, 0,8A, >100MHz	BCX 42
33818	BCW67R	BCW 67	BCX 42R
33819	BCW68	BCW 67, 60V	BCX 42
33820	BCW68R	BCW 68	BCX 42R
33821	BCW69	50V, 0,1A, 150MHz, $B > 120$	BC 856...857, BCW 89
33822	BCW69R	BCW 69	BC 856R...857R, BCW 89R
33823	BCW70	BCW 69, $B > 215$	BC 856...857, BCW 89
33824	BCW70R	BCW 70	BC 856R...857R, BCW 89R
33825	BCW71	50V, 0,1A, 300MHz, $B > 110$	BC 846...847, BCV 71...72
33826	BCW71R	BCW 71	BC 846R...847R, BCV 71R...72R
33827	BCW72	BCW 71, $B > 200$	BC 846...847, BCV 71...72
33828	BCW72R	BCW 72	BC 846R...847R, BCV 71R...72R
33829	BCW73	60V, 0,8A, 0,45W, >100MHz	BC 637, BC 639, BCX 73, 2N2221...2222
33830	BCW74	BCW 73, 75V	BC 639, BCX 74, 2N2221A...2222A
33831	BCW75	45V, 0,8A, 0,45W, >100MHz	BC 638, BC 640, BCX 75, 2N2906...2907
33832	BCW76	BCW 75, 60V	BC 640, BCX 76, 2N2906A...2907A
33833	BCW77	BCW 73, 0,87W	BC 140...141, 2N2218...2219
33834	BCW78	BCW 74, 0,87W	BC 140...141, 2N2218A...2219A
33835	BCW79	BCW 75, 0,87W	BC 161, 2N2904...2905
33836	BCW80	BCW 76, 0,87W	BC 161, 2N2904A...2905A
33837	BCW81	BCW 71, $B > 420$	BC 846...847, BCV 71...72
33838	BCW81R	BCW 81	BC 846R...847R, BCV 71R...72R
33839	BCW82	BCW 83, 60V	BC 182, BC 174, BC 190, BC 546

33840	BCW83	45V, 0,2A, 0,225W, >150MHz	BC 167, BC 183, BC 237, BC 547
33841	BCW84	BCW 83	BC 184, BC 413...414, BC 550
33842	BCW85	90V, 0,2A, 0,3W, >200MHz	BC 477, BC 556
33843	BCW86	BCW 85, 70V	BC 477, BC 556, 2N2221A...2222A
33844	BCW87	45V, 0,1A, 0,225W, >125MHz	BC 167, BC 183, BC 237, BC 547
33845	BCW88	45V, 0,1A, 0,225W, >180MHz	BC 213, BC 257, BC 307, BC 557
33846	BCW89	BCW 69, 80V	BC 856, 2SA1312, 2SA1325
33847	BCW89R	BCW 89	BC 856R
33848	BCW90	50V, 0,8A, 0,61W, >135MHz	BC 337, BC 637, BC 639, 2N2221...2222
33849	BCW90K	BCW 90, 0,8W	BCW 90
33850	BCW90K	BCW 90, 0,8W	BCW 90
33851	BCW91	BCW 90, 70V	BC 639, 2N2221A...2222A
33852	BCW91K	BCW 91, 0,8W	BCW 91
33853	BCW91K	BCW 91, 0,8W	BCW 91
33854	BCW92	50V, 0,8A, 0,61W, >135MHz	BC 327, BC 638, BC 640, 2N2906...2907
33855	BCW92K	BCW 92, 0,8W	BCW 92
33856	BCW92K	BCW 92, 0,8W	BCW 92
33857	BCW93	BCW 92, 70V	BC 640, 2N2906A...2907A
33858	BCW93K	BCW 93, 0,8W	BCW 93
33859	BCW93K	BCW 93, 0,8W	BCW 93
33860	BCW94	50V, 0,4A, 0,54W, 70MHz	BC 337, BC 637, BC 639, 2N2221...2222
33861	BCW94K	BCW 94, 0,7W	BCW 94
33862	BCW94K	BCW 94, 0,7W	BCW 94
33863	BCW95	BCW 94, 70V	BC 639, 2N2221A...2222A
33864	BCW95K	BCW 95, 0,7W	BCW 95
33865	BCW95K	BCW 95, 0,7W	BCW 95
33866	BCW96	50V, 0,4A, 0,54W, 70MHz	BC 327, BC 638, BC 640, 2N2906...2907
33867	BCW96K	BCW 96, 0,7W	BCW 96
33868	BCW96K	BCW 96, 0,7W	BCW 96
33869	BCW97	BCW 96, 70V	BC 640, 2N2906A...2907A
33870	BCW97K	BCW 97, 0,7W	BCW 97
33871	BCW97K	BCW 97, 0,7W	BCW 97
33872	BCW98	45V, 0,1A, 0,05W, >125MHz	BC 123
33873	BCW99	45V, 0,1A, 0,05W, 200MHz	BC 203
33874	BCX10	50V, 0,6A, 0,6W, 90MHz	BC 161, BC 303...304, BCX 60, BSV 16...17
33875	BCX12	125V, 0,8A, 0,625W, 100MHz	2SC4488, 2SD1312, 2SD1616A, 2SD1857
33876	BCX13	125V, 0,8A, 0,625W, 120MHz	2SA1708, 2SB984, 2SB1236, 2SB1456
33877	BCX17	50V, 0,5A, 100MHz	BC 807, BCW 68, BCX 42, 2SA1366
33878	BCX17R	BCX 17	BC 807R, BCW 68R, BCX 42R
33879	BCX18	BCX 17, 30V	BC 807...808, BCW 67...68, 2SA1366
33880	BCX18R	BCX 18	BC 807R...808R, BCW 67R...68R
33881	BCX19	50V, 0,5A, 200MHz	BC 817, BCW 65...66, BCX 41, 2SC3441
33882	BCX19R	BCX 19	BC 817R, BCW 65R...66R, BCX 41R
33883	BCX20	BCX 19, 30V	BC 817...818, BCW 65...66, 2SC3441
33884	BCX20R	BCX 20	BC 817R...818R, BCW 65R...66R



33885	BCX21	B>2000	BSS 50...52, 2SD614...615, 2SD688
33886	BCX22	125V, 0,8A, 0,45W, 100MHz	2N3700...3701, 2SC2235, 2SD667
33887	BCX23	125V, 0,8A, 0,45W, 100MHz	2N5400...5401, 2SA965, 2SB647
33888	BCX24	100V, 0,8A, 0,45W, 100MHz	BC 639, 2N3700...3701, 2SC2235, 2SD667
33889	BCX25	60V, 0,2A, 0,35W, >100MHz	BC 174, BC 182, BC 190, BC 546
33890	BCX26	60V, 0,2A, 0,35W, >100MHz	BC 212, BC 256, BC 266, BC 556
33891	BCX27	BCX 25, 80V	BC 546, 2SC2240, 2SC2459, 2SC3245
33892	BCX28	BCX 26, 80V	BC 556, 2SA970, 2SA1049, 2SA1285
33893	BCX29	BCX 25, 100V	2SC2240, 2SC2459, 2SC3245
33894	BCX30	BCX 26, 100V	2SA970, 2SA1049, 2SA1285
33895	BCX31	100V, 0,5A, 0,83W, >80MHz	BC 639, 2N3700...3701, 2SD667
33896	BCX32	80V, 1A, 0,83W, >80MHz	BC 639, 2N3700...3701, 2SD667
33897	BCX33	BCX 32, 60V	BC 637, BC 639, 2N3700...3701, 2SD667
33898	BCX34	BCX 32, 40V	BC 635, BC 637, BC 639, 2SD667
33899	BCX35	80V, 0,6A, 0,83W, >80MHz	BC 640, 2SA1013, 2SA1315, 2SB647
33900	BCX36	BCX 35, 60V	BC 638, BC 640, 2SA1315, 2SB647
33901	BCX37	BCX 35, 40V	BC 636, BC 638, BC 640, 2SB647
33902	BCX38	80V, 0,8A, 1W, B>500	BC 877, BC 879, BSR 51...52
33903	BCX39	100V, 0,8A, 0,45W, 100MHz	BC 640, 2SB647, 2SA1013
33904	BCX40	100V, 2A, 1W, >50MHz	BSS 15, 2N4239, 2N5320, 2SC2214
33905	BCX41	125V, 0,8A, 100MHz	-
33906	BCX41R	BCX 41	-
33907	BCX42	125V, 0,8A, 100MHz	-
33908	BCX42R	BCX 42	-
33909	BCX43	150V, 1A	-
33910	BCX44	90V, 0,5A	-
33911	BCX45	45V, 1A, 0,625W, >100MHz	BC 635, BC 637, BC 639
33912	BCX46	45V, 1A, 0,625W, >60MHz	BC 636, BC 638, BC 640
33913	BCX47	BCX 45, 60V	BC 637, BC 639, 2SD667
33914	BCX48	BCX 46, 60V	BC 638, BC 640, 2SB647
33915	BCX49	BCX 45, 80V	BC 639, 2SD667, 2N3700...3701
33916	BCX50	BCX 46, 80V	BC 640, 2SB647, 2SA1013
33917	BCX51	45V, 1A, 50MHz	2SA1364, 2SB804
33918	BCX52	BCX 51, 60V	2SA1364, 2SB804
33919	BCX53	BCX 51, 100V	2SB804, 2SB1025
33920	BCX54	45V, 1A, 130MHz	2SC3444, 2SD1005
33921	BCX55	BCX 54, 60V	2SC3444, 2SD1005
33922	BCX56	BCX 54, 100V	2SD1005, 2SD1418
33923	BCX58	32V, 0,1A, 0,45W, 250MHz	BC 183, BC 237, BC 547, 2N2221...2222
33924	BCX59	BCX 58, 45V	BC 182, BC 237, BC 547, 2N2221...2222
33925	BCX59	BCX 58, 45V	BC 182, BC 237, BC 547, 2N2221...2222
33926	BCX60	100V, 2A, 1W, >50MHz	BSS 17, 2N5322
33927	BCX68	25V, 1A, 65MHz	BC 868, BCX 54...56, 2SC3439, 2SC3444
33928	BCX69	25V, 1A, 65MHz	BC 869, BCX 51...53, 2SA1364, 2SA1369
33929	BCX70	BCW 60, 45V	BC 846...847, BCW 71...72, BCW 81

33930	BCX70R	BCX 70	BC 846R...847R, BCW 71R...72R, BCW 81R
33931	BCX71	BCW 61, 45V	BC 856...857, BCW 69...70, BCW 89
33932	BCX71R	BCX 71	BC 856R...857R, BCW 69R...70R, BCW 89R
33933	BCX73	60V, 0,8A, 0,625W, >100MHz	BC 637, BC 639, 2N2221...2222
33934	BCX74	BCX 73, 75V	BC 639, 2N2221A...2222A
33935	BCX75	60V, 0,8A, 0,625W, > 100MHz	BC 638, BC 640, 2N2906...2907
33936	BCX76	BCX 75, 75V	BC 640, 2N2906A...2907A
33937	BCX78	32V, 0,1A, 0,45W, 200MHz	BC 213, BC 307, BC 557, 2N2906...2907
33938	BCX79	BCX 78, 45V	BC 213, BC 307, BC 557, 2N2906...2907
33939	BCX80	50V, 0,75A, 0,5W, >120MHz	BC 337, BC 637, BC 639
33940	BCX81	50V, 0,75A, 0,5W, >120MHz	BC 327, BC 638, BC 640
33941	BCX82	100V, 0,1A, >75MHz, B>250	2SC2240, 2SC2459
33942	BCX83	BCX 82, B>600	2SC2240, 2SC2459
33943	BCX84	60V, 0,5A, 0,5W, >60MHz	BC 638, BC 640, 2SB647
33944	BCX85	60V, 0,5A, 0,5W, >80MHz	BC 637, BC 639, 2SD667
33945	BCX86	B>2000	BC 517, BC 875, BC 877, BC 879
33946	BCX87	B>2000	BC 516, BC 876, BC 878, BC 880
33947	BCX88	BCX 86, B>87000	BC 517, BC 875, BC 877, BC 879
33948	BCX89	BCX 87, B>40000	BC 516, BC 876, BC 878, BC 880
33949	BCX94	100V, 0,8A, 0,45W, 100MHz	BC 639, 2N3700...3701, 2SD667
33950	BCY10	B15	BC 327, BC 636, BC 638, BC 640
33951	BCY11	BCY 10, 60V	BC 638, BC 640, 2N2906A...2907A
33952	BCY12	BCY 10, 60V, B25	BC 638, BC 640, 2N2906A...2907A
33953	BCY13	60V, 0,2A, 0,45W, 0,4MHz	BC 140...141, BC 637, BC 639
33954	BCY14	BCY 14, 100V	BC 141, BC 639, 2SD667
33955	BCY15	BCY 13, 0,3A	BC 140...141, BC 637, BC 639
33956	BCY16	BCY 13, 100V, 0,3A	BC 141, BC 639, 2SD667
33957	BCY17	30V, 0,05A, 0,35W, 1,2MHz	BC 213, BC 257, BC 307, BC 557
33958	BCY18	30V, 0,05A, 0,35W, 2MHz	BC 213, BC 257, BC 307, BC 557
33959	BCY19	50V, 0,05A, 0,35W, 0,8MHz	BC 212, BC 257, BC 307, BC 557
33960	BCY20	100V, 0,05A, 0,35W, 0,5MHz	2N5400...5401, 2SB715...716
33961	BCY21	50V, 0,05A, 0,35W, 0,5MHz	BC 212, BC 257, BC 307, BC 557
33962	BCY22	75V, 0,05A, 0,35W, 0,5MHz	BC 256, BC 266, BC 556
33963	BCY23	30V, 0,05A, 0,35W, 1,5MHz	BC 213, BC 258, BC 308, BC 558
33964	BCY24	30V, 0,05A, 0,35W, 1MHz	BC 213, BC 258, BC 308, BC 558
33965	BCY25	30V, 0,05A, 0,35W, 2,5MHz	BC 213, BC 258, BC 308, BC 558
33966	BCY26	30V, 0,05A, 0,35W, 0,6MHz	BC 213, BC 258, BC 308, BC 558
33967	BCY27	30V, 0,05A, 0,275W, 1MHz	BC 213, BC 258, BC 308, BC 558
33968	BCY28	30V, 0,05A, 0,275W, 1,5MHz	BC 213, BC 258, BC 308, BC 558
33969	BCY29	60V, 0,05A, 0,275W, 0,5MHz	BC 212, BC 256, BC 266, BC 556
33970	BCY30	64V, 0,05A, 0,25W, 1,2MHz	BC 212, BC 256, BC 266, BC 556
33971	BCY30A	BCY 30, 0,1A, 0,6W, 7MHz	BC 212, BC 256, BC 266, BC 556
33972	BCY31	64V, 0,05A, 0,25W, 1,7MHz	BC 212, BC 256, BC 266, BC 556
33973	BCY31A	BCY 31, 0,1A, 0,6W, 7MHz	BC 212, BC 256, BC 266, BC 556
33974	BCY32	64V, 0,05A, 0,25W, 2,5MHz	BC 212, BC 256, BC 266, BC 556

33975	BCY32A	BCY 32, 0,1A, 0,6W, 7MHz	BC 212, BC 256, BC 266, BC 556
33976	BCY33	32V, 0,05A, 0,25W, 1,5MHz	BC 213, BC 258, BC 308, BC 558
33977	BCY33A	BCY 33, 0,1A, 0,6W, 7MHz	BC 213, BC 258, BC 308, BC 558
33978	BCY34	32V, 0,05A, 0,25W, 2,4MHz	BC 213, BC 258, BC 308, BC 558
33979	BCY34A	BCY 34, 0,1A, 0,6W, 7MHz	BC 213, BC 258, BC 308, BC 558
33980	BCY38	32V, 0,25A, 0,35W, 1,5MHz	BC 328, BC 636, BC 638, BC 640
33981	BCY39	64V, 0,25A, 0,35W, 1,5MHz	BC 638, BC 640, 2N2904...2905
33982	BCY40	64V, 0,25A, 0,35W, 2,5MHz	BC 638, BC 640, 2N2904...2905
33983	BCY42(P)	B>45	BC 167, BC 183, BC 237, BC 547
33984	BCY43(P)	BCY 42, B>75	BC 167, BC 183, BC 237, BC 547
33985	BCY49	15V, 20mA, 0,25W	-
33986	BCY50(r,i)	10V, 0,1A, 0,3W, >60MHz	BC 169, BC 184, BC 239, BC 549
33987	BCY51(r,i)	BCY 50, 30V, >50MHz	BC 169, BC 184, BC 239, BC 549
33988	BCY54	50V, 0,25A, 0,35W, 2MHz	BC 327, BC 638, BC 640, 2N2904...2905
33989	BCY56	45V, 0,1A, 0,3W, 250MHz	BC 184, BC 413...414, BC 550
33990	BCY57	BCY 56, 25V, 350MHz	BC 169, BC 184, BC 239, BC 549
33991	BCY58	32V, 0,2A, 0,39W, 250MHz	BC 183, BC 548, BCX 58, 2N2221...2222
33992	BCY58P	BCY 58	BCY 58
33993	BCY59	BCY 58, 45V	BC 182, BC 547, BCX 59, 2N2221...2222
33994	BCY59P	BCY 59	BCY 59
33995	BCY65	60V, 0,1A, 250MHz	BC 182, BC 546, 2N2221...2222
33996	BCY65P	BCY 65	BCY 65
33997	BCY66	45V, 0,05A, 250MHz	BC 184, BC 413...414, BC 550
33998	BCY67	45V, 0,05A, 180MHz	BC 214, BC 415...416, BC 560
33999	BCY69	20V, 0,1A, 0,3W, >150MHz	BC 168, BC 183, BC 238, BC 548
34000	BCY70(P)	50V, 0,2A, 0,35W, 450MHz	BCX 79, BCY 79, 2N2906...2907
34001	BCY71(A,AP)	BCY 70, 45V	BC 214, BC 415...416, BC 560
34002	BCY72(P)	BCY 70, 30V	BCX 78, BCY 78, 2N2906...2907
34003	BCY76	45V, 0,1A, 0,3W, 40MHz	BC 167, BC 182, BC 237, BC 547
34004	BCY77	60V, 0,1A, 0,35W, 180MHz	BC 212, BC 556, 2N2906A...2907A
34005	BCY77P	BCY 77	BCY 77
34006	BCY78	BCY 77, 32V	BC 213, BC 558, BCX 78, 2N2906...2907
34007	BCY78P	BCY 78	BCY 78
34008	BCY79	BCY 77, 45V	BC 213, BC 557, BCX 79, 2N2906...2907
34009	BCY79P	BCY 79	BCY 79
34010	BCY85	100V, 0,2A, 0,3W, >200MHz	2SC2240, 2SC2459, 2SC3245
34011	BCY86	BCY 85, 80V	BC 546, 2SC2240, 2SC2459, 2SC3245
34012	BCY90(B)	40V, 0,05A, 0,35W, 15MHz	BC 212, BC 257, BC 307, BC 557
34013	BCY91(B)	40V, 0,05A, 0,35W, 15MHz	BC 212, BC 257, BC 307, BC 557
34014	BCY92(B)	40V, 0,05A, 0,35W, 15MHz	BC 212, BC 257, BC 307, BC 557
34015	BCY93(B)	70V, 0,05A, 0,35W, 15MHz	BC 212, BC 256, BC 266, BC 556
34016	BCY94(B)	70V, 0,05A, 0,35W, 15MHz	BC 212, BC 256, BC 266, BC 556
34017	BCY95(B)	70V, 0,05A, 0,35W, 15MHz	BC 212, BC 256, BC 266, BC 556
34018	BCY96(B)	90V, 0,05A, 0,35W, 15MHz	BC 556, 2SA893, 2SA1016, 2SA1038
34019	BCY97(B)	90V, 0,05A, 0,35W, 15MHz	BC 556, 2SA893, 2SA1016, 2SA1038

34020	BCY98(B)	40V, 0,05A, 0,35W, 15MHz	BC 213, BC 257, BC 307, BC 557
34021	BCY99(B)	70V, 0,05A, 0,35W, 15MHz	BC 212, BC 256, BC 266, BC 556
34022	BCZ10	25V, 0,05A, 0,21W, $\beta > 15$	BC 213, BC 258, BC 308, BC 558
34023	BCZ11	BCZ 10, $\beta > 25$	BC 213, BC 258, BC 308, BC 558
34024	BCZ12	BCZ 10, 60V, $\beta 15$	BC 212, BC 256, BC 266, BC 556
34025	BCZ13	20V, 10mA, 85mW, $\beta > 15$	BC 213, BC 258, BC 308, BC 558
34026	BCZ14	BCZ 13, $\beta > 30$	BC 213, BC 258, BC 308, BC 558
34027	BD	BCP 54-16	BCP 54-16
34028	BD	P4 SMA-18	P4 SMA-18
34029	BD	1SS271	1SS271
34030	BD	BCX 54-16	BCX 54-16
34031	BD	2SB1189	2SB1189
34032	BD	2SB1121	2SB1121
34033	BD(p,s)	BCW 61D	BCW 61D
34034	BD106	36V, 2,5A, 11,5W, 100MHz	BDW 25, BDX 25, 2SC1398, 2SC3252
34035	BD107	BD 106, 64V	BDW 25, BDX 25, 2SC1398, 2SC3252
34036	BD109	60V, 3A, 18,5W, $> 30\text{MHz}$	BDW 25, BDX 25, 2SC3252...3253
34037	BD111	60V, 10A, 15W( $T_c 75^\circ$ )	BD 245, BDY 90...92, 2N3055, 2SC3256
34038	BD111A	BD 111, 62,5W	BD 245, BDY 90...92, 2N3055, 2SC3256
34039	BD112	80V, 2A, 15W( $T_c 75^\circ$ ), $> 30\text{MHz}$	BD 245B, BDY 90...92, 2N3055, 2SC3256
34040	BD113	$> 60\text{MHz}$	BD 245, BDY 90...92, 2N3055, 2SC3256
34041	BD115	245V, 0,15A, 0,8W, 145MHz	BF 381, BF 615, BFR 58...59, MPSU 10
34042	BD116	80V, 3A, 15W( $T_c 75^\circ$ ), $> 30\text{MHz}$	BD 245B, BDY 90...92, 2N3055, 2SC3256
34043	BD117	100V, 5A, 30W( $T_c 50^\circ$ ), 50MHz	BD 245C, BDY 90...91, 2N3055, 2SC2681
34044	BD118	80V, 15W( $T_c 75^\circ$ ), $> 30\text{MHz}$	BD 245B, BDY 90...92, 2N3055, 2SC3256
34045	BD119	300V, 0,4A, 6W( $T_c 75^\circ$ )	2SC782, 2SC1929, 2SC2022, 2SC2354
34046	BD120	150V, 0,15A, 7,5W( $T_c 75^\circ$ )	2SC1505...1507, 2SC1755...1757, 2SC1905
34047	BD121	60V, 5A, 45W, 85MHz	BD 245A, BDY 90...92, 2N3055, 2SC3256
34048	BD123	BD 121, 90V	BD 245C, BDY 90...91, 2N3055, 2SC2681
34049	BD124(A)	120MHz	BDW 25, BDX 25, 2SC1398, 2SC3252
34050	BD127	300V, 0,5A, 17,5W( $T_c 45^\circ$ )	BF 758, MJE 340, 2SC2899, 2SC3051
34051	BD127..129	, 0,25A, 16,5W	
34052	BD128	BD 127, 350V	BF 759, MJE 340, 2SC2899, 2SC3051
34053	BD129	BD 127, 400V	2SC2899, 2SC3051, 2SC3425
34054	BD130	2N3055	2N3055
34055	BD130Y	BD 130, 60V	2N3055
34056	BD131(A)	70V, 3A, 15W( $T_c 60^\circ$ ), $> 60\text{MHz}$	BD 237, BD 441, BD 787, BD 789
34057	BD132(A)	45V, 3A, 15W( $T_c 60^\circ$ ), $> 60\text{MHz}$	BD 238, BD 440, BD 786, BD 788
34058	BD133	BD 131, 90V	BD 237, BD 443, BD 791, BDX 35...37
34059	BD134	BD 238	BD 238
34060	BD135(H)	$> 50\text{MHz}$	BD 226, BD 375, BD 785
34061	BD135G	BD 135	2SC1848, 2SC2483
34062	BD136(H)	$> 50\text{MHz}$	BD 227, BD 376, BD 786
34063	BD136G	BD 136	2SA887, 2SA1195
34064	BD137(H)	BD 135, 60V	BD 228, BD 377, BD 785

34065	BD137G	BD 137	2SC1848, 2SC2483
34066	BD138(H)	BD 136, 60V	BD 229, BD 378, BD 786
34067	BD138G	BD 138	2SA887, 2SA1195
34068	BD139(H)	BD 135, 100V	BD 230, BD 379, BD 791
34069	BD139G	BD 139	2SC2483
34070	BD140(H)	BD 136, 100V	BD 231, BD 380, BD 792
34071	BD140G	BD 140	2SA1195
34072	BD141	140V, 8A, 117W, >0,8MHz	BDX 11...12, BDX 51, 2N5634, 2SD551
34073	BD142	50V, 15A, 117W, 1,3MHz	BDW 51, BDX 13, BDX 60...61, 2N3055
34074	BD144	12MHz	2SC1101, 2SC3151, 2SC3533
34075	BD145	100MHz	BU 104, BU 606...608
34076	BD148	60V, 4A, 31W(Tc45°), 1MHz	BD 243A...C, BD 543A...D, 2N3054
34077	BD149	BD 148, 80V	BD 243B...C, BD 543B...D, 2N3054
34078	BD150(A...C)	200..300V, 0,5A, 1W, 160MHz	BF 382, BF 758...759, MPSU 10
34079	BD151	35V, 1A, 20W	BD 136, BD 227, BD 376, BD 786
34080	BD152	BD 151, 50V	BD 138, BD 229, BD 378, BD 788
34081	BD153	35V, 1A, 20W	BD 135, BD 226, BD 375, BD 785
34082	BD154	BD 153, 50V	BD 137, BD 228, BD 375, BD 785
34083	BD1540	400/400V, 15A, 100W, 7MHz	BU 930...932, 2SD572...573, 2SD711
34084	BD155	BD 153, 70V	BD 139, BD 230, BD 377, BD 787
34085	BD1550	BD 1540, 500V	BU 932, 2SD572...573, 2SD683, 2SD711
34086	BD156	BD 151, 70V	BD 140, BD 231, BD 378, BD 790
34087	BD1560	BD 1540, 600/600V	2SD573, 2SD606, 2SD683, 2SD711A
34088	BD157	275V, 0,5A, 20W	BF 758...759, MJE 340, 2SC2899, 2SC3051
34089	BD158	BD 157, 325V	BF 759, MJE 340, 2SC2899, 2SC3051
34090	BD159	BD 157, 375V	BF 759, MJE 340, 2SC2899, 2SC3051
34091	BD160	250V, 5A, 25W	BU 104, BU 606...608
34092	BD161	90V, 4A, 19W(Tc85°), 1,75MHz	BD 243C, BD 543C...D, BD 953, 2N3054
34093	BD162	BD 161, 40V	BD 243, BD 543, BD 947, 2N3054
34094	BD163	BD 161, 60V	BD 243A...C, BD 543A...D, BD 949, 2N3054
34095	BD165	45V, 1,5A, 20W, >3MHz	BD 175, BD 226, BD 233, BD 437
34096	BD166	45V, 1,5A, 20W, >3MHz	BD 176, BD 227, BD 234, BD 438
34097	BD167	BD 165, 60V	BD 177, BD 228, BD 235, BD 439
34098	BD168	BD 166, 60V	BD 178, BD 229, BD 236, BD 440
34099	BD169	BD 165, 80V	BD 179, BD 230, BD 237, BD 441
34100	BD170	BD 166, 80V	BD 180, BD 231, BD 238, BD 442
34101	BD171	100V, 0,5A, 20W, 6MHz	BD 139, BD 237, MJE 340, 2SD1382
34102	BD172	BD 171, 130V	BD 524, MJE 340, 2SC2481, 2SC3117
34103	BD173	BD 171, 170V	BD 524, MJE 340, 2SC3117, 2SD669
34104	BD175	45V, 3A, 30W, >3MHz	BD 185, BD 437, BD 785, 2N5190...5192
34105	BD176	45V, 3A, 30W, >3MHz	BD 186, BD 438, BD 786, 2N5193...5195
34106	BD177	BD 175, 60V	BD 187, BD 439, BD 787, 2N5191...5192
34107	BD178	BD 176, 60V	BD 188, BD 440, BD 788, 2N5194...5195
34108	BD179	BD 175, 80V	BD 189, BD 441, BD 791, 2N5192
34109	BD180	BD 176, 80V	BD 190, BD 442, BD 792, 2N5195



34110	BD181	55V, 10A, 117W	BD 245, BD 311, BDY 39, 2N3055
34111	BD182	BD 181, 70V, 15A	BD 745A, BD 315, BDY 39, 2N3055
34112	BD183	BD 181, 85V, 15A	BD 745B, BD 317, BDY 39, 2N3055
34113	BD184	BD 181, 95V, 15A	BD 745C, BD 317, BDY 39, 2N3055
34114	BD185	40V, 4A, 40W, >2MHz	BD 437, BD 785, 2N5190
34115	BD186	40V, 4A, 40W, >2MHz	BD 438, BD 786, 2N5193
34116	BD187	BD 185, 55V	BD 439, BD 785, 2N5191
34117	BD188	BD 186, 55V	BD 440, BD 786, 2N5194
34118	BD189	BD 185, 70V	BD 441, BD 787, 2N5192
34119	BD190	BD 186, 70V	BD 442, BD 788, 2N5195
34120	BD191	100V, 15A, 37,5W, >0,8MHz	BD 743C, BD 911
34121	BD192	BD 191, 50V	BD 743A, BD 907
34122	BD193	BD 191, 140V, 8A	MJE 15030, 2SC4330, 2SD866
34123	BD195	40V, 6A, 65W, >2MHz	BD 205, MJE 3055, 2N5983, 2SD499
34124	BD196	40V, 6A, 65W, >2MHz	BD 206, MJE 2955, 2N5980, 2SB578
34125	BD197	BD 195, 55V	BD 205, MJE 3055, 2N5983, 2SD499
34126	BD198	BD 196, 55V	BD 206, MJE 2955, 2N5980, 2SB578
34127	BD199	BD 195, 70V	BD 207, MJE 3055, 2N5984, 2SD500
34128	BD200	BD 196, 70V	BD 208, MJE 2955, 2N5981, 2SB578
34129	BD201	60/45V, 8A, 60W, >7MHz	BD 243A, BD 543A, BD 707, BD 797
34130	BD201F	BD 201, , >20W	BDT 91F, BDX 77F, 2SD1411...12, 2SD1668
34131	BD202	60/45V, 8A, 60W, >7MHz	BD 244A, BD 544A, BD 708, BD 798
34132	BD202F	BD 202, , >20W	BDT 92F, BDX 78F, 2SB1018...19, 2SB1135
34133	BD203	BD 201, 60/60V	BD 243A, BD 543A, BD 707, BD 797
34134	BD203F	BD 203, , >20W	BDT 91F, BDX 77F, 2SD1411...12, 2SD1668
34135	BD204	BD 202, 60/60V	BD 244A, BD 544A, BD 708, BD 798
34136	BD204F	BD 204, , >20W	BDT 92F, BDX 78F, 2SB1018...19, 2SB1135
34137	BD205	55V, 10A, 90W, 4MHz	MJE 3055, 2N5989, 2SD491
34138	BD206	55V, 10A, 90W, 4MHz	MJE 2955, 2N5986, 2SB578
34139	BD207	BD 205, 70V	MJE 3055, 2N5990, 2SD491
34140	BD208	BD 206, 70V	MJE 2955, 2N5987, 2SB578
34141	BD213/45..80	45..80V, 15A, 90W, >3MHz	BD 245(A...C), BD 249(A...C), BD 745(A...C)
34142	BD214/45..80	45..80V, 15A, 90W, >3MHz	BD 246(A...C), BD 250(A...C), BD 746(A...C)
34143	BD215	500/300V, 0,5A, 21,5W, 10MHz	MJ4360...61, 2N4298...99, 2SC1078, 2SC1810
34144	BD216	300V, 1A, 21,5W, 10MHz	TIP47...48, 2N4296...97, 2SC867, 2SC2022...23
34145	BD220	80/70V, 4A, 36W, >0,8MHz	BD 243B, BD 537, BD 539B, BD 951
34146	BD221	BD 220, 60/40V	BD 243A, BD 535, BD 539A, BD 949
34147	BD222	BD 220, 80/60V	BD 243B, BD 537, BD 539B, BD 951
34148	BD223	80/70V, 4A, 36W, >0,8MHz	BD 244B, BD 538, BD 540B, BD 952
34149	BD224	BD 223, 60/40V	BD 244A, BD 536, BD 540A, BD 950
34150	BD225	BD 223, 80/60V	BD 244B, BD 538, BD 540B, BD 952
34151	BD226	125MHz	BD 135, BD 375, BD 785
34152	BD227	50MHz	BD 136, BD 376, BD 786
34153	BD228	BD 226, 60V	BD 137, BD 377, BD 785
34154	BD229	BD 227, 60V	BD 138, BD 378, BD 786



34155	BD230	BD 226, 100V	BD 139, BD 379, BD 791
34156	BD231	BD 227, 100V	BD 140, BD 380, BD 792
34157	BD232	500/300V, 0,25A, 15W, 20MHz	MJE 3439, 2SC2899, 2SC3051, 2SC3425
34158	BD232G	BD 232, 15W(Tc25°)	MJE 3439, 2SC2899, 2SC3051, 2SC3425
34159	BD233	45V, 2A, 25W, >3MHz	BD 175, BD 375, BD 437
34160	BD233G	BD 233, 4A, 30W	BD 243, BD 533, BD 539, BD 947
34161	BD234	45V, 2A, 25W, >3MHz	BD 176, BD 376, BD 438
34162	BD234G	BD 234, 4A, 30W	BD 244, BD 534, BD 540, BD 948
34163	BD235	BD 233, 60V	BD 177, BD 377, BD 439
34164	BD235G	BD 235, 4A, 30W	BD 243A, BD 535, BD 539A, BD 949
34165	BD236	BD 234, 60V	BD 178, BD 378, BD 440
34166	BD236G	BD 236, 4A, 30W	BD 244A, BD 536, BD 540A, BD 950
34167	BD237	BD 233, 100V	BD 379, BD 443, 2SD1177...1178
34168	BD237G	BD 237, 4A, 30W	BD 243C, BD 539C, BD 953, 2SD712
34169	BD238	BD 234, 100V	BD 380, 2SB874...875
34170	BD238G	BD 238, 4A, 30W	BD 244C, BD 540C, BD 954, 2SB682
34171	BD239	55V, 2A, 30W, >3MHz	BD 241, BD 243, BD 539A, BD 935
34172	BD239A	BD 239, 70V	BD 241A, BD 243A, BD 539B, BD 937
34173	BD239B	BD 239, 90V	BD 241B, BD 243B, BD 539C, BD 937
34174	BD239C	BD 239, 115V	BD 241C, BD 243C, BD 539D, BD 939
34175	BD239D	BD 239, 160V	BD 241D, BD 243D, 2SD759...760, 2SC2529
34176	BD239E	BD 239, 180V	BD 241E, BD 243E, 2SD760, 2SC2660
34177	BD239F	BD 239, 200V	BD 241F, BD 243F, 2SD760, 2SC2660
34178	BD240	55V, 2A, 30W, >3MHz	BD 242, BD 244, BD 540A, BD 936
34179	BD240A	BD 240, 70V	BD 242A, BD 244A, BD 540B, BD 938
34180	BD240B	BD 240, 90V	BD 242B, BD 244B, BD 540C, BD 938
34181	BD240C	BD 240, 115V	BD 242C, BD 244C, BD 540D, BD 940
34182	BD240D	BD 240, 160V	BD 242D, BD 244D, 2SB719...720, 2SA1079
34183	BD240E	BD 240, 180V	BD 242E, BD 244E, 2SB720, 2SA1133
34184	BD240F	BD 240, 200V	BD 242F, BD 244F, 2SB720, 2SA1133
34185	BD241	55V, 3A, 40W, >3MHz	BD 243, BD 539A, BD 543A, BD 935
34186	BD241A	BD 241, 70V	BD 243A, BD 539B, BD 543B, BD 937
34187	BD241B	BD 241, 90V	BD 243B, BD 539C, BD 543C, BD 937
34188	BD241C	BD 241, 115V	BD 243C, BD 539D, BD 543D, BD 939
34189	BD241D	BD 241, 160V	BD 243D, 2SD772A,B
34190	BD241E	BD 241, 180V	BD 243E, 2SD772A,B
34191	BD241F	BD 241, 200V	BD 243F, 2SD772A,B
34192	BD242	55V, 3A, 40W, >3MHz	BD 244, BD 540A, BD 544A, BD 936
34193	BD242A	BD 242, 70V	BD 244A, BD 540B, BD 544B, BD 938
34194	BD242B	BD 242, 90V	BD 244B, BD 540C, BD 544C, BD 938
34195	BD242C	BD 242, 115V	BD 244C, BD 540D, BD 544D, BD 940
34196	BD242D	BD 242, 160V	BD 244D
34197	BD242E	BD 242, 180V	BD 244E
34198	BD242F	BD 242, 200V	BD 244F
34199	BD243	55V, 6A, 65W, >3MHz	BD 543A, BD 797, BD 805

34200	BD243A	BD 243, 70V	BD 543B, BD 799, BD 807
34201	BD243B	BD 243, 90V	BD 543C, BD 801, BD 809
34202	BD243C	BD 243, 115V	BD 543D, BD 801, 2SD866
34203	BD243D	BD 243, 160V	BD 743F
34204	BD243E	BD 243, 180V	-
34205	BD243F	BD 243, 200V	-
34206	BD244	55V, 6A, 65W, >3MHz	BD 544A, BD 798, BD 808
34207	BD244A	BD 244, 70V	BD 544B, BD 800, BD 810
34208	BD244B	BD 244, 90V	BD 544C, BD 802, BD 810
34209	BD244C	BD 244, 115V	BD 544D, BD 802, 2SB870
34210	BD244D	BD 244, 160V	BD 744F
34211	BD244E	BD 244, 180V	-
34212	BD244F	BD 244, 200V	-
34213	BD245	55V, 10A, 80W, >3MHz	BD 249, BD 745A, BDV 91
34214	BD245A	BD 245, 70V	BD 249A, BD 745B, BDV 93
34215	BD245B	BD 245, 90V	BD 249B, BD 745C, BDV 95
34216	BD245C	BD 245, 115V	BD 249C, BD 745D, 2SD1047
34217	BD245D	BD 245, 160V	BD 249D, BD 745F, 2SC3263, 2SD1047
34218	BD245E	BD 245, 180V	BD 249E, 2SC3263
34219	BD245F	BD 245, 200V	BD 249F, 2SC3263
34220	BD246	55V, 10A, 80W, >3MHz	BD 250, BD 746A, BDV 92
34221	BD246A	BD 246, 70V	BD 250A, BD 746B, BDV 94
34222	BD246B	BD 246, 90V	BD 250B, BD 746C, BDV 96
34223	BD246C	BD 246, 115V	BD 250C, BD 746D, 2SB817
34224	BD246D	BD 246, 160V	BD 250D, BD 746F, 2SA1294, 2SB817
34225	BD246E	BD 246, 180V	BD 250E, 2SA1294
34226	BD246F	BD 246, 200V	BD 250F, 2SA1294
34227	BD249	55V, 25A, 125W, >3MHz	2SD1049
34228	BD249A	BD 249, 70V	2SD1049
34229	BD249B	BD 249, 90V	2SD1049
34230	BD249C	BD 249, 115V	2SD1049
34231	BD249D	BD 249, 160V	-
34232	BD249E	BD 249, 180V	-
34233	BD249F	BD 249, 200V	-
34234	BD250	55V, 25A, 125W, >3MHz	-
34235	BD250A	BD 250, 70V	-
34236	BD250B	BD 250, 90V	-
34237	BD250C	BD 250, 115V	-
34238	BD250D	BD 250, 160V	-
34239	BD250E	BD 250, 180V	-
34240	BD250F	BD 250, 200V	-
34241	BD251	40V, 3A, 20W(Tc50°), 46MHz	BD 245, BDY90...92, 2N3055, 2SC3256
34242	BD253	350V, 4A, 100W, 25MHz	BU 526, BUW 71, BUX 16C, BUY 67
34243	BD2530	300/300V, 25A, 100W, 7MHz	BUT 13
34244	BD253A	BD 253, 500V	BU 526, BUS 11, BUX 45, BUX 82

34245	BD253B	BD 253, 700V	BU 526, BUS 11, BUX 82, BUX 97
34246	BD253C	BD 253, 900V	BU 526, BUS 11A, BUX 83, 2SD802
34247	BD254	60V, 3A, 18,5W, 30MHz	BD 241A, BD 243A, BD 535, BD 935
34248	BD2540	BD 2530, 400/400V	BUT 13
34249	BD255	60V, 3A, 18,5W, 30MHz	BD 242A, BD 244A, BD 536, BD 936
34250	BD2550	BD 2530, 500/500V	BUT 13
34251	BD257/45..100	45..100V, 25A, 125W, >3MHz	BD 249(A...C)
34252	BD258/45..100	45..100V, 25A, 125W, >3MHz	BD 250(A...C)
34253	BD260	200V, 2A, 30W, >10MHz	BUX 67, 2N3583, 2SC2023, 2SD610
34254	BD261	300V, 5A, 30W, >10MHz	BUX 63, MJE 51T, 2N6234...35, 2SC2907
34255	BD262	60V, 4A, 36W, 7MHz, B>750	BD 678, BD 778, 2N6035
34256	BD262A	BD 262, 80V	BD 680, BD 780, 2N6036
34257	BD262B	BD 262, 100V	BD 682
34258	BD262C	BD 262, 120V	BD 684
34259	BD262L	BD 262, 45V	BD 678, BD 778, 2N6035
34260	BD263	80V, 4A, 36W, 7MHz, B>750	BD 679, BD 779, 2N6039
34261	BD263A	BD 263, 100V	BD 681
34262	BD263B	BD 263, 120V	BD 683
34263	BD263C	BD 263, 140V	-
34264	BD263L	BD 263, 60V	BD 677, BD 777, 2N6038
34265	BD264	60V, 4A, 40W, 7MHz, B>1000	BD 646, BD 898, BDW 24A, BDW 54A
34266	BD264A	BD 264, 80V	BD 648, BD 900, BDW 24B, BDW 54B
34267	BD264B	BD 264, 100V	BD 650, BD 902, BDW 24C, BDW 54C
34268	BD264L	BD 264, 45V	BD 644, BD 896, BDW 24, BDW 54
34269	BD265	80V, 4A, 40W, 7MHz, B>1000	BD 647, BD 899, BDW 23B, BDW 53B
34270	BD265A	BD 265, 100V	BD 649, BD 901, BDW 23C, BDW 53C
34271	BD265B	BD 265, 120V	BD 651, BDT 21, BDW 63D, 2SD1147
34272	BD265L	BD 265, 60V	BD 645, BD 897, BDW 23A, BDW 53A
34273	BD266	60V, 8A, 60W, 7MHz, B>750	BD 646, BD 898, BDW 24A, BDW 64A
34274	BD266A	BD 266, 80V	BD 648, BD 900, BDW 24B, BDW 64B
34275	BD266B	BD 266, 100V	BD 650, BD 902, BDW 24C, BDW 64C
34276	BD266L	BD 266, 45V	BD 644, BD 896, BDW 24, BDW 64
34277	BD267	80V, 8A, 60W, 7MHz, B>750	BD 647, BD 899, BDW 23B, BDW 63B
34278	BD267A	BD 267, 100V	BD 649, BD 901, BDW 23C, BDW 63C
34279	BD267B	BD 267, 120V	BD 651, BDT 21, BDW 63D, 2SD1386
34280	BD267L	BD 267, 60V	BD 645, BD 897, BDW 23A, BDW 63A
34281	BD268	80V, 10A, 75W	BDT 62A, BDT 64A, BDW 94B, BDX 34B
34282	BD268A	BD 268, 100V	BDT 62B, BDT 64B, BDW 94C, BDX 34C
34283	BD269	80V, 10A, 75W	BDT 63A, BDT 65A, BDW 93B, BDX 33B
34284	BD269A	BD 269, 100V	BDT 63B, BDT 65B, BDW 93C, BDX 33C
34285	BD271	55V, 4A, 36W, >2MHz	BD 243, BD 535, BD 539A, BD 949
34286	BD272	55V, 4A, 36W, >2MHz	BD 244, BD 536, BD 540A, BD 950
34287	BD273	BD 271, 80V	BD 243B, BD 537, BD 539B, BD 951
34288	BD274	BD 272, 80V	BD 244B, BD 538, BD 540B, BD 951
34289	BD275	BD 271, 100V	BD 243C, BD 539C, BD 953, 2SD712

34290	BD276	BD 272, 100V	BD 244C, BD 540C, BD 954, 2SB682
34291	BD277	45V, 7A, 70W, >10MHz	BD 244, BD 544A, BD 796, BD 806
34292	BD278(A,AE)	55V, 10A, 75W, >0.8MHz	BD 707, BD 805, BD 907
34293	BD279	B>10000	-
34294	BD280	B>10000	-
34295	BD281	22V, 4A, 36W, >3MHz	BD 185, BD 433, 2N5190
34296	BD282	22V, 4A, 36W, >3MHz	BD 186, BD 434, 2N5193
34297	BD283	BD 281, 32V	BD 185, BD 435, 2N5190
34298	BD284	BD 282, 32V	BD 186, BD 436, 2N5193
34299	BD285	BD 281, 45V	BD 187, BD 437, 2N5191
34300	BD286	BD 282, 45V	BD 188, BD 440, 2N5194
34301	BD287	30V, 12A, 36W, >50MHz	-
34302	BD288	BD 287, 45V	-
34303	BD291	45V, 6A, 60W, >3MHz	BD 243, BD 543A, BD 795, BD 805
34304	BD292	45V, 6A, 60W, >3MHz	BD 244, BD 544A, BD 798, BD 806
34305	BD293	BD 291, 60V	BD 243A, BD 543A, BD 797, BD 807
34306	BD294	BD 292, 60V	BD 244A, BD 544A, BD 800, BD 808
34307	BD295	BD 291, 80V	BD 243B, BD 543B, BD 799, BD 809
34308	BD296	BD 292, 80V	BD 244B, BD 544B, BD 800, BD 810
34309	BD301	60V, 8A, 55W, >3MHz	BD 543A, BD 709, BD 797, BD 807
34310	BD302	60V, 8A, 55W, >3MHz	BD 544A, BD 710, BD 798, BD 808
34311	BD303	60V, 8A, 55W, >3MHz	BD 543A, BD 707, BD 797, BD 807
34312	BD303A	BD 303, 80V	BD 543B, BD 709, BD 799, BD 809
34313	BD303B	BD 303, 100V	BD 543C, BD 711, BD 801
34314	BD304	60V, 8A, 55W, >3MHz	BD 544A, BD 708, BD 798, BD 806
34315	BD304A	BD 304, 80V	BD 544B, BD 710, BD 800, BD 810
34316	BD304B	BD 304, 100V	BD 544C, BD 712, BD 802
34317	BD306(A,B)	36V, 2.5A, 10W, 100MHz	BD 233, BD 785, 2SC2877
34318	BD307(A,B)	BD 306, 64V	BD 235, BD 785, 2SD794(A)
34319	BD311	60V, 10A, 150W, >4MHz	BD 315, BDW 21A, BDW 51A, 2N5877
34320	BD312	60V, 10A, 150W, >3MHz	BD 316, BDW 22A, BDW 52A, 2N5875
34321	BD313	BD 311, 80V	BD 315, BDW 21B, BDW 51B, 2N5878
34322	BD314	BD 312, 80V	BD 316, BDW 22B, BDW 52B, 2N5880
34323	BD315	80V, 16A, 200W, >1MHz	2N5629...5631
34324	BD316	80V, 16A, 200W, >1MHz	2N6029...6031
34325	BD317	BD 315, 100V	2N5629...5631
34326	BD318	BD 316, 100V	2N6029...6031
34327	BD320(A,B,C)	B>500	BSS 51...52, BD 877, BDX 43
34328	BD321(A,B,C)	BD 320, 2A	2SC1888, 2SD406, 2SD614...615, 2SD688
34329	BD322(A,B,C)	B>500	BSS 51...52, BD 877, BDX 43
34330	BD323(A,B,C)	BD 322, 2A	2SC1888, 2SD406, 2SD614...615, 2SD688
34331	BD329	32V, 3A, 15W(Tc45°), 130MHz	2SD882, 2SD1348, BD 785, 2SD794(A)
34332	BD330	32V, 3A, 15W(Tc45°), 100MHz	2SB772, 2SB986, BD 786, 2SB744(A)
34333	BD331	60V, 6A, 60W, >10MHz, B>750	BD 645, BD 897, BDW 23A, BDW 63A
34334	BD332	60V, 6A, 60W, >10MHz, B>750	BD 646, BD 898, BDW 24A, BDW 64A

34335	BD333	BD 331, 80V	BD 647, BD 899, BDW 23B, BDW 63B
34336	BD334	BD 332, 80V	BD 648, BD 900, BDW 24B, BDW 64B
34337	BD335	BD 331, 100V	BD 649, BD 901, BDW 23C, BDW 63C
34338	BD336	BD 332, 100V	BD 650, BD 902, BDW 24C, BDW 64C
34339	BD337	BD 331, 120V	BD 651, BDT 21, BDW 63D, BDW 74D
34340	BD338	BD 332, 120V	BD 652, BDT 20, BDW 64D, BDW 74D
34341	BD342	-/40V, 12A, 100W, 1,5MHz	BD 249, BD 315, BDW 51A, 2N5881
34342	BD343	-/40V, 12A, 100W, 1,5MHz	BD 250, BD 316, BDW 52A, 2N5879
34343	BD344	60V, 1A, 20W, >50MHz	BD 138, BD 229, BD 378, BD 786
34344	BD345	60V, 1A, 20W, >50MHz	BD 137, BD 228, BD 377, BD 785
34345	BD346	60V, 8A, 60W, >4MHz	BD 544A, BD 708, BD 798, BD 808
34346	BD347	60V, 8A, 60W, >4MHz	BD 543A, BD 707, BD 797, BD 807
34347	BD348	80V, 1A, 20W, >50MHz	BD 140, BD 231, BD 380, BD 792
34348	BD349	80V, 1A, 20W, >50MHz	BD 139, BD 230, BD 379, BD 791
34349	BD350	-/80V, 15A, 160W, >4MHz	BD 316, BD 318, 2N6029...6031
34350	BD350A	BD 350, -/70V	BD 316, BD 318, 2N6029...6031
34351	BD350B	BD 350, -/60V	BD 316, BD 318, 2N6029...6031
34352	BD351	-/80V, 15A, 160W, >4MHz	BD 315, BD 317, 2N5629...5631
34353	BD351A	BD 351, -/70V	BD 315, BD 317, 2N5629...5631
34354	BD351B	BD 351, -/60V	BD 315, BD 317, 2N5629...5631
34355	BD354(A,B,C)	>30MHz	MJE 15028, 2SC3252...3253
34356	BD355(A,B,C)	>30MHz	MJE 15029, 2SA1288...1289
34357	BD356	20V, 5A, 20W, >50MHz	MJE 210
34358	BD357	50V, 5A, 20W, >50MHz	MJE 200, 2SC2270, 2SD826
34359	BD358	BD 356, 8,3W	MJE 210
34360	BD359	BD 357, 8,3W	MJE 200, 2SC2270, 2SD826
34361	BD361(A)	32V, 3A, 15W	BD 175, BD 185, BD 435, 2N5190
34362	BD362(A)	32V, 3A, 15W	BD 176, BD 186, BD 436, 2N5193
34363	BD363(A,B)	60V, 6A, 75W	BD 243A, BD 543A, BD 797, BD 807
34364	BD364	50V, 25A, 200W, >4MHz	MJ 802, 2N5885
34365	BD365	50V, 25A, 200W, >4MHz	MJ 4502, 2N5883
34366	BD366	BD 364, 60V	MJ 802, 2N5885
34367	BD367	BD 365, 60V	MJ 4502, 2N5883
34368	BD368	BD 364, 80V	MJ 802, 2N5886
34369	BD369	BD 365, 80V	MJ 4502, 2N5884
34370	BD370A	45V, 1,5A, 2,5W, >50MHz	BC 362, BD 518, BD 526, BD 840
34371	BD370B	BD 370A, 60V	BC 363, BD 518, BD 526, BD 842
34372	BD370C	BD 370A, 80V	BC 364, BD 520, BD 528, BD 844
34373	BD370D	BD 370A, 100V	BD 530, BD 844
34374	BD371A	45V, 1,5A, 2,5W, >50MHz	BC 365, BD 517, BD 525, BD 839
34375	BD371B	BD 371A, 60V	BC 366, BD 517, BD 525, BD 841
34376	BD371C	BD 371A, 80V	BC 367, BD 519, BD 527, BD 843
34377	BD371D	BD 371A, 100V	BD 529, BD 843
34378	BD372(A...D)	BD 370A..D	BD 370A...D
34379	BD373(A...D)	BD 371A..D	BD 371A...D

34380	BD375	50V, 2A, 25W, >50MHz	BD 177, BD 235, BD 785, 2SD1177...1178
34381	BD376	50V, 2A, 25W, >50MHz	BD 178, BD 236, BD 786, 2SB874...875
34382	BD377	BD 375, 75V	BD 179, BD 237, BD 787, 2SD1177...1178
34383	BD378	BD 376, 75V	BD 180, BD 238, BD 788, 2SB874...875
34384	BD379	BD 375, 100V	BD 237, BD 791, 2SD1177...1178
34385	BD380	BD 376, 100V	BD 238, BD 792, 2SB874...875
34386	BD385	60V, 1A, 10W, >350MHz	BD 827, BD 841
34387	BD386	60V, 1A, 10W, >350MHz	BD 828, BD 842
34388	BD387	BD 385, 80V	BD 829, BD 843
34389	BD388	BD 386, 80V	BD 830, BD 844
34390	BD389	BD 385, 100V	BD 829, BD 843
34391	BD390	BD 386, 100V	BD 830, BD 844
34392	BD400	170V, 1A, 20W, 65MHz	2SC3117, 2SD669, (MJE 340)
34393	BD401	60/45V, 10A, 50W, 50MHz	BD 707, BD 743A, BD 807, BD 907
34394	BD402	60/45V, 10A, 50W, 40MHz	BD 708, BD 744A, BD 808, BD 908
34395	BD403	BD 401, 60/60V	BD 707, BD 743A, BD 807, BD 907
34396	BD404	BD 402, 60/60V	BD 708, BD 744A, BD 808, BD 908
34397	BD410	500V, 1A, 20W	BUV 93, 2SC3051
34398	BD411	50V, 2A, 10W, B>25000	MPSU 45
34399	BD412	BD 411, B>15000	MPSU 45
34400	BD413	50V, 2A, 10W, B>25000	MPSU 95
34401	BD414	BD 413, B>15000	MPSU 95
34402	BD415	60V, 1A, 10W, >75MHz	BD 517, BD 525, BD 385, BD 827
34403	BD416	60V, 1A, 10W, >75MHz	BD 518, BD 526, BD 386, BD 828
34404	BD417	BD 315, 80V	BD 519, BD 527, BD 387, BD 829
34405	BD418	BD 416, 80V	BD 520, BD 528, BD 388, BD 830
34406	BD419	BD 415, 100V	BD 529, BD 389, BD 829
34407	BD420	BD 416, 100V	BD 530, BD 390, BD 830
34408	BD421	-/100V, 2A, 10W, >100MHz	BD 879, BDX 44
34409	BD422	BD 421, -/80V	BD 779, BD 877, BDX 43
34410	BD424	160V, 0.8A, 2.5W(Tc100°)	BF 666...668, MJE 340, 2SC3117, 2SC2483
34411	BD429	32V, 3A, 10W, 130MHz	BD 329, BD 785, 2SD1348
34412	BD430	32V, 3A, 10W, 100MHz	BD 330, BD 786, 2SB986
34413	BD433	22V, 4A, 36W, >3MHz	BD 185, 2N5190
34414	BD434	22V, 4A, 36W, >3MHz	BD 186, 2N5193
34415	BD435	BD 433, 32V	BD 185, 2N5190
34416	BD436	BD 434, 32V	BD 186, 2N5193
34417	BD437	BD 433, 45V	BD 187, 2N5191
34418	BD438	BD 434, 45V	BD 188, 2N5194
34419	BD439	BD 433, 60V	BD 189, 2N5191
34420	BD440	BD 434, 60V	BD 190, 2N5194
34421	BD441	BD 433, 80V	BD 189, 2N5192
34422	BD442	BD 434, 80V	BD 190, 2N5195
34423	BD443	120V, 3A, 30W, >0.8MHz	-
34424	BD443A	BD 443, 170V	-



34425	BD450	80V, 15A, 115W, >0,8MHz	BD 315, 2N5629...5631
34426	BD451	BD 450, 95V	BD 317, 2N5629...5631
34427	BD461	35V, 4A, 30W	BD 185, BD 437, BD 785, 2N5190
34428	BD462	35V, 4A, 30W	BD 186, BD 438, BD 786, 2N5193
34429	BD463	35V, 4A, 30W	BD 185, BD 437, BD 785, 2B5190
34430	BD464	35V, 4A, 30W	BD 186, BD 438, BD 786, 2N5193
34431	BD466A	B>8000	BD 876, BDX 45...47
34432	BD466B	BD 466A, 45V	BD 876, BDX 45...47
34433	BD477A	B>8000	BD 875, BDX 42...44
34434	BD477B	BD 477A, 45V	BD 875, BDX 42...44
34435	BD487	30V, 12A, 12,5W, >50MHz	-
34436	BD488	BD 487, 45V	-
34437	BD500	60V, 10A, 75W, >5MHz	BD 708, BD 744A, BD 808, BD 908
34438	BD500A	BD 500, 70V	BD 710, BD 744A, BD 810, BD 910
34439	BD500B	BD 500, 90V	BD 712, BD 744B, BD 912
34440	BD501	60V, 10A, 75W, >5MHz	BD 707, BD 743A, BD 807, BD 907
34441	BD501A	BD 501, 70V	BD 709, BD 743A, BD 809, BD 909
34442	BD501B	BD 501, 90V	BD 711, BD 743B, BD 911
34443	BD505	30V, 2A, 10W, 250MHz	BD 515, BD 525, BD 839
34444	BD506	30V, 2A, 10W, 250MHz	BD 516, BD 526, BD 840
34445	BD507	BD 505, 40V	BD 515, BD 525, BD 839
34446	BD508	BD 506, 40V	BD 516, BD 526, BD 840
34447	BD509	BD 505, 50V	BD 517, BD 525, BD 841
34448	BD510	BD 506, 60V	BD 518, BD 526, BD 842
34449	BD512	60V, 1,5A, 10W	-
34450	BD515	45V, 2A, 10W, 160MHz	BD 525, BD 839
34451	BD516	45V, 2A, 10W, 125MHz	BD 526, BD 840
34452	BD517	BD 515, 60V	BD 525, BD 841
34453	BD518	BD 516, 60V	BD 526, BD 842
34454	BD519	BD 515, 80V	BD 527, BD 843
34455	BD520	BD 516, 80V	BD 528, BD 844
34456	BD522	60V, 1,5A, 10W	-
34457	BD524	160V, 0,8A, 5W, 100MHz	2SC3051, 2SC3117, 2SC3425, 2SD669
34458	BD525	60V, 2A, 10W, 150MHz	BD 517, BD 841
34459	BD526	60V, 2A, 10W, 100MHz	BD 518, BD 842
34460	BD527	BD 525, 80V	BD 519, BD 843
34461	BD528	BD 526, 80V	BD 518, BD 844
34462	BD529	BD 525, 100V	BD 843
34463	BD530	BD 526, 100V	BD 844
34464	BD533(A)	45V, 4A, 50W, >3MHz	BD 243, BD 539A, BD 543A, BD 947
34465	BD533FI	BD 533, , 22W	BD 947F, 2SD1408, 2SC1667, 2SD2012
34466	BD534(A)	45V, 4A, 50W, >3MHz	BD 244, BD 540A, BD 544A, BD 950
34467	BD534FI	BD 534, , 22W	BD 948F, 2SB1017, 2SA1488, 2SB1375
34468	BD535(A)	BD 533, 60V	BD 243A, BD 539A, BD 543A, BD 949
34469	BD536(A)	BD 534, 60V	BD 244A, BD 540A, BD 544A, BD 950

34470	BD537(A)	BD 533, 80V	BD 243B, BD 539B, BD 543B, BD 951
34471	BD538(A)	BD 534, 80V	BD 244B, BD 540B, BD 544B, BD 952
34472	BD539	40V, 5A, 45W, >3MHz	BD 243, BD 543, BD 795, BD 805
34473	BD539A	BD 539, 60V	BD 243A, BD 543A, BD 797, BD 807
34474	BD539B	BD 539, 80V	BD 243B, BD 543B, BD 799, BD 809
34475	BD539C	BD 539, 100V	BD 243C, BD 543C, BD 801, 2SD866
34476	BD539D	BD 539, 120V	BD 543D, 2SD866
34477	BD540	40V, 5A, 45W, >3MHz	BD 244, BD 544, BD 796, BD 806
34478	BD540A	BD 540, 60V	BD 244A, BD 544A, BD 798, BD 808
34479	BD540B	BD 540, 80V	BD 244B, BD 544B, BD 800, BD 810
34480	BD540C	BD 540, 100V	BD 244C, BD 544C, BD 802, 2SB870
34481	BD540D	BD 540, 120V	BD 544D, 2SB870
34482	BD543	40V, 8A, 70W, >3MHz	BD 705, BD 795, BD 805
34483	BD543A	BD 543, 60V	BD 707, BD 797, BD 807
34484	BD543B	BD 543, 80V	BD 709, BD 799, BD 809
34485	BD543C	BD 543, 100V	BD 711, BD 801, 2SD866
34486	BD543D	BD 543, 120V	2SD866
34487	BD544	40V, 8A, 70W, >3MHz	BD 706, BD 796, BD 806
34488	BD544A	BD 544, 60V	BD 708, BD 798, BD 808
34489	BD544B	BD 544, 80V	BD 710, BD 800, BD 810
34490	BD544C	BD 544, 100V	BD 712, BD 802, 2SB870
34491	BD544D	BD 544, 120V	2SB870
34492	BD545	40V, 15A, 85W, >3MHz	BD 249, BD 745
34493	BD545A	BD 545, 60V	BD 249A, BD 745A
34494	BD545B	BD 545, 80V	BD 249B, BD 745B
34495	BD545C	BD 545, 100V	BD 249C, BD 745C
34496	BD545D	BD 545, 120V	BD 745D
34497	BD546	40V, 15A, 85W, >3MHz	BD 250, BD 746
34498	BD546A	BD 546, 60V	BD 250A, BD 746A
34499	BD546B	BD 546, 80V	BD 250B, BD 746B
34500	BD546C	BD 546, 100V	BD 250C, BD 746C
34501	BD546D	BD 546, 120V	BD 746D
34502	BD550	130V, 7A, 150W, 5MHz	BDW 10...16, BUX 17, MJ 15015, 2SD665
34503	BD550A	BD 550, 200V	BDW 10, BUX 17, MJ 15015, 2SD665
34504	BD550B	BD 550, 275V	BUX 17A, 2SD555, 2SD583, 2SC1586
34505	BD561	45V, 4A, 40W, >3MHz	BD 187, BD 437, 2B5191
34506	BD562	45V, 4A, 40W, >3MHz	BD 188, BD 438, 2N5194
34507	BD566	-/60V, 10A, 50W, B>1000	BDT 62A, BDT 64A, BDW 94B, BDX 34B
34508	BD566A	BD 566, -/80V	BDT 62B, BDT 64B, BDW 94C, BDX 34C
34509	BD567	-/60V, 10A, 50W, B>1000	BDT 63A, BDT 65A, BDW 93B, BDX 33B
34510	BD567A	BD 567, -/80V	BDT 63B, BDT 65B, BDW 93C, BDX 33C
34511	BD575	45V, 3A, 40W, >3MHz	BD 585, BD 241, BD 533, BD 933
34512	BD575	45V, 3A, 40W, >3MHz	BD 585, BD 241, BD 533, BD 933
34513	BD576	45V, 3A, 40W, >3MHz	BD 586, BD 242, BD 534, BD 934
34514	BD576	45V, 3A, 40W, >3MHz	BD 586, BD 242, BD 534, BD 934

34515	BD577	BD 575, 60V	BD 587, BD 241A, BD 535, BD 935
34516	BD577	BD 575, 60V	BD 587, BD 241A, BD 535, BD 935
34517	BD578	BD 576, 60V	BD 588, BD 242A, BD 536, BD 936
34518	BD578	BD 576, 60V	BD 588, BD 242A, BD 536, BD 936
34519	BD579	BD 575, 80V	BD 589, BD 241B, BD 537, BD 937
34520	BD579	BD 575, 80V	BD 589, BD 241B, BD 537, BD 937
34521	BD580	BD 576, 80V	BD 590, BD 242B, BD 538, BD 938
34522	BD580	BD 576, 80V	BD 590, BD 242B, BD 538, BD 938
34523	BD581	BD 575, 100V	BD 591, BD 241C, BD 937, 2SD712
34524	BD581	BD 575, 100V	BD 591, BD 241C, BD 937, 2SD712
34525	BD582	BD 576, 100V	BD 592, BD 242C, BD 938, 2SB682
34526	BD582	BD 576, 100V	BD 592, BD 242C, BD 938, 2SB682
34527	BD585	45V, 4A, 40W, >3MHz	BD 595, BD 533, BD 539, BD 947
34528	BD585	45V, 4A, 40W, >3MHz	BD 595, BD 533, BD 539, BD 947
34529	BD586	45V, 4A, 40W, >3MHz	BD 596, BD 534, BD 540, BD 948
34530	BD586	45V, 4A, 40W, >3MHz	BD 596, BD 534, BD 540, BD 948
34531	BD587	BD 585, 60V	BD 597, BD 535, BD 539A, BD 949
34532	BD587	BD 585, 60V	BD 597, BD 535, BD 539A, BD 949
34533	BD588	BD 586, 60V	BD 598, BD 536, BD 540A, BD 950
34534	BD588	BD 586, 60V	BD 598, BD 536, BD 540A, BD 950
34535	BD589	BD 585, 80V	BD 599, BD 537, BD 539B, BD 951
34536	BD589	BD 585, 80V	BD 599, BD 537, BD 539B, BD 951
34537	BD590	BD 586, 80V	BD 600, BD 538, BD 540B, BD 952
34538	BD590	BD 586, 80V	BD 600, BD 538, BD 540B, BD 952
34539	BD591	BD 585, 100V	BD 601, BD 539C, BD 953, 2SD712
34540	BD591	BD 585, 100V	BD 601, BD 539C, BD 953, 2SD712
34541	BD592	BD 586, 100V	BD 602, BD 540C, BD 954, 2SB682
34542	BD592	BD 586, 100V	BD 602, BD 540C, BD 954, 2SB682
34543	BD595	45V, 8A, 65W, >3MHz	BD 605, BD 543, BD 795, BD 805
34544	BD595	45V, 8A, 65W, >3MHz	BD 605, BD 543, BD 795, BD 805
34545	BD596	45V, 8A, 65W, >3MHz	BD 606, BD 544, BD 796, BD 806
34546	BD596	45V, 8A, 65W, >3MHz	BD 606, BD 544, BD 796, BD 806
34547	BD597	BD 595, 60V	BD 607, BD 543A, BD 797, BD 807
34548	BD597	BD 595, 60V	BD 607, BD 543A, BD 797, BD 807
34549	BD598	BD 596, 60V	BD 608, BD 544A, BD 798, BD 808
34550	BD598	BD 596, 60V	BD 608, BD 544A, BD 798, BD 808
34551	BD599	BD 595, 80V	BD 609, BD 543B, BD 799, BD 809
34552	BD599	BD 595, 80V	BD 609, BD 543B, BD 799, BD 809
34553	BD600	BD 596, 80V	BD 610, BD 544B, BD 800, BD 810
34554	BD600	BD 596, 80V	BD 610, BD 544B, BD 800, BD 810
34555	BD601	BD 595, 100V	BD 543C, BD 801, 2SD866
34556	BD601	BD 595, 100V	BD 543C, BD 801, 2SD866
34557	BD602	BD 596, 100V	BD 544C, BD 802, 2SB869
34558	BD602	BD 596, 100V	BD 544C, BD 802, 2SB869
34559	BD605	55V, 10A, 90W, >1.5MHz	BD 743A, BD 805, BD 907

34560	BD605	55V, 10A, 90W, >1,5MHz	BD 743A, BD 805, BD 907
34561	BD606	55V, 10A, 90W, >1,5MHz	BD 744A, BD 806, BD 908
34562	BD606	55V, 10A, 90W, >1,5MHz	BD 744A, BD 806, BD 908
34563	BD607	BD 605, 70V	BD 743A, BD 807, BD 909
34564	BD607	BD 605, 70V	BD 743A, BD 807, BD 909
34565	BD608	BD 606, 70V	BD 744A, BD 808, BD 910
34566	BD608	BD 606, 70V	BD 744A, BD 808, BD 910
34567	BD609	BD 605, 80V	BD 743B, BD 809, BD 909
34568	BD609	BD 605, 80V	BD 743B, BD 809, BD 909
34569	BD610	BD 606, 80V	BD 744B, BD 810, BD 910
34570	BD610	BD 606, 80V	BD 744B, BD 810, BD 910
34571	BD611	22V, 4A, 15W, >3MHz	BD 185, BD 433, 2N5190
34572	BD612	22V, 4A, 15W, >3MHz	BD 186, BD 434, 2N5193
34573	BD613	BD 611, 32V	BD 185, BD 435, 2N5190
34574	BD614	BD 612, 32V	BD 186, BD 436, 2N5193
34575	BD615	BD 611, 45V	BD 187, BD 437, 2N5191
34576	BD616	BD 612, 45V	BD 188, BD 438, 2N5194
34577	BD617	BD 611, 60V	BD 189, BD 439, 2N5191
34578	BD618	BD 612, 60V	BD 190, BD 440, 2N5194
34579	BD619	BD 611, 80V	BD 441, 2N5192
34580	BD620	BD 612, 80V	BD 442, 2N5195
34581	BD633	45V, 2A, 30W, >3MHz	BD 239, BD 241, BD 533, BD 933
34582	BD634	45V, 2A, 30W, >3MHz	BD 240, BD 242, BD 534, BD 934
34583	BD635	BD 633, 60V	BD 239A, BD 241A, BD 535, BD 935
34584	BD636	BD 634, 60V	BD 240A, BD 242A, BD 536, BD 936
34585	BD637	BD 633, 100V	BD 239C, BD 241C, BD 937, 2SD712
34586	BD638	BD 634, 100V	BD 240C, BD 242C, BD 938, 2SB682
34587	BD643	B>750	BD 895, BDW 73, BDX 33, BDX 53
34588	BD643F	BD 643, , >20W	BDT 63(A...C)F, 2SD1415...17, 2SD1826
34589	BD644	B>750	BD 896, BDW 74, BDX 34, BDX 54
34590	BD644F	BD 644, , >20W	BDT 62(A...C)F, 2SB1020...22, 2SB1224
34591	BD645	BD 643, 80V	BD 897, BDW 73A, BDX 33A, BDX 53A
34592	BD645F	BD 645, , >20W	BDT 63AF...CF, 2SD1415...16, 2SD1791
34593	BD646	BD 644, 60V	BD 898, BDW 74A, BDX 34A, BDX 54A
34594	BD646F	BD 646, , >20W	BDT 62(A...C)F, 2SB1020...22, 2SB1224
34595	BD647	BD 643, 100V	BD 899, BDW 73B, BDX 33B, BDX 53B
34596	BD647F	BD 647, , >20W	BDT 63BF...CF, 2SD1415, 2SD1791
34597	BD648	BD 644, 80V	BD 900, BDW 74B, BDX 34B, BDX 54B
34598	BD648F	BD 648, , >20W	BDT 62AF...CF, 2SB1020...21, 2SB1283
34599	BD649	BD 643, 120V	BD 901, BDW 73C, BDX 33C, BDX 53C
34600	BD649F	BD 649, , >20W	BDT 63CF, 2SD1590, 2SD1792, 2SD1590
34601	BD650	BD 644, 100V	BD 902, BDW 74C, BDX 34C, BDX 54C
34602	BD650F	BD 650, , >20W	BDT 62AF...CF, 2SB1020, 2SB1283
34603	BD651	BD 643, 140V	BDW 73D, BDX 33D, BDX 53E, BDT 21
34604	BD651F	BD 651, , >20W	2SD1590, 2SD1792

34605	BD652	BD 644, 120V	BDW 74D, BDX 34D, BDX 54E, BDT 20
34606	BD652F	BD 652, , >20W	BDT 62CF, 2SB1193
34607	BD661	32V, 4A, 36W	BD 243, BD 533, BD 539, 945
34608	BD661K	BD 661, 50W	BD 243, BD 533, BD 539, BD 945
34609	BD662	32V ,4A, 32W	BD 244, BD 534, BD 540, BD 946
34610	BD662K	BD 662, 50W	BD 244, BD 534, BD 540, BD 946
34611	BD663(A,B)	45V, 10A, 75W, >3MHz	BD 705, BD 743, BD 805, BD 905
34612	BD664(A,B)	45V, 10A, 75W, >3MHz	BD 706, BD 744, BD 806, BD 906
34613	BD675(A)	45V, 4A, 40W, >10MHz, B>750	BD 775, 2N6038
34614	BD675H...680H	BD 675..680	BD 675...680
34615	BD676(A)	45V, 4A, 40W, >10MHz, B>750	BD 776, 2N6035
34616	BD677(A)	BD 675, 60V	BD 777, 2N6038
34617	BD678(A)	BD 676, 60V	BD 778, 2N6035
34618	BD679(A)	BD 675, 80V	BD 779, 2N6039
34619	BD680(A)	BD 676, 80V	BD 780, 2N6036
34620	BD681	BD 675, 100V	-
34621	BD682	BD 676, 100V	-
34622	BD683	BD 675, 140V	-
34623	BD684	BD 676, 120V	-
34624	BD695(A)	45V, 8A, 70W, >1MHz, B>750	BD 643, BD 895, BDW 73, BDX 53
34625	BD695(A)	45V, 8A, 70W, >1MHz, B>750	BD 643, BD 895, BDW 73, BDX 53
34626	BD696(A)	45V, 8A, 70W, >1MHz, B>750	BD 644, BD 896, BDW 74, BDX 54
34627	BD696(A)	45V, 8A, 70W, >1MHz, B>750	BD 644, BD 896, BDW 74, BDX 54
34628	BD697(A)	BD 695, 60V	BD 645, BD 897, BDW 73A, BDX 53A
34629	BD697(A)	BD 695, 60V	BD 645, BD 897, BDW 73A, BDX 53A
34630	BD698(A)	BD 696, 60V	BD 646, BD 898, BDW 74A, BDX 54A
34631	BD698(A)	BD 696, 60V	BD 646, BD 898, BDW 74A, BDX 54A
34632	BD699(A)	BD 695, 80V	BD 647, BD 899, BDW 73B, BDX 53B
34633	BD699(A)	BD 695, 80V	BD 647, BD 899, BDW 73B, BDX 53B
34634	BD700(A)	BD 696, 80V	BD 648, BD 900, BDW 74B, BDX 54B
34635	BD700(A)	BD 696, 80V	BD 648, BD 900, BDW 74B, BDX 54B
34636	BD701	BD 695, 100V	BD 649, BD 901, BDW 73C, BDX 53C
34637	BD701	BD 695, 100V	BD 649, BD 901, BDW 73C, BDX 53C
34638	BD702	BD 696, 100V	BD 650, BD 902, BDW 74C, BDX 54C
34639	BD702	BD 696, 100V	BD 650, BD 902, BDW 74C, BDX 54C
34640	BD705	45V, 12A, 75W, >3MHz	BD 743, BD 905
34641	BD706	45V, 12A, 75W, >3MHz	BD 744, BD 906
34642	BD707	BD 705, 60V	BD 743A, BD 907
34643	BD708	BD 706, 60V	BD 744A, BD 908
34644	BD709	BD 705, 80V	BD 743B, BD 909
34645	BD710	BD 706, 80V	BD 744B, BD 910
34646	BD711	BD 705, 100V	BD 743C, BD 911
34647	BD712	BD 706, 100V	BD 744C, BD 912
34648	BD713	45V, 4A, 36W, >1MHz, B>750	BD 643, BD 895, BDW 23, BDW 53
34649	BD714	45V, 4A, 36W, >1MHz, B>750	BD 644, BD 896, BDW 24, BDW 54

34650	BD715	BD 713, 60V	BD 645, BD 897, BDW 23A, BDW 53A
34651	BD716	BD 714, 60V	BD 646, BD 898, BDW 24A, BDW 54A
34652	BD717	BD 713, 80V	BD 647, BD 899, BDW 23B, BDW 53B
34653	BD718	BD 713, 80V	BD 648, BD 900, BDW 24B, BDW 54B
34654	BD719	60V, 4A, 36W, >3MHz	BD 189, BD 439, BD 441, 2N5191...92
34655	BD720	60V, 4A, 36W, >3MHz	BD 190, BD 440, BD 442, 2N5194...95
34656	BD721	BD 719, 80V	BD 441, 2N5192
34657	BD722	BD 720, 80V	BD 442, 2N5195
34658	BD723	BD 719, 100V	-
34659	BD724	BD 720, 100V	-
34660	BD725	BD 719, 120V	-
34661	BD726	BD 720, 120V	-
34662	BD733	25V, 4A, 40W, >3MHz	BD 243, BD 533, BD 539, BD 943
34663	BD734	25V, 4A, 40W, >3MHz	BD 244, BD 534, BD 540, BD 944
34664	BD735	BD 733, 35V	BD 243, BD 533, BD 539, BD 947
34665	BD736	BD 734, 35V	BD 244, BD 534, BD 540, BD 948
34666	BD737	BD 733, 45V	BD 243, BD 533, BD 539A, BD 947
34667	BD738	BD 734, 45V	BD 244, BD 534, BD 540A, BD 948
34668	BD743	50V, 15A, 90W, >5MHz	BD 907
34669	BD743A	BD 743, 70V	BD 909
34670	BD743B	BD 743, 90V	BD 911
34671	BD743C	BD 743, 110V	-
34672	BD743D	BD 743, 130V	-
34673	BD743E	BD 743, 150V	-
34674	BD743F	BD 743, 170V	-
34675	BD744	50V, 15A, 90W, >5MHz	BD 908
34676	BD744A	BD 744, 70V	BD 910
34677	BD744B	BD 744, 90V	BD 912
34678	BD744C	BD 744, 110V	-
34679	BD744D	BD 744, 130V	-
34680	BD744E	BD 744, 150V	-
34681	BD744F	50V, 15A, 90W, >5MHz	BD 908
34682	BD745	50V, 20A, 115W, >5MHz	BD 249
34683	BD745A	BD 745, 70V	BD 249A
34684	BD745B	BD 745, 90V	BD 249B
34685	BD745C	BD 745, 110V	BD 249C
34686	BD745D	BD 745, 130V	BD 249D
34687	BD745E	BD 745, 150V	BD 249D
34688	BD745F	BD 745, 170V	BD 249E
34689	BD746	50V, 20A, 115W, >5MHz	BD 250
34690	BD746A	BD 746, 70V	BD 250A
34691	BD746B	BD 746, 90V	BD 250B
34692	BD746C	BD 746, 110V	BD 250C
34693	BD746D	BD 746, 130V	BD 250D
34694	BD746E	BD 746, 150V	BD 250D



34695	BD746F	BD 746, 170V	BD 250E
34696	BD750	100V, 20A, 200W, >4MHz	BD 318, 2N6029...6031, 2SA1117
34697	BD750A	BD 750, 130V	2N6030...6031, MJ 15016, 2SA1117
34698	BD750B	BD 750, 110V, 250W	-
34699	BD750C	BD 750, 140V, 250W	-
34700	BD751	100V, 20A, 200W, >4MHz	BD 317, 2N5629...5631, 2SC2608
34701	BD751A	BD 751, 130V	MJ 15015, 2N5630...5631, 2SC2608
34702	BD751B	BD 751, 110V, 250W	-
34703	BD751C	BD 751, 140V, 250W	-
34704	BD775	45V, 4A, 15W, >20MHz, B>750	BD 675, 2N6038
34705	BD776	45V, 4A, 15W, >20MHz, B>750	BD 676, 2N6035
34706	BD777	BD 775, 60V	BD 677, 2N6038
34707	BD778	BD 776, 60V	BD 678, 2N6035
34708	BD779	BD 775, 80V	BD 679, 2N6039
34709	BD780	BD 776, 80V	BD 680, 2N6036
34710	BD785	60V, 4A, 15W, >50MHz	BDX 35...37, MJE 240...244
34711	BD786	60V, 4A, 15W, >50MHz	MJE 250...254
34712	BD787	BD 785, 80V	BDX 35...37, MJE 240...244
34713	BD788	BD 786, 80V	MJE 250...254
34714	BD789	BD 785, 80V	BDX 35...37, MJE 240...244
34715	BD790	BD 786, 80V	MJE 250...254
34716	BD791	BD 785, 100V	BDX 35...37, MJE 240...244
34717	BD792	BD 786, 100V	MJE 250...254
34718	BD795	45V, 8A, 65W, >3MHz	BD 543A, BD 705, BD 805
34719	BD796	45V, 8A, 65W, >3MHz	BD 544A, BD 706, BD 806
34720	BD797	BD 795, 60V	BD 543A, BD 707, BD 807
34721	BD798	BD 796, 60V	BD 544A, BD 708, BD 808
34722	BD799	BD 795, 80V	BD 543B, BD 709, BD 809
34723	BD800	BD 796, 80V	BD 544B, BD 710, BD 810
34724	BD801	BD 795, 100V	BD 543C, BD 711
34725	BD802	BD 796, 100V	BD 544C, BD 712
34726	BD805	55V, 10A, 90W, >1,5MHz	BD 707, BD 743A, BD 907
34727	BD806	55V, 10A, 90W, >1,5MHz	BD 708, BD 744A, BD 908
34728	BD807	BD 805, 70V	BD 709, BD 743A, BD 909
34729	BD808	BD 806, 70V	BD 710, BD 744A, BD 910
34730	BD809	BD 805, 80V	BD 709, BD 743B, BD 909
34731	BD810	BD 806, 80V	BD 710, BD 744B, BD 910
34732	BD813(A)	45V, 2A, 12,5W, >3MHz	BD 175, BD 233, BD 615
34733	BD814(A)	45V, 2A, 12,5W, >3MHz	BD 176, BD 234, BD 616
34734	BD815(A)	BD 813, 60V	BD 177, BD 235, BD 617
34735	BD816(A)	BD 814, 60V	BD 178, BD 236, BD 618
34736	BD817(A)	BD 813, 100V	BD 237, BD 443
34737	BD818(A)	BD 814, 100V	BD 238
34738	BD825(A,B)	45V, 1A, 8W, 250MHz	BD 135, BD 226, BD 385, BD 839
34739	BD826(A,B)	45V, 1A, 8W, 75MHz	BD 136, BD 227, BD 386, BD 840

34740	BD827(A,B)	BD 825, 60V	BD 137, BD 228, BD 385, BD 841
34741	BD828(A,B)	BD 826, 60V	BD 138, BD 229, BD 386, BD 842
34742	BD829(A,B)	BD 825, 100V	BD 139, BD 230, BD 389, BD 843
34743	BD830(A,B)	BD 826, 100V	BD 140, BD 231, BD 390, BD 844
34744	BD833	45V, 3A, 15W, 50MHz	2SC3252...3253
34745	BD834	45V, 3A, 15W, 40MHz	2SA1288...1289
34746	BD835	BD 833, 60V	2SC3252...3253
34747	BD836	BD 834, 60V	2SA1288...1289
34748	BD837	BD 833, 100V	-
34749	BD838	BD 834, 100V	-
34750	BD839	45V, 1,5A, 10W, 125MHz	BD 135, BD 226, BD 375
34751	BD840	45V, 1,5A, 10W, 50MHz	BD 136, BD 227, BD 376
34752	BD841	BD 839, 60V	BD 137, BD 228, BD 377
34753	BD842	BD 840, 60V	BD 138, BD 229, BD 378
34754	BD843	BD 839, 100V	BD 139, BD 230, BD 379
34755	BD844	BD 840, 100V	BD 140, BD 231, BD 380
34756	BD845	100V, 1,5A, 10W, >150MHz	BD 139, BD 379, BD 843, 2SC3117, 2SD669
34757	BD846	100V, 1,5A, 10W, >150MHz	BD 140, BD 380, BD 844, 2SA1249, 2SB649
34758	BD847	BD 845, 120V	2SC3117, 2SD669
34759	BD848	BD 846, 120V	2SA1249, 2SB649
34760	BD849	BD 845, 140V	2SC3117, 2SD669
34761	BD850	BD 845, 140V	2SA1249, 2SB649
34762	BD861	45V, 4A, 15W, 7MHz, B>750	BD 675, BD 775, 2N6038
34763	BD862	45V, 4A, 15W, 7MHz, B>750	BD 676, BD 776, 2N6035
34764	BD863	BD 861, 60V	BD 677, BD 777, 2N6038
34765	BD864	BD 862, 60V	BD 678, BD 778, 2N6035
34766	BD865	BD 861, 80V	BD 679, BD 779, 2N6039
34767	BD866	BD 862, 80V	BD 680, BD 780, 2N6036
34768	BD875	60V, 1A, 9W(Tc60°), 200MHz	BDX 42...44
34769	BD876	60V, 1A, 9W(Tc60°), 200MHz	BDX 45...47
34770	BD877	BD 875, 80V	BDX 43...44
34771	BD878	BD 876, 80V	BDX 46...47
34772	BD879	BD 875, 100V	BDX 44
34773	BD880	BD 876, 100V	BDX 47
34774	BD887	30V, 20A, 62,5W, >50MHz	BD 250, BD 746
34775	BD888	BD 887, 45V	BD 250, BD 746
34776	BD895(A)	45V, 8A, 70W, >1MHz, B>750	BD 643, BDW 73, BDX 33, BDX 53
34777	BD896(A)	45V, 8A, 70W, >1MHz, B>750	BD 644, BDW 74, BDX 34, BDX 54
34778	BD897(A)	BD 895, 60V	BD 645, BDW 73A, BDX 33A, BDX 53A
34779	BD898(A)	BD 896, 60V	BD 646, BDW 74A, BDX 34A, BDX 54A
34780	BD899(A)	BD 895, 80V	BD 647, BDW 73B, BDX 33B, BDX 53B
34781	BD900(A)	BD 896, 80V	BD 648, BDW 74B, BDX 34B, BDX 54B
34782	BD901	BD 895, 100V	BD 649, BDW 73C, BDX 33C, BDX 53C
34783	BD902	BD 896, 100V	BD 650, BDW 74C, BDX 34C, BDX 54C
34784	BD905	45V, 15A, 90W, >3MHz	BD 743

34785	BD906	45V, 15A, 90W, >3MHz	BD 744
34786	BD907	BD 905, 60V	BD 743A
34787	BD908	BD 906, 60V	BD 744A
34788	BD908FI	BD 906, , 60, 35W	BDT 82F, 2SA1444, 2SA1744
34789	BD909	BD 905, 80V	BD 743B
34790	BD910	BD 906, 80V	BD 744B
34791	BD911	BD 905, 100V	BD 743C
34792	BD912	BD 906, 100V	BD 744C
34793	BD933	45V, 3A, 30W, >3MHz	BD 241, BD 533, BD 539A, BD 947
34794	BD933F	BD 933, , >14W	BD 947F, BDT 31F, 2SD1985, 2SD2012
34795	BD934	45V, 3A, 30W, >3MHz	BD 242, BD 534, BD 540A, BD 948
34796	BD934F	BD 934, , >14W	BD 948F, BDT 32F, 2SB1015, 2SB1094
34797	BD935	BD 933, 60V	BD 241A, BD 535, BD 539A, BD 949
34798	BD935F	BD 935, , >14W	BD 949F, BDT 31F, 2SD1985, 2SD2012
34799	BD936	BD 934, 60V	BD 242A, BD 536, BD 540A, BD 950
34800	BD936F	BD 936, , >14W	BD 950F, BDT 32F, 2SB1015, 2SB1094
34801	BD937	BD 933, 100V	BD 241C, BD 539C, BD 953, 2SD712
34802	BD937F	BD 937, , >14W	BD 953F, BDT 31AF, 2SD1407, 2SD1586
34803	BD938	BD 934, 100V	BD 242C, BD 540C, BD 954, 2SB682
34804	BD938F	BD 938, , >14W	BD 954F, BDT 32AF, 2SB1095, 2SB1294
34805	BD939	BD 933, 120V	BD 241C, BD 539D, BD 955, 2SD959...961
34806	BD939F	BD 939, , >14W	BD 955F, BDT 31BF, 2SC3566, 2SC4334
34807	BD940	BD 934, 120V	BD 242C, BD 540D, BD 956, 2SB867...869
34808	BD940F	BD 940, , >14W	BD 956F, BDT 32BF, 2SA1650
34809	BD941	BD 933, 140V	BD 241D, BD 243D, 2SC2516
34810	BD941F	BD 941, , >14W	BDT 31CF, 2SC3566, 2SC4334
34811	BD942	BD 934, 140V	BD 242D, BD 244D
34812	BD942F	BD 942, , >14W	BDT 32CF, 2SA1650
34813	BD943	22V, 5A, 40W, >3MHz	BD 243, BD 539, BD 795, BD 943
34814	BD943F	BD 943, , >15W	BD 949F, BDT 41F, BDT 91F, 2SD1667
34815	BD944	22V, 5A, 40W, >3MHz	BD 244, BD 540, BD 796, BD 944
34816	BD944F	BD 944, , >15W	BD 950F, BDT 42F, BDT 92F, 2SB1134
34817	BD945	BD 943, 32V	BD 243, BD 539, BD 795, BD 945
34818	BD945F	BD 945, , >15W	BD 949F, BDT 41F, BDT 91F, 2SD1667
34819	BD946	BD 944, 32V	BD 244, BD 540, BD 796, BD 946
34820	BD946F	BD 946, , >15W	BD 950F, BDT 42F, BDT 92F, 2SB1134
34821	BD947	BD 943, 45V	BD 243A, BD 539A, BD 975, BD 947
34822	BD947F	BD 947, , >15W	BD 949F, BDT 41F, BDT 91F, 2SD1667
34823	BD948	BD 944, 45V	BD 244A, BD 540A, BD 796, BD 948
34824	BD948F	BD 948, , >15W	BD 950F, BDT 42F, BDT 92F, 2SB1134
34825	BD949	60V, 5A, 40W, >3MHz	BD 243A, BD 539A, BD 543A, BD 797
34826	BD949F	BD 949, , >15W	BDT 41F, BDT 91F, BDX 77F, 2SD1667
34827	BD950	60V, 5A, 40W, >3MHz	BD 244A, BD 540A, BD 544A, BD 798
34828	BD950F	BD 950, , >15W	BDT 42F, BDT 92F, BDX 78F, 2SB1134
34829	BD951	BD 949, 80V	BD 243B, BD 539B, BD 543B, BD 799

34830	BD951F	BD 951, , >15W	BDT 41F, BDT 93F, BDX 77F, 2SD1940
34831	BD952	BD 950, 80V	BD 244B, BD 540B, BD 544B, BD 800
34832	BD952F	BD 952, , >15W	BDT 42F, BDT 94F, BDX 78F, 2SB1294
34833	BD953	BD 949, 100V	BD 243C, BD 539C, BD 543C, BD 801
34834	BD953F	BD 953, , >15W	BDT 41AF, BDT 95F, BDX 77F, 2SD1940
34835	BD954	BD 950, 100V	BD 244C, BD 540C, BD 544C, BD 802
34836	BD954F	BD 954, , >15W	BDT 42AF, BDT 96F, BDX 78F, 2SB1294
34837	BD955	BD 949, 120V	BD 543D, 2SD866
34838	BD955F	BD 955, , >15W	BDT 41BF, 2SC4335
34839	BD956	BD 950, 120V	BD 544D, 2SB870
34840	BD956F	BD 956, , >15W	BDT 42BF, 2SA1650
34841	BD975	60V, 1A, 3,6W(Tc60°), 200MHz	BDX 42...44
34842	BD976	60V, 1A, 3,6W(Tc60°), 200MHz	BDX 45...47
34843	BD977	BD 975, 80V	BDX 43...44
34844	BD978	BD 976, 80V	BDX 46...47
34845	BD979	BD 975, 100V	BDX 44
34846	BD980	BD 976, 100V	BDX 47
34847	BDB01A	45V, 0,5A, 1W, >50MHz	2SC2235, 2SD667(A), 2SD863, 2SD1292
34848	BDB01B	BDB 01A, 60V	2SC2235, 2SD667(A), 2SD863, 2SD1292
34849	BDB01C	BDB 01A, 80V	2SC2235, 2SD667(A), 2SD1292, 2SD1812
34850	BDB01D	BDB 01A, 100V	2SC2235, 2SD667(A), 2SD1292, 2SD1812
34851	BDB02A	45V, 0,5A, 1W, >50MHz	2SA965, 2SB647(A), 2SB764, 2SB1041
34852	BDB02B	BDB 02A, 60V	2SA965, 2SB647(A), 2SB764, 2SB1041
34853	BDB02C	BDB 02A, 80V	2SA965, 2SB647(A), 2SB1041, 2SB1212
34854	BDB02D	BDB 02A, 100V	2SA965, 2SA1275, 2SB647(A), 2SB1212
34855	BDB03	60V, 1A, 1W, >150MHz	2SC2235, 2SD667(A), 2SD863, 2SD1292
34856	BDB04	60V, 1A, 1W, >150MHz	2SA965, 2SB647(A), 2SB764, 2SB1041
34857	BDB05	120V, 1A, 1W, >100MHz	2SC3228, 2SD667(A), 2SD1292, 2SD1812
34858	BDB06	80V, 1A, >150MHz	2SA965, 2SA1275, 2SB647(A), 2SB1212
34859	BDC01(A...D)	BDB 01(A...D)	BDB 01(A...D)
34860	BDC02(A...D)	BDB 02(A...D)	BDB 02(A...D)
34861	BDC03	25V, 1A, 1W, >50MHz	2SC2236, 2SD863, 2SD1146, 2SD1331
34862	BDC04	25V, 1A, 1W, >50MHz	2SA966, 2SB764, 2SB978, 2SB892
34863	BDC05	300V, 0,5A, 1W, >60MHz	BF 382, BF 461, BF 758, MPSU 10
34864	BDC06	300V, 0,5A, 1W, >60MHz	BF 464, BF 761, MPSU 60
34865	BDC07	BDC 05, 250V	BF 381, BF 460, BF 757, MPSU 10
34866	BDC08	BDC 06, 250V	BF 463, BF 760, MPSU 60
34867	BDD	SM 15T 6V8C	SM 15T...
34868	BDE	SM 15T6V8CA	SM 15T...
34869	BDF	SM 15T 7V5C	SM 15T...
34870	BDG	SM 15T7V5CA	SM 15T...
34871	BDM	2SA1808-M	2SA1808
34872	BDM	2SA1733K-M	2SA1733K
34873	BDN	2SA1733K-N	2SA1733K
34874	BDN	2SA1808-N	2SA1808

34875	BDN	SM 15T 10C	SM 15T...
34876	BDP	2SA1733K-P	2SA1733K
34877	BDP	2SA1808-P	2SA1808
34878	BDP	2SB1189-P	2SB1189
34879	BDP	SM 15T 10CA	SM 15T...
34880	BDP31	70V, 3A, 1,5W, >60MHz	-
34881	BDP32	45V, 3A, 1,5W, >60MHz	-
34882	BDQ	2SB1189-Q	2SB1189
34883	BDR	2SB1189-R	2SB1189
34884	BDS	SM 15T 12C	SM 15T...
34885	BDS201..BDS204	BD 201..204, 3A, 8W	-
34886	BDS60(A..C)	BDT 60..., 3A, 8W	-
34887	BDS61(A..C)	BDT 61..., 3A, 8W	-
34888	BDS643..BDS652	BD 643..652, 3A, 8W	-
34889	BDS77	BDX 77, 3A, 8W	-
34890	BDS78	BDX 78, 3A, 8W	-
34891	BDS933..BDS942	BD 933..942, 3A, 8W	-
34892	BDS943..BDS948	BD 943..948, 3A, 8W	-
34893	BDS949..BDS956	BD 949..956, 3A, 8W	-
34894	BDT	SM 15T 12CA	SM 15T...
34895	BDT20	130V, 8A, 62,5W, B>750	BDX 54E
34896	BDT21	130V, 8A, 62,5W, B>750	BDX 53, 2SD1386, 2SD1025, 2SD1500
34897	BDT29	80V, 1A, 30W, >3MHz	BD 239B, BD 241B, BD 537, BD 937
34898	BDT29A	BDT 29, 100V	BD 239C, BD 241C, BD 937, 2SD1138
34899	BDT29AF	BDT 29, , 100V, >15W	BD 937F, BDT 31AF, 2SC3298, 2SD1586
34900	BDT29B	BDT 29, 120V	BD 239C, BD 241C, BD 939, 2SD1138
34901	BDT29BF	BDT 29, , 120V, >15W	BD 939F, BDT 31BF, 2SC3298, 2SD1587
34902	BDT29C	BDT 29, 140V	BD 239D, BD 241D, 2SD1138, 2SD1459
34903	BDT29CF	BDT 29, , 140V, >15W	BD 941F, BDT 31CF, 2SC3298, 2SD1587
34904	BDT29DF	BDT 29, , 160V, >15W	BDT 31DF, 2SC3298(A..B), 2SD1587
34905	BDT29F	BDT 29, , >15W	BD 937F, BDT 31F, 2SC3851, 2SD1408
34906	BDT30	80V, 1A, 30W, >3MHz	BD 240B, BD 242B, BD 538, BD 938
34907	BDT30A	BDT 30, 100V	BD 240C, BD 242C, BD 938, 2SB861
34908	BDT30AF	BDT 30, , 100V, >15W	BD 938F, BDT 32AF, 2SA1306, 2SB1095
34909	BDT30B	BDT 30, 120V	BD 240C, BD 242C, BD 940, 2SB861
34910	BDT30BF	BDT 30, , 120V, >15W	BD 940F, BDT 32BF, 2SA1306, 2SB1096
34911	BDT30C	BDT 30, 140V	BD 240D, BD 242D, 2SB861, 2SB1037
34912	BDT30CF	BDT 30, , 140V, >15W	BD 942F, BDT 32CF, 2SA1306, 2SB1096
34913	BDT30DF	BDT 30, , 160V, >14W	BDT 32DF, 2SA1306(A..B), 2SB1096
34914	BDT30F	BDT 30, , >15W	BD 938F, BDT 32F, 2SA1635, 2SB1017
34915	BDT31	80V, 3A, 40W, >3MHz	BD 241B, BD 537, BD 539B, BD 937
34916	BDT31A	BDT 31, 100V	BD 241C, BD 243C, BD 539C, BD 937
34917	BDT31AF	BDT 31, , 100V, >15W	BD 937F, BD 953F, BDT 41AF, 2SD1586
34918	BDT31B	BDT 31, 120V	BD 241C, BD 243C, BD 539D, BD 939
34919	BDT31BF	BDT 31, , 120V, >15W	BD 939F, BD 955F, BDT 41BF, 2SC3566

34920	BDT31C	BDT 31, 140V	BD 241D, BD 243D, BD 941
34921	BDT31CF	BDT 31, , 140V, >15W	BD 941F, BDT 41CF, 2SC3566, 2SC4334
34922	BDT31DF	BDT 31, , 160V, >15W	2SC4153
34923	BDT31F	BDT 31, , >15W	BD 937F, BD 951F, BDT 41F, 2SD1586
34924	BDT32	80/40V, 3A, 40W, >3MHz	BD 242B, BD 538, BD 540B, BD 938
34925	BDT32A	BDT 32, 60/60V	BD 242B, BD 244B, BD 540B, BD 938
34926	BDT32AF	BDT 32, , 60/60V, >15W	BD 938F, BD 954F, BDT 42AF, 2SB1095
34927	BDT32B	BDT 32, 80/80V	BD 242C, BD 244C, BD 540D, BD 940
34928	BDT32BF	BDT 32, , 80/80V, >15W	BD 940F, BD 956F, BDT 42BF, 2SA1650
34929	BDT32C	BDT 32, 100/100V	BD 242C, BD 244C, BD 540D, BD 940
34930	BDT32CF	BDT 32, , 100/100V, >15W	BD 942F, BDT 42CF, 2SA1650
34931	BDT32DF	BDT 32, , 160/120V, >15W	-
34932	BDT32F	BDT 32, , >15W	BD 938F, BD 952F, BDT 42F, 2SB1095
34933	BDT41	80V, 6A, 65W, >3MHz	BD 243B, BD 543B, BD 799, BD 809
34934	BDT41A	BDT 41, 100V	BD 243C, BD 543C, BD 801, 2SD866
34935	BDT41AF	BDT 41, , 100V, >20W	BDT 95F, BDX 77F, 2SD1411, 2SD1588
34936	BDT41B	BDT 41, 120V	BD 243C, BD 543D, 2SD866
34937	BDT41BF	BDT 41, , 120V, >20W	2SC4335
34938	BDT41C	BDT 41, 140V	BD 243D, 2SC4329
34939	BDT41CF	BDT 41, , 140V, >20W	2SC4335
34940	BDT41F	BDT 41, , >20W	BDT 93F, BDX 77F, 2SD1411, 2SD1588
34941	BDT42	80V, 6A, 65W, >3MHz	BD 244B, BD 544B, BD 800, BD 810
34942	BDT42A	BDT 42, 100V	BD 244C, BD 544C, BD 802, 2SB870
34943	BDT42AF	BDT 42, , 100V, >20W	BDT 96F, BDX 78F, 2SB1018, 2SB1290
34944	BDT42B	BDT 42, 120V	BD 244C, BD 544D, 2SB870
34945	BDT42BF	BDT 42, , 120V, >20W	2SA1651
34946	BDT42C	BDT 42, 140V	BD 244D
34947	BDT42CF	BDT 42, , 140V, >20W	2SA1651
34948	BDT42F	BDT 42, , >20W	BDT 94F, BDX 78F, 2SB1018, 2SB1290
34949	BDT51	60V, 15A, 90W	BD 907, BDT 81
34950	BDT52	60V, 15A, 90W	BD 908, BDT 82
34951	BDT53	BDT 51, 80V	BD 909, BDT 83
34952	BDT54	BDT 52, 80V	BD 910, BDT 84
34953	BDT55	BDT 51, 100V	BD 911, BDT 85
34954	BDT56	BDT 52, 100V	BD 912, BDT 86
34955	BDT57	BDT 51, 120V	BDT 87
34956	BDT58	BDT 52, 120V	BDT 88
34957	BDT60	60V, 4A, 50W, >10MHz, B>750	BD 716, BDW 24A, BDW 54A, BDW 64A
34958	BDT60A	BDT 60, 80V	BD 718, BDW 24B, BDW 54B, BDW 64B
34959	BDT60AF	BDT 60, , 80V, >17W	BD 648F, 2SB1342, 2SB1282, 2SB1024
34960	BDT60B	BDT 60, 100V	BDW 24C, BDW 54C, BDW 64C
34961	BDT60BF	BDT 60, , 100V, >17W	BD 650F, 2SB1024, 2SB1282, 2SB1098
34962	BDT60C	BDT 60, 120V	BDW 54D, BDW 64D
34963	BDT60CF	BDT 60, , 120V, 17W	BD 652F, 2SB1193, 2SB1340
34964	BDT60F	BDT 60, , >17W	BD 646F, 2SB1257, 2SB1223, 2SB1342



34965	BDT60L	BDT 60, 45V	BD 714, BDW 24, BDW 54, BDW 64
34966	BDT61	60V, 4A, 50W, >10MHz, B>750	BD 715, BDW 23A, BDW 53A, BDW 63A
34967	BDT61A	BDT 61, 80V	BD 717, BDW 23B, BDW 53B, BDW 63B
34968	BDT61AF	BDT 61, , 80V, >17W	BD 645F, 2SD1933, 2SD2014, 2SD1788
34969	BDT61B	BDT 61, 100V	BDW 23C, BDW 53C, BDW 63C
34970	BDT61BF	BDT 61, , 100V, >17W	BD 647F, 2SD1414, 2SD1788, 2SD1589
34971	BDT61C	BDT 61, 120V	BDW 53D, BDW 63D, 2SD1147
34972	BDT61CF	BDT 61, , 120V, >17W	BD 649F, 2SD1785, 2SD1590
34973	BDT61F	BDT 61, , >17W	BD 643F, 2SD1796, 2SD1825, 2SD1933
34974	BDT61L	BDT 61, 45V	BD 713, BDW 23, BDW 53, BDW 63
34975	BDT62	B>1000	BDT 64, BDW 94A, BDX 34A
34976	BDT62A	BDT 62, 80V	BDT 64A, BDW 94B, BDX 34B
34977	BDT62AF	BDT 62, , 80V, >17W	BDT 64AF, 2SB1100, 2SB1284, 2SB1259
34978	BDT62B	BDT 62, 100V	BDT 64B, BDW 94C, BDX 34C
34979	BDT62BF	BDT 62, , 100V, >17W	BDT 64BF, 2SB1100, 2SB1284, 2SB1259
34980	BDT62C	BDT 62, 120V	BDT 64C, BDX 34D
34981	BDT62CF	BDT 62, , 120V, >17W	BDT 64CF
34982	BDT62F	BDT 62, , >17W	BDT 64F, 2SB1225, 2SB1100, 2SB1284
34983	BDT63	B>1000	BDT 65, BDW 93A, BDX 33A
34984	BDT63A	BDT 63, 80V	BDT 65A, BDW 93B, BDX 33B
34985	BDT63AF	BDT 63, , 80V, >17W	BDT 65AF, 2SD1793, 2SD1591
34986	BDT63B	BDT 63, 100V	BDT 65B, BDW 93C, BDX 33C
34987	BDT63BF	BDT 63, , 100V, >17W	BDT 65BF, 2SD1793, 2SD1591
34988	BDT63C	BDT 63, 120V	BDT 65C, BDX 33D
34989	BDT63CF	BDT 63, , 120V, >17W	BDT 65CF, 2SD1591
34990	BDT63F	BDT 63, , >17W	BDT 65F, 2SD1827, 2SD1793, 2SD1591
34991	BDT64	B>1000	BDW 45, BDW 94A
34992	BDT64A	BDT 64, 80V	BDW 46, BDW 94B
34993	BDT64AF	BDT 64, , 80V, >22W	-
34994	BDT64B	BDT 64, 100V	BDW 47, BDW 94C
34995	BDT64BF	BDT 64, , 100V, >22W	-
34996	BDT64C	BDT 64, 120V	-
34997	BDT64CF	BDT 64, , 120V, >22W	-
34998	BDT64F	BDT 64, , >22W	2SB1351
34999	BDT65	B>1000	BDW 40, BDW 93A
35000	BDT65A	BDT 65, 80V	BDW 41, BDW 93B
35001	BDT65AF	BDT 65, , 80V, >22W	BDW 93B,C
35002	BDT65B	BDT 65, 100V	BDW 42, BDW 93C
35003	BDT65BF	BDT 65, , 100V, >22W	BDW 93C
35004	BDT65C	BDT 65, 120V	-
35005	BDT65CF	BDT 64, , 120V, >22W	-
35006	BDT65F	BDT 65, , >22W	BDW 93A...C
35007	BDT81	60V, 15A, 125W, 10MHz	BD 907
35008	BDT81F	BDT 81, , >21W	2SD1964
35009	BDT82	60V, 15A, 125W, 20MHz	BD 908

35010	BDT82F	BDT 82, , >21W	-
35011	BDT83	BDT 81, 80V	BD 909
35012	BDT83F	BDT 83, , >21W	2SD1964
35013	BDT84	BDT 82, 80V	BD 910
35014	BDT84F	BDT 84, , >21W	-
35015	BDT85	BDT 81, 100V	BD 911
35016	BDT85F	BDT 85, , >21W	2SD1964
35017	BDT86	BDT 82, 100V	BD 912
35018	BDT86F	BDT 86, , >21W	-
35019	BDT87	BDT 81, 120V	-
35020	BDT87F	BDT 87, , >21W	2SD1964
35021	BDT88	BDT 82, 120V	-
35022	BDT88F	BDT 88, , >21W	-
35023	BDT91	60V, 10A, 90W, >4MHz	BD 743A, BD 807, BD 907
35024	BDT91F	BDT 91, , >20W	BDT 81F, 2SD1964
35025	BDT92	60V, 10A, 90W, >4MHz	BD 744A, BD 808, BD 908
35026	BDT92F	BDT 92, , >20W	BDT 82F
35027	BDT93	BDT 91, 80V	BD 743B, BD 809, BD 909
35028	BDT93F	BDT 93, , >20W	BDT 83F, 2SD1964
35029	BDT94	BDT 92, 80V	BD 744B, BD 810, BD 910
35030	BDT94F	BDT 93, , >20W	BDT 84F
35031	BDT95	BDT 91, 100V	BD 743C, BD 911
35032	BDT95F	BDT 95, , >20W	BDT 85F, 2SD1964
35033	BDT96	BDT 92, 100V	BD 744C, BD 912
35034	BDT96F	BDT 96, , >20W	BDT 86F
35035	BDV10	>30MHz	MJE 15028, 2SC2527, 2SD772
35036	BDV11	BDV 10, 140V	MJE 15030, 2SD772
35037	BDV12	BDV 10	MJE 15028, 2SC2527, 2SD772
35038	BDV13	45V, 4A, 36W, >3MHz, B>750	BD 713, BDW 23, BDW 53, BDW 63
35039	BDV14	45V, 4A, 36W, >3MHz, B>750	BD 714, BDW 24, BDW 54, BDW 64
35040	BDV15	BDV 13, 60V	BD 715, BDW 23A, BDW 53A, BDW 63A
35041	BDV16	BDV 14, 60V	BD 716, BDW 24A, BDW 54A, BDW 64A
35042	BDV17	BDV 13, 80V	BD 717, BDW 23B, BDW 53B, BDW 63B
35043	BDV18	BDV 14, 80V	BD 718, BDW 24B, BDW 54B, BDW 64B
35044	BDV33	45V, 5A, 40W, >3MHz	BD 243, BD 539A, BD 543A, BD 947
35045	BDV34	45V, 5A, 40W, >3MHz	BD 244, BD 540A, BD 544A, BD 948
35046	BDV35	BDV 33, 60V	BD 243A, BD 539A, BD 543A, BD 949
35047	BDV36	BDV 34, 60V	BD 244A, BD 540A, BD 544A, BD 950
35048	BDV37	BDV 33, 80V	BD 243B, BD 539B, BD 543B, BD 951
35049	BDV38	BDV 34, 80V	BD 244B, BD 540B, BD 544B, BD 952
35050	BDV45	B>750	BD 645, BD 897, BDW 73A, BDX 53A
35051	BDV46	B>750	BD 646, BD 898, BDW 74A, BDX 54A
35052	BDV47	BDV 45, 80V	BD 647, BD 899, BDW 73B, BDX 53B
35053	BDV48	BDV 46, 80V	BD 648, BD 900, BDW 74B, BDX 54B
35054	BDV49	BDV 45, 100V	BD 649, BD 901, BDW 73C, BDX 53C

35055	BDV50	BDV 46, 100V	BD 650, BD 902, BDW 74C, BDX 54C
35056	BDV64	60V, 12A, 125W, B>1000	BDV 66, BDW 84A
35057	BDV64A	BDV 64, 80V	BDV 66A, BDW 84B
35058	BDV64AF	BDV 64A, , >31W	2SB1382, 2SB1448
35059	BDV64B	BDV 64, 100V	BDV 66B, BDW 84C
35060	BDV64BF	BDV 64B, , >31W	2SB1382, 2SB1448
35061	BDV64C	BDV 64, 120V	BDV 66C, BDW 84D
35062	BDV64CF	BDV 64C, , >31W	2SB1382
35063	BDV64F	BDV 64, , >31W	2SB1352, 2SB1382, 2SB1448
35064	BDV65	60V, 12A, 125W, B>1000	BDV 67, BDW 83A
35065	BDV65A	BDV 65, 80V	BDV 67A, BDW 83B
35066	BDV65AF	BDV 65A, , >31W	2SD2082
35067	BDV65B	BDV 65, 100V	BDV 67B, BDW 83C
35068	BDV65BF	BDV 65B, , >31W	2SD2082
35069	BDV65C	BDV 65, 120V	BDV 67C, BDW 83D
35070	BDV65CF	BDV 65C, , >31W	2SD2082
35071	BDV65F	BDV 65, , >31W	2SD2082
35072	BDV66	60V, 16A, 200W, B>1000	BDW 84A, 2SB1079
35073	BDV66A	BDV 66, 100V	BDW 84C, 2SB1079
35074	BDV66AF	BDV 66A, , >35W	2SB1382, 2SB1448
35075	BDV66B	BDV 66, 120V	BDW 84D
35076	BDV66BF	BDV 66B, , >35W	2SB1382
35077	BDV66C	BDV 66, 140V	-
35078	BDV66CF	BDV 66C, , >35W	-
35079	BDV66D	BDV 66, 160V	-
35080	BDV66DF	BDV 66D, , >35W	-
35081	BDV67	60V, 16A, 200W, B>1000	BDW 83A, 2SD1559
35082	BDV67A	BDV 67, 100V	BDW 83C, 2SD1559
35083	BDV67AF	BDV 67A, , >35W	2SD2082
35084	BDV67B	BDV 67, 120V	BDW 83D
35085	BDV67BF	BDV 67B, , >35W	2SD2082
35086	BDV67C	BDV 67, 140V	-
35087	BDV67CF	BDV 67C, , >35W	-
35088	BDV67D	BDV 67, 160V	-
35089	BDV67DF	BDV 67D, , >35W	-
35090	BDV91	60V, 10A, 100W, >3MHz	BD 245A, BD 745A
35091	BDV92	60V, 10A, 100W, >4MHz	BD 246A, BD 746A
35092	BDV93	BDV 91, 80V	BD 245B, BD 745B
35093	BDV94	BDV 92, 80V	BD 246B, BD 746B
35094	BDV95	BDV 91, 100V	BD 245C, BD 745C
35095	BDV96	BDV 92, 100V	BD 246C, BD 746C
35096	BDW	SM 15T 15C	SM 15T...
35097	BDW10(A)	140V, 15A, 180W, >1MHz	BDW 30, MJ 15015, 2SC1585, 2SC2607...08
35098	BDW12(A)	BDW 10, 160V	BDW 34, MJ 15015, 2SC1585, 2SC2607...08
35099	BDW14(A)	BDW 10, 180V	BDW 34, MJ 15015, 2SC1585, 2SC2607...08

35100	BDW16(A)	BDW 10, 200V	BDW 36, MJ 15015, 2SC1585, 2SC2607...08
35101	BDW21	45V, 10A, 90W, >3MHz	BD 245, BD 311, BD 315, BDW 51
35102	BDW21A	BDW 21, 60V	BD 245A, BD 311, BD 315, BDW 51A
35103	BDW21B	BDW 21, 80V	BD 245B, BD 313, BD 315, BDW 51B
35104	BDW21C	BDW 21, 100V	BD 245C, BD 317, BDW 51C
35105	BDW22	45V, 10A, 90W, >3MHz	BD 246, BD 312, BD 316, BDW 52
35106	BDW22A	BDW 22, 60V	BD 246A, BD 312, BD 316, BDW 52A
35107	BDW22B	BDW 22, 80V	BD 246B, BD 314, BD 316, BDW 52B
35108	BDW22C	BDW 22, 100V	BD 246C, BD 316, BDW 52C
35109	BDW23	45V, 6A, 50W, B>750	BD 643, BD 895, BDW 63, BDX 53
35110	BDW23A	BDW 23, 60V	BD 645, BD 897, BDW 63A, BDX 53A
35111	BDW23B	BDW 23, 80V	BD 647, BD 899, BDW 63B, BDX 53B
35112	BDW23C	BDW 23, 100V	BD 649, BD 901, BDW 63C, BDX 53C
35113	BDW24	45V, 6A, 50W, B>750	BD 644, BD 896, BDW 64, BDX 54
35114	BDW24A	BDW 24, 60V	BD 646, BD 898, BDW 64A, BDX 54A
35115	BDW24B	BDW 24, 80V	BD 648, BD 900, BDW 64B, BDX 54B
35116	BDW24C	BDW 24, 100V	BD 650, BD 902, BDW 64C, BDX 54C
35117	BDW25	130V, 5A, 26W(Tc45°), 30MHz	BDX 25, BDV 11, MJE 15030, 2SD772
35118	BDW26	Ub22..30V, Ib<0,8mA, Itsm1A	-
35119	BDW30	140V, 30A, 250W, >1MHz	2N6276...6277
35120	BDW32	BDW 26, Ub28..36V	A9903, D32
35121	BDW32	BDW 30, 160V	2N6276...6277
35122	BDW34	BDW 30, 180V	2N6277
35123	BDW36	BDW 30, 200V	-
35124	BDW38	BDW 26, Ub34..42V	-
35125	BDW39	B>1000	-
35126	BDW40	BDW 39, 60V	-
35127	BDW41	BDW 39, 80V	-
35128	BDW42	BDW 39, 100V	-
35129	BDW44	B>1000	-
35130	BDW45	BDW 44, 60V	-
35131	BDW46	BDW 44, 80V	-
35132	BDW47	BDW 44, 100V	-
35133	BDW51	45V, 15A, 125W, >3MHz	BD 249, BD 315, BDY 55, 2N5629...31
35134	BDW51A	BDW 51, 60V	BD 249A, BD 315, BDY 55, 2N5629...31
35135	BDW51B	BDW 51, 80V	BD 249B, BD 315, BDY 55, 2N5629...31
35136	BDW51C	BDW 51, 100V	BD 249C, BD 317, BDY 55, 2N5629...31
35137	BDW52	45V, 15A, 125W, >3MHz	BD 250, BD 316, 2N6029...6031
35138	BDW52A	BDW 52, 60V	BD 250A, BD 316, 2N6029...6031
35139	BDW52B	BDW 52, 80V	BD 250B, BD 316, 2N6029...6031
35140	BDW52C	BDW 52, 100V	BD 250C, BD 318, 2N6029...6031
35141	BDW53	45V, 4A, 40W, >1MHz, B>750	BD 713, BDW 23, BDW 63
35142	BDW53A	BDW 53, 60V	BD 715, BDW 23A, BDW 63A
35143	BDW53B	BDW 53, 80V	BD 717, BDW 23B, BDW 63B
35144	BDW53C	BDW 53, 100V	BDW 23C, BDW 63C

35145	BDW53D	BDW 53, 120V	BDW 63D, 2SD1147
35146	BDW54	45V, 4A, 40W, >1MHz, B>750	BD 714, BDW 24, BDW 64
35147	BDW54A	BDW 54, 60V	BD 716, BDW 24A, BDW 64A
35148	BDW54B	BDW 54, 80V	BD 718, BDW 24B, BDW 64B
35149	BDW54C	BDW 54, 100V	BDW 24C, BDW 64C
35150	BDW54D	BDW 54, 120V	BDW 64D
35151	BDW55	BD 135, hi-rel Version	BD 135
35152	BDW56	BD 136, hi-rel Version	BD 136
35153	BDW57	BD 137, hi-rel Version	BD 137
35154	BDW58	BD 138, hi-rel Version	BD 138
35155	BDW59	BD 139, hi-rel Version	BD 139
35156	BDW60	BD 140, hi-rel Version	BD 140
35157	BDW63	45V, 6A, 60W, >1MHz, B>750	BD 643, BD 895, BDW 23, BDX 53
35158	BDW63A	BDW 63, 60V	BD 645, BD 897, BDW 23A, BDX 53A
35159	BDW63B	BDW 63, 80V	BD 647, BD 899, BDW 23B, BDX 53B
35160	BDW63C	BDW 63, 100V	BD 649, BD 901, BDW 23C, BDX 53C
35161	BDW63D	BDW 63, 120V	BD 651, BDT 21, BDX 53E
35162	BDW64	45V, 6A, 60W, >1MHz, B>750	BD 644, BD 896, BDW 24, BDX 54
35163	BDW64A	BDW 64, 60V	BD 646, BD 898, BDW 24A, BDX 54A
35164	BDW64B	BDW 64, 80V	BD 648, BD 900, BDW 24B, BDX 54B
35165	BDW64C	BDW 64, 100V	BD 650, BD 902, BDW 24C, BDX 54C
35166	BDW64D	BDW 64, 120V	BD 652, BDT 20, BDX 54E
35167	BDW69	40V, 2A, 12,5W	-
35168	BDW70	BDW 69, 60V	-
35169	BDW71	BDW 69, 90V	-
35170	BDW73	45V, 8A, 80W, >1MHz, B>750	BD 643, BD 895, BDX 33, BDX 53
35171	BDW73A	BDW 73, 60V	BD 645, BD 897, BDX 33A, BDX 53A
35172	BDW73B	BDW 73, 80V	BD 647, BD 899, BDX 33B, BDX 53B
35173	BDW73C	BDW 73, 100V	BD 649, BD 901, BDX 33C, BDX 53C
35174	BDW73D	BDW 73, 120V	BD 651, BDX 33D, BDX 53E
35175	BDW74	45V, 8A, 80W, >1MHz, B>750	BD 644, BD 896, BDX 33, BDX 53
35176	BDW74A	BDW 74, 60V	BD 646, BD 898, BDX 33A, BDX 53A
35177	BDW74B	BDW 74, 80V	BD 648, BD 900, BDX 33B, BDX 53B
35178	BDW74C	BDW 74, 100V	BD 650, BD 902, BDX 33C, BDX 53C
35179	BDW74D	BDW 74, 120V	BD 652, BDX 33D, BDX 53E
35180	BDW83	B>750	BDV 67
35181	BDW83A	BDW 83, 60V	BDV 67
35182	BDW83B	BDW 83, 80V	BDV 67A
35183	BDW83C	BDW 83, 100V	BDV 67A
35184	BDW83D	BDW 83, 120V	BDV 67B
35185	BDW84	B>750	BDV 66
35186	BDW84A	BDW 84, 60V	BDV 66
35187	BDW84B	BDW 84, 80V	BDV 66A
35188	BDW84C	BDW 84, 100V	BDV 66A
35189	BDW84D	BDW 84, 120V	BDV 66B

35190	BDW91	180V, 4A, 10W(Tc25°), 20MHz	2SC3186, 2SD1121
35191	BDW92	180V, 4A, 10W(Tc25°), 20MHz	-
35192	BDW93	B>750	BDT 65, BDW 39
35193	BDW93A	BDW 93, 60V	BDT 65, BDW 40
35194	BDW93B	BDW 93, 80V	BDT 65A, BDW 41
35195	BDW93C	BDW 93, 100V	BDT 65B, BDW 42
35196	BDW93CFI	BDW 93C, , 40W	BDT 65BF...CF, 2SC 4063
35197	BDW94	B>750	BDT 64, BDW 44
35198	BDW94A	BDW 94, 60V	BDT 64, BDW 45
35199	BDW94B	BDW 94, 80V	BDT 64A, BDW 46
35200	BDW94C	BDW 94, 100V	BDT 64B, BDW 47
35201	BDW94CFI	BDW 94C, , 40W	BDT 64BF...CF
35202	BDX	SM 15T 15CA	SM 15T...
35203	BDX10(C,H)	100V, 15A, 117W, >0,8MHz	BD 317, BD 745C, BDW 51C, 2N3055
35204	BDX11	160V, 10A, 117W, >0,8MHz	BDW 12, 2N3442, 2SD733, 2SD1047
35205	BDX12	140V, 10A, 100W, >0,8MHz	BDW 10, 2N5631, 2SC1584, 2SD1047
35206	BDX13	50V, 15A, 117W, >0,8MHz	BD 315, BD 745, BDW 51A, 2N5881
35207	BDX14	90V, 4A, 29W, >4MHz	BD 244B, BD 954, 2N5954, 2SB550
35208	BDX15	-/70V, 10A, 117W, >0,8MHz	BD 246B, BD 314, BDW 22A, 2N5875
35209	BDX16	160V, 3A, 25W, 4MHz	BD 242D, BUX 66, MJE 5850, 2SB720
35210	BDX18	100V, 15A, 117W, 4MHz	BD 318, BD 746C, BDW 52C, MJ 2955
35211	BDX18N	BDX 18, 70V	BD 316, BD 746B, BDW 52B, MJ 2955
35212	BDX20	160V, 10A, 117W, >4MHz	BD 245D, 2SA1147, 2SB600, 2SB697, 2SB817
35213	BDX22	160V, 10A, 37,5W, >0,8MHz	BD 743F, BUV 27, 2SC2867
35214	BDX23	95V, 15A, 117W, >0,8MHz	BD 317, BD 745C, BDW 51C, 2N3055
35215	BDX24	50V, 4A, 29W, >0,8MHz	BD 243, BD 535, 2N4231A, 2N6374
35216	BDX25	130V, 5A, 34W(Tc45°), 30MHz	BDW 25, BDV 11, MJE 15030, 2SD772
35217	BDX26	40V, 5A, 40W, >30MHz	BD 312, BD 246, 2SA1185, 2SA1292
35218	BDX27	40V, 5A, 50W(Tc45°), 50MHz	BD 244, BD 948, 2SA1012, 2SA1289
35219	BDX28	BDX 27, 60V	BD 244A, BD 950, 2SA1012, 2SA1289
35220	BDX29	BDX 27, 80V	BD 244B, BD 952, MJE 15029, 2SA1289
35221	BDX30	BDX 27, 125V	MJE 15031, 2SB869
35222	BDX31	2200V, 4A, 40W	2SD621, 2SD838
35223	BDX32	BDX 31, 1700V	2SD784...785
35224	BDX33	B>750	BDT 63, BDT 65, BDW 93
35225	BDX33A	BDX 33, 60V	BDT 63, BDT 65, BDW 93A
35226	BDX33B	BDX 33, 80V	BDT 63A, BDT 65A, BDW 93B
35227	BDX33C	BDX 33, 100V	BDT 63B, BDT 65B, BDW 93C
35228	BDX33D	BDX 33, 120V	BDT 63C, BDT 65C, 2SD1126, 2SD 1607
35229	BDX33E	BDX 33, 140V	2SD1500
35230	BDX34	B>750	BDT 62, BDT 64, BDW 94
35231	BDX34A	BDX 34, 60V	BDT 62, BDT 64, BDW 94A
35232	BDX34B	BDX 34, 80V	BDT 62A, BDT 64A, BDW 94B
35233	BDX34C	BDX 34, 100V	BDT 62B, BDT 64B, BDW 94C
35234	BDX34D	BDX 34, 120V	BDT 62C, BDT 64C



35235	BDX35	100MHz	-
35236	BDX36	BDX 35, 120/60V	-
35237	BDX37	BDX 35, 120/80V	-
35238	BDX40	100V, 20A, 150W, >0,8MHz	BDY 29, MJ 802, 2N3772, 2SD797
35239	BDX41	50V, 30A, 150W, >0,8MHz	BDY 29, MJ 802, 2N3771, 2SD630
35240	BDX42	60V, 1A, 5W(Tc100°), 350MHz	-
35241	BDX43	BDX 42, 80V	-
35242	BDX44	BDX 42, 100V	-
35243	BDX45	60V, 1A, 5W(Tc100°), 350MHz	-
35244	BDX46	BDX 45, 80V	-
35245	BDX47	BDX 45, 100V	-
35246	BDX50	160V, 16A, 150W, >0,8MHz	BD 249D, BD 745E, 2N3773, 2SC2608
35247	BDX51	140V, 10A, 120W, >0,8MHz	BD745E, BDW 10, 2N4348, 2N5634, 2SD425
35248	BDX53	45V, 8A, 60W, 20MHz, B>750	BD 643, BD 895, BDW 73, BDX 33
35249	BDX53A	BDX 53, 60V	BD 645, BD 897, BDW 73A, BDX 33A
35250	BDX53B	BDX 53, 80V	BD 647, BD 899, BDW 73B, BDX 33B
35251	BDX53C	BDX 53, 100V	BD 649, BD 901, BDW 73C, BDX 33C
35252	BDX53E	BDX 53, 140V	BDX 33E, 2SD1386, 2SD1500
35253	BDX53F	BDX 53, 160V	2SD1025
35254	BDX53H	BDX 53, 60V	BD 645, BD 897, BDW 73A, BDX 33A
35255	BDX53S	150V, 6A, 15W(Tc25°), 20MHz	-
35256	BDX54	45V, 8A, 60W, 20MHz, B>750	BD 644, BD 896, BDW 74, BDX 34
35257	BDX54A	BDX 54, 60V	BD 646, BD 898, BDW 74A, BDX 34A
35258	BDX54B	BDX 54, 80V	BD 648, BD 900, BDW 74B, BDX 34B
35259	BDX54C	BDX 54, 100V	BD 650, BD 902, BDW 74C, BDX 34C
35260	BDX54E	BDX 54, 140V	-
35261	BDX54F	BDX 54, 160V	-
35262	BDX54H	BDX 54, 60V	BD 646, BD 898, BDW 74A, BDX 34A
35263	BDX54S	150V, 6A, 15W(Tc25°), 20MHz	-
35264	BDX55	100V, 7A, 10W(Tc25°), >4MHz	BU 125, BUY 47...48, BUY 68, BUY 81
35265	BDX56	BDX 55, 120V	BU 125, BUY 47...48, BUY 68, BUY 81
35266	BDX57	BDX 55, 140V	BUY 47...48, BUY 68, BUY 81
35267	BDX60	100V, 15A, 150W, >0,8MHz	BD 317, BDW 51C, 2N3772, 2N5629...31
35268	BDX61	BDX 60, 80V	BD 315, BDW 51B, 2N3772, 2N5629...31
35269	BDX62	B>1000	BDX 84A, BDX 86A, MJ 900, MJ 2500
35270	BDX62A	BDX 62, 80/80V	BDX 84B, BDX 86B, MJ 901, MJ 2501
35271	BDX62B	BDX 62, 100/100V	BDX 84C, BDX 86C, 2SB638...639
35272	BDX62C	BDX 62, 120/120V	BDX 64C
35273	BDX62L	BDX 62, 45/45V	BDX 84A, BDX 86, MJ 900, MJ 2500
35274	BDX63	B>1000	BDX 83A, BDX 85A, MJ 1000, MJ 3000
35275	BDX63A	BDX 63, 100/80V	BDX 83B, BDX 85B, MJ 1001, MJ 3001
35276	BDX63B	BDX 63, 120/100V	BDX 83C, BDX 85C, 2SD628...629
35277	BDX63C	BDX 63, 140/120V	BDX 65C
35278	BDX63L	BDX 63, 60/45V	BDX 83A, BDX 85, MJ 1000, MJ 3000
35279	BDX64	7MHz,B>1000	BDX 66, BDX 88A, MJ 4030, 2N6050

35280	BDX64A	BDX 64, 80/80V	BDX 66A, BDX 88B, MJ 4031, 2N6051
35281	BDX64B	BDX 64, 100/100V	BDX 66B, BDX 88C, MJ 4032, 2N6052
35282	BDX64C	BDX 64, 120/120V	BDX 66C
35283	BDX64L	BDX 64, 45/45V	BDX 66L, BDX 88, MJ 4030, 2N6050
35284	BDX65	7MHz,B>1000	BDX 67, BDX 87A, MJ 4033, 2N6057
35285	BDX65A	BDX 65, 100/80V	BDX 67A, BDX 87B, MJ 4034, 2N6058
35286	BDX65B	BDX 65, 120/100V	BDX 67B, BDX 87C, MJ 4035, 2N6059
35287	BDX65C	BDX 65, 140/120V	BDX 67C
35288	BDX65L	BDX 65, 60/45V	BDX 67L, BDX 87, MJ 4033, 2N6057
35289	BDX66	7MHz,B>1000	BDW 84A...D, MJ 4030, 2N6285
35290	BDX66A	BDX 66, 80/80V	BDW 84B...D, MJ 4031, 2N6286
35291	BDX66B	BDX 66, 100/100V	BDW 84C...D, MJ 4032, 2N6287
35292	BDX66C	BDX 66, 120/120V	-
35293	BDX66L	BDX 66, 45/45V	BDW 84(A...D), MJ 4030, 2N6285
35294	BDX67	7MHz,B>1000	BDW 83A...D, MJ 4033, 2N6282
35295	BDX67A	BDX 67, 100/80V	BDW 83C...D), MJ 4034, 2N6283
35296	BDX67B	BDX 67, 120/100V	MJ 4035, 2N6284
35297	BDX67C	BDX 67, 140/120V	-
35298	BDX67L	BDX 67, 60/45V	BDW 83(A...D), MJ 4033, 2N6282
35299	BDX68	60/60V, 25A, 200W, B>1000	MJ 11011, 2SB694
35300	BDX68A	BDX 68, 80/80V	MJ 11013, 2SB694
35301	BDX68B	BDX 68, 100/100V	MJ 11015, 2SB694
35302	BDX68C	BDX 68, 120/120V	MJ 11015
35303	BDX69	80/60V, 25A, 200W, B>1000	MJ 11012, 2SD730
35304	BDX69A	BDX 69, 100/80V	MJ 11014, 2SD730
35305	BDX69B	BDX 69, 120/100V	MJ 11016, 2SD730
35306	BDX69C	BDX 69, 140/120V	MJ 11016
35307	BDX70	70V, 10A, 75W, >0.8MHz	BD 709, BD 743A, BD 807, BD 909
35308	BDX71	BDX 70	BD 709, BD 743A, BD 807, BD 909
35309	BDX72	BDX 70, 80V	BD 709, BD 743B, BD 809, BD 909
35310	BDX73	BDX 72	BD 709, BD 743B, BD 809, BD 909
35311	BDX74	BDX 70, 45V, 16A	BD 743, BD 905
35312	BDX75	BDX 74	BD 743, BD 905
35313	BDX77	100V, 8A, 60W, >7MHz	BD 543C, BD 711, BD 801
35314	BDX77F	BDX 77, , >20W	BDT 95F, 2SD1411, 2SD1588
35315	BDX78	80V, 8A, 60W, >7MHz	BD 544B, BD 710, BD 800, BD 810
35316	BDX78F	BDX 78, , >20W	BDT 96F, 2SB1018, 2SB1290, 2SA1396
35317	BDX83	B>1000	BDX 85, BDX 87, MJ 3000, 2N6057
35318	BDX83A	BDX 83, 60V	BDX 85A, BDX 87A, MJ 3000, 2N6057
35319	BDX83B	BDX 83, 80V	BDX 85B, BDX 87B, MJ 3001, 2N6058
35320	BDX83C	BDX 83, 100V	BDX 85C, BDX 87C, 2N6059, 2SD628...629
35321	BDX84	B>1000	BDX 86, BDX 88, MJ 2500, 2N6050
35322	BDX84A	BDX 84, 60V	BDX 86A, BDX 88A, MJ 2500, 2N6050
35323	BDX84B	BDX 84, 80V	BDX 86B, BDX 88B, MJ 2501, 2N6051
35324	BDX84C	BDX 84, 100V	BDX 86C, BDX 88C, 2N6052, 2SB638...639

35325	BDX85	B>1000	BDX 83A, BDX 87, MJ 3000, 2N6057
35326	BDX85A	BDX 85, 60V	BDX 83A, BDX 87A, MJ 3000, 2N6057
35327	BDX85B	BDX 85, 80V	BDX 83B, BDX 87B, MJ 3001, 2N6058
35328	BDX85C	BDX 85, 100V	BDX 83C, BDX 87C, 2N6059, 2SD628...629
35329	BDX86	B>1000	BDX 84A, BDX 88, MJ 2500, 2N6050
35330	BDX86A	BDX 86, 60V	BDX 84A, BDX 88A, MJ 2500, 2N6050
35331	BDX86B	BDX 86, 80V	BDX 84B, BDX 88B, MJ 2501, 2N6051
35332	BDX86C	BDX 86, 100V	BDX 84C, BDX 88C, 2N6052, 2SB638...639
35333	BDX87	B>1000	BDX 67, 2N6057, MJ 4033
35334	BDX87A	BDX 87, 60V	BDX 67, 2N6057, MJ 4033
35335	BDX87B	BDX 87, 80V	BDX 67A, 2N6058, MJ 4034
35336	BDX87C	BDX 87, 100V	BDX 67B, 2N6059, MJ 4035
35337	BDX88	B>1000	BDX 66, 2N6050, MJ 4030
35338	BDX88A	BDX 88, 60V	BDX 66, 2N6050, MJ 4030
35339	BDX88B	BDX 88, 80V	BDX 66A, 2N6051, MJ 4031
35340	BDX88C	BDX 88, 100V	BDX 66B, 2N6052, MJ 4032
35341	BDX91	60V, 8A, 90W, >4MHz	BD 245A, BD 311, BDV 91, 2N5873
35342	BDX92	60V, 8A, 90W, >4MHz	BD 246A, BD 312, BDV 92, 2N5871
35343	BDX93	BDX 91, 80V	BD 245B, BD 313, BDV 93, 2N5874
35344	BDX94	BDX 92, 80V	BD 246B, BD 314, BDV 94, 2N5872
35345	BDX95	BDX 91, 100V	BD 245C, BDV 95, 2N5632...5633
35346	BDX96	BDX 92, 100V	BD 246C, BDV 96, 2N6229...6230
35347	BDY10	50V, 2A, 150W, >1MHz	BD 311, BDW 21A, 2N3055, 2N4914
35348	BDY11	BDY 10, 100V	BD 317, BDW 21C, 2N3055, 2N5632
35349	BDY12	60V, 3A, 26W(Tc45°), 70MHz	BDW 25, BDX 25, BDV 10...12, 2SC3252
35350	BDY13	BDY 12, 80V	BDW 25, BDX 25, BDV 10...12, 2SC3252
35351	BDY15	36V, 2.5A, 11.5W, 100MHz	BDW 25, BDX 25, BDV 10...12, 2SC3252
35352	BDY16	BDY 15, 64V	BDW 25, BDX 25, BDV 10...12, 2SC3252
35353	BDY17	80V, 10A, 115W, 1MHz	BD 745B, BD 313, BDW 21B, 2N3055
35354	BDY18	BDY 17, 120V	BD745D, BDW10, 2N5633, 2SC2706, 2SD1047
35355	BDY19	BDY 17, 150V	BD745E, BDW12, 2N3442, 2SC2706, 2SD1047
35356	BDY20	100V, 15A, 117W, 1MHz	BD 317, BD 745C, BDW 51C, 2N3055
35357	BDY21	80V, 3A, 25W(Tc45°), >30MHz	BDW 25, BDX 25, BDV 10...12, 2SC3252
35358	BDY22	BDY 21, 100V	BDW 25, BDX 25, BDV 10...12, 2SD772
35359	BDY23	60V, 6A, 87.5W, >10MHz	BD 245A, BD 311, BDW 21A, 2N3055
35360	BDY24	BDY 23, 100V	BD 245C, BD 317, BDW 21C, 2N3055
35361	BDY25	BDY 23, 200V	2SC2608
35362	BDY26	BDY 23, 300V	BUX 18, BUY 18, BUY 35, BUY 67
35363	BDY27	BDY 23, 400V	BUX 18B, BUY 18S, BUY 67, BUY 77
35364	BDY28	BDY 23, 500V	BUW 34, BUX 15, BUX 45, BUY 69C...70C
35365	BDY29	100V, 30A, 220W, >0.2MHz	BDW 30, BDY 57, MJ 802, 2SD797
35366	BDY34	45V, 3A, 21W, >80MHz	BD 785, MJE 240...242, 2SD1348
35367	BDY34	45V, 3A, 13W(Tc45°), >80MHz	BDV 10...12, BDW 25, BDX 25, 2SC3252
35368	BDY37	160V, 16A, 150W, >0.2MHz	BDW 32, BDW 34, BDW 36, BDY 58, 2N3773
35369	BDY37A	BDY 37, 250W	BDW 32, BDW 34, BDW 36, 2SC2608

35370	BDY38	50V, 6A, 117W, 1MHz	BD 311, BD 745A, BDW 21A, 2N3055
35371	BDY39	100V, 15A, 117W, 1,1MHz	BD 317, BD 745C, BDW 51C, 2N3055
35372	BDY42	400V, 5A, 60W, 12MHz	BUW 71, BUX 18B, BUY 18S, BUY 67
35373	BDY43	BDY 42, 600V	BUS 11, BUW 25, BUX 82, BUY 78...79
35374	BDY44	BDY 42, 750V	BUS 11, BUW 26, BUX 82, BUY 79
35375	BDY45	400V, 15A, 95W, 13MHz	BUW 44, BUX 13, BUX 25, BUY 50
35376	BDY46	BDY 45, 600V	BUS 13, BUW 45...46, BUX 48, 2SD641
35377	BDY47	BDY 45, 750V	BUS 13, BUW 45...46, BUX 48, 2SC3094
35378	BDY48/200	200V, 3,5A, 100W, 5MHz	BUX 16...18, BUY 18, BUY 35, BUY 67
35379	BDY48/300	BDY 48/200, 300V	BUX 16A...18A, BUY 18, BUY 35, BUY 67
35380	BDY48/400	BDY 48/200, 400V	BUX 16C...18C, BUY 18S, BUY 67
35381	BDY49	-/100V, 30A, 150W	BDW 30, BDY 29, BDY 57, MJ 802, 2SD797
35382	BDY53	100V, 12A, 60W, >20MHz	BD 317, BD 745C, BDW 51C, 2N3055
35383	BDY54	BDY 53, 180V	BDW 14, BDW 16, BDY 54, BDY 56
35384	BDY55	100V, 15A, 115W, >10MHz	BD 317, BD 745C, BDW 51C, 2N3055
35385	BDY56	BDY 55, 180V	BDW 14, BDW 16, BDY 56, 2SC2607
35386	BDY57(A)	120V, 25A, 175W, >7MHz	BDW 30, 2N6032, 2N6274...6275
35387	BDY58	BDY 57, 160V	BDW 32, BDW 34, 2N6276...6277
35388	BDY58R	BDY 57, 250V	BUY 11...12, BUX 11...12, BUW 58, BUW 73
35389	BDY60	100MHz	BDY 90, 2SC2681, 2SC2706, 2SC2837
35390	BDY61	BDY 60, 100V	BDY 90...91, 2SC2681, 2SC2706, 2SC2837
35391	BDY62	BDY 60, 30V	BDY 90...92, 2SC2681, 2SC2706, 2SC2837
35392	BDY63	>40MHz	2N5542
35393	BDY64	>30MHz	2N2824...2825
35394	BDY65	>30MHz	BUY 41
35395	BDY66	BDY 65	2N5002, 2N5504, 2N5284...5285
35396	BDY67	>30MHz	2N5002, 2N5504, 2N5284...5285
35397	BDY68	BDY 67	2N5002, 2N5504, 2N5284...5285
35398	BDY69	>30MHz	2N5542
35399	BDY70	>30MHz	BUY 41
35400	BDY71	90V, 4A, 29W, >0,8MHz	BD 243B, BD 953, BDY 78, 2N3054
35401	BDY72	150V, 3A, 25W, >0,8MHz	BD241D, BDY79, 2N3441, 2SC2516
35402	BDY73	100V, 15A, 115W, >0,8MHz	BD 317, BD 745C, BDW 51C, 2N3055
35403	BDY74	BDY 73, 150V	BD745E, BDW12, 2N3773, 2SC1584, 2SD1047
35404	BDY75	50V, 30A, 150W, >0,8MHz	BDY 29, MJ 802, 2N3771, 2SD630
35405	BDY76	BDY 75, 100V, 20A	BD 249C, BDY 29, MJ 802, 2N3772, 2SD797
35406	BDY77	BDY 75, 150V, 16A	2SC2608
35407	BDY78	90V, 4A, 25W, >0,8MHz	BD 243B, BD 953, BDY 71, 2N3054
35408	BDY79	BDY 78, 150V	BD 243D, 2SC2516
35409	BDY80	40V, 4A, 36W, 3MHz	BD 243, BD 533, BD 539, BD 947
35410	BDY81	BDY 80, 60V	BD 243A, BD 535, BD 539A, BD 949
35411	BDY82	35V, 4A, 36W, 3MHz	BD 244, BD 534, BD 540, BD 948
35412	BDY83	BDY 82, 50V	BD 244A, BD 536, BD 540A, BD 950
35413	BDY90	120V, 10A, 60W, 70MHz	2SC2681, 2SC2706, 2SC2837
35414	BDY90A	BDY 90, 12A	2SC2681, 2SC2706, 2SC2837

35415	BDY91	BDY 90, 100V	2SC2681, 2SC2706, 2SC2837
35416	BDY92	BDY 90, 80V	2SC2681, 2SC2706, 2SC2837, 2SC3256
35417	BDY93	10MHz	BUS 11, BUX 46...47, BUX 82...83
35418	BDY94	BDY 93, 750/300V	BUS 11, BUX 46...47, BUX 82...83
35419	BDY95	BDY 93, 400/250V	BUW 71, BUX 16C, BUX 45, BUY 67;
35420	BDY96	10MHz	BUS 12, BUW 26, BUW 35...36, BUX 80
35421	BDY97	BDY 96, 750/300V	BUS 12, BUW 26, BUW 35...36, BUX 80
35422	BDY98	BDY 96, 400/250V	BUW 24, BUW 72, BUX 17B, BUX 43
35423	BDY99	BDY 96, 750/250V	BUS 12, BUW 26, BUW 35...36, BUX 80
35424	BE	BCP 55	BCP 55
35425	BE	P4 SMA-18A	P4 SMA-18A
35426	BE	BCW 61E	BCW 61E
35427	BE	1SV172	1SV172
35428	BE	2SC3440-E	2SC3440
35429	BE	1SV252	1SV252
35430	BE	BCX 55	BCX 55
35431	BE	2SB1122	2SB1122
35432	BE	2SC3443-E	2SC3443
35433	BED	SM 15T 18C	SM 15T...
35434	BEE	SM 15T 18CA	SM 15T...
35435	BEH	SM 15T 22C	SM 15T...
35436	BEK	SM 15T 22CA	SM 15T...
35437	BEL	SM 15T 24C	SM 15T...
35438	BEM	SM 15T 24CA	SM 15T...
35439	BEN	SM 15T 27C	SM 15T...
35440	BEP	SM 15T 27CA	SM 15T...
35441	BEQ	SM 15T 30C	SM 15T...
35442	BER	SM 15T 30CA	SM 15T...
35443	BES	SM 15T 33C	SM 15T...
35444	BET	SM 15T 33CA	SM 15T...
35445	BEU	SM 15T 36C	SM 15T...
35446	BEV	SM 15T 36CA	SM 15T...
35447	BEW	SM 15T 39C	SM 15T...
35448	BEX	SM 15T 39CA	SM 15T...
35449	BF	P4 SMA-20	P4 SMA-20
35450	BF	1SS268	1SS268
35451	BF	2SC3440-F	2SC3440
35452	BF	1SS364	1SS364
35453	BF	1SS312	1SS312
35454	BF	2SC3443-F	2SC3443
35455	BF	BCX 55-6	BCX 55-6
35456	BF	2SB1123	2SB1123
35457	BF(s)	BCW 61FF	BCW 61FF
35458	BF1	RXTA-64	RXTA-64
35459	BF1005	16V, 30mA	-

35460	BF1012	16V, 30mA	-
35461	BF108	140V, 0,15A, 0,86W, 180MHz	BF 257...259, BF 657...659, 2N5058...5059
35462	BF109	135V, 0,05A, 0,52W, >80MHz	BF 257...259, BF 657...659, 2N5058...5059
35463	BF110	160V, 0,04A, 0,75W, 150MHz	BF 257...259, BF 657...659, 2N5058...5059
35464	BF111	200V, 0,08A, 0,8W, 120MHz	BF 258...259, BF 658...659, 2N5058...5059
35465	BF114	>80MHz	BF 257...259, BF 657...659, 2N5058...5059
35466	BF115	230MHz	BF 184...185, BF 240...241, BF 254...255
35467	BF117	140V, 0,1A, 0,68W, 80MHz	BF 257...259, BF 657...659, 2N5058...5059
35468	BF118	250V, 0,1A, 0,8W, 110MHz	BF 258...258, BF 658...659, 2N5058...5059
35469	BF119	160V, 0,1A, 0,8W, 110MHz	BF 257...259, BF 657...659, 2N5058...5059
35470	BF120	220V, 0,05A, 0,3W	BF 298...299, BF 422, BF 258...259
35471	BF121	350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35472	BF123	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35473	BF125	450MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35474	BF127	350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35475	BF130	45V, 0,1A, 150MHz	BC 167, BC 182, BC 237, BC 547
35476	BF131	BF 130	BC 167, BC 182, BC 237, BC 547
35477	BF132	25V, 0,1A, 270MHz	BC 168, BC 183, BC 238, BC 548
35478	BF133	BF 132	BC 168, BC 183, BC 238, BC 548
35479	BF134	>600MHz	BF 240, BF 254, BF 310, BF 314
35480	BF136	600MHz	BF 240, BF 255, BF 495, BF 595
35481	BF137	160V, 0,1A, 0,68W, 95MHz	BF 257...259, BF 657...659, 2N5058...5059
35482	BF138	600MHz	BF 240, BF 255, BF 310, BF 314
35483	BF140	135V, 0,05A, 0,8W, 100MHz	BF 257...259, BF 657...659, 2N5058...5059
35484	BF140A	BF 140, 150V	BF 257...259, BF 657...659, 2N5058...5059
35485	BF140D	BF 140, 180V	BF 258...259, BF 658...659, 2N5058...5059
35486	BF140R	BF 140, 0,03A, 0,3W	BF 297...299, BF 422, BF 257...259
35487	BF140S	BF 140, 0,03A	BF 257...259, BF 657...659, 2N5058...5059
35488	BF152	800MHz	BF 224, BF 314, BF 496, BF 502...503
35489	BF153	400MHz	BF 241, BF 254, BF 494, BF 594
35490	BF154	30V, 0,05A, 0,3W, 400MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35491	BF155	600MHz	BF 180...183, BF 689, BF 763, 2N2857
35492	BF155R	155V, 0,05A, 0,3W, >40MHz	BF 297...299, BF 422, BF 257...259
35493	BF155S	BF 155 R, 0,8W	BF 257...259, BF 657...659, 2N2058...59
35494	BF156	120V, 0,1A, 0,8W, 60MHz	BF 257...259, BF 657...659, 2N5058...5059
35495	BF157	BF 156, 150V	BF 257...259, BF 657...659, 2N5058...5059
35496	BF157B	BF 156, 175V	BF 257...259, BF 657...659, 2N5058...5059
35497	BF158	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35498	BF159	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35499	BF160	600MHz	BF 241, BF 254, BF 494, BF 594
35500	BF161	550MHz	BF 180...183, BF 689, BF 763, 2N2857
35501	BF162	600MHz	BF 225, BF 314, BF 496, BF 502...503
35502	BF163	600MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35503	BF164	600MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35504	BF165	300MHz	BF 240...241, BF 254...255, BF 494...495



35505	BF166	500MHz	BF 225, BF 314, BF 496, BF 502...503
35506	BF167	350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35507	BF168	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35508	BF169	50V, 0,05A, 0,3W, >200MHz	BC 167, BC 182, BC 237, BC 547
35509	BF169R	BF 169	BC 167, BC 182, BC 237, BC 547
35510	BF170	160V, 0,05A, 0,8W, 100MHz	BF 257...259, BF 657...659, 2N5058...5059
35511	BF173	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35512	BF174	150V, 0,1A, 0,8W, 80MHz	BF 257...259, BF 657...659, 2N5058...5059
35513	BF175	500MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35514	BF176	450MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35515	BF177	100V, 0,04A, 0,7W, 120MHz	BF 257...259, BF 657...659, 2N5058...5059
35516	BF178	185V, 0,05A, 0,7W, 120MHz	BF 258...259, BF 658...659, 2N5058...5059
35517	BF179(A...C)	BF 178, 185..250V	BF 258...259, BF 658...659, 2N5058...5059
35518	BF180	675MHz	BF 689, BF 763, 2N918, 2N2857
35519	BF181	600MHz	BF 689, BF 763, 2N918, 2N2857
35520	BF182	650MHz	BF 689, BF 763, 2N918, 2N2857
35521	BF183	800MHz	BF 689, BF 763, 2N918, 2N2857
35522	BF184	300V	BF 240, BF 254, BF 494, BF 594
35523	BF185	220MHz	BF 241, BF 255, BF 495, BF 595
35524	BF186	190V, 0,06A, 0,8W, 120MHz	BF 258...259, BF 658...659, 2N5058...5059
35525	BF187	500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35526	BF188	600MHz	BF 224, BF 314, BF 496, BF 502...503
35527	BF189	270MHz	BF 240, BF 254, BF 494, BF 594
35528	BF194	260MHz	BF 240, BF 254, BF 494, BF 594
35529	BF194	260MHz	BF 240, BF 254, BF 494, BF 594
35530	BF195	200MHz	BF 241, BF 255, BF 495, BF 595
35531	BF195	200MHz	BF 241, BF 255, BF 495, BF 595
35532	BF196	400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35533	BF197	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35534	BF198	400MHz	BF 225, BF 310, BF 367, BF 596
35535	BF199	550MHz	BF 224, BF 311, BF 373, BF 597
35536	BF2	RXTA-76	RXTA-76
35537	BF200	650MHz	BF 225, BF 314, BF 496, BF 502...503
35538	BF202	650MHz	BF 689, BF 763, 2N918, 2N2857
35539	BF203	900MHz	BF 689, BF 763, 2N918, 2N2857
35540	BF206	500MHz	BF 225, BF 314, BF 496, BF 502...503
35541	BF207	400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35542	BF208	600MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35543	BF209	500MHz	BF 225, BF 314, BF 496, BF 502...503
35544	BF212	700MHz	BF 180...183, BF 689, BF 763, 2N2857
35545	BF213	600MHz	BF 180...182, BF 689, BF 763, 2N2857
35546	BF214	250MHz	BF 240, BF 254, BF 494, BF 594
35547	BF215	250MHz	BF 241, BF 255, BF 495, BF 595
35548	BF216	220MHz	BF 241, BF 255, BF 495, BF 595
35549	BF217	240MHz	BF 241, BF 255, BF 495, BF 595

35550	BF218	220MHz	BF 240, BF 254, BF 494, BF 594
35551	BF219	260MHz	BF 240, BF 254, BF 494, BF 594
35552	BF220	260MHz	BF 240, BF 254, BF 494, BF 594
35553	BF221[Riz]	135MHz	BF 240...241, BF 254...255, BF 494...495
35554	BF222[Riz]	135MHz	BF 240...241, BF 254...255, BF 494...495
35555	BF222[SGS]	400MHz	BF 225, BF 314, BF 496, BF 502...503
35556	BF223[AEG]	750MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35557	BF223[AEG]	750MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35558	BF223[Riz]	135MHz	BF 240...241, BF 254...255, BF 494...495
35559	BF224	45V, 700MHz	BF 199, BF 311, BF 373, BF 597
35560	BF225	700MHz	BF 198, BF 310, BF 367, BF 596
35561	BF226	250MHz	BF 240...241, BF 254...255, BF 494...495
35562	BF227	600MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35563	BF228	100V, 50mA, 0,05W, >50MHz	BF 622, BF 297...299, BF 422
35564	BF229	260MHz	BF 240, BF 254, BF 494, BF 594
35565	BF230	200MHz	BF 241, BF 255, BF 495, BF 595
35566	BF231[Riz]	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35567	BF232[Riz]	300MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35568	BF232[Siemens]	600MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35569	BF233[CSF,SGS]	500MHz	BF 240, BF 254, BF 494, BF 594
35570	BF233[Riz]	800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35571	BF234[CSF,SGS]	500MHz	BF 240...241, BF 254...255, BF 494...495
35572	BF234[Riz]	300MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35573	BF235[CSF,SGS]	500MHz	BF 241, BF 255, BF 495, BF 595
35574	BF235[Riz]	400MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35575	BF236	250MHz	BF 240...241, BF 254...255, BF 494...495
35576	BF237		BF 241, BF 255, BF 495, BF 595
35577	BF238		BF 240, BF 254, BF 494, BF 594
35578	BF240(B)	400MHz	BF 254...255, BF 494...495, BF 594...595
35579	BF240[Riz]	15V, 0,1A, 0,3W, >90MHz	BC 168, BC 183, BC 238, BC 548
35580	BF240B	BF 240	BF 240
35581	BF241(C,D)	400MHz	BF 254...255, BF 494...495, BF 594...595
35582	BF241[Riz]	30V, 0,1A, 0,3W, 125MHz	BC 168, BC 183, BC 238, BC 548
35583	BF241A[Riz]	BF 241[Riz], 60V	BC 167, BC 182, BC 237, BC 546
35584	BF241C,D[Piher]	BF 241	BF 241
35585	BF242[Riz]	30V, 0,1A, 0,3W, 140MHz	BC 168, BC 183, BC 238, BC 548
35586	BF242A[Riz]	BF 242[Riz], 60V	BC 167, BC 182, BC 237, BC 546
35587	BF243[Riz]	30V, 0,1A, 0,3W, 170MHz	BC 168, BC 183, BC 238, BC 548
35588	BF243[Texas]	>80MHz	BF 324, BF 440...441, BF 450...451
35589	BF244	30V, Idss>2mA, Up<8V	BFW 61, BFS 72, 2N3819, 2N3823
35590	BF244[Riz]	30V, 0,1A, 0,3W, 170MHz	BC 168, BC 183, BC 238, BC 548
35591	BF245	BF 244	BF 244
35592	BF246	25V, Idss>10mA, Up<14,5V	-
35593	BF247	BF 246	-
35594	BF248	30V, 0,6A, 0,4W, 250MHz	BC 337...338, BC 635, BC 637, BC 639

35595	BF249	30V, 0,6A, 0,4W, 250MHz	BC 327...328, BC 636, BC 638, BC 640
35596	BF250	15V, 0,6A, 0,4W, 20MHz	BC 337-338, BC 635, BC 637, BC 639
35597	BF251	600MHz	BF 167, BF 198, BF 225, BF 310, BF 367
35598	BF252	400MHz	BF 167, BF 198, BF 225, BF 310, BF 367
35599	BF253	>150MHz	BF 240, BF 254, BF 494, BF 594
35600	BF254	260MHz	BF 240, BF 241, BF 494, BF 594
35601	BF255	200MHz	BF 240, BF 241, BF 495, BF 595
35602	BF255[Riz]	600MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35603	BF256	1GHz	2N5397...5398, 2N5486
35604	BF256L	BF 256	BF 256
35605	BF257	160V, 0,1A, 0,8W, 90MHz	BF 657...659, 2N5058...5059
35606	BF257A	BF 257, 180V	BF 658...659, 2N5058...5059
35607	BF257B	BF 257, 220V	BF 658...659, 2N5058...5059
35608	BF257C	BF 257, 220V	BF 658...659, 2N5058...5059
35609	BF257D	BF 257, 160V	BF 657...659, 2N5058...5059
35610	BF257G	BF 257, 200V	BF 658...659, 2N5058...5059
35611	BF257N	BF 257, 180V	BF 658...659, 2N5058...5059
35612	BF257S	BF 257, 140V	BF 657...659, 2N5058...5059
35613	BF258	BF 257, 250V	BF 658...659, 2N5058...5059
35614	BF258A	BF 257, 280V	BF 659, BFS 89, 2N5058
35615	BF259(A,G)	BF 257, 300V	BF 659, BFS 89, 2N5058
35616	BF260	800MHz	BF 225, BF 314, BF 496, BF 502...503
35617	BF261[ATES,CSF]	730MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35618	BF261[Riz]		BF 199, BF 225, BF 311, BF 373, BF 597
35619	BF262	650MHz	BF 362, BF 377...378, BF 763
35620	BF263	>525MHz	BF 363, BF 377...378, BF 763
35621	BF264	>400MHz	BF 363, BF 377...378, BF 763
35622	BF265	600MHz	BF 180...183, BF 689, BF 763, 2N2857
35623	BF266	400MHz	BF 225, BF 314, BF 496, BF 502...503
35624	BF267	350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35625	BF270	600MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35626	BF271	900MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35627	BF272(A,S)	850MHz	BF 316, BF 516, BF 606, BFR 38
35628	BF272[Riz]	775MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35629	BF273[Riz]	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35630	BF273[SGS]	700MHz	BF 240...241, BF 254...255, BF 494...495
35631	BF274[SGS]	700MHz	BF 240...241, BF 254...255, BF 494...495
35632	BF275	500MHz	BF 225, BF 314, BF 496, BF 502...502
35633	BF277	350MHz	BF 225, BF 314, BF 496, BF 502...503
35634	BF278	550MHz	BF 225, BF 314, BF 496, BF 502...503
35635	BF279	500MHz	BF 225, BF 314, BF 496, BF 502...503
35636	BF280	500MHz	BF 225, BF 314, BF 496, BF 502...503
35637	BF281	700MHz	BF 225, BF 314, BF 496, BF 502...503
35638	BF282	600MHz	BF 225, BF 314, BF 496, BF 502...503
35639	BF283	250MHz	BF 225, BF 314, BF 496, BF 502...503

35640	BF284	250MHz	BF 225, BF 314, BF 496, BF 502...503
35641	BF285	250MHz	BF 225, BF 314, BF 496, BF 502...503
35642	BF286	250MHz	BF 225, BF 314, BF 496, BF 502...503
35643	BF287	600MHz	BF 241, BF 255, BF 495, BF 595
35644	BF288	500MHz	BF 240, BF 254, BF 494, BF 594
35645	BF290[Riz]	120V, 0,03A, 0,8W, 80MHz	BF 257...259, BF 657...659, 2N5058...5059
35646	BF290[SGS]	1000MHz	BF 180...183, BF 689, BF 763, 2N2857
35647	BF291(A,B)[SGS]	50V, 0,1A, 0,36W, 260MHz	BC 167, BC 182, BC 237, BC 547
35648	BF291[Riz]	150V, 0,03A, 0,8W, 80MHz	BF 257...259, BF 657...659, 2N5058...5059
35649	BF291A[Riz]	BF 291, 160V	BF 257...259, BF 657...659, 2N5058...5059
35650	BF292A	150V, 0,3A, 0,8W, 66MHz	BF 257...259, BFR 57...59, 2N5058...5059
35651	BF292B	BF 292A, 190V	BF 258...259, BFR 58...59, 2N5058...5059
35652	BF292C	BF 292A, 220V	BF 258...259, BFR 58...59, 2N5058...5059
35653	BF293(A,D)	50V, 0,1A, 0,36W, 250..380MHz	BC 167, BC 182, BC 237, BC 547
35654	BF294	160V, 0,1A, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...5059
35655	BF297	160V, 0,1A, 0,625W, 95MHz	BFR 87...89, BFT 57...59, BF 257...259
35656	BF297P	BF 297, 1W	2SC1758, BF 457...459, BF 857...859
35657	BF297P2	BF 297, 1W	BF 457...459, BF 615, BF 857...859
35658	BF298	BF 297, 250V	BFR 88...89, BFT 58...59, BF 258...259
35659	BF298P	BF 298, 1W	2SC1758, BF 458...459, BF 858...859
35660	BF298P2	BF 298, 1W	BF 458...459, BF 615, BF 858...859
35661	BF299	BF 297, 300V	BFR 89, BFT 59, BF 259
35662	BF299P	BF 299, 1W	2SC1758, BF 459, BF 859
35663	BF299P2	BF 299, 1W	BF 459, BF 617, BF 859
35664	BF302	650MHz	BF 240...241, BF 254...255, BF 494...495
35665	BF303	500MHz	BF 240...241, BF 254...255, BF 494...495
35666	BF304	500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35667	BF305	185V, 0,1A, 0,6W, 100MHz	BF 258...259, BF 658...659, 2N5058...5059
35668	BF306	1000MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35669	BF307		BF 199, BF 224, BF 311, BF 373, BF 597
35670	BF308	>800MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35671	BF309	>800MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35672	BF310	580MHz	BF 198, BF 225, BF 314, BF 367, BF 596
35673	BF311	750MHz	BF 199, BF 224, BF 373, BF 597
35674	BF314	450MHz	BF 225, BF 496, BF 502...503
35675	BF315	500MHz	BF 324, BF 440...441, BF 450...451
35676	BF316(A)	550..600MHz	BF 272, BF 516, BF 606, BFR 38
35677	BF317	BF 315	BF 315
35678	BF320	15V, Idss>0,3mA, Up<8V	2N3820, 2N3909, 2N5800, 2N5462
35679	BF321(A...F)	30V, 0,03A, 0,3W	BC 168, BC 183, BC 238, BC 548
35680	BF322	30V, 0,6A, 0,4W, 250MHz	BC 140...141, BC 337...338, BC 635
35681	BF323	30V, 0,6A, 0,4W, 250MHz	BC 160...161, BC 327...328, BC 636
35682	BF324	450MHz	BF 414, BF 506, BF 914, BF 936, BF 939
35683	BF325	700MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35684	BF327	20V, Idss>20mA, Up<3,8V	-

35685	BF329	730MHz	BF 198, BF 225, BF 310, BF 367, BF 596
35686	BF330	1000MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35687	BF332	600MHz	BF 240...241, BF 254...255, BF 494...495
35688	BF333	400MHz	BF 240...241, BF 254...255, BF 494...495
35689	BF334	430MHz	BF 240...241, BF 254...255, BF 494...495
35690	BF335	370MHz	BF 240...241, BF 254...255, BF 494...495
35691	BF336	185V, 0,1A, 0,8W, 130MHz	BF 258...259, BF 658...659, 2N5058...5059
35692	BF336D	BF 336, 0,5A	2SD413, 2SD576, 2SD624
35693	BF337	BF 336, 250V	BF 258...259, BF 658...259, 2N5058...5059
35694	BF337D	BF 337, 0,5A	2SD576, 2SD593
35695	BF338	BF 336, 300V	BF 259, BF 659, BFS 89, 2N5058
35696	BF338D	BF 338, 0,5A	2SD593
35697	BF339	500MHz	BF 324, BF 414, BF 506, BF 914, BF 936
35698	BF340	>80MHz, B>30	BF 324, BF 440...441, BF 450...451
35699	BF341	BF 430, B45..150	BF 324, BF 440...441, BF 450...451
35700	BF342	BF 340, B60..150	BF 324, BF 440...441, BF 450...451
35701	BF343	BF 340, B>30	BF 324, BF 440...441, BF 450...451
35702	BF344	500MHz	BF 240...241, BF 254...255, BF 494...495
35703	BF345	500MHz	BF 240...241, BF 254...255, BF 494...495
35704	BF346	500MHz	BF 256, BFS 71, 2N3822, 2N4416
35705	BF347	30V, Idss>0,5mA, Up<0,5V	BFW 13, 2N4338, 2SK68, 2SK106, 2SK118
35706	BF348	40V, Idss>10mA, Up<6V	BF 256, BFT 10, 2N5397, 2N5486
35707	BF350	15V, Idss>3mA, Up<5V	BF 900, 3SK40
35708	BF351	24V, Idss>5mA, Up<5V	3N201...206, 3N209...210, 3N211...213
35709	BF352	24V, Idss>5mA, Up<2V	BF 963, 3SK51, 3SK74, 3SK81
35710	BF353	24V, Idss>5mA, Up<3V	BF 963, 3SK51, 3SK74, 3SK81
35711	BF354	24V, Idss>7mA, Up>3V	BF 963, 3SK41, 3SK74, 3SK81
35712	BF355	300V, 0,1A, 0,8W, >80MHz	BF 259, BF 659, 2N5058
35713	BF356	220V, 0,2A, 0,8W, 100MHz	BF 298...299, BFT 58...59 BF 258...259
35714	BF357(K,S)	30V, 0,05A, 1,6GHz	BF 377...378, BF 689, BF 763, 2N2857
35715	BF359	850MHz	BF 606, BF 679...680, BF 967...970
35716	BF360	750MHz	BF 606, BF 679...680, BF 967...970
35717	BF362	800MHz	BF 689K, BF 763
35718	BF363	700MHz	BF 689K, BF 763
35719	BF364	260MHz	BF 240, BF 254, BF 494, BF 594
35720	BF365	200MHz	BF 241, BF 255, BF 495, BF 595
35721	BF366	>400MHz	BF 225, BF 314, BF 496, BF 502...503
35722	BF367	440MHz	BF 198, BF 225, BF 310, BF 596
35723	BF368	>250MHz	BF 240...241, BF 254...255, BF 494...495
35724	BF368K	BF 368	BF 368
35725	BF369	>400MHz	BF 240...241, BF 254...255, BF 494...495
35726	BF369K	BF 369	BF 369
35727	BF370(R)	>500MHz	BF 920...921S, BF 959
35728	BF371	720MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35729	BF372	850MHz	BF 506, BF 509, BF 914, BF 939

35730	BF373	720MHz	BF 199, BF 224, BF 311, BF 597
35731	BF374	30V, 100mA, >400MHz	BF 225, BF 314, BF 496, BF 502...503
35732	BF375	30V, 400MHz	BF 225, BF 314, BF 496, BF 502...503
35733	BF377	>1300MHz	BF 689, BF 763, 2N2857
35734	BF378	BF 377	BF 377
35735	BF379	350MHz	BF 324, BF 440...441, BF 450...451
35736	BF380	180V, 0,5A, 10W, 90MHz	MPSU 10, BF 460...462, BF 757...759
35737	BF381	BF 380, 250V	MPSU 10, BF 460...462, BF 757...759
35738	BF382	BF 380, 300V	MPSU 10, BF 461...462, BF 758...759
35739	BF384	800MHz	BF 240...241, BF 254...255, BF 494...495
35740	BF385	800MHz	BF 240...241, BF 254...255, BF 494...495
35741	BF387	100V, 0,05A, 0,8W, 120MHz	BF 257...259, BF 657...659, 2N5058...5059
35742	BF388	BF 387, 160V	BF 257...259, BF 657...659, 2N5058...5059
35743	BF389B	BF 387, 220V	BF 258...259, BF 658...659, 2N5058...5059
35744	BF389C	BF 387, 250V	BF 258...259, BF 658...659, 2N5058...5059
35745	BF390	310V, 0,1A, 0,6W, 120MHz	BF 259, BF 659, BFS 89, 2N5058
35746	BF391(K,L,M)	200V, 0,5A, 0,625W, 70MHz	BFP 22, MPSA 43
35747	BF391P1	BF 391, 0,2A, 1W	BF 460...461, BF 757...759, MPSU 10
35748	BF391P2	BF 391, 0,2A, 1W	BF 757...759, BF 460...461, MPSU 10
35749	BF392(K,L,M)	BF 391, 250V	BFP 25, MPSA 42
35750	BF392P1	BF 392, 0,2A, 1W	BF 460...461, BF 757...759, MPSU 10
35751	BF392P2	BF 392, 0,2A, 1W	BF 757...759, BF 460...461, MPSU 10
35752	BF393(K,L,M)	BF 391, 300V	BFP 25, MPSA 42
35753	BF393P1	BF 393, 0,2A, 1W	BF 461, BF 758...759, MPSU 10
35754	BF393P2	BF 393, 0,2A, 1W	BF 758...759, BF 461, MPSU 10
35755	BF394	>80MHz	BF 240...241, BF 254...255, BF 494...495
35756	BF395	>80MHz	BF 240...241, BF 254...255, BF 494...495
35757	BF397	90V, 0,1A, 0,625W	BF 435...437, BSS 68, 2SA1370...1371
35758	BF398	BF 397, 150V	BF 435...437, 2SC1370...1371
35759	BF400	>700MHz	BF 509, BF 606, BF 914, BF 939
35760	BF402	>400MHz	BF 324, BF 414, BF 506, BF 914, BF 936
35761	BF403	30V 0,05A, 300MHz	-
35762	BF404	30V 0,05A, 150MHz	-
35763	BF405	45V 0,5A, >150MHz	-
35764	BF406	45V 0,5A, >150MHz	-
35765	BF410	20V, Idss>0,3mA, Up1,5V	2N5484, 2SK152, 2SK192
35766	BF411	110V, 0,05A, 0,3W, 120MHz	BF 422, BF 297...299, BF 483, BSS 38
35767	BF412	BF 411, 150V	BF 422, BF 297...299, BF 483
35768	BF413	BF 411, 200V	BF 422, BF 298...299, BF 483
35769	BF414	400MHz	BF 324, BF 506, BF 914, BF 936, BF 939
35770	BF415	250V, 0,2A, 6W, >50MHz	BF 615, BF 757...759, BF 460...461
35771	BF416	250V, 0,2A, 6W, >50MHz	BF 616, BF 760...762, BF 464...465
35772	BF417(G)	BF 415, 300V	BF 617, BF 758...759, BF 461
35773	BF418(G)	BF 416, 300V	BF 618, BF 761...762, BF 465
35774	BF419	300V, 0,1A, 6W(Tc90°)	BF 417, BF 459, 2SC3417



35775	BF420(S)	>60MHz	BF 299, BF 483, BFR 89, 2SC3468
35776	BF420A	BF 420, 0,5A, 0,8W	BF 393, BFP 25, MPSA 42
35777	BF420L	BF 420, 0,5A, 0,625W	BF 420A
35778	BF420P	BF 420, 0,9W	BF 461...462, MPSU 10
35779	BF420P3	BF 420, 0,9W	BF 461...462, BF 758...759, MPSU 10
35780	BF421(S)	>60MHz	BF 437, 2SA1371...1372, 2SA1251
35781	BF421A	BF 421, 0,5A, 0,8W	BF 493, BFP 26, MPSA 92
35782	BF421L	BF 421, 0,5A, 0,625W	BF 421A
35783	BF421P	BF 421, 0,9W	BF 464...465, MPSU 60
35784	BF421P3	BF 421, 0,9W	BF 464...465, BF 761...762, MPSU 60
35785	BF422(S)	BF 420, 250V	BF 298...299, BF 483, BFR 88...99
35786	BF422A	BF 422, 0,5A, 0,8W	BF 392...393, BFP 25, MPSA 42
35787	BF422L	BF 422, 0,5A, 0,625W	BF 422A
35788	BF422P	BF 422, 0,9W	BF 460...462, MPSU 10
35789	BF422P3	BF 422, 0,9W	BF 460...462, BF 757...759, MPSU 10
35790	BF423(S)	BF 421, 250V	BF 436...437, 2SA1371...1372, 2SA1251
35791	BF423A	BF 423, 0,5A, 0,8W	BF 492...493, BFP 26, MPSA 92
35792	BF423L	BF 423, 0,5A, 0,625W	BF 423A
35793	BF423P	BF 423, 0,9W	BF 463...465, MPSU 60
35794	BF423P3	BF 423, 0,9W	BF 463...465, BF 760...762, MPSU 60
35795	BF424	300MHz	BF 324, BF 440...441, BF 450...451
35796	BF430(L)	20V, 70mA, 7500MHz	BFG 520, BFP 193
35797	BF431(L)	25V, 30mA, 3800MHz	BFG 93A
35798	BF432(L)	15V, 1mA, 5000MHz	MRF 9331(L), BFG 92A
35799	BF435	160V, 0,2A, 0,625W, >80MHz	BF 491...493, BFP 23, BFP 26, MPSA 92...93
35800	BF436	BF 435, 250V	BF 492...493, BFP 26, MPSA 92, 2SA1251
35801	BF437	BF 435, 300V	BF 439, BFP 26, MPSA 92, 2SA1251
35802	BF439	>900MHz	BF 316, BF 516, BF 606, BFR 38
35803	BF440	250MHz	BF 324, BF 450, BF 540...542
35804	BF441	250MHz	BF 324, BF 451, BF 540...542
35805	BF450	375MHz	BF 324, BF 440, BF 540...542
35806	BF451	325MHz	BF 324, BF 441, BF 540...542
35807	BF454	400MHz	BF 240, BF 254, BF 494, BF 594
35808	BF455	400MHz	BF 241, BF 255, BF 495, BF 595
35809	BF456	160V, 0,1A, 7W, 90MHz	BF 457...459, BF 415, BF 417, 2SC3417
35810	BF457	90MHz	BF 415, BF 417, 2SC3417
35811	BF458	BF 457, 250V	BF 415, BF 417, 2SC3417
35812	BF459	BF 457, 300V	BF 850, 2SC3417...3418
35813	BF460	250V, 0,5A, 10W, >45MHz	MPSU 10, BF 758...759
35814	BF460BA...465BA	BF 460..465	BF 460...465
35815	BF460EA...465EA	BF 460..465	BF 460...465
35816	BF461	BF 460, 300V	MPSU 10, BF 758...759
35817	BF462	BF 460, 350V	BF 759
35818	BF463	250V, 0,5A, 10W, >20MHz	MPSU 60, BF 761...762
35819	BF464	BF 463, 300V	MPSU 60, BF 761...762

35820	BF465	BF 463, 350V	BF 762
35821	BF466	200V, 1A, 10W, >100MHz	BD 410, BF 666
35822	BF467	BF 466, 250V	BD 410, BF 667
35823	BF468	BF 466, 300V	BD 410, BF 668
35824	BF469(S)	2W(Tc110°),>60MHz	BF 458...459, BF 415, BF 417, 2SC3424
35825	BF470(S)	2W(Tc110°),>60MHz	BF 416, BF 418, 2SA1361, 2SA1353
35826	BF471(S)	BF 469, 300V	BF 459, BF 417, 2SC3417...3418
35827	BF472(S)	BF 470, 300V	BF 418, 2SA1353...1354
35828	BF479	2000MHz	BF 679, BF 967...968, BF 979
35829	BF479S	BF 479, 1300MHz	BF 479
35830	BF479T	BF 479, 1850MHz	BF 479
35831	BF480	1500MHz	BF 362, 2SC2464...66, 2SC2726, 2SC2728
35832	BF481	1200MHz	BF 362, 2SC2464...66, 2SC2726, 2SC2728
35833	BF483	300V, 0,05A, 0,83W, >70MHz	BF 420(A), 2SC3468...3469, 2SC4218
35834	BF484	250V, 0,1A, 0,83W, >70MHz	BF 421A, BF 436...437, 2SA1371, 2SA1624
35835	BF485	BF 483, 350V	2SC2267, 2SC3469, 2SC4166, 2SD1385
35836	BF486	BF 484, 300V	BF 421A, BF 437, 2SA1371, 2SA1624
35837	BF487	BF 483, 400V	2SC2267, 2SC3469, 2SC4166, 2SD1385
35838	BF488	BF 484, 350V	BF 493S, 2SA1251, 2SA1372, 2SB1209
35839	BF491(K,L,M)	200V, 0,5A, 0,625W, >50MHz	BFP 23, MPSA 93
35840	BF491P1	BF 491, 0,2A, 1W	BF 463...464, BF 760...762, MPSU 60
35841	BF491P2	BF 491, 0,2A, 1W	BF 760...762, BF 463...464, MPSU 60
35842	BF492(K,L,M)	BF 491, 250V	BFP 26, MPSA 92
35843	BF492P1	BF 492, 0,2A, 1W	BF 463...464, BF 760...762, MPSU 60
35844	BF492P2	BF 492, 0,2A, 1W	BF 760...762, BF 463...464, MPSU 60
35845	BF493(K,L,M)	BF 491, 300V	BFP 26, MPSA 92
35846	BF493P1	BF 493, 0,2A, 1W	BF 464, BF 761...762, MPSU 60
35847	BF493P2	BF 493, 0,2A, 1W	BF 761...762, BF 464, MPSU 60
35848	BF493S	BF 491, 350V	2SB1074, BF 465, BF 762, 2SA1156
35849	BF494(B)	30V, 30mA, 0,3W, 260MHz	BF 240...241, BF 254...255, BF 594...595
35850	BF494..495[Mot]	BF 494..495, 0,1A 0,35W	BF 240...241, BF 254...255, BF 594...595
35851	BF495(C,D)	30V, 30mA, 0,3W, 200MHz	BF 240...241, BF 254...255, BF 594...595
35852	BF496	550MHz	BF 225, BF 314, BF 502...503, BF 505
35853	BF497	1000MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35854	BF500(A)	400MHz	BF 324, BF 414, BF 506, BF 509, BF 914
35855	BF501	300MHz	BF 324, BF 414, BF 509, BF 914, BF 939
35856	BF502	700MHz	BF 225, BF 314, BF 496, BF 505, BF 507
35857	BF502S	BF 502, 900MHz	BF 502
35858	BF503	750MHz	BF 225, BF 314, BF 496, BF 505, BF 507
35859	BF504	30V, 0,05A, 0,25W, 85MHz	BC 168, BC 183, BC 238, BC 548
35860	BF505	>750MHz	BF 502...503, BF 507
35861	BF506	40V, 30mA, 550MHz	BF 324, BF 414, BF 509, BF 914, BF 936
35862	BF506	45V, 0,05A, 0,25W, 95MHz	BC 167, BC 182, BC 237, BC 547
35863	BF506A	BF 506, 25V, 25mA, 350MHz	BF 324, BF 414, BF 509, BF 914, BF 936
35864	BF507	>750MHz	BF 502...503, BF 505

35865	BF509(S,T)	700..800MHz	BF 506, BF 914, BF 936, BF 939
35866	BF510		2SK212
35867	BF510..511[Ucp]	30V, 0,05A, 0,25W, 80MHz	BC 168, BC 183, BC 238, BC 548
35868	BF511		2SK212
35869	BF512		-
35870	BF513		-
35871	BF516	850MHz	BF 316, BF 439, BF 606, BFR 38
35872	BF517	20V, 25mA, 2GHz	BFR 35, BFT 25, 2SC3098...3099
35873	BF519	70V, 0,05A, 0,3W, 150MHz	BC 174, BC 182, BC 190, BC 546
35874	BF520	50V, 0,05A, 0,3W, 150MHz	BC 167, BC 182, BC 237, BC 547
35875	BF521	30V, 0,05A, 0,3W, 150MHz	BC 168, BC 183, BC 238, BC 548
35876	BF523	500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35877	BF536	350MHz	BF 568...569, BF 660
35878	BF540	130MHz	BF 324, BF 440...441, BF 450...451
35879	BF541	130MHz	BF 324, BF 440...441, BF 450...451
35880	BF542	130MHz	BF 324, BF 440...441, BF 450...451
35881	BF543	BF 544, SMD	-
35882	BF544	Up<1,5V	-
35883	BF545	BF 245, SMD	-
35884	BF547	30V, 0,03A, 1200MHz	BFS 17
35885	BF547W	BF 547	-
35886	BF550	40V, 25mA, 325MHz	BF 536, BF 568...569, BF 660
35887	BF550R	BF 550	BF 569R
35888	BF554	30V, 30mA, 260MHz	BF 599, BF 799, BFS 18...20
35889	BF556	BF 256, SMD	-
35890	BF559	850MHz	BF 606, BF 679...680, BF 967...970
35891	BF560	850MHz	BF 606, BF 679...680, BF 967...970
35892	BF562	600MHz	BF 225, BF 314, BF 496, BF 502...503
35893	BF568	1100MHz	BF 569, BF 579, BF 767
35894	BF569	40V, 30mA, 850MHz	BF 579, BF 767
35895	BF569R	BF 569	BF 579R
35896	BF570	40V, 0,1A,>500MHz	BF 799
35897	BF576	>800MHz	BF 316, BF 516, BF 606, BFR 38
35898	BF579	20V, 30mA, 1600MHz	-
35899	BF579R	BF 579	-
35900	BF583	300V, 0,05A, 5W, >70MHz	BF 600, BF 617, BF 758, BF 859, BF 880
35901	BF584	250V, 0,05A, 5W, >70MHz	BF 616, BF 760, BF 848, BF 872, BF 890
35902	BF585	BF 583, 350V	BF 600, BF 759, BF 880...81
35903	BF586	BF 584, 300V	BF 618, BF 761, BF 849, BF 890...91
35904	BF587	BF 583, 400V	BF 600, BF 881
35905	BF588	BF 584, 350V	BF 762, BF 890...91
35906	BF591	210V, 0,15A, 1,3W(Ta55°)	BF 460...462, BF 615, BF 757...759
35907	BF593	BF 591, 250V	BF 460...462, BF 615, BF 757...759
35908	BF594	260MHz	BF 240...241, BF 254...255, BF 494...495
35909	BF595	260MHz	BF 240...241, BF 254...255, BF 494...495

35910	BF596	400MHz	BF 198, BF 225, BF 310, BF 367
35911	BF597(A,B)	550MHz	BF 199, BF 224, BF 311, BF 373
35912	BF599	40V, 25mA, 550MHz	BF 799, BFS 20, 2SC3015, 2SC3374
35913	BF600	400V, 0,03A, >60MHz	BF 587, BF 881
35914	BF606(A,B)	370-1200MHz	BF 316, BF 439, BF 516, BFR 38
35915	BF615(BA)	250V, 0,2A, 10W, 70MHz	BF 757...759, BF 460...462, MPSU 10
35916	BF615EA...618EA	BF 615..618	BF 615...618
35917	BF616(BA)	250V, 0,2A, 10W, 70MHz	BF 760...762, BF 463...465, MPSU 60
35918	BF617(BA,G)	BF 615, 300V	BF 758...759, BF 461...462, MPSU 10
35919	BF618(BA,G)	BF 616, 300V	BF 761...762, BF 464...465, MPSU 60
35920	BF620	300V, 0,05A, >60MHz	BFN 18, BFN 20
35921	BF621	300V, 0,05A, >60MHz	BFN 19, BFN 21
35922	BF622	BF 620, 250V	BFN 16, BFN 18, BFN 20
35923	BF623	BF 621, 250V	BFN 17, BFN 19, BFN 21
35924	BF630	2000MHz	BF 377...378, BF 689K, BF 763
35925	BF639	>700MHz	BF 316, BF 516, BF 606, BFR 38
35926	BF640	650MHz	BF 316, BF 516, BF 606, BFR 38
35927	BF642	300V, 0,5A, 0,625W, >50MHz	BF 393, BF 420A, BFP 25, MPSA 42
35928	BF642P	BF 642, 0,9W	BF 393P1, MPSU 10, BF 461, BF 758...759
35929	BF642P2	BF 642, 0,9W	BF 393P2, BF 758...759, BF 461, MPSU 10
35930	BF643	BF 642, 200V	BF391...393, BF422A, BFP 22, MPSA 42...43
35931	BF643P	BF 643, 0,9W	BF 391P1, MPSU 10, BF 460, BF 757...759
35932	BF643P2	BF 643, 0,9W	BF 391P2, BF 757...759, BF 460, MPSU 10
35933	BF657	160V, 0,1A, 1W, 90MHz	BF 257...259, 2N5058...5059
35934	BF658	BF 657, 250V	BF 258...259, 2N5058...5059
35935	BF659	BF 657, 300V	BF 259, BFS 89, 2N5058
35936	BF660	40V, 25mA, 650MHz	BF 536, BF 568...569, BF 579, BF 767
35937	BF660R	BF 660	BF 569R, BF 579R
35938	BF666	200V, 1A, 10W, >100MHz	BD 410, BF 466...468
35939	BF667	BF 666, 250V	BD 410, BF 467...468
35940	BF668	BF 666, 300V	BD 410, BF 468
35941	BF679(M,S,T)	930..1000MHz	BF 479, BF 779, BF 967...968, BF 979
35942	BF680(A,H)	650..750MHz	BF 780, BF 967, BF 969...970, BF 970
35943	BF681	950MHz	BF 479, BF 779...780, BF 967...970, BF 979
35944	BF689	1000MHz	BF 377...378, BF 763, 2N2857
35945	BF689K	BF 689, 1800MHz	BF 377...378, BF 763, 2N2857
35946	BF692	300V, 0,5A, 0,625W, >50	BF 493, BF 421A, BFP 26, MPSA 92
35947	BF692P	BF 692, 0,9W	BF 493P1, MPSU 60, BF 464, BF 761...762
35948	BF692P2	BF 692, 0,9W	BF 493P2, BF 761...762, BF 464, MPSU 60
35949	BF693	BF 692, 200V	BF491...493, BF423A, BFP23, MPSA 92...93
35950	BF693P	BF 693, 0,9W	BF 491P1, MPSU 60, BF 463, BF 760...762
35951	BF693P2	BF 693, 0,9W	BF 491P2, BF 760...762, BF 463, MPSU 60
35952	BF694(A,B)	300MHz	BF 199, BF 224, BF 311, BF 373, BF 597
35953	BF706	>200MHz	BF 324, BF 440...411, BF 450...451
35954	BF709	>350MHz	BF 324, BF 414, BF 506, BF 914, BF 936

35955	BF715(BA)	250V, 0,03A, 6,25W, >60MHz	BF 858...859, BF 869, BF 861, BF 880
35956	BF715EA..718EA	BF 715..718	BF 715...718
35957	BF716(BA)	250V, 0,03A, 6,25W, >60MHz	BF 848...849, BF 870, BF 872, BF 890
35958	BF717(BA)	BF 715, 300V	BF 859, BF 871, BF 880
35959	BF718(BA)	BF 716, 300V	BF 849, BF 872, BF 890
35960	BF720	BF 620, 0,05A, 1,5W	-
35961	BF721	BF 621, 0,05A, 1,5W	-
35962	BF722	BF 622, 0,05A, 1,5W	-
35963	BF723	BF 623, 0,05A, 1,5W	-
35964	BF739	>600MHz	BF 316, BF 516, BF 606, BF 939, BFR 38
35965	BF740	>600MHz	BF 316, BF 516, BF 606, BFR 38
35966	BF747[Phi]	30V, 1200MHz	BF 775
35967	BF749	20V, 25mA, 5000MHz	-
35968	BF750	15V, 35mA, 7000MHz	-
35969	BF752	15V, 35mA, 7000MHz	-
35970	BF753	15V, 35mA, 5000MHz	-
35971	BF757	250V, 0,5A, 10W, >45MHz	BF 460...462, MPSU 10
35972	BF757BA..762BA	BF 757..762	BF 757...762
35973	BF757EA..762EA	BF 757..762	BF 757...762
35974	BF758	BF 757, 300V	BF 461...462, MPSU 10
35975	BF759	BF 757, 350V	BF 462
35976	BF760	250V, 0,5A, 10W, >20MHz	2SA1156, BF 463...465, MPSU 60
35977	BF761	BF 760, 300V	2SA1156, BF 464...465, MPSU 60
35978	BF762	BF 760, 350V	2SA1156, BF 465
35979	BF763	25V, 25mA, 1800MHz	BF 377...378, BF 689K, 2SC2570(A)
35980	BF767	950MHz	BF 568...569, BF 579
35981	BF770A	15V, 0,05A, 5,5GHz	2SC3513
35982	BF771	20V, 80mA, 7GHz	BFR 193, BFR 520, 2SC3445
35983	BF772	BF 771	BFG 520, BFP 193
35984	BF775	20V, 0,03A, 4,5GHz	BF 747, BFQ 29, BFT 75, 2SC3110
35985	BF775A	BF 775, 25V, 4200..5800MHz	BFQ 81, BFR 93, 2SC3110, 2SC3513
35986	BF777	30V, 50mA, 2200MHz	BF 747, BF 775, BFR 53, 2SC3014, 2SC3773
35987	BF779	800MHz	BF 479, BF 679, BF 967...968, BF 979
35988	BF780	700MHz	BF 680, BF 967, BF 969...970
35989	BF787	250V, 0,1A, 10W, >60MHz	BF 615, BF 858...859, BF 880...881
35990	BF788	BF 787, 300V	BF 617, BF 859, BF 880...881
35991	BF789	BF 787, 350V	BF 880...881
35992	BF790	250V, 0,1A, 10W, >60MHz	BF 616, BF 848...849, BF 890...891
35993	BF791	BF 790, 300V	BF 618, BF 849, BF 890...891
35994	BF792	BF 790, 350V	BF 890...891
35995	BF799	800..1100MHz	BF 570
35996	BF800	25V, Idss>0,3mA, Up<6V	-
35997	BF801	25V, Idss>0,3mA, Up<6V	-
35998	BF802	25V, Idss>0,3mA, Up<6V	-
35999	BF803	30V, Idss<0,8mA, Up<3V	-

36000	BF804	30V, Idss<1,2mA, Up<5V	-
36001	BF805	30V, Idss>3mA, Up<6V	-
36002	BF806	30V, Idss>3mA, Up<6V	-
36003	BF808	20V, Idss>1mA, Up<5V	-
36004	BF810(A)	30V, Idss>5mA, Up<6V	-
36005	BF811(A)	30V, Idss>5mA, Up<6V	-
36006	BF815	30V, Idss>15mA, Up<6V	-
36007	BF816	30V, Idss>15mA, Up<6V	-
36008	BF817	25V, Idss>10mA, Up<5V	-
36009	BF818	25V, Idss>10mA, Up<5V	-
36010	BF819	300V, 0,1A, 6W(Tc75°)	BF 617, BF 859, BF 880...881, MJE 340
36011	BF819A	BF 819	2SC1758, BF 617, BF 859, BF 880...881
36012	BF820(S)	300V, 25..50mA, >60MHz	BFN 26
36013	BF820W..823W	BF 820..823	-
36014	BF821(S)	300V, 25..50mA, >60MHz	BFN 27
36015	BF822(S)	BF 820, 250V	BFN 22, BFN 24, BFN 26
36016	BF823(S)	BF 822, 250V	BFN 23, BFN 25, BFN 27
36017	BF824	30V, 25mA, 450MHz	BF 568
36018	BF824W	BF 824	-
36019	BF840	BF 240, SMD	BF 554, BFS 18...19
36020	BF841	BF 241, SMD	BF 554, BFS 18...19
36021	BF844	450V, 0,3A, 0,625W, >50MHz	MPSA 44
36022	BF845	BF 844, 400V	MPSA 44...45
36023	BF847	2,5W(Tc100°),90MHz	BF 616, BF 760...762, BF 890...891
36024	BF848	BF 847, 270V	BF 618, BF 761...762, BF 890...891
36025	BF849	BF 847, 300V	BF 761...762, BF 890...891
36026	BF850	400V, 0,1A, >90MHz	2SC3418
36027	BF851	25V, Idss2..25mA	-
36028	BF857	160V, 0,2A, 6W(Tc75°), 90MHz	BF 615, BF 757...759, BF 880...881
36029	BF857A..859A	BF 857..859	BF 461...462
36030	BF857BA..859BA	BF 857..859	BF 857...859
36031	BF857EA..859EA	BF 857..859	BF 857...859
36032	BF858	BF 857, 250V	BF 617, BF 758...759, BF 880...881
36033	BF859	BF 857, 300V	BF 758...759, BF 880...881
36034	BF861	BF 851, SMD	-
36035	BF869(A,S,SA)	250V, 0,05A, 5W, >60MHz	BF 583, BF 615, BF 858...859, BF 880...881
36036	BF869BA..872BA	BF 869..872	BF 869...872
36037	BF869EA..872EA	BF 869..872	BF 869...872
36038	BF870(A,S,SA)	250V, 0,05A, 5W, >60MHz	BF 616, BF 848...849, BF 890...891
36039	BF871(A,S,SA)	BF 869, 300V	BF 583, BF 617, BF 859, BF 880...881
36040	BF872(A,S,SA)	BF 870, 300V	BF 618, BF 849, BF 890...891
36041	BF879		BF 479, BF 679...680, BF 967...970
36042	BF880	350V, 0,1A, >60MHz	BF 850, 2SC3418
36043	BF881	400V, 0,1A, >60MHz	BF 850, 2SC3418
36044	BF883(S)	300/275V, 0,05A, 7W, >60MHz	BF 759, BF 859, BF 880...881



36045	BF885(S)	300V, 0,05A, 7W, >60MHz	BF 759, BF 859, BF 880...881
36046	BF890	350V, 0,1A, >60MHz	BF 762, 2SA1156, 2SA1354, 2SB1011
36047	BF891	400V, 0,03A, >60MHz	2SA1156, 2SA1354, 2SB1011
36048	BF900	Idss>3mA, Up<5V	BF 960, BF 965...966
36049	BF901	12V, 30mA	-
36050	BF901R	BF 901	-
36051	BF904	7V, 30mA	-
36052	BF904R	BF 904	-
36053	BF905	20V, Idss>2mA, Up<5V	BF 900, BF 960, BF 965...966
36054	BF906	>200MHz	BF 324, BF 440...441, BF 450...451
36055	BF907	20V, Idss>5mA, Up<3,5V	BF 900, BF 960, BF 965...966
36056	BF908	12V, 40mA	-
36057	BF908R	BF 908	-
36058	BF910	20V, Idss>6mA	BF 900, BF 960, BF 965...966
36059	BF914	850MHz	BF 324, BF 414, BF 506, BF 509, BF 939
36060	BF915	Idss>15mA, Up<4V	BF 900, BF 960, BF 965...966
36061	BF920	1800MHz	BF 921S, BF 959
36062	BF920TS..923TS	BF 420..423, 0,46W	BF 420...423
36063	BF921(S)	1800MHz	BF 920, BF 959
36064	BF926	500MHz	BF 324, BF 414, BF 506, BF 914, BF 936
36065	BF930	12V, 40mA	-
36066	BF936	350MHz	BF 324, BF 414, BF 506, BF 509, BF 914
36067	BF939	750MHz	BF 324, BF 414, BF 506, BF 509, BF 914
36068	BF959	1100MHz	BF 920, BF 921S
36069	BF960(S)	20V, Idss>2mA, Up<2,7V	BF 900, BF 965...966
36070	BF961	Idss>2mA, Up<4V	BF 963...964, BF 981...982
36071	BF962	20V	BF 961, BF 963...964, BF 981...982
36072	BF963	Idss>6mA, Up<3,5V	BF 961, BF 964, BF 981...982
36073	BF964(S)	Idss>2mA, Up<2,5V	BF 961, BF 963, BF 981...982
36074	BF965	10V, Ids30mA, Up<4V	-
36075	BF965	20V, 30mA	BF 960, BF 966
36076	BF966(S)	20V, Idss>2mA, Up<2,5V	BF 900, BF 960, BF 965
36077	BF967	900MHz	BF 479, BF 679...680, BF 779, BF 979
36078	BF968	1100MHz	BF 479, BF 679, BF 779, BF 979
36079	BF969(S)	850MHz	BF 479, BF 679...680, BF 779, BF 979
36080	BF970(A)	900MHz	BF 479, BF 679...680, BF 779, BF 979
36081	BF979(S)	1350..1600MHz	BF 479
36082	BF980(A)	18V, Up<1,3V	BF 960, BF 965...966
36083	BF981	Idss>4mA, Up<2,5V	BF 961, BF 963...964, BF 982
36084	BF982(T)	20V, Up<1,3V	BF 961, BF 963...964, BF 981
36085	BF987	20V, Idss5..18mA	-
36086	BF988	12V, Idss>2mA, Up<2,5V	BF 960, BF 965...966
36087	BF989(S)	BF 960, SMD	BF 996
36088	BF990(A)	BF 980(A), SMD	BF 989, BF 996
36089	BF990AR	BF 980(A), SMD	-

36090	BF991	BF 981, SMD	BF 993, BF 994
36091	BF992(T)	BF 982(T), SMD	BF 993, BF 994
36092	BF992R	BF 982, SMD	-
36093	BF993	BF 963, SMD	BF 991, BF 994
36094	BF994(S)	BF 964, SMD	BF 991, BF 993
36095	BF994R	BF 964, SMD	-
36096	BF995	BF 965, SMD	BF 991, BF 993, BF 994
36097	BF996(S)	BF 966, SMD	BF 989, BF 990
36098	BF996R	BF 966, SMD	-
36099	BF997	BF 965, SMD	BF 989, BF 996
36100	BF998	BF 988, SMD	-
36101	BF999	BF 987, SMD	-
36102	BFE182	BFR 182	-
36103	BFE183	BFR 183	-
36104	BFE193	BFR 193	-
36105	BFE196	BFP 196	-
36106	BFG135(A)	25V, 0,15A, 7GHz	-
36107	BFG16A	40V, 0,15A, 1600MHz	-
36108	BFG17A	25V, 25mA, 2800MHz	-
36109	BFG193	20V, 0,08A, 8GHz	-
36110	BFG194	20V, 0,1A, 5000MHz	BFG 55, BFG 198
36111	BFG195	20V, 0,1A, 0,5W, 7,5GHz	2SC3358, 2SC3603
36112	BFG196	20V, 0,1A, 7200MHz	BFG 135
36113	BFG197	20V, 0,1A, 7500MHz	-
36114	BFG197X	BFG 197	-
36115	BFG197XR	BFG 197	-
36116	BFG198	20V, 0,1A, 8GHz	-
36117	BFG19S	20V, 0,1A, 5300MHz	-
36118	BFG23	15V, 35mA, 5GHz	BFQ 75...76
36119	BFG235	20V, 0,3A, 6GHz	-
36120	BFG25(A,X)	8V, 6,5mA, 5000MHz	-
36121	BFG31	20V, 0,1A, 5000MHz	BFG 55
36122	BFG32	20V, 75mA, 4,5GHz	BFQ 194
36123	BFG33	9V, 20mA, 12GHz	-
36124	BFG33X	BFG 33	-
36125	BFG34	25V, 150mA, 3,7GHz	BFG 96
36126	BFG35	25V, 0,15A, 4GHz	BFG 135
36127	BFG505	20V, 18mA, 9000MHz	-
36128	BFG505X	BFG 505	-
36129	BFG505XR	BFG 505	2SC4095
36130	BFG51	20V, 25mA, 5GHz	BFQ 75...76
36131	BFG520	20V, 70mA, 9000MHz	-
36132	BFG520X	BFG 520	-
36133	BFG520XR	BFG 520	-
36134	BFG540	20V, 120mA, 9000MHz	-

36135	BFG540X	BFG 540	-
36136	BFG540XR	BFG 540	-
36137	BFG541	20V, 120mA, 9000MHz	-
36138	BFG55	25V, 0,15A, 4GHz	BFG 31
36139	BFG65(T)	20V, 50mA, 7,5GHz	BFQ 65...66, 2SC3062, 2SC3584
36140	BFG67	20V, 0,05A, 8GHz	BFG 197
36141	BFG67R	BFG 67	-
36142	BFG67X	BFG 67	-
36143	BFG67XR	BFG 67	-
36144	BFG90A	20V, 25mA, 5GHz	BFQ 28, BFR 49, BFR 90
36145	BFG91A	15V, 35mA, 6GHz	BFQ 57, BFQ 58, BFQ 74
36146	BFG92(A)XR	BFG 92	-
36147	BFG92A	20V, 25mA, 5GHz	BFG 67, BFG 93A
36148	BFG92AX	BFG 92	-
36149	BFG93(A)XR	BFG 93	-
36150	BFG93A	20V, 35mA, 6GHz	BFG 197
36151	BFG93AX	BFG 93	-
36152	BFG94	15V, 60mA, 6GHz	BFG 35
36153	BFG96	20V, 150mA, 5GHz	-
36154	BFG97	20V, 0,1A, 5,5GHz	BFG 135
36155	BFJ17	60V, 1A, 400MHz	BFS 23, BFV 90, BFW 47, BFX 17
36156	BFJ18	30V, 550MHz	BFS 62, BFW 41, BFX 18...19, BFX 31
36157	BFJ19	30V, 550MHz	BFS 62, BFW 41, BFX 18...19, BFX 31
36158	BFJ45	80V, 1A, 0,8W, 120MHz	BSW 65...68, BSX 45...47, 2N3107...3110
36159	BFJ46	80V, 1A, 0,8W, 120MHz	BSW 65...68, BSX 45...47, 2N3107...3110
36160	BFJ47	120V, 1A, 0,8W, 120MHz	BSS 42...43, BSW 67...68, BSX 47
36161	BFJ48	120V, 1A, 0,8W, 120MHz	BSS 42...43, BSW 67...68, BSX 47
36162	BFJ49	120V, 1A, 0,8W, 150MHz	BSS 42...43, BSW 67...68, BSX 47
36163	BFJ50	120V, 1A, 0,8W, 150MHz	BSS 42...43, BSW 67...68, BSX 47
36164	BFJ51	35V, 0,8W, 60MHz	-
36165	BFJ52	35V, 0,8W, 75MHz	-
36166	BFJ53	64V, 0,8W, 120MHz	-
36167	BFJ54	64V, 0,8W, 120MHz	-
36168	BFJ57	125V, 0,8W, 40MHz	BF 257...259, BF 657...659, 2N5058...5059
36169	BFJ64	40V, 0,5A, 0,7W, <50/-ns	BSW 23, 2N3072...3073, 2N3467...3468
36170	BFJ67	40V, 0,36W	-
36171	BFJ68	40V, 0,36W	-
36172	BFJ70	550MHz	BF 199, BF 224, BF 311, BF 373, BF 597
36173	BFJ72	B>30	BC 167, BC 182, BC 237, BC 547
36174	BFJ73	BFJ 72, B>76	BC 167, BC 182, BC 237, BC 547
36175	BFJ74	70V, 0,3W, >250MHz	BC 174, BC 182, BC 190, BC 546
36176	BFJ75	40V, 0,3W, >300MHz	BC 167, BC 183, BC 237, BC 547
36177	BFJ77	>800MHz	BF 689, BF 763, 2N918, 2N2857
36178	BFJ78	>600MHz	BF 689, BF 763, 2N918, 2N2857
36179	BFJ79	>600MHz	BF 689, BF 763, 2N918, 2N2857

36180	BFJ92	50V, 0,1A, 0,3W, 45MHz, B>40	BC 184, BC 413...414, BC 550
36181	BFJ93	BFJ 92, B>100	BC 184, BC 413...414, BC 550
36182	BFJ98	150V, 0,1A, 0,8W, 90MHz	BF 257...259, BF 657...659, 2N5058...5059
36183	BFN	SM 15T 68C	SM 15T...
36184	BFN16	250V, 0,2A, >60MHz	2SC3554
36185	BFN17	250V, 0,2A, >60MHz	-
36186	BFN18	BFN 16, 300V	2SC3554
36187	BFN19	BFN 17, 300V	-
36188	BFN20	300V, 20..50mA, >60MHz	BFN 18, 2SC3554
36189	BFN21	300V, 20..50mA, >60MHz	BFN 19
36190	BFN22	250V, 0,02A, >60MHz	BF 820, BF 822
36191	BFN22R	BFN 22	-
36192	BFN23	250V, 0,02A, >60MHz	BF 821, BF 823
36193	BFN23R	BFN 23	-
36194	BFN24	BFN 16	-
36195	BFN25	BFN 17	-
36196	BFN26	BFN 18	-
36197	BFN27	BFN 19	-
36198	BFN36	BFN 16, 1,5W	-
36199	BFN37	BFN 17, 1,5W	-
36200	BFN38	BFN 18, 1,5W	-
36201	BFN39	BFN 19, 1,5W	-
36202	BFP	2SB1308-P	2SB1308
36203	BFP	SM 15T 68CA	SM 15T...
36204	BFP10	25V, 100mA, 0,35W, 4GHz	BFG 96, BFP 96, BFR 96, BFQ 73
36205	BFP11	150V, 0,5A, 1,25W, 60MHz	BF 391...393, BFP 22, BFP 25, MPSA 42...43
36206	BFP12	BFP 11, 250V	BF 392...393, BFP 25, MPSA 42
36207	BFP13	BFP 11, 350V	MPSA 44...45, 2SD1350
36208	BFP14	BFP 11, 450V	MPSA 44, 2SD1350A
36209	BFP17	BFS 17P	-
36210	BFP180	BFR 180	-
36211	BFP181	BFR 181	-
36212	BFP182	BFR 182	-
36213	BFP183	BFR 183	-
36214	BFP193	BFR 193	-
36215	BFP194	BFR 194	-
36216	BFP196	20V, 0,1A, 8GHz	-
36217	BFP22	>50MHz	BF 391...393, MPSA 42...43
36218	BFP23	>50MHz	BF 491...493, MPSA 92...93, 2SB918
36219	BFP25	BFP 22, 300V	BF 393, MPSA 42
36220	BFP26	BFP 23, 300V	BF 493, MPSA 92
36221	BFP280	BFR 280	-
36222	BFP29	BFQ 29P	BFG 93A
36223	BFP35A	BFR 34AP	BFG 93A
36224	BFP405	15V, 12mA, >20GHz	-

36225	BFP420	15V, 35mA, >20GHz	-
36226	BFP67	BFG 67	-
36227	BFP81	BFQ 81	-
36228	BFP90(A)	20V, 30mA, 0,25W, 5GHz	BFQ 69, BFQ 85, BFR 14, BFR 91
36229	BFP91(A)	15V, 50mA, 0,35W, 6GHz	BFG 65, BFQ 65...66, 2SC3511, 2SC3062
36230	BFP92	22V, 0,35W, 3,5GHz	BFQ 59...60, BFQ 70...71, BFT 97
36231	BFP92A	BFG 92A	-
36232	BFP93A	BFG 93A	-
36233	BFP96	20V, 100mA, 0,5W, 4,5GHz	BFG 96, BFQ 73, BFR 96
36234	BFQ	2SB1308-Q	2SB1308
36235	BFQ131	25V, 0,15A, 4GHz	-
36236	BFQ136	25V, 0,6A, 9W(Tc110°), 4GHz	-
36237	BFQ149	BFQ 32, SMD	-
36238	BFQ161	20V, 0,5A, 1GHz	-
36239	BFQ162	20V, 0,5A, 1GHz	-
36240	BFQ166	20V, 0,5A, 2W, 1000MHz	-
36241	BFQ17(P)	40V, 150mA, 1200MHz	BFQ 64
36242	BFQ18(A)	30V, 150mA, 3,5GHz	BFQ 64
36243	BFQ181	20V, 0,02A, 8GHz	BFQ 77
36244	BFQ182	20V, 35mA, 8,3GHz	BFQ 66, BFQ 645
36245	BFQ19(P,S)	20V, 75mA, 5GHz	2SC3268
36246	BFQ193	20V, 0,08A, 7,5GHz	2SC3301
36247	BFQ194	BFR 194	-
36248	BFQ196	BFR 196	-
36249	BFQ22(S)	15V, 35mA, 0,15W, 5GHz	BFQ 69, BFQ 85, BFR 14, BFR 91
36250	BFQ221	100V, 0,1A, 1GHz	BFQ 231(A)
36251	BFQ222	BFQ 221, 5W	BFQ 232(A)
36252	BFQ225	BFQ 221, 3,75W	BFQ 235(A)
36253	BFQ226	BFQ 221, 3W(Tc60°)	BFQ 236(A)
36254	BFQ23	15V, 35mA, 0,18W, 5GHz	BFQ 56, BFQ 75...76
36255	BFQ231	100V, 0,3A, >1GHz	-
36256	BFQ231A	BFQ 231, 115V, >800MHz	-
36257	BFQ232(A)	BFQ 231(A), 3W(Tc115°)	BFQ 262(A)
36258	BFQ235(A)	BFQ 231(A), 3W(Tc100°)	BFQ 265(A)
36259	BFQ236(A)	BFQ 231(A), 3W(Tc115°)	-
36260	BFQ23C	BFQ 23	BFQ 56, BFQ 75...76
36261	BFQ24	15V, 35mA, 0,15W, 5GHz	BFQ 24, BFQ 56, BFQ 75...76
36262	BFQ241	100V, 0,1A, 1GHz	BFQ 251(A)
36263	BFQ242	BFQ 241, 5W	BFQ 252(A)
36264	BFQ245	BFQ 241, 3,75W	BFQ 255(A)
36265	BFQ246	BFQ 241, 3W(Tc60°)	BFQ 256(A)
36266	BFQ251	100V, 0,3A, >1GHz	-
36267	BFQ251A	BFQ 231, 115V, >800MHz	-
36268	BFQ252(A)	BFQ 251(A), 3W(Tc115°)	-
36269	BFQ255(A)	BFQ 251(A), 3W(Tc100°)	-

36270	BFQ256(A)	BFQ 251(A), 2W(Tc115°)	-
36271	BFQ262	100V, 0,4A, 5W, >1GHz	-
36272	BFQ262A	BFQ 262, 115V, >800MHz	-
36273	BFQ265(A)	BFQ 262(A), 5W(Tc65°)	-
36274	BFQ27	15V, 25mA, 0,2W	BFQ 69, BFQ 85, BFR 14, BFR 91
36275	BFQ28	20V, 15mA, 0,2W, 5GHz	BFG 90, BFQ 85, BFR 49, BFR 90...91
36276	BFQ29(P)	20V, 30mA, 4GHz	BFR 92...93, BFT 75
36277	BFQ29R	BFQ 29	BFR 92R...93R, BFT 75R
36278	BFQ30	10V, 100mA, 0,25W, 2GHz	BFG 34, BFT 12, BFX 59
36279	BFQ31(A)	30V, 100mA, 0,2W, >600MHz	BFR 106
36280	BFQ31(A)R	BFQ 31	-
36281	BFQ32	20V, 75mA, 0,5W, 4,2GHz	BFQ 79, BFT 96
36282	BFQ32C	BFQ 32, 100mA, 4,5GHz	BFQ 194
36283	BFQ32S	BFQ 32, 100mA, 0,7W, 4,5GHz	BFQ 194
36284	BFQ33	9V, 20mA, 0,14W, 12GHz	-
36285	BFQ33C	BFQ 33	-
36286	BFQ34	25V, 150mA, 4GHz	BFQ 68
36287	BFQ34T	BFQ 34, 3,7GHz	BFG 34, BFG 96
36288	BFQ35	160V, 0,2A, 0,8W, >80MHz	BFT 44...45, 2SB606, 2SB622
36289	BFQ36	BFQ 35, 250V	BFT 44...45, 2SB606, 2SB622
36290	BFQ37	BFQ 35, 300V	BFT 44, 2SB622
36291	BFQ38	300/250V, 1A, 0,6W, >20MHz	BUX 55, BUY 59...60
36292	BFQ39	BFQ 38, 300/300V	BUX 55, BUY 59...60
36293	BFQ40	BFQ 38, 450/350V	BUX 55, BUY 59...60
36294	BFQ41	50V, 350mA, 1GHz	BFR 65, MRF 626, 2N5944
36295	BFQ42	36V, 600mA, PQ2W(175MHz)	BFW 46, BLY 33, MRF 227, 2N3924
36296	BFQ43(S)	36V, 1,25A, PQ4W(175MHz)	2N6255
36297	BFQ51	20V, 25mA, 0,18W, 5GHz	BFT 95, BFQ 23, BFQ 56, BFQ 75...76
36298	BFQ51C	BFQ 51, 30mA, 0,25W	BFT 95, BFQ 23, BFQ 56, BFQ 75...76
36299	BFQ52	20V, 25mA, 0,15W, 5GHz	BFT 95, BFQ 23...24, BFQ 56, BFQ 75...76
36300	BFQ53	20V, 25mA, 0,15W, 5GHz	BFR 14, BFR 90...92, BFQ 22, BFQ 85
36301	BFQ54T	25V, 150mA, 1W, 4,5GHz	-
36302	BFQ56	20V, 30mA, 5GHz	BFQ 23, BFQ 75...76
36303	BFQ57	25V, 35mA, 0,45W, 6,5GHz	BFG 65, BFQ 65...66, BFQ 74
36304	BFQ58	25V, 30mA, 0,45W, 6,5GHz	BFG 65, BFQ 65...66, BFQ 74
36305	BFQ59	27V, 35mA, 0,7W, 4GHz	BFT 97, BFQ 60, BFQ 70...71
36306	BFQ60	27V, 35mA, 0,7W, 4GHz	BFT 97, BFQ 59, BFQ 70...71
36307	BFQ61	15V, 30mA, 5GHz	BFT 93
36308	BFQ62	15V, 90mA, 5GHz	-
36309	BFQ63	20V, 75mA, 4,5GHz	BFG 96, BFP 96, BFR 96, BFQ 73
36310	BFQ64	30V, 200mA, 3GHz	-
36311	BFQ645	25V, 0,04A, 9GHz	-
36312	BFQ65	20V, 50mA, 0,3W, 7,5GHz	BFG 65, BFQ 66, 2SC3062
36313	BFQ66	20V, 50mA, 0,3W, 7,5GHz	BFG 65, BFQ 65, 2SC3062
36314	BFQ67	20V, 0,05A, 8GHz	3SC3356, 2SC3445, 2SC3583, 2SC4592



36315	BFQ67W	BFQ 67	3SC4593
36316	BFQ68	25V, 300mA, 4,5W, 4GHz	-
36317	BFQ69	25V, 30mA, 0,2W, 5,8GHz	BFG 91, BFP 91, BFQ 57...58, BFQ 74
36318	BFQ70	20V, 30mA, 5GHz	BFR 14, BFT 97, BFQ 59...60, BFQ 71
36319	BFQ71	20V, 30mA, 5,2GHz	BFR 14, BFR 91, BFQ 69, BFQ 85
36320	BFQ72	20V, 50mA, 5,1GHz	BFP 91, BFP 96, BFT 65, BFR 96
36321	BFQ73(S)	20V, 90mA, 0,29W, 5GHz	BFG 96, BFP 96, BFR 96
36322	BFQ74	25V, 35mA, 6GHz	BFG 65, BFQ 57...58, BFQ 65...66
36323	BFQ75	15V, 50mA, 5GHz	BFQ 23, BFQ 56, BFQ 76
36324	BFQ76	20V, 30mA, 5GHz	BFQ 23, BFQ 56, BFQ 75
36325	BFQ77	-/15V, 20mA, 0,25W, 7GHz	BFG 65, BFQ 65...66, 2SC3586...87
36326	BFQ78	25V, 50mA, 0,7W, 3,3GHz	BFQ 32, 2SA1057...1058, 2SA1223
36327	BFQ79	-/15V, 75mA, 0,29W, 4,2GHz	BFT 96, BFQ 32(S), 2SA1057, 2SA1223
36328	BFQ80	-/15V, 20mA, 0,29W, 7GHz	BFG 65, BFQ 65...66, BFQ 77
36329	BFQ81	25V, 0,03A, 4,2GHz	BFQ 29, BFR 93
36330	BFQ82	20V, 0,08A, 8GHz	-
36331	BFQ85	20V, 40mA, 0,2W, 5GHz	BFG 91, BFR 14, BFR 91, BFQ 69
36332	BFQ88	20V, 40..80mA, 5GHz	BFG 91, BFP 91, 2SC3511
36333	BFQ88A	BFQ 88, 80mA, 0,35W	BFG 96, BFR 96, BFQ 73
36334	BFQ89	20V, 20mA, 0,2W, 6GHz	BFG 91, BFQ 57...58, BFQ 74, BFQ 77
36335	BFQ98	20V, 40mA, 0,25W, 5GHz	BFT 96, BFQ 23, BFQ 56, BFQ 75...76
36336	BFR	2SC4642K-R	2SC4642K
36337	BFR	2SC4723-R	2SC4723
36338	BFR	2SB1308-R	2SB1308
36339	BFR10	75V, 0,5A, 0,8W, 14/80ns	BFX 96A...97A, BSS 27, 2N2218A...19A
36340	BFR101A	30V, Idss>0,2mA, Up<1V	-
36341	BFR101B	BFR 101A, Idss>1mA, Up<2,5V	-
36342	BFR106	20V, 0,1A, 5GHz	2SC3356, 2SC3775
36343	BFR11	BFR 10, 0,4W	BFX 94A...95A, BSW 63, 2N2221A...22A
36344	BFR12	55V, 300mA, >480MHz	BLW 10, BFX 55, 2N4428, 2SC2852
36345	BFR134	25V, 0,15A, 7GHz	-
36346	BFR14	20V, 30mA, 0,25W, 3,6GHz	BFT 97, BFQ 59...60, BFQ 70...71
36347	BFR14A	20V, 30mA, 0,25W, 5GHz	BFG 91, BFR 91, BFQ 69, BFQ 85
36348	BFR14B	BFR 14A, 6GHz	BFG 91, BFQ 57...58, BFQ 74
36349	BFR14C	4,3GHz	BFR 91, BFQ 69, BFQ 71, BFQ 85
36350	BFR15(A)	20V, 30mA, 0,2W, 3,3..4,5GHz	BFS 55, BFT 66...67, BFQ 22, BFQ 63
36351	BFR16	60V, 0,05A, 100MHz, B>150	BC 382, BC 414, BC 550, 2N2483...84
36352	BFR17	BFR 16, B>450	BC 382, BC 414, BC 550, 2N2483...84
36353	BFR18	85V, 0,5A, 0,5W, 90MHz	BC 639, BCX 24, 2N3700...01, 2SD667
36354	BFR180	15V, 4mA, 4,4GHz	-
36355	BFR180W	BFR 180	-
36356	BFR181	20V, 0,02A, 8GHz	2SC3585
36357	BFR181W	BFR 181	-
36358	BFR182	20V, 35mA, 8GHz	2SC3585
36359	BFR182W	BFR 182	-

36360	BFR183	20V, 65mA, 8GHz	BFR 193, 2SC3445
36361	BFR183W	BFR 183	2SC4593
36362	BFR19	75V, 1A, 0,8W, 100MHz	BC 140...141, 2N1990, 2N2102, 2N2405
36363	BFR193	20V, 0,08A, 8GHz	2SC3356, 2SC3445
36364	BFR193W	BFR 193	-
36365	BFR194	20V, 0,1A, 5GHz	-
36366	BFR20	75V, 1A, 0,8W, 130/450ns	BC 140...141, BSX 59...61, 2N3444
36367	BFR200	30V, 20mA, Idss>0,2m	-
36368	BFR21	120V, 1A, 0,8W, 130/450ns	BSS 42...43, BSW 67...68, BSX 47
36369	BFR22	120V, 1A, 1W, >120MHz	BSS 42...43, BSW 67...68, BSX 47, 2N2102
36370	BFR23	90V, 1A, 1W, <110/700ns	BSW 40, 2N4036
36371	BFR24	60V, 1A, 1W, <110/700ns	BSW 40, 2N4030...4033, 2N4036...4037
36372	BFR25	120V, 0,1A, 0,375W, >50MHz	BF 279...299, BSS 38, BSX 21
36373	BFR26	30V, 0,12A, 0,3W, >350MHz	BFX 59, BFW 16...17
36374	BFR27	160V, 0,4A, 0,6W	2SD413, 2SD576, 2SD624
36375	BFR28	30V, 50mA, 0,2W, 1GHz	BF 357, BF 377...378, BF 763, 2SC3037
36376	BFR280	15V, 0,01A, 5GHz	BFR 92
36377	BFR280W	BFR 280	BFR 92W
36378	BFR29	30V, Idss>10mA, Up<4V	3N142...143, 3N152, 3N154, 3N192...193
36379	BFR30	25V, Idss>4mA, Up<5V	BF 512
36380	BFR31	25V, Idss>1mA, Up<2,5V	BF 511, 2SK425
36381	BFR34(A)	20V, 30mA, 3,3..4,5GHz	BFT 97, BFQ 59...60, BFQ 70...71, 2N6620
36382	BFR35(A)R	BFR 34, SMD	BFR 92R...93R, BFT 75R, BFQ 29R
36383	BFR35(A,AP)	BFR 34, SMD	BFR 92...93, BFT 75, BFQ 29, 2N6619
36384	BFR36(A)	40V, 200mA, 0,8W, 1,3GHz	BFW 16...17, 2N4428, 2N5160
36385	BFR37	30V, 50mA, 0,25W, 1,4GHz	BFW 30, BFX 59, BFX 73
36386	BFR38	40V, 20mA, 0,2W, 1GHz	BF 272, BF 316, BF 516, BF 606
36387	BFR39	ns	BC 639, BFR 50, BFT 29, BFT 53
36388	BFR40	BFR 39, 70V	BC 639, BFR 50, BSS 26, BSS 40...41
36389	BFR41	BFR 39, 60V	BC 637, BSS 26, BSS 40...41, BFR 51
36390	BFR45	30V, Idss>2mA, Up<8V	BFW 10...11, BFS 72, 2N3823
36391	BFR46	15V, Idss<0,01mA, Up2V	-
36392	BFR47	BFR 46	-
36393	BFR48	50V, 100mA, 0,45W, >600MHz	BFR 36, BFW 16...17, BFX 55
36394	BFR49	20V, 25mA, 0,3W, 5GHz	BFG 90, BFQ 28, BFQ 85, BFR 90...91
36395	BFR50	ns	BC 639, BFR 39, BFT 29, BFT 53
36396	BFR505	20V, 18mA, 9GHz	-
36397	BFR51	BFR 50, 60V	BC 637, BFR 40, BSS 26, BSS 40...41
36398	BFR52	BFR 50, 40V	BC 637, BFR 41, BSS 26, BSS 40...41
36399	BFR520	20V, 70mA, 9GHz	-
36400	BFR53	18V, 50mA, 2GHz	BFR 93, BFT 75, 2SC3014
36401	BFR53R	BFR 53	BFR 93R, BFT 75R
36402	BFR54	40V, 500mA, 500MHz	2SC2851, BFX 55, 2SC2852
36403	BFR541	BFG 541	-
36404	BFR56	60V, 1,2A, 1W	BC 140...141, BSW 65...68, BSX 45...47

36405	BFR57	160V, 0,2A, 1W, 100MHz	BF 257...259, BF 657...659, 2N5058...5059
36406	BFR58	BFR 57, 250V	BF 258...259, BF 658...659, 2N5058...5059
36407	BFR59	BFR 57, 300V	BF 259, BF 659, 2N5058, BFS 89
36408	BFR60	ns	BC 640, BFR 79, BFT 20, BFT 69
36409	BFR61	BFR 60, 60V	BC 638, BFR 80, 2N4026...4029
36410	BFR62	BFR 60, 40V	BC 638, BFR 81, 2N4026...4029
36411	BFR63	PQ0,15W(200MHz)	BFR 64...65, BFT 91, BLX 96
36412	BFR64	PQ0,09W(800MHz)	BFT 91, BLX 96
36413	BFR65	PQ0,45W(200MHz)	BFT 91, BLX 96
36414	BFR67(A,B)	50V, 0,15A	BC 167, BC 182, BC 237, BC 547
36415	BFR68(A..C)	BFR 67, 30V	BC 169, BC 184, BC 239, BC 549
36416	BFR69(VI,A,B)	50V, 0,15A	BC 212, BC 257, BC 307, BC 557
36417	BFR70(VI,A,B)	BFR 69, 30V	BC 214, BC 259, BC 309, BC 559
36418	BFR71	85V, 0,2A, B>40	BC 546, 2SC3245
36419	BFR72	BFR 71, B>100	BC 546, 2SC3245
36420	BFR73	60V, 0,2A, B>40	BC 556, 2SA1285
36421	BFR74	BFR 73, B>100	BC 556, 2SA1285
36422	BFR75	700MHz	BF 225, BF 314, BF 496, BF 502...503
36423	BFR76	450MHz	BF 324, BF 414, BF 506, BF 914
36424	BFR77	120/80V, 1A, 0,8W, >50MHz	BSW 67...68, BSX 47, 2N3019...3020
36425	BFR78	BFR 77, 120/100V	BSW 67...68, BSX 47, 2N3019...3020
36426	BFR79	ns	BC 640, BFR 60, BFT 20, BFT 69
36427	BFR80	BFR 79, 70V	BC 640, BFR 60, 2N4026...4029
36428	BFR81	BFR 79, 60V	BC 638, BFR 61, 2N4026...4029
36429	BFR83	40V, 0,2A, 1400MHz	BFR 64...65
36430	BFR84	20V, Idss>20mA, Up<3,8V	-
36431	BFR86(A,B)	120V, 0,2A, 0,8W, 130MHz	BFT 57...59, BF 391...393, BF 422A
36432	BFR87(A,B)	BFR 86, 160V	BFT 57...59, BF 391...393, BF 422A
36433	BFR88(A,B)	BFR 86, 250V	BFT 58...59, BF 392...393, BF 422A
36434	BFR89(A,B)	BFR 86, 300V	BFT 59, BF 393, BF 420A
36435	BFR90(A,B,H)	20V, 25mA, 5GHz	BFG 90, BFQ 28, BFR 14, BFR 49
36436	BFR91(A,H)	15V, 35mA, 5..6GHz	BFG 91, BFQ 69, BFQ 85, BFR 14
36437	BFR92(A)R	BFR 90, SMD	BFT 75R
36438	BFR92(A)W	BFR 90, SMD	-
36439	BFR92(A,P)	BFR 90, SMD	BFT 75, 2SC3011, 2SC3513, 2SC3161
36440	BFR93(A)R	BFR 91, SMD	BFT 75R
36441	BFR93(A)W	BFR 91, SMD	-
36442	BFR93(A,P)	BFR 91, SMD	BFT 75, 2SC3011, 2SC3513, 2SC3161
36443	BFR94	30V, 0,15A, 3,5GHz	BFQ 34, BFQ 68, BFT 98
36444	BFR95	30V, 0,15A, 3,5GHz	BFG 34, BFG 96
36445	BFR96(H,S)	20V, 75..100mA, 5GHz	BFG 96, BFP 96, BFQ 73
36446	BFR97	55V, 0,5A, PQ>1W(400MHz)	2N3866, 2SC2852
36447	BFR98	40V, 0,5A, PQ>1W(175MHz)	BFQ 42, BFS 51, BLW 16, 2N4427
36448	BFR99(A)	25V, 50mA, 2..2,3GHz	BFT 96, BFQ 32, BFQ 78, 2SA1228
36449	BFS	2SC4642K-S	2SC4642K

36450	BFS	2SC4723-S	2SC4723
36451	BFS10	55V, 400mA, 0,5W, >500MHz	BFW 47, BFX 55, 2N3553
36452	BFS11	800MHz	BF 225, BF 314, BF 496, BF 502
36453	BFS12	40V, 1A, 0,8W, >100MHz	BC 160...161, BCX 60, 2N4234...4236
36454	BFS13E	40V, 0,05A, 90MHz	BC 123
36455	BFS13F	BFS 13E	BC 123
36456	BFS13G	BFS 13E	BC 123
36457	BFS14E	40V, 0,05A, 40MHz	BC 203
36458	BFS14F	BFS 14E	BC 203
36459	BFS14G	BFS 14E	BC 203
36460	BFS15E	40V, 0,05A, 400MHz	BC 123
36461	BFS15F	BFS 15E	BC 123
36462	BFS15G	BFS 15E	BC 123
36463	BFS16E	40V, 0,05A, 210MHz	BC 203
36464	BFS16F	BFS 16E	BC 203
36465	BFS16G	BFS 16E	BC 203
36466	BFS17(A,P,S)	25V, 25mA, 1..2,8GHz	2SC3005, 2SC3016, 2SC3161
36467	BFS17R(AR)	BFS 17	-
36468	BFS17W	BFS 17	-
36469	BFS18	30V, 30mA, 200MHz	BF 554, BF 599, BF 799, BFS 20
36470	BFS18R	BFS 18	BFS 20R
36471	BFS19	30V, 30mA, 260MHz	BF 554, BF 599, BF 799, BFS 20
36472	BFS19R	BFS 19	BFS 20R
36473	BFS20	30V 25mA, 450MHz	BF 599, BF 799, BFS 17, 2SC3015, 2SC3374
36474	BFS20R	BFS 20	BFS 17R
36475	BFS22(A,R)	36V, 0,75A, PQ4W(175MHz)	BFW 46, BFQ 43, MRF 237, 2N3924
36476	BFS22Q	BFS 22	BLY 85, 2N5589
36477	BFS23(A,R)	65V, 0,5A, PQ4W(175MHz)	BFW 47, BLY 34, 2N3553
36478	BFS25A	8V, 6,5mA, 5000MHz	BFS 505
36479	BFS26E	20V, 0,05A, 550MHz	-
36480	BFS26F	BFS 26E	-
36481	BFS26G	BFS 26E	-
36482	BFS27E	20V, 0,05A, 400MHz	-
36483	BFS27F	BFS 27	-
36484	BFS27G	BFS 27	-
36485	BFS28(R)	20V, Up<5V	3N201...206, 3N209...213
36486	BFS36	45V, 0,5A, >30MHz	BC 817R, BCW 65R...66R, BCX 19R
36487	BFS36A	BFS 36, 30V	BC 818R, BCW 65R...66R, BCX 20R
36488	BFS37	45V, 0,5A, >30MHz	BC 807R, BCW 67R...68R, BCX 17R
36489	BFS37A	BFS 37, 30V	BC 808R, BCW 67R...68R, BCX 18R
36490	BFS38	45V, 0,5A, >150MHz	BC 817R, BCW 65R...66R, BCX 19R
36491	BFS38A	BFS 38, 25V	BC 818R, BCW 65R...66R, BCX 20R
36492	BFS39	BFS 38, 60V	BCW 65R...66R, BCX 41R
36493	BFS40	45V, 0,5A, >150MHz	BC 807R, BCW 67R...68R, BCX 17R
36494	BFS40A	BFS 40, 25V	BC 808R, BCW 67R...68R, BCX 18R

36495	BFS41	BFS 40, 60V	BCW 68R, BCX 42R
36496	BFS42	60/30V, 1A, >60MHz	BCW 65R...66R, BCX 41R
36497	BFS43	BFS 42, 60/60V	BCW 65R...66R, BCX 41R
36498	BFS44	60/30V, 1A, >60MHz	BCW 68R, BCX 42R
36499	BFS45	BFS 44, 60/60V	BCW 68R, BCX 42R
36500	BFS46(A)	30V, 0,5A, >600MHz	-
36501	BFS50	36V, 0,4A, PQ>1W(400MHz)	MRF 629, 2N3948
36502	BFS505	BFG 505	-
36503	BFS51	40V, 0,75A, PQ1W(175MHz)	BFQ 42, BFR 98, BLW 16, BLY 61
36504	BFS520	BFG 520	-
36505	BFS540	BFG 540	-
36506	BFS55	20/12V, 50mA, 0,325W, 3,3GHz	BFQ 63, BFQ 72, BFT 65
36507	BFS55A	BFS 55, 20/15V, 4,5GHz	BFQ 63, BFQ 72, BFT 65
36508	BFS59(K,L,M)	60V, 1A, 0,5W, >150MHz,B>40	BC 637, BSS 26, BSS 40...41, 2N2221...22
36509	BFS60(K,L,M)	BFS 59, B>100	BC 637, BSS 26, BSS 40...41, 2N2221...22
36510	BFS61(K,L,M)	BFS 59, 80V	BC 639, 2N2221A...2222A
36511	BFS62	40V, 25mA, >580MHz	BF 225, BF 314, BF 496, BF 502...503
36512	BFS64	30V, 50mA, 0,4W	BFW 93
36513	BFS65	40V, 200mA, 0,4W	-
36514	BFS69	30V, 0,1A, >50MHz	BC 202...203
36515	BFS70	50V, Idss>0,5mA, Up<4	2N3821
36516	BFS71	50V, Idss>2mA, Up<6V	2N3822
36517	BFS72	30V, Idss>4mA, Up<8V	2N3823
36518	BFS73	50V, on<250Ohm	2N3824
36519	BFS74	40V, Idss>50mA, Up<10V	BSV 78, 2N4856
36520	BFS75	40V, Idss>20mA, Up<6V	BSV 79, 2N4857
36521	BFS76	40V, Idss>8mA, Up<4V	BSV 80, 2N4858
36522	BFS77	BFS 74, 30V	BSV 78, 2N4859
36523	BFS78	BFS 75, 30V	BSV 79, 2N4860
36524	BFS79	BFS 76, 30V	BSV 80, 2N4861
36525	BFS80	30V, Idss>5mA, Up<6V	BFW 11, 2N4416, 2N5245
36526	BFS85	25V, 25mA, >1GHz	BFS 17R
36527	BFS88	30V, 25mA, >1GHz	BFS 17R
36528	BFS89	300V, 0,15A, 0,58W, 90MHz	BF 259, BF 659, BFR 59, 2N5058
36529	BFS90(A,B)	140V, 0,1A, 0,8W	BFW 44, 2N3634...3637
36530	BFS91(A,B)	BFS 90, 80V	BSV 17, 2N3634...3637
36531	BFS92	ns	BCX 60, BSS 17, BSW 40, 2N3634...3637
36532	BFS93	BFS 92	BCX 60, BSS 17, BSW 40, 2N3634...3637
36533	BFS94	BFS 92, 80V	BCX 60, BSS 17, BSW 40, 2N3634...3637
36534	BFS95	BFS 92, 40V	BCX 60, BSS 18, BSW 40, 2N3634...3637
36535	BFS96(K,L,M)	60V, 1A, 0,5W, >150MHz,B>40	BC 638, BSW 24, 2N2906(A)...2907(A)
36536	BFS97(K,L,M)	BFS 96, B>100	BC 638, BSW 24, 2N2906(A)...2907(A)
36537	BFS98(K,L,M)	BFS 96, 80V	BC 640, 2N4027...4029
36538	BFS99	120V, 0,05A, 0,3W	BF 297...299, BSS 38, BSX 21
36539	BFT10(A...C)	40V, Idss>10mA, Up<7V	BF 256, BF 348, 2N5397, 2N5486

36540	BFT11	25V, Idss>10mA, Up<9,5V	2N4343
36541	BFT12	25V, 150mA, 2GHz	BFG 34, BFW 16, BFR 95
36542	BFT13	25V, 20mA, 0,3W, 4GHz	BFG 90, BFQ 28, BFR 49, BFR 90
36543	BFT13A,B	BFT 13, 0,15W	BFG 90, BFQ 28, BFR 49, BFR 90
36544	BFT14	25V, 60mA, 0,7W, 4GHz	BFP 96, BFQ 72...73, BFR 96, BFT 65
36545	BFT14A,B	BFT 14, 0,3W	BFP 96, BFQ 72...73, BFR 96, BFT 65
36546	BFT15	25V, 150mA, 0,8W, 3GHz	BFG 34, BFG 96
36547	BFT16	25V, 200mA, 0,7W, 3GHz	BFG 34, BFG 96
36548	BFT17	30V, 50mA, 0,2W, >1,8GHz	BFQ 63, BFS 55
36549	BFT18	25V, 50mA, 0,7W, 4GHz	BFQ 72...73, BFT 65
36550	BFT18A	BFT 18, 0,3W	BFQ 72...73, BFT 65
36551	BFT19	200V, 1A, 1W, >25MHz	BFT 28A...C, MJ 5415...5416, 2N5415...5416
36552	BFT19A	BFT 19, 300V	BFT 28C, MJ 5415...5416, 2N5416
36553	BFT19B	BFT 19, 400V	MJ 5416
36554	BFT20	ns	BC 640, BFT 69, 2N4027, 2N4029
36555	BFT21	BFT 20, 60V	BC 638, BFT 70, 2N4026...4029
36556	BFT22	BFT 20, 40V	BC 638, BFT 71, 2N4026...4029
36557	BFT24	8V, 2,5mA, 0,03W, 2,3GHz	BFQ 59...60, BFQ 70, BFR 34, BFT 97
36558	BFT25	8V, 6,5mA, 0,03W, 2,3GHz	BFQ 29, BFR 35, BFR 53, 2SC3099
36559	BFT25A	BFT 25, 5000MHz	BFR 92...93, 2SC3110
36560	BFT25R	BFT 25	BFQ 29R, BFR 35R, BFR 53R, 2SC3089
36561	BFT27	60V, 0,5A, >30MHz	BCW 65R...66R, BCX 41R
36562	BFT28	150V, 1A, 1W, >25MHz	BFT 19(A,B), 2N5415...5416, MJ 5415...5416
36563	BFT28A	BFT 28, 200V	BFT 19(A,B), 2N5415...5416, MJ 5415...5416
36564	BFT28B	BFT 28, 250V	BFT 19A...B, 2N5416, MJ 5415...5416
36565	BFT28C	BFT 28, 300V	BFT 19A...B, 2N5416, MJ 5415...5416
36566	BFT29	90V, 1A, 0,36W, >100MHz,	BC 639, BFR 39, BFR 50, BFT 53
36567	BFT30	BFT 29, 70V	BC 639, BFR 50, BSS 26, BSS 40...41
36568	BFT31	BFT 29, 60V	BC 639, BFR 51, BSS 26, BSS 40...41
36569	BFT32	80V, 5A, 1W, >100MHz	BSS 45, BUX 34, BUY 80, 2N5336...5339
36570	BFT33	BFT 32, 100V	BUX 34, BUY 80, 2N5338...5339
36571	BFT34	BFT 32, 120V	BUX 34, BUY 80, 2N4895...4897
36572	BFT35	80V, 5A, 1W, >100MHz	BSS 46, BUY 90, 2N6190...6191
36573	BFT36	BFT 35, 100V	BUY 90, 2N6192...6193
36574	BFT37	BFT 35, 120V	BUY 90
36575	BFT38	12V, 35mA, 4800MHz	BFQ 24
36576	BFT39	90V, 1A, 0,8W, >100MHz	BC 141, BSW 39, BSS 42...43, BSX 46...47
36577	BFT40	BFT 39, 70V	BC 140...141, BSW 39, BSX 45...47
36578	BFT41	BFT 39, 60V	BC 140...141, BSW 39, BSX 45...47
36579	BFT42	125/110V, 1A, 0,8W, >50MHz	BSS 42...43, BSW 67...68, BSX 47
36580	BFT43	125/100V, 1A, 0,8W, >50MHz	BSS 42...43, BSW 67...68, BSX 47
36581	BFT44	300V, 0,5A, 0,75W, 70MHz	BFT 19A...B, MJ 5415...5416, 2N5416
36582	BFT45	BFT 44, 250V	BFT 19A...B, MJ 5415...5416, 2N5416
36583	BFT46	25V, Idss>0,2mA, Up<1,2V	-
36584	BFT47	160V, 0,2A, 0,8W, 110MHz	BF 257...259, BFR 57...59, 2N5058...5059



36585	BFT48	BFT 47, 250V	BF 258...259, BFR 58...59, 2N5058...5059
36586	BFT49	BFT 47, 300V	BF 259, BFR 59, BFS 89, 2N5058
36587	BFT50	22V, 0,25W, 3,5GHz	BFR 15, BFS 55, BFT 66...67, BFW 99
36588	BFT51	35V, 0,4A, >3GHz	-
36589	BFT53	ns	BC 639, BFR 39, BFR 50, BFT 29
36590	BFT54	BFT 53, 60V	BC 637, BFT 30, BSS 26, BSS 40...41
36591	BFT55	BFT 53, 40V	BC 637, BFT 30, BSS 26, BSS 40...41
36592	BFT57	160V, 0,2A, 0,36W, 110MHz	BF 391...393, BFR 87...89, BF 422A
36593	BFT58	BFT 57, 250V	BF 392...393, BFR 88...89, BF 422A
36594	BFT59	BFT 57, 300V	BF 393, BFR 89, BF 420A
36595	BFT60	ns	BCX 60, BSW 40, 2N4031, 2N4033
36596	BFT61	BFT 60, 60V	BC 161, BSW 40, 2N4030...4033
36597	BFT62	BFT 60, 40V	BC 160...161, BSW 40, 2N4030...4033
36598	BFT65	20V, 50mA, 0,25W, 5GHz	BFP 96, BFQ 72...73, BFR 96
36599	BFT66	20V, 30mA, 0,2W, 4GHz	BFQ 22, BFQ 63
36600	BFT66S(E)	BFT 66, 25V	BFQ 22, BFQ 63
36601	BFT67	20V, 30mA, 0,2W, 4GHz	BFQ 22, BFQ 63
36602	BFT69	90V, 1A, 0,36W, >100MHz	BC 640, BFR 60, BFR 79, BFT 20
36603	BFT70	BFT 69, 70V	BC 640, BFT 20, 2N4027, 2N4029
36604	BFT71	BFT 69, 60V	BC 638, BFT 21, 2N4026...4029
36605	BFT72	160V, 0,1A, 60MHz	BF 457...459, BF 415, BF 417
36606	BFT73	BFT 72, 250V	BF 458...459, BF 415, BF 417
36607	BFT74	BFT 72, 300V	BF 459, BF 417, 2SC3417
36608	BFT75	20V, 50mA, 4,6GHz	BFR 93, 2SC3161, 2SC3513
36609	BFT75R	BFT 75	BFR 93R
36610	BFT79	90V, 1A, 0,8W, >100MHz	BCX 60, BSW 40, 2N4036
36611	BFT80	BFT 79, 70V	BCX 60, BSW 40, 2N4031, 2N4033, 2N4036
36612	BFT81	BFT 79, 60V	BC 161, BSW 40, 2N4030...33, 2N4036...37
36613	BFT82	90V, 2A, 0,8W, >100MHz	MPS 651, 2SC3328
36614	BFT83	BFT 82, 70V	MPS 651, 2SC3328
36615	BFT84	BFT 82, 60V	MPS 650...651, 2SC3328, 2SD1207
36616	BFT85	90V, 2A, 0,8W, >100MHz	MPS 751, 2SA1315
36617	BFT86	BFT 85, 70V	MPS 751, 2SA1315
36618	BFT87	BFT 85, 60V	MPS 750...751, 2SA1315
36619	BFT91	PQ>1,5W(470MHz)	BLW 89, BLW 92, BLY 76
36620	BFT92	20V, 25mA, 5GHz	-
36621	BFT92R	BFT 92	-
36622	BFT92W	BFT 92	-
36623	BFT93	15V, 35mA, 5GHz	-
36624	BFT93R	BFT 93	-
36625	BFT93W	BFT 93	-
36626	BFT95(A,B,H)	15V, 25mA, 3,6..5GHz	BFQ 23, BFQ 51, BFQ 56, BFQ 75...76
36627	BFT96(A)	20V, 75mA, 3,6-4,5GHz	BFQ 32S
36628	BFT97	20V, 30mA, 0,2W, 5GHz	BFQ 59...60, BFQ 70...71, BFR 14, BFR 91
36629	BFT98	30V, 200mA, 3,3GHz	BFQ 68

36630	BFT98B	BFT 98	-
36631	BFT98T	BFT 98, 150mA, 3,2GHz	BFG 34
36632	BFT99	30V, 350mA, 3,3GHz	BFQ 68
36633	BFT99A	BFT 99	-
36634	BFU308	25V, Idss>12mA, Up<6,5V,	BF 256C, 2N5397, 2N5486
36635	BFU309	BFU 308, Idss>12mA, Up<4V	-
36636	BFU310	BFU 308, Idss>24mA, Up<6,5V	-
36637	BFV23	<60/-ns	BSV 21, BSW 25, BSW 37, BSX 29
36638	BFV24	<60/-ns	BSV 21, BSW 25, BSW 37, BSX 29
36639	BFV56	ns	BSS 26, BSS 40...41, 2N4014
36640	BFV56A	BFV 56, 75V, >175MHz	2N4014
36641	BFV57	>300MHz,<35/-ns	BSX 48...49, BSV 59, 2N4013...4014
36642	BFV57A	BFV 57, 80V	2N4013...4014
36643	BFV63	60V, 0,8A, 0,5W, 25/200ns	BSS 26, BSS 40...41, 2N2221...2222
36644	BFV63A	BFV 63, 75V	BSW 63...64, 2N2221A...2222A
36645	BFV63B	BFV 63, 25/175ns	BSS 26, BSS 40...41, 2N2221...2222
36646	BFV64(A,B)	60V, 0,6A, 0,4W, 26/70ns	BSW 24, 2N2906...2907, 2N4026...4029
36647	BFV65	40V, 0,3A, 0,36W, <40/40ns	BSS 10, BSX 26, BSX 39, 2N3261
36648	BFV65A,B	BFV 65, <12/15ns	BSS 10, BSX 26, BSX 39, 2N3261
36649	BFV66(A)	>250MHz,<40/-ns	BSS 26, BSS 40...41, 2N2221...2222
36650	BFV67	<15/-ns	BSV 89...92, BSX 27, BSX 44, 2N2475
36651	BFV68	45V, 0,05A, 0,36W, >30MHz	BC 382...384, BC 413...414, BC 550
36652	BFV68A	BFV 68, 60V	2N2483...2484, 2N3117, 2SC2390
36653	BFV69	30V, 50mA, 0,2W, >600MHz	BF 180...183, BF 689, BF 763, 2N2857
36654	BFV69A	BFV 69, 25V	BF 180...183, BF 689, BF 763, 2N2857
36655	BFV81	>400MHz,<60/-ns	BSV 21, BSW 25, BSW 37, BSX 29
36656	BFV81A,B	BFV 81, 20V	2N3209, 2N3905...3906, 2N4125...4126
36657	BFV82(A...C)	>140MHz	2N3905...3906, 2N4125...4126
36658	BFV83(A...C)	<40/-ns	BSW 41, BSY 63, 2N708, 2N4123
36659	BFV84(A,B)	25..30V, 50mA, >600MHz	BF 362...363, BF 377...378, BF 763
36660	BFV85(B)	60V, 0,8A, 0,36W, >250MHz	BSS 26, BSS 40...41, 2N2221...2222
36661	BFV85A,C	BFV 85(B), 75V	BSW 63...64, 2N2221A...2222A
36662	BFV85D,E	45V, 0,03A, 0,3W, >30MHz	BC 382...384, BC 413...414, BC 550
36663	BFV85F,G	60V, 0,05A, 0,3W, >30MHz	2N2483...2484, 2N3117, 2SC2390
36664	BFV86(A...C)	60V, 0,6A, 0,36W, <45/-ns	BSW 24, 2N2906...2907, 2N4026...4029
36665	BFV87(A,B)	40V, 0,2A, 0,3W, <12/-ns	BSS 11, BSX 19...20, 2N2369
36666	BFV88(A...D)	60V, 0,8A, 0,36W, >250MHz	BSS 26, BSS 40...41, 2N2221...2222
36667	BFV89	30V, 0,1A, 0,3W, >20MHz	-
36668	BFV89A	BFV 89, 45V	-
36669	BFV90(A,B)	70V, 0,8A, 0,8W, >300MHz	BFX 17, BFX 96...97
36670	BFV99	75V, 1A, 0,5W	BC 639, BSW 63...64, 2N2221A...2222A
36671	BFW	SM 15T 100C	SM 15T...
36672	BFW10	30V, Idss>8mA, Up<8V	BFS 72, 2N3823
36673	BFW11	30V, Idss>4mA, Up<6V	BFS 71, 2N3822
36674	BFW12	30V, Idss>1mA, Up<2,5V	2N4340

36675	BFW13	30V, Idss>0,2mA, U<1,2V	2N4338
36676	BFW16(A)	40V, 150mA, 1200MHz	BFR 36, BLW 11
36677	BFW17(A)	40V, 150mA, 1100MHz	BFR 36, BLW 11
36678	BFW19	40V, 0,3A, >500MHz	BFS 50, BFX 33, BFX 55, 2N3137T
36679	BFW20	60V, 0,2A, 0,36W, B>100	2N3962, 2SA1137
36680	BFW21	BFW 20, 80V	2N3963, 2SA970, 2SA1049, 2SA1136
36681	BFW22	BFW 20, 45V, B>250	BC 214, BC 415...416, BC 560, 2N3964
36682	BFW23	BFW 20, B>250	2N3965, 2SA1137
36683	BFW24	100V, 1A, 0,8W, >60MHz	BC 141, BSX 46...47, 2N3107...3108
36684	BFW25	BFW 24, 80V, >70MHz	BC 140...141, BSX 45...47, 2N3107...3110
36685	BFW26	BFW 24, 80V	BC 140...141, BSX 45...47, 2N3107...3110
36686	BFW27	30V, Up<6V	-
36687	BFW29	50V, 0,4A, 0,6W, >40MHz	BC 140...141, BC 302, 2N1613, 2N1711
36688	BFW30	20V, 50mA, 1,6GHz	BFR 37, BFX 59, BFX 73
36689	BFW31	50V, 0,7A, 0,5W, 200MHz	BC 327, BC 638, 2N2906...2907
36690	BFW32	50V, 0,7A, 0,5W, 200MHz	BC 337, BC 637, 2N2221...2222
36691	BFW33	120V, 1A, 0,8W, >50MHz	BSS 42...43, BSV 84, BSX 47, 2N1893
36692	BFW34	B>40	BC 140...141, BSX 45...47, 2N4432
36693	BFW35	BFW 34, B>80	BC 140...141, BSX 45...47, 2N5203
36694	BFW36	180V, 0,4A, 0,6W, 120MHz	2SD413, 2SD624, 2SD576, 2N5073
36695	BFW37	130V, 0,2A, 0,6W, 100MHz	BFR 57...59, 2N5058...5059, BFS 89
36696	BFW38	180V, 0,4A, 0,6W, >40MHz	2SD413, 2SD624, 2SD576
36697	BFW41	30V, 30mA, 0,2W, >600MHz	BFS 62, BFW 97, BFX 60, BFX 73, BFX 89
36698	BFW42	40V, 100mA, 0,6W, >600MHz	BFR 36, BFW 16...17, BLW 11
36699	BFW43	150V, 0,1A, 0,4W, 50MHz	BF 398, BF 435...437, 2SA1370...1372
36700	BFW44	BFW 43, 0,7W	BFQ 35...37, BFT 44...45, 2SB606
36701	BFW45	165V, 0,05A, 0,8W, 120MHz	BF 257...259, BF 657...659, 2N5058...5059
36702	BFW46	36V, 500mA, PQ>4W(175MHz)	BFS 22, MRF 237, 2N3924
36703	BFW47	PQ>2,5W(175MHz)	BFS 23, BLY 34, 2N3553
36704	BFW54	50V, Idss>2mA, Up<6V	-
36705	BFW55	50V, Idss>2mA, Up<6V	-
36706	BFW56	50V, Idss>2mA, Up<6V	-
36707	BFW57	B>80	BC 639, BSX 33, 2N2221A...2222A
36708	BFW58	BSW 57, B>50	BC 939, BSX 33, 2N2221A...2222A
36709	BFW59	BFW 57, 40V	BC 635, BSV 59, BSX 48...49, 2N2221...22
36710	BFW60	BFW 57, 40V, B>50	BC 635, BSV 59, BSX 48...49, 2N2221...22
36711	BFW61	25V, Idss>2mA, Up<8V	BF 244...245, BFS 72, 2N3819, 2N3823
36712	BFW63	600MHz	BF 225, BF 314, BF 496, BF 502...503
36713	BFW64	BFW 63, 650MHz	BF 225, BF 314, BF 496, BF 502...503
36714	BFW66	60V, 1A, 0,8W, 400MHz	BC 140...141, BSW 27...29, BSX 59...61
36715	BFW67	300V, 0,4A, 0,8W, 60MHz	BFQ 38...40, BF 259, BFR 59, BFS 89
36716	BFW68	50V, 0,1A 0,36W, 30/240ns	BC 547, BSV 59, BSX 48...49, 2N3903...04
36717	BFW69	65V, 1A, >400MHz	BFS 23, BLY 34
36718	BFW70	900MHz	BF 180...183, BF 689, BF 763, 2N2857
36719	BFW71	60V, 1A, 0,5W, 400MHz	BSS 26, BSS 40...41, 2N4013...4014

36720	BFW73(A)	30V, 250mA, >950MHz, B>20	BFR 36, BFW 16...17, BLW 11
36721	BFW74	BFW 73, B>40	BFR 36, BFW 16...17, BLW 11
36722	BFW76(A)	30V, 80mA, 1,3..1,5GHz	BFR 37, BFW 30, BFX 59, BFX 73
36723	BFW77(A)	BFW 76	BFR 37, BFW 30, BFX 59, BFX 73
36724	BFW80	50V, 0,2A, 0,6W, >70MHz	BC 140...141, BC 301...302, 2N1613
36725	BFW87	B>80	BC 327, BC 638, BSW 24, 2N2906...2907
36726	BFW88	BFW 87, B>40	BC 327, BC 638, BSW 24, 2N2906...2907
36727	BFW89	BFW 87, 40V	BC 328, BC 636, BSW 24, 2N2906...2907
36728	BFW90	BFW 87, 40V, B>40	BC 328, BC 636, BSW 24, 2N2906...2907
36729	BFW91	BFW 87, 20V, B>40	BC 328, BC 636, BSW 24, 2N2906...2907
36730	BFW92	25V, 25mA, 0,13W, 1,6GHz	BFR 34, BFT 24, BFW 93
36731	BFW93	18V, 50mA, 0,19W, 1,8GHz	BFQ 59...60, BFQ 70, BFR 34, BFT 97
36732	BFW94	25V, 200mA, 3GHz	BFG 34
36733	BFW96	30V, Idss1mA, Up<6,5V	BFX 63, BSV 22, BSV 81, BSX 83
36734	BFW97(K,L,M)	30V, 50mA, 0,25W, >600MHz	BF 357, BFR 37, BFW 30, BFX 73
36735	BFW98	36V, 400mA, 1GHz	BLW 42, BLW 79, BLX 67, 2N5944...5945
36736	BFW98G	BFW 98	BLW 12, BLX 36
36737	BFW99(S)	12V, 20mA, 0,2W, 3GHz	BFR 15, BFS 55, BFT 66...67
36738	BFWP21	30V, 15mA, Up5V	-
36739	BFX	SM 15T100CA	SM 15T...
36740	BFX12	B>20	BC 213, BC 258, BC 308, BC 558
36741	BFX13	BFX 12, B>50	BC 213, BC 258, BC 308, BC 558
36742	BFX14	25V, 300mA, 0,8W, 530MHz	BFS 22...23, BFS 50, BFX 55
36743	BFX152	100V, 0,3A, 0,83W, >500MHz	-
36744	BFX154	100V,0,3A,2W(Tc110°),>500M	2SC3599
36745	BFX155	100V,0,3A,2W(Tc110°),>500M	2SA1405
36746	BFX156	BFX 154, 5W(Tc25°)	2SC3599
36747	BFX157	BFX 155, 5W(Tc25°)	2SA1405
36748	BFX17	60V, 1A, PQ1,8W(150MHz)	BFS 23, BFW 47, BLY 34, 2N3553
36749	BFX18	30V, 550MHz	BF 167, BF 198, BFX 31, BFX 60, BFX 73
36750	BFX19	30V, 550MHz	BF 167, BF 198, BFX 31, BFX 60, BFX 73
36751	BFX20	30V, 550MHz	BF 167, BF 198, BFX 31, BFX 60, BFX 73
36752	BFX21	30V, 550MHz	BF 167, BF 198, BFX 31, BFX 60, BFX 73
36753	BFX29	60V, 0,6A, 0,6W, <60/150ns	BC 161, BC 303, 2N2904...2905
36754	BFX30	65V, 0,6A, 0,6W, <50/290ns	BC 161, BC 303, 2N2904...2905
36755	BFX31	500MHz	BF 225, BF 314, BFX 60, BFX 73
36756	BFX33	55V, 400mA, 600MHz	BFS 23, BFW 47, BFX 55, 2N3866
36757	BFX34	120V, 2A,5A,0,87W, 100MHz	BFT 34, 2N4895...4896
36758	BFX35	40V, 0,6A, 0,4W, >200MHz	BC 327, BC 636, BSW 24, 2N2906...07
36759	BFX37	90V, 0,1A, 0,36W, 70MHz	2N3963, 2SA970, 2SA1049, 2SA1136
36760	BFX38	55V, 1A, 0,8W, 33/160ns, B>85	BC 161, BSV 82, BSW 40, 2N4030...4033
36761	BFX39	BFX 38, B>40	BC 161, BSV 82, BSW 40, 2N4030...4033
36762	BFX40	BFX 38, 75V	BC 461, BSV 82, BSW 40, 2N4031, 2N4033
36763	BFX41	BFX 38, 75V, B>40	BC 461, BSV 82, BSW 40, 2N4031, 2N4033
36764	BFX42	1400MHz	-

36765	BFX43	30V, 0,2A, >500MHz	BSS 10...12, BSX 19...20, 2N2368
36766	BFX44	BFX 43, 40V	BSS 10...11, BSX 19...20, 2N2369
36767	BFX45	30V, 0,1A, 0,125W, <200/400ns	BC 548, BSW 41, BSX 87...88, BSY 63
36768	BFX47	30V, 20mA, >1GHz	BFR 37, BFW 30, BFX 73
36769	BFX48	30V, 0,1A, 0,36W, 20/95ns	BSW 24, 2N3905...3906, 2N4034...4035
36770	BFX49	65V, 250mA, 1,3GHz	BFR 64...65, BFT 91, BLX 91
36771	BFX49G	BFX 49	-
36772	BFX50	80V, 1A, 0,6W, >60MHz	BC 639, BSS 59, BSX 23, 2N4014
36773	BFX51	60V, 1A, 0,6W, >50MHz	BC 637, BSS 26, BSS 40...41, 2N4014
36774	BFX52	40V, 1A, 0,6W, >60MHz	BC 635, BSS 23, BSX 23, 2N4013...14
36775	BFX53	20V, 25mA, >1,3GHz	BF 362...363, BFR 34, BFT 24
36776	BFX55	60V, 400mA, 700MHz	BFS 23, BFW 47, BFX 33, 2N3553, 2N3866
36777	BFX56(I...III)	60V, 300mA, >350MHz	BFS 23, BFW 47, BFX 55, 2N3553, 2N3866
36778	BFX57(I...III)	30V, 100mA, >600MHz	BFR 36, BFW 16...17
36779	BFX58(I...III)	60V, 400mA, >600MHz	BFS 23, BFW 47, BFX 55, 2N3553, 2N3866
36780	BFX58D	BFX 58	BFS 23, BFW 47, BFX 55, 2N3553, 2N3866
36781	BFX59(F,R)	30V, 100mA, 1GHz	BFR 37, BFW 30, BFX 73
36782	BFX60	40V, 25mA, 550MHz	BF 225, BF 314, BF 496, BF 502...503
36783	BFX61	80V, 1A, 180MHz	BC 141, BSS 42, BSX 46...47, 2N3107...08
36784	BFX62	675MHz	BF 180...183, BF 689, BF 763, 2N2857
36785	BFX63	BFW 96	BFW 96
36786	BFX65	45V, 0,05A, 0,36W, >40MHz	BC 214, BC 415...416, BC 560
36787	BFX66	100V, 0,2A, 0,5W, B>1600	2N998
36788	BFX67	60V, 0,5A, 0,5W, B>7000	2N999
36789	BFX68	75V, 1A, 0,7W, >70MHz	BC 141, BSX 45...47, BSY 53...54, 2N1711
36790	BFX68A	BFX 68, 80V, 0,8W	BC 141, BSX 45...47, 2N3109...3110
36791	BFX69	75V, 1A, 0,8W, >60MHz	BC 141, BSX 45...47, BSY 53...54, 2N1613
36792	BFX69A	BFX 69, 80V	BC 141, BSX 45...47, 2N3109...3110
36793	BFX73	30V, 50mA, 900MHz	BF 357, BFR 37, BFW 30, BFX 59
36794	BFX74	50V, 0,5A, 0,6W, 90MHz	BC 161, BC 303...304, 2N2904...2905
36795	BFX74A	BFX 74, 60V, 0,8W, 150MHz	BC 161, BC 303...304, 2N2904...2905
36796	BFX77	50V, 300MHz	BF 167, BF 198, BF 225, BF 310
36797	BFX78	15V, Idss16mA	-
36798	BFX82	25V, Idss17mA, Up5V	-
36799	BFX83	25V, Idss6,8mA, Up9V	-
36800	BFX84	B>30	BC 141, BSX 46...47, 2N3107...3108
36801	BFX85	BFX 84, B>70	BC 141, BSX 46...47, 2N3107...3108
36802	BFX86	BFX 84, 40V, B>70	BC 140...141, BSX 45...47, 2N3107...3110
36803	BFX87	50V, 0,6A, 0,53W, <60/150ns	BSW 40, 2N2904...2905, 2N3468
36804	BFX88	BFX 87, 40V	BSW 40, 2N2904...2905, 2N3468
36805	BFX89	30V, 25mA, 1,3GHz	BFR 37, BFW 30, BFW 92...93, BFX 73
36806	BFX90	180V, 0,05A, 0,4W, 60MHz	2N3930, BF 421, BF 423, BF 436...437
36807	BFX91	BFX 90, 0,7W	2N3931, BFQ 36
36808	BFX92	B>40	BC 382, BC 414, BC 550, 2N929, 2N3117
36809	BFX92A	60V, 0,05A, 0,36W, >60MHz	2N2483, 2N3117, 2SC2390



36810	BFX93	BFX 92, B>100	BC 382, BC 414, BC 550, 2N930, 2N3117
36811	BFX93A	BFX 92A, B>100	2N2484, 2N3117, 2SC2390
36812	BFX94(A)	2N2221(A)	2N2221(A)
36813	BFX95(A)	2N2222(A)	2N2222(A)
36814	BFX96(A)	2N2218(A)	2N2218(A)
36815	BFX97(A)	2N2219(A)	2N2219(A)
36816	BFX98	150V, 0,1A, 0,8W, 90MHz	BF 257...259, BF 657...659, 2N5058...5059
36817	BFY10	B>25	BC 107, BC 167, BC 182, BC 237, BC 546
36818	BFY11	BFY 10, B>40	BC 107, BC 167, BC 182, BC 237, BC 546
36819	BFY12(B,C,D)	<40/720ns	BSW 39, BSW 51...52, 2N2218...2219
36820	BFY13(B,C,D)	BFY 12, 80V, 0,35A	BSW 39, BSW 53...54, 2N2218A...2219A
36821	BFY14(B,C,D)	BFY 12, 100V, 0,25A	BSW 39, 2N1893, 2N3723
36822	BFY15	40V, 0,5A, 0,6W, 100MHz	BC 140...141, BC 300...302, 2N2218...19
36823	BFY16	BFY 15, 150MHz	BC 140...141, BC 300...302, 2N2218...19
36824	BFY17	40V, 0,1A, 0,6W, 245MHz	BC 140...141, BC 300...302, 2N2218...19
36825	BFY18	BFY 17, 0,3W	BC 107, BSW 41, BSY 63, 2N2221...22
36826	BFY19	30V, 0,1A, 0,3W, 400MHz	BC 108, BSW 41, BSY 63, 2N2221...22
36827	BFY22	5V, 0,05A, 20MHz, $\beta$ >30	BC 121...123, BC 146
36828	BFY23(a)	BFY 22, $\beta$ >70	BC 121...123, BC 146
36829	BFY24	BFY 22, $\beta$ >45	BC 121...123, BC 146
36830	BFY25	ns	BSW 27...28, BSW 51...52, 2N2218...19
36831	BFY26	BFY 25, 0,36W	BSV 59, BSX 49, 2N2221...2222
36832	BFY27	2N915	2N915
36833	BFY28	60V, 0,1A, 0,3W, 400MHz	BC 182, BC 190, BC 546, 2N2221...22
36834	BFY29	45V, 0,05A, 20MHz, $\beta$ >30	BC 123
36835	BFY30	BFY 29, $\beta$ >70	BC 123
36836	BFY31	75V, 0,5A, >60MHz	BC 140...141, BC 300...301, 2N2218A...19A
36837	BFY33	50V, 0,5A, 0,75W, 80MHz	BC 140...141, BC 300...301, 2N2218...19
36838	BFY34	BFY 33, 75V	BC 140...141, BC 300...301, 2N2218A...19A
36839	BFY37(i)	25V, 0,1A, 0,3W, 270MHz	BC 108, BC 168, BC 183, BC 238, BC 548
36840	BFY39..(i)	45V, 0,1A, 0,3W, 150MHz	BC 107, BC 167, BC 183, BC 237, BC 547
36841	BFY40	60V, 0,8A, 0,8W, 60MHz	BC 140...141, BC 300...302, 2N2218...19
36842	BFY41	120V, 0,6A, 0,8W, 60MHz	BC 300, BSX 47, BSY 55...56, 2N1893
36843	BFY43	140V, 0,1A, 0,8W, 60MHz	BF 257...259, BF 657...659, 2N5058...5059
36844	BFY44	80V, 1A, PQ2,1W(180MHz)	BFS 23, BFW 47, BLY 34, 2N3553
36845	BFY45	140V, 0,03A, 0,7W, 130MHz	BF 257...259, BF 657...659, 2N5058...5059
36846	BFY46	2N1711	2N1711
36847	BFY47	5V, 0,05A, 0,075W, 50MHz	BC 121...123, BC 146
36848	BFY48	BFY 47, 30V	BC 122...123
36849	BFY49	BFY 47, 45V	BC 123
36850	BFY50(E)	80V, 1A, 0,8W, 100MHz	BC 140...141, BSW 39, 2N3444
36851	BFY51	BFY 50, 60V	BC 140...141, BSW 27...28, 2N3252...53
36852	BFY52	BFY 50, 40V	BC 140...141, BSW 27...29, 2N3252...53
36853	BFY53	BFY 50, 40V	BC 140...141, BSW 27...29, 2N3252...53
36854	BFY55	80V, 1A, 0,7W, >60MHz	BC 140...141, BSX 45...47, 2N3707...10



36855	BFY56(A,B)	60..80V, 1A, 0,8W, 150/350ns	BC 140...141, BSW 39, 2N3444
36856	BFY57	125V, 0,1A, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...5059
36857	BFY63	30V, 100mA, 750MHz	BFR 36, BFW 16...17
36858	BFY64	40V, 0,6A, 0,7W, 35/70ns	BSV 82, BSW 23, BSW 40, 2N3467...68
36859	BFY65	100V, 0,1A, 0,6W, >50MHz	BF 257...259, BF 657...659, 2N5058...5059
36860	BFY66	2N918	2N918
36861	BFY67(A,C)	2N1613	2N1613
36862	BFY68(A)	2N1711	2N1711
36863	BFY69(A,B)	25V, 0,1A, 0,1W, >50MHz	BC 122...123
36864	BFY70	60V, 1A, PQ1,5W(180MHz)	BFS 23, BFW 47, BLY 34, 2N3553
36865	BFY72	50V, 0,5A, 0,8W, 14/80ns	BSS 13, BSS 27...29, 2N3722...3725
36866	BFY73	60V, 0,8A, 0,8W, <60/-ns	BSS 13, BSS 27...29, 2N3722...3725
36867	BFY74	B>40	BC 190, BC 546, 2N2221...2222
36868	BFY75	BFY 74, B>65	BC 190, BC 546, 2N2221...2222
36869	BFY76	B>30	BC 184, BC 413...414, BC 550
36870	BFY77	BFY 76, B>80	BC 184, BC 413...414, BC 550
36871	BFY78	25V, 50mA, 0,3W, 900MHz	BFR 37, BFW 30, BFX 59, BFX 73
36872	BFY79	30V, >400MHz	BF 167, BF 198, BF 225, BF 310
36873	BFY80	100V, 0,1A, 0,26W, >50MHz	BF 297...299, BFR 86...89, BSS 38, BSX 21
36874	BFY87(A)	25V, 0,1A, 0,05W, >50MHz	BC 122...123
36875	BFY88	850MHz	BF 180...183, BF 689, BF 763, 2N2857
36876	BFY90(B)	30V, 25mA, 1,1GHz	BFR 37, BFW 30, BFX 59, BFX 73
36877	BFY94	50V, 0,6A, 0,8W, >100MHz	BC 161, BC 303...304, 2N2904...2905
36878	BFY95	30V, 0,6A, 0,36W, >100MHz	BC 327...328, BC 636, 2N2906...2907
36879	BFY99	65V, 1A, PQ>2,5W(260MHz)	BFS 23, BFW 47, BLY 34, 2N3553
36880	BFZ10	15V, 10mA, 0,05W, 3,5MHz	BC 213, BC 258, BC 308, BC 558
36881	BG	BCP 55-10	BCP 55-10
36882	BG	P4 SMA-20A	P4 SMA-20A
36883	BG	1SS269	1SS269
36884	BG	2SC3440-G	2SC3440
36885	BG	1SS313	1SS313
36886	BG	BCX 55-10	BCX 55-10
36887	BG	2SB1124	2SB1124
36888	BG	2SC3443-G	2SC3443
36889	BG(p,s)	BCX 71G	BCX 71G
36890	BGH	SM 15T 150C	SM 15T...
36891	BGK	SM 15T150CA	SM 15T...
36892	BGU	SM 15T 200C	SM 15T...
36893	BGV	SM 15T200CA	SM 15T...
36894	BGX50(A)	50V, 0,1A, ..50MHz	-
36895	BH	P4 SMA-22	P4 SMA-22
36896	BH	1SS350	1SS350
36897	BH	1SS295	1SS295
36898	BH	BCX 56	BCX 56
36899	BH	2SB1125	2SB1125

36900	BH	2SB1001-BH	2SB1001
36901	BH(p,s)	BCX 71H	BCX 71H
36902	BHM	2SC4699K-M	2SC4699K
36903	BHM	2SC4700-M	2SC4700
36904	BHN	2SC4699K-N	2SC4699K
36905	BHN	2SC4700-N	2SC4700
36906	BHP	2SC4699K-P	2SC4699K
36907	BHP	2SC4700-P	2SC4700
36908	BHP	2SB1386-P	2SB1386
36909	BHQ	2SB1386-Q	2SB1386
36910	BHR	2SB1386-R	2SB1386
36911	BI	2SB1126	2SB1126
36912	BIQ	2SK541-BIQ	2SK541
36913	BIR	2SK541-BIR	2SK541
36914	BIS	2SK541-BIS	2SK541
36915	BJ	BCP 56	BCP 56
36916	BJ	BCX 56-6	BCX 56
36917	BJ	2SB1001-BJ	2SB1001
36918	BJ	2SB1302	2SB1302
36919	BJ(p,s)	BCX 71J	BCX 71J
36920	BJE	2SB1427-E	2SB1427
36921	BJS	2SB1427-S	2SB1427
36922	BJU	2SD2226K-U	2SD2226K
36923	BJU	2SD2351-U	2SD2351
36924	BJU	2SB1427-U	2SB1427
36925	BJV	2SD2226K-V	2SD2226K
36926	BJV	2SD2351-V	2SD2351
36927	BJW	2SD2351-W	2SD2351
36928	BJW	2SD2226K-W	2SD2226K
36929	BK	BCP 56-10	BCP 56
36930	BK	XN 4114	XN 4114
36931	BK	XP 4114	XP 4114
36932	BK	P4 SMA-22A	P4 SMA-22A
36933	BK	BCX 56-10	BCX 56
36934	BK	2SB1323	2SB1323
36935	BK(p,s)	BCX 71K	BCX 71K
36936	BL	BCP 56-16	BCP 56
36937	BL	P4 SMA-24	P4 SMA-24
36938	BL	BCX 71L	BCX 71L
36939	BL	2SA1676	2SA1676
36940	BL	2SA1341	2SA1341
36941	BL	2SB1324	2SB1324
36942	BL	BCX 56-16	BCX 56
36943	BLF145	65V, 3A, PEP30W(28MHz)	-
36944	BLF146	65V, 7A, Vp>18dB(28MHz)	-

36945	BLF147	65V, 13A,PEP150W(28MHz)	-
36946	BLF175	110V, 1,5A,PEP8W(28MHz)	-
36947	BLF177	110V, 7A,PEP150W(28MHz)	-
36948	BLF241	65V, 0,5A, PQ3W(175MHz)	-
36949	BLF242	65V, 0,5A,Vp16dB(175MHz)	-
36950	BLF244	65V, 1,5A,Vp17dB(175MHz)	-
36951	BLF245	65V, 3A, Vp16dB(175MHz)	-
36952	BLF246	65V, 7A, PQ80W(108MHz)	-
36953	BLL	2SC4771K-L	2SC4771K
36954	BLL	2SC4772-L	2SC4772
36955	BLM	2SC4772-M	2SC4772
36956	BLM	2SC4771K-M	2SC4771K
36957	BLN	2SC4772-N	2SC4772
36958	BLN	2SC4771K-N	2SC4771K
36959	BLP	2SC4771K-P	2SC4771K
36960	BLP	2SC4772-P	2SC4772
36961	BLP	2SB1561-P	2SB1561
36962	BLQ	2SB1561-Q	2SB1561
36963	BLT50	PQ1,2W(470MHz)	-
36964	BLT80	PQ0,8W(900MHz)	-
36965	BLT81	PQ1,2W(900MHz)	-
36966	BLT90/SL	20V, 0,25A, PQ0,75W(900MHz)	-
36967	BLT91/SL	20V, 0,5A, PQ1,5W(900MHz)	-
36968	BLT92/SL	20V, 1,2A, PQ3W(900MHz)	-
36969	BLT93/SL	20V, 1,2A, PQ6W(900MHz)	-
36970	BLU10/12	36V, 2A, PQ10W(470MHz)	MRF 641
36971	BLU20/12	36V, 4A, PQ20W(470MHz)	MRF 641
36972	BLU30/12	36V, 6A, PQ30W(470MHz)	MRF 644
36973	BLU45/12	36V, 9A, PQ45W(470MHz)	MRF 648
36974	BLU56	PQ1W(470MHz)	-
36975	BLU60/12	36V, 12A, PQ60W(470MHz)	MRF 648
36976	BLU86	PQ1W(900MHz)	-
36977	BLU97	36V, 1,2A, PQ7W(470MHz)	BLX 68, BLY 53
36978	BLU98	36V, 0,15A, PQ0,5W(900MHz)	-
36979	BLU99	36V, 0,8A, PQ4W(900MHz)	-
36980	BLV10	36V, 1,5A, PQ8W(175MHz)	MRF 221
36981	BLV11	36V, 3A, PQ15W(175MHz)	MRF 221...223
36982	BLV15/12	36V, 3A, PQ15W(175MHz)	MRF 215
36983	BLV20	65V, 0,9A, PQ8W(175MHz)	-
36984	BLV21	65V, 1,75A, PQ15W(175MHz)	-
36985	BLV25	65V, 17,5A, PQ175W(108MHz)	-
36986	BLV30	60V, 1,5A, PQ>1,5W(224MHz)	-
36987	BLV30/12	36V, 6A, PQ30W(175MHz)	MRF 216
36988	BLV31	60V, 3A, PQ>5W(224MHz)	BLW 75
36989	BLV32F	60V, 4A, PQ>10W(224MHz)	-

36990	BLV33	65V, 12,5A, PQ>19W(224MHz)	-
36991	BLV33F	65V, 12,5A, PQ>16W(224MHz)	-
36992	BLV34F	75V, 15A, PQ130W(225MHz)	-
36993	BLV45/12	36V, 9A, PQ45W(175MHz)	MRF 243
36994	BLV59	50V, 3A, PQ30W(860MHz)	-
36995	BLV75/12	36V, 15A, PQ75W(175MHz)	MRF 243, MRF 245
36996	BLV80/28	65V, 8,5A, PQ80W(175MHz)	BLW 78
36997	BLV90	36V, 0,2A, PQ1W(900MHz)	MRF 838A
36998	BLV90/SL	BLV 90	MRF 838
36999	BLV91	36V, 0,4A, PQ2W(900MHz)	MRF 817
37000	BLV91/SL	BLV 91	-
37001	BLV92	36V, 0,8A, PQ4W(900MHz)	MRF 840
37002	BLV93	36V, 1,6A, PQ8W(900MHz)	MRF 840
37003	BLV94	36V, 3A, PQ12,5W(900MHz)	MRF 842
37004	BLV95	36V, 5A, PQ25W(900MHz)	MRF 844
37005	BLV97	50V, 3A, PQ30W(900MHz)	-
37006	BLV98	50V, 1,5A, PQ14W(900MHz)	-
37007	BLV99	50V, 0,2A, PQ2W(900MHz)	BLX 91
37008	BLW10	55V, 0,4A, >500MHz	BFS 23, 2N3866
37009	BLW11	40V, 0,4A, >1,2GHz	BFR 36, BFW 16
37010	BLW12	36V, 0,4A, PQ>0,75W(470MHz)	BLW 39, BLX 66
37011	BLW13	36V, 2A, PQ>3,75W(470MHz)	BLW 43, BLX 68, BLY 53
37012	BLW14	36V, 2A, PQ>7W(470MHz)	BLW 44, BLX 68, BLY 53B
37013	BLW15	36V, 3A, PQ>12W(470MHz)	BLX 69
37014	BLW16	36V, 0,5A, PQ>1,4W(175MHz)	BFS 22, BFS 50...51, BLY 61, 2N4427
37015	BLW17	36V, 0,5A, PQ>2W(175MHz)	BLW 39, BLX 66
37016	BLW18	36V, 2A, PQ>5W(175MHz)	BLW 37, BLY 62, BLY 83, 2N5590
37017	BLW19	36V, 2A, PQ>8W(175MHz)	BLW 37, BLY 83, MRF 212, 2N5590
37018	BLW20	36V, 5A, PQ>25W(175MHz)	BLW 31, 2N6084
37019	BLW21	36V, 7A, 35MHz	2N5708
37020	BLW22	40V, 0,4A, 1000MHz	BFR 65, BFT 91, BLW 42, BLX 96
37021	BLW23	55V, 2A, PQ>5W(175MHz)	BLV 31, BLW 19, BLY 83
37022	BLW24	60V, 2A, PQ>17W(175MHz)	BLY 93, 2N5642
37023	BLW25	65V, 5A, PQ>40W(175MHz)	BLY 94, 2N5643
37024	BLW26	36V, 8A, >50MHz	MRF 460, 2N5706, 2N5709, 2N5941
37025	BLW27	36V, 10A, >50MHz	MRF 460, 2N5709, 2N5942
37026	BLW29	36V, 2,75A, PQ15W(175MHz)	BLY 84, BLY 88, MRF 226, 2N6081
37027	BLW31	36V, 6A, PQ28W(175MHz)	BLW 20, 2N6084
37028	BLW32	50V, 0,65A, PQ0,58W(860MHz)	BLX 97
37029	BLW33	50V, 1,25A, PQ1,07W(860MHz)	BLW 98, BLX 98
37030	BLW34	50V, 2,25A, PQ1,9W(860MHz)	BLW 98, BLX 98
37031	BLW35	39V, 1,7A, PQ>7,5W(175MHz)	BLY 36, BLY 58, BLY 79, 2N3927
37032	BLW36	39V, 3,5A, PQ>15,5W(175MHz)	BLY 36
37033	BLW37	BLW 35	BLW 19, BLY 62, BLY 83, MRF 212, 2N5590
37034	BLW38	BLW 36	BLW 20, BLY 63, BLY 84, MRF 238, 2N6083

37035	BLW39	50V, 0,5A, PQ>2W(175MHz)	BLW 17, BLX 66
37036	BLW42	50V, 0,7A, PQ>1,1W(470MHz)	BLX 92, 2N5944
37037	BLW43	50V, 1A, PQ>3,5W(470MHz)	BLU 97, BLW 80, BLX 68, BLX 93, BLY 53
37038	BLW44	50V, 2A, PQ>8W(470MHz)	BLW 14, BLW 81, BLX 94, 2N5946
37039	BLW45	25V, 0,15A, PQ0,2W(1GHz)	BLV 90, MRF 838A
37040	BLW46	BLW 45	MRF 816, MRF 838
37041	BLW47	25V, 0,2A, PQ0,5W(1GHz)	BLV 90, MRF 838A
37042	BLW48	BLW 47	MRF 816, MRF 838
37043	BLW50F	110V, 2,5A, PEP17W(28MHz)	-
37044	BLW60	36V, 8A, PQ45W(175MHz)	BLY 90
37045	BLW60C	BLY 60, 9/22A	-
37046	BLW64	60V, 4A, PQ>15W(224MHz)	BLW 75
37047	BLW65	40V, 5A, 80MHz	BUX 34, BUX 49, BUY 41, BUY 80
37048	BLW66	BLW 65, 60V	BUX 34, BUX 49, BUY 41, BUY 80
37049	BLW67	BLW 65, 80V	BUX 34, BUX 49, BUY 41, BUY 80
37050	BLW68	BLW 65, 100V	BUX 34, BUX 49, BUY 41, BUY 80
37051	BLW69	BLW 65, 120V	BUX 34, BUX 49, BUY 41, BUY 80
37052	BLW70	BLW 65, 140V	BU 125S, BUX 50, BUY 49, BUY 80
37053	BLW71	BLW 65, 160V	BU 125S, BUX 50, BUY 49
37054	BLW72	BLW 65, 180V	BU 125S, BUX 50, BUY 49
37055	BLW73	BLW 65, 200V	BU 125S, BUX 50, BUY 49
37056	BLW75	60V, 4A, PQ>14W(225MHz)	BLW 64
37057	BLW76	70V, 8A, PQ80W(108MHz)	-
37058	BLW77	70V, 12A, PQ130W(87,5MHz)	BLW 96
37059	BLW78	70V, 10A, PQ100W(170MHz)	-
37060	BLW79	36V, 0,5A, PQ2W(470MHz)	BLX 67, BLY 38, 2N5945
37061	BLW80	36V, 1A, PQ4W(470MHz)	BLU 97, BLW 43, BLX 68, BLY 53
37062	BLW81	36V, 2,5A, PQ10W(470MHz)	BLW 15, BLW 44, BLX 69, 2N5946
37063	BLW82	36V, 7A, PQ30W(470MHz)	BLU 30/12, MRF 646
37064	BLW83	65V, 3A, PEP30W(28MHz)	2N5941
37065	BLW84	65V, 3A, PQ25W(175MHz)	BLW 86, MRF 314
37066	BLW85	36V, 9A, PQ45W(175MHz)	-
37067	BLW86	65V, 4A, PQ45W(175MHz)	MRF 315
37068	BLW87	36V, 6A, PQ25W(175MHz)	MRF 224
37069	BLW89	60V, 0,32A, PQ2W(470MHz)	BFT 91, BLW 92, BLY 76, MRF 5174
37070	BLW90	60V, 0,62A, PQ4W(470MHz)	BLW 93, BLY 37
37071	BLW91	60V, 1,5A, PQ10W(470MHz)	BLW 94, BLX 94, MRF 323
37072	BLW92	60V, 0,7A, PQ>1,5W(470MHz)	BLW 90, BLX 92
37073	BLW93	60V, 1A, PQ>4,5W(470MHz)	BLW 91, BLX 93, MRF 321
37074	BLW94	60V, 2A, PQ>15W(470MHz)	BLX 94, MRF 323
37075	BLW95	110V, 8A, PEP160W(28MHz)	BLW 96
37076	BLW96	110V, 12A, PEP200W(108MHz)	-
37077	BLW97	65V, 15A, PQ175W(28MHz)	-
37078	BLW98	50V, 2A, PQ4,4W(860MHz)	BLX 98, 2N4431
37079	BLW99	36V, 18A, PEP80W(28MHz)	MRF 421, MRF 454

37080	BLX10	>10MHz	BU 125S, BUX 49...50, BUY 41
37081	BLX11	BLX 10, 145V	BU 125S, BUX 49...50, BUY 49
37082	BLX12	BLX 10, 170V	BU 125S, BUX 50...51, BUY 49
37083	BLX13(C)	65V, 3A, PQ25W(70MHz)	-
37084	BLX14	85V, 4A, PQ50W(70MHz)	-
37085	BLX15	110V, 6,5A, PQ150W(108MHz)	-
37086	BLX16	>10MHz	BU 125, BUX 34, BUY 47...48, BUY 80...81
37087	BLX17	BLX 16, 145V	BUY 47...48, BUY 68, BUY 80...81
37088	BLX18	BLX 16, 170V	BUY 48
37089	BLX19	>10MHz	2N1724, 2N5387...5389
37090	BLX20	BLX 19, 145V	2N1724, 2N5387...5389
37091	BLX21	BLX 19, 170V	2N1724A, 2N5387
37092	BLX22	>10MHz	2N5542
37093	BLX23	BLX 22, 145V	2N5542
37094	BLX24	BLX 22, 170V	2N5542
37095	BLX25	>10MHz	2N2825, 2N6324...6325
37096	BLX26	BLX 25, 145V	2N2825, 2N6324...6325
37097	BLX27	BLX 25, 170V	2N6324...6325
37098	BLX28	>10MHz	2N2825, 2N6324...6325
37099	BLX29	BLX 28, 145V	2N2825, 2N6324...6325
37100	BLX30	BLX 28, 170V	2N6324...6325
37101	BLX31	>10MHz	2N6278...6281
37102	BLX32	BLX 31, 145V	2N6278...6281
37103	BLX33	BLX 31, 170V	-
37104	BLX34	>10MHz	2N6309...6311
37105	BLX35	BLX 34, 145V	2N6310...6311
37106	BLX36	BLX 34, 170V	2N6311
37107	BLX39	65V, 3A, PQ45W(170MHz)	BLW 25, MRF 315A, 2N5643
37108	BLX40	80V, 2A, 11W(Tc50°), >20MHz	BUY 90, 2N6190...6193
37109	BLX41	BLX 40, 100V	BUY 90, 2N6192...6193
37110	BLX42	BLX 40, 120V	BUY 90
37111	BLX46	80V, 5A, 15W(Tc50°), >20MHz	BUY 90, 2N6190...6193
37112	BLX47	BLX 46, 100V	BUY 90, 2N6192...6193
37113	BLX48	BLX 46, 120V	BUY 90
37114	BLX49	80V, 5A, 45W(Tc50°), >20MHz	2N5003, 2N5005, 2N5286...87, 2N6182...85
37115	BLX50	BLX 49, 100V	2N5003, 2N5005, 2N5286...87, 2N6184...85
37116	BLX51	BLX 49, 120V	2N5286...5287
37117	BLX52	>20MHz	2N6182...6185, 2N6186...6189
37118	BLX53	BLX 52, 100V	2N6184...6185, 2N6188...6189
37119	BLX54	BLX 52, 120V	2N5290...5291
37120	BLX55	>20MHz	2N6380...6382
37121	BLX56	BLX 55, 100V	2N6380...6382
37122	BLX57	BLX 55, 120V	2N6381...6382
37123	BLX58	>20MHz	2N6380...6382
37124	BLX59	BLX 58, 100V	2N6380...6382



37125	BLX60	BLX 58, 120V	2N6381...6382
37126	BLX61	>20MHz	2N6061, 2N6063, 2N6380...6382
37127	BLX62	BLX 61, 100V	2N6061, 2N6063, 2N6380...6382
37128	BLX63	BLX 61, 120V	2N6381...6382
37129	BLX65	36V, 0,7A, PQ2W(470MHz)	2N5913
37130	BLX65E,ES	BLX 65	-
37131	BLX66	36V, 0,7A, PQ2,5W(470MHz)	-
37132	BLX67	36V, 0,7A, PQ3W(470MHz)	BLW 43, BLW 80, 2N5945
37133	BLX68	36V, 1A, PQ7,8W(470MHz)	BLU 97, BLY 53
37134	BLX69(A)	36V, 3,5A, PQ17W(470MHz)	BLW 15
37135	BLX70	-/225V, 20A, 100W(Tc45°)	2N6325
37136	BLX71	BLX 70, -/250V	2N6325
37137	BLX72	BLX 70, -/300V	2N6325
37138	BLX73	BLX 70, -/375V	-
37139	BLX74	-/225V, 10A, 50W(Tc45°)	2N5388...5389, 2N5540
37140	BLX75	BLX 74, -/250V	2N5388...5389, 2N5540
37141	BLX76	BLX 74, -/300V	2N5389, 2N5540
37142	BLX77	BLX 74, -/375V	-
37143	BLX78	-/225V, 5A, 30W(Tc45°)	-
37144	BLX79	BLX 79, -/250V	-
37145	BLX80	BLX 79, -/300V	-
37146	BLX81	BLX 79, -/375V	-
37147	BLX82	>20MHz	BD 250A, BD 367, BD 746A, 2N5883...5884
37148	BLX83	BLX 82, 80V	BD 250B, BD 369, BD 746B, 2N5884
37149	BLX84	BLX 82, 100V	BD 250C, BD 746C, MJ 4502
37150	BLX85	>10MHz	BD 249A, BD 366, BD 745A, 2N5885...5886
37151	BLX86	BLX 85, 80V	BD 249B, BD 368, BD 745B, 2N5886
37152	BLX87	BLX 85, 100V	BD 249C, BD 745C, MJ 802
37153	BLX88	50V, 0,1A, >600MHz	BFS 23, BFW 16...17, BFX 33, 2N3866
37154	BLX89	50V, 0,5A, 900MHz	BFS 23, BFX 33, BFX 55, 2N3866
37155	BLX91(A)	65V, 0,4A, PQ1W(470MHz)	BFT 91, BLW 89, BLY 76
37156	BLX91CB	BLX 91	-
37157	BLX92(A)	65V, 0,7A, PQ2,5W(470MHz)	BLW 90, BLW 92, BLY 37, MRF 5174
37158	BLX93(A)	65V, 1A, PQ7W(470MHz)	BLW 91, MRF 321
37159	BLX94(A,C)	65V, 2A, PQ20W(470MHz)	BLW 94, MRF 323
37160	BLX95(A)	65V, 3A, PQ40W(470MHz)	2N6104...6105
37161	BLX96	40V, 0,4A, PQ0,6W(860MHz)	BLW 32, BLX 91, 2N4429
37162	BLX97	40V, 0,8A, PQ1,1W(860MHz)	BLW 33, 2N4430
37163	BLX98	40V, 2A, PQ4W(860MHz)	BLW 98, 2N4431
37164	BLY10	40V, 2A, 10W(Tc45°), >50MHz	-
37165	BLY11	BLY 10, >100MHz	-
37166	BLY12	60V, 1,5A, 25W, >60MHz	-
37167	BLY14	80V, 1A, PQ3,6W(180MHz)	BLY 60
37168	BLY15	90V, 2A, 15W, 200MHz	-
37169	BLY15A	64V, 2A, 11,5W, 180MHz	-

37170	BLY16	64V, 1,5A, 11W, 250MHz	-
37171	BLY17(A,C)	100V, 10A, PQ40W(30MHz)	-
37172	BLY20	45V, 1A, PQ6W(180MHz)	BLY 57, BLY 60, 2N3632, 2N3926
37173	BLY21	70V, 1A, PQ12W(180MHz)	BLY 60, 2N3632
37174	BLY22	65V, 1,5A, PQ>7,5W(175MHz)	BLY 60, 2N3632
37175	BLY23	65V, 3A, PQ>13,5W(175MHz)	BLY 60, 2N3632
37176	BLY25	120V, 5A, 195MHz	2N4116, 2N5002, 2N5004
37177	BLY26	100V, 5A, 135MHz	2N4115, 2N5002, 2N5004
37178	BLY27	80V, 1A, PQ>4W(250MHz)	BLY 59...60, 2N3375, 2N3632
37179	BLY28	80V, 1A, PQ>4W(125MHz)	BLY 59...60, 2N3375, 2N3632
37180	BLY29	100V, 2A, 46MHz	2N2892...93, 2N4075...76, 2N4998, 2N5000
37181	BLY30	BLY 29, 50MHz	2N2892...93, 2N4075...76, 2N4998, 2N5000
37182	BLY34	40V, 0,5A, PQ3W(175MHz)	BFS 22, BFW 46, 2N3924
37183	BLY34	40V, 0,5A, PQ3W(175MHz)	BFS 22, BFW 46, 2N3924
37184	BLY35	66V, 2,5A, PQ13W(175MHz)	BLY 60, 2N3632
37185	BLY36	40V, 2,5A, PQ13W(175MHz)	BLY 58, 2N3927
37186	BLY37	65V, 0,75A, PQ6W(470MHz)	BLW 93, BLX 93, MRF 321
37187	BLY38	36V, 0,5A, PQ2W(470MHz)	BLW 43, BLW 79, BLX 67, 2N5945
37188	BLY39	60V, 2A, PQ>7W(470MHz)	BLW 91, BLX 93, MRF 321
37189	BLY47	B>30	BDY 24
37190	BLY47A	BLY 47	2N6077...6079, 2N6233...6235
37191	BLY48	BLY 47, B>60	BDY 24
37192	BLY48A	BLY 48	2N6077...6079, 2N6233...6235
37193	BLY49	BLY 47, 250V	BDY 26
37194	BLY49A	BLY 49	2N6077...6079, 2N6233...6235
37195	BLY50	BLY 47, 250V, B>60	BDY 26
37196	BLY50A	BLY 50	2N6077...6079, 2N6233...6235
37197	BLY53	36V, 1,3A, PQ6W(470MHz)	BLU 97, BLW 14, BLX 68
37198	BLY53A	36V, 1A, PQ7,8W(470MHz)	BLU 97, BLW 14, BLX 68
37199	BLY53B	36V, 2A, PQ>8,3W(470MHz)	BLW 14, BLW 44, 2N5946
37200	BLY55	40V, 1A, PQ4W(175MHz)	BLY 57, BLY 78, 2N3926
37201	BLY57	36V, 1A, PQ>7W(175MHz)	BLY 78, 2N3926
37202	BLY58	36V, 1,5A, PQ>12W(175MHz)	BLY 79, 2N3927
37203	BLY59	65V, 0,5A, PQ>7,5W(100MHz)	2N3375
37204	BLY60	65V, 1A, PQ>13,5W(175MHz)	2N3632
37205	BLY61	36V, 0,5A, PQ>1W(175MHz)	BFR 98, BFS 22, BFS 51, BLW 16, 2N4427
37206	BLY62	36V, 2A, PQ>5W(175MHz)	BLW 18...19, BLW 37, MRF 212, 2N5590
37207	BLY63	36V, 5A, PQ>15W(175MHz)	BLW 20, BLW 31, BLW 38, 2N6084
37208	BLY64	80V, 5A, 50W, >60MHz	2N5002, 2N5004
37209	BLY65	80V, 5A, 50W, >60MHz	2N5003, 2N5005
37210	BLY66(A,B)	100V, 2A, 30W, >50MHz	2N4998, 2N5000
37211	BLY67(A,B)	100V, 2A, 30W, >50MHz	2N4999, 2N5001
37212	BLY68	100V, 3A, 25W, 100MHz	BDY 90...91, 2SC2681, 2SC2706, 2SC2837
37213	BLY70	100V, 5A, 33W, 70MHz	BDY 90...91, 2SC2681, 2SC2706, 2SC2837
37214	BLY72	80V, 10A, 100W, >30MHz	2N5006, 2N5008, 2N5288...5289

37215	BLY74	65V, 0,5A, PQ>3W(400MHz)	-
37216	BLY76	65V, 0,3A, PQ2W(470MHz)	BFT 91, BLW 89, BLW 92, BLX 92
37217	BLY78	40V, 1A, PQ>4,7W(175MHz)	BLY 57, 2N3926
37218	BLY79	40V, 2A, PQ>11W(175MHz)	BLY 58, 2N3927
37219	BLY83	66V, 2,5A, PQ>7W(175MHz)	BLW 19, MRF 212, 2N5590
37220	BLY84	40V, 2,5A, PQ>13W(175MHz)	BLW 29, BLY 88, MRF 226, 2N6081
37221	BLY85	40V, 1A, PQ>4W(175MHz)	BLY 87, 2N6080
37222	BLY86	300/300V, 0,4A, 10W, 60MHz	2N3739, 2SC1929, 2SC2022, 2SC2354,
37223	BLY87(A,C)	36V, 1,25A, PQ8W(175MHz)	BLW 19, BLW 37, MRF 212, 2N5590
37224	BLY88(A,C,T)	36V, 2,5A, PQ15W(175MHz)	BLW 29, BLY 84, MRF 226, 2N6081
37225	BLY89(A,C)	36V, 3,5A, PQ25W(175MHz)	MRF 209, MRF 238, 2N5591, 2N6082...83
37226	BLY90	36V, 8A, PQ50W(175MHz)	-
37227	BLY91(A,C)	65V, 0,75A, PQ8W(175MHz)	BLY 98, 2N5641
37228	BLY92(A,C)	65V, 1,5A, PQ15W(175MHz)	BLW 24, BLY 93
37229	BLY93(A,C)	65V, 2A, PQ25W(175MHz)	BLW 24
37230	BLY94	65V, 6A, PQ50W(175MHz)	BLW 25, 2N5643
37231	BLY97	60V, 1A, PQ>4W(175MHz)	BLY 91, BLY 98, 2N5641
37232	BLY98	60V, 1A, PQ7W(175MHz)	BLY 91, BLY 97, 2N5641
37233	BLY99	30V, 0,5A, PQ>1W(470MHz)	BFS 50, BLX 65, MRF 629, 2N3948
37234	BM	BCP 55-16	BCP 55
37235	BM	P4 SMA-24A	P4 SMA-24A
37236	BM	2SB1325	2SB1325
37237	BM	BCX 55-16	BCX 55
37238	BM(p,s)	BSS 63	BSS 63
37239	BMQ	2SC4713K-Q	2SC4713K
37240	BMQ	2SC4774-Q	2SC4774
37241	BMR	2SC4713K-R	2SC4713K
37242	BMR	2SC4774-R	2SC4774
37243	BMS	2SC4774-S	2SC4774
37244	BMS	2SC4713K-S	2SC4713K
37245	BN	P4 SMA-27	P4 SMA-27
37246	BN	2SB1394	2SB1394
37247	BN(s)	BCW 61FN	BCW 61FN
37248	BN1A3Q..L4Z	AN 1A3Q..L4Z	-
37249	BN2A3Q	Rb1k, Rbe10kOhm, 25V, 0,1A	-
37250	BN2A4M	BN 2A3Q, Rb10k, Rbe10kOhm	-
37251	BN2A4P	BN 2A3Q, Rb10k, Rbe47kOhm	-
37252	BN2A4Z	BN 2A3Q, Rb10k, Rbe-	-
37253	BN2F4M	BN 2A3Q, Rb22k, Rbe22kOhm	-
37254	BN2F4N	BN 2A3Q, Rb22k, Rbe47kOhm	-
37255	BN2F4Z	BN 2A3Q, Rb22k, Rbe-	-
37256	BN2L3M	BN 2A3Q, RbRbe4,7kOhm	-
37257	BN2L3N	BN 2A3Q, Rb4,7k, Rbe10kOhm	-
37258	BN2L3Z	BN 2A3Q, Rb4,7k, Rbe-	-
37259	BN2L4L	BN 2A3Q, Rb47k, Rbe22kOhm	-

37260	BN2L4M	BN 2A3Q, Rb47k, Rbe47kOhm	-
37261	BN2L4Z	BN 2A3Q, Rb47k, Rbe-	-
37262	BN3L4Z	Rb47kOhm, 20V, 20mA	
37263	BO	BCW 61RA	BCW 61RA
37264	BO	2SB1396	2SB1396
37265	BO	KTA1660-O	KTA 1660
37266	BO	2SA1200-O	2SA1200
37267	BO102	BO 12, 1000V	BA 159, BY 204/10, BY 208/1000
37268	BO12	100V, 0,25A	BA 157...159, BY 204/4, BY 208/600
37269	BO22	BO 12, 200V	BA 157...159, BY 204/4, BY 208/600
37270	BO42	BO 12, 400V	BA 157...159, BY 204/4, BY 208/6
37271	BO62	BO 12, 600V	BA 158...159, BY 204/8, BY 208/600
37272	BO82	BO 12, 800V	BA 159, BY 204/8, BY 208/800
37273	BP	P4 SMA-27A	P4 SMA-27A
37274	BP	BCW 61RB	BCW 61RB
37275	BP	2SB1397	2SB1397
37276	BP1A3M..L3N	AP 1A3M..L3N	-
37277	BQ	2SB1627-Q	2SB1627
37278	BQ	2SC2412-BQ	2SC2412
37279	BQ	P4 SMA-30	P4 SMA-30
37280	BQ	2SB1218A-Q	2SB1218A
37281	BQ	2SC4081-Q	2SC4081
37282	BQ	2PB709AQ	2PB709A
37283	BQ	2SB709A-Q	2SB709A
37284	BQ	2SC2412K-Q	2SC2412K
37285	BQ	2SB766A-Q	2SB766A
37286	BR	2SB1627-R	2SB1627
37287	BR	2SC2412-BR	2SC2412
37288	BR	XN 4214	XN 4214
37289	BR	XP 4214	XP 4214
37290	BR	P4 SMA-30A	P4 SMA-30A
37291	BR	2SB709A-R	2SB709A
37292	BR	2SC4081-R	2SC4081
37293	BR	BCW 61RC	BCW 61RC
37294	BR	2SC2412K-R	2SC2412K
37295	BR	2PB709AR	2PB709A
37296	BR	2SB1218A-R	2SB1218A
37297	BR	2SB766A-R	2SB766A
37298	BR1	BSP 30	BSP 30
37299	BR1	BSR 30	BSR 30
37300	BR100(/03,DB3)	Ub28..36V, Ib<0,1mA, Itsm2A	1N5761, N 413M, D 3202Y, D 0201YR
37301	BR103	<10μs	BRX 44...49, TAG 60A...Y, TAG 62A...Y
37302	BR103X	BR 203, <6μs	TAG 64A...Y, TAG 103X
37303	BR2	BSP 31	BSP 31
37304	BR2	BSR 31	BSR 31

37305	BR203	<10µs	TAG 64A...Y, TAG 103X
37306	BR211-100...280	50W(1ms)	-
37307	BR3	BSP 32	BSP 32
37308	BR3	BSR 32	BSR 32
37309	BR303	30V, 1A, Igt/Ih<2/<5mA, <13µs	BR 403, TAG 66A...Y
37310	BR4	BSP 33	BSP 33
37311	BR4	BSR 33	BSR 33
37312	BR403	BR 303	BR 303, TAG 66A...Y
37313	BRX44	8µs	BRX 50...56, BRY 55S/30...800
37314	BRX45	BRX 44, 60V	BRX 51...56, BRY 55S/60...800
37315	BRX46	BRX 44, 100V	BRX 51...56, BRY 55S/100...800
37316	BRX47	BRX 44, 200V	BRX 52...56, BRY 55S/200...800
37317	BRX48	BRX 44, 300V	BRX 53...56, BRY 55S/300...800
37318	BRX49	BRX 44, 400V	BRY 54...56, BRY 55S/400...800S
37319	BRX50	Igt/Ih<0,2/<5mA	BRX 45...49, BRY 55S/60...800
37320	BRX51	BRX 50, 100V	BRX 46...49, BRY 55S/100...800
37321	BRX52	BRX 50, 200V	BRX 47...49, BRY 55S/200...800
37322	BRX53	BRX 50, 300V	BRX 48...49, BRY 55S/300...800
37323	BRX54	BRX 50, 400V	BRX 49, BRY 55S/400...800
37324	BRX55	BRX 50, 500V	BRY 55S/500...800
37325	BRX56	BRX 50, 600V	BRY 55S/600...800
37326	BRX60	Igt/Ih<0,2/<5mA	TAG 66A...F, BR 303
37327	BRX61	BRX 60, 100V	TAG 66A
37328	BRX62	BRX 60, 200V	-
37329	BRX63	BRX 60, 300V	-
37330	BRX64	BRX 60, 400V	-
37331	BRX65	BRX 60, 500V	-
37332	BRX66	BRX 60, 600V	-
37333	BRX70-03...50	Igt<0,2mA	BRX 45...49, BRX 50...56, BRY 55/...
37334	BRX71-03...50	Igt<0,2mA	BRX 45...49, BRX 50...56, BRY 55/...
37335	BRX72-03...50	Igt<0,2mA	BRX 45...49, BRX 50...56, BRY 55/...
37336	BRX73-03...50	Igt<0,2mA	BRX 45...49, BRX 50...56, BRY 55/...
37337	BRX79-03...50	30..500V, Igt<10mA	MAC 94-..., MAC 95-..., Z 106-...
37338	BRY23	<22µs	-
37339	BRY24	BRY 23, 200V	-
37340	BRY25	BRY 23, 300V	-
37341	BRY26	BRY 23, 400V	-
37342	BRY28	Igt/Ih<15/<25mA	TAG 2,5S-...
37343	BRY29	BRY 28, 200V	TAG 2,5S-...
37344	BRY30	BRY 28, 300V	TAG 2,5S-...
37345	BRY31	BRY 28, 400V	TAG 2,5S-...
37346	BRY32	1A(Tc25°),Igt/Ih<0,5/<2mA,	BRX 50...56
37347	BRY33	BRY 32, 100V	BRX 51...56
37348	BRY34	BRY 32, 200V	BRX 52...56
37349	BRY35	<22µs	-

37350	BRY36	BRY 35, 200V	-
37351	BRY37	BRY 35, 300V	-
37352	BRY40	300V	-
37353	BRY41-50...-600	Igt/Ih<25/25mA	T 2303A...M, T 2306A...F
37354	BRY45/50..600	Igt/Ih<50/<25mA	-
37355	BRY52-50...-600	Igt/Ih<50/<50mA	BT 158/..., T 2806B...M, T 2856A...M
37356	BRY53	90..125V, 0,04A, Itsm5A	-
37357	BRY54/30...600(T)	30..600V, 2,5A, Igt/Ih<20/25mA	TAG 2,5-..., TAG 611-...
37358	)	Igt/Ih<0,2/<5mA, 20µs	BRY 58/..., TAG 70D...S, TAG 72D...S
37359	BRY55/30S...800S	BRY 55/..(M), <6µs	-
37360	BRY56A	70V, Ip0,22µA, Iv2µA	-
37361	BRY56B	70V, Ip1µA, Iv10µA	-
37362	BRY56C	70V, Ip5µA, Iv50µA	-
37363	BRY57	90..125V, 0,04A, Itsm6A	-
37364	BRY58/30...800	BRY 55/..	BRY 55/...
37365	BRY59A...B	Igt<0,1mA	TAG 06A...YY, TIC 44...47, TIC 60...64
37366	BRY61	70V, Ip5µA, Iv30µA	-
37367	BRY70/200..800	200..800V, 0,5A, Igt<10mA	-
37368	BRY71/200..800	200..800V, 0,5A, Igt<0,2mA	BRY 55/..., TAG 70..., TAG 72...
37369	BS	2SB1627-S	2SB1627
37370	BS	2SC2412-BS	2SC2412
37371	BS	P4 SMA-33	P4 SMA-33
37372	BS	2SA1669	2SA1669
37373	BS	BCW 61RD	BCW 61RD
37374	BS	2SB709A-S	2SB709A
37375	BS	2SC4081-S	2SC4081
37376	BS	2SB1218A-S	2SB1218A
37377	BS	2SC2412K-S	2SC2412K
37378	BS	2PB709AS	2PB709A
37379	BS	2SB766A-S	2SB766A
37380	BS1	BSP 60	BSP 60
37381	BS1	BST 60	BST 60
37382	BS10-01A..07A	100..700V, 10A, Igt<50mA	TW10N...C, TW12N...C, TW18N..., TW25N...
37383	BS10-01B..07B	BS 10-...A	TW10N...H, TW12N...H, T6401...
37384	BS107	13/27ns	BS 108, BSS 89, BSS 101, BST 74
37385	BS107A	BS 107, <6,4Ohm	BS 107
37386	BS107P,PT	BS 107	BS 107
37387	BS108	5/20ns	BSN 205, BSS 88, BSS 89, BST 74
37388	BS109	300V, 0,15A, 0,83W	BSS 124
37389	BS110	20V, 0,2A, <12/18ns	BSV 52, 2SC3578
37390	BS112	170V, 0,2A, 0,83W	BS 107...108, BSS 101, BS 189, BSS 89
37391	BS170	13/29ns	BSS 296, BST 70, 2SK422...423
37392	BS170P	BS 170, 0,27A, 0,625W	BS 170
37393	BS189	200V, 0,2A, 0,83W	BS 108, BSS 89, BST 74, BSS 88
37394	BS192	200V, 0,18A, 0,83W	BS 208, BSS 92



37395	BS2	BSP 61	BSP 61
37396	BS2	BST 61	BST 61
37397	BS208	5/20ns	BS 192, BS 209, BSS 92
37398	BS209	300V, 0,12A, 0,83W	-
37399	BS212	170V, 0,2A, 0,83W	BS 192, BS 208
37400	BS250	5/25ns	BST 100
37401	BS270	<10/10ns	BSS 296, BST 70, 2SK422...423
37402	BS3	BSP 62	BSP 62
37403	BS3	BST 62	BST 62
37404	BS6-01A..07A	100..700V, 6A, Igt<50mA	TW6N...C, BS8...A, TW8N...C, BS10...A
37405	BS6-01B..07B	BS 6-..A	TW6N...H, BS8...B, TW8N...H, BS10...B
37406	BS7-02A..06A	200..600V, 6A, Igt<60mA	MAC216...,SC141...,T 2801...,TXC10K...M
37407	BS8-01A..07A	100..700V, 8A, Igt<50mA	TW8N...C, BS10...A, TW10M...C, TW12N...C
37408	BS8-01B..07B	BS 8-..A	TW8N...H, BS10...B, TW10M...H, TW12N...H
37409	BS9-02A..06A	200..600V, 8A, Igt<60mA	T 2802...,MAC222..., TIC226..., TXD10K...
37410	BSD10	15V, 50mA, 1/5ns	-
37411	BSD12	BSD 10, 25V	-
37412	BSD20	BSD 10, SMD	-
37413	BSD212	40V, 50mA, 1/5ns	-
37414	BSD213	BSD 212	-
37415	BSD214	40V, 50mA, 1/5ns	SD 210
37416	BSD215	BSD 214	SD 211
37417	BSD22	BSD 12, SMD	-
37418	BSD254	10/30ns	-
37419	BSD254A	BSD 254	-
37420	BSD254AR	BSD 254	-
37421	BSJ108	10/6ns	J 108, 2N5433
37422	BSJ109	BSJ 108, Idss>40mA, Up<6V	J 109
37423	BSJ110	BSJ 108, Idss>10mA, Up<4V	BFS 76, BFS 79, J 110
37424	BSJ111	40V, Idss>20mA, Up<10V	-
37425	BSJ112	BSJ 111, Idss>5mA, Up<5V	-
37426	BSJ113	BSJ 111, Idss>2mA, Up<3V	-
37427	BSJ174	7/15ns	-
37428	BSJ175	15/30ns	-
37429	BSJ176	35/35ns	-
37430	BSJ177	45/45ns	-
37431	BSJ30	-/30V, 0,8W, 250MHz	BC 140...141, 2N1613, 2N1711
37432	BSJ32	-/40V, 0,8W, 300MHz	BC 140...141, 2N1613, 2N1711
37433	BSJ36	40V, 0,5A, 0,36W, <40/-ns	BSW 24, BSX 36, 2N2906...2907
37434	BSJ61	25V, 0,36W, <40/-ns	BSW 41, BSY 62...63, 2N706A, 2N2221...22
37435	BSJ62	25V, 0,36W, <40/-ns	BSW 41, BSY 62...63, 2N706A, 2N2221...22
37436	BSJ63	40V, 0,2A, 0,36W, <40/-ns	BSW 41, BSY 63, 2N708, 2N2221...22
37437	BSJ65	25V, 0,36W, <40/-ns	BSW 41, BSY 62...63, 2N706A, 2N2221...22
37438	BSJ66	40V, 0,2A, 0,36W, <35/-ns	BSW 41, BSY 63, 2N708, 2N2221...22
37439	BSJ67	40V, 0,5A, 0,36W, <25/-ns	BSS 10, BSX 26, BSX 39, 2N3261

37440	BSJ68	40V, 0,5A, 0,36W, <9/-ns	BSS 10, BSX 26, BSX 39, 2N3261
37441	BSJ79	-/120V, 0,03A, 0,3W, 120MHz	BF 297...299, BF 422, BF 483
37442	BSN10	2/5ns	BS 170, BSS 98, BST 72
37443	BSN10A	BSN 10	BS 170, BSS 98, BST 72
37444	BSN12	<20Ohm,<4/8ns	BS 170, BSS 98, BST 72
37445	BSN12A	BSN 12	BS 170, BSS 98, BST 72
37446	BSN20	BSN 10, SMD, 0,1A	BSS 123, BSS 138, BSS 145, 2SK1590
37447	BSN204	5/20ns	BSS 88...89, BSN 254, BST 74
37448	BSN204A	BSN 204	BSS 88...89, BSN 254, BST 74
37449	BSN205	200V, 0,3A, 1W, <6Ohm, 5/15ns	BSS 88...89, BSN 254, BST 74
37450	BSN22	BSN 12, SMD, 0,1A	BSS 123, BSS 138, BSS 145, 2SK1590
37451	BSN254	250V, 0,3A, 1W, <7Ohm, 5/20ns	BSN 274
37452	BSN254A	BSN 254	BSN 274
37453	BSN274	5/20ns	BSN 304
37454	BSN274A	BSN 274	BSN 304
37455	BSN304	2,5/17ns	-
37456	BSN304A	BSN 304	-
37457	BSN65F	10/10ns	-
37458	BSP103	35V, 0,7A, 1,5W, <1,8Ohm	-
37459	BSP105	60V, 0,5A, 1,5W, <3Ohm	-
37460	BSP106	60V, 0,425A, 1,5W, <4Ohm	-
37461	BSP107	200V, 0,2A, 1,5W, 14Ohm	-
37462	BSP108	2/10ns	-
37463	BSP109	90V, 0,45A, 1,5W, <4Ohm	-
37464	BSP110	80V, 0,325A, 1,5W, <10Ohm	-
37465	BSP120	200V, 0,25A, 1,5W, <12Ohm	BSP 128
37466	BSP121	200V, 0,35A, 1,5W, <6Ohm	BSP 128
37467	BSP122	200V, 0,55A <2,5Ohm,<35/50ns	BSP 297
37468	BSP123	BSS 123, 0,38A, <6Ohm(0,38A)	-
37469	BSP124	<10/30ns	-
37470	BSP125	BSS 125, 0,12A	-
37471	BSP126	250V, 0,35A, <7Ohm, 5/20ns	BSP 121
37472	BSP127	270V, 0,35A, <8Ohm, 5/20ns	BSP 130
37473	BSP128	200V, 0,35A, <8Ohm, 5/20ns	BSP 130
37474	BSP129	BSS 129, 0,2A	BSP 124
37475	BSP130	300V, 0,3A, <8Ohm, 2,5/17ns	-
37476	BSP135	BSS 135, 0,1A	-
37477	BSP149	BSS 149, 0,48A	-
37478	BSP15	BST 15, 1,5W	-
37479	BSP152	<15/30ns	BSP 122
37480	BSP16	BST 16, 1,5W	-
37481	BSP17	50V, 3,2A, <0,10Ohm, 60/95ns	-
37482	BSP171	60V, 1,6A, <0,35Ohm, 86/510ns	-
37483	BSP19	BST 39, 1,5W	-
37484	BSP20	BST 40, 1,5W	-

37485	BSP204	5/20ns	BS 192, BS 208, BSS 92, BSS 192
37486	BSP204A	BSP 204	BS 192, BS 208, BSS 92, BSS 192
37487	BSP205	3/10ns	-
37488	BSP206	4/15ns	-
37489	BSP220	200V, 0,225A, <12Ohm, 1,5W	BSP 317
37490	BSP225	250V, 0,225A, 1,5W, <15Ohm	-
37491	BSP254	250V, 0,2A, <15Ohm, 5/20ns	BSS 92
37492	BSP254A	BSP 254	BSS 92
37493	BSP280	1000V, 0,5A, 35/140ns	-
37494	BSP295	BSS 295, 1,8A, <0,3Ohm(1,8A)	-
37495	BSP296	BSS 296, 1A	-
37496	BSP297	BSS 297, 0,65A	BSP 122
37497	BSP298	400V, 0,5A, <30Ohm, 35/50ns	-
37498	BSP299	500V, 0,4A, <40Ohm, 23/85ns	-
37499	BSP30	BSR 30, 1,5W	-
37500	BSP31	BSR 31, 1,5W	-
37501	BSP315	50V, 1,1A, <0,80Ohm, 43/220ns	BSP 171
37502	BSP316	100V, 0,65A, <2,2Ohm	-
37503	BSP317	200V, 0,37A, <6Ohm, 38/170ns	-
37504	BSP318	60V, 2,6A, <0,15Ohm, 42/160ns	-
37505	BSP319	50V, 3,8A, <0,07Ohm, 75/330ns	-
37506	BSP32	BSR 32, 1,5W	-
37507	BSP324	400V, 0,17A, <25Ohm, 15/23ns	BSP 299
37508	BSP33	BSR 33, 1,5W	-
37509	BSP372	100V, 1,7A, <0,31Ohm, 52/205ns	-
37510	BSP373	100V, 1,7A, <0,3Ohm, 40/145ns	-
37511	BSP40	BSR 40, 1,5W	-
37512	BSP41	BSR 41, 1,5W	-
37513	BSP42	BSR 42, 1,5W	-
37514	BSP43	BSR 43, 1,5W	-
37515	BSP50	BST 50, 1,5W	-
37516	BSP51	BST 51, 1,5W	-
37517	BSP52	BST 52, 1,5W	-
37518	BSP60	BST 60, 1,5W	-
37519	BSP61	BST 61, 1,5W	-
37520	BSP62	BST 62, 1,5W	-
37521	BSP88	BSS 88, 0,36A, <0,6Ohm(0,36A)	BSP 126
37522	BSP89	BSS 89, 0,34A, <6Ohm(0,34A)	BSP 121
37523	BSP92	BSS 92, 0,18A, <20Ohm(0,18A)	BSP 225
37524	BSR111	BSJ 111, SMD	PMBFJ 111
37525	BSR112	BSJ 112, SMD	PMBFJ 112
37526	BSR113	BSJ 113, SMD	PMBFJ 113
37527	BSR12	15V, 0,1A, >1,5GHz, <20/30ns	2SA1764
37528	BSR12R	BSR 12	-
37529	BSR13	60V, 0,8A, <35/285ns	BSR 14, BSS 79, BSS 81

37530	BSR13R	BSR 13	BSR 14R
37531	BSR14	75V, 0,8A, <35/285ns	BSS 79, BSS 81
37532	BSR14R	BSR 14	-
37533	BSR15	60/40V, 0,6A, <50/110ns	BSS 80, BSS 82
37534	BSR15R	BSR 15	-
37535	BSR16	BSR 15, 60/60V	BSS 80, BSS 82
37536	BSR16R	BSR 16	-
37537	BSR17(A)	60V, 0,2A, <70/250ns	BSR 13...14, BSS 79, BSS 81
37538	BSR17(A)R	BSR 17	BSR 13R...14R
37539	BSR174	BSJ 174, SMD	PMBFJ 174
37540	BSR175	BSJ 175, SMD	PMBFJ 175
37541	BSR176	BSJ 176, SMD	PMBFJ 176
37542	BSR177	BSJ 177, SMD	PMBFJ 177
37543	BSR18(A)	40V, 0,2A, <70/300ns	BSR 15...16, BSS 80, BSS 82
37544	BSR18(A)R	BSR 18	BSR 15R...16R
37545	BSR19	160V, 0,6A, >100MHz	-
37546	BSR19A	BSR 19, 180V	-
37547	BSR20	130V, 0,6A, >100MHz	-
37548	BSR20A	BSR 20, 160V	-
37549	BSR30	70V, 1A, <500/650ns, B>40	-
37550	BSR31	BSR 30, B>100	-
37551	BSR32	BSR 30, 90V	-
37552	BSR33	BSR 30, 90V, B>100	-
37553	BSR40	70V, 1A, <250/1000ns, B>40	-
37554	BSR41	BSR 40, B>100	-
37555	BSR42	BSR 40, 90V	-
37556	BSR43	BSR 40, 90V, B>100	-
37557	BSR50	B>2000	BC 618, BC 875, BC 877, BC 879
37558	BSR51	BSR 50, 80V	BC 618, BC 877, BC 879
37559	BSR52	BSR 50, 100V	BC 879
37560	BSR55	100V, 1A, >100MHz, B>1500	2SC1879, 2SD406, 2SD688
37561	BSR56	40V, Idss>50mA, Up<10V	-
37562	BSR57	BSR 56, Idss>20mA, Up<6V	-
37563	BSR58	BSR 56, Idss>8mA, Up<4V	-
37564	BSR59	15V, 5A, >100MHz, B>1500	2N5425...5426
37565	BSR60	B>2000	BC 876, BC 878, BC 880
37566	BSR61	BSR 60, 80V	BC 878, BC 880
37567	BSR62	BSR 60, 100V	BC 880
37568	BSS10	40V, 0,5A, 0,3W, <13/16ns	BSX 26, BSX 39, 2N3261
37569	BSS100	100V, 0,22A, 0,63W, <6Ohm	BS 189, BSS 89, BSS 91, BST 74, BST 76
37570	BSS101	240V, 0,13A, 0,63W, <16Ohm	BSS 89, BSN 254
37571	BSS11	40V, 0,2A, 0,36W, <12/18ns	BSX 19...20, 2N2368, 2N2369(A)
37572	BSS110	50V, 0,17A, 0,63W, <10Ohm	BSS 92, BST 100, 2SJ148
37573	BSS119	100V, 0,17A, <6Ohm, 9/24ns	BSS 123
37574	BSS12	30V, 0,2A, 0,36W, <15/20ns	BSS 11, BSW 38, 2N2368...69, 2N3011

37575	BSS123	100V, 0,17A, <6Ohm	
37576	BSS124	15/33ns	-
37577	BSS125	15/31ns	-
37578	BSS129	14/40ns	-
37579	BSS13	60V, 1A, 1W, 18/35ns	BSS 27, BSV 77, 2N5189, 2SC1386
37580	BSS131	BSS 101, SMD, 0,1A	-
37581	BSS135	14/35ns	-
37582	BSS138	BSS 98, SMD, 0,22A	BSS 145
37583	BSS139	250V, 0,04A, <100Ohm, 14/25ns	-
37584	BSS14	75V, 2A, 1W, 18/35ns	2N3506...3507, 2N5262
37585	BSS145	65V, 0,22A, <3,5Ohm, 11/27ns	PMBF 170, BST 82
37586	BSS149	27/110ns	-
37587	BSS15	100V, 2A, 1W, <80/800ns	2N5320, 2SD854
37588	BSS16	BSS 15, 75V	2N5320...5321, 2SD854
37589	BSS17	100V, 2A, 1W, <100/1000ns	2N5322
37590	BSS18	BSS 17, 75V	BSV 82, 2N5322...5323
37591	BSS19	120V, 0,05A, 0,225W, >50MHz	BF 297...299, BF 422, BSS 38, BSX 21
37592	BSS192	BSS 92, SMD	2SK848
37593	BSS20	BSS 19, 160V	BF 297...299, BF 422
37594	BSS21	30V, 0,2A, 0,25W, <15/23ns	BSS 11...12, BSW 38, 2N2369(A)
37595	BSS22	12V, 0,2A, 0,25W, <60/75ns	BSV 21, BSW 25, BSW 37, BSX 29, 2N3012
37596	BSS229	BSS 139, 0,07A	-
37597	BSS23	45V, 1A, 0,5W, 25/40ns	BSS 26, BSW 26, BSS 40...41, 2N4013...14
37598	BSS25	-/25V, 0,4A, <45/100ns	BSR 15...16, BSS 80, BSS 82
37599	BSS26	60V, 1A, 0,36W, 15/40ns	BSS 23, BSW 26, BSS 40...41, 2N4013...14
37600	BSS27	70V, 1A, 0,8W, <25/40ns	BSS 14, BSV 95, 2N3735, 2SC1386
37601	BSS28	BSS 27, 50V, <25/45ns	BSS 13, BSV 77, BSV 95, 2N3724A
37602	BSS284	50V, 0,13A, 19/30ns	2SJ185
37603	BSS29	BSS 27, 50V, <30/50ns	BSS 13, BSV 77, BSV 95, 2N3724A
37604	BSS295	50V, 1,4A, 1W, <0,3Ohm	2SK975, 2SK2085
37605	BSS296	100V, 0,8A, 1W, <0,8Ohm	2SK423, 2SK941
37606	BSS297	200V, 0,48A, 1W, <2Ohm	-
37607	BSS30	100V, 1A, 0,8W, 80MHz	BC 141, BSW 66...68, BSX 46...47
37608	BSS31	BSS 30, 100MHz	BC 141, BSW 66...68, BSX 46...47
37609	BSS32	BSS 30, 120V, 70MHz	BSS 42...43, BSW 67...68, BSX 47
37610	BSS33	200V, 0,4A, >40MHz	BFR 57...59, 2SD413, 2SD576, 2SD624
37611	BSS34	100V, 0,2A, 0,625W, >90MHz	BFR 86...89, BSS 38, BSX 21, 2SC3245
37612	BSS35	BSS 34, 120V	BFR 86...89, BSS 38, BSX 21, 2SC3245
37613	BSS36	0,6W, B>400	-
37614	BSS37	110V, 0,1A, 0,2W, 95MHz	BF 398, BF 435...437, BSS 68, BSV 68
37615	BSS38	120V, 0,1A, 0,3W, >60MHz	BF 297...299, BFR 86...89, BSX 21
37616	BSS39	120V, 0,1A, 0,225W	BF 398, BF 435...437, BSS 68, BSV 68
37617	BSS395	50V, 4,4A, 10W, <0,3Ohm	-
37618	BSS396	100V, 2A, 10W, <0,8Ohm	-
37619	BSS397	200V, 1,5A, 10W, <2Ohm	-

37620	BSS40	60/40V, 1A, 0,36W, <35/45ns	2N4014
37621	BSS41	BSS 40, 60/30V	2N4014
37622	BSS42	120V, 1,5A, 1W, 40/700ns	BSV 84, BSW 67...68, BSX 47
37623	BSS43	BSS 42, 150V	BSW 68, 2SC1860
37624	BSS44	65V, 5A, 0,87W, >70MHz	BSS 46, 2N6190...6193
37625	BSS45	85V, 5A, 0,87W, <300/1000ns	2N5338...5339, 2N4895...4897
37626	BSS46	85V, 5A, 0,87W, <300/1000ns	2N6190...6193
37627	BSS47	120V, 0,1A	-
37628	BSS48	300V, 1A, 1W, 120/500ns	BFQ 38...40, 2N3439...40, 2SC1861...62
37629	BSS49	BSS 48, 400V	BFQ 40, 2N3440, 2SC1862
37630	BSS50	B>2000	BCX 21
37631	BSS51	BSS 50, 80V	-
37632	BSS52	BSS 50, 100V	-
37633	BSS53(A,B)	-/160V, 0,1A, 0,3W, 70MHz	BF 435...437, BF 491...493, BFP 23, BFP 26
37634	BSS54(A,B)	BSS 53, -/250V	BF 436...437, BF 492...493, BFP 26
37635	BSS55(A,B)	BSS 53, -/300V	BF 437, BF 493, BFP 26
37636	BSS56	100V, 0,5A, >80MHz	BCX 41R
37637	BSS58A	BSV 58 A	BSV 58 A
37638	BSS58B	BSV 58 B	BSV 58 B
37639	BSS59	140V, 1A, 0,5W, <200/750ns	BSS 43, BSW 68
37640	BSS60	B>2000	-
37641	BSS61	BSS 60, 80V	-
37642	BSS62	BSS 60, 100V	-
37643	BSS63	110V, 0,1A, 85MHz	BCX 42, 2SA1257, 2SA1325, 2SA1330
37644	BSS63R	BSS 63	BCX 42R
37645	BSS64	120V, 0,1A, 100MHz	BCX 41, 2SC3143, 2SC3340, 2SC3360
37646	BSS64R	BSS 64	BCX 41R
37647	BSS65	12V, 0,1A, <60/90ns	BSR 15...16, BSR 18
37648	BSS65R	BSS 65	BSR 15R...16R, BSR 18R
37649	BSS66	60V, 0,1A, <70/250ns, B>50	BSR 17
37650	BSS66R	BSS 66	BSR 17R
37651	BSS67	BSS 66, B>100	BSR 17
37652	BSS67R	BSS 67	BSR 17R
37653	BSS68	110V, 0,1A, 0,3W, >50MHz	BF 398, BF 435...437, BSV 68
37654	BSS69	40V, 0,1A, <75/225ns, B>50	BSR 15...16, BSR 18
37655	BSS69R	BSS 69	BSR 15R...16R, BSR 18R
37656	BSS70	BSS 69, B>100	BSR 15...16, BSR 18
37657	BSS70R	BSS 70	BSR 15R...16R, BSR 18R
37658	BSS71(S)	200V, 0,5A, 0,5W, 70MHz	BF 391...393, BFP 22, MPSA 42...43
37659	BSS72(S)	BSS 71, 250V	BF 392...393, BFP 25, MPSA 42
37660	BSS73(S)	BSS 71, 300V	BF 393, BFP 25, MPSA 42
37661	BSS74(S)	200V, 0,5A, 0,5W, 80MHz	BF 491...493, BFP 23, MPSA 92...93
37662	BSS75(S)	BSS 74, 250V	BF 492...493, BFP 26, MPSA 92
37663	BSS76(S)	BSS 74, 300V	BF 493, BFP 26, MPSA 92
37664	BSS77	BSS 71, 0,8W	BSS 48...49, 2N3440, 2SD413, 2SD624



37665	BSS7728	60V, 0,15A, 10/25ns	BSS 123, 2SK1590
37666	BSS78	BSS 72, 0,8W	BSS 48...49, 2N3440, 2SD576
37667	BSS79(B,C)	75/40V, 0,8A, <35/310ns	BSR 14, BCX 41
37668	BSS80(B,C)	60/40V, 0,8A, <50/110ns	BCX 42
37669	BSS81(B,C)	BSS 79, 75/35V	BSR 14, BCX 41
37670	BSS82(B,C)	BSS 80, 60/60V	BCX 42
37671	BSS83	15V, Up<2V, <45Ohm, 1/5ns	-
37672	BSS84	50V, 0,13A, 19/30ns	2SJ185
37673	BSS87	200V, 0,29A, 16/55ns	-
37674	BSS88	240, 0,25A, 1W, <8Ohm	BSN 254
37675	BSS89	240V, 0,29A, 1W, <6Ohm	BSS 91, BSN 254
37676	BSS91	200V, 0,35A, 1,5W, <6Ohm	BSS 89, BSN 254
37677	BSS92	240V, 0,15A, 1W, 33/67ns	BSP 254
37678	BSS93	BSS 87, 0,5A, 2,5W	BSS 95
37679	BSS95	240V, 0,8A, 8,3W,<6Ohm(0,5A)	-
37680	BSS97	20/150ns	2SK296, 2SK375
37681	BSS98	50V, 0,3A, 0,63W, <3,5Ohm	BS 170, 2SK1336
37682	BSS99	80V, 4A, >2MHz, B>750	2SC2208, BD 679, BD 779, BD 865
37683	BST100	60V, 0,3A, 1W, <6Ohm, 4/20ns	2SJ198, 2SJ228, 2SJ231
37684	BST100	60V, 0,3A, 1W, <6Ohm, 4/20ns	2SJ198, 2SJ228, 2SJ231
37685	BST110	4/10ns	BSP 204, 2SJ198, 2SJ228, 2SJ231
37686	BST120	BST 100, SMD	2SJ199, 2SJ212...213
37687	BST122	BST 110, SMD	2SJ199, 2SJ212...213
37688	BST15	200V, 1A, >15MHz	-
37689	BST16	BST 15, 350V	-
37690	BST39	450V, 1A, >70MHz	-
37691	BST40	BST 39, 300V	-
37692	BST50	B>2000	2SD1470, 2SD1472, 2SD1511
37693	BST51	BST 50, 80V	2SD1472
37694	BST52	BST 50, 100V	2SD1472
37695	BST60	B>2000	2SB1048
37696	BST61	BST 60, 80V	-
37697	BST62	BST 60, 100V	-
37698	BST70	<10/15ns	BSS 296, 2SK423, 2SK940...41
37699	BST70A	BST 70	BST 70
37700	BST72	<10/10ns	BSS 88...89, BSS 91, 2SK1337
37701	BST72A	BST 72	BST 72
37702	BST74	<10/25ns	BSS 88...89, BSS 91, BSN 205
37703	BST76	<10/15ns	BSS 89, BSS 91, BSS 297
37704	BST76A	BST 76	
37705	BST80	BST 70, SMD	2SK601, 2SK1078...1079
37706	BST82	BST 72, SMD	-
37707	BST84	BST 74, SMD	BSS 87
37708	BST86	BST 76, SMD	BSS 87
37709	BST90	BST 70, 2,5W	-

37710	BST95	200V, 2A, <20hm, <35/50ns	-
37711	BST97	BST 76, 0,4W	-
37712	BStA3026	Igt/Ih<10/<40mA	CS0,8-04, BStA3026M, CS1,2-04
37713	BStA3026M	Igt/Ih<10/<40mA	CS08-04,CS1,2-04, TAG612-400,TAG606-400
37714	BStA3033	BStA3026, 500V	CS0,8-05, BStA3033M, CS1,2-05
37715	BStA3033M	BStA3026M, 500V	CS08-05,CS1,2-05, TAG612-600,TAG606-600
37716	BStA3040	BStA3026, 600V	CS0,8-06, BStA3040M, CS1,2-06
37717	BStA3040M	BStA3026M, 600V	CS08-06,CS1,2-06, TAG612-600,TAG606-600
37718	BStA3046	BStA3026, 700V	CS0,8-07, BStA3046M, CS1,2-07
37719	BStA3046M	BStA3026M, 700V	CS08-07,CS1,2-07, TAG612-700,TAG606-700
37720	BStA3053	BStA3026, 800V	BStA3053M, TAG613-800, TAG606-800
37721	BStA3053M	BStA3026M, 800V	TAG612-800, TAG606-800
37722	BStB0106	Igt/Ih<10/<60mA	CS0,8-02, BStA3026M, CS1,2-02
37723	BStB0113	BStB0106, 200V	CS0,8-02, CS1,2-02, BStA3026M
37724	BStB0126	BStB0106, 400V	CS0,8-04, BStA3026M, CS1,2-04
37725	BStB0133	BStB0106, 500V	CS0,8-05, BStA3033M, CS1,2-05
37726	BStB0140	BStB0106, 600V	CS0,8-06, BStA3040M, CS1,2-06
37727	BStB0146	BStB0106, 700V	CS0,8-07, BStA3046M, CS1,2-07
37728	BStB0206	Igt/Ih<10/<60mA	TAG621-100, TAG626/100, T3,5N400
37729	BStB0213	BStB0206, 200V	TAG621-200, TAG626-200, T3,5N400
37730	BStB0226	BStB0206, 400V	TAG621-400, TAG626-400, T3,5N400
37731	BStB0233	BStB0206, 500V	TAG621-500, TAG626-500, T3,5N600
37732	BStB0240	BStB0206, 600V	TAG621-600, TAG626-600, T3,5N600
37733	BStB0246	BStB0206, 700V	TAG621-700, TAG626-700, T3,5N800
37734	BStC0106	Igt/Ih<35/<90mA	BStC0313, BStD0313, CS5-02, CS8-02
37735	BStC0113	BStC0106, 200V	BStC0313, BStD0313, CS5-02, CS8-02
37736	BStC0126	BStC0106, 400V	BStC0326, BStD0326, CS5-04, CS8-04
37737	BStC0133	BStC0106, 500V	BStC0340, BStD0340, CS5-06, CS8-06
37738	BStC0140	BStC0106, 600V	BStC0340, BStD0340, CS5-06, CS8-06
37739	BStC0146	BStC0106, 700V	BStC0353, BStD0353, CS5-08, CS8-08
37740	BStC0206	Igt/Ih<20/<60mA	TAG620-100, BStC1026, TAG625-100
37741	BStC0213	BStC0206, 200V	TAG620-200, BStC1026, TAG625-200
37742	BStC0226	BStC0206, 400V	TAG620-400, BStC1026, TAG625-400
37743	BStC0233	BStC0206, 500V	TAG620-500, BStC1033, TAG625-500
37744	BStC0240	BStC0206, 600V	TAG620-600, BStC1040, TAG625-600
37745	BStC0246	BStC0206, 700V	TAG620-700, BStC1046, TAG625-700
37746	BStC0313	Igt/Ih<40/<30mA	BStD0313, CS5-02, CS8-02
37747	BStC0326	BStC0313, 400V	BStD0326, CS5-04, CS8-04
37748	BStC0340	BStC0313, 600V	BStD0340, CS5-06, CS8-06
37749	BStC0353	BStC0313, 800V	BStD0353, CS5-08, CS8-08
37750	BStC0366	BStC0313, 1000V	BStD0366, CS5-10, CS8-10
37751	BStC0380	BStC0313, 1200V	BStD0380, CS5-12, CS8-12
37752	BStC0506	Igt/Ih<20/<60mA	TAG671-100, TAG676-100
37753	BStC0513	BStC0506, 200V	TAG671-200, TAG676-200
37754	BStC0526	BStC0506, 400V	TAG671-400, TAG676-400

37755	BStC0533	BStC0506, 500V	TAG671-500, TAG676-500
37756	BStC0540	BStC0506, 600V	TAG671-600, TAG676-600
37757	BStC0546	BStC0506, 700V	TAG671-700, TAG676-700
37758	BStC0606	Igt/Ih<50/<100mA	100
37759	BStC0613	BStC0606, 200V	200
37760	BStC0626	BStC0606, 400V	400
37761	BStC0633	BStC0606, 500V	500
37762	BStC0640	BStC0606, 600V	600
37763	BStC0643	BStC0606, 650V	T3S700, TAG670S-700, TAG675S-700
37764	BStC0646	BStC0606, 700V	T3S700, TAG670S-700, TAG675S-700
37765	BStC0650	BStC0606, 750V	TAG670S-800, TAG675S-800
37766	BStC0653	BStC0606, 800V	TAG670S-800, TAG675S-800
37767	BStC0706	Igt/Ih<20/<60mA	BStC3026, TAG2,5-100, TAG611-100
37768	BStC0713	BStC0706, 200V	BStC3026, TAG2,5-200, TAG611-200
37769	BStC0726	BStC0706, 400V	BStC3026, TAG2,5-400, TAG611-400
37770	BStC0733	BStC0706, 500V	BStC3033, TAG2,5-500, TAG611-500
37771	BStC0740	BStC0706, 600V	BStC3040, TAG2,5-600, TAG611-600
37772	BStC0746	BStC0706, 700V	BStC3046, TAG2,5-700, TAG611-700
37773	BStC0926T92	400V, Igt<50mA	-
37774	BStC0930T92	450V, Igt<50mA	-
37775	BStC1026	Igt/Ih<25/<80mA	TAG625-400, C122D, TIC116D, CS6-04
37776	BStC1026M	Igt/Ih<25/<80mA	CS6-04, TAG660-400, S2800D, CS3,5-04
37777	BStC1033	BStC1026, 500V	TAG625-500, C122E, TIC116E, CS6-06
37778	BStC1033M	BStC1026M, 500V	CS6-06, TAG660-500, S2800E, CS3,5-06
37779	BStC1040	BStC1026, 600V	TAG625-600, C122M, TIC116M, CS6-06
37780	BStC1040M	BStC1026M, 600V	CS6-06, TAG660-600, S2800M, CS3,5-06
37781	BStC1046	BStC1026, 700V	TAG625-700, TIC116S, CS6-07, BStC1046M
37782	BStC1046M	BStC1026M, 700V	CS6-07, TAG660-700, S2800S, CS3,5-07
37783	BStC1053	BStC1026, 800V	TAG625-800, TIC116N, CS6-08, BStC1053M
37784	BStC1053M	BStC1026M, 800V	CS6-08, TAG660-800, S2800N, 2N6399
37785	BStC1226	Igt/Ih<50/<100mA	(BStCC02
37786	BStC1233	BStC1226, 500V	(BStCC02
37787	BStC1240	BStC1226, 600V	(BStCC02
37788	BStC1246	BStC1226, 700V	(BStCC02
37789	BStC1250	BStC1226, 750V	(BStCC02
37790	BStC1253	BStC1226, 800V	(BStCC02
37791	BStC3026	Igt/Ih<25/<80mA	TAG2,5-400, TAG611-400, TAG605-400
37792	BStC3033	BStC3026, 500V	TAG2,5-500, TAG611-600, TAG605-600
37793	BStC3040	BStC3026, 600V	TAG2,5-600, TAG611-600, TAG605-600
37794	BStC3046	BStC3026, 700V	TAG2,5-700, TAG611-700, TAG605-700
37795	BStC3053	BStC3026, 800V	TAG2,5-800, TAG611-800, TAG605-800
37796	BStC3126	Igt/Ih<25/<80mA	BStC3126M, TAG630-400, TAG620-400
37797	BStC3126M	2,5A(Tc85°C),Igt/Ih<25/<80mA	TAG630-400, TAG620-400, BStC1026
37798	BStC3133	BStC3126, 500V	BStC3133M, TAG630-500, TAG620-500
37799	BStC3133M	BStC3126M, 500V	TAG630-500, TAG620-500, BStC1033

37800	BStC3140	BStC3126, 600V	BStC3140M, TAG630-600, TAG620-600
37801	BStC3140M	BStC3126M, 600V	TAG630-600, TAG620-600, BStC1040
37802	BStC3146	BStC3126, 700V	BStC3146M, TAG630-700, TAG620-700
37803	BStC3146M	BStC3126M, 700V	TAG630-700, TAG620-700, BStC1046
37804	BStC3153	BStC3126, 800V	BStC3153M, TAG630-800, TAG620-800
37805	BStC3153M	BStC3126M, 800V	TAG630-800, TAG620-800, BStC1053
37806	BStCC0126H	3 $\mu$ s	S6087B, TD3F400H, TD4F400H
37807	BStCC0126R	5 $\mu$ s	S6087A, TD3F400R, TD4F400R
37808	BStCC0133H	BStCC0126H, 500V	S6087B, TD3F500H, TD4F500H
37809	BStCC0133R	BStCC0126R, 500V	S6087A, TD3F500R, TD4F500R
37810	BStCC0140H	BStCC0126H, 600V	S6087B, TD3F600H, TD4F600H
37811	BStCC0140R	BStCC0126R, 600V	S6087A, TD3F600R, TD4F600R
37812	BStCC0146H	BStCC0126H, 700V	S6087B, TD3F700H, TD4F700H
37813	BStCC0146R	BStCC0126R, 700V	S6087A, TD3F700R, TD4F700R
37814	BStCC0153H	BStCC0126H, 800V	TD3F800H, TD4F800H
37815	BStCC0153R	BStCC0126R, 800V	TD3F800R, TD4F800R
37816	BStCC0233H	Igt/Ih<50/<100mA,<3 $\mu$ s	S3900E, 17088
37817	BStCC0233R	5 $\mu$ s	S3901E, 17089
37818	BStCC0240H	BStCC0233H, 600V	S3900MF, 17088
37819	BStCC0240R	BStCC0233R, 600V	S3901MF, 17089
37820	BStCC0246H	BStCC0233H, 700V	S3900S, 17088
37821	BStCC0246R	BStCC0233R, 700V	S3901S, 17089
37822	BStCC0253H	BStCC0233H, 800V	17088
37823	BStCC0253R	BStCC0233R, 800V	17089
37824	BStCC0260H	BStCC0233H, 900V	17088
37825	BStCC0260R	BStCC0233R, 900V	17089
37826	BStD0220	Igt/Ih<50/120mA	BTW42/600R
37827	BStD0240	BStD0220, 600V	BTW42/600R
37828	BStD0260	BStD0220, 900V	BTW42/1000R
37829	BStD0313	Igt/Ih<30/<80mA	CS8-02
37830	BStD0326	BStD0313, 400V	CS8-04
37831	BStD0340	BStD0313, 600V	CS8-06
37832	BStD0353	BStD0313, 800V	CS8-08
37833	BStD0366	BStD0313, 1000V	CS8-10
37834	BStD0380	BStD0313, 1200V	CS8-12
37835	BStD1026	Igt/Ih<25/<80mA	400
37836	BStD1026M	10A(Tc85°C),Igt/Ih<25/<80mA	T9,5N400, CS15-04
37837	BStD1033	BStD1026, 500V	500
37838	BStD1033M	BStD1026M, 500V	T9,5N500, CS15-06
37839	BStD1040	BStD1026, 600V	600
37840	BStD1040M	BStD1026M, 600V	T9,5N600, CS15-06
37841	BStD1046	BStD1026, 700V	700
37842	BStD1046M	BStD1026M, 700V	T9,5N700, CS15-07
37843	BStD1053	BStD1026, 800V	800
37844	BStD1053M	BStD1026M, 800V	T9,5N800, CS15-08

37845	BStD1666M	Igt/Ih<10/<50mA	-
37846	BStD1666N	BStD1666M, Igt/Ih<20/<80mA	-
37847	BStD1666P	BStD1666M, Igt/Ih<50/<150mA	-
37848	BStD1680M	BStD1666M, 1200V	-
37849	BStD1680N	BStD1680M, Igt/Ih<20/<80mA	-
37850	BStD1680P	BStD1680M, Igt/Ih<50/<150mA	-
37851	BStD3666M	1A(Ta45°C),Igt/Ih<10/<50mA	BStD1666M
37852	BStD3666N	BStD3666M, Igt/Ih<20/<80mA	BStD1666N
37853	BStD3666P	BStD3666M, Igt/Ih<50/<150mA	BStD1666P
37854	BStD3680M	BStD3666M, 1200V	BStD1680M
37855	BStD3680N	BStD3680M, Igt/Ih<20/<80mA	BStD1680N
37856	BStD3680P	BStD3680M, Igt/Ih<50/<150mA	BStD1680P
37857	BStD4026	400V, 12A, Igt<10mA	T10N400H, S6200D, BStD4026M, C232D
37858	BStD4026M	400V, 15A, Igt<10mA	C 232D
37859	BStD4033	BStD4026, 500V	T10N500H, S6200M, BStD4033M, C232E
37860	BStD4033M	BStD4026M, 500V	C 232M
37861	BStD4040	BStD4026, 600V	T10N600H, S6200M, BStD4040M, C232M
37862	BStD4040M	BStD4026M, 600V	C 232M
37863	BStD4046	BStD4026, 700V	T10N700H, BStD4046M
37864	BStD4046M	BStD4026M, 700V	-
37865	BStD4053	BStD4026, 800V	T10N800H, BStD4053M
37866	BStD4053M	BStD4026M, 800V	-
37867	BStD4126	BStD4026	T10N400C, S6210D, BStD4126M, BStE4126
37868	BStD4126M	BStD4026M	C230D, BStE4126, BStE4126M
37869	BStD4133	BStD4033	T10N500C, S6210M, BStD4133M, BStE4133
37870	BStD4133M	BStD4033M	C230E, BStE4133, BStE4133M
37871	BStD4140	BStD4040	T10N600C, S6210M, BStD4140M, BStE4140
37872	BStD4140M	BStD4040M	C230M, BStE4140, BStE4140M
37873	BStD4146	BStD4046	BStE4146M
37874	BStD4146M	BStD4046M	BStE4146, BStE4146M
37875	BStD4153	BStD4053	BStE4153M
37876	BStD4153M	BStD4053M	BStE4153, BStE4153M
37877	BStE0326	0,6A(Ta45°C),Igt/Ih<35/<50mA	S5800D, BT153, TAG650S-400,TAG655S-400
37878	BStE0333	BStE0326, 500V	S5800E, BT153, TAG650S-500,TAG655S-500
37879	BStE0340	BStE0326, 600V	S5800M, TAG650S-600, TAG655S-600
37880	BStE0346	BStE0326, 700V	S5800S, CSF11-08
37881	BStE0426	4A(Tc77°C),Igt/Ih<50/<100mA	T3S400, TAG670S-400, TAG675S-400
37882	BStE0433	BStE0426, 500V	T3S500, TAG670S-500, TAG675S-500
37883	BStE0440	BStE0426, 600V	T3S600, TAG670S-600, TAG675S-600
37884	BStE0446	BStE0426, 700V	T3S700, TAG670S-700, TAG675S-700
37885	BStE4026	400V, 18A, Igt<50mA	BStE4026M
37886	BStE4026M	400V, 22A, Igt<50mA	-
37887	BStE4033	BStE4026, 500V	BStE4033M
37888	BStE4033M	BStE4026M, 500V	-
37889	BStE4040	BStE4026, 600V	BStE4040M

37890	BStE4040M	BStE4026M, 600V	-
37891	BStE4046	BStE4026, 700V	BStE4046M
37892	BStE4046M	BStE4026M, 700V	-
37893	BStE4053	BStE4026, 800V	BStE4053M
37894	BStE4053M	BStE4026M, 800V	-
37895	BStE4126	BStE4026	BTW40/400
37896	BStE4126M	BStE4026M	T17N400, T24N400, TAG24N400, CS23-04
37897	BStE4133	BStE4033	BTW40/600
37898	BStE4133M	BStE4033M	T17N600, T24N600, TAG24N600, CS23-06
37899	BStE4140	BStE4040	BTW40/600
37900	BStE4140M	BStE4040M	T17N600, T24N600, TAG24N600, CS23-06
37901	BStE4146	BStE4046	BTW40/800
37902	BStE4146M	BStE4046M	T17N800, T24N800, TAG24N800, CS23-08
37903	BStE4153	BStE4053	BTW40/800
37904	BStE4153M	BStE4053M	T17N800, T24N800, TAG24N800, CS23-08
37905	BSV10	40V, 1A, >50MHz, <500/-ns	BC 160...161, BSV 15...17, BSW 40
37906	BSV11	BSV 10, 60V	BC 161, BSV 16...17, BSW 40
37907	BSV12	BSV 10, 90V	BC 161, BCX 60, BSV 17, BSW 40
37908	BSV15	40V, 1A, >50MHz, <500/650ns	BC 160...161, BCX 60, BSV 82, BSW 40
37909	BSV16	BSV 15, 60V	BC 161, BCX 60, BSV 82, BSW 40
37910	BSV17	BSV 15, 90V	BCX 60, BSS 17, BSV 82, BSW 40
37911	BSV19	60V, 1A, 1W	-
37912	BSV20(A)	30V, 0,2A	-
37913	BSV21	12V, 0,2A, 0,36W, <60/90ns	BSW 25, BSW 37, BSX 29, 2N2894A
37914	BSV22	30V, 50mA	BFW 96, BSV 81
37915	BSV23(K,L,M)	25V, 0,2A, 0,3W, >200MHz	BSS 11...12, BSW 38, BSX 19...20, 2N3011
37916	BSV24(K,L,M)	BSV 23, 20V	BSS 11...12, BSW 38, BSX 19...20, 2N3011
37917	BSV25(K,L,M)	30V, 0,5A, 0,3W, <15/20ns	BSS 11...12, BSW 38, BSX 19...20, 2N3011
37918	BSV26(K,L,M)	40V, 0,5A, 0,3W, <12/18ns	BSS 11, BSX 19...20, 2N2369(A)
37919	BSV27(K,L,M)	30V, 0,5A, 0,3W, <15/20ns	BSS 11...12, BSW 38, BSX 19...20, 2N3011
37920	BSV28(K,L,M)	100V, 0,1A, 0,3W	BF 297...299, BFR 86, BSS 38, BSX 21
37921	BSV29(K,L,M)	BSV 28, 120V	BF 297...299, BFR 86, BSS 38, BSX 21
37922	BSV33(K,L,M)	12V, 0,2A, 0,3W, <60/60ns	BSV 21, BSW 25, BSW 37, BSX 29, 2N2894
37923	BSV35	40V, 0,5A, <12/18ns	-
37924	BSV35A	BSV 35, 25V, <40/75ns	-
37925	BSV36	15V, 0,5A, <20/15ns	-
37926	BSV37	12V, 0,5A, <60/90ns	-
37927	BSV40	B>40	BSW 41, BSY 63, 2N708, 2N4123
37928	BSV41	BSV 40, B>100	BSW 41, BSY 63, 2N708, 2N4123
37929	BSV42	70/70V, 0,5A, 0,6W, 200MHz	BC 161, BC 303, BSV 17, BSW 40
37930	BSV43(A,B)	BSV 42, 60/60V	BC 161, BC 303...304, BSV 16...17
37931	BSV44(A,B)	BSV 42, 60/40V	BC 161, BC 303...304, BSV 16...17
37932	BSV45(A,B)	BSV 42, 30/30V	BC 160...161, BC 303...304, BSV 15...17
37933	BSV46	70/70V, 0,5A, 0,4W, 200MHz	BC 640, BCY 77, 2N2906A...2907A
37934	BSV47(A,B)	BSV 46, 60/60V	BC 638, BCY 77, 2N2906A...2907A



37935	BSV48(A,B)	BSV 46, 60/40V	BC 638, BCY 77, 2N2906(A)...2907(A)
37936	BSV49(A,B)	BSV 46, 30/30V	BC 636, BC 327, BCY 78...79, 2N2906...07
37937	BSV50E	12V, 0,1A, 800MHz, <20/-ns	-
37938	BSV50F	BSV 50E	-
37939	BSV50G	BSV 50E	-
37940	BSV51	100V, 0,2A, 0,25W, >50MHz	BF 297...299, BFR 86, BSS 38, BSX 21
37941	BSV52	20V, 0,1A, <12/18ns	BSV 65
37942	BSV52R	BSV 52	BSV 65R
37943	BSV56A	35V, Ip<6μA, Iv>4mA	2N2646, 2N4871
37944	BSV56B	BSV 56 A	-
37945	BSV56C	BSV 56 A, Ip<25μA	-
37946	BSV57A,B,C	BSV 56 A,B,C	BSV 56 A,B,C
37947	BSV58A	Ip<1μA, Iv>25μA	2N6028, 2N6120
37948	BSV58B	BSV 58 A, Ip<5μA, Iv>70μA	2N6027, 2N6116, 2N6119, MPU131, MPU231
37949	BSV59	60V, 0,5A, 0,36W, 18/25ns	BSX 49, 2N3301...3302, 2N4014
37950	BSV60	45V, 3A, 0,8W, <500/1000ns	BSS 45, BSX 62...64, 2N4237...4239
37951	BSV64	<600/1200ns	BCX 40, BSS 15, 2N4239, 2N5320
37952	BSV65(A,B)	20V, 0,15A, <20/40ns	BSV 52, 2SC3578
37953	BSV65R(RA,RB)	BSV 52	BSV 52R
37954	BSV68	110V, 0,1A, 0,25W, 95MHz	BF 398, BF 435...437, BSS 68
37955	BSV69	45V, 1A, 0,8W, 25/40ns	BSS 13, BSS 27...29, BSV 77, 2N5189
37956	BSV74	<4/-ns	-
37957	BSV75	ns	-
37958	BSV76	ns	-
37959	BSV77	60V, 1A, 0,8W, 15/40ns	BSS 13, BSS 27, BSV 95, 2N5189
37960	BSV78	40V, Idss>50mA, Up<11V	BFS 74, 2N4856
37961	BSV79	40V, Idss>20mA, Up<7V	BFS 75, 2N4857
37962	BSV80	40V, Idss>10mA, Up<5V	BFS 76, 2N4858
37963	BSV81	30V, 50mA	BFW 96, BSV 22
37964	BSV82	80V, 2A, 1W, 50/250ns	2N6303
37965	BSV83	90V, 1A, 0,8W, <35/-ns	BSW 40, 2N4036
37966	BSV84	120V, 2A, 1W, <250/700ns	BSS 42...43, BSW 67...68, BSX 47
37967	BSV85	50V, 1A, 0,36W, 250MHz	BC 637, BSS 26, BSS 40...41, BSW 26
37968	BSV86	75V, 0,4A, 50/210ns, B>100	BC 639, BSW 63...64, 2N2221A...2222A
37969	BSV87	BSV 86, B>40	BC 639, BSW 63...64, 2N2221A...2222A
37970	BSV88	BSV 86, 60V	BC 637, BSW 61...62, 2N2221...2222
37971	BSV89	25V, 0,1A, 0,36W, <12/18ns	BSS 11...12, BSX 92...93, 2N2368...69
37972	BSV90	BSV 89, 30V	BSS 11...12, BSX 92...93, 2N2369...69
37973	BSV91	BSV 89, 40V	BSS 11...12, BSX 92...93, 2N2368...69
37974	BSV92	BSV 89, 40V	BSS 11...12, BSX 92...93, 2N2368...69
37975	BSV95	80V, 1A, 0,8W, 15/40ns	2N3735
37976	BSV96	B>100	BC 328, BC 636, BCY 77...79, 2N2906...07
37977	BSV97	BSV 96, B>40	BC 328, BC 636, BCY 77...79, 2N2906...07
37978	BSV98	BSV 96, B>30	BC 328, BC 636, BCY 77...79, 2N2906...07
37979	BSV99	30V, 0,2A, 0,25W, <12/-ns	BSS 11...12, BSX 92...93, 2N2368...69

37980	BSW10	90V, 0,8A, 0,6W, 100/350ns	BSS 42...43, BSW 66...68, BSX 46...47
37981	BSW11	25V, 0,03A, <25/50ns	-
37982	BSW12	40V, 0,2A, <40/80ns	-
37983	BSW13	20V, 0,05A, <20/40ns	-
37984	BSW19	35V, 0,1A, 0,3W, <150/800ns	BCY 77...79, 2N4034...35, 2N3905...06
37985	BSW20	BSW 19	BCY 77...79, 2N4034...35, 2N3905...06
37986	BSW21	25V, 0,2A, 0,3W, 200/-ns, B>75	BCY 77...79, 2N2906...07, 2N3905...06
37987	BSW21A	BSW 21, 50V	BCY 77, 2N2906...07, 2N3250...51
37988	BSW22	BSW 21, B>180	BCY 77...79, 2N2906...07, 2N3905...06
37989	BSW22A	BSW 22, 50V	BCY 77, 2N2906...07, 2N3250...51
37990	BSW23	2N2904	2N2904
37991	BSW24	2N2906	2N2906
37992	BSW25	2N2894A	2N2894A
37993	BSW26	50V, 1A, 0,5W, <40/85ns	BSS 26, BSS 40...41
37994	BSW27	60V, 1A, 0,8W, <40/85ns	BSS 14, BSS 27, BSV 95, 2N3735, 2SC1386
37995	BSW28	BSW 27, <50/85ns	BSS 14, BSS 27, BSV 95, 2N3735, 2SC1386
37996	BSW29	BSW 27, 40V	BSS 14, BSS 27...29, BSV 95, 2N3735
37997	BSW30	30V, 0,5A	-
37998	BSW31	30V, 0,5A	-
37999	BSW32	100V, 0,03A, 0,25W	BF 297...299, BSS 38, BSX 21
38000	BSW33	40V, 0,1A, 0,125W, <200/-ns	BC 167, BC 182, BC 237, BC 547
38001	BSW34	BSW 33, 50V	BC 167, BC 182, BC 237, BC 547
38002	BSW35	BSW 33, 60V	BC 174, BC 182, BC 190, BC 546
38003	BSW36	32V, 0,5A, 0,8W, <60/150ns	BSW 23, 2N2904(A)...05(A), 2N3072...73
38004	BSW37	12V, 0,2A, 0,36W, <80/90ns	BSV 21, BSW 25, BSX 29, 2N2894A
38005	BSW38	30V, 0,3A, 0,36W, <15/20ns	BSS 10, BSX 19...20, BSX 28, 2N3261
38006	BSW39	100V, 1A, 0,79W, 50/300ns	BSS 42, BSW 66...68, BSX 46...47, 2SD854
38007	BSW40	100V, 1A, 0,79W, 50/300ns	BSS 17, 2N5322
38008	BSW41(A)	40V, 0,3A, 0,32W, <60/60ns	BSX 48...49, BSY 63, 2N708, 2N4123
38009	BSW42(A,B)	B>75	BSV 59, BSX 49, 2N3301...02, 2N3903...04
38010	BSW42...45(A)K	BSW 42..45(A,B)	BSW 42...45(A,B)
38011	BSW43(A,B)	BSW 42, B>180	BSV 59, BSX 49, 2N3301...02, 2N3903...04
38012	BSW44(A,B)	215/105ns,B>75	BCY 77, BSW 24, 2N3250A...3251A
38013	BSW45(A,B)	BSW 44, B>180	BCY 77, BSW 24, 2N3250A...3251A
38014	BSW49	40V, 1A, 0,6W, <-/50ns	BSW 27...29, BSX 32, BSX 59...61, 2N3252
38015	BSW50	65V, 0,8A, 0,8W, 250MHZ	BSW 27...28, BSX 32, BSX 59...61, 2N3252
38016	BSW51	2N2218	2N2218
38017	BSW52	2N2219	2N2219
38018	BSW53	2N2218A	2N2218A
38019	BSW54	2N2219A	2N2219A
38020	BSW58	40V, 0,5A, 0,125W, <7/18ns	BSS 10, BSX 26, BSX 39, 2N3261
38021	BSW59	30V, 0,5A, 0,125W, <7/21ns	BSS 10, BSX 26, BSX28, BSX 39, 2N3261
38022	BSW60	60V, 0,8A, 0,5W, 250MHZ	BC 337, BC 637, BC 639, 2N2221...22
38023	BSW61	2N2221	2N2221
38024	BSW62	2N2222	2N2222

38025	BSW63	2N2221A	2N2221A
38026	BSW64	2N2222A	2N2222A
38027	BSW65	80V, 1A, 0,7W, 500/1000ns	BC 141, BSS 15, BSS 42...43, BSX 45...47
38028	BSW66(A)	BSW 65, 100V	BC 141, BSS 15, BSS 42...43, BSX 46...47
38029	BSW67(A)	BSW 65, 120V	BSS 42...43, BSV 84, BSX 47
38030	BSW68(A)	BSW 65, 150V	BSS 43, 2SC1860
38031	BSW69	150V, 0,05A, 0,125W, 130MHz	BF 297...299, BFR 87...89, BFT 57...59
38032	BSW70	100V, 0,05A, 0,25W	BF 297...299, BFR 86, BSS 38, BSX 21
38033	BSW72	>150Mhz,B>40	BC 327, BC 636, BCY 79, 2N2906...07
38034	BSW73	BSW 72, B>100	BC 327, BC 636, BCY 79, 2N2906...07
38035	BSW74	BSW 72, 75V	BC 640, 2SA1013, 2SB647
38036	BSW75	BSW 72, 75V, B>100	BC 640, 2SA1013, 2SB647
38037	BSW78	2N2368	2N2368
38038	BSW79	2N2369	2N2369
38039	BSW80	2N2369A	2N2369A
38040	BSW81	2N3012	2N3012
38041	BSW82	>200MHz,B>40	BC 337, BC 635, BCY 59, 2N2221...22
38042	BSW83	BSW 82, B>100	BC 337, BC 635, BCY 59, 2N2221...22
38043	BSW84	BSW 82, 75V	BC 639, 2N3700...01, 2SD667
38044	BSW85	BSW 82, 75V, B>100	BC 639, 2N3700...01, 2SD667
38045	BSW88(A,B)	35V, 0,1A, 0,3W, <150/800ns	BSW 41, BSY 63, 2N708, 2N4123
38046	BSW89(A,B)	BSW 88	BSW 41, BSY 63, 2N708, 2N4123
38047	BSW92	18V, 0,2A, 0,3W, >150MHz	BC 168, BC 183, BC 238, BC 548
38048	BSW93	30V, 1A, 1W, 25/65ns	2N3467...68, 2SA717
38049	BSW95(A)	30V, 50mA	-
38050	BSWP30	25V, 0,5A	-
38051	BSX12(A)	25V, 1A, 0,6W, 10/15ns	BSS 27...29, BSV 69, BSV 77, 2N3426
38052	BSX19	40V, 0,5A, 0,36W, <7/18ns	BSS 10, BSX 26, BSX 39, 2N2368...69(A)
38053	BSX20	40V, 0,5A, 0,36W, <7/21ns	BSS 10, BSX 26, BSX 39, 2N2368...69(A)
38054	BSX21	120V, 0,1A, 0,3W, 120MHz	BF 297...299, BFR 86...89, BSS 38
38055	BSX22	40V, 1,5A, 0,8W, 100MHz	BSW 65...68, BSX 45...47, 2N3107...10
38056	BSX23	BSX 22, 90V	BSW 66...68, BSX 46...47, 2N3107...08
38057	BSX24	32V, 0,1A, 0,3W, 25/400ns	BC 548, BSW 41, BSY 63, 2N708
38058	BSX25	40V, 0,3A, 0,36W, >50MHz	BC 337, BC 635, BCY 59, 2N2221...22
38059	BSX26	40V, 0,5A, 0,36W, 9/15ns	BSS 10, BSX 39, 2N3261
38060	BSX27	15V, 0,15A, 0,3W, <12/12ns	BSS 10...12, BSX 92...93, 2N3011
38061	BSX28	30V, 0,5A, 0,36W, 9/13ns	BSS 10, BSX 26, BSX 39, 2N3261
38062	BSX29	12V, 0,2A, 0,36W, 25/35ns	BSV 21, BSW 25, BSW 37, BSX 36, 2N2894A
38063	BSX30	60V, 0,8A, 0,8W, 22/22ns	BSS 13, BSS 27, BSV 77, 2N5189
38064	BSX31	15V	-
38065	BSX32	65V, 1A, 0,8W, 35/40ns	BSS 13, BSS 27, BSV 77, 2N5189
38066	BSX33	85V, 1A, 0,5W, 120/350ns	BC 639, 2N3700...3701, 2SD667
38067	BSX35	6V, 0,2A, 0,3W, <25/25ns	BSX 29, BSX 36, 2N2894A
38068	BSX36	40V, 0,5A, 0,36W, 17/18ns	BSX 29, BSX 35, 2N2894A
38069	BSX38(A,B)	35V, 0,1A, 0,3W, <150/800ns	BC 548, BCY 59, BSW 41, BSY 63, 2N708

38070	BSX39	45V, 0,5A, 0,36W, 9/15ns	BSS 10, BSX 26, 2N3261
38071	BSX39	45V, 0,2A, <12/18ns	-
38072	BSX40	30V, 0,5A, 0,6W, >100MHz	BC 160...161, BC 303...304, BSV 15...17
38073	BSX41	BSX 40, >150MHz	BC 160...161, BC 303...304, BSV 15...17
38074	BSX44	15V, 0,2A, <20/15ns	BSV 89...92, BSX 27, BSX 92...93, 2N2475
38075	BSX45	80V, 1A, >50MHz, <200/850ns	BSS 42...43, BSW 65...68, 2N3107...10
38076	BSX46	BSX 45, 100V	BSS 42...43, BSW 66...68, 2N3107...08
38077	BSX47	BSX 45, 120V	BSS 42...43, BSW 67...68, 2N3019...20
38078	BSX48	50V, 0,6A, 35/60ns	BSV 59, 2N2221...2222, 2N3301...3302
38079	BSX49	BSX 48, 60V, 30/50ns	BSV 59, 2N2221...2222, 2N3301...3302
38080	BSX50	120V, 1A, >50MHz, <200/850ns	BSS 42...43, BSW 67...68, 2N3019...20
38081	BSX51	B>75	BSW 41, BSY 62...63, 2N706A, 2N708
38082	BSX51A	BSX 51, 50V	BSV 59, 2N3301...3302, 2N3903...3904
38083	BSX51B	BSX 51, 60V	BSV 59, 2N3301...3302, 2N3903...3904
38084	BSX52	BSX 51, B>180	BSW 41, BSY 62...63, 2N706A, 2N708
38085	BSX52A	BSX 51, 50V, B>180	BSV 59, 2N3301...3302, 2N3903...3904
38086	BSX52B	BSX 51, 60V, B>180	BSV 59, 2N3301...3302, 2N3903...3904
38087	BSX53(A,B)	35V, 0,1A, 0,13W, <150/800ns	BC 548, BCY 59, BSW 41, BSY 62...63
38088	BSX54(A,B)	BSX 53, 50V	BC 548, BCY 59, BSW 41, BSY 62...63
38089	BSX59	70/45V, 1A, 0,8W, 17/45ns	BSS 27, BSV 95, 2N3735, 2SC1386
38090	BSX60	BSX 59, 70/30V, 17/58ns	BSS 27, BSV 95, 2N3735, 2SC1386
38091	BSX61	BSX 59, 18/70ns	BSS 27, BSV 95, 2N3735, 2SC1386
38092	BSX62	60V, 3A, 0,8W, <300/1500ns	BSS 45, 2N4238...39, 2N5336...39, 2SC2214
38093	BSX63	BSX 62, 80V	BSS 45, 2N4238...39, 2N5336...39, 2SC2214
38094	BSX64	BSX 62, 100V	2N4239, 2N5338...39, 2SC2214
38095	BSX66	30V, 0,1A, <200/400ns, B>40	BC 548, BCY 58...59, BSY 62...63, 2N708
38096	BSX67	BSX 66, B>60	BC 548, BCY 58...59, BSY 62...63, 2N708
38097	BSX68	30/15V, 0,1A, <200/400ns, B>30	BC 548, BCY 58...59, BSY 62...63, 2N708
38098	BSX69	BSX 68, 30/20V, B>60	BC 548, BCY 58...59, BSY 62...63, 2N708
38099	BSX70	B>40	BC 639, BSW 63...64, 2N2221A...22A
38100	BSX71	BSX 70, B>100	BC 639, BSW 63...64, 2N2221A...22A
38101	BSX72	40V, 1A, 0,7W, 25/150ns	BC 140...141, BSW 27...29, 2N3252...53
38102	BSX73	60V, 0,8A, 0,8W, 25/-ns, B>40	BSS 13, BSS 27, BSV 77, 2N5189, 2SC1386
38103	BSX74	BSX 73, B>100	BSS 13, BSS 27, BSV 77, 2N5189, 2SC1386
38104	BSX75	40V, 0,8A, 0,43W, 25/150ns	BC 635, BSW 61...64, 2N2221(A)...22(A)
38105	BSX76	20V, 0,1A, 0,3W, <30/-ns, B>35	BC 548, BSW 41, BSY 62...63, 2N706A
38106	BSX77	BSX 76, 40V, B>40	BC 547, BSW 41, BSY 63, 2N708, 2N4123
38107	BSX78	BSX 76, 40V, B>80	BC 547, BSW 41, BSY 63, 2N708, 2N4123
38108	BSX79(A,B)	50V, 0,1A, 0,375W, <150/800ns	BC 547, BCY 59, 2N3903...3904
38109	BSX80	35V, 0,23A, 0,15W, <40/80ns	BSW 41, BSY 63, 2N708, 2N4123
38110	BSX81(A,B)	35V, 0,1A, 0,3W, <150/800ns	BC 548, BSW 41, BSY 63, 2N708, 2N4123
38111	BSX82	30V, 50mA	BFX 63
38112	BSX83	30V, <250/-ns	-
38113	BSX84	30V, <250/-ns	-
38114	BSX87	40V, 0,5A, 0,36W, 25/25ns	BSS 10, BSX 26, BSX 39, 2N3261

38115	BSX87A	BSX 87, 9/15ns	BSS 10, BSX 26, BSX 39, 2N3261
38116	BSX88	40V, 0,5A, 0,36W, <40/75ns	BSS 10, BSX 26, BSX 39, 2N3261
38117	BSX88A	BSX 88, <30/70ns	BSS 10, BSX 26, BSX 39, 2N3261
38118	BSX89	25V, 0,5A, 0,3W, <40/75ns	BSS 10, BSX 26, BSX 39, 2N914, 2N3261
38119	BSX90	B>20	BSS 10...12, BSX 19...20, 2N2368...69
38120	BSX91	BSX 90, B>40	BSS 10...12, BSX 19...20, 2N2368...69
38121	BSX92	B>20	BSS 10...12, BSX 19...20, 2N2368...69
38122	BSX93	BSX 92, B>40	BSS 10...12, BSX 19...20, 2N2368...69
38123	BSX94	6V, 0,3W, <15/-ns	BSX 36
38124	BSX94A	60V, 0,4W, 400MHz	BSV 59, BSX 49, 2N3301...3302
38125	BSX95	B>40	BSW 53...54, BSX 59...61, 2N2218A...19A
38126	BSX96	BSX 95, B>100	BSW 53...54, BSX 59...61, 2N2218A...19A
38127	BSX97	40V, 0,5A, 0,4W, <30/-ns	BSV 59, BSX 48...49, BSX 87...88, 2N914
38128	BSX98	25V, 0,2A, 0,25W, <40/-ns	BSW 41, BSY 62...63, 2N706A, 2N4124
38129	BSX99	25V, 0,2A, 0,5W, <50/-ns	BSW 41, BSY 62...63, 2N706A, 2N4124
38130	BSY10	60V, 0,05A, 0,3W, 17,7/110ns	BSW 51...54, 2N2218...19, 2N3299...3300
38131	BSY11	BSY 10, 45V	BSW 51...54, 2N2218...19, 2N3299...3300
38132	BSY17	20V, 0,2A, 0,35W, 7/25ns, B>20	BSS 10...12, BSX 19...20, 2N2368...69
38133	BSY18	BSY 17, B>40	BSS 10...12, BSX 19...20, 2N2368...69
38134	BSY19	40V, 0,2A, 0,32W, <40/70ns	BSW 41, BSY 63, 2N708, 2N4123
38135	BSY20	25V, 0,05A, 0,3W, <40/75ns	BSW 41, BSY 62...63, 2N706B, 2N4123
38136	BSY21	2N914	2N914
38137	BSY22	2N916	2N916
38138	BSY23	2N834	2N834
38139	BSY24	B>15	BSW 51...54, 2N3299...3300, 2N2218...2219
38140	BSY25	BSY 24, 16/325ns, B>40	BSW 51...54, 2N3299...3300, 2N2218...2219
38141	BSY26	20V, 0,1A, 0,3W, 20/31ns, B>15	BSV 89...92, BSX 92...93, 2N3011
38142	BSY27	BSY 26, 19/35ns, B>25	BSV 89...92, BSX 92...93, 2N3011
38143	BSY28	15V, 0,1A, 0,3W, 14/22ns, B>20	BSV 89...92, BSX 44, BSX 92...93, 2N3011
38144	BSY29	BSX 28, 12/20ns, B>40	BSV 89...92, BSX 44, BSX 92...93, 2N3011
38145	BSY30	B>20	BSW 41, BSY 62...63, 2N706A, 2N4123
38146	BSY31	BSY 30, <180/-ns, B>30	BSW 41, BSY 62...63, 2N706A, 2N4123
38147	BSY34	60V, 0,6A, 0,8W, 30/50ns	BSS 27, BSV 77, BSV 95, 2SC1385...86
38148	BSY38(A)	2N743	2N743
38149	BSY39(A)	2N744	2N744
38150	BSY40	B>20	2N3250...51, 2N3905...06, 2N4125...26
38151	BSY41	BSY 40, B>50	2N3250...51, 2N3905...06, 2N4125...26
38152	BSY44	2N1613	2N1613
38153	BSY45	2N1893	2N1893
38154	BSY46	2N2193	2N2193
38155	BSY48	50V, 0,6A, 0,4W, <65/-ns	BSV 59, BSX 48, 2N2221...22, 2N3301...02
38156	BSY49	60V, 0,6A, 0,4W, <50/-ns	BSV 59, BSX 49, 2N2221...22, 2N3301...02
38157	BSY51	B>40	BC 140...141, BC 300...302, 2N697
38158	BSY52	BSY 51, B>100	BC 140...141, BC 300...302, 2N1420
38159	BSY53	B>40	BC 140...141, BC 300...301, 2N1613



38160	BSY54	BSY 53, B>100	BC 140...141, BC 300...301, 2N1711
38161	BSY55	B>40	BC 300, BSW 67...68, BSX 47, 2N1893
38162	BSY56	BSY 55, B>100	BC 300, BSW 67...68, BSX 47, 2N1893
38163	BSY58	50V, 0,6A, 0,8W, 35/65ns	BSS 27...29, BSV 77, 2N3724A, 2SC1386
38164	BSY59	30V, 0,8A, 0,28W, <500/850ns	BC 327...328, BC 636, 2N2906...2907
38165	BSY61(Y)	25V, 0,05..0,2A, 0,2W, <40/75ns	BSW 41, BSY 62...63, 2N706A, 2N4124
38166	BSY62(A,B)	25V, 0,2A, 0,35W, <40/75ns	BSW 41, 2N706A, 2N708, 2N4123...24
38167	BSY63	40V, 0,2A, 0,35W, <40/75ns	BSW 41, 2N708, 2N3903...04, 2N4123
38168	BSY65	15V, 0,1A, 0,3W, 200MHz	BC 548, BCY 58...59, BSW 41, 2N706A
38169	BSY68	120V, 0,05A, 0,6W, >20MHz	BF 257...259, BF 657...659, 2N5058...5059
38170	BSY70	2N706	2N706
38171	BSY71	2N1711	2N1711
38172	BSY72	25V, 0,03A, 0,3W, 170MHz	BC 169, BC 184, BC 239, BC 549
38173	BSY73	25V, 0,1A, 0,3W, 145MHz	BC 168, BC 183, BC 238, BC 548
38174	BSY74	25V, 0,1A, 0,3W, 170MHz	BC 168, BC 183, BC 238, BC 548
38175	BSY75	40V, 0,25A, 0,3W, 145MHz	BC 167, BC 182, BC 237, BC 547
38176	BSY76	BSY 75, 170MHz	BC 167, BC 182, BC 237, BC 547
38177	BSY77	BSY 75, 80V	BC 546, 2SC2240, 2SC2459, 2SC3445
38178	BSY78	BSY 75, 80V, 170MHz	BC 546, 2SC2240, 2SC2459, 2SC3445
38179	BSY79	120V, 0,03A, 0,3W, 100MHz	BF 297...299, BF 422, BSS 38, BSX 21
38180	BSY80	25V, 0,1A, 0,3W, 210MHz	BC 168, BC 183, BC 238, BC 548
38181	BSY81	40V, 1A, 0,9W, 100MHz, B>40	BC 140...141, BSW 65...68, BSX 45...47
38182	BSY82	BSY 81, 120MHz, B>100	BC 140...141, BSW 65...68, BSX 45...47
38183	BSY83	BSY 81, 80V	BC 140...141, BSW 65...68, BSX 45...47
38184	BSY84	BSY 81, 80V, 120MHz, B>100	BC 140...141, BSW 65...68, BSX 45...47
38185	BSY85	BSY 81, 120V, 110MHz	BSS 42...43, BSW 67...68, BSX 47, 2N2102
38186	BSY86	BSY 81, 120V, 130MHz, B>100	BSS 42...43, BSW 67...68, BSX 47, 2N2102
38187	BSY87	B>40	BC 141, BC 300, BSW 66...68, BSX 46...47
38188	BSY88	BSY 87, 145MHz, B>100	BC 141, BC 300, BSW 66...68, BSX 46...47
38189	BSY89	25V, 0,1A, 0,3W	-
38190	BSY90	60V, 0,5A, 0,8W, 170MHz	BC 140...141, BC 300...302, 2N2218...19
38191	BSY91	40V, 0,3A, 0,8W, >50MHz	BC 140...141, BC 300...302, 2N2218...19
38192	BSY92	BSY 91, 60V	BC 140...141, BC 300...302, 2N2218...19
38193	BSY93	BSY 91, 60V, 0,36W	BC 337, BC 637, BSV 59, 2N2221...22
38194	BSY95(A)	20V, 0,1A, 0,3W, >200MHz	BSW 42, BSY 62...63, 2N706A, 2N4124
38195	BSYP62	25V, 0,2A, 0,36W, 200MHz	-
38196	BSYP63	40V, 0,2A, 0,36W, 300MHz	-
38197	BT	P4 SMA-33A	P4 SMA-33A
38198	BT	2SC4069	2SC4069
38199	BT	BCW 61RE	BCW 61RE
38200	BT	2SB1048	2SB1048
38201	BT1	BSP 15	BSP 15
38202	BT1	BST 15	BST 15
38203	BT100A/...R	Igt/Ih<10/<15mA	TAG 631..., TAG 632..., TAG 621...
38204	BT101/300..500R	300..500V, 15A, Igt<10	-



38205	BT102/..R	BT 101/..R, Igt<50mA	BTW 42/...
38206	BT103	Igt<100mA, <1μs	-
38207	BT104	Igt<100mA, <1μs	-
38208	BT105	Igt<100mA, <1μs	-
38209	BT106	Igt/Ih<20/<25mA	-
38210	BT106A...D	100..400V, 4A, Igt/Ih<0,2/<3mA	C 106 A, 2N6236...6241, TIC 106...
38211	BT107	500V, 6,5A(Tc60°C), Igt<10mA	-
38212	BT108	500V, 6,5A(Tc60°C), Igt<50mA	BTW 42/600
38213	BT109	Igt/Ih<10/<50mA	-
38214	BT112/750R	750V, 5A, Igt<50mA, <2,4μs	S 3703 SF, TU 3F 800H, TD 3F 800 H
38215	BT113/700R	700V, 5A, Igt<50mA, <4,2μs	S 3702 S, S 6080 C, TD 3F 800 R
38216	BT117	750V, 3,2A(Tc60°C), <2,4μs	BStC12 50, 17088
38217	BT118	750V, 3,2A(Tc60°C), <4,2μs	BT 154, BStCC02 53R, 17089
38218	BT119	750V, 3A, <2,4μs	S 3703, TU 3F 800 H, TD 3F 800 H
38219	BT120	<4,5μs	TD 3F 800 R, TD 4F 800 R,
38220	BT121	500V, 2,8A, <2,4μs	S 3705, S 3703, TU 3F500H, TD 3F500H
38221	BT122	<2,4μs	BSt C09 30T92, BStE04...T, TD 3F 500 H
38222	BT123	Igt/Ih<35/<50mA	TAG 257-500
38223	BT124	Igt/Ih<15/<25mA	-
38224	BT125/700R	700V, 5A, Igt<40mA, <4,5μs	S 3702, S 6080 C, TD 3F 700 R
38225	BT126/750R	750V, 5A, Igt<40mA, <2,4μs	S 3703, TU 3F 800 H, TD 3F 800 H
38226	BT127/...(R)	Igt/Ih<40/<50mA, <10μs	TAG 670S-..., TAG 675S-...
38227	BT128/700R	700V, 5A, Igt<40mA, <4,5μs	S 6087 A, BSt CC01 46R, TD 3F 800 R
38228	BT129/..R	600..750V, 5A, <2,4μs	BStCC0140...0153H, S 6087B, TD 3F...H
38229	BT132	Igt<50mA	BTW 42/...
38230	BT133	Igt<50mA	BTW 42/...
38231	BT134/..	Igt/Ih<70/<15	-
38232	BT134/..B	BT 134/..., Igt/Ih<10/<10mA	-
38233	BT134/..E	BT 134/..., Igt/Ih<25/<15mA	-
38234	BT134/..F	BT 134/..., Igt/Ih<70/<15mA	-
38235	BT134/..G	BT 134/..., Igt/Ih<100/<30mA	-
38236	BT134W/..	Igt/Ih<35/<15	-
38237	BT136/...	Igt/Ih<70/<30mA	TXC10H..., TAG 230-..., TAG 231-...
38238	BT136/...D	Igt/Ih<10/<15mA	TXC18G..., TAG 232-..., TAG 221-...
38239	BT136/...E	Igt/Ih<25/<20mA	TAG 231-..., TAG 220-..., TAG 225-...
38240	BT136/...F	Igt/Ih<70/<30mA	TXC10H..., TAG 230-..., TAG 231-...
38241	BT136/...G	Igt/Ih<100/<45mA	TXC10H..., TAG 230-..., TAG 224-...
38242	BT137/...	Igt/Ih<70/<45mA	TAG 224-..., MAC 222A-..., TXD10H...
38243	BT137/...D	Igt/Ih<10/<20mA	TAG 226-..., MAC 228A-...
38244	BT137/...E	Igt/Ih<25/<35mA	TAG 225-..., TAG 252-..., TAG 255-...
38245	BT137/...F	Igt/Ih<70/<45mA	TAG 224-..., MAC 222A-..., TXD10H...
38246	BT137/...G	Igt/Ih<100/<60mA	TAG 224-..., MAC 222A-..., TXD10H...
38247	BT138/...	Igt/Ih<70/<60mA	TAG 255-..., TAG 256-..., TXD10H...P
38248	BT138/...E	Igt/Ih<25/<40mA	TAG 257-...
38249	BT138/...F	Igt/Ih<70/<60mA	TAG 255-..., TAG 256-..., TXD10H...P

38250	BT138/...G	Igt/Ih<100/<90mA	TAG 255-..., TAG 256-..., TXD10H...P
38251	BT139/...	Igt/Ih<70/<60mA	MAC 15A-..., TAG 280-..., TAG 281-...
38252	BT139/...E	Igt/Ih<25/<40mA	-
38253	BT139/...F	Igt/Ih<70/<60mA	MAC 15A-..., TAG 280-..., TAG 281-...
38254	BT139/...G	Igt/Ih<100/<90mA	MAC 15A-..., TAG 280-..., TAG 281-...
38255	BT143/400R	400V, 3,2A(Tc85°C), Igt<40mA	BStCC 0126T91...0153T91, BT 127/750 R
38256	BT145/..R	Igt/Ih<35/<60mA	2N6400...6405, BStD10...M, T9,5N...,CS 15...
38257	BT146	500V, 15A, Igt<35mA	2N6404, 2N6405, T9,5N..., BT 152/...
38258	BT148	500V, 6,5A(Tc60°C), Igt<35mA	2N6404, 2N6405, TIC 122D...E
38259	BT148W/..	400..600V, 0,6A, Igt/Ih<0,2/<6	-
38260	BT149A...M	50µs	TAG 59..., MCR 606-2...8, 2N6681...6685
38261	BT150	Igt/Ih<0,2/<6mA	TIC106E, TAG623-500, TAG628-500, S4060E
38262	BT151/...R	Igt/Ih<15/<20mA, 2µs	-
38263	BT152/..R	Igt/Ih<32/<60mA, 35µs	2N6504...6509
38264	BT153	500V, 6A, Igt/Ih<40/<100mA	BT 154
38265	BT154	750V, 8A, Igt<40mA, <2,4µs	-
38266	BT155/..RK	<6µs	-
38267	BT155/..RN	<9µs	-
38268	BT155/..RP	<12µs	-
38269	BT157/..R	2,2A(Tc80°C),Igt<200mA	BTW 58/1300...1500
38270	BT158/..	Igt/Ih<40/<30mA	T 2806..., T 2856..., BT 162/...
38271	BT162/..	Igt/Ih<40/<30mA	T 6006..., TAG 257-...
38272	BT169B..G	Igt/Ih<0,2/<5mA	BRX 47...49, BRY 55S/200...800
38273	BT2	BSP 16	BSP 16
38274	BT2	BST 16	BST 16
38275	BT500		-
38276	BT500A	BT 500	-
38277	BTA04-...A	Igt/Ih<25/<25mA	TAG 421..., TAG 231..., TAG 220...
38278	BTA04-...D	Igt/Ih<10/<15mA	TXC 18H..., TIC 216..., TAG 232...,
38279	BTA04-...GP	Igt/Ih<75/<13mA	TXC 18H..., TIC 216..., TAG 232...,
38280	BTA04-...S	Igt/Ih<10/<25mA	TAG 232..., TAG 231..., TXC 18G...,
38281	BTA04-...T	Igt/Ih<5/<15mA	TAG 233..., TXC 18D..., TAG 222-...,
38282	BTA06-...A	Igt/Ih<25/<25mA	TAG 421..., TAG 220..., TAG 225...
38283	BTA06-...B	6A(Tc75°),Igt/Ih<100/<50mA	TAG 420..., TAG 224..., TXC 10H...M
38284	BTA06-...C	Igt/Ih<50/<25mA	TAG 420..., TAG 224..., TXC 10H...M
38285	BTA06-...D	Igt/Ih<10/<15mA	TAG 221..., TXC 18G...M, TAG 226...
38286	BTA06-...GP	Igt/Ih<75/<13mA	MAC 216..., T 2801..., BS 7-...A, SC 141.
38287	BTA06-...S	Igt/Ih<10/<25mA	TAG 221..., TXC 18G...M, TAG 226...
38288	BTA06-...T	Igt/Ih<5/<15mA	TAG 222..., TXC 18D...M, TAG 227...
38289	..AW,BW,CW	BTA 06-..A,B,C	-
38290	BTA06-..SW,TW	BTA 06-..S,T	-
38291	BTA08-...A	Igt/Ih<25/<25mA	TAG 426..., TAG 452..., TAG 457...
38292	BTA08-...B	8A(Tc75°),Igt/Ih<100/<50mA	TAG 425..., TAG 451..., TAG 456...
38293	BTA08-...C	Igt/Ih<50/<25mA	TAG 425..., TAG 451..., TAG 456...
38294	BTA08-...S	Igt/Ih<10/<25mA	TAG 226..., MAC 228A-...

38295	..AW,BW,CW	BTA 08-..A,B,C	-
38296	BTA08-..SW,TW	BTA 08-..S, Igt/Ih<5/<15mA	-
38297	BTA10-...B	0/<50mA	TAG 456..., TAG 480..., TAG 481...
38298	BTA10-...C	10A(Tc75°),Igt/Ih<50/<25mA	TAG 456..., TAG 480..., TAG 481...
38299	..AW,BW,CW	BTA 10-..	-
38300	BTA12-...B	0/<50mA	TAG 480..., TAG 481...
38301	BTA12-...C	12A(Tc75°),Igt/Ih<50/<25mA	TAG 480..., TAG 481...
38302	..AW,BW,CW	BTA 12-..	-
38303	BTA13-...B	Igt/Ih<50/<50mA	TAG 480..., TAG 481...
38304	BTA140/..	25A(Tc89°),Igt/Ih<70/<30mA	TXE 10..., MAC 223-..., MAC 223A-...
38305	BTA16-...B	0/<50mA	MAC 15A..., BT 139/..., TAG 280...
38306	BTA16-...C	16A(Tc75°),Igt/Ih<50/<25mA	MAC 15A..., BT 139/..., TAG 280...
38307	..AW,BW,CW	BTA 16-..	-
38308	BTA20-..AW	400..800V, 20A, Igt<75mA	-
38309	BTA20-..BW	BTA 20-..AW, Igt/Ih<50/<75mA	-
38310	BTA20-..CW	BTA 20-..AW, Igt/Ih<35/<50mA	-
38311	BTA20C	Igt/Ih<80/<100mA	TXC 10L40M, TW7N400, TIC 226C
38312	BTA20D	BTA 20C, 400V	TXC 10L40M, TW7N400, TIC226D
38313	BTA20E	BTA 20C, 500V	TXC 10L50M, TW7N600, TIC226E
38314	BTA20M	BTA 20C, 600V	TXC 10L60M, TW7N600, TIC226M
38315	BTA20N	BTA 20C, 800V	TXC 10L80M, TW7N800, TIC226N
38316	BTA21C	Igt/Ih<35/<100mA	TAG 225-..., TAG 257-...
38317	BTA21D	BTA 21C, 400V	TAG 225-..., TAG 257-...
38318	BTA21E	BTA 21C, 500V	TAG 225-..., TAG 257-...
38319	BTA21M	BTA 21C, 600V	TAG 225-..., TAG 257-...
38320	BTA21N	BTA 21C, 800V	TAG 225-..., TAG 257-...
38321	BTA22B	Igt/Ih<60/<30mA	TAG 250-..., TAG 251-..., TXD 10H40M
38322	BTA22C	BTA 22B, 300V	TAG 250-..., TAG 251-..., TXD 10H40M
38323	BTA22D	BTA 22B, 400V	TAG 250-..., TAG 251-..., TXD 10H40M
38324	BTA22E	BTA 22B, 500V	TAG 250-..., TAG 251-..., TXD 10H50M
38325	BTA22M	BTA 22B, 600V	TAG 250-..., TAG 251-..., TXD 10H60M
38326	BTA22N	BTA 22B, 800V	TAG 250-..., TAG 251-..., TXD 10H80M
38327	BTA23B	Igt/Ih<60/<30mA	TAG 255-..., TAG 256-..., BT 138/...
38328	BTA23C	BTA 23B, 300V	TAG 255-..., TAG 256-..., BT 138/...
38329	BTA23D	BTA 23B, 400V	TAG 255-..., TAG 256-..., BT 138/...
38330	BTA23E	BTA 23B, 500V	TAG 255-..., TAG 256-..., BT 138/...
38331	BTA23M	BTA 23B, 600V	TAG 255-..., TAG 256-..., BT 138/...
38332	BTA23N	BTA 23B, 800V	TAG 255-..., TAG 256-..., BT 138/...
38333	BTA25-...A	Igt/Ih<150/<100mA	BTW 41/...
38334	BTA25-...B	25A(Tc65°),Igt/Ih<80/<80mA	MAC 525A...,TAG 725-..., TAG 726-...
38335	BTA26-...A	Igt/Ih<150/<100mA	BTA 41-...
38336	BTA26-...B	Igt/Ih<100/<80mA	BTA 41-...
38337	..AW,BW,CW	BTA 26-..	-
38338	BTA40-...A	Igt/Ih<150/<100mA	BTW 41/...
38339	BTA40-...B	Igt/Ih<80/<80mA	MAC 50A-...

38340	BTA41-...A	Igt/Ih<150/<100mA	-
38341	BTA41-...B	Igt/Ih<100/<80mA	-
38342	BTB04-...A	BTA 04-..A	T 2506..., T 2806..., TAG 220...
38343	BTB04-...D	BTA 04-..D	TXC 18H..., TIC 216..., TXC 18H...M
38344	BTB04-...S	BTA 04-..S	TXC 18G..., TAG 232..., TAG 221...
38345	BTB04-...T	BTA 04-..T	TXC 18D..., TAG 233..., TAG 222...
38346	BTB06-...A	BTA 06-..A	T 2506..., T 2806..., T 6006...
38347	BTB06-...B	BTA 06-..B	TXC 10K/L...M, TW7N..., MAC 222-...
38348	BTB06-...C	BTA 06-..C	TXC 10K/L...M, TW7N..., MAC 222-...
38349	BTB06-...D	BTA 06-..D	TIC 216..., TXC 18H...M
38350	BTB06-...GP	BTA 06-..GP	TXC 10K/L...M, TW7N..., MAC 222-...
38351	BTB06-...S	BTA 06-..S	TXC 18G...M, TAG 221..., TAG 226...
38352	BTB06-...T	BTA 06-..T	TAG 222..., TXC 18D...M, TAG 227...
38353	..AW,BW,CW	BTA 06-..AW,BW,CW	-
38354	BTB06-..SW,TW	BTA 06-..SW,TW	-
38355	BTB08-...A	BTA 08-..A	T 2806..., T 6006...
38356	BTB08-...B	BTA 08-..B	MAC 222-..., TIC 226..., T 2802...
38357	BTB08-...C	BTA 08-..C	MAC 222-..., TIC 226..., T 2802...
38358	BTB08-...GP	BTA 08-..GP	TAG 224-..., MAC 222A-..., BT 137/...
38359	BTB08-...S	BTA 08-..S	TAG 226..., MAC 228A-...
38360	..AW,BW,CW	BTA 08-..AW,BW,CW	-
38361	BTB08-..SW,TW	BTA 08-..SW,TW	-
38362	BTB10-...B	BTA 10-..B	TW9N..., TXD 10K/L...M, TIC 236...
38363	BTB10-...C	BTA 10-..C	TAG 250-..., TAG 251-..., TXD 10H...M
38364	..AW,BW,CW	BTA 10-..AW,BW,CW	-
38365	BTB12-...B	BTA 12-..B	TIC 236..., TW11N..., 2N6342...6345A
38366	BTB12-...C	BTA 12-..C	TIC 236..., TW11N..., 2N6342...6345A
38367	..AW,BW,CW	BTA 12-..AW,BW,CW	-
38368	BTB13-...B	BTA 13-..B	TIC 236..., TW11N..., 2N6342...6345A
38369	BTB15-...B	15A(Tc75°),Igt/Ih<75/<50mA	MAC 15-..., TIC 246..., T 6001...
38370	BTB16-...B	BTA 16-..B	MAC 15-..., TIC 246..., T 6001...
38371	BTB16-...C	BTA 16-..C	MAC 15-..., TIC 246..., T 6001...
38372	..AW,BW,CW	BTA 16-..AW,BW,CW	-
38373	BTB19-...B	0/<50mA	TXE 10..., MAC 223-..., MAC 223A-...
38374	..AW,BW,CW	BTA 20-..AW,BW,CW	-
38375	BTB24-...B	BTB 19-..B, 25A(Tc75°)	TXE 10..., MAC 223-..., MAC 223A-...
38376	BTB25-...A	BTA 25-..A	BTW 41/...
38377	BTB25-...B	BTA 25-..B	MAC 525-..., MAC 25-..., MAC 50-...
38378	BTB26-...A	BTA 26-..A	-
38379	BTB26-...B	BTA 26-..B	BTB 41-...
38380	BTB40-...A	BTA 40-..A	BTW 41/...
38381	BTB40-...B	BTA 40-..B	MAC 50-..., TAG 740-..., TAG 741-...
38382	BTB41-...A	BTA 41-..A	-
38383	BTB41-...B	BTA 41-..B	-
38384	BTD0105	Igt/Ih<25/<25mA	T 2306..., TAG 200-..., T 2303...

38385	BTD0110	Igt/Ih<25/<25mA	T 2306..., TAG 200-..., T 2303...
38386	BTD0120	Igt/Ih<25/<25mA	T 2306..., TAG 200-..., T 2303...
38387	BTD0140	Igt/Ih<25/<25mA	T 2306..., TAG 200-..., T 2303...
38388	BTD0160	Igt/Ih<25/<25mA	T 2306..., TAG 200-..., T 2303...
38389	BTD02..-2	BTD 02..-1, Igt/Ih6/<10mA	T 2301..., TAG 204-..., TAG 204A-...
38390	BTD02..-3	BTD 02..-1, Igt/Ih3/<10mA	TAG 206-..., TAG 207-...
38391	BTD0205-1	Igt/Ih10/<10mA	TAG 201..., T 2302..., TAG 202-...
38392	BTD0210-1	Igt/Ih10/<10mA	TAG 201..., T 2302..., TAG 202-...
38393	BTD0220-1	Igt/Ih10/<10mA	TAG 201..., T 2302..., TAG 202-...
38394	BTD0240-1	Igt/Ih10/<10mA	TAG 201..., T 2302..., TAG 202-...
38395	BTD03..-1	BTD 03..., Igt/Ih<10/<15mA	TAG 202-..., TAG 203-..., TAG 209-...
38396	BTD03..-2	BTD 03..., Igt/Ih<4/<10mA	TAG 204-..., TAG 205-...
38397	BTD03..-3	BTD 03..., Igt/Ih<3/<5mA	TAG 206-..., TAG 207-...
38398	BTD0305	Igt/Ih<50/<50mA	-
38399	BTD0310	Igt/Ih<50/<50mA	-
38400	BTD0320	Igt/Ih<50/<50mA	-
38401	BTD0340	Igt/Ih<50/<50mA	-
38402	BTD0360	Igt/Ih<50/<50mA	-
38403	BTD0605	Igt/Ih<50/<50mA	-
38404	BTD0610	Igt/Ih<50/<50mA	-
38405	BTD0620	Igt/Ih<50/<50mA	-
38406	BTD0640	Igt/Ih<50/<50mA	-
38407	BTD0660	Igt/Ih<50/<50mA	-
38408	BTD4L..N	Ub26..40V, Ib<0,05mA, Itsm2A	1N5761...62, D3202U,Y
38409	BTE5M	Ub29..37V, Ib<0,05mA, Itsm2A	1N5762, D3202Y
38410	BTL0405	Igt/Ih<25/<25mA	T 2506..., T 2806..., TAG 220-...
38411	BTL0410	Igt/Ih<25/<25mA	T 2506..., T 2806..., TAG 220-...
38412	BTL0420	Igt/Ih<25/<25mA	T 2506..., T 2806..., TAG 220-...
38413	BTL0440	Igt/Ih<25/<25mA	T 2506..., T 2806..., TAG 220-...
38414	BTL0460	Igt/Ih<25/<25mA	T 2506..., T 2806..., TAG 220-...
38415	BTL0605	Igt/Ih<50/<50mA	TW7N..., MAC 222-..., TIC 226..., T 2802...
38416	BTL0610	Igt/Ih<50/<50mA	TW7N..., MAC 222-..., TIC 226..., T 2802...
38417	BTL0620	Igt/Ih<50/<50mA	TW7N..., MAC 222-..., TIC 226..., T 2802...
38418	BTL0640	Igt/Ih<50/<50mA	TW7N..., MAC 222-..., TIC 226..., T 2802...
38419	BTL0660	Igt/Ih<50/<50mA	TW7N..., MAC 222-..., TIC 226..., T 2802...
38420	BTL0805	Igt/Ih<50/<50mA	TIC 226..., T 2802..., TXD 10K/L...
38421	BTL0810	Igt/Ih<50/<50mA	TIC 226..., T 2802..., TXD 10K/L...
38422	BTL0820	Igt/Ih<50/<50mA	TIC 226..., T 2802..., TXD 10K/L...
38423	BTL0840	Igt/Ih<50/<50mA	TIC 226..., T 2802..., TXD 10K/L...
38424	BTL0860	Igt/Ih<50/<50mA	TIC 226..., T 2802..., TXD 10K/L...
38425	BTL1005	Igt/Ih<100/<100mA	TW9N..., TXD 10K/L..., TIC 236...
38426	BTL1010	Igt/Ih<100/<100mA	TW9N..., TXD 10K/L..., TIC 236...
38427	BTL1020	Igt/Ih<100/<100mA	TW9N..., TXD 10K/L..., TIC 236...
38428	BTL1040	Igt/Ih<100/<100mA	TW9N..., TXD 10K/L..., TIC 236...
38429	BTL1060	Igt/Ih<100/<100mA	TW9N..., TXD 10K/L..., TIC 236...

38430	BTL1605	Igt/Ih<100/<100mA	SC 151..., MAC 15-..., TIC 246...
38431	BTL1610	Igt/Ih<100/<100mA	SC 151..., MAC 15-..., TIC 246...
38432	BTL1620	Igt/Ih<100/<100mA	SC 151..., MAC 15-..., TIC 246...
38433	BTL1640	Igt/Ih<100/<100mA	SC 151..., MAC 15-..., TIC 246...
38434	BTL1660	Igt/Ih<100/<100mA	SC 151..., MAC 15-..., TIC 246...
38435	BTM0405..0460	BTL 0405..0460	BTL 0405...0460
38436	BTM0605..0660	BTL 0605..0660	BTL 0605...0660
38437	BTM1005..1060	BTL 1005..1060	BTL 1005...1060
38438	BTM1605..1660	BTL 1605..1660	BTL 1605...1660
38439	BTR0205	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38440	BTR0205	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38441	BTR0210	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38442	BTR0210	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38443	BTR0220	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38444	BTR0220	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38445	BTR0240	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38446	BTR0240	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38447	BTR0260	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38448	BTR0260	Igt/Ih<50/<25mA	TAG 260-..., TAG 265-..., T 4700...
38449	BTR0305	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38450	BTR0305	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38451	BTR0310	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38452	BTR0310	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38453	BTR0320	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38454	BTR0320	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38455	BTR0340	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38456	BTR0340	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38457	BTR0360	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38458	BTR0360	Igt/Ih<50/<50mA	TAG 260-..., TAG 265-..., T 4700...
38459	BTR0405	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38460	BTR0405	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38461	BTR0410	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38462	BTR0410	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38463	BTR0420	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38464	BTR0420	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38465	BTR0440	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38466	BTR0440	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38467	BTR0460	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38468	BTR0460	Igt/Ih<100/<50mA	TAG 265-..., T 4700...
38469	BTR0505	50V, 15A, Igt/Ih<80/<50mA	T 4700...
38470	BTR0505	50V, 15A, Igt/Ih<80/<50mA	T 4700...
38471	BTR0510	100V, 15A, Igt/Ih<80/<50mA	T 4700...
38472	BTR0510	100V, 15A, Igt/Ih<80/<50mA	T 4700...
38473	BTR0520	200V, 15A, Igt/Ih<80/<50mA	T 4700...
38474	BTR0520	200V, 15A, Igt/Ih<80/<50mA	T 4700...



38475	BTR0530	300V, 15A, Igt/Ih<80/<50mA	T 4700...
38476	BTR0530	300V, 15A, Igt/Ih<80/<50mA	T 4700...
38477	BTR0540	400V, 15A, Igt/Ih<80/<50mA	T 4700...
38478	BTR0540	400V, 15A, Igt/Ih<80/<50mA	T 4700...
38479	BTR0550	500V, 15A, Igt/Ih<80/<50mA	T 4700...
38480	BTR0550	500V, 15A, Igt/Ih<80/<50mA	T 4700...
38481	BTR0560	600V, 15A, Igt/Ih<80/<50mA	T 4700...
38482	BTR0560	600V, 15A, Igt/Ih<80/<50mA	T 4700...
38483	BTR0605..0660	BTL 0605..0660	TAG 260-..., TAG 265-..., T 4700...
38484	BTR0605..0660	BTL 0605..0660	TAG 260-..., TAG 265-..., T 4700...
38485	BTR1005..1060	BTL 1005..1060	TAG 265-..., T 4700...
38486	BTR1005..1060	BTL 1005..1060	TAG 265-..., T 4700...
38487	BTR1605..1660	BTL 1605..1660	T 4700...
38488	BTR1605..1660	BTL 1605..1660	T 4700...
38489	BTR59/..R	Igt<0,5mA	BTS 59/...R
38490	BTR59/..R	Igt<0,5mA	BTS 59/...R
38491	BTS100	50V, 8A, 40W, <0,3Ohm	-
38492	BTS110	100V, 10A, 40W, <0,2Ohm	-
38493	BTS114	50V, 14A, 40W, <0,1Ohm	-
38494	BTS115	50V, 12,5A, 40W, <125mOhm	-
38495	BTS116	50V, 14A, 40W, <0,1Ohm	-
38496	BTS120	100V, 19A, 75W, <0,1Ohm	-
38497	BTS121A	100V, 22A, 75W, <0,1Ohm	-
38498	BTS129	60V, 27A, 75W, <0,05Ohm	-
38499	BTS130	50V, 27A, 75W, <0,05Ohm	-
38500	BTS131	50V, 25A, 75W, <0,06Ohm	-
38501	BTS132	60V, 24A, 75W, <0,065Ohm	-
38502	BTS136	50V, 27A, 75W, <0,05Ohm	-
38503	BTS140A	50V, 39A, 75W	-
38504	BTS240A	50V, 58A, 170W, <18mOhm	-
38505	BTS59/1000R	BTS 59/850R, 1000V	-
38506	BTS59/1000R	BTS 59/850R, 1000V	-
38507	BTS59/1200R	BTS 59/850R, 1200V	-
38508	BTS59/1200R	BTS 59/850R, 1200V	-
38509	BTS59/850R	850V, 15A(Tc85°), Igt<300mA	-
38510	BTS59/850R	850V, 15A(Tc85°), Igt<300mA	-
38511	BTV159/..R	+850..+1200V, 15A, Igt<300mA	-
38512	BTV160/..R	+850..+1200V, 25A, Igt<300mA	-
38513	BTV24/...R	Igt/Ih<100/<200mA	T 35N..., T 45N...
38514	BTV34/..G	BTW 34/..G	-
38515	BTV34/..H	BTW 34/..H	-
38516	BTV58/...R	+600..+1000V, 10A, Igt<200mA	-
38517	BTV59/...R	Igt<300mA	BTV 70/...R
38518	BTV59D/..R	BTW 59/..R	BTW 70D/...R
38519	BTV60/..R	Igt<500mA	-

38520	BTW60D/..R	BTW 60/..R	-
38521	BTW70/..R	Igt<300mA	-
38522	BTW70D/..R	BTW 70/..R	-
38523	BTW10/...	Igt/Ih<50/<25mA	TXC01..., T 4706..., BS7-...A, MAC 216-...
38524	BTW10/...	Igt/Ih<50/<25mA	TXC01..., T 4706..., BS7-...A, MAC 216-...
38525	BTW11/...	Igt/Ih<50/<50mA	TXC 01..., TAG 262-..., TAG 265-...
38526	BTW11/...	Igt/Ih<50/<50mA	TXC 01..., TAG 262-..., TAG 265-...
38527	BTW12/...	BTW 11/..	BS 6-...B, TW 6N...H, BS 8-...B, TW 10N...H
38528	BTW13/...	BTW 11/..	BS 6-...A, TW 6N...C, BS 8-...A, TW 8N...C
38529	BTW14/...	10A(Tc75°),Igt/Ih<100/<50mA	T 4706..., TAG 265-..., T 4700...
38530	BTW14/...	10A(Tc75°),Igt/Ih<100/<50mA	T 4706..., TAG 265-..., T 4700...
38531	BTW15/...	BTW 14/..	SC 246..., BS 10-...B, TW 10N...H
38532	BTW16/...	BTW 14/..	SC 245..., BS 10-...A, TW 10N...C
38533	BTW17/...	BTW 14/..	SC 245..., BS 10-...A, TW 10N...C
38534	BTW18/...	15A(Tc75°),Igt/Ih<100/<50mA	SC 251..., SC 261..., 2N6157...6159
38535	BTW19/...	BTW 18/..	SC 250..., TXD 98..., TXE 99...
38536	BTW20/...	25A(Tc75°),Igt/Ih<100/<100m	TXE 99..., SC 260..., T 6410...
38537	BTW21/...	BTW 20/..	SC 261..., T 6407..., T 6405...
38538	)	Igt/Ih<150/<200mA	T 51 N...B, T 71 N...B, T 99 N...B
38539	)	Igt/Ih<150/<200mA	T 35 N..., T 45 N...
38540	BTW26/...	14A(Tc50°),Igt/Ih<35/<20mA	MAC 525A-..., MAC 25A-..., TAG 725-...
38541	BTW27/...R	Igt/Ih<50/<50mA	TAG 675-..., TAG 676-..., BStD 10...
38542	BTW27S,SA/...	Igt/Ih<50/25mA, <6µs	TAG 670S-..., T3S-..., TAG 675S-...
38543	BTW28(A)/...R	Igt/Ih<150/45mA	BTW 63/..., CS 15,9-..., TAG 35S-...
38544	)	Igt/Ih<0,2/0,2A, <6µs	BTW 31/...
38545	BTW30/...RS	BTW 30/...(RM,RU), <15µS	BTW 31/...
38546	RW	Igt/Ih<0,2/0,2A, <12µs	-
38547	)	55A,Igt/Ih<0,15/0,2A,<25µs	T 31F..., CSF 34-...
38548	)	2A,<25µs	CS 38-..., CS 78-..., CS 79-..., T 71F...B
38549	U)	Igt/Ih<0,2/<0,2A	-
38550	BTW35	500V, 15A, Igt<10mA, <50µs	-
38551	BTW37(V)/...	Igt/Ih<0,1/<0,1A	BTW 43/...
38552	BTW38/...R	Igt/Ih<50/<75mA	BTW 42/..., BStC03..., CS 5-..., BStD03
38553	BTW39/...	Igt/Ih<80/20mA	BTW45/..., BTW 47/..., CS13-..., T15.1N...
38554	BTW40/...R	Igt/Ih<75/<75mA	BTW 47/...,CS 13-...,T15.1N...,TAG 16N...
38555	BTW42/...R	Igt/Ih<50/<75mA	-
38556	BTW43/...(G,H)	Igt/Ih<200/<100mA	-
38557	BTW44/...(M,U)	Igt/Ih<0,2/<0,2A	-
38558	BTW45/...R	Igt/Ih<75/<75mA	BTW 47/..., CS 13-..., T 15.1N..., CS16...
38559	)	Igt/Ih<100/<200mA	BTW 39/..., BTW 47/...,CS 13...,TAG 16N...
38560	BTW48/...[Tho]	Igt/Ih<60/30mA, 50µs	CS 23-...
38561	BTW48/..[Phi]	BTX 94/..	BTX 94/...
38562	BTW49/...	Igt/Ih<200/75mA, <20µs	BTW 30/..., BTW 31/..., CS 15,9-...
38563	BTW50/...	Igt/Ih<150/50mA	-
38564	BTW52	Igt/Ih<20/25mA, 17µs	BStC0506, TAG 671-100, TAG 676-100

38565	BTW53	BTW 52, 120V	BStC0513, TAG 671-200, TAG 676-200
38566	BTW54	BTW 52, 240V	BStC0526, TAG 671-300, TAG 676-300
38567	BTW55	BTW 52, 480V	BStC0533, TAG 671-500, TAG 676-500
38568	BTW56	BTW 52, 600V	BStC0540, TAG 671-600, TAG 676-600
38569	BTW58/...	Igt<200mA	-
38570	BTW59/...R	Igt<250mA	-
38571	BTW62/...RK	28A,Igt/Ih<0,25/<0,4A,<4μs	-
38572	BTW62/...RN	BTW 62/..RK, <9μs	-
38573	BTW62D/...	BTW 62/..RK	-
38574	BTW63/...RK	Igt/Ih<0,25/<0,4A, 4μs	BTW 28/..., CS 15,9-..., TAG 35 S-...
38575	BTW63/...RN	BTW 63/..RK, 6μs	BTW 28/..., CS 15,9-..., TAG 35 S-...
38576	BTW63/...RP	BTW 63/..RK, 8μs	BTW 28/..., CS 15,9-..., TAG 35 S-...
38577	BTW66/...	Igt/Ih<50/<20mA	BTW 67/...
38578	BTW67/...	Igt/Ih<80/<20mA	-
38579	BTW67/...N	BTW 67/..	-
38580	BTW68/..	Igt/Ih<50/<75mA	BTW 69/...
38581	BTW68/..N	BTW 68/..	BTW 69/...N
38582	BTW68/..N	BTW 68/..	BTW 69/...N
38583	BTW69/..	Igt/Ih<80/<150mA	-
38584	BTW69/..N	BTW 69/..	-
38585	BTW69/..N	BTW 69/..	-
38586	U)	Igt/Ih<100/<200mA	CS 16-..., CS 23-...
38587	BTX0605	Igt/Ih<50/<50mA	SC 245A3, T 4120F, T 4121F, SC 250A3
38588	BTX0610	BTX 0605, 100V	SC 245B3, T 4120E, T 4121E, SC 250B3
38589	BTX0620	BTX 0605, 200V	SC 245A3, T 4120E, T 4221E, SC 250A3
38590	BTX0640	BTX 0605, 400V	SC 245D3, T 4120E, T 4121E, SC 250D3
38591	BTX0660	BTX 0605, 600V	SC 245M3, T 4120M, T 4121M, SC 250M3
38592	BTX1005	Igt/Ih<100/<100mA	SC 245B3, T 4120F, T 4121F, SC 250B3
38593	BTX1010	BTX 1005, 100V	SC 245B3, T 4120E, T 4121E, SC 250B3
38594	BTX1020	BTX 1005, 200V	SC 245B3, T 4120E, T 4121E, SC 250B3
38595	BTX1040	BTX 1005, 400V	SC 245D3, T 4120E, T 4121E, SC 250D3
38596	BTX1060	BTX 1005, 600V	SC 245M3, T 4120M, T 4121M, SC 250M3
38597	BTX12/...R	Igt/Ih<50/<40mA	BTX 13/...R, CS 42-..., CS 50-...
38598	BTX13/...R	Igt/Ih<50/40mA	CS 42-..., CS 50-...
38599	BTX1605	Igt/Ih<100/<100mA	SC 260B3, T 6421F, 2N6163...6165
38600	BTX1610	BTX 1605, 100V	SC 260B3, T 6421B, 2N6163...6165
38601	BTX1620	BTX 1605, 200V	SC 260B3, T 6421B, 2N6163...6165
38602	BTX1640	BTX 1605, 400V	SC 260D3, T 6421D, 2N6164...6165
38603	BTX1660	BTX 1605, 600V	SC 260M3, T 6421M, 2N6165
38604	BTX18/...	100..500V, 1,6A, Igt/Ih<5/5mA	BTX 30/..., T1N..., S 2600..., TAG 612...
38605	BTX20	Igt/Ih<100/<100mA	-
38606	BTX21	BTX 20, 300V	-
38607	BTX22	BTX 20, 400V	-
38608	BTX23	BTX 20, 500V	-
38609	BTX24	BTX 20, 600V	-

38610	BTX25	BTX 20, 700V	-
38611	BTX2505	Igt/Ih<100/<100mA	SC 260B3, T 6421F, 2N6163...6165
38612	BTX2510	BTX 2505, 100V	SC 260B3, T 6421B, 2N6163...6165
38613	BTX2520	BTX 2505, 200V	SC 260B3, T 6421B, 2N6163...6165
38614	BTX2540	BTX 2505, 400V	SC 260D3, T 6421D, 2N6164...6165
38615	BTX2560	BTX 2505, 600V	SC 260M3, T 6421M, 2N6165
38616	BTX26	BTX 20, 800V	-
38617	BTX29/...R	Igt<100mA	CS 70-...
38618	BTX30/...	Igt/Ih<10/<25mA	T1N..., S2600..., TAG612-..., TAG613-...
38619	BTX31/...R	Igt/Ih<15/<15mA	T 10N...C
38620	BTX31S/...R	BTX 31/..R, <12µs	TAG 15S-..., T 12F...
38621	BTX32/...R	25/<25mA	T 10N...C, T 12N..., 2N5204...5207
38622	BTX32/...S	BTX 32/..R, <12µs	TAG 15S..., T 12F...
38623	BTX33/...R	50/<50mA	TAG15-..., TAG14N..., BTW39/..., CS13...
38624	BTX33/...S	BTX 33/..R, <12µs	T 12F-...
38625	BTX35/...R	60/10mA	TAG 14N-..., BTW 39/..., BStE41...
38626	BTX36/...R	Igt/Ih<40/10mA	2N681...692, T 12N..., 2N5204...5207,
38627	BTX37/...R	Igt/Ih<80/10mA	CS 42-..., CS 50-..., CS 70-...
38628	BTX38/...R	Igt/Ih<70/10mA	CS 42-..., CS 50-..., CS 70-...
38629	BTX41/...R	Igt/Ih<300/<300mA	BStN 35/..., BStP 36/..., BStP 35/...
38630	BTX44/...R	Igt/Ih<100/<100mA	CS 50-..., CS 70-...
38631	BTX45/...R	Igt/Ih<100/<100mA	CS 50-..., CS 70-...
38632	BTX46/...R	Igt/Ih<300/<300mA	BStN 35/..., BStP 36/..., BStP 35/...
38633	BTX47/...R	65/10mA	BTW47/..., TAG16N..., BTW92/..., CS16-...
38634	BTX48/...R	65/10mA	BTW47/..., TAG16N..., BTW92/..., CS16-...
38635	BTX49/...R	mA, 50µs	CS 42-..., CS 50-..., CS 70-...
38636	BTX50/...R	Igt/Ih<100/<150mA	CS 42-..., CS 50-..., CS 70-...
38637	BTX51/...R	Igt/Ih<70/10mA, 20µs	-
38638	BTX52	Igt/Ih<0,2/<2,5mA	-
38639	BTX53	BTX 52, 200V	-
38640	BTX54	BTX 52, 300V	-
38641	BTX55	BTX 52, 400V	-
38642	BTX57	Igt/Ih<15/<25mA	-
38643	BTX58	BTX 57, 200V	-
38644	BTX59	BTX 57, 300V	-
38645	BTX60	BTX 57, 400V	-
38646	BTX64/...R	65/10mA	C 234-..., MCR 1718-..., TAG 12F...
38647	BTX65/...R	12A(Tc85°C),Igt/Ih<65/10mA	C 234-..., MCR 1718-..., TAG 12F...
38648	BTX66/...R	32A(Tc85°C),Igt/Ih<80/10mA	BStH 37..., BStH 34..., BStL 37...
38649	BTX67/...R	62A(Tc85°C),Igt/Ih<80/10mA	BStL 34..., BStH 34..., BStL 37...
38650	BTX68/...R	<30/10mA	BStC 03..., BStD 03..., CS 5-..., CS 8-...
38651	BTX70/...R	Igt/Ih<50/<50mA	TAG9N..., TAG15-..., BTW39/..., BTW45/...
38652	BTX70/...S	BTX 70/..R, <12µs	TAG 15S..., T 12F...
38653	BTX71/...R	Igt/Ih<15/<15mA	T 10N...C, T 12N...
38654	BTX71/...S	BTX 71/..., <12µs	TAG 15S..., T 12F...

38655	BTX72/...R	25/<25mA	T 10N...C, T 12N...
38656	BTX72/...S	BTX 72/..., <12μs	T 12F..., TAG 15S...
38657	BTX73/...(R,A,B)	50/<50mA	T 17N..., BTW 48/..., CS 23-...
38658	BTX73/...S	BTX 73/..., <12μs	T 12F...
38659	BTX74/...R	Igt/Ih<50/<50mA	TAG 9N..., TAG 15-..., BTW 39/...
38660	BTX74/...S	Igt/Ih<50/<50mA <12μs	TAG 15S..., T 12F...
38661	BTX75/...R	<65/10mA	TAG 9N..., 2N1842...1850, TAG 15-...
38662	BTX76/...R	<40/10mA	MCR 3918-..., 2N5168...5171, T 12N...
38663	U)	80/100mA	BTW 40/..., BStE41...M, T 17N..., CS16...
38664	U)	80/100mA	BTW 48/..., CS 23-...
38665	BTX92/...R	Igt/Ih<150/<200mA	BTW 47/..., CS 23-..., BTW 92/...
38666	BTX94/...(H,J)	Igt<200mA	-
38667	BTX95/...R	50/30mA	TAG 15-..., BTW 39/..., T 15.1N...
38668	BTY20	Igt/Ih<80/<100mA	T 99N400E, T 159N400E
38669	BTY21	BTY 20, 100V	T 99N400E, T 159N400E
38670	BTY22	BTY 20, 200V	T 99N400E, T 159N400E
38671	BTY23	BTY 20, 400V	T 99N400E, T 159N400E
38672	BTY24	BTY 20, 500V	T 99N600E, T 159N600E
38673	BTY25	BTY 20, 600V	T 99N600E, T 159N600E
38674	BTY28	Igt/Ih<15/<4mA	T 6N100C, T 8N100C, BStD4126, T 10N100C
38675	BTY29	BTY 28, 150V	T 6N200C, T 8N200C, BStD4126, T 10N200C
38676	BTY30	BTY 28, 250V	T 6N300C, T 8N300C, BStD4126, T 10N300C
38677	BTY31	BTY 28, 300V	T 6N300C, T 8N300C, BStD4126, T 10N300C
38678	BTY34	Igt/Ih<15/<2mA	T 6N100C, T 8N100C, BStD4126, T 10N100C
38679	BTY34/...R	Igt<30mA	2N5168...5171, MCR 3918-..., 2N681...692
38680	BTY35	BTY 34, 150V	T 6N200C, T 8N200C, BStD4126, T 10N200C
38681	BTY36	BTY 34, 200V	T 6N200C, T 8N200C, BStD4126, T 10N200C
38682	BTY37	BTY 34, 250V	T 6N300C, T 8N300C, BStD4126, T 10N300C
38683	BTY38	BTY 34, 300V	T 6N300C, T 8N300C, BStD4126, T 10N300C
38684	BTY39	BTY 34, 400V	T 6N400C, T 8N400C, BStD4126, T 10N400C
38685	BTY41	Igt/Ih<80/<20mA	2N1843...1850, TAG 9N400, TAG 15-100
38686	BTY43	BTY 41, 150V	2N1845...1850, TAG 9N400, TAG 15-200
38687	BTY44	BTY 41, 200V	2N1846...1850, TAG 9N400, TAG 15-200
38688	BTY46	BTY 41, 300V	2N1848...1850, TAG 9N400, TAG 15-300
38689	BTY47	BTY 41, 400V	2N1850, TAG 9N400, TAG 15-400
38690	BTY50	Igt/Ih<40/<10mA	2N682...692, T 12N100, C 228A, C 35A
38691	BTY51	BTY 50, 100V	2N683...692, T 12N100, C 228A, C 35A
38692	BTY52	BTY 50, 150V	2N684...692, T 12N200, C 228B, C 35B
38693	BTY53	BTY 50, 250V	2N686...692, T 12N300, C 228C, C 35C
38694	BTY54	BTY 50, 300V	2N687...692, T 12N300, C 228C, C 35C
38695	BTY57	Igt/Ih<40/<10mA	2N682...692, T 12N100, C 228A, C 35A
38696	BTY58	BTY 57, 100V	2N683...692, T 12N100, C 228A, C 35A
38697	BTY59	BTY 57, 150V	2N684...692, T 12N200, C 228B, C 35B
38698	BTY60	BTY 57, 200V	2N685...692, T 12N200, C 228B, C 35B
38699	BTY61	BTY 57, 250V	2N686...692, T 12N300, C 228C, C 35C

38700	BTY62	BTY 57, 300V	2N687...692, T 12N300, C 228C, C 35C
38701	BTY64	Igt/Ih<70/<20mA	-
38702	BTY65	BTY 64, 100V	-
38703	BTY66	BTY 64, 150V	-
38704	BTY67	BTY 64, 200V	-
38705	BTY68	BTY 64, 250V	-
38706	BTY69	BTY 64, 300V	-
38707	BTY70	BTY 64, 400V	-
38708	BTY79/...R	30/<75mA	BTW 42/..., BStC03..., CS 5-..., BStD03...
38709	BTY79/...R/05		BTW 42/..., BStC03..., CS 5-..., BStD03...
38710	BTY79A/05	Igt/Ih<20/<25mA	BStD4126, S 6210A, T 10N100C
38711	BTY79A/10	BTY 79A/05, 100V	BStD4126, S 6210A, T 10N100C
38712	BTY79A/20	BTY 79A/05, 200V	BStD4126, S 6210B, T 10N200C
38713	BTY79A/30	BTY 79A/05, 300V	BStD4126, S 6210D, T 10N300C
38714	BTY79A/40	BTY 79A/05, 400V	BStD4126, S 6210D, T 10N400C
38715	BTY79A/50	BTY 79A/05, 500V	BStD4133, S 6210M, T 10N500C
38716	BTY80	BTY 79/200R	BTY 79/...R
38717	BTY81	BTY 79/400R	BTY 79/...R
38718	BTY84	BTY 79/100R	BTY 79/...R
38719	BTY85	BTY 79/200R	BTY 79/...R
38720	BTY86	BTY 79/300R	BTY 79/...R
38721	M)	10A(Tc85°C),Igt/Ih<65/10mA	TAG15-..., BTW39/..., CS13-..., TAG16N...
38722	BTY88	BTY 91/100R	BTY 91/...R
38723	BTY89	BTY 91/200R	BTY 91/...R
38724	BTY90	BTY 91/300R	BTY 91/...R
38725	M)	<40/25mA	T 12N..., 2N5204...5207
38726	BTY92	BTY 95/100R	BTY 95/...R
38727	BTY93	BTY 95/200R	BTY 95/...R
38728	BTY94	BTY 95/300R	BTY 95/...R
38729	BTY95/...R	32A(Tc85°C),Igt/Ih<80/10mA	CS 42-..., CS 50-..., CS 70-...
38730	BTY96	BTY 99/100R	BTY 99/...R
38731	BTY97	BTY 99/200R	BTY 99/...R
38732	BTY98	BTY 99/300R	BTY 99/...R
38733	BTY99/...R	62A(Tc85°C),Igt/Ih<70/10mA	CS 70-...
38734	BTZ10	Igt/Ih<50/<30mA	-
38735	BTZ11	BTZ 10, 100V	-
38736	BTZ12	BTZ 10, 200V	-
38737	BTZ13	BTZ 10, 400V	-
38738	BTZ15	BTZ 10, 500V	-
38739	BTZ16	BTZ 10, 600V	-
38740	BTZ18	Igt/Ih<15/4mA	T 6N200C, T 8N200C, BStD4126
38741	BTZ19	BTZ 18, 400V	T 6N400C, T 8N400C, BStD4126
38742	BTZ21	Igt/Ih<40/10mA	2N688...692, T 12N400, C 35D, MCR 64-6
38743	BTZ35	50V, 3,5A, Igt/Ih<40/10mA	2N1843...1850, TAG 9N400, TAG 15-100
38744	BTZ36	BTZ 35, 100V	2N1844...1850, TAG 9N400, TAG 15-100



38745	BTZ37	BTZ 35, 200V	2N1846...1850, TAG 9N400, TAG 15-200
38746	BTZ38	BTZ 35, 350V	16N400
38747	BTZ39	BTZ 35, 450V	16N600
38748	BU	P4 SMA-36	P4 SMA-36
38749	BU	BCX 71RG	BCX 71RG
38750	BU	2SD1005-BU	2SD1005
38751	BU100	150/60V, 10A, 15W(Tc75°)	BU 109, BUY 69C, BUY 70C, BU 606...608
38752	BU100A	25W(Tc100°)	BU 109, BUY 69C, BUY 70C, BU 606...608
38753	BU102	400/150V, 7A, 50W(Tc50°)	BU 104, BU 606, BU 608
38754	BU103	120/100V, 1A, 15W(Tc25°)	BU 125(S), BUY 41, 2SC1860
38755	BU103A	120/100V, 1A, 30W	BUX 67, 2SC782...783, 2SD610
38756	BU104	400/150V, 7A, 85W	BU 606, BU 608
38757	BU104D	BU 104	BU 606D, BU 608D
38758	BU104DP	BU 104 P	BU 406D, BU 408D, 2SC3176
38759	BU104P	BU 104, 50W	BU 406, BU 408, 2SC3175, 2SC3591
38760	BU105	1500V, 2,5A, 10W(Tc90°)	BU 205, BU 208(A), 2SC2928, 2SD350(A)
38761	BU106	325/140V, 10A, 50W	BU 109, BUY 69C, BUY 70C, BU 606...608
38762	BU107	300/120V, 10A, 50W	BU 109, BUY 69C, BUY 70C, BU 606...608
38763	BU108	1500/750V,5A,12,5W(Tc95°)	BU 208(A), 2SC2928, 2SD350(A), 2SD820
38764	BU1085	BU 108	BU 108
38765	BU109	330/120V, 10A, 85W	BUY 69C, BUY 70C, BU 606...608
38766	BU109D	BU 109, + diodo interno	BU 104D, BU 606D...608D
38767	BU109DP	BU 109P, + diodo interno	BU 406D...408D, 2SC3176
38768	BU109NP	BU 109	BU 109
38769	BU109P	BU 109, 50W	BU 406...408, 2SC3175, 2SC3591
38770	BU110	330/150V, 10A, 60W(Tc75°)	BU 109, BUY 69C, BUY 70C, BU 606...608
38771	BU112	85W(Tc30°)	BU 526, BU 626A, BUY 69C
38772	BU113(S)	85W(Tc30°)	BU 526, BU 626A, BUY 69B
38773	BU114	350/225V, 6A, 50W(Tc75°)	BU 104, BU 109, BU 526, BU 606...608
38774	BU115	800/600V, 15A, 50W(Tc75°)	BU 526, BU 626A
38775	BU116	BU 115, 400/300V	BU 526, BU 626A
38776	BU117	BU 115, 250/200V	BU 526, BU 626A
38777	BU118	400/200V, 7A, 60W	BU 104DP, BU 109DP, BU 406D, BU 408D
38778	BU120	400/200V, 10A, 50W(Tc75°)	BUY 69C, BUY 70C, BU 606, BU 608
38779	BU121	400/200V, 10A, 50W(Tc75°)	BUY 69C, BUY 70C, BU 606, BU 608
38780	BU122	250/150V, 5A, 67W(Tc75°)	BU 104, BU 109, BU 606...608
38781	BU123	BU 122, 180/120V, 50W(Tc75°)	BU 104, BU 109, BU 606...608
38782	BU124	350/150V, 10A, 50W	BU 426, BU 926
38783	BU124A	BU 124, 400/150V	BU 426, BU 926
38784	BU125	130/60V, 7A, 10W(Tc50°)	BUY 47...48, BUY 68, BUY 81, BU 406...408
38785	BU125S	BU 125, 250/150V, 3A	BUY 41, BUX 49, BU 406...408
38786	BU126(A,S,T)	750V, 3A, 50W	BU 326, BU 426, BU 526, BU 926
38787	BU127	200/120V, 10A, 62W, 70MHz	BU 109, BUY 18, BUY 69C, BUY 70C
38788	BU128	BU 127, 300/200V, 80MHz	BU 109, BUY 18, BUY 69C, BUY 70C
38789	BU129	400V, 5A, 25W(Tc100°)	BU 104, BU 606, BU 608

38790	BU130	330/150V, 10A, 15W(Tc100°)	BU 109, BUY 69C, BUY 70C, BU 606...608
38791	BU131	750/300V, 10A, 40W(Tc60°)	BU 526, BU 626A, BUY 69B, BUY 70B
38792	BU132	800/600V, 1A, 15W(Tc97°)	BU 126, 2SC1101, 2SC1167
38793	BU133	8MHz	BU 326, BUS 11, BUX 82, 2SC3091, 2SC3155
38794	BU134	500/350V, 4A, 85W	BU 326, BU 426, BU 526, BU 926
38795	BU135	8MHz	BU 126, BU 326, BU 426, BUX 45
38796	BU136	BU 135, 600/250V, 7A	BU 326, BU 426, BU 526, BU 926
38797	BU137	1000/1000V, 12A, 70W	BU 157, BU 626A, BUS 13A, 2SD1094
38798	BU137A	BU 137, 1200/1000V, 10A	BU 157, MJ 8504, 2SC3061, 2SD1279
38799	BU138	160/125V, 10A, 60W(Tc95°)	BU 109D, BU 606D...608D
38800	BU139	BU 138, 200/150V	BU 109D, BU 606D...608D
38801	BU140	BU 138, 280/175V	BU 109D, BU 606D...608D
38802	BU141	BU 138, 330/175V	BU 109D, BU 606D...608D
38803	BU142	900/350V, 12A, 70W	BUS 13A, BUW 46, BU 626A, 2SD1094
38804	BU143	BU 142, 800/350V	BUS 13, BUW 45...46, BU 626A, 2SD1094
38805	BU144	BU 142, 700/350V	BUS 13, BUW 45...46, BU 626A, 2SD1094
38806	BU1506DX	1500V, 5A, 32W	-
38807	BU1508AX	1500/700V, 8A, 35W	-
38808	BU1508DX	BU 1508AX, + diodo interno	-
38809	BU157	1500/650V, 12A, 70W	BU 2525A, BU 508(A), BU 908
38810	BU1706A	1750/850V, 5A, 100W	-
38811	BU1706AX	BU 1706A, , 32W	-
38812	BU1708AX	1750/850V, 8A, 35W	-
38813	BU180	320V, 10A, 50W, B>200	BU 284, BU 289, BU 826
38814	BU180A	BU 180, 400V	BU 284, BU 826
38815	BU181	600V, 10A, 65W, B>200	-
38816	BU181A	BU 181, 800V	-
38817	BU184	400/200V, 8A, 60W	BU 806
38818	BU189	BU 184, 330/150V	BU 806...807
38819	BU204(A)	1300/600V, 2,5A, 10W(Tc90°)	BU 207(A)...208(A), 2SC2928, 2SD350(A)
38820	BU205(A)	BU 204, 1500/700V	BU 208(A), 2SC2928, 2SD350(A), 2SD820
38821	BU206	BU 204, 1700/800V	BU 209(A), 2SD784...785
38822	BU207(A)	1300/600V, 5A, 12,5W(Tc95°)	BU 208(A), 2SC2928, 2SD350(A), 2SD820
38823	BU208(A)	BU 207, 1500/700V	BU 508(A), 2SC2928, 2SD350(A), 2SD820
38824	BU208D	BU 208, + diodo interno	BU 508D, BU 800, 2SD1171...1175
38825	BU209(A)	BU 207, 1700/800V, 4A	2SD784...785
38826	BU210	400/250V, 12A, 85W(Tc45°)	BUW 74, 2SC2123, BU 626A, BUY 69C
38827	BU211	BU 210, 600/300V	BUW 75, 2SC2123, BU 626A, BUY 69B
38828	BU212	BU 210, 750/350V	BUW 76...77, 2SC2123, BU 626A, BUY 69B
38829	BU213	150/60V, 7,5A, 38W(Tc45°)	BUW 64A...B, 2SC1863...1864, 2SC2334
38830	BU214	150/60V, 10A, 50W(Tc45°)	BUV 27(A)...28, 2SC2867
38831	BU215	150/60V, 20A, 60W(Tc45°)	BUV 26
38832	BU216	150/60V, 7,5A, 50W(Tc45°)	BUW 86...87, 2SC2769
38833	BU217	150/60V, 10A, 60W(Tc45°)	BUW 70, BUY 55, 2SC2769
38834	BU218	150/60V, 20A, 115W(Tc45°)	BUV 10, BUW 57...58, BUX 10, BUX 70

38835	BU221	800, 15A, 100W	BUS 13(A), BUW 45...46, 2SC2123
38836	BU222	450/350V, 6A, 75W, >10MHz	BUX 15, BUX 18C, BUX 44, 2SC2656
38837	BU222A	BU 222, 525/475V	BUX 15, 2SC2536, 2SC3041, 2SD640
38838	BU223	450/400V, 10A, 125W, 7,5MHz	BUW 24, BUW 72, BUX 14, 2SC2625
38839	BU223A	BU 223, 525/475V	BUW 34, BUY 69, BUW 25, 2SC2441
38840	BU225	2200/800V, 2A, 10W(Tc80°)	BUY 71, 2SD621, 2SD838
38841	BU226	2000/800V, 1,5A, 32W	BU 225, BUY 71, 2SD621, 2SD838
38842	BU2506DF	1500/700V, 5A, 45W	BU 2508DF, 2SC3892A, 2SC4765
38843	BU2506DX	BU 2506DF	BU 2506DF
38844	BU2508A	1500/700V, 8A, 125W	2SC3687...88
38845	BU2508AF	BU 2508A, , 45W	2SC3886A, 2SC3896, 2SC4542
38846	BU2508AX	BU 2508A, , 45W	BU 2508AF
38847	BU2508D	BU 2508A, + diodo interno	2SC3683...84
38848	BU2508DF	BU 2508D, , 45W	2SC3893A
38849	BU2520A	1500/800V, 10A, 125W	2SC3688
38850	BU2520AF	BU 2520A, , 45W	2SC4542
38851	BU2520AX	BU 2520A, , 45W	BU 2520AF
38852	BU2520D	BU 2520A, + diodo interno	2SC3684
38853	BU2520DF	BU 2520D, , 45W	2SC4763
38854	BU2520DX	BU 2520D, , 45W	BU 2520DF
38855	BU2522A	1500/800V, 10A, 125W	2SC3688
38856	BU2522AF	BU 2522A, , 45W	2SC4542
38857	BU2522AX	BU 2522A, , 45W	BU 2522AF
38858	BU2525A	1500/800V, 12A, 125W	BUH 1015
38859	BU2525AF	BU 2525A, , 45W	2SC4692
38860	BU2525AX	BU 2525A, , 45W	BU 2525AF
38861	BU2527A	1500/800V, 12A, 125W	BUH 1015
38862	BU2527AF	BU 2527A, , 45W	2SC4890
38863	BU2527AX	BU 2527A, , 45W	BU 2527AF
38864	BU2530AL	1500/800V, 16A, 125W	2SC3996, 2SC4289A
38865	BU2708AF	1700/825V, 8A, 45W	BUH 517, 2SC4797
38866	BU2708DF	BU 2708AF, + diodo interno	BUH 517D, 2SC4963
38867	BU2720AF	1700/825V, 10A, 45W	2SC4879
38868	BU2720DF	BU 2720AF, + diodo interno	-
38869	BU2722AF	1700/825V, 10A, 45W	BU 2727AF
38870	BU2727A	1700/825V, 12A, 125W	-
38871	BU2727AF	BU 2727A	-
38872	BU284	BU 184, 90W	BU 180A
38873	BU287	1300/600V, 8A	BU 908
38874	BU289	BU 189, 90W	BU 180
38875	BU306F	600/300V, 8A, 20W	BUT 12(A)F, 2SC4056, 2SC4441
38876	BU307F	BU 306F, 700/400V	BUT 12(A)F, BUT 22CF
38877	BU308	1500/750V, 5A, 12,5W(Tc95°)	BU 208(A), 2SC2928, 2SD350(A), 2SD820
38878	BU310	160/100V, 6A, 25W(Tc100°)	BU 104, BU 109, BU 606...608
38879	BU311	BU 310, 200/125V	BU 104, BU 109, BU 606...608

38880	BU312	BU 310, 280/150V	BU 104, BU 109, BU 606...608
38881	BU322	450/400V, 7A, 100W	2SD520...521, 2SD528, 2SD705, 2SD707
38882	BU322A	BU 322, 525/475V	2SD520...521, 2SD528, 2SD705, 2SD707
38883	BU323	500/350V, 10A, 175W, B>150	MJ 10013...10014, 2SD683
38884	BU323A	BU 323, 600/400V	MJ 10013...10014, 2SD683
38885	BU325	200/200V, 3A, 25W	-
38886	BU326	800/375V, 6A, 60W(Tc50°)	BU 426(A), BU 526, BU 926
38887	BU326(A)P	BU 326(A), 110W	BU 426(A), BU 926
38888	BU326A,R	BU 326, 900/400V	BU 426A, BU 526, BU 926
38889	BU326S	BU 326, 800/400V	BU 426(A), BU 526, BU 926
38890	BU361	800/800V, 12A, 70W	BU 157, BU 626A, BUW 77, 2SC2123
38891	BU406(H)	400/200V, 7A, 60W	BU 104P, BU 408, 2SC3175, 2SC3591
38892	BU406D	BU 406, + diodo interno	BU 104DP, BU 408D, 2SC3176
38893	BU406F	BU 406, , 18W	BU 306...307F
38894	BU407(H)	330/150V, 7A, 60W	BU 109P, BU 406, BU 408, 2SC3173
38895	BU407D	BU 407, + diodo interno	BU 109DP, BU 406D, BU 408D, 2SC3174
38896	BU407F	BU 407, , 18W	BU 306...307F
38897	BU408	400/200V, 7A, 60W	BU 104P, BU 406, 2SC3175, 2SC3591
38898	BU408D	BU 408, + diodo interno	BU 104DP, BU 406D, 2SC3176
38899	BU409	250/150V, 7A, 60W	BU 104P, BU 406...408, BUT 54, BUT 56(A)
38900	BU410	160/125V, 8A, 50W(Tc50°)	BU 104D, BU 109D, BU 606D...608D
38901	BU411	BU 410, 220/150V	BU 104D, BU 109D, BU 606D...608D
38902	BU412	BU 410, 280/175V	BU 104D, BU 109D, BU 606D...608D
38903	BU413	60W(Tc50°)	BU 109D, BU 104D, BU 606D...608D
38904	BU414	800/400V, 8A, 60W(Tc75°)	BU 426A, BU 526, BU 626A, BU 926
38905	BU414B	BU 414, 900/400V	BU 426A, BU 526, BU 626A, BU 926
38906	BU415	800/400V, 12A, 120W	BU 626A, 2SC2123
38907	BU415B	BU 415, 900/400V	BU 626A, 2SC2123
38908	BU426	800/375V, 6A, 70W(Tc73°)	BU 926
38909	BU426A	BU 426, 900/400V	BU 926
38910	BU426F,AF	BU 426(A)	-
38911	BU426FI,AFI	BU 426(A)	-
38912	BU433	BU 426, 800/375V	BU 426(A), BU 926
38913	BU500	1500/700V, 6A, 75W(Tc30°)	BU 508(A), 2SC1308, 2SD649, 2SD821
38914	BU505	1500/700V, 2,5A, 75W	BU 506
38915	BU505D	BU 505, + diodo interno	BU 506D
38916	BU505DF	BU 505D, , 20W	BU 506DF, BU 1506DX
38917	BU505F	BU 505, , 20W	BU 506F, 2SD1575
38918	BU506	1500/700V, 5A, 100W	-
38919	BU506D	BU 506, + diodo interno	-
38920	BU506DF	BU 506D, , 20W	BU 1506DX
38921	BU506F	BU 506, , 20W	-
38922	BU508(A)	1500/700V, 8A, 125W	BU 908, BU 2508A, 2SC3687
38923	BU508AF	BU 508A, , 34W	BU 2508AF, 2SC3886A, 2SC3896, 2SD1548
38924	BU508AT	BU 508A, 75W	-

38925	BU508AXI	BU 508A, , 40W	BU 1508AX
38926	BU508D	BU 508A, + diodo interno	BU 2508D, S 2055A, 2SC3683
38927	BU508DF	BU 508D, , 34W	BU 2508DF, S 2055AF, 2SC3893A, 2SC4124
38928	BU508DFI	BU 508D, , 60W	BU 2508DF, S 2055AF, 2SC3893A, 2SC4124
38929	BU508DR	BU 508D, + Rbe25Ohm	-
38930	BU508DRF	BU 508DR, , 34W	-
38931	BU508DXI	BU 508D, , 40W	BU 1508DX
38932	BU508FI,AFI	BU 508(A), , 60W	BU 2508AF, 2SC3886A, 2SC3896, 2SD1548
38933	BU508L	BU 508A	BU 2508A
38934	BU522	400/375V, 7A, 75W, B>250	2SD1533, BU 806, BU 810
38935	BU522A	BU 522, 450/425V	2SD1533, BU 810
38936	BU522B	BU 522, 475/450V	2SD1533, BU 810
38937	BU526	900/400V, 8A, 86W	BU 626A, BU 926, 2SD1094
38938	BU526A	BU 526, 900/460V	BU 626A, 2SD1094
38939	BU536	1100/480V, 8A, 62W	BU 902, BU 908
38940	BU546	1300/550V, 6A, 100W	BU 903
38941	BU603	1350/550V, 5A, 100W	-
38942	BU606	400/200V, 7A, 90W	BU 104, BU 608, BUY 69C
38943	BU606D	BU 606, + diodo interno	BU 104D, BU 608D
38944	BU607	330/200V, 7A, 90W	BU 104, BU 606, BU 608, BUY 69C
38945	BU607D	BU 607, + diodo interno	BU 104D, BU 606D, BU 608D
38946	BU608	400/200V, 7A, 90W	BU 104, BU 606, BUY 69C
38947	BU608D	BU 608, + diodo interno	BU 104D, BU 606D
38948	BU626(A)	1000/400V, 10A, 100W	S 2530A, 2SD1094
38949	BU705	1500/700V, 2,5A, 75W	BU 706, 2SC3483, 2SD1493...1494
38950	BU705D	BU 705, + diodo interno	BU 706D, 2SC3479, 2SD1290...91
38951	BU705DF	BU 705D, , 29W	BU 706DF, 2SD1553, 2SD1649, 2SD1876
38952	BU705F	BU 705, , 29W	BU 706F, 2SD1543, 2SD1653, 2SD1882
38953	BU706	1500/700V, 5A, 100W	BU 508(A), 2SC3485...86, 2SD1496...97
38954	BU706D	BU 706, + diodo interno	BU 508D, 2SC3481...82, 2SC3681, 2SD1878
38955	BU706DF	BU 706D, , 32W	BU 508DF, 2SD1555...56, 2SD1651...52
38956	BU706F	BU 706, , 32W	BU 508AF, 2SC4142...43, 2SD1545...46
38957	BU724	650/375V, 2A, 25W	BUD 46A, 2SC3259, 2SC3579
38958	BU724A	BU 724, 850/400V	-
38959	BU726	-/400V, 7A, 60W(Tc50°)	BU 426(A), BU 526, BU 536, BU 926
38960	BU800(A,S)	1500/700V, 5A, 12,5W(Tc95°)	BU 208D, BU 508D, 2SD1171...1175
38961	BU801	600/400V, 3A, 40W, B>100	-
38962	BU806	400/200V, 8A, 60W	BU 184
38963	BU806AF	BU 806	-
38964	BU806FI	BU 806, , 30W	-
38965	BU807	BU 806, 330/150V	BU 184, BU 189
38966	BU807FI	BU 807, , 30W	-
38967	BU808[Philips]	1500V, 12A, 160W	BUX 88
38968	BU808DFI[SGS]	BU 808FI, + diodo interno	-
38969	BU808DXI[SGS]	BU 808FI, 35W, + diodo interno	-

38970	BU808FI[SGS]	1400/700V, 5A, 50W, B>25	-
38971	BU810	600/400V, 7A, 75W	2SD798...799
38972	BU824	650/375V, 0,5A, 12,5W, B>325	-
38973	BU826	800/375V, 6A, 125W	-
38974	BU826A	BU 826, 1000/400V	-
38975	BU900(DT)	650/400V, 8A, 70W, B>7000	-
38976	BU902	1100/480V, 8A, 100W	BU 508(A), BU 908
38977	BU902F	BU 902	BU 508AF, 2SC3886, 2SC4144
38978	BU903	1350/550V, 6A, 125W	BU 508(A), BU 908
38979	BU903F	BU 903	BU 508AF, 2SC3885, 2SC3895, 2SC4143
38980	BU908	1500/700V, 8A, 125W	BU 508(A), BU 2508A
38981	BU908AF	BU 908	BU 508AF, BU 2508AF
38982	BU910	400/350V, 6A, 60W, B>20	BU 806, 2SD1114, 2SD1245
38983	BU911	BU 910, 450/400V	BU 806, 2SD1245
38984	BU912	BU 910, 500/450V	2SD1245
38985	BU920	400/350V, 10A, 120W, B>300	BU 930...932, BUT 51P, BUW 66
38986	BU920P	BU 920, 105W	BU 930P...932P, BUT 51P
38987	BU920PFI	BU 920, 55W	-
38988	BU920T	BU 920, 105W	2SD1162
38989	BU921	BU 920, 450/400V	BU 931...932, BUT 51P
38990	BU921P	BU 921, 105W	BU 931P...932P, BUT 51P
38991	BU921PFI	BU 921, 55W	-
38992	BU921T	BU 921, 105W	2SD1162
38993	BU921ZP	BU 921, 350V, 125W	-
38994	BU921ZPFI	BU 921, 350V, 60W	-
38995	BU921ZT	BU 921, 350V, 100W	-
38996	BU921ZTFI	BU 921, 350V, 40W	-
38997	BU922	BU 920, 500/450V	BU 932, BUT 51P
38998	BU922P	BU 922, 105W	BU 932P, BUT 51P
38999	BU922PFI	BU 922, 55W	-
39000	BU922T	BU 922, 105W	2SD1162
39001	BU926	850V, 8A, 90W	BUV 47(A), BUV 70...71, BUV 89
39002	BU930	400/350V, 15A, 150W, B>300	BU 941, BUT 13...15
39003	BU930P	BU 930, 105W	BU 941P, BUT 51P, 2SD1466
39004	BU930Z	BU 930, 175W, zener interno	-
39005	BU930ZP	BU 930, zener interno	-
39006	BU931	BU 930, 450/400V	BU 941, BUT 13...15
39007	BU931P	BU 931, 105W	BU 941P, BUT 51P, 2SD1466
39008	BU931PFI	BU 931, 60W	BU 941PFI
39009	BU931R	BU 931, 175W	BUT 13...15
39010	BU931RP	BU 931, 125W	BUT 51P, 2SD1466
39011	BU931RPFI	BU 931, 60W	-
39012	BU931T	BU 931, 125W	BU 941T
39013	BU931TFI	BU 931, , 45W	BU 941TFI
39014	BU931Z	interno	BU 941Z



39015	BU931ZP	interno	BU 941ZP
39016	BU931ZPFI	interno	BU 941ZPFI
39017	BU932	BU 930, 500/450V	BUT 13...15
39018	BU932P	BU 932, 105W	BUT 51P, 2SD1466
39019	BU932R	BU 932, 175W	BUT 13...15
39020	BU932RPFI	BU 932, 60W	-
39021	BU941	500/400V, 15A, 175W, B>300	BUT 13...15
39022	BU941P	BU 941, 150W	-
39023	BU941PFI	BU 941, , 65W	-
39024	BU941T	BU 941, 125W	-
39025	BU941TFI	BU 941, , 55W	-
39026	BU999	160/140V, 25A, 106W	BUX 69
39027	BUD46	850/400V, 4A, 70W	-
39028	BUD46A	BUD 46, 1000/450V	-
39029	BUD47	850/400V, 8A, 100W	-
39030	BUD47A	BUD 47, 1000/450V	-
39031	BUD48	850/400V, 16A, 150W	BUT 51P
39032	BUD48A	BUD 48, 1000/450V	-
39033	BUD48DI	90W	-
39034	BUD48I,AI	BUD 48(A), , 90W	-
39035	BUD600(-SMD)	600/250V, 2A, 12W, >4MHz	2SC3405, 2SC3489, 2SC3555
39036	BUD620(-SMD)	700/400V, 4A, 25W, 8MHz	-
39037	BUD630(-SMD)	700/400V, 6A, 40W, >4MHz	-
39038	BUD636(-SMD)	1000/450V, 5A, 40W, >4MHz	-
39039	BUD86(-SMD)	20W(Tc60°),20MHZ	2SC3405, 2SC3489, 2SC3555
39040	BUD87(-SMD)	BUD 86, 1000/450V	2SD1945
39041	BUD98	850/400V, 32A, 250W	-
39042	BUD98I	BUD 98, , 110W	-
39043	V	BUV 298..	-
39044	BUF405	850/450V, 7,5A, 80W	-
39045	BUF405A	BUF 405, 1000/450V	-
39046	BUF405FI,AFI	BUF 405(A), , 35W	-
39047	BUF405XI,AXI	BUF 405(A), , 35W	-
39048	BUF410	850/450V, 15A, 125W	-
39049	BUF410A	BUF 410, 1000/450V	-
39050	BUF410AFI,FI	BUF 410(A), , 60W	-
39051	BUF410AI	BUF 410A, , 85W	-
39052	BUF410I	BUF 410, , 85W	-
39053	BUF420	850/450V, 30A, 200W	-
39054	BUF420A	BUF 420, 1000/450V	-
39055	BUF420AI	BUF 420A, , 115W	-
39056	BUF420AM	BUF 420A, 200W	-
39057	BUF420I	BUF 420, , 115W	-
39058	BUF420M	BUF 420, 200W	-
39059	BUF460(F)	850/450V, 80A, 300V	-

39060	BUF460A,AF	BUF 460(F), 1000/450V	-
39061	BUF460V,AV	BUF 460(F,AF)	-
39062	BUF620	700/400V, 4A, 40W, 8MHz	-
39063	BUF630	700/400V, 6A, 50W, >4MHz	-
39064	BUF636A	1000/450V, 5A, 50W, >4MHz	-
39065	BUF640	850/400V, 6A, 70W, <0,7/2,2μs	BUT 11(A), BUT 18(A), BUV 46(A)
39066	BUF640A	BUF 640, 1000/450V	BUT 11A, BUT 12A, BUT 18A, BUV 46A
39067	BUF642	900/400V, 6A, 70W, <0,5/2,2μs	BUT 11A, BUT 12A, BUT 18A, BUV 46A
39068	BUF644	700/400V, 8A, 70W, <1,2/2μs	-
39069	BUF646	850/400V, 7A, 70W, -/3,25μs	BUT 12(A), BUT 56(A), BUF 405(A)
39070	BUF646A	BUF 646, 1000/450V	BUT 12A, BUT 56A, BUF 405A
39071	BUF650	70W,<0,6/1,65μs	-
39072	BUF654	80W,<0,7/1,65μs	-
39073	BUF656B	1100/400V, 7A, 70W, 180ns	BUT 12A, BUT 56A, BUF 405A
39074	BUH1015T	1500/700V, 16A, 160W	-
39075	BUH1215T	1500/700V, 19A, 200W	-
39076	BUH2M20AP	BUH 2M20P, 2000/1200V	2SC4913
39077	BUH2M20P	2000/900V, 30mA, 40W	2SC 4579, 2SC4913
39078	BUH313	1300/600V, 5A, 50W	BU 2508AF, 2SC3884...85, 2SC3894...95
39079	BUH315	1500/700V, 5A, 50W	BU 2508AF, 2SC3884A...85A, 2SC3894...95
39080	BUH315D	BUH 315, + diodo interno	BU 2508DF, 2SC3892A
39081	BUH315D	BUH 313, + diodo interno	BU 2508DF, 2SC3892(A)
39082	BUH315DXI	BUH 315D, , 35W	BU 1506DX, BU 1508DX
39083	BUH315XI	BUH 315, , 35W	BU 1508AX
39084	BUH414DXI	1400/700V, 5A, 35W	BU 1506DX, BU 1508DX
39085	BUH415DXI	1500/700V, 5A, 35W	BU 1506DX, BU 1508DX
39086	BUH417	1700/700V, 7A, 55W	BUH 517
39087	BUH515	1500/700V, 8A, 60W	BU 2508AF, 2SC3886A, 2SC3896
39088	BUH515D	BUH 515, + diodo interno	BU 2508DF, BU 2520DF
39089	BUH515DXI	BUH 515, + diodo interno, 40W	BU 1508DX
39090	BUH515XI	BUH 515, 40W	BU 1508AX
39091	BUH517	1700/700V, 8A, 60W	-
39092	BUH517D	BUH 517, + diodo interno	-
39093	BUH715	1500/700V, 10A, 60W	BU 2520AF, BU 2525AF
39094	BUK100-50DL	13,5A, 40W	
39095	BUK100-50GL	BUK 100-50DL, 9,5/10,5μs	-
39096	BUK100-50GS	BUK 100-50DL, 15A, 5/15μs	-
39097	BUK101-50DL	26A, 75W,	
39098	BUK101-50GL	BUK 101-50DL, 17,5/17μs	-
39099	BUK101-50GS	BUK 101-50DL, 29A, 7,5/27μs	-
39100	BUK102-50DL	45A, 125W,	
39101	BUK102-50GL	BUK 102-50DL, 10/16μs	-
39102	BUK102-50GS	BUK 102-50DL, 50A, 7/22μs	-
39103	BUK107-50DL	0,5A, <0,2	
39104	BUK107-50DS	<175mOhm(0,1A), 20/9μs	-

39105	1000AE,BE	1000V, 11..12A, 310W, <10hm	-
39106	100AE,BE	<16mOhm	-
39107	200AE,BE	<45mOhm	-
39108	500AE,BE	500V, 28..32A, 310W, 0,160hm	-
39109	BUK426-1000A,B	1000V, 1,9..2,1A, 45W, <50hm	BUK 428-1000
39110	BUK426-100A,B	100V, 19..20A, 45W, <65mOhm	-
39111	BUK426-200A,B	200V, 10..11A, 45W, <0,20hm	2SK1206, 2SK1225, 2SK1328
39112	BUK426-50A,B	50V, 30A, 45W, <30mOhm	2SK1223, 2SK1298, 2SK1424, 2SK1666
39113	BUK426-60A,B	60V, 30A, 45W, <30mOhm	2SK1223, 2SK1298, 2SK1424, 2SK1666
39114	BUK426-800A,B	800V, 2,1..2,4A, 45W, <40hm	-
39115	BUK427-400A,B	400V, 6,2..6,9A, 45W, <0,50hm	2SK1206, 2SK1225, 2SK1328
39116	BUK427-450B	450V, 5,6A, 45W, <0,60hm	2SK1206, 2SK1225, 2SK1328
39117	BUK427-500A,B	500V, 4,8..5,6A, 45W, <0,80hm	2SK1206, 2SK1523
39118	BUK427-600A,B	600V, 3,9..4,3A, 45W, <1,20hm	BUK 727-600, 2SK1463
39119	BUK428-1000A,B	<2,60hm	BUK 426-1000
39120	BUK428-500A,B	500V, 6,8..6,1A, 45W, <0,50hm	2SK1206, 2SK1523
39121	BUK428-800A,B	800V, 3..3,4A, 45W, <20hm	2SK809A, 2SK1463
39122	BUK436-1000A,B	1000V, 3,1..3,5A, 125W, <50hm	2SK696
39123	BUK436-100A,B	<65mOhm	BUZ 345, 2SK850, 2SK906, 2SK1429
39124	BUK436-200A,B	200V, 17..19A, 125W, <0,20hm	BUZ 350, 2SK851, 2SK623, 2SK901, 2SK1491
39125	BUK436-50A,B	50V, 46..50A, 125W, <30mOhm	BUZ 346, 2SK1379
39126	BUK436-60A,B	60V, 46..50A, 125W, <30mOhm	2SK1379
39127	BUK436-800A,B	800V, 3,5..4A, 125W, <40hm	BUZ 355...356, 2SK534, 2SK604, 2SK695
39128	BUK437-400A,B	400V, 12..14A, 180W, <0,50hm	-
39129	BUK437-450B	450V, 11A, 180W, <0,60hm	-
39130	BUK437-500A,B	500V, 10..11A, 180W, <0,80hm	-
39131	BUK437-600A,B	600V, 7,8..9A, 180W, <1,20hm	-
39132	BUK438-1000A,B	<2,60hm	-
39133	BUK438-500A,B	<0,50hm	2SK1678
39134	BUK438-800A,B	800V, 6,6..7,6A, 220W, <20hm	-
39135	BUK439-60A	60V, 50A, 230W, <0,130hm	BUK 539-60
39136	BUK441-100A,B	100V, 3A, 20W, <1,10hm	BUK 541-60, 2SK1264
39137	BUK441-60A,B	60V, 4,8..5A, 20W, <0,50hm	BUK 541-60, 2SK1260
39138	BUK442-100A,B	100V, 6,1..6,6A, 22W, <0,30hm	BUK 443-100, BUZ 72(A)F, 2SK1261
39139	BUK442-50A,B	50V, 9,2..10A, 22W, <0,150hm	BUK 543-50, BUZ71(A)F, 2SK1093, 2SK1974
39140	BUK442-60A,B	60V, 9,2..10A, 22W, <0,150hm	BUK 545-100, 2SK1093, 2SK1344, 2SK1974
39141	BUK443-100A,B	100V, 8..9A, 25W, <0,20hm	BUK 543-100, BUZ 72(A)F, 2SK1261
39142	BUK443-50A,B	50V, 12..13A, 25W, <0,10hm	2SK1094, 2SK1419
39143	BUK443-60A,B	60V, 12..13A, 25W, <0,10hm	2SK1094, 2SK1419
39144	BUK444-200A,B	200V, 4,7..5,3A, 25W, <0,50hm	BUK 445-200, 2SK1478, 2SK1568...69
39145	BUK444-400A,B	400V, 2,4..2,7A, 25W, <1,80hm	BUK 445-450, 2SK503, 2SK1833
39146	BUK444-450B	450V, 2,1A, 25W, <2,30hm	BUK 445-450, 2SK1833
39147	BUK444-500A,B	500V, 1,9..2,1A, 25W, <2,30hm	BUK 445-500, 2SK1758, 2SK1833...34
39148	BUK444-600A,B	600V, 1,5..1,6A, 25W, <4,50hm	BUK 445-600, 2SK1611, 2SK1758, 2SK1834
39149	BUK444-800A,B	800V, 1,2..1,4A, 25W, <80hm	BUK 446-1000, 2SK808(A)

39150	BUK445-100A,B	100V, 12..14A, 30W, <0,1Ohm	2SK1350, 2SK1431
39151	BUK445-200A,B	200V, 7..7,6A, 30W, <0,28Ohm	BUK 545-200, 2SK1478, 2SK1568...69
39152	BUK445-400A,B	400V, 3,6..4A, 30W, <1Ohm	2SK1231, 2SK1351, 2SK1377
39153	BUK445-450B	450V, 3,1A, 30W, <1,3Ohm	2SK1231, 2SK1351, 2SK1377
39154	BUK445-500A,B	500V, 2,9..3,1A, 30W, <1,5Ohm	2SK1572, 2SK1767
39155	BUK445-50A,B	50V, 20..21A, 30W, <45mOhm	BUK 545-50, BUZ 11F, 2SK1214, 2SK1420
39156	BUK445-600A,B	600V, 2,2..2,5A, 30W, <2,5Ohm	BUK 446-800, 2SK1611, 2SK1758, 2SK1834
39157	BUK445-60A,B,H	60V, 20..22,5A, 30W, <45mOhm	2SK943, 2SK1095, 2SK1214, 2SK1420
39158	BUK446-1000A,B	1000V, 1,5..1,7A, 30W, <5Ohm	-
39159	BUK446-800A,B	800V, 1,7..2A, 30W, <4Ohm	2SK1275, 2SK1459, 2SK1611, 2SK1834
39160	BUK451-100A,B	100V, 3A, 40W, <1,1Ohm	IRF 612, IRF 613, 2SK923
39161	BUK451-60A,B	60V, 5A, 40W, <0,5Ohm	IRF 511, IRF 513, 2SK346, 2SK463
39162	BUK452-100A,B	100V, 10..11A, 60W, <0,3Ohm	BUZ 20, BUZ 72, 2SK918, 2SK921
39163	BUK452-50A,B	50V, 14..15A, 60W, <0,15Ohm	IRF 531, 2SK673, 2SK971, 2SK1416
39164	BUK452-60A,B	60V, 14..15A, 60W, <0,15Ohm	IRF 531, 2SK673, 2SK971, 2SK1416
39165	BUK453-100A,B	100V, 13..14A, 75W, <0,2Ohm	BUZ 21...22, 2SK919, 2SK929, 2SK1301
39166	BUK453-500A,B	500V, 1,6..1,7A, 75W, <7Ohm	BUZ 74, IRF 820, IRF 822, 2SK822, 2SK892
39167	BUK453-50A,B	50V, 20..22A, 75W, <0,1Ohm	BUZ 10, BUZ 21, 2SK600, 2SK674, 2SK972
39168	BUK453-60A,B	60V, 20..22A, 75W, <0,1Ohm	BUZ 21, 2SK600, 2SK674, 2SK972, 2SK1417
39169	BUK454-200A,B	200V, 8,2..9,2A, 75W, <0,5Ohm	BUZ 31...32, 2SK459, 2SK477, 2SK1319
39170	BUK454-400A,B	400V, 4,2..4,6A, 75W, <1,8Ohm	BUZ 41...42, BUZ 60, 2SK552...53, 2SK1751
39171	BUK454-450B	450V, 3,7A, 75W, <2,3Ohm	BUZ 41...42, 2SK552...53, 2SK893, 2SK1751
39172	BUK454-500A,B	500V, 3,3..3,7A, 75W, <2,8Ohm	BUZ 41...42, 2SK553, 2SK893, 2SK1751
39173	BUK454-600A,B	600V, 2,6..2,8A, 75W, <4,5Ohm	2SK513, 2SK791...792, 2SK1600...1601
39174	BUK454-800A,B	800V, 2..2,4A, 75W, <8Ohm	BUZ 50, BUZ 80, 2SK1199, 2SK1323
39175	BUK455-100A,B	100V, 23..26A, 125W, <0,1Ohm	-
39176	BUK455-200A,B	<0,28Ohm	-
39177	BUK455-400A,B	400V, 6,5..7,3A, 100W, <1Ohm	-
39178	BUK455-450B	450V, 5,7A, 100W, <1,3Ohm	-
39179	BUK455-500A,B	<1,5Ohm	-
39180	BUK455-50A,B	50V, 38..41A, 125W, <45mOhm	-
39181	BUK455-600A,B	600V, 4,5..4A, 100W, <2,5Ohm	-
39182	BUK455-60A,B,H	A41A, B3	
39183	BUK456-1000A,B	1000V, 3,1..3,5A, 125W, <5Ohm	-
39184	BUK456-100A,B	<65mOhm	-
39185	BUK456-200A,B	200V, 17..19A, 150W, <0,2Ohm	-
39186	BUK456-50A,B	50V, 51..52A, 150W, <0,03Ohm	-
39187	BUK456-60A,B,H	60V, 51..60A, 150W, <0,03Ohm	-
39188	BUK456-800A,B	800V, 3,5..4A, 125W, <4Ohm	-
39189	BUK457-400A,B	400V, 11..13A, 150W, <0,5Ohm	-
39190	BUK457-450B	450V, 10A, 150W, <0,6Ohm	-
39191	BUK457-500A,B	500V, 9..10A, 150W, <0,8Ohm	-
39192	BUK457-600A,B	600V, 7,1..8A, 150W, <1,2Ohm	-
39193	BUK471-...	BUK 441-..	BUK 441-...
39194	BUK472-...	BUK 442-..	BUK 442-...

39195	BUK473-...	BUK 443-..	BUK 443-...
39196	BUK474-...	BUK 444-..	BUK 444-...
39197	BUK475-...	BUK 445-..	BUK 445-...
39198	BUK476-...	BUK 446-..	BUK 446-...
39199	BUK481-100A	<0,8Ohm(1A)	BSP 296
39200	BUK481-60A	60V, 1,6A, <0,35Ohm(1,6A)	-
39201	BUK482-100A	<0,28Ohm(1,8A)	-
39202	BUK482-60A	60V, 2,7A, <0,13Ohm(2,7A)	-
39203	BUK483-60A	60V, 3,2A, <0,10Ohm(3,2A)	-
39204	BUK539-60A	60V, 50A, 230W, <15mOhm	-
39205	BUK541-100A,B	100V, 3A, 20W, <1,1Ohm	BUK 542-200
39206	BUK541-60A,B	60V, 5A, 20W, <0,5Ohm	BUK 554-200
39207	BUK542-100A,B	100V, 5,6..6,3A,22W,<0,35Ohm	BUK 543-100, 2SK1261, 2SK1556
39208	BUK542-50A,B	50V, 8,4..9,2A, 22W,<0,18Ohm	BUK 543-50, 2SK1033, 2SK1256, 2SK1344
39209	BUK542-60A,B	60V, 8,4..9,2A, 22W,<0,18Ohm	BUK 543-60, 2SK1033, 2SK1256, 2SK1344
39210	BUK543-100A,B	100V, 7,5..8,3A,25W,<0,22Ohm	2SK1035, 2SK1261, 2SK1305
39211	BUK543-50A,B	50V, 12..13A, 25W, <0,10Ohm	2SK1033, 2SK1256, 2SK1344
39212	BUK543-60A,B	60V, 12..13A, 25W, <0,10Ohm	2SK1033, 2SK1256, 2SK1344
39213	BUK545-100A,B	100V, 12..13A, 30W,<0,11Ohm	2SK1034...1035, 2SK1558, 2SK1306
39214	BUK545-200A,B	200V, 7..7,6A, 30W,<0,28Ohm	-
39215	BUK545-50A,B	50V, 18..21A, 30W, <55mOhm	2SK943, 2SK1095, 2SK1345...1346
39216	BUK545-60A,B	H, 21A, <3	2SK943, 2SK1095, 2SK1345...1346
39217	BUK551-100A,B	100V, 3A, 40W, <1,1Ohm	-
39218	BUK552-100A,B	100V, 8,5..10A, 60W,<0,35Ohm	2SK1300...1301, 2SK1559
39219	BUK552-50A,B	50V, 13..14A, 60W, <0,18Ohm	2SK971, 2SK1555
39220	BUK552-60A,B	60V, 14/56A, 60W, <0,18Ohm	2SK971, 2SK1301, 2SK1559
39221	BUK553-100A,B	100V, 12..13A, 75W,<0,22Ohm	2SK1301, 2SK1559, 2SK1561
39222	BUK553-48C	BUK 553-50A, 30V, Gate-Prot.	2SK972, 2SK1910, 2SK1287, 2SK1302
39223	BUK553-50A,B	50V, 20..21A, 75W, <0,10Ohm	2SK972, 2SK1115...16, 2SK1302, 2SK1347
39224	BUK553-60A,B	60V, 20..21A, 75W, <0,10Ohm	2SK972, 2SK1115...16, 2SK1302, 2SK1347
39225	BUK554-200A,B	200V, 8,2..9,2A,90W,<0,5Ohm	BUK 555-200
39226	BUK555-100A,B	100V, 22..25A, 125W,<0,11Ohm	-
39227	BUK555-200A,B	200V, 13..14A, 125W,<0,28Ohm	-
39228	BUK555-50A,B	50V, 35..39A, 125W, <55mOhm	-
39229	BUK555-60A,B,H	60V, 35..41A, 125W, <55mOhm	-
39230	BUK556-60A,C	60V, 50..60A, 150W, <26mOhm	2SK1542
39231	BUK571-...	BUK 541-..	BUK 541-...
39232	BUK572-...	BUK 542-..	BUK 542-...
39233	BUK573-...	BUK 543-..	BUK 543-...
39234	BUK575-...	BUK 545-..	BUK 545-...
39235	BUK581-100A	<0,9Ohm(0,9A)	BSP 296
39236	BUK581-60A	60V, 1,5A, <0,04Ohm	-
39237	BUK582-100A	<0,31Ohm(1,7A)	-
39238	BUK582-60A	60V, 2,5A, <0,15Ohm	-
39239	BUK583-60A	60V, 3,2A, <0,10Ohm	-

39240	500AE,BE	<0,18Ohm	-
39241	BUK627-400A,B	400V, 6,2..6,9A, 45W, <0,6Ohm	-
39242	BUK627-450B	450V, 5,6A, 45W, <0,65Ohm	-
39243	500A,B,C	500V, 4,5..5,6A, 45W, 0,9Ohm	-
39244	600A,B,C	600V, 3,5..4,3A, 45W, <1,4Ohm	-
39245	BUK637-400A,B	400V, 12..14A, 180W, <0,6Ohm	BUK 638-500
39246	BUK637-450B	450V, 11A, 180W, <0,65Ohm	BUK 638-500
39247	500A,B,C	500V, 9,5..11A, 180W, <0,9Ohm	BUK 638-500
39248	600A,B,C	600V, 7..9A, 180W, <1,4Ohm	BUK 638-800
39249	BUK638-1000A,B	1000V, 5,6..6,2A, 220W, <3Ohm	-
39250	BUK638-500A,B	<0,6Ohm	-
39251	BUK638-800A,B	<2,4Ohm	-
39252	BUK655-450B	450V, 5,7A, 100W, <1,3Ohm	-
39253	500A,B,C	500V, 5..5,7A, 100W, <1,7Ohm	-
39254	BUK657-400A,B	400V, 11..13A, 150W, <0,6Ohm	-
39255	BUK657-450B	450V, 10A, 150W, <0,65Ohm	-
39256	500A,B,C	500V, 8,5..10A, 150W, <0,9Ohm	-
39257	600A,B,C	600V, 6,5..8A, 150W, <1,4Ohm	-
39258	BUK854-500TS	500V, 15A, 85W	IGT 4 D10...11
39259	BUK854-800A	800V, 12A, 85W	BUP 202
39260	BUK856-400IZ	350..500V, 20A, 125W	BUP 203
39261	BUK856-450IX	400..500V, 15A, 125W	BUP 203
39262	BUK856-800A	800V, 24A, 125W	BUP 203
39263	BUL213	1300/600V, 3A, 60W, <-/6,35µs	BU 505, 2SC4021
39264	BUL213	1300/600V, 3A, 60W, <-/6,35µs	BU 505, 2SC4021
39265	BUL216	1600/800V, 4A, 70W, <-/4,02µs	-
39266	BUL216	1600/800V, 4A, 70W, <-/4,02µs	-
39267	BUL26	600/300V, 4A, 60W, <-/3µs	BUT 11(A), MJE 13070, 2SC3830
39268	BUL381	800/400V, 5A, 70W, <-/2,72	BUT 11(A), BUT 46, BUV 46(A), 2SC3047
39269	BUL382	800/400V, 5A, 70W, <-/2,72	BUT 11(A), BUT 46, BUV 46(A), 2SC3047
39270	BUL38D	800/400V, 5A, 70W, <-/1,9µs	BUT 11(A), BUT 46, BUV 46(A), 2SC3047
39271	BUL410	1000/450V, 7A, 75W, <-/2,11µs	BUT 12A, BUT 56A, BUV 56A, BUV 66A
39272	BUL416	1600/800V, 6A, 85W, <-/2,95µs	-
39273	BUL48	800/400V, 7A, 75W, <-/2,1µs	BUT 12(A), BUT 54, BUV 56(A)
39274	BUL510	1000/450V, 8A, 75W, <-/3,55µs	BUT 12A, BUT 56A, BUV 56A, BUV 66A
39275	BUL57	700/400V, 7A, 75W, <-/2,71µs	BUF 405(A), BUT 12(A), BUT 56(A)
39276	BUL57PI	BUL 57, , 35W	BU 307F, BUT 12(A), BUT 22BF,CF
39277	BUL67	700/400V, 8A, 80W, <-/3,38µs	BUF 405(A), BUT 12(A), BUT 56(A)
39278	BUL810	1000/450V, 15A, 125W, <-/2,41	BUV 48A, BUW 13A, BUW 133A, 2SC3552
39279	BUL87	700/400V, 10A, 90W, <-/4,05µs	BUT 76(A), BUV 56(A), BUV 66(A)
39280	BULD125	600V, 12A, 125W	-
39281	BULD85	600V, 8A, 85W	-
39282	BULK26	BUL 26, 50W	-
39283	BULK381	BUL 381, 60W	-
39284	BULK382	BUL 382, 60W	-



39285	BULK38D	BUL 38D, 60W	-
39286	BUP101	1000V, 15A, 90W	-
39287	BUP200	1200V, 3,6A, 50W	-
39288	BUP202	1000V, 12A, 100W	-
39289	BUP203	1000V, 23A, 165W	-
39290	BUP213	1000V, 32A, 200W	-
39291	BUP22	550/300V, 8A, 125W	BUV 47(A), BUW 12(A), 2SC3089, 2SC3449
39292	BUP22A	BUP 22, 650/350V	BUV 47(A), BUW 12(A), 2SC3089, 2SC3449
39293	BUP22B	BUP 22, 750/400V	BUV 47(A), BUW 12(A), 2SC3089, 2SC3449
39294	BUP22BF	BUP 22B	2SC4429
39295	BUP22C	BUP 22, 850/450V	BUV 47(A), BUW 12(A), 2SC3536
39296	BUP22CF	BUP 22C	2SC4429
39297	BUP23	550/300, 15A, 175W	BUX 98AP, 2SC3988
39298	BUP23A	BUP 23, 650/350V	BUX 98AP, 2SC3988
39299	BUP23B	BUP 23, 750/400V	BUX 98AP, 2SC3988
39300	BUP23BF	BUP 23B	BUX 98API
39301	BUP23C	BUP 23, 850/450V	BUX 98AP
39302	BUP23CF	BUP 23C	BUX 98API
39303	BUP300	BUP 200, 40W	-
39304	BUP302	BUP 202, 125W	GT 15N101, GT 15Q101
39305	BUP303	BUP 203, 200W	-
39306	BUP304	1000V, 35A, 310W	-
39307	BUP305D	BUP 202	-
39308	BUP306D	BUP 203	-
39309	BUP307	BUP 304, 1200V	-
39310	BUP307D	BUP 307	-
39311	BUP309	1700V, 25A, 310W	-
39312	BUP313D	BUP 213	-
39313	BUP314	1000V, 52A, 300W	-
39314	BUP314D	BUP 314, 42A	-
39315	BUP400	600V, 22A, 100W	-
39316	BUP400D	BUP 400	-
39317	BUP401	600V, 29A, 125W	-
39318	BUP402	600V, 36A, 150W	-
39319	BUP403	600V, 42A, 150W	-
39320	BUP410D	int. Freil	-
39321	BUP602D	BUP 402	-
39322	BUP603D	BUP 403	-
39323	BUP604	600V, 80A, 300W	-
39324	BUR10	100/80V, 5A, 30W(Tc100°)	-
39325	BUR11	300/200V, 20A, 175W	2N6324...6325
39326	BUR12	200/120V, 10A, 40W	2N5540
39327	BUR13	200/125V, 70A, 250W	-
39328	BUR14	150/120V, 3A, 7W(Tc25°)	BU 125S, BUX 49...53, 2SD625
39329	BUR15	150/120V, 3A, 7W(Tc25°)	BUY 90

39330	BUR20	200/125V, 50A, 250W, 24MHz	BUT 90, BUT 100, BUV 60
39331	BUR22	350/250V, 40A, 250W, 20MHz	BUV 62
39332	BUR23	400/325V, 30A, 250W, 20MHz	BUV 23, BUX 23, 2N6323
39333	BUR24	BUR 23, 450/400V	2SC2761, 2SC2930
39334	BUR30	-/125V, 250W	-
39335	BUR31	-/200V, 250W	-
39336	BUR32	-/250V, 250W	-
39337	BUR33	-/325V, 250W	-
39338	BUR34	-/400V, 250W	-
39339	BUR50(S)	200/125V, 70A, 350W	BUS 50
39340	BUR51	300/200V, 60A, 350W	-
39341	BUR52	350/250V, 60A, 350W	-
39342	BUR53	-/325V, 350W	-
39343	BUR54	-/400V, 350W	-
39344	BUR55	-/600V, 250W	-
39345	BUR56	-/700V, 250W	-
39346	BUR60	-/125V, 350W	-
39347	BUR61	-/200V, 350W	-
39348	BUR62	-/250V, 350W	-
39349	BUS11	850/400V, 5A, 100W	BUX 47, BUX 83, 2SC3048, 2SD802
39350	BUS11A	BUS 11, 1000/450V	BUX 83, MJ 8502, 2SC3060, 2SC3214
39351	BUS12	850/400V, 8A, 125W	BUW 36, BUX 81, MJ 8504, 2SC3061
39352	BUS12A	BUS 12, 1000/450V	BUX 81, MJ 8504, 2SC3061, 2SC3215
39353	BUS13	850/400V, 15A, 175W	BUW 46, BUX 48, 2SC3593
39354	BUS131(H)	850/450V, 5A, 125W	BUS 11(A), BUX 83, 2SC3156, 2SD802
39355	BUS131A	BUS 131, 1000/500V	BUS 11A, BUX 83, 2SC3060, 2SC3214
39356	BUS132(H)	850/450V, 8A, 150W	BUS 12(A), BUW 36, BUX 81, 2SC3061
39357	BUS132A	BUS 132, 1000/500V	BUS 12A, BUX 81, MJ 8504, 2SC3061
39358	BUS133(H)	850/450V, 15A, 175W	BUS 13(A), BUS 97(A), BUW 46, BUX 48
39359	BUS133A	BUS 133, 1000/500V	BUS 13A, BUS 97A, BUX 48A...C
39360	BUS13A	BUS 13, 1000/450V	2SC3216
39361	BUS14	850/400V, 30A, 250W	BUS 98(A)
39362	BUS14A	BUS 14, 1000/450V	BUS 98A
39363	BUS21	550/300V, 5A, 100W	BUS 11(A), BUX 82...83, 2SC3048
39364	BUS21A	BUS 21, 650/350V	BUS 11(A), BUX 82...83, 2SC3048
39365	BUS21B	BUS 21, 750/400V	BUS 11(A), BUX 82...83, 2SC3048
39366	BUS21C	BUS 21, 850/450V	BUS 11(A), BUX 83, 2SC3048, 2SC3156
39367	BUS22	550/300V, 8A, 125W	BUS 12(A), BUW 36, BUX 47(A), 2SD811
39368	BUS22A	BUS 22, 650/350V	BUS 12(A), BUW 36, BUX 47(A), 2SD811
39369	BUS22B	BUS 22, 750/400V	BUS 12(A), BUW 36, BUX 47(A), 2SD811
39370	BUS22C	BUS 22, 850/450V	BUS 12(A), BUW 36, BUX 47(A), 2SD811
39371	BUS23	550/300V, 15A, 175W	BUS 13(A), BUS 97(A), BUW 45...46
39372	BUS23A	BUS 23, 650/350V	BUS 13(A), BUS 97(A), BUW 45...46
39373	BUS23B	BUS 23, 750/400V	BUS 13(A), BUS 97(A), BUW 45...46
39374	BUS23C	BUS 23, 850/450V	BUS 13(A), BUS 97(A), BUW 46, BUX 48

39375	BUS24B	750/400V, 30A, 250W	BUS 14(A), BUS 98(A), BUX 348(A)
39376	BUS24C	BUS 24B, 850/450V	BUS 14(A), BUS 98(A), BUX 348(A)
39377	BUS36	250/120V, 12A, 107W, >30MHz	BUV 27(A), BUV 28(A)
39378	BUS37	BUS 36, 300/150V	BUV 27A, BUV 28(A)
39379	BUS45P	850/450V, 3A, 75W	BUT 11(A), BUV 46(A), 2SC3490...3491
39380	BUS46P	850/450V, 5A, 80W	BUT 11(A), BUV 46(A), 2SC3047
39381	BUS47	850/450V, 9A, 150W	BUS 12(A), BUW 36, BUX 81, MJ 8504
39382	BUS47A	BUS 47, 1000/450V	BUS 12A, BUX 81, MJ 8504
39383	BUS47AP	BUS 47, 1000/450V, 107W	BUV 47A, BUW 12A
39384	BUS47P	BUS 47, 107W	BUV 47(A), BUW 12(A)
39385	BUS48	850/450V, 15A, 175W	BUS 13(A), BUW 46, BUX 48
39386	BUS48A	BUS 48, 1000/450V	BUS 13A, 2SC3216
39387	BUS48AP	BUS 48, 1000/450V, 125W	BUV 48A...C, BUW 13A, 2SC3552
39388	BUS48P	BUS 48, 125W	BUV 48(A...C), BUW 13(A), 2SC3552
39389	BUS50	200/125V, 70A, 350W	BUR 50
39390	BUS51	300/200V, 50A, 350W	BUR 51
39391	BUS52	BUS 51, 350/250V, 40A	BUR 52
39392	BUS97	850/400V, 18A, 175W	BUS 13(A), BUX 48(A...C), 2SC3593
39393	BUS97A	BUS 97, 1000/450V	BUS 13A, BUX 48A...C, 2SC3593
39394	BUS98	850/450V, 30A, 250W	BUS 14(A)
39395	BUS98A	BUS 98, 1000/450V	BUS 14A
39396	BUT100	200/125V, 50A, 300W	BUT 90, BUR 20, BUV 60...61
39397	BUT102	400/300V, 50A, 300W	BUT 92A
39398	BUT11	850/400, 5A, 100W, <1/4,8μs	BUS 46P, BUV 46(A), 2SC3047
39399	BUT11A	BUT 11, 1000/450V	BUV 46A, MJE 8502, 2SC3050
39400	BUT11AX	BUT 11A, , 20W	BUT 11AF
39401	BUT11F,AF	BUT 11(A), , 20W	BUT 18(A)F
39402	BUT11FI,AFI	BUT 11(A), , 35W	BUT 18(A)F
39403	BUT12	850/400, 6A, 125W, <1/4,8μs	BUT 76(A), BUV 56(A), BUV 66(A)
39404	BUT12A	BUT 12, 5A, 125W	BUT 76A, BUV 56A, BUV 66A
39405	BUT12AF	BUT 12(A), , 23W	-
39406	BUT12FI,AFI	BUT 12(A)	-
39407	BUT13	600/400V, 28A, 175W	MJ 10023
39408	BUT131(H)	850/450V, 5A, 80W	BUT 11(A), BUT 18(A), BUV 46(A)
39409	BUT131A	BUT 131(H), 1000/450V	BUT 11A, BUT 18A, BUV 46A, 2SC3050
39410	BUT13P	BUT 13, 150W	-
39411	BUT13PFI	BUT 13P, , 60W	-
39412	BUT14	850/500V, 25A, 175W	BUT 35...36
39413	BUT15	1000/700V, 20A, 175W	MJ 10024...10025
39414	BUT16	1400/1000V, 12A, 150W	-
39415	BUT18	850/400V, 6A, 110W	BUT 12(A), BUT 56(A)
39416	BUT18(A)F	BUT 18(A), , 33W	BUT 12(A)F
39417	BUT18A	BUT 18, 1000/450V	BUT 12A, BUT 56A
39418	BUT211	850/400, 5A, 100W, <-1/2,8μs	BUS 46P, BUV 46(A), 2SC3047
39419	BUT211X	BUT 211	BUT 11(A)F, BUT 21CF, 2SC3795A

39420	BUT21B	750/400V, 5A, 100W	BUT 12(A), BUT 56(A)
39421	BUT21BF	BUT 21B, , 20W	BUT 11(A)F, BUT 12(A)F, BUT 18(A)F
39422	BUT21C	BUT 21B, 850/450V	BUT 12(A), BUT 56(A)
39423	BUT21CF	BUT 21C, , 20W	BUT 11(A)F, BUT 12(A)F, BUT 18(A)F
39424	BUT22B	750/400V, 8A, 125W	BUT 12(A), BUT 76(A), BUV 56(A)
39425	BUT22BF	BUT 22B, , 23W	BUT 12(A)F
39426	BUT22C	BUT 22B, 850/450V	BUT 12(A), BUT 76(A), BUV 56(A)
39427	BUT22CF	BUT 22C, , 23W	BUT 12(A)F
39428	BUT230(F,V)	200/125V, 200A, 300W	-
39429	BUT232(F,V)	400/300V, 140A, 300W	-
39430	BUT30(F,V)	200/125V, 100A, 250W	-
39431	BUT30(F,V)	200/125V, 100A, 250W	-
39432	BUT32(V)	400/300V, 80A, 250W	-
39433	BUT32(V)	400/300V, 80A, 250W	-
39434	BUT33	600/400V, 56A, 250W	MJ10015...10016
39435	BUT34	850/500V, 50A, 250W	-
39436	BUT35	1000/700V, 40A, 250W	-
39437	BUT36	1400/1000V, 24A, 250W	-
39438	BUT44D	700/400V, 4A, 63W, 160/-ns	-
39439	BUT46	850/400V, 5A, 75W	BUT 11(A), BUT 18(A), BUV 46(A)
39440	BUT46A	BUT 46, 1000/450V	BUT 11A, BUT 18A, BUV 46A, 2SC3050
39441	BUT50P	850/500V, 8A, 100W	2SC3030, 2SC3032
39442	BUT51P	850/500V, 15A, 125W	BUD 48
39443	BUT54	800/430V, 8A, 100W, 10MHz	BUT 56(A), BUV 56
39444	BUT55	400/400V, 12A, 105W, B>100	-
39445	BUT56	800/400V, 8A, 100W, 10MHz	BUT 12(A), BUT 54, BUV 56(A)
39446	BUT56A	BUT 56, 1000/450V	BUT 12A, BUT 76A, BUV 56A
39447	BUT56A/668	BUT 56A	BUT 56A
39448	BUT56AF	BUT 56	BUT 12AF
39449	BUT56H,PH	BUT 56A	BUT 56A
39450	BUT56T	BUT 56A	BUT 56A
39451	BUT57	400/400V, 15A, 110W, B>200	BUT 51P
39452	BUT57I	BUT 57, , 80W	-
39453	BUT60	200/125V, 15A, 125W	BUS 36...37, BUV 27(A)
39454	BUT62	BUT 60, 400/300V	BUV 28(A)
39455	BUT70	200/125V, 40A, 200W	-
39456	BUT70	200/125V, 40A, 200W	-
39457	BUT70I	BUT 70, , 115W	-
39458	BUT71	300/200V, 40A, 175W	-
39459	BUT71I	BUT 71, , 100W	-
39460	BUT72	400/300V, 40A, 200W	-
39461	BUT72I	BUT 72, , 115W	-
39462	BUT76	850/400V, 10A, 100W	BUV 56(A), BUV 66(A)
39463	BUT76A	BUT 76, 1000/450V	BUV 56A, BUV 66A
39464	BUT76AF	BUT 76	BUT 12AF

39465	BUT90	200/125V, 50A, 250W	BUT 100, BUR 20
39466	BUT91	BUT 90, 300/200V	BUT 102, BUR 51...52
39467	BUT92	BUT 90, 350/250V	BUT 102, BUR 52
39468	BUT92A	BUT 90, 400/300V	BUT 102
39469	BUT93	600/350V, 4A, 55W, 9MHz	BUT 11(A), BUV 46(A), 2SC3086, 2SD841
39470	BUT93D		-
39471	BUT98	850/450V, 30A, 200W	-
39472	BUT98A	BUT 98, 1000/450V	-
39473	BUV10	160/125V, 25A, 150W, >8MHz	BUW 39, BUX 10, BUX 40, 2N6322
39474	BUV10N	BUV 10, 175W	2N6322
39475	BUV11	250/220V, 20A, 150W, >8MHz	BUW 58, BUW 73, BUX 11...12, 2N6322
39476	BUV11N	BUV 11, 220/160V	BUW 58, BUW 73, BUX 11...12, 2N6322
39477	BUV12	300/250V, 20A, 150W, >8MHz	BUW 73, BUX 12, 2N6322
39478	BUV18	120/60V, 50A, 250W, >8MHz	BUR 20, BUV 19...20, BUX 20
39479	BUV18A	BUV 18, 120/100V	BUR 20, BUV 19...20, BUX 20
39480	BUV19	160/80V, 50A, 250W, >8MHz	BUR 20, BUV 20, BUX 20
39481	BUV20	160/125V, 50A, 250W, >8MHz	BUR 20, BUR 50, BUX 20
39482	BUV21	250/200V, 40A, 250W, >8MHz	BUR 21...22, BUV 22, BUV 61, BUX 21...22
39483	BUV21N	BUV 21, 220/160V	BUR 21...22, BUV 22, BUV 61, BUX 21...22
39484	BUV22	300/250V, 40A, 250W, >8MHz	BUR 21...22, BUV 61...62, BUX 22
39485	BUV23	400/325V, 30A, 250W, >8MHz	BUX 23, 2N6323
39486	BUV24	450/400V, 20A, 250W, >8MHz	BUX 24
39487	BUV25	500/500V, 15A, 250W, >8MHz	BUX 25
39488	BUV26	180/90V, 20A, 85W	-
39489	BUV26A	BUV 26, 200/100V	-
39490	BUV26F,AF	BUV 26(A), , 18W	-
39491	BUV27	240/120V, 15A, 85W	BUS 36...37
39492	BUV27A	BUV 27, 300/150V	BUS 37
39493	BUV27F,AF	BUV 27(A), , 18W	-
39494	BUV28	400/200V, 12A, 85W	MJE 13008...13009
39495	BUV28A	BUV 28, 450/225V	MJE 13008...13009
39496	BUV28F,AF	BUV 28(A), , 18W	2SC4163
39497	BUV298(V)	850/400V, 60A, 250W	-
39498	BUV298(V)	850/400V, 60A, 250W	-
39499	BUV298A(V)	BUV 298, 1000/450V	-
39500	BUV298A(V)	BUV 298, 1000/450V	-
39501	BUV298C(V)	BUV 298, 1200/700V	-
39502	BUV298C(V)	BUV 298, 1200/700V	-
39503	BUV30	-/400V, 8A, 83W, B>250	-
39504	BUV36	850/400V, 2A, 50W	BUT 11(A), BUS 45, BUV 46(A), BUX 85
39505	BUV36A	BUV 36, 1000/450V	BUT 11A, BUV 46A, BUX 85, 2SC3491
39506	BUV37	450/400V, 15A, 125W, B>20	2SD1466
39507	BUV39	160/90V, 25A, 120W	BUV 10, BUX 10, BUX 40, 2N6322
39508	BUV40	250/125V, 20A, 120W	BUV 11, BUW 58, BUX 11, 2N6322
39509	BUV41	300/200V, 15A, 120W	BUV 12, BUW 73, BUX 12, 2N6322

39510	BUV42	350/250V, 12A, 120W	BUW 74, BUX 13, BUY 50, MJ 15024
39511	BUV42A	BUV 42, 400/300V	BUW 74, BUX 13, BUY 50, MJ 15024
39512	BUV46	850/400V, 6A, 85W, 12MHz	BUT 11(A), BUT 56(A), 2SC3047
39513	BUV46A	BUV 46, 1000/450V	BUT 11A, BUT 12A, BUT 56A, 2SC3050
39514	BUV46FI,AFI	BUV 46(A), , 30W	BUT 11(A)F, BUT 12(A)F, BUT 18(A)F
39515	BUV47(B)	850/400V, 9A, 120W, 7MHz	BUV 48(A...C), BUW 12(A)...13(A), 2SC3552
39516	BUV47A	BUV 47(B), 1000/450V	BUV 48A...C, BUW 12A...13A, 2SC3552
39517	BUV47AF	BUV 47A	2SC4429
39518	BUV47F	BUV 47	BUP 22CF, 2SC4429
39519	BUV47FI,AFI	BUV 47(A), , 55W	BUP 22CF, 2SC4429
39520	BUV48	850/400V, 15A, 150W, 5MHz	BUW 13(A), 2SC3552
39521	BUV48A	BUV 48, 1000/450V	BUW 13A, 2SC3552
39522	BUV48AF	BUV 48A	BUX 98API
39523	BUV48B	BUV 48, 1200/600V	2SC3644
39524	BUV48C	BUV 48, 1200/700V	2SC3644
39525	BUV48F	BUV 48	BUP 23CF, BUX 98(A)PI
39526	BUV48FI,AFI	BUV 48(A), , 65W	BUP 23CF, BUX 98(A)PI
39527	BUV48T	BUV 48	-
39528	BUV50	250/125V, 25A, 150W	BUV 11, BUX 11, 2N6322
39529	BUV51	300/200V, 20A, 150W	BUV 12, BUW 73, BUX 12, 2N6322
39530	BUV52	350/250V, 20A, 150W	BUV 23, BUX 23, 2N6323
39531	BUV52A	BUV 52, 400/300V	BUV 23, BUX 23, 2N6323
39532	BUV54	-/400V, 18A, 150W, B>20	BUT 15, MJ 10024...10025
39533	BUV54A	BUV 54, -/600V	MJ 10025
39534	BUV56	850/400V, 9A, 70W	BUV 66(A)
39535	BUV56A	BUV 56, 1000/450V	BUV 66A
39536	BUV60	250/125V, 50A, 250W	BUR 51...52
39537	BUV61	300/200V, 50A, 250W	BUR 51...52
39538	BUV62	350/250V, 40A, 250W	BUR 22, BUR 52
39539	BUV62A	BUV 62, 400/300V	-
39540	BUV63	600/350V, 1,5A, 10W	BUV 93...95
39541	BUV66	850/400V, 15A, 100W	-
39542	BUV66A	BUV 66, 1000/450V	-
39543	BUV70	1300/550V, 10A, 140W, 9MHz,	2SC4023
39544	BUV70F	BUV 70	2SC4199(A)
39545	BUV71	1500/800V, 9A, 140W, 9MHz	2SC4023
39546	BUV71F	BUV 71	2SC4199A
39547	BUV74	600/400V, 36A, 250W, B>20	MJ 10023
39548	BUV74A	BUV 74, 1000/600V	BUT 35
39549	BUV82	850/400V, 6A, 100W, 6MHz	BUW 11(A), BUW 12(A), 2SC3153, 2SC3232
39550	BUV83	BUV 82, 1000/450V	BUW 11A, BUW 12A, BUW 131A, 2SC3535
39551	BUV89	1200/800V, 8A, 125W, 7MHz	BU 908, BUV 70...71, 2SC3466
39552	BUV90(A)	650/400V, 12A, 125W	BUT 51P
39553	BUV90F	BUV 90(A), , 34W	-
39554	BUV93	600/350V, 2A, 15W, 12MHz	-



39555	BUV94	BUV 93, 800/400V	-
39556	BUV95	BUV 93, 1000/450V	-
39557	BUV98(F,V)	850/400V, 30A, 150W	-
39558	BUV98(F,V)	850/400V, 30A, 150W	-
39559	BUW11	BUS 11	BUV 82, BUW 131(A), 2SC3232, 2SC3387
39560	BUW11A	BUS 11A	BUV 83, BUW 131A, 2SC3387, 2SC3535...36
39561	BUW11AF	BUW 11A, , 32W	BUV 47AFI, 2SC4427
39562	BUW11F	BUW 11, , 32W	BUV 47(A)FI, 2SC4427
39563	BUW12	BUS 12	BUV 47(A), BUW 48(A...C), BUW 13(A)
39564	BUW12A	BUS 12A	BUV 47A, BUW 48A...C, BUW 13A
39565	BUW12AF	BUW 12A, , 34W	BUV 47AFI, 2SC4429
39566	BUW12F	BUW 12, , 34W	BUV 47(A)FI, 2SC4429
39567	BUW13	BUS 13	BUV 48(A...C), 2SC3552
39568	BUW131(H)	850/450V, 5A, 80W	BUV 82...83, BUW 11(A), 2SC3535...36
39569	BUW131A	BUW 131, 1000/450V	BUV 83, BUW 11A, 2SC3535...36
39570	BUW132(H)	850/450V, 8A, 125W	BUV 47(A), BUW 12(A), 2SC3637
39571	BUW132A	BUW 132, 1000/450V	BUV 47A, BUW 12A
39572	BUW133(H)	850/450V, 15A, 135W	BUV 48(A), BUW 13(A), 2SC3638
39573	BUW133A	BUW 133, 1000/450V	BUV 48A, BUW 13A, 2SC3552, 2SC3644
39574	BUW13A	BUS 13A	BUV 48A...C, 2SC3552
39575	BUW13AF	BUW 13A, , 37W	BUV 48AFI, BUX 98API
39576	BUW13F	BUW 13, , 37W	BUV 48(A)FI, BUX 98(A)PI
39577	BUW14	1000/450V, 0,5A, 20W, 20MHz	BUX 87, 2SC3456, 2SD1527
39578	BUW16	450/400V, 10A, 100W	BU 223, BUW 24, BUW 72, BUX 14
39579	BUW17	450/400V, 15A, 100W	BUV 25, BUW 44, BUX 25, 2SD641
39580	BUW18	250/200V, 30A, 200W	2SC1301, 2SC2249, 2SC2445
39581	BUW19	BUW 18, 450/400V	2SC1470, 2SC2250
39582	BUW22	400/350V, 6A, 100W	BUW 32, BUW 42, MJ 15025
39583	BUW22A	BUW 22, 450/400V	BUW 32A, BUW 42A
39584	BUW22AP	BUW 22, 450/400V, 60W	2SA1500, MJE 5851...5852
39585	BUW22P	BUW 22, 60W	MJ 5852
39586	BUW23	450/400V, 10A, 125W	BUW 32, BUW 42
39587	BUW24	450/350V, 10A, 100W, 20MHz	BU 223, BUW 72, BUX 14, BUX 17C
39588	BUW25	600/400V, 10A, 125W, 20MHz	BUS 12(A), BUW 35...36, 2SC3046
39589	BUW26	800/450V, 10A, 125W, 20MHz	BUS 12(A), BUW 35...36, BUX 80...81
39590	BUW28	350/350V, 10A, 100W, B>70	BU 323(A), BU 920...922, BUW 66
39591	BUW29	BUW 28, 400V, B>45	BU 323(A), BU 920...922, BUW 66
39592	BUW32	400/350V, 10A, 125W	BUW 23, BUW 42(A)
39593	BUW32A	BUW 32, 450/400V	BUW 23, BUW 42A
39594	BUW32AP	BUW 32, 450/400V, 105W	BUW 42AP
39595	BUW32P	BUW 32, 105W	BUW 42(A)P
39596	BUW32PFI,APFI	BUW 32(A), , 55W	BUW 42(A)PFI
39597	BUW34	500/400V, 10A, 125W	BUS 12(A), BUW 25, BUY 69C, 2SC3046
39598	BUW35	BUW 34, 800/400V	BUS 12(A), BUW 26, BUX 80...81
39599	BUW36	BUW 34, 900/450V	BUS 12A, BUX 81, BUY 69A, MJ 8504

39600	BUW37	>25MHz	BSS 48...49, BUX 55, BUY 59...60, 2N3440
39601	BUW38	120/60V, 30A, 150W, >8MHz	BUY 21, BUW 39, BUX 21, BUX 39
39602	BUW39	160/80V, 30A, 150W, >8MHz	BUY 21, BUX 21
39603	BUW40	450/300V, 1A, 40W, >10MHz	TIP 49...50, 2SB859B
39604	BUW40A	BUW 40, 550/350V	BUY 36(A), BUX 84...85
39605	BUW40B	BUW 40, 650/400V	BUY 36(A), BUX 84...85
39606	BUW41	450/300V, 8A, 100W, >15MHz	BUT 56(A), BUY 56(A), 2SC2427, 2SC2739
39607	BUW41A	BUW 41, 550/350V	BUT 56(A), BUY 56(A)
39608	BUW41B	BUW 41, 650/400V	BUT 56(A), BUY 56(A)
39609	BUW42	400/350V, 15A, 150W	MJ 15025
39610	BUW42A	BUW 42, 450/400V	-
39611	BUW42AP	BUW 42, 450/400V, 105W	-
39612	BUW42P	BUW 42, 105W	-
39613	BUW42PFI,APFI	BUW 42(A), , 65W	-
39614	BUW44	500/400V, 15A, 175W	BUS 13(A), BUY 25, BUX 25, BUX 48
39615	BUW45	BUW 44, 800/400V	BUS 13(A), BUX 48(A...C)
39616	BUW46	BUW 44, 900/450V	BUS 13A, BUX 48A...C
39617	BUW48	BUW 38	BUX 69
39618	BUW49	BUW 39	BUX 69
39619	BUW50	BUY 50	-
39620	BUW51	BUY 51	-
39621	BUW52	BUY 52	-
39622	BUW52I	BUW 52, , 90W	-
39623	BUW57	150/125V, 20A, 120W, 15MHz	BUY 10...12, BUX 10...12, BUX 40
39624	BUW58	BUW 57, 250/160V	BUY 11...12, BUW 73, BUX 11...12
39625	BUW60	250/125V, 40A, 175W	-
39626	BUW60I	BUW 60, , 100W	-
39627	BUW61	300/200V, 40A, 175W	-
39628	BUW61I	BUW 61, , 100W	-
39629	BUW62	400/300V, 40A, 175W	-
39630	BUW62I	BUW 62, , 100W	-
39631	BUW64A	140/90V, 7A, 50W, >50MHz	BU 409, TIP 150...152, 2SC2867
39632	BUW64B	BUW 64A, 160/110V	BU 409, TIP 150...152, 2SC2867
39633	BUW64C	BUW 64A, 180/130V	BU 409, TIP 150...152, 2SC2867
39634	BUW66	400/200V, 10A, 90W	BU 323(A), BU 920...922, BUW 29, 2SD565
39635	BUW67	BUW 66, 330/200V	BU 323(A), BU 920...922, BUW 29, 2SD565
39636	BUW70	150/100V, 10A, 80W	BU 223(A), BUW 24, BUX 17(A...C)
39637	BUW71	450/400V, 5A, 100W	BU 223(A), BUW 24...25, BUX 17C
39638	BUW72	450/400V, 10A, 100W	BU 223(A), BUW 24...25, BUX 17C
39639	BUW73	300/200V, 20A, 120W	BUY 12, BUX 12, 2N6322
39640	BUW74	400/250V, 12A, 120W, 20MHz	BUX 13, BUY 50, MJ 15024, 2SC3043
39641	BUW75	BUW 74, 600/300V	BUS 13(A), BUW 45...46, BUX 48
39642	BUW76	BUW 74, 750/350V	BUS 13(A), BUW 45...46, BUX 48
39643	BUW77	BUW 74, 800/400V	BUS 13(A), BUW 45...46, BUX 48
39644	BUW81	600/600V, 10A, 80W	MJ 10013...10014, 2SD685

39645	BUW81A	BUW 81, 800/800V	BUT 16
39646	BUW84	20MHz	BUV 36A, BUX 84...85, 2SC3531
39647	BUW85	BUW 84, 1000/450V	BUV 36A, BUX 85, 2SC3531
39648	BUW86	240/120V, 10A, 62,5W, 50MHz	BUX 17(A...C), BUW 24, BUW 72, BUW 74
39649	BUW87	BUW 86, 300/150V	BUX 17A...C, BUW 24, BUW 72, BUW 74
39650	BUW87A	BUW 86, 400/200V	BUX 17B...C, BUW 24, BUW 72, BUW 74
39651	BUW89	BUV 39	BUW 49...50, BUX 69...70
39652	BUW90	BUV 40	BUW 50...52, BUX 70
39653	BUW91	BUV 41	BUW 51...52
39654	BUW92	BUV 42	BUW 52
39655	BUW92I	BUW 92, , 75W	2SC4297, 2SC4423
39656	BUW96	200/150V, 15A, 150W	BUW 42(A)P
39657	BUX10	160/125V, 25A, 150W, >8MHz	BUV 10, BUW 39, 2N6322
39658	BUX100	<650/6500ns	BUT 93, BUX 84
39659	BUX10A	BUX 10, 170/125V, >50MHz	BUV 10, BUW 39, 2N6322
39660	BUX10P	BUX 10, 106W	BUW 49...50, BUX 69...70
39661	BUX11	250/200V, 20A, 150W, >8MHz	BUV 11...12, BUW 58, BUW 73, 2N6322
39662	BUX11A	BUX 11, 200W	2N6322
39663	BUX11N	BUX 11, 220/160V	BUV 11...12, BUW 58, BUW 73, 2N6322
39664	BUX12	300/250V, 20A, 150W, >8MHz	BUV 12, BUW 73, 2N6322
39665	BUX127	-/400V, 15A, 125W, B>200	BU 931P...932P, BUV 37, BUT 51P
39666	BUX13	400/325V, 15A, 150W, >8MHz	BUV 25, BUW 44, BUX 25, MJ 15024
39667	BUX14	450/400V, 10A, 150W, >8MHz	BUW 34, BUW 75...77, BUX 17C
39668	BUX15	500/500V, 8A, 150W, >8MHz	BUW 34, BUW 75...77
39669	BUX16	250/200V, 5A, 100W, >5MHz	BU 222(A), BUW 71, BUX 44...45
39670	BUX16A	BUX 16, 325/250V	BU 222(A), BUW 71, BUX 44...45
39671	BUX16B	BUX 16, 375/300V	BU 222(A), BUW 71, BUX 44...45
39672	BUX16C	BUX 16, 425/350V	BU 222(A), BUW 71, BUX 44...45
39673	BUX17	>2,5MHz	BUW 34, BUW 44, BUW 75, BUX 14
39674	BUX17A	BUX 17, 350/250V	BUW 34, BUW 44, BUW 75, BUX 14
39675	BUX17B	BUX 17, 400/300V	BUW 34, BUW 44, BUW 75, BUX 14
39676	BUX17C	BUX 17, 450/350V	BUW 34, BUW 44, BUW 75, BUX 14
39677	BUX18	250/200V, 8A, 120W	BUW 25, BUW 34, BUW 72, BUX 14
39678	BUX18A	BUX 18, 350/325V	BUW 25, BUW 34, BUW 72, BUX 14
39679	BUX18B	BUX 18, 400/375V	BUW 25, BUW 34, BUW 72, BUX 14
39680	BUX18C	BUX 18, 475/425V	BUW 25, BUW 34, BUW 72, BUX 14
39681	BUX20	160/125V, 50A, 350W, >8MHz	BUR 50...52
39682	BUX20A	BUX 20, 40A, 140W, >50MHz	BUR 21...22, BUV 21...22, BUV 60...62
39683	BUX21	250/200V, 40A, 350W, >8MHz	BUR 51...52, 2N6323
39684	BUX21	250/200V, 40A, 350W, >8MHz	BUR 51...52, 2N6323
39685	BUX22	300/250V, 40A, 350W, >10MHz	BUR 51...52, 2N6323
39686	BUX22	300/250V, 40A, 350W, >10MHz	BUR 51...52, 2N6323
39687	BUX23	400/325V, 30A, 350W, >8MHz	2N6323
39688	BUX24	450/400V, 20A, 350W, >8MHz	-
39689	BUX25	500/500V, 15A, 350W, >8MHz	-

39690	BUX26	750/350V, 6A, 60W(Tc75°)	BUS 12(A), BUW 35...36, BUX 47
39691	BUX27	BUX 26, 800/400V	BUS 12(A), BUW 35...36, BUX 47
39692	BUX28	B>50	BU 323(A), BUW 29, BUW 81(A)
39693	BUX28V	BUX 28, -/400V	BU 323(A), BUW 29, BUW 81(A)
39694	BUX29	BUX 28, 400/400V, B>30	BU 323(A), BUW 29, BUW 81(A)
39695	BUX30	-/400V, 10A, 90W, B>150	BU 920...922, BUW 66
39696	BUX30	-/400V, 10A, 90W, B>150	BU 920...922, BUW 66
39697	BUX30AV	BUX 30, -/350V, B>250	BU 920...922, BUW 66
39698	BUX30AVA	BUX 30, -/250V, B>250	BU 920...922, BUW 66
39699	BUX30AVB	BUX 30, -/300V, B>250	BU 920...922, BUW 66
39700	BUX30AVC	BUX 30, -/350V, B>250	BU 920...922, BUW 66
39701	BUX31	800/400V, 8A, 150W, >15MHz	BUS 12(A), BUW 35...36, MJ 8504, 2SC3061
39702	BUX31A	BUX 31, 900/450V	BUS 12A, BUW 36, MJ 8504, 2SC3061
39703	BUX31B	BUX 31, 1000/500V	BUS 12A, MJ 8504, 2SC3061, 2SC3215
39704	BUX32	800/400V, 8A, 150W, >15MHz	BUS 12(A), BUW 35...36, MJ 8504, 2SC3061
39705	BUX32A	BUX 32, 900/450V	BUS 12A, BUW 36, MJ 8504, 2SC3061
39706	BUX32B	BUX 32, 1000/500V	BUS 12A, MJ 8504, 2SC3061, 2SC3215
39707	BUX33	800/400V, 12A, 150W, >15MHz	BUS 13(A), BUW 45...46, BUX 48, 2SC3593
39708	BUX33A	BUX 33, 900/450V	BUS 13A, BUW 46, 2SC3593, 2SC3216
39709	BUX33B	BUX 33, 1000/500V	BUS 13A, 2SC3216
39710	BUX34	>70MHz	BU 125, BUY 47...48, BUY 68, BUY 80
39711	BUX348	850/400V, 45A, 300W	
39712	BUX348A	BUX 348, 1000/450V, 35A	BUS 14A, BUS 98A
39713	BUX35	250/160V, 15A, 140W, >3MHz	BUV 11...12, BUW 73, BUX 11...12, BUX 41
39714	BUX36	BUX 35, 250/200V	BUV 11...12, BUW 73, BUX 11...12, BUX 41
39715	BUX37	B>100	BU 930...932, BUT 51P
39716	BUX38	500/400V, 40A, 250W	2SC2366, 2SD642
39717	BUX39	120/90V, 30A, 120W, >8MHz	BUV 21...22, BUW 39, BUX 21...22, 2N6322
39718	BUX40(A)	160/125V, 20A, 120W, >8MHz	BUV 10...12, BUW 58, BUX 10...12, 2N6322
39719	BUX41	250/200V, 15A, 120W, >8MHz	BUV 11...12, BUW 58, BUW 73, BUX 11...12
39720	BUX41N	BUX 41, 220/160V, 18A	BUV 11...12, BUW 58, BUW 73, BUX 11...12
39721	BUX42	300/250V, 12A, 120W, >8MHz	BUW 44, BUW 74...77, BUX 13, BUY 50
39722	BUX43	400/325V, 10A, 120W, >8MHz	BUW 24...25, BUW 34, BUX 14, BUX 17C
39723	BUX44	450/400V, 8A, 120W, >8MHz	BUW 25, BUW 34, BUX 15, BUX 18C
39724	BUX45	500/500V, 5A, 120W, >8MHz	BUS 11(A), BUX 47, BUX 82...83, BUX 97
39725	BUX46	BUV 46	BUS 11(A), BUX 47, BUX 83, MJ 8502
39726	BUX46A	BUV 46A	BUS 11A, BUX 83, MJ 8502, 2SC3060
39727	BUX47(B)	BUV 47(B), 125W	BUS 12(A), BUW 36, BUX 81, MJ 8504
39728	BUX47A	BUV 47A, 125W	BUS 12A, BUX 81, MJ 8504, 2SC3061
39729	BUX48	BUV 48, 175W	BUS 13(A), BUW 46, 2SC3216
39730	BUX48A	BUV 48A, 175W	BUS 13A, 2SC3216
39731	BUX48B	BUV 48B, 175W	2SC3216
39732	BUX48C	BUV 48C, 175W	2SC3216
39733	BUX49	>8MHz	BU 125(S), BUX 50...53, BUY 49, 2SD625
39734	BUX50	>8MHz	BU 125(S), BUX 51...53, BUY 49, 2SD625

39735	BUX51	>8MHz	BUX 52...53, BUY 61...62
39736	BUX51N	BUX 51, 250/160V	BUX 52...53, BUY 61...62
39737	BUX52	>8MHz	BUX 53, BUY 61...62
39738	BUX53	>8MHz	BUY 61...62
39739	BUX54	>8MHz	BUY 61...62, 2SC1862
39740	BUX55	>8MHz	BUY 59...60
39741	BUX56	8A, 40W, B>200	-
39742	BUX57	8A, 40W, B>100	-
39743	BUX59	120/90V, 8A, 70W, >8MHz	BUS 36...37, BUY 27(A), 2SC2867
39744	BUX60	160/125V, 8A, 70W, >8MHz	BUS 36...37, BUY 27(A), 2SC2867
39745	BUX61	250/200V, 8A, 70W, >8MHz	BUS 36...37, BUY 27(A), 2SC2867
39746	BUX62	300/250V, 7A, 70W, >8MHz	BUS 36...37, BUY 27(A), 2SC2867
39747	BUX63	400/325V, 5A, 70W, >8MHz	BUT 56(A), MJE 52T...53T, 2SC2440
39748	BUX64	450/400V, 4A, 70W, >8MHz	BUT 93, BUT 56(A), MJE 53T, 2SC2440
39749	BUX65	500/500V, 3A, 70W, >8MHz	BUT 93, BUT 56(A), TIP 75C, 2SC2826
39750	BUX66	200/150V, 2A, 35W, >20MHz	2N6211...6214, 2SA1009(A), 2SB630
39751	BUX66A	BUX 66, 300/250V	2N6212...14, 2SA1009(A), 2SA1236
39752	BUX66B	BUX 66, 350/300V	2N6212...14, 2SA1009(A), 2SA1236
39753	BUX66C	BUX 66, 400/350V	2N6213...14, 2SA1009A, 2SA1236
39754	BUX67	200/150V, 2A, 35W, >10MHz	2N3583...85, 2SC2023, 2SC3055, 2SD610
39755	BUX67A	BUX 67, 300/250V	2N3584...85, 2SC2023, 2SC2333, 2SC3055
39756	BUX67B	BUX 67, 350/300V	2N3584...85, 2SC2534, 2SC2333, 2SC3055
39757	BUX67C	BUX 67, 400/350V	2N3585, 2SC2534, 2SC2333, 2SC3055
39758	BUX69	180/90V, 30A, 125W, 8MHz	-
39759	BUX70	250/125V, 20A, 125W, 8MHz	BUW 50...52
39760	BUX71	600/600V, 20A, 200W, 10MHz	-
39761	BUX72	500/500V, 40A, 200W, 10MHz	-
39762	BUX73	400/400V, 60A, 200W, 10MHz	-
39763	BUX74	300/300V, 100A, 200W, 10MHz	-
39764	BUX75	220/200V, 150A, 200W, 10MHz	-
39765	BUX76	120/100V, 200A, 200W, 10MHz	-
39766	BUX77	100/80V, 5A, 40W, >2.5MHz	BU 409, 2N6233...35, 2SC2767, 2SC3035
39767	BUX78	100/80V, 5A, 40W, >2.5MHz	MJE 5850...5852
39768	BUX80	6MHz	BUS 12(A), BUW 26, BUW 35...36, MJ 8504
39769	BUX80	6MHz	BUS 12(A), BUW 26, BUW 35...36, MJ 8504
39770	BUX81	BUX 80, 1000/450V	BUS 12A, MJ 8504, 2SC3061, 2SC3215
39771	BUX81	BUX 80, 1000/450V	BUS 12A, MJ 8504, 2SC3061, 2SC3215
39772	BUX82	6MHz	BUS 11(A), BUX 47(A), MJ 8502, 2SC3060
39773	BUX82	6MHz	BUS 11(A), BUX 47(A), MJ 8502, 2SC3060
39774	BUX83	BUX 82, 1000/450V	BUS 11A, BUX 47A, MJ 8502, 2SC3060
39775	BUX83	BUX 82, 1000/450V	BUS 11A, BUX 47A, MJ 8502, 2SC3060
39776	BUX84(A)	20MHz	BUY 36(A), MJE 8500, 2SC3178, 2SC3531
39777	BUX84F	BUX 84, , 18W	BUT 11(A), 2SC3352, 2SC4234
39778	BUX85	BUX 84, 1000/450V	BUY 36A, MJE 8501, 2SC3178, 2SC3531
39779	BUX85F	BUX 85, , 18W	BUT 11AF, 2SC4234



39780	BUX86	20W(Tc60°),20MHz	BUV 94...95
39781	BUX86P..87P	BUX 86..87, 42W	-
39782	BUX87	BUX 86, 1000/450V	BUV 95
39783	BUX88	1500/800V, 12A, 160W, 7MHz	BU 808[Philips]
39784	BUX88	1500/800V, 12A, 160W, 7MHz	BU 808[Philips]
39785	BUX90	650/400V, 12A, 125W	BUT 51P, BUW 81A
39786	BUX90	650/400V, 12A, 125W	BUT 51P, BUW 81A
39787	BUX91	BUX 71, 300W	-
39788	BUX92	BUX 72, 300W	-
39789	BUX93	BUX 73, 300W	-
39790	BUX94	BUX 74, 300W	-
39791	BUX95	BUX 75, 300W	-
39792	BUX96	BUX 76, 300W	-
39793	BUX97	20MHz	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39794	BUX97	20MHz	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39795	BUX97A	BUX 97, 800/400V	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39796	BUX97A	BUX 97, 800/400V	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39797	BUX97B	BUX 97, 800/450V	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39798	BUX97B	BUX 97, 800/450V	BUS 11(A), BUX 82...83, MJ8502, 2SC3048
39799	BUX98	850/400V, 30A, 250W, 5MHz	BUS 14(A), BUS 98(A)
39800	BUX98	850/400V, 30A, 250W, 5MHz	BUS 14(A), BUS 98(A)
39801	BUX98A	BUX 98, 1000/450V	BUS 14A, BUS 98A
39802	BUX98A	BUX 98, 1000/450V	BUS 14A, BUS 98A
39803	BUX98AP	BUX 98A, 24A, 200W	-
39804	BUX98API	BUX 98A, , 24A, 100W	-
39805	BUX98B	BUX 98, 1000/600V	BUS 14A, BUS 98A
39806	BUX98B	BUX 98, 1000/600V	BUS 14A, BUS 98A
39807	BUX98C	BUX 98, 1200/700V	-
39808	BUX98C	BUX 98, 1200/700V	-
39809	BUX98P	BUX 98, 200W	-
39810	BUX98PI	BUX 98, , 100W	-
39811	BUX99	730/300V, 1,5A, 28W, 4MHz	BUV 94
39812	BUY10	90MHz	BDY 90...92
39813	BUY10	90MHz	BDY 90...92
39814	BUY11	BUY 10, 140MHz	BDY 90...92
39815	BUY11	BUY 10, 140MHz	BDY 90...92
39816	BUY12	11MHz	BUW 24, BUX 17, BUX 42...43, BUY 18
39817	BUY12S	BUY 12, 210/90V, 85W(Tc45°)	BUW 24, BUX 17, BUX 42...43, BUY 18
39818	BUY12S	BUY 12, 210/90V, 85W(Tc45°)	BUW 24, BUX 17, BUX 42...43, BUY 18
39819	BUY12T	BUY 12, 200/-V, 50W(Tc80°)	BUW 24, BUX 17, BUX 42...43, BUY 18
39820	BUY12T	BUY 12, 200/-V, 50W(Tc80°)	BUW 24, BUX 17, BUX 42...43, BUY 18
39821	BUY13	BUY 12, 120/70V	BUW 70, BUX 17, BUX 42...43, BUY 18
39822	BUY13S	BUY 12, 120/70V, 85W(Tc45°)	BUW 70, BUX 17, BUX 42...43, BUY 18
39823	BUY13S	BUY 12, 120/70V, 85W(Tc45°)	BUW 70, BUX 17, BUX 42...43, BUY 18
39824	BUY14	11MHz	BU 409, BUW 64A...C, 2SC2334



39825	BUY16	15W(Tc100°),100MHz	2N5542
39826	BUY17	BUY 16, 120/60V	2N5288...5289
39827	BUY18	25W(Tc100°),50MHz	BUW 24, BUW 34, BUW 72, BUX 17A...C
39828	BUY18	25W(Tc100°),50MHz	BUW 24, BUW 34, BUW 72, BUX 17A...C
39829	BUY18S	30MHz	BUW 24, BUW 34, BUW 72, BUX 17B...C
39830	BUY18S	30MHz	BUW 24, BUW 34, BUW 72, BUX 17B...C
39831	BUY19	100MHz	2N5288...5289
39832	BUY20	200/120V, 10A, 85W, 25MHz	BUW 24, BUW 34, BUX 17(A...C), BUX 43
39833	BUY20	200/120V, 10A, 85W, 25MHz	BUW 24, BUW 34, BUX 17(A...C), BUX 43
39834	BUY21	BUY 20, 300/180V	BUW 24, BUW 34, BUX 17A...C, BUX 43
39835	BUY21	BUY 20, 300/180V	BUW 24, BUW 34, BUX 17A...C, BUX 43
39836	BUY21A	BUY 20, 400/230V	BUW 24, BUW 34, BUX 17B...C, BUX 43
39837	BUY21A	BUY 20, 400/230V	BUW 24, BUW 34, BUX 17B...C, BUX 43
39838	BUY22	BUY 20, 450/230V	BUW 24, BUW 34, BUX 17C, BUX 14
39839	BUY22	BUY 20, 450/230V	BUW 24, BUW 34, BUX 17C, BUX 14
39840	BUY23	600/250V, 10A, 85W, 25MHz	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39841	BUY23	600/250V, 10A, 85W, 25MHz	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39842	BUY23A	BUY 23, 700/300V	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39843	BUY23A	BUY 23, 700/300V	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39844	BUY23B	BUY 23, 700/400V	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39845	BUY23B	BUY 23, 700/400V	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39846	BUY24	100MHz	BDY 90, BUW 86...87, BUX 16(A...C)
39847	BUY24	100MHz	BDY 90, BUW 86...87, BUX 16(A...C)
39848	BUY26	200/150V, 10A, 100W(Tc45°)	-
39849	BUY27	BUY 26, 350/250V	-
39850	BUY28	BUY 26, 420/300V	-
39851	BUY29	-/200V, 8A, 125W, >50MHz	BUX 18(A...C), BUX 43...44, BUY 18S
39852	BUY29	-/200V, 8A, 125W, >50MHz	BUX 18(A...C), BUX 43...44, BUY 18S
39853	BUY30	BUY 29, -/250V	BUX 18(A...C), BUX 43...44, BUY 18S
39854	BUY30	BUY 29, -/250V	BUX 18(A...C), BUX 43...44, BUY 18S
39855	BUY32/100	BUY 32/40, -/100V	BD 245C, BUW 86...87, 2N3055
39856	BUY32/100	BUY 32/40, -/100V	BD 245C, BUW 86...87, 2N3055
39857	BUY32/40	-/40V, 6A, 60W, 0,8MHz	BD 245(A...C), BUW 86...87, 2N3055
39858	BUY32/40	-/40V, 6A, 60W, 0,8MHz	BD 245(A...C), BUW 86...87, 2N3055
39859	BUY32/70	BUY 32/40, -/70V	BD 245A...C, BUW 86...87, 2N3055
39860	BUY32/70	BUY 32/40, -/70V	BD 245A...C, BUW 86...87, 2N3055
39861	BUY33/100	BUY 33/40, -/100V	BD 245C, BUW 86...87, 2N3055
39862	BUY33/100	BUY 33/40, -/100V	BD 245C, BUW 86...87, 2N3055
39863	BUY33/40	-/40V, 10A, 90W, 0,8MHz	BD 245(A...C), BUW 86...87, 2N3055
39864	BUY33/40	-/40V, 10A, 90W, 0,8MHz	BD 245(A...C), BUW 86...87, 2N3055
39865	BUY33/70	BUY 33/40, -/70V	BD 245A...C, BUW 86...87, 2N3055
39866	BUY33/70	BUY 33/40, -/70V	BD 245A...C, BUW 86...87, 2N3055
39867	BUY35	20MHz	BUW 71, BUX 16B...C, BUX 18A...C
39868	BUY35	20MHz	BUW 71, BUX 16B...C, BUX 18A...C
39869	BUY38	90/55V, 4A, 25W, >0,8MHz	BD 243B...C, BD 543B...D, 2N3054

39870	BUY39	>40MHz	2N3996...3997
39871	BUY40	BUY 39	2N3998...3999
39872	BUY41	>40MHz	BU 125(S), BUX 49...53, BUY 41, BUY 49
39873	BUY43	50/40V, 4A, 31W(Tc45°), 1MHz	BD 243(A...C), BD 543(A...D), BDW 25
39874	BUY44	15MHz	BUX 18A...C, BUX 43...44, BUY 18S
39875	BUY44	15MHz	BUX 18A...C, BUX 43...44, BUY 18S
39876	BUY46	90/60V, 4A, 31W(Tc45°)	BD 243B...C, BD 543B...D, BDW 25
39877	BUY47	90MHz	BUY 68, BUY 81
39878	BUY48	BUY 47, 200/170V	-
39879	BUY49	BUY 47, 250/200V	-
39880	BUY49P	BUY 49, 3A, 15W	-
39881	BUY49S	BUY 49, 3A	BU 125S, BUX 51...52, 2SD625
39882	BUY50	13MHz	BUV 25, BUW 44, BUX 13, MJ 15024
39883	BUY50	13MHz	BUV 25, BUW 44, BUX 13, MJ 15024
39884	BUY51	60/60V, 30A, 150W, >10MHz	2N2823...2825
39885	BUY51A	BUY 51	BUW 38...39, BUX 39, 2N6322
39886	BUY51A	BUY 51	BUW 38...39, BUX 39, 2N6322
39887	BUY52	BUY 51	2N2823...2825
39888	BUY52A	BUY 51	BUW 38...39, BUX 39, 2N6322
39889	BUY52A	BUY 51	BUW 38...39, BUX 39, 2N6322
39890	BUY53	BUY 51, 100/100V	2N2824...2825
39891	BUY53A	BUY 51, 100/100V	BUW 38...39, BUX 39, 2N6322
39892	BUY53A	BUY 51, 100/100V	BUW 38...39, BUX 39, 2N6322
39893	BUY54	BUY 51, 100/100V	2N2824...2825
39894	BUY54A	BUY 51, 100/100V	BUW 38...39, BUX 39, 2N6322
39895	BUY54A	BUY 51, 100/100V	BUW 38...39, BUX 39, 2N6322
39896	BUY55	20MHz	BUW 70, BUX 17(A...C), BUX 42, BUY 18
39897	BUY55	20MHz	BUW 70, BUX 17(A...C), BUX 42, BUY 18
39898	BUY56	BUY 55, 250/160V	BUW 74, BUX 17A...C, BUX 42, BUY 18
39899	BUY56	BUY 55, 250/160V	BUW 74, BUX 17A...C, BUX 42, BUY 18
39900	BUY57	150/125V, 15A, 117W, 20MHz	BUW 58, BUW 73, BUX 13, BUX 41
39901	BUY57	150/125V, 15A, 117W, 20MHz	BUW 58, BUW 73, BUX 13, BUX 41
39902	BUY58	BUW 57, 250/160V	BUW 58, BUW 73, BUX 13, BUX 41
39903	BUY58	BUW 57, 250/160V	BUW 58, BUW 73, BUX 13, BUX 41
39904	BUY59	500/325V, 1A, 10W(Tc25°)	BUX 55, 2N5095, 2N5097...5099
39905	BUY60	BUY 59, 600/400V	2N5097...5099
39906	BUY61	500/325V, 3A, 10W(Tc25°)	BUT 93, 2SC2826, 2SC3038
39907	BUY62	BUY 61, 600/400V	BUT 93
39908	BUY63	500/325V, 3A, 20W, >2,5MHz	BUT 93, MJ 4380...4381, 2SC1467, 2SC2826
39909	BUY64	BUY 63, 600/400V	BUT 93, MJ 4380...4381
39910	BUY65	600/400V, 10A, 30W(Tc100°)	BUV 56(A), BUV 66(A), MJE 13008...13009
39911	BUY66	>10MHz	BUW 44, BUW 74...77, BUX 13, BUY 50
39912	BUY66	>10MHz	BUW 44, BUW 74...77, BUX 13, BUY 50
39913	BUY67	400/350V, 5A, 75W(Tc100°)	BUW 71, BUX 15, BUX 16C, BUX 44...45
39914	BUY67	400/350V, 5A, 75W(Tc100°)	BUW 71, BUX 15, BUX 16C, BUX 44...45

39915	BUY68	>50MHz	BU 125, BUY 47...49, BUY 81, 2N5338...39
39916	BUY69A	1000/400V, 10A, 100W	BU 626A, 2SC2123, 2SD1094
39917	BUY69A	1000/400V, 10A, 100W	BU 626A, 2SC2123, 2SD1094
39918	BUY69B	BUY 69A, 800/325V	BU 626A, 2SC2123, 2SD1094
39919	BUY69B	BUY 69A, 800/325V	BU 626A, 2SC2123, 2SD1094
39920	BUY69C	BUY 69A, 500/200V	BU 626A, 2SC2123, 2SD1094
39921	BUY69C	BUY 69A, 500/200V	BU 626A, 2SC2123, 2SD1094
39922	BUY70A	1000/400V, 10A, 75W	BU 626A, 2SC2123, 2SD1094
39923	BUY70A	1000/400V, 10A, 75W	BU 626A, 2SC2123, 2SD1094
39924	BUY70B	BUY 70A, 800/325V	BU 626A, 2SC2123, 2SD1094
39925	BUY70B	BUY 70A, 800/325V	BU 626A, 2SC2123, 2SD1094
39926	BUY70C	BUY 70A, 500/200V	BU 626A, 2SC2123, 2SD1094
39927	BUY70C	BUY 70A, 500/200V	BU 626A, 2SC2123, 2SD1094
39928	BUY71	2200/800V, 2A, 10W(Tc80°)	BU 225, 2SD621, 2SD838
39929	BUY71	2200/800V, 2A, 10W(Tc80°)	BU 225, 2SD621, 2SD838
39930	BUY72	280/200V, 10A, 60W(Tc75°)	BUW 74, BUX 17A...C, BUX 43, BUY 18
39931	BUY72	280/200V, 10A, 60W(Tc75°)	BUW 74, BUX 17A...C, BUX 43, BUY 18
39932	BUY73	280/200V, 15A, 117W, 20MHz	BUV 12, BUW 73, BUX 12...13, BUY 50
39933	BUY80	60MHz	-
39934	BUY81	7,5A,12W(Tc100°),60MHz	-
39935	BUY82	15W(Tc100°),60MHz	-
39936	BUY83	160/140V, 3A, 25W, 10MHz	TIP 75, 2N3441, 2SD422...423
39937	BUY89	1500/800V, 6A, 80W(Tc60°)	BU 908, BUX 88, 2SD649, 2SD821
39938	BUY89	1500/800V, 6A, 80W(Tc60°)	BU 908, BUX 88, 2SD649, 2SD821
39939	BUY90	60MHz	-
39940	BUY91	7,5A,12W(Tc100°),60MHz	-
39941	BUY92	15W(Tc100°),60MHz	-
39942	BUY94	750/300V, 15A, 100W	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39943	BUY94	750/300V, 15A, 100W	BUS 12(A), BUW 26, BUW 35...36, BUX 80
39944	BUY95	BUY 94, 600/250V	BUS 12(A), BUW 25, BUW 35...36, BUX 80
39945	BUY95	BUY 94, 600/250V	BUS 12(A), BUW 25, BUW 35...36, BUX 80
39946	BUY96	BUY 94, 450/275V	BUS 12(A), BUW 24, BUW 34...36, BUX 80
39947	BUY96	BUY 94, 450/275V	BUS 12(A), BUW 24, BUW 34...36, BUX 80
39948	BUYP52	120V, 5A, 50W, 10MHz	BD 245C, BUX 16, 2SC2908, 2SD2140
39949	BUYP52	120V, 5A, 50W, 10MHz	BD 245C, BUX 16, 2SC2908, 2SD2140
39950	BUYP53	80V, 5A, 50W, 10MHz	BD 245B...F, BUX 16, 2SC2908, 2SD2140
39951	BUYP53	80V, 5A, 50W, 10MHz	BD 245B...F, BUX 16, 2SC2908, 2SD2140
39952	BUYP54	40V, 5A, 50W, 10MHz	BD 245(B...F), BD 311, 2N5068...69, 2SD844
39953	BUYP54	40V, 5A, 50W, 10MHz	BD 245(B...F), BD 311, 2N5068...69, 2SD844
39954	BUZ10	<0,07Ohm(16A)	BUZ 11, 2SK600, 2SK674, 2SK1417
39955	BUZ10(A)L	BUZ 10, <0,07Ohm(11,5A)	2SK942, 2SK972, 2SK1115, 2SK1910
39956	BUZ100	<18mOhm(60A)	-
39957	BUZ100L	BUZ 100, <18mOhm(30A)	-
39958	BUZ101	<0,06Ohm(21A)	BUK 555-50, 2SK1291, 2SK1296
39959	BUZ102	<23mOhm(42A)	-

39960	BUZ102AL	BUZ 102, <28mOhm(21A)	-
39961	BUZ103	<40mOhm(28A)	BUZ 102, 2SK1418, 2SK1542, 2SK1911
39962	BUZ103AL	BUZ 103, 35A, <0,05(17,5A)	BUZ 102L, 2SK1542, 2SK1911
39963	BUZ104	<0,10Ohm(12,5A)	2SK1115, 2SK1287, 2SK1417, 2SK1910
39964	BUZ104L	BUZ 104, <0,10Ohm(8,5A)	2SK942, 2SK1115, 2SK1287, 2SK1910
39965	BUZ10A..	BUZ 10, <0,12Ohm(6A)	BUZ 11, 2SK600, 2SK674, 2SK1417
39966	BUZ10S2	BUZ 10, 60V, 24A	BUZ 11, 2SK600, 2SK674, 2SK1417
39967	BUZ11	<0,04Ohm(19A)	BUK 456-100, BUK 555-50, BUZ 12
39968	BUZ11A..	BUZ 11, 26A, <0,055Ohm(16A)	BUK 456-100, BUZ 12
39969	BUZ11AL	BUZ 11, 20A, 35W	2SK942, 2SK972, 2SK1115, 2SK1910
39970	BUZ11FI,P,S2FI	BUZ 11, , 21A, 35W	BUK 445-50, BUK 545-50, 2SK1214, 2SK1420
39971	BUZ11S2	BUZ 11, 60V	BUK 456-100, 2SK856, 2SK1418
39972	BUZ12	<28mOhm(32A)	PRFZ 42, 2SK856, 2SK1418
39973	BUZ12A	BUZ 12, <35mOhm(32A)	PRFZ 42, 2SK856, 2SK1418
39974	BUZ12AL	BUZ 12, <35mOhm(21A)	2SK1542, 2SK1911
39975	BUZ14	<40mOhm(22A)	BUZ 15
39976	BUZ14	<40mOhm(22A)	BUZ 15
39977	BUZ15	<0,03Ohm(29A)	BUK 439-60, BUZ 347, 2SK1258, 2SK1379
39978	BUZ15	<0,03Ohm(29A)	BUK 439-60, BUZ 347, 2SK1258, 2SK1379
39979	BUZ15S2	BUZ 15, 60V	BUK 439-60, BUZ 347, 2SK1258, 2SK1379
39980	BUZ15S2	BUZ 15, 60V	BUK 439-60, BUZ 347, 2SK1258, 2SK1379
39981	BUZ16	<18mOhm(40A)	BUK 439-60, BUZ 346, 2SK1258, 2SK1379
39982	BUZ16	<18mOhm(40A)	BUK 439-60, BUZ 346, 2SK1258, 2SK1379
39983	BUZ17	<40mOhm(22A)	BUZ 18
39984	BUZ171	50V, 8A, 40W, <0,3Ohm(5A)	2SJ122...123, 2SJ171
39985	BUZ172	<0,6Ohm(3,7A)	IRF 9643, 2SJ247
39986	BUZ173	<1,5Ohm(2,3A)	IRF 9620, IRF 9630
39987	BUZ18	<40mOhm(22A)	-
39988	BUZ20	<0,2Ohm(8,5A)	IRF530, 2SK919, 2SK922, 2SK1301, 2SK1559
39989	BUZ201	400V, 12,5A, 125W, 130/440ns	BUK 637-400
39990	BUZ201	400V, 12,5A, 125W, 130/440ns	BUK 637-400
39991	BUZ202	BUZ 201, 11,5A	-
39992	BUZ202	BUZ 201, 11,5A	-
39993	BUZ205	400V, 6A, 75W, <10Ohm(4A)	BUK 655-500, BUZ 215
39994	BUZ206	BUZ 205, 5A, <1,5Ohm(4A)	BU 655-500, BUZ 215...216
39995	BUZ21	<85mOhm(13A)	BUZ 22, IRF 540, IRF 542, 2SK1428
39996	BUZ210	125W,<0,6Ohm(6,5A)	BUK 737-500, BUZ 384, 2SK1516
39997	BUZ210	125W,<0,6Ohm(6,5A)	BUK 737-500, BUZ 384, 2SK1516
39998	BUZ211	BUZ 210, 9A, <0,8Ohm(6,5A)	BUZ 384...385, BUK 637-500, 2SK1516
39999	BUZ211	BUZ 210, 9A, <0,8Ohm(6,5A)	BUZ 384...385, BUK 637-500, 2SK1516
40000	BUZ213	BUZ 210, 8,5A, 83,3W	BUZ 384
40001	BUZ214	BUZ 210, 7A, 83,3W	BUZ 385
40002	BUZ215	500V, 5A, 75W, <1,5Ohm(3,2A)	BUK 655-500
40003	BUZ216	BUZ 215, 4,4A, <2Ohm(3,2A)	-
40004	BUZ21L	BUZ21, <85mOhm(10,5A)	BUK 555-100, 2SK1116, 2SK1302, 2SK1347

40005	BUZ22	<55mOhm(22A)	BUK 456-100
40006	BUZ220	800V, 6,5A, 125W, 150/440ns	BUZ 380
40007	BUZ220	800V, 6,5A, 125W, 150/440ns	BUZ 380
40008	BUZ221	BUZ 220, 5,5A	BUZ 381
40009	BUZ221	BUZ 220, 5,5A	BUZ 381
40010	BUZ23	100V, 10A, 78W, <0,2Ohm(6A)	BUZ 35, 2SK398, 2SK401
40011	BUZ23	100V, 10A, 78W, <0,2Ohm(6A)	BUZ 35, 2SK398, 2SK401
40012	BUZ230	<2Ohm(3,5A)	BUZ 380
40013	BUZ230	<2Ohm(3,5A)	BUZ 380
40014	BUZ231	BUZ 230, 4,9A, <2,6Ohm(3,5A)	BUZ 381
40015	BUZ231	BUZ 230, 4,9A, <2,6Ohm(3,5A)	BUZ 381
40016	BUZ24	<60mOhm(20A)	BUZ 349, 2SK561, 2SK1429, 2SK1433
40017	BUZ24	<60mOhm(20A)	BUZ 349, 2SK561, 2SK1429, 2SK1433
40018	BUZ25	100V, 19A, 78W, <0,1Ohm(9A)	BUZ 24, BUZ 36
40019	BUZ25	100V, 19A, 78W, <0,1Ohm(9A)	BUZ 24, BUZ 36
40020	BUZ255	<0,24Ohm(8,5A)	2SK2133
40021	BUZ27	<0,06Ohm(20A)	-
40022	BUZ271	<0,15Ohm(14A)	2SJ174, 2SJ291
40023	BUZ272	<0,3Ohm(9,5A)	IRF 9540, IRF 9542
40024	BUZ28	100V, 18A, 70W, <0,1Ohm(9A)	BUZ 27
40025	BUZ30	<0,75Ohm(4,5A)	BUZ 73, 2SK477, 2SK741, 2SK1319, 2SK1667
40026	BUZ305	800V, 7,5A, 150W, <1Ohm(5A)	BUK 638-800, 2SK1032, 2SK1358, 2SK1502
40027	BUZ307	800V, 3A, 75W, <3Ohm(1,5A)	2SK726, 2SK792, 2SK954, 2SK1339
40028	BUZ308	BUZ 307, 2,6A, <4Ohm(1,2A)	2SK726, 2SK792, 2SK954, 2SK1339
40029	BUZ309	1000V, 2,8A, 125W, <2Ohm	2SK696
40030	BUZ30A	<0,13Ohm(13,5A)	-
40031	BUZ31	<0,2Ohm(9A)	BUK 546-200, IRF 640, IRF 642, 2SK891
40032	BUZ310	<5Ohm(1,6A)	2SK696
40033	BUZ311	BUZ 310, 2,3A, <6Ohm(1,6A)	2SK696
40034	BUZ312	<1,5Ohm(4A)	2SK1120, 2SK1934
40035	BUZ31L	BUZ 31, 13,5A, 75W	BUK 555-200
40036	BUZ32	200V, 9,5A, 75W, <4Ohm(6A)	BUZ 31, 2SK459, 2SK890, 2SK925, 2SK1221
40037	BUZ323	<0,3Ohm(9,5A)	BUZ 338, 2SK899, 2SK1610, 2SK1745
40038	BUZ325	<0,35Ohm(8A)	BUZ 338, 2SK899, 2SK1610, 2SK1745
40039	BUZ326	<0,5Ohm(6,5A)	BUZ 338...39, 2SK899, 2SK1610, 2SK1745
40040	BUZ33	BUZ 30, 7,2A, 78W	BUZ 34...35, 2SK293
40041	BUZ33	BUZ 30, 7,2A, 78W	BUZ 34...35, 2SK293
40042	BUZ330	<0,6Ohm(6A)	BUZ 338...339, 2SK724, 2SK1488, 2SK1753
40043	BUZ331	BUZ 330, 8A, <0,8Ohm(5,5A)	BUZ 338...339, 2SK724, 2SK1488, 2SK1753
40044	BUZ332	600V, 8,5, 150W, <0,8Ohm(5A)	2SK1032, 2SK1358, 2SK1614, 2SK1968
40045	BUZ332A	BUZ 332, 8A, <0,9Ohm(5A)	2SK1032, 2SK1358, 2SK1614, 2SK1968
40046	BUZ334	<0,5Ohm(7,5A)	2SK1573, 2SK1723
40047	BUZ338	<0,4Ohm(8,5A)	BUK 638-500, 2SK1678
40048	BUZ339	<0,5Ohm(7,5A)	BUK 638-500, 2SK1678
40049	BUZ34	BUZ 31, 14A, 78W	BUZ 36



40050	BUZ34	BUZ 31, 14A, 78W	BUZ 36
40051	BUZ341	<0,07Ohm(21A)	2SK1675
40052	BUZ342	<10mOhm(60A)	-
40053	BUZ344	<35mOhm(32A)	2SK1381, 2SK1434
40054	BUZ345	<45mOhm(26A)	2SK1381, 2SK1434
40055	BUZ346	18mOhm(47A)	BUK 439-60, BUK 539-60, 2SK1379, 2SK1423
40056	BUZ346S2	BUZ 346, 60V	BUZ 346
40057	BUZ347	<30mOhm(29A)	BUK 439-60, 2SK857, 2SK1124, 2SK1665
40058	BUZ348	BUZ 347, 39A, <30mOhm(26A)	BUK 439-60, 2SK857, 2SK1124, 2SK1665
40059	BUZ349	<0,06Ohm(21A)	2SK850...51, 2SK906, 2SK1429, 2SK1433
40060	BUZ35	BUZ 32, 9,9A, 78W	BUZ 34, 2SK401
40061	BUZ35	BUZ 32, 9,9A, 78W	BUZ 34, 2SK401
40062	BUZ350	BUZ 36	BUZ 341, 2SK623, 2SK901...902
40063	BUZ351	<0,4Ohm(5,5A)	BUZ 325...326, BUZ 338...339
40064	BUZ353	<0,6Ohm(5,5A)	BUZ 330, BUZ 338...339
40065	BUZ354	BUZ 353, 8A	BUZ 331, BUZ 338...339
40066	BUZ355	<1,5Ohm(3,9A)	BUZ 305, 2SK1032, 2SK1649, 2SK1794
40067	BUZ356	BUZ 355, 5,3A, <2Ohm(3,9A)	2SK727, 2SK1649, 2SK1760, 2SK1794
40068	BUZ357	<2Ohm(3,2A)	BUZ 312, 2SK1205, 2SK1359, 2SK1773
40069	BUZ358	BUZ 357, 4,5A, <2,6Ohm(3,2A)	BUZ 312, 2SK1205, 2SK1359, 2SK1773
40070	BUZ36	200V, 22A, 125W, <0,12(14A)	BUZ 341, BUZ 350, 2SK1491, 2SK1641
40071	BUZ36	200V, 22A, 125W, <0,12(14A)	BUZ 341, BUZ 350, 2SK1491, 2SK1641
40072	BUZ360	800V, 3,6A, 75W, 80/160ns	BUZ 380...381
40073	BUZ361	BUZ 360, 2,9A	BUZ 380...381
40074	BUZ37	200V, 13A, 70W, <0,2Ohm(7A)	BUZ 38
40075	BUZ376	800V, 6,5A, 125W, <1,5Ohm	BUZ 355, 2SK684, 2SK1032
40076	BUZ377	800V, 5,5A, 125W, <2Ohm	BUZ 356, 2SK684, 2SK1032
40077	BUZ38	<12Ohm(14A)	-
40078	BUZ380	<2Ohm(3,5A)	BUK 638-1000
40079	BUZ381	BUZ 380, 4,9A, <2,6Ohm(3,5A)	BUK 638-1000
40080	BUZ382	<0,4Ohm(8A)	BUK 637-400, BUK 638-500, 2SK1515...1516
40081	BUZ383	<0,5Ohm(7,5A)	BUK 637-400, BUK 638-500, 2SK1515...1516
40082	BUZ384	125W, <0,6Ohm(6,5A)	BUK 637-500, BUK 638-500, 2SK1516
40083	BUZ385	BUZ 384, 9A, <0,8Ohm(6,5A)	BUK 637-500, BUK 638-500, 2SK1516
40084	BUZ40	<4,5Ohm(2,5A)	BUZ 74, IRF 820, IRF 822, 2SK892
40085	BUZ40B	BUZ 40, 8,5A, 0,8Ohm(5,5A)	IRF 840, 2SK894, 2SK1496, 2SK1574
40086	BUZ41	<1,1Ohm(2,5A)	IRF840, IRF842, 2SK553, 2SK893, 2SK1246
40087	BUZ41A	<1,5Ohm(3A)	IRF830, 2SK553, 2SK893, 2SK1246, 2SK1751
40088	BUZ42	500V, 4A, 75W, <2Ohm(2,6A)	IRF830, IRF832, 2SK553, 2SK893, 2SK1246
40089	BUZ43	<4,5Ohm(2,5A)	BUZ 44(A), BUZ 46
40090	BUZ43	<4,5Ohm(2,5A)	BUZ 44(A), BUZ 46
40091	BUZ44(A)	500V, 4,8..5,6A, 78W, <1,1Ohm	BUZ 46
40092	BUZ44(A)	500V, 4,8..5,6A, 78W, <1,1Ohm	BUZ 46
40093	BUZ45	<0,6Ohm(5A)	BUZ339, BUZ384, 2SK512, 2SK724, 2SK1753
40094	BUZ45	<0,6Ohm(5A)	BUZ339, BUZ384, 2SK512, 2SK724, 2SK1753



40095	BUZ45A	BUZ 45, 8,3A, <0,8Ohm(5A)	BUZ 45
40096	BUZ45A	BUZ 45, 8,3A, <0,8Ohm(5A)	BUZ 45
40097	BUZ45B	BUZ 45, 10A, <0,5Ohm(5A)	BUZ 45
40098	BUZ45B	BUZ 45, 10A, <0,5Ohm(5A)	BUZ 45
40099	BUZ45C	<0,5Ohm(5A)	BUZ 45
40100	BUZ45C	<0,5Ohm(5A)	BUZ 45
40101	BUZ46	<1,1Ohm(2,5A)	BUZ 44
40102	BUZ46	<1,1Ohm(2,5A)	BUZ 44
40103	BUZ47(A)	500V, 3,9..4,5A, 50..70W	BUZ 48
40104	BUZ48(A)	<0,8Ohm	-
40105	BUZ50	<3,5Ohm(1,4A)	BUK 456-1000, BUZ 51
40106	BUZ50A	<5Ohm(1,5A)	BUZ 50
40107	BUZ50B	<8Ohm(1,5A)	BUZ 50
40108	BUZ50C	<6Ohm(1,5A)	BUZ 50
40109	BUZ51	<4Ohm(2,2A)	BUK 456-1000
40110	BUZ53(A,C)	1000V, 2,6..3A, 78W	BUZ 54(A)
40111	BUZ53(A,C)	1000V, 2,6..3A, 78W	BUZ 54(A)
40112	BUZ54	<2Ohm(2,5A)	BUZ 357...358, 2SK1205, 2SK1359, 2SK1773
40113	BUZ54	<2Ohm(2,5A)	BUZ 357...358, 2SK1205, 2SK1359, 2SK1773
40114	BUZ54A	BUZ 54, 4,5A, <2,6Ohm(3,2A)	BUZ 54
40115	BUZ54A	BUZ 54, 4,5A, <2,6Ohm(3,2A)	BUZ 54
40116	BUZ57(A)	BUZ 50(A), 70W	BUZ 58
40117	BUZ58(A)	BUZ 54(A), 83,3W	-
40118	BUZ60	400V, 5,5A, 75W, <1Ohm(3,5A)	BUZ41, IRF830, 2SK553, 2SK1246, 2SK1751
40119	BUZ60B	BUZ 60, 4,5A, <1,5Ohm(2,5A)	BUZ 60
40120	BUZ61	<0,4Ohm(8A)	BUZ 64, 2SK1378
40121	BUZ61A	BUZ 61, 11A, <0,5Ohm(8A)	BUZ 61
40122	BUZ63(B)	BUZ 60(B), 78W	BUZ 44(A)
40123	BUZ63(B)	BUZ 60(B), 78W	BUZ 44(A)
40124	BUZ64	400V, 11,5A, 125W, <0,4Ohm	BUZ45, 2SK312, 2SK724, 2SK1488, 2SK1752
40125	BUZ64	400V, 11,5A, 125W, <0,4Ohm	BUZ45, 2SK312, 2SK724, 2SK1488, 2SK1752
40126	BUZ67	BUZ 64, 83,3W	-
40127	BUZ70	<0,15Ohm(7,5A)	BUZ 20, BUZ 72, 2SK428, 2SK442, 2SK672
40128	BUZ70L	BUZ 70, <0,15Ohm(6A)	BUK552-60, 2SK970...71, 2SK1114, 2SK1416
40129	BUZ71	50V, 14A, 40W, <0,1Ohm(9A)	BUZ 10, IRF 530, 2SK888, 2SK1416
40130	BUZ71(A)F,FLP	BUZ 71(A), , 25..30W	BUK 442-60, BUK 443-50, 2SK1093...91
40131	BUZ71(A)L	BUZ 70, <0,1Ohm(7A)	BUZ 10(A)L, BUK 552-50, 2SK971, 2SK1555
40132	BUZ71A..	BUZ 70, 13A, <0,12Ohm(7A)	BUZ 71
40133	BUZ71S2	BUZ 71, 60V	BUZ 10S2, IRF 530, 2SK888, 2SK1416
40134	BUZ72	100V, 10A, 40W, <0,2Ohm(6A)	BUZ20, IRF532, 2SK918, 2SK921, 2SK1427
40135	BUZ72(A)F	BUZ 72(A), , 7..8A, 25W	2SK1556
40136	BUZ72(A)L	BUZ 72	2SK1300...01, 2SK1559, 2SK1561
40137	BUZ72A..	BUZ 72, 9A, <0,25Ohm(6A)	BUZ 72
40138	BUZ73	200V, 7A, 40W, <0,4Ohm(4,5A)	BUZ 30...32, 2SK477, 2SK741, 2SK1319
40139	BUZ73(A)F	BUZ 73(A), , 5A, 25W	BUK 444-200

40140	BUZ73(A)L	BUZ 73	BUK 554-200
40141	BUZ73A	BUZ 73, 5,5A, <0,6Ohm(4,5A)	BUZ 73
40142	BUZ74	500V, 2,4A, 40W, <3Ohm(1,5A)	BUZ 40, IRF 820, 2SK382, 2SK892
40143	BUZ74A	BUZ 74, 2,1A, <4Ohm(1,5A)	BUZ 74
40144	BUZ76	400V, 3A, 40W, <1,8Ohm(2A)	BUZ 60, IRF 720, 2SK1244, 2SK1493
40145	BUZ76A	BUZ 76, 2,7A, <2,5Ohm(2A)	BUZ 76
40146	BUZ77A	600V, 2,7A, 75W, <4Ohm(1,7A)	BUZ 50, BUZ 80, 2SK513, 2SK858
40147	BUZ77B	BUZ 77A, 2,9A, <3,5Ohm(1,7A)	BUZ 77A
40148	BUZ78	800V, 1,5A, 40W, <8Ohm(1A)	BUZ 50, BUZ 80, 2SK602, 2SK1199, 2SK1324
40149	BUZ80	800V, 6,1A, 100W, <4Ohm(2A)	BUZ 81, 2SK1457, 2SK1643, 2SK1807
40150	BUZ80A	<3Ohm(1,5A)	BUZ 51, 2SK513, 2SK792, 2SK1793
40151	BUZ80FI,AFI	BUZ 80, , 2,1A, 40W	2SK1356, 2SK1460
40152	BUZ81	<2,5Ohm(2,8A)	2SK1501, 2SK1639, 2SK1643, 2SK1807
40153	BUZ83(A)	BUZ 80, 3,2A, 78W	BUZ 54(A), BUZ 84(A), BUZ 307, 2SK415
40154	BUZ83(A)	BUZ 80, 3,2A, 78W	BUZ 54(A), BUZ 84(A), BUZ 307, 2SK415
40155	BUZ84	800V, 5,3A, 125W, <2Ohm(3A)	BUZ 355...356, 2SK727, 2SK793, 2SK1760
40156	BUZ84	800V, 5,3A, 125W, <2Ohm(3A)	BUZ 355...356, 2SK727, 2SK793, 2SK1760
40157	BUZ84A	BUZ 84, 6A, <1,5Ohm(3A)	2SK684, 2SK1032, 2SK1614, 2SK1968
40158	BUZ84A	BUZ 84, 6A, <1,5Ohm(3A)	2SK684, 2SK1032, 2SK1614, 2SK1968
40159	BUZ88(A)	BUZ 84(A), 83,3W	-
40160	BUZ90	<1,6Ohm(2,8A)	BUK 455/600, 2SK1117, 2SK1402, 2SK1809
40161	BUZ90A	BUZ 90, 4A, <2Ohm(2,8A)	BUZ 90
40162	BUZ91	<0,8Ohm(5A)	BUK 657-600
40163	BUZ91A	BUZ 91, 8A, 0,9Ohm(5A)	BUZ 91
40164	BUZ92	600V, 3,3A, 80W, <3Ohm(2A)	BUK 456-800, 2SK791...792, 2SK1600...01
40165	BUZ93	BUZ 92, 3,6A, <2,5Ohm(2A)	BUK 456-800, 2SK791...792, 2SK1600...01
40166	BUZ94	<0,9Ohm(5A)	2SK684, 2SK1032
40167	BUZ94	<0,9Ohm(5A)	2SK684, 2SK1032
40168	BV	P4 SMA-36A	P4 SMA-36A
40169	BV	1SV233	1SV233
40170	BV	1SV247	1SV247
40171	BV	1SV247	1SV247
40172	BV	2SD1005-BV	2SD1005
40173	BV1	2SB624-BV1	2SB624
40174	BV12	11kV, 0,35A	-
40175	BV16	15kV, 0,35A	-
40176	BV2	2SB624-BV2	2SB624
40177	BV3	2SB624-BV3	2SB624
40178	BV4	2SB624-BV4	2SB624
40179	BV4	3kV, 0,05A	BYX 120G, 1N5181
40180	BV5	2SB624-BV5	2SB624
40181	BV6	6kV, 0,05A	1N5183
40182	BV8	7kV, 0,35A	BYX 110GP
40183	BW	P4 SMA-39	P4 SMA-39
40184	BW	BCX 71RH	BCX 71RH

40185	BW	2SD1005-BW	2SD1005
40186	BW1	2SB736-BW1	2SB736
40187	BW2	2SB736-BW2	2SB736
40188	BW3	2SB736-BW3	2SB736
40189	BW4	2SB736-BW4	2SB736
40190	BW5	2SB736-BW5	2SB736
40191	BX	P4 SMA-39A	P4 SMA-39A
40192	BX	BCX 71RJ	BCX 71RJ
40193	BY	P4 SMA-43	P4 SMA-43
40194	BY	BCX 71RK	BCX 71RK
40195	BY	2SC4396	2SC4396
40196	BY	2SC3395	2SC3395
40197	BY	2SA1200-Y	2SA1200
40198	BY	KTA1660-Y	KTA 1660
40199	BY	2SK1334	2SK1334
40200	BY100(S)	1250V, 0,4A	BY 127, BY 133, BY 227, G 1M, 1N4007
40201	BY101	650V, 0,4A	BY 126, BY 134, BY 226, 1N4005...4007
40202	BY102	750V, 0,6A	BY 127, BY 133, BY 227, 1N4006...4007
40203	BY103	1300V, 1A	BY 127, BY 133, BY 227, BYX 87, EM 513
40204	BY104	1250V, 0,5A	BY 127, BY 133, BY 227, G 1M, 1N4007
40205	BY105	1250V, 0,325A	BY 127, BY 133, BY 227, G 1M, 1N4007
40206	BY112	600V, 0,7A	BY 126, BY 134, BY 226, 1N4004...4007
40207	BY113	BY 112, 1200V	BY 127, BY 133, BY 227, G 1M, 1N4007
40208	BY114	650V, 0,4A	BY 126, BY 133, BY 226, 1N4005...4007
40209	BY114[Eiy]	400V, 0,1A	BA 158...159, BA 199/450, BAY 89
40210	BY115	600V, 0,5A	BY 126, BY 134, BY 226, 1N4005...4007
40211	BY116	400V, 0,45A	BY 126, BY 134, BY 226, 1N4005...4007
40212	BY118	300V, 5A	BY 229/..., BY 223/..., BYT 08/...
40213	BY118	300V, 5A	BY 229/..., BY 223/..., BYT 08/...
40214	BY120	400V, 0,45A	BY 126, BY 134, BY 226, 1N4005...4007
40215	BY121	BY 120	BY 127, BY 133, BY 227, 1N4006...4007
40216	BY122	60/120V, 0,8A	B60C800, etc.
40217	BY123	BY 122, 400/800V, 0,7A	B400C800, etc
40218	BY124	75V, 0,425A	BY 126, BY 135, BY 226, 1N4001...4007
40219	BY125[AEI]	200V, 0,425A	BY 126, BY 134, BY 226, 1N4003...4007
40220	BY125[Philips]	150V, 1A	BY 126, BY 135, BY 226, 1N4003...4007
40221	P)	650V, 1A	BY 127, BY 134, BY 226, 2N4005...4007
40222	BY127(M,GP)	BY 126, 1250V	BY 133, BY 227, BYX 87, EM 513, 1N4007
40223	BY128[Riz]	800V, 0,2A	BY 127, BY 133, BY 227, 1N4006...4007
40224	BY130	650V, 0,55A	BY 126, BY 134, BY 226, 1N4005...4007
40225	BY133(GP)	1300V, 1A	BY 127, BY 227, BYX 87, BYX 95, EM 513
40226	BY134(GP)	BY 133, 600V	BY 126...127, BY 226...227, 1N4006...07
40227	BY135(GP)	BY 133, 150V	BY 126...127, BY 226...227, 1N4003...07
40228	BY137/...	900..1300V, 1A	BY 127, BY 133, BY 227, 1N4007, EM 513
40229	BY138	800V, 1A	BYW 55...56, 1N4248...4249, 1N5062

40230	BY139	450V, 0,165A	BA 158...159, BAY 89...90, 1N4005...07
40231	BY140(A)	12..15kV, 2,5mA	BY 476, BY 609...610, BY 710...713
40232	BY141	50V, 0,125A	BA 157...159, BAY 18...20, 1N5606...09
40233	BY142	1000V, 1,1A	BY 127, BY 133, BY 227, 1N4007
40234	BY143	BY 142, 600V	BY 126, BY 134, BY 226, 1N4006...4007
40235	BY144	12,5kV, 2mA	BY 209, BY 409, BY 476, BY 710...713
40236	BY145	24kV, 2mA	BY 713...714, BY 723...724
40237	BY147	6,5kV, 0,25A	BY 167, GA 5005
40238	BY151N	400V, 1A	BY 126, BY 134, BY 226, 1N4004...4007
40239	BY152N	BY 151N, 800V	BY 127, BY 133, BY 227, 1N4006...4007
40240	BY154		-
40241	BY156	800V, 0,65A	BYW 55...56, 1N4248...4249, 1N5062
40242	BY157/...A	<300ns	BY 208/..., BY 231/..., BY 245/..., RGP10...
40243	BY157/...B	<300ns	BY 208/..., BY 231/..., BY 245/..., RGP10...
40244	BY157/...C	<300ns	BY 208/..., BY 231/..., BY 245/..., RGP10...
40245	BY157[Gen.Instr.]	800V, 0,3A	BYW 55...56, 1N4248...4249, 1N5062
40246	BY158[Gen.Instr.]	400V, 0,65A	BYW 54...56, 1N4246...4249, 1N5060...5062
40247	BY1600	1,6kV, 3A	-
40248	BY164	160V, 1,5A	B150C1500, etc.
40249	BY164	160V, 1,5A	B150C1500, etc.
40250	BY165(T)	6kV, 0,3A	BY 167, GA 5005
40251	BY166	5kV, 0,3A	BY 167, GA 5005
40252	BY167	7,5kV, 0,25A	GA 5005
40253	BY172	800V, 1,4A	BY 227, BY 254...255, 1N5398...5399
40254	BY173	BY 172, 600V	BY 226...227, BY 253...255, 1N5397...99
40255	BY174	BY 172, 400V	BY 226...227, BY 252...255, 1N5395...99
40256	BY176	15kV, 2,5mA	BY 476, BY 609...610, BY 710...713
40257	BY177	400V, 1,4A	BY 226...227, BY 252...255, 1N5395...99
40258	BY178	BY 177, 800V	BY 227, BY 254...255, 1N5398...5399
40259	BY179	500V, 1,5A	B400C1000
40260	BY179	500V, 1,5A	B400C1000
40261	BY1800	1,8kV, 3A	-
40262	BY182	12kV, 2,5mA	BY 209, BY 409, BY 476, BY 710...713
40263	BY183/...	50..600V, 0,2A	BA 157...159, BAY 88...90, BY 204/...
40264	BY184	1500/1800V, 5mA	BY 203/16...203/20, SHG 1,5...2
40265	BY186	150V, 5A	BY 500/..., MR 822...826, RGP 50C...D
40266	BY187(-01)	10..12kV, 2,5mA	BY 209, BY 409, BY 476, BY 710...713
40267	BY188A	50V, 1,2A	BY 218/..., BY 258/..., RGP 15, RGP 30
40268	BY188B	50V, 1,2A	BY 218/..., BY 258/..., RGP 15, RGP 30
40269	BY189	900V, 4A	BY 229/800, BY 277/750, BYW 19/800
40270	BY190	BY 189, 700V	BY 229/600, BY 277/600, BYW 19/800
40271	BY191/...(P)	250..400V, 4A, <500ns	BY 229/..., BY 277/..., BYW 19/...
40272	BY192	100V, 4A, <500ns	BY 229/200, BY 277/600, BYW 19/800
40273	BY193	BY 192, 200V	BY 229/200, BY 277/600, BYW 19/800
40274	BY194	BY 192, 400V	BY 229/400, BY 277/600, BYW 19/800

40275	BY195	BY 192, 800V	BY 229/800, BY 277/750, BYW 19/800
40276	BY196	100V, 1,2A, <500ns	BY 201/2, BYX 58/100, MR 811, RGP 10B
40277	BY197	BY 196, 200V	BY 201/2, BYX 58/200, MR 812, RGP 10D
40278	BY198	BY 196, 400V	BY 201/4, BYX 58/400, MR 814, RGP 10G
40279	BY199	BY 196, 800V	BY 231/800, BY 245/800, MR 817, RGP 10K
40280	BY200	BY 196, 1200V	BY 231/1200, BY 245/1200, BY 400
40281	BY2000	2kV, 3A	-
40282	BY201/2.../6	250..650V, 1A, <200ns	BYV 13...16, RGP 10D...J, RGP 15D...J
40283	BY202/...	250..650V, 1,5A, <350ns	BY 218/..., BYV 95A...E, RGP 15D...J
40284	BY203/12.../25(S)	1200..2500V, 0,25A, <300ns	SHG 1...2,5
40285	BY204/...	400..1000V, 0,4A <550ns	BA 157...159, BY 208/..., RGP 10G...M
40286	BY205/...	100..1000V, 3A, <850ns	BY 229/..., BYT 71/..., RGP 80B...M
40287	BY206(GP)	350V, 0,4A, <300ns	BA 157...159, BY 204/4, BY 406..407
40288	BY207(GP)	BY 206, 600V	BA 158...159, BY 204/8, BY 407
40289	BY208/...(GP)	600..1000V, 0,75A, <350ns	BY 245/..., BY 268...269, RGP 10J...M
40290	BY209	12,5kV, 2,5mA	BY 409, BY 476, BY 509, BY 710...713
40291	BY210/...	400..800V, 1A, <300ns	BYV 13...16, BYV 95B...E, RGP 10G...M
40292	BY211/2.../6	250..650V, 2A, <350ns	BY 218/..., BY 296...299, BYW 32...36
40293	BY212/...R	500..750V, 4A, <300ns	BY 229/800, BY 277/750, BYW 19/800
40294	BY213/...R	BY 212, 600..700V	BY 229/800, BY 277/750, BYW 19/800
40295	BY214/...	50..1000V, 6A	MR 750...756
40296	BY217/...	50..400V, 1A	BY 126, BY 134, BY 226, 1N4001...07
40297	BY218/...	100..800V, 2A, <200ns	BYW 33...36, BYT 77...78, RGP 30B...M
40298	BY223	1500V, 5A	BY 359/1500
40299	BY224/...	400..850V, 3,2A	B220C3200...B280C3200, etc.
40300	BY225/...	BY 224, 100..200V	B80C3200...B150C3200, etc.
40301	BY226(GP,MGP)	650V, 1,5A	BY 253...255, BY 259/600, 1N5397...99
40302	BY227(GP,MGP)	BY 226, 1250V	BY 255, BY 259/1000, BY 350/1300
40303	BY228/...	1000..1500V, 3A	BY 328
40304	BY229/...	200..1000V, 7A, <135ns	BY 359/..., RGP 80D...M
40305	BY229/...R	BY 229/...	BY 359/..., RGP 80D...M
40306	BY229F/...	BY 229/..	BYR 29F/..., BY 359F/...
40307	BY231/...	800..1500V, 1,25A	BY 228/..., BY 448
40308	BY233/...(A)	200..600V, 10A, <150ns	BY 329/..., RGP 80D...M
40309	BY238	1500V, 0,8A	BY 350/1500, DM 513, EM 516, GP 10W...Y
40310	BY239/..	200..1250V, 10A	-
40311	BY239/...A,L	BY 239	BYT 12P/...
40312	BY239/...R	BY 239	-
40313	BY245/...	800..1200V, 1,3A	BY 227, BY 255, BY 350/1300, BYX 87
40314	BY246/...	600..1200V, 2,5A	BY 255, BY 259/..., BYW 17/...
40315	BY249/...	300..600V, 6,5A(Tc110°)	BY 229/..., BY 239/..., GP 80G...M
40316	BY249/...R	BY 249/..	BY 229/...R, BY 239/...R, GP 80G...M
40317	BY249F/...	BY 249/..	BY 229F/..., BY 239/..., GP 80G...M
40318	BY250	1000V, 1,25A	BY 127, BY 133, BY 227, 1N4007
40319	BY251(G,GP)	200V, 3A	BYW 17/200, (R)GP 30D...M, 1N5402...08

40320	BY252(G,GP)	BY 251, 400V	BYW 17/400, (R)GP 30G...M, 1N5404...08
40321	BY253(G,GP)	BY 251, 600V	BYW 17/600, (R)GP 30J...M, 1N5406...08
40322	BY254(G,GP)	BY 251, 800V	BYW 17/800, (R)GP 30K...M, 1N5407...08
40323	BY255(G,GP)	BY 251, 1300V	BY 228, BY 448, BY 458, BYW 17/1200
40324	BY256	200V, 1,5A	B80C1500, etc.
40325	BY257	BY 256, 600V	B280C1500, etc.
40326	BY258/...	100..800V, 1,7A, 150ns	BYV 12...16, BY 218/..., RGP 15B...M
40327	BY259/...	150..1000V, 2,4A	BY 251...255, BYW 17/..., (R)GP 30D...M
40328	BY261/...	200..600V, 25A	KBPC 25-02...06
40329	BY268	1400V, 0,8A, <500ns	BY 228, BY 231/1500, BY 448
40330	BY269	BY 268, 1600V	BY 228, BY 231/1500, BY 448
40331	BY277/...R	600..750V, 3A	BYW 19/...R, BYX 71/...R, BY 229/...R
40332	BY288/...	150..1000V, 0,32A, 300ns	BY 208/..., BY 231/..., RGP 10B...M
40333	BY289/...	150..1000V, 0,52A, 300ns	BY 208/..., BY 231/..., RGP 10B...M
40334	BY290/...	150..600V, 150ns	BY 208/..., BY 231/..., RGP 10B...M
40335	BY291/...	75..600V, 1,1A, 150ns	BY 258/..., BYX 55/..., RGP 15B...M
40336	BY292/...	75..300V, 1,3A, 150ns	BY 258/..., BYX 55/..., RGP 15B...M
40337	BY293/...	75..300V, 3A, 150ns	BY 205/..., BY 229/..., BYV 87/...
40338	BY294/...	75..600V, 2,5A, 150ns	BY 205/..., BY 229/..., BYV 87/...
40339	BY295/...	150..600V, 1,05A, 150ns	BY 258/..., BYX 55/..., RGP 15D...M
40340	BY296(G,GP)	200V, 2A, <500ns	BY 218/200, BY 246/600, RGP 30D...M
40341	BY297(G,GP)	BY 296, 300V	BY 218/400, BY 246/600, RGP 30G...M
40342	BY298(G,GP)	BY 296, 500V	BY 218/600, BY 246/600, RGP 30J...M
40343	BY299(G,GP)	BY 296, 1000V	BY 228, BY 246/1000, BY 400, RGP 30M
40344	BY302/...	75..300V, 2,5A, 250ns	BY 205/..., BY 229/..., RGP 80B...M
40345	BY312/..	75..300V, 1,7A, <250ns	BYV 12...16, BY 218/..., RGP 15B...M
40346	BY318/...	100..600V, 3A, <200ns	BYW 16/..., BYW 72...76, RGP 30B...J
40347	BY328	1400V, 3A, <500ns, ..32kHz	-
40348	BY329/...	800..1200V, 7A, <135ns	BY 359/..., RGP 80M
40349	BY330	50V, 1A, <750ns	BY 201/2, BYX 55/350, RGP 10A...M
40350	BY331	BY 330, 100V	BY 201/2, BYX 55/350, RGP 10B...M
40351	BY332	BY 330, 200V	BY 201/2, BYX 55/350, RGP 10D...M
40352	BY333	BY 330, 300V	BY 201/3, BYX 55/350, RGP 10G...M
40353	BY334	BY 330, 400V	BY 201/4, BYX 55/600, RGP 10G...M
40354	BY335	BY 330	BY 201/5, BYX 55/600, RGP 10J...M
40355	BY336	BY 330, 500V	BY 201/5, BYX 55/600, RGP 10J...M
40356	BY337	BY 330, 800V	BY 231/800, BY 245/800, RGP 10K...M
40357	BY338	BY 330, 1000V	BY 231/1000, BY 245/1200, RGP 10M
40358	BY339	BY 330, 1500V	BY 231/1500, BY 228, BY 448
40359	BY350/...	1300..1500V, 1,5A, <4μs	BY 228, BY 448
40360	BY359/...	1000..1500V, 6,5A, <600ns	-
40361	BY359F-...	BY 359/..	-
40362	BY359X-...	BY 359/..	-
40363	BY360/600	600V, 1A, <400ns	BY 201/4, BYX 55/600, RGP 10J...M
40364	BY396(GP,P)	100V, 3A, <500ns	BY 318/100, BYW 14...16/100, RGP 30B...M



40365	BY397(GP,P)	BY 396, 200V	BY 318/200, BYW 14...16/200, RGP 30D...M
40366	BY398(GP,P)	BY 396, 400V	BY 318/400, BYW 14...16/400, RGP 30G...M
40367	BY399(GP,P)	BY 396, 800V	BY 438, BYW 14...16/800, RGP 30K...M
40368	BY399S	BY 396, 1000V	BY 228, BY 438, RGP 30M
40369	BY400	1300V, 2A, <500ns	BY 228, BY 448
40370	BY4000	3kV, 1,5A	-
40371	BY401	50V, 0,5A	BY 126, BY 135, BY 226, 1N4001...4007
40372	BY402	BY 401, 100V	BY 126, BY 134, BY 226, 1N4002...4007
40373	BY403	BY 401, 200V	BY 126, BY 134, BY 226, 1N4003...4007
40374	BY404	BY 401, 400V	BY 126, BY 134, BY 226, 1N4004...4007
40375	BY405	BY 401, 600V	BY 126, BY 134, BY 226, 1N4005...4007
40376	BY406(A)	BY 206, 0,8A	BY 201/4, BYX 55/350, RGP 10G...M
40377	BY407(A)	BY 207, 0,8A	BY 201/6, BYX 55/600, RGP 10J...M
40378	BY409(A)	12,5kV, 2,5mA	BY 209, BY 509, BY 476, BY 710...713
40379	BY410	100V, 1A, <100ns	EGP 10B...D, FE 1A...D, BYX 92/...
40380	BY428	1300V, 4A, <500ns,	-
40381	BY430F/1000	1000V, 5A, <110ns	-
40382	BY431F/1000	1000V, 5A, <85ns	-
40383	BY438	1200V, 5A	BY 228, BY 328, BY 428
40384	BY448	1500V, 2A	BY 228
40385	BY458	BY 448, 1200V	BY 228, BY 328, BY 438
40386	BY459-1500	1500V, 10A, <350ns	MUR 10150E
40387	BY459F-1500	BY 459-1500	-
40388	BY476(A)	18kV, 2,5mA	BY 711...713
40389	BY477	23kV, 2mA	BY 713
40390	BY478	BY 477, 27,5kV	BY 713
40391	BY500-...	50..1000V, 5A, <200ns	MR 821...826
40392	BY505	2000/2200V, 0,05A, 200ns	BY 203/20, SHG 2...2,5
40393	BY509	12,5kV, 4mA	BY 609...610
40394	BY510	BY 509, 17kV	BY 610
40395	BY520-10..-20	1000..2000V, 0,5A, 500ns	RGP 15-...
40396	BY527	1250V, 0,8A	BYW 18/1000, BYW 56, BYW 86, 1N4249
40397	BY530-...	50..1000V, 3A	BY 251...255, BYW 17/..., 1N5400...5408
40398	BY550-...	50..1000V, 5A	BY 214/..., BY 500/..., MR 750...760
40399	BY584	1800V, 0,05A, 200ns	BY 203/20, SHG 1,5...2
40400	BY588	25V, 1,5A	BYW 52, BYX 82, GP 15A...M, 1N5391...96
40401	BY6000	5kV, 1A	-
40402	BY601	50V, 1,5A	BY 226...227, BY 251...255, 1N5391...99
40403	BY602	BY 601, 100V	BY 226...227, BY 251...255, 1N5392...99
40404	BY603	BY 601, 200V	BY 226...227, BY 251...255, 1N5393...99
40405	BY604	BY 601, 400V	BY 226...227, BY 252...255, 1N5395...99
40406	BY605	BY 601, 600V	BY 226...227, BY 253...255, 1N5397...99
40407	BY606	BY 601, 800V	BY 227, BY 254...255, 1N5398...5399
40408	BY607	BY 601, 1000V	BY 227, BY 255, BY 350/1300, 1N5399
40409	BY608	BY 601, 1250V	BY 227, BY 255, BY 350/1300

40410	BY609	15kV, 4mA, 200ns	BY 619, BY 710...713
40411	BY610	BY 609, 17kV	BY 620, BY 710...713
40412	BY614	2200V, 0,05A, <300ns	BY 203/20, SHG 2,5
40413	BY617	9kV, 4mA, 100ns	BY 708...709
40414	BY619	15kV, 4mA, 100ns	BY 609, BY 710...713
40415	BY620	BY 619, 17kV	BY 610, BY 710...713
40416	BY627	1250V, 2A	-
40417	BY705	5kV, 20mA, 200ns	BY 715, CY 5, HS 6
40418	BY706	BY 705, 6kV	BY 716, CY 6, HS 6
40419	BY707	10kV, 4mA, 200ns	BY 609...610, BY 619...620, BY 717...719
40420	BY708	12kV, 4mA, 200ns	BY 609...610, BY 619...620, BY 718...719
40421	BY709	14kV, 4mA, 200ns	BY 609...610, BY 619...620, BY 719
40422	BY710	17kV, 3mA, 200ns	BY 610, BY 620, BY 711...714, BY 720...724
40423	BY711	19kV, 3mA, 200ns	BY 712...713, BY 721...724
40424	BY712	22kV, 3mA, 200ns	BY 713...714, BY 722...724
40425	BY712	22kV, 3mA, 200ns	BY 713...714, BY 722...724
40426	BY713	24kV, 3mA, 200ns	BY 714, BY 723...724
40427	BY713	24kV, 3mA, 200ns	BY 714, BY 723...724
40428	BY714	30kV, 3mA, 200ns	BY 724
40429	BY714	30kV, 3mA, 200ns	BY 724
40430	BY715	5kV, 20mA, 100ns	BY 705, CY 5, HS 6
40431	BY716	BY 705, 6kV	BY 706, CY 6, HS 6
40432	BY717	10kV, 4mA, 100ns	BY 609...610, BY 619...620, BY 707...709
40433	BY718	12kV, 4mA, 100ns	BY 609...610, BY 619...620, BY 708...709
40434	BY719	14kV, 4mA, 100ns	BY 609...610, BY 619...620, BY 709
40435	BY720	17kV, 3mA, 100ns	BY 610, BY 620, BY 710...714
40436	BY721	19kV, 3mA, 100ns	BY 711...714
40437	BY722	22kV, 3mA, 100ns	BY 712...714
40438	BY723	24kV, 3mA, 100ns	BY 713...714
40439	BY724	30kV, 3mA, 100ns	BY 714
40440	BY8000	7kV, 0,7A	-
40441	BY8004	4/5kV, 20mA, 200ns	-
40442	BY8006	BY 8004, 6/8kV, 10mA	-
40443	BY8008	BY 8004, 8/10kV, 5mA	-
40444	BY8010	BY 8004, 10/12kV, 5mA	-
40445	BY8012	BY 8004, 12/14kV, 5mA	-
40446	BY8014	BY 8004, 14/17kV, 5mA	-
40447	BY8016	BY 8004, 16/19kV, 3mA	-
40448	BY8104	4/5kV, 20mA, 100ns	-
40449	BY8106	BY 8104, 6/8kV, 10mA	-
40450	BY8108	BY 8104, 8/10kV, 5mA	-
40451	BY8110	BY 8104, 10/12kV, 5mA	-
40452	BY8112	BY 8104, 12/14kV, 5mA	-
40453	BY8114	BY 8104, 14/17kV, 5mA	-
40454	BY8116	BY 8104, 16/19kV, 5mA	-

40455	BY8404	4/5kV, 20mA, 200ns	-
40456	BY8406	BY 8404, 6/8kV, 10mA	-
40457	BY8408	BY 8404, 8/10kV, 5mA	-
40458	BY8410	BY 8404, 10/12kV, 5mA	-
40459	BY8412	BY 8404, 12/14kV, 5mA	-
40460	BY8414	BY 8404, 14/17kV, 5mA	-
40461	BY8416	BY 8404, 16/19kV, 3mA	-
40462	BY8418	BY 8404, 18/22kV, 3mA	-
40463	BY8420	BY 8404, 20/24kV, 3mA	-
40464	BY8424	BY 8404, 24/30kV, 3mA	-
40465	BYD11D...M	200..1000V, 0,58A	BYD 33D...M, BYV 26B...E, 1N4245...49
40466	BYD13D...M	200..1000V, 1,4A	BYD 33D...M, BYW 52...56, 1N5060...5062
40467	BYD14D...M	200..1000V, 2A, 2,5µs	BYW 52...56, 1N5060...5062
40468	BYD17D...M	BYD 13D..M, SMD	BYD 37D...M
40469	BYD31D...M	200..1000V, 0,4A, <300ns	BYD 33D...N, BYV 26B...E, BYV 95...96/...
40470	BYD33D...M	200..1000V, 1,3A, <300ns	BYM 26A...E, BYV 36A...E, BYV 95...96/...
40471	BYD33U...V	<500ns	RGP 15-12...-14
40472	BYD34D...M	200..1000V, 1,8A, <300ns	BYM 26A...E, BYW 95...96/...
40473	BYD37D...M	BYD 33D..M, SMD	-
40474	BYD43-20	2kV, 0,64A, <300ns	-
40475	BYD57D...M	<30..75ns	-
40476	BYD71A...G	50..400V, 0,5A, <50ns	EGP 10A...G, FE 1A...D
40477	BYD73A...G	50..400V, 1,75A, <50ns	BYV 27/..., EGP 20A...G, FE 2A...D
40478	BYD74A...G	50..400V, 2A, <50ns	BYV 27/..., EGP 20A...D, FE 2A...D
40479	BYD77A...G	BYD 73A..G, SMD	-
40480	BYG10D...M	200..1000V, 1,5A	FS 2D...M
40481	BYG20D...J	200..600V, 1,5A, <75ns	-
40482	BYG21K...M	800..1000V, 1,5A, <120ns	-
40483	BYG22A..D	50..200V, 2A, <25ns	-
40484	BYM05-...	50..1000V, 0,5A	BYD 37D...M
40485	BYM06-...	50..1000V, 0,5A, <500ns	BYD 37D...M
40486	BYM07-...	50..400V, 0,5A, <50ns	BYD 77A...G
40487	BYM10-...	50..1000V, 1A	BYD 17D...M
40488	BYM11-...	50..1000V, 1A, <500ns	-
40489	BYM12-...	50..400V, 1A, <50ns	SFE 1A...H
40490	BYM26A...E	200..1000V, 2,3A, <75ns	BYM 36A...E
40491	BYM30-...	50..1000V, 3A	-
40492	BYM31-...	50..1000V, 3A, <500ns	-
40493	BYM32-...	50..400V, 3A, <50ns	-
40494	BYM36A..E	200..1000V, 3A, <150ns	BYW 95A...C, BYW 96D...E
40495	BYM56A..E	200..1000V, 3,5A	BYW 18/..., BYW 82...86
40496	BYP100	1000V, 5A(Tc90°), 55ns	-
40497	BYP101	1000V, 15A(Tc90°), 80ns	-
40498	BYP102	1000V, 28A(Tc90°), 130ns	-
40499	BYP103	1000V, 45A(Tc90°), 140ns	-

40500	BYP20-..	50..150V, 10A, <30ns	BYQ 28/..., BYT 28/..., BYV 32/..., FE 16...
40501	BYP21-..	50..200V, 8A, <25ns	BYW 29/..., BYW 80/..., FE 8A...J
40502	BYP22-..	50..200V, 20A, <25ns	BYV 44/..., BYW 51/...
40503	BYP300	1200V, 4A(Tc90°), 50ns	-
40504	BYP301	1200V, 12A(Tc90°), 80ns	-
40505	BYP302	1200V, 25A(Tc90°), 130ns	-
40506	BYP303	1200V, 40A(Tc90°), 140ns	-
40507	BYP59-..M,U	300..400V, 60A, <60ns	BYT 60/...
40508	BYQ27/..	50..200V, 10A, <20ns	-
40509	BYQ28-..	50..200V, 10A, <20ns	BYP 20-..., BYV 32-..., FE 16A...J
40510	BYQ28E-..	BYQ 28-..	BYV 32E-...
40511	BYQ28F-..	BYQ 28-..	BYV 32F-...
40512	BYR210	PBYR 2100CT	PBYR 2100
40513	BYR28	PBYR 280CT	PBYR 280CT
40514	BYR28/..	500..800V, 10A, <80ns	-
40515	BYR29	PBYR 290CT	PBYR 290CT
40516	BYR29-..	500..800V, 8A, <75ns	MUR 850...8100
40517	BYR29F-..	BYR 29-..	-
40518	BYR30-..(U)	500..700V, 14A, <100ns	BYV 31/...
40519	BYR34-..	500..800V, 20A, <80ns	BYV 44/...
40520	BYR79-..	500..800V, 14A, <100ns	BYT 87/...
40521	BYS05-..	20..40V, 15A	BYS 15
40522	BYS08-..	20..50V, 8A	BYS 15
40523	BYS10-..	25..45V, 1,5A	-
40524	BYS11-90	90V, 1,5A	BYS 12-90
40525	BYS12-90	90V, 1,5A	BYS 11-90
40526	BYS15	45V, 15A	BYS 31-50, BYS 32
40527	BYS16-..	20..40V, 15A	MBR 1520...1540, 1N5826...28
40528	BYS21-..	45..90V, 1A	BYS 22-..., HRP 22, HRP 32
40529	BYS22-..	45..90V, 2A	BYS 26-...
40530	BYS24-..	45..90V, 2x5A	MBR 2060...20100
40531	BYS25-..	20..40V, 25A	BYV 121-..., MBR 2520...2540, 1N5829...31
40532	BYS26-..	45..90V, 3A	BYS 27/..., SB 350...380
40533	BYS27-45	45V, 5A	SB 550...580
40534	BYS28-..	45..90V, 2x15A	BYV 73/..., MBR 3045PT...3060PT
40535	BYS28-..	45..90V, 2x15A	BYV 73/..., MBR 3045PT...3060PT
40536	BYS30	45V, 30A	BYS 31/..., BYS 32, BYS 35/...
40537	BYS31-..	40..50V, 30A	BYS 32, BYS 35/..., MBR 3545
40538	BYS32	BYS 31, 50V	BYS 31/50, BYS 35/50
40539	BYS35-..	20..50V, 35A	BYV 22/..., MBR 3520...3545
40540	BYS40-..	20..40V, 40A	MBR 4020...4040, 1N5832...34
40541	BYS41(-35)	35V, 30A	BYS 30...32, BYS 35-45, MBR 3535...3545
40542	BYS42(-45)	45V, 60A	-
40543	BYS50	45V, 60A	BYS 60-45, BYV 23/45, MBR 6045
40544	BYS51(-35)	35V, 60A	BYS 50, BYS 60-45, BYV 23/45, MBR 6035

40545	BYS60-...	20..50V, 60A	BYS 50...51, BYV 23/..., MBR 6020...6045
40546	BYS71-..	40..50V, 80A	BYS 72, BYS 75/..., MBR 8045
40547	BYS72	50V, 75A	BYS 75-50, BYS 76-45, BYV 23/45, MBR7545
40548	BYS75-...	20..50V, 75A	BYS 71/..., BYS 72, BYS 76-45, BYV 23/...
40549	BYS76(-45)	45V, 75A	BYS 71/..., BYS 72, BYS 75-45, BYV 23/45
40550	BYS79-..	40..50V, 30A	BYS 42-45, MBR 3045...3060
40551	BYT01-...	200..400V, 1A, <50ns	BYV 26B...E
40552	BYT03-...	200..400V, 3A, <50ns	BYT 56G...M
40553	BYT08-...	200..400V, 8A, <35ns	BYV 29/..., ESM 980/..., FE 8D...G
40554	BYT08P-...A	200..1000V, 8A, <65ns	-
40555	BYT08PI-...		BYQ 28F-...
40556	BYT106/1300	1300V, 5A, <120ns	BY 359/1300, BYT 86/1300
40557	BYT108/..	200..400V, 8A, <50ns	BYV 29/..., FE 8D...J, RGP 80D...M
40558	BYT11-...	600..1000V, 1A, <100ns	BYV 26C...E
40559	BYT115/..	200..400V, 15A, <50ns	BYV 79/200, MUR 1520...1560
40560	BYT12-...(M)	200..1000V, 12A, <65ns	BYT 61/..., 1N3891...3893
40561	BYT12-...R	BYT 12-...(M)	BYT 61/...R, 1N3891R...3893R
40562	BYT12P...A	BYT 12-...(M)	BYR 79-..., BYT 87/...
40563	BYT12PI...A	BYT 12-...(M)	-
40564	BYT13-...	600..1000V, 3A, <150ns	BYT 56J...M
40565	BYT130/..	600..1000V, 30A, 90ns	-
40566	BYT16P-...A	200..400V, 16A, <35ns	BYV 34/..., FE 16D...J
40567	BYT230PI(V)200..		
40568	BYT230PI(V)600..		
40569	BYT231PI(V)...	BYT 230..	-
40570	BYT25/...	50..1000V, 25A	KBPC 25-005...-10
40571	BYT254(V)...	BYT 54..	-
40572	BYT260PI(V)...	BYT 261..	-
40573	BYT261PI(V)...	200..1000V, 2x60A,<170ns	-
40574	BYT28-...	300..500V, 10A, <60ns	BYR 28-..., BYV 34-..., FE 16F...J
40575	BYT30-...(M)	200..1000V, 30A, <70ns	BYT 65/..., BYV 92/...
40576	BYT30-...R(RM)	BYT 30/...(M)	BYT 65/...R, BYV 92/...R
40577	BYT30P-..	BYT 30-...(M)	-
40578	BYT30PI-..	BYT 30P-..	-
40579	BYT51A..M	50..1000V, 1,5A, <4µs	BY 127, BY 133, BYW 37...43, 1N4001...07
40580	BYT52A..M	50..1000V, 1,4A, <200ns	BY 218/..., BYV 13...16, BYV 36A...E
40581	BYT53A..G	50..400V, 1,5A, <50ns	BYM 27..., BYV 27/..., EGP 20..., FE2...
40582	BYT54A..M	50..1000V, 1,25A, <100ns	BYM 26A...E, BYV 36A...E
40583	BYT56A..M	50..1000V, 3A, <100ns	BYT 13/..., BYM 36A...E, BYW 16/...
40584	BYT60-...(M)	200..1000V, 60A, <70ns	-
40585	BYT60-...R,RM	BYT 60-..	-
40586	BYT60P-..	BYT 60-..	-
40587	BYT61(B)-...(M)	600..1000V, 12A, <200ns	BYT 12-..., BYX 62/..., BYX 66/...
40588	BYT61-...R,RM	BYT 61(B)-..	BYT 12-...R, BYX 62/...R, BYX 66/...R
40589	BYT62	2400V, 0,35A	-

40590	BYT65(B)-...(M)	600..1000V, 30A, <200ns	BYT 30-..., BYX 64/..., BYX 67/...
40591	BYT65-...R, RM	BYT 65(B)-..	BYT 30-...R, BYX 64/...R, BYX 67/...R
40592	BYT67-...	800..1000V, 50A, <100ns	-
40593	BYT71-...	100..800V, 6A, <300ns	BY 233/..., BYT 86/..., RGP 80B...M
40594	BYT71-...A	BYT 71-..., contr. av.	-
40595	BYT71-...R	BYT 71-..	BY 229/...R
40596	BYT71F-..	BYT 71-..	BY 229F/...
40597	BYT75-...K	200..600V, 120A	DS 85-02C...06C, 1N4588...4596
40598	BYT77	800V, 3A, <300ns	BYT 13/..., BYT 56K...M, BYW 16/800
40599	BYT78	BYT 77, 1000V	BYT 13/1000, BYT 56M
40600	BYT79-...	300..500V, 12,5A, <60ns	BYT 12-..., BYT 87-..., BYR 79-...
40601	BYT85/..	600..1000V, 4A, <80ns	BY 329/..., BYR 29/...
40602	BYT86/..	600..1000V, 8A, <80ns	BY 329/..., BYR 29/...
40603	BYT86/1300	BYT 86/..., 1300V, 5A, <150ns	BY 359/1300, BYT 106/1300
40604	BYT87/..	600..1000V, 15A, <80ns	BYR 79-...
40605	BYV10-...(A)	20..60V, 1A, <30ns	BYS 21/..., SB 120...180, 1N5817...5819
40606	BYV118-...	35..45V, 9A	BYS 24-45, BYV 33-..., BYV 133-...
40607	BYV118F-...	BYV 118-..	BYV 33F-..., BYV 133F-...
40608	BYV12	100..1000V, 1,5A, <300ns	BY 218/100, BYW 32...36, RGP 15B...M
40609	BYV120-...(M)	35..45V, 13,5A	BYS 15, MBR 1535...1540, 1N2528
40610	BYV121-...(M)	35..45V, 27A	BYS 31-..., BYS 32, MBR 2535...40, 1N5831
40611	BYV123-45	45V, 70A	BYS 71-50, BYS 72, BYS 76-45, MBR 7545
40612	BYV13	BYV 12, 400V	BY 218/400, BYW 34...36, RGP 15G...M
40613	BYV133-...	35..45V, 18A	BYV 33-..., BYV 133-..., MBR 2035...2045
40614	BYV133F-...	BYV 133-..	BYV 33F-..., BYV 43F-..., BYV 143F-...
40615	BYV14	BYV 12, 600V	BY 218/600, BYW 36, RGP 15J...M
40616	BYV143-...	35..45V, 2x15A	BYV 43-..., MBR 2535CT...2545CT
40617	BYV143F-...	BYV 143-..., 2x10A	BYV 43F-...
40618	BYV15	BYV 12, 800V	BY 218/800, BYT 77...78, RGP 15K...M
40619	BYV16	BYV 12, 1000V	BYT 78, BYV 96E, RGP 15M
40620	BYV18/...	30..45V, 8,8A	BYS 24/..., BYV 118/..., MBR 2060
40621	BYV19/...	30..45V, 9A	BYV 39/..., MBR 1035...10100
40622	BYV20/...	30..45V, 12,5A	BYS 15, MBR 1535...1540, 1N5827...5828
40623	BYV21/...	30..45V, 27A	BYS 30...32, BYV 121/..., MBR 2535...2540
40624	BYV22/...	30..45V, 50A	BYS 50...51, BYS 60/..., MBR 6030...6045
40625	BYV23/...	30..45V, 70A	BYS 71...72, BYS 75/..., BYS 76, BYV 123/...
40626	BYV24/...	800..1000V, 12A, <450ns	BYT 61/..., BYX 66/...
40627	BYV24/...R	BYV 24	BYT 61/...R, BYX 66/...R
40628	BYV25/...	50..1000V, 25A	KBPC 25-005...10
40629	BYV255(V)/...	50..200V, 2x100A, <80ns	-
40630	BYV26(A...E)	200..1000V, 1A, <30ns	EGP 10D...G, FE 1D...H
40631	BYV27/...	50..200V, 2A, <50ns	BYV 28/..., EGP 20A...G, FE 2A...D
40632	BYV28/...	50..200V, 3,5A, <50ns	EGP 30A...G, FE 3A...D
40633	BYV29-...	300..500V, 8A, <60ns	BYT 08-..., BYR 29-..., FE 8F...J
40634	BYV29F-...	BYV 29-..	BYR 29F-...



40635	BYV30-...(M,U)	200..500V, 12,5A, <50ns	BYT 12-..., BYX 61/...
40636	BYV30-...R,RM	BYV 30-...(M,U)	BYT 12-...R, BYX 61/...R
40637	BYV31-...(U)	300..500V, 25A, <50ns	-
40638	BYV32-...	50..200V, 18A, <25ns	BYT 16P-...A, BYW 51/..., FE 16A...G
40639	BYV32D-...	BYV 32-..	-
40640	BYV32E-..	BYV 32-..	-
40641	BYV32F-...	BYV 32-..., , 12A	-
40642	BYV32N-...	BYV 32-..	-
40643	BYV33-...	30..45V, 18A	BYV 43-..., BYV 133-..., MBR 1550...1560
40644	BYV33F-...	BYV 33-..	BYV 43F-..., BYV 133F-...
40645	BYV34-...	300..500V, 2x9A, <60ns	BYR 34-..., BYT 16P...A, FE 16F...J
40646	BYV36A...E	200..1000V, 1,6A, <150ns	BYD 34D...M, BYM 26A...E
40647	BYV37	800V, 2A, <300ns	BY 218/800, BYT 77...78, BYW 96D...E
40648	BYV38	BYV 37, 1000V	BYT 78, BYW 96E
40649	BYV39-...	30..45V, 12,5A	MBR 1635...1645
40650	BYV40-..	100..200V, 1,35A, <25ns	-
40651	BYV42-...	50..200V, 30A, <25ns	-
40652	BYV42E-..	BYV 42-..	-
40653	BYV43-...	30..45V, 30A	BYV 143-..., MBR 2535CT...2545CT
40654	BYV43F-...	BYV 43-..., , 26A	-
40655	BYV44-...	300..500V, 27A, <60ns	BYR 34-...
40656	BYV52-...	50..200V, 2x30A, <50ns	-
40657	BYV52-...	50..200V, 2x30A, <50ns	-
40658	BYV52-..PI	BYV 52-..	-
40659	BYV52-..PI	BYV 52-..	-
40660	BYV54(V)-...	50..200V, 2x50A, <60ns	-
40661	BYV541(V)/...	BYV 54(V)/..	-
40662	BYV61	50V, 6A, <30ns	FE 6A...D
40663	BYV62	BYV 61, 100V	FE 6B...D
40664	BYV63	BYV 61, 150V	FE 6C...D
40665	BYV71-...	BYT 71-..	BY 229-...R
40666	BYV71-...R	BYT 71-..R	
40667	BYV72-...	50..200V, 27A, <28ns	BYW 99P-..., MUR 3005PT...3060PT
40668	BYV72-...	50..200V, 27A, <28ns	BYW 99P-..., MUR 3005PT...3060PT
40669	BYV72E-..	BYV 72-..	-
40670	BYV72E-..	BYV 72-..	-
40671	BYV72F-..	BYV 72-..	BYW 77PI-..., BYW 99PI-...
40672	BYV73-...	30..45V, 30A	BYS 79-..., MBR 4035PT...4060PT
40673	BYV73-...	30..45V, 30A	BYS 79-..., MBR 4035PT...4060PT
40674	BYV74-...	300..500V, 27A, <60ns	MUR 3030PT...3060PT
40675	BYV74-...	300..500V, 27A, <60ns	MUR 3030PT...3060PT
40676	BYV74F-..	BYV 74-..., , 20A	BYT 30PI-...
40677	BYV79-...	50..200V, 12,7A, <35ns	BYR 79-...
40678	BYV79E-..	BYV 72-..	-
40679	BYV88-...	200..1000V, 1A, <150ns	BY 218/..., BYV 37...38, RGP 10D...M

40680	BYV92-...(M)	200..500V, 35A, <50ns	MR 862...866
40681	BYV92-...R,RM	BYV 92/..	MR 862R...866R
40682	BYV95A...C	200..600V, 1,5A, <250ns	BYW 95A...C, BYW 96D,E
40683	BYV96D..E	BYV 95, 800..1000V, <300ns	BYW 96D,E
40684	BYW07/...(M)	50..200V, 70A, <50ns	BYT 60/..., BYW 08/..., BYW 94/...
40685	BYW07/...R,RM	BYW 07/...(M)	BYT 60/...R
40686	BYW08/...(M)	50..200V, 80A, <60ns	-
40687	BYW10/...	50..1000V, 1,5A, <400ns	BY 218/..., BY 258/..., RGP 15A...M
40688	BYW10/...R	BYW 10/..	BY 218/..., BY 258/..., RGP 15A...M
40689	BYW100/..	50..200V, 1,5A, <35ns	BYD 74A...G, BYV 27/..., EGP 20A...D
40690	BYW11/...	50..1000V, 6A, <400ns	BYT 61/..., BYX 50/..., BYX 66/...
40691	BYW11/...R	BYW 11/..	BYT 61/...R, BYX 50/...R, BYX 66/...R
40692	BYW12/...	50..1000V, 15A, <400ns	BYX 30/...
40693	BYW12/...R	BYW 12/..	BYX 30/...R
40694	BYW13/...	25..30V, 40A	BYS 50...51, BYS 60/..., MBR 4030...4040
40695	BYW14/...	100..800V, 3A, <750ns	BYT 77...78, BYW 72...76, RGP 30B...M
40696	BYW15/...	BYW 14/..., <500ns	BYT 77...78, BYW 72...76, RGP 30B...M
40697	BYW16/...	BYW 14/..., <200ns	BYT 77...78, BYW 72...76, BYW 96D...E
40698	BYW17/...	100..1200V, 3A	BY 251...255, 1N5402...5408, GP 30B...M
40699	BYW172D..G	200..400V, 3A, <100ns	BYT 56...
40700	BYW178	800V, 3A, <60ns	BYT 56K...M
40701	BYW18/...	400..1000V, 3A	BYW 84...86, BYW 95B,C, BYW 96D,E
40702	BYW19/...	800..1000V, 7A, <450ns	BY 229/..., RGP 80K...M
40703	BYW19/...R	BYW 19/..	BY 229/...R
40704	BYW20	50V, 15A	KBPC 15-005
40705	BYW21	BYW 20, 100V	KBPC 15-02
40706	BYW22	BYW 20, 200V	KBPC 15-02
40707	BYW23	BYW 20, 300V	KBPC 15-04
40708	BYW24	BYW 20, 400V	KBPC 15-04
40709	BYW25/...	800..1000V, 40A, <450ns	BYT 67/...
40710	BYW25/...R	BYW 25/..	-
40711	BYW26	BYW 20, 600V	KBPC 15-06
40712	BYW27/...(GP)	50..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
40713	BYW28	BYW 20, 800V	KBPC 15-08
40714	BYW29-...	50..200V, 7,6A, <25ns	BYW 80-..., FE 8A...G
40715	BYW29-...A	BYW 29-..	BYW 80-...A
40716	BYW29-...F	BYW 29-..	-
40717	BYW29E-..	BYW 29-..	-
40718	BYW30/...(U)	50..200V, 10A, <35ns	BYT12/..., BYV30/..., BYW81/..., BYX61/...
40719	BYW31/...(U)	50..200V, 23A, <50ns	MUR 2505...2520
40720	BYW32	200V, 2A, <200ns	BY 218/200, BYW 72...76, BYW 95A
40721	BYW33	BYW 32, 300V	BY 218/400, BYW 73...76, BYW 95B
40722	BYW34	BYW 32, 400V	BY 218/400, BYW 74...76, BYW 95B
40723	BYW35	BYW 32, 500V	BY 218/600, BYW 76, BYW 95C
40724	BYW36	BYW 32, 600V	BY 218/600, BYW 76, BYW 95C

40725	BYW37	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
40726	BYW38	BYW 37, 100V	BY 126...127, BY 133...135, 1N4002...07
40727	BYW39	BYW 37, 200V	BY 126...127, BY 133...134, 1N4003...07
40728	BYW40	BYW 37, 400V	BY 126...127, BY 133...134, 1N4004...07
40729	BYW41	BYW 37, 600V	BY 126...127, BY 133...134, 1N4005...07
40730	BYW42	BYW 37, 800V	BY 127, BY 133, BY 227, 1N4006...07
40731	BYW43	BYW 37, 1000V	BY 127, BY 133, BY 227, 1N4007
40732	BYW48/...	100..300V, 12A, <200ns	BYT 12/..., BYV 30/..., 1N3890...3893
40733	BYW48/...R	BYW 48/..	BYT 12/..., BYV 30/...R, 1N3890R...3893R
40734	BYW51-...	50..200V, 2x10A, <35ns	BYP 22/..., BYV 42/..., BYV 44/...
40735	BYW51F-..	BYW 51-..	-
40736	BYW52	200V, 2A, <4μs	BYW 18/400, BYW 82...86, 1N5060...5062
40737	BYW53	BYW 52, 400V	BYW 18/400, BYW 83...86, 1N5060...5062
40738	BYW54	BYW 52, 600V	BYW 18/600, BYW 84...86, 1N5061...5062
40739	BYW55	BYW 52, 800V	BYW 18/800, BYW 85...86, 1N5062
40740	BYW56	BYW 52, 1000V	BYW 18/1000, BYW 86
40741	BYW58/...	50..600V, 1A, <200ns	BY 201/..., BYV 12...16, RGP 10A...M
40742	BYW59/...	50..600V, 3A, <200ns	BYW 16/..., BYW 72...76, BYW 95A...C
40743	BYW60	50V, 35A	KBPC 35-005
40744	BYW61	BYW 60, 100V	KBPC 35-02
40745	BYW62	BYW 60, 200V	KBPC 35-02
40746	BYW63	BYW 60, 300V	KBPC 35-04
40747	BYW64	BYW 60, 400V	KBPC 35-04
40748	BYW65/...	200..1000V, 1A	BY 126...127, BY 133...134, 1N4003...07
40749	BYW66	BYW 60, 600V	KBPC 35-06
40750	BYW67/...	200..800V, 3A	BY 251...255, 1N5402...08, RGP 30D...M
40751	BYW68	BYW 60, 800V	KBPC 35-08
40752	BYW69(A,B)	20..60V, 15A	BYS 15, BYV 120/...
40753	BYW70(A,B)	20..60V, 25A	BYS 31...32, BYS 35/..., BYS 41
40754	BYW71(A,B)	20..60V, 10A	BYS 15, BYV 120/..., MBR 1520...1540
40755	BYW72	200V, 3A, <200ns	BY 318/200, BYW 16/200, BYW 95A
40756	BYW73	BYW 72, 300V	BY 318/400, BYW 16/400, BYW 95B
40757	BYW74	BYW 72, 400V	BY 318/400, BYW 16/400, BYW 95B
40758	BYW75	BYW 72, 500V	BY 318/600, BYW 16/600, BYW 95C
40759	BYW76	BYW 72, 600V	BY 318/600, BYW 16/800, BYW 95C
40760	BYW77-...(M)	50..200V, 25A, <50ns	BYV 31/..., BYW 31/..., MUR 2505...2520
40761	BYW77-...R(RM)	BYW 77-..	-
40762	BYW77P-...	BYW 77-..	BYT 30P-...
40763	BYW77PI-..	BYW 77P-..	BYT 30PI-...
40764	BYW78-...(M)	50..200V, 50A, <60ns	BYW 07/...(M), BYW 93/..., BYW 94/...
40765	BYW78-...R(RM)	BYW 78-..	BYW 07/...R(RM)
40766	BYW79	1000V, 15A	KBPC 15-10
40767	BYW80-...	50..200V, 10A, <35ns	BYP 21-..., BYW 29/..., FE 8A...G
40768	BYW80-...A	BYW 80/..	-
40769	BYW80F-..	BYW 80P-..	BYW 29/...F

40770	BYW80PI-..	BYW 80P-..	BYW 29/...F
40771	BYW81-...(M)	50..200V, 15A, <35ns	BYV 31/..., BYW 31/..., BYW 77/...M
40772	BYW81-...R,RM	BYW 81-..	BYW 77/...R(RM)
40773	BYW81P-..	BYW 81P-...(M)	BYV 79/...
40774	BYW81PI-..	BYW 81P-..	-
40775	BYW82	200V, 3A	BYW 18/400, BYW 95A
40776	BYW83	BYW 82, 400V	BYW 18/400, BYW 95B
40777	BYW84	BYW 82, 600V	BYW 18/600, BYW 95C
40778	BYW85	BYW 82, 800V	BYW 18/800, BYW 96D
40779	BYW86	BYW 82, 1000V	BYW 18/1000, BYW 96E
40780	BYW88-...(M)	50..1200V, 12A	BYX 75...81, BYX 99/..., 1N4506...11
40781	BYW88-...R,RM	BYW 88-..	BYX 75...81R, BYX 99/...R
40782	BYW89	1000V, 15A	KBPC 15-10
40783	BYW92/...(U)	50..200V, 23A, <50ns	BYX 65/...
40784	BYW92/...R	BYW 92/..	BYX 65/...R
40785	BYW93/...(U)	50..200V, 50A, <60ns	BYW 07/..., BYW 78/..., BYW 94/...
40786	BYW94/...	50..200V, 70A, <60ns	BYW 07/..., BYW 08/...
40787	BYW95(A..C)	200..600V, 3A, <250ns	BYM 36A...E
40788	BYW96(D,E)	BYW 95, 800..1000V, <300ns	BYM 36A...E
40789	BYW98/...	50..200V, 3A, <50ns	BYV 28/..., EGP 30A...D, FE 3A...D
40790	BYW99-..	50..200V, 2x15A, <50ns	-
40791	BYW99P-..	BYW 99-..	BYV 72/..., MUR 3005PT...3060PT
40792	BYW99P-..	BYW 99-..	BYV 72/..., MUR 3005PT...3060PT
40793	BYW99PI-..	BYW 99P-..	BYV 52/...PI
40794	BYW99PI-..	BYW 99P-..	BYV 52/...PI
40795	BYX10(G,GP)	800/1600V, 0,36A	BY 231/1500, BY 269, EM 516, GP 10Y
40796	BYX11	2000V, 0,01A	BAY 91, BY 203/20, SHG 2...2,5
40797	BYX110GP	..400Hz, 9kV, 0,35A	-
40798	BYX120G	3kV, 0,1A	-
40799	BYX13/...	400..1600V, 20A	-
40800	BYX13/...R	BYX 13/..	D21S/..., D24/...
40801	BYX14/...	400..1200V, 150A	-
40802	BYX14/...R	BYX 14/..	-
40803	BYX15	1200V, 40A	-
40804	BYX16	BYX 15	D30S/..., D34/...
40805	BYX20/200	200V, 25A	1N3493...3495
40806	BYX20/200R	BYX 20/200	DS 25-02A...06A, 1N3493R...3495R
40807	BYX21(L)/...	50..200V, 25A	1N3491...3495
40808	BYX21(L)/...R	BYX 21(L)/..	DS 25-01A...06A, 1N3491R...3495R
40809	BYX22/...	200..1200V, 1,4A	BY 226...227, GP 15D...M, 1N5393...99
40810	BYX23/...	400..1000V, 100A	1N3291...32979
40811	BYX24	800V, 0,8A	-
40812	BYX25/...	600..1400, 20A	-
40813	BYX25/...R	BYX 25/..	DS 17-07A...16A, SSi E2040...E20100
40814	BYX26/...	60..150V, 0,25A	BA 157...159, BY 401...405, 1N4001...07

40815	BYX27/...	400..1000V, 250A	-
40816	BYX28/...	200..400V, 25A	1N3493...3495
40817	BYX28/...R	BYX 28/..	DS 25-02A...06A, 1N3493R...3495R
40818	BYX30/...	200..600V, 14A,<350ns	BYX 46/...
40819	BYX30/...R	BYX 30/..	BYX 46/...R
40820	BYX32/...	200..1600V, 100A	1N3289...3297
40821	BYX32/...R	BYX 32/..	DS 80-...A, 1N3289R...3297R
40822	BYX34/...	200..500V, 60A,<600ns	BYT 60/...
40823	BYX34/...R	BYX 34/..	BYT 60/...R
40824	BYX35	37kV, 0,05A	-
40825	BYX36/...	150..600V, 1A	BYW 27/..., BYX 55/..., 1N4003...4007
40826	BYX38/...	300..1200V, 6A	BYX 39/...
40827	BYX38/...R	BYX 38/..	BYX 39/...R
40828	BYX39/...	600..1400V, 6A	-
40829	BYX39/...R	BYX 39/..	-
40830	BYX40/...	600..1000V, 12A	1N4508...4511
40831	BYX40/...R	BYX 40/..	-
40832	BYX42/...	300..1200V, 10A	BYW 88/..., BYX 98/..., BYX 99/...
40833	BYX42/...R	BYX 42/..	BYW 88/...R, BYX 98/...R, BYX 99/...R
40834	BYX42/...T	BYX 42/..	BYW 88/...R, BYX 98/...R, BYX 99/...R
40835	BYX45/...R	200..1400V, 1,5A	BYW 52...56, SSiB9860A...9890A
40836	BYX46/...	200..600V, 15A,<200ns	BYX 30/...
40837	BYX46/...R	BYX 30/..	BYX 30/...R
40838	BYX47	2000V, 6A	-
40839	BYX48/...	300..1200V, 6A	BYX 38/..., BYX 39/..., BYX 42/...
40840	BYX48/...R	BYX 48/..	BYX 38/...R, BYX 39/...R, BYX 42/...R
40841	BYX49/...	300..1200V, 6A	-
40842	BYX49/...R	BYX 49/..	-
40843	BYX50/...	200..600V, 7A, <500ns	-
40844	BYX50/...R	BYX 50/..	-
40845	BYX52/...	300..1200V, 40A	BYX 56..., BYX 97/...
40846	BYX52/...R	BYX 52/..	BYX 56...R, BYX 97/...R
40847	BYX53	2000V, 0,05A	BY 203/20, SHG 2...2,5, 1N5181
40848	BYX54	BYX 53, 3000V	1N5181
40849	BYX55/...(GP,P)	350..600V, 1,2A, <750ns	BY 231/..., RGP 15G...M, MR 814...818
40850	BYX56/...	600..1400V, 40A	-
40851	BYX56/...R	BYX 56/..	-
40852	BYX57/...	500..600V, 0,4A, <200ns	BYT 11/..., BYV 26C...E, BYV 95C
40853	BYX58/...	50..400V, 1A, <250ns	BYV 12...16, BYX 92/..., RGP 10A...M
40854	BYX59/...	200..500V, 40A, <600ns	BYX 56/..., BYX 97/...
40855	BYX60/...	50..1000V, 0,4A	BA 157...159, BYW 27/..., 1N4001...07
40856	BYX61/...(M)	50..400V, 12A, <100ns	BYT 12/..., BYT 61/..., BYV 30/...
40857	BYX61/...R,RM	BYX 61/..	BYT 12/...R, BYT 61/..., BYV 30/...R
40858	BYX62/...(M)	600..800V, 12A, <200ns	BYT 12/..., BYT 61/..., BYV 30/...
40859	BYX62/...R,RM	BYX 62/..	BYT 12/...R, BYT 61/...R, BYV 30/...

40860	BYX63/600(M)	600V, 20A, <200ns	BYT 65/..., BYX 64/...
40861	BYX63/600R, RM	BYX 63/600(M)	BYT 65/...R, BYX 64/...R
40862	BYX64/600(M)	600V, 30A, <200ns	BYT 65/..., MR 866
40863	BYX64/600R, RM	BYX 64/..	BYT 65/...R, MR 866R
40864	BYX65/...(M)	50..400V, 30A, <100ns	BYT 30/..., BYV 92/...
40865	BYX65/...R, RM	BYX 65/..	BYT 30/...R, BYV 92/...R
40866	BYX66/...(M)	400..1000V, 12A, <500ns	BYT 61/...
40867	BYX66/...R, RM	BYX 66/..	BYT 61/...R
40868	BYX67/...	400..1000V, 30A, <500ns	BYT 65/...
40869	BYX67/...R	BYX 67/..	BYT 65/...R
40870	BYX68	1000V, 1A	BY 127, BY 133, BY 227, 1N4007
40871	BYX69	BYX 68	BY 127, BY 133, BY 227, 1N4007
40872	BYX70/...	100..600V, 1A, <200ns	BY 201/..., BYX 92/..., RGP 10B...M
40873	BYX71/...	350..600V, 7A, <450ns	BYW 19/..., BY 229/...
40874	BYX71/...R	BYX 71/..	BY 277/...R, BYW 19/...R
40875	BYX72/...	150..500V, 10A	BY 239/...
40876	BYX72/...R	BYX 72/..	BY 239/...R
40877	BYX73(A,B)	20..60V, 5A	BYS 15, BYV 120/..., MBR 1520...1540
40878	BYX74/...	100..800V, 1,5A	B80C1500...B600C1500, etc.
40879	BYX75	50V, 12A	BYW 88/50, BYX 99/300, 1N4506...4511
40880	BYX75R	BYX 75	BYW 88/50R, BYX 99/300R
40881	BYX76	100V, 12A	BYW 88/100, BYX 99/300, 1N4506...4511
40882	BYX76R	BYX 76	BYW 88/100R, BYX 99/300R
40883	BYX77	200V, 12A	BYW 88/200, BYX 99/300, 1N4506...4511
40884	BYX77R	BYX 77	BYW 88/200R, BYX 99/300R
40885	BYX78	400V, 12A	BYW 88/400, BYX 99/600, 1N4507...4511
40886	BYX78R	BYX 78	BYW 88/400R, BYX 99/600R
40887	BYX79	600V, 12A	BYW 88/600, BYX 99/600, 1N4508...4511
40888	BYX79R	BYX 79	BYW 88/600R, BYX 99/600R
40889	BYX80	800V, 12A	BYW 88/800, BYX 99/900, 1N4509...4511
40890	BYX80R	BYX 80	BYW 88/800R, BYX 99/900R
40891	BYX81	1000V, 12A	BYW 88/1000, BYX 99/1200, 1N4510...4511
40892	BYX81R	BYX 81	BYW 88/1000R, BYX 99/1200R
40893	BYX82	200V, 1,5A	BY 226...227, (R)GP 15D...M, 1N5393...99
40894	BYX83	BYX 82, 400V	BY 226...227, (R)GP 15G...M, 1N5395...99
40895	BYX84	BYX 82, 600V	BY 226...227, (R)GP 15J...M, 1N5397...99
40896	BYX85	BYX 82, 800V	BY 227, (R)GP 15K...M, 1N5398...5399
40897	BYX86	BYX 82, 1000V	BY 227, BY 350/1300, (R)GP 15M, 1N5399
40898	BYX87	BYX 82, 1200V	BY 227, BY 255, BY 350/1300
40899	BYX88	20V, 30A	-
40900	BYX89(A,B)	20..60V, 50A	BYS 50...51, BYS 60/..., BYV 23/...
40901	BYX90	7,5kV, 0,2A	-
40902	BYX90G	BYX 90, 8kV, 0,5A	-
40903	BYX92/...	50..400V, 1A, <100ns	BY 218/..., FE 1A...D, RGP 10A...G
40904	BYX93	200V, 60A	-



40905	BYX93R	BYX 93	-
40906	BYX94	1250V, 1A	BY 133, BY 255, EM 513, GP 10V...Y
40907	BYX95	1300V, 1A	BY 133, BY 255, EM 513, GP 10V...Y
40908	BYX96/...(U)	300..1600V, 30A	-
40909	BYX96/...R	BYX 96/..	-
40910	BYX97/...	300..1600V, 40A	BYX 56/...
40911	BYX97/...R	BYX 97/..	BYX 56/...R
40912	BYX98/...	300..1200V, 10A	BYW 88/..., BYX 42/..., 1N4606...4611
40913	BYX98/...R	BYX 98/..	BYW 88/...R, BYX 42/...R
40914	BYX99/...	300..1200V, 15A	BYX 25/..., BYX 96/...
40915	BYX99/...R	BYX 99/..	BYX 25/...R, BYX 96/...R
40916	BYY15	800V, 36A	-
40917	BYY16	BYY 15	D30S/...
40918	BYY19	1500V, 4A	BY 359/1500
40919	BYY20(200)	200V, 18A	1N3493...3495
40920	BYY21(200)	200V, 18A	DS25-02A...06A, 1N3493R...3495R
40921	BYY22	400V, 12A	-
40922	BYY23	BYY 22	D24/400B...1800B, D21S/1000...1400
40923	BYY24	800V, 12A	-
40924	BYY25	BYY 24	D24/800B...1800B, D21S/1000...1400
40925	BYY27	300V, 220A	1N3737...3744
40926	BYY28	BYY 27, 500V	1N3739...3744
40927	BYY29	BYY 27, 650V	1N3740...3744
40928	BYY30	BYY 27, 800V	1N3741...3744
40929	BYY31	150V, 1A	BY 126, BY 135, BY 226, 1N4003...07
40930	BYY32	BYY 31, 300V	BY 126, BY 134, BY 226, 1N4004...07
40931	BYY33	BYY 31, 450V	BY 126, BY 134, BY 226, 1N4005...07
40932	BYY34	BYY 31, 600V	BY 126, BY 134, BY 226, 1N4005...07
40933	BYY35	BYY 31, 750V	BY 127, BY 133, BY 227, 1N4006...07
40934	BYY36	BYY 31, 900V	BY 127, BY 133, BY 227, 1N4007
40935	BYY37	BYY 31, 1050V	BY 127, BY 133, BY 227, 1N4007
40936	BYY38	BYY 27, 1000V	1N3742...3744
40937	BYY39	BYY 27, 1200V	1N3743...3744
40938	BYY39/...	200..2400V, 220A	1N3736...3744
40939	BYY39/...R	BYY 39/..	1N3736R...3744R
40940	BYY56	1200V, 0,56A	BY 208/1000, BY 245/1200, (R)GP 10M
40941	BYY57/...	75..700V, 35A	SSi E1205...1240, 1N3660R...3665R
40942	BYY58/...	BYY 57/..	SSi E1105...1140, 1N3660...3665
40943	BYY59	300V, 1,2A	BY 226, (R)GP 15G...M, 1N5394...5399
40944	BYY60	BYY 59, 600V	BY 226, (R)GP 15J...M, 1N5397...5399
40945	BYY61	BYY 59, 900V	BY 227, BY 350/1300, (R)GP 15M, 1N5399
40946	BYY62	BYY 59, 1200V	BY 227, BY 350/1300, GH 3E...F
40947	BYY67	600V, 10A	-
40948	BYY68	BYY 67	D24/800B...1800B, D21S/1000...1400
40949	BYY69	1000V, 10A	-

40950	BYY70	BYY 69	D24/1200B...1800B, D21S/1000...1400
40951	BYY71	1200V, 10A	-
40952	BYY72	BYY 71	D24/1200B...1800B, D21S/1000...1400
40953	BYY73	600V, 40A	-
40954	BYY74	BYY 73	D60/800...1400, DS42-07A...16A
40955	BYY75	1000V, 40A	-
40956	BYY76	BYY 75	D60/1200...1400, DS42-11A...16A
40957	BYY77	1200V, 36A	-
40958	BYY78	BYY 77	D30S/1200...1400, D34/1200B...1800B
40959	BYY88	150V, 1..4A	BYX 38/300...1200, BY 205/200...1000
40960	BYY89	BYY 88, 300V	BYX 38/300...1200, BY 205/400...1000
40961	BYY90	BYY 88, 600V	BYX 38/600...1200, BY 205/600...1000
40962	BYY91	BYY 88, 1200V	BYX 38/1200, BY 359/1300
40963	BYY92	BYY 88, 1600V	BY 359/1500
40964	BYY93	800V, 150A	-
40965	BYY94	BYY 93	-
40966	BYY95	1200V, 150A	-
40967	BYY96	BYY 95	-
40968	BYZ10	1200V, 6A	BYX 38/1200, BY 359/1300
40969	BYZ11	BYZ 10, 900V	BYX 38/900...1200V, BY 359/1000
40970	BYZ12	BYZ 10, 600V	BYX 38/600...1200, BY 205/600...1000
40971	BYZ13	BYZ 10, 300V	BYX 38/300...1200, BY 205/400...1000
40972	BYZ14	400V, 36A	-
40973	BYZ15	BYZ 14	D30S/1000...1400, D34/400B...1800B
40974	BYZ16	BYZ 10	BYX 38/1200R, BY 359/1300
40975	BYZ17	BYZ 11	BYX 38/900R...1200R, BY 359/1000
40976	BYZ18	BYZ 12	BYX 38/600R...1200R, BY 205/600...1000
40977	BYZ19	BYZ 13	BYX 38/300R...1200R, BY 205/400...1000
40978	BZ	P4 SMA-43A	P4 SMA-43A
40979	BZ	BCX 71RL	BCX 71RL
40980	BZ-050...-350	5..35V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N4733...53
40981	BZ100	3,9V, 10%, 0,3W	BZX55/C3V9, BZX79/C3V9, ZPD3,9, 1N4730
40982	BZ102/0V7...3V4	0,7..3,4V, 0,25W	BZX 75/...
40983	BZD10/C3V3...200	3,3..200V, 5%, 1,3W	BZW22/..., BZX61/..., ZPY..., 1N5313...56
40984	BZD23/C3V9...270	3,9..270V, 5%, 2,5W	BZW 04/...
40985	BZD27/C3V6...270	3,9..270V, 5%, 2,3W	HZK ..., RLZ 5221B...
40986	BZG03-10...-270	BZD 27/10..270, 1,25W	BZG 04/..., HZF ..., MA 1Z...
40987	BZG04/8V2..430	300W(10/1000µs)	-
40988	BZG05/3V3..15	3,3..15V, 5%, 1,25W	BZG 03/..., PTZ..., RD...FM
40989	BZM85/C2V7..200	BZX 85/C..., SMD	-
40990	70	6,2..270V, 1,3W, 600W(100µs)	BZW 04/..., BZW 06/...
40991	BZT55/C2,4..75	BZX 55/C..., 0,5W	BZD 27/C...
40992	BZV10	6,5V, 5%, 0,4W, +-0,01%/°C	BZV 27, BZX 90, 1N4575, 1N4580
40993	BZV11	BZV 10, +-0,005%/°C	BZV 28, BZX 91, 1N4576, 1N4581
40994	BZV12	BZV 10, +-0,002%/°C	BZV 29, BZX 92, 1N4577, 1N4582

40995	BZV13	BZV 10, +0,001%/°C	BZV 30, BZX 93, 1N4578, 1N4583
40996	BZV14	BZV 10, +0,0005%/°C	BZV 31, BZX 94, 1N4579, 1N4584
40997	BZV15/C7V5...75	7,5..75V, 5%, 15W(Tc82°)	-
40998	R	7,5..75V, 5%, 15W(Tc82°)	-
40999	BZV16/C3V3...100	3,3..100V, 5%, 3W	BZT03/..., BZV40/..., BZV48/..., 1N5333...78
41000	BZV17/C5V6...56	5,6..56V, 5%, 0,25W,	BZV39/..., 1N4099...4127
41001	BZV18/C5V6...12	5,6..12V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N4734...42
41002	7	4,7..47V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5728...52
41003	7	BZV 19M/..	BZV 19M/...
41004	7	BZV 19M/..	BZV 19M/...
41005	BZV21A	8,5V, 0,4W, +0,001%/°C	1N3157, 1N4778, 1N4783
41006	BZV21B	BZV 21A, +0,002%/°C	1N3156, 1N4777, 1N4782
41007	BZV21C	BZV 21A, +0,005%/°C	1N3155, 1N4776, 1N4781
41008	BZV21D	BZV 21A, +0,01%/°C	1N3154, 1N4775, 1N4780
41009	BZV22(A..D)	BZV 21(A..D), 12,5V	1N4907...04, 1N4911...08, 1N4915...12
41010	BZV23(A..D)	BZV 21(A..D), 18,5V	-
41011	BZV24(A..D)	BZV 21(A..D), 8,7V	BZV 21(A..D)
41012	BZV25(A..D)	BZV 21(A..D), 13V	-
41013	BZV26(A..D)	BZV 21(A..D), 19V	2N4924...22, 1N4928...25, 1N4932...29
41014	BZV27(A)	6,2V, 0,4W, +0,01%/°C	BZV 10, BZX 90, 1N4575, 1N4580
41015	BZV28(A)	BZV 27(A), +0,005%/°C	BZV 11, BZX 91, 1N4576, 1N4581
41016	BZV29(A)	BZV 27(A), +0,002%/°C	BZV 12, BZX 92, 1N4577, 2N4582
41017	BZV30(A)	BZV 27(A), +0,001%/°C	BZV 13, BZX 93, 1N4578, 1N4583
41018	BZV31(A)	BZV 27(A), +0,0005%/°C	BZV 14, BZX 94, 1N4579, 1N4584
41019	BZV32(A..B)	9V, 0,5W, +0,01%/°C	1N935, 1N4765
41020	BZV33(A..B)	BZV 32(A..B), +0,005%/°C	1N936, 1N4766, 1N4771
41021	BZV34(A..B)	BZV 32(A..B), +0,002%/°C	1N937, 1N4767, 1N4772
41022	BZV35(A..B)	BZV 32(A..B), +0,001%/°C	1N938, 1N4768, 1N4773
41023	BZV36(A..B)	BZV 32(A..B), +0,0005%/°C	1N939, 1N4769, 1N4774
41024	BZV37	6,5V, 5%, 0,4W	-
41025	BZV38	6,4V, 5%	BZV 10...14, BZX 90...94, 1N4565...84
41026	BZV39/C0V8	0,8V, 0,5W	BZX 55/C0V8
41027	BZV39/C2V4...75	2,4..75V, 5%, 0,5W	1N4099...4131
41028	BZV40/C3V3...200	3,3..200V, 5%, 5W	BZV 48/..., 2N5338B...5388B
41029	BZV41/C2V7...47	2,7..47V, 5%, 0,75W	BZV85/..., BZX61/..., ZPY..., 1N4728...56
41030	BZV42/C2V7...47	2,7..47V, 5%, 0,75W	BZV85/..., BZX61/..., ZPY..., 1N4728...56
41031	BZV43(A..C)	6,2V, 1..5%, 0,25W	BZV 10...14, BZX 90...94, 1N4565...4584
41032	BZV44(A..C)	6,2V, 1..5%, 0,25W	BZV 10...14, BZX 90...94, 1N4565...4584
41033	BZV45(A..C)	6,2V, 1..5%, 0,25W	BZV 10...14, BZX 90...94, 1N4565...4584
41034	BZV46/C1V5	1,35..1,55V(5mA), 0,25W	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
41035	BZV46/C2V0	2..2,3V, 0,25W	BZ 102/2V1, BZX 75/C2V1, ZTE 2
41036	BZV47/C3V3...200	3,3..200V, 5%, 2W	BZD 23/..., BZT 03/..., ZY ...
41037	BZV48/C3V3...200	3,3..200V, 5%, 5W	BZV 40/..., 1N5333B...5388B
41038	BZV49/C0V8	0,73..0,83V, 1W(Tc25°)	-
41039	BZV53A...B	5,89..6,51V(7,5mA)	-

41040	BZV54A...B	6,08..6,72V(0,5mA)	-
41041	BZV55/..0V8..200	BZX 55/..., SMD	BZD 27/..., HZK..., RLZ 5221B...
41042	BZV58/3V3..200	3,3..200V, 5%, 1,43W	BZV 40/..., BZV 48/..., 1N5333B...5388B
41043	BZV60/C...	BZV 49/C..., 0,5W	BZW22/..., BZX55/..., ZPD..., 1N5221...67
41044	BZV80	BZV 53A, SMD	-
41045	BZV81	BZV 53B, SMD	-
41046	BZV85/C3V6...75	3,6..75V, 5%, 1W	BZW22/..., BZX61..., ZPY..., 1N4729...61A
41047	BZV86/1V4..3V2	1,4..3,2V(5mA), 0,33W	BZ 102/..., BZX 75/...
41048	BZV87/1V4..3V2	1,4..3,2V(5mA), 0,35W	-
41049	BZV90/C2V4..C75	BZV 49/C..., 1,3W	-
41050	BZW03/..7V5..270	7,5..270V, 5..10%, 1kW(0,1ms)	BZW07/..., BZW70/..., BZX70/..., BZY93/...
41051	BZW04/..B	BZW 04/..., bidirecional	BZW 06/...B, 1N6102...6137
41052	P)	5,5..376V, 5%, 400W(1ms)	BZW 06/..., 1N6102...6137
41053	BZW06/..B	BZW 06/..., bidirecional	-
41054	P)	5,8..376V, 5%, 600W(1ms)	BZW70/..., BZX70/..., BZY93/...
41055	BZW07/10...110	10..110V, 700W(1ms)	BZW 70/..., BZX 70/..., BZY 93/...
41056	BZW07/10B..110B	BZW 07/..., bidirecional	-
41057	BZW10/12...15	12..15V	-
41058	BZW100/20..24	20..24V, 1,8kW(15ms)	-
41059	BZW11/7V0...171	7,5..171V, 1kW(1ms)	1N5630...5663
41060	B	BZW 11/..., bidirecional	1N6036...6069, 1N6139...6172
41061	BZW12/11...390	11..390V, 420W(10ms)	-
41062	BZW13/11...390	11..390V, 1,2kW(10ms)	-
41063	BZW14	12V	-
41064	BZW20		-
41065	BZW22/C1	0,65..0,75V(5mA), 1,3W	ZPY 1, ZY 1
41066	0	2,7..200V, 5%, 1,3W	BZX61/..., BZX85/..., BZY97/..., 2N5913...56
41067	BZW25/12...120	12..120V, 2,5kW(1ms)	-
41068	BZW30/12...324	12..324V, 3kW(1ms)	-
41069	BZW50/8V2...180	8,2..180V, 5kW(1ms)	-
41070	B	BZW 50/..., bidirecional	-
41071	BZW70/5V6...62	5,6..62V, 700W(1ms)	BZX 70/..., BZY 93/...
41072	BZW86/7V5...62	7,5..62V, 13kW(1ms)	-
41073	R	BZW 86/..	-
41074	BZW91/5V6...62	5,6..62V, 9,5kW(1ms)	BZY 91/...
41075	R	BZW 91/..	BZY 91/...R
41076	BZW93/5V6...62	5,6..62V, 400W(1ms)	BZY 93/...
41077	R	BZW 93/..	BZY 93/...R
41078	BZW95/5V6...62	5,6..62V, 400W(1ms)	BZW 04/...
41079	BZW96/3V9...7V5	3,9..7,5V, 110W(1ms)	BZW 04/...
41080	BZX10	6,2V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5234...57
41081	BZX11	BZX 10, 6,8V	BZX 10
41082	BZX12	BZX 10, 7,5V	BZX 10
41083	BZX13	BZX 10, 8,2V	BZX 10
41084	BZX14	BZX 10, 9,1V	BZX 10

41085	BZX15	BZX 10, 10V	BZX 10
41086	BZX16	BZX 10, 11V	BZX 10
41087	BZX17	BZX 10, 12V	BZX 10
41088	BZX18	BZX 10, 13V	BZX 10
41089	BZX19	BZX 10, 15V	BZX 10
41090	BZX20	BZX 10, 16V	BZX 10
41091	BZX21	BZX 10, 18V	BZX 10
41092	BZX22	BZX 10, 20V	BZX 10
41093	BZX23	BZX 10, 22V	BZX 10
41094	BZX24	BZX 10, 24V	BZX 10
41095	BZX25	BZX 10, 27V	BZX 10
41096	BZX26	BZX 10, 30V	BZX 10
41097	BZX27	BZX 10, 33V	BZX 10
41098	BZX29/C3V3...100	3,3..100V, 5%, 1,5W	BZV47/..., BZY97/..., ZY..., 1N5913...49
41099	BZX30/C3V3...27	3,3..27V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5226...54
41100	BZX30/D3V3...27	BZX 30/C., 10%	BZX 30/C...
41101	1	3,6..9,1V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5227...39
41102	BZX32/C3V6...27	3,6..27V, 5%, 5W(Tc25°)	BZX 98/..., 1N2970...88
41103	BZX32/D3V6...27	BZX 32/C., 10%	BZX 32/C...
41104	BZX33	8,6V, 0,2W, +0,5mV/°C	1N3154...3157, 1N4775...4784
41105	BZX34	8,6V, 0,2W, +0,1mV/°C	1N3154...3157, 1N4775...4784
41106	BZX35	10V, 0,2W, +-1,5mV/°C	-
41107	BZX36	6,2V, 0,2W, -0,5..+1mV/°C	BZV 10...14, BZX 90...94, 1N4575...4584
41108	BZX43	6,7V, +-0,001%/°C	BZV 13, BZX 48, BZX 93, 1N4578, 1N4890
41109	BZX44	6,7V, +-0,002%/°C	BZV 12, BZX 49, BZX 92, 1N4577, 1N4582
41110	BZX45	6,7V, +-0,003%/°C	BZV 12, BZX 49, BZX 92, 1N4577, 1N4582
41111	BZX46/C2V7...200	2,7..200V, 5%, 0,5W	BZX55/..., BZX79/..., ZPD..., 1N5223...81
41112	BZX47	6,5V, 10mA, +-0,0005%/°C	BZV 14, BZX 94, 1N4574, 1N4579, 1N4584
41113	BZX48	6,5V, +-0,001%/°C	BZV 13, BZX 43, BZX 93, 1N4578, 1N4583
41114	BZX49	6,5V, +-0,002%/°C	BZV 12, BZX 44, BZX 92, 1N4577, 1N4582
41115	BZX50	6,5V, +-0,005%/°C	BZV 11, BZX 45, BZX 91, 1N4576, 1N4581
41116	BZX51	0,01%/°C	1N3154, 1N4775, 1N4780
41117	BZX52	0,005%/°C	1N3155, 1N4776, 1N4781
41118	BZX53	0,002%/°C	1N3156, 1N4777, 1N4782
41119	BZX54	0,001%/°C	1N3157, 1N4778, 1N4783
41120	0	BZX 55/C., 1%	BZX 55/C...
41121	BZX55/B2V4...200	BZX 55/C., 2%	BZX 55/C...
41122	BZX55/C0V8	0,73..0,83V(5mA), 0,5W	BZ 102/0V7, BZX 83/C0V8, ZPD 1
41123	BZX55/C2V4...200	2,4..200V, 5%, 0,5W	BZW 22/..., BZX79/..., ZPD..., 1N5221...81
41124	0	BZX 55/D., 10%	BZX 55/C...
41125	BZX57	7,5V, 5%, 0,25W	BZX55/C7V5, BZX79/C7V5, ZPD7,5, 1N5236
41126	BZX58/C6V8...10	6,8..10V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5235...40
41127	BZX59/C11...27	11..27V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5241...54
41128	BZX60/C30...56	30..56V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5256...63
41129	BZX61/C3V6...200	3,6..200V, 5%, 1,3W	BZW22/..., BZX85/..., ZPY..., 1N5914...56

41130	BZX62	0,65..0,75V(5mA), 0,25W	BA 220, BZ 102/0V8, BZX 55/0V8, ZPD 1
41131	BZX63/C6V8...10	6,8..10V, 5%, 0,25W	BZX 58/...
41132	BZX64/C11...27	11..27V, 5%, 0,25W	BZX 59/...
41133	BZX65/C30...56	30..56V, 5%, 0,25W	BZX 60/...
41134	BZX66	0,005..+0,08%/°C	BZV 14, BZX 43...45, BZX 47...50, 1N4895
41135	BZX67/C12...200	12..200V, 5%, 10,7W(Tc45°)	BZX 98/..., 1N2976...3015
41136	BZX68A	58..61V, 10,7W(Tc45°)	BZX 98/C62, 1N3000
41137	BZX68B	BZX 68A, 61..63V	BZX 98/C62, 1N3000
41138	BZX68C	BZX 68A, 63..66V	BZX 98/C62, 1N3000
41139	BZX69/C7V5...12	7,5..12V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5236...42
41140	BZX70/C7V5...75	7,5..75V, 5%, 2,5W	BZD 23/..., BZT 03/..., BZW 70/...
41141	BZX71/B5V1...24	5,1..24V, 2%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5231...52
41142	BZX71/C5V1...24	BZX 71/B..., 5%	BZX 71/B...
41143	BZX72(A...C)	9V(5mA), 5%, 0,0567W	1N938...936, 1N4768...66, 1N4773...71
41144	BZX74/C5V6...12	5,6..12V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5232...42
41145	6	1,4..3,6V(10mA), 5%, 0,4W	BZ 102/..., BZV 86/...
41146	BZX76	13V, 5%, 0,4W	BZX55/C13, BZX79/C13, ZPD13, 1N5243
41147	BZX79/B2V4...200	2,4..200V, 2%, 0,4W	BZX55/..., BZX85/..., ZPD..., 1N5221...81
41148	BZX79/C2V4...200	BZX 79/B..., 5%	BZX 79/B...
41149	BZX79/F2V4...200	BZX 79/B..., 3%	BZX 79/B...
41150	BZX80/C6V8...10	6,8..10V, 5%, 0,8W	BZX 58/...
41151	BZX81/C11...27	11..27V, 5%, 0,8W	BZX 59/...
41152	BZX82/C30...56	30..56V, 5%, 0,8W	BZX 60/...
41153	BZX83/C0V8	0,73..0,83V(5mA), 0,4A, 0,5W	BZW 22/C0V8, ZPY 1
41154	BZX83/C2V4...75	2,4..75V, 5%, 0,5W	BZX55/..., BZX79/..., ZPD..., 1N5221...67
41155	BZX84/A2V4...75	BZX 84/C..., 1%	-
41156	BZX84/B2V4...75	BZX 84/C..., 2%	-
41157	BZX84/C0V8	0,73..0,83V(5mA)	-
41158	BZX84/C2V4...75	2,4..75V, 5%	HZM ..., RD ...M
41159	BZX85/C2V7...200	2,7..200V, 5%, 1,3W	BZW22/..., BZX61/..., ZPY..., 1N5913...56
41160	BZX86-E36	35..45V	-
41161	BZX87/C4V7...75	4,7..75V, 5%, 1,3W	BZW22/..., BZX61/..., ZPY..., 1N5917...46
41162	BZX88/C2V7...47	2,7..47V, 5%	-
41163	BZX90	0,01%/°C	BZV 10, 1N4565, 1N4570, 1N4575, 1N4580
41164	BZX91	0,005%/°C	BZV 11, 1N4566, 1N4571, 1N4576, 1N4581
41165	BZX92	0,002%/°C	BZV 12, 1N4567, 1N4572, 1N4577, 1N4582
41166	BZX93	0,001%/°C	BZV 13, 1N4568, 1N4573, 1N4578, 1N4583
41167	BZX94	0,0005%/°C	BZV 14, 1N4569, 1N4574, 1N4579, 1N4584
41168	BZX95/C4V7...36	4,7..36V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5230...58
41169	BZX96/C2V4...33	2,4..33V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5221...57
41170	BZX97/C0V8	0,73..0,83V(5mA), 0,5W	BA 315, BZX 62, BZ 102/0V7, BZX 55/C0V8
41171	BZX97/C2V4...62	2,4..62V, 5%, 0,5W	BZX55/..., BZX79/..., ZPD..., 1N5221...65
41172	BZX98/C3V9...200	3,9..200V, 5%, 13W(Tc85°)	BZY 93/...
41173	BZY1	0,7..0,9V, 0,1A, 1,25W(Ta25°)	-
41174	BZY10	BZY 5, 10V	BZY 5



41175	BZY12	BZY 5, 12V	BZY 5
41176	BZY14	5,6V, 10%, 3,5W(Tc45°)	BZY 98/...
41177	BZY15	BZY 14, 6,8V	BZY 14
41178	BZY16	BZY 14, 8,2V	BZY 14
41179	BZY17	BZY 14, 10V	BZY 14
41180	BZY18	BZY 14, 12V	BZY 14
41181	BZY19	BZY 14, 15V	BZY 14
41182	BZY20	BZY 14, 18V	BZY 14
41183	BZY21	BZY 14, 22V	BZY 14
41184	BZY22	0,01%/°C	-
41185	BZY22	0,01%/°C	-
41186	BZY23	0,005%/°C	-
41187	BZY23	0,005%/°C	-
41188	BZY24	0,002%/°C	-
41189	BZY24	0,002%/°C	-
41190	BZY25	0,001%/°C	-
41191	BZY25	0,001%/°C	-
41192	BZY5	5,5V, 10%, 1,25W(Ta25°)	BZX 98/...
41193	BZY56	4,7V, 5%, 0,28W	BZX55/..., BZX79/..., ZPD..., 1N5230...
41194	BZY57	BZY 56, 5,1V	BZY 56
41195	BZY58	BZY 56, 5,6V	BZY 56
41196	BZY59	BZY 56, 6,2V	BZY 56
41197	BZY6	BZY 5, 6,5V	BZY 5
41198	BZY60	BZY 56, 6,8V	BZY 56
41199	BZY61	BZY 56, 7,5V	BZY 56
41200	BZY62	BZY 56, 8,2V	BZY 56
41201	BZY63	BZY 56, 9,1V	BZY 56
41202	BZY64	BZY 56, 4,3V, 15%	BZY 56
41203	BZY65	BZY 56, 5,1V, 15%	BZY 56
41204	BZY66	BZY 56, 6,2V, 15%	BZY 56
41205	BZY67	BZY 56, 7,5V, 15%	BZY 56
41206	BZY68	BZY 56, 9,1V, 15%	BZY 56
41207	BZY69	BZY 56, 12V, 15%	BZY 56
41208	BZY7	BZY 5, 7,5V	BZY 5
41209	BZY74	6,2V, 15%	BZX 98/C6V2
41210	BZY75	BZY 74, 7,5V	BZX 98/C7V5
41211	BZY76	BZY 74, 9,2V	BZX 98/C9V2
41212	BZY78(P)	5,3V, 5%, 0,28W	BZX55/C5V1, BZX79/C5V1, ZPD5,1, 1N5231
41213	BZY8	BZY 5, 8,5V	BZY 5
41214	V5	4,7..24,5V, 5%, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5230...53
41215	BZY83/D1	0,62..0,78V(5mA), 0,2A, 0,25W	BZ 102/0V8, BZX 55/C0V8, ZPD 1
41216	BZY83/D4V7...22	BZY 83/C., 10%	BZY 83/C...
41217	BZY84/D1	0,7..0,9V(100mA), 14W(Tc45°)	-
41218	BZY84/D5V6...12	5,6..12V, 10%, 14W(Tc45°)	BZX 98/...
41219	BZY85/B2V7...33	2,7..33V, 2%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5223...57

41220	BZY85/C2V7...33	BZY 85/B..., 5%	BZY 85/B...
41221	BZY85/D1	0,62..0,78V(5mA), 0,2A, 0,4W	BZ 102/0V7, BZX 55/C0V8, ZPD 1
41222	BZY85/D4V7...22	BZY 85/B..., 10%	BZY 85/B...
41223	BZY87/0V7...3V4	0,7..3,4V(5mA), 0,25W	BZ 102/...
41224	BZY88/C0V7	0,71..0,8V(5mA), 0,25A, 0,4W	BZ 102/0V7, BZX 55/C0V8, ZPD 1
41225	BZY88/C2V7...36	2,7..36V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5223...58
41226	BZY91/C7V5...75	7,5..75V, 5%, 75W(Tc65°)	BZW 91/...
41227	R	BZY 91/C..	BZW 91/...R
41228	BZY92/C3V9...36	3,9..36V, 5%, 1,1W	BZW22/..., BZX61/..., ZY..., 1N5915...38
41229	BZY93/C6V8...75	6,8..75V, 5%, 20W(Tc75°)	BZW 93/...
41230	R	BZY 93/C..	BZW 93/...R
41231	BZY94/C10...75	10..75V, 5%, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5240...67
41232	BZY95/C10...75	10..75V, 5%, 1,5W	BZW22/..., BZX61/..., ZY..., 2N5925...46
41233	BZY96/C4V7...10	4,7..10V, 5%, 1,5W	BZW22/..., BZX61/..., ZY..., 1N5917...25
41234	BZY97/C3V3...200	3,3..200V, 5%, 1,5W	BZW22/..., BZX61/..., ZY..., 1N5913...56
41235	BZZ10	6,15V, 10%, 0,28W	BZX55/..., BZX79/..., ZPD..., 1N5233...
41236	BZZ11	BZZ 10, 6,55V	BZZ 10
41237	BZZ12	BZZ 10, 7,25V	BZZ 10
41238	BZZ13	BZZ 10, 8,05V	BZZ 10
41239	BZZ14	5,6V, 5%, 10W(Tc50°)	BZX 98/C5V6
41240	BZZ15	BZZ 14, 6,2V	BZX 98/C6V2
41241	BZZ16	BZZ 14, 6,8V	BZX 98/C6V8
41242	BZZ17	BZZ 14, 7,5V	BZX 98/C7V5
41243	BZZ18	BZZ 14, 8,2V	BZX 98/C8V2
41244	BZZ19	BZZ 14, 9,1V	BZX 98/C9V1
41245	BZZ20	BZZ 14, 10V	BZX 98/C10
41246	BZZ21	BZZ 14, 11V	BZX 98/C11
41247	BZZ22	BZZ 14, 12V	BZX 98/C12
41248	BZZ23	BZZ 14, 13V	BZX 98/C13
41249	BZZ24	BZZ 14, 15V	BZX 98/C15
41250	BZZ25	BZZ 14, 16V	BZX 98/C16
41251	BZZ26	BZZ 14, 18V	BZX 98/C18
41252	BZZ27	BZZ 14, 20V	BZX 98/C20
41253	BZZ28	BZZ 14, 22V	BZX 98/C22
41254	BZZ29	BZZ 14, 24V	BZX 98/C24
41255	C	2SK649	2SK649
41256	C	HVR 17	HVR 17
41257	C	HVU 89	HVU 89
41258	C	MA 2S784	MA 784
41259	C	2SK1375	2SK1375
41260	C1	1SS352	1SS352
41261	C1	1SS368	1SS368
41262	C1	HSM 88(A)SR	HSM 88(A)SR
41263	C1	SST 111	SST 111
41264	C1	BFS 38A	BFS 38A

41265	C1	HSM 88(A)S	HSM 88(A)S
41266	C1(p)	BCW 29	BCW 29
41267	C10	BA 101	BA 101
41268	C106A	Igt/Ih<0,2/<3mA	TAG 106A, X 0403B, TAG 108A, C 108A
41269	C106B	C 106A, 200V	TAG 106B, X 0403B, TAG 108B, C 108B
41270	C106C	C 106A, 300V	TAG 106C, X 0403D, TAG 108C, C 108C
41271	C106D	C 106A, 400V	TAG 106D, X 0403D, TAG 108D, C 108D
41272	C106E	C 106A, 500V	TAG 106E, X 0403M, TAG 108E, C 108E
41273	C106F	C 106A, 50V	TAG 106F, X 0403B, TAG 108F, C 108F
41274	C106G	C 106A, 150V	TAG 106G, X 0403B, TAG 108G, C 108G
41275	C106M	C 106A, 600V	TAG 106M, X 0403M, TAG 108M, C 108M
41276	C106Q	C 106A, 15V	TAG 106Q, X 0403B, TAG 108Q, C 108Q
41277	C106Y	C 106A, 30V	TAG 106Y, X 0403B, TAG 108Y, C 108Y
41278	C107A	Igt/Ih<0,5/<3mA	TAG 107A, X 0403B, C 108A, TAG 108A
41279	C107B	C 107A, 200V	TAG 107B, X 0403B, C 108B, TAG 108B
41280	C107C	C 107A, 300V	TAG 107C, X 0403D, C 108C, TAG 108C
41281	C107D	C 107A, 400V	TAG 107D, X 0403D, C 108D, TAG 108D
41282	C107E	C 107A, 500V	TAG 107E, X 0403M, C 108E, TAG 108E
41283	C107F	C 107A, 50V	TAG 107F, X 0403B, C 108F, TAG 108F
41284	C107G	C 107A, 150V	TAG 107G, X 0403B, C 108G, TAG 108G
41285	C107M	C 107A, 600V	TAG 107M, X 0403M, C 108M, TAG 108M
41286	C107Q	C 107A, 15V	TAG 107Q, X 0403B, C 108Q, TAG 108Q
41287	C107Y	C 107A, 30V	TAG 107Y, X 0403B, C 108Y, TAG 108Y
41288	C108A	Igt/Ih<0,2/<3mA	TAG 108A, TIC 106A, TAG 623-100
41289	C108B	C 108A, 200V	TAG 108B, TIC 106B, TAG 623-200
41290	C108C	C 108A, 300V	TAG 108C, TIC 106C, TAG 623-300
41291	C108D	C 108A, 400V	TAG 108D, TIC 106D, TAG 623-400
41292	C108E	C 108A, 500V	TAG 108E, TIC 106E, TAG 623-500
41293	C108F	C 108A, 50V	TAG 108F, TIC 106F, TAG 623-100
41294	C108G	C 108A, 150V	TAG 108G, TIC 106B, TAG 623-200
41295	C108M	C 108A, 600V	TAG 108M, TIC 106M, TAG 623-600
41296	C108Q	C 108A, 15V	TAG 108Q, TIC 106Y, TAG 623-100
41297	C108Y	C 108A, 30V	TAG 108Y, TIC 106Y, TAG 623-100
41298	C116A	100V, 8A, Igt/Ih<25/<30mA	TAG625-100, C122A, TIC116A, CS6-02
41299	C116B	C 116A, 200V	TAG625-200, C 122B, TIC116B, CS6-02
41300	C116C	C 116A, 300V	TAG625-300, C 122C, TIC116C, CS6-04
41301	C116D	C 116A, 400V	TAG625-400, C 122D, TIC116D, CS6-04
41302	C116E	C 116A, 500V	TAG625-500, C 122E, TIC116E, CS6-06
41303	C116F	C 116A, 50V	TAG625-100, C 122F, TIC116F, CS6-02
41304	C116M	C 116A, 600V	TAG625-600, C 122M, TIC116M, CS6-06
41305	C118A	100V, 8A, Igt/Ih<0,2/<6mA	TAG628-100, S 4060A
41306	C118B	C 118A, 200V	TAG 628-200, S 4060B, MCR 72-4
41307	C118C	C 118A, 300V	TAG 628-300, S 4060C, MCR 72-5
41308	C118D	C 118A, 400V	TAG 628-400, S 4060D, MCR 72-6
41309	C118E	C 118A, 500V	TAG 628-500, S 4060E, MCR 72-7

41310	C118F	C 118A, 50V	TAG 628-100, S 4060F, MCR 72-2
41311	C118M	C 118A, 600V	TAG 628-600, S 4060M, MCR 72-8
41312	C122A	Igt/Ih<25/<30mA	TIC116A, BStC1026M, CS6-02, TAG660-100
41313	C122B	C 122A, 200V	TIC116B, BStC1026M, CS6-02, TAG660-200
41314	C122C	C 122A, 300V	TIC116C, BStC1026M, CS6-04, TAG660-400
41315	C122D	C 122A, 400V	TIC116D, BStC1026M, CS6-04, TAG660-400
41316	C122E	C 122A, 500V	TIC116E, BStC1033M, CS6-06, TAG660-500
41317	C122F	C 122A, 50V	TIC116F, BStC1026M, CS6-02, TAG660-100
41318	C122M	C 122A, 600V	TIC116M, BStC1040M, CS6-02, TAG660-600
41319	C1406(G)	100V, 3,2..4,8A	B40C3700/2200, etc
41320	C1406(G)	100V, 3,2..4,8A	B40C3700/2200, etc
41321	C15	2SA1612-C15	2SA1612
41322	C15	2SA811A-C15	2SA811A
41323	C15	BA 102	BA 102
41324	C16	2SA811A-C16	2SA811A
41325	C16	2SA1612-C16	2SA1612
41326	C17	2SA811A-C17	2SA811A
41327	C17	2SA1612-C17	2SA1612
41328	C18	2SA811A-C18	2SA811A
41329	C18	2SA1612-C18	2SA1612
41330	C1G	HN1C01F-GR	HN 1C01F
41331	C1G	HN1C01FU-GR	HN 1C01FU
41332	C1G	KSC 1632-G	KSC 1632
41333	C1L	KSC 1632-L	KSC 1632
41334	C1O	KSC 1632-O	KSC 1632
41335	C1Y	HN1C01F-Y	HN 1C01F
41336	C1Y	HN1C01FU-Y	HN 1C01FU
41337	C1Y	KSC 1632-Y	KSC 1632
41338	C2	BFQ 32C	BFQ 32C
41339	C2	HSC 276	HSC 276
41340	C2	SST 112	SST 112
41341	C2	HSM 276S	HSM 276S
41342	C2	BFS 38	BFS 38
41343	C2(p)	BCW 30	BCW 30
41344	C20	2SK595-20	2SK595
41345	C20	BA 102	BA 102
41346	C203A	Igt/Ih<0,2/<5mA	BRX 46...49, BRX 51...56, BRY55/...S
41347	C203B	C 203A, 200V	BRX 47...49, BRX 52...56, BRY55/...S
41348	C203C	C 203A, 300V	BRX 48...49, BRX 53...56, BRY55/...S
41349	C203D	C 203A, 400V	BRX 49, BRX 54...56, BRY55/...S
41350	C203Y	C 203A, 30V	BRX 44...49, BRX 50...56, BRY55/...S
41351	C203YY	C 203A, 60V	BRX 45...49, BRX 51...56, BRY55/...S
41352	C205A	100V, 1,2A, Igt/Ih<0,2/<5mA	BRX 61...66
41353	C205B	C 205A, 200V	BRX 62...66
41354	C205C	C 205A, 300V	BRX 63...66

41355	C205D	C 205A, 400V	BRX 64...66
41356	C205Y	C 205A, 30V	BRX 60...66
41357	C205YY	C 205A, 60V	BRX 61...66
41358	C21	2SK595-21	2SK595
41359	C22	2SK595-22	2SK595
41360	C228A	100V, 35A, Igt/Ih<40/<75mA	100
41361	C228A...U3	C228 A..U	-
41362	C228B	C 228A, 200V	200
41363	C228C	C 228A, 300V	300
41364	C228D	C 228A, 400V	400
41365	C228E	C 228A, 500V	2N3899, MCR3935-7, C35E, TAG35-500
41366	C228F	C 228A, 50V	2N3896...3899, MCR3935-2, C35F, TAG35-100
41367	C228M	C 228A, 600V	2N3899, MCR3935-8, C35M, TAG35-600
41368	C228U	C 228A, 25V	100
41369	C229A...U	C228 A..U	2N3870...3873, MCR3835..., MCR63...
41370	C23	2SK595-23	2SK595
41371	C230A	100V, 25A, Igt/Ih<25/<50mA	BStE4126N, BStE4126MN
41372	C230A...U3	C230 A..U	-
41373	C230B	C 230A, 200V	BStE4126N, BStE4126MN
41374	C230C	C 230A, 300V	BStE4126N, BStE4126MN
41375	C230D	C 230A, 400V	BStE4126N, BStE4126MN
41376	C230E	C 230A, 500V	BStE4133N, BStE4133MN
41377	C230F	C 230A, 50V	BStE4126N, BStE4126MN
41378	C230M	C 230A, 600V	BStE4140N, BStE4140MN
41379	C230U	C 230A, 25V	BStE4126N, BStE4126MN
41380	C231A...U	C230 A..U, Igt/Ih<9/<50mA	-
41381	C231A...U3	C230 A..U, Igt/Ih<9/<50mA	-
41382	C232A...U	C230 A..U	BStE40...N, BStE40...MN
41383	C233A...U	C231 A..U	-
41384	C24	2SK595-24	2SK595
41385	C25	2SA1247-C25	2SA1247
41386	C26	2SA1247-C26	2SA1247
41387	C27	2SA1247-C27	2SA1247
41388	C28	2SA1247-C28	2SA1247
41389	C3	KST 4126	KST 4126
41390	C3	1SS302	1SS302
41391	C3	KDS 226	KDS 226
41392	C3	MMBT 4126	MMBT 4126
41393	C3	1SS226	1SS226
41394	C3	BFS 39	BFS 39
41395	C3	SST 113	SST 113
41396	C3	1SS362	1SS362
41397	C3	HSM 88(S)R	HSM 88(S)R
41398	C3A	HN 1C03F-A	HN 1C03F
41399	C3B	HN 1C03F-B	HN 1C03F

41400	C3T	1PS226	1PS226
41401	C4	2SA811	2SA811
41402	C4	BCW 29R	BCW 29R
41403	C4	HSM 88WK	HSM 88WK
41404	C4	BFS 40A	BFS 40A
41405	C4	MC 804	MC 804
41406	C4160	BC 237	BC 237
41407	C5	CFY 25-17	CFY 25
41408	C5	2SA811-C5	2SA811
41409	C5	BCW 30R	BCW 30R
41410	C5	HSM 107S	HSM 107S
41411	C5	MMBA 811C5	MMBA 811
41412	C5	BFS 40	BFS 40
41413	C6	CFY 25-20	CFY 25
41414	C6	2SA811-C6	2SA811
41415	C6	BFS 41	BFS 41
41416	C6	MMBA 811C6	MMBA 811
41417	C6	HSM 198S	HSM 198S
41418	C7	CFY 25-23	CFY 25
41419	C7	HSM 88WA	HSM 88WA
41420	C7	2SA811-C7	2SA811
41421	C7	MMBA 811C7	MMBA 811
41422	C7(p)	BCF 29	BCF 29
41423	C71	BCW 61A	BCW 61A
41424	C72	BCW 61B	BCW 61B
41425	C73	BCW 61C	BCW 61C
41426	C74	BCW 61D	BCW 61D
41427	C77	BCF 29R	BCF 29R
41428	C8	MMBA 811C8	MMBA 811
41429	C8	HSM 198SR	HSM 198SR
41430	C8	2SA811-C8	2SA811
41431	C8(p)	BCF 30	BCF 30
41432	C9	BCF 30R	BCF 30R
41433	C9	HSM 276SR	HSM 276SR
41434	C9	1SS307	1SS307
41435	C91	BCV 62	BCV 62
41436	C92	BCV 62A	BCV 62A
41437	C93	BCV 62B	BCV 62B
41438	C94	BCV 62C	BCV 62C
41439	C95	BCV 64	BCV 64
41440	C96	BCV 64B	BCV 64B
41441	CA	BCP 68	BCP 68
41442	CA	XN 4314	XN 4314
41443	CA	XP 4314	XP 4314
41444	CA	μPA503T	æPA503T



41445	CA	BFS 18	BFS 18
41446	CA	BCW 61RA	BCW 61RA
41447	CA	SST 4391	SST 4391
41448	CA	BB 510	BB 510
41449	CA	BCX 68	BCX 68
41450	CA	2SC3645	2SC3645
41451	CA	2SD1368-CA	2SD1368
41452	CAC	BC 868	BC 868
41453	CB	μPA573T	æPA573T
41454	CB	XN 4315	XN 4315
41455	CB	XP 4315	XP 4315
41456	CB	BCW 61RB	BCW 61RB
41457	CB	BFS 19	BFS 19
41458	CB	SST 4392	SST 4392
41459	CB	2SC3646	2SC3646
41460	CB	2SD1368-CB	2SD1368
41461	CB	BCX 68-10	BCX 68-10
41462	CB	RXT 2222A	RXT 2222A
41463	CBC	BC 868-..	BC 868
41464	CBG	2SC3324-GR	2SC3324
41465	CBL	2SC3324-BL	2SC3324
41466	CBN	2SC4132-N	2SC4132
41467	CBP	2SC4132-P	2SC4132
41468	CBQ	2SC4132-Q	2SC4132
41469	CBR	2SC4132-R	2SC4132
41470	CC	SST 4393	SST 4393
41471	CC	2SA1122-C	2SA1122
41472	CC	BF 544	BF 544
41473	CC	BCW 61RC	BCW 61RC
41474	CC	2SA1364-C	2SA1364
41475	CC	2SC3647	2SC3647
41476	CC	2SD1368-CC	2SD1368
41477	CC	BCX 68-16	BCX 68
41478	CCA	2SC3326A	2SC3326A
41479	CCB	2SC3326B	2SC3326B
41480	CCC	BC 868-..	BC 868
41481	CD	P4 SMA-47	P4 SMA-47
41482	CD	2SA1366-D	2SA1366
41483	CD	2SA1122-D	2SA1122
41484	CD	BCW 61RD	BCW 61RD
41485	CD	BCX 68-25	BCX 68-25
41486	CD	RXT 3904	RXT 3904
41487	CD	2SC3648	2SC3648
41488	CD	2SA1364-D	2SA1364
41489	CD(s)	BSS 81B	BSS 81B

41490	CD0000	1N34	1N34
41491	CD0089	BA 100	BA 100
41492	CD0099	BA 100	BA 100
41493	CD0140	7,5V	BZW22/..., BZX61/..., ZYP..., 1N5236
41494	CD021	BA 127	BA 127
41495	CD15000C,D	BC 237	BC 237
41496	CD15000E	BF 254	BF 254
41497	CD5000D	BF 255	BF 255
41498	CD624	RGP 30	RGP 30 G...M
41499	CD9000	BC 307	BC 307
41500	CD951	BC 309	BC 309
41501	CDC	BC 868-..	BC 868
41502	CDD5000	AA 119	AA 119
41503	CDG00	BA 216	BA 216
41504	CDG20	1N4148	1N4148
41505	CDG21	AA 119	AA 119
41506	CDG22	AA 119	AA 119
41507	CDG23	BA 127	BA 127
41508	CDG24	BA 216	BA 216
41509	CDG25	BA 127	BA 127
41510	CDG26	BA 127	BA 127
41511	CDG27	BA 216	BA 216
41512	CDT1310	40V, 5A, 45W	AL 102, AUY 28, 2N1539...43, 2N1544...48
41513	CDT1310	40V, 5A, 45W	AL 102, AUY 28, 2N1539...43, 2N1544...48
41514	CDT1311	CDT 1310, 60V	AL 102, AUY 28, 2N1540...43, 2N1545...48
41515	CDT1311	CDT 1310, 60V	AL 102, AUY 28, 2N1540...43, 2N1545...48
41516	CDT1312	CDT 1310, 80V	AL 102, AUY 28, 2N1541...43, 2N1546...48
41517	CDT1312	CDT 1310, 80V	AL 102, AUY 28, 2N1541...43, 2N1546...48
41518	CDT1313	CDT 1310, 100V	AL 102, AUY 37, 2N1542...43, 2N1547...48
41519	CDT1313	CDT 1310, 100V	AL 102, AUY 37, 2N1542...43, 2N1547...48
41520	CDT1315	100V, 8A, 45W	AL 100, AUY 37, 2N2290, 2N2293
41521	CDT1315	100V, 8A, 45W	AL 100, AUY 37, 2N2290, 2N2293
41522	CDT1319	40V, 5A, 45W	AL 102, AUY 28, 2N1539...43, 2N1544...48
41523	CDT1319	40V, 5A, 45W	AL 102, AUY 28, 2N1539...43, 2N1544...48
41524	CDT1320	CDT 1319, 60V	AL 102, AUY 28, 2N1540...43, 2N1545...48
41525	CDT1320	CDT 1319, 60V	AL 102, AUY 28, 2N1540...43, 2N1545...48
41526	CDT1321	CDT 1319, 80V	AL 102, AUY 28, 2N1541...43, 2N1546...48
41527	CDT1321	CDT 1319, 80V	AL 102, AUY 28, 2N1541...43, 2N1546...48
41528	CDT1322	CDT 1319, 100V	AL 102, AUY 37, 2N1542...43, 2N1547...48
41529	CDT1322	CDT 1319, 100V	AL 102, AUY 37, 2N1542...43, 2N1547...48
41530	CDT1349(A)	2N2063..2064	2N2063...2064
41531	CDT1349(A)	2N2063..2064	2N2063...2064
41532	CDT1350(A)	2N2065..2066	2N2065...2066
41533	CDT1350(A)	2N2065..2066	2N2065...2066
41534	CE	BCP 69	BCP 69

41535	CE	P4 SMA-47A	P4 SMA-47A
41536	CE	2SA1366-E	2SA1366
41537	CE	2SA1122-E	2SA1122
41538	CE	2SC3649	2SC3649
41539	CE	BCX 69	BCX 69
41540	CE	2SA1364-E	2SA1364
41541	CE(s)	BSS 79B	BSS 79B
41542	CE1A3Q	Rb1k,Rbe10kOhm, 60V, +-2A	
41543	CE1F3P	CE 1A3Q, Rb2,2k, Rbe10kOhm	-
41544	CE1N2R	Rbe10kOhm	-
41545	CE2A3Q..N2R	CE 1A3Q..N2R	-
41546	CEC	BC 869	BC 869
41547	CEN	2SC4505-N	2SC4505
41548	CEO	2SC3325-O	2SC3325
41549	CEP	2SC4505-P	2SC4505
41550	CEQ	2SC4505-Q	2SC4505
41551	CEY	2SC3325-Y	2SC3325
41552	CF	P4 SMA-51	P4 SMA-51
41553	CF	2SA1366-F	2SA1366
41554	CF	2SC3650	2SC3650
41555	CF	BCX 69-10	BCX 69-10
41556	CF(s)	BSS 79C	BSS 79C
41557	CF1	CF 910	CF 910
41558	CF100	..2GHz, 10V, 80mA	-
41559	CF121	CF 100	-
41560	CF221	..2GHz, 10V, 80mA	-
41561	CF2386	25V, 0,5W, Idss<9mA, Up<-8V	BF 244...245, BFW 10, 2N3819, 2N4222
41562	CF3	CF 912	CF 912
41563	CF300	..2GHz, 10V, 80mA	-
41564	CF4	CF 922	CF 922
41565	CF400	..2GHz, 10V, 80mA	-
41566	CF5	CF 930	CF 930
41567	CF5R	CF 930R	CF 930R
41568	CF739	10V, 80mA	-
41569	CF750		
41570	CF910	CF 100, SMD	-
41571	CF912	CF 121, SMD	-
41572	CF922	CF 221, SMD	-
41573	CF930	CF 300, SMD	-
41574	CF940	CF 400, SMD	-
41575	CFK10	..2GHz, 10V, 50mA	-
41576	CFK12	CFK 10	-
41577	CFK22	CFK 10	-
41578	CFK30	..2GHz, 10V, 80mA	-
41579	CFK40	..2GHz, 10V, 80mA	-

41580	CFM13026	40V, Idss<50mA, Up<-7V	BF 348, BFT 10, 2N4091...4092
41581	CFQ	2SD2150-Q	2SD2150
41582	CFR	2SD2150-R	2SD2150
41583	CFS	2SD2150-S	2SD2150
41584	CFX13	12GHz, 5V, 100mA	-
41585	CFX14	CFX 13, 16GHz	-
41586	CFX21	11GHz, 8V, 110mA	-
41587	CFX30	11GHz, 15V, 130mA	-
41588	CFX31	11GHz, 15V, 250mA	-
41589	CFX32	8,5GHz, 15V, 500mA	-
41590	CFX33	8,5GHz, 15V, 600mA	-
41591	CFY10	6GHz, 5V, 100mA	-
41592	CFY11	6GHz, 5V, 100mA	-
41593	CFY12	6GHz, 5V, 100mA	-
41594	CFY13	6GHz, 5V, 100mA	-
41595	CFY14	6GHz, 5V, 100mA	-
41596	CFY15	6GHz, 5V, 100mA	-
41597	CFY16	12GHz, 5V, 100mA	-
41598	CFY17	6GHz, 5V, 100mA	-
41599	CFY18	6GHz, 5V, 100mA	-
41600	CFY19	6GHz, 5V, 100mA	-
41601	CFY20		-
41602	25)	5V, 80mA	-
41603	CFY35(-20,-23)	5V, 60mA	-
41604	CFY65(-12,-14)	4V, 70mA	-
41605	CFY66	3,5V, 60mA	-
41606	CFY75(-13,-15)	..20GHz, 5V, 70mA	-
41607	CFY76-08	3,5V, 60mA	-
41608	CG	P4 SMA-51A	P4 SMA-51A
41609	CG	BCX 71RG	BCX 71RG
41610	CG	2SA1587-GR	2SA1587
41611	CG	2SA1163-GR	2SA1163
41612	CG	2SC3651	2SC3651
41613	CG	BCX 69-16	BCX 69-16
41614	CG(s)	BSS 81C	BSS 81C
41615	CG1	1400V, 1,5A	BY 228, BY 448
41616	CG2	CG 1, 2A	BY 228, BY 448
41617	CG3	CG 1, 3A	BY 228
41618	CG61H	AA 133	AA 133
41619	CGC	BC 869-..	BC 869
41620	CGG	2SC3426-GR	2SC3426
41621	CGL	2SC3426-BL	2SC3426
41622	CGP	2SC5053-P	2SC5053
41623	CGQ	2SC5053-Q	2SC5053
41624	CGR	2SC5053-R	2SC5053

41625	CGY	2SC3426-Y	2SC3426
41626	CH	P4 SMA-56	P4 SMA-56
41627	CH	1SS351	1SS351
41628	CH	BCX 69-25	BCX 69
41629	CH	2SC4272	2SC4272
41630	CH	2SB1002-CH	2SB1002
41631	CH(s)	BSS 80B	BSS 80B
41632	CHC	BC 869-..	BC 869
41633	CHO	2SC4667-O	2SC4667
41634	CHO	2SC3437-O	2SC3437
41635	CHR	2SC3437-R	2SC3437
41636	CHR	2SC4667-R	2SC4667
41637	CHY	2SC4667-Y	2SC4667
41638	CHY	2SC3437-Y	2SC3437
41639	CI	2SD1777	2SD1777
41640	CI	2SC4080	2SC4080
41641	CJ	2SK1067	2SK1067
41642	CJ	2SK543	2SK543
41643	CJ	2SB1002-CJ	2SB1002
41644	CJ	2SC4390	2SC4390
41645	CJ(s)	BSS 80C	BSS 80C
41646	CK	XN 6114	XN 6114
41647	CK	XP 6114	XP 6114
41648	CK	P4 SMA-56A	P4 SMA-56A
41649	CK	BCX 71RK	BCX 71RK
41650	CK	2SD999-CK	2SD999
41651	CK	2SC4520	2SC4520
41652	CL	P4 SMA-62	P4 SMA-62
41653	CL	2SA1342	2SA1342
41654	CL	2SA1163-BL	2SA1163
41655	CL	2SA1677	2SA1677
41656	CL	2SA1587-BL	2SA1587
41657	CL	2SD999-CL	2SD999
41658	CL	2SC4521	2SC4521
41659	CL(s)	BSS 82B	BSS 82B
41660	CL055(A...D)	25V, 1A, 0,625W, 120MHz	BC 327...328, BC 636, BC 638, BC 640
41661	CL055..P	CL 055..., 0,75W	2SB968, 2SB1181...82, BD 506, BD 508
41662	CL066(A...D)	25V, 1A, 0,625W, 120MHz	BC 337...338, BC 635, BC 637, BC 639
41663	CL066..P	CL 066..., 0,75W	2SD1078, 2SD1295, BD 505, BD 507
41664	CL116P	BC 307	BC 307
41665	CL151-3(A..C)	-/10V, 0,1A, 0,1W	BC 122...123, BC 146
41666	CL151-4(A..C)	-/10V, 0,1A, 0,1W	BC 122...123, BC 146
41667	CL152-3(A..C)	-/10V, 0,1A, 0,1W	BC 200, BC 202...203
41668	CL152-4(A..C)	-/10V, 0,1A, 0,1W	BC 200, BC 202...203
41669	CL155(A...D)	30V, 1,5A, 0,625W, 120MHz	MPS 650...51, 2SC2236, 2SD1146, 2SD1207

41670	CL155..P	CL 155., 0,75W	2SB968, 2SD1181...82, BD 506, BD 508
41671	CL166(A...D)	30V, 1,5A, 0,625W, 120MHz	MPS 750...51, 2SA966, 2SA1315, 2SA1382
41672	CL166..P	CL 166..., 0,75W	2SD1078, 2SD1295, BD 505, BD 507
41673	CL168	-/7V, 3A, 0,625W, 120MHz	2SD879, 2SD1347, 2SD1507, 2SD1617
41674	CL169	-/9V, 3A, 0,625W, 100MHz	2SD879, 2SD1347, 2SD1507, 2SD1617
41675	CL266	-/60V, 2A, 0,625W	MPS 651, 2SC3328, 2SC3669, 2SC4145
41676	CL266P	CL 166..., 0,75W	2SD1079, 2SD1281...82, BD 519, BD 527
41677	CL855(A...C)	70V, 1A, 0,625W, 150MHz	BC 640, 2SB647, 2SA1013
41678	CL866(A...C)	70V, 1A, 0,625W, 150MHz	BC 639, 2SD667, 2N3700...3701
41679	CLY10	8V, 2A	-
41680	CLY5	8V, 1,2A	-
41681	CM	P4 SMA-62A	P4 SMA-62A
41682	CM	2SD999-CM	2SD999
41683	CM	2SC4504	2SC4504
41684	CM(s)	BSS 82C	BSS 82C
41685	CN	P4 SMA-68	P4 SMA-68
41686	CN	2SC4548	2SC4548
41687	CO	2SC5087-O	2SC5087
41688	CO	2SC4209-O	2SC4209
41689	CO	KTC4373-O	KTC 4373
41690	CO	2SC2881-O	2SC2881
41691	CP	2SC2411-CP	2SC2411
41692	CP	P4 SMA-68A	P4 SMA-68A
41693	CP	2SC2411K-P	2SC2411K
41694	CP	2SC4097-P	2SC4097
41695	CP	2SB767-P	2SB767
41696	CP	HC 1L2N	HC 1...
41697	CP8C..G	Igt/Ih<50/60mA	BTW48/..., CS23-..., MCR64-..., TAG35-...
41698	CP9C..G	CP 8 C..G	-
41699	CQ	2SB1582-Q	2SB1582
41700	CQ	2SC2411-CQ	2SC2411
41701	CQ	P4 SMA-75	P4 SMA-75
41702	CQ	2SB1219-Q	2SB1219
41703	CQ	2SC4097-Q	2SC4097
41704	CQ	2SC2411K-Q	2SC2411K
41705	CQ	2PB710Q	2PB710
41706	CQ	2SB710-Q	2SB710
41707	CQ	2PB1219Q	2PB1219
41708	CQ	2SB767-Q	2SB767
41709	CQ	HC 1A3M	HC 1...
41710	CR	2SC2411-CR	2SC2411
41711	CR	2SB1582-R	2SB1582
41712	CR	XP 6210	XP 6210
41713	CR	P4 SMA-75A	P4 SMA-75A
41714	CR	2SB710-R	2SB710



41715	CR	2SC2411K-R	2SC2411K
41716	CR	2PB710R	2PB710
41717	CR	2SB1219-R	2SB1219
41718	CR	2SC4097-R	2SC4097
41719	CR	2PB1219R	2PB1219
41720	CR	2SC4422	2SC4422
41721	CR	2SB767-R	2SB767
41722	CR	HC 1F3M	HC 1...
41723	CR02AM-...	BRX 49	BRX 49
41724	CR126	1400V, 1,5A	BY 228, BY 448, BY 350/1500
41725	CRT1544	60V, 25A, 90W	2N1651...1653, 2N2285...2287
41726	CRT1544	60V, 25A, 90W	2N1651...1653, 2N2285...2287
41727	CRT1545	80V, 25A, 90W	2N1652...1653, 2N2286...2287
41728	CRT1545	80V, 25A, 90W	2N1652...1653, 2N2286...2287
41729	CRT1552	40V, 25A, 90W	2N1651...1653, 2N2285...2287
41730	CRT1552	40V, 25A, 90W	2N1651...1653, 2N2285...2287
41731	CRT1553	100V, 25A, 90W	2N1652...1653, 2N2286...2287
41732	CRT1553	100V, 25A, 90W	2N1652...1653, 2N2286...2287
41733	CRT1592	80V, 35A	2N5693...5696
41734	CRT1592	80V, 35A	2N5693...5696
41735	CS	2SB1582-S	2SB1582
41736	CS	P4 SMA-82	P4 SMA-82
41737	CS	2PB1219S	2PB1219
41738	CS	2SA1682	2SA1682
41739	CS	2PB710S	2PB710
41740	CS	2SB710-S	2SB710
41741	CS	2SB1219-S	2SB1219
41742	CS	HC 1F3P	HC 1...
41743	CS	2SD1870	2SD1870
41744	CS	2SB767-S	2SB767
41745	CS0,6-02...-12	Igt<10mA	-
41746	CS0,8-02...-07	10/20mA	BStA30...M, TAG 632-..., TAG 621-...
41747	CS0014	BA 100	BA 100
41748	CS0080	BA 100	BA 100
41749	CS1,2-02...-07	15/25mA	BStC07..., TAG 630-..., TAG 620-...
41750	CS1-02...-12	15/40mA	BStD36...
41751	CS10-02...08	25/100mA	T 9,5N..., BStD10...M
41752	CS1312F,G	BF 450	BF 450
41753	CS1312H	BC 309	BC 309
41754	CS1312I	BC 307	BC 307
41755	CS15-02...08	25/100mA	-
41756	CS1506F,G	BC 307	BC 307
41757	CS1508E,G	BF 255	BF 255
41758	CS1509E,F	BF 254	BF 254
41759	CS1655	BF 494	BF 494

41760	CS1659	BC 338	BC 338
41761	CS1660	BC 328	BC 328
41762	CS1774	BC 548	BC 548
41763	CS1909	BC 337	BC 337
41764	CS1910	BC 327	BC 327
41765	CS1914(H)	BC 307	BC 307
41766	CS1978(A)	BC 337	BC 337
41767	CS2,5-04...06	15/25mA	TAG 620-..., BStC10..., TIC 116...
41768	CS3,5-02...07	gt/Ih<15/25mA	S 2800..., TAG 665-..., TIC 126...
41769	CS3-02...07	Igt/Ih<10/20mA	T 3,5N..., TAG 661-..., TAG 662-...
41770	CS6-02...08	Igt/Ih<15/25mA	S 2800..., TAG 665-..., TIC 126...
41771	CS6203H,I	BC 309	BC 309
41772	CS6208	BC 337	BC 337
41773	CS6209	BC 327	BC 327
41774	CS6305(A)	BC 307	BC 307
41775	CS9003	BC 547	BC 547
41776	CS9010	BC 547	BC 547
41777	CS9011(D...I)	SS 9011	SS 9011
41778	CS9012(D...I)	SS 9012	SS 9012
41779	CS9013(D...I)	SS 9013	SS 9013
41780	CS9014(A...C)	SS 9014	SS 9014
41781	CS9015(A...C)	SS 9015	SS 9015
41782	CS9016(D...H)	SS 9016	SS 9016
41783	CS9017	-/18V	BF 225, BF 255, BF 314, BF 495, BF 595
41784	CS9018(D...H)	SS 9018	SS 9018
41785	CS9020(G,H)	BF 450	BF 450
41786	CS9021	BF 495	BF 495
41787	CS9022	BC 547	BC 547
41788	CS9126	BC 548	BC 548
41789	CS9127	BC 558	BC 558
41790	CSF0,7-04	Igt/Ih<50/<200mA	BT153, TAG650S-400, TAG655S-400
41791	CSF02AM1	0,26A(Ta45°C),Igt/Ih<0,25/<2,3	BRX45...46, BRX 50...51, TAG60F, TAG62F
41792	CSF02AM10	CSF02AM1, 500V	BRX 55...56, BRY55S/500
41793	CSF02AM2	CSF02AM1, 100V	BRX46...47, BRX 50...51, TAG60A, TAG 62A
41794	CSF02AM4	CSF02AM1, 200V	BRX47...48, BRX 52...54, BRY55S/200
41795	CSF02AM8	CSF02AM1, 400V	BRX49, BRX 54...56, BRY55S/400
41796	CSF11-02...08	10A(Tc85°C),Igt/Ih<35/80mA	-
41797	CSF7,9-04...08	Igt/Ih<100/<100mA	-
41798	CSM2B2	200V, 2A(Tc71°), Igt/Ih1/1,5mA	C 107..., TAG 107..., C 106..., TAG 106...
41799	CSM2B4	CSM2B2, 400V	C 107..., TAG 107..., C 106..., TAG 106...
41800	CSM3B2	200V, 3A(Tc63°), Igt/Ih1/1,5mA	C 107..., TAG 107..., C 106..., TAG 106...
41801	CSM3B4	CSM3B2, 400V	C 107..., TAG 107..., C 106..., TAG 106...
41802	CSM5B2	Igt/Ih30/25mA	TAG 651-..., TAG 656-..., CS 2,5-...
41803	CSM5B4	CSM5B2, 400V	TAG 651-..., TAG 656-..., CS 2,5-...
41804	CT	P4 SMA-82A	P4 SMA-82A

41805	CT	2SD1935	2SD1935
41806	CT	HC 1L2Q	HC 1...
41807	CT	2SD1472	2SD1472
41808	CT005..06	50..600V, 2A	B...C2200
41809	CTG-G12	200V, 5A, 100ns	BY 229/200, BY 233/200, RGP 80D...M
41810	CTG-G12S	CTG-G12, 4A(104°)	BY 229/200, BY 233/200, RGP 80D...M
41811	CTP1104	40V, 3A, 40W	AD 149, AL 102, AUY 19...20, 2SB449
41812	CTP1104	40V, 3A, 40W	AD 149, AL 102, AUY 19...20, 2SB449
41813	CTP1108	2N2061	2N2061
41814	CTP1108	2N2061	2N2061
41815	CTP1109	2N2062	2N2062
41816	CTP1109	2N2062	2N2062
41817	CTP1111	80V, 3A, 45W	AL 102, AUY 20, 2N1541...43, 2N1546...48
41818	CTP1111	80V, 3A, 45W	AL 102, AUY 20, 2N1541...43, 2N1546...48
41819	CTP1500	100V, 15A, 50W(Tc45°)	AUY 37, 2N1552, 2N1556, 2N1560
41820	CTP1500	100V, 15A, 50W(Tc45°)	AUY 37, 2N1552, 2N1556, 2N1560
41821	CTP1503	CTP 1500, 80V	2N1551...52, 2N1555...56, 2N1559...60
41822	CTP1503	CTP 1500, 80V	2N1551...52, 2N1555...56, 2N1559...60
41823	CTP1504	CTP 1500, 60V	2N1550...52, 2N1554...56, 2N1558...60
41824	CTP1504	CTP 1500, 60V	2N1550...52, 2N1554...56, 2N1558...60
41825	CTP1508	40V, 15A, 50W(Tc45°)	2N1549...52, 2N1553...56, 2N1557...60
41826	CTP1508	40V, 15A, 50W(Tc45°)	2N1549...52, 2N1553...56, 2N1557...60
41827	CTP1544	60V, 25A, 50W(Tc45°)	2N1651...1653, 2N2285...2287
41828	CTP1544	60V, 25A, 50W(Tc45°)	2N1651...1653, 2N2285...2287
41829	CTP1545	CTP 1544, 80V	2N1652...1653, 2N2286...2287
41830	CTP1545	CTP 1544, 80V	2N1652...1653, 2N2286...2287
41831	CTP1552	40V, 25A, 50W(Tc45°)	2N1651...1653, 2N2285...2287
41832	CTP1552	40V, 25A, 50W(Tc45°)	2N1651...1653, 2N2285...2287
41833	CTP1553	CTP 1552, 100V	2N1652...1653, 2N2286...2287
41834	CTP1553	CTP 1552, 100V	2N1652...1653, 2N2286...2287
41835	CU	P4 SMA-91	P4 SMA-91
41836	CU	HC 1F2Q	HC 1...
41837	CV	XN 4404	XN 4404
41838	CV	P4 SMA-91A	P4 SMA-91A
41839	CV	1SV234	1SV234
41840	CV	1SV246	1SV246
41841	CW	XN 4381	XN 4381
41842	CW	P4 SMA-100	P4 SMA-100
41843	CW01B	1/5mA	MCR 1906-..., 2N1595...1599, TAG 2-...
41844	CW01C	CW01B, 200V	MCR 1906-..., 2N1595...1599, TAG 2-...
41845	CW12B	1/5mA	MCR 1906-..., 2N1595...1599, TAG 2-...
41846	CW12C	CW12C, 200V	MCR 1906-..., 2N1595...1599, TAG 2-...
41847	CX	3SK227	2SK227
41848	CX	3SK271	3SK271
41849	CX	P4 SMA-100A	P4 SMA-100A

41850	CX	HC 1A4A	HC 1...
41851	CX701	150/120V, 2A, 25W	BD 239D, 2SD578, 2SD608(A), 2SD1138
41852	CX701A	CX 701, 180/150V	BD 239E, 2SD578, 2SD608A, 2SD1138
41853	CX702	160/80V, 5A, 40W	BU 104P, BU 406...408, 2SD823
41854	CX702A	CX 702, 200/100V	BU 104P, BU 406...408, 2SD823
41855	CX703	160V, 0,1A, 0,625W, >50MHz	BFR 87...89, BFT 57...59, BF 257...259
41856	CX703A	CX 703, 200V	BFR 88...89, BFT 58...59, BF 258...259
41857	CX703B	CX 703, 250V	BFR 88, BFT 58, BF 259
41858	CX704(A...C)	60V, 4A, 30W, >3MHz	BD 243A, BD 535, BD 539A, BD 949
41859	CX705	55V, 7A, 75W, >0,5MHz	BD 245A, BD 311, BDV 91, 2N5873
41860	CX705	55V, 7A, 75W, >0,5MHz	BD 245A, BD 311, BDV 91, 2N5873
41861	CX705A	CX 705, 70V	BD 245A, BD 313, BDV 93, 2N5874
41862	CX705A	CX 705, 70V	BD 245A, BD 313, BDV 93, 2N5874
41863	CX754(A...C)	60V, 4A, 30W, >3MHz	BD 244A, BD 536, BD 540A, BD 950
41864	CX901		-
41865	CX904(B...E)	45V, 0,1A, 0,3W, 200MHz	BC 184, BC 413...414, BC 550
41866	CX906(A...D)	45V, 0,5A, 0,5W, 200MHz	BC 337, BC 635, BC 637, BC 639
41867	CX908(B...D)	45V, 1A, 0,625W, 150MHz	BC 337, BC 635, BC 635, BC 639
41868	CX917	330MHz	BF 240...241, BF 254, BF 494, BF 594
41869	CX918	620MHz	BF 198, BF 225, BF 310, BF 367, BF 596
41870	CX954(B...E)	45V, 0,1A, 0,3W, 200MHz	BC 214, BC 415...416, BC 560
41871	CX956(A...D)	45V, 0,5A, 0,5W, 200MHz	BC 327, BC 636, BC 638, BC 640
41872	CX958(B...D)	45V, 1A, 0,625W, 150MHz	BC 327, BC 636, BC 638, BC 640
41873	CY	2SC5087-Y	2SC5087
41874	CY	P4 SMA-110	P4 SMA-110
41875	CY	2SC4209-Y	2SC4209
41876	CY	2SC3396	2SC3396
41877	CY	2SC4397	2SC4397
41878	CY	BFS 18R	BFS 18R
41879	CY	KTC4373-Y	KTC 4373
41880	CY	2SJ186	2SJ186
41881	CY	2SC2881-Y	2SC2881
41882	CYQ	2SC4661-Q	2SC4661
41883	CYR	2SC4661-R	2SC4661
41884	CYS	2SC4661-S	2SC4661
41885	CZ	P4 SMA-110A	P4 SMA-110A
41886	CZ	BFS 19R	BFS 19R
41887	D	HVU 187	HVU 187
41888	D	2SA1687	2SA1687
41889	D01	SD 914	SD 914
41890	D1	SST 211	SST 211
41891	D1	BAW 63	BAW 63
41892	D1(p)	BCW 31	BCW 31
41893	D10N05	RFD 10N05	RFD 10N05
41894	D118	1N4148	1N4148

41895	D1201A	1N4002	1N4002
41896	D1201B	1N4003	1N4003
41897	D1201D	1N4004	1N4004
41898	D1201F	1N4001	1N4001
41899	D1201M	1N4005	1N4005
41900	D1201N	1N4006	1N4006
41901	D1201P	1N4007	1N4007
41902	D129	BA 127	BA 127
41903	D1300A...D	150..525V, 0,25A	BA 157...159, BA 199/..., BY 204/...
41904	D13H1	0,5A	-
41905	D13H2	D 13 H1	-
41906	D13K1	Iv70µA, Ip5µA	2N6027, 2N6116, 2N6119, MPU 131, MPU 231
41907	D13K2	Iv50µA, Ip2µA	2N6117, MPU 132, MPU 232
41908	D13K3	Iv50µA, Ip1µA	2N6118, MPU 133, MPU 233
41909	D13T1	Iv70µA, Ip5µA	2N6027, 2N6116, 2N6119, MPU 131, MPU 231
41910	D13T2	Iv25µA, Ip1µA	2N6028, 2N6120
41911	D147	BA 136	BA 136
41912	D14N05	RFD 14N05	RFD 14N05
41913	D15	2SC4180-D15	2SC4180
41914	D15	2SC1622A-D15	2SC1622A
41915	D16	2SC4180-D16	2SC4180
41916	D16	2SC1662A-D16	2SC1662A
41917	D16E7	25V, 0,2W, 135MHz	-
41918	D16E9	30V, 0,2W, 135MHz	-
41919	D16G6	>500MHz	BF 377...378, BF 763, 2N918, 2N2857
41920	D16K1...K4	580..650MHz	BF 225, BF 314, BF 496, BF 502...503
41921	D16N05	RFD 16N05	RFD 16N05
41922	D16P1...P4	18..20V, 0,2A, 0,32W, >60MHz	BC 517, BC 875, BC 877, BC 879, MPSA 25
41923	D17	2SC1662A-D17	2SC1662A
41924	D17	2SC4180-D17	2SC4180
41925	D18	2SC1662A-D18	2SC1662A
41926	D18	2SC4180-D18	2SC4180
41927	D1F10	100V, 1A	BYG 10D...M, U 1BC44...JC44
41928	D1F20	D 1 F10, 200V	BYG 10D...M, U 1DC44...JC44
41929	D1F40	D 1 F10, 400V	BYG 10G...M, U 1GC44...JC44
41930	D1F60	D 1 F10, 600V	BYG 10J...M, U 1JC44...JC44
41931	D1FL20	200V, 1,1A, <50ns	ER 2D...M, MURS 120
41932	D1FL20U	D 1FL20, <35ns	ER 2D...M, MURS 120
41933	D1FL40	D 1FL20, 400V, 0,8A	ER 2G...M, MURS 160
41934	D1FS4	40V, 1,1A	-
41935	D1FS4A	D1 FS4, 1,5A	-
41936	D1FS6	D1 FS4, 60V	-
41937	D1G	HN1A01FU-GR	HN 1A01FU
41938	D1G	HN 1A01F-GR	HN 1A01F
41939	D1G	KSA 812-G	KSA 812

41940	D1L	KSA 812-L	KSA 812
41941	D1O	KSA 812-O	KSA 812
41942	D1Y	HN 1A01F-Y	HN 1A01F
41943	D1Y	HN 1A01FU-Y	HN 1A01FU
41944	D1Y	KSA 812-Y	KSA 812
41945	D2	BAW 63A	BAW 63A
41946	D2(p)	BCW 32	BCW 32
41947	D21	2SK931-21	2SK931
41948	D2101(S)	600V, 1A, <700ns	BYX 55/600, MR 816...818, RGP 10J...M
41949	D2103S,SF	750V, 3A, <500ns	BY 399, RGP 30K...M, BY 229/800...1000
41950	D22	2SK931-22	2SK931
41951	D2201A...N	50..800V, 1A, <500ns	BY 218/..., BY 258/..., RGP 15A...M
41952	D228	BA 159	BA 159
41953	D23	2SK931-23	2SK931
41954	D232	BA 159	BA 159
41955	D24	2SK931-24	2SK931
41956	D2406A-R...M-R	D 2406A..M	BYX 50/...R
41957	D2406A...M	100..600V 6A, <350ns	BYX 50/...
41958	D2412A-R..M-R	D 2412A..M	BYT 61/...R, BYX 62/...R, BYV 24/...R
41959	D2412A...M	100..600V, 12A, <350ns	BYT 61/..., BYX 62/..., BYV 24/...
41960	D24A3391(A)	25V, 0,1A, 120MHz	BC 122...123
41961	D24A3392	25V, 0,1A, 140MHz	BC 122...123
41962	D24A3393	25V, 0,1A, 140MHz	BC 122...123
41963	D24A3394	25V, 0,1A, 140MHz	BC 122...123
41964	D24A3900(A)	18V, 0,1A, 160MHz	BC 122...123
41965	D25	2SK931-25	2SK931
41966	D25	2SC3115-D25	2SC3115
41967	D2520A-R...M-R	D 2520A..M	BYT 65/...R, BYX 63/...R, BYX 64/...R
41968	D2520A...M	100..600V, 20A, <350ns	BYT 65/..., BYX 63/..., BYX 64/...
41969	D2540A-R...M-R	D 2540A..M	871R...876R
41970	D2540A...M	100..600, 40A, <350ns	BYW 25/..., MR 861...866, MR 871...876
41971	D26	2SC3115-D26	2SC3115
41972	D2600EF,M	550..600V, 0,5A, <700ns	BY 407, BY 208/600, BY 201/6, RGP 10J
41973	D2601A...N	100..800V, 1A, <500ns	BY 258/..., BYV 12...16, RGP 15B...M
41974	D26B1...B2	40V, <12/18ns	-
41975	D26C1...C5	25V, 0,09W	BC 122...123
41976	D26E1...E7	18..45V, 0,09W	BC 123
41977	D26G1	>600MHz	-
41978	D26P1...P3	18..25V, 0,09W	-
41979	D27	2SC3115-D27	2SC3115
41980	D28	2SC3115-D28	2SC3115
41981	D28A5...A13	35..50V, 0,5A	BD 385, BD 415, BD 827, BD 841
41982	D28B	150V, 0,1A	BF 615, BF 617, BF 857...859
41983	D29A4...A12	35..60V, 0,5A, 0,33W	BC 327, BC 638, BC 640
41984	D29E1...E10(J1)	35..70V, 0,75A, 0,5W	BC 327, BC 638, BC 640



41985	D29F1...F7	40...60V, 0,1A, 0,36W, >90MHz	BC 212, BC 257, BC 307, BC 556
41986	D3	SST 213	SST 213
41987	D3	KDS 187	KDS 187
41988	D3	ISS 187	2SS 187
41989	D3	BAW 63B	BAW 63B
41990	D3(p)	BCW 33	BCW 33
41991	D30A1...A5	25V, 0,09W	BC 202...203
41992	D32	Ub28..36V, Ib<0,3mA, Itsm1A	A 9903
41993	D3202U	Ub25..40V, Ib<25μA, Itsm2A	1N5760, N 413L
41994	D3202Y	D 3202 U, Ub29..35V	1N5761, N 413M, BR 100, DO 201 YR
41995	D32H1...H9	60..100V, 0,5A, 0,5W	BC 639, 2N3700...3701, 2SD667
41996	D32K1...K2	30..50V, 0,75A, 0,5W	BC 337, BC 637, BC 639, 2N3700...3701
41997	D32L1...L6	25..40V, 0,5A, >80MHz	BC 517, BC 875, BC 877, BC 879, MPSA 25
41998	D32P1...P4		BF 240...241, BF 254, BF 494, BF 594
41999	D32S1...S10	30..60V, 0,1A, 0,4W	BC 174, BC 182, BC 190, BC 546
42000	D32W7...W14	>75MHz	2SC2240, 2SC2459, 2SC3245
42001	D335	AA 119	AA 119
42002	D336	1N4148	1N4148
42003	D33D1...D6	40..50V, 0,5A, 0,4W	BC 337, BC 637, BC 639, 2N3700...01
42004	D34C1...C6	25..40V, 0,5A, >80MHz	BC 516, BC 876, BC 878, BC 880, MPSA 75
42005	D34J1...J9	60..100V, 0,5A, 0,5W, >60MHz	BC 640, 2SA965, 2SB647
42006	D352	BA 282	BA 282
42007	D377	FDH 600	FDH 600
42008	D38H1...H9	60..100V, 0,5A, 0,5A, >80MHz	BC 637, BC 639, 2N3700...01, 2SD667
42009	D38L1...L6	25..40V, 0,5A, >80MHz	BC 517, BC 875, BC 877, BC 879, MPSA 25
42010	D38S1...S10	30..60V, 0,1A, 0,4W, 100MHz	BC 174, BC 182, BC 190, BC 546
42011	D38V1...V3	>50MHz	BF 298...299, BFR 88...89, BFT 58...59
42012	D38W7...W14	>75MHz	2SC2240, 2SC2459, 2SC3245
42013	D39C1...C6	25..40V, 0,5A, >80MHz	BC 516, BC 876, BC 878, BC 880, MPSA 75
42014	D39J1...J9	60..100V, 0,5A, 0,5W, >60MHz	BC 638, BC 640, 2SA965, 2SB647
42015	D4	BAW 63B	BAW 64
42016	D4	MMBD 4148SE	MMBD 4148SE
42017	D4	BCW 31R	BCW 31R
42018	D4	2SA1252-4	2SA1252
42019	D40C1...C8(U)	30..50V, 0,5A, 6,25W, 75MHz	MPSU 45
42020	D40D1...D14(U)	45..90V, 1A, 6,25W, 200MHz	BD 419, BD 519, BD 529
42021	D40E1...E7	45..90V, 2A, 8W, 230MHz	BD 525, BD 527, BD 529
42022	D40K1...K4	B>10k	MPSU 45
42023	D40N1...N5(U)	250..300V, 0,1A, 6,25W, 80MHz	BF 382, BF 461...462, MPSU 10, 2SC1758
42024	D40P1...P5(U)	>50MHz	BF 382, BF 461...462, MPSU 10
42025	D40V1...V6	300..400V, 0,1A, >50MHz	BF 462, BF 881
42026	D41D1...D14(U)	45..90V, 1A, 6,25W, 150MHz	BD 420, BD 520, BD 530
42027	D41E1...E7	40..90V, 2A, 8W, 175MHz	BD 526, BD 528, BD 530
42028	D41K1...K4	100MHz, B>10k	MPSU 95
42029	D42C1...C12(J,U)	40..90V, 3A, 12,5W, 50MHz	BDV 10...12

42030	D42D1...D6	50..90V, 4A, 12W, 50MHz	BD 679, BD 681, BD 779, 2N6039
42031	D42R1...R2	250..300V, 1A, 55MHz	BF 468, BF 668
42032	D42T1...T8	300..400V, 2A, 15W, 45MHz	BUV 93...95
42033	D43C1...C12(J,U)	40..90V, 3A, 12,5W, 40MHz	BD 242A...F, 2SA1293
42034	D43D1...D6	B10k	BD 680, BD 682, BD 780, 2N6036
42035	D44C1...C12	40..90V, 4A, 30W, 50MHz	BD 243(A...C), BD 539(A...C), BD 953
42036	D44D1...D6	B>2k	BDT 63(A...C), BDX 33(A...D)
42037	D44E1...E3	40..80V, 10A, 50W, B>1000	BDT 65(A...C), BDW 93(A...C)
42038	D44H1...H11	30..80V, 10A, 50W, 50MHz	BD 711, BD 809, 2SC2527
42039	D44Q1...Q5	200..300V, 4A, 31W, 50MHz	BU 406...409, MJE 51T...53T, TIP 75
42040	D44R1...R8	400..500V, 1A, 31W, 40MHz	BUW 40A...B, BUX 84...85, TIP 50
42041	D44T1...T8	300..400V, 2A, 45MHz	BUW 40(A...B), BUX 84...85, TIP 49...59
42042	D44TD3...TD5	400..600V, 2A, 50W	2SC3148
42043	D44TE3...TE5	400..600V, 4A, 75W	2SC3148
42044	D44TQ1..TQ2	650..750V, 12A, 100W	BUV 66(A)
42045	D44VH1...VH10	50..100V, 15A, 83W, 50MHz	-
42046	D44VM1..VM10	50..100V, 8A, 50W, 50MHz	-
42047	D45	BA 170	BA 170
42048	D45C1...C12	40..90V, 4A, 30W, 40MHz	BD 244(A...C), BD 540(A...C), BD 954
42049	D45D1...D6	B>2k	BDT 62(A...C), BDX 34(A...D)
42050	D45E1...E3	40..80V, 10A, 50W, B>1000	BDT 64(A...C), BDW 94(A...C)
42051	D45H1...H12	30..80V, 10A, 50W, 40MHz	BD 712, BD 810, 2SA1077
42052	D45VH1...VH10	40..100V, 15A, 83W, 50MHz	-
42053	D45VM1..VM10	50..100V, 8A, 50W, 50MHz	-
42054	D46TQ1..TQ2	650..750V, 12A, 110W	BUV 48(A...C), BUW 13(A), BUW 133(A)
42055	D47	BZX 84/C3V9	BZX 84
42056	D473	BA 127	BA 127
42057	D474	1N4148	1N4148
42058	D475	1N4148	1N4148
42059	D48	BZX 84/C4V3	BZX 84
42060	D49	BAY 84	BAY 84
42061	D5	2SA1252-5	2SA1252
42062	D5	MMBD 4148CC	MMBD 4148CC
42063	D5	BCW 32R	BCW 32R
42064	D5	SST 215	SST 215
42065	D5	2SC1622-D5	2SC1622
42066	D5	BAW 65	BAW 65
42067	D51	2SD780A-D51	2SD780A
42068	D52	SoBRY55/30	SoBRY55/30
42069	D52	2SD780A-D52	2SD780A
42070	D52	BY 133	BY 133
42071	D53	2SD780A-D53	2SD780A
42072	D53	BAY 85	BAY 85
42073	D54	2SD780A-D54	2SD780A
42074	D54	BZX 84/C3V3	BZX 84

42075	D54A7D	100/100V, 7A, 30W, B>2k	BD 647F, 2SD1415, 2SD1791, 2SD1830
42076	D54D6D	600/400V, 6A, 25W, B>600	2SD1409
42077	D54FY7D	80/80V, 7A, 30W, B>2000	BD 645F, 2SD1415, 2SD1791, 2SD1830
42078	D54H6D	300/250V, 6A, 25W, B>2000	2SD1410, 2SD2017
42079	D55	2SD780A-D55	2SD780A
42080	D55A7D	100/100V, 7A, 30W, B>2000	BD 647F, 2SD1415, 2SD1791, 2SD1830
42081	D55FY7D	80/80V, 7A, 30W, B>2000	BD 645F, 2SD1415, 2SD1791, 2SD1830
42082	D56W1...W2	1400V, 5A, 78W	BU 208(A), BU 508(A), 2SC2928, 2SD820
42083	D56W1...W2	1400V, 5A, 78W	BU 208(A), BU 508(A), 2SC2928, 2SD820
42084	D5E29	Iv>25mA, Ip<25μA	-
42085	D5E35	Iv>10mA	-
42086	D5E36	Iv>10mA	-
42087	D5E37	Iv>4mA, Ip<25μA	-
42088	D5E43	Iv>6mA, Ip<2μA	-
42089	D5E44	Iv>4mA, Ip<5μA	-
42090	D5E45	Iv>8mA, Ip<2μA	2N2647
42091	D5K1	Iv>1mA, Ip<5μA	2N6114
42092	D5K2	Iv>1mA, Ip<15μA	2N6115
42093	D6	BAW 66	BAW 66
42094	D6	2SA1252-6	2SA1252
42095	D6	2SC1622-D6	2SC1622
42096	D6	MMBD 4148CA	MMBD 4148CA
42097	D6	BCW 33R	BCW 33R
42098	D62	BAT 53	BAT 53
42099	D64	BZX 84/C3V6	BZX 84
42100	D64DS5..DS7	500..700V, 20A, 125W, B>100	BUT 15, MJ 10009, MJ 10024...25
42101	D64DS5..DS7	500..700V, 20A, 125W, B>100	BUT 15, MJ 10009, MJ 10024...25
42102	D64DV5..DV7	500..700V, 50A, 185W, B>100	BUT 34, MJ 10016
42103	D64DV5..DV7	500..700V, 50A, 185W, B>100	BUT 34, MJ 10016
42104	D64ES5..ES7	D64DS	-
42105	D64ES5..ES7	D64DS	-
42106	D64EV5..EV7	D64DV	-
42107	D64EV5..EV7	D64DV	-
42108	D64TS3..TS5	195W	-
42109	D64TS3..TS5	195W	-
42110	D64VS3..VS5	450..550V, 15A, 195W	BUS 13(A), BUS 23(A...B), BUW 45...46
42111	D64VS3..VS5	450..550V, 15A, 195W	BUS 13(A), BUS 23(A...B), BUW 45...46
42112	D65	SoBRY55/30R	SoBRY55/30R
42113	D66	SoBRY55/60	SoBRY55/60
42114	D66DS5..DS7	D64DS5..7, , 62,5W	-
42115	D66DV5..DV7	D64DV5..7, , 125W	-
42116	D66DW1..DW3	800..900V, 50A, 167W	-
42117	D66ES5..ES7	D64ES5..7, , 62,5W	-
42118	D66EV5..EV7	D64EV5..7, , 125W	-
42119	D66EW1..EW3	D66DW1..3	-

42120	D66GV5..GV7	600..700V, 50A, 125W	-
42121	D67	SoBRY55/60R	SoBRY55/60R
42122	D7	BAW 67	BAW 67
42123	D7	2SA1252-7	2SA1252
42124	D7	2SC1662-D7	2SC1662
42125	D7(p)	BCF 32	BCF 32
42126	D70F2T1	50V, 2A, 100/1100ns	2SD1623, 2SC4409
42127	D70G.05T1	200/150V, 0,05A	BF 622, 2SC2880, 2SC4372, 2SC4080
42128	D70Y.8T1	35V, 0,8A	BCX 54...56, 2SC3444, 2SC4539, 2SD1623
42129	D70Y1.5T1	30V, 1,5A	2SC3439, 2SC4377, 2SD1766
42130	D71	BCW 60A	BCW 60A
42131	D71F2T1	50V, 2A, 100/1100ns	2SA1681, 2SB1123
42132	D71G.05T1	150/150V, 0,05A	BF 623, 2SA1200, 2SA1660, 2SB1046...47
42133	D71Y.8T1	35V, 0,8A	BCX 51...53, 2SA1364, 2SB1122, 2SB1260
42134	D71Y1.5T1	30V, 1,5A	2SA1213, 2SA1681, 2SB1313, 2SB1123
42135	D72	BCW 60B	BCW 60B
42136	D72F5T1..2	60V, 5A, 20W	2SC3074, 2SD1803
42137	D72FY4D1..2	100/80V, 4A, 15W, B>2000	2SC4345, 2SD1223, 2SD1520
42138	D72K3D1..2	60/40V, 3A, 15W, B>2000	2SD1222...23, 2SD1520, 2SD1817
42139	D72Y1.5D1..2	30V, 1,5A, 10W, B>4000	2SD1759, 2SD1980
42140	D73	BA 579A	BA 579A
42141	D73	BCW 60C	BCW 60C
42142	D73F5T1..2	60/50V, 5A, 20W	2SA1244, 2SB1203...04
42143	D73FY4D1..2	100/80V, 4A, 15W, B>2000	2SB908, 2SB1072
42144	D73K3D1..2	60/40V, 3A, 15W, B>2000	2SB907, 2SB1214, 2SB1303
42145	D74	BA 579C	BA 579C
42146	D74	BCW 60D	BCW 60D
42147	D75	BA 579S	BA 579S
42148	D76	BAR 18	BAR 18
42149	D764A	BAV 45	BAV 45
42150	D77	BCF 32R	BCF 32R
42151	D78	1N4148	1N4148
42152	D797	1N4148	1N4148
42153	D8	BAW 68	BAW 68
42154	D8	BCF 33	BCF 33
42155	D8	2SC1662-D8	2SC1662
42156	D81	BAR 43A	BAR 43A
42157	D81	BCF 33R	BCF 33R
42158	D82	BAR 43C	BAR 43C
42159	D83	BB 503DK	BB 503DK
42160	D837(A)	1N4148	1N4148
42161	D838	BA 159	BA 159
42162	D84	BAT 18DK	BAT 18DK
42163	D85	BAT 17DS	BAT 17DS
42164	D91	BCV 61	BCV 61

42165	D92	BCV 61A	BCV 61
42166	D93	BCV 61B	BCV 61
42167	D94	BCV 61C	BCV 61
42168	D94	BAR 42	BAR 42
42169	D95	BCV 63	BCV 63
42170	D95	BAR 43	BAR 43
42171	D96	BCV 63B	BCV 63
42172	D96	BAS 70-04	BAS 70-04
42173	D97	BAS 70-05	BAS 70-05
42174	D98	BAS 70-06	BAS 70-06
42175	DA	BF 722	BF 722
42176	DA	$\mu$ PA502T	$\mu$ PA502T
42177	DA	2SD1664	2SD1664
42178	DA	2SD1618	2SD1618
42179	DA	BF 622	BF 622
42180	DA	2SD1418-DA	2SD1418
42181	DA(s)	BCW 67A	BCW 67A
42182	DA2	SD BAX 12	SD BAX 12
42183	DA3	Ub28..36V, Ib<0,3mA, Itsm1A	A 9903, D 32
42184	DA4	Ub35..45V, Ib<0,15mA, Itsm2A	1N5762, N 413N, D 3202U
42185	DA5	BAR 43S	BAR 43S
42186	DA6	BZV 53A	BZV 53A
42187	DA7	BZV 53B	BZV 53B
42188	DA8	BZV 54A	BZV 54A
42189	DA9	BZV 54B	BZV 54B
42190	DB	BF 723	BF 723
42191	DB	$\mu$ PA572T	$\mu$ PA572T
42192	DB	2SD1619	2SD1619
42193	DB	2SD1766	2SD1766
42194	DB	BF 623	BF 623
42195	DB	2SD1418-DB	2SD1418
42196	DB(s)	BCW 67B	BCW 67B
42197	DB1	BAR 43A	BAR 43A
42198	DB2	BAR 43B	BAR 43B
42199	DB3	Ub28..36V, Ib<0,3mA	-
42200	DB3-1-35	Ub28..36V, Ib<0,05mA	-
42201	DB3TG	Ub30..34V, Ib<15 $\mu$ A	-
42202	DB4	DB 3, Ub35..45V	-
42203	DB6	BAY 85S	BAY 85S
42204	DB6	DB 3, Ub56..70V	-
42205	DBC146-4(A...C)	BC 146	BC 146
42206	DBC201	BC 201	BC 201
42207	DBC202	BC 202	BC 202
42208	DBC203	BC 203	BC 203
42209	DBP	2SD1766-P	2SD1766

42210	DBQ	2SD1766-Q	2SD1766
42211	DBR	2SD1766-R	2SD1766
42212	DC	BF 720	BF 720
42213	DC	2SD1418-DC	2SD1418
42214	DC	2SD1620	2SD1620
42215	DC	2SC3444-C	2SC3444
42216	DC	BFN 20	BFN 20
42217	DC	BF 620	BF 620
42218	DC	2SD1767	2SD1767
42219	DC(s)	BCW 67C	BCW 67C
42220	DC34	Ub30..38V, Ib<50μA	-
42221	DC38	Ub34..42V, Ib<50μA	-
42222	DC42	Ub39..45V, Ib<50μA	-
42223	DCP	2SD1767-P	2SD1767
42224	DCQ	2SD1767-Q	2SD1767
42225	DCR	2SD1767-R	2SD1767
42226	DD	P4 SMA-120	P4 SMA-120
42227	DD	2SC4933-D	2SC4933
42228	DD	2SC2463-D	2SC2463
42229	DD	2SC3441-D	2SC3441
42230	DD	2SD1419-DD	2SD1419
42231	DD	2SD1621	2SD1621
42232	DD	SM 6T 6V8	SM 6T...
42233	DD	2SC3444-D	2SC3444
42234	DD	BFN 16	BFN 16
42235	DD1000	DD 300, 10kV	-
42236	DD1200	DD 300, 12kV	-
42237	DD1300	DD 300, 13kV	-
42238	DD1600	DD 300, 16kV	-
42239	DD1800	DD 300, 18kV	-
42240	DD300	3kV, 20mA, <55ns	-
42241	DD600	DD 300, 6kV	-
42242	DE	P4 SMA-120A	P4 SMA-120A
42243	DE	2SC3441-E	2SC3441
42244	DE	2SC2463-E	2SC2463
42245	DE	2SA1037KLN-E	2SA1037KLN
42246	DE	2SC4933-E	2SC4933
42247	DE	2SC3444-E	2SC3444
42248	DE	SM 6T 6V8A	SM 6T...
42249	DE	2SD1622	2SD1622
42250	DE	2SD1834	2SD1834
42251	DE	2SD1419-DE	2SD1419
42252	DE	BFN 18	BFN 18
42253	DE3L20U	200V, 3A(Tc113°), <35ns	-
42254	DE3L40	400V, 3A(Tc99°), <50ns	-



42255	DE3S4M	40V, 3A(Tc98°)	-
42256	DE3S6M	DE 3S4M, 60V	-
42257	DE5LC20U	200V, 5A(Tc81°), <35ns	-
42258	DE5LC40	400V, 3A(Tc61°), <50ns	-
42259	DE5PC3M	30V, 5A	-
42260	DE5S4M	40V, 5A(Tc82°)	-
42261	DE5S6M	60V, 5A(Tc74°)	-
42262	DE5SC3ML	30V, 5A(Tc92°)	-
42263	DE5SC4M	40V, 5A(Tc80°)	-
42264	DE5SC6M	60V, 5A(Tc69°)	-
42265	DF	BF 721	BF 721
42266	DF	P4 SMA-130	P4 SMA-130
42267	DF	2SC2463-F	2SC2463
42268	DF	2SC3441-F	2SC3441
42269	DF	2SC4933-F	2SC4933
42270	DF	SM 6T 7V5	SM 6T...
42271	DF	2SD1623	2SD1623
42272	DF	BF 621	BF 621
42273	DF	BFN 21	BFN 21
42274	DF(s)	BCW 68F	BCW 68F
42275	DF01		
42276	DFA007	AA 143	AA 143
42277	DFA08C..E	200..400V, 0,8A, <300ns	BYG 20D...M
42278	DFB03R,T,W	1500..2000V, 0,3A, <1µs	BY 203/..., BYD 43-20
42279	DFB20(T)B..L	100..1000V, 2A, <150..300ns	BYM 26A...E, BYM 36A...E, BYT 56G...M
42280	DFC03G..W	600..2000V, 0,3A, <2..2,5µs	BA 157...159, BY 203/..., BYD 43-20
42281	DFC05J..R	800..1500V, 0,5A, <1µs	DM513, DM516, EM513, EM516, GP 10Q...Y
42282	DFC15(T)B..R	100..1500V, 1,5A, <150..300ns	BYV 12...16, BYV 36A...E, RGP 15-10...-20
42283	DFD05(T)B..T	100..1700V, 0,5A, <150..300ns	BYT 11/..., BYT 52B...M, RGP 15-10...-20
42284	DFD30(T)B..L	100..1000V, 3A, <150..300ns	BYM 36A...E, BYT 56G...M
42285	DFH10(T)B..R	100..1500V, 1A, <150..300ns	BYT 11/..., BYT 52B...E, RGP 15-10...-20
42286	DG	P4 SMA-130A	P4 SMA-130A
42287	DG	2SC2713-GR	2SC2713
42288	DG	2SC4117-GR	2SC4117
42289	DG	2SD1624	2SD1624
42290	DG	RXTA-14	RXTA-14
42291	DG	BFN 17	BFN 17
42292	DG	SM 6T 7V5A	SM 6T...
42293	DG(s)	BCW 68G	BCW 68G
42294	DG1	CG 1	CG 1
42295	DG13	120V, 3A	AY 102, AY 106
42296	DG130	120V, 3A	AY 102, AY 106
42297	DG14	DG 13, 250V	AY 102
42298	DG140	DG 130, 250V	AY 102
42299	DG2	CG 2	CG 2

42300	DG3	CG 3	CG 3
42301	DGQ	2SD1963-Q	2SD1963
42302	DGR	2SD1963-R	2SD1963
42303	DGS	2SD1963-S	2SD1963
42304	DH	P4 SMA-150	P4 SMA-150
42305	DH	RXTA-28	RXTA-28
42306	DH	BFN 19	BFN 19
42307	DH	2SB1025-DH	2SB1025
42308	DH	2SD1625	2SD1625
42309	DH(s)	BCW 68H	BCW 68H
42310	DI	2SD1626	2SD1626
42311	DI-	2SC3867	2SC3867
42312	DJ	2SB1025-DJ	2SB1025
42313	DJ	2SD1627	2SD1627
42314	DJ4	3SK180-4	3SK180
42315	DJ5	3SK180-5	3SK180
42316	DJ6	3SK180-6	3SK180
42317	DJQ	2SD2098-Q	2SD2098
42318	DJR	2SD2098-R	2SD2098
42319	DJS	2SD2098-S	2SD2098
42320	DK	2SB1025-DK	2SB1025
42321	DK	2SD1628	2SD1628
42322	DK	2SB798-DK	2SB798
42323	DK(s)	BCX 42	BCX 42
42324	DKP	2SC4672-P	2SC4672
42325	DKQ	2SC4672-Q	2SC4672
42326	DKS21	B>2000	BC 517, BC 617, BC 875, MPSA 25...29
42327	DKS22	DKS 21, B>10000	BC 517, BC 617, MPSA 25...29
42328	DKS23	B>2000	BC 516, BC 876, MPSA 63...64, MPSA 75...77
42329	DKS24	DKS 23, B>1000	BC 516, MPSA 63...64, MPSA 75...77
42330	DL	P4 SMA-150A	P4 SMA-150A
42331	DL	2SC4117-BL	2SC4117
42332	DL	2SA1343	2SA1343
42333	DL	2SC2713-BL	2SC2713
42334	DL	2SB798-DL	2SB798
42335	DL	2SD2099	2SD2099
42336	DL	2SB1026-DL	2SB1025
42337	DLN	2SD2167-N	2SD2167
42338	DLP	2SD2167-P	2SD2167
42339	DLQ	2SD2167-Q	2SD2167
42340	DM	P4 SMA-160	P4 SMA-160
42341	DM	2SD2170	2SD2170
42342	DM	2SD1998	2SD1998
42343	DM	2SB798-DM	2SB798
42344	DM	2SB1026-DM	2SB1025

42345	DM513	1600V, 1A	BY 228, EM 516, GP 10Y
42346	DM516	DM 513, 1800V	RGP 15-18...-20
42347	DN	P4 SMA-160A	P4 SMA-160A
42348	DN	SM 6T 10	SM 6T...
42349	DN	2SD1999	2SD1999
42350	DNE	2SD2153-E	2SD2153
42351	DNU	2SD2153-U	2SD2153
42352	DNV	2SD2153-V	2SD2153
42353	DNW	2SD2153-W	2SD2153
42354	DO	2SC5092-O	2SC5092
42355	DO	2SA1620-O	2SA1620
42356	DO	KTA1661-O	KTA 1661
42357	DO	2SA1201-O	2SA1201
42358	DO	2SD1997	2SD1997
42359	DO201YR	Ub26..32V, Ib<50µA, Itsm2A	1N5761, N 413M, BR 100, D 3202Y
42360	DP	P4 SMA-170	P4 SMA-170
42361	DP	2SB789-P	2SB789
42362	DP	HQ 1L2N	HQ 1...
42363	DP	2SD2195	2SD2195
42364	DP	2SD2100	2SD2100
42365	DP	SM 6T 10A	SM 6T...
42366	DQ	P4 SMA-170A	P4 SMA-170A
42367	DQ	2PB1219AQ	2PB1219A
42368	DQ	2SB1219A-Q	2SB1219A
42369	DQ	2PB710AQ	2PB710A
42370	DQ	2SB710A-Q	2SB710A
42371	DQ	2SB789-Q	2SB789
42372	DQ	2SD2176	2SD2176
42373	DQ	HQ 1A3M	HQ 1...
42374	DQN	2SD2211-N	2SD2211
42375	DQP	2SD2211-P	2SD2211
42376	DQQ	2SD2211-Q	2SD2211
42377	DR	2SC5092-R	2SC5092
42378	DR	P4 SMA-180	P4 SMA-180
42379	DR	2PB710AR	2PB710A
42380	DR	2SA1037KLN-R	2SA1037KLN
42381	DR	2SB1219A-R	2SB1219A
42382	DR	2PB1219AR	2PB1219A
42383	DR	2SB710A-R	2SB710A
42384	DR	2SD2212	2SD2212
42385	DR	2SC4643	2SC4643
42386	DR	2SB789-R	2SB789
42387	DR	HQ 1F3M	HQ 1...
42388	DRA01B..E	Igt/Ih<0,2/3mA	BRX51...56, BRY55/..., MCR100-..., TAG06-...
42389	DRA03TB..TG	Igt/Ih<0,2/4mA	BRX51...56, BRY55/..., MCR100-..., TAG06-...

42390	DRA2TB..TG	Igt/Ih<0,2/3mA	C 106-..., TAG 106-...
42391	DRA3B..G	100..600V, 3A(Tc87°)	C 108-..., TAG 108-...
42392	DRA5B..G	Igt/Ih<40/<60mA	MCR 218-..., TAG 625-..., TIC 116-...
42393	DRA8B..G	Igt/Ih<40/<60mA	TAG 680-..., TIC 122-..., TIC 126-...
42394	DRB2B..E	2A(Tc35°),Igt/Ih<1,5/12mA	S 3060...
42395	DRB3B..E	100..400V, 3A(Tc87°)	CSF 0,7..., S5800...5802...
42396	DRC2E	Igt/Ih<50/<120mA	-
42397	DRC3E	Igt/Ih<50/<120mA	BStC10..., TAG 620-...
42398	DRD3B..G	100..600V, 3A, Igt/Ih<15/60mA	TAG 620-...
42399	DRE3B..G	Igt/Ih<0,2/4mA	C 108-..., TAG 108-...
42400	DS	P4 SMA-180A	P4 SMA-180A
42401	DS	2PB1219AS	2PB1219A
42402	DS	2SB710A-S	2SB710A
42403	DS	BCX 42R	BCX 42R
42404	DS	2SB1219A-S	2SB1219A
42405	DS	2SA1037KLN-S	2SA1037KLN
42406	DS	2SA1728	2SA1728
42407	DS	2PB710AS	2PB710A
42408	DS	2SB789-S	2SB789
42409	DS	2SD1946	2SD1946
42410	DS	HQ 1F3P	HQ 1...
42411	DS0,9-04A..16A	400..1600V, 1,2A	BY 226...228, BY 252...255, BY 350/...
42412	DS1,2-04A..16A	400..1600V, 1,7A	BY 228, BY 252...255, BY 448, GP 20G...M
42413	DS1,8-04A..16A	400..1600V, 1,7A	BY 228, BY 252...255, BY 448, GP 20G...M
42414	DS10-01B..05B	100..500V, 12A	BYW 88/...R, BYX 99/...R, SSi E20...
42415	DS113A...C	1000..1500V, 1,5A	BY 228, BY 448
42416	DS118A...E	200..1000V, 1,5A	BY 226...227, BY 251...255, GP 20B...M
42417	DS130A...E	100..800V, 1A	BY 126...127, BY 133...135, 1N4002...07
42418	DS130NA...NE	DS 130A..E	DS 130A...E
42419	DS130TA...TE	DS 130A..E	DS 130A...E
42420	DS130YA...YE	DS 130A..E	DS 130A...E
42421	DS131A,B	100..200V, 2x0,9A	2xBY251...255, 2xBY259/..., 2xGP20B...M
42422	DS132A,B	DS 131A,B	DS 131A,B
42423	DS133A,B	DS 131A,B	DS 131A,B
42424	DS135C...F	50..400V, 1A	BY 126...127, BY 133...135, 1N4001...07
42425	DS13A,B	300..500V, 1,5A	BY 226...227, BY 252...255, GP 20G...M
42426	DS13C..J	200..800V, 20A	1N3765...3768, 1N4525...4530
42427	DS140	750V, 13A	BY 399, BYW 14...16/..., BYW 96/...
42428	DS14C..J	DS 13 C..J	D 24/...C, 1N3765...3768R
42429	DS150A...C	200..600V, 1,5A	BY 226...227, BY 251...255, GP 20D...M
42430	DS15A,B	600..800V, 0,3A, <1,5µs	BA 158...159, BY 126...127, BY 204/...
42431	DS16(N)A...(N)E	50..800V, 0,5A	BY 126...127, BY 133...135, 1N4001...07
42432	DS17	100V, 2x0,5A	2xBY126...127, 2xBY133...135, 2x1N4002...07
42433	DS18	DS 17	2xBY126...127, 2xBY133...135, 2x1N4002...07
42434	DS185D...F	50..200V, 1,3A	B30C1500...B150C1500, etc.

42435	DS19	DS 17	2xBY126...127, 2xBY133...135, 2x1N4002...07
42436	DS1H...P	300..1800V, 1,1A	BY 226...228, BY 251...255, GP 15B...M
42437	DS2-04A..16A	400..1600V, 1,8A	BY 228, BY 252...255, BY 448, GP 30G...M
42438	DS230A...D	300..1000V, 0,3A, <300ns	BA 157...159, BY 204/..., BY 208/...
42439	DS2H...P	DS 1H..P, 1,65A	BY 228, BY 251...255, BYW 52...56
42440	DS2S	BA 100	BA 100
42441	DS330A...D	400..1000V, 0,13A, <300ns	BA 157...159, BY 204/..., BY 208/...
42442	DS38	70V, 0,15A	BA 188...190, BAY 19...21, 1N4148
42443	DS410	BA 127	BA 127
42444	DS430	0,55..0,8V(1,5mA)	BA 216, BA 314...315
42445	DS441	35V, 0,1A	BA 127, BA 147/50, BA 187...190, 1N4148
42446	DS442	35V, 0,12A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
42447	DS442X	DS 442, 55V, 0,13A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
42448	DS446	105V, 0,2A, 2<4ns	BAV 14
42449	DS448	35V, 0,12A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
42450	DS452	220V, 0,1A	BAY 20, BAY 46, BAY 88, BA 157...159
42451	DS454	DS 452, 320V	BA 157...159, BAY 46, BAY 88...89
42452	DS462	250V, 0,2A, <60ns	BAY 21, BAY 46, BAY 88, BA 157...159
42453	DS464	DS 462, 300V	BAY 21, BAY 46, BAY 88, BA 157...159
42454	DS6-04A..16A	400..1600V, 10A	BYX 42/...R, BYX 98/...R, SSi D04...
42455	DS8-04A..16A	400..1600V, 11A	BYW 88/...R, BYX 99/...R, SSi E20...
42456	DT	XN 6A554	XN 6A554
42457	DT	P4 SMA-200	P4 SMA-200
42458	DT	2SC4112	2SC4112
42459	DT	BCW 67RA	BCW 67RA
42460	DT	2SD1471-DT	2SD1471
42461	DT	HQ 1L2Q	HQ 1...
42462	DT06-02...10	Igt10mA	TAG 612-..., S 2600..., TAG 613-...
42463	DT1-02...12	Igt15mA	BStA30...M, BStC07...
42464	DTA08E	Igt/Ih<10/<10mA	MAC 94(A)-..., MAC 95(A)-..., MAC 96(A)-...
42465	DTA10C..G	Igt/Ih<80/30mA	BTA 22-..., TAG 250-..., TAG 251-...
42466	,V)	0,3W	-
42467	,V)	0,3W	-
42468	DTA113TC,TK(A)	DTA 113T..., SMD	-
42469	DTA113TE	DTA 113T..., SMD	-
42470	DTA113TU(A)	DTA 113T..., SMD	-
42471	,V)	100mA, 0,3W	AN 1A3Q, UN 4119
42472	,V)	100mA, 0,3W	AN 1A3Q, UN 4119
42473	DTA113ZC,ZK(A)	DTA 113Z..., SMD	FN 1A3Q, UN 2119
42474	DTA113ZE	DTA 113Z..., SMD	UN 9119
42475	DTA113ZU(A)	DTA 113Z..., SMD	UN 5119
42476	,V)	0,3W	AN 1A4M, RN 2002, UN 4111, 2SA1348
42477	,V)	0,3W	AN 1A4M, RN 2002, UN 4111, 2SA1348
42478	DTA114EC,EK(A)	DTA 114E..., SMD	FN 1A4M, RN 2402, UN2111, 2SA1344
42479	DTA114EE	DTA 114E..., SMD	RN 2102, UN 9111

42480	DTA114EU(A)	DTA 114E..., SMD	RN 2302, UN 5111, 2SA1678
42481	,V)	0,3W	-
42482	,V)	0,3W	-
42483	)	DTA 114G..., SMD	-
42484	DTA114GE	DTA 114G..., SMD	-
42485	DTA114GU(A)	DTA 114G..., SMD	-
42486	,V)	0,3W	AN 1A4Z, RN 2011, UN 4115, 2SA1497
42487	,V)	0,3W	AN 1A4Z, RN 2011, UN 4115, 2SA1497
42488	DTA114TC,TK(A)	DTA 114T..., SMD	FN 1A4Z, RN 2411, UN 2115, 2SA1496
42489	DTA114TE	DTA 114T..., SMD	RN 2111, UN 9115
42490	DTA114TU(A)	DTA 114T..., SMD	RN 2311, UN 5115
42491	S,V)	100mA, 0,3W	UN 411K
42492	S,V)	100mA, 0,3W	UN 411K
42493	A)	DTA 114W..., SMD	UN 211K
42494	DTA114WE	DTA 114W..., SMD	UN 911K
42495	DTA114WU(A)	DTA 114W..., SMD	UN 511K
42496	,V)	100mA, 0,3W	AN 1A4P, RN 2007, UN 4114, 2SA1564
42497	,V)	100mA, 0,3W	AN 1A4P, RN 2007, UN 4114, 2SA1564
42498	)	DTA 114Y..., SMD	FN 1A4P, RN 2407, UN 2114, 2SA1563
42499	DTA114YE	DTA 114Y..., SMD	RN 2107, UN 9114
42500	DTA114YU(A)	DTA 114Y..., SMD	RN 2307, UN 5114
42501	,V)	0,3W	-
42502	,V)	0,3W	-
42503	DTA115EC,EK(A)	DTA 115E..., SMD	-
42504	DTA115EE	DTA 115E..., SMD	-
42505	DTA115EU(A)	DTA 115E..., SMD	-
42506	,V)	0,3W	-
42507	,V)	0,3W	-
42508	)	DTA 115G..., SMD	-
42509	DTA115GE	DTA 115G..., SMD	-
42510	DTA115GU(A)	DTA 115G..., SMD	-
42511	,V)	100mA, 0,3W	-
42512	,V)	100mA, 0,3W	-
42513	DTA115TC,TK(A)	DTA 115T..., SMD	-
42514	DTA115TE	DTA 115T..., SMD	-
42515	DTA115TU(A)	DTA 115T..., SMD	-
42516	DTA115TU(A)	DTA 115T..., SMD	-
42517	,V)	100mA, 0,3W	-
42518	,V)	100mA, 0,3W	-
42519	)	DTA 115U..., SMD	-
42520	DTA115UE	DTA 115U..., SMD	-
42521	DTA115UU(A)	DTA 115U..., SMD	-
42522	DTA115UU(A)	DTA 115U..., SMD	-
42523	,V)	0,3W	-
42524	,V)	0,3W	-



42525	DTA123EC,EK(A)	DTA 123E..., SMD	-
42526	DTA123EE	DTA 123E..., SMD	-
42527	DTA123EU(A)	DTA 123E..., SMD	-
42528	DTA123EU(A)	DTA 123E..., SMD	-
42529	V)	100mA, 0,3W	KSR 2013, RN 2005
42530	V)	100mA, 0,3W	KSR 2013, RN 2005
42531	DTA123JC,JK(A)	DTA 123J..., SMD	KSR 2113, RN 2405, UN 211M
42532	DTA123JE	DTA 123J..., SMD	RN 2105
42533	DTA123JU(A)	DTA 123J..., SMD	RN 2305
42534	DTA123JU(A)	DTA 123J..., SMD	RN 2305
42535	,V)	100mA, 0,3W	UN 411H, 2SA1503
42536	,V)	100mA, 0,3W	UN 411H, 2SA1503
42537	)	DTA 123Y..., SMD	UN 211H, 2SA1502
42538	DTA123YE	DTA 123Y..., SMD	UN 911H
42539	DTA123YU(A)	DTA 123Y..., SMD	UN 511H, 2SA1722
42540	DTA123YU(A)	DTA 123Y..., SMD	UN 511H, 2SA1722
42541	,V)	100mA, 0,3W	AN 1F4M, RN 2003, UN 4112, 2SA1346
42542	,V)	100mA, 0,3W	AN 1F4M, RN 2003, UN 4112, 2SA1346
42543	DTA124EC,EK(A)	DTA 124E..., SMD	FN 1F4M, RN 2403, UN 2112, 2SA1342
42544	DTA124EE	DTA 124E..., SMD	RN 2103, UN 9112
42545	DTA124EU(A)	DTA 124E..., SMD	RN 2303, UN 5112, 2SA1677
42546	DTA124EU(A)	DTA 124E..., SMD	RN 2303, UN 5112, 2SA1677
42547	,V)	0,3W	2SA1574
42548	,V)	0,3W	2SA1574
42549	)	DTA 124G..., SMD	2SA1573
42550	DTA124GE	DTA 124G..., SMD	-
42551	DTA124GU(A)	DTA 124G..., SMD	-
42552	DTA124GU(A)	DTA 124G..., SMD	-
42553	,V)	0,3W	AN 1F4Z, KSR 2011, UN 4117, 2SA1590
42554	,V)	0,3W	AN 1F4Z, KSR 2011, UN 4117, 2SA1590
42555	DTA124TC,TK(A)	DTA 124T..., SMD	FN 1F4Z, KSR 2111, UN 2117, 2SA1598
42556	DTA124TE	DTA 124T..., SMD	RN 2112, UN 9117
42557	DTA124TU(A)	DTA 124T..., SMD	RN 2312, UN 5117
42558	DTA124TU(A)	DTA 124T..., SMD	RN 2312, UN 5117
42559	,V)	30mA, 0,3W	UN 411D
42560	,V)	30mA, 0,3W	UN 411D
42561	,V)	100mA, 0,3W	AN 1F4N, KSR 2007, RN 2008
42562	,V)	100mA, 0,3W	AN 1F4N, KSR 2007, RN 2008
42563	)	DTA 124X..., SMD	FN 1F4N, KSR 2107, RN 2408
42564	DTA124XE	DTA 124X..., SMD	RN 2108
42565	DTA124XU(A)	DTA 124X..., SMD	RN 2308
42566	DTA124XU(A)	DTA 124X..., SMD	RN 2308
42567	,V)	100mA, 0,3W	-
42568	,V)	100mA, 0,3W	-
42569	DTA125TC,TK	DTA 125T..., SMD	-

42570	DTA125TU	DTA 125T..., SMD	-
42571	DTA125TU	DTA 125T..., SMD	-
42572	DTA12C..G	200..600V, 12A(Tc92°)	BT 162/..., SC 149..., TIC 236...
42573	,V)	0,3W	AN 1L3M, RN 2001, UN 411L, 2SA1656
42574	,V)	0,3W	AN 1L3M, RN 2001, UN 411L, 2SA1656
42575	DTA143EC,EK(A)	DTA 143E..., SMD	FN 1L3M, RN 2401, UN 211L, 2SA1655
42576	DTA143EE	DTA 143E..., SMD	RN 2101, UN 911L
42577	DTA143EU(A)	DTA 143E..., SMD	RN 2301, UN511L
42578	DTA143EU(A)	DTA 143E..., SMD	RN 2301, UN511L
42579	,V)	0,3W	AN 1L3Z, RN 2010, UN 4116, 2SA1511
42580	,V)	0,3W	AN 1L3Z, RN 2010, UN 4116, 2SA1511
42581	DTA143TC,TK(A)	DTA 143T..., SMD	FN 1L3Z, RN 2410, UN 2116, 2SA1510
42582	DTA143TE	DTA 143T..., SMD	RN 2110, UN 9116
42583	DTA143TU(A)	DTA 143T..., SMD	RN 2310, UN 5116
42584	DTA143TU(A)	DTA 143T..., SMD	RN 2310, UN 5116
42585	,V)	100mA, 0,3W	AN 1L3N, KSR 2005, UN 411F, 2SA1654
42586	,V)	100mA, 0,3W	AN 1L3N, KSR 2005, UN 411F, 2SA1654
42587	)	DTA 143X..., SMD	FN 1L3N, KSR 2105, UN 211F, 2SA1653
42588	DTA143XE	DTA 143X..., SMD	UN 911F
42589	DTA143XU(A)	DTA 143X..., SMD	UN 511F
42590	DTA143XU(A)	DTA 143X..., SMD	UN 511F
42591	,V)	100mA, 0,3W	-
42592	,V)	100mA, 0,3W	-
42593	)	DTA 143Y..., SMD	-
42594	DTA143YE	DTA 143Y..., SMD	-
42595	DTA143YU(A)	DTA 143Y..., SMD	-
42596	DTA143YU(A)	DTA 143Y..., SMD	-
42597	,V)	100mA, 0,3W	RN 2006, 2SA1591, 2SA1616
42598	,V)	100mA, 0,3W	RN 2006, 2SA1591, 2SA1616
42599	DTA143ZC,ZK(A)	DTA 143Z..., SMD	RN 2406, 2SA1597
42600	DTA143ZE	DTA 143Z..., SMD	RN 2106
42601	DTA143ZU(A)	DTA 143Z..., SMD	RN 2306
42602	DTA143ZU(A)	DTA 143Z..., SMD	RN 2306
42603	,V)	0,3W	AN 1L4M, RN 2004, UN 4113, 2SA1345
42604	,V)	0,3W	AN 1L4M, RN 2004, UN 4113, 2SA1345
42605	DTA144EC,EK(A)	DTA 144E..., SMD	FN 1L4M, RN 2404, UN 2113, 2SA1341
42606	DTA144EE	DTA 144E..., SMD	RN 2104, UN 9113
42607	DTA144EU(A)	DTA 144E..., SMD	RN 2304, UN 5113, 2SA1676
42608	DTA144EU(A)	DTA 144E..., SMD	RN 2304, UN 5113, 2SA1676
42609	,V)	0,3W	2SA1572
42610	,V)	0,3W	2SA1572
42611	)	DTA 144G..., SMD	2SA1571
42612	DTA144GE	DTA 144G..., SMD	-
42613	DTA144GU(A)	DTA 144G..., SMD	-
42614	DTA144GU(A)	DTA 144G..., SMD	-

42615	,V)	0,3W	AN 1L4Z, KSR 2012, UN 4110, 2SA1509
42616	,V)	0,3W	AN 1L4Z, KSR 2012, UN 4110, 2SA1509
42617	DTA144TC,TK(A)	DTA 144T..., SMD	FN 1L4Z, KSR 2112, UN 2110, 2SA1508
42618	DTA144TE	DTA 144T..., SMD	RN 2113, UN 9110
42619	DTA144TU(A)	DTA 144T..., SMD	RN 2313, UN 5110
42620	DTA144TU(A)	DTA 144T..., SMD	RN 2313, UN 5110
42621	)	DTA 144V..., SMD	UN 211D
42622	DTA144VE	DTA 144V..., SMD	UN 911D
42623	DTA144VU(A)	DTA 144V..., SMD	UN 511D
42624	DTA144VU(A)	DTA 144V..., SMD	UN 511D
42625	S,V)	100mA, 0,3W	AN 1L4L, RN 2009, UN 411E, 2SA1347
42626	S,V)	100mA, 0,3W	AN 1L4L, RN 2009, UN 411E, 2SA1347
42627	A)	DTA 144W..., SMD	FN 1L4L, RN 2409, UN 211E, 2SA1343
42628	DTA144WE	DTA 144W..., SMD	RN 2109, UN 911E
42629	DTA144WU(A)	DTA 144W..., SMD	RN 2309, UN 511E
42630	DTA144WU(A)	DTA 144W..., SMD	RN 2309, UN 511E
42631	DTA16C..G	200..600V, 16A(Tc80°)	SC 151..., MAC 15-..., TIC 246...
42632	DTA1C..E	1A(Tc74°),Igt/Ih10/<10mA	Z 0101..., Z 0104..., Z 0106
42633	S,V)	70mA, 0,3W	-
42634	S,V)	70mA, 0,3W	-
42635	DTA1D3RE	DTA 1D3R..., SMD	-
42636	DTA1D3RK(A)	DTA 1D3R..., SMD	-
42637	DTA1D3RU(A)	DTA 1D3R..., SMD	-
42638	,V)	100mA, 0,3W	AN 1A4P, RN 2007, UN 4114, 2SA1564
42639	,V)	100mA, 0,3W	AN 1A4P, RN 2007, UN 4114, 2SA1564
42640	)	DTA 214Y..., SMD	FN 1A4P, RN 2407, UN 2114, 2SA1563
42641	DTA214YE	DTA 214Y..., SMD	RN 2107, UN 9114
42642	DTA214YU(A)	DTA 214Y..., SMD	RN 2307, UN 5114
42643	DTA214YU(A)	DTA 214Y..., SMD	RN 2307, UN 5114
42644	DTA25C..G	Igt/Ih<50/<70mA	MAC 525(A)-...
42645	DTA2B..E	2A(Tc70°),Igt/Ih<15/<25mA	TAG 137-..., TAG 138-...
42646	DTA3C..G	3A(Tc77°),Igt/Ih<45/25mA	Z 0409..., Z 0410...
42647	DTA6C..G(-N)	/<50mA	MAC 216A-..., T 2500..., TAG 220-...
42648	DTA8C..G	200..600V, 8A(Tc97°)	MAC 222-..., MAC 228-..., TIC 225...226...
42649	DTB10C..G	200..600V, 10A(Tc86°)	BTA 22..., TAG 250-...TAG 252-...
42650	V)	0,6W	RN 2221
42651	V)	0,6W	RN 2221
42652	DTB113EC,EK	DTB 113E..., SMD	-
42653	V)	500mA, 0,6W	RN 2226
42654	V)	500mA, 0,6W	RN 2226
42655	DTB113ZC,ZK	DTB 113Z..., SMD	-
42656	V)	0,6W	RN 2224, UN 4123, 2SA1522, 2SA1526
42657	V)	0,6W	RN 2224, UN 4123, 2SA1522, 2SA1526
42658	DTB114EC,EK	DTB 114E..., SMD	UN 2123, 2SA1518
42659	,V)	0,6W	-

42660	,V)	0,6W	-
42661	DTB114GC,GK	DTB 114G..., SMD	-
42662	V)	0,6W	-
42663	V)	0,6W	-
42664	DTB114TC,TK	DTB 114T..., SMD	-
42665	V)	500mA, 0,6W	-
42666	V)	500mA, 0,6W	-
42667	DTB122JC,JK	DTB 122J..., SMD	-
42668	V)	0,6W	RN 2222, UN 4121, 2SA1525, 2SA1529
42669	V)	0,6W	RN 2222, UN 4121, 2SA1525, 2SA1529
42670	DTB123EC,EK	DTB 123E..., SMD	UN 2121, 2SA1521
42671	V)	0,6W	-
42672	V)	0,6W	-
42673	DTB123TC,TK	DTB 123T..., SMD	-
42674	,V)	500mA, 0,6W	RN 2227, UN 4124, 2SA1524, 2SA1528
42675	,V)	500mA, 0,6W	RN 2227, UN 4124, 2SA1524, 2SA1528
42676	DTB123YC,YK	DTB 123Y..., SMD	UN 2124, 2SA1520
42677	DTB12C..G	200..600V, 12A(Tc75°)	BTA 23..., TAG 255-...TAG 257-...
42678	,V)	500mA, 0,6W	-
42679	,V)	500mA, 0,6W	-
42680	DTB133HC,HK	DTB 133Y..., SMD	-
42681	V)	0,6W	RN 1223, UN 4122, 2SA1523, 2SA1527
42682	V)	0,6W	RN 1223, UN 4122, 2SA1523, 2SA1527
42683	DTB143EC,EK	DTB 143E..., SMD	UN 2122, 2SA1519
42684	V)	0,6W	-
42685	V)	0,6W	-
42686	DTB143TC,TK	DTB 143T..., SMD	-
42687	V)	0,6W	-
42688	V)	0,6W	-
42689	DTB163TC,TK	DTB 163T..., SMD	-
42690	DTB16C..G	200..600V, 16A(Tc75°)	TIC 253...
42691	DTB3B..G	3A(Tc71°),Igt/Ih<30/<25mA	TAG 136-..., TAG 137-...
42692	DTB8C..G	200..600V, 8A(Tc86°)	T 2800..., T 2850..., TAC 224...227...
42693	DTC10C-N..G-N	Igt/Ih<50/<50mA	BTA 22-..., TAG 250-..., TAG 251-...
42694	V)	100mA, 0,3W	AA 1A3Q, UN 4219
42695	V)	100mA, 0,3W	AA 1A3Q, UN 4219
42696	DTC113ZC,ZK(A)	DTC 113Z..., SMD	FA 1A3Q, UN 2219
42697	DTC113ZE	DTC 113Z..., SMD	UN 9219
42698	DTC113ZU(A)	DTC 113Z..., SMD	UN 5219
42699	DTC113ZU(A)	DTC 113Z..., SMD	UN 5219
42700	V)	0,3W	AA 1A4M, RN 1002, UN 4211, 2SC3402
42701	V)	0,3W	AA 1A4M, RN 1002, UN 4211, 2SC3402
42702	DTC114EC,EK(A)	DTC 114E..., SMD	FA 1A4M, RN 1402, UN 2211, 2SC3398
42703	DTC114EE	DTC 114E..., SMD	RN 1102, UN 9211
42704	DTC114EU(A)	DTC 114E..., SMD	RN 1302, UN 5211, 2SC4398

42705	DTC114EU(A)	DTC 114E..., SMD	RN 1302, UN 5211, 2SC4398
42706	,V)	0,3W	-
42707	,V)	0,3W	-
42708	)	DTC 114G..., SMD	-
42709	DTC114GE	DTC 114G..., SMD	-
42710	DTC114GU(A)	DTC 114G..., SMD	-
42711	DTC114GU(A)	DTC 114G..., SMD	-
42712	V)	0,3W	AA 1A4Z, RN 1011, UN 4215, 2SC3860
42713	V)	0,3W	AA 1A4Z, RN 1011, UN 4215, 2SC3860
42714	DTC114TC,TK(A)	DTC 114T..., SMD	FA 1A4Z, RN 1411, UN 2215, 2SC3859
42715	DTC114TE	DTC 114T..., SMD	RN 1111, UN 9215
42716	DTC114TU(A)	DTC 114T..., SMD	RN 1311, UN 5215
42717	DTC114TU(A)	DTC 114T..., SMD	RN 1311, UN 5215
42718	S,V)	100mA, 0,3W	UN 421K
42719	S,V)	100mA, 0,3W	UN 421K
42720	A)	DTC 114W..., SMD	UN 221K
42721	DTC114WE	DTC 114W..., SMD	UN 921K
42722	DTC114WU(A)	DTC 114W..., SMD	UN 521K
42723	DTC114WU(A)	DTC 114W..., SMD	UN 521K
42724	,V)	70mA, 0,3W	AA 1A4P, RN 1007, UN 4214, 2SC4048
42725	,V)	70mA, 0,3W	AA 1A4P, RN 1007, UN 4214, 2SC4048
42726	)	DTC 114Y..., SMD	FA 1A4P, RN 1407, UN 2214, 2SC4047
42727	DTC114YE	DTC 114Y..., SMD	RN 1107, UN 9214
42728	DTC114YU(A)	DTC 114Y..., SMD	RN 1307, UN 5214
42729	DTC114YU(A)	DTC 114Y..., SMD	RN 1307, UN 5214
42730	V)	0,3W	-
42731	V)	0,3W	-
42732	DTC115EC,EK(A)	DTC 115E..., SMD	-
42733	DTC115EE	DTC 115E..., SMD	-
42734	DTC115EU(A)	DTC 115E..., SMD	-
42735	DTC115EU(A)	DTC 115E..., SMD	-
42736	,V)	0,3W	-
42737	,V)	0,3W	-
42738	)	DTC 115G..., SMD	-
42739	DTC115GE	DTC 115G..., SMD	-
42740	DTC115GU(A)	DTC 115G..., SMD	-
42741	DTC115GU(A)	DTC 115G..., SMD	-
42742	V)	100mA, 0,3W	-
42743	V)	100mA, 0,3W	-
42744	DTC115TC,TK(A)	DTC 115T..., SMD	-
42745	DTC115TE	DTC 115T..., SMD	-
42746	DTC115TU(A)	DTC 115T..., SMD	-
42747	,V)	20mA, 0,3W	-
42748	,V)	20mA, 0,3W	-
42749	DTC115UC,UK	DTC 115U..., SMD	-

42750	DTC115UU	DTC 115U..., SMD	-
42751	V)	0,3W	-
42752	V)	0,3W	-
42753	DTC123EC,EK(A)	DTC 123E..., SMD	-
42754	DTC123EE	DTC 123E..., SMD	-
42755	DTC123EU(A)	DTC 123E..., SMD	-
42756	DTC123JC,JK(A)	DTC 123J..., SMD	KSR 1113, RN 1405
42757	DTC123JE	DTC 123J..., SMD	RN 1105
42758	DTC123JU(A)	DTC 123J..., SMD	RN 1305
42759	,V)	100mA, 0,3W	UN 421H, 2SC3864
42760	,V)	100mA, 0,3W	UN 421H, 2SC3864
42761	)	DTC 123Y..., SMD	UN 221H, 2SC3863
42762	DTC123YE	DTC 123Y..., SMD	UN 921H
42763	DTC123YU(A)	DTC 123Y..., SMD	UN 521H, 2SC4498
42764	V)	0,3W	AA 1F4M, RN 1003, UN 4212, 2SC3400
42765	V)	0,3W	AA 1F4M, RN 1003, UN 4212, 2SC3400
42766	DTC124EC,EK(A)	DTC 124E..., SMD	FA 1F4M, RN 1403, UN 2212, 2SC3396
42767	DTC124EE	DTC 124E..., SMD	RN 1103, UN 9212
42768	DTC124EU(A)	DTC 124E..., SMD	RN 1303, UN 5212, 2SC4397
42769	,V)	0,3W	2SC4070
42770	,V)	0,3W	2SC4070
42771	)	DTC 124G..., SMD	2SC4069
42772	DTC124GE	DTC 124G..., SMD	-
42773	DTC124GU(A)	DTC 124G..., SMD	-
42774	V)	0,3W	AA 1F4Z, KSR 1011, UN 4217, 2SC4121
42775	V)	0,3W	AA 1F4Z, KSR 1011, UN 4217, 2SC4121
42776	DTC124TC,TK(A)	DTC 124T..., SMD	FA 1F4Z, KSR 1111, UN 2217, 2SC4120
42777	DTC124TE	DTC 124T..., SMD	RN 1112, UN 9217
42778	DTC124TU(A)	DTC 124T..., SMD	RN 1312, UN 5217
42779	,V)	100mA, 0,3W	AA 1F4N, KSR 1007, RN 1008
42780	,V)	100mA, 0,3W	AA 1F4N, KSR 1007, RN 1008
42781	)	DTC 124X..., SMD	FA 1F4N, KSR 1107, RN 1408
42782	DTC124XE	DTC 124X..., SMD	RN 1108
42783	DTC124XU(A)	DTC 124X..., SMD	RN 1308
42784	V)	100mA, 0,3W	-
42785	V)	100mA, 0,3W	-
42786	DTC125TC,TK	DTC 125T..., SMD	-
42787	DTC125TU	DTC 125T..., SMD	-
42788	DTC12C..G(-N)	Igt/Ih<50/<50mA	BTA23-..., BT138-..., TAG255-..., TAG256-...
42789	V)	100mA, 0,3W	AA 1L3M, RN 1001, UN 421L, 2SC4363
42790	V)	100mA, 0,3W	AA 1L3M, RN 1001, UN 421L, 2SC4363
42791	DTC143EC,EK(A)	DTC 143E..., SMD	FA 1L3M, RN 1401, UN 221L, 2SC5362
42792	DTC143EE	DTC 143E..., SMD	RN 1101, UN 921L
42793	DTC143EU(A)	DTC 143E..., SMD	RN 1301, UN 521L
42794	V)	0,3W	AA 1L3Z, RN 1010, UN 4216, 2SC3901



42795	V)	0,3W	AA 1L3Z, RN 1010, UN 4216, 2SC3901
42796	DTC143TC,TK(A)	DTC 143T..., SMD	FA 1L3Z, RN 1410, UN 2216, 2SC3900
42797	DTC143TE	DTC 143T..., SMD	RN 1110, UN 9216
42798	DTC143TU(A)	DTC 143T..., SMD	RN 1310, UN 5216
42799	,V)	100mA, 0,3W	AA 1L3N, KSR 1005, UN 421F, 2SC4361
42800	,V)	100mA, 0,3W	AA 1L3N, KSR 1005, UN 421F, 2SC4361
42801	)	DTC 143X..., SMD	FA 1L3N, UN 221F, 2SC4360
42802	DTC143XE	DTC 143X..., SMD	UN 921F
42803	DTC143XU(A)	DTC 143X..., SMD	UN 521F
42804	V)	100mA, 0,3W	RN 1006, 2SC4133, 2SC4195
42805	V)	100mA, 0,3W	RN 1006, 2SC4133, 2SC4195
42806	DTC143ZC,ZK(A)	DTC 143Z..., SMD	RN 1406, 2SC4146
42807	DTC143ZE	DTC 143Z..., SMD	RN 1106
42808	DTC143ZU(A)	DTC 143Z..., SMD	RN 1306
42809	V)	0,3W	AA 1L4M, RN 1004, UN 4213, 2SC3399
42810	V)	0,3W	AA 1L4M, RN 1004, UN 4213, 2SC3399
42811	DTC144EC,EK(A)	DTC 144E..., SMD	FA 1L4M, RN 1404, UN 2213, 2SC3395
42812	DTC144EE	DTC 144E..., SMD	RN 1104, UN 9213
42813	DTC144EU(A)	DTC 144E..., SMD	RN 1304, UN 5213, 2SC4396
42814	)	DTC 144G..., SMD	2SC4066
42815	DTC144GE	DTC 144G..., SMD	-
42816	DTC144GU(A)	DTC 144G..., SMD	-
42817	V)	0,3W	AA 1L4Z, KSR 1012, UN 4210, 2SC3899
42818	V)	0,3W	AA 1L4Z, KSR 1012, UN 4210, 2SC3899
42819	DTC144TC,TK(A)	DTC 144T..., SMD	FA 1L4Z, KSR 1112, UN 2210, 2SC3898
42820	DTC144TE	DTC 144T..., SMD	RN 1113, UN 9210
42821	DTC144TU(A)	DTC 144T..., SMD	RN 1313, UN 5210
42822	,V)	30mA, 0,3W	UN 421D
42823	,V)	30mA, 0,3W	UN 421D
42824	)	DTC 144V..., SMD	UN 221D
42825	DTC144VE	DTC 144V..., SMD	UN 921D
42826	DTC144VU(A)	DTC 144V..., SMD	UN 521D
42827	S,V)	30mA, 0,3W	AA 1L4L, RN 1009, UN 421E, 2SC3401
42828	S,V)	30mA, 0,3W	AA 1L4L, RN 1009, UN 421E, 2SC3401
42829	A)	DTC 144W..., SMD	FA 1L4L, RN 1409, UN 221E, 2SC3397
42830	DTC144WE	DTC 144W..., SMD	RN 1109, UN 921E
42831	DTC144WU(A)	DTC 144W..., SMD	RN 1309, UN 521E
42832	DTC16C..G	200..600V, 16A(Tc75°)	TIC 253...
42833	,V)	70mA, 0,3W	-
42834	,V)	70mA, 0,3W	-
42835	)	DTC 1D3R..., SMD	-
42836	DTC1D3RE	DTC 1D3R..., SMD	-
42837	DTC1D3RU(A)	DTC 1D3R..., SMD	-
42838	DTC1D3RU(A)	DTC 1D3R..., SMD	-
42839	V)	0,3W	DTD 114T...

42840	V)	0,3W	DTD 114T...
42841	DTC314TC,TK	DTC 314T..., SMD	DTD 114TK
42842	V)	0,3W	DTD 123T...
42843	V)	0,3W	DTD 123T...
42844	DTC323TC,TK	DTC 323T..., SMD	DTD 123TK
42845	V)	0,3W	DTD 143T...
42846	V)	0,3W	DTD 143T...
42847	DTC343TC,TK	DTC 343T..., SMD	DTD 143TK
42848	V)	0,3W	2SD1676
42849	V)	0,3W	2SD1676
42850	DTC363EC,EK	DTC 363E..., SMD	-
42851	V)	0,3W	DTD 163T...
42852	V)	0,3W	DTD 163T...
42853	DTC363TC,TK	DTC 363T..., SMD	DTD 163TK
42854	DTC8C..G(-N)	/<50mA	T 2800..., T 2850..., TAG 224-...
42855	,V)	0,6W	RN 1221
42856	,V)	0,6W	RN 1221
42857	DTD113EC,EK	DTD 113E..., SMD	-
42858	,V)	500mA, 0,6W	RN 1226
42859	,V)	500mA, 0,6W	RN 1226
42860	DTD113ZC,ZK	DTD 113Z..., SMD	-
42861	,V)	0,6W	RN 1224, UN 4223, 2SC3916, 2SC 3920
42862	,V)	0,6W	RN 1224, UN 4223, 2SC3916, 2SC 3920
42863	DTD114EC,EK	DTD 114E..., SMD	UN 2223, 2SC3912
42864	,V)	0,6W	-
42865	,V)	0,6W	-
42866	DTD114GC,GK	DTD 114G..., SMD	-
42867	,V)	0,6W	DTC 314T...
42868	,V)	0,6W	DTC 314T...
42869	DTD114TC,TK	DTD 114T..., SMD	DTC 314TK
42870	V)	500mA, 0,6W	-
42871	V)	500mA, 0,6W	-
42872	DTD122JC,JK	DTD 122J..., SMD	-
42873	,V)	0,6W	RN 1222, UN 4221, 2SC3919, 2SC 3923
42874	,V)	0,6W	RN 1222, UN 4221, 2SC3919, 2SC 3923
42875	DTD123EC,EK	DTD 123E..., SMD	UN 2221, 2SC3915
42876	,V)	0,6W	DTC 323T...
42877	,V)	0,6W	DTC 323T...
42878	DTD123TC,TK	DTD 123T..., SMD	DTC 323TK
42879	,V)	500mA, 0,6W	RN 1227, UN 4224, 2SC3918, 2SC3922
42880	,V)	500mA, 0,6W	RN 1227, UN 4224, 2SC3918, 2SC3922
42881	DTD123YC,YK	DTD 123Y..., SMD	UN 2224, 2SC3914
42882	,V)	500mA, 0,6W	-
42883	,V)	500mA, 0,6W	-
42884	DTD133HC,HK	DTD 133H..., SMD	-

42885	,V)	0,6W	RN 1223, UN 4222, 2SC3917, 2SC 3921
42886	,V)	0,6W	RN 1223, UN 4222, 2SC3917, 2SC 3921
42887	DTD143EC,EK	DTD 143E..., SMD	UN 2222, 2SC3913
42888	,V)	0,6W	DTC 343T...
42889	,V)	0,6W	DTC 343T...
42890	DTD143TC,TK	DTD 143T..., SMD	DTC 343TK
42891	,V)	0,6W	DTC 363T...
42892	,V)	0,6W	DTC 363T...
42893	DTD163TC,TK	DTD 163T..., SMD	DTC 363TK
42894	DTDG14GP	Rbe10kOhm, 60V, 1A	-
42895	DTDG23YP	1A	-
42896	DTDK14GP	Rbe10kOhm, -/10V, 2A	-
42897	DTDM12ZP	3A	-
42898	DTE16E	Igt/Ih<80/30mA	MAC 515A-..., MAC 525A-...
42899	DTF16C..G	Igt/Ih<50/<50mA	MAC 515(A)-..., MAC 525(A)-...
42900	DTM10C-N..G-N	Igt/Ih<50/<50mA	TAG 456-..., TAG 457-...
42901	DTM12C..G(-N)	Igt/Ih<50/<50mA	TAG480-..., TAG481-..., BTA23-...,BT138-...
42902	DTM6C..G(-N)	6A(Tc70°),Igt/Ih<50/<50mA	TAG 420-... MAC 216-..., T 2500...
42903	DTM8C..G(-N)	8A(Tc83°),Igt/Ih<50/<50mA	TAG425-..., TAG451-..., T2800..., T2850...
42904	DTP	2SD2391-P	2SD2391
42905	DTQ	2SD2391-Q	2SD2391
42906	DTV32(F)-..B	DTV 32(F)-..., <175ns	-
42907	DTV32-1000A	1000V, 3A, <72ns	BYT 56M, BYW 96E
42908	DTV32-1200A	1200V, 6A, <600ns	BY 329/1200, BY 359/1500
42909	DTV32-1500A	DTV 32-1200A, 1500V	BY 359/1500
42910	DTV32F-..	DTV 32-..	-
42911	DTV64-1200C	1200V, 6A, <100ns	-
42912	DTV64F-1200C	DTV 64-1200C	-
42913	DTZ2.0..36..	2,0..36V, 0,2W	HZU ..., RD ...S
42914	DU	3SK241	3SK241
42915	DU	3SK272	3SK272
42916	DU	P4 SMA-200A	P4 SMA-200A
42917	DU	BCW 67RB	BCW 67RB
42918	DU	HQ 1F2Q	HQ 1...
42919	DV	P4 SMA-220	P4 SMA-220
42920	DV1	2SD596-DV1	2SD596
42921	DV2	2SD596-DV2	2SD596
42922	DV3	2SD596-DV3	2SD596
42923	DV4	2SD596-DV4	2SD596
42924	DV5	2SD596-DV5	2SD596
42925	DVP	2SC4782-P	2SC4782
42926	DVP	2SC4755-P	2SC4755
42927	DVQ	2SC4782-Q	2SC4782
42928	DVQ	2SC4755-Q	2SC4755
42929	DVR	2SC4782-R	2SC4782

42930	DVR	2SC4755-R	2SC4755
42931	DW	BCW 67RC	BCW 67RC
42932	DW	SM 6T 15	SM 6T...
42933	DW1	2SD780-DW1	2SD780
42934	DW2	2SD780-DW2	2SD780
42935	DW3	2SD780-DW3	2SD780
42936	DW4	2SD780-DW4	2SD780
42937	DW5	2SD780-DW5	2SD780
42938	DW6089	BC 154	BC 154
42939	DW6170	BC 237	BC 237
42940	DW6208	BC 237	BC 237
42941	DW6335	BC 237	BC 237
42942	DW6577	BF 199	BF 199
42943	DW6618	BC 337	BC 337
42944	DW6619	BC 327	BC 327
42945	DW6737	BC 237	BC 237
42946	DW6969	BC 307	BC 307
42947	DW7000	BF 198	BF 198
42948	DW7035	BC 237	BC 237
42949	DW7039	BSX 24	BSX 24
42950	DW7050	BF 199	BF 199
42951	DW7975	BC 154	BC 154
42952	DX	P4 SMA-220A	P4 SMA-220A
42953	DX	BCW 68RF	BCW 68RF
42954	DX	HQ 1A4A	HQ 1...
42955	DX	SM 6T 15A	SM 6T...
42956	DX0107TA		B380C2200, etc.
42957	DX0107TA		B380C2200, etc.
42958	DX0118CE		B40C3300, etc.
42959	DX0118CE		B40C3300, etc.
42960	DX0128CE	RGP 30M	RGP 30M
42961	DY	2SA1620-Y	2SA1620
42962	DY	2SC3397	2SC3397
42963	DY	BCW 68RG	BCW 68RG
42964	DY	2SK1579	2SK1579
42965	DY	2SA1201-Y	2SA1201
42966	DY	KTA1661-Y	KTA 1661
42967	DZ	XN 4505	XN 4505
42968	DZ	BCW 68RH	BCW 68RH
42969	DZ...		
42970	DZB6.2..30(C)	6,2..30V, +-10%, C+-5%, 1W	BZW 22/..., BZX 61/..., BZX 85/...
42971	)	2,5,+5%	BZX 84/...
42972	E	HVU 17	HVU 17
42973	E	2SA1688	2SA1688
42974	E:	2SA1688	2SA1688

42975	E0100AD	Igt/Ih<0,02/5mA	-
42976	E0100FD	E 0100AD, 60V	-
42977	E0100YD	E 0100AD, 30V	-
42978	E0102AA	Igt/Ih0,2/5mA	BRX 46...47, BRX 51...52, TAG 62...
42979	E0102AB	Igt/Ih0,2/5mA	BRX 46...47, BRX 51...52, TAG 62...
42980	E0102AD	Igt/Ih0,2/5mA	BRX 46...47, BRX 51...52, TAG 62...
42981	E0102AG	Igt/Ih0,2/5mA	BRX 46...47, BRX 51...52, TAG 62...
42982	E0102FA	E 0102AA, 60V	BRX 46...47, BRX 51...52, TAG 62...
42983	E0102FB	E 0102AB, 60V	BRX 46...47, BRX 51...52, TAG 62...
42984	E0102FD	E 0102AD, 60V	BRX 46...47, BRX 51...52, TAG 62...
42985	E0102FG	E 0102AG, 60V	BRX 46...47, BRX 51...52, TAG 62...
42986	E0102YA	E 0102AA, 30V	BRX 46...47, BRX 51...52, TAG 62...
42987	E0102YB	E 0102AB, 30V	BRX 46...47, BRX 51...52, TAG 62...
42988	E0102YB	BR 103	BR 103
42989	E0102YD	E 0102AD, 30V	BRX 46...47, BRX 51...52, TAG 62...
42990	E0102YG(9004)	E 0102AG, 30V	BRX 46...47, BRX 51...52, TAG 62...
42991	E1	BFS 17W	BFS 17W
42992	E1	HRB 0103A	HRB 0103A
42993	E1	2SA1737	2SA1737
42994	E1(p)	BFS 17	BFS 17
42995	E15	BF 747	BF 747
42996	E16	BF 547W	BF 547W
42997	E1617	BD 115	BD 115
42998	E1694	BC 143	BC 143
42999	E2	BAL 99	BAL 99
43000	E2	HRB 0103B	HRB 0103B
43001	E2	2SA1226-2	2SA1226
43002	E2(p)	BFS 17A	BFS 17A
43003	E21	2SK932-21	2SK932
43004	E22	2SK932-22	2SK932
43005	E23	2SK932-23	2SK932
43006	E24	2SK932-24	2SK932
43007	E3	1SS190	1SS190
43008	E3	KDS 190	KDS 190
43009	E3	2SA1226-3	2SA1226
43010	E3	BAR 99	BAR 99
43011	E3	2SA1256-3	2SA1256
43012	E300	25V, Idss>6mA, Up<6V	BF 256B...C, BF 348, BFT 10A, 2N5397
43013	E304	30V, Idss>5mA, Up<6V	BFS 80, BFW 11, 2N4416, 2N5245
43014	E305	E 304, Idss>1mA, Up<3V	2N5457, 2SK246, 2SK330
43015	E308	25V, Idss>12mA, Up<6,5V	BFT 10B...C, 2SK125
43016	E309	E 308, Up<4V	-
43017	E310	E 308, Idss>24mA	BFT 10C, 2SK125
43018	E311	E 308, Idss<30mA, Up<4V	-
43019	E312	E 308, Idss<60mA	BFT 10C, 2SK125

43020	E4	2SA1226-4	2SA1226
43021	E4	BFS 17R	BFS 17R
43022	E4	2SA1256-4	2SA1256
43023	E5	BFS 17AR	BFS 17AR
43024	E5	2SA1256-5	2SA1256
43025	E5565	MPF 111	MPF 111
43026	E6	ZC 2800E	ZC 2800E
43027	E7	ZC 2810E	ZC 2810E
43028	E7140	BF 960	BF 960
43029	E7359	BF 966	BF 966
43030	E8	ZC 2811E	ZC 2811E
43031	E9	ZC 5800E	ZC 5800E
43032	EA	μPA574T	æPA574T
43033	EA	μPA504T	æPA504T
43034	EA	2SA1790-A	2SA1790
43035	EA	2SA1532-A	2SA1532
43036	EA	2SA1022-A	2SA1022
43037	EA	HC 2A4A	HC 2...
43038	EA	2SD1420-EA	2SD1420
43039	EA(s)	BCW 65A	BCW 65A
43040	EA961	2SB681	2SB681
43041	EA961	2SB681	2SB681
43042	EB	2SA1888-B	2SA1888
43043	EB	2SA1022-B	2SA1022
43044	EB	2SA1790-B	2SA1790
43045	EB	2SA1532-B	2SA1532
43046	EB	2SD1420-EB	2SD1420
43047	EB(s)	BCW 65B	BCW 65B
43048	EBP	2SK1842-P	2SK1842
43049	EBQ	2SK1842-Q	2SK1842
43050	EBR	2SK1842-R	2SK1842
43051	EBS	2SK1842-S	2SK1842
43052	EC	2SA1888-C	2SA1888
43053	EC	3SK247	3SK247
43054	EC	2SC2732	2SC2732
43055	EC	2SA1790-C	2SA1790
43056	EC	2SA1022-C	2SA1022
43057	EC	2SA1532-C	2SA1532
43058	EC	2SC4462	2SC4422
43059	EC	2SA1368-C	2SA1368
43060	EC	2SD1420-EC	2SD1420
43061	EC(s)	BCW 65C	BCW 65C
43062	EC961	2SD551	2SD551
43063	EC961	2SD551	2SD551
43064	ED	XP 4654	XP 4654



43065	ED	Z1 SMA-7V5	Z1 SMA-7V5
43066	ED	SM 6T 18	SM 6T...
43067	ED	2SD1421-ED	2SD1421
43068	ED	2SA1368-D	2SA1368
43069	ED	BCV 28	BCV 28
43070	ED1401(A...E)	TED 1402	TED 1402
43071	ED1402(A...E)	TED 1402	TED 1402
43072	ED1501(A...E)	TED 1502	TED 1502
43073	ED1502(A...E)	TED 1502	TED 1502
43074	ED1601(A...E)	TED 1602	TED 1602
43075	ED1602(A...E)	TED 1602	TED 1602
43076	ED1701(K...N)	TED 1702	TED 1702
43077	ED1702(K...N)	TED 1702	TED 1702
43078	ED1801(K...N)	TED 1802	TED 1802
43079	ED1802(K...N)	TED 1802	TED 1802
43080	ED2502	BF 255	BF 255
43081	ED592	BF 254	BF 254
43082	ED8050	SS 8050	SS 8050
43083	ED8550	SS 8550	SS 8550
43084	EE	Z1 SMA-6V8	Z1 SMA-6V8
43085	EE	BCV 48	BCV 48
43086	EE	2SA1368-E	2SA1368
43087	EE	2SD1421-EE	2SD1421
43088	EE	SM 6T 18A	SM 6T...
43089	EF	Z1 SMA-8V2	Z1 SMA-8V2
43090	EF	BCV 29	BCV 29
43091	EF(s)	BCW 66F	BCW 66F
43092	EFD108	SFD 108	SFD 108
43093	EFV1	BY 228	BY 228
43094	EG	Z1 SMA-9V1	Z1 SMA-9V1
43095	EG	BCV 49	BCV 49
43096	EG(s)	BCW 66G	BCW 66G
43097	EG01	400V, 0,7A, 100ns	BYV 26B...E, BYV 36B...E, RGP 10G...M
43098	EG01A	600V, 0,5A, 100ns	BYV 26C...E, BYV 36C...E, RGP 10J...M
43099	EG01C	1000V, 0,5A, 100ns	BYV 26E, BYV 36E, BYT 52M, RGP 10M
43100	EG01Y	70V, 1A, 100ns	BYV 26B...E, BYV 36A...E, RGP 10A...M
43101	EG01Z	200V, 0,7A, 100ns	BYV 26B...E, BYV 36A...E, RGP 10D...M
43102	EG1	400V, 0,8A, 100ns	BYV 26B...E, BYV 36B...E, RGP 10G...M
43103	EG1A	600V, 0,6A, 100ns	BYV 26C...E, BYV 36C...E, RGP 10J...M
43104	EG1Y	70V, 1,1A, 100ns	BYV 26B...E, BYV 36A...E, RGP 10A...M
43105	EG1Z	200V, 0,8A, 100ns	BYV 26B...E, BYV 36A...E, RGP 10D...M
43106	EGP10A...G	50..400V, 1A, <50ns	BYV 26B...E, FE 1A...H
43107	EGP20A...G	50..400V, 2A, <50ns	BYD 74A...G, BYV 27/..., FE 2A...H
43108	EGP30A...G	50..400V, 3A, <50ns	BYV 28/..., FE 3A...H
43109	EGP50A...G	50..400V, 5A, <50ns	BYV 61...63, FE 5A...H, FE 6A...H

43110	EH	Z1 SMA-10	Z1 SMA-10
43111	EH	SM 6T 22	SM 6T...
43112	EH	2SB1027-EH	2SB1027
43113	EH(s)	BCW 66H	BCW 66H
43114	EH1(A,Z)	200..600V, 0,6A, 4 $\mu$ s	BY 126...127, BY 133...134, 1N4003...07
43115	EI	UN 211M	UN 211M
43116	EI	UN 511M	UN 511M
43117	EL-	3SK182	3SK182
43118	EJ	2SB1027-EJ	2SB1027
43119	EJ4	3SK181-4	3SK181
43120	EJ5	3SK181-5	3SK181
43121	EJ5027	2N3055	2N3055
43122	EJ5027	2N3055	2N3055
43123	EJ6	3SK181-6	3SK181
43124	EK	XN 111M	XN 111M
43125	EK	Z1 SMA-11	Z1 SMA-11
43126	EK	2SB1027-EK	2SB1027
43127	EK	SM 6T 22A	SM 6T...
43128	EK	2SD1001-EK	2SD1001
43129	EK(s)	BCX 41	BCX 41
43130	EK03	30V, 1A, 200ns	BYV 10-30, SB 130...160, 1N5818...19
43131	EK04	40V, 1A, 200ns	BYS 21-45, BYV 10-40, SB140...160, 1N5819
43132	EK06	60V, 0,7A, 100ns	BYS 21-90, BYV 10-60, SB 160, MBR 160
43133	EK09	90V, 0,7A, 100ns	BYS 21-90, HRP 32
43134	EK13	30V, 1,5A, 200ns	BYS 22-45, BYS 26-45, 1N5821...22
43135	EK14	40V, 1,5A, 200ns	BYS 22-45, BYS 26-45, 1N5822
43136	EK16	60V, 1,5A, 100ns	BYS 22-90, BYS 26-90, HRP 34, MBR 360
43137	EK19	90V, 1,5A, 100ns	BYS 22-90, BYS 26-90
43138	EL	Z1 SMA-12	Z1 SMA-12
43139	EL	2SA1678	2SA1678
43140	EL	UN 521M	UN 521M
43141	EL	UN 221M	UN 221M
43142	EL	2SA1344	2SA1344
43143	EL	SM 6T 24	SM 6T...
43144	EL	2SB1028-EL	2SB1028
43145	EL	2SD1001-EL	2SD1001
43146	EL133	BF 245	BF 245
43147	EL1Z	200V, 1,5A, 50ns	BYD 73D...G, EGP 20D...G, FE 2D
43148	EM	XN 121M	XN 121M
43149	EM	Z1 SMA-13	Z1 SMA-13
43150	EM	2SB1028-EM	2SB1028
43151	EM	2SD1001-EM	2SD1001
43152	EM	SM 6T 24A	SM 6T...
43153	EM01(A,Y,Z)	100..600V, 1A	BY 126...127, BY 133...134, 1N4002...07
43154	EM1(A,B,C,Y,Z)	100..1000V, 1A	BY 126...127, BY 133...134, 1N4002...07

43155	EM2(A,B)	400..800V, 1,2A	BY 226...227, BYW 53...56, GP 15G...M
43156	EM502	1N4003	1N4003
43157	EM504	1N4004	1N4004
43158	EM506	1N4005	1N4005
43159	EM508	1N4006	1N4006
43160	EM510	1N4007	1N4007
43161	EM513	1N4007, Itt, 1300V	BY 228, BY 231/1500, DM 513, GP 10Y
43162	EM516	1N4007, Itt, 1600V	BY 228, BY 231/1500, DM 516, GP 10Y
43163	EM518	1N4007, 2000V	RGP 15-20
43164	EN	XN 4506	XN 4506
43165	EN	Z1 SMA-15	Z1 SMA-15
43166	EN	SM 6T 27	SM 6T...
43167	EN1132	2N1132, 0,3W	2N1132
43168	EN1613	2N1613, 0,3W	2N1613
43169	EN1711	2N1711, 0,3W	2N1711
43170	EN2218	2N2218, 0,35W	2N2218
43171	EN2219	2N2219, 0,35W	2N2219
43172	EN2221	2N2221, 0,2W	2N2221
43173	EN2222	2N2222, 0,2W	2N2222
43174	EN2369A	2N2369A, 0,2W	2N2369A
43175	EN2484	2N2484, 0,2W	2N2484
43176	EN2894A	2N2894A, 0,2W	2N2894A
43177	EN2904	2N2904, 0,3W	2N2904
43178	EN2905	2N2905, 0,3W	2N2905
43179	EN2906	2N2906, 0,2W	2N2906
43180	EN2907	2N2907, 0,2W	2N2907
43181	EN3009	2N3009, 0,2W	2N3009
43182	EN3011	2N3011, 0,2W	2N3011
43183	EN3013	2N3013, 0,2W	2N3013
43184	EN3014	2N3014, 0,2W	2N3014
43185	EN3250	2N3250, 0,2W	2N3250
43186	EN3502	2N3502, 0,3W	2N3502
43187	EN3504	2N3504, 0,2W	2N3504
43188	EN3903	2N3903, 0,31W	2N3903
43189	EN3904	2N3904, 0,31W	2N3904
43190	EN3905	2N3905, 0,31W	2N3905
43191	EN3906	2N3906, 0,31W	2N3906
43192	EN3962	2N3962, 0,2W	2N3962
43193	EN4123	2N4123, 0,2W	2N4123
43194	EN4124	2N4124, 0,2W	2N4124
43195	EN4125	2N4125, 0,2W	2N4125
43196	EN4126	2N4126, 0,2W	2N4126
43197	EN5172	2N5172, 0,2W	2N5172
43198	EN697	2N697, 0,3W	2N697
43199	EN706	2N706, 0,2W	2N706

43200	EN708	2N708, 0,2W	2N708
43201	EN718A	2N718A, 0,22W	2N718 A
43202	EN722	2N722, 0,2W	2N722
43203	EN744	2N744, 0,2W	2N744
43204	EN870	2N870, 0,22W	2N870
43205	EN871	2N871, 0,22W	2N871
43206	EN914	2N914, 0,2W	2N914
43207	EN915	2N915, 0,2W	2N915
43208	EN916	2N916, 0,2W	2N916
43209	EN918	2N918, 0,2W	2N918
43210	EN930	2N930, 0,2W	2N930
43211	EN956	2N956, 0,22W	2N956
43212	EO	2SC5097-O	2SC5097
43213	EO	2SC3265-O	2SC3265
43214	EO	2SC2882-O	2SC2882
43215	EO	KTC4374-O	KTC 4374
43216	EP	XN 4556	XN 4556
43217	EP	Z1 SMA-16	Z1 SMA-16
43218	EP	2SB789A-P	2SB789A
43219	EP	SM 6T 27A	SM 6T...
43220	EP01C	1000V, 0,2A, 200ns	BA 159, BYT 11/1000, BYT 52M, BYV 26E
43221	EQ	XP 1D874	XP 1D874
43222	EQ	Z1 SMA-18	Z1 SMA-18
43223	EQ	2SB789A-Q	2SB789A
43224	EQ	SM 6T 30	SM 6T...
43225	EQA01-05...-35	5..35V, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5231...58
43226	EQB01-05...-35	5..35V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5918...38
43227	ER	XP 4683	XP 4683
43228	ER	2SC5097-R	2SC5097
43229	ER	Z1 SMA-20	Z1 SMA-20
43230	ER	2SB789A-R	2SB789A
43231	ER	2SC4807	2SC4807
43232	ER	SM 6T 30A	SM 6T...
43233	ER1A..E	50..300V, 0,6A, <35ns	D 1FL20, D 1FL40, MURS 120
43234	ER2	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
43235	ER2A..E	50..300V, 1,5A, <35ns	BYG 22A...D
43236	ER900	BDW 32	A 9903, D 32
43237	ERB06-13	1300, 1A, <4μs	BY 231/1400, BY 350/1300, BY 400
43238	ERB12-01...-10	100..1000V, 1A	BY 126...127, BY 133...135, 1N4002...07
43239	ERB24-04C...06C	400..600V, 1A, <700ns	BYX 55/600, MR 814...818, RGP 10G...M
43240	ERB24-04D...06D	400..600V, 0,7A, <1μs	BYX 55/600, MR 814...818, RGP 10G...M
43241	ERC01-06	600V, 1,5A	BYD 13J...M, BY 227...227, GP 15J...M
43242	ERC01-10	ERC 01-06, 1000V	BYD 13M, BY 227, GP 15M, RGP 15M
43243	ERC05-08	800V, 1,2A	BYD 13K...M, BY 227, GP 15K...M
43244	ERC06-13	1300V, 1,5A, <4μs	BY 231/1400, BY 350/1300, BY 400

43245	ERC06-15	ERC 06-13, 1500V	BY 231/1500, BY 350/1500, BY 448
43246	ERD29-06	600, 2,5A, <400ns	BYW 14/600, BYW 95C, RGP 30J...M
43247	ES	Z1 SMA-22	Z1 SMA-22
43248	ES	2SA1745	2SA1745
43249	ES	BCX 41R	BCX 41R
43250	ES	2SA1753	2SA1753
43251	ES	2SB789A-S	2SB789A
43252	ES	2SD1974	2SD1974
43253	ES	SM 6T 33	SM 6T...
43254	ES1,01(A,Z)	200..600V, 0,7A, 1,5µs	BY 126...127, BY 133...134, 1N4003...07
43255	ES1F	1500V, 0,5A, <400ns	BY 269, BY 231/1500, RGP 15-16
43256	50	<2,7µs	S 3703..., BStCC01...H, TD3F...H
43257	50	450..750V, 5A, Igt<60mA, <5µs	S 6080C..., BStCC01...R, TD3F...R
43258	ESM217	B>1000	BDT 63(A...C), BDW 93A...C, BDX 33A...D
43259	ESM218	ESM 217, 80V	BDT 63A...C, BDW 93B...C, BDX 33B...D
43260	100..600(N)	Igt/Ih<40/<30mA	T 2303..., TAG 208-...
43261	50	<2,7µs	BStCC01...H, TD3F...H, TD4F...H
43262	50	450..750V, 5A, Igt<60mA, <5µs	BStCC01...R, TD3F...R, TD4F...R
43263	ESM23-100...600	100..600V, 6A, Igt<80mA	TAG 260-..., TAG 265-..., T 4700...
43264	ESM23-100...600	100..600V, 6A, Igt<80mA	TAG 260-..., TAG 265-..., T 4700...
43265	ESM249R/500	500V, 5A, Igt<60mA, <25µs	TD3F500H, TD4F500H, S 6087B
43266	ESM261	B>1000	BDT 62(A...C), BDW 94A...C, BDX 34A...D
43267	ESM262	ESM 261, 80V	BDT 62A...C, BDW 94B...C, BDX 34B...D
43268	ESM2633	2N3055	2N3055
43269	ESM2633	2N3055	2N3055
43270	ESM2666	1500/600V, 6A, 75W(Tc95°)	BU 508A, 2SD350A, 2SD649, 2SD821
43271	ESM2666	1500/600V, 6A, 75W(Tc95°)	BU 508A, 2SD350A, 2SD649, 2SD821
43272	ESM2667	ESM2666, 1500/700V	BU 508A, 2SD350A, 2SD821, 2SD649
43273	ESM2667	ESM2666, 1500/700V	BU 508A, 2SD350A, 2SD821, 2SD649
43274	ESM2668	BU 526	BU 526
43275	ESM2668	BU 526	BU 526
43276	ESM2731	BU 526	BU 526
43277	ESM2731	BU 526	BU 526
43278	ESM28	30V, 4A, 25W, 3MHz	BD 243, BD 533, BD 539, BD 947
43279	ESM2808	BU 800	BU 800
43280	ESM2808	BU 800	BU 800
43281	ESM29	30V, 4A, 25W, 3MHz	BD 244, BD 534, BD 540, BD 948
43282	ESM313/...R	Igt/Ih<150/<200mA,<5µs	-
43283	ESM313/...R	Igt/Ih<150/<200mA,<5µs	-
43284	ESM400(A)	170V, 1,5A, 20W, 1MHz	BD 239E, 2SD386, 2SD578, 2SD1138
43285	ESM4629		-
43286	ESM504/...	25µs	TAG 630-..., TAG 620-..., TIC 116...
43287	ESM508/...	50..600V, 8A, Igt/Ih<40/<60mA	TAG 655-..., 2N6394...6399, BStD10...
43288	ESM509/...	Igt/Ih<40/<60mA	2N6394...6399, BStD10..., BT 152/...
43289	ESM740(G)	<15µs	-

43290	ESM7545DF,V	600/450V, 75A, 250W	-
43291	ESM765/..PI	ESM 765/..	BYT 12PI-...
43292	A	100..800V, 10A(Tc100°),<300ns	BYT 12P-..., BYT 79-..., BYV 79-...
43293	ESMT5070DF,V	1000/700V, 50A, 300W	-
43294	ET	3SK273	3SK273
43295	ET	Z1 SMA-24	Z1 SMA-24
43296	ET	2SC4120	2SC4120
43297	ET	BCW 65RA	BCW 65RA
43298	ET	SM 6T 33A	SM 6T...
43299	ET	2SD1471-ET	2SD1471
43300	EU	Z1 SMA-27	Z1 SMA-27
43301	EU	BCW 65RB	BCW 65RB
43302	EU	SM 6T 36	SM 6T...
43303	EU(0)1(A,Z)	200..600V, 0,25A, 400ns	BA 157...159, BY 204/..., BYX 57/...
43304	EU(0)2(A,Z)	200..600V, 1A, 400ns	BYD 33J...M, BYT 11/600, BYT 52J...M
43305	EU2YX	100V, 1,2A, 200ns	BYD 33D...M, BYT 11/600, BYT 52B...M
43306	EV	1SV241	1SV241
43307	EV	Z1 SMA-30	Z1 SMA-30
43308	EV	SM 6T 36A	SM 6T...
43309	EW	Z1 SMA-33	Z1 SMA-33
43310	EW	BCW 65RC	BCW 65RC
43311	EW	SM 6T 39	SM 6T...
43312	EX	Z1 SMA-36	Z1 SMA-36
43313	EX	BCW 66RF	BCW 66RF
43314	EX	SM 6T 39A	SM 6T...
43315	EX	2SD2402-EX	2SD2402
43316	EX0022TA	11,5V	
43317	EX0048CE	6,2V	
43318	EX0074CE	115V	
43319	EY	Z1 SMA-39	Z1 SMA-39
43320	EY	BCW 66RG	BCW 66RG
43321	EY	KTC3265-Y	KTC 3265
43322	EY	2SC3265-Y	2SC3265
43323	EY	2SC4398	2SC4398
43324	EY	2SC3398	2SC3398
43325	EY	2SC2882-Y	2SC2882
43326	EY	2SK1697	2SK1697
43327	EY	2SD2402-EY	2SD2402
43328	EY	KTC4374-Y	KTC 4374
43329	EYV-320(D)	BA 127	BA 127
43330	EZ	Z1 SMA-43	Z1 SMA-43
43331	EZ	BCW 66RH	BCW 66RH
43332	EZ	2SD2402-EZ	2SD2402
43333	EZ-055...-372	5..37V, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5231...58
43334	F	HVU 352	HVU 352



43335	F	2SC4399	2SC3499
43336	F01J3	30V, 0,1A, 30ns	-
43337	F01J3	30V, 0,1A, 30ns	-
43338	F02	SO 4091	SO 4091
43339	F02J3	30V, 0,2A, 30ns	-
43340	F02J3	30V, 0,2A, 30ns	-
43341	F03	SO 4391	SO 4391
43342	F07	SO 4392	SO 4392
43343	F08	SO 4393	SO 4393
43344	F0810BH	<25/75mA	TIC 116..., BStC10...M, CS6-..., TAG 660...
43345	F0810DH	F 0810BH, 400V	TIC 116..., BStC10...M, CS6-..., TAG 660...
43346	F0810MH	F 0810BH, 600V	TIC 116..., BStC10...M, CS6-..., TAG 660...
43347	F0810NH	F 0810BH, 800V	TIC 116..., BStC10...M, CS6-..., TAG 660...
43348	F09	SO 3966	SO 3966
43349	F099	BA 159	BA 159
43350	F1	FRS 1A	FRS 1A
43351	F1	KST 1009F1	KST 1009
43352	F1	2SC1009-F1	2SC1009
43353	F1(p)	BFS 18	BFS 18
43354	F10	SO 4092	SO 4092
43355	F11	SO 4093	SO 4093
43356	F114B...F	200..600V, 0,8A, <200ns	BY 201/..., BYV 13...16, RGP 10D...M
43357	F12	2SC4178-F12	2SC4178
43358	F12	2SC2223-F12	2SC2223
43359	F12	SO 245B	SO 245
43360	F13	2SC2223-F13	2SC2223
43361	F13	BFR 30R	BFR 30R
43362	F13	2SC4178-F13	2SC4178
43363	F133	BY 133	BY 133
43364	F14	BFR 31R	BFR 31R
43365	F14	2SC2223-F14	2SC2223
43366	F14	2SC4178-F14	2SC4178
43367	F14A...J	100..1000V, 1A	BY 126...127, BY 133...135, 1N4002...07
43368	F14N05	RFD 14N05	RFD 14N05
43369	F14N06	RFD 14N06	RFD 14N06
43370	F15	SO 5432	SO 5432
43371	F15P05	RFD 15P05	RFD 15P05
43372	F15P06	RFD 15P06	RFD 15P06
43373	F16	F 1F16	F 1F16
43374	F16	SO 5432R	SO 5432R
43375	F16	SM-1XF16	SM-1XF16
43376	F1612BH	25/100mA	T 9,5N..., CS15-..., BStD10...M
43377	F1612DH	F 1612BH, 400V	T 9,5N..., CS15-..., BStD10...M
43378	F1612MH	F 1612BH, 600V	T 9,5N..., CS15-..., BStD10...M
43379	F1612NH	F 1612BH, 800V	T 9,5N..., CS15-..., BStD10...M

43380	F16N05	RFD 16N05	RFD 15N05
43381	F16N06	RFD 16N06	RFD 15N06
43382	F17	SO 5433	SO 5433
43383	F18	SO 5433R	SO 5433R
43384	F19	SO 5434	SO 5433R
43385	F1B..CC	F 1B..CA	BYP 20-..., BYQ 28-..., BYT 28-...
43386	F1B1CA	100V, 10A, 400ns	-
43387	F1B2CA	F 1B1CA, 200V	-
43388	F1C57..5120	7,5..340V	BZG 04/...
43389	F1F16	1600V, 0,5A, 1500ns	-
43390	F1F16	1600V, 0,5A, 1500ns	-
43391	F1H2	200V, 1A, 400ns	-
43392	F1H2	200V, 1A, 400ns	-
43393	F1H4	F 1H2, 400V	-
43394	F1H4	F 1H2, 400V	BYG 20G...M, BYG 21K...M, FR 2G...M
43395	F1H4	F 1H2, 400V	-
43396	F1H6	F 1H2, 600V	BYG 20J...M, BYG 21K...M, FR 2J...M
43397	F1J2	20V, 1A, 30ns	-
43398	F1J3U	30V, 1A, 30ns	-
43399	F1J4	40V, 1A, 30ns	-
43400	F1J6	60V, 1A, 30ns	-
43401	F1J9	90V, 0,7A, 30ns	-
43402	F1N2	200V, 1A	-
43403	F1N2	200V, 1A	-
43404	F1N4	F 1N2, 400V	-
43405	F1N4	F 1N2, 400V	BYG 10G...M, D 1F40...60, U 1GC44...JC44
43406	F1N4	F 1N2, 400V	-
43407	F1N6	F 1N2, 600V	BYG 10J...M, D 1F60, U 1DCJC44
43408	F1O	KSA 1182-O	KSA 1182
43409	F1P2	200V, 1A, 50ns	-
43410	F1P2	200V, 1A, 50ns	-
43411	F1P2S	F 1P2, 60ns	-
43412	F1P2S	F 1P2, 60ns	-
43413	F1S0P05	RF 1S0P05	RF 1S0P05
43414	F1S0P06	RF 1S0P06	RF 1S0P06
43415	F1S25N06	RF 1S25N06	RF 1S25N06
43416	F1S45N06	RF 1S45N06	RF 1S45N06
43417	F1S50N06	RF 1S50N06	RF 1S50N06
43418	F1S60P03	RF 1S60P03	RF 1S60P03
43419	F1S70N03	RF 1S70N03	RF 1S70N03
43420	F1S70N06	RF 1S70N06	RF 1S70N06
43421	F1Y	KSA 1182-Y	KSA 1182
43422	F2	FRS 1B	FRS 1B
43423	F2	2SC1009-F2	2SC1009
43424	F2	KST 1009F2	KST 1009

43425	F2	2SC2814-F2	2SC2814
43426	F2(p)	BFS 19	BFS 19
43427	F20	SO 245BR	SO 245
43428	F20	SM-1XF20	SM-1XF20
43429	F21	SO 245A	SO 245
43430	F22	SO 4091R	SO 4091R
43431	F23	SO 4391R	SO 4391R
43432	F23N06LE	RF1S23N06LE	RF 1S23N06LE
43433	F24	SO 245AR	SO 245AR
43434	F25	SO 245C	SO 245C
43435	F26	SO 245CR	SO 245CR
43436	F27	SO 4392R	SO 4392R
43437	F28	SO 4393R	SO 4393R
43438	F29	SO 3966R	SO 3966R
43439	F2B..CC	F 2B..CA	BYV 72F-..., BYV 74F-..., MA 651
43440	F2B..CC	F 2B..CA	BYV 72F-..., BYV 74F-..., MA 651
43441	F2B1CA	100V, 20A, 400ns	-
43442	F2B1CA	100V, 20A, 400ns	-
43443	F2B2CA	F 2B1CA, 200V	-
43444	F2B2CA	F 2B1CA, 200V	-
43445	F2P2	200V, 2A, 50ns	-
43446	F3	FRS 1D	FRS 1D
43447	F3	BF 840	BF 840
43448	F3	KST 1009F3	KST 1009
43449	F3	1SS193	1SS193
43450	F3	KDS 193	KDS 193
43451	F3	2SC1009-F3	2SC1009
43452	F3	2SC2814-F3	2SC2814
43453	F30	SO 4092R	SO 4092R
43454	F30N06LE	RFP 30N06LE	RFP 30N06LE
43455	F31	BF 841	BF 841
43456	F31	SO 4093R	SO 4093R
43457	F32	SO 5434R	SO 5434R
43458	F3N08L	RFD 3N08L	RFD 3N08L
43459	F3T	1PS193	1PS193
43460	F4	FRS 1G	FRS 1G
43461	F4	2SC2814-F4	2SC2814
43462	F4	BFS 18R	BFS 18R
43463	F4	KST 1009F4	KST 1009
43464	F4	2SC1009-F4	2SC1009
43465	F40N10LE	RF1S40N10LE	RF 1S40N10LE
43466	F45N03L	RF 1S45N03L	RF 1S45N03L
43467	F5	FRS 1J	FRS 1J
43468	F5	1SS250	1SS250
43469	F5	1SS370	1SS370

43470	F5	KST 1009F5	KST 1009
43471	F5	2SC2814-F5	2SC2814
43472	F5	2SC1009-F5	2SC1009
43473	F5	BFS 19R	BFS 19R
43474	F5A..CC	F 5A..CA	BYP 20-..., BYQ 28-..., BYT 28-...
43475	F5A1CA	100V, 5A, 200ns	-
43476	F5A2CA	F 5A1CA, 200V	-
43477	F6	FRS 1K	FRS 1K
43478	F6	2SC2223-F6	2SC2223
43479	F7	FRS 1M	FRS 1M
43480	F7	HSB 83J	HSB 83J
43481	F7	HSM 83	HSM 83
43482	F8	HSM 122	HSM 122
43483	F8	SM-1XF08	SM-1XF08
43484	F8(p)	BF 824	BF 824
43485	F9	1SS321	1SS321
43486	F9010...9022	CS 9010..9022	
43487	FA	BFP 81	BFP 81
43488	FA	μPA505T	æPA505T
43489	FA	2SC2619-A	2SC2619
43490	FA	BSV 65A	BSV 65A
43491	FA	BFQ 17	BFQ 17
43492	FA	HQ 2A4A	HQ 2...
43493	FA1A3Q	AA 1A3Q, SMD	DTC 113ZK, UN 2219
43494	FA1A4M	AA 1A4M, SMD	DTC 113EK, RN 1402, UN 2211, 2SC3398
43495	FA1A4P	AA 1A4P, SMD	DTC 114YK, RN 1407, UN 2214, 2SC4047
43496	FA1A4Z	AA 1A4Z, SMD	DTC 114TK, RN 1411, UN 2215, 2SC3859
43497	FA1F4M	AA 1F4M, SMD	DTC 124EK, RN 1403, UN 2212, 2SC3396
43498	FA1F4N	AA 1F4N, SMD	DTC 124XK, KSR 1107, RN 1408
43499	FA1F4Z	AA 1F4Z, SMD	DTC 124TK, KSR 1111, UN 2217, 2SC4120
43500	FA1L3M	AA 1L3M, SMD	DTC 143EK, RN 1401, UN 221L, 2SC4362
43501	FA1L3N	AA 1L3N, SMD	DTC 143XK, KSR 1105, UN 221F, 2SC4360
43502	FA1L3Z	AA 1L3Z, SMD	DTC 143TK, RN 1410, UN 2216, 2SC3900
43503	FA1L4L	AA 1L4L, SMD	DTC 144WK, RN 1409, UN 221E, 2SC3397
43504	FA1L4M	AA 1L4M, SMD	DTC 144EK, RN 1404, UN 2213, 2SC3395
43505	FA1L4Z	AA 1L4Z, SMD	DTC 144TK, KSR 1112, UN 2210, 2SC3898
43506	FA3	2SC4179-FA3	2SC4179
43507	FA3L4Z	BA 3L4Z, SMD	-
43508	FA4	2SC4179-FA4	2SC4179
43509	FB	2SC5016	2SC5016
43510	FB	BFP 17	BFP 17
43511	FB	BSV 65B	BSV 65B
43512	FB	2SC2619-B	2SC2619
43513	FB	2SC3053-B	2SC3053
43514	FB	2SC4258-B	2SC4258

43515	FB	BFQ 19	BFQ 19
43516	FB1A3M..L3N	AB 1A3M..L3N, SMD	-
43517	FC	BFP 29	BFP 29
43518	FC	2SC4258-C	2SC4258
43519	FC	2SC2619-C	2SC2619
43520	FC	2SC3053-C	2SC3053
43521	FC	2SC3438-C	2SC3438
43522	FC	BFQ 64	BFQ 64
43523	FC101	2x 2SA1622	-
43524	FC102	2x 2SC4211	-
43525	FC103	2x 2SA1622	-
43526	FC104	2x 2SC4211	-
43527	FC105	2x 2SA1341	-
43528	FC106	2x 2SC3395	-
43529	FC107	2x 2SA1341	-
43530	FC108	2x 2SC3395	-
43531	FC109	2x 2SA1342	-
43532	FC11	2x 2SK772	-
43533	FC110	2x 2SC3396	-
43534	FC111	2x 2SA1342	-
43535	FC112	2x 2SC3396	-
43536	FC113	2x 2SA1344	-
43537	FC114	2x 2SC3398	-
43538	FC115	2x 2SA1344	-
43539	FC116	2x 2SC3398	-
43540	FC117	2x 2SA1745	-
43541	FC118	2x 2SC4555	-
43542	FC119	2x 2SC2814	-
43543	FC120	2x 2SC3142	-
43544	FC121	2x 2SA1502	-
43545	FCS6208...6209	CS 6208..6209	
43546	FCS9010...9022	CS 9010..9022	
43547	FD	BFP 35A	BFP 35A
43548	FD	Z1 SMA-47	Z1 SMA-47
43549	FD	2SC4258-D	2SC4258
43550	FD	2SC3053-D	2SC3053
43551	FD	BCV 26	BCV 26
43552	FD	BFQ 17P	BFQ 17P
43553	FD	2SC3438-D	2SC3438
43554	FD100	75V, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
43555	FD111	75V, <5ns	BAW 62, BAW 76, BAX 95, 1N4148...49
43556	FD200	200V, <50ns	BA 197...198, BAV 20...21, BAW 50
43557	FD222	150V, <60ns	BA 196...198, BAV 16, BAV 20...21, BAW 50
43558	FD300	150, Ir<1nA(125V)	BAS 45, FDH 300, FDH 333
43559	FD333	150, Ir<3nA(125V)	BAS 45, FDH 300, FDH 333

43560	FD600	75V, <4ns	BAV 12, BAV 14, BAW 26...27, BAX 81
43561	FD6666	75V, <5ns	BAW 26...27, BAV 12, BAV 14, BAX 81
43562	FD700	20V, 0,05A, <0,7ns	FDH 700
43563	FD777	8V, 0,05A, <0,75ns	FDH 777
43564	FDH1000	50V, 0,2A	BAW 24...27
43565	FDH300	125V, 0,2A, Ir<1nA(125V)	BAS 45
43566	FDH333	125V, 0,2A, Ir<3nA(125V)	BAS 45
43567	FDH3595	150V, 0,2A, <3µs, (1N3595)	BA 157...159, BAW 52, BAY 20...21
43568	FDH400	175V, 0,2A, <50ns	BA 197...198, BAV 20...21, BAW 50
43569	FDH444	125V, 0,2A, <60ns	BA 196...198, BAV 15...16, BAV 19...21
43570	FDH600	50V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
43571	FDH666	25V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
43572	FDH700	20V, 0,05A, <0,7ns	FD 700
43573	FDH777	8V, 0,05A, <0,75ns	FD 777
43574	FDH900	40V, 0,2A, <4ns	BAV 10, BAW 24...27, BAX 81, 1N4150
43575	FDH999	25V, 0,2A, <5ns	BAV 10, BAW 24...27, BAX 81, 1N4150
43576	FDLL1000	FDH 1000, SMD	BAS 45L
43577	FDLL300	FDH 300, SMD	BAS 45L
43578	FDLL3064	1N3064, SMD	BAS 32, LL 4148
43579	FDLL3070	1N3070, SMD	-
43580	FDLL333	FDH 333, SMD	BAS 45L
43581	FDLL3595	1N3595, SMD	HSK 83, HSK 122
43582	FDLL3600	1N3600, SMD	BAS 32, LL 4148
43583	FDLL400	FDH 400, SMD	-
43584	FDLL4009	1N4009, SMD	BAS 32, LL 4148
43585	FDLL4148..4154	1N4148..4154, SMD	BAS 32, LL 4148
43586	FDLL4305	1N4305, SMD	BAS 32, LL 4148
43587	FDLL444	FDH 444, SMD	-
43588	FDLL4446..4450	1N4446..4450, SMD	BAS 32, LL 4148
43589	FDLL4454	1N4454, SMD	BAS 32, LL 4148
43590	FDLL456(A)	1N456(A), SMD	BAS 32, LL 4148
43591	FDLL457(A)	1N457(A), SMD	BAS 32, LL 4148
43592	FDLL458(A)	1N458(A), SMD	HSK 83
43593	FDLL459(A)	1N459(A), SMD	HSK 83
43594	FDLL461A	1N461A, SMD	BAS 32, LL 4148
43595	FDLL462A	1N462A, SMD	BAS 32, LL 4148
43596	FDLL463A	1N463A, SMD	HSK 83
43597	FDLL482B	1N482B, SMD	BAS 32, LL 4148
43598	FDLL483B	1N483B, SMD	BAS 32, LL 4148
43599	FDLL484B	1N484B, SMD	HSK 83
43600	FDLL485B	1N485B, SMD	HSK 83
43601	FDLL4938	1N4938, SMD	-
43602	FDLL600	FDH 600, SMD	BAS 32, LL 4148
43603	FDLL6099	1N6099, SMD	HSK 83, HSK 122
43604	FDLL625	1N625, SMD	BAS 32, LL 4148



43605	FDLL626	1N626, SMD	BAS 32, LL 4148
43606	FDLL627	1N627, SMD	LL 4148
43607	FDLL628	1N628, SMD	HSK 83
43608	FDLL629	1N629, SMD	HSK 83
43609	FDLL658	1N658, SMD	BAS 32, LL 4148
43610	FDLL659	1N659, SMD	BAS 32, LL 4148
43611	FDLL660	1N660, SMD	LL 4148
43612	FDLL661	1N661, SMD	HSK 83
43613	FDLL666	FDH 666, SMD	BAS 32, LL 4148
43614	FDLL700	FDH 700, SMD	-
43615	FDLL777	FDH 777, SMD	-
43616	FDLL900	FDH 900, SMD	BAS 32, LL 4148
43617	FDLL914..	1N914.., SMD	BAS 32, LL 4148
43618	FDLL916..	1N916.., SMD	BAS 32, LL 4148
43619	FDLL920	1S920, SMD	BAS 45L, HSK 83
43620	FDLL921	1S921, SMD	BAS 45L, HSK 83
43621	FDLL922	1S922, SMD	BAS 45L, HSK 83
43622	FDLL923	1S923, SMD	HSK 83
43623	FDLL999	FDH 999, SMD	BAS 32, LL 4148
43624	FDN600	FDH 600	FDH 600
43625	FDN666	FDH 666	FDH 666
43626	FDR300	250V, <325ns	-
43627	FDR600	75V, <4ns	-
43628	FDR700	30V, <0,7ns	-
43629	FE	BFP 93A	BFP 93A
43630	FE	BFQ 19P	BFQ 19P
43631	FE	2SC3438-E	2SC3438
43632	FE(p,s)	BCV 46	BCV 46
43633	FE0654A...C	HF/S 25V, Idss1..40mA, Up<8V	BF 244A...C, BF 245A...C, 2N5163
43634	FE0655A...C	30V, Idss>3mA, Up<10V	BFS 74...79, BSV 78...80, 2N4856...4861
43635	FE16A...J	50..600V, 16A, <35ns	BYV 34/...
43636	FE16AD...JD	FE 16A...J	FED 16AT...JT
43637	FE16AN...JN	FE 16A...J	FEN 16AT...JT
43638	FE1A...H	50..400V, 1A, <30ns	EGP 10A...G
43639	FE2A...H	50..400V, 2A, <35ns	BYV 27/..., EGP 20A...G
43640	FE30A...J	50..600V, 30A, <35..50ns	BYV 72/..., BYV 74/..., MUR 3005...3060PT
43641	FE30AD...JD	FE 30A..J	-
43642	FE30AN...JN	FE 30A..J	-
43643	FE3819	2N3819, 0,3W	2N3819
43644	FE3A...H	50..400V, 3A, <35ns	BYV 28/..., EGP 30A...G
43645	FE4302...4304	2N4302..4304, 0,3W	2N4302...4303
43646	FE5245...5247	2N5245..5247, 0,36W	2N5245...5247
43647	FE5257...5259	2N5257..5259, 0,31W	2N5257...5259
43648	FE5284...5286	2N5284..5286, 0,31W	2N5284...5286
43649	FE5A...D	50..200V, 5A, <35ns	BYV 61...63, EGP 50A...G

43650	FE6A...H	50..400V, 6A, <35ns	BYV 61...63
43651	FE8A...J	50..600V, 8A, <35ns	BYT 79/..., BYV 29/..., BYR 29/...
43652	FED16AT...JT	FEP 16AT...JT	FE 16AD...JD
43653	FEN16AT...JT	FEP 16AT...JT	FE 16AN...JN
43654	FEN30AP...JP	FEP 30AP...JP	-
43655	FEN30AP...JP	FEP 30AP...JP	-
43656	FEP16AT...JT	50..600V, 16A, <50ns	BYV 34/..., FE 16A...J
43657	FEP30AT...JT	50..600V, 30A, <50ns	BYV 74/..., MUR 3005PT...3060PT
43658	FEP30AT...JT	50..600V, 30A, <50ns	BYV 74/..., MUR 3005PT...3060PT
43659	FER16AT...JT	FES 16AT...JT	-
43660	FER8AT...JT	FES 8AT...JT	-
43661	FES16AT...JT	50..600V, 16A, <35ns	BYR 79/..., BYT 87/..., FE 16A...J
43662	FES1A..G	50..400V, 1A, <50ns	D 1FL20, MURS 120, MURS 160
43663	FES2A..G	50..400V, 2A, <50ns	BYG 22A...D
43664	FES8AT...JT	50..600V, 8A, <35ns	BYR 29/..., BYT 86/..., FE 8A...J
43665	FF	Z1 SMA-51	Z1 SMA-51
43666	FF	BFQ 18A	BFQ 18A
43667	FF(p,s)	BCV 27	BCV 27
43668	FF1001	50V, 1A, <150ns	BY 201/3, BYT 52A, BYV 12, RGP 10A
43669	FF1002	FF 1001, 100V	BY 201/3, BYT 52B, BYV 12, RGP 10B
43670	FF1003	FF 1001, 200V	BY 201/3, BYT 52D, BYV 13, RGP 10D
43671	FF1004	FF 1001, 400V	BY 201/4, BYT 52G, BYV 13, RGP 10G
43672	FF1005	FF 1001, 500V	BY 201/5, BYT 52J, BYV 14, RGP 10J
43673	FF1501	100V, 1,5A, <150..250ns	BYD 73B, BYV 12, BYV 36A, RGP 15B
43674	FF1502	FF 1501, 200V	BYD 73D, BYV 13, BYV 36A, RGP 15D
43675	FF1504	FF 1501, 400V	BYD 73G, BYV 13, BYV 36B, RGP 15G
43676	FF1506	FF 1501, 600V, <250ns	BYD 34J, BYV 14, BYV 36C, RGP 15J
43677	FF1508	FF 1501, 800V, <250ns	BYD 34K, BYV 15, BYV 36D, RGP 15K
43678	FF1510	FF 1501, 1000V, <250ns	BYD 34M, BYV 16, BYV 36E, RGP 15M
43679	FG	Z1 SMA-56	Z1 SMA-56
43680	FG	BFQ 19S	BFQ 19S
43681	FG	BFQ 149	BFQ 149
43682	FG(p,s)	BCV 47	BCV 47
43683	FG2N	300V, 1A	BY 201/3, BYX 55/350, MR 813, RGP 10G
43684	FG40N10L	RFG 40N10	RFG 40N10(LE)
43685	FH	Z1 SMA-62	Z1 SMA-62
43686	FH(s)	BFN 24	BFN 24
43687	FHP	2SC5020-P	2SC5020
43688	FHQ	2SC5020-Q	2SC5020
43689	FHR	2SC5020-R	2SC5020
43690	FI-	3SK186	3SK186
43691	FI-	3SK217	3SK217
43692	FJ	2SK1069	2SK1069
43693	FJ(s)	BFN 26	BFN 26
43694	FJ2501	BDX 34A	BDX 34(A...D)

43695	FJ3	2SK771-3	2SK771
43696	FJ3001	BDX 33A	BDX 33(A...D)
43697	FJ4	2SK771-4	2SK771
43698	FJ5	2SK771-5	2SK771
43699	FK	Z1 SMA-68	Z1 SMA-68
43700	FK	2SB800-FK	2SB800
43701	FK(s)	BFN 25	BFN 25
43702	FKE4F2/...	SKE 4F2/..	
43703	FL	Z1 SMA-75	Z1 SMA-75
43704	FL	2SA1434	2SA1434
43705	FL	2SB800-FL	2SB800
43706	FL(s)	BFN 27	BFN 27
43707	FL005..08	50..800V, 5A	B...C5000
43708	FM	Z1 SMA-82	Z1 SMA-82
43709	FM	BB 804	BB 804
43710	FM	2SB800-FM	2SB800
43711	FMA1(A)	RbRbe22kOhm, 50V, 30mA	-
43712	FMA10A	100mA	-
43713	FMA11A	RbRbe4,7kOhm, 50V, 100mA	-
43714	FMA2(A)	RbRbe47kOhm, 50V, 30mA	-
43715	FMA3(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
43716	FMA4(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
43717	FMA5(A)	100mA	-
43718	FMA6(A)	Rb47kOhm, Rbe-, 50V, 100mA	-
43719	FMA7A	100mA	-
43720	FMA8A	100mA	-
43721	FMA9A	50mA	-
43722	FMC1(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
43723	FMC2(A)	RbRbe22kOhm, 50V, 100mA	-
43724	FMC3(A)	RbRbe10kOhm, 50V, 50mA	-
43725	FMC4A	RbRbe47kOhm, 50V, 100mA	-
43726	FMC5A	RbRbe47kOhm, 50V, 100mA	-
43727	FMC6A	RbRbe100kOhm, 50V, 100mA	-
43728	FMG1(A)	RbRbe22kOhm, 50V, 30mA	-
43729	FMG10A	100mA	-
43730	FMG11A	100mA	-
43731	FMG2(A)	RbRbe47kOhm, 50V, 30mA	-
43732	FMG3(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
43733	FMG4(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
43734	FMG5(A)	100mA	-
43735	FMG6(A)	Rb47kOhm, Rbe-, 50V, 100mA	-
43736	FMG7(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
43737	FMG8(A)	100mA	-
43738	FMG9A	RbRbe10kOhm, 50V, 50mA	-
43739	FMJ1A	RbRbe47kOhm, 50V, 50mA	-

43740	FMMD914	1N914, SMD	MMBD 914, PMBD 914
43741	FMMT-A05..06	MPSA 05..06, SMD	MMBTA 05...06
43742	FMMT-A12..14	MPSA 12..14, SMD	MMBTA 12...13
43743	FMMT-A20	MPSA 20, SMD	MMBTA 20
43744	FMMT-A42..43	MPSA 42..43, SMD	MMBTA 42...43
43745	FMMT-A42R..43R	MPSA 42..43, SMD	-
43746	FMMT-A55..56	MPSA 55..56, SMD	MMBTA 55...56
43747	FMMT-A70	MPSA 70, SMD	MMBTA 70
43748	FMMT-A92..93	MPSA 92..93, SMD	MMBTA 92...93
43749	FMMT-A92R..93R	MPSA 92..93, SMD	-
43750	FMMT2222(A)	2N2222(A), SMD	MMBT 2222(A)
43751	FMMT2222(A)R	2N2222(A), SMD	-
43752	FMMT2369(A)	2N2369(A), SMD	MMBT 2369(A)
43753	FMMT2484	2N2484, SMD	MMBT 2484
43754	FMMT2907(A)	2N2907(A), SMD	MMBT 2907(A)
43755	FMMT2907(A)R	2N2907(A), SMD	-
43756	FMMT3903..3904	2N3903..3904, SMD	MMBT 3903...3904
43757	FMMT3905..3906	2N3905..3906, SMD	MMBT 3905...3906
43758	FMMT4124	2N4124, SMD	MMBT 4124
43759	FMMT4125	2N4125, SMD	MMBT 4125
43760	FMMT5087	2N5087, SMD	MMBT 5087
43761	FMMT5087R	2N5087, SMD	-
43762	FMMT918	2N918, SMD	MMBT 918
43763	FMP18N05	50V, 18A, 75W, <0.10Ohm(10A)	BUZ 21...22, IRF 540...543, 2SK674
43764	FMP18N06	FMP 18N05, 60V	BUZ 21...22, IRF 540...543, 2SK674
43765	FMP20N05	<85mOhm(10A)	BUZ 21...22, IRF 540...543, 2SK674
43766	FMP20N06	FMP 20N05, 60V	BUZ 21...22, IRF 540...543, 2SK674
43767	FMP30N05	50V, 30A, 100W, 0,05Ohm	BUZ 11...12, PRFZ 42, 2SK856
43768	FMP35N05	50V, 35A, 100W, 0,04Ohm	BUZ 11...12, PRFZ 42, 2SK856
43769	FMPS-A05	MPSA 05	MPSA 05
43770	FMPS-A06	MPSA 06	MPSA 06
43771	FMPS-A55	MPSA 55	MPSA 55
43772	FMQ1A	ReRc4700Ohm, 20V, 50mA	-
43773	FMQ2	-/30V, 30+500mA	-
43774	FMS1(A)	50V, 100mA	-
43775	FMS2(A)	50V, 100mA	-
43776	FMS3	120V, 50mA	-
43777	FMS4	120V, 50mA	-
43778	FMW1	50V, 100mA	-
43779	FMW10	30V, 50mA, >600MHz	-
43780	FMW11	30V, 50mA, >600MHz	-
43781	FMW12	50V, 100mA	-
43782	FMW13	30V, 50mA, >900MHz	-
43783	FMW2	50V, 100mA	-
43784	FMW3	120V, 50mA	-

43785	FMW4	120V, 50mA	-
43786	FMW5	50V, 100mA	-
43787	FMW6	30V, 50mA, >600MHz	-
43788	FMW7	20V, 50mA, >1400MHz	-
43789	FMW8	20V, 50mA, >1400MHz	-
43790	FMW9	20V, 50mA, >1400MHz	-
43791	FMY1(A)	50V, 100mA, 140MHz	-
43792	FMY3(A)	50V, 100mA, 140MHz	-
43793	FMY4(A)	50V, 100mA, 140MHz	-
43794	FMY5	120V, 50mA, 140MHz	-
43795	FMY6	40V, 500mA, 200MHz	-
43796	FN	Z1 SMA-91	Z1 SMA-91
43797	FN1A3Q	AN 1A3Q, SMD	DTA 113ZK, UN 2119
43798	FN1A4M	AN 1A4M, SMD	DTA 114EK, RN 2402, UN 2111, 2SA1344
43799	FN1A4P	AN 1A4P, SMD	DTA 114YK, RN 2407, UN 2114, 2SA1563
43800	FN1A4Z	AN 1A4Z, SMD	DTA 114TK, RN 2411, UN 2115, 2SA1496
43801	FN1F4M	AN 1F4M, SMD	DTA 124EK, RN 2403, UN 2112, 2SA1342
43802	FN1F4N	AN 1F4N, SMD	DTA 124XK, KSR 2107, RN 2408
43803	FN1F4Z	AN 1F4Z, SMD	DTA 124TK, KSR 2111, UN 2117, 2SA1589
43804	FN1L3M	AN 1L3M, SMD	DTA 143EK, RN 2401, UN 211L, 2SA1655
43805	FN1L3N	AN 1L3N, SMD	DTA 143XK, KSR 2105, UN 211F, 2SA1653
43806	FN1L3Z	AN 1L3Z, SMD	DTA 143TK, RN 2410, UN 2116, 2SA1510
43807	FN1L4L	AN 1L4L, SMD	DTA 144WK, RN 2409, UN 211E, 2SA1343
43808	FN1L4M	AN 1L4M, SMD	DTA 144EK, RN 2404, UN 2113, 2SA1341
43809	FN1L4Z	AN 1L4Z, SMD	DTA 144TK, KSR 2112, UN 2110, 2SA1508
43810	FO	2SC2716-O	2SC2716
43811	FO	KTC3878-O	KTC 3878
43812	FO	KTA1662-O	KTA 1662
43813	FO	2SA1202-O	2SA1202
43814	FOI	SO 4416	SO 4416
43815	FP	Z1 SMA-100	Z1 SMA-100
43816	FP	SM 6T 68	SM 6T...
43817	FP08C	Igt/Ih50/30mA	T 6417..., T 6410..., 2N5444...5446
43818	FP08D	FP 08C, 300V	T 6417..., T 6410..., 2N5445...5446
43819	FP08E	FP 08C, 400V	T 6417..., T 6410..., 2N5445...5446
43820	FP08F	FP 08C, 500V	T 6417..., T 6410..., 2N5446
43821	FP08G	FP 08C, 600V	T 6417..., T 6410..., 2N5446
43822	FP14N05L	RFP 14N05L	RFP 14N05L
43823	FP14N06L	RFP 14N06L	RFP 14N06L
43824	FP1A3M..L3N	AP 1A3M..L3N, SMD	-
43825	FP23N06L	RFP 23N06LE	RFP 23N06LE
43826	FP3055LE	RFP 3055LE	RFP 3055LE
43827	FP40N10L	RFP 40N10LE	RFP 40N10LE
43828	FP45N03L	RFP 45N03L	RFP 45N03L
43829	FPT6004	BD 902	BD 902

43830	FPT6005	BD 901	BD 901
43831	FQ	2SA1037-FQ	2SA1037
43832	FQ	2SB1610	2SB1610
43833	FQ	Z1 SMA-110	Z1 SMA-110
43834	FQ	2SA1037K-Q	2SA1037K
43835	FQ	2SA1576-Q	2SA1576
43836	FQ	2PA1576Q	2PA1576
43837	FQ	2SA1774-FQ	2SA1774
43838	FQ	2SB1618	2SB1618
43839	FQ	SM 6T 68A	SM 6T...
43840	FQ08C	50/30mA	TXE 99..., SC 260..., T 6411..., T 6410...
43841	FQ08D	FQ 08C, 300V	TXE 99..., SC 260..., T 6411..., T 6410...
43842	FQ08E	FQ 08C, 400V	TXE 99..., SC 260..., T 6411..., T 6410...
43843	FQ08F	FQ 08C, 500V	TXE 99..., SC 260..., T 6411..., T 6410...
43844	FQ08G	FQ 08C, 600V	TXE 99..., SC 260..., T 6411..., T 6410...
43845	FR	2SA1037-FR	2SA1037
43846	FR	2SD2472	2SD2472
43847	FR	Z1 SMA-120	Z1 SMA-120
43848	FR	2SA1774-FR	2SA1774
43849	FR	2SA1576-R	2SA1576
43850	FR	2SA1034-R	2SA1034
43851	FR	2SA1531-R	2SA1531
43852	FR	2SA1037K-R	2SA1037K
43853	FR	2SC2716-R	2SC2716
43854	FR	KTC3878-R	KTC 3878
43855	FR	2SD2482	2SD2482
43856	FR	2PA1576R	2PA1576
43857	FR	2SC4988	2SC4988
43858	FR101	50V, 1A	BY 126...127, BY 226...227, 1N4001...07
43859	FR102	FR 101, 100V	BY 126...127, BY 226...227, 1N4002...07
43860	FR103	FR 101, 200V	BY 126...127, BY 226...227, 1N4003...07
43861	FR104	FR 101, 400V	BY 126...127, BY 226...227, 1N4004...07
43862	FR105	FR 101, 600V	BY 126...127, BY 226...227, 1N4005...07
43863	FR106	FR 101, 800V	BY 127, BY 227, 1N4006...07
43864	FR107	FR 101, 1000V	BY 127, BY 227, 1N4007
43865	FR151	50V, 1.5A	BY 226...227, BY 251...255, 1N5391...99
43866	FR152	FR 151, 100V	BY 226...227, BY 251...255, 1N5392...99
43867	FR153	FR 151, 200V	BY 226...227, BY 251...255, 1N5393...99
43868	FR154	FR 151, 400V	BY 226...227, BY 252...255, 1N5395...99
43869	FR155	FR 151, 600V	BY 226...227, BY 253...255, 1N5397...99
43870	FR156	FR 151, 800V	BY 227, BY 254...255, 1N5398...99
43871	FR157	FR 151, 1000V	BY 227, BY 255, 1N5399
43872	FR1A..M	50..1000V, 0,6A, <500ns	BYG 20G...M, FR 2A...M
43873	FR1L	TFR 1L	TFR 1L...T
43874	FR1N	TFR 1N	TFR 1L...T



43875	FR1Q	TFR 1Q	TFR 1L...T
43876	FR1T	TFR 1T	TFR 1L...T
43877	FR2/-02...-12	200..1200V, 1,1A	BY 126...127, BY 133...135, 1N4003...07
43878	FR2A..M	50..1000V, 1,5A, <500ns	BYG 20G...M, BYG 21K...M
43879	FR2L	TFR 2L	TFR 2L...T
43880	FR2N	TFR 2N	TFR 2L...T
43881	FR2Q	TFR 2Q	TFR 2L...T
43882	FR2T	TFR 2T	TFR 2L...T
43883	FR301	50V, 3A	BY 251...255, BY 396...399, 1N5400...08
43884	FR302	FR 301, 100V	BY 251...255, BY 396...399, 1N5401...08
43885	FR303	FR 301, 200V	BY 251...255, BY 397...399, 1N5402...08
43886	FR304	FR 301, 400V	BY 252...255, BY 398...399, 1N5404...08
43887	FR305	FR 301, 600V	BY 253...255, BY 399, 1N5406...08
43888	FR306	FR 301, 800V	BY 254...255, BY 399, 1N5407...08
43889	FR307	FR 301, 1000V	BY 255, BY 399S, 1N5408
43890	FR3205CC	50V, 32A, <50ns	BYT 30P/200, BYV 72/50, BYW 99P/50
43891	FR3210CC	FR 3205, 100V	BYT 30P/200, BYV 72/100, BYW 99P/100
43892	FR3215CC	FR 3205, 150V	BYT 30P/200, BYV 72/150, BYW 99P/150
43893	FR3220CC	FR 3205, 180V	BYT 30P/200, BYV 72/200, BYW 99P/200
43894	FR34	100V, 0,2A, Uf<1V(0,2A)	BAW 52, BAY 19...21, BAY 45
43895	FR3L	TFR 3L	TFR 3L...T
43896	FR3N	TFR 3N	TFR 3L...T
43897	FR3Q	TFR 3Q	TFR 3L...T
43898	FR3T	TFR 3T	TFR 3L...T
43899	FR4L	TFR 4L	TFR 4L...T
43900	FR4N	TFR 4N	TFR 4L...T
43901	FR4Q	TFR 4Q	TFR 4L...T
43902	FR4T	TFR 4T	TFR 4L...T
43903	FR601	50V, 6A	BY 214/50.../1000, MR 750...760
43904	FR602	FR 601, 100V	BY 214/100.../1000, MR 751...760
43905	FR603	FR 601, 200V	BY 214/200.../1000, MR 752...760
43906	FR604	FR 601, 400V	BY 214/400.../1000, MR 754...760
43907	FR605	FR 601, 600V	BY 214/600.../1000, MR 756...760
43908	FR606	FR 601, 800V	BY 214/800.../1000, MR 758...760
43909	FR607	FR 601, 1000V	BY 214/1000, MR 760
43910	FRM3205CC	50V, 32A, <50ns	BYT 30P/200, BYV 72/50, BYW 99P/50
43911	FRM3210CC	FRM 3205, 100V	BYT 30P/200, BYV 72/100, BYW 99P/100
43912	FRM3215CC	FRM 3205, 150V	BYT 30P/200, BYV 72/150, BYW 99P/150
43913	FRM3220CC	FRM 3205, 180V	BYT 30P/200, BYV 72/200, BYW 99P/200
43914	FRP1005	50V, 10A, <50ns	BYT 79/300, BYV 79/50
43915	FRP1010	FRP 1005, 100V	BYT 79/300, BYV 79/100
43916	FRP1015	FRP 1005, 150V	BYT 79/300, BYV 79/150
43917	FRP1020	FRP 1005, 180V	BYT 79/300, BYV 79/200
43918	FRP1605	50V, 16A, <50ns	BYV 79/50, MUR 1505
43919	FRP1605..1620CC	FRP 1605..1620	BYV 32/..., BYP 22/..., FE 16A...D

43920	FRP1610	FRP 1605, 100V	BYV 79/100, MUR 1510
43921	FRP1615	FRP 1605, 150V	BYV 79/150, MUR 1515
43922	FRP1620	FRP 1605, 180V	BYV 79/200, MUR 1520
43923	FRP2005CC	50V, 20A, <50ns	BYW 51/50, BYP 22-50, BYV 44/300
43924	FRP2010CC	FRP 2005CC, 100V	BYW 51/100, BYP 22-100, BYV 44/300
43925	FRP2015CC	FRP 2005CC, 150V	BYW 51/150, BYP 22-150, BYV 44/300
43926	FRP2020CC	FRP 2005CC, 180V	BYP 22-200, BYV 44/300
43927	FRP805	50V, 8A, <50ns	BYP 21-50, BYT 79/300, BYW 29/50, FE 8A
43928	FRP810	FRP 805, 100V	BYP 21-100, BYT 79/300, BYW 29/100, FE8B
43929	FRP815	FRP 805, 150V	BYP 21-150, BYT 79/300, BYW 29/150, FE8C
43930	FRP820	FRP 805, 180V	BYP 21-200, BYT 79/300, BYW 29/200, FE8D
43931	FRP840	400V, 8A, <75ns	BYT 79/400, BYV 29/400, FE 8G
43932	FRP850	FRP 840, 500V	BYT 79/500, BYV 29/500, FE 8H
43933	FRP860	FRP 840, 600V	BYT 12P/600, FE 8J
43934	FRS1A..M	50..1000V, 1A, <300ns	BYG 20G...M, BYG 21K...M, FR 2A...M
43935	FRS2A..M	50..1000V, 1,5A, <500ns	BYG 20G...M, BYG 21K...M, FR 2A...M
43936	FS	2SB1611	2SB1611
43937	FS	2SA1037-FS	2SA1037
43938	FS	Z1 SMA-130	Z1 SMA-130
43939	FS	2SA1576-S	2SA1576
43940	FS	2SA1531-S	2SA1531
43941	FS	2PA1576S	2PA1576
43942	FS	2SA1763	2SA1763
43943	FS	2SA1774-FS	2SA1774
43944	FS	2SB1619	2SB1619
43945	FS	2SA1034-S	2SA1034
43946	FS	2SA1764	2SA1764
43947	FS	2SA1037K-S	2SA1037K
43948	FS	2SB1519	2SB1519
43949	FS1G..M	400..1000V, 1A, 4µs	BYG 10G...M
43950	FS2A..M	50..1000V, 1,5, 4µs	BYG 10G...M
43951	FSM10B4	Igt/Ih30/20mA	TAG 457-..., BT 162/...
43952	FSM16C2	Igt/Ih50/30mA	MAC 515-..., MAC 525-..., MAC 515A-...
43953	FSM16C4	FSM 16C2, 400V	MAC 515-..., MAC 525-..., MAC 515A-...
43954	FSM16C6	FSM 16C2, 600V	MAC 515-..., MAC 525-..., MAC 515A-...
43955	FSM20C2	FSM 16C2, 20A(Tc74°C)	MAC 525-..., MAC 525A-...
43956	FSM20C4	FSM 16C4, 20A(Tc74°C)	MAC 525-..., MAC 525A-...
43957	FSM30C2	FSM 16C2, 30A(Tc63°C)	MAC 50-..., MAC 50A-..., TAG 740-...
43958	FSM30C4	FSM 16C4, 30A(Tc63°C)	MAC 50-..., MAC 50A-..., TAG 740-...
43959	FSM3B2	Igt/Ih40/20mA	TAG 136..., ZO 410...
43960	FSM3B4	FSM 3B2, 400V	TAG 136..., ZO 410...
43961	FSM6B2	Igt/Ih30/20mA	T 2856..., TAG 426-..., TAG 452-...
43962	FSM6B4	FSM 6B2, 400V	T 2856..., TAG 426-..., TAG 452-...
43963	FST1045	45V, 10A	BYS 24-45, HRW 36, MBR 2060
43964	FST1090	90V, 10A	BYS 24-90, HRW 36, MBR 2090

43965	FST2045	45V, 20A	BYV 43/45, BYV 143/45, MBR 2045
43966	FST2090	90V, 20A	-
43967	FST3045	45V, 30A	BYS 28-45, BYV 73/45, MBR 3045PT
43968	FST3060	60V, 30A	BYS 28-90, MBR 3060PT
43969	FST3090	90V, 30A	BYS 28-90
43970	FST5050	50V, 50A	MBR 6045PT
43971	FST5090	90V, 50A	-
43972	FT	2SD2473	2SD2473
43973	FT	Z1 SMA-150	Z1 SMA-150
43974	FT	2SD2483	2SD2483
43975	FT	2SA1034-T	2SA1034
43976	FT	2SC4146	2SC4146
43977	FT	2SA1531-T	2SA1531
43978	FT034A	>80MHz	2N5542
43979	FT034B	FT 34A, 120V	2N5542
43980	FT034C	150V, 5A, 0,8W, >80MHz	BU 125, BUY 48...49, BUY 80...81
43981	FT034D	FT 34C, 120V	BU 125, BUY 48...49, BUY 80...81
43982	FT0654(A...C)	FE 0654(A..C)	FE 0654(A...C)
43983	FT0655(A...C)	FE 0655(A..C)	FE 0655(A...C)
43984	FT06B	100V, 6A(Tc88°C), Igt <75mA	TAG 260-..., TAG 265-..., T 4700...
43985	FT06C	FT 06B, 200V	TAG 260-..., TAG 265-..., T 4700...
43986	FT06D	FT 06B, 300V	TAG 260-..., TAG 265-..., T 4700...
43987	FT06E	FT 06B, 400V	TAG 260-..., TAG 265-..., T 4700...
43988	FT07C	Igt/Ih50/20mA	TAG 260-..., TAG 265-..., T 4700...
43989	FT07D	FT 07C, 300V	TAG 260-..., TAG 265-..., T 4700...
43990	FT07E	FT 07C, 400V	TAG 260-..., TAG 265-..., T 4700...
43991	FT07F	FT 07C, 500V	TAG 260-..., TAG 265-..., T 4700...
43992	FT07G	FT 07C, 600V	TAG 260-..., TAG 265-..., T 4700...
43993	FT08C	Igt/Ih50/20mA	BS6-...A, TW6N...C, BS8-...A, TW8N...C
43994	FT08D	FT 08C, 300V	BS6-...A, TW6N...C, BS8-...A, TW8N...C
43995	FT08E	FT 08C, 400V	BS6-...A, TW6N...C, BS8-...A, TW8N...C
43996	FT08F	FT 08C, 500V	BS6-...A, TW6N...C, BS8-...A, TW8N...C
43997	FT08G	FT 08C, 600V	BS6-...A, TW6N...C, BS8-...A, TW8N...C
43998	FT107A	30V, 0,05A, 0,26W, B>1200	2SC3112...13, 2SD1010...11, 2SD1512
43999	FT107B	FT 107A, 45V, B>600	2SC3112...13, 2SD1010...11, 2SD1512
44000	FT107C	FT 107A, 60V, B>150	2N2483...2484, 2N3117
44001	FT109	15V, 0,2A, 0,3W, >600MHz	BSS 10...12, BSY 17...18, 2N2369(A)
44002	FT118	20V, 500MHz	BF 173, BF 199, BF 224, BF 311, BF 373
44003	FT1210	2N917	2N917
44004	FT123	300V, 0,1A, 1W, >60MHz	BF 259, BF 659, BFS 89, 2N5058
44005	FT12C	200V, 6A, Igt/Ih75/20mA	MAC 216-..., T 2801..., SC 141..., BS7-...
44006	FT12E	FT 12C, 400V	MAC 216-..., T 2801..., SC 141..., BS7-...
44007	FT1310	5V, <15/-ns	BSS 10...12, BSY 17...18, 2N2368...69
44008	FT1324(B,C)	25V, 0,5A, >640MHz	BFX 55, 2SC2852
44009	FT1341	25V, 0,1A, 0,36W, <65/-ns	BSW 41, BSY 62...63, 2N706A, 2N708

44010	FT17	>1GHz, PQ>35mW(1GHz)	BF 357, BF 378...379, BFW 30, BFX 59
44011	FT1702	12V, 0,1A, 0,3W, <60/75ns	BSV 21, BSW 25, BSW 37, BSX 36
44012	FT1724	2N1724	2N1724
44013	FT1725	2N1725	2N1725
44014	FT1746	35V, 0,36W, 150MHz	BC 213, BC 258, BC 308, BC 558
44015	FT1869...1874	2N1869..1874	2N1869...1874
44016	FT1881...1885	2N1881..1885	2N1881...1885
44017	FT1M,N,P	140..600V, 0,3A, <3μs	BA 157...159, BY 204/..., BY 208/...
44018	FT2009...2013	2N2009..2013	2N2009...2013
44019	FT2955	BD 204	BD 204
44020	FT3055	BD 203	BD 203
44021	FT3352	hFE>50, hFC>20	-
44022	FT3553	hFE>50, hFC>20	-
44023	FT3567	2N3567, 0,5W	2N3567
44024	FT3568	2N3568, 0,5W	2N3568
44025	FT3569	2N3569, 0,5W	2N3569
44026	FT3641	2N3641, 0,45W	2N3641
44027	FT3642	2N3642, 0,45W	2N3642
44028	FT3643	2N3643, 0,45W	2N3643
44029	FT3644	2N3644, 0,45W	2N3644
44030	FT3645	2N3645, 0,45W	2N3645
44031	FT3722	2N3722, 0,5W	2N3722
44032	FT3723	2N3723	2N3723
44033	FT3820	2N3820, 0,2W	2N3820
44034	FT3883	hFE>50, hFC>20	-
44035	FT3883	hFE>50, hFC>20	-
44036	FT40	1,4GHz,	-
44037	FT400A,B	120MHz	2N6186...6189
44038	FT401	-/400V, 2A, 100W, >2MHz	BUX 46, 2SC3091, 2SC3099, 2SC3155
44039	FT401	-/400V, 2A, 100W, >2MHz	BUX 46, 2SC3091, 2SC3099, 2SC3155
44040	FT402	FT 401, 3,5A	BUX 46, 2SC3091, 2SC3099, 2SC3155
44041	FT402	FT 401, 3,5A	BUX 46, 2SC3091, 2SC3099, 2SC3155
44042	FT410	-/200V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44043	FT410	-/200V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44044	FT411	FT 410, -/300V	BUX 47, 2SC3090, 2SC3092, 2SD811
44045	FT411	FT 410, -/300V	BUX 47, 2SC3090, 2SC3092, 2SD811
44046	FT413	-/400V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44047	FT413	-/400V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44048	FT423	-/400V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44049	FT423	-/400V, 7,5A, 100W, 5MHz	BUX 47, 2SC3090, 2SC3092, 2SD811
44050	FT430	-/400V, 10A, 100W, B15..45	BUS 12, BUW 26, BUW 12, BUW 35...36
44051	FT430	-/400V, 10A, 100W, B15..45	BUS 12, BUW 26, BUW 12, BUW 35...36
44052	FT431	FT 430, B15..35	BUS 12, BUW 26, BUW 12, BUW 35...36
44053	FT431	FT 430, B15..35	BUS 12, BUW 26, BUW 12, BUW 35...36
44054	FT4354...4356	2N4354..4356, 0,5W	2N4354...4356

44055	FT45	>425MHz	BF 173, BF 199, BF 224, BF 311, BF 373
44056	FT5040...5041	2N5040..5041, 0,5W	2N5040...5041
44057	FT5415	2N5415, 0,5W	2N5415
44058	FT6045	30V, 17A, <65mOhm(10A)	2SK1115, 2SK1287, 2SK1910, 2SK2334
44059	FT6046	30V, 45A, <26mOhm(20A)	2SK1542, 2SK1911
44060	FT6240	200V, 5A, 45W, <0,8Ohm(3A)	IRF 620, 2SK924, 2SK1391, 2SK1921
44061	FT6241	200V, 8A, 65W, <45mOhm(5A)	BUZ 30, BUZ 73, IRF 630, 2SK1319
44062	FT6540	500V, 4A, 70W, <2,2Ohm(2A)	BUZ 41A...42, IRF 830, 2SK893, 2SK1246
44063	FT6840	800V, 2A, 70W, <9Ohm(1A)	BUZ 81, 2SK1457, 2SK1501, 2SK1643
44064	FT703	40V, 0,5A, Up<0,6V, 66/-ns	-
44065	FT704	25V, 20mA, Up<0,6V, 150/-ns	-
44066	FT709	2N709	2N709
44067	FT7207A	>70MHz	2N5284...5285
44068	FT7207B	FT 7207A, 100V	2N5002, 2N5004, 2N5284...5285
44069	FTSO706..6571	2N706..2N6571, SMD	-
44070	FTSOA05..51	MPSA 05..MPSA 51, SMD	-
44071	FU	Z1 SMA-160	Z1 SMA-160
44072	FU12B	100V, 3A, Igt/Ih30/20mA	TAG 230-..., TAG 231-..., TAG 220-...
44073	FU12C	FU 12B, 200V	TAG 230-..., TAG 231-..., TAG 220-...
44074	FU12D	FU 12B, 300V	TAG 230-..., TAG 231-..., TAG 220-...
44075	FU12E	FU 12B, 400V	TAG 230-..., TAG 231-..., TAG 220-...
44076	FU1M,N,P	140..600V, 0,2A, <400ns	BA 157...159, BY 204/..., BY 208/...
44077	FUF5400	50V, 3A, <50ns	BYV 28/50, EGP 30A, FE 3A
44078	FUF5401	FUF 5400, 100V	BYV 28/100, EGP 30B, FE 3B
44079	FUF5402	FUF 5400, 200V	BYV 28/200, EGP 30D, FE 3D
44080	FUF5404	FUF 5400, 400V	EGP 30G, FE 3H
44081	FUF5406	FUF 5400, 600V	BYW 178
44082	FUF5407	FUF 5400, 800V	BYW 178
44083	FV	Z1 SMA-180	Z1 SMA-180
44084	FV	1SV250	1SV250
44085	FV	1SV248	1SV248
44086	FW	Z1 SMA-200	Z1 SMA-200
44087	FX	2SB1571-FX	2SB1571
44088	FX	SM 6T 100	SM 6T...
44089	FX107(A...C)	FT 107(A..C)	FT 107(A...C)
44090	FX2368...2369(A)	2N2368..2369(A), 0,25W	2N2368...2369(A)
44091	FX2483...2484	2N2483..2484, 0,25W	2N2483...2484
44092	FX2894(A)	2N2894(A), 0,25W	2N2894(A)
44093	FX3299...3300	2N3299..3300, 0,25W	2N3299...3300
44094	FX3502...3503	2N3502..3503, 0,25W	2N3502...3503
44095	FX3724...3725	2N3724..3725, 0,25W	2N3724...3725
44096	FX3962...3965	2N3962..3965, 0,25W	2N3962...3965
44097	FX4046...4047	2N4046..4047, 0,25W	2N4046...4047
44098	FX4207	2N4207, 0,25W	2N4207
44099	FX4960	2N4960, 0,25W	2N4960

44100	FX914	2N914, 0,25W	2N914
44101	FX918	2N918, 0,25W	2N918
44102	FY	BSV 65RA	BSV 65RA
44103	FY	KTC3878-Y	KTC 3878
44104	FY	2SC2761-Y	2SC2761
44105	FY	2SC3661	2SC3661
44106	FY	SM 6T 100A	SM 6T...
44107	FY	2SA1202-Y	2SA1202
44108	FY	2SK1698	2SK1698
44109	FY	2SB1571-FY	2SB1571
44110	FY	KTA1662-Y	KTA 1662
44111	FZ	BSV 65RB	BSV 65RB
44112	FZ	2SB1571-FZ	2SB1571
44113	G	S 5566G	S 5566G
44114	G088	BZ 102/0V7	BZ 102/0V7
44115	G1	FRS 2A	FRS 2A
44116	G1	MMBT 5551	MMBT 5551
44117	G1	D70Y1.5T1	D70Y1.5T1
44118	G1(p)	BFS 20	BFS 20
44119	G11	2SK1133	2SK1133
44120	G13	2SK1580	2SK1580
44121	G14	2SK1581	2SK1581
44122	G16	2SK1590	2SK1590
44123	G17	2SK1589	2SK1589
44124	G18	2SK1591	2SK1591
44125	G18	2SK1582	2SK1582
44126	G19	2SK1657	2SK1657
44127	G1A...M	50..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
44128	G2	FRS 2B	FRS 2B
44129	G2	BF 599	BF 599
44130	G2	BF 550	BF 550
44131	G20	2SK1658	2SK1658
44132	G21	2SK1958	2SK1958
44133	G22	2SK2090	2SK2090
44134	G23	2SK2158	2SK2158
44135	G2A...M	50..1000V, 2A	BY 251...255, BY 259/..., GP 20A...M
44136	G2N2955	BD 318	BD 318
44137	G2N2955	BD 318	BD 318
44138	G2N3055	BD 317	BD 317
44139	G2N3055	BD 317	BD 317
44140	G3	FRS 2D	FRS 2D
44141	G3	1SS196	1SS196
44142	G3	2SA1257-3	2SA1257
44143	G3	2SC2107-G3	2SC2107
44144	G3	KDS 196	KDS 196



44145	G3	BF 536	BF 536
44146	G3A...M	50..1000V, 3A	BY 251...255, GP 30A...M, 1N5400...08
44147	G4	FRS 2G	FRS 2G
44148	G4	2SC2107-G4	2SC2107
44149	G4	2SA1257-4	2SA1257
44150	G4	BFS 20R	BFS 20R
44151	G4A...M	50..1000V, 3A	BY 251...255, GP 30A...M, 1N5400...08
44152	G5	FRS 2J	FRS 2J
44153	G5	BF 550R	BF 550R
44154	G5	2SA1257-5	2SA1257
44155	G5	2SC2107-G5	2SC2107
44156	G5/2	OA 70	OA 70
44157	G5/61	AA 119	AA 119
44158	G580	20V, 0,2A	AA 139, 1N270
44159	G6	FRS 2K	FRS 2K
44160	G6	2SC2107-G6	2SC2107
44161	G6	BF 569	BF 569
44162	G6004	BD 700	BD 700
44163	G6004	BD 700	BD 700
44164	G6005	BD 699	BD 699
44165	G6005	BD 699	BD 699
44166	G61	BF 569R	BF 569R
44167	G7	FRS 2M	FRS 2M
44168	G7	BF 579	BF 579
44169	G8	BF 660	BF 660
44170	G81	BF 660R	BF 660R
44171	G9	BF 767	BF 767
44172	GA	μPA600T	æPA600T
44173	GA	S 416 T	S 416 T
44174	GA	BFR 35	BFR 35
44175	GA	2SD1463-GA	2SD1463
44176	GA	BAW 78A	BAW 78A
44177	GA1	2SA1871-GA1	2SA1871
44178	GA100	26V, 0,02A	AA 132...134, 1N34, 1N54, 1N60
44179	GA101	50V, 0,015A	AA 132...134, 1N34, 1N54, 1N60
44180	GA102	60V, 0,012A	AA 132...134, 1N34, 1N54, 1N60
44181	GA103	90V, 0,01A	AA 117...118, AA 132...133
44182	GA104	115V, 0,01A	AA 117...118, AA 132...133
44183	GA105	26V, 0,02A	AA 132...134, 1N34, 1N54, 1N60
44184	GA106	35V, 0,03A, 500ns	AAZ 49, AAZ 15, AAZ 17, 1N276
44185	GA107	90V, 0,15A, 500ns	AAZ 15
44186	GA108	90V, 0,02A	AA 117...118, AA 132...133
44187	GA1A3Q	AA 1A3Q, SMD	DTC 113ZU
44188	GA1A4M	AA 1A4M, SMD	DTC 114EU, 2SC4398
44189	GA1A4P	AA 1A4P, SMD	DTC 114YU

44190	GA1A4Z	AA 1A4Z, SMD	DTC 114TU
44191	GA1F4M	AA 1F4M, SMD	DTC 124EU, 2SC4397
44192	GA1F4N	AA 1F4N, SMD	DTC 124XU
44193	GA1F4Z	AA 1F4Z, SMD	DTC 124TU
44194	GA1L3M	AA 1L3M, SMD	DTC 143EU
44195	GA1L3N	AA 1L3N, SMD	DTC 143XU
44196	GA1L3Z	AA 1L3Z, SMD	DTC 143TU
44197	GA1L4L	AA 1L4L, SMD	DTC 144WU
44198	GA1L4M	AA 1L4M, SMD	DTC 144EU, 2SC4396
44199	GA1L4Z	AA 1L4Z, SMD	DTC 144TU
44200	GA2	2SA1871-GA2	2SA1871
44201	GA3	2SA1871-GA3	2SA1871
44202	GAY60	20V, 0,075A	AA 132...134, 1N34, 1N54, 1N60
44203	GAY61	20V, 0,1A	AA 135...136, AA 139
44204	GAY62	20V, 0,1A	AA 135...136, AA 139
44205	GAY63	40V, 0,1A	AA 136, 1N270
44206	GAY64	80V, 0,075A	1N270
44207	GAZ14	25V, 0,02A, 500ns	AAZ 49, AAZ 15, AAZ 17, 1N276
44208	GAZ15	25V, 0,02A	AA 132...134, 1N34, 1N54, 1N60
44209	GAZ16	GAZ 14	GAZ 14
44210	GAZ17	GAZ 15	GAZ 15
44211	GB	BFR 35A	BFR 35A
44212	GB	BAW 78B	BAW 78B
44213	GB	2SD1463-GB	2SD1463
44214	GB1	2SB1578-GB1	2SA1578
44215	GB2	2SB1578-GB2	2SA1578
44216	GB3	2SB1578-GB3	2SA1578
44217	GBC107	BC 237	BC 237
44218	GBC108	BC 238	BC 238
44219	GBC109	BC 239	BC 239
44220	GBD179	BD 179	BD 179
44221	GBD189	BD 189	BD 189
44222	GBD190	BD 190	BD 190
44223	GBD266	BD 700	BD 700
44224	GBD266	BD 700	BD 700
44225	GBD267	BD 699	BD 699
44226	GBD267	BD 699	BD 699
44227	GBD645	BD 699	BD 699
44228	GBD645	BD 699	BD 699
44229	GBD646	BD 700	BD 700
44230	GBD646	BD 700	BD 700
44231	GC	U 1GC44	U 1GC44
44232	GC	2SC4264	2SC4264
44233	GC	2SC2734	2SC2734
44234	GC	BAW 78C	BAW 78C

44235	GC100	15V, 15mA, 0,03W	AC 122, AC 125...126, AC 151
44236	GC101	15V, 15mA, 0,03W	AC 122, AC 125...126, AC 151
44237	GC102	15V, 50mA	AC 122, AC 125...126, AC 151
44238	GC103	15V, 15mA	AC 122, AC 125...126, AC 151
44239	GC104	GC 103	AC 151r, ACY 32
44240	GC111	80V, 0,125A, 0,07W	ACY 39, 2N2042...2043
44241	GC112	80V, 0,125A, 0,07W	ACY 39, 2N2042...2043
44242	GC115	20V, 0,15A, 0,07W	AC 122, AC 125...126, AC 151
44243	GC116	20V, 0,15A, 0,07W	AC 122, AC 125...126, AC 151
44244	GC117	GC 116	AC 151r, ACY 32
44245	GC118	GC 116	AC 151r, ACY 32
44246	GC120	20V, 0,15A, 0,07W	AC 128, AC 152...153, AC 188
44247	GC121	20V, 0,15A, 0,07W	AC 128, AC 152...153, AC 188
44248	GC122	30V, 0,15A, 0,07W	AC 128, AC 152...153, AC 188
44249	GC123	GC 122, 60V	ACY 24, ASY 48, ASY 77
44250	g]	BC 181	BC 181
44251	GC189[Grundig]	BC 238	BC 238
44252	GC195[Grundig]	BC 517	BC 517
44253	GC196[Grundig]	BC 337	BC 337
44254	GC197[Grundig]	BC 327	BC 327
44255	GC214[Grundig]	BC 214	BC 214
44256	GC214[Grundig]	BC 214	
44257	GC216	20V, 0,1A, 0,075W	AC 122, AC 125...126, AC 151
44258	GC217	20V, 0,1A, 0,075W	AC 122, AC 125...126, AC 151
44259	GC221	20V, 0,1A, 0,075W	AC 122, AC 125...126, AC 151
44260	GC223	GC 221, 60V	ACY 24, ASY 48, ASY 77
44261	]	BC 337	BC 337
44262	GC237[Grundig]	BC 237	BC 237
44263	GC238[Grundig]	BC 238	BC 238
44264	GC239[Grundig]	BC 239	BC 239
44265	GC269[Grundig]	BC 328	BC 328
44266	GC300	20V, 0,5A, 0,6W	AC 128, AC 152...153, AC 188
44267	GC301	32V, 0,5A	AC 128, AC 153, AC 188
44268	GC307[Grundig]	BC 307	BC 307
44269	GC308[Grundig]	BC 308	BC 308
44270	GC309[Grundig]	BC 309	BC 309
44271	GC371[Grundig]	BC 338	BC 338
44272	GC372[Grundig]	BC 328	BC 328
44273	GC373[Fairch.]	BC 368	BC 368
44274	GC374[Fairch.]	BC 369	BC 369
44275	GC500	24V, 0,3A, 0,55W	AC 128, AC 152...153, AC 188
44276	GC501	24V, 0,3A, 0,55W	AC 128, AC 152...153, AC 188
44277	GC502	32V, 0,3A, 0,55W	AC 128, AC 152...153, AC 188
44278	GC503	7V, 5mA, 0,01W	OC 57...60
44279	GC504	7V, 5mA, 0,01W	OC 57...60

44280	GC505	7V, 5mA, 0,01W	OC 57...60
44281	GC506	7V, 5mA, 0,01W	OC 57...60
44282	GC507	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44283	GC508	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44284	GC509	60V, 0,125A, 0,125W	ACY 24, ASY 48, ASY 77
44285	GC510	32V, 1A, 0,2W	AC 128, AC 153, AC 188
44286	GC510K	GC 510, 0,3W	AC 128K, AC 153K, AC 188K
44287	GC511	25V, 1A, 0,2W	AC 128, AC 153, AC 188
44288	GC511K	GC 511, 0,3W	AC 128K, AC 153K, AC 188K
44289	GC512	25V, 1A, 0,2W	AC 128, AC 153, AC 188
44290	GC512K	GC 512, 0,3W	AC 128K, AC 153K, AC 188K
44291	GC515	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44292	GC516	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44293	GC517	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44294	GC518	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44295	GC519	32V, 0,125A, 0,125W	AC 122, AC 125...126, AC 151
44296	GC520	32V, 1A, 0,2W	AC 176, AC 187
44297	GC520K	GC 520, 0,3W	AC 176K, AC 187K
44298	GC521	25V, 1A, 0,2W	AC 176, AC 187
44299	GC521K	GC 521, 0,3W	AC 176K, AC 187K
44300	GC522	20V, 1A, 0,2W	AC 176, AC 187
44301	GC522K	GC 522, 0,3W	AC 176K, AC 187K
44302	GC525	15V, 0,125A, 0,125W	AC 127, AC 176, AC 187
44303	GC526	32V, 0,125A, 0,125W	AC 127, AC 176, AC 187
44304	GC527	32V, 0,125A, 0,125W	AC 127, AC 176, AC 187
44305	GCN53	30V, 0,25A, 0,125W	AC 127, AC 176, AC 187
44306	GCN54	48V, 0,25A, 0,125W	-
44307	GCN55	32V, 0,125A, 0,125W	AC 128, AC 152...153, AC 188
44308	GCN56	60V, 0,125A, 0,125W	ACY 24, ASY 48, ASY 77
44309	GD	Z2 SMB-7V5	Z2 SMB-7V5
44310	GD	BAW 78D	BAW 78D
44311	GD100	20V, 1,3A, 2W(Tc45°)	AD 162
44312	GD110	20V, 1,3A, 2W(Tc45°)	AD 162
44313	GD114[Grundig]	BD 246B	BD 246B
44314	GD115[Grundig]	BD 245B	BD 245B
44315	GD120	33V, 1,3A, 2W(Tc45°)	AD 162
44316	GD125	66V, 1,3A, 2W(Tc45°)	-
44317	GD130	66V, 1,3A, 2W(Tc45°)	-
44318	GD133[Grundig]	BD 140	BD 140
44319	GD142[Grundig]	2N3055	2N3055
44320	GD142[Grundig]	2N3055	2N3055
44321	GD150	20V, 3A, 5,3W	AD 162, 2SB474
44322	GD151[Grundig]	BD 433	BD 433
44323	GD152[Grundig]	BD 434	BD 434
44324	GD160(A...C)	20V, 3A, 5,3W	AD 162, 2SB474

44325	GD170(A...C)	GD 160, 33V	AD 162, 2SB474
44326	GD175(A...C)	GD 160, 50V	-
44327	GD180(A...C)	GD 160, 66V	-
44328	GD183[Grundig]	BD 136	BD 136
44329	GD190	30V, 1,5A	AD 162
44330	GD191	40V, 1,5A	AD 162
44331	GD192	50V, 1,5A	-
44332	GD200	30V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44333	GD200	30V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44334	GD203[Grundig]	BD 243B	BD 243B
44335	GD204[Grundig]	BD 244B	BD 244B
44336	GD207[Grundig]	BD 243B	BD 243B
44337	GD210	60V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44338	GD210	60V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44339	GD220	80V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44340	GD220	80V, 6A, 12W(Tc50°)	AL 102...103, AUY 22(A), AUY 28
44341	GD240	30V, 3A, 10W	AD 162, 2SB474
44342	GD241	40V, 3A, 10W	AD 162, 2SB474
44343	]	BD 241A,B	BD 241A,B
44344	GD242	50V, 3A, 10W	-
44345	GD243	65V, 3A, 10W	-
44346	GD243[Grundig]	BD 243	BD 243
44347	GD244	75V, 3A, 10W	-
44348	GD340[Grundig]	BD 438	BD 438
44349	GD341[Grundig]	BD 437	BD 437
44350	GD361[Grundig]	BD 433	BD 433
44351	GD362[Grundig]	BD 434	BD 434
44352	GD363[Grundig]	BD 433	BD 433
44353	GD364[Grundig]	BD 434	BD 434
44354	GD384[Grundig]	BD 525	BD 525
44355	GD607	32V, 1A, 4W(Tc60°)	AD 161
44356	GD608	25V, 1A, 4W(Tc60°)	AD 161
44357	GD609	20V, 1A, 4W(Tc60°)	AD 161
44358	GD617	32V, 1A, 4W(Tc60°)	AD 162
44359	GD618	25V, 1A, 4W(Tc60°)	AD 162
44360	GD619	20V, 1A, 4W(Tc60°)	AD 162
44361	GE	Z2 SMB-6V8	Z2 SMB-6V8
44362	GE	BFR 35AP	BFR 35AP
44363	GE	2SA1455K-E	2SA1455K
44364	GE	BAW 79A	BAW 79A
44365	GE10000..10009	MJ 10000..10009	MJ 10000...10009
44366	GE10000..10009	MJ 10000..10009	MJ 10000...10009
44367	GE1001	50V, 1A, <35ns	BYV 26B, EGP 10A, FE 1A
44368	GE10015..10016	MJ 10015..10016	MJ 10015...10016
44369	GE10015..10016	MJ 10015..10016	MJ 10015...10016

44370	GE1002	GE 1001, 100V	BYV 26B, EGP 10B, FE 1B
44371	GE10020..10023	MJ 10020..10023	MJ 10020...10023
44372	GE10020..10023	MJ 10020..10023	MJ 10020...10023
44373	GE1003	GE 1001, 150V	BYV 26B, EGP 10C, FE 1C
44374	GE1004	GE 1001, 200V	BYV 26B, EGP 10D, FE 1D
44375	GE1101	50V, 2,5A, <35ns	BYV 28/50, EGP 30A, FE 3A
44376	GE1102	GE 1101, 100V	BYV 28/100, EGP 30B, FE 3B
44377	GE1103	GE 1101, 150V	BYV 28/150, EGP 30C, FE 3C
44378	GE1104	GE 1101, 200V	BYV 28/200, EGP 30D, FE 3D
44379	GE1301	50V, 6A, <35ns	BYV 61, FE 6A
44380	GE1302	GE1301, 100V	BYV 62, FE 6B
44381	GE1303	GE1301, 150V	BYV 63, FE 6C
44382	GE1304	GE1301, 200V	FE 6D
44383	P	MJ 13070..13071, 100W	BUW 11(A), BU 131(A), BUV 82...83
44384	P	MJ 13080..13081, 110W	BUW 12(A), BU 132(A), BUP 22B...C
44385	T	MJ 13080..13081, 90W	BUT 12(A), BUT 54(A), BUT 56(A)
44386	P	MJ 13100..13101, 125W	BUX 98(A)P, 2SC3988
44387	GE3055P	80V, 10A, 70W	BD 245B...F, BD 545B...D, 2SD1187
44388	GE5060	400/350V, 20A, 125W, B>100	BUT 13, MJ 10000...01, MJ 10004...05
44389	GE5060	400/350V, 20A, 125W, B>100	BUT 13, MJ 10000...01, MJ 10004...05
44390	GE5061	GE 5060, 450/400V	BUT 13, MJ 10000...01, MJ 10004...05
44391	GE5061	GE 5060, 450/400V	BUT 13, MJ 10000...01, MJ 10004...05
44392	GE5062	GE 5060, 500/450V	BUT 13, MJ 10001, MJ 10005, MJ 10008...09
44393	GE5062	GE 5060, 500/450V	BUT 13, MJ 10001, MJ 10005, MJ 10008...09
44394	GE6060	GE 5060	MJ 10004...5, MJ 10008...09
44395	GE6060	GE 5060	MJ 10004...5, MJ 10008...09
44396	GE6061	GE 5061	MJ 10004...5, MJ 10008...09
44397	GE6061	GE 5061	MJ 10004...5, MJ 10008...09
44398	GE6062	GE 5062	MJ 10005, MJ 10008...09
44399	GE6062	GE 5062	MJ 10005, MJ 10008...09
44400	GE6251	450/400V, 10A, 125W	MJ 10006...07, MJ 10013...14
44401	GE6251	450/400V, 10A, 125W	MJ 10006...07, MJ 10013...14
44402	GE6252	GE 6251, 500/450V	MJ 10007, MJ 10013...14
44403	GE6252	GE 6251, 500/450V	MJ 10007, MJ 10013...14
44404	GE6253	GE 6251, 550/500V	MJ 10013...14
44405	GE6253	GE 6251, 550/500V	MJ 10013...14
44406	GER4001..4007	1N4001..4007	1N4001...4007
44407	GES2218..2219(A)	2N2218..2219(A), 0,625W	2N2218...2219(A)
44408	GES2221..2222(A)	2N2221..2222(A), 0,36W	2N2221...2222(A)
44409	GES2483	2N2483, 0,36W	2N2483
44410	GES2646	2N2646	2N2646
44411	GES2647	2N2647	2N2647
44412	GES2904..2905(A)	2N2904..2905(A), 0,6W	2N2904...2905(A)
44413	GES2906..2907(A)	2N2906..2907(A), 0,36W	2N2906...2907(A)
44414	GES3053	2N3053, 0,625W	BC 337A, BC 637, BC 639, 2SD1616



44415	GES3414..3417	2N3414..3417, 0,625W	2N3414...3417
44416	GES3565..3569	2N3565..3569, 0,625W	2N3565...3569
44417	GES4121..4122	2N4121..4122, 0,2W	2N4121...4122
44418	GES4248	2N4248, 0,4W	2N4248
44419	GES4891..4894	2N4891..4894	2N4891...4894
44420	GES5305..5308(A)	2N5305..5308(A), 0,9W	2N5305...5308(A)
44421	GES5368..5375	2N5368..5375, 0,36W	2N5368...5375
44422	GES5401	2N5401	2N5401
44423	GES5447..5451	2N5447..5451, 0,36W	2N5447...5451
44424	GES5551	2N5551	2N5551
44425	GES5810..5823	2N5810..5823, 0,5W	2N5810...5823
44426	GES5824..5828(A)	2N5824..5828(A), 0,36W	2N5824...5828(A)
44427	GES6000..6007	2N6000..6007, 0,4W	2N6000...6007
44428	GES6010..6017	2N6010..6017, 0,5W	2N6010...6017
44429	GES6027	2N6027	2N6027
44430	GES6028	2N6028	2N6028
44431	GES6218..6221	2N6218..6221, 0,5W	2N6218...6221
44432	GES6222	2N6222, 0,36W	2N6222
44433	GES6224	2N6224, 0,36W	2N6224
44434	GES6426..6427	2N6426..6427, 0,625W	2N6426...6427
44435	GES6560..6563	2N6560..6563, 0,625W	2N6560...6563
44436	GES92	40V, 0,4A, 0,625W, 100MHz	BC 337, BC 635, 2SC3377, 2SC3939
44437	GES929..930	2N929..930, 0,36W	2N929...930
44438	GES93	40V, 0,4A, 0,625W, 100MHz	BC 327, BC 636, 2SB910, 2SD1116
44439	GES97	60V, 0,1A, 0,36W, 100MHz	BC 174, BC 546, 2SC2240, 2SC2459
44440	GES98	80V, 0,1A, 0,36W, 100MHz	BC 546, 2SC2240, 2SC2459, 2SC3378
44441	GET2221(A)	2N2221(A), 0,36W	2N2221(A)
44442	GET2222(A)	2N2222(A), 0,36W	2N2222(A)
44443	GET2369	2N2369, 0,36W	2N2369
44444	GET2483	2N2483, 0,36W	2N2483
44445	GET2484	2N2484, 0,36W	2N2484
44446	GET2904...2907	2N2904..2907, 0,36W	2N2904...2907
44447	GET3013...3014	2N3013..3014, 0,36W	2N3013...3014
44448	GET3562...3563	2N3562..3563, 0,25W	2N3562...3563
44449	GET3638(A)	2N3638(A), 0,25W	2N3638(A)
44450	GET3646	2N3646, 0,36W	2N3646
44451	GET3903...3906	2N3903..3906, 0,31W	2N3903...3906
44452	GET4870	2N4870	2N4870
44453	GET4871	2N4871	2N4871
44454	)	2N5305..5308(A), 0,4W	2N5305...5308(A)
44455	GET706	2N706, 0,36W	2N706
44456	GET708	2N708, 0,36W	2N708
44457	GET914	2N914, 0,36W	2N914
44458	GET929	2N929, 0,36W	2N929
44459	GET930	2N930, 0,36W	2N930

44460	GF	Z2 SMB-8V2	Z2 SMB-8V2
44461	GF	BFN 22	BFN 22
44462	GF	BFR 92P	BFR 92P
44463	GF	BAW 79B	BAW 79B
44464	GF100		AF 127, AF 200, AF 139, AF 239(S)
44465	GF105		AF 126, AF 200, AF 139, AF 239(S)
44466	GF108		AF 126, AF 200, AF 139, AF 239(S)
44467	GF120	30MHz	AF 126, AF 200, AF 139, AF 239(S)
44468	GF121	50MHz	AF 126, AF 200, AF 139, AF 239(S)
44469	GF122	50MHz	AF 126, AF 200, AF 139, AF 239(S)
44470	GF125	60MHz	AF 125...126, AF 200, AF 239(S)
44471	GF126		AF 125...126, AF 200, AF 239(S)
44472	GF127	75MHz	AF 125, AF 200, AF 139, AF 239(S)
44473	GF128	100MHz	AF 124...125, AF 200, AF 239(S)
44474	GF129	75MHz	AF 124...125, AF 200, AF 239(S)
44475	GF130		AF 125...126, AF 200, AF 239(S)
44476	GF131	85MHz	AF 124...125, AF 200, AF 239(S)
44477	GF132	85MHz	AF 124, AF 200, AF 139, AF 239(S)
44478	GF134	180MHz	AF 106, AF 109R, AF 239(S), AF 306
44479	GF135	150MHz	AF 106, AF 109R, AF 239(S), AF 306
44480	GF136	150MHz	AF 106, AF 109R, AF 239(S), AF 306
44481	GF137	180MHz	AF 106, AF 109R, AF 239(S), AF 306
44482	GF138	180MHz	AF 106, AF 109R, AF 239(S), AF 306
44483	GF139		AF 106, AF 109R, AF 200, AF 239(S)
44484	GF140	300MHz	AF 139, AF 239(S)
44485	GF141	300MHz	AF 139, AF 239(S)
44486	GF142	300MHz	AF 139, AF 239(S)
44487	GF143	300MHz	AF 139, AF 239(S)
44488	GF145	>250MHz	AF 139, AF 239(S)
44489	GF146	>600MHz	AF 139, AF 239(S)
44490	GF147	>600MHz	AF 139, AF 239(S)
44491	GF180		AF 106, AF 109R, AF 200, AF 306
44492	GF181	100MHz	AF 106, AF 109R, AF 200, AF 306
44493	GF268	BF 245	BF 245
44494	GF501	300MHz	AF 139, AF 239(S)
44495	GF502	300MHz	AF 139, AF 239(S)
44496	GF503	300MHz	AF 139, AF 239(S)
44497	GF504	300MHz	AF 139, AF 239(S)
44498	GF505	170MHz	AF 106, AF 109R, AF 239(S), AF 306
44499	GF506	170MHz	AF 106, AF 109R, AF 239(S), AF 306
44500	GF507	250MHz	AF 106, AF 109R, AF 239(S), AF 306
44501	GF515	60MHz	AF 127, AF 200, AF 139, AF 239(S)
44502	GF516	60MHz	AF 127, AF 200, AF 139, AF 239(S)
44503	GF517	50MHz	AF 127, AF 200, AF 139, AF 239(S)
44504	GF522	BF 245	BF 245

44505	GFT20A6	100/200mA	-
44506	GFT20B12	GFT 20A6, 1200V, 7A(Tc60°C)	-
44507	GFT50A6	300/600mA	-
44508	GFT50A6	300/600mA	-
44509	GFT50B12	18A(Tc60°C)	-
44510	GFT50B12	18A(Tc60°C)	-
44511	GG	Z2 SMB-9V1	Z2 SMB-9V1
44512	GG	BF 579R	BF 579R
44513	GG	BFR 93P	BFR 93P
44514	GG	BAW 79C	BAW 79C
44515	GG	2SA1369-G	2SA1369
44516	GH	Z2 SMB-10	Z2 SMB-10
44517	GH	2SA1369-H	2SA1369
44518	GH	BAW 79D	BAW 79D
44519	GH1E,F	1300..1500V, 1A, <6µs	BY 228, BY 448, DM 513, EM 516, GP 10W
44520	GH3E,F	1300..1500V, 1,5A, <10µs	BY 228, BY 448, BY 350/...
44521	GI1-1200	1200V, 1A	BY133, BY350/1300, CH 3E, EM 513, GP 10Q
44522	GI1-1400	GI 1-1200, 1400V	BY 350/1500, CH 3E, EM 516, GP 10V
44523	GI1-1600	GI 1-1200, 1600V	DM 513, DM 516, EM 516, GP 10Y
44524	GI1001	50V, 1A, <25..40ns	BYV 26B, EGP 10A, FE 1A
44525	GI1002	GI 1001, 100V	BYV 26B, EGP 10B, FE 1B
44526	GI1003	GI 1001, 150V	BYV 26B, EGP 10C, FE 1C
44527	GI1004	GI 1001, 200V	BYV 26B, EGP 10D, FE 1D
44528	GI1101	50V, 2,4A, <25ns	EGP 30A, FE 3A
44529	GI1102	100V, 2,4A, <25ns	EGP 30B, FE 3B
44530	GI1103	150V, 2,4A, <25ns	EGP 30C, FE 3C
44531	GI1104	200V, 2A, <50ns	EGP 30D, FE 3D
44532	GI1301	50V, 6A, <30ns	BYV 61, FE 6A, BYT 08/200, RGP 80A
44533	GI1302	100V, 6A, <30ns	BYV 62, FE 6B, BYT 08/200, RGP 80B
44534	GI1303	150V, 6A, <30ns	BYV 63, FE 6C, BYT 08/200, RGP 80C
44535	GI1304	200V, 5A, <50ns	FE 6D, BYT 08/200, RGP 80D
44536	GI1401	50V, 8A, <35ns	BYP 51-50, BYW 29/50, BYW 80/50, FE 8A
44537	GI1401R..1404R	GI 1401..1404	-
44538	GI1402	GI 1401, 100A	BYP 51-100, BYW 29/100, BYW80/100, FE 8B
44539	GI1403	GI 1401, 150A	BYP 51-150, BYW 29/150, BYW80/150, FE 8C
44540	GI1404	GI 1401, 200A	BYP 51-200, BYW 29/200, BYW80/200, FE 8D
44541	GI2401	50V, 16A, <35ns	1605CT
44542	GI2401R..2404R	GI 2401..2404	BYV 32N/..., FE 16...N
44543	GI2402	GI 2401, 100V	1610CT
44544	GI2403	GI 2401, 150V	1615CT
44545	GI2404	GI 2401, 200V	1620CT
44546	GI250-1	1000V, 0,25A	BA 159, BY 203/12, BY 204/10, MR 250-1
44547	GI250-2	GI 250-1, 2000V	BY 203/20, GP 02-20, MR 250-2
44548	GI250-3	GI 250-1, 3000V	GP 02-30, MR 250-3
44549	GI250-4	GI 250-1, 4000V	GP 02-40, MR 250-4

44550	GI500	50V, 3A	BY 251, G3A, GP 30A, MR 500, 1N5400
44551	GI501	GI 500, 100V	BY 251, G3B, GP 30B, MR 501, 1N5401
44552	GI502	GI 500, 200V	BY 251, G3D, GP 30D, MR 502, 1N5402
44553	GI504	GI 500, 400V	BY 252, G3G, GP 30G, MR 504, 1N5404
44554	GI506	GI 500, 600V	BY 253, G3J, GP 30J, MR 506, 1N5406
44555	GI508	GI 500, 800V	BY 254, G3K, GP 30K, MR 508, 1N5407
44556	GI510	GI 500, 1000V	BY 255, G3M, GP 30M, MR 510, 1N5408
44557	GI5823	20V, 5A	SB 520, 1N5823
44558	GI5824	GI 5823, 30V	SB 530, 1N5824
44559	GI5825	GI 5823, 40V	SB 540, 1N5825
44560	GI750	50V, 6A	BY 214/50, BY 500/100, MR 750
44561	GI751	MR 750, 100V	BY 214/100, BY 500/100, MR 751
44562	GI752	MR 750, 200V	BY 214/200, BY 500/200, MR 752
44563	GI754	MR 750, 400V	BY 214/400, BY 500/400, MR 754
44564	GI756	MR 750, 600V	BY 214/600, BY 500/600, MR 756
44565	GI758	MR 750, 800V	BY 214/800, BY 500/800, MR 758
44566	GI810	50V, 1A, <750ns	BYD 33D, BYT 52A, RGP 10A, MR 810
44567	GI811	GI 810, 100V	BYD 33D, BYT 52B, RGP 10B, MR 811
44568	GI812	GI 810, 200V	BYD 33D, BYT 52D, RGP 10D, MR 812
44569	GI814	GI 810, 400V	BYD 33G, BYT 52G, RGP 10G, MR 814
44570	GI816	GI 810, 600V	BYD 33J, BYT 52J, RGP 10J, MR 816
44571	GI817	GI 810, 800V	BYD 33K, BYT 52K, RGP 10K, MR 817
44572	GI818	GI 810, 1000V	BYD 33M, BYT 52M, RGP 10M, MR 818
44573	GI820	50V, 5A, <200ns	BY 500/100, EGP 50A, MR 820
44574	GI821	GI 820, 100V	BY 500/100, EGP 50B, MR 821
44575	GI822	GI 820, 200V	BY 500/200, EGP 50D, MR 822
44576	GI824	GI 820, 400V	BY 500/400, EGP 50G, MR 824
44577	GI826	GI 820, 600V	BY 500/600, MR 826, BY 229/600
44578	GI850	50V, 3A, <200ns	BYW 95A, BYW 72, RGP 30A, MR 850
44579	GI851	GI 850, 100V	BYW 95A, BYW 72, RGP 30B, MR 851
44580	GI852	GI 850, 200V	BYW 95A, BYW 72, RGP 30D, MR 852
44581	GI854	GI 850, 400V	BYW 95B, BYW 74, RGP 30G, MR 854
44582	GI856	GI 850, 600V	BYW 95C, BYW 76, RGP 30J, MR 856
44583	GI910	50V, 3A, <750ns	BYW 95A, BYW 72, RGP 30A, MR 850
44584	GI911	GI 910, 100V	BYW 95A, BYW 72, RGP 30B, MR 851
44585	GI912	GI 910, 200V	BYW 95A, BYW 72, RGP 30D, MR 852
44586	GI914	GI 910, 400V	BYW 95B, BYW 74, RGP 30G, MR 854
44587	GI916	GI 910, 600V	BYW 95C, BYW 76, RGP 30J, MR 856
44588	GI917	GI 910, 800V	BY 399, BYW 96D, BYT 77, RGP 30K
44589	GI918	GI 910, 1000V	BY 399S, BYW 96E, BYT 78, RGP 30M
44590	GIA	2SC3957-GIA	2SC3957
44591	GIB	2SC3957-GIB	2SC3957
44592	GJ2	2SK968-2	2SK968
44593	GJ3	2SK968-3	2SK968
44594	GJ4	2SK968-4	2SK968

44595	GJ5	2SK968-5	2SK968
44596	GK	Z2 SMB-11	Z2 SMB-11
44597	GK	2SD1615-GK	2SD1615
44598	GK	SM 6T 150	SM 6T...
44599	GL	Z2 SMB-12	Z2 SMB-12
44600	GL	2SA1496	2SA1496
44601	GL	2SD1615-GL	2SD1615
44602	GL	SM 6T 150A	SM 6T...
44603	GLL4735..4763	1N4735..4763, SMD	-
44604	GLT12	BZW 25/12	BZW 25/12
44605	GLT120	BZW 25/120	BZW 25/120
44606	GLT24	BZW 25/24	BZW 25/24
44607	GLT47	BZW 25/47	BZW 25/47
44608	GM	Z2 SMB-13	Z2 SMB-13
44609	GM	2SD1615-GM	2SD1615
44610	GM-1A...Z	200..1000V, 1,3A	BY 226...227, BY 251...255, 1N5391...99
44611	GM0290(A)	750MHz	AF 139, AF 239(S)
44612	GM0378(A)	600MHz	AF 139, AF 239(S)
44613	GM0656(A)		AF 139, AF 239(S)
44614	GM0760		AF 106, AF 109R, AF 239(S), AF 306
44615	GM0761		AF 106, AF 109R, AF 239(S), AF 306
44616	GM30A...M	50..1000V, 30A	BYV 72/..., BYW 99P/..., RP 30AP...MP
44617	GM30AD...MD	GM 30A..M	-
44618	GM30AN...MN	GM 30A..M	-
44619	GM3A...Z	100..1000V, 2,7A	BY 251...255, GP 30B...M, 1N5401...08
44620	GMA01	60V, 0,12A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
44621	GMA01U	GMA 01, 105V	BAV 14
44622	GMB01(U)	GMA 01	GMA 01(U)
44623	GMJ2955	BD 208	BD 208
44624	GMJ3055	BD 207	BD 207
44625	GN	Z2 SMB-15	Z2 SMB-15
44626	GN12015C	1200V, 15A, 150W	GT 15Q101
44627	GN12030E	1200V, 30A, 200W	GT 25Q101
44628	GN12050E	1200V, 50A, 200W	-
44629	GN1A3Q	AN 1A3Q, SMD	DTA 113ZU
44630	GN1A4M	AN 1A4M, SMD	DTA 114EU, 2SA1678
44631	GN1A4P	AN 1A4P, SMD	DTA 114YU
44632	GN1A4Z	AN 1A4Z, SMD	DTA 114TU
44633	GN1F4M	AN 1F4M, SMD	DTA 124EU, 2SA1677
44634	GN1F4N	AN 1F4N, SMD	DTA 124XU
44635	GN1F4Z	AN 1F4Z, SMD	DTA 124TU
44636	GN1L3M	AN 1L3M, SMD	DTA 143EU
44637	GN1L3N	AN 1L3N, SMD	DTA 143XU
44638	GN1L3Z	AN 1L3Z, SMD	DTA 143TU
44639	GN1L4L	AN 1L4L, SMD	DTA 143WU

44640	GN1L4M	AN 1L4M, SMD	DTA 144EU, 2SA1676
44641	GN1L4Z	AN 1L4Z, SMD	DTA 144TU
44642	GN4530C	450V, 30A, 150W	-
44643	GN6010A	600V, 10A, 50W	-
44644	GN6015A	600V, 15A, 60W	-
44645	GN6020C	600V, 20A, 100W	GT 25J101
44646	GN6030C	600V, 30A, 150W	-
44647	GN6050E	600V, 50A, 200W	GT 50J101
44648	GN6075E	600V, 75A, 250W	-
44649	GN9060E	900V, 60A, 200W	GT 60M102...M104
44650	GO	2SC2996-O	2SC2996
44651	GO	2SA2883-O	2SA2883
44652	GO	KTC4375-O	KTC 4375
44653	GP	Z2 SMB-16	Z2 SMB-16
44654	GP	2SD1615A-GP	2SD1615A
44655	GP02-20...-40	2..4kV, 0,25A	MR 250-2...-5, 1N1732A...1734A
44656	GP08A...J	50..600V, 0,8A	BY 126...127, BY 133...135, 1N4001...07
44657	GP10A...M	50..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
44658	GP10N..Y	GP 10A..M, 1100..1600V	BY 350/1500, GH 3F, DM 513, EM 516
44659	GP140	BDW 83C	BDW 83C
44660	GP145	BDW 84C	BDW 84C
44661	GP15A...M	50..1000V, 1,5A	BY 226...227, BY 251...255, 1N5391...99
44662	GP20A...M	50..1000V, 2A	BY 251...255, MR 500...510, 1N5400...08
44663	GP30A...M	50..1000V, 3A	BY 251...255, MR 500...510, 1N5400...08
44664	GP80A...M	50..1000V, 8A	BY 239/..., BY 359/..., RGP 80...
44665	GPP10A..M	GP 10A..M	GP 10A...M
44666	GPP15A..M	GP 15A..M	GP 15A...M
44667	GPP20A..M	GP 20A..M	GP 20A...M
44668	GPP30A..M	GP 30A..M	GP 30A...M
44669	GPP60A..M	50..1000V, 6A	BY 214/..., MR 750...760
44670	GQ	Z2 SMB-18	Z2 SMB-18
44671	GQ	2SD1615A-GQ	2SD1615A
44672	GR	Z2 SMB-20	Z2 SMB-20
44673	GR	2SA1455K-R	2SA1455K
44674	GR	2SC2996-R	2SC2996
44675	GR	2SC4990	2SC4990
44676	GS	Z2 SMB-22	Z2 SMB-22
44677	GS	2SA1455K-S	2SA1455K
44678	GS	2SB1520	2SB1520
44679	GS100(B...D)	25V, 0,05A, 0,03W, <1500/-ns	AC 122, AC 125...126, AC 151, ASY 26...27
44680	GS109(B...D)	20V, 0,05A, 0,083W, <1500/-ns	AC 122, AC 125...126, AC 151, ASY 26...27
44681	GS110	20V, 0,3A, 0,083W, <1500/-ns	AC 128, AC 152...153, AC 188, ASY 76...77
44682	GS111(B...E)	<1200/1500ns	AC 128, AC 152...153, AC 188, ASY 76...77
44683	GS112(B...E)	GS 111, <900/1500ns	AC 128, AC 152...153, AC 188, ASY 76...77
44684	GS121(B...D)	20V, 0,1A, 0,15W, <10µs	AC 128, AC 152...153, AC 188, ASY 76...77



44685	GS122	GS 121, 30V	AC 128, AC 152...153, AC 188, ASY 76...77
44686	GSA15B..G	100..600V, 1,5A	BY 226...227, BY 251...255, 1N5391...99
44687	GSA17B..E	100..400V, 1,7A	BY 251...255, MR 500...510, 1N5400...08
44688	GSA26B..E	100..400V, 2,6A	BY 251...255, MR 500...510, 1N5400...08
44689	GSA30B..J	100..800V, 3A	BY 251...255, MR 500...510, 1N5400...08
44690	GT	Z2 SMB-24	Z2 SMB-24
44691	GT	2SC4443	2SC4443
44692	GT	2SC4168	2SC4168
44693	GT	SM 6T 200	SM 6T...
44694	GT	2SD2423	2SD2423
44695	GT10G101	400V, 10A, 30W	-
44696	GT10G102	400V, 10A, 30W	-
44697	GT15G101	400V, 15A, 40W	-
44698	GT15J101	600V, 15A, 100W	GN 6020C
44699	GT15J102	GT 15J101, 35W	-
44700	GT15N101	1000V, 15A, 150W	BUP 303, GN 12015C
44701	GT15Q101	1200V, 15A, 150W	GN 12015C
44702	GT20D101	250V, 20A, 180W	-
44703	GT20D201	250V, 20A, 180W	-
44704	GT25J101	600V, 25A, 150W	GN 6030C
44705	GT25Q101	1200V, 25A, 200W	GN 12030E
44706	GT322	>80MHz	AF 139, AF 200, AF 239(S)
44707	GT328(A,B)	>400MHz	AF 139, AF 239(S)
44708	GT346(A,B)	600..700MHz	AF 139, AF 239(S)
44709	GT40T101	1500V, 40A	-
44710	GT50J101	600V, 50A, 200W	GN 6050E
44711	GT50J102	600V, 50A, 200W	GN 6050E
44712	GT50J301	GT 50J101	-
44713	GT50M101	900V, 50A, 180W	GN 9060E
44714	GT60J101	600V, 60A, 200W	GN 6075E
44715	GT60M102	900V, 60A, 200W	GN 9060E
44716	GT60M103	900V, 60A, 200W	GN 9060E
44717	GT60M104	900V, 60A, 200W	GN 9060E
44718	GT60M301	GT 50J101	-
44719	GT80J101	600V, 80A, 200W	-
44720	GT8J101	600V, 8A, 30W	-
44721	GT8N101	1000V, 8A, 100W	BUP 302
44722	GT8Q101	1200V, 8A, 100W	-
44723	GU	Z2 SMB-27	Z2 SMB-27
44724	GU	SM 6T 200A	SM 6T...
44725	GU-1(A,B,Z)	200..800V, 0,8A, <1μs	BA157...159, BY204/..., BY208/..., BY268
44726	GU-1E	1300V, 0,3A, <2μs	BY 228, BY 231/1400, DM 513, GP 10V...Y
44727	GU-1F	GU-1E, 1500V	BY 228, BY 231/1500, DM 516, GP 10Y
44728	GU-3(A,B,Z)	200..800V, 1A, <500ns	BYT 52A...M, BYV 12...16, RG 1A...M
44729	GU-3SY..SZ	100..200V, 3A, <500ns	BYW 95A...C, BYW 96D...E, RG 3A...M

44730	GV	Z2 SMB-30	Z2 SMB-30
44731	GV	1SV251	1SV251
44732	GV	1SV249	1SV249
44733	GV	SM 6T 220	SM 6T...
44734	GW	Z2 SMB-33	Z2 SMB-33
44735	GW	SM 6T 220A	SM 6T...
44736	GX	Z2 SMB-36	Z2 SMB-36
44737	GX	2SD2403-GX	2SD2403
44738	GY	Z2 SMB-39	Z2 SMB-39
44739	GY	2SC3689	2SC3689
44740	GY	2SC4413	2SC4413
44741	GY	2SC2996-Y	2SC2996
44742	GY	KTC4375-Y	KTC 4375
44743	GY	2SD2403-GY	2SD2403
44744	GY	2SA2883-Y	2SA2883
44745	GZ	Z2 SMB-43	Z2 SMB-43
44746	GZ	BFR 35AR	BFR 35AR
44747	GZ	2SD2403-GZ	2SD2403
44748	)	2,5,+6%	BZW 22/..., BZX 55/..., BZX 85/..., ZPD...
44749	GZB2.0...36(B,C)	2...36V, 1W, B6%, C0..+12%	BZV 85/..., BZW 22/..., BZX 61/..., ZPY...
44750	GZS2.0...39(R..Z)	2,0..39V, 0,4W, R,X,Y,Z-8..+3%	BZW 22/..., BZX 55/..., BZX 85/..., ZPD...
44751	H	2SK1229	2SK1229
44752	H	2SK1100	2SK1100
44753	H	HVU 354	HVU 354
44754	H	2SC4446	2SC4446
44755	H0	2SC4255	2SC4255
44756	H0	2SC4252	2SC4252
44757	H1	BFS 46	BFS 42
44758	H1	HVM 187WK	HVM 187WK
44759	H1	SST 4416	SST 4416
44760	H1	HSU 119	HSU 119
44761	H1	D71Y1.5T1	D71Y1.5T1
44762	H1	HSU 119	HSU 119
44763	H1(p)	BCW 69	BCW 69
44764	H11	BCX 71G	BCX 71G
44765	H11	2SJ166	2SJ166
44766	H12	2SJ185	2SJ185
44767	H12	SM-1XH12	SM-1XH12
44768	H13	2SJ202	2SJ202
44769	H14	BCX 71K	BCX 71K
44770	H14	2SJ203	2SJ203
44771	H15	2SJ204	2SJ204
44772	H16	2SJ210	2SJ210
44773	H16	SM-1XH16	SM-1XH16
44774	H17	2SJ209	2SJ209

44775	H18	2SJ211	2SJ211
44776	H1O	KSA 2755-O	KSA 2755
44777	H1O	KSA 2859-O	KSA 2859
44778	H1R	KSA 2755-R	KSA 2755
44779	H1Y	KSA 2755-Y	KSA 2755
44780	H1Y	KSA 2859-Y	KSA 2859
44781	H2	F 1H2	F 1H2
44782	H2	HVM 13	HVM 13
44783	H2	BFS 46A	BFS 42A
44784	H2	SM-1XH02	SM-1XH02
44785	H2(p)	BCW 70	BCW 70
44786	H2O	KSC 2756-Y	KSC 2756
44787	H2R	KSC 2756-R	KSC 2756
44788	H2Y	KSC 2756-Y	KSC 2756
44789	H3	KDV 153	KDV 153
44790	H3	HVM 187S	HVM 187S
44791	H3	2SA956-H3	2SA956
44792	H3(p)	BCW 89	BCW 89
44793	H31	BCW 89R	BCW 89R
44794	H32	1N4148	1N4148
44795	H3O	KSC 2757-O	KSC 2757
44796	H3R	KSC 2757-R	KSC 2757
44797	H3Y	KSC 2757-Y	KSC 2757
44798	H4	F 1H4	F 1H4
44799	H4	F 1H4	F 1H4
44800	H4	SST 5484	SST 5484
44801	H4	HVM 121WK	HVM 121WK
44802	H4	2SA956-H4	2SA956
44803	H4	2SC3134-4	2SC3134
44804	H4	BCW 69R	BCW 69R
44805	H4	SM-1XH04	SM-1XH04
44806	H4Z	KSC 2758	KSC 2758
44807	H5	HVM 14	HVM 14
44808	H5	SST 5485	SST 5485
44809	H5	2SA956-H5	2SA956
44810	H5	2SC3134-5	2SC3134
44811	H5	BCW 70R	BCW 70R
44812	H5O	KSC 2223-O	KSC 2223
44813	H5R	KSC 2223-R	KSC 2223
44814	H5Y	KSC 2223-Y	KSC 2223
44815	H6	F 1H6	F 1H4
44816	H6	HVM 14SR	HVM 14SR
44817	H6	2SC3134-6	2SC3134
44818	H6	SST 5486	SST 5486
44819	H6	2SA956-H6	2SA956

44820	H6	BCW 89R	BCW 89R
44821	H6	HVM 14S	HVM 14S
44822	H6	HVB 14S	HVB 14S
44823	H6	SM-1XH06	SM-1XH06
44824	H6O	KSC 2759-O	KSC 2759
44825	H6R	KSC 2759-R	KSC 2759
44826	H6Y	KSC 2759-Y	KSC 2759
44827	H7	2SC3134-7	2SC3134
44828	H7	BCF 70	BCF 70
44829	H71	BCF 70R	BCF 70R
44830	H8	SM-1XH08	SM-1XH08
44831	H8Z	KSC 2734	2SC2734
44832	H9	1SS344	1SS344
44833	H9Z	KSC 3120	2SC3120
44834	HA	μPA601T	æPA601T
44835	HA	CFY 65-12	CFY 55
44836	HA	2SC3119	2SC3119
44837	HA	BSS 25	BSS 25
44838	HA	2SD1464-HA	2SD1464
44839	HA	2SC2804	2SC2804
44840	HAF2001	20A, 50W,	
44841	HAO	KSC 3123	KSC 3123
44842	HB	CFY 65-14	CFY 55
44843	HB	CFY 75-13	-
44844	HB	2SC3120	2SC3120
44845	HB	2SC4245	2SC4245
44846	HB	2SD1464-HB	2SD1464
44847	HB	2SC3137	2SC3137
44848	HB(s)	BFN 22	BFN 22
44849	HC	CFY 75-15	-
44850	HC	2SC4463	2SC4463
44851	HC	2SC3121	2SC3121
44852	HC	2SC2733	2SC2733
44853	HC	2SC4246	2SC4246
44854	HC(s)	BFN 23	BFN 23
44855	HC1A3M..L2Q	AC 1A3M..L2Q, SMD	-
44856	HD	Z2 SMB-47	Z2 SMB-47
44857	HD	2SC3122	2SC3122
44858	HD	2SC4249	2SC4249
44859	HD1A3M..L3N	AD 1A3M..L3N, SMD	-
44860	HD2A3M..L3N	AD 2A3M..L3N, SMD	-
44861	HE	2SC4250	2SC4250
44862	HE	2SC3123	2SC3123
44863	HF	Z2 SMB-51	Z2 SMB-51
44864	HF	KTC 3882	KTC 3882

44865	HF	2SC4251	2SC4251
44866	HF	BFN 23	BFN 23
44867	HF	2SC3124	2SC4251
44868	HF	2SC2805	2SC2805
44869	HF7757	1700V, 20A, 150W	-
44870	HFSD-1A...Z	200..1000V, 0,3A, <800ns	BA 157...159, BY 204/..., BY 208/...
44871	HG	Z2 SMB-56	Z2 SMB-56
44872	HG	2SC3439-G	2SC3439
44873	HG	2SC2806	2SC2806
44874	HH	Z2 SMB-62	Z2 SMB-62
44875	HH	2SC4253	2SC4253
44876	HH	KTC 3881	KTC 3881
44877	HH	2SC3125	2SC3125
44878	HH	2SC3439-H	2SC3439
44879	HI	2SC4247	2SC4247
44880	HI-	3SK188	3SK188
44881	HJ	2SC3439-J	2SC3439
44882	HJ	2SC3602	2SC3602
44883	HK	2SC3828	2SC3828
44884	HK	Z2 SMB-68	Z2 SMB-68
44885	HK	2SD1006-HK	2SD1006
44886	HL	Z2 SMB-75	Z2 SMB-75
44887	HL	2SA1502	2SA1502
44888	HL	2SA1722	2SA1722
44889	HL	2SC3862	2SC3862
44890	HL	2SD1006-HL	2SD1006
44891	HM	Z2 SMB-82	Z2 SMB-82
44892	HM	2SC3547B	2SC3547B
44893	HM	2SC4248	2SC4248
44894	HM	2SD1006-HM	2SD1006
44895	HN	2SC4214	2SC4214
44896	HN	Z2 SMB-91	Z2 SMB-91
44897	HN	2SC4244	2SC4244
44898	HN1A01F	50V, 0,15A, >80MHz	-
44899	HN1A01FU	HN 1 A01F	-
44900	HN1B01F	50V, 0,15A, 120MHz	-
44901	HN1B01FU	HN 1 B01F	-
44902	HN1C01F	60V, 0,15A, >80MHz	-
44903	HN1C01FU	HN 1 C01F	-
44904	HN1C03F	50V, 0,3A, 30MHz	-
44905	HN1C03FU	HN 1 C03F	-
44906	HN1D01F	4 Di, SS, 85V, 0,1A, <4ns	Pin-Code: K1K2A34K3K4A12
44907	HN1D01FU	HN 1 D01F	-
44908	HN1D02F	4 Di, SS, 85V, 0,1A, <4ns	Pin-Code: A1A2K34A3A4K12
44909	HN1D02FU	HN 1 D02F	-

44910	HN1D03F	4 Di, SS, 85V, 0,1A, <4ns	Pin-Code: A1A2A34K3K4K12
44911	HN1D03FU	HN 1 D03F	-
44912	HN2AO1FU	50V, 0,15A, >80MHz	-
44913	HN2CO1FU	60V, 0,15A, >80MHz	-
44914	HN2D01F	3 Di, SS, 85V, 0,08A, <4ns	Pin-Code: K1K2K3A3A2A1
44915	HN2D01FU	HN 2 D01F	-
44916	HN2D02FU	3 Di, SS, 85V, 0,08A, <4ns	Pin-Code: A1A2A3K3K2K1
44917	HN3BO1F	50V, 0,15A, 120MHz	-
44918	HN3CO1F	30V, 50mA, 1400MHz	-
44919	HN3CO2F	30V, 50mA, 2400MHz	-
44920	HN3CO3F	20V, 30mA, 4000MHz	-
44921	HN3CO6F	20V, 80mA, 7000MHz	-
44922	HN3CO7F	20V, 40mA, 10GHz	-
44923	HN3CO8F	20V, 15mA, 10GHz	-
44924	HN3G01J	NPN (60V, 0,15A)	-
44925	HO	KTA1663-O	KTA 1663
44926	HO	2SA1203-O	2SA1203
44927	HP	2SA1036-HP	2SA1036
44928	HP	Z2 SMB-100	Z2 SMB-100
44929	HP	2SA1036K-P	2SA1036K
44930	HP	2SA1577-P	2SA1577
44931	HP	2SC4527	2SC4527
44932	HP	2SD1007-HP	2SD1007
44933	HPA100R	1500/800V, 10A, 150W	2SC3995
44934	HPA150R	1500/800V, 15A, 150W	2SC3996
44935	HPA72R	1500/800, 7A, 60W	BU 508DF, 2SC3892A, 2SC4123...24, 2SD2251
44936	HPG10	HPG 8, 10kV, 0,04A	1N5184
44937	HPG15	HPG 8, 15kV, 0,03A	1N3054
44938	HPG20	HPG 8, 20kV, 0,02A	1N3056
44939	HPG8	8kV, 0,05A	1N5184
44940	HQ	2SA1036-HQ	2SA1036
44941	HQ	Z2 SMB-110	Z2 SMB-110
44942	HQ	2SA1036K-Q	2SA1036K
44943	HQ	2SC4155-Q	2SC4155
44944	HQ	2SA1577-Q	2SA1577
44945	HQ	2SC3928-Q	2SC3928
44946	HQ	2SD1007-HQ	2SD1007
44947	HQ	2SB956-Q	2SB956
44948	HQ1A3M..L3N	AQ 1A3M..L3N, SMD	-
44949	HR	2SA1036-HR	2SA1036
44950	HR	Z2 SMB-120	Z2 SMB-120
44951	HR	2SA1577-R	2SA1577
44952	HR	2SC4155-R	2SC4155
44953	HR	2SA1531A-R	2SA1531A
44954	HR	2SA1035-R	2SA1035



44955	HR	2SA1036K-R	2SA1036K
44956	HR	2SC3928-R	2SC3928
44957	HR	2SD1007-HR	2SD1007
44958	HR	2SB956-R	2SB956
44959	HR100(R)	100V, 3A	BY 251...255, GP 30B...M, 1N5401...08
44960	HR1000(R)	HR 100, 1000V	BY 255, GP 30M, MR 510, 1N5408
44961	HR1A3M..L3N	AR 1A3M..L3N, SMD	-
44962	HR200(R)	HR 100, 200V	BY 251...255, GP 30D...M, 1N5402...08
44963	HR400(R)	HR 100, 400V	BY 252...255, GP 30G...M, 1N5404...08
44964	HR5A,B	100..200V, 0,4A	BA 157...159, BY 204/..., BY 208/...
44965	HR600(R)	HR 100, 600V	BY 253...255, GP 30J...M, 1N5406...08
44966	HR800(R)	HR 100, 800V	BY 254...255, GP 30K...M, 1N5407...08
44967	HRB0103A	HRU 0103A	-
44968	HRB0103B	HRU 0103A	-
44969	HRC0202A	20V, 0,2A	-
44970	HRF22	40V, 1A	-
44971	HRF32	90V, 1A	-
44972	HRP100	50V, 1A	BYV 10-60, HRP 22, MBR 150, SB 150
44973	HRP22	50V, 1A	BYV 10-60, HRP 100, MBR 150, SB 150
44974	HRP24	40V, 3A	BYS 26-45, MBR 340, SB 340, 1N5822
44975	HRP32	90V, 1A	BYS 21-90, MBR 190, SB 190
44976	HRP34	60V, 3A	BYS 26-90, MBR 360, SB 360
44977	HRU0103A	30V, 0,1A	-
44978	HRU0103A	30V, 0,1A	-
44979	HRU0203A	HRW 0203A	-
44980	HRU0203A	HRW 0203A	-
44981	HRU0302A	HRW 0302A	-
44982	HRU0302A	HRW 0302A	-
44983	HRW0202A,B	20V, 0,2A	BAT 54C, BAT 64-05
44984	HRW0203A	30V, 0,2A	BAT 54, BAT 64
44985	HRW0302A	20V, 0,3A	1SS344
44986	HRW0502A	20V, 0,5A	1SS344
44987	HRW0503A	30V, 0,5A	-
44988	HRW0702A	20V, 0,7A	1SS349
44989	HRW0703A	30V, 0,7A	-
44990	HRW1002A(L,S)	20V, 10A	-
44991	HRW1002B	HRW 1002A	MA 750(A)
44992	HRW2502A(L,S)	20V, 25A	-
44993	HRW2502B	HRW 2502A	BYV 43F/30.../45
44994	HRW26	40V, 2x5A(Tc95°)	BYS 24-45...-90, MBR 2060...20100
44995	HRW26F	HRW 26	MA 750(A), MBRF 2060...20100
44996	HRW34	90V, 5A(Tc95°)	BYS 24-90, MBR 2090...20100
44997	HRW34F	HRW 34	MA 760, MBRF 20100
44998	HRW36	90V, 2x5A(Tc95°)	BYS 24-90, MBR 2090...20100
44999	HRW36F	HRW 36	MA 761, MBRF 20100

45000	HRW37F	90V, 2x10A(Tc95°)	-
45001	HS	Z2 SMB-130	Z2 SMB-130
45002	HS	2SA1531A-S	2SA1531A
45003	HS	2SA1035-S	2SA1035
45004	HS	2SC4155-S	2SC4155
45005	HS	2SC3928-S	2SC3928
45006	HS	2SB956-S	2SB956
45007	HS	2SD2540	2SC2540
45008	HS5157	60V, 0,5A, <1,7Ohm(0,25A)	BST 80, 2SK1592, 2SK1697, 2SK2109
45009	HS5159	100V, 0,3A, <4,5Ohm(0,15A)	2SK1698
45010	HS5161	30V, 1A, <0,7Ohm(0,5A)	2SK1485, 2SK1726, 2SK1728
45011	HS5810...5823	2N5810..5823, 0,7W	2N5810...5823
45012	HS5810...5823	2N5810..5823, 0,7W	2N5810...5823
45013	HS6010...6017	2N6010..6017, 0,7W	2N6010...6017
45014	HS6018...6021	2N6018..6021, 0,7W	2N6018...6021
45015	HS6018...6021	2N6018..6021, 0,7W	2N6018...6021
45016	HSB123	HSM 123	-
45017	HSB124SJ	HSM 124S	-
45018	HSB2836	HSM 2836C	BAW 66, BAW 68
45019	HSB2838	HSM 2838C	BAW 64, BAW 65, BAW 67
45020	HSB83J	HSM 83	-
45021	HSC101WK	SS, 30V, 35mA	-
45022	HSC2692	HSM 2692	-
45023	HSC2693	HSM 2693	-
45024	HSC2694	HSM 2694	-
45025	HSC276	1SS276, SMD	-
45026	HSC277	35V, <0,7Ohm(100MHz)	-
45027	HSC2836	HSM 2836	-
45028	HSC2838	HSM 2838	-
45029	HSE11S	HSE 11	-
45030	HSK110		BA 682...683
45031	HSK120	70V, 0,15A, <3ns	-
45032	HSK122	410V, 0,15A, <10µs	-
45033	HSK151	3V	TMMBAT 29
45034	HSK23	0,58..0,65V(3mA)	-
45035	HSK277		BA 683
45036	HSK83	300V, 0,15A, <100ns	-
45037	HSM107S	8V, Ifm0,1A	BAT 68-04
45038	HSM109WK	HSM 122WK, D110V, D210V	-
45039	HSM112WK	D18V, D210V, 30mA	-
45040	HSM113WK	20V, D10,2A, D20,1A	-
45041	HSM122	420V, 0,1A, <10µs	1SS311
45042	HSM123	85V, 0,1A, <3ns	BAV 99, MA 157A
45043	HSM124S	85V, 0,1A, <100ns	BAV 99
45044	HSM125WK	20V, D10,5A, D20,1A	-

45045	HSM126S	20V, 0,2A	BAT 54S, BAT 64-04
45046	HSM198S	10V, 30mA, <1,5pF	1SS366
45047	HSM198SR	HSM 198S	-
45048	HSM221C	85V, 0,1A, <3ns	MMBD 914, MMBD 4148
45049	HSM223C	HSM 221C	-
45050	HSM2692	<0,9Ohm(100MHz)	-
45051	HSM2693(A)	HSM 2692	1SS268
45052	HSM2694(A)	HSM 2692	1SS269
45053	HSM276S	3V, 30mA, <0,9pF	MA 730, 1SS295, 1SS366
45054	HSM276SR	HSM 276S	-
45055	HSM2836C	85V, 0,1A, <20ns	BAW 56, KDS 181, 1SS181
45056	HSM2838C	85V, 0,1A, <3ns	BAV 70, KDS 184, 1SS184
45057	HSM402S	HSS 402, SMD,	-
45058	HSM402WK	HSS 402, SMD,	-
45059	HSM83	300V, 0,1A, <100ns	-
45060	HSM88AS	HSM 88S	BAT 68-04
45061	HSM88ASR	HSM 88S	-
45062	HSM88S	CATV-M, 10V, 15mA	BAT 68-04, 1SS271
45063	HSM88SR	HSM 88S	-
45064	HSM88WA	HSM 88S	BAT 68-06
45065	HSM88WK	HSM 88S	BAT 68-05
45066	HSR101	S, 30V, 35mA, <1,5pF	-
45067	HSR276	1SS276, SMD	-
45068	HSR277	1SS277, SMD	-
45069	HSS100	60V, 35mA, <2,2pF	BAT 83, 1N6263
45070	HSS101	30V, 35mA, <1,5pF	BAT 81, 1N6263
45071	HSS102	70V, 35mA, <2,2pF	BAR 28, 1N5711, 1SS285
45072	HSS104	40V, 0,11A, <3ns	BAW 62, BAW 76, BAX 95, 1N4148
45073	HSS271	60V, 0,12A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148
45074	HSS400J	100V, 0,1A	-
45075	HSS401J	100V, 0,1A	-
45076	HSS402J	100V, 0,1A	-
45077	HSS81	1SS81	-
45078	HSS82	1SS82	-
45079	HSS83	1SS83	-
45080	HSU119	85V, 0,1A, <3ns	1SS352...353
45081	HSU119	85V, 0,1A, <3ns	1SS352...353
45082	HSU276	1SS276, SMD	1SS315
45083	HSU276	1SS276, SMD	1SS315
45084	HSU277	1SS277, SMD	BA 592, MA 77, 1SS314, 1SS356
45085	HSU277	1SS277, SMD	BA 592, MA 77, 1SS314, 1SS356
45086	HSU402J	HSS 402J, SMD	-
45087	HSU402J	HSS 402J, SMD	-
45088	HSU83	HSM 83	-
45089	HSU83	HSM 83	-

45090	HSU88	1SS88, SMD	-
45091	HSU88	1SS88, SMD	-
45092	HT	Z2 SMB-150	Z2 SMB-150
45093	HT	2SC4155-T	2SC4155
45094	HT	2SA1531A-T	2SA1531A
45095	HT	2SA1035-T	2SA1035
45096	HT	2SC3928-T	2SC3928
45097	HT	2SB956-T	2SB956
45098	HT2	90V, 0,1A, 0,3W, <500/2000ns	2SC4050
45099	HT3	90V, 0,1A, 0,3W, <500/1000ns	2SA1566
45100	HU	Z2 SMB-160	Z2 SMB-160
45101	HV	Z2 SMB-180	Z2 SMB-180
45102	HV-03SS	3kV, 2mA <180ns	-
45103	HV-05	5kV, 1mA <500ns	-
45104	HV-06SS	6kV, 2mA <180ns	-
45105	HV-08	8kV, 1mA <500ns	BY 617, BY 707, BY 717
45106	HV-08SS	8kV, 2mA <180ns	BY 617, BY 707, BY 717
45107	HV10	BA 127	BA 127
45108	HV100	70..115V(1mA)	-
45109	)	HV 23(GBL..GYL)	HV 23...
45110	HV13	BA 127	BA 127
45111	HV23D,E,F	0,66..0,8V(3mA)	BA 216, BA 314
45112	HV23G	0,58..0,69V(3mA)	BA 216, BA 314
45113	HV23GBL	0,58..0,69V(3mA)	BA 216, BA 314
45114	HV23GWT	0,58..0,65V(3mA)	BA 216, BA 314
45115	HV23GYL	0,62..0,69V(3mA)	BA 216, BA 314
45116	HV25	BA 127	BA 127
45117	HV26	0,68..0,75V(30mA)	BA 220, BZ 102/0V7, BZX 55/C0V8
45118	HV46	BA 102	BA 102
45119	HV46(RD)	1,17..1,4V(3mA)	BZV 86/1V4, BZX 75/C1V4, ZTE 1,5
45120	HV70	0,61..0,81V(0,5mA)	BA 216, BA 314
45121	HV75	1A, 0,77..0,87V(100mA)	ZY 1
45122	HV80	0,55..0,75V(3mA)	BA 216, BA 314...315
45123	HV82	STHV 82	STHV 82
45124	HVB14S	HVM 14S	-
45125	HVC131	HVU 131	-
45126	HVC132	HVU 132	-
45127	HVC133	HVU 133	-
45128	HVC200A	HVU 200A	-
45129	HVC202A	HVU 202A	1SV278
45130	HVC300A	HVU 300A	-
45131	HVC306A	HVU 306A	1SV283
45132	HVC308A	HVU 308A	-
45133	HVC317B		-
45134	HVC350B	HVU 350B	1SV281

45135	HVC351	HVU 351	1SV257, 1SV279
45136	HVC355B	HVU 355B	-
45137	HVC357	HVU 357	-
45138	HVC358B	HVU 358B	-
45139	HVC359	HVU 359	-
45140	HVC362	HVU 362	-
45141	HVC363A	HVU 363A	-
45142	HVC365	HVU 365	-
45143	HVC369B	<0,50hm	1SV285
45144	HVC372B	15V, 15..17pF(1V), <0,40hm	-
45145	HVE200A	HVU 200A	-
45146	HVE202A	HVU 202A	-
45147	HVE300A	HVU 300A	-
45148	HVE306A	HVU 306A	-
45149	HVE350	HVU 350	-
45150	HVE351	HVU 351	1SV257, 1SV279
45151	HVE355	HVU 355	-
45152	HVE358	HVU 358	-
45153	HVG1	1kV, 0,3A, 2μs	GP 02-20, MR 250-2, 1N1732(A)
45154	HVG100	12..19pf(8V)	FC 54M, MA 345...346, SD 115
45155	HVG2	HVG 1, 2kV, 0,3A	GP 02-20, MR 250-2, 1N1732(A)
45156	HVG3	HVG 1, 3kV, 0,25A	GP 02-30, MR 250-3, 1N1733(A)
45157	HVG4	HVG 1, 4kV, 0,2A	GP 02-40, MR 250-4, 1N1734(A)
45158	HVG5	HVG 1, 5kV, 0,15A	MR 250-5, 1N1734(A)
45159	HVK89(A,B)	3,3..5,7pF(10V)	MA 342
45160	HVM100	HVR 100	-
45161	HVM11	3,6..5,6pF(1V)	MA 370
45162	HVM121WK	100V, 0,1A	-
45163	HVM13	60V, 50mA	-
45164	HVM131S	60V, 0,1A	-
45165	HVM131SR	HVM 131S	-
45166	HVM132	60V, 0,1A	-
45167	HVM132WK	HVM 132	-
45168	HVM14	50V, 50mA	MA 551, 1SV128, 1SV2333
45169	HVM14S	HVM 14	1SV234
45170	HVM14SR	HVM 14	-
45171	HVM15	HVM 11	-
45172	HVM16	43..48pF(2V)	BB 404, BB 804, BB 814
45173	HVM17	50..85pF(1V)	-
45174	HVM187S	HVM 13	RN 719D
45175	HVM187WK	HVM 13	-
45176	HVM25	36..45pF(3V)	BB 404, BB 804, BB 814
45177	HVM27WK	52..62pF(1V)	1SV225
45178	HVM306	32pF(2V)	-
45179	HVM55	37..42pF(3V)	-

45180	HVM89	3,6..5,9pF(10V)	-
45181	HVP100	440..520pF(1V)	BB 112, BB 130, BB 509, MV 1401, 1SV100
45182	HVP21	130..170pF(1V)	-
45183	HVR100	421..524pF(1V)	BB 512
45184	HVR12	3,6..5,6pF(1V)	1SV186
45185	HVR17	50..85pF(1V)	-
45186	HVR300	38,5..46,1pF(2V)	BB 419, BB 619...620, MA 329, MA 335
45187	HVS303	35,8..42pF(1V)	BB 405G, BB 505G, BB 809, 1SV124
45188	HVS304	15..18pF(1V)	BB 141...142, BB 405A,B, 1SV110...113
45189	HVT-15(SS)	11kV, 15mA, <180ns	HS 10
45190	HVT-18	12kV, 15mA, <500ns	HS 10
45191	HVT-20(SS)	14kV, 15mA, <180ns	HS 13
45192	HVT-22	14kV, 15mA, <500ns	HS 13
45193	HVT-25(SS)	17kV, 15mA, <180ns	HS 13
45194	HVT-30(E,S,SS)	18..24kV, 10mA, <200ns	-
45195	HVU12	HVR 12	MA 368, MA 373, 1SV245
45196	HVU12	HVR 12	MA 368, MA 373, 1SV245
45197	HVU131	65V, 0,1A, <1Ohm(10mA)	-
45198	HVU131	65V, 0,1A, <1Ohm(10mA)	-
45199	HVU132	65V, 0,1A, <2Ohm(10mA)	-
45200	HVU132	65V, 0,1A, <2Ohm(10mA)	-
45201	HVU133	15V, <0,7Ohm(2mA)	-
45202	HVU133	15V, <0,7Ohm(2mA)	-
45203	HVU17	HVR 17	-
45204	HVU17	HVR 17	-
45205	HVU187	HVM 13	-
45206	HVU187	HVM 13	-
45207	HVU200	26,5..31,4pF(2V)	BB 439, MA 366, 1SV215, 1SV232
45208	HVU200	26,5..31,4pF(2V)	BB 439, MA 366, 1SV215, 1SV232
45209	HVU200A	HVU 200, 27,7..31,8pF(2V)	BB 439, MA 366, 1SV215, 1SV232
45210	HVU200A	HVU 200, 27,7..31,8pF(2V)	BB 439, MA 366, 1SV215, 1SV232
45211	HVU202	14..16,3pF(2V)	BB 535, MA 360, MA 372, 1SV214, 1SV223
45212	HVU202	14..16,3pF(2V)	BB 535, MA 360, MA 372, 1SV214, 1SV223
45213	HVU202A	HVU 202, 14,1..16,5pF(2V)	BB 535, MA 360, MA 372, 1SV214, 1SV223
45214	HVU202A	HVU 202, 14,1..16,5pF(2V)	BB 535, MA 360, MA 372, 1SV214, 1SV223
45215	HVU300	38,5..46,1pF(2V)	BB 639, MA 365, MA 374, 1SV231
45216	HVU300	38,5..46,1pF(2V)	BB 639, MA 365, MA 374, 1SV231
45217	HVU300A	HVU 300, 39,5..47,4pF(2V)	BB 639
45218	HVU300A	HVU 300, 39,5..47,4pF(2V)	BB 639
45219	HVU305	33,2..36,7pF(2V)	BB 439, BB 639, MA 361, MA 364
45220	HVU305	33,2..36,7pF(2V)	BB 439, BB 639, MA 361, MA 364
45221	HVU306	29,3..33,2pF(2V)	BB 439, MA 355, MA 357, MA 366
45222	HVU306	29,3..33,2pF(2V)	BB 439, MA 355, MA 357, MA 366
45223	HVU306A	HVU 306, 29,3..34,2pF(2V)	BB 439, MA 361, MA 364
45224	HVU306A	HVU 306, 29,3..34,2pF(2V)	BB 439, MA 361, MA 364



45225	HVU307	32,2..37,5pF(2V)	BB 439, BB 639, MA 371, 1SV217
45226	HVU307	32,2..37,5pF(2V)	BB 439, BB 639, MA 371, 1SV217
45227	HVU308	13,9..16,1pF(2V)	BB 535, MA 360, MA 363, MA 372
45228	HVU308	13,9..16,1pF(2V)	BB 535, MA 360, MA 363, MA 372
45229	HVU308A	HVU 308, 13,7..15,9pF(2V)	BB 535, MA 360, MA 363, MA 372
45230	HVU308A	HVU 308, 13,7..15,9pF(2V)	BB 535, MA 360, MA 363, MA 372
45231	HVU314	4,4..6,4pF(1V)	MA 368, 1SV245
45232	HVU314	4,4..6,4pF(1V)	MA 368, 1SV245
45233	HVU315	27,6..32,1pF(2V)	-
45234	HVU315	27,6..32,1pF(2V)	-
45235	HVU316	5,16..7,22pF(1V)	MA 368, MA 373, 1SV245
45236	HVU316	5,16..7,22pF(1V)	MA 368, MA 373, 1SV245
45237	HVU350(B)	15..17,5pF(1V)	1SV270
45238	HVU350(B)	15..17,5pF(1V)	1SV270
45239	HVU351	14..16pF(2V)	1SV229
45240	HVU351	14..16pF(2V)	1SV229
45241	HVU352	VCO ..1GHz, 6..8pF(1V)	-
45242	HVU352	VCO ..1GHz, 6..8pF(1V)	-
45243	HVU354	16..18,5pF(1V)	-
45244	HVU354	16..18,5pF(1V)	-
45245	HVU355	6,4..7,4pF(1V)	-
45246	HVU355	6,4..7,4pF(1V)	-
45247	HVU355B	HVU 355, 6,4..7,2pF(1V)	-
45248	HVU355B	HVU 355, 6,4..7,2pF(1V)	-
45249	HVU356	27,7..31,8pF(2V)	-
45250	HVU356	27,7..31,8pF(2V)	-
45251	HVU357	19,5..23,5pF(1V)	-
45252	HVU357	19,5..23,5pF(1V)	-
45253	HVU358	19..21pF(1V)	-
45254	HVU358	19..21pF(1V)	-
45255	HVU359	24,8..29,8pF(1V)	-
45256	HVU359	24,8..29,8pF(1V)	-
45257	HVU362	41,6..49,9pF(1V)	-
45258	HVU362	41,6..49,9pF(1V)	-
45259	HVU363A	34,6..42,3pF(1V)	BB 639
45260	HVU363A	34,6..42,3pF(1V)	BB 639
45261	HVU365	27..28,55pF(1V)	-
45262	HVU365	27..28,55pF(1V)	-
45263	HVU89	HVK 89	MA 367
45264	HVU89	HVK 89	MA 367
45265	HW	Z2 SMB-200	Z2 SMB-200
45266	HX	2SB1572-HX	2SB1572
45267	HY	2SK1772	2SK1772
45268	HY	2SA1203-Y	2SA1203
45269	HY	2SB1572-HY	2SB1572

45270	HY	KTA1663-Y	KTA 1663
45271	HZ	2SB1572-HZ	2SB1572
45272	HZ1C3	1,5..1,7V(5mA), 0,5W	-
45273	HZ2..36(H)...	15..+8%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
45274	HZ2..5(A,B,C)LL	2..5V, 0,25W, A,B,C-12..+10%	BZV 39/..., 1N4615...25
45275	HZ2.0..36(B,C)P	CP0..+12%	BZV 85/..., BZW 22/..., BZX 61/..., ZPY...
45276	HZ2.7..39E(B1..4)	2,7..39V, 0,5W, B1..B4-8..+3%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
45277	HZ6..36(... )L	12..+8%	BZV 39/..., 1N4099...4122
45278	HZF2.0..36(B,C)P	HZ 2.0..36(B,C)P, SMD, 0,9W	BZG 03-..., MA 1Z..., PTZ..., RD...FM
45279	HZK2..36A,B,C	HZ 2..36(H)A,B,C, SMD, 0,5W	BZD 27/..., BZV 55/..., RLZ ... (J)
45280	L	HZ 2..5(A,B,C)LL, SMD, 0,25W	-
45281	HZK6..36(A,B,C)L	HZ 6..36(A,B,C)L, SMD, 0,4W	-
45282	HZM2.0..36N(B..)	2,0..36V, B..B3-5..+5%	BZX 84/..., RD ...M
45283	HZM27WA	2x Z, TAZ, 25,1..28,9V	-
45284	HZM6.2ZWA	2x Z, TAZ, 5,9..6,5V	-
45285	HZM6.8WA	2x Z, TAZ, 6,47..7V	-
45286	HZS2..36...	HZ 2..36(H)..., 0,4W	HZ 2...36(H)...
45287	HZS2..5LL..	HZ 2..5LL..., 0,25W	HZ 2...5LL...
45288	HZS2.0..39N(B..)	2,0..39V, 0,4W, B1..B4-8..+3%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
45289	HZS2.7..39E...	HZ 2.7..39E..., 0,4W	HZ 2.7...39E...
45290	HZS5.6..36J(B..)	5,6..36V, 0,4W, B1..B3-6..+5%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
45291	HZS5.6..36S...	HZS 5.6..36J..., 0,4W	HZS 5.6...36J...
45292	HZS6..36L..	HZ 6..36L..., 0,4W	HZ 6...36L...
45293	HZS6..36L..	HZ 6..36L..., 0,4W	HZ 6...36L...
45294	HZT7A1	<20Ohm(10mA)	-
45295	HZT7A2	<20Ohm(10mA)	-
45296	HZT7A3	<20Ohm(10mA)	-
45297	HZT7B1	<25Ohm(5mA)	-
45298	HZT7B2	<25Ohm(5mA)	-
45299	HZT7B3	<25Ohm(5mA)	-
45300	HZT7C1	<100Ohm(1mA)	-
45301	HZT7C2	<100Ohm(1mA)	-
45302	HZU2.0..36...	HZM 2.0..36N..	DTZ ..., RD ...S
45303	HZU2.0..36...	HZM 2.0..36N..	DTZ ..., RD ...S
45304	HZU2LL..5LL..	HZ 2LL..5LL	DTZ ..., RD ...S
45305	HZU2LL..5LL..	HZ 2LL..5LL	DTZ ..., RD ...S
45306	I	2SK1196	2SK1196
45307	I9	1SS336	1SS336
45308	IA	µPA602T	æPA602T
45309	IC	UN 7231	UN 7231
45310	IC-	2SC3016	2SC3016
45311	ID-	2SC3127	2SC3127
45312	IE	2SC3722K-E	2SC3722K
45313	IFB	2SB973-B	2SB973
45314	IFC	2SB973-C	2SB973

45315	IGD	2SK1215-D	2SK1215
45316	IGD	2SK360-D	2SK360
45317	IGE	2SK1215-E	2SK1215
45318	IGE	2SK360-E	2SK360
45319	IGF	2SK1215-F	2SK1215
45320	IGF	2SK360-F	2SK360
45321	IGT4D10..11	400V, 18A, 75W	-
45322	IGT4E10..11	IGT 4D10..11, 500V	-
45323	IGT6D20..21	400V, 32A, 125W	GN 4530C
45324	IGT6E10..11	IGT 4 D/E10..11	GT 25J101
45325	IGT6E20..21	IGT 6D20..21, 500V	-
45326	IGT8D/E20..21	IGT 6 D/E20..21	GN 4530C
45327	IGTH10N40	400V, 10A, 75W	GT 15J101
45328	IGTH10N50	IGTH 10N40, 500V	GT 15J101
45329	IGTH20N40	400V, 20A, 100W	GT 25J101
45330	IGTH20N50	IGTH 20N40, 500V	GT 25J101
45331	IGTM10N..	IGTH 10N..	GT 15J101
45332	IGTM20N..	IGTH 20N..	GT 25J101
45333	IGTP10N..	IGTH 10N..	GN 6010A
45334	IGTP20N..	IGTH 20N..	-
45335	IHC	2SK431-C	2SK431
45336	IHD	2SK431-D	2SK431
45337	IHE	2SK431-E	2SK431
45338	IHF	2SK431-F	2SK431
45339	IJ-	2SC3374	2SC3374
45340	IK	2SA1463-IK	2SA1463
45341	IKB	2SC3521-B	2SC3521
45342	IKC	2SC3521-C	2SC3521
45343	IL	2SC3493	2SC3493
45344	IL-	2SC4263	2SC4263
45345	IL-	2SA1463-IL	2SA1463
45346	IMB1(A)	RbRbe22kOhm, 50V, 30mA	-
45347	IMB10A	100mA	-
45348	IMB11A	RbRbe10kOhm, 50V, 100mA	-
45349	IMB14A	Rb47kOhm, Rbe-, 50V, 100mA	-
45350	IMB2(A)	RbRbe47kOhm, 50V, 30mA	-
45351	IMB3(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
45352	IMB4(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
45353	IMB5(A)	RbRbe22kOhm, 50V, 30mA	-
45354	IMB6(A)	RbRbe47kOhm, 50V, 30mA	-
45355	IMB7(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
45356	IMB8(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
45357	IMB9A	100mA	-
45358	IMBT3903..3904	2N3903..3904, SMD	BC 846, BCV 71...72, 2SC4209
45359	IMBT3905..3906	2N3905..3906, SMD	BC 856...857, BCX 71, 2SA1620

45360	IMD1A	Rb22kOhm, Rbe-, 50V, 100mA	-
45361	IMD2(A)	RbRbe22kOhm, 50V, 30mA	-
45362	IMD3(A)	RbRbe10kOhm, 50V, 100mA	-
45363	IMD6(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
45364	IMD8A	Rb47kOhm, Rbe-, 50V, 100mA	-
45365	IMD9A	70mA	-
45366	IMH1(A)	RbRbe22kOhm, 50V, 30mA	-
45367	IMH10A	100mA	-
45368	IMH11A	RbRbe10kOhm, 50V, 100mA	-
45369	IMH14A	Rb47kOhm, Rbe-, 50V, 100mA	-
45370	IMH15A	Rb47kOhm, Rbe-, 50V, 100mA	-
45371	IMH2(A)	RbRbe47kOhm, 50V, 30mA	-
45372	IMH3(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
45373	IMH4(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
45374	IMH5(A)	RbRbe22kOhm, 50V, 30mA	-
45375	IMH6(A)	RbRbe47kOhm, 50V, 30mA	-
45376	IMH7(A)	Rb4,7kOhm, Rbe-, 50V, 100mA	-
45377	IMH8(A)	Rb10kOhm, Rbe-, 50V, 100mA	-
45378	IMH9A	100mA	-
45379	IMT1	50V, 0,1A	-
45380	IMT17	-/50V, 0,5A	-
45381	IMT2(A)	50V, 0,1A	-
45382	IMT3(A)	50V, 0,1A	-
45383	IMT4	120V, 0,05A	-
45384	IMT5A	-/25V, 0,1A	-
45385	IMX1	50V, 0,1A	-
45386	IMX11	25V, 20mA	-
45387	IMX17	-/50, 0,5A	-
45388	IMX2	50V, 0,1A	-
45389	IMX3	50V, 0,1A	-
45390	IMX4	30V, 50mA, >600MHz	-
45391	IMX5	20V, 50mA	-
45392	IMX6	40V, 50mA, >150MHz	-
45393	IMX7	40V, 0,5A	-
45394	IMX8	120V, 0,05A	-
45395	IMX9	25V, 0,5A, B>560	-
45396	IMZ1(A)	50V, 0,1A	-
45397	IMZ2(A)	50V, 0,1A	-
45398	IMZ3A	60+30V, 0,1A	-
45399	INB	2SA1468-B	2SA1468
45400	INC	2SA1468-C	2SA1468
45401	IO	2SA1298-O	2SA1298
45402	IO	KTA1298-O	KTA 1298
45403	IO	2SC3515-O	2SC3515
45404	IO	2SC3515-O	2SC3515

45405	IP	2SB1073-P	2SB1073
45406	IP-	2SC4262	2SC4262
45407	IP-	2SC3793	2SC3793
45408	IP100	30V, 0,8A, Igt/Ih<0,2/<5mA	TAG62Y
45409	IP101	IP100, 60V	BRX46...47, BRX51...52, TAG60A, TAG62A
45410	IP102	IP100, 100V	BRX46...47, BRX51...52, TAG60A, TAG62A
45411	IP103	IP100, 150V	BRX 47...49, BRX 52...54
45412	IP104	IP100, 200V	BRX 47...49, BRX 52...54
45413	IP105	IP100, 300V	BRX 48...49, BRX 53...56
45414	IP106	IP100, 400V	BRX49, BRX54...56
45415	IQ	2SB792-Q	2SB792
45416	IQ	2SB1220-Q	2SB1220
45417	IQ	2SB1073-Q	2SB1073
45418	IR	2SB1220-R	2SB1220
45419	IR	2SC3722K-R	2SC3722K
45420	IR	2SB792-R	2SB792
45421	IR	2SB1463-R	2SB1463
45422	IR	2SB1073-R	2SB1073
45423	IRD	2SA1484-D	2SA1484
45424	IRE	2SA1484-E	2SA1484
45425	IRF034	<0,05Ohm(18A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
45426	IRF034	<0,05Ohm(18A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
45427	IRF035	<0,07Ohm(18A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
45428	IRF035	<0,07Ohm(18A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
45429	IRF044	<0,028Ohm(33A)	BUZ 24, 2N6764, 2SK561, 2SK906, 2SK1429
45430	IRF044	<0,028Ohm(33A)	BUZ 24, 2N6764, 2SK561, 2SK906, 2SK1429
45431	IRF045	<0,035Ohm(33A)	BUZ 24, 2N6764, 2SK561, 2SK906, 2SK1429
45432	IRF045	<0,035Ohm(33A)	BUZ 24, 2N6764, 2SK561, 2SK906, 2SK1429
45433	IRF1010	55V, 75A, 150W, 136/128ns	-
45434	IRF1010S	IRF 1010	-
45435	IRF120	<0,27Ohm(5,6A)	MTM 12N10, 2N6765, 2SK398...399, 2SK405
45436	IRF120	<0,27Ohm(5,6A)	MTM 12N10, 2N6765, 2SK398...399, 2SK405
45437	IRF121	IRF 120, 80V	MTM 12N08, 2N6765, 2SK398...399, 2SK405
45438	IRF121	IRF 120, 80V	MTM 12N08, 2N6765, 2SK398...399, 2SK405
45439	IRF122	<0,36Ohm(5,6A)	MTM 12N10, 2N6765, 2SK398...399, 2SK405
45440	IRF122	<0,36Ohm(5,6A)	MTM 12N10, 2N6765, 2SK398...399, 2SK405
45441	IRF123	IRF 122, 80V	MTM 12N08, 2N6765, 2SK398...399, 2SK405
45442	IRF123	IRF 122, 80V	MTM 12N08, 2N6765, 2SK398...399, 2SK405
45443	IRF130	<0,16Ohm(8,3A)	BUZ 36, MTM 12N10, 2N6765, 2SK572
45444	IRF130	<0,16Ohm(8,3A)	BUZ 36, MTM 12N10, 2N6765, 2SK572
45445	IRF131	IRF 130, 80V	BUZ 36, MTM 12N08, 2N6765, 2SK572
45446	IRF131	IRF 130, 80V	BUZ 36, MTM 12N08, 2N6765, 2SK572
45447	IRF132	<0,23Ohm(8,3A)	BUZ 36, MTM 12N10, 2N6765, 2SK572
45448	IRF132	<0,23Ohm(8,3A)	BUZ 36, MTM 12N10, 2N6765, 2SK572
45449	IRF133	IRF 132, 80V	BUZ 36, MTM 12N08, 2N6765, 2SK572

45450	IRF133	IRF 132, 80V	BUZ 36, MTM 12N08, 2N6765, 2SK572
45451	IRF140	<0,077Ohm(17A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45452	IRF140	<0,077Ohm(17A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45453	IRF141	IRF 140, 80V	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45454	IRF141	IRF 140, 80V	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45455	IRF142	<0,10Ohm(17A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45456	IRF142	<0,10Ohm(17A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45457	IRF143	IRF 142, 80V	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45458	IRF143	IRF 142, 80V	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45459	IRF150	<0,055Ohm(20A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45460	IRF150	<0,055Ohm(20A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45461	IRF151	IRF 150, 60V	BUZ 24, BUZ 349, 2N6763, 2SK906, 2SK1433
45462	IRF151	IRF 150, 60V	BUZ 24, BUZ 349, 2N6763, 2SK906, 2SK1433
45463	IRF152	<0,080Ohm(20A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45464	IRF152	<0,080Ohm(20A)	BUZ 24, BUZ 349, 2N6764, 2SK906, 2SK1433
45465	IRF153	IRF 152, 60V	BUZ 24, BUZ 349, 2N6763, 2SK906
45466	IRF153	IRF 152, 60V	BUZ 24, BUZ 349, 2N6763, 2SK906
45467	IRF220	200V, 5A, 40W, <0,80Ohm(2,5A)	BUZ 63, MTM 8N20, 2SK400
45468	IRF220	200V, 5A, 40W, <0,80Ohm(2,5A)	BUZ 63, MTM 8N20, 2SK400
45469	IRF221	IRF 220, 150V	BUZ 63, MTM 8N18, 2SK400
45470	IRF221	IRF 220, 150V	BUZ 63, MTM 8N18, 2SK400
45471	IRF222	200V, 4A, 40W, <1,20Ohm(2,5A)	BUZ 63, MTM 8N20, 2SK400
45472	IRF222	200V, 4A, 40W, <1,20Ohm(2,5A)	BUZ 63, MTM 8N20, 2SK400
45473	IRF223	IRF 222, 150V	BUZ 63, MTM 8N18, 2SK400
45474	IRF223	IRF 222, 150V	BUZ 63, MTM 8N18, 2SK400
45475	IRF224	<1,10Ohm(2,1A)	BUZ 63, 2SK259...260, 2SK2264
45476	IRF224	<1,10Ohm(2,1A)	BUZ 63, 2SK259...260, 2SK2264
45477	IRF225	<1,50Ohm(2,1A)	BUZ 63, 2SK259...260, 2SK2264
45478	IRF225	<1,50Ohm(2,1A)	BUZ 63, 2SK259...260, 2SK2264
45479	IRF230	200V, 9A, 75W, <0,40Ohm(5A)	MTM 8N20, 2SK400...401, 2SK412
45480	IRF230	200V, 9A, 75W, <0,40Ohm(5A)	MTM 8N20, 2SK400...401, 2SK412
45481	IRF231	IRF 230, 150V	MTM 8N18, 2SK400...401, 2SK412
45482	IRF231	IRF 230, 150V	MTM 8N18, 2SK400...401, 2SK412
45483	IRF232	200V, 8A, 75W, <0,60Ohm(5A)	MTM 8N20, 2SK400...401, 2SK412
45484	IRF232	200V, 8A, 75W, <0,60Ohm(5A)	MTM 8N20, 2SK400...401, 2SK412
45485	IRF233	IRF 232, 150V	MTM 8N18, 2SK400...401, 2SK412
45486	IRF233	IRF 232, 150V	MTM 8N18, 2SK400...401, 2SK412
45487	IRF234	<0,45Ohm(4,1A)	BUZ 64, BUZ 325, 2SK293, 2SK501
45488	IRF234	<0,45Ohm(4,1A)	BUZ 64, BUZ 325, 2SK293, 2SK501
45489	IRF235	<0,68Ohm(4,1A)	BUZ 64, BUZ 325, 2SK293, 2SK501
45490	IRF235	<0,68Ohm(4,1A)	BUZ 64, BUZ 325, 2SK293, 2SK501
45491	IRF236	IRF 234, 275V	BUZ 64, BUZ 325, 2SK293, 2SK501
45492	IRF236	IRF 234, 275V	BUZ 64, BUZ 325, 2SK293, 2SK501
45493	IRF237	IRF 235, 275V	BUZ 64, BUZ 325, 2SK293, 2SK501
45494	IRF237	IRF 235, 275V	BUZ 64, BUZ 325, 2SK293, 2SK501



45495	IRF240	<0,18Ohm(10A)	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45496	IRF240	<0,18Ohm(10A)	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45497	IRF241	IRF 240, 150V	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45498	IRF241	IRF 240, 150V	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45499	IRF242	<0,22Ohm(10A)	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45500	IRF242	<0,22Ohm(10A)	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45501	IRF243	IRF 242, 150V	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45502	IRF243	IRF 242, 150V	BUZ 36, BUZ 350, MTM 15N20, 2SK901
45503	IRF244	<0,28Ohm(8A)	BUZ 323, 2SK559...560, 2SK573, 2SK1135
45504	IRF244	<0,28Ohm(8A)	BUZ 323, 2SK559...560, 2SK573, 2SK1135
45505	IRF245	<0,34Ohm(8A)	BUZ 323, 2SK559...560, 2SK573, 2SK1135
45506	IRF245	<0,34Ohm(8A)	BUZ 323, 2SK559...560, 2SK573, 2SK1135
45507	IRF246	IRF 244, 275V	BUZ 323, 2SK559...560, 2SK868, 2SK1401
45508	IRF246	IRF 244, 275V	BUZ 323, 2SK559...560, 2SK868, 2SK1401
45509	IRF247	IRF 245, 275V	BUZ 323, 2SK559...560, 2SK868, 2SK1401
45510	IRF247	IRF 245, 275V	BUZ 323, 2SK559...560, 2SK868, 2SK1401
45511	IRF250	<85mOhm(16A)	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45512	IRF250	<85mOhm(16A)	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45513	IRF251	IRF 250, 150V	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45514	IRF251	IRF 250, 150V	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45515	IRF252	<0,12Ohm(16A)	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45516	IRF252	<0,12Ohm(16A)	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45517	IRF253	IRF 250, 150V	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45518	IRF253	IRF 250, 150V	BUZ 341, 2N6766, 2SK851, 2SK902, 2SK1492
45519	IRF254	<0,14Ohm(12A)	2SK623, 2SK901, 2SK944, 2SK1641, 2SK2007
45520	IRF254	<0,14Ohm(12A)	2SK623, 2SK901, 2SK944, 2SK1641, 2SK2007
45521	IRF255	<0,17Ohm(12A)	2SK623, 2SK901, 2SK944, 2SK1641, 2SK2007
45522	IRF255	<0,17Ohm(12A)	2SK623, 2SK901, 2SK944, 2SK1641, 2SK2007
45523	IRF256	IRF 254, 275V	2SK868(A), 2SK1169...70, 2SK1497...1500
45524	IRF256	IRF 254, 275V	2SK868(A), 2SK1169...70, 2SK1497...1500
45525	IRF257	IRF 255, 275V	2SK868(A), 2SK1169...70, 2SK1497...1500
45526	IRF257	IRF 255, 275V	2SK868(A), 2SK1169...70, 2SK1497...1500
45527	IRF320	<1,8Ohm(1,8A)	MTM 5N40, 2SK635
45528	IRF320	<1,8Ohm(1,8A)	MTM 5N40, 2SK635
45529	IRF321	IRF 320, 350V	MTM 5N35, 2SK635
45530	IRF321	IRF 320, 350V	MTM 5N35, 2SK635
45531	IRF322	<2,5Ohm(1,8A)	MTM 5N40, 2SK635
45532	IRF322	<2,5Ohm(1,8A)	MTM 5N40, 2SK635
45533	IRF323	IRF 322, 350V	MTM 5N35, 2SK635
45534	IRF323	IRF 322, 350V	MTM 5N35, 2SK635
45535	IRF330	400V, 5,5A, 75W, <1Ohm(3A)	BUZ 63, MTM 5N40, 2SK260, 2SK2264
45536	IRF330	400V, 5,5A, 75W, <1Ohm(3A)	BUZ 63, MTM 5N40, 2SK260, 2SK2264
45537	IRF331	IRF 320, 350V	BUZ 63, MTM 5N35, 2SK259...260, 2SK2264
45538	IRF331	IRF 320, 350V	BUZ 63, MTM 5N35, 2SK259...260, 2SK2264
45539	IRF332	400V, 4,5A, 75W, <46/80ns	BUZ 63, MTM 5N40, 2SK260, 2SK2264

45540	IRF332	400V, 4,5A, 75W, <46/80ns	BUZ 63, MTM 5N40, 2SK260, 2SK2264
45541	IRF333	IRF 322, 350V	BUZ 63, MTM 5N35, 2SK259...260, 2SK2264
45542	IRF333	IRF 322, 350V	BUZ 63, MTM 5N35, 2SK259...260, 2SK2264
45543	IRF340	<0,55Ohm(5,2A)	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45544	IRF340	<0,55Ohm(5,2A)	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45545	IRF341	IRF 340, 350V	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45546	IRF341	IRF 340, 350V	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45547	IRF342	<0,80Ohm(5,2A)	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45548	IRF342	<0,80Ohm(5,2A)	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45549	IRF343	IRF 342, 350V	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45550	IRF343	IRF 342, 350V	BUZ 64, BUZ 325...326, 2SK642, 2SK896
45551	IRF350	<0,30Ohm(8A)	BUZ 323, MTM 15N40, 2SK559...60, 2SK899
45552	IRF350	<0,30Ohm(8A)	BUZ 323, MTM 15N40, 2SK559...60, 2SK899
45553	IRF351	IRF 350, 350V	BUZ 323, MTM 15N35, 2SK559...60, 2SK899
45554	IRF351	IRF 350, 350V	BUZ 323, MTM 15N35, 2SK559...60, 2SK899
45555	IRF352	<0,40Ohm(8A)	BUZ 323, MTM 15N40, 2SK559...60, 2SK899
45556	IRF352	<0,40Ohm(8A)	BUZ 323, MTM 15N40, 2SK559...60, 2SK899
45557	IRF353	IRF 352, 350V	BUZ 323, MTM 15N35, 2SK559...60, 2SK899
45558	IRF353	IRF 352, 350V	BUZ 323, MTM 15N35, 2SK559...60, 2SK899
45559	IRF360	<0,20Ohm(14A)	-
45560	IRF360	<0,20Ohm(14A)	-
45561	IRF362	<0,25Ohm(14A)	-
45562	IRF362	<0,25Ohm(14A)	-
45563	IRF420	500V, 2,5A, 50W, <30Ohm(1,4A)	BUZ 308, MTM 3N55, 2SK635
45564	IRF420	500V, 2,5A, 50W, <30Ohm(1,4A)	BUZ 308, MTM 3N55, 2SK635
45565	IRF421	IRF 420, 450V	BUZ 308, MTM 3N55, 2SK635
45566	IRF421	IRF 420, 450V	BUZ 308, MTM 3N55, 2SK635
45567	IRF422	500V, 2,2A, 50W, <40Ohm(1,4A)	BUZ 308, MTM 3N55, 2SK635
45568	IRF422	500V, 2,2A, 50W, <40Ohm(1,4A)	BUZ 308, MTM 3N55, 2SK635
45569	IRF423	IRF 422, 450V	BUZ 308, MTM 3N55, 2SK635
45570	IRF423	IRF 422, 450V	BUZ 308, MTM 3N55, 2SK635
45571	IRF430	<1,50Ohm(2,5A)	BUZ 84, BUZ 355...356, MTM 4N50, 2SK351
45572	IRF430	<1,50Ohm(2,5A)	BUZ 84, BUZ 355...356, MTM 4N50, 2SK351
45573	IRF431	IRF 430, 450V	BUZ 84, BUZ 355...356, MTM 4N45, 2SK351
45574	IRF431	IRF 430, 450V	BUZ 84, BUZ 355...356, MTM 4N45, 2SK351
45575	IRF432	500V, 4A, 75W, <20Ohm(2,5A)	BUZ 84, BUZ 355...356, MTM 4N50, 2SK351
45576	IRF432	500V, 4A, 75W, <20Ohm(2,5A)	BUZ 84, BUZ 355...356, MTM 4N50, 2SK351
45577	IRF433	IRF 432, 450V	BUZ 84, BUZ 355...356, MTM 4N45, 2SK351
45578	IRF433	IRF 432, 450V	BUZ 84, BUZ 355...356, MTM 4N45, 2SK351
45579	IRF440	<0,85Ohm(4,4A)	BUZ 94, BUZ 330...331, MTM 7N50, 2SK636
45580	IRF440	<0,85Ohm(4,4A)	BUZ 94, BUZ 330...331, MTM 7N50, 2SK636
45581	IRF441	IRF 440, 450V	BUZ 94, BUZ 330...331, MTM 7N45, 2SK636
45582	IRF441	IRF 440, 450V	BUZ 94, BUZ 330...331, MTM 7N45, 2SK636
45583	IRF442	<1,10Ohm(4,4A)	BUZ 94, BUZ 330...331, MTM 7N50, 2SK636
45584	IRF442	<1,10Ohm(4,4A)	BUZ 94, BUZ 330...331, MTM 7N50, 2SK636

45585	IRF443	IRF 442, 450V	BUZ 94, BUZ 330...331, MTM 7N45, 2SK636
45586	IRF443	IRF 442, 450V	BUZ 94, BUZ 330...331, MTM 7N45, 2SK636
45587	IRF448	<0,6Ohm(5,4A)	BUZ 45, BUZ 339, 2SK512, 2SK683, 2SK724
45588	IRF448	<0,6Ohm(5,4A)	BUZ 45, BUZ 339, 2SK512, 2SK683, 2SK724
45589	IRF449	<0,75Ohm(5,4A)	BUZ 45, BUZ 339, 2SK512, 2SK683, 2SK724
45590	IRF449	<0,75Ohm(5,4A)	BUZ 45, BUZ 339, 2SK512, 2SK683, 2SK724
45591	IRF450	<0,4Ohm(7,2A)	BUZ 323, BUZ 338, MTM 15N50, 2SK899
45592	IRF450	<0,4Ohm(7,2A)	BUZ 323, BUZ 338, MTM 15N50, 2SK899
45593	IRF451	IRF 450, 450V	BUZ 323, BUZ 338, MTM 15N45, 2SK899
45594	IRF451	IRF 450, 450V	BUZ 323, BUZ 338, MTM 15N45, 2SK899
45595	IRF452	<0,5Ohm(7,2A)	BUZ 323, BUZ 338, MTM 15N50, 2SK899
45596	IRF452	<0,5Ohm(7,2A)	BUZ 323, BUZ 338, MTM 15N50, 2SK899
45597	IRF453	IRF 452, 450V	BUZ 323, BUZ 338, MTM 15N45, 2SK899
45598	IRF453	IRF 452, 450V	BUZ 323, BUZ 338, MTM 15N45, 2SK899
45599	IRF460	<0,27Ohm(12A)	-
45600	IRF460	<0,27Ohm(12A)	-
45601	IRF462	<0,35Ohm(12A)	-
45602	IRF462	<0,35Ohm(12A)	-
45603	IRF510	<0,54Ohm(3,4A)	BUZ 20, BUZ 72, 2SK628, 2SK917, 2SK920
45604	IRF510S..540S	IRF 510..540	-
45605	IRF511	IRF 510, 80V	BUZ 20, BUZ 72, 2SK628, 2SK917, 2SK920
45606	IRF512	<0,74Ohm(3,4A)	BUZ 20, BUZ 72, 2SK628, 2SK917, 2SK920
45607	IRF513	IRF 510, 80V	BUZ 20, BUZ 72, 2SK628, 2SK917, 2SK920
45608	IRF520	<0,27Ohm(5,5A)	BUZ 20, BUZ 72, 2SK918, 2SK921, 2SK1427
45609	IRF520..523FL,P	75% I <sub>max</sub> , 35W	BUZ 72(A)F, BUK 443-100, BUK 543-100
45610	IRF521	IRF 520, 80V	BUZ 20, BUZ 72, 2SK918, 2SK921, 2SK1427
45611	IRF522	<0,36Ohm(5,6A)	BUZ 20, BUZ 72, 2SK918, 2SK921, 2SK1427
45612	IRF523	IRF 520, 80V	BUZ 20, BUZ 72, 2SK918, 2SK921, 2SK1427
45613	IRF530	<0,16Ohm(8,4A)	BUZ21, 2SK919, 2SK922, 2SK1301, 2SK1559
45614	IRF530..533FL,P	67% I <sub>max</sub> , 40W	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
45615	IRF531	IRF 530, 80V	BUZ21, 2SK919, 2SK922, 2SK1301, 2SK1559
45616	IRF532	<0,23Ohm(8,3A)	BUZ21, 2SK919, 2SK922, 2SK1301, 2SK1559
45617	IRF533	IRF 532, 80V	BUZ21, 2SK919, 2SK922, 2SK1301, 2SK1559
45618	IRF540	<77mOhm(17A)	BUK 456-100, BUZ 22
45619	IRF540..543FL,P	55% I <sub>max</sub> , 45W	BUK 445-100, 2SK1306...07, 2SK1318
45620	IRF541	IRF 540, 80V	BUK 456-100, BUZ 22
45621	IRF542	<0,1Ohm(17A)	BUK 456-100, BUZ 22
45622	IRF543	IRF 542, 80V	BUK 456-100, BUZ 22
45623	IRF610	200V, 3,3A, 36W, <1,5Ohm(2A)	MTP 5N20, 2SK923...924, 2SK1391
45624	IRF610S..640S	IRF 610..640	-
45625	IRF611	IRF 610, 150V	MTP 5N18, 2SK923...924, 2SK1391
45626	IRF612	<2,4Ohm(1,6A)	MTP 5N20, 2SK923...924, 2SK1391
45627	IRF613	IRF 612, 150V	MTP 5N18, 2SK923...924, 2SK1391
45628	IRF614	250V, 2,7A, 36W, <2Ohm(1,6A)	BUZ 76, 2SK310, 2SK923
45629	IRF615	250V, 1,8A, 36W, <3Ohm(1A)	BUZ 74, 2SK382, 2SK892

45630	IRF620	<0,8Ohm(3,1A)	2SK1391
45631	IRF620..623FI,P	80%Imax, 30W	BUZ 73(A)F, BUK 444-200
45632	IRF621	IRF 620, 150V	2SK1391
45633	IRF622	200V, 4A, 50W, <1,2Ohm(2,5A)	2SK1391
45634	IRF623	IRF 622, 150V	2SK1391
45635	IRF624	<1,1Ohm(2,6A)	BUZ 60, BUZ 41A, 2SK358, 2SK924, 2SK1391
45636	IRF625	<1,5Ohm(2,1A)	BUZ 60, BUZ 41A, 2SK358, 2SK924, 2SK1391
45637	IRF626	IRF 624, 275V	BUZ 60, BUZ 41A, 2SK553
45638	IRF627	IRF 625, 275V	BUZ 60, BUZ 41A, 2SK553
45639	IRF630	200V, 9A, 74W, <0,4Ohm(5,4A)	BUZ 31...32, 2SK459, 2SK925, 2SK1393
45640	IRF630FI	IRF 630, , 6A, 35W	2SK1478, 2SK1578, 2SK1957, 2SK2425
45641	IRF631	IRF 630, 150V	BUZ 31...32, 2SK740, 2SK925, 2SK1393
45642	IRF632	200V, 8A, 74W, <0,6Ohm(5A)	BUZ 31...32, 2SK459, 2SK925, 2SK1393
45643	IRF633	IRF 632, 150V	BUZ 31...32, 2SK740, 2SK925, 2SK1393
45644	IRF634	<0,45Ohm(5,1A)	2SK741, 2SK925, 2SK1221, 2SK1393
45645	IRF635	<0,68Ohm(4,1A)	2SK741, 2SK925, 2SK1221, 2SK1393
45646	IRF636	IRF 634, 275V	2SK554...555, 2SK894, 2SK1495...96
45647	IRF637	IRF 634, 275V	2SK554...555, 2SK894, 2SK1495...96
45648	IRF640	<0,18Ohm(11A)	BUZ 30A
45649	IRF640FI	IRF 640, , 10A, 40W	2SK526, 2SK1036, 2SK1762
45650	IRF641	IRF 640, 150V	BUZ 30A, PRF 540, PRF 542
45651	IRF642	<0,22Ohm(10A)	BUZ 30A
45652	IRF643	IRF 642, 150V	BUZ 30A, PRF 540, PRF 542
45653	IRF644	<0,28Ohm(8,4A)	BUZ 255
45654	IRF645	<0,34Ohm(8A)	BUZ 255
45655	IRF646	IRF 644, 275V	-
45656	IRF647	IRF 645, 275V	-
45657	IRF710	400V, 2A, 36W, <3,6Ohm(1,2A)	BUZ 74, MTP 2N40, 2SK382, 2SK892
45658	IRF711	IRF 710, 350V	BUZ 74, MTP 2N35, 2SK382, 2SK892
45659	IRF712	<3,6Ohm(1,1A)	BUZ 74, MTP 2N40, 2SK382, 2SK892
45660	IRF713	IRF 712, 350V	BUZ 74, MTP 2N35, 2SK382, 2SK892
45661	IRF720	400V, 3,3A, 50W, <1,8Ohm(2A)	BUZ 76, MTP 4N45, 2SK310...311, 2SK1244
45662	IRF720..723FI,P	71%Imax, 35W	BUK 445-450, 2SK503, 2SK1862...63
45663	IRF721	IRF 720, 350V	BUZ 76, MTP 4N45, 2SK310...311, 2SK1244
45664	IRF722	<2,5Ohm(1,8A)	BUZ 76, MTP 4N45, 2SK310...311, 2SK1244
45665	IRF723	IRF 722, 350V	BUZ 76, MTP 4N45, 2SK310...311, 2SK1244
45666	IRF730	400V, 5,5A, 74W, <1Ohm(3,3A)	BUZ 60, 2SK552...553, 2SK1156, 2SK1246
45667	IRF730..733FI,P	64%Imax, 35W	BUK 445-400, 2SK1231...32, 2SK1608
45668	IRF731	IRF 730, 350V	BUZ 60, 2SK552...553, 2SK1156, 2SK1246
45669	IRF732	400V, 4,5A, 74W, <1,5Ohm(3A)	BUZ 60, 2SK552...553, 2SK1156, 2SK1246
45670	IRF733	IRF 732, 350V	BUZ 60, 2SK552...553, 2SK1156, 2SK1246
45671	IRF740	<0,55Ohm(6A)	BUZ 61, MTP 10N40, 2SK1378
45672	IRF740..743FI,P	55%Imax, 40W	BUK 445-400, 2SK1231...32, 2SK1566
45673	IRF741	IRF 740, 350V	BUZ 61, MTP 10N35, 2SK1378
45674	IRF742	<0,8Ohm(5,2A)	BUZ 61, MTP 10N40, 2SK554...555, 2SK894

45675	IRF743	IRF 742, 350V	BUZ 61, MTP 10N35, 2SK554...555, 2SK894
45676	IRF820	500V, 2,5A, 50W, <3Ohm(1,5A)	2SK1244
45677	IRF820..823FI,P	70% I <sub>max</sub> , 35W	BUK 444-500, BUK 445-600, 2SK1833
45678	IRF821	IRF 820, 450V	2SK1244
45679	IRF822	500V, 2,2A, 50W, <4Ohm(1,4A)	2SK1244
45680	IRF823	IRF 822, 450V	2SK1244
45681	IRF830	<1,5Ohm(2,7A)	BUZ 41A...42, MTP 6N55, 2SK553, 2SK893
45682	IRF830..833FI,P	63% I <sub>max</sub> , 35W	BUK 445-500, 2SK1232, 2SK1608, 2SK1627
45683	IRF831	IRF 830, 450V	BUZ 41A...42, MTP 6N55, 2SK553, 2SK893
45684	IRF832	500V, 4A, 74W, <2Ohm(2,5A)	BUZ 41A...42, MTP 6N55, 2SK553, 2SK893
45685	IRF833	IRF 832, 450V	BUZ 41A...42, MTP 6N55, 2SK553, 2SK893
45686	IRF840	<0,85Ohm(4,8A)	MTP 8N50, 2SK555, 2SK894, 2SK1496
45687	IRF840..843FI,P	56% I <sub>max</sub> , 40W	2SK1232, 2SK1608, 2SK1567, 2SK1627
45688	IRF841	IRF 840, 450V	MTP 8N45, 2SK555, 2SK894, 2SK1495...96
45689	IRF842	<1,1Ohm(4,4A)	MTP 8N50, 2SK555, 2SK894, 2SK1496
45690	IRF843	IRF 842, 450V	MTP 8N45, 2SK555, 2SK894, 2SK1495...96
45691	IRF9120..9123	IRF 9520..9523	2SJ115, 2SJ118...119
45692	IRF9120..9123	IRF 9520..9523	2SJ115, 2SJ118...119
45693	IRF9130	<0,3Ohm(6,5A)	MTM 12P10, 2SJ112...113
45694	IRF9130	<0,3Ohm(6,5A)	MTM 12P10, 2SJ112...113
45695	IRF9131	IRF 9130, 60V	MTM 12P06, 2SJ112...113
45696	IRF9131	IRF 9130, 60V	MTM 12P06, 2SJ112...113
45697	IRF9132	<0,4Ohm(6,5A)	MTM 12P10, 2SJ112...113
45698	IRF9132	<0,4Ohm(6,5A)	MTM 12P10, 2SJ112...113
45699	IRF9133	IRF 9132, 60V	MTM 12P06, 2SJ112...113
45700	IRF9133	IRF 9132, 60V	MTM 12P06, 2SJ112...113
45701	IRF9140	<0,2Ohm(10A)	MTH 20P10
45702	IRF9140	<0,2Ohm(10A)	MTH 20P10
45703	IRF9141	IRF 9140, 60V	MTH 20P08
45704	IRF9141	IRF 9140, 60V	MTH 20P08
45705	IRF9142	<0,3Ohm(10A)	MTH 20P10
45706	IRF9142	<0,3Ohm(10A)	MTH 20P10
45707	IRF9143	IRF 9142, 60V	MTH 20P08
45708	IRF9143	IRF 9142, 60V	MTH 20P08
45709	IRF9150	<0,15Ohm(10A)	-
45710	IRF9150	<0,15Ohm(10A)	-
45711	IRF9151	IRF 9150, 60V	MTH 25P06
45712	IRF9151	IRF 9150, 60V	MTH 25P06
45713	IRF9220..9223	IRF 9620..9623	-
45714	IRF9220..9223	IRF 9620..9623	-
45715	IRF9230	<0,8Ohm(3,5A)	MTM 8P20, 2SJ56, 2SJ114, 2SJ351...352
45716	IRF9230	<0,8Ohm(3,5A)	MTM 8P20, 2SJ56, 2SJ114, 2SJ351...352
45717	IRF9231	IRF 9230, 150V	MTM 8P18, 2SJ55...56, 2SJ114, 2SJ351...352
45718	IRF9231	IRF 9230, 150V	MTM 8P18, 2SJ55...56, 2SJ114, 2SJ351...352
45719	IRF9232	<1,2Ohm(3,5A)	MTM 8P20, 2SJ56, 2SJ114, 2SJ351...352



45720	IRF9232	<1,2Ohm(3,5A)	MTM 8P20, 2SJ56, 2SJ114, 2SJ351...352
45721	IRF9233	IRF 9232, 150V	MTM 8P18, 2SJ55...56, 2SJ114, 2SJ351...352
45722	IRF9233	IRF 9232, 150V	MTM 8P18, 2SJ55...56, 2SJ114, 2SJ351...352
45723	IRF9240	<0,5Ohm(6A)	2SJ131
45724	IRF9240	<0,5Ohm(6A)	2SJ131
45725	IRF9241	IRF 9240, 150V	2SJ131, 2SJ200
45726	IRF9241	IRF 9240, 150V	2SJ131, 2SJ200
45727	IRF9242	200V, 9A, 125W, <0,7Ohm(6A)	2SJ131
45728	IRF9242	200V, 9A, 125W, <0,7Ohm(6A)	2SJ131
45729	IRF9243	IRF 9242, 150V	2SJ131, 2SJ200
45730	IRF9243	IRF 9242, 150V	2SJ131, 2SJ200
45731	IRF9510	100V, 4A, 43W, <1,2Ohm(2,4A)	BUZ 172, MTP 5P18...25, 2SJ134
45732	IRF9510S..9540S	IRF 9510S..9540S	-
45733	IRF9511	IRF 9510, 60V	BUZ 172, MTP 5P18...25, 2SJ102, 2SJ134
45734	IRF9512	<1,5Ohm(1,5A)	BUZ 172, MTP 5P18...25, 2SJ134
45735	IRF9513	IRF 9512, 60V	BUZ 172, MTP 5P18...25, 2SJ102, 2SJ134
45736	IRF9520	<0,6Ohm(4,1A)	MTP 8P10, 2SJ247
45737	IRF9521	IRF 9520, 60V	MTP 8P08, 2SJ247
45738	IRF9522	100V, 5A, 60W, <0,8Ohm(3,5A)	MTP 8P10, 2SJ247
45739	IRF9523	IRF 9522, 60V	MTP 8P08, 2SJ247
45740	IRF9530	<0,3Ohm(7,2A)	MTP 12P10, 2SJ127, 2SJ138
45741	IRF9531	IRF 9530, 60V	MTP 12P06, 2SJ123, 2SJ127, 2SJ138
45742	IRF9532	<0,4Ohm(6,5A)	MTP 12P10, 2SJ127, 2SJ138
45743	IRF9533	IRF 9532, 60V	MTP 12P06, 2SJ123, 2SJ127, 2SJ138
45744	IRF9540	<0,2Ohm(11A)	2SJ221
45745	IRF9541	IRF 9540, 60V	MTP 20P06, 2SJ174, 2SJ221, 2SJ291
45746	IRF9542	<0,3Ohm(10A)	2SJ221
45747	IRF9543	IRF 9542, 60V	MTP 20P06, 2SJ174, 2SJ221, 2SJ291
45748	IRF9610	200V, 1,8A, 20W, <3Ohm(0,9A)	BUZ 173, MTP 3P25
45749	IRF9610S..9640S	IRF 9610S..9640S	-
45750	IRF9611	IRF 9610, 150V	BUZ 173, MTP 3P25
45751	IRF9612	<5,5Ohm(0,9A)	BUZ 173, MTP 3P25
45752	IRF9613	IRF 9612, 150V	BUZ 173, MTP 3P25
45753	IRF9620	<1,5Ohm(1,5A)	BUZ 173, MTP 3P25
45754	IRF9621	IRF 9620, 150V	BUZ 173, MTP 3P25
45755	IRF9622	200V, 3A, 40W, <2,4Ohm(1,5A)	BUZ 173, MTP 3P25
45756	IRF9623	IRF 9622, 150V	BUZ 173, MTP 3P25
45757	IRF9630	<0,8Ohm(3,9A)	-
45758	IRF9631	IRF 9630, 150V	-
45759	IRF9632	<1,2Ohm(3,5A)	-
45760	IRF9633	IRF 9632, 150V	-
45761	IRF9640	<0,5Ohm(6,6A)	-
45762	IRF9641	IRF 9640, 150V	2SJ127
45763	IRF9642	200V, 9A, 125W, <0,7Ohm(6A)	-
45764	IRF9643	IRF 9642, 150V	2SJ127



45765	IRF9Z..S	IRF 9Z..	-
45766	IRF9Z10	<0,50hm(2,5A)	BUZ 171...172, IRF 9521, 2SJ102, 2SJ153
45767	IRF9Z12	IRF 9Z10, 4A, <0,70hm(2,5A)	IRF 9Z10
45768	IRF9Z14	60V, 6,7A, 43W, <0,50hm(4A)	IRF 9630...33, 2SJ247
45769	IRF9Z15	IRF 9Z14, 4A, <0,70hm(2,5A)	IRF 9Z14
45770	IRF9Z20	<0,280hm(5,6A)	IRF 9531, IRF 9533, 2SJ122...123, 2SJ169
45771	IRF9Z22	<0,330hm(5,6A)	IRF 9Z20
45772	IRF9Z24	<0,280hm(6,6A)	IRF 9531, IRF 9533, 2SJ122...123, 2SJ169
45773	IRF9Z25	<0,330hm(5,6A)	IRF 9Z24
45774	IRF9Z30	<0,140hm(9,3A)	BUZ 271, IRF 9541, 2SJ174, 2SJ291
45775	IRF9Z32	<0,210hm(9,3A)	IRF 9Z30
45776	IRF9Z34	<0,140hm(11A)	IRF 9541, 2SJ174, 2SJ291
45777	IRF9Z35	<0,210hm(9,3A)	IRF 9Z34
45778	IRFAC30	600V, 3,6A, 74W, <2,20hm(2A)	BUZ 84, BUZ 307, 2SK351, 2SK954, 2SK1213
45779	IRFAC32	600V, 3,2A, 74W, <2,70hm(2A)	BUZ 84, BUZ 307, 2SK351, 2SK954, 2SK1213
45780	IRFAC40	<1,20hm(3,4A)	BUZ 94, BUZ 332A, 2SK684, 2SK1032
45781	IRFAC42	<1,50hm(3,4A)	BUZ 94, BUZ 332A, 2SK684, 2SK1032
45782	IRFAE40	<20hm(2,8A)	BUZ 84, BUZ 355...356, 2SK351, 2SK695
45783	IRFAE42	<2,40hm(2,8A)	BUZ 84, BUZ 355...356, 2SK351, 2SK695
45784	IRFAE50	<1,20hm(4,2A)	BUK 638-800, BUZ 305, 2SK684, 2SK1032
45785	IRFAE52	<1,40hm(4,2A)	BUK 638-800, BUZ 305, 2SK684, 2SK1032
45786	IRFAF40	<2,50hm(2,5A)	BUZ 54, BUZ 357...358, 2SK727, 2SK1461
45787	IRFAF42	<30hm(2,5A)	BUZ 54, BUZ 357...358, 2SK727, 2SK1461
45788	IRFAF50	<1,60hm(3,6A)	2SK1358, 23SK1502, 2SK1692, 2SK1795...96
45789	IRFAF52	<1,90hm(3,6A)	BUZ 54, BUZ 357...358, 2SK685, 2SK727
45790	IRFAG40	<3,50hm(2,3A)	BUZ 54, BUZ 357...358, 2SK685, 2SK1359
45791	IRFAG42	<4,20hm(2,3A)	BUZ 54, BUZ 357...358, 2SK685, 2SK1359
45792	IRFAG50	<20hm(3,2A)	BUZ 54, BUZ 357, 2SK685, 2SK1120
45793	IRFAG52	<2,40hm(3,2A)	BUZ 54, BUZ 357...358, 2SK685, 2SK1120
45794	IRFBC20	<4,40hm(1,3A)	BUK 456-800, BUZ 80, 2SK858, 2SK1323
45795	IRFBC30	<2,20hm(2,2A)	BUZ 90, 2SK1117, 2SK1402, 2SK1809
45796	IRFBC32	600V, 3,2A, 74W, <2,70hm(2A)	BUZ 90, 2SK1117, 2SK1402, 2SK1809
45797	IRFBC40	<1,20hm(3,7A)	BUK 657-600, BUZ 91
45798	IRFBC42	<1,60hm(3,4A)	BUK 657-600, BUZ 91
45799	IRFBE20	<6,50hm(1,1A)	BUZ 80, 2SK1199, 2SK1324, 2SK1456
45800	IRFBE30	<30hm(2,5A)	BUZ 81, 2SK1639, 2SK1501, 2SK1807
45801	IRFBF20	900V, 1,7A, 54W, <80hm(1A)	BUZ 50, 2SK1199, 2SK1324, 2SK1456
45802	IRFBF30	<3,70hm(2,2A)	2SK1501, 2SK1639, 2SK1643, 2SK1807
45803	IRFBG20	<110hm(0,84A)	BUK 456-1000, BUZ 51
45804	IRFBG30	<50hm(1,9A)	BUK 456-1000, BUZ 51
45805	IRFF110..113	60..100V, 3..3,5A, 15W(Tc25°)	-
45806	IRFF120..123	60..100V, 5..6A, 20W(Tc25°)	-
45807	IRFF130..133	60..100V, 7..8A, 25W(Tc25°)	-
45808	IRFF210..213	1,8..2,2A, 15W(Tc25°)	-
45809	IRFF220..223	150..200V, 3..3,5A, 20W(Tc25°)	-

45810	IRFF230..233	4,5..5,5A,25W(Tc25°)	-
45811	IRFF310..313	5°	-
45812	IRFF320..323	350..400V, 2..2,5A, 20W(Tc25°)	-
45813	IRFF330..333	350..400V, 3..3,5A, 25W(Tc25°)	-
45814	IRFF420..423	1,4..1,6A,20W(Tc25°)	-
45815	IRFF430..433	5°	-
45816	IRFF9110..9113	60..100V, 2,3..2,6A,15W(Tc25°)	-
45817	IRFF9120..9123	60..100V, 3,5..4A, 20W(Tc25°)	-
45818	IRFF9130..9133	60..100V, 5,5..6,5A,25W(Tc25°)	-
45819	IRFF9210..9213	1,3..1,6A,15W(Tc25°)	-
45820	IRFF9220..9223	150..200V, 2..2,5A, 20W(Tc25°)	-
45821	IRFF9230..9233	150..200V, 3,5..4A, 25W(Tc25°)	-
45822	IRFH150	100V, 30A, 150W, <135/225ns	-
45823	IRFH250	200V, 30A, 150W, <135/225ns	-
45824	IRFH350	400V, 15A, 150W, <100/225ns	-
45825	IRFH450	500V, 13A, 150W, <85/220ns	-
45826	IRFI510G	<0,54Ohm(2,7A)	BUK 442-100, BUK 542-100, 2SK1260
45827	IRFI520G	<0,27Ohm(4,3A)	BUK 443-100, BUZ 72(A)F, 2SK1261
45828	IRFI530G	<0,16Ohm(5,8A)	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
45829	IRFI540G	<77mOhm(10A)	BUK 426-100, 2SK1307, 2SK1318, 2SK1432
45830	IRFI614G	250V, 2,1A, 23W, <2Ohm(1,3A)	BUK 444-400, 2SK1833
45831	IRFI620G	<0,8Ohm(2,5A)	BUK 444-200, BUZ 73(A)F
45832	IRFI624G	250V, 3,4A, 30W, <1,1Ohm(2A)	BUK 445-400, 2SK530, 2SK1377
45833	IRFI630G	<0,40Ohm(3,5A)	BUK 445-200, 2SK1478, 2SK1668, 2SK1957
45834	IRFI634G	<0,45Ohm(3,4A)	2SK1478, 2SK1568, 2SK1668
45835	IRFI640G	<0,18Ohm(5,9A)	BUK 426-200, 2SK526, 2SK1036, 2SK2212
45836	IRFI644G	<0,28Ohm(4,7A)	2SK1478, 2SK1568, 2SK1668..69
45837	IRFI720G	<1,8Ohm(1,6A)	BUK 445-450, 2SK503, 2SK1862...63
45838	IRFI730G	400V, 3,7A, 35W, <1Ohm(2,7A)	BUK 445-400, 2SK530, 2SK1231...32
45839	IRFI740G	<0,55Ohm(3,2A)	BUK 445-400, 2SK530, 2SK1231...32
45840	IRFI820G	500V, 2,1A, 30W, <3Ohm(1,3A)	BUK 444-500, 2SK1833
45841	IRFI830G	<1,5Ohm(1,9A)	BUK 445-500, 2SK1863
45842	IRFI840G	<0,85Ohm(2,8A)	BUK 427-500, 2SK1232, 2SK1608, 2SK1627
45843	IRFI9520G	<0,6Ohm(3,1A)	2SJ248, 2SJ350
45844	IRFI9530G	<0,3Ohm(4,6A)	2SJ139
45845	IRFI9540G	<0,2Ohm(6,6A)	2SJ139
45846	IRFI9620G	200V, 2A, 30W, <1,5Ohm(1,8A)	-
45847	IRFI9630G	<0,8Ohm(2,6A)	-
45848	IRFI9640G	<0,5Ohm(3,7A)	-
45849	IRFI9Z14G	<0,5Ohm(3,1A)	2SJ248, 2SJ350
45850	IRFI9Z24G	<0,28Ohm(5,1A)	2SJ137, 2SJ147, 2SJ175
45851	IRFI9Z34G	<0,14Ohm(7,2A)	2SJ143, 2SJ176, 2SJ293, 2SJ321
45852	IRFIBC20G	600V, 1,7A, 30W, <4,4Ohm(1A)	BUK 445-600, 2SK1758, 2SK1834
45853	IRFIBC30G	<2,2Ohm(1,5A)	2SK1572, 2SK1767, 2SK2144
45854	IRFIBC40G	<1,2Ohm(2,1A)	2SK1572, 2SK1767, 2SK2144

45855	IRFIBE20G	<6,5Ohm(0,84A)	BUK 446-800, 2SK1459, 2SK1834
45856	IRFIBE30G	800V, 2,1A, 35W, <30hm(1,3A)	BUK 446-800, 2SK1459, 2SK1834
45857	IRFIBF20G	<80hm(0,72A)	BUK 446-1000, 2SK808A
45858	IRFIBF30G	<3,70hm(1,1A)	2SK1143, 2SK1275, 2SK1459
45859	IRFIP044	<28mOhm(26A)	2SK1298, 2SK1424, 2SK1666, 2SK2203
45860	IRFIP054	<14mOhm(38A)	2SK1425
45861	IRFIP140	<77mOhm(14A)	BUK 426-100, 2SK1435
45862	IRFIP150	<55mOhm(19A)	2SK1435...36
45863	IRFIP240	<0,180hm(8,4A)	2SK2008
45864	IRFIP244	<0,280hm(6,6A)	-
45865	IRFIP250	<85mOhm(13A)	-
45866	IRFIP254	<0,140hm(10A)	-
45867	IRFIP340	<0,550hm(4,8A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
45868	IRFIP350	<0,30hm(6,6A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
45869	IRFIP440	<0,850hm(3,8A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
45870	IRFIP448	<0,60hm(4,4A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
45871	IRFIZ14G	60V, 8A, 27W, <0,20hm(4,8A)	BUK 442-60, 2SK1033, 2SK1099, 2SK1344
45872	IRFIZ24G	60V, 14A, 37W, <0,10hm(8,4A)	2SK1094, 2SK1419
45873	IRFIZ34G	<0,050hm(12A)	2SK943, 2SK1095, 2SK1345...46, 2SK1420
45874	IRFIZ44G	<28mOhm(18A)	2SK1262
45875	IRFIZ48G	<18mOhm(22A)	2SK1257, 2SK1653, 2SK1952
45876	IRFJ120	100V, 8A, 40W, <0,30hm(4A)	BUZ 20, BUZ 72, 2SK470, 2SK740, 2SK918
45877	IRFJ121	IRFJ 120, 60V	BUZ 20, BUZ 72, 2SK470, 2SK740, 2SK918
45878	IRFJ122	100V, 7A, 40W, <0,40hm(4A)	BUZ 20, BUZ 72, 2SK470, 2SK740, 2SK918
45879	IRFJ123	IRFJ 122, 60V	BUZ 20, BUZ 72, 2SK470, 2SK740, 2SK918
45880	IRFJ130	<0,180hm(6A)	BUZ 20, BUZ 72, 2SK740, 2SK918, 2SK921
45881	IRFJ131	IRFJ 130, 60V	BUZ 20, BUZ 72, 2SK740, 2SK918, 2SK921
45882	IRFJ132	<0,250hm(6A)	BUZ 20, BUZ 72, 2SK740, 2SK918, 2SK921
45883	IRFJ133	IRFJ 132, 60V	BUZ 20, BUZ 72, 2SK740, 2SK918, 2SK921
45884	IRFJ140	<85mOhm(10A)	BUZ 21...22, 2SK919, 2SK922
45885	IRFJ141	IRFJ 140, 60V	BUZ 21...22, 2SK919, 2SK922
45886	IRFJ142	<0,110hm(10A)	BUZ 20...21, 2SK918...919, 2SK921...922
45887	IRFJ143	IRFJ 142, 60V	BUZ 20...21, 2SK918...919, 2SK921...22
45888	IRFJ220	200V, 5A, 40W, <0,80hm(2,5A)	BUZ 30, BUZ 73, 2SK477, 2SK741, 2SK924
45889	IRFJ221	IRFJ 220, 150V	BUZ 30, BUZ 73, 2SK477, 2SK741, 2SK924
45890	IRFJ222	200V, 4A, 40W, <1,20hm(2,5A)	BUZ 30, BUZ 73, 2SK477, 2SK741, 2SK924
45891	IRFJ223	IRFJ 222, 150V	BUZ 30, BUZ 73, 2SK477, 2SK741, 2SK924
45892	IRFJ230	200V, 8A, 50W, <0,40hm(4A)	BUZ 30, BUZ 73, 2SK477, 2SK741
45893	IRFJ231	IRFJ 230, 150V	BUZ 30, BUZ 73, 2SK477, 2SK741
45894	IRFJ232	200V, 6,5A, 50W, <0,60hm(4A)	BUZ 30, BUZ 73, 2SK477, 2SK741
45895	IRFJ233	IRFJ 232, 150V	BUZ 30, BUZ 73, 2SK477, 2SK741
45896	IRFJ240	<0,180hm(7A)	BUK 456-200, BUZ 30A, IRF 640, 2SK891
45897	IRFJ241	IRFJ 240, 150V	BUK 456-200, BUZ 30A, IRF 640, 2SK891
45898	IRFJ242	<0,220hm(7A)	BUZ 31...32, 2SK459, 2SK925
45899	IRFJ243	IRFJ 242, 150V	BUZ 31...32, 2SK459, 2SK470, 2SK925

45900	IRFJ320	400V, 3A, 40W, <1,8Ohm(1,6A)	BUZ 76, IRF 720, IRF 722, 2SK310...311
45901	IRFJ321	IRF 320, 350V	BUZ 76, IRF 720, IRF 722, 2SK310...311
45902	IRFJ322	<2,5Ohm(1,6A)	BUZ 76, IRF 720, IRF 722, 2SK310...311
45903	IRFJ323	IRF 322, 350V	BUZ 76, IRF 720, IRF 722, 2SK310...311
45904	IRFJ330	400V, 4,5A, 50W, <1Ohm(2,5A)	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45905	IRFJ331	IRFJ 330, 350V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45906	IRFJ332	400V, 4A, 50W, <1,5Ohm(2,5A)	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45907	IRFJ333	IRFJ 332, 350V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45908	IRFJ340	70W, <0,55Ohm(6,2A)	IRF 840, IRF 842, 2SK554...555
45909	IRFJ341	IRFJ 340, 350V	IRF 840, IRF 842, 2SK554...555
45910	IRFJ342	400V, 6A, 70W, <0,8Ohm(6,2A)	IRF 840, IRF 842, 2SK554...555
45911	IRFJ343	IRFJ 342, 350V	IRF 840, IRF 842, 2SK554...555
45912	IRFJ420	500V, 2,5A, 40W, <3Ohm(1A)	BUZ 74, IRF 820, 2SK382
45913	IRFJ421	IRFJ 420, 450V	BUZ 74, IRF 820, 2SK382
45914	IRFJ422	500V, 2A, 40W, <4Ohm(1A)	BUZ 74, IRF 820, IRF 822, 2SK382
45915	IRFJ423	IRFJ 422, 450V	BUZ 74, IRF 820, IRF 822, 2SK382
45916	IRFJ430	500V, 4A, 50W, <1,5Ohm(2,1A)	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45917	IRFJ431	IRFJ 430, 450V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45918	IRFJ432	500V, 3A, 50W, <2Ohm(2,1A)	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45919	IRFJ433	IRFJ 432, 450V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
45920	IRFJ440	<0,85Ohm(3,3A)	IRF 840, IRF 842, 2SK555
45921	IRFJ441	IRFJ 440, 450V	IRF 840, IRF 842, 2SK555
45922	IRFJ442	500V, 5A, 70W, <1,1Ohm(3,3A)	BUZ 41A...42, IRF 830, 2SK553
45923	IRFJ443	IRFJ 440, 450V	BUZ 41A...42, IRF 830, 2SK553
45924	IRFL110	23/24ns	-
45925	IRFL14	60/32ns	-
45926	IRFL210	200V, 0,96A, <1,5Ohm(0,58A)	-
45927	IRFL214	250V, 0,79A, <2Ohm(0,47A)	-
45928	IRFL9014	74/41ns	-
45929	IRFL9110	100V, 1,1A, <1,2Ohm(0,66A)	-
45930	IRFM040	<0,04Ohm(23A)	-
45931	IRFM040	<0,04Ohm(23A)	-
45932	IRFM140	<0,1Ohm(15A)	-
45933	IRFM140	<0,1Ohm(15A)	-
45934	IRFM150	<65mOhm(21A)	-
45935	IRFM150	<65mOhm(21A)	-
45936	IRFM240	200V, 15A, 96W, <0,2Ohm(9A)	-
45937	IRFM240	200V, 15A, 96W, <0,2Ohm(9A)	-
45938	IRFM250	<0,1Ohm(16A)	-
45939	IRFM250	<0,1Ohm(16A)	-
45940	IRFM340	<0,56Ohm(5,4A)	-
45941	IRFM340	<0,56Ohm(5,4A)	-
45942	IRFM350	<0,31Ohm(8,6A)	-
45943	IRFM350	<0,31Ohm(8,6A)	-
45944	IRFM440	<0,86Ohm(4,3A)	-

45945	IRFM440	<0,86Ohm(4,3A)	-
45946	IRFM450	<0,42Ohm(7,2A)	-
45947	IRFM450	<0,42Ohm(7,2A)	-
45948	IRFM9140	<0,21Ohm(9,8A)	-
45949	IRFM9140	<0,21Ohm(9,8A)	-
45950	IRFM9240	<0,51Ohm(5,9A)	-
45951	IRFM9240	<0,51Ohm(5,9A)	-
45952	IRFP040	<28mOhm(32A)	BUZ 347...348, 2SK849, 2SK905, 2SK1297
45953	IRFP042	<35mOhm(32A)	BUZ 347...348, 2SK849, 2SK905, 2SK1297
45954	IRFP044	<28mOhm(34A)	2SK849, 2SK857, 2SK1124, 2SK1297
45955	IRFP045	<35mOhm(36A)	2SK849, 2SK857, 2SK1124, 2SK1297
45956	IRFP048	<18mOhm(44A)	2SK1423
45957	IRFP054	<14mOhm(54A)	-
45958	IRFP064	<9mOhm(78A)	-
45959	IRFP120..123	IRF 520..523	2SK631, 2SK1529
45960	IRFP130..133	IRF 530..533	2SK572
45961	IRFP140	<77mOhm(19A)	BUZ 349, 2SK906, 2SK1429, 2SK1433
45962	IRFP140	<77mOhm(19A)	BUZ 349, 2SK906, 2SK1429, 2SK1433
45963	IRFP141	IRFP 140, 80V	BUZ 349, 2SK906, 2SK1429, 2SK1433
45964	IRFP141	IRFP 140, 80V	BUZ 349, 2SK906, 2SK1429, 2SK1433
45965	IRFP142	<99mOhm(19A)	BUZ 349, 2SK906, 2SK1429, 2SK1433
45966	IRFP142	<99mOhm(19A)	BUZ 349, 2SK906, 2SK1429, 2SK1433
45967	IRFP143	IRFP 142, 80V	BUZ 349, 2SK906, 2SK1429, 2SK1433
45968	IRFP143	IRFP 142, 80V	BUZ 349, 2SK906, 2SK1429, 2SK1433
45969	IRFP150	<55mOhm(25A)	BUZ 345, 2SK1263, 2SK1304
45970	IRFP150	<55mOhm(25A)	BUZ 345, 2SK1263, 2SK1304
45971	IRFP151	IRFP 150, 60V	BUZ 345, 2SK1263, 2SK1304
45972	IRFP151	IRFP 150, 60V	BUZ 345, 2SK1263, 2SK1304
45973	IRFP152	<80mOhm(22A)	BUZ 345, 2SK1263, 2SK1304
45974	IRFP152	<80mOhm(22A)	BUZ 345, 2SK1263, 2SK1304
45975	IRFP153	IRFP 152, 60V	BUZ 345, 2SK1263, 2SK1304
45976	IRFP153	IRFP 152, 60V	BUZ 345, 2SK1263, 2SK1304
45977	IRFP220..223	IRF 620..623	BUK 426-200
45978	IRFP230..233	IRF 630..633	BUK 426-200
45979	IRFP240	<0,18Ohm(12A)	BUZ 350, 2SK623, 2SK901, 2SK1491
45980	IRFP240	<0,18Ohm(12A)	BUZ 350, 2SK623, 2SK901, 2SK1491
45981	IRFP240FI	IRFP 240, , 12A, 55W	2SK820
45982	IRFP241	IRFP 240, 150V	BUZ 350, 2SK622...23, 2SK901, 2SK1267
45983	IRFP241	IRFP 240, 150V	BUZ 350, 2SK622...23, 2SK901, 2SK1267
45984	IRFP242	<0,22Ohm(11A)	BUZ 350, 2SK623, 2SK901, 2SK1491
45985	IRFP242	<0,22Ohm(11A)	BUZ 350, 2SK623, 2SK901, 2SK1491
45986	IRFP243	IRFP 242, 150V	BUZ 350, 2SK622...23, 2SK901, 2SK1267
45987	IRFP243	IRFP 242, 150V	BUZ 350, 2SK622...23, 2SK901, 2SK1267
45988	IRFP244	<0,28Ohm(9A)	BUZ323, 2SK623, 2SK901, 2SK1135, 2SK1401
45989	IRFP244	<0,28Ohm(9A)	BUZ323, 2SK623, 2SK901, 2SK1135, 2SK1401



45990	IRFP245	<0,34Ohm(8A)	BUZ323, 2SK623, 2SK901, 2SK1135, 2SK1401
45991	IRFP245	<0,34Ohm(8A)	BUZ323, 2SK623, 2SK901, 2SK1135, 2SK1401
45992	IRFP246	IRFP 244, 275V	BUZ323, 2SK788, 2SK899, 2SK1135, 2SK1401
45993	IRFP247	IRFP 245, 275V	BUZ323, 2SK788, 2SK899, 2SK1135, 2SK1401
45994	IRFP250	<85mOhm(18A)	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
45995	IRFP250	<85mOhm(18A)	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
45996	IRFP251	IRFP 250, 150V	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
45997	IRFP251	IRFP 250, 150V	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
45998	IRFP252	<0,12Ohm(17A)	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
45999	IRFP252	<0,12Ohm(17A)	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
46000	IRFP253	IRFP 252, 150V	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
46001	IRFP253	IRFP 252, 150V	BUZ341, 2SK851, 2SK902, 2SK1492, 2SK1669
46002	IRFP254	<0,14Ohm(14A)	2SK623, 2SK901, 2SK1641, 2SK1673...74
46003	IRFP254	<0,14Ohm(14A)	2SK623, 2SK901, 2SK1641, 2SK1673...74
46004	IRFP255	<0,17Ohm(13A)	2SK623, 2SK901, 2SK1641, 2SK1673...74
46005	IRFP255	<0,17Ohm(13A)	2SK623, 2SK901, 2SK1641, 2SK1673...74
46006	IRFP256	IRFP 254, 275V	2SK1674
46007	IRFP257	IRFP 256, 275V	2SK1674
46008	IRFP260	<55mOhm(28A)	-
46009	IRFP264	<75mOhm(23A)	-
46010	IRFP320..323	IRF 720..723	2SK635
46011	IRFP330..333	IRF 730..733	2SK501, 2SK2264
46012	IRFP340	<0,55Ohm(6,6A)	BUZ 325...326, 2SK351, 2SK634, 2SK724
46013	IRFP340	<0,55Ohm(6,6A)	BUZ 325...326, 2SK351, 2SK634, 2SK724
46014	IRFP341	IRFP 340, 350V	BUZ 325...326, 2SK351, 2SK634, 2SK724
46015	IRFP341	IRFP 340, 350V	BUZ 325...326, 2SK351, 2SK634, 2SK724
46016	IRFP342	<0,8Ohm(5,5A)	BUZ 325...326, 2SK351, 2SK634, 2SK724
46017	IRFP342	<0,8Ohm(5,5A)	BUZ 325...326, 2SK351, 2SK634, 2SK724
46018	IRFP343	IRFP 342, 350V	BUZ 325...326, 2SK351, 2SK634, 2SK724
46019	IRFP343	IRFP 342, 350V	BUZ 325...326, 2SK351, 2SK634, 2SK724
46020	IRFP350	<0,3Ohm(9,6A)	BUZ 323, 2SK788, 2SK899, 2SK1610
46021	IRFP350	<0,3Ohm(9,6A)	BUZ 323, 2SK788, 2SK899, 2SK1610
46022	IRFP350FI	IRFP 350	2SK1268...69, 2SK1331, 2SK1524
46023	IRFP351	IRFP 350, 350V	BUZ 323, 2SK788, 2SK899, 2SK1610
46024	IRFP351	IRFP 350, 350V	BUZ 323, 2SK788, 2SK899, 2SK1610
46025	IRFP352	<0,4Ohm(8,9A)	BUZ 323, 2SK788, 2SK899, 2SK1610
46026	IRFP352	<0,4Ohm(8,9A)	BUZ 323, 2SK788, 2SK899, 2SK1610
46027	IRFP353	IRFP 352, 350V	BUZ 323, 2SK788, 2SK899, 2SK1610
46028	IRFP353	IRFP 352, 350V	BUZ 323, 2SK788, 2SK899, 2SK1610
46029	IRFP360	<0,2Ohm(14A)	-
46030	IRFP362	<0,25Ohm(13A)	-
46031	IRFP420..423	IRF 820..823	2SK635
46032	IRFP430..433	IRF 830..833	-
46033	IRFP440	<0,85Ohm(6,3A)	BUZ 339, 2SK557, 2SK637, 2SK644, 2SK724
46034	IRFP440	<0,85Ohm(6,3A)	BUZ 339, 2SK557, 2SK637, 2SK644, 2SK724



46035	IRFP441	IRFP 440, 450V	BUZ 339, 2SK557, 2SK637, 2SK644, 2SK724
46036	IRFP441	IRFP 440, 450V	BUZ 339, 2SK557, 2SK637, 2SK644, 2SK724
46037	IRFP442	<1,1Ohm(4,9A)	BUZ 385, 2SK557, 2SK637, 2SK644, 2SK724
46038	IRFP442	<1,1Ohm(4,9A)	BUZ 385, 2SK557, 2SK637, 2SK644, 2SK724
46039	IRFP443	IRFP 442, 450V	BUZ 385, 2SK557, 2SK637, 2SK644, 2SK724
46040	IRFP443	IRFP 442, 450V	BUZ 385, 2SK557, 2SK637, 2SK644, 2SK724
46041	IRFP448	<0,6Ohm(6,6A)	BUZ 339, 2SK557, 2SK637, 2SK644, 2SK724
46042	IRFP450	<0,4Ohm(8,4A)	BUZ 338, 2SK788, 2SK899, 2SK1610
46043	IRFP450	<0,4Ohm(8,4A)	BUZ 338, 2SK788, 2SK899, 2SK1610
46044	IRFP450..453FI,P	IRFP 450..453, , 64%Imax, 70W	2SK1206, 2SK1268...1269, 2SK1523...24
46045	IRFP451	IRFP 450, 450V	BUZ 338, 2SK788, 2SK899, 2SK1610
46046	IRFP451	IRFP 450, 450V	BUZ 338, 2SK788, 2SK899, 2SK1610
46047	IRFP452	<0,5Ohm(7,9A)	BUZ 338, 2SK788, 2SK899, 2SK1610
46048	IRFP452	<0,5Ohm(7,9A)	BUZ 338, 2SK788, 2SK899, 2SK1610
46049	IRFP453	IRFP 452, 450V	BUZ 338, 2SK788, 2SK899, 2SK1610
46050	IRFP453	IRFP 452, 450V	BUZ 338, 2SK788, 2SK899, 2SK1610
46051	IRFP460	<0,27Ohm(12A)	2SK1411, 2SK1680
46052	IRFP462	<0,35Ohm(11A)	2SK1411, 2SK1680
46053	IRFP9120..9123	IRF 9520..9523	2SJ115, 2SJ118...119
46054	IRFP9130..9133	IRF 9530..9533	2SJ113, 2SJ200
46055	IRFP9140	<0,2Ohm(13A)	-
46056	IRFP9140	<0,2Ohm(13A)	-
46057	IRFP9141	IRFP 9140, 60V	-
46058	IRFP9141	IRFP 9140, 60V	-
46059	IRFP9142	<0,3Ohm(10A)	-
46060	IRFP9142	<0,3Ohm(10A)	-
46061	IRFP9143	IRFP 9142, 60V	-
46062	IRFP9143	IRFP 9142, 60V	-
46063	IRFP9150..9151	IRF 9150..9151	2SJ215
46064	IRFP9220..9223	IRF 9620..9623	IRF 9620...9623
46065	IRFP9230..9233	IRF 9630..9633	2SJ114, 2SJ351...352
46066	IRFP9240	<0,5Ohm(7,2A)	2SJ131
46067	IRFP9240	<0,5Ohm(7,2A)	2SJ131
46068	IRFP9241	IRFP 9240, 150V	2SJ131
46069	IRFP9241	IRFP 9240, 150V	2SJ131
46070	IRFP9242	<0,7Ohm(6,3A)	2SJ131
46071	IRFP9242	<0,7Ohm(6,3A)	2SJ131
46072	IRFP9243	IRFP 9242, 150V	2SJ131
46073	IRFP9243	IRFP 9242, 150V	2SJ131
46074	IRFPC30	<2,2Ohm(2,6A)	2SK695, 2SK793, 2SK1213, 2SK1403
46075	IRFPC40	<1,2Ohm(4,1A)	BUZ 305, BUZ 332A, 2SK684, 2SK1032
46076	IRFPC42	<1,6Ohm(3,7A)	BUZ 305, BUZ 332A, 2SK684, 2SK1032
46077	IRFPC50	<0,6Ohm(6A)	BUZ 334, 2SK1723, 2SK1968
46078	IRFPC60	<2,2Ohm(2,6A)	2SK1573
46079	IRFPE30	<2,2Ohm(2,6A)	BUZ 355...356, 2SK534, 2SK604, 2SK695

46080	IRFPE40	<20hm(3,2A)	BUZ 355...356, 2SK534, 2SK604, 2SK695
46081	IRFPE42	800V, 5,3A, 150W, <20hm(3A)	BUZ 355...356, 2SK534, 2SK604, 2SK695
46082	IRFPE50	<1,20hm(4,7A)	BUZ 305, 2SK684, 2SK1032, 2SK1358
46083	IRFPE52	<1,40hm(4,5A)	BUZ 305, 2SK684, 2SK1032, 2SK1358
46084	IRFPP30	<3,70hm(2,2A)	BUZ 357...358, 2SK685, 2SK727, 2SK1341
46085	IRFPP40	<2,50hm(2,8A)	BUZ 357...358, 2SK685, 2SK727, 2SK1341
46086	IRFPP42	<30hm(2,7A)	BUZ 357...358, 2SK685, 2SK727, 2SK1341
46087	IRFPP50	<1,60hm(4A)	-
46088	IRFPP52	<1,90hm(3,9A)	-
46089	IRFPG30	<50hm(1,9A)	2SK696
46090	IRFPG40	<3,50hm(2,6A)	BUZ 312, BUZ 357...358, 2SK685, 2SK1205
46091	IRFPG42	<4,20hm(2,5A)	BUZ 312, BUZ 357...358, 2SK685, 2SK1205
46092	IRFPG50	<20hm(3,6A)	2SK1120, 2SK1934
46093	IRFPG52	<2,40hm(3,5A)	2SK1120, 2SK1934
46094	IRFR010	<0,20hm(4,2A)	2SK1472, 2SK1748
46095	IRFR012	<0,30hm(4,2A)	2SK1472, 2SK1748
46096	IRFR014	<0,20hm(4,6A)	2SK1472, 2SK1748
46097	IRFR015	<0,30hm(4,2A)	2SK1472, 2SK1748
46098	IRFR020	50V, 15A, 42W, <0,10hm(8,7A)	-
46099	IRFR022	<0,120hm(8,7A)	-
46100	IRFR024	60V, 15A, 42W, <0,10hm(8,4A)	-
46101	IRFR025	<0,120hm(8,7A)	-
46102	IRFR110	<0,540hm(2,6A)	2SK1474, 2SK1804, 2SK2016
46103	IRFR111	IRFR 110, 80V	2SK1474, 2SK1804, 2SK2016
46104	IRFR120	<0,270hm(4,6A)	2SK1475, 2SK1557
46105	IRFR121	IRFR 120, 80V	2SK1475, 2SK1557
46106	IRFR210	<1,50hm(1,6A)	2SK1335
46107	IRFR212	<2,40hm(1,3A)	2SK1335
46108	IRFR214	250V, 2,2A, 25W, <20hm(1,3A)	-
46109	IRFR215	250V, 1,7A, 25W, <30hm(1A)	-
46110	IRFR220	<0,80hm(2,9A)	2SK1920
46111	IRFR221	IRFR 220, 150V	2SK1920
46112	IRFR222	<1,20hm(2,4A)	2SK1920
46113	IRFR224	<1,10hm(2,3A)	2SK1920
46114	IRFR310	400V, 1,7A, 25W, <3,60hm(1A)	2SK579...580, 2SK1151...52
46115	IRFR311	400V, 1A, 25W, <50hm(0,8A)	2SK579...580, 2SK1151...52
46116	IRFR320	<1,80hm(1,9A)	-
46117	IRFR321	IRFR 320, 350V	-
46118	IRFR322	<2,50hm(1,4A)	-
46119	IRFR410	500V, 1,5A, 42W, <70hm(1,5A)	2SK580, 2SK1152
46120	IRFR420	500V, 2,4A, 42W, <30hm(1,4A)	-
46121	IRFR421	IRFR 420, 450V	-
46122	IRFR422	500V, 2,2A, 42W, <40hm(1,4A)	-
46123	IRFR9010	<0,50hm(2,8A)	2SJ183, 2SJ239, 2SJ245, 2SJ279
46124	IRFR9012	<0,70hm(2,8A)	2SJ183, 2SJ239, 2SJ245, 2SJ279

46125	IRFR9014	<0,5Ohm(3,1A)	2SJ183, 2SJ239, 2SJ245, 2SJ279
46126	IRFR9015	<0,7Ohm(2,8A)	2SJ183, 2SJ239, 2SJ245, 2SJ279
46127	IRFR9020	<0,28Ohm(5,7A)	2SJ389
46128	IRFR9022	50V, 9A, 42W, <0,33Ohm(5,7A)	2SJ389
46129	IRFR9024	<0,28Ohm(5,3A)	2SJ389
46130	IRFR9025	60V, 9A, 42W, <0,33Ohm(5,7A)	2SJ389
46131	IRFR9110	<1,2Ohm(1,9A)	2SJ319
46132	IRFR9111	IRFR 9110, 80V	2SJ319
46133	IRFR9120	<0,6Ohm(3,4A)	2SJ195
46134	IRFR9121	IRFR 9120, 80V	2SJ195
46135	IRFR9210	200V, 1,9A, 25W, <3Ohm(1,1A)	2SJ319
46136	IRFR9212	200V, 1,6A, 25W, <4,5Ohm(1A)	2SJ319
46137	IRFR9220	<1,5Ohm(2,2A)	2SJ319
46138	IRFR9222	<2,4Ohm(1,8A)	2SJ319
46139	IRFRC20	600V, 2A, 42W, <4,4Ohm(1,2A)	-
46140	IRFS130	<0,16Ohm(8,3A)	BUK 426-200
46141	IRFS131	IRFS 130, 80V	BUK 426-200
46142	IRFS132	<0,23Ohm(8,3A)	BUK 426-200
46143	IRFS133	IRFS 132, 80V	BUK 426-200
46144	IRFS140	<77mOhm(17A)	BUK 426-100
46145	IRFS141	IRFS 140, 80V	BUK 426-100
46146	IRFS142	<0,1Ohm(17A)	BUK 426-100
46147	IRFS143	IRFS 142, 80V	BUK 426-100
46148	IRFS150	<55mOhm(22A)	2SK1435
46149	IRFS151	IRFS 150, 80V	2SK1435
46150	IRFS152	<80mOhm(22A)	2SK1435
46151	IRFS153	IRFS 152, 80V	2SK1435
46152	IRFS1Z0	100V, 0,82A, <2,4Ohm(0,49A)	2SK1485
46153	IRFS1Z3	80V, 0,75A, <3,2Ohm(0,45A)	2SK1078...79, 2SK1485
46154	IRFS230	200V, 6,2A, 42W, <0,4Ohm(5A)	BUK 426-200
46155	IRFS231	IRFS 230, 150V	BUK 426-200
46156	IRFS232	200V, 5,5A, 42W, <0,6Ohm(5A)	BUK 426-200
46157	IRFS233	IRFS 232, 150V	BUK 426-200
46158	IRFS240	<0,18Ohm(10A)	2SK2008
46159	IRFS241	IRFS 240, 150V	2SK2008
46160	IRFS242	<0,22Ohm(10A)	2SK2008
46161	IRFS243	IRFS 242, 150V	2SK2008
46162	IRFS250	<85mOhm(16A)	2SK2008
46163	IRFS251	IRFS 250, 150V	2SK2008
46164	IRFS252	<0,12Ohm(16A)	2SK2008
46165	IRFS253	IRFS 252, 150V	2SK2008
46166	IRFS330	400V, 3,8A, 42W, <1Ohm(3A)	BUK 427-450
46167	IRFS331	IRFS 330, 350V	BUK 427-450
46168	IRFS332	400V, 3,5A, 42W, <1,5Ohm(3A)	BUK 427-450
46169	IRFS333	IRFS 332, 350V	BUK 427-450

46170	IRFS340	<0,55Ohm(5,2A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
46171	IRFS341	IRFS 340, 350V	2SK1206, 2SK1225, 2SK1328, 2SK1831
46172	IRFS342	<0,80Ohm(5,2A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
46173	IRFS343	IRFS 342, 350V	2SK1206, 2SK1225, 2SK1328, 2SK1831
46174	IRFS350	<0,30Ohm(8A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
46175	IRFS351	IRFS 350, 350V	2SK1206, 2SK1225, 2SK1328, 2SK1831
46176	IRFS352	400V, 9A, 70W, <0,40Ohm(8A)	2SK1206, 2SK1225, 2SK1328, 2SK1831
46177	IRFS353	IRFS 352, 350V	2SK1206, 2SK1225, 2SK1328, 2SK1831
46178	IRFS430	<1,50Ohm(2,5A)	BUK 427-500
46179	IRFS431	IRFS 430, 450V	BUK 427-500
46180	IRFS432	500V, 2,8A, 42W, <20Ohm(2,5A)	BUK 427-500
46181	IRFS433	IRFS 432, 450V	BUK 427-500
46182	IRFS440	<0,85Ohm(4A)	BUK 427-500
46183	IRFS441	IRFS 440, 450V	BUK 427-500
46184	IRFS442	500V, 4,8A, 65W, <1,10Ohm(4A)	BUK 427-500
46185	IRFS443	IRFS 442, 450V	BUK 427-500
46186	IRFS450	500V, 9A, 70W, <0,40Ohm(7A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
46187	IRFS451	IRFS, 450, 450V	2SK1206, 2SK1329, 2SK1523, 2SK1696
46188	IRFS452	500V, 8,3A, 70W, <0,50Ohm(7A)	2SK1206, 2SK1329, 2SK1523, 2SK1696
46189	IRFS453	IRFS, 452, 450V	2SK1206, 2SK1329, 2SK1523, 2SK1696
46190	IRFS520	<0,270Ohm(5,6A)	BUK443-100, BUZ72(A)F, 2SK1261, 2SK1556
46191	IRFS521	IRFS 520, 80V	BUK443-100, BUZ72(A)F, 2SK1261, 2SK1556
46192	IRFS522	<0,360Ohm(5,6A)	BUK443-100, BUZ72(A)F, 2SK1261, 2SK1556
46193	IRFS523	IRFS 521, 80V	BUK443-100, BUZ72(A)F, 2SK1261, 2SK1556
46194	IRFS530	<0,160Ohm(8,3A)	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
46195	IRFS531	IRFS 530, 80V	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
46196	IRFS532	<0,230Ohm(8,3A)	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
46197	IRFS533	IRFS 532, 80V	BUK 545-100, 2SK1230, 2SK1305, 2SK1430
46198	IRFS540	<77mOhm(17A)	2SK1034, 2SK1306, 2SK1431, 2SK1558
46199	IRFS541	IRFS 540, 80V	2SK1034, 2SK1306, 2SK1431, 2SK1558
46200	IRFS542	<0,10Ohm(17A)	BUK445-100, 2SK1306, 2SK1034, 2SK1431
46201	IRFS543	IRFS 542, 80V	BUK445-100, 2SK1306, 2SK1034, 2SK1431
46202	IRFS620	200V, 4A, 30W, <0,80Ohm(2,5A)	BUK 444-200, BUZ 73(A)F
46203	IRFS621	IRFS 620, 150V	BUK 444-200, BUZ 73(A)F
46204	IRFS622	<1,20Ohm(2,5A)	BUK 444-200, BUZ 73(A)F
46205	IRFS623	IRFS 622, 150V	BUK 444-200, BUZ 73(A)F
46206	IRFS624	<1,10Ohm(2,1A)	BUK 445-400, 2SK530, 2SK1377
46207	IRFS625	<1,50Ohm(2,1A)	BUK 445-400, 2SK530, 2SK1377
46208	IRFS630	200V, 6,1A, 35W, <0,40Ohm(5A)	BUK 445-200, BUZ 73F, 2SK1957
46209	IRFS631	IRFS 630, 150V	BUK 445-200, BUZ 73F, 2SK1957
46210	IRFS632	200V, 5,5A, 35W, <0,40Ohm(5A)	BUK 445-200, BUZ 73F, 2SK1957
46211	IRFS633	IRFS 632, 150V	BUK 445-200, BUZ 73F, 2SK1957
46212	IRFS634	<0,450Ohm(4,1A)	2SK1478, 2SK1568...69, 2SK1668
46213	IRFS635	<0,680Ohm(4,1A)	2SK1478, 2SK1568...69, 2SK1668
46214	IRFS640	<0,180Ohm(10A)	2SK526, 2SK1036, 2SK1762, 2SK2212

46215	IRFS641	IRFS 640, 150V	2SK526, 2SK1036, 2SK1762, 2SK2212
46216	IRFS642	<0,22Ohm(10A)	2SK526, 2SK1036, 2SK1762, 2SK2212
46217	IRFS643	IRFS 642, 150V	2SK526, 2SK1036, 2SK1762, 2SK2212
46218	IRFS644	<0,28Ohm(8A)	2SK526, 2SK1036, 2SK1478, 2SK1762
46219	IRFS645	<0,34Ohm(8A)	2SK526, 2SK1036, 2SK1478, 2SK1762
46220	IRFS720	<1,8Ohm(1,8A)	BUK 444-400, 2SK1833
46221	IRFS721	IRFS 720, 350V	BUK 444-400, 2SK1833
46222	IRFS722	400V, 2A, 30W, <2,5Ohm(1,8A)	BUK 444-400, 2SK1833
46223	IRFS723	IRFS 722, 350V	BUK 444-400, 2SK1833
46224	IRFS730	400V, 3,5A, 35W, <1Ohm(3A)	BUK 445-450, 2SK503, 2SK1862...63
46225	IRFS731	IRFS 730, 350V	BUK 445-450, 2SK503, 2SK1862...63
46226	IRFS732	400V, 3A, 35W, <1,5Ohm(3A)	BUK 445-450, 2SK503, 2SK1862...63
46227	IRFS733	IRFS 732, 350V	BUK 445-450, 2SK503, 2SK1862...63
46228	IRFS740	<0,55Ohm(5,2A)	2SK1608, 2SK1231...32, 2SK1351, 2SK1377
46229	IRFS741	IRFS 740, 350V	2SK1608, 2SK1231...32, 2SK1351, 2SK1377
46230	IRFS742	<0,8Ohm(5,2A)	2SK1608, 2SK1231...32, 2SK1351, 2SK1377
46231	IRFS743	IRFS 742, 350V	2SK1608, 2SK1231...32, 2SK1351, 2SK1377
46232	IRFS820	500V, 2A, 30W, <3Ohm(1,4A)	BUK 444-500, BUK 445-600, 2SK1758
46233	IRFS821	IRFS 820, 450V	BUK 444-500, BUK 445-600, 2SK1758
46234	IRFS822	500V, 1,5A, 30W, <4Ohm(1,4A)	BUK 444-500, BUK 445-600, 2SK1758
46235	IRFS823	IRFS 822, 450V	BUK 444-500, BUK 445-600, 2SK1758
46236	IRFS830	500V, 3A, 35W, <1,5Ohm(2,5A)	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
46237	IRFS831	IRFS 830, 450V	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
46238	IRFS832	500V, 2,5A, 35W, <2Ohm(2,5A)	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
46239	IRFS833	IRFS 832, 450V	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
46240	IRFS840	<0,85Ohm(4A)	2SK1232, 2SK1351, 2SK1404, 2SK1608
46241	IRFS841	IRFS 840, 450V	2SK1232, 2SK1351, 2SK1404, 2SK1608
46242	IRFS842	500V, 4A, 40W, <1,1Ohm(4A)	2SK1232, 2SK1351, 2SK1404, 2SK1608
46243	IRFS843	IRFS 842, 450V	2SK1232, 2SK1351, 2SK1404, 2SK1608
46244	IRFS9130	<0,3Ohm(6,5A)	-
46245	IRFS9131	IRFS 9130, 60V	-
46246	IRFS9132	<0,4Ohm(6,5A)	-
46247	IRFS9133	IRFS 9132, 60V	-
46248	IRFS9140	<0,2Ohm(10A)	-
46249	IRFS9141	IRFS 9140, 60V	-
46250	IRFS9142	<0,3Ohm(10A)	-
46251	IRFS9143	IRFS 9142, 60V	-
46252	IRFS9230	<0,8Ohm(3,5A)	-
46253	IRFS9231	IRFS 9230, 150V	-
46254	IRFS9232	<1,2Ohm(3,5A)	-
46255	IRFS9233	IRFS 9232, 150V	-
46256	IRFS9240	200V, 7,6A, 65W, <0,5Ohm(6A)	-
46257	IRFS9241	IRFS 9240, 150V	-
46258	IRFS9242	200V, 6,2A, 65W, <0,7Ohm(6A)	-
46259	IRFS9243	IRFS 9242, 150V	-



46260	IRFS9520	100V, 5A, 30W, <0,6Ohm(3A)	2SJ248, 2SJ350
46261	IRFS9521	IRFS 9520, 60V	2SJ248, 2SJ350
46262	IRFS9522	100V, 4,3A, 30W, <0,8Ohm(3A)	2SJ248, 2SJ350
46263	IRFS9523	IRFS 9522, 60V	2SJ248, 2SJ350
46264	IRFS9530	100V, 8A, 35W, <0,3Ohm(6,5A)	2SJ139
46265	IRFS9531	IRFS 9530, 60V	2SJ137, 2SJ139, 2SJ147, 2SJ175
46266	IRFS9532	<0,4Ohm(6,5A)	2SJ248, 2SJ350
46267	IRFS9533	IRFS 9532, 60V	2SJ248, 2SJ350
46268	IRFS9540	<0,2Ohm(10A)	2SJ139
46269	IRFS9541	IRFS 9540, 60V	2SJ137, 2SJ139, 2SJ147, 2SJ175
46270	IRFS9542	<0,3Ohm(10A)	2SJ139
46271	IRFS9543	IRFS 9542, 60V	2SJ137, 2SJ139, 2SJ147, 2SJ175
46272	IRFS9620	200V, 3A, 30W, <1,5Ohm(1,5A)	2SJ306
46273	IRFS9621	IRFS 9620, 150V	2SJ159
46274	IRFS9622	<2,4Ohm(1,5A)	2SJ306
46275	IRFS9623	IRFS 9622, 150V	2SJ159
46276	IRFS9630	<0,8Ohm(3,5A)	2SJ410
46277	IRFS9631	IRFS 9630, 150V	2SJ410
46278	IRFS9632	200V, 3A, 35W, <1,2Ohm(3,5A)	2SJ410
46279	IRFS9633	IRFS 9632, 150V	2SJ410
46280	IRFS9640	200V, 6,2A, 40W, <0,5Ohm(6A)	2SJ410
46281	IRFS9641	IRFS 9640, 150V	2SJ410
46282	IRFS9642	200V, 5A, 40W, <0,7Ohm(6A)	2SJ410
46283	IRFS9643	IRFS 9642, 150V	2SJ410
46284	IRFSZ20	50V, 12,9A, 30W, <0,1Ohm(9A)	BUK 443-50, 2SK1094, 2SK1419
46285	IRFSZ22	50V, 12A, 30W, <0,12Ohm(9A)	BUK 443-50, 2SK1094, 2SK1419
46286	IRFSZ24	IRFSZ 20, 60V	2SK1094, 2SK1419
46287	IRFSZ25	IRFSZ 22, 60V	2SK1094, 2SK1419
46288	IRFSZ30	<50mOhm(18A)	BUK445-50, 2SK1095, 2SK1345...46, 2SK1420
46289	IRFSZ32	<70mOhm(18A)	BUK445-50, 2SK1095, 2SK1345...46, 2SK1420
46290	IRFSZ34	IRFSZ 30, 60V	2SK943, 2SK1095, 2SK1345...46, 2SK1420
46291	IRFSZ35	IRFSZ 32, 60V	2SK943, 2SK1095, 2SK1345...46, 2SK1420
46292	IRFSZ40	<28mOhm(23A)	2SK1257, 2SK1262, 2SK1421, 2SK1653
46293	IRFSZ42	<35mOhm(23A)	2SK1257, 2SK1262, 2SK1421, 2SK1653
46294	IRFSZ44	IRFSZ 40, 60V	2SK1257, 2SK1262, 2SK1421, 2SK1653
46295	IRFSZ45	IRFSZ 42, 60V	2SK1257, 2SK1262, 2SK1421, 2SK1653
46296	IRFU010..9222	IRFR 010..9222	IRFR 010...9222
46297	IRFUC20	IRFRC 20	IRFRC 20
46298	IRFW450	500V, 14A, 180W, <0,4Ohm	2SK1411, 2SK1678
46299	IRFZ010	<0,2Ohm(3,7A)	BUZ 71, 2SK464, 2SK428, 2SK442
46300	IRFZ012	<0,3Ohm(3,7A)	BUZ 71, 2SK464, 2SK428, 2SK442
46301	IRFZ14	60V, 10A, 43W, <0,2Ohm(6A)	BUZ 20, BUZ 72, 2SK428, 2SK442, 2SK970
46302	IRFZ14S	IRFZ 14	-
46303	IRFZ15	<0,3Ohm(5,8A)	BUZ 20, BUZ 72, 2SK428, 2SK442, 2SK970
46304	IRFZ20	50V, 15A, 40W, <0,1Ohm(9A)	BUZ 10, 2SK673, 2SK971, 2SK1416



46305	IRFZ20..22FI,P	IRFZ 20..22, , 83%Imax, 30W	BUZ 71(A)F, BUK 442-50, BUK 543-50
46306	IRFZ22	50V, 14A, 40W, <0,12Ohm(9A)	BUZ 10, 2SK673, 2SK971, 2SK1416
46307	IRFZ24	60V, 17A, 60W, <0,10Ohm(10A)	BUZ 21, 2SK942, 2SK1115, 2SK1417
46308	IRFZ24S	IRFZ 24	-
46309	IRFZ25	60V, 14A, 60W, <0,12Ohm(9A)	BUZ 21, 2SK673, 2SK971, 2SK1416
46310	IRFZ30	<50mOhm(16A)	BUK 555-50, BUZ 11, 2SK1296
46311	IRFZ32	<70mOhm(16A)	BUK 555-60, BUZ 11, 2SK972, 2SK1296
46312	IRFZ34	<50mOhm(18A)	BUK 555-60, 2SK856, 2SK1296
46313	IRFZ34S	IRFZ 34	-
46314	IRFZ35	<70mOhm(18A)	BUK 555-60, BUZ 21, 2SK942, 2SK1296
46315	IRFZ40	<28mOhm(29A)	BUZ 11...12, PRFZ 42, 2SK1418, 2SK1542
46316	IRFZ40FI	IRFZ 40, , 27A, 45W	2SK1262
46317	IRFZ42	<35mOhm(29A)	BUZ 11...12, PRFZ 42, 2SK1418, 2SK1542
46318	IRFZ44	<28mOhm(31A)	BUK 556-60
46319	IRFZ44S..48S	IRFZ 44..48	-
46320	IRFZ45	<35mOhm(33A)	2SK1911
46321	IRFZ46	<24mOhm(32A)	BUK 456-50, BUK 556-60, BUZ 100
46322	IRFZ48	<18mOhm(43A)	BUZ 100
46323	IRH150	100V, 38A, 150W, <55mOhm	-
46324	IRH254	250V, 19A, 150W, <0,19Ohm	-
46325	IRH450	500V, 10A, 150W, <0,6Ohm	-
46326	IRL510	100V, 5,6A, 43W, <0,54Ohm	BUK 552-100
46327	IRL520	100V, 9,2A, 60W, <0,27Ohm	2SK1300
46328	IRL530	100V, 15A, 88W, <0,16(9A)	2SK1301, 2SK1559, 2SK1561
46329	IRL540	100V, 28A, 150W, <77mOhm	-
46330	IRL541S..540S	IRL 510..540	-
46331	IRLI520G	100V, 7,2A, 37W, <0,27Ohm	BUK 543-100, 2SK1261, 2SK1556
46332	IRLI530G	100V, 9,7A, 42W, <0,16Ohm	BUK 545-100, 2SK1035, 2SK1305
46333	IRLI540G	100V, 17A, 48W, <77mOhm	2SK1266, 2SK1307, 2SK1348...49
46334	IRLIZ14G	60V, 8A, 27W, <0,2Ohm(4,8A)	BUK 542-60, 2SK1093, 2SK1256, 2SK1344
46335	IRLIZ24G	60V, 14A, 37W, <0,10Ohm(8,4A)	2SK1034, 2SK1094, 2SK1306, 2SK1558
46336	IRLIZ34G	<50mOhm(12A)	2SK943, 2SK1095, 2SK1345...46, 2SK1951
46337	IRLIZ44G	<28mOhm(18A)	2SK1257, 2SK1262, 2SK1653, 2SK1952
46338	IRLL014	60V, 2,7A, <0,2Ohm	-
46339	IRLL110	100V, 1,5A, <0,54Ohm	2SK1473, 2SK1485
46340	IRLR014	60V, 7,7A, 25W, <0,2Ohm	2SK1472, 2SK1748
46341	IRLR024	60V, 14A, 42W, <0,10Ohm	-
46342	IRLR110	100V, 4,3A, 25W, <0,54Ohm	2SK1474, 2SK1804, 2SK2016
46343	IRLR120	100V, 7,7A, 42W, <0,27Ohm	2SK1475, 2SK1557, 2SK1560
46344	IRLU014..120	IRLR 014..120	IRLR 014...120
46345	IRLZ14	60V, 10A, 43W, <0,2Ohm(6A)	2SK970, 2SK1114, 2SK1300
46346	IRLZ14S..44S	IRLZ 14..44	-
46347	IRLZ24	60V, 17A, 60W, <0,10Ohm(10A)	BUK 552-60, 2SK971...972, 2SK1115
46348	IRLZ34	<50mOhm(18A)	BUK 555-60, 2SK1291, 2SK1296
46349	IRLZ44	150W, <28mOhm(31A)	BUK 556-60

46350	IS	2SC3722K-S	2SC3722K
46351	IS	2SB792-S	2SB792
46352	IS	2SB1463-S	2SB1463
46353	IS	2SB1220-S	2SB1220
46354	IS-	2SC3513	2SC3513
46355	IS-	2SC4537	2SC4537
46356	ISS-53	BA 127	BA 127
46357	IT	2SB1463-T	2SB1463
46358	IT	2SB1220-T	2SB1220
46359	IT	2SB792-T	2SB792
46360	IT-	3SK162	3SK162
46361	ITR17052	17052	17052
46362	ITR17053	17053	17053
46363	ITT2001	100V, 0,15A, <50ns	BA 195, BA 197...198, BAV 19...21
46364	ITT2002	ITT 2001, 200V	BA 195, BA 197...198, BAV 20...21
46365	ITT2003	ITT 2001, 250V	BA 198, BAV 21
46366	ITT210	BA 102	BA 102
46367	ITT3001	70V, 0,1A, 250ns	BA 157...159, BAX 17, BY 206...207
46368	ITT3002	ITT 3001, 150V	BA 157...159, BAX 17, BY 206...207
46369	ITT3003	ITT 3001, 200V	BA 157...159, BAX 17, BY 206...207
46370	ITT410	BA 102	BA 102
46371	ITT600(DPD)	75V, 0,2A, <6ns	BAW 62, BAW 76, BAX 95, 1N4148...49
46372	ITT601(DPD)	50V, 0,2A, <6ns	BAW 62, BAW 76, BAX 95, 1N4148...49
46373	ITT789(A)	1N4148	1N4148
46374	IU	2SB1589	2SB1589
46375	IU-	2SK668	2SK668
46376	IV-	3SK136	3SK136
46377	IW	2SC5019	2SC5019
46378	IW-	3SK137	3SK137
46379	IW10612	BC 337	BC 337
46380	IW12134	BC 237	BC 237
46381	IW8377	BF 199	BF 199
46382	IW9288	BC 141	BC 141
46383	IX-	3SK138	3SK138
46384	IY	2SA1298-Y	2SA1298
46385	IY	KTA1298-Y	KTA 1298
46386	IY	2SC3515-Y	2SC3515
46387	IY-	3SK194	3SK194
46388	IZ-	3SK154	3SK15
46389	IZ2	3SK167-2	3SK167
46390	IZ3	3SK167-3	3SK167
46391	IZ4	3SK167-4	3SK167
46392	IZ5	3SK167-5	3SK167
46393	J	2SK1687	2SK1687
46394	J	HVC 357	HVC 357

46395	J	HVU 357	HVU 357
46396	J	S 5566J	S 5566J
46397	J005..06	50..600V, 10A	B...C10A
46398	J01	SO 2906R	SO 2906R
46399	J03	SO 2907AR	SO 2907AR
46400	J05	SO 2907R	SO 2907R
46401	J06	SO 2894R	SO 2894R
46402	J1	ZC 830A	ZC 830A
46403	J1	HSM 402WK	HSM 402WK
46404	J105	<3Ohm	-
46405	J106	<6Ohm	-
46406	J107	4/6ns	-
46407	J108	J 107, Idss>80mA, Up<10V	BFS 74, BFS 77, BSJ 108
46408	J109	<12Ohm	BSJ 109
46409	J110	<18Ohm	BFS 76, BFS 79, BSJ 110
46410	J111	13/35ns	BSJ 111
46411	J112	J 111, Idss>5mA, Up<5V	BSJ 112
46412	J113	J 111, Idss>2mA, Up<3V	BSJ 113
46413	J12	SO 2906AR	SO 2906AR
46414	J174	7/15ns	BSJ 174
46415	J175	15/30ns	BSJ 175
46416	J176	35/35ns	BSJ 176
46417	J177	25/45ns	BSJ 177
46418	J18	SO 679R	SO 679R
46419	J1O	KSA 1298-O	KSA 1298
46420	J1Y	KSA 1298-Y	KSA 1298
46421	J2	2SK67-J2	2SK67
46422	J2	F 1J2	F 1J2
46423	J2	2SC3142-2	2SC3142
46424	J2	2SK67-2	2SK67
46425	J2	2SK2552-J2	2SK2552
46426	J201	40V, Idss0,2..1mA, Up<1,5V	BFW 13, 2N4338
46427	J202	J 201, Idss0,9..4,5mA, Up<4V	2N5246, 2N5360
46428	J204	J 201, Idss0,2..3mA, Up<2V	-
46429	J210	25V, Idss2..15mA, Up<3V	BC 264A...B, BF 410B, 2SK192, 2SK370
46430	J211	J 210, Idss7..20mA, Up<4,5V	-
46431	J212	J 210, Idss15..40mA, Up<6V	BFT 10B
46432	J25	SO 3906R	SO 3906R
46433	J25	SS 05J25	SS 05J25
46434	J26	SO 3905R	SO 3905R
46435	J270	30V, Idss2..15mA, Up<2V	2SJ104, 2SJ107
46436	J271	J 270, Idss6..50mA, Up<4,5V	-
46437	J3	2SK67-J3	2SK67
46438	J3	2SC3142-3	2SC3142
46439	J3	2SK2552-J3	2SK2552

46440	J3	ZC 831A	ZC 831A
46441	J3	KDS 2236S	KDS 2236S
46442	J3	HSM 402S	HSM 402S
46443	J3	2SK67-3	2SK67
46444	J304	30V, Idss5..15mA, Up<6V	BF 256A, 2N5398
46445	J305	J 305, Idss1..8mA, Up<3V	-
46446	J308	25V, Idss12..60mA, Up<6,5V	BF 256C, BF 348, BFT 10A...B
46447	J309	J 308, Idss12..30mA, Up1..4V	BF 256C, BF 348, BFT 10A...B
46448	J310	J 308, Idss24..60mA, Up2..6,5V	BFT 10B...C, 2SK582
46449	J32	SO 5400R	SO 5400R
46450	J33	SO 5401R	SO 5401R
46451	J39	SO 692R	SO 692R
46452	J3U	SS 1J3U	SS 1J3U
46453	J3U	SS 3J3U	SS 3J3U
46454	J4	2SK67-J4	2SK67
46455	J4	F 1J4	F 1J4
46456	J4	2SK67-4	2SK67
46457	J4	2SK2552-J4	2SK2552
46458	J4	ZC 832A	ZC 832A
46459	J4	2SC3142-4	2SC3142
46460	J4	SS 1.5J4	SS 1.5J4
46461	J4	SS 1J4	SS 1J4
46462	J4	SS 3J4	SS 3J4
46463	J40	SO 506R	SO 506R
46464	J5	2SK67-J5	2SK67
46465	J5	2SK67-5	2SK67
46466	J5	ZC 834A	ZC 834A
46467	J5	2SK2552-J5	2SK2552
46468	J5	SS 1.5J5	SS 1.5J5
46469	J500	Uf25V(0,2	1N5287...5289
46470	J501	>2,2MOhm, Ulim<1,3V	1N5289...5291
46471	J502	>1,5MOhm, Ulim<1,5V	1N5291...5293
46472	J503	>1,2MOhm, Ulim<1,7V	1N5293...5295
46473	J504	Ulim<1,9V	1N5295...5297
46474	J505	Ulim<2,1V	1N5298...5301
46475	J506	Ulim<2,5V	1N5302...5305
46476	J507	Ulim<2,8V	1N5306...5309
46477	J508	Ulim<3,1V	1N5308...5311
46478	J509	Ulim<3,5V	1N5309...5313
46479	J510	Ulim<3,9V	1N5310...5314
46480	J511	Ulim<4,2V	1N5311...5314
46481	J6	2SK67-J6	2SK67
46482	J6	F 1J6	F 1J6
46483	J6	2SK2552-J6	2SK2552
46484	J6	ZC 835A	ZC 835A

46485	J6	2SK67-6	2SK67
46486	J6	SS 3J6	SS 3J6
46487	J6	SS 1J6	SS 1J6
46488	J7	2SK67-J7	2SK67
46489	J7	ZC 836A	ZC 836A
46490	J7	2SK67-7	2SK67
46491	J7	2SK2552-J7	2SK2552
46492	J8	2SK67-J8	2SK67
46493	J8	BCX 71RJ	BCX 71RJ
46494	J8	2SK67-8	2SK67
46495	J88	SO 970R	SO 970R
46496	J9	F 1J9	F 1J9
46497	J9	SS 1J9	SS 1J9
46498	J9	SS 2J9	SS 2J9
46499	JA	μPA603T	æPA603T
46500	JA	2SJ187	2SJ187
46501	JA(p,s)	BAV 74	BAV 74
46502	JA100	30V, 0,1A, 0,5W, 130MHz	BC 213, BC 258, BC 308, BC 558
46503	JA101	JA 100, 50V	BC 212, BC 257, BC 307, BC 557
46504	JB(s)	BAR 74	BAR 74
46505	JC	2SC2735	2SC2735
46506	JC	2SJ125-C	2SJ125
46507	JC	2SC4265	2SC4265
46508	JC	2SJ145-C	2SJ145
46509	JC(p,s)	BAL 74	BAL 74
46510	JC327(A)..328	BC 327(A)..328	BC 327(A)...328
46511	JC337(A)..338	BC 337(A)..338	BC 337(A)...338
46512	JC500	30V, 0,1A, 0,5W, 250MHz	BC 168, BC 183, BC 238, BC 548
46513	JC501	JC 500, 50V	BC 167, BC 182, BC 237, BC 547
46514	JC546..550	BC 546..550	BC 546...550
46515	JC556..560	BC 556..560	BC 556...560
46516	JD	2SJ125-D	2SJ125
46517	JD	BAW 56	BAW 56
46518	JD	2SJ145-D	2SJ145
46519	JD	2SJ287	2SJ287
46520	JE	BAV 99	BAV 99
46521	JE	2SJ125-E	2SJ125
46522	JE	2SJ145-E	2SJ145
46523	JE9011(D..I)	SS 9011(D..I)	SS 9011
46524	JE9012(D..H)	SS 9012(D..H)	SS 9012
46525	JE9013(D..H)	SS 9013(D..H)	SS 9013
46526	JE9014(A..D)	SS 9014(A..D)	SS 9014
46527	JE9015(A..C)	SS 9015(A..C)	SS 9015
46528	JE9016(D..I)	SS 9016(D..I)	SS 9016
46529	JE9018(D..I)	SS 9018(D..I)	SS 9018

46530	JE9100(A..G)	60V, 0,1A, 0,625W, 300MHz	BC 174, BC 546, 2SC2240, 2SC2459
46531	JE9101(A..D)	40V, 0,1A, 0,625W, 300MHz	BC 167, BC 182, BC 237, BC 547
46532	JF(p,s)	BAL 99	BAL 99
46533	JF494	BF 494	BF 494
46534	JF495	BF 495	BF 495
46535	JG	2SK879-GR	2SK879
46536	JG	2SK208-G	2SK208
46537	JG	2SJ316	2SJ316
46538	JG(s)	BAR 99	BAR 99
46539	JH	BAV 70	BAV 70
46540	JH	2SB1518-D	2SB1518
46541	JID	2SA1566-D	2SA1566
46542	JIE	2SA1566-E	2SA1566
46543	JJ	BAW 56	BAW 56
46544	JJ	BAV 70	BAV 70
46545	JJ	2SB1518-E	2SB1518
46546	JL	2SA1508	2SA1508
46547	JM	2SC2059-JM	2SC2059
46548	JM	2SC2059K-M	2SC2059K
46549	JM	2SC4099-M	2SC4099
46550	JN	2SC2059-JN	2SC2059
46551	JN	2SC2059K-N	2SC2059K
46552	JN	2SC4099-N	2SC4099
46553	JO	2SK208-O	2SK208
46554	JO	2SK879-O	2SK879
46555	JO	2SA1384-O	2SA1384
46556	JO1006	60V, 12A, PQ100W(175MHz)	-
46557	JO2015	65V, 9A, PQ50W(400MHz)	MRF 327[Motorola]
46558	JO2017	65V, 15A, PQ65W(440MHz)	-
46559	JO3037	36V, 5A, PQ37W(470MHz)	MRF 646[Motorola]
46560	JO3501	50V, 2A, PQ15W(470MHz)	-
46561	JO3502	50V, 4A, PQ35W(960MHz)	-
46562	JO4036	36V, 6,5A, PQ36W(175MHz)	-
46563	JO4045	36V, 6,5A, PQ45W(175MHz)	-
46564	JP	2SC2059-JP	2SC2059
46565	JP	BAW 56GT	BAW 56GT
46566	JP	2SC2059K-P	2SC2059K
46567	JP	2SC4099-P	2SC4099
46568	JP(p,s)	BAS 19	BAS 19
46569	JP(s)	BAW 101	BAW 101
46570	JPAD5	35V, 10mA, Ir<5pA(20V)	-
46571	JPAD50	35V, 10mA, Ir<50pA(20V)	-
46572	JR	2SK879-R	2SK879
46573	JR	2SK208-R	2SK208
46574	JR	2SA1384-R	2SA1384



46575	JR(p,s)	BAS 20	BAS 20
46576	JS	BAW 56G	BAW 56G
46577	JS	2SD2532	2SD2532
46578	JS(p,s)	BAS 21	BAS 21
46579	JS(s)	BAW 100	BAW 100
46580	JT	2SC4006	2SC4006
46581	JT	2SC4269	2SC4269
46582	JT(s)	BAS 28	BAS 28
46583	JU	BAS 16	BAS 16
46584	JV	1SV266	1SV266
46585	JV	1SV263	1SV263
46586	JV(s)	BAS 116	BAS 116
46587	JXs	BAV 170	BAV 170
46588	JY	2SK879-Y	2SK879
46589	JY	2SC3770	2SC3770
46590	JY	2SK208-Y	2SK208
46591	JY	2SJ244	2SJ244
46592	JYs	BAV 199	BAV 199
46593	JZ(s)	BAW 156	BAW 156
46594	K	2SK1688	2SK1688
46595	K	HVU 315	HVU 315
46596	K	2SB1208	2SB1208
46597	K005..06	50..600V, 25A	B...C25A
46598	K1	2SK57-1	2SK57
46599	K1	2SK2741	2SK2741
46600	K1(p)	BCW 71	BCW 71
46601	K1,5/20	OA 161	OA 161
46602	K11	BCX 70G	BCX 70G
46603	K12	BCX 70H	BCX 70H
46604	K13	BCX 70J	BCX 70J
46605	K14	BCX 70K	BCX 70K
46606	K14	2SK238-K14	2SK238
46607	K15	2SK238-K15	2SK238
46608	K16	2SK238-K16	2SK238
46609	K17	2SK238-K17	2SK238
46610	K1O	KSC 3265-O	KSC 3265
46611	K1V(A)10..16	K1V10..16, Itsm16A	-
46612	K1V10	K1V5, Ub95..113V, Itsm20A	-
46613	K1V11	K1V5, Ub104..118V, Itsm20A	-
46614	K1V12	K1V5, Ub110..125V, Itsm20A	-
46615	K1V14	Itsm20A	-
46616	K1V16	K1V14, Ub145..170V	-
46617	K1V22	Itsm20A	-
46618	K1V22(W)	Itsm16A	-
46619	K1V24	K1V22, Ub220..250V	-

46620	K1V24(W)	K1V22(W), Ub220..250V	-
46621	K1V26	K1V22, Ub240..270V	-
46622	K1V26(W)	K1V22(W), Ub240..265V	-
46623	K1V5	Ub45..60V, Ib<0,5mA, Itsm13A	-
46624	K1V6	K1V5, Ub55..65V	-
46625	K1V8	Ub77..95V, Ib<0,5mA, Itsm20A	-
46626	K1Y	KSC 3265-Y	KSC 3265
46627	K2	2SK57-2	2SK57
46628	K2(p)	BCW 72	BCW 72
46629	K2,5/15	OA 161	OA 161
46630	K24	2SK160A-K24	2SK160A
46631	K24	2SK853A-K24	2SK853A
46632	K25	2SK160A-K25	2SK160A
46633	K25	2SK853A-K25	2SK853A
46634	K26	2SK853A-K26	2SK853A
46635	K26	2SK160A-K26	2SK160A
46636	K27	2SK853A-K27	2SK853A
46637	K27	2SK160A-K27	2SK160A
46638	K2C5	Ub44..61V, Ib<0,5mA, Itsm20A	K1V5
46639	K2C6	K2C5, Ub56..67V	K1V6
46640	K2F5	K2C5	K1V5
46641	K2F6	K2C6	K1V6
46642	K3	2SK57-3	2SK57
46643	K3	2SC3143-3	2SC3143
46644	K3(p)	BCW 81	BCW 81
46645	K31	BCW 81R	BCW 81R
46646	K3A	KDV 804S	KDV 804S
46647	K3B	KDV 804S	KDV 804S
46648	K3C	KDV 804S	KDV 804S
46649	K3D	KDV 804S	KDV 804S
46650	K3E	KDV 804S	KDV 804S
46651	K4	2SK160-4	2SK160
46652	K4	BCW 71R	BCW 71R
46653	K4	2SC3143-4	2SC3143
46654	K4	2SK853-K4	2SK853
46655	K41	2SK520-K41	2SK520
46656	K42	2SK520-K42	2SK520
46657	K43	2SK520-K43	2SK520
46658	K44	2SK520-K44	2SK520
46659	K45	2SK520-K45	2SK520
46660	K5	2SC3143-5	2SC3143
46661	K5	2SK160-5	2SK160
46662	K5	BCW 72R	BCW 72R
46663	K5	2SK853-K5	2SK853
46664	K5/6	OA 161	OA 161

46665	K51	2SK508-K51	2SK508
46666	K52	2SK508-K52	2SK508
46667	K53	2SK508-K53	2SK508
46668	K6	2SK853-K6	2SK853
46669	K6	BCV 71R	BCV 71R
46670	K6	2SK160-6	2SK160
46671	K7	2SK853-K7	2SK853
46672	K7	2SK160-7	2SK160
46673	K7(p)	BCV 71	BCV 71
46674	K71	BCV 71R	BCV 71R
46675	K8(p)	BCV 72	BCV 72
46676	K81	BCV 72R	BCV 72R
46677	K9	1SS348	1SS348
46678	K9	BCV 72R	BCV 72R
46679	K9(p)	BCF 81	BCF 81
46680	K91	BCF 81R	BCF 81R
46681	KA	μPA670T	æPA670T
46682	KA	μPA604T	æPA604T
46683	KA	BFT 75	BFT 75
46684	KA	2SC4409	2SC4409
46685	KA	BSS 87	BSS 87
46686	KAG	2SK368-GR	2SK368
46687	KAO	2SK368-O	2SK368
46688	KAY	2SK368-Y	2SK368
46689	KB	2SC4972-B	2SC4972
46690	KB	2SC4655-B	2SC4655
46691	KB	2SC3936-B	2SC3936
46692	KB	2SK323-B	2SK323
46693	KB	2SK433-B	2SK433
46694	KB	BFQ 29	BFQ 29
46695	KB	2SC2778-B	2SC2778
46696	KB	2SK1311	2SK1311
46697	KB	BSS 192	BSS 192
46698	KB	2SC4539	2SC4539
46699	KB-162	0,59..0,65V(3mA)	BA 216, BA 314
46700	KB-165	0,62..0,69V(3mA)	BA 216, BA 314
46701	KB-169	0,66..0,72V(3mA)	BA 216, BA 314
46702	KB-262(C4,M)	1,18..1,30V(3mA)	BZV 86/1V4, BZX 75/C1V4, ZTE 1,5
46703	KB-265(C4)	1,24..1,38V(3mA)	BZV 86/1V4, BZX 75/C1V4, ZTE 1,5
46704	KB-269	1,32..1,44V(3mA)	BZV 86/1V4, BZX 75/C1V4, ZTE 1,5
46705	KB-362(M)	1,77..1,95V(3mA)	BZ102/2V1, BZV86/2V0, BZX75/C2V1, ZTE 2
46706	KB-365	1,86..2,07V(3mA)	BZ102/2V1, BZV86/2V0, BZX75/C2V1, ZTE 2
46707	KB-369	1,98..2,16V(3mA)	BZ102/2V1, BZV86/2V0, BZX75/C2V1, ZTE 2
46708	KB-462	2,36..2,60V(3mA)	BZ 102/2V8, BZV 86/2V6, BZX 85/C2V8
46709	KB-465	2,48..2,76V(3mA)	BZ 102/2V8, BZV 86/2V6, BZX 75/C2V8

46710	KB-469	2,64..2,88V(3mA)	BZ 102/2V8, BZV 86/2V6, BZX 75/C2V8
46711	KC	2SC4972-C	2SC4972
46712	KC	2SK433-C	2SK433
46713	KC	BFQ 29P	BFQ 29P
46714	KC	2SC3936-C	2SC3936
46715	KC	2SC4655-C	2SC4655
46716	KC	2SC2778-C	2SC2778
46717	KC	2SK323-C	2SK323
46718	KC	2SK1467	2SK1467
46719	KC	2SC4540	2SC4540
46720	KC147	BC 147	
46721	KC148	BC 148	
46722	KC149	BC 149	
46723	KC507	BC 547	BC 547
46724	KC508	BC 548	BC 548
46725	KC509	BC 549	BC 549
46726	KC510	BC 550	BC 550
46727	KCG	2SK625-G	2SK625
46728	KCO	2SK625-O	2SK625
46729	KCR	2SK625-R	2SK625
46730	KCY	2SK625-Y	2SK625
46731	KD	P6 SMB-6.8	P6 SMB-6.8
46732	KD	2SK433-D	2SK433
46733	KD	2SK323-D	2SK323
46734	KD	2SK930-D	2SK930
46735	KD	2SC4541	2SC4541
46736	KD	2SK1470	2SK1470
46737	KD501	-/40V, 20A, 150W, 2MHz	BD 249A, BD 368, 2N3772, 2N5886
46738	KD502	-/60V, 20A, 150W, 2MHz	BD 249B, BD 368, 2N3772, 2N5886
46739	KD503	-/80V, 20A, 150W, 2MHz	BD 249C, BD 368, 2N3772, 2N5886
46740	KD601	40V, 10A, 35W, 10MHz	BD 245, BD 311, BDW 21, 2N5055
46741	KD602	110V, 40A, 35W, 0,5MHz	2N6032, 2N6274...6275
46742	KD605	-/40V, 10A, 70W, 2MHz	BD 245A, BD 311, BD 315, 2N5877...78
46743	KD606	-/60V, 10A, 70W, 2MHz	BD 245B, BD 313, BD 315, 2N5878
46744	KD607	-/80V, 10A, 70W, 2MHz	BC 245C, BD 317, BDY 53, 2N3055
46745	KD610	-/40V, 10A, 35W	BDV 65(A...C), BDX 65(A...C), MJ 3000
46746	KDS181	1SS181	1SS181
46747	KDS184	1SS184	1SS184
46748	KDS187	1SS187	1SS187
46749	KDS190	1SS190	1SS190
46750	KDS193	1SS193	1SS193
46751	KDS196	1SS196	1SS196
46752	KDS200	1SS200	1SS200
46753	KDS201	1SS201	1SS201
46754	KDS2236	1S2236	1S2236

46755	KDS2236S	1S2236, SMD	-
46756	KDS226	1SS226	1SS226
46757	KDV147	1SV147	1SV147
46758	KDV149	1SV149	1SV149
46759	KDV152M		-
46760	KDV152S	KDV 152M, SMD	-
46761	KDV153		-
46762	KDV173	20V	-
46763	KDV251M		-
46764	KDV251S	KDV 251M, SMD	-
46765	KDV804M	BB 304, 15V	BB 304
46766	KDV804S	BB 804, 15V	BB 804
46767	KE	P6 SMB-6.8A	P6 SMB-6.8A
46768	KE	2SK930-E	2SK930
46769	KE	2SK433-E	2SK433
46770	KE	2SK1062	2SK1062
46771	KE	2SK323-E	2SK323
46772	KE	2SK1473	2SK1473
46773	KF	P6 SMB-7.5	P6 SMB-7.5
46774	KF	2SJ168	2SJ168
46775	KF	2SK1724	2SK1724
46776	KF124	BF 254	BF 254
46777	KF125	BF 255	BF 255
46778	KF167	BF 167	BF 167
46779	KF173	BF 173	BF 173
46780	KF257	BF 257	BF 257
46781	KF258	BF 258	BF 258
46782	KF259	BF 259	BF 259
46783	KF272	BF 272	BF 272
46784	KF503	-/60V, 0,05A, 0,7W, 150MHz	BC 546, 2SC1890(A), 2SC2363, 2SD755
46785	KF504	-/100V, 0,05A, 0,7W, 150MHz	2SC1890A, 2SC2363, 2SC3245, 2SD756(A)
46786	KF506	BC 141	BC 141
46787	KF507	BC 140	BC 140
46788	KF508	BC 141	BC 141
46789	KF517	BC 160	BC 160
46790	KF521		-
46791	KF524	BF 254	BF 254
46792	KF525	BF 255	BF 255
46793	KG	P6 SMB-7.5A	P6 SMB-7.5A
46794	KG	2SK881-GR	2SK881
46795	KG	2SK211-GR	2SK211
46796	KG	KTK 211-G	KTK 211
46797	KG	2SK1726	2SK1726
46798	KH	P6 SMB-8.2	P6 SMB-8.2
46799	KH	2SK1827	2SK1827

46800	KH	2SK1826	2SK1826
46801	KH	2SK1728	2SK1728
46802	KI	2SK1829	2SK1829
46803	KI	2SK1830	2SK1830
46804	KI	2SK1828	2SK1828
46805	KID	2SC4050-D	2SC4050
46806	KIE	2SC4050-E	2SC4050
46807	KJ	2SK2036	2SK2036
46808	KJ	2SK2037	2SK2037
46809	KK	P6 SMB-8.2A	P6 SMB-8.2A
46810	KK	2SB805-KK	2SB805
46811	KL	P6 SMB-9.1	P6 SMB-9.1
46812	KL	2SA1510	2SA1510
46813	KL	KTK 211-L	KTK 211
46814	KL	2SB805-KL	2SB805
46815	KM	P6 SMB-9.1A	P6 SMB-9.1A
46816	KM	2SK2009	2SK2009
46817	KM	2SB805-KM	2SB805
46818	KM	BST 80	BST 80
46819	KM901(D...H)	140MHz	BF 240...241, BF 254, BF 494, BF 594
46820	KM9011	-/20V, 0,1A, 0,3W, >150MHz	BC 237, BC 547, BF 240...41, BF 254...55
46821	KM9012	-/20V, 0,6A, 0,5W, 150MHz	BC 327, BC 636, BC 638, 2SB909...910
46822	KM9013	-/20V, 0,6A, 0,5W, 200MHz	BC 337, BC 635, BC 637, 2SD1225...26
46823	KM9014(A...D)	25V, 0,1A, 0,3W, 140MHz	BC 168, BC 183, BC 238, BC 548
46824	KM9015(A...D)	25V, 0,1A, 0,3W, 120MHz	BC 213, BC 258, BC 308, BC 558
46825	KM9016	-/20V, 0,05A, 0,3W, >500MHz	BF 240...241, BF 254...255, BF 594...595
46826	KM9018	-/15V, 0,05A, 0,3W, >400MHz	BF 225, BF 255, BF 314, BF 505, BF 507
46827	KM904(D...I)	25V, 0,5A, 0,5W, 200MHz	BC 337...338, BC 635, BC 637, BC 639
46828	KM905(D...I)	25V, 0,5A, 0,5W, 120MHz	BC 327...328, BC 636, BC 638, BC 640
46829	KM917(D..H)	210MHz	BF 240...241, BF 254, BF 494, BF 594
46830	KM918(D..H)	450MHz	BF 240...241, BF 255, BF 495, BF 595
46831	KM928(A,B)	800MHz	BF 377...378, BF 689, BF 763, 2N2857
46832	KM934(B...D)	35V, 0,5A, 0,5W, 180MHz	BC 337...338, BC 635, BC 637, BC 639
46833	KM935(B...D)	35V, 0,5A, 0,5W, 180MHz	BC 327...328, BC 636, BC 638, BC 640
46834	KM951	BC 559	BC 559
46835	KN	P6 SMB-10	P6 SMB-10
46836	KN	2SJ305	2SJ305
46837	KN	BST 84	BST 84
46838	KO	2SK211-O	2SK211
46839	KO	KTK 211-O	KTK 211
46840	KO	2SK881-O	2SK881
46841	KO	BST 86	BST 86
46842	KO	KTA1001-O	KTA 1001
46843	KP	P6 SMB-10A	P6 SMB-10A
46844	KP	2SK2034	2SK2034



46845	KP	2SK2035	2SK2035
46846	KP	2SK2033	2SK2033
46847	KP	2SB806-KP	2SB806
46848	KP4-5	Ih>50mA	-
46849	KP4-8	Ih>95mA	-
46850	KQ	P6 SMB-11	P6 SMB-11
46851	KQ	2SJ344	2SJ344
46852	KQ	2SJ343	2SJ343
46853	KQ	2SB806-KQ	2SB806
46854	KR	P6 SMB-11A	P6 SMB-11A
46855	KR	2SB806-KR	2SB806
46856	KRA101M	RbRbe4,7kOhm, 50V, 0,1A	AN 1L3M, DTA 143ES, RN 2001, UN 411L
46857	KRA101S	KRA 101M, SMD	FN 1L3M, DTA 143EK, RN 2401, UN 211L
46858	KRA102M	KRA 101M, RbRbe10kOhm	AN 1A4M, DTA 114ES, RN 2002, UN 4111
46859	KRA102S	KRA 102M, SMD	FN 1A4M, DTA 114EK, RN 2402, UN 2111
46860	KRA103M	KRA 101M, RbRbe22kOhm	AN 1F4M, DTA 124ES, RN 2003, UN 4112
46861	KRA103S	KRA 103M, SMD	FN 1F4M, DTA 124EK, RN 2403, UN 2112
46862	KRA104M	KRA 101M, RbRbe47kOhm	AN 1L4M, DTA 144ES, RN 2004, UN 4113
46863	KRA104S	KRA 104M, SMD	FN 1L4M, DTA 144EK, RN 2404, UN 2113
46864	KRA105M	Rbe47kOhm	DTA 123JS, RN 2005
46865	KRA105S	KRA 105M, SMD	DTA 123JK, RN 2405
46866	KRA106M	Rbe47kOhm	DTA 143ZS, RN 2006, 2SA1591, 2SA1616
46867	KRA106S	KRA 106M, SMD	DTA 143ZK, RN 2406, 2SA1597
46868	KRA107M	Rbe47kOhm	AN 1A4P, DTA 114YS, RN 2007, UN 4114
46869	KRA107S	KRA 107M, SMD	FN 1A4P, DTA 114YK, RN 2407, UN 2114
46870	KRA108M	Rbe47kOhm	AN 1F4N, DTA 124XS, KSR 2007, RN 2008
46871	KRA108S	KRA 108M, SMD	FN 1F4N, DTA 124XK, KSR 2107, RN 2408
46872	KRA109M	Rbe22kOhm	AN 1L4L, DTA 144WS, RN 2009, UN 411E
46873	KRA109S	KRA 109M, SMD	FN 1L4L, DTA 144WK, RN 2409, UN 211E
46874	KRA110M	KRA 101M, Rb4,7kOhm, Rbe-	AN 1L3Z, DTA 143TS, RN 2010, UN 4116
46875	KRA110S	KRA 110M, SMD	FN 1L3Z, DTA 143TK, RN 2410, UN 2116
46876	KRA111M	KRA 101M, Rb10kOhm, Rbe-	AN 1A4Z, DTA 114TS, RN 2011, UN 4115
46877	KRA111S	KRA 111M, SMD	FN 1A4Z, DTA 114TK, RN 2411, UN 2115
46878	KRA112M	KRA 101M, Rb100kOhm, Rbe-	DTA 115TS
46879	KRA112S	KRA 112M, SMD	DTA 115TK
46880	KRA113M	KRA 101M, Rb22kOhm, Rbe-	AN 1F4Z, DTA 124TS, UN 4117, 2SA1590
46881	KRA113S	KRA 113M, SMD	FN 1F4Z, DTA 124TK, UN 2117, 2SA1589
46882	KRA114M	KRA 101M, Rb47kOhm, Rbe-	AN 1L4Z, DTA 144TS, UN 4110, 2SA1509
46883	KRA114S	KRA 114M, SMD	FN 1L4Z, DTA 144TK, UN 2110, 2SA1508
46884	KRA221M	RbRbe1kOhm, 50V, 0,8A	-
46885	KRA221S..226S	KRA 221M..226M, SMD	-
46886	KRA222M	KRA 221M, RbRbe2,2kOhm	-
46887	KRA223M	KRA 221M, RbRbe4,7kOhm	-
46888	KRA224M	KRA 221M, RbRbe10kOhm	-
46889	KRA225M	KRA 221M, Rb1k, Rbe10kOhm	-

46890	KRA226M	Rbe10kOhm	-
46891	KRA231M	Rb2,2kOhm, Rbe-, 50V, 0,6A	DTC 323TS, DTD 123TS
46892	KRA231S	KRC 231M, SMD	DTC 323TK, DTD 123TK
46893	KRA232M	KRC 231M, Rb5,6kOhm, Rbe-	-
46894	KRA232S	KRC 232M, SMD	-
46895	KRA233M	KRC 231M, Rb10kOhm, Rbe-	DTC 314TS, DTD 114TS
46896	KRA233S	KRC 232M, SMD	DTC 314TK, DTD 114TK
46897	KRA241S..246S	KRC 241M..246M, SMD	-
46898	KRC101M	RbRbe4,7kOhm, 50V, 0,1A	AA 1L3M, DTC 143ES, RN 1001, UN 421L
46899	KRC101S	KRC 101M, SMD	FA 1L3M, DTC 143EK, RN 1401, UN 221L
46900	KRC102M	KRC 101M, RbRbe10kOhm	AA 1A4M, DTC 114ES, RN 1002, UN 4211
46901	KRC102S	KRC 102M, SMD	FA 1A4M, DTC 114EK, RN 1402, UN 2211
46902	KRC103M	KRC 101M, RbRbe22kOhm	AA 1F4M, DTC 124ES, RN 1003, UN 4212
46903	KRC103S	KRC 103M, SMD	FA 1F4M, DTC 124EK, RN 1403, UN 2212
46904	KRC104M	KRC 101M, RbRbe47kOhm	AA 1L4M, DTC 144ES, RN 1004, UN 4213
46905	KRC104S	KRC 104M, SMD	FA 1L4M, DTC 144EK, RN 1404, UN 2213
46906	KRC105M	Rbe47kOhm	DTC 123JS, RN 1005
46907	KRC105S	KRC 105M, SMD	DTC 123JK, RN 1405
46908	KRC106M	Rbe47kOhm	DTC 143ZS, RN 1006, 2SC4133, 2SC4195
46909	KRC106S	KRC 106M, SMD	DTC 143ZK, RN 1406, 2SC4146
46910	KRC107M	KRC 101M, Rb10k, Rbe47kOhm	AA 1A4P, DTC 114YS, RN 1007, UN 4214
46911	KRC107S	KRC 107M, SMD	FA 1A4P, DTC 114YK, RN 1407, UN 2214
46912	KRC108M	KRC 101M, Rb22k, Rbe47kOhm	AA 1F4N, DTC 124XS, KSR 1007, RN 1008
46913	KRC108S	KRC 108M, SMD	FA 1F4N, DTC 124XK, KSR 1107, RN 1408
46914	KRC109M	KRC 101M, Rb47k, Rbe22kOhm	AA 1L4L, DTC 144WS, RN 1009, UN 421E
46915	KRC109S	KRC 109M, SMD	FA 1L4L, DTC 144WK, RN 1409, UN 221E
46916	KRC110M	KRC 101M, Rb4,7kOhm, Rbe-	AA 1L3Z, DTC 143TS, RN 1010, UN 4216
46917	KRC110S	KRC 110M, SMD	FA 1L3Z, DTC 143TK, RN 1410, UN 2216
46918	KRC111M	KRC 101M, Rb10kOhm, Rbe-	AA 1A4Z, DTC 114TS, RN 1011, UN 4215
46919	KRC111S	KRC 111M, SMD	FA 1A4Z, DTC 114TK, RN 1411, UN 2215
46920	KRC112M	KRC 101M, Rb100kOhm, Rbe-	DTC 115TS
46921	KRC112S	KRC 112M, SMD	DTC 115TK
46922	KRC113M	KRC 101M, Rb22kOhm, Rbe-	AA 1F4Z, DTC 124TS, KSR 1011, UN 4217
46923	KRC113S	KRC 113M, SMD	FA 1F4Z, DTC 124TK, KSR 1111, UN 2217
46924	KRC114M	KRC 101M, Rb47kOhm, Rbe-	AA 1L4Z, DTC 144TS, KSR 1012, UN 4210
46925	KRC114S	KRC 114M, SMD	FA 1L4Z, DTC 144TK, KSR 1112, UN 2210
46926	KRC241M	RbRbe1kOhm, 50V, 0,8A	-
46927	KRC242M	KRC 241M, RbRbe2,2kOhm	-
46928	KRC243M	KRC 241M, RbRbe4,7kOhm	-
46929	KRC244M	KRC 241M, RbRbe10kOhm	-
46930	KRC245M	KRC 241M, Rb1k, Rbe10kOhm	-
46931	KRC246M	Rbe10kOhm	-
46932	KS	P6 SMB-12	P6 SMB-12
46933	KS	2SJ345	2SJ345
46934	KS	2SJ347	2SJ347

46935	KS	2SJ346	2SJ346
46936	KS	2SD2533	2SD2533
46937	KSA1010	2SA1010	2SA1010
46938	KSA1013	2SA1013	2SA1013
46939	KSA1015	2SA1015	2SA1015
46940	KSA1142	2SA1142	2SA1142
46941	KSA1150	40V, 0,5A, 0,3W	BC 327...328, BC 636, BC 638, BC 640
46942	KSA1174	2SA1174	2SA1174
46943	KSA1175	2SA1175	2SA1175
46944	KSA1182	2SA1182	2SA1182
46945	KSA1201	2SA1201	2SA1201
46946	KSA1203	2SA1203	2SA1203
46947	KSA1220(A)	2SA1220(A)	2SA1220(A)
46948	KSA1298	2SA1298	2SA1298
46949	KSA1370	2SA1370	2SA1370
46950	KSA1378	30V, 0,3A, 0,3W	BC 327...328, BC 636, BC 638, 2SB910
46951	KSA1625	2SA1625	2SA1625
46952	KSA473	2SA473	2SA473
46953	KSA539	2SA539, 0,4W	2SA539
46954	KSA542	30V, 0,05A, 0,25W, 100MHz	BC 214, BC 258, BC 308, BC 558, 2SB725
46955	KSA545	2SA545	2SA545
46956	KSA614	80V, 3A, 25W	BD 242B, BD 538, BD 540B, 2SB690
46957	KSA634	2SA634, 2A	2SA634
46958	KSA636	2SA636, 2A	2SA636
46959	KSA640	2SA640	2SA640
46960	KSA642	2SA642	2SA642
46961	KSA643	2SA643	2SA643
46962	KSA707	60V, 0,7A, 0,8W	BC 327A, BC 638, BC 640, 2SB910
46963	KSA708	80V, 0,7A, 0,8W, 50MHz	BC 640, 2SB647, 2SB910, 2SB1116A
46964	KSA709	160/50V, 0,7A, 0,8W, 50MHz	2SA1013, 2SA1319, 2SB1212
46965	KSA733	60V, 0,15A, 0,25W, 180MHz	BC 212, BC 256, BC 266, BC 556, 2SB725
46966	KSA812	2SA812	2SA812
46967	KSA910	100MHz	BF 423, 2SA1019, 2SA1281, 2SA1285A
46968	KSA916	120/120V, 0,8A, 0,9W, 120MHz	2SA965, 2SA1013, 2SB647, 2SB984
46969	KSA928A	30V, 2A, 1W, 120MHz	MPS 750...751, 2SA1382, 2SB822, 2SB911
46970	KSA931	80V, 0,7A, 1W, 100MHz	BC 640, 2SA965, 2SB647, 2SB984
46971	KSA940	2SA940	2SA940
46972	KSA952	2SA952	2SA952
46973	KSA953	2SA953	2SA953
46974	KSA954	2SA954	2SA954
46975	KSA992	2SA992	2SA992
46976	KSB1116(A)	2SB1116(A)	2SB1116(A)
46977	KSB1121	2SB1121	2SB1121
46978	KSB1149	2SB1149	2SB1149
46979	KSB1150	2SB1150	2SB1150

46980	KSB1151	2SB1151	2SB1151
46981	KSB546	2SB546	2SB546
46982	KSB564A	2SB564	2SB564
46983	KSB596	2SB596	2SB596
46984	KSB601	2SB601	2SB601
46985	KSB707	2SB707	2SB707
46986	KSB708	2SB708	2SB708
46987	KSB744(A)	2SB744(A)	2SB744(A)
46988	KSB772	2SB772	2SB772
46989	KSB794	2SB794	2SB794
46990	KSB795	2SB795	2SB795
46991	KSB798	2SB798	2SB798
46992	KSB810	2SB810	2SB810
46993	KSB811	2SB811	2SB811
46994	KSB834	2SB834	2SB834
46995	KSC1008	80V, 0,7A, 0,8W, 50MHz	BC 639, 2SD667, 2SD1226, 2SD1616A
46996	KSC1009	160/140V, 0,7A, 0,8W, 50MHz	2SC2383, 2SC3228, 2SC3332, 2SD1812
46997	KSC1070(-1,-2)	2SC1070	2SC1070
46998	KSC1072	60V, 0,7A, 0,8W	BC 337A, BC 637, BC 639, 2SD1226
46999	KSC1096	2SC1096, 2A	2SC1096
47000	KSC1098	2SC1098, 2A	2SC1098
47001	KSC1173	2SC1173	2SC1173
47002	KSC1187	2SC1187	2SC1187
47003	KSC1188	2SC1188	2SC1188
47004	KSC1222	2SC1222	2SC1222
47005	KSC1330	2SC1330	2SC1330
47006	KSC1393	2SC1393	2SC1393
47007	KSC1394	2SC1394	2SC1394
47008	KSC1395	2SC1395	2SC1395
47009	KSC1506	300/300V, 0,1A, 0,75W, 80MHz	BF 299, BF 393, BF 420A, 2SC3468
47010	KSC1507	2SC1505	2SC1505
47011	KSC1520	2SC1519	2SC1519
47012	KSC1520A	2SC1520	2SC1520
47013	KSC1623	2SC1623	2SC1623
47014	KSC1674	2SC1674	2SC1674
47015	KSC1675	2SC1675	2SC1675
47016	KSC1730	2SC1730	2SC1730
47017	KSC1815	2SC1815	2SC1815
47018	KSC184	30V, 0,05A, 0,25W, 100MHz	BF 240...241, BF 254...255, BF 594...595
47019	KSC1845	2SC1845	2SC1845
47020	KSC1983	2SC1983	2SC1983
47021	KSC2001	2SC2001	2SC2001
47022	KSC2002	2SC2002	2SC2002
47023	KSC2003	2SC2003	2SC2003
47024	KSC2073	2SC2073	2SC2073

47025	KSC2223	2SC2223	2SC2223
47026	KSC2233	2SC2233	2SC2233
47027	KSC2310	100MHz	BF 391...393, BF 420, BF 422
47028	KSC2316	120V, 0,8A, 0,9W, 120MHz	2SC2235, 2SC2383, 2SD667, 2SD1665
47029	KSC2328A	30V, 2A, 1W, 120MHz	MPS650...51, 2SD1055, 2SD1100, 2SD1227
47030	KSC2330	300/300V, 0,1A, 1W, 50MHz	BF 393, BF 420A, 2SC3249, 2SC3468
47031	KSC2331	80V, 0,7A, 1W, 50MHz	BC 639, 2SC2235, 2SD667, 2SD1665
47032	KSC2334	2SC2334	2SC2334
47033	KSC2335	2SC2335	2SC2335
47034	KSC2340	350/350V, 0,1A, 1W, >50MHz	BF 485, BF 487, 2N6517, 2SC3469
47035	KSC2383	2SC2383	2SC2383
47036	KSC2500	2SC2500	2SC2500
47037	KSC2517	2SC2517	2SC2517
47038	KSC2518	2SC2518	2SC2518
47039	KSC2669	2SC2669	2SC2669
47040	KSC2682	2SC2682	2SC2682
47041	KSC2688	2SC2688	2SC2688
47042	KSC2690(A)	2SC2690(A)	2SC2690(A)
47043	KSC2710	40V, 0,5A, 0,3W	BC 337...338, BC 635, BC 637, 2SC2710
47044	KSC2715	2SC2715	2SC2715
47045	KSC2734	2SC2734	2SC2734
47046	KSC2749	2SC2749	2SC2749
47047	KSC2751	2SC2751	2SC2751
47048	KSC2752	2SC2752	2SC2752
47049	KSC2753	2SC2753	2SC2753
47050	KSC2755	2SC2755	2SC2755
47051	KSC2756	2SC2756	2SC2756
47052	KSC2757	2SC2757	2SC2757
47053	KSC2758	2SC2758	2SC2758
47054	KSC2759	2SC2759	2SC2759
47055	KSC2784	2SC2784	2SC2784
47056	KSC2785	2SC2785	2SC2785
47057	KSC2786	2SC2786	2SC2786
47058	KSC2787	2SC2787	2SC2787
47059	KSC2859	2SC2859	2SC2859
47060	KSC2881	2SC2881	2SC2881
47061	KSC2883	2SC2883	2SC2883
47062	KSC2982	2SC2982	2SC2982
47063	KSC3120	2SC3120	2SC3120
47064	KSC3123	2SC3123	2SC3123
47065	KSC3125	2SC3125	2SC3125
47066	KSC3265	2SC3265	2SC3265
47067	KSC3488	30V, 0,3A, 0,3W	BC 337...338, BC 635, BC 637, 2SC3488
47068	KSC3502	2SC3502	2SC3502
47069	KSC3503	2SC3503	2SC3503

47070	KSC3552	2SC3552	2SC3552
47071	KSC3569	2SC3569	2SC3569
47072	KSC388	2SC388ATM	2SC388
47073	KSC3953	2SC3953	2SC3953
47074	KSC5019	30V, 2A, 0,75W, 150MHz	2SC4484, 2SD1246, 2SD1835, 2SD2177
47075	KSC5020	<500/3300ns	BUT 11(A), MJE 13071, 2SC3086, 2SD841
47076	KSC5020F	KSC 5020, , 30W	BUT 11(A)F, 2SC3749, 2SC4517, 2SC4908
47077	KSC5021	<500/3300ns	BUT 11(A), MJE 13071, 2SC3047, 2SC3087
47078	KSC5022	-/500V, 4A, 60W, <500/3300ns	BUW 11(A), BUW 131(A), BUV 82...83
47079	KSC5023	<500/3300ns	BUP 22B...C, 2SC3089, 2SC3449, 2SC3636
47080	KSC5024	<500/3300ns	BUV 47(A), BUW 12(A), 2SC3450, 2SC3637
47081	KSC5025	<500/3300ns	BUV 48(A), BUW 13(A), 2SC3451, 2SC3638
47082	KSC5026	<500/3300ns	MJE 8500, 2SC3178, 2SC3456, 2SC4230
47083	KSC5027	<500/3300ns	MJE 8502, 2SC3050, 2SC3457
47084	KSC5028	-/800V, 3A, 80W, <500/3300ns	2SC3387, 2SC3459, 2SC4236
47085	KSC5029	<500/3300ns	2SC3387, 2SC3459, 2SC4236
47086	KSC5030	<500/3300ns	BUV 89, 2SC3466, 2SC3643
47087	KSC5031	-/800V, 8A, 140W, <500/3300ns	BUV 70...71, 2SC3461, 2SC4237
47088	KSC5039	800/400V, 5A, 70W, <1/3,8µs	BUT 11(A), MJE 13071, 2SC3047, 2SC3087
47089	KSC5039F	KSC 5039, , 30W	BUT 11(A)F, 2SC3750, 2SC3795, 2SC4518
47090	KSC5047	100V, 15A, 100W	-
47091	KSC5054	500/400V, 0,5A, 10W, <1/3,5µs	2SC3129, 2SC3588, 2SC4499
47092	KSC5060	<500/3300ns	BUT 11(A), MJE 13071, 2SC3086, 2SD841
47093	KSC5061	<500/3300ns	BUT 11(A), MJE 13071, 2SC3047, 2SC3087
47094	KSC5086	1500/800V, 7A, 50W	2SC3892A, 2SC4762, 2SC4916
47095	KSC5088	1500/800V, 8A, 50W	BU 2522AF, 2SC3886A, 2SC3896, 2SC4758
47096	KSC5089	1500/800V, 8A, 150W	BU 2522A, 2SC3687
47097	KSC815	2SC815, 0,4W	2SC815
47098	KSC838	35V, 30mA, 0,25W, 250MHz	BF 240...241, BF 254...255, BF 594...595
47099	KSC839	35V, 0,1A, 200MHz	BF 240...241, BF 254...255, BF 594...595
47100	KSC853	2SC853	2SC853
47101	KSC900	2SC900	2SC900
47102	KSC921	35V, 0,1A, 250MHz	BFX 59, (BF 240...241, BF 254...255)
47103	KSC945	60V, 0,15A, 0,25W, 300MHz	BC 174, BC 182, BC 190, BC 546, 2SB725
47104	KSD1020	2SD1020	2SD1020
47105	KSD1021	2SD1021	2SD1021
47106	KSD1616(A)	2SD1616(A)	2SD1616(A)
47107	KSD1621	2SD1621	2SD1621
47108	KSD1691	2SD1691	2SD1691
47109	KSD1692	2SD1692	2SD1692
47110	KSD1693	2SD1693	2SD1693
47111	KSD227	2SD227	2SD227
47112	KSD261	2SD261	2SD261
47113	KSD288	80V, 3A, 25W	BD 241B, BD 537, BD 539B, 2SD726
47114	KSD362	150/70V, 5A, 40W, 10MHz	BU 406...409, 2SD823, 2SD1150, 2SD1163



47115	KSD363	300/120V, 6A, 40W, 10MHz	BU 406...409, 2SC3590, 2SD1069, 2SD1163
47116	KSD401	2SD401	2SD401
47117	KSD471A	2SD471A	2SD471A
47118	KSD5000	1500/800V, 2,5A, 80W	BU 706D, 2SC3479, 2SD1290...1291
47119	KSD5001	1500/800V, 3,5A, 80W	BU 706D, 2SC3480, 2SD1729
47120	KSD5002	1500/800V, 5A, 120W	BU 706D, 2SC3481...82, 2SC4291...92
47121	KSD5003	1500/800V, 6A, 120W	BU 2508D, 2SC3482, 2SC4292, 2SD1731
47122	KSD5004	1500/800V, 2,5A, 80W	BU 705, 2SC3483, 2SD1493...94
47123	KSD5005	1500/800V, 3,5A, 80W	BU 706, 2SC3484, 2SD1495
47124	KSD5006	1500/800V, 5A, 120W	BU 706, BU 2508A, 2SC3485...86, 2SC3685
47125	KSD5007	1500/800V, 6A, 120W	BU 2508A, 2SC3486, 2SC3685
47126	KSD5010	KSD 5000, 50W	BU 705DF, 2SD1553, 2SD1649, 2SD1876
47127	KSD5011	KSD 5001, 50W	BU 706DF, 2SD1554, 2SD1650, 2SD1877
47128	KSD5012	KSD 5002, 60W	BU 706DF, 2SD1555, 2SD1651, 2SD1878
47129	KSD5013	KSD 5003, 60W	BU 2508DF, 2SD1556, 2SD1652, 2SD1879
47130	KSD5014	KSD 5004, 50W	BU 705F, 2SD1543, 2SD1653, 2SD1882
47131	KSD5015	KSD 5005, 50W	BU 706F, 2SD1544, 2SD1654, 2SD1883
47132	KSD5016	KSD 5006, 60W	BU 706F, 2SD1545, 2SD1655, 2SD1884
47133	KSD5017	KSD 5007, 60W	BU 2508AF, 2SD1546, 2SD1656, 2SD1885
47134	KSD5041	40V, 5A, 0,75W	2SC3671, 2SD1961...62, 2SD2097, 2SD2179
47135	KSD5060	1500/800V, 2,5A, 80W	BU 705D, 2SD1290...91, 2SD1728
47136	KSD5061	1500/800V, 3,5A, 80W	BU 706D, 2SC3480, 2SD1729
47137	KSD5062	1500/800V, 5A, 120W	BU 706D, BU 2508D, 2SC3481, 2SC3681
47138	KSD5064	1500/800V, 2,5A, 80W	2SD705, 2SC3483, 2SD1493...94
47139	KSD5065	1500/800V, 3,5A, 80W	2SD706, 2SC3484, 2SD1495
47140	KSD5066	1500/800V, 5A, 120W	2SD706, BU 2508A, 2SC3685, 2SD1496...97
47141	KSD5068	1500/800V, 8A, 150W	BU 2508A, BU 2520A, 2SC3687...88
47142	KSD5070	1500/800V, 2,5A, 50W	BU 705DF, 2SD1553, 2SD1649, 2SD1876
47143	KSD5071	1500/800V, 3,5A, 50W	BU 706DF, 2SD1554, 2SD1650, 2SD1877
47144	KSD5072	1500/800V, 5A, 60W	BU 706DF, BU 2508DF, 2SC4122, 2SD1555
47145	KSD5074	1500/800V, 2,5A, 50W	BU 705F, 2SD1543, 2SD1653, 2SD1882
47146	KSD5075	1500/800V, 3,5A, 50W	BU 706F, 2SD1544, 2SD1654, 2SD1883
47147	KSD5075T	KSD 5075, 75W	BU 505, MJE 12007, 2SD1575
47148	KSD5076	1500/800V, 5A, 60W	BU 706F, BU 2508AF, 2SC4142, 2SD1545
47149	KSD5078	1500/800V, 8A, 70W	BU 2508AF, 2SC4770, 2SD1547, 2SD1886
47150	KSD5080	1500/800V, 8A, 70W	BU 2508DF, 2SC4124, 2SC4763, 2SD1880
47151	KSD5090	1500/800V, 8A, 150W	BU 2508D, BU 2520D, 2SC3683, 2SD1881
47152	KSD526	2SD526	2SD526
47153	KSD560	2SD560	2SD560
47154	KSD568	2SD568	2SD568
47155	KSD569	2SD569	2SD569
47156	KSD73	100V, 5A, 30W, 20MHz	BD 243C, BD 539C, BD 953, 2SD613
47157	KSD794(A)	2SD794(A)	2SD794(A)
47158	KSD818	1500/600V, 2,5A, 50W	BU 705, BU 706, 2SC3483, 2SD1493...94
47159	KSD819	1500/600V, 3,5A, 50W	BU 706, 2SC3484, 2SD1495

47160	KSD820	1500/600V, 5A, 50W	BU 2508(A), BU 908, 2SD1496...97
47161	KSD821	1500/600V, 6A, 50W	BU 2508(A), BU 908, 2SD1496...97
47162	KSD868	1500/600V, 2,5A, 50W	BU 706D, 2SC3479, 2SD1290...1291
47163	KSD869	1500/600V, 3,5A, 50W	BU 706D, 2SC3480, 2SD 1729
47164	KSD870	1500/600V, 5A, 50W	BU 2508D, 2SC3481...82, 2SC3681...82
47165	KSD871	1500/600V, 6A, 50W	BU 2508D, 2SC3482, 2SC3681...83
47166	KSD880	2SD880	2SD880
47167	KSD882	2SD882	2SD882
47168	KSD985	2SD985	2SD985
47169	KSD986	2SD986	2SD986
47170	KSE13004..13009	MJE 13004..13009	MJE 13004...13009
47171	KSK117	2SK117	2SK117
47172	KSK123	2SK123	2SK123
47173	KSK161	2SK161	2SK161
47174	KSK211	2SK211	2SK211
47175	KSK30	2SK30	2SK30
47176	KSK596	20V, Idss>0,1..0,8mA	2SK 596
47177	KSK65	2SK65	2SK65
47178	KSP10	MPSH 10	MPSH 10
47179	KSP11	MPSH 11	MPSH 11
47180	KSP12	MPSA 12	MPSA 12
47181	KSP13	MPSA 13	MPSA 13
47182	KSP14	MPSA 14	MPSA 14
47183	KSP17	MPSH 17	MPSH 17
47184	KSP20	MPSH 20	MPSH 20
47185	KSP2222(A)	2N2222(A), 0,6A, 0,625W	2N2222(A)
47186	KSP24	MPSH 24	MPSH 24
47187	KSP25	MPSA 25	MPSA 25
47188	KSP26	MPSA 26	MPSA 26
47189	KSP27	MPSA 27	MPSA 27
47190	KSP2907(A)	2N2906(A), 0,625W	2N2907(A)
47191	KSP42	MPSA 42	MPSA 42
47192	KSP43	MPSA 43	MPSA 43
47193	KSP44	MPSA 44	MPSA 44
47194	KSP45	MPSA 45	MPSA 45
47195	KSP5	MPSA 05	MPSA 05
47196	KSP5172	2N5172, 0,625W	2N5172
47197	KSP5179	2N5179, 0,2W	2N5179
47198	KSP55	MPSA 55	MPSA 55
47199	KSP56	MPSA 56	MPSA 56
47200	KSP6	MPSA 06	MPSA 06
47201	KSP62	MPSA 62	MPSA 62
47202	KSP63	MPSA 63	MPSA 63
47203	KSP64	MPSA 64	MPSA 64
47204	KSP6520	MPS 6520	MPS 6520

47205	KSP6521	MPS 6521	MPS 6521
47206	KSP75	MPSA 75	MPSA 75
47207	KSP76	MPSA 76	MPSA 76
47208	KSP77	MPSA 77	MPSA 77
47209	KSP8097	MPS 8097, 0,625W	MPS 8097
47210	KSP8098	MPS 8098	MPS 8098
47211	KSP8099	MPS 8099	MPS 8099
47212	KSP8598	MPS 8598	MPS 8598
47213	KSP8599	MPS 8599	MPS 8599
47214	KSP92	MPSA 92	MPSA 92
47215	KSP93	MPSA 93	MPSA 93
47216	KSP94	400/400V, 0,3A, 0,625W	2SA1625, 2SB1074, 2SB1488
47217	KSR1001	0,3W	AA 1L3M, DTC 143ES, RN 1001, UN 421L
47218	KSR1002	KSR 1001, RbRbe10kOhm	AA 1A4M, DTC 114ES, RN 1002, UN 4211
47219	KSR1003	KSR 1001, RbRbe22kOhm	AA 1F4M, DTC 124ES, RN 1009, UN 4212
47220	KSR1004	KSR 1001, RbRbe47kOhm	AA 1L4M, DTC 144ES, RN 1004, UN 4213
47221	KSR1005	Rbe10kOhm	AA 1L3N, DTC 143XS, UN 421F, 2SC4361
47222	KSR1006	Rbe47kOhm	AA 1A4P, DTC 114YS, RN 1007, UN 4214
47223	KSR1007	Rbe47kOhm	AA 1F4N, DTC 124XS, RN 1008
47224	KSR1008	Rbe22kOhm	AA 1L4L, DTC 144WS, RN 1009, UN 421E
47225	KSR1009	Rbe-	AA 1L3Z, DTC 143TS, RN 1010, UN 4216
47226	KSR1010	Rbe-	AA 1A4Z, DTC 114TS, RN 1011, UN 4215
47227	KSR1011	Rbe-	AA 1F4Z, DTC 124TS, UN 4217, 2SC4121
47228	KSR1012	Rbe-	AA 1L4Z, DTC 144TS, UN 4210, 2SC3899
47229	KSR1013	Rbe47kOhm	DTC 123JS, RN 1005
47230	KSR1014	Rbe47kOhm	DTC 143ZS, RN 1006, 2SC4133, 2SC4195
47231	KSR1101	KSR 1001, SMD	FA 1L3M, DTC 143EK, RN 1401, UN 221L
47232	KSR1102	KSR 1002, SMD	FA 1A4M, DTC 114EK, RN 1402, UN 2211
47233	KSR1103	KSR 1003, SMD	FA 1F4M, DTC 124EK, RN 1403, UN 2212
47234	KSR1104	KSR 1004, SMD	FA 1L4M, DTC 144EK, RN 1404, UN 2213
47235	KSR1105	KSR 1005, SMD	FA 1L3N, DTC 143XK, UN 221F, 2SC4360
47236	KSR1106	KSR 1006, SMD	FA 1A4P, DTC 114YK, RN 1407, UN 2214
47237	KSR1107	KSR 1007, SMD	FA 1F4N, DTC 124XK, RN 1408
47238	KSR1108	KSR 1008, SMD	FA 1L4L, DTC 144WK, RN 1409, UN 221E
47239	KSR1109	KSR 1009, SMD	FA 1L3Z, DTC 143TK, RN 1410, UN 2216
47240	KSR1110	KSR 1010, SMD	FA 1A4Z, DTC 114TK, RN 1411, UN 2215
47241	KSR1111	KSR 1011, SMD	FA 1F4Z, DTC 124TK, UN 2217, 2SC4120
47242	KSR1112	KSR 1012, SMD	FA 1L4Z, DTC 144TK, UN 2210, 2SC3898
47243	KSR1113	KSR 1013, SMD	DTC 123JK, RN 1405
47244	KSR1114	KSR 1014, SMD	DTC 143ZK, RN 1406, 2SC4146
47245	KSR1201..1214	KSR 1001..1014	KSR 1001...1014
47246	KSR2001	0,3W	AN 1L3M, DTA 143ES, RN 2001, UN 411L
47247	KSR2002	KSR 2001, RbRbe10kOhm	AN 1A4M, DTA 114ES, RN 2002, UN 4111
47248	KSR2003	KSR 2001, RbRbe22kOhm	AN 1F4M, DTA 124ES, RN 2003, UN 4112
47249	KSR2004	KSR 2001, RbRbe47kOhm	AN 1L4M, DTA 144ES, RN 2004, UN 4113

47250	KSR2005	Rbe10kOhm	AN 1L3N, DTA 143XS, UN 411F, 2SA1654
47251	KSR2006	Rbe47kOhm	AN 1A4P, DTA 114YS, RN 2007, UN 4114
47252	KSR2007	Rbe47kOhm	AN 1F4N, DTA 124XS, RN 2008
47253	KSR2008	Rbe22kOhm	AN 1L4L, DTA 144WS, RN 2009, UN 411E
47254	KSR2009	Rbe-	AN 1L3Z, DTA 143TS, RN 2010, UN 4116
47255	KSR2010	Rbe-	AN 1A4Z, DTA 114TS, RN 2011, UN 4115
47256	KSR2011	Rbe-	AN 1F4Z, DTA 124TS, UN 4117, 2SA1590
47257	KSR2012	Rbe-	AN 1L4Z, DTA 144TS, UN 4110, 2SA1509
47258	KSR2013	Rbe47kOhm	DTA 123JS, RN 2005
47259	KSR2014	Rbe47kOhm	DTA 143ZS, RN 2006, 2SA1591, 2SA1616
47260	KSR2101	KSR 2001, SMD	FN 1L3M, DTA 143EK, RN 2401, UN 211L
47261	KSR2102	KSR 2002, SMD	FN 1A4M, DTA 114EK, RN 2402, UN 2111
47262	KSR2103	KSR 2003, SMD	FN 1F4M, DTA 124EK, RN 2403, UN 2112
47263	KSR2104	KSR 2004, SMD	FN 1L4M, DTA 144EK, RN 2404, UN 2113
47264	KSR2105	KSR 2005, SMD	FN 1L3N, DTA 143XK, UN 211F, 2SA1653
47265	KSR2106	KSR 2006, SMD	FN 1A4P, DTA 114YK, RN 2407, UN 2114
47266	KSR2107	KSR 2007, SMD	FN 1F4N, DTA 124XK, RN 2408
47267	KSR2108	KSR 2008, SMD	FN 1L4L, DTA 144WK, RN 2409, UN 211E
47268	KSR2109	KSR 2009, SMD	FN 1L3Z, DTA 143TK, RN 2410, UN 2116
47269	KSR2110	KSR 2010, SMD	FN 1A4Z, DTA 114TK, RN 2411, UN 2115
47270	KSR2111	KSR 2011, SMD	FN 1F4Z, DTA 124TK, UN 2117, 2SA1589
47271	KSR2112	KSR 2012, SMD	FN 1L4Z, DTA 144TK, UN 2210, 2SA1508
47272	KSR2113	KSR 2013, SMD	DTA 123JK, RN 2405
47273	KSR2114	KSR 2014, SMD	DTA 143ZK, RN 2406, 2SA1597
47274	KSR2201..2214	KSR 2001..2014	KSR 2001...2014
47275	KST05	MPSA 05, SMD	MMBTA 05
47276	KST06	MPSA 06, SMD	MMBTA 06
47277	KST10	MPSH 10, SMD	MMBTH 10
47278	KST1009	2SC1009, SMD	2SC1009
47279	KST13	MPSA 13, SMD	MMBTA 13
47280	KST14	MPSA 14, SMD	MMBTA 14
47281	KST1623	2SC1623, SMD	2SC1623
47282	KST17	MPSH 17, SMD	MMBTH 17
47283	KST20	MPSA 20, SMD	MMBTA 20
47284	KST2222(A)	2N2222(A), SMD	MMBT 2222(A)
47285	KST24	MPSH 24, SMD	MMBTH 24
47286	KST2484	2N2484, SMD	MMBT 2484
47287	KST2907(A)	2N2907(A), SMD	MMBT 2907(A)
47288	KST3903	2N3903, SMD	MMBT 3903
47289	KST3904	2N3904, SMD	MMBT 3904
47290	KST3905	2N3905, SMD	MMBT 3905
47291	KST3906	2N3906, SMD	MMBT 3906
47292	KST4123	2N4123, SMD	MMBT 4123
47293	KST4124	2N4124, SMD	MMBT 4124
47294	KST4125	2N4125, SMD	MMBT 4125

47295	KST4126	2N4126, SMD	MMBT 4126
47296	KST42	MPSA 42, SMD	MMBTA 42
47297	KST43	MPSA 43, SMD	MMBTA 43
47298	KST4401	2N4401, SMD	MMBT 4401
47299	KST4403	2N4403, SMD	MMBT 4403
47300	KST5086	2N5086, SMD	MMBT 5086
47301	KST5087	2N5087, SMD	MMBT 5087
47302	KST5088	2N5088, SMD	MMBT 5088
47303	KST5089	2N5089, SMD	MMBT 5089
47304	KST5179	2N5179, SMD	MMBT 5179
47305	KST5401	2N5401, SMD	MMBT 5401
47306	KST55	MPSA 55, SMD	MMBTA 55
47307	KST5550	2N5550, SMD	MMBT 5550
47308	KST5551	2N5551, SMD	MMBT 5551
47309	KST56	MPSA 56, SMD	MMBTA 56
47310	KST63	MPSA 63, SMD	MMBTA 63
47311	KST64	MPSA 64, SMD	MMBTA 64
47312	KST6428	2N6428, SMD	MMBT 6428
47313	KST812	2SA812, SMD	2SA812
47314	KST92	MPSA 92, SMD	MMBTA 92
47315	KST93	MPSA 93, SMD	MMBTA 93
47316	KT	P6 SMB-12A	P6 SMB-12A
47317	KT	2SC4007	2SC4007
47318	KT	2SC4270	2SC4270
47319	KT208(A...V)	20..60V, 0,15A, 0,2W	BC 212, BC 556, 2SA970, 2SA1049
47320	KT209(A...V)	15..60V, 0,3A, 0,2W	BC 327...328, BC 636, BC 638, BC 640
47321	KT3107(A...V)	25..60V, 0,1A, 0,2W, 200MHz	BC 212, BC 556, 2SA970, 2SA1049
47322	KT814A,B,G,V	40..100V, 1,5A, 10W, 3MHz	BD 140, BD 238, BD 380, BD 792
47323	KT815A,B,G,V	40..100V, 1,5A, 10W, 3MHz	BD 139, BD 237, BD 379, BD 791
47324	KT816A,B,G,V	40..100V, 3A, 20W, 3MHz	BD 190, BD 724, BD 726
47325	KT817A,B,G,V	40..100V, 3A, 20W, 3MHz	BD 189, BD 723, BD 725, BD 443
47326	KT818A,B,G,V	-/40..90V, 15A, 100W, 3MHz	BD 744C...F
47327	KT819A,B,G,V	-/40..100V, 15A, 100W, 3MHz	BD 743C...F
47328	KTA1001	-/20V, 3A, 170MHz	2SA1730, 2SA1736, 2SB1124
47329	KTA1015	2SA1015	2SA1015
47330	KTA1021	-/30V, 0,5A, 0,4W	BC 327...328, BC 638, BC 640, 2SB910
47331	KTA1023	-/120V, 0,8A, 1W, 120MHz	2SA1013, 2SA1275, 2SB1456
47332	KTA1024	-/150V, 0,05A, 1W	2SA1016K, 2SA1123...24, 2SA1482
47333	KTA1070	-/200V, 0,1A, 1W	BF 421A, BF 423A, 2SA1370...71
47334	KTA1099	-/120V, 0,3A, 8W	2SA1799
47335	KTA1241	-/20V, 5A, 1W, 170MHz	2SA1050, 2SA1431, 2SB1288, 2SB1306
47336	KTA1266	-/50V, 0,15A, 0,625W	BC 556, BC 212, BC 256, 2SA1436
47337	KTA1267(L)	KTA 1266	BC 556, BC 212, BC 256, 2SA1436
47338	KTA1268	-/120V, 0,1A, 0,625W	2SA1016K, 2SA1123...24, 2SA1482
47339	KTA1270	-/30V, 0,5A, 0,625W	BC 327...328, BC 638, BC 640, 2SB910

47340	KTA1271	-/30V, 0,8A, 0,625W	BC 327...328, BC 638, BC 640, 2SB910
47341	KTA1272	-/30V, 0,8A, 0,4W	BC 327...328, BC 638, BC 640, 2SB910
47342	KTA1273	-/30V, 2A, 1W, 120MHz	2SA1382, 2SB892, 2SB1312, 2SA1434
47343	KTA1274	-/80V, 0,4A, 1W	BC 640, 2SB647, 2SB1041, 2SB1437
47344	KTA1275	-/160V, 1A, 1W, 20MHz	2SA1013, 2SA1275, 2SA1770, 2SB1212
47345	KTA1276	-/30V, 3A, 10W, 100MHz	2SA1012, 2SA1288, 2SB1064, 2SB1273
47346	KTA1298	2SA1298	2SA1298
47347	KTA1302	2SA1302	2SA1302
47348	KTA1504	-/50V, 0,15A	BC 856...857, BCF 70, BCW 69...70
47349	KTA1505	-/30V, 0,5A	BC 807, BCW 67...68, BCX 17, 2SA1313
47350	KTA1517	-/120V, 0,1A	2SA1312
47351	KTA1657	-/150V, 1,5A, 20W	2SA1306(A,B), 2SA1332, 2SA1606, 2SB1186A
47352	KTA1658	-/30V, 3A, 15W, 100MHz	2SA1440, 2SB1185, 2SB1274, 2SB1314
47353	KTA1659	-/160V, 1,5A, 20W, 100MHz	2SA1306(A,B), 2SA1332, 2SA1606, 2SA1859A
47354	KTA1659A	KTA 1659, 180V	2SA1306A,B, 2SA1606, 2SA1859A, 2SA1837
47355	KTA1660	-/150V, 0,05A	2SA1200, 2SA1660, 2SB807, 2SB1046...47
47356	KTA1661	-/120V, 0,8A	2SA1201, 2SA1661, 2SB806, 2SB1025...26
47357	KTA1662	-/80V, 0,4A	2SA1202, 2SA1368, 2SA1662, 2SB767
47358	KTA1663	-/30V, 1,5A	2SA1213, 2SA1663, 2SB1313, 2SB1519
47359	KTA1664	-/30V, 0,8A	BCX 51, 2SA1204, 2SA1664, 2SA1734
47360	KTA200	-/50V, 0,5A, 0,625W	BC 327A, BC 638, BC 640, 2SB910
47361	KTA2400	-/120V, 0,1A, 100MHz	2SA970, 2SA1049, 2SA1136, 2SA1335
47362	KTA473	2SA473	2SA473
47363	KTA940	2SA940	2SA940
47364	KTA950	2SA950	2SA950
47365	KTA968(A)	2SA968(A)	2SA968
47366	KTB1366(v)	-/60, 3A, 25W, 3MHz	BDT 32(A...C)F, 2SA1440, 2SA1635, 2SB1335
47367	KTB1367(v)	-/100, 5A, 30W, 12MHz	BD 956F, 2SA1741, 2SB1016, 2SB1294
47368	KTB1368(v)	-/80, 4A, 25W, 8MHz	BD 954F, 2SA1741, 2SB1095, 2SB1294
47369	KTB2955	-/120, 10A, 40W, 12MHz	BD 744D...F, 2SA1077
47370	KTB595	2SB595	2SB595
47371	KTB596	2SB596	2SB596
47372	KTB778	-/120, 10A, 80W, 12MHz	2SA1672, 2SA1805, 2SA1909, 2SB1860
47373	KTB834	2SB834	2SB834
47374	KTB988	-/60, 3A, 30W, 3MHz	BD 242C...F, BD 538, BD 938, 2SB690
47375	KTB989	-/80, 4A, 30W, 8MHz	BD 244C...F, BD 538, BD 952, 2SB690
47376	KTC1001	-/300, 0,15A, 12,5W	2SC3565, 2SC3946, 2SC4075
47377	KTC1003	-/60, 4A, 30W	2SD1958, 2SD1136, 2SD1159
47378	KTC1006	-/80, 0,8A, 1W	-
47379	KTC1020	-/30, 0,8A, 0,4W	BC 337, BC 635, BC 637, 2SD1225
47380	KTC1026	-/180, 0,1A, 1W, 50MHz	2SC3248, 2SD2031
47381	KTC1027	-/120, 0,8A, 1W, 120MHz	2SC2383, 2SC3228, 2SD2184
47382	KTC1094	-/60, 50mA, 1W	2SC3526, 2SC4829
47383	KTC1095	-/20, 0,5A, 5W	2SC4605, 2SC4201...02, 2SC4411
47384	KTC1170	-/200, 0,1A, 5W	2SC3565, 2SC4075



47385	KTC1173	2SC1173	2SC1173
47386	KTC1199	-/120, 0,3A, 8W	2SC3612, 2SC4714
47387	KTC1815	2SC1815	2SC1815
47388	KTC1959	2SC1959	2SC1959
47389	KTC200	-/50V, 0,5A, 0,625W	BC 337A, BC 637, BC 639, 2SD1226
47390	KTC2068	2SC2068	2SC2068
47391	KTC2073	2SC2073	2SC2073
47392	KTC2078	-/80, 4A, 10W	2SC1816, 2SC2075, 2SC2078, 2SC2119
47393	KTC2120	2SC2120	2SC2120
47394	KTC2236(A)	2SC2236(A), 2A, 1W	2SC2236
47395	KTC2238(A)	2SC2238(A)	2SC2238
47396	KTC2347	2SC2347	2SC2347
47397	KTC2553	2SC2553	2SC2553
47398	KTC3112	2SC3112	2SC3112
47399	KTC3113	2SC3113	2SC3113
47400	KTC3120	2SC3120	2SC3120
47401	KTC3121	2SC3121	2SC3121
47402	KTC3190	2SC3190	2SC3190
47403	KTC3191	2SC3191	2SC3191
47404	KTC3192	2SC3192	2SC3192
47405	KTC3193	2SC3193	2SC3193
47406	KTC3194	2SC3194	2SC3194
47407	KTC3195	2SC3195	2SC3195
47408	KTC3197	2SC3197	2SC3197
47409	KTC3198	2SC3198	2SC3198
47410	KTC3199	2SC3199	2SC3199
47411	KTC3200	2SC3200	2SC3200
47412	KTC3203	2SC3203	2SC3203
47413	KTC3204	2SC3204	2SC3204
47414	KTC3205	2SC3205	2SC3205
47415	KTC3206	2SC3206	2SC3206
47416	KTC3207	2SC3207	2SC3207
47417	KTC3208	2SC3208	2SC3208
47418	KTC3226	2SC3226	2SC3226
47419	KTC3227	2SC3227	2SC3227
47420	KTC3228	2SC3228	2SC3228
47421	KTC3229	2SC3229	2SC3229
47422	KTC3230	2SC3230	2SC3230
47423	KTC3231	2SC3231	2SC3231
47424	KTC3265	2SC3265	2SC3265
47425	KTC3281	2SC3281	2SC3281
47426	KTC3295	2SC3295	2SC3295
47427	KTC3400	-/120V, 0,1A, 100MHz	2SC2362K, 2SC2631...32, 2SC3800
47428	KTC3875	2SC3875	2SC3875
47429	KTC3876	2SC3876	2SC3876

47430	KTC3878	2SC3878	2SC3878
47431	KTC3879	2SC3879	2SC3879
47432	KTC388(A)	2SC388(A)	2SC388(A)
47433	KTC3880	2SC3880	2SC3880
47434	KTC3881	2SC3881	2SC3881
47435	KTC3882	-/15V, 0,05A	BF 599, BFS 17, BFS 20, 2SC3015...3016
47436	KTC3883	-/15V, 0,2A	-
47437	KTC3911	-/120V, 0,1A	2SC3324, 2SC4117
47438	KTC3920	-/30V, 0,5A	BC 817, BCW 65, BCX 19, 2SC3325
47439	KTC4368	2SC4368	2SC4368
47440	KTC4369	2SC4369	2SC4369
47441	KTC4370	2SC4370	2SC4370
47442	KTC4371	2SC4371	2SC4371
47443	KTC4372	2SC4372	2SC4372
47444	KTC4373	2SC4373	2SC4373
47445	KTC4374	2SC4374	2SC4374
47446	KTC4375	2SC4375	2SC4375
47447	KTC4376	2SC4376	2SC4376
47448	KTC4377	2SC4377	2SC4377
47449	KTC8050	-/25, 0,8A, 0,625W	BC 337, BC 635, BC 637, 2SD1225
47450	KTC8550	-/25, 0,8A, 0,625W	BC 327, BC 636, BC 636, 2SB909
47451	KTC9011	-/30V, 50mA, 0,625W	BF 240...41, BF 254...55, BF 594...595
47452	KTC9012	-/30V, 0,5A, 0,625W	BC 327, BC 636, BC 638, 2SB909
47453	KTC9013	-/30V, 0,5A, 0,625W	BC 337, BC 635, BC 637, 2SD1225
47454	KTC9014	-/50V, 0,15A, 0,625W	BC 414, BC 550, 2SC2240, 2SC2675
47455	KTC9015	-/50V, 0,15A, 0,625W	BC 416, BC 560, 2SA970, 2SA1137
47456	KTC9016	-/30V, 20mA, 0,625W	BF 240...241, BF 254...255, BF 594...595
47457	KTC9018	-/30V, 20mA, 0,625W	BF 225, BF 255, BF 314, BF 505, BF 507
47458	KTD1003	KTD 1028, SMD	-
47459	KTD1028	-/50V, 1A, B>300	2SC3247
47460	KTD1145	2SD1145	2SD1145
47461	KTD1302	-/20V, 0,3A, 0,625W	BC 338...337, BC 635, 2SC3377, 2SD1302
47462	KTD1303	KTD 1302, -/16V, 0,4W	BC 338...337, BC 635, 2SC3377, 2SD1302
47463	KTD1304	KTD 1302, SMD, -/16V	BC 817...818, BCX 19...20, 2SC3341
47464	KTD1351	2SD1351	2SD1351
47465	KTD1352	2SD1352	2SD1352
47466	KTD1414	2SD1414	2SD1414
47467	KTD1554A	2SD1554	2SD1554
47468	KTD1555A	2SD1555	2SD1555
47469	KTD1937	-/80V, 10A, B>500	2SC4024, 2SD1947
47470	KTD1945	-/60V, 3A, 25W	2SC3540, 2SC3746, 2SC4549, 2SC4596
47471	KTD2058	2SD2058	2SD2058
47472	KTD2059	2SD2059	2SD2059
47473	KTD2060	2SD2060	2SD2060
47474	KTD2066(v)	-/80V, 5A, 30W, B>500	2SC4553, 2SC4558, 2SD1474, 2SD2076

47475	KTD2092	2SD2092	2SD2092
47476	KTD3055	-/120V, 10A, 40W, 12MHz	BD 743D...F, 2SC2527
47477	KTD525	2SD525	2SD525
47478	KTD526	2SD526	2SD526
47479	KTD686	200/2100ns	BDW 23C, BDW 63C...D, 2SD1147
47480	KTD880	2SD880	2SD880
47481	KTD998	-/120V, 10A, 80W, 12MHz	2SC4690, 2SC4886
47482	KTK1021	KTK 821	BUK 445-450, 2SK1444, 2SK1862...63
47483	KTK1031	KTK 831	2SK1231, 2SK1351, 2SK1445, 2SK1608
47484	KTK1040	KTK 840	2SK1352, 2SK1446, 2SK1609, 2SK1566...67
47485	KTK1140	KTK 740	-
47486	KTK117	2SK117, 0,625W	2SK117
47487	KTK123	15V, 0,625W, Idss5..14mA	-
47488	KTK127	2SK123, 0,4W	-
47489	KTK136	2SK123, SMD	-
47490	KTK161	2SK161, 0,4W	2SK161
47491	KTK184	2SK184, 0,4W	2SK184
47492	KTK192A	2SK192A, 0,4W	2SK192A
47493	KTK209	2SK209	2SK209
47494	KTK211	2SK211	2SK211
47495	KTK24	60V, 16A, 60W, <65mOhm(8A)	BUK 552-60, 2SK971...72, 2SK1115, 2SK1416
47496	KTK596	2SK596, 0,4W	2SK596
47497	KTK740	<0,7Ohm(5A)	2SK1442, 2SK1503
47498	KTK821	450V, 3A, 40W, <2,6Ohm(1A)	2SK1154, 2SK1244, 2SK1439, 2SK1493...94
47499	KTK831	450V, 5A, 75W, <1,6Ohm(3A)	BUZ 41...42A, IRF 830, 2SK1156, 2SK1246
47500	KTK840	<0,75Ohm(8A)	IRF 840, 2SK894, 2SK1495...96, 2SK1574
47501	KTK930	900V, 5A, 150W, <3Ohm(5A)	2SK539, 2SK1465
47502	KTN2222(A)	2N2222(A), 0,625W	2N2222
47503	KTN2222(A)S	2N2222(A), SMD	BSR14, BSS79, PMBT2222(A), SMBT2222(A)
47504	KTN2369(A)	2N2369(A), 0,625W	2N2369
47505	KTN2369(A)	2N2369(A), SMD	2SC4168, PMBT 2369(A)
47506	KTN2907(A)	2N2907(A), 0,625W	2N2907
47507	KTN2907(A)	2N2907(A), SMD	A)
47508	KTQ127	3SK127	3SK127
47509	KU	P6 SMB-13	P6 SMB-13
47510	KU601	60V, 2A, 10W(Tc105°), 15MHz	BUX 16, 2SC2809
47511	KU602	15MHz	BUX 16, 2SC2809
47512	KU605	200V, 10A, 50W(Tc80°), 5MHz	BU 109, BUX 17, TIP 160, 2SC2769
47513	KU606	120V, 8A, 50W(Tc80°), 5MHz	BU 109, BUX 17, TIP 160, 2SC2769
47514	KU607	210V, 10A, 70W(Tc45°)	BU 109, BUX 17, TIP 160, 2SC2769
47515	KU608	250V, 10A, 70W(Tc45°), 9MHz	BU 109, BUX 17, TIP 160, 2SC2769
47516	KU611	60V, 3A, 10W(Tc105°), 30MHz	BD 241B, BD 243B, BU 409, 2SD422...423
47517	KU612	30MHz	BD 241C, BD 243C, BU 409, 2SD422...423
47518	KV	P6 SMB-13A	P6 SMB-13A
47519	KV	1SV267	1SV267

47520	KV	1SV264	1SV264
47521	KW	P6 SMB-15	P6 SMB-15
47522	KX	P6 SMB-15A	P6 SMB-15A
47523	KX	PMBF 170	PMBF 170
47524	KY	P6 SMB-16	P6 SMB-16
47525	KY	2SC3771	2SC3771
47526	KY	2SK881-Y	2SK881
47527	KY	KTK 211-Y	KTK 211
47528	KY	2SK211-Y	2SK211
47529	KY	KTA1001-Y	KTA 1001
47530	KY	2SK1764	2SK1764
47531	KZ	P6 SMB-16A	P6 SMB-16A
47532	L	2SK1689	2SK1689
47533	L	HVU 356	HVU 356
47534	L	2SC4211	2SC4211
47535	L	2SK690	2SK690
47536	L1	BSS 65	BSS 65
47537	L1	BFS 36	BFS 36
47538	L15	2SC3624A-L15	2SC3624A
47539	L15	2SC4181A-L15	2SC4181A
47540	L16	2SC4181A-L16	2SC4181A
47541	L16	2SC3624A-L16	2SC3624A
47542	L17	2SC3624-L17	2SC3624
47543	L17	2SC4181-L17	2SC4181
47544	L18	2SC4181-L18	2SC4181
47545	L18	2SC3624-L18	2SC3624
47546	L1G	HN 2C01FU-GR	HN 2C01FU
47547	L1X	KSK 123	2SK123
47548	L1Y	HN 2C01FU-Y	HN 2C01FU
47549	L2	BSS 69	BSS 69
47550	L2	BFS 36A	BFS 36A
47551	L20	BAS 29	BAS 29
47552	L21	BAS 31	BAS 31
47553	L22	BAS 35	BAS 35
47554	L2X	KSK 211	2SK211
47555	L3	2SC1623-L3	2SC1623
47556	L3	BSS 70	BSS 70
47557	L3	BFS 37	BFS 37
47558	L3	KST 1623L3	KST 1623
47559	L30	BAV 23	BAV 23
47560	L30	FA 1L4L	FA 1...
47561	L30	GA 1L4L	GA 1...
47562	L31	FA 1L4M	FA 1...
47563	L31	GA 1L4M	GA 1...
47564	L31	BAV 23S	BAV 23S

47565	L32	FA 1F4M	FA 1...
47566	L32	GA 1F4M	GA 1...
47567	L33	GA 1A4M	GA 1...
47568	L33	FA 1A4M	FA 1...
47569	L34	GA 1A4P	GA 1...
47570	L34	FA 1A4P	FA 1...
47571	L35	GA 1F4N	GA 1...
47572	L35	FA 1F4N	FA 1...
47573	L36	GA 1L3Z-O	GA 1...
47574	L36	FA 1L3Z-O	FA 1...
47575	L37	GA 1L3Z-P	GA 1...
47576	L37	FA 1L3Z-P	FA 1...
47577	L38	FA 1L3Z-K	FA 1...
47578	L38	GA 1L3Z-K	GA 1...
47579	L4	D 1FL40	D 1FL40
47580	L4	2SC2812-L4	2SC2812
47581	L4	KST 1623L4	KST 1623
47582	L4	2SC1623-L4	2SC1623
47583	L4	BSS 65R	BSS 65R
47584	L4	BAT 54W	BAT 54W
47585	L4	BFS 37A	BFS 37A
47586	L4	2SC4177-L4	2SC4177
47587	L4	2SC4783-L4	2SC4783
47588	L4(p)	BAT 54	BAT 54
47589	L41	BAT 74	BAT 74
47590	L42	BAT 54A	BAT 54A
47591	L43	BAT 54C	BAT 54C
47592	L44	BAT 54S	BAT 54S
47593	L5	BFT 27	BFT 27
47594	L5	2SC4177-L5	2SC4177
47595	L5	KST 1623L5	KST 1623
47596	L5	2SC4783-L5	2SC4783
47597	L5	BSS 69R	BSS 69R
47598	L5	2SC1623-L5	2SC1623
47599	L5	2SC2812-L5	2SC2812
47600	L5(p)	BAS 55	BAS 55
47601	L51	BAS 56	BAS 56
47602	L52	BAS 678	BAS 678
47603	L6	BSS 47	BSS 47
47604	L6	2SC4177-L6	2SC4177
47605	L6	2SC4783-L6	2SC4783
47606	L6	KST 1623L6	KST 1623
47607	L6	BSS 70R	BSS 70R
47608	L6	BAR 17	BAR 17
47609	L6	2SC2812-L6	2SC2812

47610	L6	2SC1623-L6	2SC1623
47611	L61	GA 1L4Z-Q	GA 1...
47612	L61	FA 1L4Z-Q	FA 1...
47613	L62	GA 1L4Z-P	GA 1...
47614	L62	FA 1L4Z-P	FA 1...
47615	L63	FA 1L4Z-K	FA 1...
47616	L63	GA 1L4Z-K	GA 1...
47617	L64	FA 1F4Z-Q	FA 1...
47618	L64	GA 1F4Z-Q	GA 1...
47619	L65	GA 1F4Z-P	GA 1...
47620	L65	FA 1F4Z-P	FA 1...
47621	L66	GA 1F4Z-K	GA 1...
47622	L66	FA 1F4Z-K	FA 1...
47623	L67	FA 1A4Z-Q	FA 1...
47624	L67	GA 1A4Z-Q	GA 1...
47625	L68	FA 1A4Z-P	FA 1...
47626	L68	GA 1A4Z-P	GA 1...
47627	L69	FA 1A4Z-K	FA 1...
47628	L69	GA 1A4Z-K	GA 1...
47629	L7	2SC4177-L7	2SC4177
47630	L7	2SC4783-L7	2SC4783
47631	L7	BAR 14-1	BAR 14
47632	L7	BSS 56	BSS 56
47633	L7	2SC1623-L7	2SC1623
47634	L7	2SC2812-L7	2SC2812
47635	L7	KST 1623L7	KST 1623
47636	L8	BAR 15-1	BAR 15
47637	L81	GA 1L3M	GA 1...
47638	L81	FA 1L3M	FA 1...
47639	L82	GA 1L3N	GA 1...
47640	L82	FA 1L3N	FA 1...
47641	L83	FA 1A3Q	FA 1...
47642	L83	GA 1A3Q	GA 1...
47643	L9	BAR 16-1	BAR 16
47644	L9	1SS349	1SS349
47645	LA	μPA605T	æPA605T
47646	LA	μPA671T	æPA671T
47647	LA	HD 2A3M	HD 2...
47648	LA	KTD1003-A	KTD 1003
47649	LA	2SA1681	2SA1681
47650	LA(p)	BF 550	BF 550
47651	LB	BF 999	BF 999
47652	LB	2SC2462-B	2SC2462
47653	LB	HD 2F3P	HD 2...
47654	LB	KTD1003-B	KTD 1003



47655	LB	2SA1734	2SA1734
47656	LC	2SC2462-C	2SC2462
47657	LC	2SC4357-C	2SC4357
47658	LC	2SA1735	2SA1735
47659	LC	HD 2L3N	HD 2...
47660	LC	KTD1003-C	KTD 1003
47661	LD	P6 SMB-18	P6 SMB-18
47662	LD	BF 543	BF 543
47663	LD	2SC2462-D	2SC2462
47664	LD	SM 6T 6V8C	SM 6T...
47665	LD	2SC4357-D	2SC4357
47666	LD	2SA1736	2SA1736
47667	LD	HD 2A4M	HD 2...
47668	LD1	FA 3L4Z	FA 3...
47669	LE	2SC2412L-LE	2SC2412L
47670	LE	P6 SMB-18A	P6 SMB-18A
47671	LE	2SC4154-E	2SC4154
47672	LE	2SC3052-E	2SC3052
47673	LE	2SC2412KLN-E	2SC2412KLN
47674	LE	HD 2L2Q	HD 2...
47675	LE	SM 6T 6V8CA	SM 6T...
47676	LE	2SC4357-E	2SC4357
47677	LE(p)	BF 660	BF 660
47678	LF	P6 SMB-20	P6 SMB-20
47679	LF	2SC3052-F	2SC3052
47680	LF	2SC4154-F	2SC4154
47681	LF	SM 6T 7V5C	SM 6T...
47682	LF	HD 2F2Q	HD 2...
47683	LFs	BF 770	BF 770
47684	LG	2SC4207-GR	2SC4207
47685	LG	2SC4944-GR	2SC4944
47686	LG	P6 SMB-20A	P6 SMB-20A
47687	LG	2SC2712-GR	2SC2712
47688	LG	BF 767	BF 767
47689	LG	2SC4738-GR	2SC4738
47690	LG	BF 775A	BF 775A
47691	LG	2SC3052-G	2SC3052
47692	LG	2SC4116-GR	2SC4116
47693	LG	2SC4154-G	2SC4154
47694	LG	SM 6T 7V5CA	SM 6T...
47695	LH	P6 SMB-22	P6 SMB-22
47696	LH(p)	BF 569	BF 569
47697	LJ(p)	BF 579	BF 579
47698	LK	P6 SMB-22A	P6 SMB-22A
47699	LK	BF 799	BF 799

47700	LK	BF 568	BF 568
47701	LK	2SD1000-LK	2SD1000
47702	LL	2SC4207-BL	2SC4207
47703	LL	P6 SMB-24	P6 SMB-24
47704	LL	2SA1518	2SA1518
47705	LL	2SC2712-BL	2SC2712
47706	LL	2SC4738-BL	2SC4738
47707	LL	2SC4116-BL	2SC4116
47708	LL	2SD1000-LL	2SD1000
47709	LL4148	1N4148, SMD	BAS 32
47710	LL4150	1N4150, SMD	BAS 32
47711	LL4151	1N4151, SMD	BAS 32
47712	LL4448	1N4448, SMD	BAS 32
47713	LM	P6 SMB-24A	P6 SMB-24A
47714	LM	BF 569R	BF 569R
47715	LM	BST 120	BST 120
47716	LM	2SD1000-LM	2SD1000
47717	LM1014	BF 273	BF 273
47718	LM1015	BF 240	BF 240
47719	LM1098	BF 255	BF 255
47720	LM1181	BC 239	BC 239
47721	LM1403	BC 337	BC 337
47722	LM1404	BC 327	BC 327
47723	LM1410K	BC 307	BC 307
47724	LM1427	BC 337	BC 337
47725	LM1428	BC 327	BC 327
47726	LM2501J	BC 337	BC 337
47727	LM2502J	BC 327	BC 327
47728	LM2636	BC 337	BC 337
47729	LM390(A)	BC 328	BC 328
47730	LM399(A)	BC 338	BC 338
47731	LN	P6 SMB-27	P6 SMB-27
47732	LN	BST 122	BST 122
47733	LN	SM 6T 10C	SM 6T...
47734	LN9014(B...D)	30V, 0,1A, 0,3W, 120MHz	BC 169, BC 184, BC 239, BC 549
47735	LN9015(B...D)	30V, 0,1A, 0,3W, 120MHz	BC 214, BC 259, BC 309, BC 559
47736	LO	2SC4116-O	2SC4116
47737	LO	BF 775	BF 775
47738	LO	BSR174	BSR174
47739	LO	2SC2712-O	2SC2712
47740	LP	P6 SMB-27A	P6 SMB-27A
47741	LP	BSR 175	BSR 175
47742	LP	SM 6T 10CA	SM 6T...
47743	LP	HD 1A3M	HD 1...
47744	LQ	P6 SMB-30	P6 SMB-30

47745	LQ	BSR 176	BSR 176
47746	LQ	2SD1821A-Q	2SD1821A
47747	LQ	2SD2240A-Q	2SD2240A
47748	LQ	2SD814A-Q	2SD814A
47749	LQ	HD 1F3P	HD 1...
47750	LR	2SC2412L-LR	2SC2412L
47751	LR	P6 SMB-30A	P6 SMB-30A
47752	LR	2SD1821A-R	2SD1821A
47753	LR	BSR 177	BSR 177
47754	LR	2SD2240A-R	2SD2240A
47755	LR	2SD814A-R	2SD814A
47756	LR	BF 517	BF 517
47757	LR	2SC2412KLN-R	2SC2412KLN
47758	LR	HD 1L3N	HD 1...
47759	LS	2SC2412L-LS	2SC2412L
47760	LS	P6 SMB-33	P6 SMB-33
47761	LS	2SC2412KLN-S	2SC2412KLN
47762	LS	BF 770A	BF 770A
47763	LS	2SD2240A-S	2SD2240A
47764	LS	2SD1821A-S	2SD1821A
47765	LS	2SD814A-S	2SD814A
47766	LS	HD 1A4M	HD 1...
47767	LS4148	1N4148, SMD	BAS 32
47768	LS4150	1N4150, SMD	BAS 32
47769	LS4151	1N4151, SMD	BAS 32
47770	LS4154	1N4154, SMD	BAS 32
47771	LS4448	1N4448, SMD	BAS 32
47772	LT	P6 SMB-33A	P6 SMB-33A
47773	LT	2SD1821A-T	2SD1821A
47774	LT	2SD2240A-T	2SD2240A
47775	LT	2SD814A-T	2SD814A
47776	LT	2SD2028	2SD2028
47777	LT	HD 1L2Q	HD 1...
47778	LT1001A	40V, 0,2A	MRF 586[Motorola]
47779	LT1016	BF 255	BF 255
47780	LT1739	100V, 0,3A, >900MHz	-
47781	LT1814	120V, 0,4A, >1GHz	-
47782	LT1817	120V, 0,4A, >1GHz	-
47783	LT1839	120V, 0,3A, >1GHz	-
47784	LT2001	40V, 0,2A, 3GHz	MRF 587[Motorola]
47785	LT3005	40V, 0,2A, 3GHz	MRF 587[Motorola]
47786	LT3014	40V, 0,2A, 3GHz	MRF 587[Motorola]
47787	LT3046	40V, 0,15A, 3GHz	BRF 96, MRF 965[Motorola]
47788	LT4217	20V, 0,4A, 5,5GHz	-
47789	LT4239	LT 4217, 5GHz	-

47790	LT4700	20V, 50mA, 6GHz	MRF 572[Motorola]
47791	LT4746	20V, 50mA, 6GHz	MRF 905[Motorola]
47792	LT4772	LT 4746	MRF 914[Motorola]
47793	LT5817	80V, 0,4A, >1,5GHz	-
47794	LT5839	80V, 0,3A, >1,5GHz	-
47795	LTVG10	10kV, 0,02A	HS 8
47796	LTVG11	11kV, 0,02A	HS 10
47797	LTVG5	5kV, 0,02A	HS 6
47798	LU	P6 SMB-36	P6 SMB-36
47799	LU	HD 1F2Q	HD 1...
47800	LV	1SV265	1SV265
47801	LV	P6 SMB-36A	P6 SMB-36A
47802	LW	P6 SMB-39	P6 SMB-39
47803	LW	SM 6T 15C	SM 6T...
47804	LX	P6 SMB-39A	P6 SMB-39A
47805	LX	HD 1A4A	HD 1...
47806	LX	SM 6T 15CA	SM 6T...
47807	LY	2SC4207-Y	2SC4207
47808	LY	2SC4944-Y	2SC4944
47809	LY	P6 SMB-43	P6 SMB-43
47810	LY	2SC4116-Y	2SC4116
47811	LY	2SC4003	2SC4003
47812	LY	2SC3772	2SC3772
47813	LY	2SC2712-Y	2SC2712
47814	LY	2SC4738-Y	2SC4738
47815	LZ	P6 SMB-43A	P6 SMB-43A
47816	M	2SK1962	2SK1962
47817	M	2SA1622	2SA1622
47818	M.B	MA 1U152A	MA 152A
47819	M.I	MA 1U152K	MA 152K
47820	M.O	MA 1U152WA	MA 152WA
47821	M.S	MA 1U157A	MA 157A
47822	M.U	MA 1U152WK	MA 152WK
47823	M01..10	100..1000V, 2A	B...C2200
47824	M03	BSS 83	BSS 83
47825	M05	SO 960	SO 960
47826	M06	SO 961	SO 961
47827	M08	PMBFJ 308	PMBFJ 308
47828	M09	PMBFJ 309	PMBFJ 309
47829	M1	2SC5066-O	2SC5066
47830	M1	D70F2T1	D70F2T1
47831	M1(p)	BFR 30	BFR 30
47832	M10	PMBFJ 310	PMBFJ 310
47833	M102	M 12, 1000V	BA 159, BAY 90, BY 204/10, BY 208/1000
47834	M11	MC 911	MC 911

47835	M12	100V, 0,2A	BA 188...190, BAY 20...21, BAY 45...46
47836	M15	2SA1613-M15	2SA1613
47837	M15	2SA1411-M15	2SA1411
47838	M16	PMBF 4416A	PMBF 4416...
47839	M16	2SA1411-M16	2SA1411
47840	M16	2SA1613-M16	2SA1613
47841	M18	BSN 22	BSN 22
47842	M193(A...D)	BF 450	BF 450
47843	M1A	MA 159	MA 159
47844	M1B	MA 159A	MA 159A
47845	M1B	MA 4S159	MA 159
47846	M1B	MMBT 2222	MMBT 2222
47847	M1C	MA 158	MA 158
47848	M1D	MA 160	MA 160
47849	M1E	MA 160A	MA 160A
47850	M1E	MMBTA 43	MMBTA 43
47851	M1F	MA 194	MA 194
47852	M1F	MMBT 5550	MMBT 5550
47853	M1G	HN 2A01FU-GR	HN 2A01FU
47854	M1I	MA 862	MA 862
47855	M1J	MMBT 2369	MMBT 2369
47856	M1K	MA 704	MA 704
47857	M1L	MA 704A	MA 704A
47858	M1L	MA 741	MA 741
47859	M1L	MA 781	MA 781
47860	M1M	MA 721	MA 721
47861	M1N	MA 713	MA 713
47862	M1N	MA 4S713	MA 713
47863	M1O	MA 726	MA 726
47864	M1P	MA 714	MA 714
47865	M1S	MA 348	MA 348
47866	M1T	MA 724	MA 724
47867	M1U	MA 716	MA 716
47868	M1U	MA 742	MA 742
47869	M1X	MA 75WA	MA 75WA
47870	M1X	MA 80WA	MA 80WA
47871	M1Y	HN 2A01FU-Y	HN 2A01FU
47872	M1Y	MA 75WK	MA 75WK
47873	M1Y	MA 80WK	MA 80WK
47874	M1Z	MA 727	MA 727
47875	M2	100V, 1A	BYG 10D...M, D 1F20...60, U 1DC44...JC44
47876	M2	2SC5066-Y	2SC5066
47877	M2(p)	BFR 31	BFR 31
47878	M20	BFR 200	BFR 200
47879	M21	MC 921	MC 921

47880	M21C,CA	Igt/Ih<1/3mA	BRX 45...49, BRX 50...56, BRY 55/...
47881	M22	M 12, 200V	BA 190, BAW 52, BAY 20...21, BAY 88
47882	M23C,CA	Igt/Ih<1/2mA	C 106..., C 107..., TAG 106..., TAG 107...
47883	M2A	MA 122	MA 122
47884	M2B	MA 123	MA 123
47885	M2B	MMBT 2907	MMBT 2907
47886	M2C	MA 124	MA 124
47887	M2C	MMBTA 70	MMBTA 70
47888	M2D	MA 1S121	MA 1S121
47889	M2D	MA 121	MA 121
47890	M2D	MA 6S121	MA 121
47891	M2E	MA 164	MA 164
47892	M2F	MA 198	MA 198
47893	M2H	MA 555	MA 555
47894	M2I	MA 125	MA 125
47895	M2K	MA 351	MA 351
47896	M2L	MA 78	MA 78
47897	M2M	MA 795	MA 795
47898	M2M	MA 717	MA 717
47899	M2M	MA 745	MA 745
47900	M2M	MA 795	MA 795
47901	M2N	MA 718	MA 718
47902	M2N	MA 6S718	MA 718
47903	M2P	MA 704WA	MA 704WA
47904	M2P	MA 741WA	MA 741WA
47905	M2Q	MA 174	MA 174
47906	M2R	MA 704WK	MA 704WK
47907	M2R	MA 741WK	MA 741WK
47908	M2S	MA 126	MA 126
47909	M2T	MA 556	MA 556
47910	M2U	MA 127	MA 127
47911	M2V	MA 128	MA 128
47912	M2W	MA 744	MA 744
47913	M2W	MA 720	MA 744
47914	M2X	MA 730	MA 730
47915	M2Y	MA 715	MA 715
47916	M2Z	MA 193	MA 193
47917	M3	200V, 1A	BYG 10D...M, D 1F20...60, U 1DC44...JC44
47918	M3	KST 812M3	KST 812
47919	M3	BFT 46	BFT 46
47920	M3	KDV 173	KDV 173
47921	M3	2SA812-M3	2SA812
47922	M3	MMBA 812M3	MMBA 812
47923	M30	GN 1L4L	GN 1...
47924	M30	FN 1L4L	FN 1...



47925	M30	MA 557	MA 557
47926	M31	BSD 20	BSD 20
47927	M31	FN 1L4M	FN 1...
47928	M31	GN 1L4M	GN 1...
47929	M31	MC 931	MC 931
47930	M32	BSD 22	BSD 22
47931	M32	FN 1F4M	FN 1...
47932	M32	GN 1F4M	GN 1...
47933	M32	MC 932	MC 932
47934	M33	BF 861A	BF 861
47935	M33	GN 1A4M	GN 1...
47936	M33	FN 1A4M	FN 1...
47937	M34	BF 861B	BF 861
47938	M34	FN 1A4P	FN 1...
47939	M34	GN 1A4P	GN 1...
47940	M35	GN 1F4N	GN 1...
47941	M35	FN 1F4N	FN 1...
47942	M35	BF 861C	BF 861
47943	M36	GN 1L3Z-Q	GN 1...
47944	M36	FN 1L3Z-Q	FN 1...
47945	M37	GN 1L3Z-P	GN 1...
47946	M37	FN 1L3Z-P	FN 1...
47947	M38	GN 1L3Z-K	GN 1...
47948	M38	FN 1L3Z-K	FN 1...
47949	M3A	MMBTH 24	MMBTH 24
47950	M3A	MA 199	MA 199
47951	M3B	MMBT 918	MMBT 918
47952	M3C	MA 740	MA 740
47953	M3D	MA 717WK	MA 717WK
47954	M3D	MA 745WK	MA 745WK
47955	M3D	MA 795WK	MA 795WK
47956	M3E	MA 745WA	MA 745WA
47957	M3E	MA 717WA	MA 717WA
47958	M3F	MA 721WK	MA 721WK
47959	M3H	MA 721WA	MA 721WA
47960	M3I	MA 743	MA 743
47961	M3J	MMBTH 69	MMBTH 69
47962	M3K	MA 999	MA 999
47963	M3M	MA 746	MA 746
47964	M3S	MA 57	MA 57
47965	M3T	MA 786	MA 786
47966	M3T	MA 792	MA 792
47967	M3U	MA 787	MA 787
47968	M3V	MA 788	MA 788
47969	M3W	MA 789	MA 789

47970	M3X	MA 790	MA 790
47971	M3Y	MA 786WA	MA 786WA
47972	M3Y	MA 792WA	MA 792WA
47973	M3Z	MA 792WK	MA 792WK
47974	M3Z	MA 786WK	MA 786WK
47975	M4	400V, 1A	BYG 10G...M, D 1F40...60, U 1GC44...JC44
47976	M4	2SA1611-M4	2SA1611
47977	M4	2SA1836-M4	2SA1836
47978	M4	KST 812M4	KST 812
47979	M4	MMBA 812M4	MMBA 812
47980	M4	2SA812-M4	2SA812
47981	M4	2SA1179-M4	2SA1179
47982	M4(p)	BSR 56	BSR 56
47983	M41	BSR 111	BSR 111
47984	M42	BSR 112	BSR 112
47985	M42	M 12, 400V	BA 157...159, BA 199/450, BAY 89
47986	M43	BSR 113	BSR 113
47987	M4A	MA 793	MA 793
47988	M4A	MMBV 109	MMBV 109
47989	M4A	MA 791	MA 791
47990	M4B	MA 796	MA 796
47991	M4B	MMBV 432	MMBV 432
47992	M4C	MA 558	MA 558
47993	M4C	MMBV 3102	MMBV 3102
47994	M4E	MMBV 105G	MMBV 105G
47995	M4E	MA 748	MA 748
47996	M4F	MA 129	MA 129
47997	M4F	MMBD 353	MMBD 353
47998	M4G	MMBV 2101	MMBV 2101
47999	M4L3052	1N5158	1N5158
48000	M4L3053	1N5159	1N5159
48001	M4L3054	1N5160	1N5160
48002	M4L3055	1N5779	1N5779
48003	M4L3056	1N5780	1N5780
48004	M5	600V, 1A	BYG 10J...M, D 1F60, U 1GJC44
48005	M5	KST 812M5	KST 812
48006	M5	MMBA 812M5	MMBA 812
48007	M5	2SA1179-M5	2SA1179
48008	M5	2SA812-M5	2SA812
48009	M5	2SA1611-M5	2SA1611
48010	M5	2SC5086-O	2SC5086
48011	M5	2SA1836-M5	2SA1836
48012	M5(p)	BSR 57	BSR 57
48013	M50	BF990AR	BF 990AR
48014	M52	BF992R	BF 992R

48015	M53	BF994SR	BF 994SR
48016	M5C	MMBD 7000	MMBD 7000
48017	M5G	MMBD 352	MMBD 352
48018	M6	800V, 1A	BYG 10K...M
48019	M6	BSS 66	BSS 66
48020	M6	KST 812M6	KST 812
48021	M6	2SA1179-M6	2SA1179
48022	M6	2SA1836-M6	2SA1836
48023	M6	2SC5086-Y	2SC5086
48024	M6	MMBA 812M6	MMBA 812
48025	M6	2SA812-M6	2SA812
48026	M6	2SA1611-M6	2SA1611
48027	M6(p)	BSR 58	BSR 58
48028	M61	GN 1L4Z-Q	GN 1...
48029	M61	FN 1L4Z-Q	FN 1...
48030	M62	PMBF 4391	PMBF 4391
48031	M62	GN 1L4Z-P	GN 1...
48032	M62	FN 1L4Z-P	FN 1...
48033	M62	M 12, 600V	BA 158...159, BA 199/550, BAY 89
48034	M63	FN 1L4Z-K	FN 1...
48035	M63	GN 1L4Z-K	GN 1...
48036	M63	PMBF 4392	PMBF 4392
48037	M64	PMBF 4393	PMBF 4393
48038	M64	FN 1F4Z-Q	FN 1...
48039	M64	GN 1F4Z-Q	GN 1...
48040	M65	GN 1F4Z-P	GN 1...
48041	M65	FN 1F4Z-P	FN 1...
48042	M65	BF 545A	BF 545A
48043	M66	BF 545B	BF 545B
48044	M66	FN 1F4Z-K	FN 1...
48045	M66	GN 1F4Z-K	GN 1...
48046	M67	FN 1A4Z-Q	FN 1...
48047	M67	BF 545C	BF 545C
48048	M67	GN 1A4Z-Q	GN 1...
48049	M68	FN 1A4Z-P	FN 1...
48050	M68	GN 1A4Z-P	GN 1...
48051	M69	FN 1A4Z-K	FN 1...
48052	M69	GN 1A4Z-K	GN 1...
48053	M6A	MMBF 4416	MMBF 4416
48054	M6F	MMBF 4860	MMBF 4860
48055	M6H	MMBD 354	MMBD 354
48056	M7	1000V, 1A	BYG 10M
48057	M7	MMBA 812M7	MMBA 812
48058	M7	KST 812M7	KST 812
48059	M7	BSS 67	BSS 67

48060	M7	2SA812-M7	2SA812
48061	M7	2SA1179-M7	2SA1179
48062	M7	2SA1836-M7	2SA1836
48063	M7	2SA1611-M7	2SA1611
48064	M7	2SC5091-O	2SC5091
48065	M74	BSS 83	BSS 83
48066	M8	BSS 66R	BSS 66R
48067	M8	2SC5091-Y	2SC5091
48068	M81	FN 1L3M	FN 1...
48069	M81	GN 1L3M	GN 1...
48070	M82	GN 1L3N	GN 1...
48071	M82	FN 1L3N	FN 1...
48072	M82	M 12, 800V	BA 159, BAY 90, BY 204/8, BY 208/800
48073	M83	BF997	BF 997
48074	M83	GN 1A3Q	GN 1...
48075	M83	FN 1A3Q	FN 1...
48076	M84	BF556A	BF 556
48077	M85	BF556B	BF 556
48078	M86	BF990A	BF 990A
48079	M86	BF556C	BF 556
48080	M87	BF990A	BF 990A
48081	M89	BF 989	BF 989
48082	M9	2SC5096-R	2SC5096
48083	M9	BSS 67R	BSS 67R
48084	M90	BF 990	BF 990
48085	M91	BF 991	BF 991
48086	M92	BF 992	BF 992
48087	M93	BF 994S	BF 994S
48088	M94	BF 994	BF 994
48089	M95	BF 996S	BF 996S
48090	M95	BF996SR	BF 996SR
48091	M96	BF 996	BF 996
48092	M97	BFR 101A	BFR 101A
48093	M98	BFR 101B	BFR 101B
48094	MA	μPA672T	æPA672T
48095	MA	2SC3011	2SC3011
48096	MA	MA 141A	MA 141A
48097	MA	2SC5096-O	2SC5096
48098	MA	2SC4392	2SC4392
48099	MA	BFS 17	BFS 17
48100	MA	MA 151A	MA 151A
48101	MA	2SC3301	2SC3301
48102	MA	2SC2876	2SC2876
48103	MA(p)	BF 989	BF 989
48104	MA100	60V, 0,5A, 0,2W	ACY 24, ASY 77, ASY 48

48105	MA1020..1390..	2,0...39V, 5%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5221...59
48106	MA104	500V, 1A, 100ns	-
48107	MA11	90V, 35mA	AA 117...118, AA 132...133
48108	MA110	40V, 0,1A, <3ns	-
48109	MA110	40V, 0,1A, <3ns	-
48110	MA111	MA 110, 80V	-
48111	MA111	MA 110, 80V	-
48112	MA112	15V, 0,2A, 0,175W, $\beta$ 30..70	AC 125...126, AC 151
48113	MA112	40V, 0,2A, <10ns	-
48114	MA112	40V, 0,2A, <10ns	-
48115	MA113	MA 112, $\beta$ 50..125	AC 125...126, AC 151
48116	MA113	MA 112, 80V	-
48117	MA113	MA 112, 80V	-
48118	MA114	MA 112, $\beta$ 100..250	AC 125...126, AC 151
48119	MA114	150V, 0,2A	-
48120	MA114	150V, 0,2A	-
48121	MA115	MA 112, $\beta$ 30..125	AC 125...126, AC 151
48122	MA115	200V, 0,2A	-
48123	MA115	200V, 0,2A	-
48124	MA116	MA 112, $\beta$ 50..250	AC 125...126, AC 151
48125	MA116	40V, 0,1A, <100ns	-
48126	MA116	40V, 0,1A, <100ns	-
48127	MA117	MA 112, $\beta$ 30..250	AC 125...126, AC 151
48128	MA121	3x SS, 80V, 0,1A, <3ns	-
48129	MA122	4x SS, 80V, 0,1A, <10ns	-
48130	MA123	4x SS, 80V, 0,1A, <3ns	-
48131	MA124	4x SS, 80V, 0,1A, <3ns	-
48132	MA125	4x S, 40V, 0,1A, 150ns	-
48133	MA126	4x SS, 80V, 0,1A, <10ns	-
48134	MA127	4x SS, 80V, 0,1A, <10ns	-
48135	MA128	4x SS, 80V, 0,1A, <3ns	-
48136	MA13	8V, 30mA	AAY 48
48137	K	MA 152..	-
48138	MA133	MA 153A	-
48139	MA143(A)	MA 153(A)	-
48140	MA147	MA 157A	-
48141	MA150	35V, 0,1A, <10ns	BA 200...203, BA 317,...318, 1N4148...49
48142	MA151A	40V, 0,1A, <10ns	-
48143	MA151K	40V, 0,1A, <3ns	BAR 74
48144	MA151WA	MA 151A	BAV 99, 1S2836, 1SS181
48145	MA151WK	MA 151K	BAV 74, 1S2838, 1SS184
48146	MA152A	MA 151A, 80V	-
48147	MA152K	MA 151K, 80V	BAR 74
48148	MA152WA	MA 151WA, 80V	BAW 56, 1S2836, 1SS181
48149	MA152WK	MA 151WK, 80V	BAV 99, 1S2838, 1SS184

48150	MA153	40V, 0,1A, 150ns	-
48151	MA153A	MA 153, 80V	-
48152	MA154WA	40V, 0,1A, <10ns	MC 911, 1SS236
48153	MA154WK	MA 154WA	MC 921, 1SS234
48154	MA155WA	MA 154WA, 80V	MC 911, 1SS236
48155	MA155WK	MA 154WA, 80V	MC 921, 1SS234
48156	MA156	40V, 0,1A	-
48157	MA157	40V, 0,1A, <3ns	BAV 99, HSM 123
48158	MA157A	MA 157, 80V	BAV 99
48159	MA158	250V, 0,1A	BAS 27
48160	MA159	40V, 0,1A, <3ns	BAW 100
48161	MA159A	MA 159, 80V	BAW 100
48162	MA160	80V, 0,1A, <3ns	-
48163	MA161	50V, 0,1A, <4ns	BAW 62, BAW 76, BAX 80, 1N4148...49
48164	MA162	MA 161, 75V	BAW 62, BAW 76, BAX 95, 1N4148...49
48165	MA162A	MA 162, 120V	1SS116
48166	MA164	MA 153	-
48167	MA165	35V, 0,1A, <10ns	BA 318, BAY 69, BAY 71, 1N4148...49
48168	MA166	50V, 0,1A, <10ns	BA 318, BAY 38, BAY 69, 1N4148...49
48169	MA167	MA 166, 75V	BA 201, BAW 46, BAY 61, 1N4148...49
48170	MA17	50V, 110mA	AAZ 17, AA 117...118, AA 132...134
48171	MA170	40V, 0,2A, <20ns	BAY 41...43, BAY 61, 1N4148...49
48172	MA1702	45V, 0,5A, 0,2W	ASY 77, 2N1189...1190
48173	MA1703	25V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48174	MA1704	25V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48175	MA1705	25V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48176	MA1706	15V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48177	MA1707	15V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48178	MA1708	15V, 0,5A, 0,2W	AC 128, AC 152...153, AC 188
48179	MA171	MA 170, 80V	BAW 62, BAW 76, BAY 61, 1N4148...49
48180	MA174	MA 158	-
48181	MA175WA	40V, 0,1A, <10ns	MA 154WA, MC 911, 1SS236
48182	MA175WK	MA 175WA	MA 154WK, MC 921, 1SS234
48183	MA176WA	MA 175WA, 80V	MA 155WA, MC 911, 1SS236
48184	MA176WK	MA 175WA, 80V	MA 155WK, MC 921, 1SS234
48185	MA177	40V, 0,1A	MC 931
48186	MA178	40V, 0,2A, <20ns	BAY 41...43, BAY 61, 1N4148...49
48187	MA179	MA 178, 80V	BAW 62, BAW 76, BAY 61, 1N4148...49
48188	MA18	20V, 180mA	AAZ 49, AAZ 15, AAZ 17
48189	MA180	40V, 0,2A, 200ns	BA 173, BAX 15...17, BAW 21
48190	MA182	250V, 0,2A	BA 157, BA 173, BAY 21, BAY 46
48191	MA185	250V, 0,2A	BA 157, BA 173, BAY 21, BAY 46
48192	MA188	250V, 0,2A, <60ns	BA 198, BAV 21, 1SS82...83
48193	MA190	35V, 0,1A, <200ns	BAV 17, BAX 90, BAX 94, 1N4148
48194	MA194	40V, 0,1A, <100ns	BAW 100



48195	MA195	35V, 0,1A, <200ns	BAV 17, BAX 90, BAX 94, 1N4148
48196	MA196	50V, 0,1A, <200ns	BAV 18, BAX 90, BAX 94, 1N4148
48197	MA198	MA 194	BAV 99
48198	MA199	250V, 0,1A, <60ns	BAS 21, 1SS250
48199	MA1U152A	MA 152A	MA 152A
48200	MA1U152K	MA 152K	MA 152K
48201	MA1U152WA	MA 152WA	MA 152WA
48202	MA1U152WK	MA 152WK	MA 152WK
48203	MA1U157A	MA 157A	MA 157A
48204	MA1Z047..510	4,7..51V, +-10%, 1W	BZG 03-..., HZF ..., PTZ..., RD...FM
48205	MA200	105V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48206	MA201	105V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48207	MA202	105V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48208	MA203	105V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48209	MA204	90V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48210	MA2043	105V, 0,2A, 0,2W	ACY 39, 2N2042...2043
48211	MA204WA,WK	MA 175..	MA 175...
48212	MA204WA,WK	MA 175..	MA 175...
48213	MA205	75V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48214	B)	5,1...56V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N4733...58
48215	MA205WA,WK	MA 176..	MA 176...
48216	MA205WA,WK	MA 176..	MA 176...
48217	MA206	MA 177	MA 177
48218	MA206	60V, 0,2A, 0,15W	ACY 24, ASY 48, ASY 77, 2N2042...2043
48219	MA207	MA 177, 80V	-
48220	MA21	15V, 20mA, <12ns	AAY 21
48221	MA221	MA 165, SMD	-
48222	MA222	MA 166, SMD	-
48223	MA223	MA 167, SMD	-
48224	MA240	8V, 10mA, 0,0W, >25MHz	-
48225	MA26	0,56..0,61V(1,5mA)	BA 216, BA 314, BZ 102/0V7
48226	MA26T,TO(-A,-B)	1,78..2,03V(3mA)	BZ 102/2V1
48227	B)	1,19..1,35V(3mA)	BZ 102/1V4, ZTE 1,5
48228	MA27(-A,-B,-C)	0,05A, 0,56..0,67V(1,5mA)	BA 314...315, BZ 102/0V7, BZX 55/C0V8
48229	MA27Q(-A,-B)	0,05A, 2,2..2,54V(3mA)	-
48230	MA27T(-A,-B)	0,07A, 1,76..2,04V(3mA)	BZ 102/2V1, BZX 75/C2V1, ZTE 2
48231	MA27W(-A,-B)	0,1A, 1,18..1,36V(3mA)	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
48232	MA28(-A,-B)	MA 27(-A,-B), SMD	BAS 17, BZX 84/C0V8
48233	MA286	10V, 0,2A, 0,175W, $\beta$ 14..40	AC 125...126, AC 151
48234	MA287	MA 286, $\beta$ 30..250	AC 125...126, AC 151
48235	MA288	MA 286, $\beta$ >180	AC 125...126, AC 151
48236	MA28T(-A,-B)	MA 27T..., SMD	-
48237	MA28W(-A,-B)	MA 27W..., SMD	-
48238	MA29...	MA 27..	MA 27...
48239	MA291	250V, 0,2A	-

48240	MA291	250V, 0,2A	-
48241	MA292	MA 291, 400V	-
48242	MA292	MA 291, 400V	-
48243	MA2S111	80V, 0,1A, <3ns	1SS352, 1SS353
48244	MA2S111	80V, 0,1A, <3ns	1SS352, 1SS353
48245	MA2S728	MA 728	MA 728
48246	MA2S784	MA 784	MA 784
48247	MA2Z200...330	200..330V, +-10%, 1W	-
48248	MA30(-A,-B)	MA 27(-A,-B), SMD	-
48249	MA30(-A,-B)	MA 27(-A,-B), SMD	-
48250	MA30(S)	3kV, 0,01A	HS 3
48251	MA3020...3360	2,0...36V, 5%	BZX84/...
48252	MA3020L...3360L	MA 3020..3360	-
48253	MA30W(-A,-B)	MA 27W(-A,-B), SMD	-
48254	MA30W(-A,-B)	MA 27W(-A,-B), SMD	-
48255	MA311	BA 102	BA 102
48256	MA320		BB 105A,B, BB 205A,B, BB 405A,B
48257	MA321		BB 515, BB 721, BB 723, 1SV202
48258	MA322		BB 105G, BB 205G, BB 405G, BB 505G
48259	MA322-FM		BB 110, BB 203, MV 310, 1SV68, 1SV84
48260	MA323		BB 105G, BB 205G, BB 405G, BB 505G
48261	MA324		BB 105A,B, BB 205A,B, BB 405A,B
48262	MA325		BB 105A,B, BB 205A,B, BB 405A,B
48263	MA326		BB 105A,B, BB 205A,B, BB 405A,B
48264	MA327		BB 515, BB 721, BB 723, 1SV202
48265	MA328		BB 105A,B, BB 205A,B, BB 405A,B
48266	MA329		BB 419, BB 619...620, 1SV200
48267	MA330		-
48268	MA331		-
48269	MA331		-
48270	MA332		-
48271	MA332		MA 367
48272	MA332		MA 367
48273	MA333		-
48274	MA334		BB 515, BB 721, BB 723, 1SV202
48275	MA335		BB 419, BB 619...620, 1SV200
48276	MA337		-
48277	MA338		-
48278	MA339		BB 515, BB 721, BB 723, 1SV202
48279	MA340		-
48280	MA341		-
48281	MA342-B,-M	MA 341	-
48282	MA345	10..16pf(10V)	FC 54M, SD 115
48283	MA346	10..16pf(10V)	FC 54M, SD 115
48284	MA348	MA 345, SMD,	-

48285	MA353		-
48286	MA355	BA 201	BA 201
48287	MA355		MA 357, MA 366, 1SV238, 1SV269
48288	MA355		MA 357, MA 366, 1SV238, 1SV269
48289	MA357		MA 355, MA 366, 1SV238, 1SV269
48290	MA357		MA 355, MA 366, 1SV238, 1SV269
48291	MA360	MA 321	BB 535, 1SV214, 1SV223
48292	MA360	MA 321	BB 535, 1SV214, 1SV223
48293	MA361	MA 329	BB 439, MA 364
48294	MA361	MA 329	BB 439, MA 364
48295	MA363	MA 334	BB 535, 1SV214
48296	MA363	MA 334	BB 535, 1SV214
48297	MA364	MA 335	BB 439, MA 361
48298	MA364	MA 335	BB 439, MA 361
48299	MA365	MA 337	BB 639, MA 374, 1SV231
48300	MA365	MA 337	BB 639, MA 374, 1SV231
48301	MA366	MA 338	MA 355, MA 357, 1SV238, 1SV269
48302	MA366	MA 338	MA 355, MA 357, 1SV238, 1SV269
48303	MA367	MA 341	MA 311, MA 332
48304	MA367	MA 341	MA 311, MA 332
48305	MA368		MA 373, 1SV245
48306	MA368		MA 373, 1SV245
48307	MA370	MA 368	-
48308	MA371	MA 353	MA 355, MA 365...366, MA 374, 1SV217
48309	MA371	MA 353	MA 355, MA 365...366, MA 374, 1SV217
48310	MA372	MA 339	BB 535, MA 360, 1SV214, 1SV223
48311	MA372	MA 339	BB 535, MA 360, 1SV214, 1SV223
48312	MA373		MA 368, 1SV245
48313	MA373		MA 368, 1SV245
48314	MA374		BB 639, MA 365, 1SV231
48315	MA374		BB 639, MA 365, 1SV231
48316	MA374[Old]		BB 104, BB 204, BB 304, 1SV55, 1SV109
48317	MA376		-
48318	MA376		-
48319	MA377		-
48320	MA377		-
48321	MA381		BB 107, BB 212, BB 312
48322	MA386		BB 130, BB 509, MV 1401, MV 1403...1405
48323	MA391	10V, 3,7<5pF(1V)	-
48324	MA391	10V, 3,7<5pF(1V)	-
48325	MA392	10V, 3,5..6,5pF(1V)	-
48326	MA392	10V, 3,5..6,5pF(1V)	-
48327	MA393	10V, 8..13pF(1V)	-
48328	MA393	10V, 8..13pF(1V)	-
48329	MA3Z200..240	200..240V, +-10%, 1W	-

48330	MA4020...4390	2,0...39V, 5%, 0,37W	BZX55/..., BZX83/..., ZPD..., 1N5221...59
48331	MA4020N..4390N	MA 4020..4039, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5221...59
48332	MA47	25V, 50mA	AA 132...134, 1N34, 1N54, 1N60
48333	MA48	30V, 50mA	AA 114, AA 116, 1N34, 1N54, 1N60
48334	MA49	20V, 50mA	AA 114, AA 116, 1N34, 1N54, 1N60
48335	MA4S159	MA 159	-
48336	MA4S713	MA 713	-
48337	MA5047...5240	4,7...24V, 5%	-
48338	MA51(A)	15V, 35mA	AA 112, AA 114, AA 116, 1N34, 1N54, 1N60
48339	MA522	Tunnel-Di (2x JFET)	-
48340	MA53		BA 182, BA 243, BA 283, BA 483...484
48341	MA550	30V, 0,1A	-
48342	MA551	MA 553, SMD	1SV128, 1SV233
48343	MA553	45V, 0,1A	-
48344	MA555	MA 553, SMD,	-
48345	MA557	MA 553, SMD,	-
48346	MA558	MA 553, SMD,	-
48347	MA56		BA 182, BA 243, BA 283, BA 483...484
48348	MA57		BAT 18, 1SS153
48349	MA6	MMBD 2838	MMBD 2838
48350	MA60	Ub28..36V, Ib<0,1mA, Itsm2A	1N5761, BR 100, D 3202 Y, DO 201 YR
48351	MA61	MA61	1N5761, BR 100, D 3202 Y, DO 201 YR
48352	MA615	9kV, 5mA, <350ns	BY 707...709, BY 717...719
48353	MA619	MA 615, 12kV	BY 509...510, BY 709, BY 719
48354	MA62	MA60	1N5761, BR 100, D 3202 Y, DO 201 YR
48355	MA622	MA 615, 13kV	BY 609...610, BY 709, BY 719
48356	MA625	MA 615, 15kV	BY 609...610, BY 619...620
48357	MA630	MA 615, 18kV	-
48358	MA64	Ub28..40V, Ib<0,1mA, Itsm2A	1N5761, BR 100, D 3202 Y, DO 201 YR
48359	MA643	200V, 1A, <50ns	-
48360	MA649	200V, 5A, <100ns	BYQ 28F/200
48361	MA650	200V, 10A, <100ns	BYQ 28F/200
48362	MA651	200V, 20A, <100ns	BYV 72F/200, BYV 74F/300
48363	MA652	200V, 20A, <100ns	-
48364	MA653	300V, 5A, <100ns	-
48365	MA654	300V, 10A, <100ns	-
48366	MA655	300V, 20A, <100ns	BYV 72F/300
48367	MA661	200V, 10A, <100ns	BYV 72F/200
48368	MA669	200V, 5A, 100ns	-
48369	MA670	200V, 10A, 100ns	-
48370	MA671	200V, 20A, 100ns	-
48371	MA673	MA 669, 300V	-
48372	MA674	MA 670, 300V	-
48373	MA675	MA 671, 300V	-
48374	MA689	200V, 2,5A, <100ns	BYW 29/200F

48375	MA690	200V, 5A, <100ns	BYW 29/200F
48376	MA691	200V, 10A, <100ns	BYV 72F200
48377	MA693	400V, 5A, <100ns	-
48378	MA694	400V, 10A, <100ns	-
48379	MA695	400V, 20A, <100ns	BYV 74F/400
48380	MA6D49	MA 649	MA 649
48381	MA6D50	MA 650	MA 650
48382	MA6D52	MA 652	MA 652
48383	MA6D53	MA 653	MA 653
48384	MA6D54	MA 654	MA 654
48385	MA6D89	MA 689, <40ns	MA 689
48386	MA6D90	MA 690, <45ns	MA 690
48387	MA6D93	MA 693	MA 693
48388	MA6D94	MA 694	MA 694
48389	MA6S121	MA 121	-
48390	MA6S718	MA 718	-
48391	MA70		-
48392	MA700	15V, 30mA, 1ns	BAT 45, HSS 101, 1S1992, 1SS108
48393	MA700A	MA 700, 30V	BAT 81, HSS 101, 1S1992, 1SS108
48394	MA701	20V, 1A, 14ns	-
48395	MA701A	MA 701, 40V	-
48396	MA704	15V, 30mA, 1ns	-
48397	MA704A	MA 704, 30V	-
48398	MA704WA	MA 704	-
48399	MA704WK	MA 704	-
48400	MA7051...7360	5,1...36V, 5%, 0,2W	BZX55/..., BZX79/..., ZPD..., 1N5221...58
48401	MA707	5V	-
48402	MA713	MA 704A	-
48403	MA714	MA 704A	-
48404	MA715	MA 704A	-
48405	MA715[Old]	MA 615, <250ns	-
48406	MA716	MA 704A	-
48407	MA717	MA 704A	-
48408	MA717WA	MA 704A	-
48409	MA717WK	MA 704A	-
48410	MA719	40V, 0,5A, 5ns	-
48411	MA72		BA 582, 1SS241
48412	MA720	MA 719, SMD	-
48413	MA720[Old]	MA 622, <250ns	-
48414	MA721	MA 723, SMD	-
48415	MA721WA	MA 723, SMD,	-
48416	MA721WK	MA 723, SMD,	-
48417	MA723	30V, 0,2A, 3ns	-
48418	MA724	MA 723, SMD,	-
48419	MA725	MA 625, <250ns	-

48420	MA726	MA 723, SMD,	-
48421	MA727	MA 723, SMD, 50V	-
48422	MA728	MA 704A, SMD	-
48423	MA728	MA 704A, SMD	-
48424	MA729	MA 723, SMD	-
48425	MA729	MA 723, SMD	-
48426	MA73		BA 582, 1SS241
48427	MA730	MA 707	1SS295, 1SS366
48428	MA730[Old]	MA 630, <250ns	-
48429	MA732	MA 704A	-
48430	MA732	MA 704A	-
48431	MA733	MA 707	-
48432	MA733	MA 707	-
48433	MA735	30V, 1A, <30ns	-
48434	MA736	MA 735, 40V	-
48435	MA737	30V, 1.5A, <50ns	-
48436	MA738	MA 737, 40V	-
48437	MA739	90V, 0.7A, <100ns	-
48438	MA73WA	MA 73	-
48439	MA73WK	MA 73	-
48440	MA740	MA 723, SMD,	-
48441	MA741	MA 704A	-
48442	MA741WA	MA 704A	-
48443	MA741WP	MA 704A	-
48444	MA742	MA 704A	-
48445	MA743	MA 704A + MA 723	-
48446	MA744	MA 723, SMD	-
48447	MA745	MA 704A	-
48448	MA745WA	MA 704A	-
48449	MA745WK	MA 704A	-
48450	MA746	MA 723, SMD,	-
48451	MA748	MA 719, SMD, 20V	-
48452	MA749(A)	40(A45)V, 5A	BYV 118F/...
48453	MA750(A)	40(A45)V, 10A	-
48454	MA751(A)	40(A45)V, 20A	-
48455	MA752(A)	40(A45)V, 20A	BYV 34F/...
48456	MA753(-DS)(A)	40(A45)V, 5A	-
48457	MA755	60V, 5A	HRW 34F
48458	MA756	60V, 10A	MBR 2060
48459	MA760	90V, 5A	HRW 34F
48460	MA761	90V, 10A	HRW 36F, BYS 24-90, MBR 2090
48461	MA762	90V, 20A	BYS 28-90
48462	MA763	MA 723, SMD	-
48463	MA768	150V, 5A	-
48464	MA769	150V, 10A	-



48465	MA77	MA 73	BA 592, 1SS314, 1SS356
48466	MA77	MA 73	BA 592, 1SS314, 1SS356
48467	MA774	30V, 0,1A, 1,5ns	-
48468	MA775	MA 774, 50V	-
48469	MA776	40V, 30mA, 2ns	-
48470	MA777	40V, 0,2A, 3ns	-
48471	MA780	MA 775, SMD	-
48472	MA781	MA 704A	-
48473	MA782	MA 777, SMD	-
48474	MA784	30V, 0,1A, 2ns	-
48475	MA784	30V, 0,1A, 2ns	-
48476	MA785	MA 784, 50V, 3ns	-
48477	MA785	MA 784, 50V, 3ns	-
48478	MA786	MA 784	-
48479	MA786WA	MA 784	-
48480	MA786WK	MA 784	-
48481	MA787	MA 784, 50V	-
48482	MA788	60V, 0,2A, 3ns	-
48483	MA789	60V, 0,5A, 4,5ns	-
48484	MA79		BA 582, 1SS241
48485	MA79		BA 582, 1SS241
48486	MA790	10V, 15mA, <0,85pF	-
48487	MA791	MA 784	-
48488	MA792	MA 784	-
48489	MA792WA	MA 784	-
48490	MA792WK	MA 784	-
48491	MA793	MA 784	-
48492	MA795	MA 704A	-
48493	MA795WK	MA 704A	-
48494	MA796	MA 784, , 50V	-
48495	MA7D49(A)	MA 749	MA 749
48496	MA7D50(A)	MA 750	MA 750
48497	MA7D52(A)	MA 752	MA 752
48498	MA7D55(A)	MA 755	MA 755
48499	MA7D56(A)	MA 756	MA 756
48500	MA7D68(A)	MA 768	MA 768
48501	MA7D69(A)	MA 769	MA 769
48502	MA8024...8390	2,4...39V, 5%	DTZ ..., HZU ...
48503	MA8024...8390	2,4...39V, 5%	DTZ ..., HZU ...
48504	MA80WA	MA 73	-
48505	MA80WK	MA 73	-
48506	MA81		BA 582, 1SS241
48507	MA81		BA 582, 1SS241
48508	MA840(A,B,M)		BB 117, BB 417, 1SV89
48509	MA856		BA 283, BA 483...484, 1SS150, 2SS152

48510	MA858		BA 283, BA 483...484, 1SS150, 2SS152
48511	MA859		BA 283, BA 483...484, 1SS150, 2SS152
48512	MA860	MA 859, SMD	BA 683
48513	MA862	MA 859, SMD,	-
48514	MA881	60V, 0,5A, 0,2W, B30..70	ASY 77
48515	MA882	MA 881, B50..120	ASY 77
48516	MA883	MA 881, B100..225	ASY 77
48517	MA884	MA 881, B190..400	ASY 77
48518	MA885	50V, 0,5A, 0,2W, B15..40	ASY 77
48519	MA886	MA 885, B30..70	ASY 77
48520	MA887	MA 885, B50..120	ASY 77
48521	MA888	MA 885, B100..225	ASY 77
48522	MA889	MA 885, B190..400	ASY 77
48523	MA890	40V, 0,2A, 0,175W, B30..70	AC 125...126, AC 151, ASY 48
48524	MA891	MA 891, B50..120	AC 125...126, AC 151, ASY 48
48525	MA892	MA 891, B100..225	AC 125...126, AC 151, ASY 48
48526	MA893	MA 891, B190..400	AC 125...126, AC 151, ASY 48
48527	MA894	30V, 0,2A, 0,15W, B>20	AC 125...126, AC 151, ASY 48
48528	MA895	MA 894, B>40	AC 125...126, AC 151, ASY 48
48529	MA896	MA 894, B>90	AC 125...126, AC 151, ASY 48
48530	MA897	MA 894, B>180	AC 125...126, AC 151, ASY 48
48531	MA898	25V, 0,1A, B>20	AC 125...126, AC 151
48532	MA899	MA 898, B>40	AC 125...126, AC 151
48533	MA90	15V, 50mA	AA 112, AA 114, AA 116, 1N34, 1N54, 1N60
48534	MA900	MA 898, B>90	AC 125...126, AC 151
48535	MA900	10mA	-
48536	MA901	MA 898, B>20	AC 125...126, AC 151
48537	MA902	MA 898, 15V, B>15	AC 125...126, AC 151
48538	MA903	MA 898, 15V, B>20	AC 125...126, AC 151
48539	MA904	MA 898, 15V, B>180	AC 125...126, AC 151
48540	MA909	75V, 0,2A, 0,15W	ACY 39, 2N2042...2043
48541	MA910	MA 909, 90V	ACY 39, 2N2042...2043
48542	MA999	MA 704A + MA 151K	-
48543	MAC10-1	25V, 10A, Igt/Ih<75/<50mA	BTA 22B, TAG 250-100, TAG 251-100
48544	MAC10-2	MAC 10-1, 50V	BTA 22B, TAG 250-100, TAG 251-100
48545	MAC10-3	MAC 10-1, 100V	BTA 22B, TAG 250-100, TAG 251-100
48546	MAC10-4	MAC 10-1, 200V	BTA 22B, TAG 250-200, TAG 251-200
48547	MAC10-5	MAC 10-1, 300V	BTA 22C, TAG 250-300, TAG 251-300
48548	MAC10-6	MAC 10-1, 400V	BTA 22D, TAG 250-400, TAG 251-400
48549	MAC10-7	MAC 10-1, 500V	BTA 22E, TAG 250-500, TAG 251-500
48550	MAC10-8	MAC 10-1, 600V	BTA 22M, TAG 250-600, TAG 251-600
48551	MAC11-1	25V, 10A, Igt<50mA	BTA 22B, TAG 250-100, TAG 251-100
48552	MAC11-2	MAC 11-1, 50V	BTA 22B, TAG 250-100, TAG 251-100
48553	MAC11-3	MAC 11-1, 100V	BTA 22B, TAG 250-100, TAG 251-100
48554	MAC11-4	MAC 11-1, 200V	BTA 22B, TAG 250-200, TAG 251-200

48555	MAC11-5	MAC 11-1, 300V	BTA 22C, TAG 250-300, TAG 251-300
48556	MAC11-6	MAC 11-1, 400V	BTA 22D, TAG 250-400, TAG 251-400
48557	MAC11-7	MAC 11-1, 500V	BTA 22E, TAG 250-500, TAG 251-500
48558	MAC11-8	MAC 11-1, 600V	BTA 22M, TAG 250-600, TAG 251-600
48559	MAC15-10	MAC 15-4, 800V	TIC 246N, TXE 10L80, BT 139/...
48560	MAC15-4	200V, 15A, Igt/Ih<50/<40mA	TIC 246B, TXE 10L20, BT 139/...
48561	MAC15-6	MAC 15-4, 400V	TIC 246D, TXE 10L40, BT 139/...
48562	MAC15-8	MAC 15-4, 600V	TIC 246M, TXE 10L60, BT 139/...
48563	MAC15A-4...10	Igt/Ih<75/<40mA	TAG 280-..., TAG 281-., BT 139/...
48564	MAC15A..FP	MAC 15A..	-
48565	MAC20-10	MAC 20-4, 800V	MAC 25(A)-10
48566	MAC20-4	200V, 15A, Igt/Ih<50/<40mA	MAC 25(A)-4
48567	MAC20-5	MAC 20-4, 300V	MAC 25(A)-5
48568	MAC20-6	MAC 20-4, 400V	MAC 25(A)-6
48569	MAC20-7	MAC 20-4, 500V	MAC 25(A)-7
48570	MAC20-8	MAC 20-4, 600V	MAC 25(A)-8
48571	MAC20-9	MAC 20-4, 700V	MAC 25(A)-9
48572	MAC20A-4..-10	Igt/Ih<75/<40mA	MAC 25A-...
48573	MAC216-4	200V, 6A, Igt<50mA	SC 141B, T 2801B, BTA 20C, TXC 10K40M
48574	MAC216-6	MAC 216-4, 400V	SC 141D, T 2801D, BTA 20D, TXC 10K40M
48575	MAC216-7	MAC 216-4, 500V	SC 141E, T 2801E, BTA 20E, TXC 10K50M
48576	MAC216-8	MAC 216-4, 600V	SC 141M, T 2801M, BTA 20M, TXC 10K60M
48577	MAC216A-4..-8	MAC 216-4..8, Igt<70mA	T 2800...,T 2850...,TAG 224-...,BT 137/...
48578	MAC220(A)-2	2N6342(A), 50V	2N6342(A)
48579	MAC220(A)-3	2N6342(A), 100V	2N6342(A)
48580	MAC220(A)-5	2N6342(A), 300V	2N6343(A)
48581	MAC220(A)-7	2N6342(A), 500V	2N6344(A)
48582	MAC220(A)-9	2N6342(A), 700V	2N6345(A)
48583	MAC221(A)-2	2N6346(A), 50V	2N6346(A)
48584	MAC221(A)-3	2N6346(A), 100V	2N6346(A)
48585	MAC221(A)-5	2N6346(A), 300V	2N6347(A)
48586	MAC221(A)-7	2N6346(A), 500V	2N6348(A)
48587	MAC221(A)-9	2N6346(A), 700V	2N6349(A)
48588	MAC222-1	25V, 8A, Igt/Ih<50/<40mA	TIC 226A, TXD 10K40, TW9N400, 2N6342
48589	MAC222-10	MAC 222-1, 800V	TIC 226N, TXD 10K80, TW9N800, 2N6345
48590	MAC222-2	MAC 222-1, 50V	TIC 226A, TXD 10K40, TW9N400, 2N6342
48591	MAC222-3	MAC 222-1, 100V	TIC 226A, TXD 10K40, TW9N400, 2N6342
48592	MAC222-4	MAC 222-1, 200V	TIC 226B, TXD 10K40, TW9N400, 2N6342
48593	MAC222-5	MAC 222-1, 300V	TIC 226C, TXD 10K40, TW9N400, 2N6343
48594	MAC222-6	MAC 222-1, 400V	TIC 226D, TXD 10K40, TW9N400, 2N6343
48595	MAC222-7	MAC 222-1, 500V	TIC 226E, TXD 10K50, TW9N500, 2N6344
48596	MAC222-8	MAC 222-1, 600V	TIC 226M, TXD 10K60, TW9N600, 2N6344
48597	MAC222-9	MAC 222-1, 700V	TIC 226S, TXD 10K70, TW9N700, 2N6345
48598	MAC222A-1..-10	Igt/Ih<75/<40mA	TAG 224-..., BT 137/..., TXD10H...
48599	MAC223-10	MAC 223-3, 800V	TXE 10L80

48600	MAC223-3	100V, 25A, Igt/Ih<50/<50mA	TXE 10L20
48601	MAC223-4	MAC 223-3, 200V	TXE 10L20
48602	MAC223-5	MAC 223-3, 300V	TXE 10L40
48603	MAC223-6	MAC 223-3, 400V	TXE 10L40
48604	MAC223-7	MAC 223-3, 500V	TXE 10L60
48605	MAC223-8	MAC 223-3, 600V	TXE 10L60
48606	MAC223-9	MAC 223-3, 700V	TXE 10L80
48607	MAC223A-3..-10	Igt/Ih<75/<50mA	-
48608	MAC223A..FP	MAC 223A..	-
48609	MAC228-10	MAC 228-2, 800V	TIC 225N, TAG 227-800
48610	MAC228-2	50V, 8A, Igt/Ih<5/<15mA	TIC 225A, TAG 227-100
48611	MAC228-3	MAC 228-2, 100V	TIC 225A, TAG 227-100
48612	MAC228-4	MAC 228-2, 200V	TIC 225B, TAG 227-200
48613	MAC228-5	MAC 228-2, 300V	TIC 225C, TAG 227-300
48614	MAC228-6	MAC 228-2, 400V	TIC 225D, TAG 227-400
48615	MAC228-7	MAC 228-2, 500V	TIC 225E, TAG 227-500
48616	MAC228-8	MAC 228-2, 600V	TIC 225M, TAG 227-600
48617	MAC228-9	MAC 228-2, 700V	TIC 225S, TAG 227-700
48618	MAC228A-2..-10	Igt/Ih<10/<15mA	TAG 226-...
48619	MAC25-4..-10	Igt/Ih<70/<75mA	MAC 50-..., TAG 725
48620	MAC25A-4..-10	Igt/Ih<100/<70mA	MAC 50A-..., TAG 725-..., TAG 726-...
48621	MAC3030-15	250V, 15A, Igt/Ih<40/<40mA	T 6006C
48622	MAC3030-25	250V, 25A, Igt/Ih<40/<40mA	TXE 10L40, MAC 223-5, MAC 223A-5
48623	MAC3030-4	250V, 4A, Igt/Ih<30/<40mA	TAG 96C, 2N6072...6075
48624	MAC3030-40	250V, 40A, Igt/Ih<40/<50mA	T 6414D, T 6410D, 2N5445...5446
48625	MAC3030-8	250V, 8A, Igt/Ih<40/<40mA	BTA 21C, BT 158/400, T 2806C, T 2856D
48626	MAC35-1..-10	Igt/Ih<100/<75mA	-
48627	MAC36-1..-10	Igt/Ih<100/<75mA	-
48628	MAC37-1..-10	Igt/Ih<75/<75mA	-
48629	MAC38-1..-10	Igt/Ih<75/<75mA	-
48630	MAC40688	2N5441	2N5441
48631	MAC40689	2N5442	2N5442
48632	MAC40690	2N5443	2N5443
48633	MAC40795	2N5567, 600V	T 4101M, T 6401M
48634	MAC40796	2N5569, 600V	T 4111M
48635	MAC40797	2N5571, 600V	2N6159, T 6400M, 2N5443
48636	MAC40798	2N5573, 600V	T 6411M, 2N6162, T 6410M, 2N5446
48637	MAC40799	2N6145	2N6145
48638	MAC40800	2N6146	2N6146
48639	MAC40801	T 4100 M	T 4100 M
48640	MAC4688	200V, 40A, Igt/Ih<70/<70mA	T 6420B
48641	MAC4689	400V, 40A, Igt/Ih<70/<70mA	T 6420D
48642	MAC4690	600V, 40A, Igt/Ih<70/<70mA	T 6420M
48643	MAC50-4..-10	Igt/Ih<70/<75mA	TAG 740-..., TAG 741-...
48644	MAC50A-4..-10	Igt/Ih<100/<75mA	TAG 740..., TAG 741-...

48645	MAC515-10	MAC 515-4, 800V	MAC 525(A)-10
48646	MAC515-4	200V, 15A, Igt/Ih<50/<40mA	MAC 525(A)-4
48647	MAC515-5	MAC 515-4, 300V	MAC 525(A)-5
48648	MAC515-6	MAC 515-4, 400V	MAC 525(A)-6
48649	MAC515-7	MAC 515-4, 500V	MAC 525(A)-7
48650	MAC515-8	MAC 515-4, 600V	MAC 525(A)-8
48651	MAC515-9	MAC 515-4, 700V	MAC 525(A)-9
48652	MAC515A-4..-10	Igt/Ih<75/<40mA	MAC 525A-..., TAG 725-..., TAG 726-...
48653	MAC525-4..-10	MAC 515-4..10, 25A	TAG 725-..., TAG 726-...
48654	MAC525A-4...10	MAC 515A-4..10, 25A	TAG 725-..., TAG 726-..., TAG 740-...
48655	MAC5441...5446	2N5441..5446	2N5441...5446
48656	MAC77-1	25V, 4A, Igt/Ih<30/<30mA	TAG231-200, TAG220-100, BT158/400
48657	MAC77-1	25V, 4A, Igt/Ih<30/<30mA	TAG231-200, TAG220-100, BT158/400
48658	MAC77-2	MAC 77-1, 50V	TAG231-200, TAG220-100, BT158/400
48659	MAC77-2	MAC 77-1, 50V	TAG231-200, TAG220-100, BT158/400
48660	MAC77-3	MAC 77-1, 100V	TAG231-200, TAG220-100, BT158/400
48661	MAC77-3	MAC 77-1, 100V	TAG231-200, TAG220-100, BT158/400
48662	MAC77-4	MAC 77-1, 200V	TAG231-200, TAG220-200, BT158/400
48663	MAC77-4	MAC 77-1, 200V	TAG231-200, TAG220-200, BT158/400
48664	MAC77-5	MAC 77-1, 300V	TAG231-400, TAG220-300, BT158/400
48665	MAC77-5	MAC 77-1, 300V	TAG231-400, TAG220-300, BT158/400
48666	MAC77-6	MAC 77-1, 400V	TAG231-400, TAG220-400, BT158/400
48667	MAC77-6	MAC 77-1, 400V	TAG231-400, TAG220-400, BT158/400
48668	MAC77-7	MAC 77-1, 500V	TAG231-600, TAG220-500, BT158/600
48669	MAC77-7	MAC 77-1, 500V	TAG231-600, TAG220-500, BT158/600
48670	MAC77-8	MAC 77-1, 600V	TAG231-600, TAG220-600, BT158/600
48671	MAC77-8	MAC 77-1, 600V	TAG231-600, TAG220-600, BT158/600
48672	MAC800-02...80	25..800V, 4A, Igt/Ih<30/<30mA	-
48673	MAC800A-02...80	MAC 800-..., Igt/Ih<10/<15mA	-
48674	MAC800B-02...80	MAC 800-..., Igt/Ih<3/<15mA	-
48675	MAC91-1	25V, 0,6A, Igt/Ih<10/<10mA	MAC 94-1, MAC 94A-1, Z 0106B
48676	MAC91-2	MAC 99-1, 50V	MAC 94-2, MAC 94A-2, Z 0106B
48677	MAC91-3	MAC 99-1, 100V	MAC 94-3, MAC 94A-3, Z 0106B
48678	MAC91-4	MAC 99-1, 200V	MAC 94-4, MAC 94A-4, Z 0106B
48679	MAC91-5	MAC 99-1, 300V	MAC 94-5, MAC 94A-5, Z 0106D
48680	MAC91-6	MAC 99-1, 400V	MAC 94-6, MAC 94A-6, Z 0106D
48681	MAC91-7	MAC 99-1, 500V	MAC 94-7, MAC 94A-7, Z 0106M
48682	MAC91-8	MAC 99-1, 600V	MAC 94-8, MAC 94A-8, Z 0106M
48683	MAC91A-1..-8	MAC 91-1..8, Igt/Ih<10/<10mA	MAC 94A-..., Z 0106...
48684	MAC92-1..-8	MAC 91-1..8, Igt/Ih<5/<10mA	MAC 95-..., Z 0104...
48685	MAC92A-1..-8	MAC 91-1..8, Igt/Ih<5/<10mA	MAC 95A-...
48686	MAC93-1..-8	MAC 91-1..8, Igt/Ih<3/<10mA	MAC 96-..., Z 0101...
48687	MAC93A-1..-8	MAC 91-1..8, Igt/Ih<3/<10mA	MAC 96A-...
48688	MAC94-1..-8	MAC 91-1..8, 0,8A	Z 0106...
48689	MAC94A-1..-8	MAC 91A-1..8, 0,8A	Z 0106...

48690	MAC95-1..-8	MAC 92-1..8, 0,8A	Z 0104...
48691	MAC95A-1..-8	MAC 92A-1..8, 0,8A	Z 0405..., T 2327..., T 2301P...,TXC18D...
48692	MAC96-1..-8	MAC 93-1..8, 0,8A	Z 0101...
48693	MAC96A-1..-8	MAC 93A-1..8, 0,8A	T 2320..., Z 0402..., T 2300P...
48694	MAO	2SC5065-O	2SC5065
48695	MAO	2SC5064-O	2SC5064
48696	MAX	KTD 1304	KTD 1304
48697	MAY	2SC5065-Y	2SC5065
48698	MAY	2SC5064-Y	2SC5064
48699	MB	BF995	BF 995
48700	MB	MA 142A	MA 142A
48701	MB	2SC5108-O	2SC5108
48702	MB	MA 132A	MA 132A
48703	MB	2SA1052-B	2SA1052
48704	MB	2SC3098	2SC3098
48705	MB	MA 152A	MA 152A
48706	MB-1(D)	1000V, 1A, 1 $\mu$ s	BY 127, BY 133, BY 227, 1N4007, 1N5622
48707	MB-1F	MB-1(D), 1500V	BY 231/1500, DM 513, EM 516, GP 10W
48708	MBD101	7V	BA 480...481, BAR 19, BAT 29, 1S1925
48709	MBD102	MBD 101	BA 480...481, BAR 19, BAT 29, 1S1925
48710	MBD201	20V	BAR 10, BAT 45, 1N5712
48711	MBD301	MBD 201, 30V	HSS 101, 1S1992, 1SS108
48712	MBD501	50V	BAT 82...83, HSS100, 1N6263
48713	MBD502	MBD 501	BAT 82...83, HSS100, 1N6263
48714	MBD701	MBD 501, 70V	BAR 28, HSS102, 1N5711
48715	MBD702	MBD 501, 70V	BAR 28, HSS102, 1N5711
48716	MBR030	30V, 0,5A	BYV 10-30, BYS 21-45, SB 130, 1N5818
48717	MBR040	MBR 030, 40V	BYV 10-40, BYS 21-45, SB 140, 1N5819
48718	MBR0520	20V, 0,5A	-
48719	MBR0530	30V, 0,5A	-
48720	MBR0540	40V, 0,5A	-
48721	MBR10100	MBR 1050, 100V	-
48722	MBR1020	20V, 10A(Tc135°)	BYV 39/30, MBR 1050
48723	MBR1035	MBR 1020, 35V	BYV 39/35, MBR 1050
48724	MBR1045	MBR 1020, 45V	BYV 39/45, MBR 1050
48725	MBR1050	50V, 10A(Tc133°)	-
48726	MBR1060	MBR 1050, 60V	-
48727	MBR1070	MBR 1050, 70V	-
48728	MBR1080	MBR 1050, 80V	-
48729	MBR1090	MBR 1050, 90V	-
48730	MBR1100	MBR 170, 100V	SB 1100
48731	MBR150	50V, 1A	BYV 10-60, BYS 21-90, SB 150, HRP 32
48732	MBR1520	20V, 15A(Tc80°)	1N5826...28
48733	MBR1530	MBR 1520, 30V	1N5827...28
48734	MBR1535	MBR 1520, 35V	1N5828



48735	MBR1535CT	35V, 15A(Tc105°)	BYV 33/35, BYV 133/35, MBR 1550
48736	MBR1540	MBR 1520, 40V	1N5828
48737	MBR1545CT	MBR 1535CT, 45V	BYV 33/45, BYV 133/45, MBR 1550
48738	MBR1550CT	50V, 15A(Tc117°)	HRW 73F
48739	MBR1560CT	MBR 1550, 60V	HRW 73F
48740	MBR160	MBR 150, 60V	BYV 10-60, BYS 21-90, SB 160, HRP 32
48741	MBR1635	35V, 16A(Tc125°)	-
48742	MBR1645	MBR 1635, 45V	-
48743	MBR170	70V, 1A	BYS 21-90, SB 180, HRP 32
48744	MBR180	MBR 170, 80V	BYS 21-90, SB 180, HRP 32
48745	MBR190	MBR 170, 90V	BYS 21-90, SB 190, HRP 32
48746	MBR20100CT	MBR 2060CT, 100V	-
48747	MBR2015CTL	15V, 10A	BYS 24-45
48748	MBR2030CTL	MBR 2015CTL, 30V	BYS 24-45
48749	MBR2035CT	35V, 20A(Tc135°)	BYV 43/35, BYV 143/35
48750	MBR2045CT	MBR 2035CT, 45V	BYV 43/45, BYV 143/45
48751	MBR2060CT	60V, 10A(Tc133°)	BYS 24-90, HRW 36
48752	MBR2070CT	MBR 2060CT, 70V	BYS 24-90, HRW 36
48753	MBR2080CT	MBR 2060CT, 80V	BYS 24-90, HRW 36
48754	MBR2090CT	MBR 2060CT, 90V	BYS 24-90, HRW 36
48755	MBR240100V	100V, 2x40A(Tc125°)	-
48756	MBR2515L	15V, 25A(Tc90°)	-
48757	MBR2520	20V, 25A(Tc80°)	BYV 121-35, 1N5829...31
48758	MBR2530	MBR 2520, 30V	BYV 121-35, 1N5830...31
48759	MBR2535	MBR 2520, 35V	BYV 121-35, 1N5831
48760	MBR2535CT	35V, 30A(Tc130°)	BYV 43/35, BYV 143/35
48761	MBR2535CTL	35V, 12,5A(Tc110°)	BYV 33/35, BYV 133/35
48762	MBR2540	MBR 2520, 40V	BYV 121-40, 1N5831
48763	MBR2545CT	MBR 2535CT, 45V	BYV 43/45, BYV 143/45
48764	MBR28045V	45V, 2x80A(Tc125°)	-
48765	MBR3020CT	20V, 30A(Tc105°)	BYS 28-45, BYV 73/30
48766	MBR3035..45WT	MBR 3035..45CT	BYS 28-45, BYV 73/30...45
48767	MBR3035CT	MBR 3020CT, 35V	BYS 28-45, BYV 73/35
48768	MBR3045CT	MBR 3020CT, 45V	BYS 28-45, BYV 73/45
48769	MBR3045ST	45V, 30A(Tc130°)	BYV 43/45, BYV 143/45
48770	MBR3050PT	50V, 30A(Tc125°)	BYS 28-90, BYS 79/50
48771	MBR3060	MBR 3050PT, 60V	BYS 28-90
48772	MBR3100	MBR 370, 100V	-
48773	MBR320(P)	20V, 3A	HRP 24, SB 320, 1N5820
48774	MBR330(P)	MBR 320, 30V	HRP 24, SB 330, 1N5821
48775	MBR340(P)	MBR 320, 40V	HRP 24, SB 340, 1N5822
48776	MBR350(P)	MBR 320, 50V	HRP 34, SB 350
48777	MBR3520	20V, 35A(Tc110°)	BYS 35-20
48778	MBR3535	MBR 3520, 35V	BYS 35-45
48779	MBR3545	MBR 3520, 45V	BYS 35-45

48780	MBR360(P)	MBR 320, 60V	HRP 34, SB 360
48781	MBR370	70V, 3A	BYS 26-90, SB 380
48782	MBR380	MBR 370, 80V	BYS 26-90, SB 380
48783	MBR390	MBR 370, 90V	BYS 26-90, SB 390
48784	MBR4015LWT	35V, 40A(Tc125°)	BYS 79-40, MBR 4035PT
48785	MBR4020	20V, 40A(Tc70°)	BYS 51-35, BYS 60-20, 1N5832...34
48786	MBR4020..4040PF	MBR 4020..4040	-
48787	MBR4030	MBR 4020, 30V	BYS 51-35, BYS 60-30, 1N5833...34
48788	MBR4035	MBR 4020, 35V	BYS 51-35, BYS 60-45, 1N5834
48789	MBR4035PT	35V, 40A(Tc95°)	BYS 79-40
48790	MBR4040	MBR 4020, 40V	BYS 60-45, 1N5834
48791	MBR4045WT	MBR 4035PT, 45V	BYS 79-50
48792	MBR4050PT	MBR 4035PT, 50V	BYS 79-50
48793	MBR4060PT	MBR 4035PT, 60V	-
48794	MBR5025L	25V, 50A(Tc125°)	-
48795	MBR5823(H,H1)	1N5823	1N5823
48796	MBR5831	1N5831	1N5831
48797	MBR6015(L)	15V, 60A(Tc120°)	BYS 51-35, BYS 60-20
48798	MBR6015..6045B	MBR 6015..6045(L)	-
48799	MBR6020(L)	MBR 6015(L), 20V	BYS 51-35, BYS 60-20
48800	MBR6025(L)	MBR 6015(L), 25V	BYS 51-35, BYS 60-30
48801	MBR6030(L)	MBR 6015(L), 30V	BYS 51-35, BYS 60-30
48802	MBR6035(L)	MBR 6015(L), 35V	BYS 51-35, BYS 60-45
48803	MBR6045(L)	MBR 6015(L), 45V	BYS 51, BYS 60-45
48804	MBR6045PT	45V, 60A(Tc125°)	-
48805	MBR6045PT	45V, 60A(Tc125°)	-
48806	MBR6045WT	MBR 6045PT	-
48807	MBR6535	35V, 65A(Tc120°)	BYS 71-50, BYS 72, BYS 75-45, BYS 76-45
48808	MBR6545	MBR 6535, 45V	BYS 71-50, BYS 72, BYS 75-45, BYS 76-45
48809	MBR735	35V, 7.5A(Tc105°)	BYV 19/35, MBR 1035
48810	MBR745	MBR 735, 45V	BYV 19/45, MBR 1045
48811	MBR750	50V, 7.5A(Tc117°)	MBR 1050
48812	MBR7520	20V, 70A(Tc90°)	BYS 71-40, BYS 72, BYS 75-20, BYS 76-45
48813	MBR7530	MBR 7520, 30V	BYS 71-40, BYS 72, BYS 75-30, BYS 76-45
48814	MBR7535	MBR 7520, 35V	BYS 71-40, BYS 72, BYS 75-45, BYS 76-45
48815	MBR7540	MBR 7520, 40V	BYS 71-40, BYS 72, BYS 75-45, BYS 76-45
48816	MBR7545	MBR 7520, 45V	BYS 71-50, BYS 72, BYS 75-45, BYS 76-45
48817	MBR760	MBR 750, 60V	MBR 1060
48818	MBR8035	35V, 80A(Tc120°)	BYS 71-40, BYS 72, BYS 75-45, BYS 76-45
48819	MBR8045	MBR 8035, 45V	BYS 71-50, BYS 72, BYS 75-45, BYS 76-45
48820	MBRB1545CT	45V, 15A(Tc105°)	-
48821	MBRB20100CT	100V, 20A(Tc100°)	-
48822	MBRB20200CT	200V, 20A(Tc100°)	-
48823	MBRB2060CT	60V, 20A(Tc100°)	-
48824	MBRB2515L	15V, 25A(Tc90°)	-

48825	MBRB2535CTL	35V, 12,5A(Tc110°)	-
48826	MBRB2545CT	45V, 30A(Tc130°)	-
48827	MBRB3030CT	30V, 30A(Tc134°)	-
48828	MBRB4030CT	30V, 40A(Tc115°)	-
48829	MBRD320	20V, 3A(Tc125°)	-
48830	MBRD330	MBRD 320, 30V	-
48831	MBRD340	MBRD 320, 40V	-
48832	MBRD350	MBRD 320, 50V	-
48833	MBRD360	MBRD 320, 60V	-
48834	MBRD620CT	20V, 2x3A(Tc130°)	-
48835	MBRD630CT	MBRD 620CT, 30V	-
48836	MBRD640CT	MBRD 620CT, 40V	-
48837	MBRD650CT	MBRD 620CT, 50V	-
48838	MBRD660CT	MBRD 620CT, 60V	-
48839	MBRD835L	35V, 8A(Tc80°)	-
48840	MBRF1045	MBR 1045	-
48841	MBRF1545CT	MBR 1545CT	-
48842	MBRF20100CT	MBR 20100CT	MA 769
48843	MBRF20200CT	MBR 20200CT	-
48844	MBRF2045CT	MBR 2045CT	BYV 143F/45, MA 752A
48845	MBRF2060CT	MBR 2060CT	MA 756
48846	MBRF2545CT	MBR 2545CT	-
48847	MBRF745	MBR 745	-
48848	MBRL120	20V, 1A	-
48849	MBRL130	MBRL 120, 30V	-
48850	MBRL140	MBRL 120, 40V	-
48851	MBRS1100	100V, 1A	-
48852	MBRS130	30V, 1A	SK 13...18
48853	MBRS140	40V, 1A	SK 14...18
48854	MBS100	Ub3..5V, Is0,1..0,4mA, Itsm6A	-
48855	MBS4991	2N4991	-
48856	MBS4992	2N4992	-
48857	MC	BF 994	BF 994
48858	MC	2SC3099	2SC3099
48859	MC	MA 143	MA 143
48860	MC	2SC5108-Y	2SC5108
48861	MC	BFS 17P	BFS 17P
48862	MC	2SA1052-C	2SA1052
48863	MC	MA 153	MA 153
48864	MC103A		BA 243, BA 283, BA 483...484, 1SS152
48865	MC107	45V, 0,2A, 2W, 300MHz	BD 509, BD 517, BD 525
48866	MC108	MC 107, 30V	BD 505, BD 515, BD 525
48867	MC140	80/40V, 1A, 3,5W, 105MHz	BD 519, BD 527, BD 529
48868	MC141	MC 140, 100/60V	BD 529
48869	MC142	MC 140, 100/100V	BD 529

48870	MC150	50/40V, 1A, 3W, 135MHz	BD 520, BD 528, BD 530
48871	MC151	MC 150, 100/60V	BD 530
48872	MC152	MC 150, 100/100V	BD 530
48873	MC160	80V, 1,5A, 3,5W	BD 519, BD 527, BD 529
48874	MC161	MC 160, 100V	BD 529
48875	MC170	70V, 3A, 4W(Tc60°), 60MHz	BD 179, BD 441, BD 787, BD 789
48876	MC172	70V, 3A, 4W(Tc60°), 60MHz	BD 180, BD 442, BD 788, BD 790
48877	MC301		BA 244, BA 282, BA 284, BA 482
48878	MC302		BA 243, BA 283, BA 483...484, 1SS152
48879	MC328	-/20V, 0,8A, 3,5W, 100MHz	BD 505, BD 515, BD 525
48880	MC338	-/20V, 0,8A, 3,5W, 100MHz	BD 506, BD 516, BD 526
48881	MC340	35V, 1A, 3,5W	BD 505, BD 515, BD 525
48882	MC350	35V, 1A, 3W, 60MHz	BD 506, BD 516, BD 526
48883	MC800	B>20	BD 507, BD 515, BD 525
48884	MC804	VHF-Band-S	-
48885	MC810	MC 800, B>100	BD 507, BD 515, BD 525
48886	MC900	B>50	BD 506, BD 516, BD 526
48887	MC910	MC 900, 40V, B>100	BD 508, BD 516, BD 526
48888	MC911	75V, 0,1A, <4ns	1SS236
48889	MC921	75V, 0,1A, <3ns	1SS234
48890	MC931	75V, 0,1A, <4ns	-
48891	MC932	35V, 0,1A	-
48892	MCO	2SC5088-O	2SC5088
48893	MCO	2SC5085-O	2SC5085
48894	MCO	2SC5084-O	2SC5084
48895	MCR100-3	Igt/Ih<0,2/<5mA	TIC 63, BRY55/100, TAG 70D, TAG 72D
48896	MCR100-4	MCR 100-3, 200V	TIC 64, BRY55/200, TAG 70D, TAG 72D
48897	MCR100-5	MCR 100-3, 300V	BRY55/300, TAG 70D, TAG 72D, 2N6565
48898	MCR100-6	MCR 100-3, 400V	BRY55/400, TAG 70D, TAG 72D, 2N6565
48899	MCR100-7	MCR 100-3, 500V	BRY55/500, TAG 70E, TAG 72E, TAG 59E
48900	MCR100-8	MCR 100-3, 600V	BRY55/600, TAG 70M, TAG 72M, TAG 59M
48901	MCR101	15V, 0,8A, Igt/Ih<0,2/<5mA	BRY 55/30, TAG 70D, TAG 72D, TAG 59F
48902	MCR102	MCR 101, 30V	BRY 55/30, TAG 70D, TAG 72D, TAG 59F
48903	MCR103	MCR 101, 60V	BRY 55/60, TAG 70D, TAG 72D, TAG 59A
48904	MCR104	MCR 101, 100V	BRY 55/100, TAG 70D, TAG 72D, TAG 59A
48905	MCR106-1	Igt/Ih<0,2/<5mA	2N6236, S 2060Y, TAG 633-100, TAG 623-100
48906	MCR106-10	MCR 106-1, 1000V	-
48907	MCR106-2	MCR 106-1, 60V	2N6238, S 2060A, TAG 633-100, TAG 623-100
48908	MCR106-3	MCR 106-1, 100V	2N6238, S 2060A, TAG 633-100, TAG 623-100
48909	MCR106-4	MCR 106-1, 200V	2N6239, S 2060B, TAG 633-200, TAG 623-200
48910	MCR106-5	MCR 106-1, 300V	2N6240, S 2060C, TAG 633-300, TAG 623-300
48911	MCR106-6	MCR 106-1, 400V	2N6240, S 2060D, TAG 633-400, TAG 623-400
48912	MCR106-7	MCR 106-1, 500V	2N6241, S 2060E, TAG 633-500, TAG 623-500
48913	MCR106-8	MCR 106-1, 600V	2N6241, S 2060M, TAG 633-600, TAG 623-600
48914	MCR106-9	MCR 106-1, 700V	TAG 633-700, TAG 623-700, TIC 106M

48915	MCR107-1	Igt/Ih<20/<20mA	TAG 630-100, TAG 620-100, BStC1026
48916	MCR107-10	MCR 107-1, 1000V	BStD1666N
48917	MCR107-2	MCR 107-1, 60V	TAG 630-100, TAG 620-100, BStC1026
48918	MCR107-3	MCR 107-1, 100V	TAG 630-100, TAG 620-100, BStC1026
48919	MCR107-4	MCR 107-1, 200V	TAG 630-200, TAG 620-200, BStC1026
48920	MCR107-5	MCR 107-1, 300V	TAG 630-300, TAG 620-300, BStC1026
48921	MCR107-6	MCR 107-1, 400V	TAG 630-400, TAG 620-400, BStC1026
48922	MCR107-7	MCR 107-1, 500V	TAG 630-500, TAG 620-500, BStC1033
48923	MCR107-8	MCR 107-1, 600V	TAG 630-600, TAG 620-600, BStC1040
48924	MCR107-9	MCR 107-1, 700V	TAG 630-700, TAG 620-700, BStC1046
48925	MCR115	150V, 0,8A, Igt/Ih<0,2/<5mA	TIC 62, MCR 100-3, BRY 55/100, TAG 70D
48926	MCR120	200V, 0,8A, Igt/Ih<0,2/<5mA	TIC 63, MCR 100-4, BRY 55/200, TAG 70D
48927	MCR1308-1	Igt/Ih<50/8mA	BStE4126P, BTW 40/200, CS 16-02
48928	MCR1308-2	MCR 1308-1, 50V	BStE4126P, BTW 42/200, CS 16-02
48929	MCR1308-3	MCR 1308-1, 100V	BStE4126P, BTW 42/200, CS 16-02
48930	MCR1308-4	MCR 1308-1, 200V	BStE4126P, BTW 42/200, CS 16-02
48931	MCR1308-5	MCR 1308-1, 300V	BStE4126P, BTW 42/400, CS 16-04
48932	MCR1308-6	MCR 1308-1, 400V	BStE4126P, BTW 42/400, CS 16-04
48933	MCR1336-10	MCR 1336-5, 800V	-
48934	MCR1336-5	300V, Igt/Ih<40/<50mA	-
48935	MCR1336-6	MCR 1336-5, 400V	-
48936	MCR1336-7	MCR 1336-5, 500V	-
48937	MCR1336-8	MCR 1336-5, 600V	-
48938	MCR1336-9	MCR 1336-5, 700V	-
48939	MCR1718-5	20μs	C 234C, T 12F300, 2N687
48940	MCR1718-6	MCR 1718-5, 400V	C 234D, T 12F400, 2N688
48941	MCR1718-7	MCR 1718-5, 500V	C 234E, T 12F500, 2N689
48942	MCR1718-8	MCR 1718-5, 600V	C 234M, T 12F600, 2N690
48943	MCR1906-1	25V, 1,6A, Igt/Ih<1/<5mA	2N1595A, TAG 2-50, TAG 614-100
48944	MCR1906-2	MCR 1906-1, 50V	2N1595A, TAG 2-50, TAG 614-100
48945	MCR1906-3	MCR 1906-1, 100V	2N1596A, TAG 2-100, TAG 614-100
48946	MCR1906-4	MCR 1906-1, 200V	2N1597A, TAG 2-200, TAG 614-200
48947	MCR1906-5	MCR 1906-1, 300V	2N1598A, TAG 2-300, TAG 614-400
48948	MCR1906-6	MCR 1906-1, 400V	2N1599A, TAG 2-400, TAG 614-400
48949	MCR1907-1	<12μs	C 234U, MCR 1718-5, T 12F100
48950	MCR1907-2	MCR 1907-1, 50V	C 234F, MCR 1718-5, T 12F100
48951	MCR1907-3	MCR 1907-1, 100V	C 234A, MCR 1718-5, T 12F100
48952	MCR1907-4	MCR 1907-1, 200V	C 234B, MCR 1718-5, T 12F200
48953	MCR1907-5	MCR 1907-1, 300V	C 234C, MCR 1718-5, T 12F300
48954	MCR1907-6	MCR 1907-1, 400V	C 234D, MCR 1718-6, T 12F400
48955	MCR201	15V, 0,5A, Igt/Ih<0,2/<5mA	TAG 06Y, BRY 58/30
48956	MCR202	MCR 201, 30V	TAG 06Y, BRY 58/30
48957	MCR203	MCR 201, 60V	TAG 06YY, BRY 58/60
48958	MCR204	MCR 201, 100V	TAG 06A, BRY 58/100
48959	MCR205	MCR 201, 150V	TAG 06B, BRY 58/200

48960	MCR206	MCR 201, 200V	TAG 06B, BRY 58/200
48961	MCR2130-4	200V, Igt/Ih<10/<3mA	-
48962	MCR2130-5	MCR 2130-4, 300V	-
48963	MCR2130-6	MCR 2130-4, 400V	-
48964	MCR2130-7	MCR 2130-4, 500V	-
48965	MCR2130-8	MCR 2130-4, 600V	-
48966	MCR22-2...8	50..600V, Igt<0,2mA	-
48967	MCR220-5	2N6394, 300V	TAG 665-300, TIC 126C, T 7,5N400
48968	MCR220-7	2N6394, 500V	TAG 665-500, TIC 126E, T 7,5N600
48969	MCR220-9	2N6394, 700V	TAG 665-700, TIC 126S, T 7,5N700
48970	MCR221-5	2N6400, 300V	TAG 680-400, T 9,5N400, CS 15-04
48971	MCR221-7	2N6400, 500V	TAG 680-500, T 9,5N600, CS 15-06
48972	MCR221-9	2N6400, 700V	TAG 680-700, T 9,5N700, CS 15-07
48973	MCR23-2...8	50..600V, Igt<0,2m	-
48974	MCR2315-1	Igt/Ih<40/<50mA	MCR 67-1, BStC0313, CS 5-02, BStD0313
48975	MCR2315-2	MCR 2315-1, 50V	MCR 67-2, BStC0313, CS 5-02, BStD0313
48976	MCR2315-3	MCR 2315-1, 100V	MCR 67-3, BStC0313, CS 5-02, BStD0313
48977	MCR2315-4	MCR 2315-1, 200V	BStC0313, CS 5-02, BStD0313, CS 8-02
48978	MCR2315-5	MCR 2315-1, 300V	BStC0326, CS 5-04, BStD0326, CS 8-04
48979	MCR2315-6	MCR 2315-1, 400V	BStC0326, CS 5-04, BStD0326, CS 8-04
48980	MCR2818-1	25V, 25A, Igt/Ih<40/<50mA	MCR 63-1, BStE4026M, 2N3870, MCR 3835-1
48981	MCR2818-2	MCR 2818-1, 50V	MCR 63-2, BStD4026M, 2N3870, MCR 3835-2
48982	MCR2818-3	MCR 2818-1, 100V	MCR 63-3, BStD4026M, 2N3870, MCR 3835-3
48983	MCR2818-4	MCR 2818-1, 200V	MCR 63-4, BStD4026M, 2N3871, MCR 3835-4
48984	MCR2818-5	MCR 2818-1, 300V	MCR 63-5, BStD4026M, 2N3872, MCR 3835-5
48985	MCR2818-6	MCR 2818-1, 400V	MCR 63-6, BStD4026M, 2N3872, MCR 3835-6
48986	MCR2818-7	MCR 2818-1, 500V	MCR 63-7, BStD4033M, 2N3873, MCR 3835-7
48987	MCR2818-8	MCR 2818-1, 600V	MCR 63-8, BStD4040M, 2N3873, MCR 3835-8
48988	MCR2819-1...8	MCR 2818-..	MCR 3935-...
48989	MCR2835-1	25V, 35A, Igt/Ih<40/<50mA	MCR 63-1
48990	MCR2835-2	MCR 2835-1, 50V	MCR 63-2
48991	MCR2835-3	MCR 2835-1, 100V	MCR 63-3
48992	MCR2835-4	MCR 2835-1, 200V	MCR 63-4
48993	MCR2835-5	MCR 2835-1, 300V	MCR 63-5
48994	MCR2835-6	MCR 2835-1, 400V	MCR 63-6
48995	MCR2835-7	MCR 2835-1, 500V	MCR 63-7
48996	MCR2835-8	MCR 2835-1, 600V	MCR 63-8
48997	MCR2918-1...8	MCR 2818-..	2N681...692, T 12N..., C 228..., MCR 3935...
48998	MCR2935-1...8	MCR 2835-..	TAG 35-..., MCR 64-...
48999	MCR3000-1	Igt/Ih<30/<4mA	TIC 126F, T 7,5N400, TAG 680-100
49000	MCR3000-10	MCR 3000-1, 800V	TIC 126N, T 7,5N800, TAG 680-800
49001	MCR3000-2	MCR 3000-1, 50V	TIC 126F, T 7,5N400, TAG 680-100
49002	MCR3000-3	MCR 3000-1, 100V	TIC 126A, T 7,5N400, TAG 680-100
49003	MCR3000-4	MCR 3000-1, 200V	TIC 126B, T 7,5N400, TAG 680-200
49004	MCR3000-7	MCR 3000-1, 500V	TIC 126E, T 7,5N500, TAG 680-500



49005	MCR3000-8	MCR 3000-1, 600V	TIC 126M, T 7,5N600, TAG 680-600
49006	MCR3000-9	MCR 3000-1, 700V	TIC 126S, T 7,5N700, TAG 680-700
49007	MCR320-1...8	25..600V, 7A, Igt/Ih<20/<20mA	-
49008	MCR3818-1	Igt/Ih<40/<50mA	BStD4026M, BStE4026M, MCR 3835-1
49009	MCR3818-10	MCR 3818-1, 800V	BStD4053M, BStE4053M, MCR 3835-10
49010	MCR3818-2	MCR 3818-1, 50V	BStD4026M, BStE4026M, MCR 3835-2
49011	MCR3818-3	MCR 3818-1, 100V	BStD4026M, BStE4026M, MCR 3835-3
49012	MCR3818-4	MCR 3818-1, 200V	BStD4026M, BStE4026M, MCR 3835-4
49013	MCR3818-5	MCR 3818-1, 300V	BStD4026M, BStE4026M, MCR 3835-5
49014	MCR3818-6	MCR 3818-1, 400V	BStD4026M, BStE4026M, MCR 3835-6
49015	MCR3818-7	MCR 3818-1, 500V	BStD4033M, BStE4033M, MCR 3835-7
49016	MCR3818-8	MCR 3818-1, 600V	BStD4040M, BStE4040M, MCR 3835-8
49017	MCR3818-9	MCR 3818-1, 700V	BStD4046M, BStE4046M, MCR 3835-9
49018	MCR3835-1	25V, 35A, Igt/Ih<40/<50mA	BStE4026M, MCR 63-1
49019	MCR3835-10	MCR 3835-1, 800V	BStE4053M, MCR 63-10
49020	MCR3835-2	MCR 3835-1, 50V	BStE4026M, MCR 63-2
49021	MCR3835-3	MCR 3835-1, 100V	BStE4026M, MCR 63-3
49022	MCR3835-4	MCR 3835-1, 200V	BStE4026M, MCR 63-4
49023	MCR3835-5	MCR 3835-1, 300V	BStE4026M, MCR 63-5
49024	MCR3835-6	MCR 3835-1, 400V	BStE4026M, MCR 63-6
49025	MCR3835-7	MCR 3835-1, 500V	BStE4033M, MCR 63-7
49026	MCR3835-8	MCR 3835-1, 600V	BStE4040M, MCR 63-8
49027	MCR3835-9	MCR 3835-1, 700V	BStE4046M, MCR 63-9
49028	MCR3918-1...10	MCR 3818-..	BStD41...M, 2N681...692, T 12N...
49029	MCR3935-1...10	MCR 3835-..	BStE41...M,C 35-...,2N5204...5207,TAG 35...
49030	MCR406-1	30V, 4A, Igt/Ih<0,2/<3mA	S 2060Y, TAG 106Y, TIC 106Y
49031	MCR406-2	MCR 406-1, 60V	S 2060A, TIC 106A, TAG 633-100
49032	MCR406-3	MCR 406-1, 100V	S 2060A, TIC 106A, TAG 633-100
49033	MCR406-4	MCR 406-1, 200V	S 2060B, TIC 106B, TAG 633-200
49034	MCR407-1	Igt/Ih<0,5/<5mA	S 2061Y, TIC 108Y, S 2060Y,TIC 106Y
49035	MCR407-2	MCR 407-1, 60V	S 2061A, TIC 108A, S 2060A,TIC 106A
49036	MCR407-3	MCR 407-1, 100V	S 2061A, TIC 108A, S 2060A,TIC 106A
49037	MCR407-4	MCR 407-1, 200V	S 2061B, TIC 108B, S 2060B,TIC 106B
49038	MCR525-10	MCR 525-4, 800V	-
49039	MCR525-4	Igt/Ih<40/<40mA	MCR 569-6
49040	MCR525-5	MCR 525-4, 300V	MCR 569-6
49041	MCR525-6	MCR 525-4, 400V	MCR 569-6
49042	MCR525-7	MCR 525-4, 500V	-
49043	MCR525-8	MCR 525-4, 600V	-
49044	MCR525-9	MCR 525-4, 700V	-
49045	MCR568-1	Igt/Ih<30/<50mA	MCR 525-4, MCR 569-1
49046	MCR568-2	MCR 568-1, 50V	MCR 525-4, MCR 569-2
49047	MCR568-3	MCR 568-1, 100V	MCR 525-4, MCR 569-3
49048	MCR568-6	MCR 568-1, 400V	MCR 525-6, MCR 569-6
49049	MCR569-1	Igt/Ih<30/<50mA	-

49050	MCR569-2	MCR 569-1, 50V	-
49051	MCR569-3	MCR 569-1, 100V	-
49052	MCR569-6	MCR 569-1, 400V	-
49053	MCR606-2	50V, 4A, Igt/Ih<0,2/<3mA	C 106F, TAG 106F, X 0403B, C 108F
49054	MCR606-3	MCR 606-2, 100V	C 106A, TAG 106A, X 0403B, C 108A
49055	MCR606-4	MCR 606-2, 200V	C 106B, TAG 106B, X 0403B, C 108B
49056	MCR606-5	MCR 606-2, 300V	C 106C, TAG 106C, X 0403D, C 108C
49057	MCR606-6	MCR 606-2, 400V	C 106D, TAG 106D, X 0403D, C 108D
49058	MCR606-7	MCR 606-2, 500V	C 106E, TAG 106E, X 0403M, C 108E
49059	MCR606-8	MCR 606-2, 600V	C 106M, TAG 106M, X 0403M, C 108M
49060	MCR63-1	Igt/Ih<40/<60mA	-
49061	MCR63-10	MCR 63-1, 1000V	-
49062	MCR63-2	MCR 63-1, 50V	-
49063	MCR63-3	MCR 63-1, 100V	-
49064	MCR63-4	MCR 63-1, 200V	-
49065	MCR63-5	MCR 63-1, 300V	-
49066	MCR63-6	MCR 63-1, 400V	-
49067	MCR63-7	MCR 63-1, 500V	-
49068	MCR63-8	MCR 63-1, 600V	-
49069	MCR63-9	MCR 63-1, 700V	-
49070	MCR64-1...10	MCR 63-1..10	TAG 35...
49071	MCR649-1	25V, 20A, Igt/Ih<80/20mA	-
49072	MCR649-10	MCR 649-1, 800V	-
49073	MCR649-2	MCR 649-1, 50V	-
49074	MCR649-3	MCR 649-1, 100V	-
49075	MCR649-4	MCR 649-1, 200V	-
49076	MCR649-5	MCR 649-1, 300V	-
49077	MCR649-6	MCR 649-1, 400V	-
49078	MCR649-7	MCR 649-1, 500V	-
49079	MCR649-8	MCR 649-1, 600V	-
49080	MCR649-9	MCR 649-1, 700V	-
49081	MCR649A(P)-1	MCR 649-1, Igt/Ih<40/20mA	2N2573
49082	MCR649A(P)-10	MCR 649-10, Igt/Ih<40/20mA	-
49083	MCR649A(P)-2	MCR 649-2, Igt/Ih<40/20mA	2N2574
49084	MCR649A(P)-3	MCR 649-3, Igt/Ih<40/20mA	2N2575
49085	MCR649A(P)-4	MCR 649-4, Igt/Ih<40/20mA	2N2576
49086	MCR649A(P)-5	MCR 649-5, Igt/Ih<40/20mA	2N2577
49087	MCR649A(P)-6	MCR 649-6, Igt/Ih<40/20mA	2N2578
49088	MCR649A(P)-7	MCR 649-7, Igt/Ih<40/20mA	2N2579
49089	MCR649A(P)-8	MCR 649-8, Igt/Ih<40/20mA	-
49090	MCR649A(P)-9	MCR 649-9, Igt/Ih<40/20mA	-
49091	MCR65-1...10	MCR 63-1..10	-
49092	MCR67-1	Igt/Ih<30/<50mA	BStC0313, CS 5-02, BStD0313, CS 8-02
49093	MCR67-2	MCR 67-1, 50V	BStC0313, CS 5-02, BStD0313, CS 8-02
49094	MCR67-3	MCR 67-1, 100V	BStC0313, CS 5-02, BStD0313, CS 8-02

49095	MCR68-1...3	Igt/Ih<30/<50mA	BStD1026, BStD1666, BT 152/400
49096	MCR69-1	Igt/Ih<30/<50mA	2N6504...6509
49097	MCR69-2	MCR 69-1, 50V	2N6504...6509
49098	MCR69-3	MCR 69-1, 100V	2N6505...6509
49099	MCR70-1...3	Igt/Ih<30/<50mA	C 228A, 2N3896...3899,C 35A, MCR 64-...
49100	MCR71-1...3	Igt/Ih<30/<50mA	MCR 64-..., TAG 35-...
49101	MCR72-1	Igt/Ih<0,2/<6mA	S 4060 U
49102	MCR72-2	MCR 72-1, 50V	S 4060 F
49103	MCR72-3	MCR 72-1, 100V	S 4060 A
49104	MCR72-4	MCR 72-1, 200V	S 4060 B
49105	MCR72-5	MCR 72-1, 300V	S 4060 C
49106	MCR72-6	MCR 72-1, 400V	S 4060 D
49107	MCR72-7	MCR 72-1, 500V	S 4060 E
49108	MCR72-8	MCR 72-1, 600V	S 4060 M
49109	MCR729-10	MCR 729-5, 800V	T 6F800C, TAG 15S-800, T 12F800
49110	MCR729-5	<15µs	T 6F300C, TAG 15S-400, T 12F300
49111	MCR729-6	MCR 729-5, 400V	T 6F400C, TAG 15S-400, T 12F400
49112	MCR729-7	MCR 729-5, 500V	T 6F500C, TAG 15S-500, T 12F500
49113	MCR729-8	MCR 729-5, 600V	T 6F600C, TAG 15S-600, T 12F600
49114	MCR729-9	MCR 729-5, 700V	T 6F700C, TAG 15S-700, T 12F700
49115	MCR808-1	Igt/Ih<50/8mA	BStE4026P, BStE4026PM
49116	MCR808-2	MCR 808-1, 50V	BStE4026P, BStE4026PM
49117	MCR808-3	MCR 808-1, 100V	BStE4026P, BStE4026PM
49118	MCR808-4	MCR 808-1, 200V	BStE4026P, BStE4026PM
49119	MCR808-5	MCR 808-1, 300V	BStE4026P, BStE4026PM
49120	MCR808-6	MCR 808-1, 400V	BStE4026P, BStE4026PM
49121	MCR846-1	25V, 2A, Igt/Ih<50/15mA	BTW 42/600
49122	MCR846-2	MCR 846-1, 50V	BTW 42/600
49123	MCR846-3	MCR 846-1, 100V	BTW 42/600
49124	MCR846-4	MCR 846-1, 200V	BTW 42/600
49125	MCR914-1	25V, 1,6A(Tc65°C), Igt<8mA	2N1595, BTX 30/50, T 1N100, TAG 1-50
49126	MCR914-2	MCR 914-1, 50V	2N1595, BTX 30/50, T 1N100, TAG 1-50
49127	MCR914-3	MCR 914-1, 100V	2N1596, BTX 30/100, T 1N100, TAG 1-100
49128	MCR914-4	MCR 914-1, 200V	2N1597, BTX 30/200, T 1N200, TAG 1-200
49129	MCR914-5	MCR 914-1, 300V	2N1598, BTX 30/300, T 1N300, TAG 1-300
49130	MCR914-6	MCR 914-1, 400V	2N1599, BTX 30/400, T 1N400, TAG 1-400
49131	MCY	2SC5088-Y	2SC5088
49132	MCY	2SC5085-Y	2SC5085
49133	MCY	2SC5084-Y	2SC5084
49134	MD	BF 996	BF 996
49135	MD	P6 SMB-47	P6 SMB-47
49136	MD	2SC5111-O	2SC5111
49137	MD	2SA1052-D	2SA1052
49138	MD	MA 28-A	MA 28-A
49139	MD	2SA1245	2SA1245

49140	MD	SM 6T 18C	SM 6T...
49141	MD1	FN 3L4Z	FN 3...
49142	MD1	0,75..0,85V(100mA)	BZ 102/0V7, BZX 55/C0V8, ZPD 1
49143	MD2	1,55..1,8V(100mA)	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
49144	MD3	2,22..2,5V(100mA)	BZ 102/2V1, BZX 75/C2V1, ZTE 2
49145	MD34	1N34A	
49146	MD35	1N35	
49147	MD38	1N38A	
49148	MD4	2,92..3,2V(100mA)	BZ 102/2V8, BZX 75/C2V8
49149	MD46	1N46	
49150	MD54	1N54A	
49151	MD56	1N56	
49152	MD58	1N58A	
49153	MD60(A)	1N60(A)	
49154	MDC3105LT1	Rb1k, Rbe33kOhm, 6V, 0,3A	-
49155	MDD	SM 15T 6V8	SM 15T...
49156	MDE	SM 15T 6V8A	SM 15T...
49157	MDF	SM 15T 7V5	SM 15T...
49158	MDG	SM 15T 7V5A	SM 15T...
49159	MDN	SM 15T 10	SM 15T...
49160	MDO	2SC5093-O	2SC5093
49161	MDO	2SC5090-O	2SC5090
49162	MDO	2SC5089-O	2SC5089
49163	MDP	SM 15T 10A	SM 15T...
49164	MDR	2SC5093-R	2SC5093
49165	MDR	2SC5090-R	2SC5090
49166	MDR	2SC5089-R	2SC5089
49167	MDS	SM 15T 12	SM 15T...
49168	MDS1678	65V, 3A, 10W, PQ>4W(27MHz)	-
49169	MDS20	250V, 0,5A, 10W, >60MHz	BF 381...382, MPSU 10, BF 757...759
49170	MDS21	MDS 20, 300V	BF 382, MPSU 10, BF 758...759
49171	MDS26	60V, 3A, 12,5W, >50MHz	2SC2562, 2SC3252...3253, 2SD1912
49172	MDS27	MDS 26, 80V	2SC3252...3253
49173	MDS60	300V, 0,5A, 10W, >45MHz	BF 382, MPSU 60, BF 758...759
49174	MDS76	60V, 3A, 12,5W, >50MHz	2SA1012, 2SA1288...1289, 2SB1273
49175	MDS77	MDS 76, 80V	2SA1288...1289
49176	MDT	SM 15T 12A	SM 15T...
49177	MDV04-600	600V, 4A, 55ns	MUR 460, MUR 480, MUR 4100
49178	MDW	SM 15T 15	SM 15T...
49179	MDX	SM 15T 15A	SM 15T...
49180	ME	BF 993	BF 993
49181	ME	P6 SMB-47A	P6 SMB-47A
49182	ME	2SC5111-Y	2SC5111
49183	ME	2SA1602-E	2SA1602
49184	ME	2SC4393	2SC4393

49185	ME	MA 28-B	MA 28-B
49186	ME	2SA1235-E	2SA1235
49187	ME	2SC3429	2SC3429
49188	ME	SM 6T 18CA	SM 6T...
49189	ME	2SC3268	2SC3268
49190	ME	2SC3302	2SC3302
49191	ME1,5	1,35..1,55V(5mA)	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
49192	ME2	1,9..2,2V(5mA)	BZ 102/2V1, BZX 75/C2V1, ZTE 2
49193	ME3001	600MHz	BF 225, BF 314, BF 496, BF 505, BF 507
49194	ME3002	900MHz	BF 377...378, BF 689(K), BF 689
49195	ME3011	900MHz	BF 377...378, BF 689(K), BF 689
49196	ME8001	40V, 0,8A, 0,4W	BC 337, BC 635, BC 637, BC 639
49197	ME8002	120V, 0,8A, 0,4W, 200MHz	2N3700...3701, 2SC2235, 2SD667, 2N2405
49198	ME8003	ME 8002, 80V	BC 639, 2N3700...3701, 2SC2235, 2SD667
49199	MED	SM 15T 18	SM 15T...
49200	MEE	SM 15T 18A	SM 15T...
49201	MEF101	30V, Idss>0,2mA, Up<10V	2N3365
49202	MEF102	40V, Idss>0,2mA, Up<1,5V	BFW 13, 2N4338
49203	MEF103	40V, Idss>0,9mA, Up<4V	2N5246, 2N5360, 2SK107, 2SK116
49204	MEF104	50V, Idss>4mA, Up<10V	2SK113
49205	MEF3069...3071	2N3069..3071	
49206	MEF3458...3460	2N3458..3460	
49207	MEF3684...3687	2N3684..3687	
49208	MEF3819...3823	2N3819..3823	
49209	MEF4220...4224	2N4220..4224	
49210	MEF4302...4304	2N4302..4304	
49211	MEF4338...4341	2N4338..4341	
49212	MEF4391...4393	2N4391..4393	
49213	MEF4416	2N4416	
49214	MEF4856...4861	2N4856..4861	
49215	MEF5103...5105	2N5103..5105	
49216	MEF5163	2N5163	
49217	MEF5245...5248	2N5245..5248	
49218	MEF5358...5364	2N5358..5364	
49219	MEF5391...5396	2N5391..5396	
49220	MEF5457...5459	2N5457..5359	
49221	MEF5484...5486	2N5484..5486	
49222	MEF5556...5558	2N5556..5558	
49223	MEF5561...5563	2N5561..5563	
49224	MEH	SM 15T 22	SM 15T...
49225	MEK	SM 15T 22A	SM 15T...
49226	MEL	SM 15T 24	SM 15T...
49227	MEM	SM 15T 24A	SM 15T...
49228	MEN	SM 15T 27	SM 15T...
49229	MEO	2SC5098-O	2SC5098

49230	MEO	2SC5095-O	2SC5095
49231	MEO	2SC5094-O	2SC5094
49232	MEP	SM 15T 27A	SM 15T...
49233	MEQ	SM 15T 30	SM 15T...
49234	MER	2SC5098-R	2SC5098
49235	MER	2SC5095-R	2SC5095
49236	MER	2SC5094-R	2SC5094
49237	MER	SM 15T 30A	SM 15T...
49238	MES	SM 15T 33	SM 15T...
49239	MET	SM 15T 33A	SM 15T...
49240	MEU	SM 15T 36	SM 15T...
49241	MEU21	$I_p < 2\mu A, I_v > 70\mu A$	-
49242	MEU22	$I_p < 0,15\mu A, I_v > 25\mu A$	-
49243	MEV	SM 15T 36A	SM 15T...
49244	MEW	SM 15T 39	SM 15T...
49245	MEX	SM 15T 39A	SM 15T...
49246	MF	BF 989S	BF 989S
49247	MF	P6 SMB-51	P6 SMB-51
49248	MF	2SA1602-F	2SA1602
49249	MF	2SC3445	2SC3445
49250	MF	MA 28W-A	MA 28W-A
49251	MF	2SA1235-F	2SA1235
49252	MF120	220V, 0,05A, 2,5W, 120MHz	BF 459, BF 471, BF 583, BF 871
49253	MF177	100V, 0,05A, 2,5W, 120MHz	BF 457, BF 469, BF 858, BF 869
49254	MF178	160V, 0,1A, 2,5W, 120MHz	BF 457, BF 415, BF 615, BF 858
49255	MF179(A...C)	250V, 0,1A, 2,5W, 120MHz	BF 459, BF 417, BF 617, BF 859
49256	MF3304	18V, 0,2W, <60/60ns	BSV 21, BSW 25, BSW 37, BSX 36, 2N3012
49257	MF4391	2N4391	
49258	MF4392	2N4392	
49259	MF4393	2N4393	
49260	MF500	30V, 0,06A, 730MHz	-
49261	MFE120	20V, $I_{dss} > 2mA, U_p < 4V$	BF 350, BF 960...961, BF 981, 3SK48...49
49262	MFE121	20V, $I_{dss} > 5mA, U_p < 4V$	BF 352...353, BF 963, BF 981, 3SK81
49263	MFE122	20V, $I_{dss} > 2mA, U_p < 4V$	BF 350, BF 960...961, BF 981, 3SK48...49
49264	MFE130	25V, $I_{dss} > 3mA, U_p < 4V$	BF 350...351, BF 960...961, BF 981
49265	MFE131	25V, $I_{dss} > 3mA, U_p < 4V$	BF 350...351, BF 960...961, BF 981
49266	MFE132	25V, $I_{dss} > 3mA, U_p < 4V$	BF 350...351, BF 960...961, BF 981
49267	MFE140	25V, $I_{dss} < 30mA, U_p < 4V$	BF 350...351, BF 960...961, BF 981
49268	MFE2000	25V, $I_{dss} > 4mA, U_p < 4V$	BF 256, 2N5485
49269	MFE2001	25V, $I_{dss} > 8mA, U_p < 7,5V$	BF 256, 2N5397, 2N5486
49270	MFE2003	25V, $I_{dss} > 0,5mA, U_p < 8V$	BF 244...245, BFS 71, 2N3822, 2N4416
49271	MFE2004	30V, <60/80ns	BSV 80, 2N4093, 2N4858, 2N4861
49272	MFE2005	30V, <35/60ns	BFS 75, BSV 79, 2N4092, 2N4857, 2N4860
49273	MFE2006	30V, <20/40ns	BFS 74, BSV 78, 2N4391, 2N4856, 2N4859
49274	MFE2007	25V, <16/100ns	BSV 80, 2N4093, 2N4858, 2N5861



49275	MFE2008	25V, <16/60ns	BFS 75, BSV 79, 2N4092, 2N4857, 2N4860
49276	MFE2009	25V, <16/37ns	BFS 74, BSV 78, 2N4391, 2N4856, 2N4859
49277	MFE2010	25V, <16/110ns	BFS 75, BSV 79, 2N4092, 2N4857, 2N4860
49278	MFE2011	25V, <16/65ns	BFS 74, BSV 78, 2N4091, 2N4856, 2N4859
49279	MFE2012	25V, <16/37ns	2N5432
49280	MFE2093	50V, Idss>0,1mA, Up<2,5V	2N4117, 2SK92...93, 2SK103
49281	MFE2094	50V, Idss>0,4mA, Up<4,5V	2N4339, 2N5358, 2SK83, 2SK193, 2SK195
49282	MFE2095	50V, Idss>1mA, Up<5,5V	2N5246, 2N5360, 2SK161
49283	MFE2097	50V, Idss>15mA, Up>7V	-
49284	MFE2098	50V, Idss>40mA, Up>10V	-
49285	MFE2133	30V, Idss>25mA	-
49286	MFE3001	20V, Idss>0,5mA, Up<8V	-
49287	MFE3002	20V, Up<3V	-
49288	MFE3003	20V, Up<4V	-
49289	MFE3004	20V, Idss>2mA, Up<5V	-
49290	MFE3005	20V, Idss>2mA, Up<5V	-
49291	MFE3006	25V, Idss>2mA, Up<3V	BF 350, BF 960...961, BF 981, 3SK48...49
49292	MFE3007	25V, Idss>5mA, Up<3V	BF 351,...353, BF 963, 3SK51, 3SK74
49293	MFE3008	25V, Idss>2mA, Up<3V	BF 350, BF 960...961, BF 981, 3SK48...49
49294	MFE4007	40V, Idss>0,5mA, Up<3V	2N2844, 2N5020
49295	MFE4008	40V, Idss>0,8mA, Up<3V	2N5021, 2SJ14
49296	MFE4009	40V, Idss>1,5mA, Up<6V	2N5460...5461, 2N5463...5464, 2SJ103
49297	MFE4010	40V, Idss>2,5mA, Up<6V	2N5461, 2N5464
49298	MFE4011	40V, Idss>4mA, Up<8V	BF 320, 2N5462, 2N5465
49299	MFE4012	40V, Idss>7mA, Up<8V	BF 320C, BFT 11, 2N4343
49300	MFE4302	2N4302	
49301	MFE521	30V, Up<2V	-
49302	MFE590	30V	-
49303	MFE591	30V	-
49304	MFE824	20V, Idss>1mA, Up<6V	-
49305	MFE825	20V, Idss>1mA, Up<2V	-
49306	MFE910	60V, 0,5A, 6,25W(Tc25°)	BST 90
49307	MFE9200	200V, 0,4A, <15/15ns	BSS 88...89, BSS 91, BST 74
49308	MFE930	35V, 2A, 6,25W(Tc25°)	BST 95
49309	MFE960	60V, 2A, 6,25W(Tc25°)	BST 95
49310	MFE990	90V, 2A, 6,25W(Tc25°)	BST 95
49311	MFN	SM 15T 68	SM 15T...
49312	MFO	2SC5106-O	2SC5106
49313	MFO	2SC5107-O	2SC5107
49314	MFP	SM 15T 68A	SM 15T...
49315	MFW	SM 15T 100	SM 15T...
49316	MFY	SM 15T 100A	SM 15T...
49317	MFY	2SC5106-Y	2SC5106
49318	MFY	2SC5107-Y	2SC5107
49319	MG	P6 SMB-51A	P6 SMB-51A

49320	MG	2SA1235-G	2SA1235
49321	MG	2SA1602-G	2SA1602
49322	MG(p)	BF 994S	BF 994S
49323	MGH	SM 15T 150	SM 15T...
49324	MGK	SM 15T 150A	SM 15T...
49325	MGM20N45	450V, 20A, 100W	GN 6020C, GT 25J101
49326	MGM20N50	MGM 20 N45, 500V	GN 6020C, GT 25J101
49327	MGM5N45	450V, 5A, 50W	GT 15J101
49328	MGM5N50	MGM 5 N45, 500V	GT 15J101
49329	MGO	2SC5109-O	2SC5109
49330	MGO	2SC5110-O	2SC5110
49331	MGP20N14CL	>135V, 20A, 150W	-
49332	MGP20N35CL	>320V, 20A, 150W	-
49333	MGP20N40CL	>320V, 20A, 150W	-
49334	MGP20N45,N50	MGM 20 N45..50	-
49335	MGP5N45,N50	MGM 5 N45..50	GN 6010A
49336	MGU	SM 15T 200	SM 15T...
49337	MGV	SM 15T 200A	SM 15T...
49338	MGW	SM 15T 220	SM 15T...
49339	MGW12N120	1200V, 20A, 123W	GT 25Q101
49340	MGW12N120D	MGW 12N120	-
49341	MGW20N120	1200V, 28A, 174W	GT 25Q101
49342	MGW20N60D	600V, 32A, 142W	BUP 602D
49343	MGW30N60	600V, 50A, 202W	BUP 604, GN 6050E, GT 60J101
49344	MGX	SM 15T 220A	SM 15T...
49345	MGY	2SC5109-Y	2SC5109
49346	MGY	2SC5110-Y	2SC5110
49347	MGY20N120D	1200V, 28A, 174W	-
49348	MGY25N120	1200V, 38A, 212W	GN 12050E
49349	MGY25N120D	MGY 25N120	-
49350	MGY30N60D	600V, 50A, 202W	GT 60M301
49351	MGY40N60	600V, 66A, 260W	GN 6075E, GT 80J101
49352	MGY40N60D	MGY 40N60	-
49353	MH	2SC3609	2SC3609
49354	MH	P6 SMB-56	P6 SMB-56
49355	MH	2SC3606	2SC3606
49356	MH	MA 141K	MA 141K
49357	MH	2SC4394	2SC4394
49358	MH	MA 151K	MA 151K
49359	MH	2SC4839	2SC4839
49360	MH	SM 6T 22C	SM 6T...
49361	MH	2SC3607	2SC3607
49362	MH	2SC3608	2SC3608
49363	MH(p)	BF 996S	BF 996S
49364	MH0821	35V, 1,2A, 15W, 100MHz, B>30	2SA748

49365	MH0822	MH 0821, B>50	2SA748
49366	MH0823	MH 0821, B>100	2SA748
49367	MH8221	35V, 1,2A, 15W, 100MHz, B>30	2SC1398
49368	MH8222	MH 8221, B>50	2SC1398
49369	MH8223	MH 8221, B>100	2SC1398
49370	MI	2SC3745	2SC3745
49371	MI	MA 152K	MA 152K
49372	MI	MA 142K	MA 142K
49373	MI	MA 132K	MA 132K
49374	MI-	2SC4126	2SC4126
49375	MJ1000	60V, 8A, 90W, B>1000	BDX 63(A...C), BDV 65(A...C), 2N6055...56
49376	MJ1000	60V, 8A, 90W, B>1000	BDX 63(A...C), BDV 65(A...C), 2N6055...56
49377	MJ10000	450/350V, 20A, 175W, B>50	BUT 13, 2SD831
49378	MJ10000	450/350V, 20A, 175W, B>50	BUT 13, 2SD831
49379	MJ10001	MJ 10000, 500/400V	BUT 13, 2SD831
49380	MJ10001	MJ 10000, 500/400V	BUT 13, 2SD831
49381	MJ10002	450/350V, 10A, 150W, B>40	BU 921...922, BUW 81, 2SD685
49382	MJ10002	450/350V, 10A, 150W, B>40	BU 921...922, BUW 81, 2SD685
49383	MJ10003	MJ 10002, 500/400V	BU 922, BUW 81, 2SD685
49384	MJ10003	MJ 10002, 500/400V	BU 922, BUW 81, 2SD685
49385	MJ10004	MJ 10000, +	-
49386	MJ10004	MJ 10000, +	-
49387	MJ10004P	MJ 10004, 150W	-
49388	MJ10004PFI	MJ 10004, , 60W	-
49389	MJ10005	MJ 10001, +	-
49390	MJ10005	MJ 10001, +	-
49391	MJ10005P	MJ 10005, 150W	-
49392	MJ10005PFI	MJ 10005, , 60W	-
49393	MJ10006	MJ 10002, +	-
49394	MJ10006	MJ 10002, +	-
49395	MJ10007	MJ 10003, +	-
49396	MJ10007	MJ 10003, +	-
49397	MJ10008	650/450V, 20A, 175W	-
49398	MJ10008	650/450V, 20A, 175W	-
49399	MJ10009	MJ 10008, 700/500V	-
49400	MJ10009	MJ 10008, 700/500V	-
49401	MJ1001	MJ 1000, 80V	BDX 63A...C, BDV 65A...C, 2N6056
49402	MJ1001	MJ 1000, 80V	BDX 63A...C, BDV 65A...C, 2N6056
49403	MJ10011	-/1400V, 8A, 80W	-
49404	MJ10011	-/1400V, 8A, 80W	-
49405	MJ10012	600/400V, 10A, 175W, B>100	BUW 81(A), 2SD685
49406	MJ10012	600/400V, 10A, 175W, B>100	BUW 81(A), 2SD685
49407	MJ10013	650/550V, 10A, 175W	-
49408	MJ10013	650/550V, 10A, 175W	-
49409	MJ10014	MJ 10013, 700/600V	-

49410	MJ10014	MJ 10013, 700/600V	-
49411	MJ10015	600/400V, 50A, 250W	-
49412	MJ10015	600/400V, 50A, 250W	-
49413	MJ10016	MJ 10015, 700/500V	-
49414	MJ10016	MJ 10015, 700/500V	-
49415	MJ10020	300/200V, 60A, 250W	-
49416	MJ10020	300/200V, 60A, 250W	-
49417	MJ10021	MJ 10020, 350/250V	-
49418	MJ10021	MJ 10020, 350/250V	-
49419	MJ10022	450/350V, 40A, 250W	-
49420	MJ10022	450/350V, 40A, 250W	-
49421	MJ10023	MJ 10022, 600/400V	-
49422	MJ10023	MJ 10022, 600/400V	-
49423	MJ10024	1000/750V, 20A, 250W	-
49424	MJ10024	1000/750V, 20A, 250W	-
49425	MJ10025	MJ 10024, 1200/850V	-
49426	MJ10025	MJ 10024, 1200/850V	-
49427	MJ105	1400V, 2.5A, 10W(Tc90°)	BU 205(A), BU 208(A), 2SC1922, 2SD575
49428	MJ11011	60V, 30A, 200W, B>1000	BDX 68A...C
49429	MJ11011	60V, 30A, 200W, B>1000	BDX 68A...C
49430	MJ11012	60V, 30A, 200W, B>1000	BDX 69A...C
49431	MJ11012	60V, 30A, 200W, B>1000	BDX 69A...C
49432	MJ11013	MJ 11011, 90V	BDX 68B...C
49433	MJ11013	MJ 11011, 90V	BDX 68B...C
49434	MJ11014	MJ 11012, 90V	BDX 69B...C
49435	MJ11014	MJ 11012, 90V	BDX 69B...C
49436	MJ11015	MJ 11011, 120V	BDX 68C
49437	MJ11015	MJ 11011, 120V	BDX 68C
49438	MJ11016	MJ 11012, 120V	BDX 69C
49439	MJ11016	MJ 11012, 120V	BDX 69C
49440	MJ11017	150/150V, 15A, 175W, B>400	BDV 67D
49441	MJ11017	150/150V, 15A, 175W, B>400	BDV 66D
49442	MJ11017	150/150V, 15A, 175W, B>400	BDV 66D
49443	MJ11017	150/150V, 15A, 175W, B>400	BDV 67D
49444	MJ11018	150/150V, 15A, 175W, B>400	BDV 66D
49445	MJ11018	150/150V, 15A, 175W, B>400	BDV 66D
49446	MJ11019	MJ 11017, 200/200V	-
49447	MJ11019	MJ 11017, 200/200V	-
49448	MJ11020	MJ 11018, 200/200V	-
49449	MJ11020	MJ 11018, 200/200V	-
49450	MJ11021	MJ 11017, 250/250V	-
49451	MJ11021	MJ 11017, 250/250V	-
49452	MJ11022	MJ 11018, 250/250V	-
49453	MJ11022	MJ 11018, 250/250V	-
49454	MJ11028	60V, 50A, 300W, B>1000	-

49455	MJ11028	60V, 50A, 300W, B>1000	-
49456	MJ11029	60V, 50A, 300W, B>1000	-
49457	MJ11029	60V, 50A, 300W, B>1000	-
49458	MJ11030	MJ 11028, 90V	-
49459	MJ11030	MJ 11028, 90V	-
49460	MJ11031	MJ 11029, 90V	-
49461	MJ11031	MJ 11029, 90V	-
49462	MJ11032	MJ 11028, 120V	-
49463	MJ11032	MJ 11028, 120V	-
49464	MJ11033	MJ 11029, 120V	-
49465	MJ11033	MJ 11029, 120V	-
49466	MJ12002	1500/750V, 2,6A, 75W	BU 205(A), BU 208(A), 2SD350(A)
49467	MJ12002	1500/750V, 2,6A, 75W	BU 205(A), BU 208(A), 2SD350(A)
49468	MJ12003	1500/750V, 4A, 100W	BU 500, BU 508(A), 2SC2928
49469	MJ12003	1500/750V, 4A, 100W	BU 500, BU 508(A), 2SC2928
49470	MJ12004	1500/750V, 5A, 100W	BU 500, BU 508(A), 2SC2928
49471	MJ12004	1500/750V, 5A, 100W	BU 500, BU 508(A), 2SC2928
49472	MJ12005	1500/750V, 8A, 100W	BU 508(A)
49473	MJ12005	1500/750V, 8A, 100W	BU 508(A)
49474	MJ12010	950/400V, 10A, 100W	BU 508(A), 2SD1279
49475	MJ12010	950/400V, 10A, 100W	BU 508(A), 2SD1279
49476	MJ12020	850/450V, 5A, 125W, >15MHz	BUS 11(A), BUX 83, 2SD807, 2SD1103...04
49477	MJ12020	850/450V, 5A, 125W, >15MHz	BUS 11(A), BUX 83, 2SD807, 2SD1103...04
49478	MJ12021	850/450V, 8A, 150W, >15MHz	BUS 12(A), BUX 47(A), BUY 69A, BUY 70A
49479	MJ12021	850/450V, 8A, 150W, >15MHz	BUS 12(A), BUX 47(A), BUY 69A, BUY 70A
49480	MJ12022	850/450V, 15A, 175W, >15MHz	BUS 13(A), BUX 48(A)
49481	MJ12022	850/450V, 15A, 175W, >15MHz	BUS 13(A), BUX 48(A)
49482	MJ13010	-/400V, 30A, 175W, >6MHz	BUS 14(A), BUS 98(A), 2SC3058
49483	MJ13010	-/400V, 30A, 175W, >6MHz	BUS 14(A), BUS 98(A), 2SC3058
49484	MJ13014	550/350V, 10A, 150W	BUW 25...26, BUW 34...36, 2SC3046
49485	MJ13014	550/350V, 10A, 150W	BUW 25...26, BUW 34...36, 2SC3046
49486	MJ13015	MJ 13014, 600/400V	BUW 25...26, BUW 34...36, 2SC3046
49487	MJ13015	MJ 13014, 600/400V	BUW 25...26, BUW 34...36, 2SC3046
49488	MJ13070	650/400V, 5A, 125W	BUS 11(A), BUW 11(A), BUX 82...83
49489	MJ13070	650/400V, 5A, 125W	BUS 11(A), BUW 11(A), BUX 82...83
49490	MJ13071	MJ 13070, 750/450V	BUS 11(A), BUW 11(A), BUX 82...83
49491	MJ13071	MJ 13070, 750/450V	BUS 11(A), BUW 11(A), BUX 82...83
49492	MJ13080	650/400V, 8A, 150W	BUS 12(A), BUW 12(A), BUW 35, BUW 132
49493	MJ13080	650/400V, 8A, 150W	BUS 12(A), BUW 12(A), BUW 35, BUW 132
49494	MJ13081	MJ 13080, 750/450V	BUS 12(A), BUW 12(A), BUW 35, BUW 132
49495	MJ13081	MJ 13080, 750/450V	BUS 12(A), BUW 12(A), BUW 35, BUW 132
49496	MJ13090	650/400V, 15A, 175W	BUS 13(A), BUW 13(A), BUW 45...46
49497	MJ13090	650/400V, 15A, 175W	BUS 13(A), BUW 13(A), BUW 45...46
49498	MJ13091	MJ 13090, 750/450V	BUS 13(A), BUW 13(A), BUW 45...46
49499	MJ13091	MJ 13090, 750/450V	BUS 13(A), BUW 13(A), BUW 45...46

49500	MJ13100	650/400V, 20A, 175W	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
49501	MJ13100	650/400V, 20A, 175W	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
49502	MJ13101	MJ 13100, 750/450V	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
49503	MJ13101	MJ 13100, 750/450V	BUX 98AP, 2SC3094, 2SC3593, 2SC3988
49504	MJ13330	400/200V, 20A, 175W	BUV 23...24, BUX 23...24, 2SC3085
49505	MJ13330	400/200V, 20A, 175W	BUV 23...24, BUX 23...24, 2SC3085
49506	MJ13331	MJ 13330, 450/250V	BUV 23...24, BUX 23...24, 2SC3085
49507	MJ13331	MJ 13330, 450/250V	BUV 23...24, BUX 23...24, 2SC3085
49508	MJ13332	650/350V, 20A, 175W	2SC3085, 2SC3094, 2SC3216, 2SC3593
49509	MJ13333	MJ 13332, 700/400V	2SC3094, 2SC3216, 2SC3593
49510	MJ13334	MJ 13332, 750/450V	2SC3094, 2SC3216, 2SC3593
49511	MJ13335	MJ 13332, 800/500V	2SC3094, 2SC3216, 2SC3593
49512	MJ14000	60V, 60A, 300W	-
49513	MJ14001	60V, 60A, 300W	-
49514	MJ14002	MJ 14000, 80V	-
49515	MJ14003	MJ 14001, 80V	-
49516	MJ15001	140V, 15A, 200W, >2MHz	2N5631, 2SC2608, MJ 15015
49517	MJ15002	140V, 15A, 200W, >2MHz	2N6031, 2SA1117, MJ 15016
49518	MJ15003	140V, 20A, 250W, >2MHz	-
49519	MJ15004	140V, 20A, 250W, >2MHz	-
49520	MJ15011	250/250V, 10A, 200W	-
49521	MJ15012	250/250V, 10A, 200W	-
49522	MJ15015	>0,8MHz	2SC2608
49523	MJ15016	>2,2MHz	2SA1117
49524	MJ15022	350/200V, 16A, 250W, >4MHz	-
49525	MJ15023	350/200V, 16A, 250W, >4MHz	-
49526	MJ15024	MJ 15022, 400/250V	-
49527	MJ15025	MJ 15023, 400/250V	-
49528	MJ15026	200/200V, 16A, 250W, >15MHz	-
49529	MJ15027	200/200V, 16A, 250W, >15MHz	-
49530	MJ16002	850/450V, 5A, 125W, B>5	BUS 11(A), BUW 11(A), BUX 83, 2SC3156
49531	MJ16002A	MJ 16002, 1000/500V, 100W	BUS 11A, BUW 11A, BUX 83, 2SC3343
49532	MJ16004	MJ 16002, B>7	BUS 11(A), BUW 11(A), BUX 83, 2SC3156
49533	MJ16006	850/450V, 8A, 150W, B>5	BUS 12(A), BUW 12(A), BUW 36, BUX 81
49534	MJ16006A	MJ 16006, 1000/500V	BUS 12A, BUW 12A, BUW 47A, BUX 81
49535	MJ16008	MJ 16006, B>7	BUS 12(A), BUW 12(A), BUW 36, BUX 81
49536	MJ16010	850/450V, 15A, 175W, B>5	48A...C
49537	MJ16010A	MJ 16010, 1000/500V	BUS 13A, BUW 13A, BUX 48A...C, BUX 81
49538	MJ16012	MJ 16010, B>7	48A...C
49539	MJ16014	850/450V, 20A, 250W, B>5	-
49540	MJ16016	MJ 16014, B>7	-
49541	MJ16018	1500/800V, 10A, 175W	BUV 71, BUX 88, 2SC4023
49542	MJ1800	500/250V, 5A, 100W	BUX 45, 2SC3083, 2SD418, 2SD807
49543	MJ1800	500/250V, 5A, 100W	BUX 45, 2SC3083, 2SD418, 2SD807
49544	MJ2249	60V, 2A, 20W, >10MHz	BD 239A...C, BD 241A...C, 2N4232...33



49545	MJ2250	MJ 2249, 80V	BD 239B...C, BD 241B...C, 2N4233
49546	MJ2251	-/225V, 0,5A, 10(Tc70°)	BUW 40A...B, 2N4298...99, 2SC1078, 2SC1810
49547	MJ2252	MJ 2251, -/300V	BUW 40A...B, 2N4298...99, 2SC1078, 2SC1810
49548	MJ2253	70V, 3A, 25W, >3MHz	BDX 14, BD 242A...C, BD 244A...C, 2N3741
49549	MJ2254	MJ 2253, 90V	BDX 14, BD 242B...C, BD 244B...C
49550	MJ2267	40V, 5A, 150W, >3MHz	BD 312, BD 314, BDW 22A...C, 2N5875...76
49551	MJ2267	40V, 5A, 150W, >3MHz	BD 312, BD 314, BDW 22A...C, 2N5875...76
49552	MJ2268	MJ 2268, 55V	BD 312, BD 314, BDW 22A...C, 2N5875...76
49553	MJ2268	MJ 2268, 55V	BD 312, BD 314, BDW 22A...C, 2N5875...76
49554	MJ2500	60V, 10A, 150W, B>1000	BDW 84A...D, BDX 64A...C, 2N6050...52
49555	MJ2500	60V, 10A, 150W, B>1000	BDW 84A...D, BDX 64A...C, 2N6050...52
49556	MJ2501	MJ 2500, 80V	BDW 84B...D, BDX 64B...C, 2N6051...52
49557	MJ2501	MJ 2500, 80V	BDW 84B...D, BDX 64B...C, 2N6051...52
49558	MJ2801	50V, 15A, 115W, >1MHz	BD 249(A...C), BD 745(A...D), BD 315
49559	MJ2801	50V, 15A, 115W, >1MHz	BD 249(A...C), BD 745(A...D), BD 315
49560	MJ2802	-/60V, 120W	BD 249A...C, BD 745A...D, BD 315
49561	MJ2802	-/60V, 120W	BD 249A...C, BD 745A...D, BD 315
49562	MJ2814	-/100V, 150W	BD 249C, BD 745C...D, BD 317
49563	MJ2814	-/100V, 150W	BD 249C, BD 745C...D, BD 317
49564	MJ2816	-/100V, 150W	BD 249C, BD 745C...D, BD 317
49565	MJ2816	-/100V, 150W	BD 249C, BD 745C...D, BD 317
49566	MJ2832	-/100V, 115W	BD 249C, BD 745C...D, BD 317
49567	MJ2832	-/100V, 115W	BD 249C, BD 745C...D, BD 317
49568	MJ2840	60V, 10A, 150W, >2MHz	BD 249A...C, BD 745A...D, BD 311
49569	MJ2840	60V, 10A, 150W, >2MHz	BD 249A...C, BD 745A...D, BD 311
49570	MJ2841	MJ 2840, 80V	BD 249B...C, BD 745B...D, BD 313
49571	MJ2841	MJ 2840, 80V	BD 249B...C, BD 745B...D, BD 313
49572	MJ2855	-/100V, 115W	BD 249C, BD 745C...D, BD 317
49573	MJ2855	-/100V, 115W	BD 249C, BD 745C...D, BD 317
49574	MJ2865	-/60V, 115W	BD 249A...C, BD 745A...D, BD 315
49575	MJ2865	-/60V, 115W	BD 249A...C, BD 745A...D, BD 315
49576	MJ2901	50V, 15A, 115W, >1MHz	BD 250(A...C), BD 746(A...C), BD 316
49577	MJ2901	50V, 15A, 115W, >1MHz	BD 250(A...C), BD 746(A...C), BD 316
49578	MJ2940	60V, 10A, 150W, >4MHz	BD 250A...C, BD 746A...C, BD 312
49579	MJ2940	60V, 10A, 150W, >4MHz	BD 250A...C, BD 746A...C, BD 312
49580	MJ2941	MJ 2940, 80V	BD 250B...C, BD 746B...D, BD 314
49581	MJ2941	MJ 2940, 80V	BD 250B...C, BD 746B...D, BD 314
49582	MJ2955	100V, 15A, 150W, >4MHz	BD 250C, BD 318, BD 746C...D, 2N6029...31
49583	MJ2955	100V, 15A, 150W, >4MHz	BD 250C, BD 318, BD 746C...D, 2N6029...31
49584	MJ3000	60V, 10A, 150W, B>1000	BDW 83A...D, BDX 65A...C, 2N6057...59
49585	MJ3000	60V, 10A, 150W, B>1000	BDW 83A...D, BDX 65A...C, 2N6057...59
49586	MJ3001	MJ 3000, 80V	BDW 83B...D, BDX 65B...C, 2N6058...59
49587	MJ3001	MJ 3000, 80V	BDW 83B...D, BDX 65B...C, 2N6058...59
49588	MJ3010	-/200V, 100W	BUW 71...72, BUX16(A...C), BUX 43...44
49589	MJ3010	-/200V, 100W	BUW 71...72, BUX16(A...C), BUX 43...44

49590	MJ3011	-/325V, 100W	BUW 71...72, BUX16(B...C), BUX 43...44
49591	MJ3011	-/325V, 100W	BUW 71...72, BUX16(B...C), BUX 43...44
49592	MJ3026	500/275V, 2A, 80W	BUS 11, BUX 82...83, 2SC1295, 2SC2962
49593	MJ3026	500/275V, 2A, 80W	BUS 11, BUX 82...83, 2SC1295, 2SC2962
49594	MJ3027	MJ 3026, 700/300V	BUS 11, BUX 82...83, 2SC1295, 2SC2962
49595	MJ3027	MJ 3026, 700/300V	BUS 11, BUX 82...83, 2SC1295, 2SC2962
49596	MJ3028	700/300V, 3,5A, 100W	BUS 11, BUX 82...83, 2SC2962, 2SD1098
49597	MJ3028	700/300V, 3,5A, 100W	BUS 11, BUX 82...83, 2SC2962, 2SD1098
49598	MJ3029	500/250V, 5A, 125W	BU 426(A), BU 526, 2SD418, 2SD807
49599	MJ3029	500/250V, 5A, 125W	BU 426(A), BU 526, 2SD418, 2SD807
49600	MJ3030	700/325V, 5A, 125W	BU 426(A), BU 526, BU 926, 2SC2122
49601	MJ3030	700/325V, 5A, 125W	BU 426(A), BU 526, BU 926, 2SC2122
49602	MJ3040	400/300V, 10A, 175W, B>100	MJ 10002, Mj 10003
49603	MJ3040	400/300V, 10A, 175W, B>100	MJ 10002, Mj 10003
49604	MJ3041	400/300V, 10A, 175W, B>250	MJ 10002, MJ 10003
49605	MJ3041	400/300V, 10A, 175W, B>250	MJ 10002, MJ 10003
49606	MJ3042	500/350V, 10A, 175W, B>250	MJ 10013, MJ 10014
49607	MJ3042	500/350V, 10A, 175W, B>250	MJ 10013, MJ 10014
49608	MJ3101	50V, 2A, 20W, >10MHz	BD 239(A...C), BD 241(A...C), 2N4231...33
49609	MJ3201	225/225V, 0,1A, 15W, >10MHz	2SC1505...1507, 2SC1755...1757, 2SC1819
49610	MJ3202	MJ 3201, 300/300V	2SC1505...1507, 2SC1755...1757, 2SC1819
49611	MJ3237	MJ 4237, 75W	MJE 5850...5852
49612	MJ3238	MJ 4238, 75W	MJE 5850...5852
49613	MJ3247	MJ 4247, 75W	BU 409, BUW 64A...C, BUX 60...61, 2SC2334
49614	MJ3248	MJ 4248, 75W	BU 409, BUW 64A...C, BUX 60...61, 2SC2334
49615	MJ3260	700/250V, 6A, 80W	BU 426(A), BU 526, BU 926, BUY 69A...B
49616	MJ3260	700/250V, 6A, 80W	BU 426(A), BU 526, BU 926, BUY 69A...B
49617	MJ3430	400/300V, 5A, 125W, >2,5MHz	BUW 71...72, BUX 16C, BUX 43...45
49618	MJ3480	1300/700V, 5A, 56W	BU 207...208(A), 2SC2928, 2SD350(A)
49619	MJ3520	40V, 15A, 150W, B>500	BDW 83(A...D), BDX 67(A...C), 2N6282...84
49620	MJ3521	100V, 15A, 150W, B>500	BDW 83C...D, BDX 67B...C, 2N6284
49621	MJ3583	250/175V, 1A, 35W, >10MHz	BUX 66A...C, 2N6211...14, 2N6421...23
49622	MJ3584	MJ 3583, 375/250V	BUX 66C, 2N6213...14, 2N6421...23
49623	MJ3585	MJ 3583, 500/300V	2N6422...6423
49624	MJ3701	50V, 3A, 25W, >3MHz	BD 242(A...C), BDX 14, 2N3740...3741
49625	MJ3738	250/225V, 0,5A, 20W, >10MHz	2N5344...45, 2SA1009(A), 2SA1236, 2SA1397
49626	MJ3739	MJ 3738, 325/300V	2N5345, 2SA1009(A), 2SA1236, 2SA1397
49627	MJ3760	750/550V, 6A, 80W	BU 426(A), BU 526, BU 926, 2SD1503
49628	MJ3761	MJ 3760, 8A	BU 526, BU 926
49629	MJ3771	2N3771, 200W	BDW 30, BDY 29, MJ 802
49630	MJ3772	2N3772, 200W	BDW 30, BDY 29, MJ 802
49631	MJ3773	2N3773, 200W	BDW 32, BDW 34, BDW 36
49632	MJ400	350V, 0,25A, 6,67W(Tc75°)	BUW 40, TIP 47...48, 2N4296...97, 2SD1263
49633	MJ4000	60V, 4A, 75W, B>1000	BDX 63A...C, MJ 1000...1001, 2N6055...56
49634	MJ4001	MJ 4000, 80V	BDX 63B...C, MJ 1001, 2N6056

49635	MJ4010	60V, 4A, 75W, B>1000	BDX 62A...C, MJ 900...901, 2N6053...54
49636	MJ4011	MJ 4010, 80V	BDX 62B...C, MJ 901, 2N6054
49637	MJ4030	60V, 16A, 150W, B>1000	BDV 66(A...D), BDW 84A...D, BDX 66(A...C)
49638	MJ4031	MJ 4030, 80V	BDV 66A...D, BDW 84B...D, BDX 66A...C
49639	MJ4032	MJ 4030, 100V	BDV 66A...D, BDW 84C...D, BDX 66B...C
49640	MJ4033	60V, 16A, 150W, B>1000	BDV 67(A...D), BDW 83A...D, BDX 67(A...C)
49641	MJ4034	MJ 4033, 80V	BDV 67A...D, BDW 83B...D, BDX 67A...C
49642	MJ4035	MJ 4033, 100V	BDV 67A...D, BDW 83C...D, BDX 67B...C
49643	MJ410	200/200V, 5A, 100W(Tc75°)	BUW 71...72, BUX 16B...C, BUX 17A...C
49644	MJ4101	50V, 25W, >4MHz	BD 243A...C, BD 543A...D, 2N4231...33(A)
49645	MJ411	MJ 410, 300/300V	BUW 71...72, BUX 16B...C, BUX 17A...C
49646	MJ413	400V, 10A, 125W, >2,5MHz	BUW 34, BUW 72, BUX 17B...C, BUX 43
49647	MJ420(S)	275V, 0,1A, 0,8W, >15MHz	BF 259, BF 659, BFS 89, 2N5058
49648	MJ421(S)	MJ 420, 350V	2SD593, BF 880...881, BF 759
49649	MJ423	400V, 10A, 125W, >2,5MHz	BUW 34, BUW 72, BUX 17B...C, BUX 43
49650	MJ4237	120V, 8A, 90W, >20MHz	BDX 20, MJE 15031, 2SB600
49651	MJ4238	MJ 4237, 150V	BDX 20, MJE 15031, 2SB600
49652	MJ424	700/350V, 5A, 100W(Tc75°)	BUS 12, BUW 26, BUW 35...36, BUX 47
49653	MJ4240	500/300V, 2A, 35W, >15MHz	2N6422...6423
49654	MJ4247	120V, 8A, 90W, >20MHz	BDX 11, 2N3442, MJE 15030, 2SD733
49655	MJ4248	MJ 4247, 150V	BDX 11, 2N3442, MJE 15030, 2SD733
49656	MJ425	MJ 424, 700/400V	BUS 12, BUW 26, BUW 35...36, BUX 47
49657	MJ431	400V, 10A, 125W, >2,5MHz	BUW 34, BUW 72, BUX 17B...C, BUX 43
49658	MJ432	-/400V, 125W, >2,5MHz	BUW 34, BUW 72, BUX 17B...C, BUX 43
49659	MJ4360	600/300V, 1,5A, 40W, >4MHz	BUV 36(A), BUW 40B, BUX 84, 2SC1828
49660	MJ4361	MJ 4360, 700/400V	BUV 36(A), BUX 84...85, 2SC1828
49661	MJ4380	600/300V, 4A, 75W, >4MHz	BUT 11(A), BUV 46(A), 2SC3036, 2SD841
49662	MJ4381	MJ 4380, 700/400V	BUT 11(A), BUV 46(A), 2SC3036, 2SD841
49663	MJ440	-/40V, 6W(Tc25°), >3MHz	-
49664	MJ450	40V, 30A, 150W, >2MHz	MJ 4502, 2N4398...4399
49665	MJ4502	100V, 30A, 200W, >2MHz	2N6377...6379
49666	MJ4645	200/200V, 0,5A, 5W(Tc25°)	BFT 19(A...B), 2N5415...5416, 2N5091
49667	MJ4646	MJ 4645, 300/300V	BFT 19A...B, 2N5416, 2N5091, 2N5093...94
49668	MJ4647	MJ 4645, 400/400V	BFT 19B, 2N5093...94
49669	MJ4648	MJ 4645, 435/350V	BFT 19B, 2N5416, 2N5093...94
49670	MJ480	40V, 4A, 87,5, >4MHz	BD 245, BD 311, BDV 91, BDW 21
49671	MJ481	MJ 480, 60V	BD 245A, BD 311, BDV 91, BDW 21A
49672	MJ490	40V, 4A, 87,5W, >4MHz	BD 246, BD 312, BDV 92, BDW 22
49673	MJ491	MJ 490, 60V	BD 246A, BD 312, BDV 92, BDW 22A
49674	MJ500	60V, 7A, 60W, >30MHz	2N6182...6189
49675	MJ501	MJ 500, 80V	2N6182...6189
49676	MJ5415	2N5415	2N5415
49677	MJ5416	2N5416	2N5416
49678	MJ6257	2N6257, 200W	2N6257
49679	MJ6302	2N6302, 200W	2N6302

49680	MJ6502	300/250V, 8A, 125W	BUW 22...23, BUW 32
49681	MJ6503	MJ 6502, 450/400V	BUW 23, BUW 32
49682	MJ6700	60V, 7A, 60W, >30MHz	2N6186...6189
49683	MJ6701	MJ 6700	2N6182...6185
49684	MJ7000	100V, 30A, 150W, >30MHz	2N2824...2825
49685	MJ7160	325/300V, 8A, 140W, >30MHz	BUW 24, BUW 72, BUX 17A...C, BUX 43
49686	MJ7161	MJ 7160, 425/400V	BUW 24, BUW 34, BUW 72, BUX 17C
49687	MJ7200	100V, 60A, 300W, >20MHz	2N6209...6311
49688	MJ7201	MJ 7200, 120V	2N6209...6311
49689	MJ7260	325/300V, 15A, 175W, >30MHz	BUV 25, BUW 44, BUX 13, BUX 25
49690	MJ7261	MJ 7260, 425/400V	BUV 25, BUW 44, BUX 25
49691	MJ802	100V, 30A, 200W, >2MHz	BDW 30, BDY 29, 2SD797
49692	MJ8100	60V, 5A, 10W(Tc25°), >30MHz	BUY 90, 2N6192...6193
49693	MJ8101	MJ 8100, 80V	BUY 90, 2N6192...6193
49694	MJ8400	-/600V, 4A, 125W	BU 208(A), BU 508(A), 2SD350(A)
49695	MJ8501	MJ 8500, 1400/800V	2SC3594
49696	MJ8502	1200/700V, 5A, 150W	2SC3060, 2SC3214, 2SC3343...3344
49697	MJ8503	MJ 8502, 1400/800V	2SC3594
49698	MJ8504	1200/700V, 10A, 175W	BUX 88, 2SC3061, 2SC3215
49699	MJ8505	MJ 8504, 1400/800V	BUX 88
49700	MJ900	60V, 8A, 90W, B>1000	BDX 62(A...C), BDV 64(A...C), 2N6053...54
49701	MJ9000	700/325V, 10A, 125W	2SD1279
49702	MJ901	MJ 901, 80V	BDX 62A...C, BDV 64A...C, 2N6054
49703	MJE101	40/40V, 5A, 75W	BD 244, BD 544, BD 796, BD 806
49704	MJE102	MJE 101, 60/60V	BD 244A, BD 544A, BD 798, BD 808
49705	MJE103	MJE 101, 80/60V	BD 244B, BD 544B, BD 800, BD 810
49706	MJE104	MJE 101, 80/80V	BD 244C, BD 544C, BD 802, BD 810
49707	MJE105	50V, 5A, 65W	BD 198, BD 206, 2N5974, 2N5980, 2SB579
49708	MJE105K	MJE 105	BD 244, BD 540A, BD 544, BD 948
49709	MJE105K	MJE 105	BD 244, BD 540A, BD 544, BD 948
49710	MJE1090	60V, 5A, 70W, B>750	BD 646, BD 898, BDW 24A, BDW 64A
49711	MJE1091	MJE 1090	BD 646, BD 898, BDW 24A, BDW 64A
49712	MJE1092	MJE 1090, 80V	BD 648, BD 900, BDW 24B, BDW 64B
49713	MJE1093	MJE 1090, 80V	BD 648, BD 900, BDW 24B, BDW 64B
49714	MJE1100	60V, 5A, 70W, B>750	BD 645, BD 897, BDW 23A, BDW 63A
49715	MJE1101	MJE 1100	BD 645, BD 897, BDW 23A, BDW 63A
49716	MJE1102	MJE 1100, 80V	BD 647, BD 899, BDW 23B, BDW 63B
49717	MJE1103	MJE 1100, 80V	BD 647, BD 899, BDW 23B, BDW 63B
49718	MJE12007	1500/750V, 2.5A, 65W	BU 505
49719	MJE1290	40V, 15A, 90W, >3MHz	BD 744, BD 906
49720	MJE1291	MJE 1290, 60V	BD 744A, BD 908
49721	MJE13002	MJ 4360	BUW 40B, BUX 84...85, 2SC3352
49722	MJE13003	MJ 4361	BUV 36A, BUX 84...85, 2SC3352
49723	MJE13004	MJ 4380	BUT 11(A), BUV 46(A), 2SC3086, 2SD841
49724	MJE13005	MJ 4381	BUT 11(A), BUV 46(A), 2SC3086, 2SD841

49725	MJE13006	600/300V, 8A, 80W, >4MHz	BUT 56(A), BUT 54, BUT 56(A), BUV 56(A)
49726	MJE13007	MJE 13006, 700/400V	BUT 54, BUT 56(A), BUV 56(A)
49727	MJE13007A	MJE 13006, 850/400V	BU 902...903, BU 908, BUT 56A, BUV 56A
49728	MJE13008	600/300V, 12A, 100W, >4MHz	BUV 66(A)
49729	MJE13009	MJE 13008, 700/400V	BUV 66(A)
49730	MJE13070	650/400V, 5A, 80W	BUT 11(A), BUT 18(A), BUV 46(A)
49731	MJE13071	MJE 13070, 750/450V	BUT 11(A), BUT 18(A), BUV 46(A)
49732	MJE15028	120V, 8A, 50W, >30MHz	2SC2527
49733	MJE15029	120V, 8A, 50W, >30MHz	2SA1077
49734	MJE15030	MJE 15028, 150V	-
49735	MJE15031	MJE 15029, 150V	-
49736	MJE16002	850/450V, 5A, 80W, B>5	BUT 11A, BUV 46A, MJE 8502...8503
49737	MJE16004	MJE 16002, B>7	BUT 11A, BUV 46A, MJE 8502...8503
49738	MJE1660	40V, 15A, 90W, >3MHz	BD 743, BD 905
49739	MJE1661	MJE 1660, 60V	BD 743A, BD 907
49740	MJE170	60V, 3A, 12.5W, >50MHz	BD 786, MJE 250...254
49741	MJE171	MJE 170, 80V	BD 788, BD 790, MJE 250...254
49742	MJE172	MJE 170, 100V	BD 792, MJE 253...254
49743	MJE180	60V, 3A, 12.5W, >50MHz	BD 785, MJE 240...244
49744	MJE18004	MJE 13004	MJE 13004
49745	MJE181	MJE 180, 80V	BD 787, BD 789, MJE 240...244
49746	MJE182	MJE 180, 100V	BD 791, MJE 243...244
49747	MJE1909	75V, 3A, PQ>4W(27MHz)	2SC1306, 2SC1816, 2SC1909, 2SC2092
49748	MJE200	40V, 5A, 15W, >65MHz	BDX 35...37, 2SC2594, 2SC3420, 2SD741
49749	MJE201	40/40V, 5A, 75W	BD 243, BD 543, BD 795, BD 805
49750	MJE2010	40V, 5A, 80W, >3MHz	BD 244, BD 540, BD 596, BD 948
49751	MJE2010	40V, 5A, 80W, >3MHz	BD 244, BD 540, BD 596, BD 948
49752	MJE2011	MJE 2010, 60V	BD 244A, BD 540A, BD 598, BD 950
49753	MJE2011	MJE 2010, 60V	BD 244A, BD 540A, BD 598, BD 950
49754	MJE202	MJE 201, 60/60V	BD 243A, BD 543A, BD 797, BD 807
49755	MJE2020	40V, 5A, 80W, >3MHz	BD 243, BD 539, BD 595, BD 947
49756	MJE2020	40V, 5A, 80W, >3MHz	BD 243, BD 539, BD 595, BD 947
49757	MJE2021	MJE 2020, 60V	BD 243A, BD 539A, BD 597, BD 949
49758	MJE2021	MJE 2020, 60V	BD 243A, BD 539A, BD 597, BD 949
49759	MJE203	MJE 201, 80/60V	BD 243B, BD 543B, BD 799, BD 809
49760	MJE204	MJE 201, 80/80V	BD 243C, BD 543C, BD 801, BD 809
49761	MJE205	50V, 5A, 65W	BD 197, BD 205, 2N5977, 2N5983, 2SD493
49762	MJE2050	45V, 5A, 15W	BDX 35...37, 2SC3420, 2SD826
49763	MJE205K	MJE 205	BD 243, BD 539, BD 543, BD 947
49764	MJE205K	MJE 205	BD 243, BD 539, BD 543, BD 947
49765	MJE2090	MJE 1090	BD 644, BD 896, BDW 24, BDW 64
49766	MJE2090	MJE 1090	BD 644, BD 896, BDW 24, BDW 64
49767	MJE2091	MJE 1091	BD 644, BD 896, BDW 24, BDW 64
49768	MJE2091	MJE 1091	BD 644, BD 896, BDW 24, BDW 64
49769	MJE2092	MJE 1092	BD 644A, BD 898, BDW 24A, BDW 64A



49770	MJE2092	MJE 1092	BD 644A, BD 898, BDW 24A, BDW 64A
49771	MJE2093	MJE 1093	BD 644A, BD 898, BDW 24A, BDW 64A
49772	MJE2093	MJE 1093	BD 644A, BD 898, BDW 24A, BDW 64A
49773	MJE210	40V, 5A, 15W, >65MHz	2SA1120, 2SA1357
49774	MJE2100	MJE 1100	BD 643, BD 895, BDW 23, BDW 63
49775	MJE2100	MJE 1100	BD 643, BD 895, BDW 23, BDW 63
49776	MJE2101	MJE 1101	BD 643, BD 895, BDW 23, BDW 63
49777	MJE2101	MJE 1101	BD 643, BD 895, BDW 23, BDW 63
49778	MJE2102	MJE 1102	BD 643A, BD 897, BDW 23A, BDW 63A
49779	MJE2102	MJE 1102	BD 643A, BD 897, BDW 23A, BDW 63A
49780	MJE2103	MJE 1103	BD 643A, BD 897, BDW 23A, BDW 63A
49781	MJE2103	MJE 1103	BD 643A, BD 897, BDW 23A, BDW 63A
49782	MJE2150	25V, 5A, 15W	2SA1120, 2SA1357
49783	MJE2160	-/300V, 1,5A, 50W	BUW 40(A...B), BUX 84...85, TIP 50
49784	MJE2160	-/300V, 1,5A, 50W	BUW 40(A...B), BUX 84...85, TIP 50
49785	MJE220	60V, 4A, 15W, >50MHz	BD 785, MJE 240...244
49786	MJE221	MJE 220	BD 785, MJE 240...244
49787	MJE222	MJE 220	BD 785, MJE 240...244
49788	MJE223	MJE 220, 80V	BD 787, BD 789, MJE 240...244
49789	MJE224	MJE 220, 80V	BD 787, BD 789, MJE 240...244
49790	MJE225	MJE 220, 80V	BD 787, BD 789, MJE 240...244
49791	MJE230	60V, 4A, 15W, >50MHz	BD 786, MJE 250...254
49792	MJE231	MJE 230	BD 786, MJE 250...254
49793	MJE232	MJE 230	BD 786, MJE 250...254
49794	MJE233	MJE 230, 80V	BD 788, BD 790, MJE 250...254
49795	MJE234	MJE 230, 80V	BD 788, BD 790, MJE 250...254
49796	MJE235	MJE 230, 80V	BD 788, BD 790, MJE 250...254
49797	MJE2360	375/350V, 0,5A, 30W, B>25	BUW 40(A...B), BUX 84...85, 2SD1263A
49798	MJE2360	375/350V, 0,5A, 30W, B>25	BUW 40(A...B), BUX 84...85, 2SD1263A
49799	MJE2360T	MJE 2360	BUW 40(A...B), BUX 84...85, 2SD1263A
49800	MJE2361	MJE 2360, B>50	BUW 40(A...B), BUX 84...85, 2SD1263A
49801	MJE2361	MJE 2360, B>50	BUW 40(A...B), BUX 84...85, 2SD1263A
49802	MJE2361T	MJE 2361	BUW 40(A...B), BUX 84...85, 2SD1263A
49803	MJE2370	40V, 3A, 40W, >3MHz	BD 242, BD 244, BD 576, BD 586
49804	MJE2370	40V, 3A, 40W, >3MHz	BD 242, BD 244, BD 576, BD 586
49805	MJE2371	MJE 2370, 60V	BD 242A, BD 244A, BD 578, BD 588
49806	MJE2371	MJE 2370, 60V	BD 242A, BD 244A, BD 578, BD 588
49807	MJE240	80V, 4A, 15W, >40MHz	BD 787, BD 789, BD 791, BDX 35...37
49808	MJE241	MJE 240	BD 787, BD 789, BD 791, BDX 35...37
49809	MJE242	MJE 240	BD 787, BD 789, BD 791, BDX 35...37
49810	MJE243	MJE 240, 100V	BD 791, BDX 35...37
49811	MJE244	MJE 240, 100V	BD 791, BDX 35...37
49812	MJE2480	40V, 4A, 60W, >2MHz	BD 243, BD 539, BD 585, BD 947
49813	MJE2480	40V, 4A, 60W, >2MHz	BD 243, BD 539, BD 585, BD 947
49814	MJE2481	MJE 2480, 60V	BD 243A, BD 539A, BD 587, BD 949



49815	MJE2481	MJE 2480, 60V	BD 243A, BD 539A, BD 587, BD 949
49816	MJE2482	MJE 2480	BD 243, BD 539, BD 585, BD 947
49817	MJE2482	MJE 2480	BD 243, BD 539, BD 585, BD 947
49818	MJE2483	MJE 2480, 60V	BD 243A, BD 539A, BD 587, BD 949
49819	MJE2483	MJE 2480, 60V	BD 243A, BD 539A, BD 587, BD 949
49820	MJE2490	40V, 3A, 60W	BD 242, BD 244, BD 576, BD 586
49821	MJE2490	40V, 3A, 60W	BD 242, BD 244, BD 576, BD 586
49822	MJE2491	MJE 2490, 60V	BD 242A, BD 244A, BD 578, BD 588
49823	MJE2491	MJE 2490, 60V	BD 242A, BD 244A, BD 578, BD 588
49824	MJE250	80V, 4A, 15W, >40MHz	BD 788, BD 790, BD 792
49825	MJE251	MJE 250	BD 788, BD 790, BD 792
49826	MJE252	MJE 250	BD 788, BD 790, BD 792
49827	MJE2520	40V, 3A, 40W, >3MHz	BD 241, BD 243, BD 575, BD 585
49828	MJE2520	40V, 3A, 40W, >3MHz	BD 241, BD 243, BD 575, BD 585
49829	MJE2521	MJE 2520, 60V	BD 241A, BD 243A, BD 577, BD 587
49830	MJE2521	MJE 2520, 60V	BD 241A, BD 243A, BD 577, BD 587
49831	MJE2522	MJE 2520	BD 241, BD 243, BD 575, BD 585
49832	MJE2522	MJE 2520	BD 241, BD 243, BD 575, BD 585
49833	MJE2523	MJE 2520, 60V	BD 241A, BD 243A, BD 577, BD 587
49834	MJE2523	MJE 2520, 60V	BD 241A, BD 243A, BD 577, BD 587
49835	MJE253	MJE 250, 100V	BD 792
49836	MJE254	MJE 250, 100V	BD 792
49837	MJE270	B>1500	BDT 61B...C, BDW 53C...D, 2SD837B
49838	MJE271	B>1500	BDT 60B...C, BDW 54C...D, 2SB751B
49839	MJE2801	60V, 10A, 90W	BD 207, MJE 3055, 2N5989...91, 2SD491
49840	MJE2801K	MJE 2801	BD 607, BD 707, BD 807
49841	MJE2801K	MJE 2801	BD 607, BD 707, BD 807
49842	MJE2801T	MJE 2801	BD 707, BD 743A, BD 807
49843	MJE29	40V, 1A, 30W, >3MHz	MJE 31, BD 239, BD 241, BD 933
49844	MJE2901	60V, 10A, 90W	BD 208, MJE 2955, 2N5986...88, 2SB578
49845	MJE2901K	MJE 2901	BD 608, BD 708, BD 808
49846	MJE2901K	MJE 2901	BD 608, BD 708, BD 808
49847	MJE2901T	MJE 2901	BD 708, BD 744A, BD 808
49848	MJE2955	BD 208	BD 208
49849	MJE2955K	BD 208	BD 608, BD 708, BD 808
49850	MJE2955K	BD 208	BD 608, BD 708, BD 808
49851	MJE2955T	BD 208	BD 708, BD 744A, BD 808
49852	MJE29A	MJE 29, 60V	MJE 31A, BD 239A, BD 241A, BD 935
49853	MJE29B	MJE 29, 80V	MJE 31B, BD 239B, BD 241B, BD 937
49854	MJE29C	MJE 29, 100V	MJE 31C, BD 239C, BD 241C, BD 937
49855	MJE30	40V, 1A, 30W, >3MHz	MJE 32, BD 240, BD 242, BD 934
49856	MJE3054	90V, 4A, 40W	BD 243B, BD 539C, BD 591, BD 953
49857	MJE3054	90V, 4A, 40W	BD 243B, BD 539C, BD 591, BD 953
49858	MJE3055	BD 207	BD 207
49859	MJE3055K	BD 207	BD 545A, BD 607, BD 707, BD 807

49860	MJE3055K	BD 207	BD 545A, BD 607, BD 707, BD 807
49861	MJE3055T	BD 207	BD 545A, BD 707, BD 743A, BD 807
49862	MJE30A	MJE 30, 60V	MJE 32A, BD 240A, BD 242A, BD 936
49863	MJE30B	MJE 30, 80V	MJE 32B, (BD 240B, BD 242B, BD 938)
49864	MJE30C	MJE 30, 100V	MJE 32C, (BD 240C, BD 242C, BD 938)
49865	MJE31	40V, 3A, 40W, >3MHz	BD 241, BD 243, BD 533, BD 933
49866	MJE31A	MJE 31, 60V	BD 241A, BD 243A, BD 535, BD 935
49867	MJE31B	MJE 31, 80V	BD 241B, BD 243B, BD 537, BD 937
49868	MJE31C	MJE 31, 100V	BD 241C, BD 243C, BD 937, 2SD712
49869	MJE32	40V, 3A, 40W, >3MHz	BD 242, BD 244, BD 534, BD934
49870	MJE32A	MJE 32, 60V	BD 242A, BD 244A, BD 536, BD936
49871	MJE32B	MJE 32, 80V	BD 242B, BD 244B, BD 538, BD938
49872	MJE32C	MJE 32, 100V	BD 242C, BD 244C, BD938, 2SB682
49873	MJE33	40V, 10A, 80W, >2MHz	BD 607, BD 705, BD 805
49874	MJE33	40V, 10A, 80W, >2MHz	BD 607, BD 705, BD 805
49875	MJE3300	B>1000	BD 675, BD 775, 2N6037...6039
49876	MJE3301	MJE 3300, 60V	BD 677, BD 777, 2N6038...6039
49877	MJE3302	MJE 3300, 80V	BD 679, BD 779, 2N6039
49878	MJE3310	B>1000	BD 676, BD 776, 2N6034...6036
49879	MJE3311	MJE 3310, 60V	BD 678, BD 778, 2N6035...6036
49880	MJE3312	MJE 3310, 80V	BD 680, BD 780, 2N6036
49881	MJE3370	MJE 370	BD 176, BD 186, BD 436, 2N5193...95
49882	MJE3371	MJE 371	BD 186, BD 438, 2N5193...95
49883	MJE33A	MJE 33, 60V	BD 607, BD 707, BD 807
49884	MJE33A	MJE 33, 60V	BD 607, BD 707, BD 807
49885	MJE33B	MJE 33, 80V	BD 609, BD 709, BD 809
49886	MJE33B	MJE 33, 80V	BD 609, BD 709, BD 809
49887	MJE33C	MJE 33, 100V	BD 711
49888	MJE33C	MJE 33, 100V	BD 711
49889	MJE34	40V, 10A, 80W, >2MHz	BD 608, BD 706, BD 806
49890	MJE34	40V, 10A, 80W, >2MHz	BD 608, BD 706, BD 806
49891	MJE340	-/300V, 0,5A, 20,8W, >10MHz	BD 410, 2SC2899, 2SC3051, 2SC3425
49892	MJE340K	MJE 340, 30W	BUW 40(A...B), TIP 49...50, 2SD1263A
49893	MJE340K	MJE 340, 30W	BUW 40(A...B), TIP 49...50, 2SD1263A
49894	MJE340T	MJE 340	BUW 40(A...B), TIP 49...50, 2SD1263A
49895	MJE341	175V, 0,5A, 20,8W, >15MHz	BD 410, MJE 340, 2SC2899, 2SC3051
49896	MJE341K	MJE 341, 30W	BUW 40(A...B), MJE 340K, TIP 49...50
49897	MJE341K	MJE 341, 30W	BUW 40(A...B), MJE 340K, TIP 49...50
49898	MJE3439	450/350V, 0,3A, 15W, >15MHz	BUX 86...87, 2SC2899
49899	MJE344	200V, 0,5A, 20,8W, >15MHz	BD 410, MJE 340, 2SC2899, 2SC3051
49900	MJE3440	MJE 3439, 350/350V	BUX 86...87, 2SC2899
49901	MJE344K	MJE 344, 30W	BUW 40(A...B), MJE 340K, TIP 49...50
49902	MJE344K	MJE 344, 30W	BUW 40(A...B), MJE 340K, TIP 49...50
49903	MJE345	325V, 0,5A, 20,8W, >15MHz	BD 410, MJE 340, 2SC2899, 2SC3051
49904	MJE34A	MJE 34, 60V	BD 608, BD 708, BD 808

49905	MJE34A	MJE 34, 60V	BD 608, BD 708, BD 808
49906	MJE34B	MJE 34, 80V	BD 610, BD 710, BD 810
49907	MJE34B	MJE 34, 80V	BD 610, BD 710, BD 810
49908	MJE34C	MJE 34, 100V	BD 712
49909	MJE34C	MJE 34, 100V	BD 712
49910	MJE350	-/300V, 0,5A, 20W	2SA1156
49911	MJE350T	MJE 350	MJE 5732, 2SA1009A, 2SA1236
49912	MJE3520	MJE 250	BD 175, BD 185, BD 435, 2N5190...92
49913	MJE3521	MJE 251	BD 185, BD 437, 2N5190...92
49914	MJE370	30V, 3A, 25W	BD 176, BD 186, BD 436, 2N5193...95
49915	MJE370K	MJE 370, 40W	BD 242, BD 244, BD 534, BD 934
49916	MJE370K	MJE 370, 40W	BD 242, BD 244, BD 534, BD 934
49917	MJE371	40V, 4A, 40W	BD 186, BD 438, 2N5193...5195
49918	MJE371K	MJE 371, 60W	BD 244, BD 534, BD 540, BD 948
49919	MJE371K	MJE 371, 60W	BD 244, BD 534, BD 540, BD 948
49920	MJE3738	250/225V, 0,5A, 30W, 10MHz	BUW 40(A...B), TIP 47...50, 2SD859(A)
49921	MJE3738	250/225V, 0,5A, 30W, 10MHz	BUW 40(A...B), TIP 47...50, 2SD859(A)
49922	MJE3739	MJE3738, 325/300V	BUW 40(A...B), TIP 47...50, 2SD859(A)
49923	MJE3739	MJE3738, 325/300V	BUW 40(A...B), TIP 47...50, 2SD859(A)
49924	MJE3740	60V, 4A, 40W, >4MHz	BD 244A, BD 540A, BD 588, BD 950
49925	MJE3740	60V, 4A, 40W, >4MHz	BD 244A, BD 540A, BD 588, BD 950
49926	MJE3741	MJE 3740, 80V	BD 244B, BD 540B, BD 590, BD 952
49927	MJE3741	MJE 3740, 80V	BD 244B, BD 540B, BD 590, BD 952
49928	MJE41	40V, 6A, 65W	BD 243, BD 543, BD 595, BD 795
49929	MJE41	40V, 6A, 65W	BD 243, BD 543, BD 595, BD 795
49930	MJE41A	MJE 41, 60V	BD 243A, BD 543A, BD 597, BD 797
49931	MJE41A	MJE 41, 60V	BD 243A, BD 543A, BD 597, BD 797
49932	MJE41B	MJE 41, 80V	BD 243B, BD 543B, BD 599, BD 799
49933	MJE41B	MJE 41, 80V	BD 243B, BD 543B, BD 599, BD 799
49934	MJE41C	MJE 41, 100V	BD 243C, BD 543C, BD 601, BD 801
49935	MJE41C	MJE 41, 100V	BD 243C, BD 543C, BD 601, BD 801
49936	MJE42	40V, 6A, 65W, >2MHz	BD 244, BD 544, BD 596, BD 796
49937	MJE42	40V, 6A, 65W, >2MHz	BD 244, BD 544, BD 596, BD 796
49938	MJE42A	MJE 42, 60V	BD 244A, BD 544A, BD 598, BD 798
49939	MJE42A	MJE 42, 60V	BD 244A, BD 544A, BD 598, BD 798
49940	MJE42B	MJE 42, 80V	BD 244B, BD 544B, BD 600, BD 800
49941	MJE42B	MJE 42, 80V	BD 244B, BD 544B, BD 600, BD 800
49942	MJE42C	MJE 42, 100V	BD 244C, BD 544C, BD 602, BD 802
49943	MJE42C	MJE 42, 100V	BD 244C, BD 544C, BD 602, BD 802
49944	MJE4340	100V, 16A, 125W, >1MHz	BD 249C...F, BD 745C...F
49945	MJE4341	MJE 4340, 120V	BD 249D...F, BD 745D...F
49946	MJE4342	MJE 4340, 140V	BD 249D...F, BD 745E...F, 2SC3263
49947	MJE4343	MJE 4340, 160V	BD 249D...F, BD 745F, 2SC3263
49948	MJE4350	100V, 16A, 125W, >1MHz	BD 250C...F, BD 746C...F
49949	MJE4351	MJE 4350, 120V	BD 250D...F, BD 746D...F

49950	MJE4352	MJE 4350, 140V	BD 250D...F, BD 746E...F, 2SA1294
49951	MJE4353	MJE 4350, 160V	BD 250D...F, BD 746F, 2SA1294
49952	MJE47	350/250V, 1,5A, 50W, >5MHz	BUW 40(A...B), TIP 47...50, BUX 84
49953	MJE47	350/250V, 1,5A, 50W, >5MHz	BUW 40(A...B), TIP 47...50, BUX 84
49954	MJE48	MJE 47, 400/300V	BUW 40(A...B), TIP 48...50, BUX 84
49955	MJE48	MJE 47, 400/300V	BUW 40(A...B), TIP 48...50, BUX 84
49956	MJE488	50V, 5A, 40W	BD 187, BD 439, 2N5191...5192
49957	MJE49	MJE 47, 450/350V	BUW 40(A...B), TIP 49...50, BUX 84
49958	MJE49	MJE 47, 450/350V	BUW 40(A...B), TIP 49...50, BUX 84
49959	MJE4918	2N4918, 40W	BD 240, BD 242, BD 576, BD 586
49960	MJE4918	2N4918, 40W	BD 240, BD 242, BD 576, BD 586
49961	MJE4919	2N4919, 40W	BD 240A, BD 242A, BD 578, BD 588
49962	MJE4919	2N4919, 40W	BD 240A, BD 242A, BD 578, BD 588
49963	MJE4920	2N4920, 40W	BD 240B, BD 242B, BD 580, BD 590
49964	MJE4920	2N4920, 40W	BD 240B, BD 242B, BD 580, BD 590
49965	MJE4921	2N4921, 40W	BD 239, BD 241, BD 575, BD 585
49966	MJE4921	2N4921, 40W	BD 239, BD 241, BD 575, BD 585
49967	MJE4922	2N4922, 40W	BD 239A, BD 241A, BD 577, BD 587
49968	MJE4922	2N4922, 40W	BD 239A, BD 241A, BD 577, BD 587
49969	MJE4923	2N4923, 40W	BD 239B, BD 241B, BD 579, BD 589
49970	MJE4923	2N4923, 40W	BD 239B, BD 241B, BD 579, BD 589
49971	MJE51	350/250V, 5A, 80W, >2,5MHz	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
49972	MJE51	350/250V, 5A, 80W, >2,5MHz	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
49973	MJE5170	120V, 6A, 65W, >1MHz	BD 244C...F, MJE 15029, MJE 15031
49974	MJE5171	MJE 5170, 140V	BD 244D...F, MJE 15031
49975	MJE5172	MJE 5170, 160V	BD 244E...F, MJE 15031
49976	MJE5180	120V, 6A, 65W, >1MHz	BD 243C...F, MJE 15028, MJE 15030
49977	MJE5181	MJE 5180, 140V	BD 243D...F, MJE 15030
49978	MJE5182	MJE 5180, 160V	BD 243E...F, MJE 15030
49979	MJE5190	2N5190, 60W	BD 243, BD 533, BD 539, BD 585
49980	MJE5190	2N5190, 60W	BD 243, BD 533, BD 539, BD 585
49981	MJE5190J	2N5190	2N5190
49982	MJE5191	2N5191, 60W	BD 243A, BD 535, BD 539A, BD 587
49983	MJE5191	2N5191, 60W	BD 243A, BD 535, BD 539A, BD 587
49984	MJE5191J	2N5191	2N5191
49985	MJE5192	2N5192, 60W	BD 243B, BD 537, BD 539B, BD 589
49986	MJE5192	2N5192, 60W	BD 243B, BD 537, BD 539B, BD 589
49987	MJE5192J	2N5192	2N5192
49988	MJE5193	2N5193, 60W	BD 244, BD 534, BD 540, BD 586
49989	MJE5193	2N5193, 60W	BD 244, BD 534, BD 540, BD 586
49990	MJE5194	2N5194, 60W	BD 244A, BD 536, BD 540A, BD 588
49991	MJE5194	2N5194, 60W	BD 244A, BD 536, BD 540A, BD 588
49992	MJE5195	2N5195, 60W	BD 244B, BD 538, BD 540B, BD 590
49993	MJE5195	2N5195, 60W	BD 244B, BD 538, BD 540B, BD 590
49994	MJE51T	MJE 51	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518

49995	MJE52	MJE 51, 400/300V	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
49996	MJE520	30V, 3A, 25W	BD 177, BD 185, BD 435, 2N5190...92
49997	MJE520K	MJE 520, 40W	BD 241, BD 243, BD 533, BD 933
49998	MJE520K	MJE 520, 40W	BD 241, BD 243, BD 533, BD 933
49999	MJE521	40V, 4A, 40W	BD 185, BD 437, 2N5190...5192
50000	MJE521K	MJE 521, 60W	BD 243, BD 533, BD 539, BD 947
50001	MJE521K	MJE 521, 60W	BD 243, BD 533, BD 539, BD 947
50002	MJE52T	MJE 52	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
50003	MJE53	MJE 51, 450/350V	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
50004	MJE53T	MJE 53	BUT 11(A), BUV 46(A), 2SC2440, 2SC2518
50005	MJE5655	2N5655, 30W	BUW 40(A...B), TIP 47...50, 2SD1263(A)
50006	MJE5655	2N5655, 30W	BUW 40(A...B), TIP 47...50, 2SD1263(A)
50007	MJE5656	2N5656, 30W	BUW 40(A...B), TIP 47...50, 2SD1263(A)
50008	MJE5656	2N5656, 30W	BUW 40(A...B), TIP 47...50, 2SD1263(A)
50009	MJE5657	2N5657, 30W	BUW 40(A...B), TIP 48...50, 2SD1263A
50010	MJE5657	2N5657, 30W	BUW 40(A...B), TIP 48...50, 2SD1263A
50011	MJE5730	300/300V, 1A, 40W, >10MHz	2SA1009(A)
50012	MJE5731	MJE 5730, 350/350V	2SA1009(A)
50013	MJE5732	MJE 5730, 400/400V	2SA1009A
50014	MJE5740	600/300V, 8A, 80W, B>200	BUD 47(A)
50015	MJE5741	MJE 5740, 700/350V	BUD 47(A)
50016	MJE5742	MJE 5740, 800/400V	BUD 47(A)
50017	MJE5850	350/300V, 8A, 80W	-
50018	MJE5851	MJE 5850, 400/350V	-
50019	MJE5852	MJE 5850, 450/400V	-
50020	MJE5974	2N5974	BD 244A, BD 544A, BD 598, BD 798
50021	MJE5975	2N5975	BD 244B, BD 544B, BD 600, BD 800
50022	MJE5976	2N5976	BD 244C, BD 544C, BD 602, BD 802
50023	MJE5977	2N5977	BD 243A, BD 543A, BD 597, BD 797
50024	MJE5978	2N5978	BD 243B, BD 543B, BD 599, BD 799
50025	MJE5979	2N5979	BD 243C, BD 543C, BD 601, BD 801
50026	MJE5980	2N5980	BD 544A, BD 598, BD 798, BD 808
50027	MJE5981	2N5981	BD 544B, BD 600, BD 800, BD 810
50028	MJE5982	2N5982	BD 544C, BD 602, BD 802
50029	MJE5983	2N5983	BD 543A, BD 597, BD 797, BD 807
50030	MJE5984	2N5984	BD 543B, BD 599, BD 799, BD 809
50031	MJE5985	2N5985	BD 543C, BD 601, BD 801
50032	MJE6040	2N6040	BD 646, BD 898, BDW 74A, BDX 54A
50033	MJE6041	2N6041	BD 648, BD 900, BDW 74B, BDX 54B
50034	MJE6042	2N6042	BD 650, BD 902, BDW 74C, BDX 54C
50035	MJE6043	2N6043	BD 645, BD 897, BDW 73A, BDX 53A
50036	MJE6044	2N6044	BD 647, BD 899, BDW 73B, BDX 53B
50037	MJE700	60V, 4A, 40W, B>750	BD 678, BD 778, 2N6035...6036
50038	MJE700T	MJE 700, 50W	BD 716, BDW 24A, BDW 54A, BDW 64A
50039	MJE701	MJE 700	BD 678, BD 778, 2N6035...6036

50040	MJE701T	MJE 701, 50W	BD 716, BDW 24A, BDW 54A, BDW 64A
50041	MJE702	MJE 700, 80V	BD 680, BD 780, 2N6036
50042	MJE702T	MJE 702, 50W	BD 718, BDW 24B, BDW 54B, BDW 64B
50043	MJE703	MJE 700, 80V	BD 680, BD 780, 2N6036
50044	MJE703T	MJE 703, 50W	BD 718, BDW 24B, BDW 54B, BDW 64B
50045	MJE710	BD 166	BD 166
50046	MJE711	BD 168	BD 168
50047	MJE712	BD 170	BD 170
50048	MJE720	BD 165	BD 165
50049	MJE721	BD 167	BD 167
50050	MJE722	BD 169	BD 169
50051	MJE800	60V, 4A, 40W, B>750	BD 677, BD 777, 2N6038...6039
50052	MJE800T	MJE 800, 50W	BD 715, BDW 23A, BDW 53A, BDW 63A
50053	MJE801	MJE 800	BD 677, BD 777, 2N6038...6039
50054	MJE801T	MJE 801, 50W	BD 715, BDW 23A, BDW 53A, BDW 63A
50055	MJE802	MJE 800, 80V	BD 679, BD 779, 2N6039
50056	MJE802T	MJE 802, 50W	BD 717, BDW 23B, BDW 53B, BDW 63B
50057	MJE803	MJE 800, 80V	BD 679, BD 779, 2N6039
50058	MJE803T	MJE 803, 50W	BD 717, BDW 23B, BDW 53B, BDW 63B
50059	MJE8500	1200/700V, 2,5A, 65W	BU 505, 2SC3178
50060	MJE8501	MJE 8500, 1400/800V	BU 505
50061	MJE8502	1200/700V, 5A, 80W	BU 506, 2SC3050
50062	MJE8503	MJE 8502, 1400/800V	BU 506
50063	MJE9450	BD 136	BD 136
50064	MJH12004	MJ 12004	BU 508(A), BU 706, BU 908, 2SD1496...97
50065	MJH13090	MJ 13090	BUV 48(A), BUW 13(A), BUW 133(A)
50066	MJH13091	MJ 13091	BUV 48(A), BUW 13(A), BUW 133(A)
50067	MJH16002	MJE 16002	BUW 11(A), BUV 82...83, BUW 131(A)
50068	MJH16002A	MJ 16002A	BUW 11A, BUV 83, BUV 89, BUW 131A
50069	MJH16004	MJE 16004	BUW 11(A), BUV 82...83, BUW 131(A)
50070	MJH16006	MJ 16006	BUW 12(A), BUV 47(A), 2SC3637
50071	MJH16006A	MJ 16006A	BUW 12A, BUV 47A, BUV 70...71, 2SC4023
50072	MJH16008	MJ 16008	BUW 12(A), BUV 47(A), 2SC3637
50073	MJH16010	MJ 16010	BUW 13(A), BUV 48(A), BUW 133(A)
50074	MJH16010A	MJ 16010A	BUW 13A, BUV 48A, BUW 133A, 2SC3552
50075	MJH16012	MJ 16012	BUW 13(A), BUV 48(A), BUW 133(A)
50076	MJH16018	MJ 16018	BUV 71, 2SC4023, 2SC3688
50077	MK	2SC4842	2SC4842
50078	MK	BF 997	BF 997
50079	MK	2SC4315	2SC4315
50080	MK	P6 SMB-56A	P6 SMB-56A
50081	MK	MA 28W-B	MA 28W-B
50082	MK	2SB799-MK	2SB799
50083	MK	SM 6T 22CA	SM 6T...
50084	ML	P6 SMB-62	P6 SMB-62



50085	ML	2SA1519	2SA1519
50086	ML	MA 28T-A	MA 28T-A
50087	ML	2SB799-ML	2SB799
50088	ML	SM 6T 24C	SM 6T...
50089	MLD1N06CL	59..65V, 2	
50090	MLD2N06CL	58..66V, 3	
50091	MLP1N06CL	MLD 1N06CL	-
50092	MLP2N06CL	MLD 2N06CL	-
50093	MM	P6 SMB-62A	P6 SMB-62A
50094	MM	MA 28T-B	MA 28T-B
50095	MM	2SB799-MM	2SB799
50096	MM	SM 6T 24CA	SM 6T...
50097	MM1139	550MHz	AF 109(R), AF 139, AF 239(S)
50098	MM1500	PQ>0,25W(1500MHz)	-
50099	MM1500A	MM 1500	-
50100	MM1501	PQ>0,15W(1500MHz)	-
50101	MM1505	15V, 0,05A, 0,3W, <12/12ns	BSV 89...92, BSX 27, BSX 44, 2N3011
50102	MM1549	2N5635	
50103	MM1550	2N5636	
50104	MM1551	2N5637	
50105	MM1557	2N5641	
50106	MM1558	2N5642	
50107	MM1559	2N5643	
50108	MM1605	>2GHz	BFR 15, BFS 55, BFT 66...67
50109	MM1606	>2GHz	BFR 15, BFS 55, BFT 66...67
50110	MM1607	>1,7GHz	BFR 15, BFS 55, BFT 66...67
50111	MM1613	60V, 0,2A, 0,8W, 26/70ns	BSS 27, BSV 77, BSV 95, 2SC1385
50112	MM1614	60V, 0,2A, 0,8W, 26/70ns	2N3468
50113	MM1619	48V, 3,5A	-
50114	MM1620	48V, 7A	-
50115	MM1711	60V, 0,8W, 26/70ns	BSS 27, BSV 77, BSV 95, 2SC1385
50116	MM1712	-/40V, >200MHz	2N3468
50117	MM1748(A)	15V, 0,15A, 0,3W, 12/12ns	BSS 11...12, BSX 27, 2N2368...69(A)
50118	MM1756	75V, >250MHz, <35/285ns	BSW 63...64, 2N2221A...2222A
50119	MM1757	60V, >250MHz	BSW 61...64, 2N2221...2222(A)
50120	MM1758	75V, >300MHz, <35/285ns	BSW 63...64, 2N2221A...2222A
50121	MM1803	50V, 0,15A, >500MHz	BFR 36, BFW 16, 2N3866, 2N4428
50122	MM1812	175/175V, 0,1A, 5W(Tc25°)	-
50123	MM1941	30V, 0,2A, PQ>0,1W(175MHz)	BFR 36, BFX 55
50124	MM1943	40V, 0,2A, 0,3W, >500MHz	BSS 11, BSX 19...20, 2N2369...69(A)
50125	MM2005-2	25V, 0,6A, 0,4W, 300MHz	BC 327...328, BC 636, BC 638, BC 640
50126	MM2090	3N124	
50127	MM2091	3N125	
50128	MM2092	3N126	
50129	MM2102	25V, <70/850ns	-

50130	MM2103	25V, <80/850ns	-
50131	MM2193A	80V, 1W, <-/200ns	BSW 39, 2N3444
50132	MM2258	120V, 0,5A, 1W, >150MHz	BC 300, 2N1893, 2SD413, 2SD624, 2SD576
50133	MM2259	MM 2258, 175V, 0,3A	BFR 58...59, 2SD576
50134	MM2260	MM 2258, 175V, 0,3A	BFR 58...59, 2SD576
50135	MM2261	60V, 1A, 1W, >100MHz	BC 140...141, 2N1990, 2N2102, 2N2405
50136	MM2262	MM 2261, 100V	BC 141, 2N1990, 2N2102, 2N2405
50137	MM2263	MM 2261, 150V	2N3019...3020, 2SC1860
50138	MM2264	-/25V, 1,5A, 1,1W, >50MHz	BC 440, BC 441, BCX 40, 2N4237...4239
50139	MM2270	60V, 1A, 1W, >100MHz	BC 140...141, 2N1990, 2N2102, 2N2405
50140	MM2503	>1000MHz	AF 379
50141	MM2550	20V, 0,1A, 0,16W, <2,5/2,5ns	-
50142	MM2552	20V, 0,1A, 0,3W, <3,5/2,5ns	-
50143	MM2554	20V, 0,2A, 0,3W, <3,5/2,5ns	-
50144	MM2613	60V, 0,5W, 26/70ns	BSS 26, BSW 61...64, 2N2221...2222(A)
50145	MM2614	60V, 0,5W, 26/70ns	BSW 24, 2N2906...2907(A), 2N4026...4029
50146	MM3000	-/100V, 0,2A, 1W, >150V	BC 300, BFR 57...59, 2N1890, 2N1893
50147	MM3001	MM 3000, -/150V	BFR 57...59, 2SD413, 2SD 624
50148	MM3002	MM 3000, -/200V, 0,05A	BF 258...259, BF 658...659, 2N5058...59
50149	MM3003	MM 3000, -/250V, 0,05A	BF 259, BF 659, BFS 89, 2N5058
50150	MM3004	-/25V, 1,5A, 1,1W, >50MHz	BC 440...441, BCX 40, 2N4237...4239
50151	MM3005	80V, 2,5A, 1W, >50MHz	BFT 32...34, 2N4238...39, 2N5336...39
50152	MM3006	MM 3005, 100V	BFT 33...34, 2N4239, 2N5338...39
50153	MM3007	MM 3005, 120V	BFT 34, 2N4895...4896
50154	MM3008	-/120V, 0,4A, 1W, >50MHz	2SD576, BF 380...382, BF 757...759
50155	MM3009	-/120V, 0,4A, 1W, >50MHz	2SD576, BF 380...382, BF 757...759
50156	MM3220	50V, 1A, 1W, <35/50ns	BSS 27...29, BSV 77, 2N3724A, 2N5189
50157	MM3375(A)	2N3375(A)	
50158	MM3724	-/30V, 1,5A, 1W, <30/50ns	BSS 14, 2N3724...3725, 2N5262
50159	MM3725	80/40V, 0,5A, 1W, <35/60ns	BSS 14, 2N3725, 2N5262
50160	MM3726	-/50V, 1,5A, 1W, <30/90ns	BSV 82
50161	MM380	600MHz	AF 139, AF 239(S)
50162	MM4000	100V, 0,1A, 0,6W	2N3634...3637, 2N5415
50163	MM4001	150V, 0,5A, 1W	2N3636...3637, 2N5415
50164	MM4002	200V, 0,5A, 1W	BFT 44...45, 2N5415...5416, 2SB606
50165	MM4003	250V, 0,5A, 1W	BFT 44...45, 2N5416, 2SB606
50166	MM4005	60V, 1A, 1W, 250MHz	BC 161, BC 461, BCX 60, 2N4235...36
50167	MM4006	MM 4005, 80V	BCX 60, BSW 40, 2N4041, 2N4033, 2N4236
50168	MM4007	MM 4005, 100V	BCX 60, BSS 17, BSW 40, 2N3634...35
50169	MM4008	60V, 0,5A, 0,6W, 325MHz	BC 161, BC 303...304, 2N2904...05
50170	MM4009	MM 4008, 80V, 150MHz	BC 303, BSW 40, 2N4031, 2N4033, 2N4036
50171	MM4010	MM 4008, 100V, 150MHz	BSS 17, BSW 40, 2N3634...35
50172	MM4018	40V, 0,4A, PQ>0,5W(175MHz)	2N5160
50173	MM4019	60V, 1A, PQ>2,5W(175MHz)	-
50174	MM4020	36V, 1A	-

50175	MM4021	36V, 2,5A	-
50176	MM4022	36V, 4A	-
50177	MM4023	36V, 6A	-
50178	MM404(A)	190/300ns	2N2955...57, (ASY 76...77)
50179	MM4048	45V, 0,05A, 0,36W, >100MHz	BC 214, BC 415...416, BC 560
50180	MM4049	15V, 0,03A, >4GHz	BFQ 23...24, BFQ 56, BFQ 75...76
50181	MM4052	30V, 0,5A, 0,5W	-
50182	MM420	275V, 0,1A, 0,8W, >15MHz	BF 259, BF 659, BFS 89, 2N5058
50183	MM421	MM 420, 350V	BF 880...881, BF 850, 2SC3418
50184	MM4261H	2N4261	-
50185	MM439	1000MHz	BF 272, BF 316, BF 516, BF 606, BFR 38
50186	MM4404(A)	40V, 0,25A, 0,15W	-
50187	MM4429	2N4429	
50188	MM4430	2N4430	
50189	MM4545	200/200V, 2,5A, 25W, >40MHz	2SA1009(A), 2SA1236, 2SA1397, 2SB630
50190	MM4546	MM 4545, 300/300V	2SA1009(A), 2SA1236, 2SA1397
50191	MM4547	MM 4545, 400/400V	2SA1009A, 2SA1236, 2SA1397
50192	MM4645	MM 4545, 5W	2SA1009(A), 2SA1236, 2SA1397, 2SB630
50193	MM4646	MM 4546, 5W	2SA1009(A), 2SA1236, 2SA1397
50194	MM4647	MM 4547, 5W	2SA1009A, 2SA1236, 2SA1397
50195	MM5000	>800MHz	AF 139, AF 239(S)
50196	MM5001	>800MHz	AF 139, AF 239(S)
50197	MM5002	>800MHz	AF 139, AF 239(S)
50198	MM5005	80V, 2A, 1,5W, >30MHz	BCX 60, BSS 17...18, 2N4236, 2N5322...23
50199	MM5006	MM 5005, 100V	BCX 60, BFT 36...37, BSS 17, 2N5322
50200	MM5007	MM 5005, 120V	BFT 37
50201	MM5043	2N5043	
50202	MM5044	2N5044	
50203	MM709	15V, 0,1A, >300MHz, <12/10ns	BSV 89...92, BSX 27, BSX 44, 2N2475
50204	MM8000	40V, 0,4A, >700MHz	BFQ 42, BFR 98, BLW 16, BLY 61
50205	MM8001	MM 8000, >900MHz	BFS 50, MRF 515, MRF 629, 2N3948
50206	MM8002	40V, 0,4A, >1200MHz	BFS 50, MRF 515, MFR 629, 2N3948
50207	MM8003	MM 8002	BLW 79, BLX 67, BLY 38, 2N5945
50208	MM8006	>1000MHz	BF 377...378, BF 689, BF 763, BFW 99
50209	MM8007	>1000MHz	BF 377...378, BF 689, BF 763, BFW 99
50210	MM8008	35V, 0,1A, PQ>0,3W(2GHz)	BFG 34, BFR 95
50211	MM8009	45V, 0,4A, PQ>0,9W(1GHz)	BLX 91, 2N4429, 2N6268
50212	MM8010	MM 8008, PQ>0,2W(2GHz)	BFG 34, BFR 95
50213	MM8011	MM 8008, PQ>0,1W(2GHz)	BFG 34, BFR 95
50214	MM8012	2N5947	
50215	MM869B	30V 0,2A, 0,36W, 10/60ns	BSS 11...12, BSX 19...20, 2N2368...69
50216	MMBD101	MBD 101, SMD	BAT 17
50217	MMBD1201	50V, 0,2A, <4ns	BAR 74
50218	MMBD1203	MMBD 1201	-
50219	MMBD1204	MMBD 1201	MMBD 2838

50220	MMBD1205	MMBD 1201	MMBD 2836
50221	MMBD1401	175V, 0,2A, <50ns	BAS 20...21, 1SS250
50222	MMBD1403	MMBD 1401	-
50223	MMBD1404	MMBD 1401	-
50224	MMBD1405	MMBD 1401	-
50225	MMBD1501(A)	180V, 0,2A	BAS 20...21, 1SS250
50226	MMBD1503(A)	MMBD 1501	-
50227	MMBD1504(A)	MMBD 1501	-
50228	MMBD1505(A)	MMBD 1505	-
50229	MMBD1701(A)	20V, 0,05A, 0,7ns	-
50230	MMBD1703(A)	MMBD 1701	-
50231	MMBD1704(A)	MMBD 1701	-
50232	MMBD1705(A)	MMBD 1701	-
50233	MMBD201	MBD 201, SMD	-
50234	MMBD2835	35V, 0,1A, <4ns	1S2835
50235	MMBD2836	MMBD 2835, 75V	1S2836
50236	MMBD2837	MMBD 2835	1S2837
50237	MMBD2838	MMBD 2835, 75V	1S2838
50238	MMBD301	MBD 301, SMD	-
50239	MMBD352	UHF-M, 7V	-
50240	MMBD353	MMBD 352	-
50241	MMBD354	MMBD 352	-
50242	MMBD4148	75V, 0,2A, <4ns, (1N4148)	FMMD 914, MMBD 914, PMBD 914
50243	MMBD4148CA	MMBD 4148	MMBD 2836
50244	MMBD4148CC	MMBD 4148	MMBD 2838
50245	MMBD4148SE	MMBD 4148	-
50246	MMBD6050	70V, 0,2A, <4ns	-
50247	MMBD6100	MMBD 6050	-
50248	MMBD7000	Mot, <15ns	
50249	MMBD914	1N914, SMD	FMMD 914, PMBD 914
50250	MMBF170	BS 170, SMD	BSS 145, BST 82
50251	MMBF4117	2N4117, SMD	-
50252	MMBF4118	2N4118, SMD	-
50253	MMBF4119	2N4119, SMD	-
50254	MMBF4416	2N4416, SMD	-
50255	MMBF4856	2N4856, SMD	-
50256	MMBF4860	2N4860, SMD	BSR 57
50257	MMBF5461	2N5461, SMD	-
50258	MMBF5485	2N5485, SMD	BFR 30
50259	MMBFJ111	J 111, SMD	-
50260	MMBFJ112	J 112, SMD	-
50261	MMBFJ113	J 113, SMD	-
50262	MMBFJ174	J 174, SMD	-
50263	MMBFJ175	J 175, SMD	-
50264	MMBFJ176	J 176, SMD	-

50265	MMBFJ177	J 177, SMD	-
50266	MMBFJ201	J 201, SMD	-
50267	MMBFJ202	J 202, SMD	2SK1682
50268	MMBFJ211	J 211, SMD	2SK322
50269	MMBFJ212	J 212, SMD	-
50270	MMBFU310	U 310, SMD	-
50271	MMBPU131	2N6116	2N6116
50272	MMBR2060	30V, 50mA, 1GHz	BFR 53, 2SC3014, 2SC3773
50273	MMBR2857	30V, 40mA, >1GHz	BFR 53, 2SC3014, 2SC3773
50274	MMBR4957	30V, 30mA, 1,2GHz	BFT 93, 2SA1424
50275	MMBR5031	15V, 20mA, 1GHz	BF 517, BFT 25, BFQ 29, 2SC3098
50276	MMBR5179	20V, 50mA, 900MHz	BF 771, BF 775, 2SC3014, 2SC3016
50277	MMBR536	MPS 536, SMD	BFT 93
50278	MMBR571	MPS 571, SMD, 8GHz	2SC3445, 2SC3704, 2SC3937
50279	MMBR901	25V, 30mA, 4GHz	BFQ 29, BFQ 81, BFR 93, BFT 75
50280	MMBR911	MPS 911, SMD	BFR 193, 2SC3356, 2SC3445
50281	MMBR920	20V, 35mA, 4,5GHz	BFR 93, BFT 75
50282	MMBR930	15V, 35mA, 5,5GHz	BF 770A, 2SC3011, 2SC3513
50283	MMBR931	10V, 5mA, 3GHz	BFR 92, 2SC3099, 2SC3110
50284	MMBR941	MRF 941, SMD	BFQ 67, BFR 193, 2SC3445, 2SC3904
50285	MMBR951	MRF 951, SMD	2SC3356
50286	MMBS5060	2N5060, SMD	-
50287	MMBS5061	2N5061, SMD	-
50288	MMBS5062	2N5062, SMD	-
50289	MMBT100(A)	PN 100(A), SMD	BCW 66, MMBTA 06, 2SD1782
50290	MMBT101	PN 101, SMD	BCW 66, MMBTA 06, 2SD1782
50291	MMBT200(A)	PN 200(A), SMD	BCW 68, MMBTA 56, 2SB1198
50292	MMBT201	PN 201, SMD	BCW 68, MMBTA 56, 2SB1198
50293	MMBT2218(A)	2N2218(A), SMD	BSS 79, BSS 81, PMBT 2222, SMBT 2222
50294	MMBT2219(A)	2N2219(A), SMD	BSS 79, BSS 81, PMBT 2222, SMBT 2222
50295	MMBT2221(A)	2N2221(A), SMD	BSS 79, BSS 81, PMBT 2222, SMBT 2222
50296	MMBT2222(A)	2N2222(A), SMD	BSS 79, BSS 81, PMBT 2222, SMBT 2222
50297	MMBT2369(A)	2N2369(A), SMD	PMBT 2369, 2SC4168, 2SC4453
50298	MMBT2484	2N2484, SMD	2SC3323...24
50299	MMBT2710	2N2710, SMD	-
50300	MMBT2904(A)	2N2904(A), SMD	BSR 15, BSS 82, PMBT 2907, SMBT 2907
50301	MMBT2905(A)	2N2905(A), SMD	BSR 15, BSS 82, PMBT 2907, SMBT 2907
50302	MMBT2906(A)	2N2906(A), SMD	BSR 15, BSS 82, PMBT 2907, SMBT 2907
50303	MMBT2907(A)	2N2907(A), SMD	BSR 15, BSS 82, PMBT 2907, SMBT 2907
50304	MMBT2924	2N2924, SMD	BC 849...850, BCF 32...33, 2SC3323...24
50305	MMBT3013	2N3013, SMD	2SC4168, 2SC4453
50306	MMBT3014	2N3014, SMD	2SC4168, 2SC4453
50307	MMBT3117	2N3117, SMD	2SC3323...24
50308	MMBT3251	2N3251, SMD	BSR 16, BSS 82, PMBT 2907, SMBT 2907
50309	MMBT3392	2N3392, SMD	BC 849...850, BCF 32...33, 2SC3323...24

50310	MMBT3393	2N3393, SMD	BC 849...850, BCF 32...33, 2SC3323...24
50311	MMBT3414	2N3414, SMD	BC 818, BCX 20, PMBT 2222, SMBT 2222
50312	MMBT3415	2N3415, SMD	BC 818, BCX 20, PMBT 2222, SMBT 2222
50313	MMBT3416	2N3416, SMD	BC 817, BCX 19, PMBT 2222, SMBT 2222
50314	MMBT3417	2N3417, SMD	BC 817, BCX 19, PMBT 2222, SMBT 2222
50315	MMBT3467	2N3467, SMD	-
50316	MMBT3563	2N3563, SMD	BF 517, BFS 17, 2SC3014, 2SC3016
50317	MMBT3565	2N3565, SMD	BC 846...850, BCW 31...33, 2SC4076
50318	MMBT3566	2N3566, SMD	BC 846...847, BCW 71...72, 2SC4076
50319	MMBT3567	2N3567, SMD	BCW 66, BCX 41, 2SD1782
50320	MMBT3568	2N3568, SMD	BCW 66, BCX 41, 2SD1782
50321	MMBT3569	2N3569, SMD	BCW 66, BCX 41, 2SD1782
50322	MMBT3638(A)	2N3638(A), SMD	BSR 15, BSS 80, PMBT 2907, SMBT 2907
50323	MMBT3639	2N3639, SMD	BSR 12, PMBT 3640, 2SA1764
50324	MMBT3640	2N3640, SMD	BSR 12, PMBT 3640, 2SA1764
50325	MMBT3641	2N3641, SMD	BCW 65...66, PMBT 2222, SMBT 2222
50326	MMBT3642	2N3642, SMD	BCW 65...66, PMBT 2222, SMBT 2222
50327	MMBT3643	2N3643, SMD	BCW 65...66, PMBT 2222, SMBT 2222
50328	MMBT3644	2N3644, SMD	BSR 15, BSS 80, PMBT 2907, SMBT 2907
50329	MMBT3645	2N3645, SMD	BSR 16, BSS 82, PMBT 2907, SMBT 2907
50330	MMBT3646	2N3646, SMD	2SC4168, 2SC4453
50331	MMBT3693	2N3693, SMD	BF 570, BF 799, 2SC2480, 2SC3015
50332	MMBT3694	2N3694, SMD	BF 570, BF 799, 2SC2480, 2SC3015
50333	MMBT3700	2N3700, SMD	-
50334	MMBT3702	2N3702, SMD	BC 807, BCX 71, 2SA1366, 2SA1620
50335	MMBT3703	2N3703, SMD	BC 807, BCX 71, 2SA1366, 2SA1620
50336	MMBT3903	2N3903, SMD	BC 846, BSR 17, PMBT 3903, SMBT 3904
50337	MMBT3904	2N3904, SMD	BC 846, BSR 17, PMBT 3903, SMBT 3904
50338	MMBT3905	2N3905, SMD	BC 856, BSR 16, PMBT 3905, SMBT 3906
50339	MMBT3906	2N3906, SMD	BC 856, BSR 16, PMBT 3905, SMBT 3906
50340	MMBT3946	2N3946, SMD	BC 846, BSR 17, PMBT 3903, SMBT 3904
50341	MMBT3962	2N3962, SMD	2SA1311...12
50342	MMBT404(A)	MPS 404(A), SMD	BSR 18, 2SA1607
50343	MMBT4121	2N4121, SMD	2SA1607
50344	MMBT4122	2N4122, SMD	2SA1607
50345	MMBT4123	2N4123, SMD	BC 846...47, BSR 17, SMBT 4124, 2SC3392
50346	MMBT4124	2N4124, SMD	BC 846...48, BSR 17, SMBT 4124, 2SC3392
50347	MMBT4125	2N4125, SMD	BC 856...58, BSR 18, SMBT 4126, 2SA1607
50348	MMBT4126	2N4126, SMD	BC 856...58, BSR 18, SMBT 4126, 2SA1607
50349	MMBT4143	2N4143, SMD	-
50350	MMBT4248	2N4248, SMD	BC 860, 2SA1311...12
50351	MMBT4249	2N4249, SMD	2SA1311...12
50352	MMBT4250(A)	2N4250(A), SMD	2SA1311...12
50353	MMBT4258	2N4258, SMD	BSR 12, 2SA1607, 2SA1764
50354	MMBT4274	2N4274, SMD	2SC3578, 2SC4168, 2SC4453



50355	MMBT4275	2N4275, SMD	2SC3578, 2SC4168, 2SC4453
50356	MMBT4291	2N4291, SMD	BC 860, 2SA1311...12
50357	MMBT4354	2N4354, SMD	BSR 16, BSS 82, PMBT 2907, SMBT 2907
50358	MMBT4355	2N4355, SMD	BSR 16, BSS 82, PMBT 2907, SMBT 2907
50359	MMBT4356	2N4356, SMD	2SB1198
50360	MMBT4400	2N4400, SMD	BSR 13...14, BSS 79, BSS 81, PMBT4401
50361	MMBT4401	2N4401, SMD	BSR 13...14, BSS 79, BSS 81, PMBT4401
50362	MMBT4402	2N4402, SMD	BSR 15...16, BSS 80, BSS 82, PMBT4403
50363	MMBT4403	2N4403, SMD	BSR 15...16, BSS 80, BSS 82, PMBT4403
50364	MMBT4409	2N4409, SMD	PMBT 5550...51, MMBTA 42...43
50365	MMBT4410	2N4410, SMD	PMBT 5550...51, MMBTA 42...43
50366	MMBT4888	2N4448, SMD	BFN 25, 2SA1257, 2SA1330
50367	MMBT4889	2N4449, SMD	BFN 25, 2SA1257, 2SA1330
50368	MMBT4916	2N4916, SMD	BSR 18, 2SA1331, 2SA1607
50369	MMBT4917	2N4917, SMD	BSR 18, 2SA1331, 2SA1607
50370	MMBT5086	2N5086, SMD	BC 860, BCF 70, SMBT 5086, 2SA1311...12
50371	MMBT5087	2N5087, SMD	BC 860, BCF 70, SMBT 5087, 2SA1311...12
50372	MMBT5088	2N5088, SMD	BC 850, BCF 81, PMBT 5088, 2SC3323...24
50373	MMBT5089	2N5089, SMD	BC 850, BCF 81, PMBT 5088, 2SC3323...24
50374	MMBT5128	2N5128, SMD	BSR 13...14, BSS 79, BSS 81, 2SC3392
50375	MMBT5130	2N5130, SMD	BF 517, BFS 17, 2SC3014, 2SC3016
50376	MMBT5133	2N5133, SMD	BC 846...850, BCW 31...33, 2SC1622
50377	MMBT5134	2N5134, SMD	BSV 52, 2SC3578, 2SC3757, 2SC4168
50378	MMBT5135	2N5135, SMD	BCW 60, BCX 70, 2SC4209
50379	MMBT5136	2N5136, SMD	BC 817...818, BCX 19...20, 2SC3265
50380	MMBT5137	2N5137, SMD	BC 817...818, BCX 19...20, 2SC3265
50381	MMBT5138	2N5138, SMD	BC 857, BCW 69...70, 2SA1311...12
50382	MMBT5139	2N5139, SMD	BSR 18, 2SA1331, 2SA1607
50383	MMBT5142	2N5142, SMD	BSR 15...16, BSS 80, BSS 82, 2SA1338
50384	MMBT5143	2N5143, SMD	BSR 15...16, BSS 80, BSS 82, 2SA1338
50385	MMBT5172	2N5172, SMD	BC 846...850, BCW 31...33, 2SC1622
50386	MMBT5179	2N5179, SMD	BF 547, BFS 17, 2SC3014, 2SC3773
50387	MMBT5209	2N5209, SMD	BC 850, BCF 81, 2SC3323...24
50388	MMBT5210	2N5210, SMD	BC 850, BCF 81, 2SC3323...24
50389	MMBT5223	2N5223, SMD	BC 856...850, BCW 31...33, 2SC1622
50390	MMBT5224	2N5224, SMD	2SC1621, 2SC4453, 2SC4699K, 2SC4894
50391	MMBT5226	2N5226, SMD	BC 807...808, BCX 17...18, 2SA1621
50392	MMBT5227	2N5227, SMD	BC 856...860, BCW 29...30, 2SA1311
50393	MMBT5228	2N5228, SMD	BSR 12, 2SA1607, 2SA1764
50394	MMBT5400	2N5400, SMD	MMBTA 92...93, PMBT 5401
50395	MMBT5401	2N5401, SMD	MMBTA 92...93, PMBT 5401
50396	MMBT5447	2N5447, SMD	BCX 71, 2SA1620
50397	MMBT5451	2N5451, SMD	BCX 70, 2SC4209
50398	MMBT5550	2N5550, SMD	MMBTA 42...43, PMBT 5550...51
50399	MMBT5551	2N5551, SMD	MMBTA 42...43, PMBT 5551

50400	MMBT5769	2N5769, SMD	2SC4168, 2SC4453
50401	MMBT5771	2N5771, SMD	BSR 12, 2SA1607, 2SA1764
50402	MMBT5772	2N5772, SMD	2SC4168, 2SC4453
50403	MMBT5830	2N5830, SMD	BCX 41, MMBTA 42...43, PMBT 5550...51
50404	MMBT5831	2N5831, SMD	MMBTA 42...43, PMBT 5550...51
50405	MMBT5833	2N5833, SMD	MMBTA 42...43
50406	MMBT5855	2N5855, SMD	-
50407	MMBT5857	2N5857, SMD	-
50408	MMBT5910	2N5910, SMD	BSR 12, 2SA1607, 2SA1764
50409	MMBT5961	2N5961, SMD	2SC3323...24
50410	MMBT5962	2N5962, SMD	2SC3323...24, 2SC3689
50411	MMBT5963	2N5963, SMD	2SC3689
50412	MMBT6426	2N6426, SMD	BCV 27, BCV 47, SMBT 6427
50413	MMBT6427	2N6427, SMD	BCV 27, BCV 47, SMBT 6427
50414	MMBT6428	2N6428, SMD	PMBT 6428, SMBT 6428, 2SC3323...24
50415	MMBT6429	2N6429, SMD	PMBT 6429, SMBT 6429, 2SC3323...24
50416	MMBT6502	2N6502, SMD	-
50417	MMBT6514	MPS 6514, SMD	BC 847, BCW 71...72, BCW 81, 2SC4076
50418	MMBT6515	MPS 6515, SMD	BC 847, BCW 71...72, BCW 81, 2SC4076
50419	MMBT6517	2N6517, SMD	-
50420	MMBT6518	MPS 6518, SMD	BC 857, BCW 69...70, 2SA1311...12
50421	MMBT6520	2N6520, SMD	-
50422	MMBT6520	MPS 6520, SMD	BC 850, BCF 81, 2SC3323...24
50423	MMBT6521	MPS 6521, SMD	BC 850, BCF 81, 2SC3323...24
50424	MMBT6543	MPS 6543, SMD	BF 547, BFS 17, 2SC3014, 2SC3773
50425	MMBT6560	2N6560, SMD	BC 817...818, BCX 19...20, 2SC3265
50426	MMBT6561	2N6561, SMD	BC 817...818, BCX 19...20, 2SC3265
50427	MMBT6562	2N6562, SMD	BC 807...808, BCX 17...18, 2SA1621
50428	MMBT706(A)	MPS 706(A), SMD	2SC1621, 2SC4894, 2SC4699K
50429	MMBT8599	MPS 8599, SMD	2SB1198
50430	MMBT918	2N918, SMD	BF 517, BFS 17, 2SC3014, 2SC3016
50431	MMBT930(A)	2N930(A), SMD	2SC3323...24
50432	MMBTA05	MPSA 05, SMD	2SD1782
50433	MMBTA06	MPSA 06, SMD	BCW 66, PMBTA 06, SMBTA 06, 2SD1782
50434	MMBTA12	MPSA 12, SMD	BCV 27, BCV 47, PMBTA 12, SMBTA 14
50435	MMBTA13	MPSA 13, SMD	BCV 27, BCV 47, PMBTA 13, SMBTA 13
50436	MMBTA14	MPSA 14, SMD	BCV 27, BCV 47, PMBTA 14, SMBTA 14
50437	MMBTA18	MPSA 18, SMD	BCX 70, 2SC4209
50438	MMBTA20	MPSA 20, SMD	BC 846...847, SMBTA 20, 2SC1622
50439	MMBTA28	MPSA 28, SMD	BCV 47
50440	MMBTA42	MPSA 42, SMD	PMBTA 42, SMBTA 42
50441	MMBTA43	MPSA 43, SMD	PMBTA 42...43, SMBTA 42...43
50442	MMBTA517	30V, 0,5A, 220MHz	-
50443	MMBTA55	MPSA 55, SMD	BCW 68, BCX 42, PMBTA 55, SMBTA 55
50444	MMBTA56	MPSA 56, SMD	BCX 42, PMBTA 56, SMBTA 56

50445	MMBTA63	MPSA 63, SMD	BCV 26, BCV 46, PMBTA 63, SMBTA 63
50446	MMBTA64	MPSA 64, SMD	BCV 26, BCV 46, PMBTA 64, SMBTA 64
50447	MMBTA65	MPSA 66, SMD	BCV 26, BCV 46, PMBTA 64, SMBTA 64
50448	MMBTA70	MPSA 70, SMD	BC 856...857, SMBTA 70, 2SA1311...12
50449	MMBTA92	MPSA 92, SMD	PMBTA 92, SMBTA 92
50450	MMBTA93	MPSA 93, SMD	PMBTA 92...93, SMBTA 92...93
50451	MMBTH10	MPSH 10, SMD	BF517, BF547, BFS17, PMBTH10, 2SC3161
50452	MMBTH11	MPSH 11, SMD	BF517, BF547, BFS17, PMBTH10, 2SC3161
50453	MMBTH20	MPSH 20, SMD	BF 599, BF 799, BFS 20, 2SC3015
50454	MMBTH24	MPSH 24, SMD	BF 599, BF 799, BFS 20, 2SC3015
50455	MMBTH30	MPSH 30, SMD	BF 570, BF 799, 2SC3374
50456	MMBTH34	MPSH 34, SMD	BF 570, BF 799, 2SC3374
50457	MMBTH69	MPSH 69, SMD	2SA1245, 2SA1424
50458	MMBTH81	MPSH 81, SMD	BF 567, BF 569, BF 579, PMBTH 81
50459	MMBTL01	MPSL 01, SMD	BFN 24, MMBT 5550...51, MMBTA 42...43
50460	MMBTL51	MPSL 51, SMD	BCX 42, MMBT 5401, MMBTA 92...93
50461	MMBV105G	1,8..2,8pF(25V)	-
50462	MMBV109	MV 109, SMD	-
50463	MMBV2101	MV 2101, SMD	-
50464	MMBV2102	MV 2102, SMD	-
50465	MMBV2103	MV 2103, SMD	-
50466	MMBV2104	MV 2104, SMD	-
50467	MMBV2105	MV 2105, SMD	-
50468	MMBV2106	MV 2106, SMD	-
50469	MMBV2107	MV 2107, SMD	-
50470	MMBV2108	MV 2108, SMD	-
50471	MMBV2109	MV 2109, SMD	-
50472	MMBV3102	MV 3102, SMD	-
50473	MMBV3401	MPN 3401, SMD	-
50474	MMBV3700	MPN 3700, SMD	-
50475	MMBV409	MV 409, SMD	-
50476	MMBV432	43..48,1pF(2V)	-
50477	MMBV609	26..32pF(3V)	-
50478	MMBV809	4,5..6,1pF(2V)	-
50479	MMBZ5226..5257	1N5226..5257, SMD	BZX 84/..., HZM ..., RD ...M
50480	MMCM2222	2N2222	-
50481	MMCM2369	2N2369	-
50482	MMCM2484	2N2484	-
50483	MMCM2857	2N2857	-
50484	MMCM2907	2N2907	-
50485	MMCM3798	2N3798	-
50486	MMCM3799	2N3799	-
50487	MMCM3903	2N3903	-
50488	MMCM3904	2N3904	-
50489	MMCM3905	2N3905	-

50490	MMCM3906	2N3906	-
50491	MMCM3960A	2N3960A	-
50492	MMCM918	2N918	-
50493	MMCM930	2N930	-
50494	MMF1...6	MFE 2003, 2N3823	MFE 2003, 2N3823
50495	MMFT107	200V, 0,25A, <14Ohm(0,2A)	BSP 128, BSP 130
50496	MMFT1N10E	100V, 1A, <0,25Ohm(0,5A)	BSP 296
50497	MMFT2406	240V, 0,7A, <6Ohm(0,5A)	-
50498	MMFT2955E	60V, 1,2A, <0,3Ohm(0,6A)	BSP 171
50499	MMFT2N02EL	20V, 1,6A, <0,15Ohm	BUK 582-60A
50500	MMFT3055V	60V, 1,7A, <0,13Ohm(0,85A)	-
50501	MMFT3055VL	<0,14Ohm	-
50502	MMFT6661	90V, 0,5A, <4Ohm(1A)	BSP 297
50503	MMFT960	60V, 0,3A, <1,7Ohm(1A)	BSP 109, BSP 110
50504	MMSD914	1N914, SMD, 100V, 0,2A, <4ns	-
50505	MMST1130	(Japan)	SST 1130
50506	MMST1139	(Japan)	SST 1130
50507	MMST2222(A)	(Japan)	SST 2222(A)
50508	MMST2907(A)	(Japan)	SST 2907(A)
50509	MMST3904	(Japan)	SST 3904
50510	MMST3906	(Japan)	SST 3906
50511	MMST4124	(Japan)	SST 4124
50512	MMST4126	(Japan)	SST 4126
50513	MMST4401	(Japan)	SST 4401
50514	MMST4403	(Japan)	SST 4403
50515	MMST5086	(Japan)	SST 5086
50516	MMST5087	(Japan)	SST 5087
50517	MMST5088	(Japan)	SST 5088
50518	MMST5089	(Japan)	SST 5089
50519	MMST5101	(Japan)	SST 5101
50520	MMST5424	(Japan)	SST 5424
50521	MMST6428	(Japan)	SST 6428
50522	MMST6838	(Japan)	SST 6838
50523	MMST6839	(Japan)	SST 6839
50524	MMST7157	(Japan)	SST 7157
50525	MMST8245	(Japan)	SST 8245
50526	MMST8598	(Japan)	SST 8598
50527	MMST918S	(Japan)	SST 918S
50528	MMSTA06	(Japan)	SSTA 06
50529	MMSTA13	(Japan)	SSTA 13
50530	MMSTA14	(Japan)	SSTA 14
50531	MMSTA20	(Japan)	SSTA 20
50532	MMSTA28	(Japan)	SSTA 28
50533	MMSTA56	(Japan)	SSTA 56
50534	MMSTA63	(Japan)	SSTA 63

50535	MMSTA64	(Japan)	SSTA 64
50536	MMSTA70	(Japan)	SSTA 70
50537	MMSV3401	MPN 3401, SMD	-
50538	MMT2222	2N2222	-
50539	MMT2369	2N2369	-
50540	MMT2484	2N2484	-
50541	MMT2857(A)	2N2857(A)	-
50542	MMT2907	2N2907	-
50543	MMT3014	2N3014	-
50544	MMT3546	2N3546	-
50545	MMT3798	2N3798	-
50546	MMT3799	2N3799	-
50547	MMT3823	2N3823	-
50548	MMT3903	2N3903	-
50549	MMT3904	2N3904	-
50550	MMT3905	2N3905	-
50551	MMT3906	2N3906	-
50552	MMT3960(A)	2N3960(A)	-
50553	MMT4261	2N4261	-
50554	MMT5031(A)	2N5031(A)	-
50555	MMT8006	15V, 1000MHz	BF 679...680, BF 967...970, BF 979...980
50556	MMT8007	15V, 1000MHz	BF 679...680, BF 967...970, BF 979...980
50557	MMT8008	8V, 1000MHz	BF 679...680, BF 967...970, BF 979...980
50558	MMT8015	15V, 15mA, 2000MHz	BF 979, 2SC2464...66, 2SC2726, 2SC2728
50559	MMT806	8V, 2100MHz	-
50560	MMT807	8V, 2100MHz	-
50561	MMT808	8V, 2500MHz	-
50562	MMT809	8V, 2500MHz	-
50563	MMT918	2N918	-
50564	MMT930	2N930	-
50565	MMUN2111	UN 1111, SMD	UN 2111
50566	MMUN2112	UN 1112, SMD	UN 2112
50567	MMUN2113	UN 1113, SMD	UN 2113
50568	MMUN2114	UN 1114, SMD	UN 2114
50569	MMUN2115	UN 1115, SMD	UN 2115
50570	MMUN2116	UN 1116, SMD	UN 2116
50571	MMUN2130	UN 1111, SMD, RbRbe1kOhm	-
50572	MMUN2131	UN 1111, SMD, RbRbe2,2kOhm	DTA 123EK
50573	MMUN2132	UN 1111, SMD, RbRbe4,7kOhm	FN 1L3M, DTA 143EK, RN 2401, UN 211L
50574	MMUN2133	Rbe47kOhm	DTA 143ZK, RN 2406, 2SA1597
50575	MMUN2134	Rbe47kOhm	FN 1F4N, DTA 143XK, KSR 2107, RN 2408
50576	MMUN2211	UN 1211, SMD	UN 2211
50577	MMUN2212	UN 1212, SMD	UN 2212
50578	MMUN2213	UN 1213, SMD	UN 2213
50579	MMUN2214	UN 1214, SMD	UN 2214

50580	MMUN2215	UN 1215, SMD	UN 2215
50581	MMUN2216	UN 1216, SMD	UN 2216
50582	MMUN2230	UN 1211, SMD, RbRbe1kOhm	-
50583	MMUN2231	UN 1211, SMD, RbRbe2,2kOhm	DTC 123EK
50584	MMUN2232	UN 1211, SMD, RbRbe4,7kOhm	FA 1L3M, DTC 143EK, RN 1401, UN 221L
50585	MMUN2233	Rbe47kOhm	DTC 143ZK, RN 1406, 2SC4146
50586	MMUN2234	Rbe47kOhm	FA 1F4N, DTC 143XK, KSR 1107, RN 1408
50587	MN	2SC4843	2SC4843
50588	MN	2SC4320	2SC4320
50589	MN	P6 SMB-68	P6 SMB-68
50590	MN	2SC4840	2SC4840
50591	MN	MA 151WA	MA 151WA
50592	MN	MA 141WA	MA 141WA
50593	MN	2SC4321	2SC4321
50594	MN	2SC4317	2SC4317
50595	MN	SM 6T 27C	SM 6T...
50596	MN	2SC4318	2SC4318
50597	MN	2SC4319	2SC4319
50598	MO	2SC4324	2SC4324
50599	MO	2SC4844	2SC4844
50600	MO	MA 132WA	MA 132WA
50601	MO	2SC4841	2SC4841
50602	MO	MA 142WA	MA 142WA
50603	MO	2SC4325	2SC4325
50604	MO	2SA1255-O	2SA1255
50605	MO	MA 152WA	MA 152WA
50606	MO	2SC4322	2SC4322
50607	MO	2SC2873-O	2SC2873
50608	MO	2SC4323	2SC4323
50609	MO(p)	BF 998(R)	BF 998(R)
50610	MO1	BF 901	BF 901
50611	MO2	BF 901R	BF 901R
50612	MO51	100V, 0,2A	BA 157...159, BAY 45...46, BY 206...207
50613	MO52	MO 51, 200V	BA 157...159, BAY 46, BY 206...207
50614	MO53	MO 51, 300V	BA 157...159, BAY 46, BY 206...207
50615	MO54	MO 51, 400V	BA 157...159, BAY 89, BY 204/4, BY 207
50616	MO55	MO 51, 500V	BA 158...159, BAY 89, BY 204/8, BY 207
50617	MO56	MO 51, 600V	BA 158...159, BAY 89, BY 204/8, BY 207
50618	MP	P6 SMB-68A	P6 SMB-68A
50619	MP	MA 133	MA 133
50620	MP	2SC4470	2SC4470
50621	MP	MA 153A	MA 153A
50622	MP	MA 143A	MA 143A
50623	MP	SM 6T 27CA	SM 6T...
50624	MP	HR 1A3M	HR 1...



50625	MP104	-/60V, 1,2A, >100MHz	2SC1398, 2SC2275(A), 2SC2528...2529
50626	MP104A	MP 104, -/80V	2SC2275(A), 2SC2528...2529
50627	MP110	65V, 7A, 106W	AL 100...101, AUY 22A, 2N3615...3618
50628	MP110B	90V, 25A, 106W	2N1652...53, 2N2286...87
50629	MP1529...1560(A)	2N1529..1560(A)	2N1529...1560(A)
50630	MP1612	100V, 20A, 85W	-
50631	MP1612A	MP 1612, 140V	-
50632	MP1612B	MP 1612, 160V	-
50633	MP1613	100V, 7A, 85W	AU 108, AU 210
50634	MP2000(A,B)	-/30V, 25A, 106W	2N1651...1653, 2N2285...2287
50635	MP2060	40V, 7A, 85W	AL 100...101, AUY 22A, 2N3611...3618
50636	MP2061	MP 2060, 60V	AL 100...101, AUY 22A, 2N3615...3618
50637	MP2062	MP 2060, 75V	AL 100...101, AUY 22A, 2N3615...3618
50638	MP2063	MP 2060, 90V	AL 100...101, AUY 37, 2N3616, 2N3618
50639	MP2100(A,B)	MP 2000, -/60V	2N1652...1653, 2N2286...2287
50640	MP2137...2146(A)	2N2137..2146(A)	2N2137...2146(A)
50641	MP2200(A,B)	MP 2000, -/80V	2N1652...1653, 2N2286...2287
50642	MP2300(A,B)	MP 2000, -/100V	2N1652...1653, 2N2286...2287
50643	MP2357...2359	2N2357..2359	2N2357...2359
50644	MP2400(A,B)	MP 2000, -/120V	2N1653, 2N2287
50645	MP2526...2528	2N2526..2528	2N2526...2528
50646	MP2832...2834	2N2832..2834	2N2832...2834
50647	MP3611...3618	2N3611..3618	2N3611...3618
50648	MP3730	200V, 5A, 56W	AU 106...107, AU 213, 2N5324...5325
50649	MP3730A	MP 3730, 250V	AU 106, AU 213, 2N5324...5325
50650	MP3730B	MP 3730, 280V	AU 106, 2N5325
50651	MP3731	320V, 10A, 56W	AU 106, 2N5325
50652	MP4048...4053	2N4048..4053	2N4048...4053
50653	MP4276...4283	2N4276..4283	2N4276...4283
50654	MP500(A)	45V, 60A, 170W, B>30	2N4048...4053
50655	MP501(A)	MP 500, 60V	2N4049...4050, 2N4052...5053
50656	MP502(A)	MP 500, 75V	2N4050, 2N4053
50657	MP503(A)	MP 500, 90V	-
50658	MP504(A)	MP 500, B>50	2N4048...4053
50659	MP505(A)	MP 501, B>50	2N4049...4050, 2N4052...5053
50660	MP506(A)	MP 502, B>50	2N4050, 2N4053
50661	MP507(A)	MP 503, B>50	-
50662	MP525	60V, 7A, 106W	AL 100...101, AUY 22A, 2N3615...3618
50663	MP5435...5440	2N5435..5440	2N5435...5440
50664	MP5692...5696	2N5692..5696	2N5692...5696
50665	MP600(A)	75/50V, 25A, 85W	2N1652...1653, 2N2286...2287
50666	MP601(A)	MP 600, 75/60V	2N1652...1653, 2N2286...2287
50667	MP602(A)	MP 600, 90/70V	2N1652...1653, 2N2286...2287
50668	MP603(A)	MP 600, 90/80V	2N1652...1653, 2N2286...2287
50669	MP939	AU 103	AU 103

50670	MPF1010	100V, 0,5A, 1W, <15/15ns	BSS 396, 2SK458, 2SK468
50671	MPF102	25V, Idss>2mA, Up<8	BF 244...245, BFS 72, 2N3823, 2N5245
50672	MPF103	25V, Idss>1mA, Up<6V	BF 244...245, BFS 71, 2N3822, 2N5457
50673	MPF104	MPF 103, Idss>2mA, Up<7V	BF 244...245, BFS 71, 2N3822, 2N4221
50674	MPF105	MPF 103, Idss>4mA, Up<8V	BF 244...245, BFS 72, 2N3823, 2N5245
50675	MPF106	25V, Idss>4mA, Up<4V	BF 244...245, BF 256, 2N3823, 2N5485
50676	MPF107	MPF 106, Idss>8mA, Up<6V	BF 244...245, BF 256, BF 348, BFT 10A
50677	MPF108	25V, Idss>1,5mA, Up<8V	BF 244...245, BF 256, BFS 72, 2N3823
50678	MPF109	25V, Idss>0,5mA, Up<8V	BF 244...245, BF 256, BFS 72, 2N3823
50679	MPF110	20V, Idss>0,5mA, Up<10V	BF 244...245, BF 256, BFS 72, 2N3823
50680	MPF111	20V, Idss>0,5mA, Up<10V	BF 244...245, BF 256, BFS 72, 2N3823
50681	MPF112	25V, Idss>1mA, Up<10V	BF 244...245, BF 256, BFS 72, 2N3823
50682	MPF120	MFE 120	MFE 120
50683	MPF121	MFE 121	MFE 121
50684	MPF122	MFE 122	MFE 122
50685	MPF151	2N5460	2N5460
50686	MPF152	2N5461	2N5461
50687	MPF153	2N5462	2N5462
50688	MPF154	2N5463	2N5463
50689	MPF155	2N5464	2N5464
50690	MPF156	2N5465	2N5465
50691	MPF161	40V, Idss>0,5mA, Up<8V	2N5460...5465
50692	MPF201..203	3N201..203	3N201...203
50693	MPF208	25V, Idss>0,5mA, Up<8V	BF 244...245, BF 256, BFS 72, 2N3823
50694	MPF209	25V, Idss>0,5mA, Up<8V	BF 244...245, BF 256, BFS 72, 2N3823
50695	MPF209	3N209	3N209
50696	MPF211..213	3N211..213	3N211...213
50697	MPF256	30V, Idss>3mA, Up<7,5V	BF 244...245, BF 256, BFS 72, 2N3823
50698	MPF3821..3822	2N3821..3822	2N3821...3822
50699	MPF4091..4093	2N4091..4093	2N4091...4093
50700	MPF4117..4119(A)	2N4117..4119(A)	2N4117...4119(A)
50701	MPF4150	Idss>0,1A	-
50702	MPF4220..4222(A)	2N4220..4222(A)	2N4220...4222(A)
50703	MPF4391	2N4391	2N4391
50704	MPF4392	2N4392	2N4392
50705	MPF4393	2N4393	2N4393
50706	MPF4416(A)	2N4416(A)	2N4416(A)
50707	MPF4856..4861(A)	2N4856..4861(A)	2N4856...4861(A)
50708	MPF521	30V, 30mA, Up<-2V	BF 960, BF 966, 3SK48, 3SK80
50709	MPF6659..6661	2N6659..6661, 1W	BSS 396, BST 95, 2SK468
50710	MPF820	25V, Idss>10mA, Up<5V	BF 256, BF 348, BFT 10, 2SK125
50711	MPF910	MFE 910, 1W	2SK422...423, 2SK940...941
50712	MPF9200	MFE 9200	MFE 9200
50713	MPF930	MFE 930, 1W	2SK 462, 2SK468, 2SK973
50714	MPF960	MFE 960, 1W	2SK 462, 2SK468, 2SK973

50715	MPF970	30V, 3,5/13ns	2N3993, 2N5114
50716	MPF971	30V, 5/88ns	2N3994, 2N5116
50717	MPF990	MFE 990, 1W	BSS 396, 2SK468
50718	MPI-3401	MPN 3401	MPN 3401
50719	MPM5006	600MHz	BF 198, BF 225, BF 314, BF 502, BF 505
50720	MPN3401		BA 382
50721	MPN3402		BA 382
50722	MPN3403		BA 382
50723	MPN3404		BA 382
50724	MPN3411		BA 379, BA 382
50725	MPN3412		BA 379, BA 382
50726	MPN3700	200V	-
50727	MPS-K70	3x MPSA 70	MPSA 70
50728	MPS1983	MPS 901	2SC2570(A), 2SC3355, 2SC3512
50729	MPS2218...2222(A)	2N2218..2222(A), 0,625W	2N2218...2222(A)
50730	MPS2369(A)	2N2369, 0,625W	2N2369(A)
50731	MPS2484	2N2484, 0,5W	2N2484
50732	MPS2711...2716	2N2711..2716, 0,35W	2N2711...2716
50733	MPS2894	2N2894, 0,3W	2N2894
50734	MPS2904..2907(A)	2N2904..2907(A), 0,625W	2N2904...2907(A)
50735	MPS2923...2925	2N2923..2925, 0,35W	2N2923...2925
50736	MPS2926	2N2926, 0,35W	2N2926
50737	MPS3013	2N3013, 0,35W	2N3013
50738	)	2N3390..3398(A), 0,35W	2N3390...3398(A)
50739	MPS3402...3405	2N3402..3405, 0,56W	2N3402...3405
50740	MPS3414...3418	2N3414..3418, 0,5W	2N3414...3418
50741	MPS3563	2N3563, 0,625W	2N3563
50742	MPS3567...3569	2N3567..3569, 0,35W	2N3567...3569
50743	MPS3608	-/25V, 0,5A, 0,35W, >100MHz	BC 637, BC 639, 2SD667, 2SD1616(A)
50744	MPS3638(A)	2N3638(A), 0,625W	2N3638(A)
50745	MPS3639...3640	2N3639..3640, 0,625W	2N3639...3640
50746	MPS3641...3643	2N3641..3643, 0,5W	2N3641...3643
50747	MPS3644...3645	2N3644..3645, 0,5W	2N3644...3645
50748	MPS3646	2N3646, 0,625W	2N3646
50749	MPS3693...3694	2N3693..3694, 0,35W	2N3693...3694
50750	MPS3702...3703	2N3702..3703, 0,625W	2N3702...3703
50751	MPS3704...3711	2N3704..3711, 0,625W	2N3704...3711
50752	MPS3721	2N3721, 0,35W	2N3721
50753	MPS3725	2N3725, 0,625W	2N3725
50754	MPS3826...3827	2N3826..3827, 0,35W	2N3826...3827
50755	MPS3866	2N3866, 0,625W	2N3866
50756	MPS3903...3906	2N3903..3906, 0,625W	2N3903...3906
50757	MPS404(A)	25(A40)V, 0,15A, 223/835ns	BSW 24, 2N3250...51(A), 2N4034...35
50758	MPS4123..4126	2N4123..4126, 0,625W	2N4123...4126
50759	)	2N4248..4250(A), 0,625W	2N4248...4250(A)

50760	MPS4257...4258	2N4257..4258, 0,625W	2N4257...4258
50761	MPS4274...4275	2N4274..4275, 0,2W	2N4274...4275
50762	MPS4354...4356	2N4354..4356, 0,625W	2N4354...4356
50763	MPS4888...4889	2N4888..4889, 0,625W	2N4888...4889
50764	MPS5127	2N5127, 0,2W	2N5127
50765	MPS5128...5129	2N5128..5129, 0,625W	2N5128...5129
50766	MPS5131...5132	2N5131..5132, 0,625W	2N5131...5132
50767	MPS5134...5139	2N5134..5139, 0,625W	2N5134...5139
50768	MPS5142...5143	2N5142..5143, 0,625W	2N5142...5143
50769	MPS5172	2N5172, 0,625W	2N5172
50770	MPS5179	2N5179, 0,35W	2N5179
50771	MPS536	15V, 30mA, 4,5GHz	-
50772	MPS5551(M)	2N5551, 0,625W	2N5551
50773	MPS571	20V, 80mA, 6GHz	2SC2570(A), 2SC3355, 2SC3605
50774	MPS5770	2N5770	2N5770
50775	MPS5771	2N5771, 0,625W	2N5771
50776	MPS5855...5858	2N5855..5858, 0,625W	2N5855...5858
50777	MPS6076	2N6076, 0,36W	2N6076
50778	MPS6172	25V, 0,1A, 0,35W, 120MHz	BC 213, BC 258, BC 308, BC 558, 2SB725
50779	MPS6428	2N6428, 0,625W	2N6428
50780	MPS650	60V, 2A, 0,625W, >75MHz	2SD1207, 2SC3328, BD 525, BD 527
50781	MPS6507	30V, 0,1A, 800MHz	BF 377...378, BF 689, BF 763, 2N2857
50782	MPS651	MPS 650, 80V	2SC3328, BD 519, BD 527, BD 529
50783	MPS6511		BF 225, BF 689, BF 763, BF 959
50784	MPS6512	B>50	BC 167, BC 183, BC 237, BC 547
50785	MPS6513	MPS 6512, B>90	BC 167, BC 183, BC 237, BC 547
50786	MPS6514	MPS 6512, B>150	BC 167, BC 183, BC 237, BC 547
50787	MPS6515	MPS 6512, B>250	BC 167, BC 183, BC 237, BC 547
50788	MPS6516	B>50	BC 213, BC 257, BC 307, BC 557
50789	MPS6517	MPS 6516, B>90	BC 213, BC 257, BC 307, BC 557
50790	MPS6518	MPS 6516, B>150	BC 213, BC 257, BC 307, BC 557
50791	MPS6519	MPS 6516, B>250	BC 213, BC 257, BC 307, BC 557
50792	MPS6520	40V, 0,1A, 0,625W, B>200	BC 184, BC 413...414, BC 550
50793	MPS6521	MPS 6520, B>300	BC 184, BC 413...414, BC 550
50794	MPS6522	40V, 0,1A, 0,625W, B>200	BC 214, BC 415...416, BC 560
50795	MPS6523	MPS 6522, B>300	BC 214, BC 415...416, BC 560
50796	MPS6530	60V, 0,6A, 0,625W, B>40	BC 337A, BC 637, BC 639, 2SD1226
50797	MPS6531	MPS 6530, B>90	BC 337A, BC 637, BC 639, 2SD1226
50798	MPS6532	MPS 6530, 50V	BC 337, BC 637, BC 639, 2SD1226
50799	MPS6533	40V, 0,6A, 0,625W, B>40	BC 327, BC 636, BC 638, 2SB910
50800	MPS6534	MPS 6533, B>90	BC 327, BC 636, BC 638, 2SB910
50801	MPS6535	MPS 6533, 30V	BC 327...328, BC 636, BC 638, 2SB910
50802	MPS6539	20V, 0,05A, >500MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50803	MPS6540	30V, 0,1A, 800MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50804	MPS6541	30V, 0,1A, >600MHz	BF 225, BF 314, BF 496, BF 502, BF 505

50805	MPS6542	>700MHz	BF 224, BF 314, BF 496, BF 503, BF 505
50806	MPS6543	35V, 0,05A, 1100MHz	BF 377...378, BF 689, BF 763, 2N2857
50807	MPS6544	60V, 0,1A, 0,625W	BF 199, BF 224, BF 311, BF 373, BF 597
50808	MPS6545	60V, 0,1A, 0,625W	BF 199, BF 224, BF 311, BF 373, BF 597
50809	MPS6546	35V, 0,05A, 1000MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50810	MPS6547	35V, 0,05A, 1000MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50811	MPS6548	30V, 0,05A, 1500MHz	BF 377...378, BF 689, BF 763
50812	MPS6552	35V, 0,6A, 0,31W, B>100	BC 337, BC 635, BC 637, BC 639
50813	MPS6553	35V, 0,6A, 0,31W, B>100	BC 337, BC 635, BC 637, BC 639
50814	MPS6554	35V, 0,6A, 0,31W, B>200	BC 337, BC 635, BC 637, BC 639
50815	MPS6555	35V, 0,6A, 0,31W, B>200	BC 337, BC 635, BC 637, BC 639
50816	MPS6560	25/25V, 0,5A, 0,625W, >60MHz	BC 337...338, BC 635, BC 637, BC 639
50817	MPS6561	MPS 6560, 25/20V	BC 337...338, BC 635, BC 637, BC 639
50818	MPS6562	25/25V, 0,5A, 0,625W, >60MHz	BC 327...328, BC 636, BC 638, BC 640
50819	MPS6563	MPS 6562, 25/20V	BC 327...328, BC 636, BC 638, BC 640
50820	MPS6564	-/45V, 0,05A, 0,31W	BC 167, BC 182, BC 237, BC 547
50821	MPS6565	B>40	BC 174, BC 182, BC 190, BC 546
50822	MPS6566	MPS 6565, B>100	BC 174, BC 182, BC 190, BC 546
50823	MPS6567	800MHz,	BF 198, BF 225, BF 310, BF 367, BF 596
50824	MPS6568(A)	20V, 0,05A, >375MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50825	MPS6569(A)	MPS 6568, 300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50826	MPS6570(A)	MPS 6568, 300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50827	MPS6571	20V, 0,05A, 0,625W, 175MHz	BC 169, BC 184, BC 239, BC 549, 2SD767
50828	MPS6573	B>200	BC 167, BC 183, BC 237, BC 547
50829	MPS6574	MPS 6573, B>100	BC 167, BC 183, BC 237, BC 547
50830	MPS6575	MPS 6573, 45V	BC 167, BC 183, BC 237, BC 547
50831	MPS6576	MPS 6573, 45V, B>100	BC 167, BC 183, BC 237, BC 547, 2SD767
50832	MPS6579	400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50833	MPS6580	450MHz	BF 324, BF 440...441, BF 450...451
50834	MPS6590	-/80V, 0,25A, 0,35W, >60MHz	BC 546
50835	MPS6591	MPS 6590, -/50V	BC 174, BC 182, BC 190, BC 546
50836	MPS6595	20V, 0,05A, >1200MHz	BF 630, BFR 15, BFS 55, BFW 99, 2SC2570
50837	MPS6601	25V, 1A, 0,625W, >100MHz	BC 337...338, BC 635, BC 637, 2SD1225
50838	MPS6602	MPS 6601, 40V	BC 337, BC 635, BC 637, 2SD1225
50839	MPS6651	25V, 1A, 0,625W, >100MHz	BC 327...328, BC 636, BC 638, 2SB909
50840	MPS6652	MPS 6651, 40V	BC 327...328, BC 636, BC 638, 2SB909
50841	MPS6714	2N6714, 1A, 1W	2SC3328, 2SC4145, 2SD1207, 2SD2069
50842	MPS6715	2N6715, 1A, 1W	2SC3328, 2SC4145, 2SD1207, 2SD2069
50843	MPS6717	2N6717, 0,5A, 1W	2SC3328, 2SC4145, 2SD2485
50844	MPS6724	2N6724, 50V, 1A, 1W, B4k..40k	2SD1153, 2SD1854, 2SD1929, 2SD1931
50845	MPS6725	MPS 6724, 60V	2SD1153, 2SD1854, 2SD1929, 2SD1931
50846	MPS6726..6727	2N6726..6727, 1A, 1W	2SA1315, 2SA1382, 2SB892, 2SB1459
50847	MPS6733	2N6733	2SC3249, 2SC3467...68
50848	MPS6734	2N6734	2SC3249, 2SC3467...68
50849	MPS6735	2N6735	2SC3249, 2SC3467...68

50850	MPS706(A)	2N706(A), 0,625W	2N706(A)
50851	MPS708	2N708, 0,35W	2N708
50852	MPS750	60V, 2A, 0,625W, >75MHz	2SA1315, 2SA1706, 2SB892, 2SB1229
50853	MPS751	MPS 750, 80V	2SA1315, 2SA1429, 2SA1709, 2SB1459
50854	MPS753	2N753, 0,35W	2N753
50855	MPS8000	60V, 0,5A, PQ>0,35W(27MHz)	2SC2086, MRF 8003, 2SC781
50856	MPS8001	-/25V, 0,1A, 0,35W, >100MHz	BC 168, BC 183, BC 238, BC 548
50857	MPS8050	40V, 1A, 0,625W	BC 635, BC 637, 2SD1225, 2SD1616(A)
50858	MPS8093	40V, 0,2A, 0,625W	BC 213, BC 257, BC 307, BC 557, 2SB725
50859	MPS8097	60V, 0,2A, 0,35W, >200MHz	BC 414, BC 550, 2SC2240, 2SC2459
50860	MPS8098	60V, 0,5A, 0,625W, >150MHz	BC 337A, BC 637, BC 639, 2SD667(A)
50861	MPS8099	MPS 8098, 80V	BC 639, 2SC3939, 2SD667(A), 2SD1226
50862	MPS834...835	2N834..835, 0,35W	2N834...835
50863	MPS8550	40V, 0,8A, 0,625W	BC 636, BC 638, 2SB909, 2SB1116(A)
50864	MPS8598	60V, 0,5A, 0,625W, >150MHz	BC 327A, BC 638, BC 640, 2SB647(A)
50865	MPS8599	MPS 8598, 80V	BC 640, 2SA1533, 2SB647, 2SB1116A
50866	MPS901	25V, 30mA, 4,5GHz	2SC2570(A), 2SC3355, 2SC3512
50867	MPS911	20V, 60mA, 7GHz	2SC3355, 2SC3605
50868	MPS918	2N918, 0,625W	2N918
50869	MPS929...930(A)	2N929..930(A), 0,625W	2N929...930(A)
50870	MPS9410(A)	-/12V, 0,5A, 0,35, 200MHz	BC 337...338, BC 635, BC 637, 2SC3377
50871	MPS9411	MPS 9410, -/18V	BC 337...338, BC 635, BC 637, 2SC3377
50872	MPS9412	MPS 9410, -/25V	BC 337...338, BC 635, BC 637, 2SC3377
50873	MPS9416(A,AS)	-/18V, 0,6..1A, 0,625W,300MHz	BC 337...338, BC 635, BC 637, 2SD1225
50874	MPS9417(A)	MPS 9416(A), -/25V	BC 337, BC 637, BC 639, 2SD1616(A)
50875	MPS9418	-/25V, 1,5A, 0,625W, 350MHz	2SC3225, 2SD1051, 2SD1207, 2SD1331
50876	MPS9420	BF 314	BF 314
50877	MPS9423	BF 240, BF 241	BF 240, BF 241
50878	MPS9425	>300MHz	BF 254...255, BF 494...495, BF 594...595
50879	MPS9433	BC 337	BC 337
50880	MPS9434	-/50V, 0,6, 0,625W, 200MHz	BC 337, BC 637, BC 639, 2SD1616(A)
50881	MPS9436	BC 337	BC 337
50882	MPS9460	-/12V, 0,5A, 0,35W, 150W	BC 327...328, BC 636, BC 638, 2SA1515
50883	MPS9461	MPS 9460, -/18V	BC 327...328, BC 636, BC 638, 2SA1515
50884	MPS9462	MPS 9460, -/25V	BC 327...328, BC 636, BC 638, 2SA1515
50885	MPS9466(A,AS)	-/18V, 0,6..1A, 0,625W,300MHz	BC 327...328, BC 636, BC 638, BC 640
50886	MPS9467(A)	MPS 9466(A), -/25V	BC 327, BC 636, BC 638, BC 640, 2SB1116
50887	MPS9468	-/25V, 1,5A, 0,625W, 200MHz	MPS 750...751, 2SB819, 2SB892, 2SB978
50888	MPS9483	BC 327	BC 327
50889	MPS9484	-/50V, 0,6A, 0,625W, 100MHz	BC 327, BC 636, BC 638, 2SB1116(A)
50890	MPS9486	BC 327	BC 327
50891	MPS9600	-/12V, 0,1A, 0,3W, >50MHz	BC 169, BC 173, BC 184, BC 239, BC 549
50892	MPS9600G	BF 495	BF 495
50893	MPS9601	MPS 9600, -/18V	BC 169, BC 173, BC 184, BC 239, BC 549
50894	MPS9602	MPS 9600, -/30V	BC 169, BC 173, BC 184, BC 239, BC 549



50895	MPS9603	BF 494	BF 494
50896	MPS9604E	BF 240	BF 240
50897	MPS9605	BF 255	BF 255
50898	MPS9606	BF 494	BF 494
50899	MPS9607	BF 494	BF 494
50900	MPS9608	BF 494	BF 494
50901	MPS9610	BC 549	BC 549
50902	MPS9616	BC 338	BC 338
50903	MPS9623	-/18V, 0,1A, 0,31W, >100MHz	BF 254...255, BF 494...495, BF 594...595
50904	MPS9624	MPS 9623, -/30V	BF 254...255, BF 494...495, BF 594...595
50905	MPS9625	-/18V, 0,1A, 0,31W, >100MHz	BF 254...255, BF 494...495, BF 594...595
50906	MPS9626	BF 255	BF 255
50907	MPS9630	-/12V, 0,1A, 0,35W	BC 168, BC 172, BC 183, BC 238, BC 548
50908	MPS9631	MPS 9630, -/18V	BC 168, BC 172, BC 183, BC 238, BC 548
50909	MPS9632	MPS 9630, -/30V	BC 167, BC 171, BC 182, BC 237, BC 547
50910	MPS9633	-/30V, 0,05A, 0,31W, >150MHz	BC 413...414, BC 550, 2SC2240, 2SC2675
50911	MPS9634	-/30V, 0,05A, 0,31W, >150MHz	BC 413...414, BC 550, 2SC2240, 2SC2675
50912	MPS9636	BC 548	BC 548
50913	MPS9644	BC 548	BC 548
50914	MPS9656	BF 450	BF 450
50915	MPS9657	BF 450	BF 450
50916	MPS9658	BF 450	BF 450
50917	MPS9666	BC 328	BC 328
50918	MPS9680	BC 559	BC 559
50919	MPS9682	BC 557	BC 557
50920	MPS9686	BC 548	BC 548
50921	MPS9696	BC 546	BC 546
50922	MPSA05	60V, 0,5A, 0,625W, >100MHz	BC 337A, BC 637, BC 639, 2SD1616(A)
50923	MPSA06	MPSA 05, 80V	BC 639, 2SD667, 2SD1226, 2SD1616A
50924	MPSA09	50V, 0,05A, 0,35W, 80MHz	BC 184, BC 414, BC 550, 2SC2240
50925	MPSA10	-/40V, 0,1A, 0,21W, >20MHz	BC 167, BC 182, BC 237, BC 547, 2SD767
50926	MPSA12	20V, 0,5A, 0,625W, B>20000	BC 517, BC 617, MPSA 14, MPSA 25
50927	MPSA13	>125MHz, B>5000	BC 517, BC 617, MPSA 25...26
50928	MPSA14	MPSA 13, B>10000	BC 517, BC 617, MPSA 25...26
50929	MPSA16	-/40V, 0,1A, 0,625W, >100MHz	2SC3069, 2SC3114, 2SC3135, 2SC3836
50930	MPSA17	-/40V, 0,1A, 0,625W, >80MHz	2SC3069, 2SC3114, 2SC3135, 2SC3836
50931	MPSA18	B>500	BC 184, BC 413...414, BC 550, 2SC3112...13
50932	MPSA20	-/40V, 0,1A, 0,35W, >125MHz	BC 167, BC 183, BC 237, BC 547, 2SD767
50933	MPSA23	-/80V, 2A, 0,625W, B>5000	2SD1153, 2SD1579, 2SD1978, 2SD1981
50934	MPSA24	MPSA 23, -/100V	2SD1579, 2SD1978, 2SD2067, 2SD2206
50935	MPSA25	40V, 0,5A, 0,625W, B>10000	BC 517, BC 617, 2SC4009
50936	MPSA26	MPSA 25, 50V	BC 617...618
50937	MPSA27	MPSA 25, 60V	BC 618
50938	MPSA28	80V, 0,5A, 0,625W, B>10000	BC 618
50939	MPSA29	MPSA 28, 100V	-

50940	MPSA42	>50MHz	BF 393, BF 420A, BFP 25, 2SD1350
50941	MPSA43	MPSA 42, 200/200V	BF 391...393, BF 420A, BFP 22, BFP 25
50942	MPSA44	>20MHz	2SD1350A, 2SD593
50943	MPSA45	MPSA44, 400/350V	2SD1350, 2SD593
50944	MPSA55	60V, 0,5A, 0,625A, >100MHz	BC 327A, BC 638, BC 640, 2SB1116(A)
50945	MPSA56	MPSA 55, 80V	BC 640, 2SB647, 2SB910, 2SB1116A
50946	MPSA62	20V, 0,5A, 0,625W, B>20000	BC 516, 2SA790, 2SA1555
50947	MPSA63	MPSA 62, 30V, B>5000	BC 516, 2SA790, 2SA1555
50948	MPSA64	MPSA 62, 30V, B>10000	BC 516, 2SA790, 2SA1555
50949	MPSA65	30V, 0,3A, 0,625W, B>50000	BC 516
50950	MPSA66	MPSA 65, B>75000	BC 516
50951	MPSA70	-/40V, 0,1A, 0,35W, >125MHz	BC 213, BC 257, BC 307, BC 557, 2SB725
50952	MPSA75	40V, 0,5A, 0,625W, B>10000	BC 516, 2SA790, 2SA1555
50953	MPSA76	MPSA 75, 50V	2SB888, 2SB1405
50954	MPSA77	MPSA 75, 60V	2SB888, 2SB1405
50955	MPSA92	>50MHz	BF 493, BF 421A, BFP 26, 2SB1074
50956	MPSA93	MPSA 92, 200/200V	BF 491...493, BF 423A, BFP 23, BFP 26
50957	MPSD01	>40MHz	BF 298...299, BFR 88...89, BFT 58...59
50958	MPSD02	>40MHz	BF 297...299, BFR 87...89, BFT 57...59
50959	MPSD03	MPSD 02, 100/100V	BF 297...299, BFR 87...89, BFT 57...59
50960	MPSD04	25V, 0,3A, 0,625W, B>2000	BC 517, BC 617, MPSA 13...14
50961	MPSD05	25V, 0,5A, 0,35W, >100MHz	BC 337...338, BC 635, BC 637, 2SC3377
50962	MPSD06	-/25V, 0,05A, 0,35W, >100MHz	BC 168, BC 183, BC 238, BC 548, 2SD767
50963	MPSD51	>40MHz	BF 436...437, 2SA1371, 2SA1624
50964	MPSD52	>40MHz	BF 398, BF 435...437
50965	MPSD53	MPSD 52, 100/100V	BF 398, BF 435...437, BSS 68
50966	MPSD54	25V, 0,3A, 0,625W, B>2000	BC 516, BC 876, MPSA 63...64
50967	MPSD55	25V, 0,5A, 0,35W, >100MHz	BC 327...328, BC 636, BC 638, 2SA1515
50968	MPSD56	-/25V, 0,05A, 0,35W, >100MHz	BC 213, BC 258, BC 308, BC 558, 2SB725
50969	MPSH02	20V, 30mA, >375MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50970	MPSH04	-/80V, 0,1A, 180MHz	BC 546, 2SC2240, 2SC2459
50971	MPSH05	-/80V, 0,1A, 180MHz	BC 546, 2SC2240, 2SC2459
50972	MPSH07(A)	30V, 30mA, >400MHz	BF 225, BF 314, BF 496, BF 502, BF 505
50973	MPSH08	MPSH 07, >500MHz	BF 225, BF 314, BF 596, BF 502, BF 505
50974	MPSH10	30V, 50mA, >650MHz	BF 180...183, BF 689, BF 763, 2N2857
50975	MPSH11	30V, 50mA, >650MHz	BF 180...183, BF 689, BF 763, 2N2857
50976	MPSH17	20V, >800MHz	BF 357, BFR 37, BFW 30, BFX 59, BFX 89
50977	MPSH19	30V, >300MHz	BF 224, BF 502...503, BF 505, BF 507
50978	MPSH20	40V, 100mA, 620MHz	BF 224, BF 502...503, BF 505, BF 507
50979	MPSH24	40V, 100mA, 620MHz	BF 224, BF 502...503, BF 505, BF 507
50980	MPSH30	20V, 50mA, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50981	MPSH31	20V, 50mA, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50982	MPSH32	40V, 440MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50983	MPSH33	30V, 950MHz	BF 377...378, BF 689, BF 763, 2N2857
50984	MPSH34	45V, 100mA, 720MHz	BF 199, BF 224, BF 311, BF 373, BF 497

50985	MPSH37	-/40V, 50mA, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
50986	MPSH54	-/80V, 0,1A, 185MHz	BC 556, 2SA970, 2SA1049, 2SA1136
50987	MPSH55	-/80V, 0,1A, 185MHz	BC 556, 2SA970, 2SA1049, 2SA1136
50988	MPSH69	15V, 0,35W, >2000MHz	2SA1161
50989	MPSH81	20V, 50mA, >600MHz	BF 272, BF 316, BF 516, BF 606, BFR 38
50990	MPSH83	30V, 950MHz	BF 272, BF 316, BF 516, BF 606, BFR 38
50991	MPSH85	30V, >350MHz	BF 324, BF 414, BF 505, BF 914, BF 939
50992	MPSK20	3x MPSA 20	MPSA 20
50993	MPSK21	5x MPSA 20	MPSA 20
50994	MPSK22	9x MPSA 20	MPSA 20
50995	MPSK71	5x MPSA 70	MPSA 70
50996	MPSK72	9x MPSA 70	MPSA 70
50997	MPSL01	>60MHz	BF 422A, BF 297...299, BFR 87...89
50998	MPSL01A	MPSL 01, 140/140V	BF 422A, BF 297...299, BFR 87...89
50999	MPSL01B	MPSL 01, 170/170V	BF 422A, BF 298...299, BFR 88...89
51000	MPSL07	<20/40ns	BSX 36, 2N5056...57
51001	MPSL08	MPSL 07, 12V, >1,2GHz	BSX 36, 2N5056...57
51002	MPSL51	100V, 0,6A, 0,625W, >60MHz	BC 640, BCX 23, BCX 39, 2SA965, 2SB647
51003	MPSU01	40V, 2A, 10W, >50MHz	BC 365, BD 507, BD 515, BD 525
51004	MPSU01A	MPSU 01, 50V	BC 365, BD 509, BD 517, BD 525
51005	MPSU02	60V, 0,8A, 10W, >150MHz	BC 366, BD 517, BD 525, 2SC2194
51006	MPSU03	120/120V, 1A, 10W, >100MHz	BF 466...468, 2SC2384
51007	MPSU04	MPSU 03, 180/180V	BF 466...468
51008	MPSU05	60V, 2A, 10W, 170MHz	BC 366, BD 517, BD 525
51009	MPSU06	MPSU 05, 80V	BC 367, BD 519, BD 527
51010	MPSU07	100V, 2A, 10W, 175MHz	BD 529
51011	MPSU10	300/300V, 0,5A, 10W, >60MHz	BF 382, BF 461...462
51012	MPSU31	65V, 0,5A, PQ>3,5W(27MHz)	-
51013	MPSU45	B>25000	BD 411...412
51014	MPSU51	40V, 2A, 10W, >50MHz	BC 362, BD 508, BD 516, BD 526
51015	MPSU51A	MPSU 51, 50V	BC 362, BD 510, BD 518, BD 526
51016	MPSU52	60V, 1,5A, 10W, >150MHz	BC 363, BD 518, BD 526, 2SA962
51017	MPSU55	60V, 2A, 10W, 100MHz	BC 363, BD 518, BD 526
51018	MPSU56	MPSU 55, 80V	BC 364, BD 520, BD 528
51019	MPSU57	100V, 2A, 10W, 100MHz	BD 530
51020	MPSU60	300/300V, 0,5A, 10W, >60MHz	BF 464...465
51021	MPSU95	B>25000	BD 413...414
51022	MPSW01	40V, 1A, 1W, >50MHz	2SD667(A), 2SD863, 2SD1292, 2SD1331
51023	MPSW01A	MPSW 01, 50V	2SD667(A), 2SD863, 2SD1292
51024	MPSW05	60V, 0,5A, 1W, >50MHz	2SC2235, 2SC3939, 2SD1211, 2SD1937
51025	MPSW06	MPSW 05, 80V	2SC2235, 2SC3939, 2SD1211, 2SD1937
51026	MPSW10	300/300V, 0,5A, 1W, >45MHz	BF 393, BF 420A, BFP 25, MPSA 42
51027	MPSW13	B>10000	BC 617...618, 2SD1198A, 2SD2258
51028	MPSW14	MPSW 13, B>20000	BC 617...618, 2SD1198A, 2SD2258
51029	MPSW42	300/300V, 0,5A, 1W, >50MHz	BF 393, BF 420A, BFP 25, MPSA 42

51030	MPSW43	MPSW 42, 200/200V	BF 391, BF 422A, BFP 22, MPSA 42...43
51031	MPSW45	B>25000	-
51032	MPSW45A	MPSW 45, 60V	-
51033	MPSW51	40V, 1A, 1W, >50MHz	2SB647(A), 2SB764, 2SB978, 2SB1041
51034	MPSW51A	MPSW 51, 50V	2SB647(A), 2SB764, 2SB1041
51035	MPSW55	60V, 0,5A, 1W, >50MHz	2SA965, 2SA1533, 2SB987, 2SB1297
51036	MPSW56	MPSW 55, 80V	2SA965, 2SA1533, 2SB987, 2SB1297
51037	MPSW60	300/300V, 0,5A, 1W, >60MHz	BF 493, BF 421A, BFP 26, MPSA 92
51038	MPSW63	B>10000	BC 516, 2SB888, 2SB1405
51039	MPSW64	MPSW 63, B>20000	BC 516, 2SB888, 2SB1405
51040	MPSW92	300/300V, 0,5A, 1W, >50MHz	BF 493, BF 421A, BFP 26, MPSA 92
51041	MPSW93	MPSW 92, 200/200V	BF 491, BF 423A, BFP 23, MPSA 92...93
51042	MPT20	1N5758	1N5758
51043	MPT28	1N5760	1N5760
51044	MPT32	1N5761	1N5761
51045	MPU131	2N6116	2N6116
51046	MPU132	2N6117	2N6117
51047	MPU133	2N6118	2N6118
51048	MPU231	2N6116	2N6116
51049	MPU232	2N6117	2N6117
51050	MPU233	2N6118	2N6118
51051	MPU6027	2N6027	2N6027
51052	MPU6028	2N6028	2N6028
51053	MQ	P6 SMB-75	P6 SMB-75
51054	MQ	HR 1F3P	HR 1...
51055	MQ	SM 6T 30C	SM 6T...
51056	MR	P6 SMB-75A	P6 SMB-75A
51057	MR	MA 157	MA 157
51058	MR	SM 6T 30CA	SM 6T...
51059	MR	HR 1L3N	HR 1...
51060	MR-1	400V, 1,2A	BY 226...227, BY 252...255, 1N5395...99
51061	MR-1C	MR-1, 1000V	BY 227, BY 255, GP 15M, 1N5399
51062	MR-1Z	MR-1, 200V	BY 226...227, BY 251...255, 1N5393...99
51063	MR05	50V, 0,1A, <1μs	BA 157...159, BAY 18...21, BY 204/4
51064	MR1-1000	1000V, 1A	BY 228, BY 448, EM 513, GP 10Q...Y
51065	MR1-1200	1200V, 1A	BY 228, BY 448, EM 513, GP 10Q...Y
51066	MR1-1400	1400V, 1A	BY 228, BY 448, EM 516, GP 10V...Y
51067	MR1-1600	1600V, 1A	BY 228, BY 448, EM 516, DM 513, GP 10Y
51068	MR1030...1040R	1N4719R..4725R	1N4719R...4725R
51069	MR1030A	1N4719	1N4719
51070	MR1031A	1N4720	1N4720
51071	MR1032A	1N4721	1N4721
51072	MR1033A	1N4721, 300V	1N4722
51073	MR1034A	1N4722	1N4722
51074	MR1035A	1N4722, 500V	1N4723

51075	MR1036A	1N4723	1N4723
51076	MR1038A	1N4724	1N4724
51077	MR1040A	1N4725	1N4725
51078	MR11	MR 05, 100V	BA 157...159, BAY 19...21, BY 204/4
51079	MR1120	50V, 12A	BYW 88/50, BYX 75, BYX 99/300, 1N4506
51080	MR1120R	MR 1120	BYW 88/50R, BYX 75R, BYX 99/300R
51081	MR1121	MR 1120, 100V	BYW 88/100, BYX 76, BYX 99/300, 1N4506
51082	MR1121R	MR 1121	BYW 88/100R, BYX 76R, BYX 99/300R
51083	MR1122	MR 1120, 200V	BYW 88/200, BYX 77, BYX 99/300, 1N4506
51084	MR1122R	MR 1122	BYW 88/200R, BYX 77R, BYX 99/300R
51085	MR1123	MR 1120, 300V	BYW 88/300, BYX 78, BYX 99/300, 1N4507
51086	MR1123R	MR 1123	BYW 88/300R, BYX 78R, BYX 99/300R
51087	MR1124	MR 1120, 400V	BYW 88/400, BYX 78, BYX 99/600, 1N4507
51088	MR1124R	MR 1124	BYW 88/400R, BYX 78R, BYX 99/600R
51089	MR1125	MR 1120, 500V	BYW 88/500, BYX 79, BYX 99/600, 1N4508
51090	MR1125R	MR 1125	BYW 88/500R, BYX 79R, BYX 99/600R
51091	MR1126	MR 1120, 600V	BYW 88/600, BYX 79, BYX 99/600, 1N4508
51092	MR1126R	MR 1126	BYW 88/600R, BYX 79R, BYX 99/600R
51093	MR1128	MR 1120, 800V	BYW 88/800, BYX 80, BYX 99/900, 1N4509
51094	MR1128R	MR 1128	BYW 88/800R, BYX 80R, BYX 99/900R
51095	MR1130	MR 1120, 1000V	BYW88/1000, BYX81, BYX99/1200, 1N4510
51096	MR1130R	MR 1130	BYW 88/1000R, BYX 81R, BYX 99/1200R
51097	MR1337-1	50V, 1A, <200ns	BY 201/2, BYV 12, RGP 10A, RGP 15A
51098	MR1337-2	MR 1337-1, 100V	BY 201/2, BYV 12, RGP 10B, RGP 15B
51099	MR1337-3	MR 1337-1, 200V	BY 201/2, BYV 13, RGP 10D, RGP 15D
51100	MR1337-4	MR 1337-1, 300V	BY 201/4, BYV 13, RGP 10G, RGP 15G
51101	MR1337-5	MR 1337-1, 400V	BY 201/4, BYV 13, RGP 10G, RGP 15G
51102	MR1366	600V, 6A, <200ns	BYX 50/600
51103	MR1366R	MR 1366	BYX 50/600R
51104	MR1376	600V, 12A, <200ns	BYT 61/600, BYX 62/600, BYX 66/600
51105	MR1376R	MR 1376	BYT 61/600R, BYX 62/600R, BYX 66/600R
51106	MR1386	600V, 20A, <200ns	BYX 63/600
51107	MR1386R	MR 1386	BYX 63/600R
51108	MR1396	600V, 30A, <200ns	BYT 65/600, BYX 64/600, BYX 67/600
51109	MR1396R	MR 1396	BYT 65/600R, BYX 64/600R, BYX 67/600R
51110	MR2000	50V, 20A	BYX 25/600, BYX 96/300
51111	MR2000R...2010R	MR 2000..2010	BYX 25/...R, BYX 96/...R
51112	MR2001	MR 2000, 100V	BYX 25/600, BYX 96/300
51113	MR2002	MR 2000, 200V	BYX 25/600, BYX 96/300
51114	MR2004	MR 2000, 400V	BYX 25/600, BYX 96/600
51115	MR2006	MR 2000, 600V	BYX 25/600, BYX 96/600
51116	MR2008	MR 2000, 800V	BYX 25/800, BYX 96/900
51117	MR2010	MR 2000, 1000V	BYX 25/1000, BYX 96/1200
51118	MR21	MR 05, 250V	BA 157...159, BAY 21, BAY 46, BY 204/4
51119	MR2271	1N4935, 300V	1N4936

51120	MR2272	400V, 1A, <1,5μs	BY 201/4, BYX 55/600, RGP 10G, MR 814
51121	MR2273	MR 2266, 200V	BY 201/2, BYX 55/350, RGP 10D, MR 812
51122	MR2400	50V, 24A	BYT 30/600
51123	MR2400F..2406F	MR 2400..2406, <200ns	BYT 30/600
51124	MR2400R..2406R	MR 2400..2406	-
51125	MR2401	MR 2400, 100V	BYT 30/600
51126	MR2402	MR 2400, 200V	BYT 30/600
51127	MR2404	MR 2400, 400V	BYT 30/600
51128	MR2406	MR 2400, 600V	BYT 30/600
51129	MR250-1	1kV, 0,25A	GP 02-20, 1N1732A
51130	MR250-2	MR 250-1, 2kV	GP 02-20, 1N1732A
51131	MR250-3	MR 250-1, 3kV	GP 02-30, 1N1733A
51132	MR250-4	MR 250-1, 4kV	GP 02-40, 1N1734A
51133	MR250-5	MR 250-1, 5kV	1N1734A
51134	MR251	BY 251	BY 251
51135	MR2520L	24..32V, 68A(Ifsm)	-
51136	MR2525L	24..32V, 110A(Ifsm)	-
51137	MR2530L	24..32V, 150A(Ifsm)	-
51138	MR2535L	24..32V, 600A(Ifsm)	-
51139	MR2540L	24..32V, 800A(Ifsm)	-
51140	MR31	MR 05, 350V	BA 157...159, BAY 89, BY 204/4
51141	MR41	MR 05, 450V	BA 158...159, BAY 89, BY 204/8
51142	MR4422CT	100V, 2x15A(Tc125°)	BYV 72/100, BYW 99/100, MUR 3010
51143	MR4422CTR	MR 4422CT	
51144	MR500	50V, 3A	BY 251...255, GP 30A...M, 1N5400...08
51145	MR5005	50V, 50A	-
51146	MR501	MR 500, 100V	BY 251...255, GP 30B...M, 1N5401...08
51147	MR5010	MR 5005, 100V	-
51148	MR502	MR 500, 200V	BY 251...255, GP 30D...M, 1N5402...08
51149	MR5020	MR 5005, 200V	-
51150	MR5030	MR 5005, 300V	-
51151	MR504	MR 500, 400V	BY 252...255, GP 30G...M, 1N5404...08
51152	MR5040	MR 5005, 400V	-
51153	MR506	MR 500, 600V	BY 253...255, GP 30J...M, 1N5406...08
51154	MR5060	400V, 1,5A	BYD 13G...M, BYD 34G...M, BYW 53...56
51155	MR5061	MR 5060, 600V	BYD 13J...M, BYD 34J...M, BYW 54...56
51156	MR508	MR 500, 800V	BY 254...255, GP 30K...M, 1N5407...08
51157	MR510	MR 500, 1000V	BY 228, BY 255, GP 30M, 1N5408
51158	MR52Z	500V, 0,2A, <200ns	BYX 57/500
51159	MR62Z	MR 52Z, 600V	BYX 57/600
51160	MR750	50V, 6A	BY 214/50.../1000
51161	MR751	MR 750, 100V	BY 214/100.../1000
51162	MR752	MR 750, 200V	BY 214/200.../1000
51163	MR754	MR 750, 400V	BY 214/400.../1000
51164	MR756	MR 750, 600V	BY 214/600.../1000



51165	MR758	MR 750, 800V	BY 214/800.../1000
51166	MR760	MR 750, 1000V	BY 214/1000
51167	MR810	50V, 1A, <750ns	BY 231/800, BY 245/800, RGP 10A...M
51168	MR811	MR 810, 100V	BY 231/800, BY 245/800, RGP 10B...M
51169	MR812	MR 810, 200V	BY 231/800, BY 245/800, RGP 10D...M
51170	MR813	MR 810, 300V	BY 231/800, BY 245/800, RGP 10G...M
51171	MR814	MR 810, 400V	BY 231/800, BY 245/800, RGP 10G...M
51172	MR816	MR 810, 600V	BY 231/800, BY 245/800, RGP 10J...M
51173	MR817	MR 810, 800V	BY 231/800, BY 245/800, RGP 10K...M
51174	MR818	MR 810, 1000V	BY 231/1000, BY 245/1200, RGP 10M
51175	MR820	50V, 5A, <200ns	FE 5A, EGP 50A, BY 229/200, RGP 80A
51176	MR821	MR 820, 100V	FE 5B, EGP 50B, BY 229/200, RGP 80B
51177	MR822	MR 820, 200V	FE 5D, EGP 50D, BY 229/200, RGP 80D
51178	MR824	MR 820, 400V	BY 229/400, BY 359/1000, RGP 80G
51179	MR826	MR 820, 600V	BY 229/600, BY 359/1000, RGP 80J
51180	MR828	MR 820, 800V	BY 229/800, BY 359/1000, RGP 80K
51181	MR830	50V, 3A, <200ns	BY 318/100, BY 396, BYW 72, BYW 95A
51182	MR831	MR 830, 100V	BY 318/100, BY 396, BYW 72, BYW 95A
51183	MR832	MR 830, 200V	BY 318/200, BY 397, BYW 72, BYW 95A
51184	MR834	MR 830, 400V	BY 318/400, BY 398, BYW 74, BYW 95B
51185	MR836	MR 830, 600V	BY 318/600, BY 399, BYW 76, BYW 95C
51186	MR840...846	MR 830..836, <1μs	MR 830...836
51187	MR850	50V, 3A, <200ns	BY 318/100, BYW 16/100, BYW 72, BYW 95A
51188	MR850GP..856GP	MR 850..856, <150ns	MR 850...856
51189	MR851	MR 850, 100V	BY 318/100, BYW 16/100, BYW 72, BYW 95A
51190	MR852	MR 850, 200V	BY 318/200, BYW 16/200, BYW 72, BYW 95A
51191	MR854	MR 850, 400V	BY 318/400, BYW 16/400, BYW 74, BYW 95B
51192	MR856	MR 850, 600V	BY 318/600, BYW 16/600, BYW 76, BYW 95C
51193	MR860	50V, 40A, <200ns	870
51194	MR860R	MR 860	BYW 25/800R, BYW 78/50R, MR 870R
51195	MR861	MR 860, 100V	MR871
51196	MR861R	MR 861	BYW 25/800R, BYW 78/100R, MR 871R
51197	MR862	MR 860, 200V	MR872
51198	MR862R	MR 862	BYW 25/800R, BYW 78/200R, MR 872R
51199	MR864	MR 860, 400V	BYW 25/800, MR 874
51200	MR864R	MR 864	BYW 25/800R, MR 874R
51201	MR866	MR 860, 600V	BYW 25/800, MR 876
51202	MR866R	MR 866	BYW 25/800R, MR 876R
51203	MR870	50V, 50A, <200ns	BYT 60/200, BYW 78/50, BYW 93/50
51204	MR870R	MR 870	BYT 60/200R, BYW 78/50R
51205	MR871	MR 870, 100V	BYT 60/200, BYW 78/100, BYW 93/100
51206	MR871R	MR 871	BYT 60/200R, BYW 78/100R
51207	MR872	MR 870, 200V	BYT 60/200, BYW 78/200, BYW 93/200
51208	MR872R	MR 872	BYT 60/200R, BYW 78/200R
51209	MR874	MR 870, 400V	BYT 60/400

51210	MR874R	MR 874	BYT 60/400R
51211	MR876	MR 870, 600V	-
51212	MR876R	MR 876	-
51213	MR880	50V, 12A, <1 $\mu$ s	BYT 61/600, BYX 30/200, BYX 61/50
51214	MR881	MR 880, 100V	BYT 61/600, BYX 30/200, BYX 61/100
51215	MR882	MR 880, 200V	BYT 61/600, BYX 30/200, BYX 61/200
51216	MR884	MR 880, 400V	BYT 61/600, BYX 30/400, BYX 61/400
51217	MR886	MR 880, 600V	BYT 61/600, BYX 30/600, BYX 61/600
51218	MR890	50V, 30A, <1 $\mu$ s	BYT 65/600, BYX 64/600, BYX 67/400
51219	MR891	MR 890, 100V	BYT 65/600, BYX 64/600, BYX 67/400
51220	MR892	MR 890, 200V	BYT 65/600, BYX 64/600, BYX 67/400
51221	MR894	MR 890, 400V	BYT 65/600, BYX 64/600, BYX 67/400
51222	MR896	MR 890, 600V	BYT 65/600, BYX 64/600, BYX 67/600
51223	MR910	50V, 3A, <750ns	BY 318/100, BY 396, BYW 72, RGP 30A
51224	MR911	MR 910, 100V	BY 318/100, BY 396, BYW 72, RGP 30B
51225	MR912	MR 910, 200V	BY 318/200, BY 397, BYW 72, RGP 30D
51226	MR914	MR 910, 400V	BY 318/400, BY 398, BYW 74, RGP 30G
51227	MR916	MR 910, 600V	BY 318/600, BY 399, BYW 76, RGP 30J
51228	MR917	MR 910, 800V	BY 228, BY 399, BY 458, RGP 30K
51229	MR918	MR 910, 800V	BY 228, BY 448, BY 458, RGP 30M
51230	MR990A	1kV, 0,25A	GP 02-20, MR 250-1
51231	MR991A	MR 990A, 1,5kV	GP 02-20, MR 250-2
51232	MR992A	MR 990A, 2kV	GP 02-20, MR 250-2
51233	MR993A	MR 990A, 2,5kV	GP 02-25, MR 250-3
51234	MR994A	MR 990A, 3kV	GP 02-30, MR 250-3
51235	MR995A	MR 990A, 4kV	GP 02-40, MR 250-4
51236	MR996A	MR 990A, 5kV	MR 250-5
51237	MRF0211	30V, 70mA, 5,5GHz	BFP 193, 2SC4092
51238	MRF10005	55V, 1,25A, PQ5W(1215MHz)	-
51239	MRF1000MA	50V, 0,2A, PQ0,7W(1090MHz)	-
51240	OMB	MRF 1000MA..1090MA	-
51241	OMC	MRF 1000MA..1090MA	-
51242	MRF1002MA	50V, 0,25A, PQ2W(1090MHz)	-
51243	MRF10030	55V, 5A, PQ30W(1215MHz)	-
51244	MRF1004MA	50V, 0,25A, PQ4W(1090MHz)	-
51245	MRF1008MA	50V, 0,5A, PQ8W(1090MHz)	-
51246	MRF1015MA	60V, 1A, PQ15W(1090MHz)	-
51247	MRF1035MA	60V, 2A, PQ35W(1090MHz)	-
51248	MRF1090MA	70V, 6A, PQ90W(1090MHz)	-
51249	MRF1150M	70V, 12A, PQ150W(1090MHz)	-
51250	MRF1150MA	MRF 1150M	-
51251	MRF1150MB	MRF 1150M	-
51252	MRF1150MC	MRF 1150M	-
51253	MRF1250M	70V, 24A, PQ250W(1090MHz)	-
51254	MRF1325M	70V, 24A, PQ325W(1090MHz)	-

51255	MRF134	65V, 0,9A, PQ5W(400MHz)	-
51256	MRF136	65V, 2,5A, PQ15W(150MHz)	-
51257	MRF137	65V, 5A, PQ30W(150MHz)	-
51258	MRF138	65V, 6A, PEP30W(30MHz)	-
51259	MRF140	65V, 16A, PEP150W(30MHz)	-
51260	MRF148	120V, 6A, PEP30W(30MHz)	-
51261	MRF150	125V, 16A, PEP150W(30MHz)	-
51262	MRF161	65V, 0,9A, PQ5W(400MHz)	-
51263	MRF162	65V, 2,5A, PQ15W(400MHz)	-
51264	MRF163	65V, 5A, PQ25W(400MHz)	-
51265	MRF171	65V, 4,5A, PQ45W(150MHz)	-
51266	MRF172	65V, 9A, PQ80W(150MHz)	-
51267	MRF174	65V, 13A, PQ125W(150MHz)	-
51268	MRF1946	36V, 8A, PQ30W(175MHz)	-
51269	MRF1946A	MRF 1946	-
51270	MRF2001	45V, 0,25A, PQ1W(2GHz)	-
51271	M	MRF 2001..2010	-
51272	MRF2003	45V, 0,5A, PQ3W(2GHz)	-
51273	MRF2005	45V, 1A, PQ5W(2GHz)	-
51274	MRF2010	45V, 2A, PQ10W(2GHz)	-
51275	MRF2016M	45V, 3A, PQ16W(2GHz)	-
51276	MRF207	36V, 0,4A, PQ1W(220MHz)	BFR 98, BLW 16, BLY 61, MRF 225, MRF 607
51277	MRF208	36V, 2A, PQ10W(220MHz)	BLW 19, MRF 212, 2N5590
51278	MRF209	36V, 4A, PQ25W(220MHz)	MRF239[Motorola],MRF222, 2N5591, 2N6082
51279	MRF212	36V, 2A, PQ10W(175MHz)	BLW 19, MRF 208, 2N5590
51280	MRF215	36V, 2,5A, PQ20W(175MHz)	-
51281	MRF216	36V, 6A, PQ40W(175MHz)	BLV 45/12
51282	MRF221	36V, 2,5A, PQ15W(175MHz)	BLV 11
51283	MRF222	36V, 4A, PQ25W(175MHz)	BLW 87
51284	MRF223	36V, 4A, PQ30W(175MHz)	BLW 85
51285	MRF224	36V, 6A, PQ40W(175MHz)	BLW 85
51286	MRF225	36V, 0,25A, PQ1,5W(225MHz)	BFR 98, BLW 16, BLY 61, MRF 607
51287	MRF226	36V, 2,5A, PQ13W(225MHz)	MRF 209
51288	MRF227	36V, 0,6A, PQ3W(220MHz)	-
51289	MRF229	36V, 0,5A, PQ1,5W(90MHz)	-
51290	MRF230	MRF 229	BFR 98, BLW 16, BLY 61
51291	MRF231	36V, 1A, PQ3,5W(90MHz)	BLY 85, 2N6080
51292	MRF232	36V, 2A, PQ7,5W(90MHz)	BLW 19, BLW 37, MRF 212, 2SC2985
51293	MRF233	36V, 3,5A, PQ15W(90MHz)	BLY 89, MRF 209, 2N5591, 2N6082
51294	MRF234	36V, 4A, PQ25W(90MHz)	BLY 89, MRF 209, 2N5591, 2N6082
51295	MRF235	PQ50W(90MHz)	BLY 90
51296	MRF2369	30V, 70mA, 6GHz	BFQ 82
51297	MRF237	36V, 1A, PQ4W(175MHz)	-
51298	MRF238	36V, 4A, PQ30W(160MHz)	BLW 20, BLW 31, 2N6083
51299	MRF239	36V, 6A, PQ30W(160MHz)	BLW 20, BLW 31, 2N6084

51300	MRF240	36V, 8A, PQ40W(160MHz)	BLW 60
51301	MRF240A	MRF 240	BLW 85
51302	MRF243	36V, 15A, PQ60W(175MHz)	-
51303	MRF244	36V, 20A, PQ70W(175MHz)	MRF 247[Motorola]
51304	MRF245	36V, 20A, PQ80W(175MHz)	MRF 247[Motorola]
51305	MRF247	36V, 20A, PQ75W(175MHz)	MFR 245, 2SC2694, 2SC2782
51306	MRF260	36V, 1A, PQ5W(175MHz)	-
51307	MRF261	36V, 2A, PQ10W(175MHz)	-
51308	MRF262	36V, 2,5A, PQ15W(175MHz)	-
51309	MRF2628	36V, 2,5A, PQ15W(175MHz)	-
51310	MRF264	36V, 6A, PQ30W(175MHz)	-
51311	MRF304	60V, 2A, PQ10W(400MHz)	-
51312	MRF305	60V, PQ30W(400MHz)	MRF 325[Motorola], MRF 326
51313	MRF306	60V, PQ60W(400MHz)	MRF 375, 2N6439
51314	MRF309	60V, PQ50W(450MHz)	MRF 375, 2N6439
51315	MRF313	40V, 0,15A, PQ1W(400MHz)	MRF 509
51316	MRF313A	MRF 313	BFT 91, BLW 89, BLX 91
51317	MRF314	65V, 3,4A, PQ30W(150MHz)	BLW 86
51318	MRF314A	MRF 314	BLX 39
51319	MRF315	65V, 4A, PQ45W(150MHz)	-
51320	MRF315A	MRF 315	BLX 39
51321	MRF316	65V, 9A, PQ80W(150MHz)	-
51322	MRF317	65V, 12A, PQ100W(150MHz)	-
51323	MRF321	60V, 1,1A, PQ10W(400MHz)	BLW 91
51324	MRF323	60V, 2,2A, PQ20W(400MHz)	BLX 94
51325	MRF325	60V, 3,4A, PQ30W(400MHz)	-
51326	MRF326	60V, 4,5A, PQ40W(400MHz)	2N6439
51327	MRF327	60V, 9A, PQ80W(400MHz)	-
51328	MRF329	60V, 9A, PQ100W(400MHz)	-
51329	MRF331	60V, 1,1A, PQ10W(400MHz)	BLW 91, MRF 321
51330	MRF338	60V, 9A, PQ80W(470MHz)	-
51331	MRF340	65V, 1A, PQ8W(136MHz)	-
51332	MRF342	65V, 2,2A, PQ24W(136MHz)	-
51333	MRF344	65V, 5A, PQ60W(136MHz)	-
51334	MRF390	60V, 7A, PQ60W(400MHz)	-
51335	MRF392	60V, 16A, PQ125W(400MHz)	-
51336	MRF393	60V, 16A, PQ100W(500MHz)	-
51337	MRF401	-/30V, 3,3A, PEP25W(30MHz)	-
51338	MRF402	36V, 0,5A, PQ1W(50MHz)	-
51339	MRF404	60V, 0,5A	-
51340	MRF406	40V, 4A, PEP20W(30MHz)	2SC2099
51341	MRF4070	36V, 20A, PQ70W(175MHz)	-
51342	MRF410	65V, 1,5A, PEP10W(30MHz)	-
51343	MRF410A	MRF 410	-
51344	MRF412	36V, 20A, PEP70W(30MHz)	-

51345	MRF412A	MRF 412	-
51346	MRF420	45V, 10A, PEP75W(30MHz)	MRF 454[Motorola], 2SC2100
51347	MRF421	45V, 20A, PEP100W(30MHz)	2SC2510, 2SC2879
51348	MRF422	85V, 20A, PEP150W(30MHz)	BLW 97
51349	MRF426	65V, 3A, PEP25W(30MHz)	BLW 83
51350	MRF426A	MRF 426	MRF 401
51351	MRF427	110V, 6A, PEP25W(30MHz)	-
51352	MRF427A	MRF 427	-
51353	MRF428	110V, 20A, PEP150W(30MHz)	-
51354	MRF428A	MRF 428	-
51355	MRF429	100V, 16A, PEP150W(30MHz)	-
51356	MRF432	36V, 2,5A, PEP12,5W(30MHz)	-
51357	MRF433	36V, 2,5A, PEP12,5W(30MHz)	MRF 406, 2SC2395
51358	MRF435	60V, 16A, PEP150W(30MHz)	-
51359	MRF448	100V, 16A, PEP250W(30MHz)	-
51360	MRF449	40V, PQ30W(30MHz)	-
51361	MRF449A	MFR 449	-
51362	MRF450	40V, 7,5A, PQ50W(30MHz)	-
51363	MRF450A	MRF 450	-
51364	MRF452	45V, 12A	MRF 453[Motorola]
51365	MRF452A	MRF 452	-
51366	MRF453	36V, 15A, PQ60W(30MHz)	MRF 455
51367	MRF453A	MRF 453	MRF 455A
51368	MRF454	45V, 20A, PQ80W(30MHz)	BLW 99, 2SC2290
51369	MRF454A	MRF 454	-
51370	MRF455	36V, 15A, PQ60W(30MHz)	MRF 453
51371	MRF455A	MRF 455	MRF 453A
51372	MRF458	36V, 10A, PQ80W(30MHz)	-
51373	MRF458A	MRF 456	-
51374	MRF460	40V, 15A, PEP40W(30MHz)	2SC2100
51375	MRF463	65V, 10A, PEP80W(30MHz)	-
51376	MRF464	65V, 10A, PEP80W(30MHz)	-
51377	MRF464A	MRF 464	-
51378	MRF466	65V, 6A, PEP40W(30MHz)	-
51379	MRF472	65V, 1A	-
51380	MRF475	48V, 4A, PEP12W(30MHz)	2SC1969, 2SC2075, 2SC2098, 2SC2207
51381	MRF476	36V, 1A, PEP3W(30MHz)	2SC1678
51382	MRF477	36V, 5A, PEP40W(30MHz)	-
51383	MRF479	36V, 2A, PEP15W(30MHz)	-
51384	MRF485	65V, 1A, PEP15W(30MHz)	-
51385	MRF486	65V, 3A, PEP40W(30MHz)	-
51386	MRF492	36V, 20A, PQ70W(50MHz)	-
51387	MRF492A	MRF 492	-
51388	MRF497	36V, 6A, PQ40W(50MHz)	-
51389	MRF501	1GHz	BFR 37, BFW 30, BFX 73

51390	MRF502	1,2GHz	BFR 37, BFW 30, BFX 73
51391	MRF509	55V, 0,4A, PQ1W(400MHz)	MRF 313A
51392	MRF511	35V, 0,25A, 2,1GHz	BFT 98
51393	MRF515	35V, 0,15A, PQ0,75W(470MHz)	BFS 50, 2N3948
51394	MRF517	35V, 0,15A, PQ2W(300MHz)	-
51395	MRF5174	60V, 0,5A, PQ2W(400MHz)	BLW 90, BLW 92, BLX 92
51396	MRF5175	60V, 1A, PQ5W(400MHz)	BLW 93, BLX 93, MRF 321, MFR 331
51397	MRF5176	60V, 2A, PQ15W(400MHz)	BLW 94, BLX 94, MRF 323
51398	MRF5177	60V, 4A, PQ30W(400MHz)	-
51399	MRF5177A	MRF 5177	-
51400	MRF519	35V, 0,25A, >2,2GHz	-
51401	MRF521	20V, 70mA, 4,2GHz	BFG 32, BFQ 79
51402	MRF5211(L)	MRF 521, SMD, 70mA	BFP 194
51403	MRF522	20V, 50mA, 4200GHz	BFG 32, BFQ 79
51404	MRF524	20V, 50mA, 4200GHz	2SA1228
51405	MRF525	35V, 0,15A, PQ0,08W(400MHz)	-
51406	MRF531	100V, 800MHz	-
51407	MRF532	80V, >500MHz	-
51408	MRF534	15V, 0,03A, >4GHz	BFQ 24
51409	MRF536	15V, 0,03A, >5GHz	2SA1230
51410	MRF542	120V, 0,4A	-
51411	MRF543	100V, 0,4A	-
51412	MRF544	120V, 0,4A	-
51413	MRF545	100V, 0,4A	-
51414	MRF546	120V, 0,6A	-
51415	MRF547	100V, 0,6A	-
51416	MRF548	120V, 0,4A	-
51417	MRF549	100V, 0,4A	-
51418	MRF553	36V, 0,5A, PQ1,5W(175MHz)	-
51419	MRF555	36V, 0,4A, PQ1,5W(470MHz)	-
51420	MRF557	36V, 0,4A, PQ1,5W(870MHz)	-
51421	MRF559	36V, 0,15A, PQ0,5W(870MHz)	MRF 816, MRF 838
51422	MRF571	20V, 0,07A, 8GHz	2SC3358, 2SC3603
51423	MRF5711(L)	BF 430(L)	BF 430
51424	MRF572	20V, 0,07A, 8GHz	2SC3358, 2SC3603
51425	MRF573	20V, 0,07A, 8GHz	2SC3358, 2SC3603
51426	MRF580	36V, 0,2A, 5GHz	-
51427	MRF581	MRF 580	-
51428	MRF586	34V, 0,2A, 4,5GHz	-
51429	MRF587	MRF 586	-
51430	MRF603	36V, 2A, PQ10W(175MHz)	BLW 19, MRF 208, MRF 212, 2N5590
51431	MRF604	40V, PQ1W(175MHz)	MRF 207, MRF 225, MRF 607
51432	MRF607	36V, 0,33A, PQ1,75W(175MHz)	MRF 225, MRF 227
51433	MRF618	36V, 2,5A, PQ15W(470MHz)	MRF 641[Motorola], BLU 20/12
51434	MRF619	36V, 6A, PQ25W(470MHz)	MRF 644[Motorola], BLU 30/12



51435	MRF620	36V, 8A, PQ35W(470MHz)	BLW 82, MRF 646
51436	MRF621	36V, 11A, PQ45W(470MHz)	MRF 646[Motorola], BLU 45/12, MRF 648
51437	MRF626	30V, 0,15A, PQ0,5W(470MHz)	BLV 90, MRF 838A
51438	MRF627	MRF 626	MRF 816, MRF 838
51439	MRF628	36V, 0,2A, PQ0,5W(470MHz)	2N6256
51440	MRF629	36V, 0,4A, PQ2W(470MHz)	-
51441	MRF630	36V, 1A, PQ3W(470MHz)	-
51442	MRF641	36V, 3A, PQ15W(470MHz)	BLU 20/12
51443	MRF644	36V, 4A, PQ25W(470MHz)	BLU 30/12
51444	MRF646	36V, 9A, PQ45W(470MHz)	BLU 45/12
51445	MRF648	36V, 11A, PQ60W(470MHz)	BLU 60/12
51446	MRF652	36V, 2A, PQ5W(512MHz)	-
51447	MRF653	38V, 2,75A, PQ10W(512MHz)	-
51448	MRF654	36V, 4A, PQ15W(512MHz)	-
51449	MRF660	36V, 2,4A, PQ7W(470MHz)	-
51450	MRF750	-/13V, 0,2A, PQ0,5W(470MHz)	-
51451	MRF752	-/13V, 1,2A, PQ2,5W(470MHz)	-
51452	MRF754	-/13V, 3A, PQ8W(470MHz)	-
51453	MRF8003	50V, 0,5A, PQ0,5W(27MHz)	MRF 402
51454	MRF8004	50V, 1A, PQ3,5W(27MHz)	-
51455	MRF816	0,175A,PQ0,75W(900MHz)	MRF 838
51456	MRF817	36V, 0,4A, PQ2,5W(900MHz)	BLU 99
51457	MRF818	36V, 1,5A, PQ8W(900MHz)	-
51458	MRF823	36V, 1,5A, PQ>4W	BLU 10/12
51459	MRF824	36V, 2,5A, PQ>13W	BLU 20/12, MRF 641
51460	MRF825	36V, 6A, PQ>25W	BLU 30/12, MRF 644
51461	MRF835	36V, 4A	-
51462	MRF837	36V, 0,2A, PQ0,75W(870MHz)	-
51463	MRF838	36V, 0,3A, PQ1W(870MHz)	BLW 12
51464	MRF838A	MRF 838	2N5944
51465	MRF839	36V, 0,6A, PQ3W(870MHz)	-
51466	MRF839F	MRF 839	-
51467	MRF840	36V, 3,8A, PQ10W(870MHz)	BLV 93
51468	MRF841	36V, 2A, PQ5W(870MHz)	-
51469	MRF841F	MRF 841	-
51470	MRF842	36V, 7,6A, PQ20W(870MHz)	BLV 95
51471	MRF843	36V, 4A, PQ15W(870MHz)	-
51472	MRF843F	MRF 843	-
51473	MRF844	36V, 10,9A, PQ30W(870MHz)	BLV 95
51474	MRF846	36V, 14A, PQ40W(870MHz)	BLV 95
51475	MRF847	38V, 12A, PQ45W(870MHz)	-
51476	MRF870	36V, 0,75A, PQ3W(870MHz)	-
51477	MRF870A	MRF 870	-
51478	MRF873	38V, 2,4A, PQ15W(870MHz)	-
51479	MRF890	55V, 0,5A, PQ2W(900MHz)	-

51480	MRF891	55V, 0,6A, PQ5W(900MHz)	-
51481	MRF892	50V, 2,5A, PQ14W(900MHz)	-
51482	MRF894	50V, 7A, PQ30W(900MHz)	-
51483	MRF898	55V, 10A, PQ60W(900MHz)	-
51484	MRF901	25V, 0,03A, 4,5GHz	BFQ 71, BFQ 85, BFR 14, BFR 91
51485	MRF9011(L)	BF 431(L)	BF 431(L)
51486	MRF902	25V, 0,03A, 4,5GHz	BFQ 71, BFQ 85, BFR 14, BFR 91, 2N6603
51487	MRF904	25V, 0,03A, 4GHz	BFQ 22, BFT 66...67
51488	MRF905	35V, 0,15A, PQ0,5W(1680MHz)	BFG 34, BFR 95
51489	MRF911	20V, 0,04A, 5GHz	BFQ 69, BFQ 85, BFR 14, BFR 91
51490	MRF912	20V, 0,05A, 5GHz	BFP 91, BFQ 72, BFT 65, 2N6604
51491	MRF914	20V, 0,04A, 4,5GHz	BFQ 22, BFT 66...67
51492	MRF931	10V, 5mA, 3GHz	BFG 90, BFQ 28, BFR 49, BFR 90
51493	MRF9331(L)	BF 432(L)	BF 432(L)
51494	MRF941	20V, 0,05A, 8GHz	-
51495	MRF9411(L)	MRF 941, SMD	BFG 67, 2SC4094, 2SC4127
51496	MRF951	20V, 0,1A, 8GHz	-
51497	MRF9511(L)	MRF 951, SMD	BFP 196
51498	MRF961	20V, 0,1A, 4,5GHz	BFG 96, BFP 96, BFQ 73, BFR 96
51499	MRF962	20V, 0,1A, 4,5GHz	BFG 96, BFP 96, BFQ 73, BFR 96
51500	MRF965	20V, 0,1A, 4,5GHz	BFG 96, BFP 96, BFQ 73, BFR 96
51501	MRF966	1GHz, 10V, 80mA	-
51502	MRF967	MRF 966	-
51503	MS	CF 739	CF 739
51504	MS	P6 SMB-82	P6 SMB-82
51505	MS	MA 147	MA 147
51506	MS	MA 157A	MA 157A
51507	MS	HR 1A4M	HR 1...
51508	MS	SM 6T 33C	SM 6T...
51509	MS1045	45V, 10A	MBR 1045...1090
51510	MS106	60V, 1A	BYS 21-90, BYV 10-60, HRP 32, MBR 160
51511	MS1060	60V, 10A	MBR 1060...1090
51512	MS109	90V, 1A	BYS 21-90, HRP 32, MBR 190, SB 190
51513	MS1090	90V, 10A	MBR 1090
51514	MS1635	35V, 16A	MBR 1635...1645
51515	MS1645	45V, 16A	MBR 1645
51516	MS1690	90V, 16A	-
51517	MS306	60V, 3A	BYS 26-90, HRP 34, MBR 360, SB 360
51518	MS309	90V, 3A	BYS 26-90, MBR 390, SB 390
51519	MS345	45V, 3A	BYS 26-45, HRP 34, MBR 350, SB 350
51520	MS506	60V, 5A	SB 560
51521	MS509	90V, 5A	SB 590
51522	MS545	45V, 5A	BYS 27-45, SB 550
51523	MS809	90V, 8A	-
51524	MS845	45V, 8A	BYS 08-45...-50

51525	MSA1022-..	2SA1022-..	2SA1022
51526	MSA7505	65V, 3A, PQ10W(400MHz)	-
51527	MSA8505	65V, 3A, PQ10W(400MHz)	BLW 94, BLX 94, MRF 323
51528	MSA8506	-/18V, 1A	BLU 97, BLW 43, BLW 80, BLX 68, BLY 53
51529	MSA8507	-/18V, 2A	BLW 13...14, BLW 44, 2N5946
51530	MSA8508	-/18V	BLW 15, BLX 69
51531	MSB1218A-..	2SB1218A-..	2SB1218A
51532	MSB492(B,C,D)	25V, 2A, 0,625W, 100MHz	2SA1382, 2SB926...927, 2SB1312
51533	MSB709-..	2SB709-..	2SB709
51534	MSB710-..	2SB710-..	2SB710
51535	MSC1621-..	2SC1621-..	2SC1621
51536	MSC2295-..	2SC2295-..	2SC2295
51537	MSC2404-..	2SC2404-..	2SC2404
51538	MSC3130-..	2SC3130-..	2SC3130
51539	MSD1328-..	2SD1328-..	2SD1328
51540	MSD1819A-..	2SD1819A-..	2SD1819A
51541	MSD601-..	2SD601-..	2SD601
51542	MSD602-..	2SD602-..	2SD602
51543	MSD6150	70V, 0,2A, <100ns	-
51544	MSP145	45V, 1A	BYS 21-45, BYV 10-60, HRP 22, MBR 150
51545	MSP345	45V, 3A	BYS 26-45, HRP 34, MBR 350, SB 350
51546	MSP545	45V, 5A	BYS 27-45, SB 550
51547	MSP835	35V, 8A	BYS 08-45...-50
51548	MSP845	45V, 8A	BYS 08-45...-50
51549	MT	P6 SMB-82A	P6 SMB-82A
51550	MT	MA 141WK	MA 141WK
51551	MT	MA 151WK	MA 151WK
51552	MT	2SC4360	2SC4360
51553	MT	HR 1L2Q	HR 1...
51554	MT	SM 6T 33CA	SM 6T...
51555	MT146	BC 146	BC 146
51556	MT200	BC 200	BC 200
51557	MT9630	MPS 9630	MPS 9630
51558	MTB10N40E	<0,55Ohm(5A)	-
51559	MTB15N06V	<0,12Ohm(7,5A)	-
51560	MTB16N25E	<0,25Ohm(8A)	MTP 16N25E
51561	MTB1N100E	1000V, 1A, 75W, <9Ohm(0,5A)	-
51562	MTB20N20E	<0,16Ohm(10A)	-
51563	MTB23P06V	<0,12Ohm(11,5A)	-
51564	MTB2N40E	400V, 2A, 40W, <3,5Ohm(1A)	2SK1721
51565	MTB2N60E	600V, 2A, 50W, <3,8Ohm(1A)	2SK1746, 2SK1980
51566	MTB2P50E	500V, 2A, 75W, <6Ohm(1A)	MTP 2P50
51567	MTB30N06VL	60V, 30A, 90W, <0,05Ohm	MTP 30N06VL
51568	MTB30P06V	<0,08Ohm(15A)	MTP 30P06V
51569	MTB33N10E	<0,06Ohm(16,5A)	-

51570	MTB35N06ZL	60V, 35A, 94W, <26mOhm	MTP 35N06ZL
51571	MTB36N06V	<40mOhm(16A)	-
51572	MTB3N100E	<4Ohm(1,5A)	2SK2004
51573	MTB3N120E	<5Ohm(1,5A)	MTP 3N120E
51574	MTB4N80E	800V, 4A, 125W, <3Ohm(2A)	2SK2089
51575	MTB50P03HDL	30V, 50A, 125W, <25mOhm	-
51576	MTB52N06V	<22mOhm(26A)	MTP 52N06V
51577	MTB52N06VL	60V, 52A, 165W, <25mOhm	MTP 52N06VL
51578	MTB55N06Z	<16mOhm(15A)	-
51579	MTB60N06HD	<14mOhm(30A)	MTP 60N06HD
51580	MTB6N60E	600V, 6A, 125W, <1,2Ohm(3A)	2SK1915
51581	MTB75N03HDL	25V, 75A, 125W, <9mOhm	MTP 75N03HDL
51582	MTB75N05HD	<9,5mOhm(20A)	MTP 75N05HD
51583	MTB8N50E	500V, 8A, 125W, <0,8Ohm(4A)	-
51584	MTB9N25E	<0,45Ohm(4,5A)	-
51585	MTD10N05E	50V, 10A, 20W, <0,1Ohm(5A)	-
51586	MTD10N10EL	100V, 10A, 40W, <0,22Ohm(5A)	-
51587	MTD12N06EZL	60V, 12A, 45W, <0,18Ohm(6A)	-
51588	MTD15N06V	<0,12Ohm(7,5A)	-
51589	MTD15N06VL	60V, 15A, 60W, <85mOhm	-
51590	MTD1N40	400V, 1A, 20W, <5Ohm(0,5A)	2SK535, 2SK579...580, 2SK1672
51591	MTD1N50E	500V, 1A, 40W, <5Ohm(0,5A)	-
51592	MTD1N60E	600V, 1A, 40W, <8Ohm(0,5A)	-
51593	MTD1N80E	800V, 1A, 48W, <12Ohm(0,5A)	-
51594	MTD1P50E	500V, 1A, 50W, <15Ohm(0,5A)	-
51595	MTD20N03HDL	30V, 20A, 74W, <35mOhm	-
51596	MTD20N06HD	<45mOhm(10A)	-
51597	MTD20N06HDL	60V, 20A, 40W, <45mOhm	-
51598	MTD20N06V	<85mOhm(10A)	-
51599	MTD20P03HDL	30V, 19A, 75W, <99mOhm	-
51600	MTD20P06HDL	60V, 15A, 45W, <175mOhm	-
51601	MTD2955	85/225ns	2SJ389
51602	MTD2955V	60V, 12A, 60W, <0,2Ohm(6A)	-
51603	MTD2N20	200V, 2A, 25W, <1,5Ohm(1A)	2SK2235, 2SK2250
51604	MTD2N40E	400V, 2A, 40W, <3,5Ohm(1A)	-
51605	MTD2N50	500V, 2A, 20W, <4Ohm(1A)	-
51606	MTD2N50E	500V, 2A, 40W, <3,1Ohm(1A)	-
51607	MTD3055E	60V, 8A, 20W, <0,15Ohm(4A)	-
51608	MTD3055EL	60V, 12A, 40W, <0,18Ohm	-
51609	MTD3055V	60V, 12A, 48W, <0,15Ohm(6A)	-
51610	MTD3055VL	60V, 12A, 48W, <0,18Ohm	-
51611	MTD3N25E	250V, 3A, 40W, <1,4Ohm(1,5A)	-
51612	MTD4N20	200V, 4A, 20W, <0,7Ohm(2A)	2SK1920, 2SK2099
51613	MTD4N20E	200V, 4A, 40W, <1,2Ohm(2A)	-
51614	MTD4P05	50V, 4A, 20W, <0,6Ohm(2A)	2SJ183, 2SJ192, 2SJ239, 2SJ245, 2SJ279

51615	MTD4P06	MTD 4P05, 60V	2SJ183, 2SJ192, 2SJ239, 2SJ245, 2SJ279
51616	MTD5N05	50V, 5A, 20W, <0,4Ohm(2,5A)	2SK1059, 2SK1112, 2SK1471, 2SK1719
51617	MTD5N06	MTD 5N05, 60V	2SK1059, 2SK1112, 2SK1471, 2SK1719
51618	MTD5N25E	250V, 5A, 50W, <1Ohm(2,5A)	-
51619	MTD5P06V	60V, 5A, 40W, <0,45Ohm(2,5A)	-
51620	MTD6N08	80V, 6A, 20W, <0,25Ohm(3A)	2SK1475, 2SK1557
51621	MTD6N10	MTD 6N08, 100V	2SK1475, 2SK1557
51622	MTD6N10E	100V, 6A, 40W, <0,4Ohm(3A)	-
51623	MTD6N15	150V, 6A, 20W, <0,3Ohm(3A)	2SK1560
51624	MTD6N20E	200V, 6A, 50W, <0,7Ohm(3A)	-
51625	MTD6P10E	100V, 6A, 50W, <0,66Ohm(3A)	-
51626	MTD9N10E	<0,25Ohm(4,5A)	-
51627	MTF101..104	MEF 101..104	-
51628	MTH13N45	<0,4Ohm(7A)	BUZ 338, 2SK559...560, 2SK788, 2SK899
51629	MTH13N50	MTH 13N45, 500V	BUZ 338, 2SK559...560, 2SK788, 2SK899
51630	MTH15N20	<0,16Ohm(7,5A)	BUZ 350, 2SK623, 2SK901, 2SK1401
51631	MTH15N35	<0,3Ohm(8A)	BUZ 323, 2SK788, 2SK899, 2SK1610
51632	MTH15N40	MTH 15N35, 400V	BUZ 323, 2SK788, 2SK899, 2SK1610
51633	MTH20N15	<0,12Ohm(10A)	BUZ 350, 2SK622...623, 2SK901, 2SK1267
51634	MTH20P08	<0,15Ohm(10A)	-
51635	MTH20P10	MTH 20P08, 100V	-
51636	MTH25N08	<75mOhm(12,5A)	BUZ349, IRFP140...43, 2SK906, 2SK1433
51637	MTH25N10	MTH 25N08, 100V	BUZ349, IRFP140...43, 2SK906, 2SK1433
51638	MTH25P05	<0,14Ohm(12,5A)	2SJ215, 2SJ331
51639	MTH25P06	MTH 25P05, 60V	2SJ215, 2SJ331
51640	MTH30N20	<80mOhm(15A)	BUZ 341, 2SK851, 2SK902, 2SK1675...76
51641	MTH30N25	MTH 30N20, 250V	2SK902, 2SK1492, 2SK1669, 2SK1675...76
51642	MTH35N05	<55mOhm(17,5A)	IRFP150...53, 2SK849, 2SK857, 2SK1124
51643	MTH35N06	MTH 35N05, 60V	IRFP150...53, 2SK849, 2SK857, 2SK1124
51644	MTH35N06E	MTH 35N05, 60V	-
51645	MTH35N15	<60mOhm(17,5A)	BUZ 341, 2SK851
51646	MTH40N05	<28mOhm(20A)	BUZ347...48, IRFP150...51, 2SK849, 2SK857
51647	MTH40N06	MTH 40N05, 60V	IRFP150...51, 2SK849, 2SK857, 2SK1124
51648	MTH40N06FI,P	MTH 40N05, , 60V, 26A, 65W	2SK1298, 2SK1424, 2SK1435...36, 2SK1666
51649	MTH40N08	<40mOhm(20A)	BUZ 345, IRFP 150, 2SK1122, 2SK1263
51650	MTH40N10	MTH 40N08, 100V	BUZ 345, IRFP 150, 2SK1122, 2SK1263
51651	MTH50N05E	<28mOhm(25A)	-
51652	MTH5N100	MTH 5N95, 1000V	BUZ 357...358, 2SK685, 2SK1205, 2SK1359
51653	MTH5N95	950V, 5A, 150W, <3Ohm(2,5A)	BUZ 357...358, 2SK685, 2SK1205, 2SK1359
51654	MTH6N100	1000V, 6A, 180W, <2Ohm(3A)	2SK1120, 2SK1934
51655	MTH6N55	550V, 6A, 150W, <1,2Ohm(3A)	BUZ 332A, 2SK684, 2SK1032, 2SK1925
51656	MTH6N60	MTH 6N55, 600V	BUZ 332A, 2SK684, 2SK1032, 2SK1925
51657	MTH6N60FI	MTH 6 N60, , 3,5A, 40W	BUK 427-600, BUK 627-600
51658	MTH6N85	850V, 6A, 150W, <3Ohm(3A)	2SK1462, 2SK1358, 2SK1614, 2SK1692
51659	MTH6N90	MTH 6N85, 900V	2SK1462, 2SK1358, 2SK1614, 2SK1692

51660	MTH7N45	<0,8Ohm(3,5A)	BUZ 330...331, BUZ 385, 2SK636
51661	MTH7N50	MTH 7N45, 500V	BUZ 330...331, BUZ 385, 2SK636
51662	MTH8N35	<0,55Ohm(4A)	BUZ 330...331, 2SK636, 2SK501
51663	MTH8N40	MTH 8N35, 400V	BUZ 330...331, 2SK636, 2SK501
51664	MTH8N55	550V, 8A, 150W, <0,5Ohm(4A)	BUZ 332A, 2SK684, 2SK1032, 2SK1925
51665	MTH8N60	MTH 8N55, 600V	BUZ 332A, 2SK684, 2SK1032, 2SK1925
51666	MTH8N90	900V, 8A, 180W, <1,8Ohm(4A)	2SK1462, 2SK1358, 2SK1614, 2SK1692
51667	MTH8P18	180V, 8A, 125W, <0,7Ohm(4A)	2SJ114
51668	MTH8P20	MTH 8P18, 200V	2SJ114
51669	MTM10N05	50V, 10A, 75W, <0,28Ohm(5A)	IRF 130...133, 2SK398...399, 2SK500
51670	MTM10N06	MTM 10N05, 60V	IRF 130...133, 2SK398...399, 2SK500
51671	MTM10N06E	<0,2Ohm(5A)	-
51672	MTM10N08	80V, 10A, 75W, <0,33Ohm(5A)	IRF 130...133, 2SK398...399, 2SK631
51673	MTM10N10	MTM 10N08, 100V	IRF 130...133, 2SK398...399, 2SK631
51674	MTM10N10E	<0,25Ohm(5A)	-
51675	MTM10N12	120V, 10A, 75W, <0,3Ohm(5A)	2SK401, 2SK631, 2SK633
51676	5L	MTM 10N12..N15	2SK1529
51677	MTM10N15	MTM 10N12, 150V	2SK401, 2SK631, 2SK633
51678	MTM10N25	250V, 10A, 100W, <0,45(5A)	2SK401, 2SK412
51679	MTM1224	60V, 12A, 75W, <0,25Ohm(6A)	IRF 130...133, 2N6765
51680	MTM1225	MTM 1224, 100V	IRF 130, IRF 132, 2N6765
51681	MTM12N05	50V, 12A, 75W, <0,2Ohm(6A)	IRF 130...133, 2SK398...399, 2SK500
51682	MTM12N06	MTM 12N05, 60V	IRF 130...133, 2SK398...399, 2SK500
51683	MTM12N08	80V, 12A, 75W, <0,18Ohm(6A)	IRF 130...133, 2SK398...399, 2SK631
51684	MTM12N10	MTM 12N08, 100V	IRF 130...133, 2SK398...399, 2SK631
51685	MTM12P05	50V, 12A, 75W, <0,3Ohm(6A)	IRF 9530...9531, 2SJ112...113, 2SJ131
51686	MTM12P06	MTM 12P05, 60V	IRF 9530...9531, 2SJ112...113, 2SJ131
51687	MTM12P08	MTM 12P05, 80V	IRF 9530, 2SJ112...113, 2SJ131, 2SJ200
51688	MTM12P10	MTM 12P05, 100V	IRF 9530, 2SJ112...113, 2SJ131, 2SJ200
51689	MTM15N05	<0,16Ohm(7,5A)	2N6765, 2SK572...573, 2SK629
51690	6L	MTM 15 N05..N06	-
51691	MTM15N06	MTM 15N05, 60V	2N6765, 2SK572...573, 2SK629
51692	MTM15N06E	MTM 15 N05, 60V	-
51693	MTM15N20	<0,16Ohm(7,5A)	BUZ 36, BUZ 350, IRF 240, IRF 242
51694	MTM15N35	<0,3Ohm(7,5A)	-
51695	MTM15N40	MTM 15N35, 400V	-
51696	MTM15N45	<0,4Ohm(7,5A)	-
51697	MTM15N50	MTM 15N45, 500V	-
51698	MTM1N100	MTM 1N95, 1000V	BUZ 310...311
51699	MTM1N95	950V, 1A, 75W, <10Ohm(0,5A)	BUZ 310...311
51700	MTM20N08	<0,15Ohm(10A)	BUZ 24, IRF 140...143, 2SK622, 2SK629
51701	MTM20N10	MTM 20N08, 100V	BUZ 24, IRF 140, IRF 142, 2SK622, 2SK629
51702	MTM20N15	<0,12Ohm(10A)	BUZ 36, BUZ 350, IRF 250...253, 2SK901
51703	MTM20P08..P10	MTH 20P08..P10	MTH 20P08...P10
51704	MTM25N05	<80mOhm(12,5A)	BUZ 24, BUZ 349, IRF 140...143, 2N6763



51705	6L	MTM 25N05..N06	-
51706	MTM25N06	MTM 25N05, 60V	BUZ 24, BUZ 349, IRF 140...143, 2N6763
51707	MTM25N10	<75mOhm(12,5A)	BUZ 24, BUZ 349, IRF140, IRF142, 2N6764
51708	MTM25P05..P06	MTH 25P05..P06	MTH 25P05...P06
51709	MTM2N45	75W,<40hm(1A),<100/90ns	BUZ 308, IRF 420...423, 2SK635
51710	MTM2N50	MTM 2N45, 500V	BUZ 308, IRF 420, IRF 422, 2SK635
51711	MTM2N85	75W,<80hm(1A),<200/300ns	BUZ 310...311, 2SK696, 2SK726, 2SK1339
51712	MTM2N90	MTM 2N85, 900V	BUZ 310...311, 2SK696, 2SK726, 2SK1339
51713	MTM2P45	450V, 2A, 75W, <60hm(1A)	-
51714	MTM2P50	MTM P45, 500V	-
51715	E)	MTH 35N05..N06(E)	MTH 35N05...N06(E)
51716	MTM3N100	MTM 3N95, 1000V	BUZ 54, BUZ 357...358, 2SK696, 2SK1359
51717	MTM3N35	350V, 3A, 75W, <3,30hm(1,5A)	3SK635
51718	MTM3N40	MTM 3N35, 400V	3SK635
51719	MTM3N55	550V, 3A, 75W, <2,50hm(1,5A)	BUZ 307, 2SK415, 2SK603, 2SK954
51720	MTM3N60	MTM 3N55, 600V	BUZ 307, 2SK415, 2SK603, 2SK954
51721	MTM3N75	750V, 3A, 75W, <70hm(1,5A)	BUZ 307, 2SK415, 2SK603, 2SK954
51722	MTM3N80	MTM 3N75, 800V	BUZ 307, 2SK415, 2SK603, 2SK954
51723	MTM3N95	950V, 3A, 125W, <40hm(1,5A)	BUZ 54, BUZ 357...358, 2SK696, 2SK1359
51724	MTM3P25	250V, 3A, 75W, <40hm(1,5A)	-
51725	MTM40N20	<80mOhm(20A)	-
51726	MTM45N05E	<35mOhm(29A)	-
51727	MTM45N15	<80mOhm(22,5A)	-
51728	MTM474	450V, 4A, 75W, <2,250hm(2A)	BUZ 84, BUZ 355...356, 2SK604, 2SK695
51729	MTM475	MTM 474, 500V	BUZ 84, BUZ 355...356, 2SK604, 2SK695
51730	MTM4N45	450V, 4A, 75W, <1,50hm(2A)	BUZ 355...356, 2SK534, 2SK604, 2SK695
51731	MTM4N50	MTM 4N45, 500V	BUZ 355...356, 2SK534, 2SK604, 2SK695
51732	MTM4N85	850V, 4A, 125W, <40hm(2A)	BUZ 54, BUZ 357...358, 2SK727, 2SK794
51733	MTM4N90	MTM 4N85, 900V	BUZ 54, BUZ 357...358, 2SK727, 2SK794
51734	MTM50N05E	<28mOhm(25A)	-
51735	MTM55N08	<40mOhm(27,5A)	-
51736	MTM55N10	MTM 55 N08, 100V	-
51737	MTM564	350V, 5A, 75W, <1,50hm(2,5A)	BUZ 63, IRF 330...333, 2SK277, 2SK298
51738	MTM565	MTM 564, 500V	BUZ 63, IRF 330, IRF 332, 2SK277, 2SK298
51739	MTM5N18	180V, 5A, 75W, <10hm(2,5A)	BUZ 63, IRF 220
51740	MTM5N20	MTM 5N18, 200V	BUZ 63, IRF 220
51741	MTM5N35	350V, 5A, 75W, <10hm(2,5A)	BUZ 63, IRF 330...331
51742	MTM5N40	MTM 5N35, 400V	BUZ 63, IRF 330
51743	MTM5N95..N100	MTH 5N95..N100	MTH 5N95...N100
51744	MTM5P18	180V, 5A, 75W, <10hm(2,5A)	2SJ114
51745	MTM5P20	MTM 5P18, 200V	2SJ114
51746	MTM5P25	250V, 5A, 75W, <30hm(2,5A)	2SJ116
51747	MTM60N05	<28mOhm(30A)	-
51748	MTM60N06	MTM 60N05, 60V	-
51749	MTM6N55..N60	MTH 6 N55..N60	MTH 6 N55...N60

51750	MTM6N85..N100	MTH 6 N85..N100	MTH 6 N85...N100
51751	MTM7N45..N50	MTH 7 N45..N50	MTH 7 N45...N50
51752	MTM814	80V, 8A, 75W, <0,4Ohm(4A)	IRF 9130, IRF 9132, 2SJ114...115
51753	MTM815	MTM 814, 100V	IRF 9130, IRF 9132, 2SJ114...115
51754	MTM8N12	120V, 8A, 75W, <0,5Ohm(4A)	IRF 230...233, 2SK405, 2SK631, 2SK1529
51755	MTM8N15	MTM 8N12, 150V	IRF 230...233, 2SK405, 2SK631, 2SK1529
51756	MTM8N18	180V, 8A, 75W, <0,4Ohm(4A)	IRF 230, IRF 232, 2SK400, 2SK633
51757	MTM8N20	MTM 8N18, 200V	IRF 230, IRF 232, 2SK400, 2SK633
51758	MTM8N35..N40	MTH 8N35..N40	MTH 8N35...N40
51759	MTM8N55..N60	MTH 5N55..N60	MTH 5N55...N60
51760	MTM8P08	80V, 8A, 75W, <0,4Ohm(4A)	IRF 9130, IRF 9132, 2SJ114, 2SJ118...119
51761	MTM8P10	MTM 8P08, 200V	IRF 9130, IRF 9132, 2SJ114, 2SJ118...119
51762	MTM8P18	180V, 8A, 75W, <0,7Ohm(4A)	IRF 9240, IRF 9242, 2SJ114
51763	MTM8P20	MTM 8P18, 200V	IRF 9240, IRF 9242, 2SJ114
51764	MTM8P25	250V, 8A, 75W, <2Ohm(4A)	2SJ116
51765	MTP10N05	50V, 10A, 75W, <0,28Ohm(5A)	BUZ 20, BUZ 71, IRF 530...533, 2SK672
51766	MTP10N06	MTP 10N05, 60V	BUZ 20, BUZ 72, IRF 530...533, 2SK672
51767	MTP10N06E	<0,2Ohm(5A)	-
51768	MTP10N08	80V, 10A, 75W, <0,33Ohm(5A)	BUZ 20, BUZ 72, IRF 530...533, 2SK918
51769	MTP10N10	MTP 10N08, 100V	BUZ20, BUZ72, IRF530, IRF532, 2SK918
51770	MTP10N10E	MTP 10 N10, <0,25Ohm(5A)	BUZ20, BUZ72, IRF530, IRF532, 2SK918
51771	MTP10N10EL	100V, 10A, 40W, <0,22Ohm	2SK1300
51772	MTP10N12	120V, 10A, 75W, <0,3Ohm(5A)	BUZ31...32, IRF640...43, 2SK740, 2SK921
51773	L	MTP 10N12..N15	-
51774	MTP10N15	MTP 10N12, 150V	BUZ31...32, IRF640...43, 2SK740, 2SK890
51775	MTP10N25	250V, 10A, 75W, <0,45(5A)	IRF 644...647, 2SK925, 2SK1221, 2SK1393
51776	MTP10N35	350V, 10A, 125W, <0,55(5A)	BUZ 61, 2SK1378
51777	MTP10N40(E)	MTP 10N35, 400V	BUZ 61, 2SK1378
51778	MTP12N05	<0,2Ohm(6A)	BUZ 20, IRF 530...533, 2SK919, 2SK1416
51779	MTP12N06	MTP 12N05, 60V	BUZ 20, IRF 530...533, 2SK919, 2SK1416
51780	MTP12N08	80V, 12A, 75W, <0,18Ohm(6A)	BUZ 20, IRF 530...533, 2SK888, 2SK919
51781	MTP12N08L	MTP 12N08	2SK1301, 2SK1559, 2SK1561
51782	L	MTP 12N08..N10	2SK1301, 2SK1559, 2SK1561
51783	MTP12N10	MTP 12N08, 100V	BUZ 20, IRF 530...533, 2SK888, 2SK919
51784	MTP12N10E	<0,16Ohm(6A)	BUZ 20, IRF 530...533, 2SK888, 2SK919
51785	MTP12N18	MTP 12N20, 180V	BUZ 31, IRF 640, IRF 642, 2SK925
51786	MTP12N20	<0,35Ohm(6A)	BUZ 31, IRF 640, IRF 642, 2SK925
51787	MTP12P05	50V, 12A, 75W, <0,3Ohm(6A)	BUZ 272, IRF 9530, 2SJ127, 2SJ140
51788	MTP12P06	MTP 12P05, 60V	BUZ 272, IRF 9530, 2SJ127, 2SJ140
51789	MTP15N05	<0,16Ohm(7,5A)	IRF 530...531, 2SK673, 2SK971, 2SK1416
51790	FI	MTP 15N05..06(L), , 10A, 30W	BUK 442-..., 2SK1033, 2SK1256, 2SK1344
51791	L	MTP 15N05..N06	BUK552-..., 2SK971, 2SK2175
51792	MTP15N06	MTP 15N05, 60V	IRF 530...531, 2SK673, 2SK971, 2SK1416
51793	MTP15N06E	MTP 15 N06	-
51794	MTP15N06V	<0,12Ohm(7,5A)	MTB 15N06V

51795	MTP15N06VL	60V, 15A, 60W, <85mOhm	-
51796	MTP15N15	<0,25Ohm(7,5A)	BUZ 30A, IRF 640...43, 2SK891, 2SK1561
51797	MTP16N25E	<0,25Ohm(8A)	MTB 16N25E
51798	MTP1N100	MTP 1N95, 1000V	BUZ 50
51799	MTP1N100E	1000V, 1A, 75W, <9Ohm(0,5A)	BUZ 50
51800	MTP1N45	450V, 1A, 50W, <8Ohm(0,5A)	BUZ 74, BUZ 78, IRF 820...823, 2SK602
51801	MTP1N50	500V, 1A, 40W, <5Ohm(0,5A)	BUZ 74, BUZ 78, IRF 820, IRF 822, 2SK602
51802	MTP1N55	550V, 1A, 50W, <12Ohm(0,5A)	BUZ 78, BUZ 80, 2SK602, 2SK858, 2SK1922
51803	MTP1N60	600V, 1A, 50W, <8Ohm(0,5A)	BUZ 78, BUZ 80, 2SK602, 2SK858, 2SK1922
51804	MTP1N80	800V, 1A, 48W, <12Ohm(0,5A)	BUZ 78, BUZ 80, 2SK602, 2SK1199, 2SK1324
51805	MTP1N95	950V, 1A, 50W, <10Ohm(0,5A)	BUZ 50
51806	MTP20N06V	<85mOhm(10A)	-
51807	MTP20N08	<0,15Ohm(10A)	BUZ 21, IRF 540...543, 2SK1428
51808	MTP20N10(E)	MTP 20N08, 100V	BUZ 21, IRF 540, IRF 542, 2SK1428
51809	MTP20N20E	<0,16Ohm(10A)	BUZ 30A
51810	MTP20P06	<0,2Ohm(10A)	IRF 9540
51811	MTP23P06V	<0,12Ohm(11,5A)	2SJ174
51812	MTP25N05	<80mOhm(12,5A)	BUK 555-50, BUZ 11, IRF 540...543
51813	E	MTP 25 N05..N06, <60/80ns	-
51814	L	<0,1Ohm(12,5A)	BUK 555-..., 2SK1291, 2SK1296, 2SK2411
51815	MTP25N06	MTP 25N05, 60V	BUK 555-60, IRF 540...543, 2SK1291
51816	MTP25N10	<85mOhm(12,5A)	BUK 456-100, IRF 540, IRF 542
51817	MTP25N10E	<75mOhm(12,5A)	-
51818	MTP27N10E	<70mOhm(13,5A)	BUK 456-100, BUZ 22, 2SK1429, 2SK2050
51819	MTP2955	60V, 12A, 75W, <0,3Ohm(6A)	IRF 9530...31, IRF 9540...43, 2SJ169
51820	MTP2955V	60V, 12A, 60W, <0,2Ohm(6A)	-
51821	MTP2N18	MTP 2N20, 180V	IRF 612, IRF 614, 2SK923
51822	MTP2N20	200V, 2A, 50W, <1,8Ohm(1A)	IRF 612, IRF 614, 2SK923
51823	MTP2N25	250V, 2A, 50W, <2,8Ohm(1A)	IRF 614, 2SK923
51824	MTP2N35	350V, 2A, 50W, <5Ohm(2A)	BUZ 74, IRF 710...711, 2SK892
51825	MTP2N40	MTP 2N35, 400V	BUZ 74, IRF 710...711, 2SK892
51826	MTP2N40E	400V, 2A, 40W, <3,5Ohm(1A)	BUZ 74, IRF 710...711, 2SK892
51827	MTP2N45	450V, 2A, 50W, <4Ohm(1A)	BUZ 74, IRF 820...823, 2SK892
51828	MTP2N50	MTP 2N45, 500V	BUZ 74, IRF 820, IRF 822, 2SK892
51829	MTP2N50E	500, 2A, 75W, <4Ohm(1A)	BUZ 74, IRF 820, IRF 822, 2SK892
51830	MTP2N55	550V, 2A, 75W, <6Ohm(1A)	BUZ 80, 2SK858, 2SK1323, 2SK1922
51831	MTP2N60	MTP 2N55, 600V	BUZ 80, 2SK858, 2SK1323, 2SK1922
51832	MTP2N60E	600V, 2A, 50W, <3,8Ohm(1A)	BUZ 80, 2SK858, 2SK1323, 2SK1922
51833	MTP2N85	850V, 2A, 75W, <8Ohm(1A)	BUZ 50, 2SK1199, 2SK1324, 2SK1338
51834	MTP2N90	MTP 2N85, 900V	BUZ 50, 2SK1199, 2SK1324, 2SK1338
51835	MTP2P45	450V, 2A, 75W, <6Ohm(1A)	MTB 2P50E
51836	MTP2P50	MTP 2P45, 500V	MTB 2P50E
51837	MTP2P50E	500V, 2A, 75V, <6Ohm(1A)	MTB 2P50E
51838	MTP3055A,E	60V, 12A, 40W, <0,15Ohm(6A)	BUZ 20, IRF 530...533, 2SK919, 2SK1427
51839	EFI	MTP 3055A,E, , 10A, 30W	BUK 442-60, 2SK1093...1094, 2SK1430

51840	MTP3055EL	MTP 3055A,E, <0,18Ohm(6A)	BUK 552-60, 2SK971, 2SK2175
51841	MTP3055V	60V, 12A, 48W, <0,15Ohm(6A)	MTB 15N06V
51842	MTP3055VL	60V, 12A, 48W, <0,18Ohm	-
51843	MTP30N05E	<50mOhm,<60/80ns	-
51844	MTP30N06VL	60V, 30A, 90W, <50mOhm	MTB 30N06VL
51845	MTP30P06V	<0,08Ohm(15A)	MTB 30P06V
51846	MTP33N10E	<60mOhm(16,5A)	BUK 456-100, BUZ 22
51847	MTP35N06E	<55mOhm(17,5A)	-
51848	MTP35N06ZL	60V, 35A, 94W, <46mOhm	MTB 35N06ZL
51849	MTP36N06V	<40mOhm(16A)	-
51850	MTP3N08L	80V, 3A, 25W, <0,8Ohm(2A)	2SK702, 2SK991
51851	MTP3N100	MTP 3N95, 1000V	BUZ 51, 2SK1119
51852	MTP3N100E	<4Ohm(1,5A)	BUZ 51, 2SK1119
51853	MTP3N10L	MTP 3N08L, 100V	2SK702, 2SK991
51854	MTP3N120E	<5Ohm(1,5A)	MTB 3N120E
51855	MTP3N35	350V, 3A, 75W, <3,3Ohm(1,5A)	BUZ 76, IRF 720...723, 2SK1244, 2SK 1439
51856	MTP3N40	MTP 3N35, 400V	BUZ 76, IRF 720...723, 2SK1244, 2SK 1439
51857	MTP3N45	450V, 3A, 75W, <3Ohm(1,5A)	BUZ 41A...42, IRF 830...833, 2SK1244
51858	MTP3N50	MTP 3N45, 500V	BUZ 41A...42, IRF 830, IRF 832, 2SK1244
51859	MTP3N50E	500V, 3A, 50W, <3Ohm(1,5A)	BUZ 41A...42, IRF 830, IRF 832, 2SK1244
51860	MTP3N60	600V, 3A, 75W, <2,5Ohm(1,5A)	BUK 456-800, BUZ 90, 2SK513, 2SK1923
51861	MTP3N60E	<2,5Ohm(1,5A)	BUK 456-800, BUZ 90, 2SK513, 2SK1923
51862	MTP3N60FI	MTP 3 N60, , 2,5A, 35W	2SK1572, 2SK1767
51863	MTP3N75	750V, 3A, 75W, <7Ohm(1,5A)	BUK456-800, 2SK513, 2SK791...792, 2SK1600
51864	MTP3N80	MTP 3N75, 800V	BUK456-800, 2SK513, 2SK792, 2SK1600
51865	MTP3N95	950V, 3A, 75W, <4Ohm(1,5A)	BUZ 51, 2SK1119
51866	MTP3P25	250V, 3A, 75W, <4Ohm(1,5A)	-
51867	MTP40N06EL	60V, 40A, 150W, <40mOhm	-
51868	MTP45N05E	125W, <35mOhm, <85/95ns	-
51869	MTP4N05L	50V, 4A, 25W, <0,6Ohm(2A)	IRL 510, 2SK702, 2SK991
51870	MTP4N06L	MTP 4N05L, 60V	IRL 510, 2SK702, 2SK991
51871	MTP4N08	80V, 4A, 50W, <0,8Ohm(2A)	IRF 510...513, 2SK628, 2SK917, 2SK920
51872	MTP4N10	MTP 4N08, 100V	IRF510, IRF512, 2SK628, 2SK917, 2SK920
51873	MTP4N40E	400V, 4A, 74W, <1,8Ohm(2A)	BUZ 41A...42, IRF 830...833, 2SK552...553
51874	MTP4N45	450V, 4A, 50W, <1,5Ohm(2A)	BUZ 41A...42, IRF 830...833, 2SK552...553
51875	MTP4N50	MTP 4N45, 500V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
51876	MTP4N50E	500V, 4A, 75W, <1,5Ohm(2A)	BUZ 41A...42, IRF 830, IRF 832, 2SK553
51877	MTP4N80E	800V, 4A, 125W, <3Ohm(2A)	2SK1643
51878	MTP4N85	850V, 4A, 50W, <4Ohm(2A)	2SK1457, 2SK1639, 2SK1643, 2SK1807
51879	MTP4N90	MTP 4N85, 900V	2SK1457, 2SK1639, 2SK1643, 2SK1807
51880	MTP50N05E	125W, <28mOhm, <85/95ns	-
51881	MTP50N05EL	150W, <32mOhm(25A)	-
51882	MTP50P03HDL	30V, 50A, 125W, <25mOhm	-
51883	MTP52N06V	<22mOhm(26A)	MTB 52N06V
51884	MTP52N06VL	60V, 52A, 165W, <25mOhm	MTB 52N06VL

51885	MTP55N06Z	<16mOhm(15A)	-
51886	MTP5N05	50V, 5A, 50W, <0,6Ohm(2,5A)	IRF 510...513, 2SK346, 2SK463, 2SK917
51887	MTP5N06	MTP 5N05, 60V	IRF 510...513, 2SK346, 2SK463, 2SK917
51888	MTP5N12	120V, 5A, 50W, <0,9Ohm(2,5A)	IRF 620...621, 2SK920, 2SK924, 2SK1391
51889	MTP5N18	180V, 5A, 50W, <1Ohm(2,5A)	BUZ 60, IRF 620, 2SK924, 2SK1391
51890	MTP5N20	200V, 5A, 75W, <1Ohm(2,5A)	BUZ 60, IRF 620, 2SK924, 2SK1391
51891	MTP5N35	350V, 5A, 50W, <1Ohm(2,5A)	BUZ 60, IRF 830...831, 2SK553, 2SK1246
51892	MTP5N40	MTP 5N35, 400V	BUZ 60, IRF 830...831, 2SK553, 2SK1246
51893	MTP5N40E	400V, 5A, 75W, <1Ohm(2,5A)	BUZ 60, IRF 830...831, 2SK553, 2SK1246
51894	MTP5P06V	60V, 5A, 40W, <0,45Ohm(2,5A)	-
51895	MTP5P18	180V, 5A, 50W, <1Ohm(2,5A)	IRF 9630, IRF 9632
51896	MTP5P20	MTP 5P18, 200V	IRF 9630, IRF 9632
51897	MTP5P25	250V, 5A, 50W, <3Ohm(2,5A)	-
51898	MTP60N06HD	<14mOhm(30A)	MTB 60N06HD
51899	MTP6N10	100V, 6A, 50W, <0,6Ohm(3A)	BUZ 30, IRF 520, IRF 522, 2SK470
51900	MTP6N55	550V, 6A, 125W, <1,2Ohm(3A)	BUZ 91, BUZ 305, 2SK1117, 2SK1809
51901	MTP6N60	MTP 6N55, 600V	BUZ 91, BUZ 305, 2SK1117, 2SK1809
51902	MTP6N60E	600V, 6A, 125W, <1,2Ohm(3A)	BUZ 91, BUZ 305, 2SK1117, 2SK1809
51903	MTP6P20E	200V, 6A, 75W, <1Ohm(3A)	IRF 9630, IRF 9632
51904	MTP75N03HDL	25V, 75A, 150W, <9mOhm	MTB 75N03HDL
51905	MTP75N05HD	<9,5mOhm(37,5A)	MTB 75N05HD
51906	MTP75N06HD	<10mOhm(37,5A)	-
51907	MTP7N18	MTP 7N20, 180V	BUZ30, BUZ73, IRF632, 2SK741, 2SK1319
51908	MTP7N20	200V, 7A, 75W, <0,7Ohm(3,3A)	BUZ30, BUZ73, IRF632, 2SK741, 2SK1319
51909	MTP7N20E	200V, 7A, 50W, <0,7Ohm(3,5A)	BUZ30, BUZ73, IRF632, 2SK741, 2SK1319
51910	MTP7P05	50V, 7A, 75W, <0,6Ohm(3,5A)	BUZ 171, IRF 9530...9533, 2SJ171
51911	MTP7P06	MTP 7P05, 60V	BUZ 171, IRF 9530...9533, 2SJ171
51912	MTP814	80V, 8A, 75W, <0,4Ohm(4A)	IRF 9530, IRF 9532
51913	MTP815	MTP 814, 100V	IRF 9530, IRF 9532
51914	MTP8N08	80V, 8A, 75W, <0,5Ohm(4A)	BUZ 30, BUZ 73, IRF 520...523, 2SK470
51915	MTP8N10	MTP 8N08, 100V	BUZ 30, BUZ 73, IRF 520...523, 2SK470
51916	MTP8N10E	MTP 8 N10	-
51917	MTP8N12	120V, 8A, 75W, <0,5Ohm(4A)	BUK554-200, BUZ30, BUZ73, IRF630...33
51918	MTP8N15	MTP 8N12, 150V	BUK554-200, BUZ30, BUZ73, IRF630...33
51919	MTP8N15L	MTP 8N12, 150V, 0,45Ohm(5A)	BUK 554-200
51920	MTP8N18	180V, 8A, 75W, <0,4Ohm(4A)	BUZ 30...BUZ 73, IRF630, IRF632, 2SK741
51921	MTP8N20	MTP 8N18, 200V	BUZ 30...BUZ 73, IRF630, IRF632, 2SK741
51922	MTP8N45	450V, 8A, 125W, <0,8Ohm(4A)	IRF840...41, 2SK894
51923	MTP8N50	MTP 8N45, 500V	IRF840, 2SK894
51924	MTP8N50E	500V, 8A, 125W, <0,8Ohm(4A)	IRF840, 2SK894
51925	MTP8P08	80V, 8A, 75W, <0,4Ohm(4A)	IRF 9530, IRF 9532
51926	MTP8P10	MTP 8P08, 100V	IRF 9530, IRF 9532
51927	MTP8P18	180V, 8A, 75W, <0,7Ohm(4A)	IRF 9640, IRF 9642
51928	MTP8P20	MTP 8P18, 200V	IRF 9640, IRF 9642
51929	MTP8P25	250V, 8A, 75W, <2Ohm(4A)	-



51930	MTP9N25E	250V, 9A, 80W, <0,45(4,5A)	IRF 644...647, 2SK925, 2SK1221, 2SK1393
51931	MTU21	MEU 21, , 75mW	-
51932	MTU22	MEU 22, , 75mW	-
51933	MTV10N100E	<1,3Ohm(5A)	2SK1489
51934	MTV16N50E	<0,4Ohm(8A)	2SK1678, 2SK1745
51935	MTV20N50E	<0,24Ohm(10A)	-
51936	MTV25N50E	<0,2Ohm(12,5A)	-
51937	MTV32-400A	400V, 3A, <22ns	BYT 56G, FE 3H
51938	MTV32-600A	600V, 3A, <55ns	BYT 56J
51939	MTV32N20E	<75mOhm(16A)	BUZ 341, 2SK851, 2SK902, 2SK1675...76
51940	MTV32N25E	<80mOhm(16A)	2SK1675...76
51941	MTV32N25E	<80mOhm(16A)	2SK1675...76
51942	MTV6N100E	<1,5Ohm(3A)	BUZ 312, 2SK1120, 2SK1934
51943	MTV6N100E	<1,5Ohm(3A)	BUZ 312, 2SK1120, 2SK1934
51944	MTV7N80E	800V, 7A, 180W, <1Ohm(3,5A)	2SK1465
51945	MTV8N60E	<0,55Ohm(4A)	2SK1465
51946	MTW10N100E	<1,3Ohm(5A)	2SK1489
51947	MTW14N50E	<0,4Ohm(7A)	2SK1678, 2SK1745
51948	MTW16N40E	<0,24Ohm(8A)	BUZ 323, 2SK1678, 2SK1745
51949	MTW20N50E	<0,24Ohm(10A)	2SK1411, 2SK1680
51950	MTW24N40E	<0,16Ohm(12A)	2SK1409, 2SK1411, 2SK1680
51951	MTW32N20E	<75mOhm(16A)	BUZ 341, 2SK851, 2SK902, 2SK1675...76
51952	MTW35N15E	<50mOhm(17,5A)	BUZ 341, 2SK851, 2SK902, 2SK1675...76
51953	MTW45N10E	<35mOhm(22,5A)	-
51954	MTY100N10E	<11mOhm(50A)	-
51955	MTY14N100E	<0,8Ohm(7A)	-
51956	MTY16N80E	<0,5Ohm(8A)	2SK1466
51957	MTY20N50E	<0,26Ohm(10A)	2SK1544
51958	MTY25N60E	<0,21Ohm(12,5A)	-
51959	MTY30N50E	<0,15Ohm(15A)	2SK1520, 2SK1629, 2SK1971
51960	MTY55N20E	<28mOhm(27,5A)	2SK1948
51961	MTZ2.0..20	9..+4%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
51962	MTZJ2.0..39	9..+4%	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...
51963	MU	P6 SMB-91	P6 SMB-91
51964	MU	MA 132WK	MA 132WK
51965	MU	MA 142WK	MA 142WK
51966	MU	MA 152WK	MA 152WK
51967	MU	HR 1F2Q	HR 1...
51968	MU	SM 6T 36C	SM 6T...
51969	MU10	Ip<5μA, Iv>1mA	MU 20
51970	MU20	MU 10	MU 10
51971	MU2646..2647	2N2646..2647	2N2646...47
51972	MU2646..2647M	2N2646..2647	2N2646...47
51973	MU4891	2N4891	2N4891
51974	MU4892	2N4892	2N4892



51975	MU4893	2N4893	2N4893
51976	MU4894	2N4894	2N4894
51977	MU851	$I_p < 2\mu A, I_v > 2mA$	2N4851, 2N4947, 2N4948, 2N4893
51978	MU852	MU 851, $I_v > 4mA$	2N4852, 2N4892
51979	MU853	MU 851, $I_p < 0,4\mu A, I_v > 4mA$	-
51980	MUN2111..2134	2,9x1,6x1,1mm(Japan)	MMUN 2111...2134
51981	MUN2211..2234	2,9x1,6x1,1mm(Japan)	MMUN 2211...2234
51982	MUN5111..5134	2,9x1,6x1,1mm(Japan)	UN 5111...
51983	MUN5211..5234	2,9x1,6x1,1mm(Japan)	UN 5211...
51984	MUR10120E	1200V, 10A( $T_c 125^\circ$ ), $< 175ns$	BY 459-1500
51985	MUR10150E	1500V, 10A( $T_c 125^\circ$ ), $< 175ns$	BY 459-1500
51986	MUR105	50V, 1A, $< 25ns$	BYV 26B...E, EGP 10A...G, FE 1A...H
51987	MUR110	MUR 105, 100V	BYV 26B...E, EGP 10B...G, FE 1B...H
51988	MUR1100(E)	MUR 190, 1000V	BYV 26E
51989	MUR115	MUR 105, 150V	BYV 26B...E, EGP 10C...G, FE 1C...H
51990	MUR120	200V, 1A, $< 25ns$	BYV 26B...E, EGP 10D...G, FE 1D...H
51991	MUR130	MUR 120, 300V	BYV 26B...E, EGP 10F...G, FE 1F...H
51992	MUR140	MUR 120, 400V, $< 50ns$	BYV 26B...E, EGP 10G, FE 1H
51993	MUR150	MUR 120, 500V, $< 50ns$	BYV 26C
51994	MUR1505	50V, 15A( $T_c 150^\circ$ ), $< 35ns$	BYR 79-500..., BYT 87/600...
51995	MUR1510	MUR 1505, 100V	BYR 79-500..., BYT 87/600...
51996	MUR1515	MUR 1505, 150V	BYR 79-500..., BYT 87/600...
51997	MUR1520	MUR 1505, 200V	BYR 79-500..., BYT 87/600...
51998	MUR1530	MUR 1505, 300V, $< 60ns$	BYR 79-500..., BYT 87/600...
51999	MUR1540	MUR 1505, 400V, $< 60ns$	BYR 79-500..., BYT 87/600...
52000	MUR1550	MUR 1505, 500V, $< 60ns$	BYR 79-500..., BYT 87/600...
52001	MUR1560	MUR 1505, 600V, $< 60ns$	BYR 79-600..., BYT 87/600...
52002	MUR160	MUR 120, 600V, $< 50ns$	BYV 26C
52003	MUR1605CT	50V, $2 \times 8A(T_c 150^\circ)$ , $< 25ns$	BYV 32-50..., FE 16A...J
52004	MUR1610CT	MUR 1605CT, 100V	BYV 32-100..., FE 16B...J
52005	MUR1615CT	MUR 1605CT, 150V	BYV 32-150..., FE 16C...J
52006	MUR1620CT	MUR 1605CT, 200V	BYV 32-200..., FE 16D...J
52007	MUR1620TR	MUR 1605CT, 200V, $< 35ns$	BYV 32-200..., FE 16D...J
52008	MUR1630CT	MUR 1605CT, 300V, $< 50ns$	BYV 34-300..., FE 16F...J
52009	MUR1640CT	MUR 1605CT, 400V, $< 50ns$	BYV 34-400..., FE 16G...J
52010	MUR1650CT	MUR 1605CT, 500V, $< 50ns$	BYV 34-500, FE 16H...J
52011	MUR1660CT	MUR 1605CT, 600V, $< 50ns$	BYR 34-600..., FE 16J
52012	MUR170	MUR 120, 700V, $< 75ns$	BYV 26D
52013	MUR180	MUR 120, 800V, $< 75ns$	BYV 26D
52014	MUR190	900V, 1A, $< 75ns$	BYV 26E
52015	MUR2505	50V, 25A( $T_c 145^\circ$ ), $< 50ns$	BYW 31/50.../200
52016	MUR2510	MUR 2505, 100V	BYW 31/100.../200
52017	MUR2515	MUR 2505, 150V	BYW 31/150.../200
52018	MUR2520	MUR 2505, 200V	BYW 31/200
52019	MUR3005PT	50V, 30A( $T_c 150^\circ$ ), $< 35ns$	BYV 72-50..., BYW 99P/50...

52020	MUR3005PT	50V, 30A(Tc150°), <35ns	BYV 72-50..., BYW 99P/50...
52021	MUR3010PT	MUR 3005PT, 100V	BYV 72-100..., BYW 99P/100...
52022	MUR3010PT	MUR 3005PT, 100V	BYV 72-100..., BYW 99P/100...
52023	MUR3015PT	MUR 3005PT, 150V	BYV 72-150..., BYW 99P/150...
52024	MUR3015PT	MUR 3005PT, 150V	BYV 72-150..., BYW 99P/150...
52025	MUR3020PT	MUR 3005PT, 200V	BYV 72-200, BYW 99P/200
52026	MUR3020PT	MUR 3005PT, 200V	BYV 72-200, BYW 99P/200
52027	MUR3020WT	MUR 3005PT, 200V	BYV 72-200, BYW 99P/200
52028	MUR3030PT	MUR 3005PT, 300V, <60ns	BYV 74-300
52029	MUR3030PT	MUR 3005PT, 300V, <60ns	BYV 74-300
52030	MUR3040	MUR 3005PT, 400V, <100ns	BYV 74-400
52031	MUR3040	MUR 3005PT, 400V, <100ns	BYV 74-400
52032	MUR3040PT	MUR 3005PT, 400V, <60ns	BYV 74-400
52033	MUR3040PT	MUR 3005PT, 400V, <60ns	BYV 74-400
52034	MUR3040WT	MUR 3005PT, 400V	BYV 74-400
52035	MUR3050PT	MUR 3005PT, 500V, <60ns	BYV 74-500
52036	MUR3050PT	MUR 3005PT, 500V, <60ns	BYV 74-500
52037	MUR3060PT	MUR 3005PT, 600V, <60ns	-
52038	MUR3060PT	MUR 3005PT, 600V, <60ns	-
52039	MUR3060WT	MUR 3005PT, 600V	-
52040	MUR3080	800V, 30A, <110ns	BYT 30P-800...
52041	MUR405	50V, 4A, <25ns	EGP 50A...G, FE 5A...D
52042	MUR410	MUR 405, 100V	EGP 50B...G, FE 5B...D
52043	MUR4100(E)	MUR 420, 1000V, <75ns	-
52044	MUR415	MUR 405, 150V	EGP 50C...G, FE 5C...D
52045	MUR420	200V, 4A, <25ns	EGP 50D...G, FE 5D
52046	MUR430	MUR 420, 300V	EGP 50F...G
52047	MUR440	MUR 420, 400V	EGP 50G
52048	MUR450	MUR 420, 500V	-
52049	MUR460	600V, 4A, <50ns	-
52050	MUR470	MUR 420, 700V	-
52051	MUR480	MUR 420, 800V	-
52052	MUR490(E)	MUR 420, 900V	-
52053	MUR5005	50V, 50A(Tc125°), <50ns	BYW 78/50..., BYW 93/50...
52054	MUR5010	MUR 5005, 100V	BYW 78/100..., BYW 93/100...
52055	MUR5015	MUR 5005, 150V	BYW 78/150..., BYW 93/150...
52056	MUR5020	MUR 5005, 200V	BYW 78/200, BYW 93/200
52057	MUR5150E	1500V, 5A, <175ns	-
52058	MUR6040	400V, 60A(Tc70°), <100ns	BYT 60P/400
52059	MUR605CT	50V, 2x3A(Tc130°), <35ns	BYP 20-50...-150, BYQ 28-50...-200
52060	MUR610CT	MUR 605CT, 100V	BYP 20-100...-150, BYQ 28-100...-200
52061	MUR615CT	MUR 605CT, 150V	BYP 20-150, BYQ 28-150...-200
52062	MUR620CT	MUR 605CT, 200V	BYQ 28-200
52063	MUR7005	50V, 70A(Tc125°), <60ns	BYW 08/50..., BYW 94/50..., BYT 60/200...
52064	MUR7010	MUR 7005, 100V	BYW 08/100..., BYW 94/100..., BYT 60/200...

52065	MUR7015	MUR 7005, 150V	BYW 08/150..., BYW 94/150..., BYT 60/200...
52066	MUR7020	MUR 7005, 200V	BYW 08/200, BYW 94/200, BYT 60/200...
52067	MUR805	50V, 8A(Tc150°), <25ns	BYP 21-50..., BYW 29-50..., FE 8A...J
52068	MUR810	MUR 805, 100V	BYP 21-100..., BYW 29-100..., FE 8B...J
52069	MUR815	MUR 805, 150V	BYP 21-150..., BYW 29-150..., FE 8C...J
52070	MUR820	MUR 805, 200V	BYP 21-200, BYW 29-200, FE 8D...J
52071	MUR830	MUR 805, 300V, <50ns	BYR 29-500..., BYV 29-300..., FE 8F...J
52072	MUR840	MUR 805, 400V, <50ns	BYR 29-500..., BYV 29-400..., FE 8G...J
52073	MUR850	MUR 805, 500V, <50ns	BYR 29-500..., BYV 29-500, FE 8H...J
52074	MUR860	MUR 805, 600V, <50ns	BYR 29-600..., BYT 12P/600..., FE 8J
52075	MUR870	MUR 805, 700V, <50ns	BYR 29-800, BYT 12P/800...
52076	MUR880	MUR 805, 800V, <50ns	BYR 29-800, BYT 12P/800...
52077	MUR890(E)	900V, 8A(Tc150°), <75ns	BYT 12P/1000
52078	MURB1620CT	200V, 2x8A, <35ns	-
52079	MURB1660CT	600V, 2x8A, <60ns	-
52080	MURD305	50V, 3A(Tc158°), <35ns	-
52081	MURD310	MURD 305, 100V	-
52082	MURD315	MURD 305, 150V	-
52083	MURD320	MURD 305, 200V	-
52084	MURD605CT	50V, 2x3A(Tc145°), <35ns	-
52085	MURD610CT	MURD 605CT, 100V	-
52086	MURD615CT	MURD 605CT, 150V	-
52087	MURD620CT	MURD 605CT, 200V	-
52088	MURF1620CT	MUR 1620	-
52089	MURF1620CT	MUR 1620	-
52090	MURF1660CT	MUR 1660	-
52091	MURF820	MUR 820	BY 229F-200..., BYW 29-200F
52092	MURH840CT	400V, 2x4A, <28ns	BYR 28-500..., BYT 28-400...
52093	MURH860CT	600V, 2x4A, <35ns	BYR 28-600...
52094	MURHB840CT	400V, 2x4A, <28ns	BYR 28-500..., BYT 28-400...
52095	MURS120	200V, 1A, <25ns	D 1FL20, ER 2D...E
52096	MURS160	600V, 1A, <50ns	-
52097	MUS4987	2N4987	2N49832N4987
52098	MUS4988	2N4988	2N49842N4988
52099	MV	P6 SMB-91A	P6 SMB-91A
52100	MV	1SV272	1SV272
52101	MV	SM 6T 36CA	SM 6T...
52102	MV-1	0,58..0,65V(3mA)	BA 216, BA 314
52103	MV-103	1,82..1,92V(3mA)	BZ102/2V1, BZX75/C2V1, BZV86/2V0, ZTE 2
52104	MV-104	1,98..2,15V(3mA)	BZ102/2V1, BZX75/C2V1, BZV86/2V0, ZTE 2
52105	MV-11	1,18..1,3V(3mA)	ZTE1,5
52106	MV-12	1,24..1,38V(3mA)	ZTE1,5
52107	MV-13	1,18..1,38V(3mA)	ZTE1,5
52108	MV-2	0,62..0,69V(3mA)	BA 216, BA 314
52109	MV-203	1,88..1,98V(3mA)	BZ102/2V1, BZX75/C2V1, BZV86/2V0, ZTE 2

52110	MV-3	0,58..0,69V(3mA)	BA 216, BA 314
52111	MV-303	2,38..2,58V(3mA)	-
52112	MV-4	0,59..0,69V(10mA)	BA 220, BZ 102/0V7, BZX 55/C0V8
52113	MV-5	0,58..0,66V(10mA)	BA 220, BZ 102/0V7, BZX 55/C0V8
52114	MV-5T	1,8..1,9V(10mA)	BZ 102/2V1, BZV 86/C2V0, BZX 75/C2V1
52115	MV-5W	1,2..1,3V(10mA)	BZ 102/1V4, BZX 75/C1V4, ZTE 1,5
52116	MV102		BB 105A,B, BB 205A,B, BB 405A,B
52117	MV103		BB 105A,B, BB 205A,B, BB 405A,B
52118	MV104		BB 104, BB 204, BB 304, 1SV55, 1SV109
52119	MV104		BB 105A,B, BB 205A,B, BB 405A,B
52120	MV104G	BB 204G	BB 204G
52121	MV109		BB 105G, BB 205G, BB 305G, BB 405G
52122	MV201		BA 111, BA 124, MV 2201, MV 2203
52123	MV209		BB 309, BB 409, BB 609, BB 709, BB 809
52124	MV2101...2115		BB 109, BB 143, MV 109, 1SV 50
52125	MV306		BA 125, BB 119, 1SV114, 1SV125
52126	MV309		BB 209, BB 309, BB 609, BB 709, BB 809
52127	MV310		BB 101, BB 110, BB 203, 1SV68, 1SV84
52128	MV409		BB 309, BB 409, BB 609, BB 709, BB 809
52129	MV7005	400..520pF(1V)	-
52130	MV7404	96..144pF(2V)	-
52131	MW	BF 996S	BF 996S
52132	MW	P6 SMB-100	P6 SMB-100
52133	MW	SM 6T 39C	SM 6T...
52134	MX	P6 SMB-100A	P6 SMB-100A
52135	MX	MA 57	MA 57
52136	MX	SM 6T 39CA	SM 6T...
52137	MX	HR 1A4A	HR 1...
52138	MXTA14	MPSA14, SMD	PXTA 14
52139	MXTA27	MPSA27, SMD	PXTA 27
52140	MXTA42..44	MPSA42..44, SMD	PXTA 42...44
52141	MXTA64	MPSA64, SMD	PXTA 64
52142	MXTA77	MPSA77, SMD	PXTA 77
52143	MXTA92..92	MPSA92..93, SMD	PXTA 92...93
52144	MY	P6 SMB-110	P6 SMB-110
52145	MY	2SC3773	2SC3773
52146	MY	MA 551	MA 551
52147	MY	2SA1255-Y	2SA1255
52148	MY	2SC2873-Y	2SC2873
52149	MY	2SJ278	2SJ278
52150	MYs	BF 1012	BF 1012
52151	MZ	P6 SMB-110A	P6 SMB-110A
52152	MZ	BFS 17R	BFS 17R
52153	MZ	MA 370	MA 370
52154	MZ203...224	3...24V, 0,3W	BZX55/..., BZX79/..., ZPD..., 1N5225...52

52155	MZ303...343A,B,C	3...43V, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5225...60
52156	MZ406...424	6...24V, 1W	BZW22/..., BZX61/..., ZPY..., 1N4735...49
52157	MZ92-2,4...-200	2,4..200V, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5221...81
52158	MZD3,9..200	3,9..200V, 1,32W	BZW22/..., BZX61/..., ZPY..., 1N5915...56
52159	MZF2,7...33	2,7..33V, 0,4W	BZX55/..., BZX79/..., ZPD..., 1N5222...57,...
52160	MZs	BF 1005	BF 1005
52161	N	2SK1963	2SK1963
52162	N	HVU 316	HVU 316
52163	N	S 5566N	S 5566N
52164	N0	BFS 505	BFS 505
52165	N1	RT 1N141M	RT 1N141M
52166	N1	BFR 53	BFR 53
52167	N1	TN 0201T	TN 0201T
52168	N1	RT 1N141C	RT 1N141C
52169	N1	30V	BA 127, BAY 18...21, 1N4148...49
52170	N1	D71F2T1	D71F2T1
52171	N1	RT 1N137P	RT 1N137P
52172	N10	SO 918	SO 918
52173	N10	BA 176	BA 176
52174	N103	50V	BY 126...127, BY 133...135, 1N4001...07
52175	N11	SO 2369	SO 2369
52176	N11	2SK334-N11	2SK334
52177	N11	20V	BA 127, BAY 17...21, 1N4148...49
52178	N12	2SK334-N12	2SK334
52179	N12	SO 2221	SO 2221
52180	N12	SM-1XN12	SM-1XN12
52181	N12	BA 127	BA 127
52182	N125	50V, 0,15A	BA 127, BAY 18...21, 1N4148...49
52183	N13	SO 2222	SO 2222
52184	N13	2SK334-N13	2SK334
52185	N13H1	2N6027	2N6027
52186	N13H2	2N6028	2N6028
52187	N13T1	2N6027	2N6027
52188	N13T2	2N6028	2N6028
52189	N14	2SK334-N14	2SK334
52190	N140	RT 1N140S	RT 1N140S
52191	N141	RT 1N141S	RT 1N141S
52192	N144	RT 1N144S	RT 1N144S
52193	N15	2SC3360-N15	2SC3360
52194	N16	2SC3360-N16	2SC3360
52195	N16	SM-1XN16	SM-1XN16
52196	N17	2SC3360-N17	2SC3360
52197	N17	SO 1613	SO 1613
52198	N17	20V	BA 127, BAY 17...21, 1N4148...49
52199	N18	SO 1711	SO 1711

52200	N180	1N4148	1N4148
52201	N2	F 1N2	F 1N2
52202	N2	BFS 520	BFS 520
52203	N2	RT 1N241C	RT 1N241C
52204	N2	2SC1653-N2	2SC1653
52205	N2	RT 1N241M	RT 1N241M
52206	N2	MMBT 200	MMBT 200
52207	N2	SM-1XN02	SM-1XN02
52208	N2	BA 127	BA 127
52209	N20	SO 2222A	SO 2222A
52210	N20	75V, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
52211	N203A..YY	<0,2/<5mA, 25µs	BT 149/..., TAG 59-..., 2N6681...85
52212	N24	35V	BA 127, BAY 18...21, 1N4148...49
52213	N241	RT 1N241S	RT 1N241S
52214	N27	SO 1893	SO 1893
52215	N28	SO 3572	SO 3572
52216	N28	BFR 520	BFR 520
52217	N2A	MMBT 200A	MMBT 200A
52218	N3	2SC1653-N3	2SC1653
52219	N3	KDV 152S	KDV 152S
52220	N3	RT 1N441C	RT 1N441C
52221	N3	RT 1N441M	RT 1N441M
52222	N30	BFR 505	BFR 505
52223	N32	10V	BA 127, BAY 17...21, 1N4148...49
52224	N33	BFG 505	BFG 505
52225	N36	BFG 520	BFG 520
52226	N37	BFG 540	BFG 540
52227	N39	BFG 505X	BFG 505X
52228	N4	F 1N4	F 1N4
52229	N4	F 1N4	F 1N4
52230	N4	BFS 540	BFS 540
52231	N4	RT 1N434C	RT 1N434C
52232	N4	2SC1653-N4	2SC1653
52233	N4	BFR 53R	BFR 53R
52234	N4	RT 1N434M	RT 1N434M
52235	N4	SM-1XN04	SM-1XN04
52236	N413L	Ub26..32V, Ib<0,05mA, Itsm2A	1N5761, D3202U
52237	N413M	N413L, Ub29..37V	1N5762, D3202Y, BR100, DO201YR
52238	N413N	N413L, Ub34..40V	1N5762, D3202U
52239	N42	BFG 520X	BFG 520X
52240	N43	BFG 540X	BFG 505X
52241	N430	RT 1N430S	RT 1N430S
52242	N434	RT 1N434S	RT 1N434S
52243	N44	SO 3571	SO 3571
52244	N441	RT 1N441S	RT 1N441S



52245	N45	BFG 505XR	BFG 505XR
52246	N47	SO 3570	SO 3570
52247	N48	BFG 520XR	BFG 520XR
52248	N49	BFG 540XR	BFG 540XR
52249	N5	RT 1N144M	RT 1N144M
52250	N5	2SC1653-N5	2SC1653
52251	N5	RT 1N144C	RT 1N144C
52252	N54	SO 2221A	SO 2221A
52253	N6	F 1N6	F 1N6
52254	N6	RT 1N430C	RT 1N430C
52255	N6	2SC1653-N6	2SC1653
52256	N6	BFS 25A	BFS 25A
52257	N6	RT 1N430M	RT 1N430M
52258	N6	SM-1XN06	SM-1XN06
52259	N6	1N4148	1N4148
52260	N62	BA 127	BA 127
52261	N66	SO 269	SO 269
52262	N7	RT 1N140C	RT 1N140C
52263	N7	2SC1653-N7	2SC1653
52264	N7	RT 1N140M	RT 1N140M
52265	N71	SO 3904	SO 3904
52266	N72	SO 3903	SO 3903
52267	N79	SO 5550	SO 5550
52268	N8	SM-1XN08	SM-1XN08
52269	N8	20V	BA 127, BAY 17...21, 1N4148...49
52270	N80	SO 5551	SO 5551
52271	N81	SO 2369A	SO 2369A
52272	N87	SO 502S	SO 502S
52273	N88	SO 970	SO 970
52274	N9	1SS372	1SS372
52275	N9	1SS374	1SS374
52276	N91	SO 642	SO 642
52277	N94	SO 517	SO 517
52278	NA	CFY 35-20	-
52279	NA	KRC101S	KRC 101S
52280	NA	BFS 20	BFS 20
52281	NA	MMBT 100	MMBT 100
52282	NA	2SK1273	2SK1273
52283	NA01E...	25V, 0,8A, 0,6W, 200MHz	BC 337...338, BC 635, BC 637, BC 639
52284	NA01F...	NA 01E	BC 337...338, BC 635, BC 637, BC 639
52285	NA01H...	NA 01E	BC 337...338, BC 635, BC 637, BC 639
52286	NA02E...	25V, 0,8A, 0,6W, 200MHz	BC 327...328, BC 636, BC 638, BC 640
52287	NA02F...	NA 02E	BC 327...328, BC 636, BC 638, BC 640
52288	NA02H...	NA 02E	BC 327...328, BC 636, BC 638, BC 640
52289	NA1	MMBT 100A	MMBT 100A

52290	NA1	2SK2053	2SK2053
52291	NA11E...	25V, 1A, 0,6W, 200MHz	BC 337...338, BC 635, BC 637, BC 639
52292	NA11F...	NA 11E	BC 337...338, BC 635, BC 637, BC 639
52293	NA11H...	NA 11E	BC 337...338, BC 635, BC 637, BC 639
52294	NA12E...	25V, 1A, 0,6W, 200MHz	BC 327...328, BC 636, BC 638, BC 640
52295	NA12F...	NA 12E	BC 327...328, BC 636, BC 638, BC 640
52296	NA12H...	NA 12E	BC 327...328, BC 636, BC 638, BC 640
52297	NA2	2SK2054	2SK2054
52298	NA21E...	25V, 1,5A, 0,6W, 200MHz	MPS 650, 2SC2236, 2SD1146, 2SD1207
52299	NA21F...	NA 21E	MPS 650, 2SC2236, 2SD1146, 2SD1207
52300	NA21H...	NA 21E	MPS 650, 2SC2236, 2SD1146, 2SD1207
52301	NA21X...	NA 21E, 0,75W	2SD1295, 2SD1801, BD 515, BD 525
52302	NA21Y...	NA 21E, 0,75W	2SD1295, 2SD1801, BD 515, BD 525
52303	NA21Z...	NA 21E, 0,75W	BD 515, BD 525, 2SD1295, 2SD1801
52304	NA22E...	25V, 1,5A, 0,6W, 200MHz	MPS 750, 2SA966, 2SA1382, 2SB892
52305	NA22F...	NA 22E	MPS 750, 2SA966, 2SA1382, 2SB892
52306	NA22H...	NA 22E	MPS 750, 2SA966, 2SA1382, 2SB892
52307	NA22X...	NA 22E, 0,75W	2SB968, 2SB1201, BD 516, BD 526
52308	NA22Y...	NA 22E, 0,75W	2SB968, 2SB1201, BD 516, BD 526
52309	NA22Z...	NA 22E, 0,75W	BD 516, BD 526, 2SD968, 2SD1201
52310	NA3	2SK2055	2SK2055
52311	NA31K...	35V, 2A, 1,75W, >20MHz	BC 365, BD 505, BD 515, BD 525
52312	NA31L...	NA 31K	BD 429, BD 813, BD 815, BD 817
52313	NA31M...	NA 31K	2SC1226
52314	NA31X...	NA 31K, 0,75W	2SD1078, 2SD1801, BD 515, BD 525
52315	NA31Y...	NA 31K, 0,75W	2SD1078, 2SD1801, BD 515, BD 525
52316	NA31Z...	NA 31K, 0,75W	BD 375, 2SD1380, 2SD1078, 2SD1801
52317	NA32K...	35V, 2A, 1,75W, >20MHz	BC 362, BD 506, BD 516, BD 526
52318	NA32L...	NA 32K	BD 430, BD 814, BD 616, BD 818
52319	NA32M...	NA 32K	2SA699
52320	NA32X...	NA 32K, 0,75W	2SB838, 2SB1201, BD 516, BD 526
52321	NA32Y...	NA 32K, 0,75W	2SB838, 2SB1201, BD 516, BD 526
52322	NA32Z...	NA 32K, 0,75W	BD 376, 2SB1009, 2SB838, 2SD1201
52323	NA4	2SK2157	2SK2157
52324	NA41U...	35V, 2,5A, 25W	BD 175, BD 185, BD 233, BD 437
52325	NA41W...	NA 41U	BD 241, BD 243, BD 533, BD 933
52326	NA42U...	35V, 2,5A, 25W	BD 176, BD 186, BD 234, BD 438
52327	NA42W...	NA 42U	BD 242, BD 244, BD 534, BD 934
52328	NA51U	50V, 3,5A, 30W	BD 177, BD 187, BD 439, 2N5191...92
52329	NA51W	NA 51U	BD 243, BD 535, BD 539A, BD 949
52330	NA52U	50V, 3,5A, 30W	BD 178, BD 188, BD 440, 2N5194...95
52331	NA52W	NA 52U	BD 244, BD 536, BD 540A, BD 950
52332	NA61U	50V, 4,5A, 40W	BD 187, BD 439, 2N5191...5192
52333	NA61W	NA 61U	BD 243, BD 539A, BD 543A, BD 949
52334	NA62U	50V, 4,5A, 40W	BD 188, BD 440, 2N5194...5195

52335	NA62W	NA 62U	BD 244, BD 540A, BD 544A, BD 950
52336	NA71U...	65V, 3,5A, 40W	BD 189, BD 441, 2N5192
52337	NA71W...	NA 71U	BD 243A, BD 537, BD 539B, BD 951
52338	NA72U...	65V, 3,5A, 40W	BD 190, BD 442, 2N5195
52339	NA72W...	NA 72U	BD 244A, BD 538, BD 540B, BD 952
52340	NAS29(A...C)	BD 239(A..C)	BD 239
52341	NAS30(A...C)	BD 240(A..C)	BD 240
52342	NAS31(A...C)	BD 241(A..C)	BD 241
52343	NAS32(A...C)	BD 242(A..C)	BD 242
52344	NAS41(A...C)	BD 243(A..C)	BD 243
52345	NAS42(A...C)	BD 244(A..C)	BD 244
52346	NB	CFY 35-23	-
52347	NB	BF 599	BF 599
52348	NB	KRC102S	KRC 102S
52349	NB	2SK1483	2SK1483
52350	NB011F...	NB 011E	BC 167, BC 182, BC 237, BC 547
52351	NB011H...	NB 011E	BC 167, BC 182, BC 237, BC 547
52352	NB012F...	NB 011F, 55V	BC 167, BC 182, BC 237, BC 547
52353	NB012H...	NB 011H, 55V	BC 167, BC 182, BC 237, BC 547
52354	NB013E...	NB 011E	BC 184, BC 413...414, BC 550
52355	NB013F...	NB 011F	BC 184, BC 413...414, BC 550
52356	NB013H...	NB 011H	BC 184, BC 413...414, BC 550
52357	NB014E...	NB 011E, 55V,	BC 550, 2SC2240, 2SC2459
52358	NB014F...	NB 011F, 55V,	BC 550, 2SC2240, 2SC2459
52359	NB014H...	NB 011H, 55V,	BC 550, 2SC2240, 2SC2459
52360	NB021E...	40V, 0,03A, 0,6W, 120MHz	BC 212, BC 257, BC 307, BC 557
52361	NB021F...	NB 021F	BC 212, BC 257, BC 307, BC 557
52362	NB021H...	NB 021H	BC 212, BC 257, BC 307, BC 557
52363	NB022E...	NB 021E, 55V	BC 212, BC 257, BC 307, BC 557
52364	NB022F...	NB 021F, 55V	BC 212, BC 257, BC 307, BC 557
52365	NB022H...	NB 021H, 55V	BC 212, BC 257, BC 307, BC 557
52366	NB023E...	NB 021E	BC 212, BC 415...416, BC 560
52367	NB023F...	NB 021F	BC 212, BC 415...416, BC 560
52368	NB023H...	NB 021H	BC 212, BC 415...416, BC 560
52369	NB024E...	NB 021E, 55V,	BC 560, 2SA970, 2SA1049
52370	NB024F...	NB 021F, 55V,	BC 560, 2SA970, 2SA1049
52371	NB024H...	NB 021H, 55V,	BC 560, 2SA970, 2SA1049
52372	NB111E...	40V, 0,1A, 0,6W, >100MHz	BC 167, BC 182, BC 237, BC 547
52373	NB111F...	NB 111E	BC 167, BC 182, BC 237, BC 547
52374	NB111H...	NB 111E	BC 167, BC 182, BC 237, BC 547
52375	NB112E...	NB 111E, 55V	BC 174, BC 182, BC 190, BC 546
52376	NB112F...	NB 111F, 55V	BC 174, BC 182, BC 190, BC 546
52377	NB112H...	NB 111H, 55V	BC 174, BC 182, BC 190, BC 546
52378	NB113E...	NB 111E, 70V	BC 546, 2SC2240, 2SC2459, 2SC3245(A)
52379	NB113F...	NB 111F, 70V	BC 546, 2SC2240, 2SC2459, 2SC3245(A)

52380	NB121E...	40V, 0,1A, 0,6W, >100MHz	BC 212, BC 257, BC 307, BC 557
52381	NB121F...	NB 121E	BC 212, BC 257, BC 307, BC 557
52382	NB121H...	NB 121E	BC 212, BC 257, BC 307, BC 557
52383	NB122E...	NB 121E, 55V	BC 212, BC 256, BC 266, BC 556
52384	NB122F...	NB 121F, 55V	BC 212, BC 256, BC 266, BC 556
52385	NB122H...	NB 121H, 55V	BC 212, BC 256, BC 266, BC 556
52386	NB123E...	NB 121E, 70V	BC 556, 2SA970, 2SA 1049, 2SA1285(A)
52387	NB123F...	NB 121F, 70V	BC 556, 2SA970, 2SA1049, 2SA1285(A)
52388	NB123H...	NB 121H, 70V	BC 556, 2SA970, 2SA1049, 2SA1285(A)
52389	NB211E...	40V, 0,5A, 0,6W, >50MHz	BC 337, BC 635, BC 637, BC 639
52390	NB211F...	NB 211E	BC 337, BC 635, BC 637, BC 639
52391	NB211H...	NB 211E	BC 337, BC 635, BC 637, BC 639
52392	NB211X...	NB 211E, 0,75W	BC 365, BD 507, BD 515, BD 525
52393	NB211Y...	NB 211E, 0,75W	BC 365, BD 507, BD 515, BD 525
52394	NB211Z...	NB 211E, 0,75W	BC 365, BD 507, BD 515, BD 525
52395	NB212E...	NB 211E, 55V	BC 337A, BC 637, BC 639, 2SD667
52396	NB212F...	NB 211F, 55V	BC 337A, BC 637, BC 639, 2SD667
52397	NB212H...	NB 211H, 55V	BC 337A, BC 637, BC 639, 2SD667
52398	NB212X...	NB 211E, 55V, 0,75W	BC 366, BD 517, BD 525
52399	NB212Y...	NB 211E, 55V, 0,75W	BC 366, BD 517, BD 525
52400	NB212Z...	NB 211E, 55V, 0,75W	BC 366, BD 517, BD 525
52401	NB213E...	NB 211E, 70V	BC 639, 2SD667
52402	NB213F...	NB 211F, 70V	BC 639, 2SD667
52403	NB213H...	NB 211H, 70V	BC 639, 2SD667
52404	NB213X...	NB 211E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52405	NB213Y...	NB 211E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52406	NB213Z...	NB 211E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52407	NB221E...	40V, 0,5A, 0,6W, >50MHz	BC 327, BC 636, BC 638, BC 640
52408	NB221F...	NB 221E	BC 327, BC 636, BC 638, BC 640
52409	NB221H...	NB 221E	BC 327, BC 636, BC 638, BC 640
52410	NB221X...	NB 221E, 0,75W	BC 362, BD 508, BD 516, BD 526
52411	NB221Y...	NB 221E, 0,75W	BC 362, BD 508, BD 516, BD 526
52412	NB221Z...	NB 221E, 0,75W	BC 362, BD 508, BD 516, BD 526
52413	NB222E...	NB 221E, 55V	BC 327A, BC 638, BC 640, 2SB647
52414	NB222F...	NB 221F, 55V	BC 327A, BC 638, BC 640, 2SB647
52415	NB222H...	NB 221H, 55V	BC 327A, BC 638, BC 640, 2SB647
52416	NB222X...	NB 221E, 55V, 0,75W	BC 363, BD 518, BD 526
52417	NB222Y...	NB 221E, 55V, 0,75W	BC 363, BD 518, BD 526
52418	NB222Z...	NB 221E, 55V, 0,75W	BC 363, BD 518, BD 526
52419	NB223E...	NB 221E, 70V	BC 640, 2SB647
52420	NB223F...	NB 221F, 70V	BC 640, 2SB647
52421	NB223H...	NB 221H, 70V	BC 640, 2SB647
52422	NB223X...	NB 221E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530
52423	NB223Y...	NB 221E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530
52424	NB223Z...	NB 221E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530

52425	NB311E...	40V, 1,5A, 0,6W, >20MHz	MPS 650...651, 2SD1146, 2SC3328
52426	NB311F...	NB 311E	MPS 650...651, 2SD1146, 2SC3328
52427	NB311H...	NB 311E	MPS 650...651, 2SD1146, 2SC3328
52428	NB311K...	NB 311E, 1,75W	BC 365, BD 507, BD 515, BD 525
52429	NB311L...	NB 311E, 1,75W	BD 813, BD 815, BD 817
52430	NB311M...	NB 311E, 1,75W	2SC1226, 2SC1848
52431	NB311X...	NB 311E, 0,75W	BC 365, BD 507, BD 515, BD 525
52432	NB311Y...	NB 311E, 0,75W	BC 365, BD 507, BD 515, BD 525
52433	NB311Z...	NB 311E, 0,75W	BC 365, BD 507, BD 515, BD 525
52434	NB312E...	NB 311E, 55V	MPS 650...651, 2SC3328
52435	NB312F...	NB 311F, 55V	MPS 650...651, 2SC3328
52436	NB312H...	NB 311H, 55V	MPS 650...651, 2SC3328
52437	NB312K...	NB 311E, 55V, 1,75W	BC 366, BD 517, BD 525
52438	NB312L...	NB 311E, 55V, 1,75W	BD 815, BD 817
52439	NB312M...	NB 311E, 55V, 1,75W	2SC1848
52440	NB312X...	NB 311E, 55V, 0,75W	BC 366, BD 517, BD 525
52441	NB312Y...	NB 311E, 55V, 0,75W	BC 366, BD 517, BD 525
52442	NB312Z...	NB 311E, 55V, 0,75W	BC 366, BD 517, BD 525
52443	NB313E...	NB 311E, 70V	MPS 651, 2SC3328
52444	NB313F...	NB 311F, 70V	MPS 651, 2SC3328
52445	NB313H...	NB 311H, 70V	MPS 651, 2SC3328
52446	NB313K...	NB 311E, 70V, 1,75W	BC 367, BD 519, BD 527, BD 529
52447	NB313L...	NB 311E, 70V, 1,75W	BD 817
52448	NB313M...	NB 311E, 70V, 1,75W	2SC1848
52449	NB313X...	NB 311E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52450	NB313Y...	NB 311E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52451	NB313Z...	NB 311E, 70V, 0,75W	BC 367, BD 519, BD 527, BD 529
52452	NB321E...	40V, 1,5A, 0,6W, >20MHz	MPS 750...751, 2SA1382, 2SA1315
52453	NB321F...	NB 321E	MPS 750...751, 2SA1382, 2SA1315
52454	NB321H...	NB 321E	MPS 750...751, 2SA1382, 2SA1315
52455	NB321K...	NB 321E, 1,75W	BC 362, BD 508, BD 516, BD 526
52456	NB321L...	NB 321E, 1,75W	BD 814, BD 816, BD 818
52457	NB321M...	NB 321E, 1,75W	2SA699, 2SA887
52458	NB321X...	NB 321E, 0,75W	BC 362, BD 508, BD 516, BD 526
52459	NB321Y...	NB 321E, 0,75W	BC 362, BD 508, BD 516, BD 526
52460	NB321Z...	NB 321E, 0,75W	BC 362, BD 508, BD 516, BD 526
52461	NB322E...	NB 321E, 55V	MPS 750...751, 2SA1315
52462	NB322F...	NB 321F, 55V	MPS 750...751, 2SA1315
52463	NB322H...	NB 321H, 55V	MPS 750...751, 2SA1315
52464	NB322K...	NB 321E, 55V, 1,75W	BC 363, BD 518, BD 526
52465	NB322L...	NB 321E, 55V, 1,75W	BD 816, BD 818
52466	NB322M...	NB 321E, 55V, 1,75W	2SA887
52467	NB322X...	NB 321E, 55V, 0,75W	BC 363, BD 518, BD 526
52468	NB322Y...	NB 321E, 55V, 0,75W	BC 363, BD 518, BD 526
52469	NB322Z...	NB 321E, 55V, 0,75W	BC 363, BD 518, BD 526

52470	NB323E...	NB 321E, 70V	MPS 751, 2SA1315
52471	NB323F...	NB 321F, 70V	MPS 751, 2SA1315
52472	NB323H...	NB 321H, 70V	MPS 751, 2SA1315
52473	NB323K...	NB 321E, 70V, 1,75W	BC 364, BD 520, BD 528, BD 530
52474	NB323L...	NB 321E, 70V, 1,75W	BD 818
52475	NB323M...	NB 321E, 70V, 1,75W	2SA887
52476	NB323X...	NB 321E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530
52477	NB323Y...	NB 321E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530
52478	NB323Z...	NB 321E, 70V, 0,75W	BC 364, BD 520, BD 528, BD 530
52479	NBD517	BD 517	BD 517
52480	NBD518	BD 518	BD 518
52481	NC	KRC103S	KRC 103S
52482	NC	2SK1485	2SK1485
52483	NCp	BF 840	BF 840
52484	ND	P6 SMB-120	P6 SMB-120
52485	ND	2SD1306-D	2SD1306
52486	ND	KRC104S	KRC 104S
52487	ND	2SK1583	2SK1583
52488	ND16AT..MT	NP 16 AT..MT	-
52489	ND2012E	ND 2012L, 0,22A, 1,5W	-
52490	ND2012L	<12Ohm(20mA)	-
52491	ND2020E	ND 2020L, 0,18A, 1,5W	-
52492	ND2020L	<20Ohm(20mA)	-
52493	ND2406B	ND 2406L, 0,57A, 5W	-
52494	ND2406L	<6Ohm(30mA)	-
52495	ND2410B	ND 2410L, 0,46A, 5W	-
52496	ND2410L	<10Ohm(30mA)	-
52497	ND30AP..MP	NP 30 AP..MP	-
52498	NDB4050..	NDP 4050..	NDP 4050...
52499	NDB4060..	NDP 4060..	NDP 4060...
52500	NDB506..	NDP 506..	NDP 506...
52501	NDB603..	NDP 603..	NDP 603...
52502	NDB6030..	NDP 6030..	NDP 6030...
52503	NDB6050..	NDP 6050..	NDP 6050...
52504	NDB6051..	NDP 6051..	NDP 6051...
52505	NDB6060..	NDP 6060..	NDP 6060...
52506	NDB7051..	NDP 7051..	NDP 7051...
52507	NDB7052..	NDP 7052..	NDP 7052...
52508	NDB7060..	NDP 7060..	NDP 7060...
52509	NDB7061..	NDP 7061..	NDP 7061...
52510	NDC7001	T1NDC7002C, T2NDC7003P	-
52511	NDC7002C	<2Ohm(0,51A)	-
52512	NDC7003P	<5Ohm(0,34A)	-
52513	NDp	BF 841	BF 841
52514	NDP4050	<0,1Ohm(7,5A)	IRF 530...533, 2SK673, 2SK919, 2SK1416



52515	NDP4050L..4060L	NDP 4050..4060	BUK 552-..., 2SK971, 2SK1301
52516	NDP4060	NDP 4050, 60V	IRF 530...533, 2SK673, 2SK919, 2SK1416
52517	NDP506A	<50mOhm(13A)	BUK 456-100, 2SK1291, 2SK1296, 2SK2411
52518	NDP506AL,BL	NDP 506A,B	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
52519	NDP506B	<60mOhm(12A)	BUK 456-100, 2SK1291, 2SK1296, 2SK2411
52520	NDP6030L	75W,<135mOhm(26A)	BUK 556-60,
52521	NDP603AL	<22mOhm(25A)	BUK 555-50, 2SK1291, 2SK1296, 2SK2411
52522	NDP6050	<25mOhm(24A)	BUK 456-50, BUZ 100, PRFZ 40
52523	NDP6050L	NDP 6050	BUK 556-60
52524	NDP6051	<22mOhm(24A)	BUK 456-50, BUZ 100, PRFZ 40
52525	NDP6060	NDP 6050, 60V	BUK 556-60
52526	NDP6060L	NDP 6060	BUK 556-60
52527	NDP7051	<16mOhm(35A)	-
52528	NDP7051L	<14mOhm(34A)	-
52529	NDP7052	<10mOhm(37,5A)	-
52530	NDP7052L	NDP 7052	-
52531	NDP7060	<13mOhm(40A)	-
52532	NDP7060L	NDP 7060, <13mOhm(37,5A)	-
52533	NDP7061	<16mOhm(35A)	-
52534	NDP7061L	NDP 7061, <18mOhm(30A)	-
52535	NDS0605	60V, 0,18A, <50hm(0,5A)	2SJ210..211
52536	NDS0610	NDF 0610, 0,12A	2SJ210...211
52537	NDS331N	20V, 1,3A, <0,16Ohm	-
52538	NDS332P	20V, 1A, <0,41Ohm(1A)	-
52539	NDS335N	20V, 1,7A, <0,11Ohm	-
52540	NDS336P	20V, 1,2A, <0,27Ohm	-
52541	NDS351N	30V, +-1,1A, <0,25Ohm	-
52542	NDS352AP	NDS 352P, 30V, +-0,9A	-
52543	NDS352P	20V, +-0,85A, <0,5Ohm	-
52544	NDS355N	30V, +-1,6A, <0,125Ohm	-
52545	NDS356AP	NDS 352P, 30V, +-1,1A	-
52546	NDS356P	20V, +-1,1A, <0,3Ohm	-
52547	NDS7002A	60V, 0,28A, <2Ohm(0,5A)	BSS 145, BST82
52548	NDT014	60V, +-2,7A, <0,2Ohm(1,6A)	-
52549	NDT014L	<0,16Ohm(3,4A)	-
52550	NDT2955	<0,3Ohm(2,5A),<55/60ns	-
52551	NDT3055	<75/125ns	-
52552	NDT3055L	<0,12Ohm(3,7A)	-
52553	NDT410EL	100V, 2,1A, <0,25Ohm(2,1A)	-
52554	NDT451AN	<35mOhm(7,2A)	-
52555	NDT451N	30V, +-5,5A, <0,05Ohm(5,5A)	-
52556	NDT452AP	NDT 452P, 5A, <65mOhm(5A)	-
52557	NDT452P	30V, +-3A, <0,18Ohm(3A)	-
52558	NDT453N	<50/100ns	-
52559	NDT454P	30V, +-5,9A, <50mOhm(5,9A)	-

52560	NDT455N	<15mOhm(11,5A)	-
52561	NDT456P	30V, +-7,5A, <30mOhm(7,5A)	-
52562	NE	P6 SMB-120A	P6 SMB-120A
52563	NE	2SD1306-E	2SD1306
52564	NE	KRC105S	KRC 105S
52565	NE	2SK1585	2SK1585
52566	NF	P6 SMB-130	P6 SMB-130
52567	NF	KRC106S	KRC 106S
52568	NF	2SK1587	2SK1587
52569	NG	P6 SMB-130A	P6 SMB-130A
52570	NG	2SK1588	2SK1588
52571	NH	P6 SMB-150	P6 SMB-150
52572	NH	KRC107S	KRC 107S
52573	NH	2SK1584	2SK1584
52574	NI	KRC108S	KRC 108S
52575	NI	2SK1586	2SK1586
52576	NI-	3SK191	3SK191
52577	NJ	KRC109S	KRC 109S
52578	NK	P6 SMB-150A	P6 SMB-150A
52579	NK	KRC110S	KRC 110S
52580	NK	2SC2780-NK	2SC2780
52581	NL	P6 SMB-160	P6 SMB-160
52582	NL	2SA1520	2SA1520
52583	NL	2SC2780-NL	2SC2780
52584	NM	P6 SMB-160A	P6 SMB-160A
52585	NM	KRC111S	KRC 111S
52586	NM	2SC2780-NM	2SC2780
52587	NM400	170V, 2A, 30W, >10MHz	2SC779, 2SC825, 2SC1025, 2SD610
52588	NMT2222	2N2222, SMD	-
52589	NMT2907	2N2907, SMD	-
52590	NN	P6 SMB-170	P6 SMB-170
52591	NN	KRC112S	KRC 112S
52592	NN16AT..MT	NP 16 AT..MT	-
52593	NO	2SC3138-O	2SC3138
52594	NO	KRC113S	KRC 113S
52595	NO	2SK1592	2SK1592
52596	NO	2SA1213-O	2SA1213
52597	NO5	SO 2484	SO 2484
52598	NO8	SO 930	SO 930
52599	NP	P6 SMB-170A	P6 SMB-170A
52600	NP	KRC114S	KRC 114S
52601	NP	2SK1593	2SK1593
52602	NP	SM 6T 68C	SM 6T...
52603	NP16AT..MT	50..1000V, 16A	FE 16A...J, MUR 1605CT...1660CT
52604	NP30AP..MP	50..1000V, 30A	RGP 30AP...MP, MUR 3005PT...3060PT

52605	NPS...		
52606	NQ	P6 SMB-180	P6 SMB-180
52607	NQ	KRC241S	KRC 241S
52608	NQ	SM 6T 68CA	SM 6T...
52609	NQ	2SK1959	2SK1959
52610	NR	P6 SMB-180A	P6 SMB-180A
52611	NR	KRC242S	KRC 242S
52612	NR	2SD1679-R	2SD1679
52613	NR	2SK1960	2SK1960
52614	NR-001E	BC 548	BC 548
52615	NR-071E	BC 548	BC 548
52616	NR041E	20V, 0,03A, 0,6W	BC 169, BC 184, BC 239, BC 549
52617	NR041F	NR 041E	BC 169, BC 184, BC 239, BC 549
52618	NR041H	NR 041E	BC 169, BC 184, BC 239, BC 549
52619	NR421D...	700MHz	BF 225, BF 314, BF 496, BF 502, BF 505
52620	NR421F...	NR 421D	BF 225, BF 314, BF 496, BF 502, BF 505
52621	NR431E...	600MHz	BF 255, BF 314, BF 496, NF 502, BF 505
52622	NR431F...	NR 431E	BF 255, BF 314, BF 496, NF 502, BF 505
52623	NR431H...	NR 431E	BF 255, BF 314, BF 496, NF 502, BF 505
52624	NR461E...	300MHz	BF 240...241, BF 254...255, BF 594...595
52625	NR461F...	NR 461E	BF 240...241, BF 254...255, BF 494...495
52626	NR461H...	NR 461E	BF 240...241, BF 254...255, BF 494...495
52627	NR601E	BC 328	BC 328
52628	NR8AT..MT	NS 8 AT..MT	-
52629	NS	P6 SMB-200	P6 SMB-200
52630	NS	KRC243S	KRC 243S
52631	NS	2SD1679-S	2SD1679
52632	NS	2SK2109	2SK2109
52633	NS3903	2N3903, 0,36W	2N3903
52634	NS3904	2N3904, 0,36W	2N3904
52635	NS8AT..MT	50..1000V, 8A	BY 239/..., GP 80A...M
52636	NSD-U...		
52637	NSDJ105	J 105, SMD	-
52638	NT	P6 SMB-200A	P6 SMB-200A
52639	NT	KRC244S	KRC 244S
52640	NT	2SC4362	2SC4362
52641	NT	2SD1679-T	2SD1679
52642	NT-P5V6...P15	5,6...15V, 5%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5232...45
52643	NT0,6C0V7	0,7V(5mA)	BZ 102/0V7, BZX 55/C0V8, ZPD 1
52644	NT0,6C2V7...C75	2,7...75V, 5%, 0,3W	BZX55/..., BZX79/..., ZPD..., 1N5223...67
52645	NT05E15...E150	15..150V, 0,29A	BAS 11, BYX 57/...
52646	NT3C10...C100	10...100V, 5%, 3W(Tc45°)	BZV 15/...
52647	NT50C4V7...C33	4,7...33V, 5%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5230...57
52648	NT55C0V7	0,7V(5mA), 0,5W	BZW 22/C1, BZX 83/C0V8, ZPY 1
52649	NT55C1V4	1,4V(5mA), 0,5W	BZ 102/1V4

52650	NT55C2V1	2,1V(5mA), 0,5W	BZ 102/2V1, BZX 75/C2V1, ZTE 2
52651	NT55C2V7...200	2,7...200V, 5%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5223...81
52652	NT77C0V7	0,7V(100mA), 1,5W	BZW 22/C1, ZPY 1, ZY 1
52653	NT77C1V4	1,4V(100mA), 1,5W	-
52654	NT77C2V7...C200	2,7...200V, 5%, 1,5W	BZW22/..., BZY97/..., ZY..., 1N5913...6031
52655	NT80C5V6...27	5,6...27V, 5%, 10W(Tc100°)	-
52656	NT9967	BA 157	BA 157
52657	NTM2222(A)	2N2222(A), SMD	BSR14, BSS79, PMBT2222(A), SMBT2222(A)
52658	NTM2369(A)	2N2369(A), SMD	FMMT 2369(A), PMBT 2369(A), 2SC4168
52659	NTM2907(A)	2N2907(A), SMD	A)
52660	NTM3904	2N3904, SMD	BC 846, BCV 71...70, PMBT 3904, 2SC4209
52661	NTM3906	2N3906, SMD	BC 856...857, BCX 71, PMBT 3906, 2SA1620
52662	NU	P6 SMB-220	P6 SMB-220
52663	NU	KRC245S	KRC 245S
52664	NU	2SK2111	2SK2111
52665	NV	P6 SMB-220A	P6 SMB-220A
52666	NV	KRC246S	KRC 246S
52667	NV	2SK2112	2SK2112
52668	NW	KRC231S	KRC 231S
52669	NW	2SK2159	2SK2159
52670	NX	SM 6T 100C	SM 6T...
52671	NY	2SC4004	2SC4004
52672	NY	2SC3138-Y	2SC3138
52673	NY	KRC232S	KRC 232S
52674	NY	2SC3774	2SC3774
52675	NY	2SJ317	2SJ317
52676	NY	2SA1213-Y	2SA1213
52677	NY	SM 6T 100CA	SM 6T...
52678	NZ	BFS 20R	BFS 20R
52679	NZ	KRC233S	KRC 233S
52680	NZT44H8	D 44H8	-
52681	NZT45H8	D 45H8	-
52682	NZT651	80V, 4A, >75MHz	-
52683	NZT6714	2N6714	-
52684	NZT6715	2N6715	-
52685	NZT6717	2N6717	-
52686	NZT6726	2N6726, 1,5A	-
52687	NZT6728	2N6728, 1,2A	-
52688	NZT6729	2N6729, 1A	-
52689	NZT7053	2N7053	-
52690	NZT751	80V, 4A, >75MHz	-
52691	O05	SO 2484R	SO 2484R
52692	O08	SO 930R	SO 930R
52693	O11	SO 2369R	SO 2369R
52694	O12	SO2221R	SO 2221R

52695	O13	SO 2222R	SO 2222R
52696	O15	2SA1609-O15	2SA1609
52697	O16	2SA1609-O16	2SA1609
52698	O17	SO 1613R	SO 1613R
52699	O17	2SA1609-O17	2SA1609
52700	O18	SO 1711R	SO 1711R
52701	O2	BST 82	BST 82
52702	O20	SO 1711AR	SO 1711AR
52703	O27	SO 1893R	SO 1893R
52704	O4	2SA1331-4	2SA1331
52705	O5	2SA1331-5	2SA1331
52706	O5	2SA1330-O5	2SA1330
52707	O54	SO 2221AR	SO 2221AR
52708	O6	2SA1331-6	2SA1331
52709	O6	2SA1330-O6	2SA1330
52710	O7	2SA1330-O7	2SA1330
52711	O71	SO 3904R	SO 3904R
52712	O72	SO 3903R	SO 3903R
52713	O79	SO 5550R	SO 5550R
52714	O80	SO 5551R	SO 5551R
52715	O81	SO 2369AR	SO 2369AR
52716	OA	μPA608T	αPA608T
52717	OA1154Q	OA 154Q	OA 154Q
52718	OA1161	OA 161	OA 161
52719	OA1180	OA 180	OA 180
52720	OA1182	OA 182	OA 182
52721	OA1182D	OA 182, 60V	OA 182
52722	OA126/5...18	5...18V, 0,25W	BZX55/..., BZX79/..., ZPD..., 1N5230...48
52723	OA127	19V, 0,15A	BA 147/25, BA 127, BAY 17, 1N4148
52724	OA128	OA 127, 35V	BA 147/50, BA 127, BAY 18, 1N4148
52725	OA129	OA 127, 75V	BA 147/100, BA 188, BAY 19, 1N4148
52726	OA130	OA 127, 135V	BA 147/150, BA 189, BAY 20, BAY 45
52727	OA131	OA 127, 230V	BA 147/230, BAY 21, BAY 46, BA 157
52728	OA132	OA 127, 320V	BA 147/300, BAY 21, BAY 46, BA 157
52729	OA150	100V, 35mA	AA 117...118, AA 132...133
52730	OA154(Q)	55V, 30mA	-
52731	OA159	40V, 20mA	AA 113, AA 119, 1N54, 1N60
52732	OA160	25V, 20mA	AA 112, AA 114, AA 116, 1N60
52733	OA161	140V, 35mA	AA 133
52734	OA172	40V, 10mA	AA 113, AA 119, 1N34, 1N54, 1N60
52735	OA174	70V, 35mA	AA 117...118, AA 132...134
52736	OA180	30V, 150mA	AAZ 49, AAZ 15, AAZ 17
52737	OA181		AA 113, AA 119, 1N34, 1N54, 1N60
52738	OA182	100V, 150mA	AA 117...118, AA 132...133
52739	OA182B	70V, 150mA	-

52740	OA182R	75V, 150mA	-
52741	OA200	50V, 0,16A	BA 127, BAY 18, BAY 44, 1N4148...49
52742	OA202	OA 200, 150V	BA 157, BA 189, BAY 20, BAY 45
52743	OA210	400V, 0,5A	BY 126...127, BY 134...135, 1N4004...09
52744	OA211	OA 210, 800V	BY 127, BY 133, BY 227, 1N4006...07
52745	OA212	BY 127	BY 127
52746	OA213	BY 127	BY 127
52747	OA214	OA 210, 700V	BY 127, BY 133, BY 227, 1N4006...07
52748	OA257	OA 90	OA 90
52749	OA261	OA 81	OA 81
52750	OA31	120V, 3,8A	-
52751	OA47	25V, 0,11A, <70ns	AAZ 18
52752	OA5	100V, 0,13A	AA 132...133, 1N270
52753	OA625	GA 100	GA 100
52754	OA626	GA 105	GA 105
52755	OA645	GA 101	GA 101
52756	OA647	GA 106	GA 106
52757	OA665	GA 102	GA 102
52758	OA666	GA 107	GA 107
52759	OA685	GA 103	GA 103
52760	OA686	GA 108	GA 108
52761	OA7	25V, 0,14A	AAZ 49, AAZ 15, AAZ 17...18
52762	OA70	22,5V, 50mA	AA 114, AA 116, 1N60
52763	OA705	GA 104	GA 104
52764	OA72	45V, 35mA	AA 113, AA 119, 1N34, 1N54, 1N60
52765	OA720	25V, 50mA	AA 117...118, AA 132...134, 1N34, 1N54
52766	OA721	25V, 75mA	AA 135...136
52767	OA73	30V, 15mA	AA 113, AA 119, 1N34, 1N54, 1N60
52768	OA741	50V, 75mA	AA 136
52769	OA780	95V, 50mA	AA 117...118, AA 132...133
52770	OA79	45V, 35mA	AA 113, AA 119, 1N34, 1N54, 1N60
52771	OA81	OA 91	OA 91
52772	OA85	OA 95	OA 95
52773	OA86	90V, 35mA	AAZ 15
52774	OA87	90V, 35mA	AAZ 15
52775	OA9	25V, 0,27A	AAZ 18
52776	OA90	30V, 30mA	AA 114, AA 116, 1N60
52777	OA900	25V	BA 127, BA 147/25, BAY 17, 1N4148...49
52778	OA901	OA 900, 50V	BA 127, BA 147/50, BAY 18, 1N4148...49
52779	OA902	OA 900, 75V	BA 188, BA 147/100, BAY 19, BAY 45
52780	OA903	OA 900, 150V	BA 189, BA 147/150, BAY 20, BAY 45
52781	OA904	OA 900, 250V	BA 147/300, BAY 21, BAY 46, BAY 88
52782	OA905	OA 900, 350V	BA 157, BA 199/350, BAY 21, BAY 88
52783	OA91(S)	115V, 50mA	AA 117...118, AA 132...133
52784	OA910		BA 111, BA 124, 1S2790, 1SV50



52785	OA92	15V, 10mA	AAY 21, AAY 27
52786	OA95(S)	115V, 50mA	AA 117...118, AA 132...133
52787	OA99(S)	45V, 50mA	1N60
52788	OAZ200	4,7V, 5%	BZX55/C4V7, BZX79/C4V7, ZPD4,7, 1N5230
52789	OAZ201	5,1V, 5%	BZX55/C5V1, BZX79/C5V1, ZPD5,1, 1N5231
52790	OAZ202	5,6V, 5%	BZX55/C5V6, BZX79/C5V6, ZPD5,6, 1N5232
52791	OAZ203	6,2V, 5%	BZX55/C6V2, BZX79/C6V2, ZPD6,2, 1N5234
52792	OAZ204	6,8V, 5%	BZX55/C6V8, BZX79/C6V8, ZPD6,8, 1N5235
52793	OAZ205	7,5V, 5%	BZX55/C7V5, BZX79/C7V5, ZPD7,5, 1N5236
52794	OAZ206	8,2V, 5%	BZX55/C8V2, BZX79/C8V2, ZPD8,2, 1N5237
52795	OAZ207	9,1V, 5%	BZX55/C9V1, BZX79/C9V1, ZPD9,1, 1N5239
52796	OAZ208	4,3V, 15%	BZX55/C4V3, BZX79/C4V3, ZPD4,3, 1N5229
52797	OAZ209	5,1V, 15%	BZX55/C5V1, BZX79/C5V1, ZPD5,1, 1N5231
52798	OAZ210	6,2V, 15%	BZX55/C6V2, BZX79/C6V2, ZPD6,2, 1N5234
52799	OAZ211	7,5V, 15%	BZX55/C7V5, BZX79/C7V5, ZPD7,5, 1N5236
52800	OAZ212	9,1V, 15%	BZX55/C9V1, BZX79/C9V1, ZPD9,1, 1N5239
52801	OAZ213	12V, 15%	BZX55/C12, BZX79/C12, ZPD12, 1N5242
52802	OC	XP 1D873	XP 1D873
52803	OC	XN 1D873	XN 1D873
52804	OC122	32V, 0,5A, 0,2W	AC 128, AC 153, AC 188
52805	OC123	50V, 0,5A, 0,2W	ACY 24, ASY 48, ASY 77
52806	OC139	20V, 0,25A, 0,085W, B>20	ASY 28...29, ASY 73...75
52807	OC140	OC 139, 0,4A, B>50	ASY 28...29, ASY 73...75
52808	OC141	OC 139, 0,4A, B>80	ASY 28...29, ASY 73...75
52809	OC169	70MHz	AF 126...127, AF 200
52810	OC170	70MHz	AF 126, AF 200
52811	OC171(M,V)	80MHz	AF 124...125, AF 200
52812	OC19	32V, 3A, 50W	AD 149, AUY 19...20, 2N2137...2146
52813	OC20	100V, 8A, 30W(Tc45°)	AL 100...101, ASZ 15, ASZ 18, 2N2527
52814	OC200	30V, 0,05A, 0,25W, 1,2MHz	BC 213, BC 258, BC 308, BC 558
52815	OC201	25V, 0,05A, 0,25W, 3,2MHz	BC 213, BC 258, BC 308, BC 558
52816	OC202	15V, 0,05A, 0,25W, 3,2MHz	BC 213, BC 258, BC 308, BC 558
52817	OC203	60V, 0,05A, 0,25W, 1,2MHz	BC 212, BC 257, BC 307, BC 556
52818	OC204	32V, 0,25A, 0,3W, >0,45MHz	BC 327...328, BC 636, BC 638, BC 640
52819	OC205	60V, 0,25A, 0,3W, >0,45MHz	BC 327A, BC 638, BC 640
52820	OC206	32V, 0,25A, 0,3W, >0,85MHz	BC 327...327, BC 636, BC 638, BC 640
52821	OC207	50V, 0,25A, 0,3W, 2MHz	BC 327, BC 638, BC 640
52822	OC22	47/32V, 1A, 21,5W	AD 149, AUY 19...20, 2N2137...2146
52823	OC23	OC 22, 55/40V	AD 149, AUY 19...20, 2N2137...2146
52824	OC24	OC 22, 47/40V	AD 149, AUY 19...20, 2N2137...2146
52825	OC25	40V, 4A, 22W(Tc45°)	AL 102...103, AUY 28, 2N1529...1548
52826	OC26	40V, 3,5A, 12,5W(Tc75°)	AD 149, AUY 19...20, 2N1529...1548
52827	OC27	16V, 3,5A, 12W(Tc45°)	AD 149, AUY 19...20, 2N2137...2146
52828	OC28	80V, 6A, 30W(Tc45°)	AL 102...103, AUY 22A, ASZ 15, ASZ 18
52829	OC29	OC 28, 60V	AL 102...103, AUY 22A, ASZ 15, ASZ 18

52830	OC30	32V, 1,4A, 6,7W	AD 162
52831	OC303	32V, 0,05A, 0,067W	AC 125...126, AC 151
52832	OC304	32V, 0,05A, 0,067W	AC 125...126, AC 151
52833	OC305	32V, 0,05A, 0,067W	AC 125...126, AC 151
52834	OC306	32V, 0,05A, 0,067W	AC 151r, ACY 32
52835	OC307	32V, 0,25A, 0,075W	AC 128, AC 153, AC 188
52836	OC308	32V, 0,25A, 0,075W	AC 128, AC 153, AC 188
52837	OC309	60V, 0,25A, 0,075W	ACY 24, ASY 48, ASY 77
52838	OC30A	OC 30, 4W	AD 162
52839	OC30B	OC 30, 60V, 4W	-
52840	OC318	20V, 0,3A, 0,135W	AC 128, AC 153, AC 188
52841	OC32	25V, 10mA, 0,05W, $\beta$ 13	AC 125...126, AC 151
52842	OC320	20V, 35mA, 0,045W, $\beta$ 13	-
52843	OC320	20V, 35mA, 0,045W, $\beta$ 13	-
52844	OC33	OC 32, B24	AC 125...126, AC 151
52845	OC330	15V, 35mA, 0,045W, $\beta > 20$	-
52846	OC331	7V, 30mA, 0,03W, $\beta > 20$	OC 57...60
52847	OC34	OC 32, B39	AC 125...126, AC 151
52848	OC340	OC 330, $\beta > 30$	-
52849	OC341	OC 331, $\beta > 30$	OC 57...60
52850	OC342	OC 331, $\beta > 50$	OC 57...60
52851	OC343	OC 331, $\beta > 80$	OC 57...60
52852	OC35	80V, 6A, 30W( $T_c 45^\circ$ )	AL 102...103, AUY 22A, ASZ 15, ASZ 18
52853	OC350	OC 330, 8V	OC 57...60
52854	OC351	OC 331, 5V	OC 57...60
52855	OC36	OC 35, 60V	AL 102...103, AUY 22A, ASZ 15...18
52856	OC360	OC 330	-
52857	OC361	OC 331, $\beta > 30$	OC 57...60
52858	OC362	OC 331, $\beta > 50$	OC 57...60
52859	OC363	OC 331, $\beta > 80$	OC 57...60
52860	OC364	OC 331, $\beta > 50$	OC 57...60
52861	OC37	30V, 0,125A, 0,065W	AC 125...126, AC 151
52862	OC38	30V, 0,065W	AC 125...126, AC 151
52863	OC390		AF 126, AF 200
52864	OC400	OC 390, B75	AF 126, AF 200
52865	OC410	OC 390, B110	AF 126, AF 200
52866	OC430(K)	10V, 0,05A, 0,2W, $\beta > 10$	BC 213, BC 258, BC 308, BC 558
52867	OC44	15MHz	AF 126, AF 200
52868	OC440(K)	OC 430(K), 30V	BC 213, BC 258, BC 308, BC 558
52869	OC443(K)	25V, 0,05A, 0,2W, $\beta > 15$	BC 213, BC 258, BC 308, BC 558
52870	OC445(K)	OC 430(K), 50V	BC 212, BC 257, BC 307, BC 557
52871	OC449(K)	OC 443(K), 60V	BC 212, BC 256, BC 266, BC 556
52872	OC45	6MHz	AF 126, AF 200
52873	OC450(K)	OC 430(K), 75V	BC 556, 2SA893(A), 2SA1017, 2SB715
52874	OC460(K)	OC 430(K), $\beta > 20$	BC 213, BC 258, BC 308, BC 558

52875	OC463(K)	OC 430(K), $\beta > 20$	BC 213, BC 258, BC 308, BC 558
52876	OC465(K)	OC 430(K), 20V, $\beta > 20$	BC 213, BC 258, BC 308, BC 558
52877	OC466(K)	OC 430(K), $\beta > 20$	BC 214, BC 259, BC 309, BC 559
52878	OC467(K)	OC 430(K), 25V, $\beta > 25$	BC 213, BC 258, BC 308, BC 558
52879	OC468(K)	OC 430(K), $\beta > 40$	BC 213, BC 258, BC 308, BC 558
52880	OC469(K)	OC 430(K), 32V, B25	BC 213, BC 258, BC 308, BC 558
52881	OC470(K)	OC 430(K), 30V, $\beta > 20$	BC 213, BC 258, BC 308, BC 558
52882	OC480(K)	OC 430(K), 125V	2SA893A, 2SA1017, 2SA1285(A), 2SB716
52883	OC57	7V, 5mA, 0,02W, $\beta 35$	-
52884	OC58	OC 57, $\beta 55$	-
52885	OC59	OC 57, $\beta 80$	-
52886	OC60	OC 57, $\beta 75$	-
52887	OC601	50V, 20mA, 0,05W	AC 125...126, AC 151
52888	OC602	22V, 0,05A, 0,05W	AC 125...126, AC 151
52889	OC602sp	40V, 0,5A, 0,175W	AC 128, AC 153, AC 188
52890	OC603	22V, 0,05A, 0,05W	AC 125...126, AC 151
52891	OC604	22V, 0,05A, 0,05W	AC 125...126, AC 151
52892	OC604sp	40V, 0,5A, 0,175W	AC 128, AC 153, AC 188
52893	OC612		AF 127, AF 200
52894	OC613		AF 126, AF 200
52895	OC614		AF 126, AF 200
52896	OC615(M,V)		AF 124...125, AF 200
52897	OC622	15V, 30mA, 0,03W, $\beta > 20$	-
52898	OC623	OC 622, $\beta > 50$	-
52899	OC624	OC 622, $\beta > 75$	-
52900	OC70	32V, 10mA, 0,125W, $\beta > 20$	AC 125...126, AC 151
52901	OC71	OC 70, $\beta > 30$	AC 125...126, AC 151
52902	OC72	32V, 0,05A, 0,125W	AC 125...126, AC 151
52903	OC73	32V, 10mA, 0,125W	AC 125...126, AC 151
52904	OC74	20V, 0,3A, 0,22W	AC 128, AC 153, AC 188
52905	OC75	32V, 10mA, 0,125W	AC 125...126, AC 151
52906	OC76	32V, 0,125A, 0,125W	AC 125...126, AC 151
52907	OC77	OC 76, 60V	ACY 24, ASY 48, ASY 77
52908	OC79	26V, 0,3A, 0,22W	AC 128, AC 153, AC 188
52909	OC80(A)	20V, 0,3A, 0,22W	AC 128, AC 153, AC 188
52910	OC81	32V, 0,2A, 0,6W	AC 128, AC 153, AC 188
52911	OC82	16V, 0,2A, 0,6W	AC 125...126, AC 151
52912	OC83	32V, 0,5A, 0,6W	AC 128, AC 153, AC 188
52913	OC84	32V, 0,5A, 0,6W	AC 128, AC 153, AC 188
52914	OE	XN 421F	XN 421F
52915	OF	XN 4130	XN 4130
52916	OF010	1N4007	1N4007
52917	OF132	1N4148	1N4148
52918	OF156	1N4148	1N4148
52919	OF157	10V, 0,075A	BA 127, BA 147/25, BA 215, 1N4148...49

52920	OF158	40V, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
52921	OF160	BY 127	BY 127
52922	OF161	1N4148	1N4148
52923	OF162	1N4148	1N4148
52924	OF164	BZX 75/C2V1	BZX 75/C2V1
52925	OF184	40V, 0,2A	BA 127, BA 147/50, BA 215, 1N4148...49
52926	OF194	BY 206	BY 206
52927	OF208	1N4148	1N4148
52928	OF223	BA 148	BA 148
52929	OF238	BZX 79C15	BZX 79C15
52930	OF241	BY 127	BY 127
52931	OF249	1N4148	1N4148
52932	OF276	BZX 75C2V1	BZX 75C2V1
52933	OF340	BZX 79C5V1	BZX 79C5V1
52934	OF341(/15)	BZX 79C15	BZX 79C15
52935	OF342	BZX 79C18	BZX 79C18
52936	OF343	BZX 79C47	BZX 79C47
52937	OF344	BZX 79C56	BZX 79C56
52938	OF345	BZX 79C68	BZX 79C68
52939	OF417	BAX 12	BAX 12
52940	OF420	BZX 79C18	BZX 79C18
52941	OF449	BAV 21	BAV 21
52942	OF582	1600V, 1,2A	BY 228, BY 448, DM 513, EM 516, GP 10Y
52943	OH	XN 4402	XN 4402
52944	OK	SM 6T 150C	SM 6T...
52945	OK	2SC3736-OK	2SC3736
52946	OL	XN 1117	XN 1117
52947	OL	XP 1117	XP 1117
52948	OL	2SA1521	2SA1521
52949	OL	SM 6T 150CA	SM 6T...
52950	OL	2SC3736-OL	2SC3736
52951	OM	XP 1118	XP 1118
52952	OM	XN 1118	XN 1118
52953	ON	XN 4482	XN 4482
52954	ON328	BRY 39	BRY 39
52955	ON595	BD 135	BD 135
52956	ON974	BU 508	BU 508
52957	OO	2SA1255-O	2SA1255
52958	OR100	Ub28..36V, Ib<0,1mA, Itsm2A	1N5761, N413M, BR 100, D3202Y, DO201YR
52959	OT	2SC4001	2SC4001
52960	OT	2SC4364	2SC4364
52961	OT	SM 6T 200C	SM 6T...
52962	OU	SM 6T 200CA	SM 6T...
52963	OY	2SC4005	2SC4005
52964	OY	2SC3775	2SC3775

52965	OY	2SA1255-Y	2SA1255
52966	OY101	800V, 0,5A	BY 127, BY 133, BY 227, 1N4006...07
52967	OY1011	1000V, 0,6A	BY 127, BY 133, BY 227, 1N4007
52968	OY1011/3	OY 1011, 1,5A	BY 227, BY 255, GP 15M, 1N5399
52969	OY1011/4	OY 1011, 0,95A	BY 127, BY 133, BY 227, 1N4007
52970	OY102	OY 101, 400V	BY 126, BY 134, BY 226, 1N4004...07
52971	OY1021	OY 1011, 600V	BY 126, BY 134, BY 226, 1N4006...07
52972	OY241	800V, 0,45A	BY 127, BY 133, BY 227, 1N4006...07
52973	OY5061	100V, 4A(Tc50°)	BYX 38/300, BY 229/200, BY 249/300
52974	OY5062	OY 5061, 200V	BYX 38/300, BY 229/200, BY 249/300
52975	OY5063	OY 5061, 300V	BYX 38/300, BY 229/400, BY 249/600
52976	OY5064	OY 5061, 400V	BYX 38/600, BY 229/400, BY 249/600
52977	OY5065	OY 5061, 500V	BYX 38/600, BY 229/600, BY 249/600
52978	OY5066	OY 5061, 600V	BYX 38/600, BY 229/600, BY 249/600
52979	OY5067	OY 5061, 700V	BYX 38/900, BY 229/800
52980	P	2SK1964	2SK1964
52981	P	HVU 314	HVU 314
52982	P0	BFP 90A	BFP 90A
52983	P01	SO 2906	SO 2906
52984	P0100AD	0,02/5mA	2N2322...2329A
52985	P0100BA	0,02/5mA	-
52986	P0100BB..NB	P 0100BA..BN	-
52987	P0100BD	P 0100AD, 200V	2N2322...2329A
52988	P0100CD	P 0100AD, 300V	2N2322...2329A
52989	P0100DA	P 0100BA, 400V	-
52990	P0100DD	P 0100AD, 400V	2N2322...2329A
52991	P0100MA	P 0100BA, 600V	-
52992	P0100NA	P 0100BA, 800V	-
52993	P0102AA	0,2/5mA	MCR 100-..., BRY 55/..., TAG 70...
52994	P0102AB..DB	P 0102AA..DA	MCR 100-..., BRY 55/..., TAG 70...
52995	P0102BA	P 0102AA, 200V	MCR 100-..., BRY 55/..., TAG 70...
52996	P0102CA	P 0102AA, 300V	MCR 100-..., BRY 55/..., TAG 70...
52997	P0102DA	P 0102AA, 400V	MCR 100-..., BRY 55/..., TAG 70...
52998	P0103AD..DD	P 0102AD..DA	2N2322...2329, 2N6332...6337, TAG 615-...,
52999	P0103BA..NA	P 0102BA..NA	MCR 100-..., BRY 55/..., TAG 70...
53000	P0103BB..NB	P 0102BA..NA	MCR 100-..., BRY 55/..., TAG 70...
53001	P03	SO 2907A	SO 2907A
53002	P04	PMSS 3904	PMSS 3904
53003	P05	SO 2907	SO 2907
53004	P06	SO 2894	SO 2894
53005	P06	PMSS 3906	PMSS 3906
53006	P08	PMBFJ 108	PMBFJ 108
53007	P09	PMBFJ 109	PMBFJ 109
53008	P1	BFP 91A	BFP 91A
53009	P1	HVC 131	HVC 131

53010	P1	BB 131	BB 131
53011	P1	HVU 131	HVU 131
53012	P1	RT 1P141C	RT 1P141C
53013	P1	2SK1577-1	2SK1577
53014	P1	SST 201	SST 201
53015	P1	BFS 42	BFS 42
53016	P1	RT 1P141M	RT 1P141M
53017	P1	RT 1P137P	RT 1P137P
53018	P1	D70Y.8T1	D70Y.8T1
53019	P1(p)	BFR 92	BFR 92
53020	P10	PMBFJ 110	PMBFJ 110
53021	P10	SM-1XP10	SM-1XP10
53022	P1086	<75Ohm	MPF 970, 2N3993
53023	P1086E	P 1086	P 1086
53024	P1087	<150Ohm	2N5116
53025	P1087E	P 1087	P 1087
53026	P11	PMBFJ 111	PMBFJ 111
53027	P12	SO 2906A	SO 2906A
53028	P12	PMBFJ 112	PMBFJ 112
53029	P13	PMBFJ 113	PMBFJ 113
53030	P140	RT 1P140S	RT 1P140S
53031	P141	RT 1P141S	RT 1P141S
53032	P144	RT 1P144S	RT 1P144S
53033	P18	SO 679	SO 679
53034	P1A	PZT 3904	PZT 3904
53035	P1A	PMBT 3904	PMBT 3904
53036	P1A	PMST 3904	PMST 3904
53037	P1A(p1A)	PXT 3904	PXT 3904
53038	P1B	PMBT 2222	PMBT 2222
53039	P1B(p1B)	PXT 2222	PXT 2222
53040	P1D	PZTA 42	PZTA 42
53041	P1D	PMBTA 42	PMBTA 42
53042	P1D(p1D)	PXTA 42	PXTA 42
53043	P1E	PZTA 43	PZTA 43
53044	P1E	PMBTA 43	PMBTA 43
53045	P1E(p1E)	PXTA 43	PXTA 43
53046	P1F	PMBT 5550	PMBT 5550
53047	P1G	PMBTA 06	PMBTA 06
53048	P1H	PMBTA 05	PMBTA 05
53049	P1J	PMBT 2369	PMBT 2369
53050	P1K	PMBT 6428	PMBT 6428
53051	P1L	PMBT 6429	PMBT 6429
53052	P1M	PZTA 13	PZTA 13
53053	P1M	PMBTA 13	PMBTA 13
53054	P1N	PZTA 14	PZTA 14



53055	P1N	PMBTA 14	PMBTA 14
53056	P1N(p1N)	PXTA 14	PXTA 14
53057	P1P	PMBT 2222A	PMBT 2222A
53058	P1P(p1P)	PXT 2222A	PXT 2222A
53059	P1Q	PMBT 5088	PMBT 5088
53060	P1Q	PMST 5088	PMST 5088
53061	P1R	PMST 5089	PMST 5089
53062	P1Y	PMBT 3903	PMBT 3903
53063	P2	BB 132	BB 132
53064	P2	HVU 132	HVU 132
53065	P2	F 1P2	F 1P2
53066	P2	F 2P2	F 2P2
53067	P2	HVC 132	HVC 132
53068	P2	SST 202	SST 202
53069	P2	2SK1577-2	2SK1577
53070	P2	RT 1P241C	RT 1P241C
53071	P2	SM-1XP02	SM-1XP02
53072	P2	RT 1P241M	RT 1P241M
53073	P2	BFR 92AW	BFR 92AW
53074	P2	BFS 43	BFS 43
53075	P2(p)	BFR 92A	BFR 92A
53076	P2221(A)	2N2221(A)	
53077	P2222(A)	2N2222(A)	
53078	P241	RT 1P241S	RT 1P241S
53079	P25	SO 3906	SO 3906
53080	P26	SO 3905	SO 3905
53081	P2646..2647	2N2646..2647	2N2646...2647
53082	P2906(A)	2N2906(A)	
53083	P2907(A)	2N2907(A)	
53084	P2A	PZT 3906	PZT 3906
53085	P2A	PMBT 3906	PMBT 3906
53086	P2A	PMST 3906	PMST 3906
53087	P2A(p2A)	PXT 3906	PXT 3906
53088	P2B	PZT 2907	PZT 2907
53089	P2B	PMBT 2907	PMBT 2907
53090	P2B(p2B)	PXT 2907	PXT 2907
53091	P2D	PZTA 92	PZTA 92
53092	P2D	PMBTA 92	PMBTA 92
53093	P2D(p2D)	PXTA 92	PXTA 92
53094	P2E	PZTA 93	PZTA 93
53095	P2E	PMBTA 93	PMBTA 93
53096	P2E(p2E)	PXTA 93	PXTA 93
53097	P2F	PZT 2907A	PZT 2907A
53098	P2F	PMBT 2907A	PMBT 2907A
53099	P2F(p2F)	PXT 2907A	PXT 2907A

53100	P2G	PMBTA 56	PMBTA 56
53101	P2H	PMBTA 55	PMBTA 55
53102	P2L	PMBT 5401	PMBT 5401
53103	P2N2222(A)	2N2222(A), 0,625W	2N2222(A)
53104	P2N2907(A)	2N2907(A), 0,625W	2N2907(A)
53105	P2S	F 1P2S	F 1P2S
53106	P2T	PMBT 4403	PMBT 4403
53107	P2T	PMST 4403	PMST 4403
53108	P2T(p2T)	PXT 4403	PXT 4403
53109	P2U	PZTA 63	PZTA 63
53110	P2U	PMBTA 63	PMBTA 63
53111	P2V	PZTA 64	PZTA 64
53112	P2V	PMBTA 64	PMBTA 64
53113	P2V(p2V)	PXTA 64	PXTA 64
53114	P2X	PMBT 4401	PMBT 4401
53115	P2X	PMST 4401	PMST 4401
53116	P2X(p2X)	PXT 4401	PXT 4401
53117	P3	HVC 133	HVC 133
53118	P3	HVU 133	HVU 133
53119	P3	BB 133	BB 133
53120	P3	HVM 132	HVM 132
53121	P3	2SK1577-3	2SK1577
53122	P3	RT 1P441C	RT 1P441C
53123	P3	RT 1P441M	RT 1P441M
53124	P3	BFS 44	BFS 44
53125	P30	FB 1A4A	FB 1...
53126	P300A...M	50..1000V, 5A(Tc100°), 5μs	BY 500/..., MR 820...826
53127	P31	FB 1L2Q	FB 1...
53128	P32	FB 1A3M	FB 1...
53129	P32	SO 5400	SO 5400
53130	P33	SO 5401	SO 5401
53131	P33	FB 1F3P	FB 1...
53132	P34	FB 1L3N	FB 1...
53133	P35	FB 1A4M	FB 1...
53134	P36	FB 1J3P	FB 1...
53135	P39	SO 692	SO 692
53136	P4	BB 134	BB 134
53137	P4	2SD1161-P4	2SD1161
53138	P4	SST 204	SST 204
53139	P4	HVM 132WK	HVM 132WK
53140	P4	RT 1P434C	RT 1P434C
53141	P4	BFR 92R	BFR 92R
53142	P4	SM-1XP04	SM-1XP04
53143	P4	BFS 45	BFS 45
53144	P4	RT 1P434M	RT 1P434M

53145	P40	SO 506	SO 506
53146	P41	BFR 92R	BFR 92R
53147	P430	RT 1P430S	RT 1P430S
53148	P434	RT 1P434S	RT 1P434S
53149	P441	RT 1P441S	RT 1P441S
53150	P4SMA6.8..220	BZW 04-6V8..200, SMD	BZG 04/...
53151	P5	BB 135	BB 135
53152	P5	FMMT2369A	FMMT2369A
53153	P5	2SD1161-P5	2SD1161
53154	P5	HVM 131S	HVM 131S
53155	P5	BFR 92AR	BFR 92AR
53156	P5	RT 1P144C	RT 1P144C
53157	P5	RT 1P144M	RT 1P144M
53158	P511	1N4007, 1300V	BY 228, BY 231/1500, DM 513, GP 10V...Y
53159	P513	1N4007, 1600V	BY 228, BY 231/1500, DM 513, GP 10Y
53160	p5A	PMMBD 6050	PMBD 6050
53161	p5B	PMMBD 6100	PMBD 6100
53162	p5C	PMMBD 7000	PMBD 7000
53163	p5D	PMMBD 914	PMBD 914
53164	P6	BFP 96	BFP 96
53165	P6	2SD1161-P6	2SD1161
53166	P6	HVM 131SR	HVM 131SR
53167	P6	RT 1P430C	RT 1P430C
53168	P6	SM-1XP06	SM-1XP06
53169	P6	RT 1P430M	RT 1P430M
53170	P6009	25V, 1A, 5W, B>4000	BD 466(A...B), BD 876, BDX 45
53171	P600A..M	50..1000V, 6A	BY 214/..., MR 750...760
53172	P6021	BD 166	BD 166
53173	P6A	PMBF 4416	PMBF 4416
53174	p6B	PMBF 5484	PMBF 5484
53175	p6G	PMBF 4393	PMBF 4393
53176	p6H	PMBF 5486	PMBF 5486
53177	p6J	PMBF 4391	PMBF 4391
53178	p6K	PMBF 4392	PMBF 4392
53179	P6KE6.8..440(A)	6,8..440V, 600W(1ms)	BZW06/..., BZW70/..., BZX70/..., BZY93/...
53180	P6KE6.8..440C(A)		BZW06/...B
53181	p6M	PMBF 5485	PMBF 5485
53182	p6S	PMBFJ 176	PMBFJ 176
53183	P6SMB6.8..220	BZW 06-6V8..200, SMD	-
53184	P6SMB6.8C..220C	BZW 06-6V8B..200B, SMD	-
53185	p6W	PMBFJ 175	PMBFJ 175
53186	p6X	PMBFJ 174	PMBFJ 174
53187	p6Y	PMBFJ 177	PMBFJ 177
53188	P7	RT 1P140C	RT 1P140C
53189	P7	RT 1P140M	RT 1P140M

53190	P7002	BD 400	BD 400
53191	P7009	25V, 1A, 5W, B>4000	BD 477(A...B), BD 875, BDX 42
53192	P7010	BD 139	BD 139
53193	P7020	BD 135	BD 135
53194	P7027	BD 135	BD 135
53195	P7029	BD 410	BD 410
53196	P7T-...B	P 7 T-..., bidirecional	BZW 07/...B
53197	P7T-10.-110	10..110V, 700W(1ms)	BZW07/..., BZW70/..., BZX70/..., BZY93/...
53198	P8	BFG 92A	BFG 92A
53199	P9	BCX 70RK	BCX 70RK
53200	P9	1SS379	1SS379
53201	p9A	PMBS 3904	PMBS 3904
53202	p9A	PLVA 650A	PLVA 650A
53203	p9B	PLVA 653A	PLVA 653A
53204	p9C	PLVA 656A	PLVA 656A
53205	p9D	PLVA 659A	PLVA 659A
53206	p9E	PLVA 662A	PLVA 662A
53207	p9F	PLVA 665A	PLVA 665A
53208	p9G	PLVA 668A	PLVA 668A
53209	PA	μPA609T	æPA609T
53210	PA	MA 735	MA 735
53211	PA	KRA101S	KRA 101S
53212	PA	2SC3295-A	2SC3295
53213	PA	BA 885	BA 885
53214	PA	2SC4666A	2SC4666A
53215	PA	2SJ179	2SJ179
53216	PA125N40	0,04Ohm(10A)	2SK1258, 2SK1379, 2SK1422, 2SK2121
53217	PA125N60	0,06Ohm(10A)	2SK1297, 2SK1514, 2SK1665, 2SK2096
53218	PA145	BA 145	BA 145
53219	PA148	BA 148	BA 148
53220	pA2	PMBD 2836	PMBD 2836
53221	pA3	PMBD 2835	PMBD 2835
53222	PA40N200	60V, 9A, 40W, 0,2Ohm(2,5A)	BUZ 20, IRF 532...533, 2SK918, 2SK1114
53223	PA40N300	PA 40N200, 8A, 0,3Ohm(2,5A)	BUZ 20, IRF 532...533, 2SK918, 2SK1114
53224	pA5	PMBD 2837	PMBD 2837
53225	pA6	PMBD 2838	PMBD 2838
53226	PA75N120	PA 75N85, 15A, 0,12Ohm(5A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
53227	PA75N150	PA 75N85, 15A, 0,15Ohm(5A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
53228	PA75N85	60V, 23A, 75W, 0,085Ohm(5A)	BUZ 24, 2N6763, 2SK561, 2SK906, 2SK1429
53229	PAD1	45V, 50mA, Ir<1pA(20V)	-
53230	PAD5	45V, 50mA, Ir<5pA(20V)	-
53231	PAD50	35V, 50mA,Ir<50pA(20V)	-
53232	PB	MA 736	MA 736
53233	PB	2SC3295-B	2SC3295
53234	PB	KRA102S	KRA 102S

53235	PB	2SC4666B	2SC4666B
53236	PB	2SJ197	2SJ197
53237	PB125N60	0,06Ohm(10A)	BUZ 345, 2SK1122, 2SK1363, 2SK1304
53238	PB125N80	0,08Ohm(10A)	BUZ 345, 2SK1122, 2SK1363, 2SK1304
53239	PB40N280	100V, 8A, 40W, 0,28Ohm(2,5A)	BUK 552-100, IRF 522, 2SK470, 2SK918
53240	PB40N400	0,4Ohm(2,5A)	BUK 552-100, IRF 522, 2SK470, 2SK918
53241	PB75N140	100V, 16A, 75W, 0,14Ohm(5A)	BUZ 36, IRF 130, MTM12N10, 2N6765
53242	PB75N180	0,18Ohm(5A)	BUZ 36, IRF 130, MTM12N10, 2N6765
53243	PBC107	BC 107	
53244	PBC108	BC 108	
53245	PBC109	BC 109	
53246	PBC182	BC 182	
53247	PBC183	BC 183	
53248	PBC184	BC 184	
53249	PBF259(S)	>40MHz	BF 393, BF 420A, BFP 25, MPSA 42
53250	PBF259R,RS	PBF 259(S)	PBF 259(S)
53251	PBF493(S)	>50MHz	BF 493, BF 421A, BFP 26, MPSA 92
53252	PBF493R,RS	PBF 493(S)	PBF 493(S)
53253	PBYR10100-100	PBYR 10100-60, 100V	MBR 10100
53254	PBYR10100-100	PBYR 10100-60, 100V	MBR 10100
53255	PBYR10100-60	60V, 10A(Tc133°)	MBR 1060...10100
53256	PBYR10100-60	60V, 10A(Tc133°)	MBR 1060...10100
53257	PBYR10100-80	PBYR 10100-60, 80V	MBR 1080...10100
53258	PBYR10100-80	PBYR 10100-60, 80V	MBR 1080...10100
53259	PBYR1035	35V, 10A(Tc135°)	MBR 1035...1080
53260	PBYR1035	35V, 10A(Tc135°)	MBR 1035...1080
53261	F	PBYR 1035..1045	MBRF 1045
53262	PBYR1040	PBYR 1035, 40V	MBR 1045...1080
53263	PBYR1040	PBYR 1035, 40V	MBR 1045...1080
53264	PBYR1045	PBYR 1035, 45V	MBR 1045...1080
53265	PBYR1045	PBYR 1035, 45V	MBR 1045...1080
53266	PBYR12035T,TV	35V, 2x60A(Tc90°)	-
53267	PBYR12040T,TV	PBYR 12035..., 40V	-
53268	PBYR12045T,TV	PBYR 12035..., 45V	-
53269	TF	PBYR 1535CT..1545CT	BYV 33F-...
53270	PBYR1535CT	35V, 15A(Tc130°)	BYV 33-..., MBR 1550...1560CT
53271	PBYR1540CT	PBYR 1535CT, 40V	BYV 33-..., MBR 1550...1560CT
53272	PBYR1545CT	PBYR 1535CT, 45V	BYV 33-..., MBR 1550...1560CT
53273	PBYR16035T,TV	35V, 2x80A(Tc75°)	-
53274	PBYR16040T,TV	PBYR 16035..., 40V	-
53275	PBYR16045T,TV	PBYR 16035..., 45V	-
53276	PBYR1635	35V, 16A(Tc130°)	MBR 1635...1645
53277	PBYR1635	35V, 16A(Tc130°)	MBR 1635...1645
53278	F	PBYR 1635..1645	-
53279	PBYR1640	PBYR 1635, 40V	MBR 1645

53280	PBYR1640	PBYR 1635, 40V	MBR 1645
53281	PBYR1645	PBYR 1635, 45V	MBR 1645
53282	PBYR1645	PBYR 1635, 45V	MBR 1645
53283	PBYR20100-100	PBYR 20100-60, 100V	-
53284	PBYR20100-60	60V, 2x10A(Tc133°)	-
53285	PBYR20100-80	PBYR 20100-60, 80V	-
53286	TF	PBYR 2035CT..2045CT	BYV 143F-...
53287	PBYR2035CT	35V, 2x10A(Tc135°)	MBR 2035...2045CT
53288	PBYR2040CT	PBYR 2035CT, 40V	MBR 2045CT
53289	PBYR2045CT	PBYR 2035CT, 45V	MBR 2045CT
53290	PBYR2100CT	PBYR 280CT, 100V	-
53291	PBYR245CT	35V, 2x1A(Tc118°)	-
53292	TF	PBYR 2535CT..2545CT	-
53293	PBYR2535CT	35V, 2x15A(Tc135°)	BYV 43-..., MBR 2535...2545CT
53294	PBYR2540CT	PBYR 2535CT, 40V	BYV 43-..., MBR 2545CT
53295	PBYR2545CT	PBYR 2535CT, 45V	BYV 43-..., MBR 2545CT
53296	PBYR280CT	80V, 1A	-
53297	PBYR290CT	PBYR 280CT, 90V	-
53298	PBYR30100-100	PBYR 30100-60, 100V	-
53299	PBYR30100-100	PBYR 30100-60, 100V	-
53300	PBYR30100-60	60V, 2x15A(Tc124°)	MBR 3060PT
53301	PBYR30100-60	60V, 2x15A(Tc124°)	MBR 3060PT
53302	PBYR30100-80	PBYR 30100-60, 80V	-
53303	PBYR30100-80	PBYR 30100-60, 80V	-
53304	TF	PBYR 3035PT..3045PT	-
53305	PBYR3035PT	35V, 2x10A	BYV 73-..., MBR 3035...3050PT
53306	PBYR3035PT	35V, 2x10A	BYV 73-..., MBR 3035...3050PT
53307	PBYR3040PT	PBYR 3035PT, 40V	BYV 73-..., MBR 3045...3050PT
53308	PBYR3040PT	PBYR 3035PT, 40V	BYV 73-..., MBR 3045...3050PT
53309	PBYR3045PT	PBYR 3035PT, 45V	BYV 73-..., MBR 3045...3050PT
53310	PBYR3045PT	PBYR 3035PT, 45V	BYV 73-..., MBR 3045...3050PT
53311	PBYR635CT	35V, 2x5A(Tc118°)	-
53312	PBYR640CT	PBYR 635CT, 40V	-
53313	PBYR645CT	PBYR 635CT, 45V	-
53314	PBYR735	35V, 7,5A(Tc130°)	MBR 735...760
53315	PBYR735F..745F	PBYR 735..745	MBRF 745
53316	PBYR740	PBYR 735, 40V	MBR 745...760
53317	PBYR745	PBYR 735, 45V	MBR 745...760
53318	PC	MA 737	MA 737
53319	PC	BA 886	BA 886
53320	PC	KRA103S	KRA 103S
53321	PC	2SJ199	2SJ199
53322	PC125N130	0,130hm(10A)	BUZ 341, 2SK851, 2SK902, 2SK1675
53323	PC125N180	0,180hm(10A)	BUZ 341, 2SK851, 2SK902, 2SK1675
53324	PC40N500	150V, 6A, 40W, 0,50hm(2,5A)	IRF 620, 2SK357



53325	PC40N800	0,8Ohm(2,5A)	IRF 620, 2SK357
53326	PC75N250	150V, 10A, 75W, 0,25Ohm(5A)	IRF 233, MTM8N18, 2SK400...401, 2SK412
53327	PC75N400	0,4Ohm(5A)	IRF 231, MTM8N18, 2SK400...401, 2SK412
53328	PD	P6 SMB-6.8C	P6 SMB-6.8C
53329	PD	MA 738	MA 738
53330	PD	2SA1171-D	2SA1171
53331	PD	KRA104S	KRA 104S
53332	PD	2SJ205	2SJ205
53333	PDTA114ET	DTA 114 EK	DTA 114EK
53334	PDTA124ET	DTA 124 EK	DTA 124EK
53335	PDTA143ET	DTA 143 EK	DTA 143EK
53336	PDTA144ET	DTA 144 EK	DTA 144EK
53337	PDTB114ET	DTB 114 EK	DTB 114EK
53338	PDTC114ET	DTC 114 EK	DTC 114EK
53339	PDTC124ET	DTC 124 EK	DTC 124EK
53340	PDTC143ET	DTC 143 EK	DTC 143EK
53341	PDTC144ET	DTC 144 EK	DTC 144EK
53342	PDTD114ET	DTD 114 EK	DTD 114EK
53343	PE	MA 739	MA 739
53344	PE	P6SMB-6.8CA	P6 SMB-6.8CA
53345	PE	KRA105S	KRA 105S
53346	PE	2SA1171-E	2SA1171
53347	PE	2SJ207	2SJ207
53348	PE3100	30V, >500MHz	BF 314, BF 502, BF 505, BF 507, BF 959
53349	PE4001	SE 4001	SE 4001
53350	PE4002	SE 4002	SE 4002
53351	PE4010	SE 4010, 0,625W	SE 4010
53352	PE4020	SE 4020, 0,625W	SE 4020
53353	PE5251	400/400V, 100W, B>140	BU 322(A), BUW 81(A), 2SD520...521
53354	PE5252	PE 5251, 450/450V	BU 322(A), BUW 81(A), 2SD520...521
53355	PE5253	PE 5251, 500/500V	BU 322A, BUW 81(A), 2SD520...521
53356	PE6020	SE 6020	SE 6020
53357	PE6021	SE 6021	SE 6021
53358	PE6022	SE 6022	SE 6022
53359	PE7058	>40MHz	BF 392...93, BF 422A, BFP 25, MPSA 42...43
53360	PE7059	PE 7058, 300/300V	BF 393, BF 420A, BFP 25, MPSA 42
53361	PE8050	30V, 1,5A, >100MHz	MPS 650...51, 2SD1051, 2SD1207, 2SD1331
53362	PE8051	PE 8050, 45V	MPS 650...51, 2SD1051, 2SD1207, 2SD1331
53363	PE8052	PE 8050, 20V	MPS 650...51, 2SD1051, 2SD1207, 2SD1331
53364	PE8550	30V, 1,5A, >100MHz	MPS 750...51, 2SB819, 2SB892, 2SB987
53365	PE8551	PE 8550, 45V	MPS 750...51, 2SB819, 2SB892, 2SB987
53366	PE8552	PE 8550, 20V	MPS 750...51, 2SB819, 2SB892, 2SB987
53367	PF	P6 SMB-7.5C	P6 SMB-7.5C
53368	PF	KRA106S	KRA 106S
53369	PF	2SJ208	2SJ208

53370	PF4HZ...10HZ	400..1000V, 3A	BYW 18/..., BYW 83...86, BYM 56B...E
53371	PF8Z6V8...Z180	6,8...180V, Pbr800W(1ms)	BZW 03/..., BZW 11/...
53372	PFC6V4..171	6,4...171V, Pbr1,5kW(1ms)	1N5629...5663
53373	PFR305	50V, 3A, <50ns	BYV 28/50, EGP 30A, FE 3A
53374	PFR310	PFR 305, 100V	BYV 28/100, EGP 30B, FE 3B
53375	PFR850	50V, 3A, <200ns	BY 318/..., BYM 36A, BYW 72, MR 850
53376	PFR851	PFR 850, 100V	BY 318/..., BYM 36A, BYW 72, MR 851
53377	PFR852	PFR 850, 200V	BY 318/..., BYM 36A, BYW 72, MR 852
53378	PFR853	PFR 850, 300V	BY 318/..., BYM 36B, BYW 73, MR 854
53379	PFR854	PFR 850, 400V	BY 318/..., BYM 36B, BYW 77, MR 854
53380	PFR855	PFR 850, 500V	BY 318/..., BYM 36C, BYW 76, MR 856
53381	PFR856	PFR 850, 600V	BY 318/..., BYM 36C, BYW 76, MR 856
53382	PFZ6V8...400(A)	6,8...400V, Pbr1,5kW(1ms)	1N5629...5665
53383	PFZD6V8..180	PF 8Z..., bidirecional	BZW 11/...B
53384	PG	P6SMB-7.5CA	P6 SMB-7.5CA
53385	pGI	PMBT 5551	PMBT 5551
53386	PH	MA 643	MA 643
53387	PH	P6 SMB-8.2C	P6 SMB-8.2C
53388	PH	KRA107S	KRA 107S
53389	PH	2SJ206	2SJ206
53390	PH13002	MJ 4360, 28W	BUX 99, BUV 63, BUV 93, BUX 84...85
53391	PH13003	MJ 4361, 28W	BUX 99, BUV 63, BUV 93, BUX 84...85
53392	PH2222(A)	2N2222(A), 0,625W	2N2222(A)
53393	PH2369	2N2369, 0,5W	2N2369
53394	PH2907(A)	2N2907, 0,625W	2N2907(A)
53395	PH2955(T)	TIP 2955	BD 743C...F, BD 911, BDT 85, BDT 87
53396	PH3055(T)	TIP 3055	BD 744C...F, BD 912, BDT 86, BDT 88
53397	PH5415	2N5415, 0,5W	2SA1626
53398	PH5416	2N5416, 0,5W	2SA1626
53399	PH6659	2N6659, 1W	-
53400	PH6660	2N6660, 1W	-
53401	PH6661	2N6661, 1W	-
53402	PI	KRA108S	KRA 108S
53403	PIB	2SK1070-B	2SK1070
53404	PIC	2SK1070-C	2SK1070
53405	PIC120	Igt/Ih<2/<1,5mA	-
53406	PIC121	Igt/Ih<5/<3mA	-
53407	PIC122	Igt/Ih<2/<1,5mA	-
53408	PIC123	Igt/Ih<5/<3mA	-
53409	PIC130	Igt/Ih<5/<3mA	-
53410	PIC131	Igt/Ih<5/<3mA	-
53411	PID	2SK1070-D	2SK1070
53412	PIE	2SK1070-E	2SK1070
53413	PJ	KRA109S	KRA 109S
53414	PK	P6SMB-8.2CA	P6 SMB-8.2CA

53415	PK	KRA110S	KRA 110S
53416	PK	2SA1173-PK	2SA1173
53417	pKX	PMBF 170	PMBF 170
53418	PL	P6 SMB-9.1C	P6 SMB-9.1C
53419	PL	2SB1234	2SB1234
53420	PL	2SA1173-PL	2SA1173
53421	PL3V3Z...200Z	BZY 97 C3V3..C200	BZY 93/...
53422	PL4001	1N4001	
53423	PL4003	1N4003	
53424	PL4004	1N4004	
53425	PL4005	1N4005	
53426	PL4006	1N4006	
53427	PL4007	1N4007	
53428	PLE0,7	0,65..0,75V(5mA)	BZX 83/C0V8, BZW 22/C1, ZPY 1
53429	PLE1,5	1,35..1,55V(5mA)	-
53430	PLE2	1,9..2,2V(5mA)	-
53431	PLQ0,8	50V, 1A, <50ns	BYV 26B, EGP 10A, FE 1A
53432	PLQ1	PLQ 0,8, 100V	BYV 26B, EGP 10B, FE 1B
53433	PLR810	50V, 1A, <300ns	BY 201/..., MR 810...818, RGP 10A...M
53434	PLR811	PLR 810, 100V	BY 201/..., MR 811...818, RGP 10B...M
53435	PLR812	PLR 810, 200V	BY 201/..., MR 812...818, RGP 10D...M
53436	PLR813	PLR 810, 300V	BY 201/..., MR 813...818, RGP 10G...M
53437	PLR814	PLR 810, 400V	BY 201/..., MR 814...818, RGP 10G...M
53438	PLR815	PLR 810, 500V	BY 201/..., MR 816...818, RGP 10J...M
53439	PLR816	PLR 810, 600V	BY 201/..., MR 816...818, RGP 10J...M
53440	PLR817	PLR 810, 800V	BY 245/..., MR 817...818, RGP 10K...M
53441	PLR818	PLR 810, 1000V	BY 245/..., BY 400, MR 818, RGP 10M
53442	PM	P6SMB-9.1CA	P6 SMB-9.1CA
53443	PM	KRA111S	KRA 111S
53444	PM	2SA1173-PM	2SA1173
53445	PM10PNP	30V, 3A, 10W, 150MHz	2SA473, 2SA1288, 2SB1273
53446	PMBD7000	100V, 0,2A, <15ns	MMBD 7000
53447	PMBD914	1N914, SMD	FMMD 914, MMBD 914
53448	PMBF107	BS 107, SMD, 0,1A	BSS 131
53449	PMBF170	BS 170, SMD, 0,25A	BSS 145, BST 82
53450	PMBF4391..4393	2N4391..4393, SMD	BSR 56...58, SO 4391...93, SST 4391...93
53451	PMBF4416(A)	2N4416(A), SMD	-
53452	PMBF5484..5486	2N5484..5486, SMD	-
53453	PMBFJ108..110	J 108..110, SMD	SST 108...110
53454	PMBFJ111..113	J 111..113, SMD	BSR 111...113, SST 111...113
53455	PMBFJ170	PMBF 170	-
53456	PMBFJ174..177	BSJ 174..177, SMD	BSR 174...177, SST 174...177
53457	PMBFJ308..310	J 308..310, SMD	-
53458	PMBS3904	2N3904, SMD	MMBT 3904
53459	PMBS3906	2N3906, SMD	MMBT 3906

53460	PMBT100(A)	PN 100(A), SMD	BCW 66, BCX 41, 2SD1782
53461	PMBT101	PN 101, SMD	BCW 66, BCX 41, 2SD1782
53462	PMBT200(A)	PN 200(A), SMD	BCX 42
53463	PMBT201	PN 201, SMD	BCX 42
53464	PMBT2222(A)	2N2222(A), SMD	MMBT 2222(A)
53465	PMBT2369	2N2369, SMD	MMBT 2369
53466	PMBT2907(A)	2N2907(A), SMD	MMBT 2907(A)
53467	PMBT3640	2N3640, SMD	MMBT 3640
53468	PMBT3903..3904	2N3903..3904, SMD	MMBT 3903...3904
53469	PMBT3905..3906	2N3905..3906, SMD	MMBT 3905...3906
53470	PMBT4401	2N4401, SMD	MMBT 4401
53471	PMBT4403	2N4403, SMD	MMBT 4403
53472	PMBT5088	2N5088, SMD	MMBT 5088
53473	PMBT5401	2N5401, SMD	MMBT 5401
53474	PMBT5550	2N5550, SMD	MMBT 5550
53475	PMBT5551	2N5551, SMD	MMBT 5551
53476	PMBT6428	2N6428, SMD	MMBT 6428
53477	PMBT6429	2N6429, SMD	MMBT 6429
53478	PMBTA05..06	MPSA 05..06, SMD	MMBTA 05...06
53479	PMBTA12..14	MPSA 12..14, SMD	MMBTA 12...14
53480	PMBTA42..43	MPSA 42..43, SMD	MMBTA 42...43
53481	PMBTA55..56	MPSA 55..56, SMD	MMBTA 55...56
53482	PMBTA63..64	MPSA 63..64, SMD	MMBTA 63...64
53483	PMBTA92..93	MPSA 92..93, SMD	MMBTA 92...93
53484	PMBTH10	MPSH 10, SMD	MMBTH 10
53485	PMBTH81	MPSH 81, SMD	MMBTH 81
53486	PMBZ5226..5257	1N5226..5257, SMD	BZX 84/..., HZM ..., RD ...M
53487	PMLL4148	100V, 0.2A, <4ns	BAS 32, LL 4148
53488	PMSS3904	2N3904, SMD	2SC4116
53489	PMSS3906	2N3906, SMD	2SA1602, 2SA1622
53490	PMST2369	2N2369, SMD	2SC4175...76
53491	PMST3904	2N3904, SMD	2SC4116
53492	PMST3906	2N3906, SMD	2SA1602, 2SA1622
53493	PMST4401	2N4401, SMD	2SD1820A
53494	PMST4403	2N4403, SMD	2SB1219A
53495	PMST5088	2N5088, SMD	BC 850W, 2SC4116
53496	PMST5089	2N5089, SMD	BC 850W, 2SC4116
53497	PMST5401	2N5401, SMD	-
53498	PMST5550..5551	2N5550..5551, SMD	-
53499	PMST6428..6429	2N6428..6429, SMD	2SD1820A
53500	PN	P6 SMB-10C	P6 SMB-10C
53501	PN	KRA112S	KRA 112S
53502	PN	BA 779	BA 779
53503	PN100(A)	75V, 0.5A, 0.625W, >250MHz	BC 639, 2SC3665, 2SC4414, 2SD1226
53504	PN101	80V, 0.5A, 0.625W, >250MHz	BC 639, 2SC3665, 2SC4414, 2SD1226

53505	PN107	BC 107, 0,2W	BC 107
53506	PN108	BC 108, 0,2W	BC 108
53507	PN109	BC 109, 0,2W	BC 109
53508	PN10NPN	30V, 3A, 10W, 150MHz	2SC1173, 2SC3252, 2SD1912
53509	PN1613	2N1613, 0,625W	2N1613
53510	PN1711	2N1711, 0,625W	2N1711
53511	PN1893	2N1893	2N1893
53512	PN200(A)	60V, 0,5A, 0,625W, >250MHz	BC 640, 2SA1425, 2SA1683, 2SB910
53513	PN201	80V, 0,5A, 0,625W, >100MHz	BC 640, 2SA1425, 2SA1683, 2SB910
53514	PN2218..2222(A)	2N2218..2222(A), 0,625W	2N2218...2222(A)
53515	PN2369(A)	2N2369(A), 0,625W	2N2369(A)
53516	PN2484	2N2484, 0,625W	2N2484
53517	PN2904..2907(A)	2N2904..2907(A), 0,625W	2N2904...2907(A)
53518	PN30	50V, 3A, 25W, 1MHz	BD 241(A...C), BD 539(A...D), BD 935
53519	PN3014	2N3014	2N3014
53520	PN3054	50V, 4A, 25W, 0,8MHz	BD 243(A...C), BD 539(A...D), BD 535
53521	PN3250..3251(A)	2N3250..3251(A), 0,625W	2N3250...3251(A)
53522	PN3439..3440	2N3439..3440, 0,625W	2N3439...3440
53523	PN3548	2N3548	2N3548
53524	PN3563..3569	2N3563..3569, 0,625W	2N3563...3569
53525	PN3638..3640(A)	2N3638..3640(A), 0,625W	2N3638...3640(A)
53526	PN3641..3646	2N3641..3646, 0,625W	2N3641...3646
53527	PN3684..3687	2N3684..3687, 0,36W	2N3684...3687
53528	PN3688..3692	2N3688..3692, 0,625W	2N3688...3692
53529	PN3693..3694	2N3693..3694, 0,625W	2N3693...3694
53530	PN3819	2N3819, 0,36W	2N3819
53531	PN3962	2N3962, 0,625W	2N3962
53532	PN4013..4014	2N4013..4014, 0,625W	2N4013...4014
53533	PN4054	NF/S-L, 50V, 4A, 25W, 0,8MHz	BD 244(A...C), BD 540(A...D), BD 536
53534	PN4091..4093	2N4091..4093, 0,36W	2N4091...4093
53535	PN4117..4119(A)	2N4117..4119(A), 0,35W	2N4117...4119(A)
53536	PN4120	2N4120	2N4120
53537	PN4121..4122	2N4121..4122, 0,625W	2N4121...4122
53538	PN4140..4143	2N4140..4143, 0,625W	2N4140...4143
53539	PN4220..4224	2N4220..4224, 0,36W	2N4220...4224
53540	PN4248..4250(A)	2N4248..4250(A), 0,625W	2N4248...4250(A)
53541	PN4257..4258(A)	2N4257..4258(A), 0,625W	2N4257...4258(A)
53542	PN4274..4275	2N4274..4275, 0,625W	2N4274...4275
53543	PN4302..4304	2N4302..4304, 0,36W	2N4302...4304
53544	PN4313	2N4313, 0,625W	2N4313
53545	PN4338..4339	2N4338..4339, 0,36W	2N4338...4339
53546	PN4342..4343	2N4342..4343, 0,35W	2N4342...4343
53547	PN4354..4357	2N4354..4357, 0,625W	2N4354...4357
53548	PN4360	2N4360, 0,35W	2N4360
53549	PN4391..4393	2N4391..4393, 0,36W	2N4391...4393

53550	PN4416(A)	2N4416(A), 0,36W	2N4416(A)
53551	PN4423	2N4423, 0,625	2N4423
53552	PN4856..4861	2N4856..4861, 0,36W	2N4856...4861
53553	PN4888..4889	2N4888..4889, 0,625	2N4888...4889
53554	PN4916..4917	2N4916..4917, 0,625	2N4916...4917
53555	PN4945..4946	2N4945..4946	2N4945...4946
53556	PN4965	2N4965	2N4965
53557	PN5033	2N5033, 0,35	2N5033
53558	PN5126..5137	2N5126..5137, 0,625W	2N5126...5137
53559	PN5138..5139	2N5138..5139, 0,625W	2N5139...5139
53560	PN5140..5143	2N5140..5143, 0,625W	2N5139...5139
53561	PN5163	2N5163, 0,36W	2N5163
53562	PN5179	2N5179, 0,625W	2N5179
53563	PN5415..5416	2N5415..5416, 0,625W	2N5415...5416
53564	PN5432..5434	2N5432..5434	2N5432...5434
53565	PN5447..5449	2N5447..5448	2N5447...5448
53566	PN5770	2N5770, 0,625W	2N5770
53567	PN5816	2N5816	2N5816
53568	PN5855..5858	2N5855..5858, 0,625W	2N5855...5858
53569	PN5910	2N5910, 0,625W	2N5910
53570	PN5964..5965	2N5964..5965, 0,625W	2N5964...65
53571	PN6076	2N6076	2N6076
53572	PN70	B>50	BC 212, BC 257, BC 307, BC 557
53573	PN7055	>50MHz	BF 298...299, BF 420(A), BF 422(A)
53574	PN71	PN 70, 45V, B>100	BC 212, BC 257, BC 307, BC 557
53575	PN72	PN 70, 25V, B>50	BC 214, BC 259, BC 309, BC 559
53576	PN918	2N918, 0,625W	2N918
53577	PN929	2N929, 0,625W	2N929
53578	PN930(A)	2N930(A), 0,625W	2N930
53579	PO	BFP 90A	BFP 90A
53580	PO	2SA1712-O	2SA1712
53581	PO	KRA113S	KRA 113S
53582	PO	KTC4376-O	KTC 4376
53583	PO	2SC2884-O	2SC2884
53584	PO	2SJ212	2SJ212
53585	PO38[Mic]	300/300V, 0,5A, 0,6W, >35MHz	BF 393, BF 420A, BFP 25, MPSA42
53586	PO38[Mot]	300/300V, 0,5A, 0,8W, >35MHz	BF 461...462, BF 758...759, MPSU 10
53587	PO39[Mic]	300/300V, 0,5A, 0,6W, >10MHz	BF 393, BF 420A, BFP 25, MPSA42
53588	PO39[Mot]	300/300V, 0,5A, 0,6W, >10MHz	BF 464...465, BF 761...762, MPSU 60
53589	PO6	PMBS 3906	PMBS 3906
53590	POs	BAR 64	BAR 64
53591	PP	P6 SMB-10CA	P6 SMB-10CA
53592	PP	KRA114S	KRA 114S
53593	PP	2SJ213	2SJ213
53594	PPs	BAR 64-04	BAR 64-04



53595	PQ	P6 SMB-11C	P6 SMB-11C
53596	PQ	2SD2240-Q	2SD2240
53597	PQ	KRA221S	KRA 221S
53598	PQ	2SD814-Q	2SD814
53599	PQ	2SD1821-Q	2SD1821
53600	PQ	2SD1511-Q	2SD1511
53601	PQ	2SJ355	2SJ355
53602	PR	P6 SMB-11CA	P6 SMB-11CA
53603	PR	2SD2240-R	2SD2240
53604	PR	KRA222S	KRA 222S
53605	PR	2SA1712-R	2SA1712
53606	PR	2SD814-R	2SD814
53607	PR	2SD1821-R	2SD1821
53608	PR	2SD1511-R	2SD1511
53609	PR	2SJ356	2SJ356
53610	PR121	1200V, 1A, <500ns	BY 231/1200, BY 245/1200, BY 228, BY 458
53611	PR141	PR 121, 1400V	BY 231/1400, BY 228, BY 448
53612	PR5400..5408	1N5400..5408	
53613	PRF540	100V, 27A, 125W, <30/80ns	BUZ 341, BUZ 349, 2SK851, 2SK906
53614	PRF542	100V, 24A, 125W, <30/80ns	BUZ 341, BUZ 349, 2SK851, 2SK906
53615	PRF640	200V, 18A, 125W, <30/80ns	BUZ 341, BUZ 350, 2SK851, 2SK901
53616	PRF642	200V, 16A, 125W, <30/80ns	BUZ 341, BUZ 350, 2SK851, 2SK901
53617	PRFZ40	50V, 51A, 125W, <25/70ns	STVHD 90, BUZ 346, 2SK1379
53618	PRFZ42	50V, 46A, 125W, <25/70ns	STVHD 90, BUZ 346, 2SK1379
53619	PRs	BAR 64-05	BAR 64-05
53620	PS	P6 SMB-12C	P6 SMB-12C
53621	PS	2SD814-S	2SD814
53622	PS	2SD2240-S	2SD2240
53623	PS	KRA223S	KRA 223S
53624	PS	2SD1821-S	2SD1821
53625	PS	2SD1511-S	2SD1511
53626	PSs	BAR 64-06	BAR 64-06
53627	PT	P6 SMB-12CA	P6 SMB-12CA
53628	PT	2SD2240-T	2SD2240
53629	PT	KRA224S	KRA 224S
53630	PT	2SC4002	2SC4002
53631	PT	2SC4365	2SC4365
53632	PT	2SD814-T	2SD814
53633	PT	2SD1821-T	2SD1821
53634	PT1011	BD 241B	BD 241B
53635	PT1013	BD 244A	BD 244A
53636	PT1014	BD 243A	BD 243A
53637	PT1017	BD 239B	BD 239B
53638	PT1021	BD 243B	BD 243B
53639	PT1142	BD 243	BD 243

53640	PT2013	BD 244B	BD 244B
53641	PT2014	BD 246B	BD 246B
53642	PT2070	BD 136	BD 136
53643	PT6042	BD 647	BD 647
53644	PTE801	55V, 0,75A, PQ2W(960MHz)	-
53645	PTN1	Iv>70µA	-
53646	PTN2	Iv>25µA	-
53647	PTZ2.0..43(A,B)	0..+10%	BZG 03/..., HZF ..., MA 1Z..., RD...FM
53648	PU	P6 SMB-13C	P6 SMB-13C
53649	PU	KRA225S	KRA 225S
53650	PU393	BF 393	BF 393
53651	PV	P6 SMB-13CA	P6 SMB-13CA
53652	PV	1SV294	1SV294
53653	PV	KRA226S	KRA 226S
53654	PW	P6 SMB-15C	P6 SMB-15C
53655	PX	P6 SMB-15CA	P6 SMB-15CA
53656	PXT2222(A)	2N2222(A), SMD	BCX 55...56, SXT 2222, 2SD1005...1006
53657	PXT2907(A)	2N2907(A), SMD	BCX 52...53, SXT 2907, 2SB803...805
53658	PXT3904	2N3904, SMD	SXT 3904, 2SC3803
53659	PXT3906	2N3906, SMD	SXT 3906, 2SA1483
53660	PXT4401	2N4401, SMD	BCX 55...56, 2SD1005...1006, 2SD1767
53661	PXT4403	2N4403, SMD	BCX 52...53, 2SB803...805, 2SB1260
53662	PXTA14	MPSA14, SMD	BCV 29, BCV 49, BST 50, 2SD1470...1471
53663	PXTA27	MPSA27, SMD	BCV 29, BCV 49, BST 50, 2SD1470...71
53664	PXTA42	MPSA42, SMD	BST 40, SXTA 42
53665	PXTA43	MPSA43, SMD	BST 40, SXTA 43
53666	PXTA64	MPSA64, SMD	BCV 28, BCV 48, BST 60, 2SB1125
53667	PXTA77	MPSA77, SMD	BCV 28, BCV 48, BST 60, 2SB1125
53668	PXTA92	MPSA92, SMD	BST 16, SXTA 92
53669	PXTA93	MPSA93, SMD	BST 15...16, SXTA 93
53670	PY	P6 SMB-16C	P6 SMB-16C
53671	PY	2SC3859	2SC3859
53672	PY	2SC2884-Y	2SC2884
53673	PY	2SJ363	2SJ363
53674	PY	KTC4376-Y	KTC 4376
53675	PY126	BY 126	
53676	PY127	BY 127	
53677	PY206	BY 206	
53678	PY207	BY 207	
53679	PY208/...	BY 208/...	
53680	PY210/...	BY 210/...	
53681	PY55/...	BYX 55/...	
53682	PZ	P6 SMB-16CA	P6 SMB-16CA
53683	PZ627	27V, 5%, Pbr1500W(10ms)	-
53684	PZFJ108..110	J 108..110, 1,5W	-

53685	PZT2222(A)	2N2222(A), 1,5W	-
53686	PZT2907(A)	2N2907(A), 1,5W	-
53687	PZT3904	2N3904, 1,5W	-
53688	PZT3906	2N3906, 1,5W	-
53689	PZT651	80V, 2A, 0,8W, >75MHz	-
53690	PZT751	80V, 2A, 0,8W, >75MHz	-
53691	PZTA05..06	MPSA05..06, 1,5W	-
53692	PZTA13..14	MPSA13..14, 1,5W	-
53693	PZTA28	MPSA28, 1W	-
53694	PZTA42..43	MPSA42..43, 1,5W	-
53695	PZTA44..45	MPSA 44..45, 1,5W	-
53696	PZTA55..56	MPSA 55..56, 1,5W	-
53697	PZTA63..64	MPSA 63..64, 1,5W	-
53698	PZTA92..93	MPSA 92..93, 1,5W	-
53699	PZTA96	450/450V, 0,5A, 1,5W	-
53700	Q	HVC 202A	HVC 202A
53701	Q	HVU 202A	HVU 202A
53702	Q2	2SC2813-Q2	2SC2813
53703	Q2	2SC1321-Q2	2SC1321
53704	Q3	BFQ 33C	BFQ 33C
53705	Q3	KDV 251S	KDV 215S
53706	Q3	2SC1321-Q3	2SC1321
53707	Q3	2SC2813-Q3	2SC2813
53708	Q4	2SC1321-Q4	2SC1321
53709	Q4	2SA1331-04	2SA1331
53710	Q4	2SC2813-Q4	2SC2813
53711	Q5	2SC1321-Q5	2SC1321
53712	Q5	2SC2813-Q5	2SC2813
53713	Q5	2SA1331-05	2SA1331
53714	Q6	BFQ 66	BFQ 66
53715	Q6	2SA1331-06	2SA1331
53716	QA	µPA673T	æPA673T
53717	QA	2SC2620-A	2SC2620
53718	QA	RN 1421	RN 1421
53719	QB	RN 1422	RN 1422
53720	QB	2SC2620-B	2SC2620
53721	QC	RN 1423	RN 1423
53722	QC	2SC2620-C	2SC2620
53723	QD	P6 SMB-18C	P6 SMB-18C
53724	QD	RN 1424	RN 1424
53725	QD	SM 4T 6V8	SM 4T...
53726	QE	P6 SMB-18CA	P6 SMB-18CA
53727	QE	RN 1425	RN 1425
53728	QE	SM 4T 6V8A	SM 4T...
53729	QF	P6 SMB-20C	P6 SMB-20C

53730	QF	RN 1426	RN 1426
53731	QF	SM 4T 7V5	SM 4T...
53732	QG	P6 SMB-20CA	P6 SMB-20CA
53733	QG	RN 1427	RN 1427
53734	QG	SM 4T 7V5A	SM 4T...
53735	QH	P6 SMB-22C	P6 SMB-22C
53736	QI-	2SC4196	2SC4196
53737	QI-	2SC4261	2SC4261
53738	QK	P6 SMB-22CA	P6 SMB-22CA
53739	QL	P6 SMB-24C	P6 SMB-24C
53740	QL	2SA1580	2SA1580
53741	QM	P6 SMB-24CA	P6 SMB-24CA
53742	QN	P6 SMB-27C	P6 SMB-27C
53743	QN	SM 4T 10	SM 4T...
53744	QO	2SC2714-O	2SC2714
53745	QO	2SC4915-O	2SC4915
53746	QO	2SC4215-O	2SC4215
53747	QP	P6 SMB-27CA	P6 SMB-27CA
53748	QP	SM 4T 10A	SM 4T...
53749	QQ	P6 SMB-30C	P6 SMB-30C
53750	QR	P6 SMB-30CA	P6 SMB-30CA
53751	QR	2SC4915-R	2SC4915
53752	QR	2SC2714-R	2SC2714
53753	QR	2SC4215-R	2SC4215
53754	QS	P6 SMB-33C	P6 SMB-33C
53755	QS	SM 4T 12	SM 4T...
53756	QT	P6 SMB-33CA	P6 SMB-33CA
53757	QT	2SC4412	2SC4412
53758	QT	SM 4T 12A	SM 4T...
53759	QU	P6 SMB-36C	P6 SMB-36C
53760	QV	1SV298	1SV298
53761	QV	P6 SMB-36CA	P6 SMB-36CA
53762	QW	P6 SMB-39C	P6 SMB-39C
53763	QW	SM 4T 15	SM 4T...
53764	QX	P6 SMB-39CA	P6 SMB-39CA
53765	QX	SM 4T 15A	SM 4T...
53766	QY	P6 SMB-43C	P6 SMB-43C
53767	QY	2SC3863	2SC3863
53768	QY	2SC4498	2SC4498
53769	QY	2SC2714-Y	2SC2714
53770	QY	2SC4915-Y	2SC4915
53771	QY	2SC4215-Y	2SC4215
53772	QY	2SK2247	2SK2247
53773	QZ	P6 SMB-43CA	P6 SMB-43CA
53774	R	HVE 358	HVE 358

53775	R	HVU 358	HVU 358
53776	R01	KSR 1101	KSR 1101
53777	R0103AA	<5/25mA	MAC 92(A)-..., MAC 95-..., Z0104...
53778	R0103BA	R 0103AA, 200V	MAC 92(A)-..., MAC 95-..., Z0104...
53779	R0103CA	R 0103AA, 300V	MAC 92(A)-..., MAC 95-..., Z0104...
53780	R0103DA	R 0103AA, 400V	MAC 92(A)-..., MAC 95-..., Z0104...
53781	R0106AA	<10/25mA	MAC 91A-..., MAC 94(A)-...
53782	R0106BA	R 0106AA, 200V	MAC 91A-..., MAC 94(A)-...
53783	R0106CA	R 0106AA, 300V	MAC 91A-..., MAC 94(A)-...
53784	R0106DA	R 0106AA, 400V	MAC 91A-..., MAC 94(A)-...
53785	R0107AA..DA	R 0106AA..DA	TAG 91-..., MAC 92-..., MAC 94-...
53786	R02	KSR 1102	KSR 1102
53787	R03	KSR 1103	KSR 1103
53788	R04	KSR 1104	KSR 1104
53789	R05	KSR 1105	KSR 1105
53790	R06	KSR 1106	KSR 1106
53791	R07	KSR 1107	KSR 1107
53792	R08	KSR 1108	KSR 1108
53793	R09	KSR 1109	KSR 1109
53794	R1	TN 2010T	TN 2010T
53795	R1	D71Y.8T1	D71Y.8T1
53796	R1(p)	BFR 93	BFR 93
53797	R10A...M	50..1000V, 1A, <150..500ns	BYT 52A...M, BYV 12...16, RG 1A...M
53798	R11	KSR 1111	KSR 1111
53799	R12	KSR 1112	KSR 1112
53800	R13	KSR 1113	KSR 1113
53801	R14	KSR 1114	KSR 1114
53802	R1A	MMST 3904	MMST 3904
53803	R1A	SST 3904	SST 3904
53804	R1A	UMT 3904	UMT 3904
53805	R1B	SST 2222	SST 2222
53806	R1B	MMST 2222	MMST 2222
53807	R1C	MMST 1130	MMST 1130
53808	R1C	SSTA 20	SSTA 20
53809	R1C	MMSTA 20	MMSTA 20
53810	R1C	SST 1130	SST 1130
53811	R1G	MMSTA 06	MMSTA 06
53812	R1G	SSTA 06	SSTA 06
53813	R1H	SSTA 05	SSTA 05
53814	R1J	SST 6427	SST 6427
53815	R1K	SST 6428	SST 6428
53816	R1K	MMST 6428	MMST 6428
53817	R1M	MMSTA 13	MMSTA 13
53818	R1M	SSTA 13	SSTA 13
53819	R1N	SSTA 14	SSTA 14

53820	R1N	MMSTA 14	MMSTA 14
53821	R1P	MMST 2222A	MMST 2222A
53822	R1P	SST 2222A	SST 2222A
53823	R1P	UMT 2222A	UMT 2222A
53824	R1Q	SST 5088	SST 5088
53825	R1Q	MMST 5088	MMST 5088
53826	R1R	MMST 5089	MMST 5089
53827	R1R	SST 5089	SST 5089
53828	R2	2SC4225-R2	2SC4225
53829	R2	2SC2351-R2	2SC2351
53830	R2	BFR 93AW	BFR 93AW
53831	R2008	BU 208(A)	BU 208(A)
53832	R22	2SC4226-R22	2SC4226
53833	R22	2SC3356	2SC3356
53834	R23	2SC4226-R23	2SC4226
53835	R24	2SC4226-R24	2SC4226
53836	R24	MMST 5424	MMST 5424
53837	R24	SST 5424	SST 5424
53838	R2406	BD 243	BD 243
53839	R2499	BD 245	BD 245
53840	R25	2SC4226-R25	2SC4226
53841	R250-(L)A..M	50..800V, 6A	MR 750...760, P 600A...K
53842	R2513	BD 242A	BD 242A
53843	R2A	SST 3906	SST 3906
53844	R2A	MMST 3906	MMST 3906
53845	R2A	UMT 3906	UMT 3906
53846	R2B	SST 2907	SST 2907
53847	R2B	MMST 2907	MMST 2907
53848	R2C	MMSTA 70	MMSTA 70
53849	R2C	SSTA 70	SSTA 70
53850	R2F	SST 2907A	SST 2907A
53851	R2F	MMST 2907A	MMST 2907A
53852	R2F	UMT 2907A	UMT 2907A
53853	R2G	MMSTA 56	MMSTA 56
53854	R2G	SSTA 56	SSTA 56
53855	R2H	SSTA 55	SSTA 55
53856	R2K	SST 8598	SST 8598
53857	R2K	MMST 8598	MMST 8598
53858	R2M	135..180V, 1A(100µs)	-
53859	R2P	MMST 5086	MMST 5086
53860	R2P	SST 5086	SST 5086
53861	R2Q	MMST 5087	MMST 5087
53862	R2Q	SST 7157	SST 7157
53863	R2Q	SST 5087	SST 5087
53864	R2Q	MMST 7157	MMST 7157



53865	R2T	MMST 4403	MMST 4403
53866	R2T	SST 4403	SST 4403
53867	R2T	UMT 4403	UMT 4403
53868	R2U	MMSTA 63	MMSTA 63
53869	R2U	SSTA 63	SSTA 63
53870	R2V	MMSTA 64	MMSTA 64
53871	R2V	SSTA 64	SSTA 64
53872	R2X	MMST 4401	MMST 4401
53873	R2X	SST 4401	SST 4401
53874	R2X	UMT 4401	UMT 4401
53875	R2Z	SST 4400	SST 4400
53876	R3	2SK283-R3	2SK283
53877	R3	2SC2351-R3	2SC2351
53878	R3	2SC4225-R3	2SC4225
53879	R30A...M	50..1000V, 3A, <150..500ns	BYW 95A...C, BYW 96D...E, RG 3A...M
53880	R32	2SC4226-R32	2SC4226
53881	R3272	BU 908	BU 908
53882	R33	2SC4226-R33	2SC4226
53883	R34	2SC4226-R34	2SC4226
53884	R3460	850/400V, 2,5A, 50W	-
53885	R35	2SC4226-R35	2SC4226
53886	R39	MMST 1139	MMST 1139
53887	R39	SST 1139	SST 1139
53888	R3B	SST 8245	SST 8245
53889	R3B	MMST 8245	MMST 8245
53890	R3B	SST 918	SST 918
53891	R3B	UMT 918	UMT 918
53892	R4	FS 1G	FS 1G
53893	R4	BFR 93R	BFR 93R
53894	R4	2SK283-R4	2SK283
53895	R4050	1300/600V, 4A, 100W	BU 508A, BU 903, BU 908, 2SC4022
53896	R4051	R 4050, 1100/550V	BU 508A, BU 903, BU 908, 2SC3387
53897	R4060	R 4050, 80W	BU 506, BU 603
53898	R4061	R 4051, 80W	BU 506, BU 603
53899	R42	2SC4228-R42	2SC4228
53900	R43	2SC4228-R43	2SC4228
53901	R44	2SC4228-R44	2SC4228
53902	R4422R	MR 4422CTR	MR 4422CTR
53903	R4422T	MR 4422CT	MR 4422CT
53904	R45	2SC4228-R45	2SC4228
53905	R5	FS 1J	FS 1J
53906	R5	2SK283-R5	2SK283
53907	R5	BFR 93AR	BFR 93AR
53908	R503C-02	200V, 5A, <35ns	BYW 29-200F, MA 690
53909	R503D-02	R 503C-02	MA 649

53910	R51	KSR 2101	KSR 2101
53911	R52	KSR 2102	KSR 2102
53912	R53	KSR 2103	KSR 2103
53913	R54	KSR 2104	KSR 2104
53914	R55	KSR 2105	KSR 2105
53915	R56	KSR 2106	KSR 2106
53916	R57	KSR 2107	KSR 2107
53917	R58	KSR 2108	KSR 2108
53918	R59	KSR 2109	KSR 2109
53919	R5F400..900CP	Igt50mA	-
53920	R6	FS 1K	FS 1K
53921	R6	2SK283-R6	2SK283
53922	R60	KSR 2110	KSR 2110
53923	R61	KSR 2111	KSR 2111
53924	R62	KSR 2112	KSR 2112
53925	R63	KSR 2113	KSR 2113
53926	R64	KSR 2114	KSR 2114
53927	R7	FS 1M	FS 1M
53928	R7(p)	BFR 106	BFR 106
53929	R750	MR 750	MR 750
53930	R751	MR 751	MR 751
53931	R752	MR 752	MR 752
53932	R754	MR 754	MR 754
53933	R756	MR 756	MR 756
53934	R758	MR 758	MR 758
53935	R760	MR 760	MR 760
53936	R8	BFG 93A	BFG 93A
53937	R850	MR 850	MR 850
53938	R851	MR 851	MR 851
53939	R852	MR 852	MR 852
53940	R854	MR 854	MR 854
53941	R856	MR 856	MR 856
53942	R93	SSTTIS 93	SSTTIS 93
53943	R97	SSTTIS 97	SSTTIS 97
53944	RA	BF 772	BF 772
53945	RA	RN 2421	RN 2421
53946	RA	BFQ 81	BFQ 81
53947	RA-1(A...Z)	100..1500V, 0,5..1A	BY 126...127, BY 133...135, BY 269
53948	RA-2(C)	600..1000V, 1,2A	BY 226...227, GP 15J...M, 1N5397...99
53949	RAF	SSTA 29	SSTA 29
53950	RAO	2SC3718-O	2SC3718
53951	RAT	SSTA 28	SSTA 28
53952	RAT	MMSTA 28	MMSTA 28
53953	RAY	2SC3718-Y	2SC3718
53954	RB	2SC2618-B	2SC2618

53955	RB	BF 771	BF 771
53956	RB	RN 2422	RN 2422
53957	RB015T-40	40V, 10A	MA 750
53958	RB025T-40	40V, 5A	MA 749
53959	RB035B-20	20V, 4A	-
53960	RB100A	40V, 1A	BYS 21-45, BYV 10-40, MBR 150, 1N5819
53961	RB110C	40V, 1A	-
53962	RB111C	40V, 1A	-
53963	RB160L-40	40V, 1A	-
53964	RB400D	20V, 0,5A	1SS344
53965	RB401D	20V, 0,5A	MA 789
53966	RB411D	20V, 0,5A	1SS344
53967	RB420D	25V, 0,1A	BAR 42, BAS 125
53968	RB421D	20V, 0,1A	BAR 42, BAS 125
53969	RB435C	20V, 0,1A	-
53970	RB441Q	20V, 0,1A	-
53971	RB500H	RB 420D	-
53972	RB500H	RB 420D	-
53973	RB501H	RB 421D	-
53974	RB501H	RB 421D	-
53975	RB701D	25V, 0,03A	MA 704A
53976	RB705D	RB 701D	-
53977	RB721Q	RB 701D	-
53978	RB751H	RB 701D	-
53979	RB751H	RB 701D	-
53980	RB751H-40	RB 701D, 40V	-
53981	RB751H-40	RB 701D, 40V	-
53982	RBG	2SK711-GR	2SK711
53983	RBL	2SK711-BL	2SK711
53984	RBQ	SST 7208	SST 7208
53985	RBR	MMST 6838	MMST 6838
53986	RBR	SST 6838	SST 6838
53987	RBV	2SK711-V	2SK711
53988	RC	2SC2618-C	2SC2618
53989	RC	RN 2423	RN 2423
53990	RC	U 1CL49	U 1CL49
53991	RC(s)	BFR 193	BFR 193
53992	RC-2	2000V, 0,2A, <800ns	BY 203/20, SHG 2
53993	RCA1000..1001	MJ 1000..1001	MJ 1000...1001
53994	RCA29	40V, 3A, 30W, >3MHz	BD 241, BD 243, BD 533, BD 933
53995	RCA29A	RCA 29, 60V	BD 241A, BD 243A, BD 535, BD 935
53996	RCA29B	RCA 29, 80V	BD 241B, BD 243B, BD 537, BD 937
53997	RCA29C	RCA 29, 100V	BD 241C, BD 243C, BD 937, 2SD712
53998	RCA30	40V, 3A, 30W, >3MHz	BD 242, BD 244, BD 534, BD 934
53999	RCA3054	90V, 4A, 36W, >0,8MHz	BD 243B, BD 539C, BD 953, 2SD613

54000	RCA3055	100V, 15A, 75W, >0,8MHz	BD 545C, BD 743C, BD 911
54001	RCA30A	RCA 30, 60V	BD 242A, BD 244A, BD 536, BD 936
54002	RCA30B	RCA 30, 80V	BD 242B, BD 244B, BD 538, BD 938
54003	RCA30C	RCA 30, 100V	BD 242C, BD 244C, BD 938, 2SB682
54004	RCA31	40V, 5A, 40W, >3MHz	BD 243, BD 539, BD 543, BD 947
54005	RCA31A	RCA 31, 60V	BD 243A, BD 539A, BD 543A, BD 949
54006	RCA31B	RCA 31, 80V	BD 243B, BD 539B, BD 543B, BD 951
54007	RCA31C	RCA 31, 100V	BD 243C, BD 539C, BD 543C, BD 953
54008	RCA32	40V, 5A, 40W, >3MHz	BD 244, BD 540, BD 544, BD 948
54009	RCA32A	RCA 32, 60V	BD 244A, BD 540A, BD 544A, BD 950
54010	RCA32B	RCA 32, 80V	BD 244B, BD 540B, BD 544B, BD 952
54011	RCA32C	RCA 32, 100V	BD 244C, BD 540C, BD 544C, BD 954
54012	RCA3773	2N3773	2N3773
54013	RCA41	40V, 7A, 65W, >3MHz	BD 543, BD 705, BD 795, BD 805
54014	RCA410	200/200V, 7A, 125W, 4MHz	BUX 18(A,B), TIP 55(A), 2SC3835
54015	RCA411	RCA 410, 300/300V	BUX 18A,B, TIP 55A...56A, 2SC3813
54016	RCA413	B20-80	BUX 18B, BUX 44, TIP 56A...57A, 2SC3040
54017	RCA41A	RCA 41, 60V	BD 543A, BD 707, BD 797, BD 807
54018	RCA41B	RCA 41, 80V	BD 543B, BD 709, BD 799, BD 809
54019	RCA41C	RCA 41, 100V	BD 543C, BD 711, BD 801
54020	RCA42	40V, 7A, 65W, >3MHz	BD 544, BD 706, BD 796, BD 806
54021	RCA423	RCA 413, B30..90	BUX 18B, BUX 44, TIP 56A...57A, 2SC3040
54022	RCA42A	RCA 42, 60V	BD 544A, BD 708, BD 798, BD 808
54023	RCA42B	RCA 42, 80V	BD 544B, BD 710, BD 800, BD 810
54024	RCA42C	RCA 42, 100V	BD 544C, BD 712, BD 802
54025	RCA431	400/325V, 7A, 125W	BUX 18B, BUX 44, TIP 56A...57A, 2SC3040
54026	RCA6340..6341	2N6340..6341	2N6340...6341
54027	RCA8203(A..B)	40..80V, 8A, 60W, B1k..20k	BDW 47(A...D), BDX 54(A...F), BD 900
54028	RCA8350(A..B)	40..80V, 10A, 70W, B1k..20k	86(A...C)
54029	RCA8638(C..E)	140..100V, 20A, 200, >2MHz	BDW 30, BDY 58, 2N5671...72
54030	RCA8766(A..E)	350..450V, 10A, 150W, B>100	BU 922(P), BUW 81(A), MJ 10002...03
54031	RCA9113(A..B)	300..400V, 15A, 175W	BUW 44, BUX 13, BUS 23(A...B), 2SC4140
54032	RCA9116(C..E)	140..100V, 20A, 200W, >2MHz	-
54033	RCA9166A..B	275..225V, 16A, 250W, >4MHz	-
54034	RCA9202(B..C)	300..400V, 4A, 65W, B>750	2SD977...978, 2SD987, 2SD1072
54035	RCA9203A..B	250..300V, 4A, 50W, B>500	2SD816, 2SD977, 2SD1073
54036	RCA9228A..D	60..120V, 50A, 300W, B>2000	-
54037	RCA9229A..D	60..120V, 50A, 300W, B>2000	-
54038	RCs	BFP 193	BFP 193
54039	RCs	BFR 193	BFR 193
54040	RCs	BFQ 193	BFQ 193
54041	RD	2SC2618-D	2SC2618
54042	RD	RN 2424	RN 2424
54043	RD	SM 4T 18	SM 4T...
54044	RD	U 1DL49	U 1DL49

54045	RD(s)	BFP 193	BFP 193
54046	RD10	0,2A, 0,22..0,35V(100mA)	-
54047	RD2.0E..120E..	2...120V, 0,4W	BZX55/..., BZX79/..., BZX83/..., ZPD...
54048	RD2.0F...82F	2...82V, 1W	BZV85/..., BZX61/..., ZPY..., 1N4728...62
54049	RD2.0HS..4.7HS	2,0..4,7V, 5%, 0,25W	BZX55/..., BZX79/..., BZX83/..., ZPD...
54050	..)	2,0...47V, 5%, 0,15W	BZX 84/..., HZM ...
54051	RD2.0P..120P	2,0..120V, 5%, 1W	BZV 49/...
54052	RD2.0S..39S	RD 2.0M..39M, 0,2W	DTZ ..., HZU ...
54053	RD2.0S..39S	RD 2.0M..39M, 0,2W	DTZ ..., HZU ...
54054	RD2.0UH..4.7UH	RD 2.0HS..4.7HS, SMD, 0,15W	RD ...UJ, RD ...UM
54055	RD2.0UM..39UM	RD 2.0M..39M, 0,15W	RD ...UJ
54056	W	RD 2,4M..9.1M	-
54057	RD3,9...200	3,9..200V, +-5%, 1,3W	BZD10/..., BZW22/..., BZX61/..., ZPY...
54058	RD4.7FM..51FM	4,7..51V, 5%, 1W	BZG 04/..., HZF ..., MA 1Z..., PTZ...
54059	RD4.7J...39J	4,7..39V, 5%, 0,4W	BZV 39/..., 1N4099...4123
54060	RD4.7UJ..39UJ	RD 4.7S..39S, SMD, 0,15W	RD ...UM
54061	RD4A...35A	4...35V, 0,2W	BZX55/..., BZX85/..., BZX97/..., ZPD...
54062	RD4B...35B	4...35V, 1W	BZD10/..., BZV85/..., BZW22/..., ZPY...
54063	RD5C...35C	5...35V, 3W	BZX 98/..., 1N2970...91, 1N3996...4000
54064	RD5D...35D	5...35V, 10W	BZX 98/..., 1N2970...91, 1N3996...4000
54065	RD6.2Z	5,9..6,5V	-
54066	RD7H..10H	7..10V, 0,1W	-
54067	RD8.2EW..9.1EW	8,2..9,1V, 10%, 0,4W	-
54068	RDs	BFP 180	BFP 180
54069	RDs	BFR 180	BFR 180
54070	RE	2SA1514K-E	2SA1514K
54071	RE	RN 2425	RN 2425
54072	RE	2SA1579-E	2SA1579
54073	RE	SM 4T 18A	SM 4T...
54074	REs	BFP 280	BFP 280
54075	REs	BFR 280	BFR 280
54076	RF	RN 2426	RN 2426
54077	RF-1(A,B,Z)	200..800V, 0,6A, <400ns	BY 201/..., BYX 55/..., RGP 10D...M
54078	M)	RFP 23N06LE	2SK1622, 2SK1918
54079	RF1S25N06(SM)	RFP 25N06	2SK1900, 2SK2411Z
54080	RF1S30N06LE	RFP 30N06LE	2SK1900, 2SK2411Z
54081	RF1S30P05(SM)	RFP 30P05	2SJ280
54082	RF1S30P06(SM)	RFP 30P06	2SJ280
54083	RF1S40N10LE	RFP 40N10LE	-
54084	RF1S45N03L	RFP 45N03L	2SK1919, 2SK2164, 2SK2266, 2SK2376
54085	RF1S45N06	RFP 45N06	-
54086	RF1S50N06	RFP 50N06	-
54087	RF1S60P03	RFP 60P03	-
54088	RF1S70N03	RFP 70N03	-
54089	RF1S70N06	RFP 70N06	-

54090	RF2,7...200	BZX 46 C2V7..C200, 0,4W	BZX 46/...
54091	RF2001	50V, 2A	BY 251...255, BY 259/150..., GP 20A...M
54092	RF2002	RF 2001, 100V	BY 251...255, BY 259/150..., GP 20B...M
54093	RF2003	RF 2001, 200V	BY 251...255, BY 259/300..., GP 20D...M
54094	RF2004	RF 2001, 400V	BY 252...255, BY 259/600..., GP 20G...M
54095	RF2005	RF 2001, 600V	BY 253...255, BY 259/600..., GP 20J...M
54096	RF2006	RF 2001, 800V	BY 254...255, BY 259/900..., GP 20K...M
54097	RF2007	RF 2001, 1000V	BY 255, BY 259/1000, G 2M, GP 20M
54098	RF400		BA 111, BA 124, 1S2970, 1SV50
54099	RF401		BA 111, BA 124, 1S2970, 1SV50
54100	RF500		BB 104, BB 204, BB 304, MV 104, 1SV55
54101	RFD10N05(SM)	50V, 10A, 20W, <0,1Ohm(10A)	2SK1754, 2SK2414
54102	RFD10P03L(SM)	RFP 10P03L	-
54103	M)	RFP 12N06RLE	-
54104	M)	RFP 14N05..06	-
54105	RFD14N05L..06L..	RFP 14N05L..06L	-
54106	)	RFP 15P05..06	-
54107	RFD16N03L(SM)	<22mOhm(16A)	-
54108	RFD16N05(SM)	<47mOhm(16A)	-
54109	RFD16N05L(SM)	RFD 16N05	-
54110	RFD16N06(SM)	RFD 16N05, 60V	-
54111	)	<47mOhm(16A)	-
54112	RFD3055(SM)	RFP 3055	-
54113	RFD3055LE(SM)	RFP 3055LE	-
54114	RFD3N08L(SM)	80V, 3A, 30W, <0,8Ohm(3A)	-
54115	RFD4N06L(SM)	60V, 4A, 30W, <0,6Ohm(1A)	-
54116	RFD7N10LE(SM)	RFP 7N10LE	-
54117	RFD8P05(E)(SM)	RFP 8P05(E)	-
54118	RFD8P06(E)(SM)	RFP 8P06(E)	-
54119	RFG30P05..06	RFP 30P05..06	2SJ215, 2SJ331
54120	RFG40N10	RFP 40N10	BUZ 345, MTW 45N10E
54121	RFG40N10LE	RFP 40N10LE	2SK1122, 2SK1263, 2SK1304
54122	RFG45N06	RFP 45N06	BUZ 345, 2SK1124, 2SK1514, 2SK2233
54123	RFG50N05..06	RFP 50N05..06	BUK 439-60, BUZ 344, 2SK1422, 2SK1434
54124	RFG50N05L..06L	RFP 50N05L..06L	BUK 539-60, 2SK1258, 2SK1379, 2SK2173
54125	RFG60P05E..06E	<0,03Ohm(60A)	
54126	RFG70N06	RFP 70N06	2SK1423
54127	RFG75N05E	RFH 75N05E	2SK1426
54128	RFH10N45	<0,6Ohm(5A)	BUZ 339, 2SK 557, 2SK642, 2SK644, 2SK724
54129	RFH10N50	RFH 10N45, 500V	BUZ 339, 2SK 557, 2SK642, 2SK644, 2SK724
54130	RFH12N35	<0,38Ohm(6A)	BUZ 325...326, 2SK634, 2SK644, 2SK896
54131	RFH12N40	RFH 12N35, 400V	BUZ 325...326, 2SK634, 2SK644, 2SK896
54132	RFH25N18	<0,15Ohm(12,5A)	BUZ 341, 2SK851, 2SK902, 2SK1669
54133	RFH25N20	RFH 25N18, 200V	BUZ 341, 2SK851, 2SK902, 2SK1669
54134	RFH25P08	<0,15Ohm(12,5A)	-



54135	RFH25P10	RFH 25P08, 100V	-
54136	RFH30N12	<75mOhm(15A)	BUZ 341, 2SK851, 2SK902, 2SK1669
54137	RFH30N15	RFH 30N12, 150V	BUZ 341, 2SK851, 2SK902, 2SK1669
54138	RFH35N08	<55mOhm(17,5A)	BUZ 349, 2SK850, 2SK906, 2SK1263
54139	RFH35N10	RFH 35N08, 100V	BUZ 349, 2SK850, 2SK906, 2SK1263
54140	RFH45N05	<40mOhm(22,5A)	BUK 439-60, 2SK1258, 2SK1379, 2SK1422
54141	RFH45N06	RFH 45N05, 60V	BUK 439-60, 2SK1258, 2SK1379, 2SK1422
54142	RFH75N05(E)	<10mOhm(75A)	
54143	RFK25N18	<0,15Ohm(12,5A)	BUZ341, IRF250, IRF252, 2SK851, 2SK902
54144	RFK25N20	RFK 25N18, 200V	BUZ341, IRF250, IRF252, 2SK851, 2SK902
54145	RFK25P08	<0,15Ohm(12,5A)	IRF 9150
54146	RFK25P10	RFK 25P08, 100V	IRF 9150
54147	RFK30N12	<75mOhm(15A)	BUZ 341, IRF 250...251, 2SK851, 2SK902
54148	RFK30N15	RFKS30N12, 150V	BUZ 341, IRF 250...251, 2SK851, 2SK902
54149	RFK35N08	<55mOhm(17,5A)	BUZ 345, 2N6764, 2SK850...851, 2SK1263
54150	RFK35N10	RFK 35N08, 100V	BUZ 345, 2N6764, 2SK850...851, 2SK1263
54151	RFK45N05	<40mOhm(22,5A)	BUZ 345, 2SK1258, 2SK1379, 2SK1422
54152	RFK45N06	RFK 45N05, 60V	BUZ 344, 2SK1258, 2SK1379, 2SK1422
54153	RFL1N08	80V, 1A, 8,33W, <1,4Ohm(1A)	IRFF 110, IRFF 112
54154	RFL1N08L..N10L	RFL 1N08..N10, <1,2Ohm(1A)	-
54155	RFL1N10	RFL 1N08, 100V	IRFF 110, IRFF 112
54156	RFL1N12	<2,15Ohm(1A)	IRFF 210...213
54157	RFL1N12L..N15L	RFL 1N12..N15, <1,9Ohm(1A)	-
54158	RFL1N15	RFL 1N12, 150V	IRFF 210...213
54159	RFL1N18	<3,65Ohm(1A)	IRFF 220, IRFF 222
54160	RFL1N20	RFL 1N18, 200V	IRFF 220, IRFF 222
54161	RFL1N20L	RFL 1N18L..N20L	-
54162	RFL1P08	80V, 1A, 8,33W, <3,15Ohm(1A)	IRFF 9110, IRFF 9112
54163	RFL1P10	RFL 1P08, 100V	IRFF 9110, IRFF 9112
54164	RFL2N05	50V, 2A, 8,33W, <0,75Ohm(1A)	IRFF 110...113
54165	RFL2N05L..N06L	RFL 2N05..N06	-
54166	RFL2N06	RFL 2N05, 60V	IRFF 110...113
54167	RFL4N12	120V, 4A, 8,33W, <0,4Ohm(2A)	IRFF 230...233
54168	RFL4N15	RFL 7N12, 150V	IRFF 230...233
54169	RFM10N12	120V, 10A, 75W, <0,3Ohm(5A)	IRF 240...243, 2SK401, 2SK631, 2SK633
54170	L	RFM 10N12..N15	2SK1529
54171	RFM10N15	RFM 10N12, 150V	IRF 240...243, 2SK401, 2SK631, 2SK633
54172	RFM10N45	<0,6Ohm(5A)	BUZ 45, BUZ 339, IRF 450...453, 2SK724
54173	RFM10N50	RFM 10N45, 500V	BUZ45, BUZ339, IRF450, IRF452, 2SK724
54174	RFM10P12	<0,5Ohm(5A)	IRF 9240...9243, 2SJ131, 2SJ200
54175	RFM10P15	RFM 10P12, 200V	IRF 9240...9243, 2SJ131, 2SJ200
54176	RFM12N08	80V, 12A, 75W, <0,2Ohm(6A)	IRF 130...133, 2N6765
54177	RFM12N10	RFM 12N10, 100V	IRF 130, IRF 132, 2N6765
54178	L	RFM 12N10..N12	-
54179	RFM12N18	<0,25Ohm(6A)	BUZ36, BUZ350, IRF240, IRF243, 2SK901

54180	RFM12N20	RFM 12N18, 200V	BUZ36, BUZ350, IRF240, IRF243, 2SK901
54181	RFM12N35	<0,50hm(6A)	BUZ 323, IRF 350...353, 2SK788, 2SK899
54182	RFM12N40	RFM 12N35, 400V	BUZ323, IRF350, IRF352, 2SK788, 2SK899
54183	RFM12P08	80V, 12A, 100W, <0,30hm(6A)	IRF 9130, IRF 9132, 2SJ112...113
54184	RFM12P10	RFM 12P08, 100V	IRF 9130, IRF 9132, 2SJ112...113
54185	RFM15N05	<0,140hm(7,5A)	IRF 130...131, 2N6765, 2SK629
54186	L	RFM 15N05..N06	IRF 130...131, 2N6765, 2SK629
54187	RFM15N06	RFM 15N05, 60V	IRF 130...131, 2N6765, 2SK629
54188	RFM15N12	<0,150hm(7,5A)	BUZ 36, BUZ 350, IRF 240...243, 2SK901
54189	RFM15N15	RFM 15N12, 150V	BUZ 36, BUZ 350, IRF 240...243, 2SK901
54190	RFM18N08	80V, 18A, 100W, <0,10hm(9A)	BUZ 36, BUZ 350, IRF 140...143, 2SK629
54191	RFM18N10	RFM 18N08, 100V	BUZ36, BUZ350, IRF140, IRF142, 2SK629
54192	RFM25N06	<70m0hm(7,5A)	BUZ 24, BUZ 349, IRF 140...143, 2N6763
54193	RFM3N45	450V, 3A, 75W, <30hm(1,5A)	BUZ 84, BUZ 355...356, IRF 430...433
54194	RFM3N50	RFM 3N45, 500V	BUZ 84, BUZ 355...356, IRF 430, IRF 432
54195	RFM4N35	350V, 4A, 75W, <20hm(2A)	BUZ 63, IRF 330...333, 2SK2264
54196	RFM4N40	RFM 4N35, 400V	BUZ 63, IRF 330, IRF 332, 2SK2264
54197	RFM5P12	120V, 5A, 75W, <10hm(2,5A)	IRF 9230...9233, 2SJ114...115
54198	RFM5P15	RFM 5P12, 150V	IRF 9230...9233, 2SJ114...115
54199	RFM6N45	<1,250hm(3A)	BUZ 94, BUZ 330...331, IRF 440...443
54200	RFM6N50	RFM 6N45, 500V	BUZ 94, BUZ 330...331, IRF 440, IRF 442
54201	RFM6P08	80V, 6A, 75W, <0,60hm(3A)	IRF 9230...9233, 2SJ114...115
54202	RFM6P10	RFM 6P08, 100V	IRF 9230...9233, 2SJ114...115
54203	RFM7N35	<0,750hm(3,5A)	BUZ 330...331, IRF 340...343, 2SK501
54204	RFM7N40	RFM 7N35, 400V	BUZ 330...331, IRF 340, IRF 342, 2SK501
54205	RFM8N18	180V, 8A, 75W, <0,50hm(4A)	BUZ 64, IRF 230, IRF 232, 2SK633
54206	RFM8N18L..N20L	RFM 8N18..N20	2SK1529
54207	RFM8N20	RFM 8N18, 200V	BUZ 64, IRF 230, IRF 232, 2SK633
54208	RFM8P08	80V, 8A, 100W, <0,4(4A)	IRF 9130, IRF 9132, 2SJ114...115
54209	RFM8P10	RFM 8P08, 100V	IRF 9130, IRF 9132, 2SJ114...115
54210	RFP10N12	120V, 10A, 60W, <0,30hm(5A)	BUZ 31...32, IRF 630, 2SK740, 2SK925
54211	RFP10N12	120V, 10A, 60W, <0,30hm(5A)	BUZ 31...32, IRF 630, 2SK740, 2SK925
54212	L	RFP 10N12..N15	BUK 555-200
54213	L	RFP 10N12..N15	BUK 555-200
54214	RFP10N15	RFP 10N12, 150V	BUZ 31...32, IRF 630, 2SK740, 2SK925
54215	RFP10N15	RFP 10N12, 150V	BUZ 31...32, IRF 630, 2SK740, 2SK925
54216	RFP10P03L	30V, 10A, 60W, <0,20hm(10A)	IRF 9530...9533, 2SJ122...123, 2SJ169...170
54217	RFP10P03L	30V, 10A, 60W, <0,20hm(10A)	IRF 9530...9533, 2SJ122...123, 2SJ169...170
54218	RFP10P12	120V, 10A, 75W, <0,50hm(5A)	IRF 9640...9641, 2SJ127
54219	RFP10P12	120V, 10A, 75W, <0,50hm(5A)	IRF 9640...9641, 2SJ127
54220	RFP10P15	RFP 10P12, 150V	IRF 9640...9641, 2SJ127
54221	RFP10P15	RFP 10P12, 150V	IRF 9640...9641, 2SJ127
54222	RFP12N06LE	<135m0hm(12A)	
54223	RFP12N06LE	<135m0hm(12A)	
54224	RFP12N08	80V, 12A, 60W, <0,20hm(6A)	BUZ 20, IRF 640...643, 2SK919, 2SK922

54225	RFP12N08	80V, 12A, 60W, <0,2Ohm(6A)	BUZ 20, IRF 640...643, 2SK919, 2SK922
54226	L	RFP 12N08..N10	BUK 555-200, 2SK1559, 2SK1561
54227	L	RFP 12N08..N10	BUK 555-200, 2SK1559, 2SK1561
54228	RFP12N10	RFP 12N08, 100V	BUZ 20, IRF 640...643, 2SK919, 2SK922
54229	RFP12N10	RFP 12N08, 100V	BUZ 20, IRF 640...643, 2SK919, 2SK922
54230	RFP12N18	<0,25Ohm(6A)	BUZ 31, IRF 640, IRF 642, 2SK925
54231	RFP12N18	<0,25Ohm(6A)	BUZ 31, IRF 640, IRF 642, 2SK925
54232	RFP12N20	RFP 12N18, 200V	BUZ 31, IRF 640, IRF 642, 2SK925
54233	RFP12N20	RFP 12N18, 200V	BUZ 31, IRF 640, IRF 642, 2SK925
54234	RFP12P08	80V, 12A, 75W, <0,3Ohm(6A)	IRF 9540, IRF 9542, 2SJ127
54235	RFP12P08	80V, 12A, 75W, <0,3Ohm(6A)	IRF 9540, IRF 9542, 2SJ127
54236	RFP12P10	RFP 12P08, 100V	IRF 9540, IRF 9542, 2SJ127
54237	RFP12P10	RFP 12P08, 100V	IRF 9540, IRF 9542, 2SJ127
54238	RFP14N05	50V, 14A, 48W, <0,1Ohm(14A)	BUZ 21, IRF 640...643, 2SK673, 2SK971
54239	RFP14N05	50V, 14A, 48W, <0,1Ohm(14A)	BUZ 21, IRF 640...643, 2SK673, 2SK971
54240	RFP14N05L	RFP 14N05	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54241	RFP14N05L	RFP 14N05	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54242	RFP14N06	RFP 14N05, 60V	BUZ 21, IRF 640...643, 2SK673, 2SK971
54243	RFP14N06	RFP 14N05, 60V	BUZ 21, IRF 640...643, 2SK673, 2SK971
54244	RFP14N06L	RFP 14N05, 60V	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54245	RFP14N06L	RFP 14N05, 60V	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54246	RFP15N05	<0,14Ohm(7,5A)	BUZ 21, IRF 640...643, 2SK673, 2SK971
54247	RFP15N05	<0,14Ohm(7,5A)	BUZ 21, IRF 640...643, 2SK673, 2SK971
54248	L	RFP 15N05..N06	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54249	L	RFP 15N05..N06	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54250	RFP15N06	RFP 15N05, 60V	BUZ 21, IRF 640...643, 2SK673, 2SK971
54251	RFP15N06	RFP 15N05, 60V	BUZ 21, IRF 640...643, 2SK673, 2SK971
54252	RFP15N08L	80V, 15A, 72W, <0,14Ohm	BUK 555-200, 2SK1301, 2SK1559, 2SK1561
54253	RFP15N08L	80V, 15A, 72W, <0,14Ohm	BUK 555-200, 2SK1301, 2SK1559, 2SK1561
54254	RFP15N12	<0,15Ohm(7,5A)	BUZ 255, BUZ 30A, IRF 640...643, 2SK891
54255	RFP15N12	<0,15Ohm(7,5A)	BUZ 255, BUZ 30A, IRF 640...643, 2SK891
54256	RFP15N15	RFP 15N12, 150V	BUZ 255, BUZ 30A, IRF 640...643, 2SK891
54257	RFP15N15	RFP 15N12, 150V	BUZ 255, BUZ 30A, IRF 640...643, 2SK891
54258	RFP15P05	<0,15Ohm(15A)	IRF 9541...9543, 2SJ140, 2SJ173
54259	RFP15P05	<0,15Ohm(15A)	IRF 9541...9543, 2SJ140, 2SJ173
54260	RFP15P06	RFP 15P05, 60V	IRF 9541...9543, 2SJ140, 2SJ173
54261	RFP15P06	RFP 15P05, 60V	IRF 9541...9543, 2SJ140, 2SJ173
54262	RFP17N06L	60V, 17A, 60W, <0,1Ohm(8,5A)	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54263	RFP17N06L	60V, 17A, 60W, <0,1Ohm(8,5A)	BUK 552-60, 2SK971, 2SK1559, 2SK1561
54264	RFP18N08	80V, 18A, 75W, <0,1Ohm(9A)	BUZ21, BUZ30A, IRF540...43, 2SK1428
54265	RFP18N08	80V, 18A, 75W, <0,1Ohm(9A)	BUZ21, BUZ30A, IRF540...43, 2SK1428
54266	RFP18N10	RFP 18N08, 100V	BUZ21, BUZ30A, IRF540, IRF542, 2SK1428
54267	RFP18N10	RFP 18N08, 100V	BUZ21, BUZ30A, IRF540, IRF542, 2SK1428
54268	RFP22N10	<80mOhm(22A)	BUZ 21, BUZ 30A, IRF 540, IRF 542
54269	RFP22N10	<80mOhm(22A)	BUZ 21, BUZ 30A, IRF 540, IRF 542

54270	RFP23N06LE	<65mOhm(23A)	2SK1115...16, 2SK1287, 2SK1347, 2SK1910
54271	RFP23N06LE	<65mOhm(23A)	2SK1115...16, 2SK1287, 2SK1347, 2SK1910
54272	RFP25N05	<47mOhm(25A)	BUZ 21...22, BUZ 30A, IRF 540...543
54273	RFP25N05	<47mOhm(25A)	BUZ 21...22, BUZ 30A, IRF 540...543
54274	L	RFP 25N05..N06	BUK 555-..., 2SK1291, 2SK1296, 2SK2411
54275	L	RFP 25N05..N06	BUK 555-..., 2SK1291, 2SK1296, 2SK2411
54276	RFP25N06	<47mOhm(25A)	BUZ 21...22, BUZ 30A, IRF 540...543
54277	RFP25N06	<47mOhm(25A)	BUZ 21...22, BUZ 30A, IRF 540...543
54278	RFP2N08	80V, 2A, 25W, <1,05Ohm(1A)	BUZ 76, IRF 610...613, 2SK923
54279	RFP2N08L..N10L	RFP 2N08..N10	-
54280	RFP2N10	RFP 2N08, 100V	BUZ 76, IRF 610...613, 2SK923
54281	RFP2N12	120V, 2A, 25W, <2Ohm(1A)	BUZ 76, IRF 610...613, 2SK923
54282	RFP2N12L..N15L	RFP 2N12..N15, <1,75Ohm(1A)	-
54283	RFP2N15	RFP 2N12, 150V	BUZ 76, IRF 610...613, 2SK923
54284	RFP2N18	180V, 2A, 25W, <3,5Ohm(1A)	BUZ 76, IRF 610, IRF 612, 2SK923
54285	RFP2N18L..N20L	RFP 2N18..N20	-
54286	RFP2N20	RFP 2N18, 200V	BUZ 76, IRF 610, IRF 612, 2SK923
54287	RFP2P08	<70/70ns	BUZ 172, IRF 9510, IRF 9512
54288	RFP2P10	RFP 2P08, 100V	BUZ 172, IRF 9510, IRF 9512
54289	RFP3055	<0,15Ohm(12A)	BUZ 20, IRF 530...533, 2SK919, 2SK1427
54290	RFP3055	<0,15Ohm(12A)	BUZ 20, IRF 530...533, 2SK919, 2SK1427
54291	RFP3055LE	ESD Protec	
54292	RFP3055LE	ESD Protec	
54293	RFP30N06LE	<47mOhm(30A)	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
54294	RFP30N06LE	<47mOhm(30A)	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
54295	RFP30P05	<65mOhm(30A)	-
54296	RFP30P05	<65mOhm(30A)	-
54297	RFP30P06	RFP 30P05, 60V	-
54298	RFP30P06	RFP 30P05, 60V	-
54299	RFP3N45	450V, 3A, 60W, <3Ohm(1,5A)	BUZ 41A...42, IRF 830...833, 2SK1493
54300	RFP3N50	RFP 2N45, 500V	BUZ41A...42, IRF830, IRF833, 2SK1494
54301	RFP40N10	<40mOhm(40A)	-
54302	RFP40N10	<40mOhm(40A)	-
54303	RFP40N10LE	ESD Protec	
54304	RFP40N10LE	ESD Protec	
54305	RFP45N03L	<22mOhm(45A)	BUZ 102AL
54306	RFP45N03L	<22mOhm(45A)	BUZ 102AL
54307	RFP45N06	<28mOhm(45A)	2SK856, 2SK1542
54308	RFP45N06	<28mOhm(45A)	2SK856, 2SK1542
54309	RFP4N05	50V, 4A, 25W, <0,6Ohm(1A)	IRF 510...513, 2SK346, 2SK463, 2SK917
54310	RFP4N05L..N06L	RFP 4N05..N06	2SK702, 2SK991
54311	RFP4N06	RFP 4N05, 60V	IRF 510...513, 2SK346, 2SK463, 2SK917
54312	RFP4N100	<3,5Ohm(2,5A)	-
54313	RFP4N100	<3,5Ohm(2,5A)	-
54314	RFP4N35	350V, 4A, 60W, <2Ohm(2A)	BUZ 60, IRF 830...833, 2SK552...553

54315	RFP4N40	RFP 4N35, 400V	BUZ 60, IRF 830...833, 2SK552...553
54316	RFP4N40	RFP 4N35, 400V	BUZ 60, IRF 830...833, 2SK552...553
54317	RFP50N05	<22mOhm(50A)	BUZ 100, BUK 456-50, PRFZ 40
54318	RFP50N05	<22mOhm(50A)	BUZ 100, BUK 456-50, PRFZ 40
54319	RFP50N05L	RFP 50N05	BUZ 100L, BUK 556-60
54320	RFP50N05L	RFP 50N05	BUZ 100L, BUK 556-60
54321	RFP50N06	RFP 50N05, 60V	BUK 556-60
54322	RFP50N06	RFP 50N05, 60V	BUK 556-60
54323	RFP5P12	120V, 5A, 60W, <10hm(2,5A)	IRF 9630...9633
54324	RFP5P15	RFP 5P12, 150V	IRF 9630...9633
54325	RFP60P03	<27mOhm(60A)	-
54326	RFP60P03	<27mOhm(60A)	-
54327	RFP6N45	450V, 6A, 75W, <1,25Ohm(3A)	IRF 840...43, 2SK554...55, 2SK1495...96
54328	RFP6N50	RFP 6N45, 500V	IRF 840, IRF 842, 2SK555, 2SK1496
54329	RFP6P08	80V, 6A, 60W, <0,6Ohm(3A)	IRF 9520
54330	RFP6P10	RFP 6P08, 100V	IRF 9520
54331	RFP70N03	<10mOhm(70A)	-
54332	RFP70N03	<10mOhm(70A)	-
54333	RFP70N06	<14mOhm(70A)	-
54334	RFP70N06	<14mOhm(70A)	-
54335	RFP7N10LE	ESD Protec	
54336	RFP7N35	<0,75Ohm(3,5A)	IRF 840...43, 2SK554...55, 2SK1495...96
54337	RFP7N40	RFP 7N35, 400V	IRF 840...43, 2SK554...55, 2SK1495...96
54338	RFP8N18	180V, 8A, 60W, <0,5Ohm(4A)	BUZ 30, BUZ 73, IRF 630, IRF 632, 2SK741
54339	RFP8N18L..N20L	RFP 8N18..N20	BUK 554-200
54340	RFP8N20	RFP 8N18, 200V	BUZ 30, BUZ 73, IRF 630, IRF 632, 2SK741
54341	RFP8P05	50V, 8A, 48W, <0,3Ohm(8A)	BUZ 171, 2SJ171
54342	RFP8P06E	RFP 8P05, 60V	BUZ 171, 2SJ171
54343	RFP8P08	80V, 8A, 75W, <0,4Ohm(4A)	IRF 9640...9643
54344	RFP8P10	RFP 8P08, 100V	IRF 9640...9643
54345	RFQ	MMST 6839	SST 6839
54346	RFQ	SST 6839	SST 6839
54347	RFs	BFP 181	BFP 181
54348	RFs	BFR 181	BFR 181
54349	RG	RN 2427	RN 2427
54350	RG10	400V, 1,2A, 100ns	BYD 33G...M, BYV 13...16, BYV 95B...E
54351	RG10A	600V, 1A, 100ns	BYD 33J...M, BYV 14...16, BYV 95C...E
54352	RG10Y	70V, 1,5A, 100ns	BYD 33D...M, BYV 13...16, BYV 95A...E
54353	RG1A...M	50..1000V, 1A, <150..500ns	BYT 52A...M, BYV 12...16, RGP 10A...M
54354	RG1C	1000V, 0,7A, 100ns	BA 159, BYT 52M, MR 818, RGP 10M
54355	RG2(A,Y,Z)	70..600V, 0,5A, 100ns	BY 201/..., BYX 55/..., RGP 10B...M
54356	RG2A...M	50..1000V, 2A, <150..500ns	BY 218/..., BYV 37...38, BYW 95...96...
54357	RG2A2	1300V, 0,5A, 100ns	BY 231/1400, BY 268...269, RGP 15-14
54358	RG3A...M	50..1000V, 3A, <150..500ns	BYW 95A...C, BYW 96D...E, RGP 30A...M
54359	RG4	400V, 3A, 100ns	BYT 56G...M, BYW 74...76, BYW 95...96...



54360	RG4A	600V, 2A, 100ns	BYT 56J...M, BYW 76, BYW 95...96...
54361	RG4A...M	50..1000V, 3A, <150..500ns	BYW 95A...C, BYW 96D...E, RGP 30A...M
54362	RG4C	1000V, 2A, 100ns	BYT 56M, BYT 78, BYW 96E, , RGP 30M
54363	RG4Y	70V, 3,5A, 100ns	BYT 56G...M, BYW 72...76, BYW 95...96
54364	RG4Z	200V, 1,5A, 100ns	BYT 56G...M, BYW 72...76, BYW 95...96
54365	RGM30A...M	50..1000V, 30A, <500ns	BYV 74/..., FE 30A...G, MUR 3005...3060PT
54366	RGM30AD...MD	RGM 30A..M	FE 30AD...GD
54367	RGM30AN...MN	RGM 30A..M	FE 30AN...GN
54368	RGP01-10...-20	1000..2000V, 0,1A, <300ns	BY 203/..., SHG 1,5...2
54369	RGP10A...M	50..1000V, 1A, <150..500ns	BYT 52A...M, BYV 12...16, RG 1A...M
54370	RGP15-10...-20	1000..2000V, 1A, <250ns	BY 231/..., BY 228, BY 448
54371	RGP15A...M	50..1000V, 1,5A, <150..500ns	BYV 12...16, BYV 36A...E, RG 2A...M
54372	RGP20A...J	50..600V, 2A, <150..250ns	BYM 26A...E, BYW 95A...C, BYW 32...36
54373	RGP25A...M	50..1000V, 2,5A, <150..500ns	BYT 56G...M, BYW 95A...C, BYW 96D...E
54374	RGP30A...M	50..1000V, 3A, <150..500ns	BYW 95A...C, BYW 96D...E, RG 3A...M
54375	RGP5005	50V, 0,5A, <750ns	BY 208/..., RGP 10A...M, MR 810...818
54376	RGP5010	RGP 5005, 100V	BY 208/..., RGP 10B...M, MR 811...818
54377	RGP5020	RGP 5005, 200V	BY 208/..., RGP 10D...M, MR 812...818
54378	RGP5040	RGP 5005, 400V	BY 208/..., RGP 10G...M, MR 814...818
54379	RGP5060	RGP 5005, 600V	BY 208/..., RGP 10J...M, MR 816...818
54380	RGP5080	RGP 5005, 800V, <1µs	BY 208/..., RGP 10K...M, MR 817...818
54381	RGP50A...M	50..1000V, 5A, <150..500ns	BY 500/..., MR 820...828
54382	RGP5100	RGP 5005, 1000V, <1µs	BY 208/..., BY 268, RGP 10M, MR 818
54383	RGP80A...M	50..1000V, 8A, <150..500ns	BY 329/..., BY 359/..., ESM 765/...
54384	RGPP10A...M	RGP 10A..M	RGP 10A...M
54385	RGPP15A...M	RGP 15A..M	RGP 15A...M
54386	RGPP20A...M	RGP 20A..M	RGP 20A...M
54387	RGPP30A...M	RGP 30A..M	RGP 30A...M
54388	RGPP60A...M	50..1000V, 6A, <150..500ns	BYV 61...63, FE 6A...H
54389	RGs	BFP 182	BFP 182
54390	RGs	BFR 182	BFR 182
54391	RH	SM 4T 22	SM 4T...
54392	RH1(A,B,C,Z)	200..1000V, 0,6A, <4µs	BY 126...127, BY 133...134, 1N4003...07
54393	RH10F	1500V, 0,8A, <4µs	BY 228, BY 448, DM 513, GP 10W...Y
54394	RH1H	2000V, 0,1A, 200ns	BY 203/20, SHG 2
54395	RH2F	1500V, 1A, <4,2µs	BY 228, BY 448, DM 513, GP 10W...Y
54396	RH3F	1500V, 2,5A, <4µs	BY 228, BY 448
54397	RH4F	1500V, 1,5A, <4µs	BY 228, BY 448, BY 350/1500, GH 3F
54398	RHF1203CX	12MHz	-
54399	RHs	BFP 183	BFP 183
54400	RHs	BFR 183	BFR 183
54401	RIs	BFP 196	BFP 196
54402	RJH6674	2N6674	BUV 47(A), BUW 12(A), 2SC3042, 2SC4138
54403	RJH6675	2N6675	BUV 47(A), BUW 12(A), 2SC3450, 2SC3637
54404	RJH6676	2N6676	BUV 48(A), BUW 13(A), 2SC3520, 2SC4140



54405	RJH6677	2N6677	BUV 48(A), BUW 13(A), 2SC3451, 2SC3638
54406	RJH6678	2N6678	BUV 48(A), BUW 13(A), 2SC3451, 2SC3638
54407	RJH6686	2N6686	BUW 50...52, BUX 70
54408	RJH6687	2N6687	BUW 51...52
54409	RJH6688	2N6688	BUW 51...52
54410	RK	SM 4T 22A	SM 4T...
54411	RK13	30V, 1,7A, 200ns	-
54412	RK14	40V, 1,7A, 200ns	-
54413	RK14		
54414	RK16	60V, 1,5A, 100ns	-
54415	RK16		
54416	RK19	90V, 1,5A, 100ns	-
54417	RK19		
54418	RK33	30V, 2,5A, 100ns	-
54419	RK34	40V, 2,5A, 100ns	-
54420	RK35	60V, 2A, 100ns	-
54421	RK39	90V, 2A, 100ns	-
54422	RK42	20V, 3A, 100ns	-
54423	RK43	30V, 3A, 100ns	-
54424	RK44	40V, 3A, 100ns	-
54425	RK46	60V, 3,5A, 100ns	-
54426	RK49	90V, 3,5A, 100ns	-
54427	RKs	BFP 194	BFP 194
54428	RKs	BFR 194	BFR 194
54429	RL	2SA1563	2SA1563
54430	RL	SM 4T 24	SM 4T...
54431	RL10Z	200V, 2A, 50ns	BY 218/200, BYV 27/200, BYW 32...36
54432	RL232(g)	2x RL 32	RL 32
54433	RL233	2x AA 113	AA 113
54434	RL246(g)	AA 118	AA 118
54435	RL247(g)	2x RL 44	RL 44
54436	RL252	2x RL 52	RL 52
54437	RL2Z	200V, 2A, 50ns	BY 218/200, BYV 27/200, BYW 32...36
54438	RL31(g)	AA 113	AA 113
54439	RL32(g)	45V, 15mA	AA 113, AA 119, 1N34, 1N54, 1N60
54440	RL34(g)	75V, 50mA	AA 117...118, AA 132...133
54441	RL3Z	200V, 3,5A, 50ns	BY 318/200, BYV 28/200, BYW 16/200
54442	RL41(g)	22,5V, 50mA	AA 114, AA 116, 1N60
54443	RL43(g)	115V, 50mA	AA 117...118, AA 132...133
54444	RL44(g)	115V, 50mA	AA 117...118, AA 132...133
54445	RL4Z	200V, 3,5A, 50ns	BY 318/200, BYV 28/200, BYW 16/200
54446	RL52	45V, 20mA	AA 113, AA 119, 1N34, 1N54, 1N60
54447	M)	RLP 03N06CLE	-
54448	RLP03N06CLE	60V, <0,42A, 30W	-
54449	RLP1N06CLE	55V, <3A, 36W	-

54450	RLP1N08LE	80/5,5V, 1A, 75W	-
54451	RLP5N08LE	80V, <14A, 72W	-
54452	RLR4001..4004	1N4001..4004, 0,8A	SM 4001...4004
54453	RLS4148..4154	1N4148..4154, SMD	BAS 32, LL 4148
54454	RLS4446..4450	1N4446..4450, SMD	BAS 32, LL 4148
54455	RLS4454	1N4454, SMD	BAS 32, LL 4148
54456	RLS4606	1N4606, SMD	-
54457	RLZ2.0..24J(A..C)	5..+5%	BZD 27/..., BZV 55/..., HZK ...(L)
54458	RLZ2.0..56(A..D)	9..+2%	BZD 27/..., BZV 55/..., HZK ...(L)
54459	RLZ5221B..5252B	1N5221B..5252B, SMD, 0,4W	BZD27/..., BZV55/..., HZK...(L), RLZ...(J)
54460	RM	SM 4T 24A	SM 4T...
54461	RM1(A..Z)	200..1500V, 1..0,5A	BY 126...127, GP 10Q...Y, 1N4003...07
54462	RM10(A..Z)	200..800V, 1,2A	BY 226...227, BY 251...255, 1N5393...99
54463	RM11A,B,C	600..1000V, 1,2A	BY 226...227, BY 251...255, 1N5397...99
54464	RM2(A..Z)	200..1000V, 1,2A	BY 226...227, BY 251...255, 1N5393...99
54465	RM25	50..61,5V	-
54466	RM26	60..70V	-
54467	RM3(A)	400..600V, 2,5A	BY 251...255, BYW 17/..., 1N5406...08
54468	RM3,3..39	BZX 84C3V3..C39	BZX 84C...
54469	RM4(A..Z)	100..1000V, 3A	BY 251...255, BYW 17/..., 1N5401...08
54470	RN	SM 4T 27	SM 4T...
54471	RN1001	0,4W	AA 1L3M, DTC 143ES, UN 421L, 2SC4363
54472	RN1002	RN 1001, RbRbe10kOhm	AA 1A4M, DTC 114ES, UN 4211, 2SC3402
54473	RN1003	RN 1001, RbRbe22kOhm	AA 1F4M, DTC 124ES, UN 4212, 2SC3400
54474	RN1004	RN 1001, RbRbe47kOhm	AA 1L4M, DTC 144ES, UN 4213, 2SC3399
54475	RN1005	RN 1001, Rb2,2k, Rbe47kOhm	DTC 123JS, KSR 1013
54476	RN1006	RN 1001, Rb4,7k, Rbe47kOhm	DTC 143ZS, KSR 1014, 2SC4133, 2SC4195
54477	RN1007	RN 1001, Rb10k, Rbe47kOhm	AA 1A4P, DTC 114YS, UN 4214, 2SC4048
54478	RN1008	RN 1001, Rb22k, Rbe47kOhm	AA 1F4N, DTC 124XS, KSR 1007
54479	RN1009	RN 1001, Rb47k, Rbe22kOhm	AA 1L4L, DTC 144WS, UN 421E, 2SC3401
54480	RN1010	RN 1001, Rb4,7kOhm, Rbe-	AA 1L3Z, DTC 143TS, UN 4216, 2SC3901
54481	RN1011	RN 1001, Rb10kOhm, Rbe-	AA 1A4Z, DTC 114TS, UN 4215, 2SC3860
54482	RN1012	RN 1001, Rb22kOhm, Rbe-	AA 1F4Z, DTC 124TS, UN 4217, 2SC4121
54483	RN1013	RN 1001, Rb47kOhm, Rbe-	AA 1L4Z, DTC 144TS, UN 4210, 2SC3899
54484	RN1014	RbRbe2,2Ohm, 50V, 0,5A	DTD 123ES, RN 1222, UN 4221, 2SC3923
54485	RN1015	RbRbe4,7Ohm, 50V, 0,5A	DTD 143ES, RN 1223, UN 4222, 2SC3921
54486	RN1016	RbRbe10kOhm, 50V, 0,5A	DTD 114ES, RN 1224, UN 4223, 2SC3920
54487	RN1017	Rb2,2k, Rbe10kOhm, 50V, 0,5A	DTD 123YS, RN 1227, UN 4224, 2SC3922
54488	RN1018	Rb1k, Rbe10kOhm, 50V, 0,5A	DTD 133ZS, RN 1226
54489	RN1101	RN 1001, SMD	DTC 143EE
54490	RN1102	RN 1002, SMD	DTC 114EE
54491	RN1103	RN 1003, SMD	DTC 124EE
54492	RN1104	RN 1004, SMD	DTC 144EE
54493	RN1105	RN 1005, SMD	DTC 123JE
54494	RN1106	RN 1006, SMD	DTC 143ZE

54495	RN1107	RN 1007, SMD	DTC 114YE
54496	RN1108	RN 1008, SMD	DTC 124XE
54497	RN1109	RN 1009, SMD	DTC 144WE
54498	RN1110	RN 1010, SMD	DTC 143TE
54499	RN1111	RN 1011, SMD	DTC 114TE
54500	RN1112	RN 1012, SMD	DTC 124TE
54501	RN1113	RN 1013, SMD	DTC 144TE
54502	RN1201..1211	RN 1001..1011	RN 1001...1011
54503	RN1214..1218	RN 1014..1018	RN 1014...1018
54504	RN1221	RbRbe1kOhm, 50V, 0,8A, 0,3W	-
54505	RN1222	RN 1221, RbRbe2,2kOhm	-
54506	RN1223	RN 1221, RbRbe4,7kOhm	-
54507	RN1224	RN 1221, RbRbe10kOhm	-
54508	RN1225	RN 1221, Rb0,47k, Rbe10kOhm	-
54509	RN1226	RN 1221, Rb1k, Rbe10kOhm	-
54510	RN1227	RN 1221, Rb2,2k, Rbe10kOhm	-
54511	RN1241	0,3W	-
54512	RN1242	RN 1241, Rb10kOhm, Rbe-	-
54513	RN1243	RN 1241, Rb22kOhm, Rbe-	-
54514	RN1244	RN 1241, Rb2,2kOhm, Rbe-	-
54515	RN1301	RN 1001, SMD	DTC 143EU
54516	RN1302	RN 1002, SMD	DTC 114EU, 2SC4398
54517	RN1303	RN 1003, SMD	DTC 124EU, 2SC4397
54518	RN1304	RN 1004, SMD	DTC 144EU, 2SC4396
54519	RN1305	RN 1005, SMD	DTC 123JU
54520	RN1306	RN 1006, SMD	DTC 143ZU
54521	RN1307	RN 1007, SMD	DTC 114YU
54522	RN1308	RN 1008, SMD	DTC 124XU
54523	RN1309	RN 1009, SMD	DTC 144WU
54524	RN1310	RN 1010, SMD	DTC 143TU
54525	RN1311	RN 1011, SMD	DTC 114TU
54526	RN1312	RN 1012, SMD	DTC 124TU
54527	RN1313	RN 1013, SMD	DTC 144TU
54528	RN1401	RN 1001, SMD	FA 1L3M, DTC 143EK, UN 221L, 2SC4362
54529	RN1402	RN 1002, SMD	FA 1A4M, DTC 114EK, UN 2211, 2SC3398
54530	RN1403	RN 1003, SMD	FA 1F4M, DTC 124EK, UN 2212, 2SC3396
54531	RN1404	RN 1004, SMD	FA 1L4M, DTC 144EK, UN 2213, 2SC3395
54532	RN1405	RN 1005, SMD	DTC 123JK, KSR 1113
54533	RN1406	RN 1006, SMD	DTC 143ZK, KSR 1114, 2SC4146
54534	RN1407	RN 1007, SMD	FA 1A4P, DTC 114YK, UN 2214, 2SC4047
54535	RN1408	RN 1008, SMD	FA 1F4N, DTC 124XK, KSR 1107
54536	RN1409	RN 1009, SMD	FA 1L4L, DTC 144WK, UN 221E, 2SC3397
54537	RN1410	RN 1010, SMD	FA 1L3Z, DTC 143TK, UN 2216, 2SC3900
54538	RN1411	RN 1011, SMD	FA 1A4Z, DTC 114TK, UN 2215, 2SC3859
54539	RN1411	RN 1011, SMD	FA 1A4Z, DTC 114TK, UN 2215, 2SC3859

54540	RN1412	RN 1012, SMD	FA 1F4Z, DTC 124TK, UN 2217, 2SC4120
54541	RN1413	RN 1013, SMD	FA 1L4Z, DTC 144TK, UN 2210, 2SC3898
54542	RN1421..1427	RN 1221..1227, SMD	-
54543	RN1441..1444	RN 1241..1244, SMD	-
54544	RN1501..1511	RN 1001..1011, SMD,	-
54545	RN1601..1611	RN 1001..1011, SMD,	-
54546	RN1701..1711	RN 1001..1011, SMD,	-
54547	RN1901..1911	RN 1001..1011, SMD,	-
54548	RN1961..1971	RN 1001..1011, SMD,	-
54549	RN2001	0,4W	AN 1L3M, DTA 143ES, UN 411L, 2SA1656
54550	RN2002	RN 2001, RbRbe10kOhm	AN 1A4M, DTA 114ES, UN 4111, 2SA1348
54551	RN2003	RN 2001, RbRbe22kOhm	AN 1F4M, DTA 124ES, UN 4112, 2SA1346
54552	RN2004	RN 2001, RbRbe47kOhm	AN 1L4M, DTA 144ES, UN 4113, 2SA1345
54553	RN2005	RN 2001, Rb2,2k, Rbe47kOhm	DTA 123JS, KSR 2013
54554	RN2006	RN 2001, Rb4,7k, Rbe47kOhm	DTA 143ZS, KSR 2014, 2SA1591, 2SA1616
54555	RN2007	RN 2001, Rb10k, Rbe47kOhm	AN 1A4P, DTA 114YS, UN 4114, 2SA1564
54556	RN2008	RN 2001, Rb22k, Rbe47kOhm	AN 1F4N, DTA 124XS, KSR 2007
54557	RN2009	RN 2001, Rb47k, Rbe22kOhm	AN 1L4L, DTA 144WS, UN 411E, 2SA1347
54558	RN2010	RN 2001, Rb4,7kOhm, Rbe-	AN 1L3Z, DTA 143TS, UN 4116, 2SA1511
54559	RN2011	RN 2001, Rb10kOhm, Rbe-	AN 1A4Z, DTA 114TS, UN 4115, 2SA1497
54560	RN2012	RN 2001, Rb22kOhm, Rbe-	AN 1F4Z, DTA 124TS, UN 4117, 2SA1590
54561	RN2013	RN 2001, Rb47kOhm, Rbe-	AN 1L4Z, DTA 144TS, UN 4110, 2SA1509
54562	RN2014	RbRbe2,2Ohm, 50V, 0,5A	DTB 123ES, RN 2222, UN 4121, 2SA1529
54563	RN2015	RbRbe4,7Ohm, 50V, 0,5A	DTB 143ES, RN 2223, UN 4122, 2SA1527
54564	RN2016	RbRbe10kOhm, 50V, 0,5A	DTB 144ES, RN 2224, UN 4123, 2SA1526
54565	RN2017	Rb2,2k, Rbe10kOhm, 50V, 0,5A	DTB 123YS, RN 2227, UN 4124, 2SA1528
54566	RN2018	Rb1k, Rbe10kOhm, 50V, 0,5A	DTB 113ZS, RN 2226
54567	RN2101	RN 2001, SMD	DTA 143EE
54568	RN2102	RN 2002, SMD	DTA 114EE
54569	RN2103	RN 2003, SMD	DTA 124EE
54570	RN2104	RN 2004, SMD	DTA 144EE
54571	RN2105	RN 2005, SMD	DTA 123JE
54572	RN2106	RN 2006, SMD	DTA 143ZE
54573	RN2107	RN 2007, SMD	DTA 114YE
54574	RN2108	RN 2008, SMD	DTA 124XE
54575	RN2109	RN 2009, SMD	DTA 144WE
54576	RN2110	RN 2010, SMD	DTA 143TE
54577	RN2111	RN 2011, SMD	DTA 114TE
54578	RN2112	RN 2012, SMD	DTA 124TE
54579	RN2113	RN 2013, SMD	DTA 144TE
54580	RN2201..2211	RN 2001..2011	RN 2001...2011
54581	RN2214..2218	RN 2014..2018	RN 2014...2018
54582	RN2221	RbRbe1kOhm, 50V, 0,8A, 0,3W	-
54583	RN2222	RN 2221, RbRbe2,2kOhm	-
54584	RN2223	RN 2221, RbRbe4,7kOhm	-

54585	RN2224	RN 2221, RbRbe10kOhm	-
54586	RN2225	RN 2221, Rb0,47k, Rbe10kOhm	-
54587	RN2226	RN 2221, Rb1k, Rbe10kOhm	-
54588	RN2227	RN 2221, Rb2,2k, Rbe10kOhm	-
54589	RN2301	RN 2001, SMD	DTA 143EU
54590	RN2302	RN 2002, SMD	DTA 114EU, 2SA1678
54591	RN2303	RN 2003, SMD	DTA 124EU, 2SA1677
54592	RN2304	RN 2004, SMD	DTA 144EU, 2SA1676
54593	RN2305	RN 2005, SMD	DTA 123JU
54594	RN2306	RN 2006, SMD	DTA 143ZU
54595	RN2307	RN 2007, SMD	DTA 114YU
54596	RN2308	RN 2008, SMD	DTA 124XU
54597	RN2309	RN 2009, SMD	DTA 144WU
54598	RN2310	RN 2010, SMD	DTA 143TU
54599	RN2311	RN 2011, SMD	DTA 114TU
54600	RN2312	RN 2012, SMD	DTA 124TU
54601	RN2313	RN 2013, SMD	DTA 144TU
54602	RN2401	RN 2001, SMD	FN 1L3M, DTA 143EK, UN 211L, 2SA1655
54603	RN2402	RN 2002, SMD	FN 1A4M, DTA 114EK, UN 2111, 2SA1344
54604	RN2403	RN 2003, SMD	FN 1F4M, DTA 124EK, UN 2112, 2SA1342
54605	RN2404	RN 2004, SMD	FN 1L4M, DTA 144EK, UN 2113, 2SA1341
54606	RN2405	RN 2005, SMD	DTA 123JK, KSR 2113
54607	RN2406	RN 2006, SMD	DTA 143ZK, KSR 2114
54608	RN2407	RN 2007, SMD	FN 1A4P, DTA 114YK, UN 2114, 2SA1563
54609	RN2408	RN 2008, SMD	FN 1F4N, DTA 124XK, KSR 2107
54610	RN2409	RN 2009, SMD	FN 1L4L, DTA 144WK, UN 211E, 2SA1343
54611	RN2410	RN 2010, SMD	FN 1L3Z, DTA 143TK, UN 2116, 2SA1510
54612	RN2411	RN 2011, SMD	FN 1A4Z, DTA 114TK, UN 2115, 2SA1496
54613	RN2412	RN 2012, SMD	FN 1F4Z, DTA 124TK, UN 2117, 2SA1589
54614	RN2413	RN 2013, SMD	FN 1L4Z, DTA 144TK, UN 2110, 2SA1508
54615	RN2421..2427	RN 2221..2227, SMD	-
54616	RN2501..2511	RN 2001..2011, SMD,	-
54617	RN2601..2611	RN 2001..2011, SMD,	-
54618	RN2701..2711	RN 2001..2011, SMD,	-
54619	RN2901..2911	RN 2001..2011, SMD,	-
54620	RN2961..2971	RN 2001..2011, SMD,	-
54621	RN4601	RN 2001+1001, SMD	-
54622	RN4602	RN 2002+1002, SMD	-
54623	RN4603	RN 2003+1003, SMD	-
54624	RN4604	RN 2004+1004, SMD	-
54625	RN4605	RN 2005+1005, SMD	-
54626	RN4606	RN 2006+1006, SMD	-
54627	RN4607	RN 2007+1007, SMD	-
54628	RN4608	RN 2008+1008, SMD	-
54629	RN4609	RN 2009+1009, SMD	-

54630	RN4610	RN 2010+1010, SMD	-
54631	RN4611	RN 2011+1011, SMD	-
54632	RN4612	RN 2012+1012, SMD	-
54633	RN4901..4911	RN 4601..4611	-
54634	RN5001	Rbe2kOhm, 30V, 2A, 120MHz	-
54635	RN5002	RN 5001, Rbe5,6kOhm	-
54636	RN5003	RN 5001, Rbe10kOhm	-
54637	RN5006	RN 5001, Rbe10kOhm, 140MHz	-
54638	RN6001	Rbe2kOhm, 30V, 2A, 120MHz	-
54639	RN6002	RN 6001, Rbe5,6kOhm	-
54640	RN6003	RN 6001, Rbe10kOhm	-
54641	RN6006	RN 6001, Rbe10kOhm, 140MHz	-
54642	RN711H	RN 719D	-
54643	RN711H	RN 719D	-
54644	RN719D	50V, 50mA, <100Ohm(10mA)	HVM 187S
54645	RN719F	RN 719D	-
54646	RO	KTC3879-O	KTC 3879
54647	RO	2SC2715-O	2SC2715
54648	RO	2SA1204-O	2SA1204
54649	RO	KTA1664-O	KTA 1664
54650	RO2(A..Z)	200..1000V, 1,2A	BY 226...227, BY 251...255, 1N5393...99
54651	RP	SM 4T 27A	SM 4T...
54652	RP16AT..KT	50..800V, 16A, <150..500ns	FE 16A...J, MUR 1605CT...1660CT
54653	RP2,7...33	ZP 2,7..33	BZX55/..., BZX83/..., BZX97/..., ZPD...
54654	RP30..M	RP 30 AP..MP	-
54655	RP300A...M	50..1000V, 3A, <200..500ns	BYW 95A...C, BYW 96D...E, RGP 30A...M
54656	RP30A..M	50..1000V, 3A, <250..500ns	BYW 95A...C, BYW 96D...E, RG 3A...M
54657	RP30AP..MP	50..1000V, 30A,<150..500ns	RGP 30AP...MP, MUR 3005PT...3060PT
54658	RP4Z	200V, 3A, 400ns	BY 397...399, BYW 72...76, BYW 95A...C
54659	RPD2,7...130	2,7..130V, 5%, 0,5W	BZX55/..., BZX83/..., BZX97/..., ZPD...
54660	RPY1...100	ZPY 1..100	BZW22/..., BZX61/..., BZX85/..., ZY...
54661	RQ	2SD1280-Q	2SD1280
54662	RQ	SM 4T 30	SM 4T...
54663	RR	KTC3879-R	KTC 3879
54664	RR	2SC2715-R	2SC2715
54665	RR	2SA1514K-R	2SA1514K
54666	RR	2SA1579-R	2SA1579
54667	RR	2SD1280-R	2SD1280
54668	RR	SM 4T 30A	SM 4T...
54669	RR8AT..MT	RS 8 AT..MT	-
54670	RS	2SC4974-S	2SC4974
54671	RS	2SA1514K-S	2SA1514K
54672	RS	2SC2480-S	2SC2480
54673	RS	2SC3932-S	2SC3932
54674	RS	2SA1579-S	2SA1579



54675	RS	SM 4T 33	SM 4T...
54676	RS	2SD1280-S	2SD1280
54677	RS1(A..Z)	200..1000V, 0,7A, 1,5µs	BY 126...127, BY 133...134, 1N4003...07
54678	RS3FS	1500V, 2A, 2µs	BY 228, BY 448
54679	RS4FS	1500V, 1,5A, 2µs	BY 228, BY 448
54680	RS8AT..MT	50..1000V, 8A, 150..500ns	BY 229/..., BY 329/..., RGP 80A...M
54681	RSR	SST 5210	SST 5210
54682	RT	2SC4974-T	2SC4974
54683	RT	2SC4000	2SC4000
54684	RT	2SC4432	2SC4432
54685	RT	2SC2480-T	2SC2480
54686	RT	2SC3932-T	2SC3932
54687	RT	2SC4400	2SC4400
54688	RT	2SD1280-T	2SD1280
54689	RT	SM 4T 33A	SM 4T...
54690	RT1N137L	0,9W	-
54691	RT1N137P	RT 1N137L, SMD	-
54692	RT1N140C	RT 1N140S, SMD	FA 1A4Z, DTC 114TK, RN 1411, UN 2215
54693	RT1N140M	RT 1N140S, SMD	DTC 114TU, RN 1311
54694	RT1N140S	0,3W	AA 1A4Z, DTC 114TS, RN 1011, UU 4215
54695	RT1N141C	RT 1N141S, SMD	FA 1A4M, DTC 114EK, RN 1402, UN 2211
54696	RT1N141M	RT 1N141S, SMD	DTC 114EU, RN 1302, 2SC4398
54697	RT1N141S	RT 1N140S, RbRbe10kOhm	AA 1A4M, DTC 114ES, RN 1002, UN 4211
54698	RT1N144C	RT 1N144S, SMD	FA 1A4P, DTC 114YK, RN 1407, UN 2214
54699	RT1N144M	RT 1N144S, SMD	DTC 114YU, RN 1307
54700	RT1N144S	Rbe47kOhm	AA 1A4P, DTC 114YS, RN 1007, UN 4214
54701	RT1N241C	RT 1N241S, SMD	FA 1F4M, DTC 124EK, RN 1403, UN 2212
54702	RT1N241M	RT 1N241S, SMD	DTC 124EU, RN 1303, 2SC4397
54703	RT1N241S	RT 1N140S, RbRbe22kOhm	AA 1F4M, DTC 124ES, RN 1003, UN 4212
54704	RT1N430C	RT 1N430S, SMD	FA 1L3Z, DTC 143TK, RN 1410, UN 2216
54705	RT1N430M	RT 1N430S, SMD	DTC 143TU, RN 1310
54706	RT1N430S	RT 1N140S, Rb4,7kOhm, Rbe-	AA 1L3Z, DTC 143TS, RN 1010, UN 4216
54707	RT1N434C	RT 1N434S, SMD	-
54708	RT1N434M	RT 1N434S, SMD	-
54709	RT1N434S	Rbe22kOhm	-
54710	RT1N441C	RT 1N441S, SMD	FA 1L4M, DTC 114EK, RN 1404, UN 2213
54711	RT1N441M	RT 1N441S, SMD	DTC 144EU, RN1304, 2SC4396
54712	RT1N441S	RT 1N140S, RbRbe47kOhm	AA 1L4M, DTC 144ES, RN 1004, UN 4213
54713	RT1P137L	0,9W	-
54714	RT1P137P	RT 1P137L, SMD	-
54715	RT1P140C	RT 1P140S, SMD	FN 1A4Z, DTA 114TK, RN 2411, UN 2115
54716	RT1P140M	RT 1P140S, SMD	DTA 114TU, RN 2311
54717	RT1P140S	0,3W	AN 1A4Z, DTA 114TS, RN 2011, UU 4115
54718	RT1P141C	RT 1P141S, SMD	FN 1A4M, DTA 114EK, RN 2402, UN 2111
54719	RT1P141M	RT 1P141S, SMD	DTA 114EU, RN 2302, 2SA1678

54720	RT1P141S	RT 1N140S, RbRbe10kOhm	AN 1A4M, DTA 114ES, RN 2002, UN 4111
54721	RT1P144C	RT 1P144S, SMD	FN 1A4P, DTA 114YK, RN 2407, UN 2114
54722	RT1P144M	RT 1P144S, SMD	DTA 114YU, RN 2307
54723	RT1P144S	Rbe47kOhm	AN 1A4P, DTA 114YS, RN 2007, UN 4114
54724	RT1P241C	RT 1P241S, SMD	FN 1F4M, DTA 124EK, RN 2403, UN 2112
54725	RT1P241M	RT 1P241S, SMD	DTA 124EU, RN 2303, 2SA1677
54726	RT1P241S	RT 1N140S, RbRbe22kOhm	AN 1F4M, DTA 124ES, RN 2003, UN 4112
54727	RT1P430C	RT 1P430S, SMD	FN 1L3Z, DTA 143TK, RN 2410, UN 2116
54728	RT1P430M	RT 1P430S, SMD	DTA 143TU, RN 2310
54729	RT1P430S	RT 1N140S, Rb4,7kOhm, Rbe-	AN 1L3Z, DTA 143TS, RN 2010, UN 4116
54730	RT1P434C	RT 1P434S, SMD	-
54731	RT1P434M	RT 1P434S, SMD	-
54732	RT1P434S	Rbe22kOhm	-
54733	RT1P441C	RT 1P441S, SMD	FN 1L4M, DTA 144EK, RN 2404, UN 2113
54734	RT1P441M	RT 1P441S, SMD	DTA 144EU, RN 2304, 2SA1676
54735	RT1P441S	RT 1N140S, RbRbe47kOhm	AN 1L4M, DTA 144ES, RN 2004, UN 4113
54736	RTC0803	Igt/Ih<2μA/1mA	-
54737	RTC0806	RTC 0803, 60V	-
54738	RTC0810	RTC 0803, 100V	-
54739	RTC0815	RTC 0803, 150V	-
54740	RTC0820	RTC 0803, 200V	-
54741	RTD0203	Igt/Ih<0,1/<5mA	-
54742	RTD0203...0240-1	RTD 0203..0240, Igt<5μA	-
54743	RTD0203...0240-2	RTD 0203..0240, Igt<10μA	-
54744	RTD0203...0240-3	Igt/Ih<0,25/<20mA	-
54745	RTD0206	RTD 0203, 60V	-
54746	RTD0210	RTD 0203, 100V	-
54747	RTD0220	RTD 0203, 200V	-
54748	RTD0230	RTD 0203, 300V	-
54749	RTD0240	RTD 0203, 400V	-
54750	RTD0301	1A(Tc80°C),Igt/Ih<0,2/10mA	2N2322...2329, TAG 615-100
54751	RTD0303	RTD 0301, 30V	2N2323...2329, TAG 615-100
54752	RTD0306	RTD 0301, 60V	2N2324...2329, TAG 615-100
54753	RTD0310	RTD 0301, 100V	2N2324...2329, TAG 615-100
54754	RTD0315	RTD 0301, 150V	2N2325...2329, TAG 615-200
54755	RTD0320	RTD 0301, 200V	2N2326...2329, TAG 615-200
54756	RTD0330	RTD 0301, 300V	2N2328...2329, TAG 615-400
54757	RTD0340	RTD 0301, 400V	2N2329, TAG 615-400
54758	RTD0350	RTD 0301, 500V	TAG 615-600
54759	RTD0401	Igt/Ih<0,1/5mA	-
54760	RTD0403	RTD 0401, 30V	-
54761	RTD0406	RTD 0401, 60V	-
54762	RTD0410	RTD 0401, 100V	-
54763	RTD0415	RTD 0401, 150V	-
54764	RTD0420	RTD 0401, 200V	-

54765	RTD0430	RTD 0401, 300V	-
54766	RTD0440	RTD 0401, 400V	-
54767	RTD2103	Igt/Ih<10/20mA	BTX30/50, S2600B, T1N100A, TAG612-100
54768	RTD2106	RTD 2103, 60V	BTX30/100, S2600B, T1N100A, TAG612-100
54769	RTD2110	RTD 2103, 100V	BTX30/100, S2600B, T1N100A, TAG612-100
54770	RTD2120	RTD 2103, 200V	BTX30/200, S2600B, T1N200A, TAG612-200
54771	RTD2130	RTD 2103, 300V	BTX30/300, S2600D, T1N300A, TAG612-400
54772	RTD2140	RTD 2103, 400V	BTX30/400, S2600D, T1N400A, TAG612-400
54773	RTED0302	Igt/Ih<15/20mA	S 2620B
54774	RTED0305	RTED 0302, 50V	S 2620B
54775	RTED0310	RTED 0302, 100V	S 2620B
54776	RTED0320	RTED 0302, 200V	S 2620B
54777	RTED0330	RTED 0302, 300V	S 2620D
54778	RTED0340	RTED 0302, 400V	S 2620D
54779	RTED0350	RTED 0302, 500V	S 2620M
54780	RTF0101	Igt/Ih<0,2/<5mA	2N2322...2329, TAG 615-100
54781	RTF0103	RTF 0101, 30V	2N2323...2329, TAG 615-100
54782	RTF0106	RTF 0101, 60V	2N2324...2329, TAG 615-100
54783	RTF0110	RTF 0101, 100V	2N2324...2329, TAG 615-100
54784	RTF0115	RTF 0101, 150V	2N2325...2329, TAG 615-200
54785	RTF0120	RTF 0101, 200V	2N2326...2329, TAG 615-200
54786	RTF0125	RTF 0101, 250V	2N2327...2329, TAG 615-400
54787	RTF0130	RTF 0101, 300V	2N2328...2329, TAG 615-400
54788	RTF0135	RTF 0101, 350V	2N2329, TAG 615-400
54789	RTF0140	RTF 0101, 400V	2N2329, TAG 615-400
54790	RTF0201...0240	Igt/Ih<1/<10mA	TAG 1..., TAG 2..., MCR 1906-..., TAG 614...
54791	RTF0301...0340	Igt/Ih<0,2/<10mA	2N2322...2329, TAG 615-...
54792	RTF0401...0440	Igt/Ih<0,1/<5mA	-
54793	RTF0501...0540	Igt/Ih<0,02/<3mA	2N2322...2329A, 2N6322...6337
54794	RTF0601...0640	Igt/Ih<0,02/<2mA	2N2322...2329A, 2N6322...6337
54795	RTF10...60R	RTF 10..60	ESM 765/...
54796	RTF10...80	100..800V, 10A, <300ns	ESM 765/...
54797	RTGC0101	Igt/Ih<0,5/<10mA	-
54798	RTGC0103	RTGC 0101, +30V	-
54799	RTGC0106	RTGC 0101, +60V	-
54800	RTGC0110	RTGC 0101, +100V	-
54801	RTGC0115	RTGC 0101, +150V	-
54802	RTGC0120	RTGC 0101, +200V	-
54803	RTGC0125	RTGC 0101, +250V	-
54804	RTGD0101	Igt/Ih<0,5/<10mA	-
54805	RTGD0103	RTGD 0101, +30V	-
54806	RTGD0106	RTGD 0101, +60V	-
54807	RTGD0110	RTGD 0101, +100V	-
54808	RTGD0115	RTGD 0101, +150V	-
54809	RTGD0120	RTGD 0101, +200V	-

54810	RTGD0125	RTGD 0101, +250V	-
54811	RTGD0130	RTGD 0101, +300V	-
54812	RTJ0103	Igt/Ih<0,1/<5mA	-
54813	RTJ0103...0140-1	RTJ 0103..0140, Igt<2μA	-
54814	RTJ0103...0140-2	RTJ 0103..0140, Igt<5μA	-
54815	RTJ0106	RTJ 0103, 60V	-
54816	RTJ0110	RTJ 0103, 100V	-
54817	RTJ0120	RTJ 0103, 200V	-
54818	RTJ0130	RTJ 0103, 300V	-
54819	RTJ0140	RTJ 0103, 400V	-
54820	RTJ0203	Igt/Ih<1/10mA	BRY 55/30, BT 149F, TAG 70D, TAG 72D
54821	RTJ0206	RTJ 0203, 60V	BRY 55/60, BT 149A, TAG 70D, TAG 72D
54822	RTJ0210	RTJ 0203, 100V	BRY 55/100, BT 149A, TAG 70D, TAG 72D
54823	RTJ0215	RTJ 0203, 150V	BRY 55/200, BT 149B, TAG 70D, TAG 72D
54824	RTJ0220	RTJ 0203, 200V	BRY 55/200, BT 149B, TAG 70D, TAG 72D
54825	RTJ0230	RTJ 0203, 300V	BRY 55/300, BT 149D, TAG 70D, TAG 72D
54826	RTJ0501	Igt/Ih<0,02/3mA	-
54827	RTJ0503	RTJ 0501, 30V	-
54828	RTJ0506	RTJ 0501, 60V	-
54829	RTJ0510	RTJ 0501, 100V	-
54830	RTJ0515	RTJ 0501, 150V	-
54831	RTJ0520	RTJ 0501, 200V	-
54832	RTJ0525	RTJ 0501, 250V	-
54833	RTJ0530	RTJ 0501, 300V	-
54834	RTL0605	Igt/Ih<50/<100mA	BT 152/400R, BStD1026, 2N6400...6405
54835	RTL0610	RTL 0605, 100V	BT 152/400R, BStD1026, 2N6401...6405
54836	RTL0620	RTL 0605, 200V	BT 152/400R, BStD1026, 2N6402...6405
54837	RTL0640	RTL 0605, 400V	BT 152/400R, BStD1026, 2N6403...6405
54838	RTL0660	RTL 0605, 600V	BT 152/600R, BStD1040, 2N6404...6405
54839	RTL0805	Igt/Ih<50/<100mA	BT 152/400R, BStD1026, 2N6504...6509
54840	RTL0810	RTL 0805, 100V	BT 152/400R, BStD1026, 2N6505...6509
54841	RTL0820	RTL 0805, 200V	BT 152/400R, BStD1026, 2N6506...6509
54842	RTL0840	RTL 0805, 400V	BT 152/400R, BStD1026, 2N6507...6509
54843	RTL0860	RTL 0805, 600V	BT 152/600R, BStD1040, 2N6508...6509
54844	RTL1005	Igt/Ih<50/<100mA	BStD1026M, BT 152/400R, 2N6504...6509
54845	RTL1010	RTL 1005, 100V	BStD1026M, BT 152/400R, 2N6505...6509
54846	RTL1020	RTL 1005, 200V	BStD1026M, BT 152/400R, 2N6506...6509
54847	RTL1030	RTL 1005, 300V	BStD1026M, BT 152/400R, 2N6507...6509
54848	RTL1040	RTL 1005, 400V	BStD1026M, BT 152/400R, 2N6507...6509
54849	RTL1050	RTL 1005, 500V	BStD1033M, BT 152/600R, 2N6508...6509
54850	RTL1060	RTL 1005, 600V	BStD1040M, BT 152/600R, 2N6508...6509
54851	RTL1510	Igt/Ih<100/<100mA	MCR 69-3, 2N6504...6509
54852	RTL1520	RTL 1510, 200V	2N6505...6509
54853	RTL1540	RTL 1510, 400V	2N6507...6509
54854	RTL1560	RTL 1510, 600V	2N6508...6509

54855	RTL1610	Igt/Ih<50/<100mA	MCR 69-3, 2N6504...6509
54856	RTL1620	RTL 1610, 200V	2N6505...6509
54857	RTL1640	RTL 1610, 400V	2N6507...6509
54858	RTL1660	RTL 1610, 600V	2N6508...6509
54859	RTM1005...1060	RTL 1005..1060	-
54860	RTN0805...0860	RTL 0805..0860	BTW 42/..., TAG 9N..., TAG 15..., CS 13...
54861	RTR0305	Igt/Ih<20/25mA	BStC0506, TAG 671-100, TAG 676-100
54862	RTR0310	RTR 0305, 100V	BStC0506, TAG 671-100, TAG 676-100
54863	RTR0320	RTR 0305, 200V	BStC0513, TAG 671-200, TAG 676-200
54864	RTR0330	RTR 0305, 300V	BStC0526, TAG 671-300, TAG 676-300
54865	RTR0340	RTR 0305, 400V	BStC0526, TAG 671-400, TAG 676-400
54866	RTR0350	RTR 0305, 500V	BStC0533, TAG 671-500, TAG 676-500
54867	RTR0360	RTR 0305, 600V	BStC0540, TAG 671-600, TAG 676-600
54868	RTR0605...0660	RTL 0605..0660	TAG 675-...
54869	RTR1005...1060	RTL 1005..1060	-
54870	RTS0605...0660	RTL 0605..0660	BStE40...M
54871	RTS1005...1060	RTL 1005..1060	BStE40...M
54872	RTS1610...1660	RTL 1610..1660	BStE40...M
54873	RTS2505	Igt/Ih<50/<100mA	-
54874	RTS2510	RTS 2505, 100V	-
54875	RTS2520	RTS 2505, 200V	-
54876	RTS2540	RTS 2505, 400V	-
54877	RTS2560	RTS 2505, 600V	-
54878	RTT2505...2560	RTS 2505..2560	BTW 48/..., CS 23-..., T 24N..., TAG 24N...
54879	RTU0605...0660	RTL 0605..0660	TAG 9N..., TAG 15-..., BTW 39/..., CS 13...
54880	RTU0710	Igt/Ih<50/200mA	BTW48/200, CS23-02, T24N200, TAG24N400
54881	RTU0720	RTU 0710, 200V	BTW48/200, CS23-02, T24N200, TAG24N400
54882	RTU0730	RTU 0710, 300V	BTW48/400, CS23-04, T24N400, TAG24N400
54883	RTU0740	RTU 0710, 400V	BTW48/400, CS23-04, T24N400, TAG24N400
54884	RTU0750	RTU 0710, 500V	BTW48/500, CS23-06, T24N600, TAG24N600
54885	RTU0760	RTU 0710, 600V	BTW48/600, CS23-06, T24N600, TAG24N600
54886	RTU1005...1060	RTL 1005..1060	2N1842...1850, TAG 9N..., TAG 15-...
54887	RTU1610...1660	RTL 1610..1660	TAG 14N..., BTW 39/..., BTW 47/..., CS 13...
54888	RTU2505...2560	RTS 2505..2560	BTW 48/..., CS 23-..., T 24N..., TAG 24N...
54889	RTV0102	Igt/Ih<50/<200mA	TAG 9N400, TAG 15-100, TAG 14N400
54890	RTV0105	RTV 0102, 50V	TAG 9N400, TAG 15-100, TAG 14N400
54891	RTV0110	RTV 0102, 100V	TAG 9N400, TAG 15-100, TAG 14N400
54892	RTV0120	RTV 0102, 200V	TAG 9N400, TAG 15-200, TAG 14N400
54893	RTV0130	RTV 0102, 300V	TAG 9N400, TAG 15-400, TAG 14N400
54894	RTV0140	RTV 0102, 400V	TAG 9N400, TAG 15-400, TAG 14N400
54895	RTV0150	RTV 0102, 500V	TAG 9N600, TAG 15-500, TAG 14N600
54896	RTV0160	RTV 0102, 600V	TAG 9N600, TAG 15-600, TAG 14N600
54897	RTV0202	Igt/Ih<50/<200mA	BTW 40/200R, BTW 92/200R, T 17N200
54898	RTV0205	RTV 0202, 50V	BTW 40/200R, BTW 92/200R, T 17N200
54899	RTV0210	RTV 0202, 100V	BTW 40/200R, BTW 92/200R, T 17N200

54900	RTV0220	RTV 0202, 200V	BTW 40/200R, BTW 92/200R, T 17N200
54901	RTV0230	RTV 0202, 300V	BTW 40/400R, BTW 92/400R, T 17N400
54902	RTV0240	RTV 0202, 400V	BTW 40/400R, BTW 92/400R, T 17N400
54903	RTV0250	RTV 0202, 500V	BTW 40/600R, BTW 92/600R, T 17N600
54904	RTV0260	RTV 0202, 600V	BTW 40/600R, BTW 92/600R, T 17N600
54905	RTV0302	Igt/Ih<25/<50mA	C 230U, BStE4126N
54906	RTV0305	RTV 0302, 50V	C 230F, BStE4126N
54907	RTV0310	RTV 0302, 100V	C 230A, BStE4126N
54908	RTV0320	RTV 0302, 200V	C 230B, BStE4126N
54909	RTV0330	RTV 0302, 300V	C 230C, BStE4126N
54910	RTV0340	RTV 0302, 400V	C 230D, BStE4126N
54911	RTV0350	RTV 0302, 500V	C 230E, BStE4133N
54912	RTV0360	RTV 0302, 600V	C 230M, BStE4140N
54913	RTV0402...0460	RTV 0102..0160	RTV 0102...0160
54914	RTV0502...0560	RTV 0202..0260	RTV 0202...0260
54915	RTV0602...0660	RTV 0302..0360	RTV 0302...0360
54916	RU	SM 4T 36	SM 4T...
54917	RU-1AV	BY 298	BY 298
54918	RU1(A,B,C)	400..1000V, 0,25A, <400ns	BA 157...159, BY 204/..., BY 208/...
54919	RU101	Rb10kOhm, R	
54920	RU1P	1000V, 0,4A, 100ns	BA 159, BY 204/10, BY 208/1000
54921	RU2	600V, 1A, <400ns	BY 231/800, BYX 55/600, RGP 10J...M
54922	RU201	RbeRcb47	
54923	RU2AM	RU 2, 600V, 1,1A	BY 231/800, BYX 55/600, RGP 10J...M
54924	RU2B	RU 2, 800V, 1A	BYD 33K...M, BY 231/800, RGP 10K...M
54925	RU2C	RU 2, 1000V, 0,8A	BYD 33M, BY 231/800, RGP 10M
54926	RU2M	RU 2, 400V, 1,1A	BY 231/800, BYX 55/600, RGP 10G...M
54927	RU2YX	RU 2, 100V, 1,5A, 200ns	BY 231/800, BYX 55/350, RGP 10B...M
54928	RU2Z	RU 2, 200V	BY 231/800, BYX 55/350, RGP 10D...M
54929	RU3	400V, 1,5A, 400ns	BY 258/400, BYW 95B...C, RGP 15G...M
54930	RU30(A,Z)	200..600V, 2A, 400ns	BY 296...299, BYW 32...36, BYW 95A...C
54931	RU3A	RU 3, 600V	BY 258/650, BYW 95C, RGP 15J...M
54932	RU3AM	RU 3, 600V	BY 258/650, BYW 95C, RGP 15J...M
54933	RU3B	RU 3, 800V, 1,1A	BY 258/800, BYW 96D...E, RGP 15K...M
54934	RU3C	RU 3, 1000V	BY 299, BY 438, BYW 96E, RGP 15M
54935	RU3M	RU 3, 400V	BY 258/400, BYW 95B...C, RGP 15G...M
54936	RU3YX	RU 3, 100V, 2A, 200ns	BY 258/100, BYW 95A...C, RGP 15B...M
54937	RU4	400V, 3A, 400ns	BY 398...399, BYW 95B...C, RGP 30G...M
54938	RU4A	RU 4, 600V	BY 399, BYW 95C, MR 856, RGP 30J...M
54939	RU4AM	RU 4, 600V, 3,5A	BY 399, BYW 95C, MR 856, RGP 30J...M
54940	RU4B	RU 4, 800V	BY 399, BYW 96D...E, RGP 30K...M
54941	RU4C	RU 4, 1000V, 2,5A	BY 399S, BY 438, BYW 96E, RGP 30M
54942	RU4D	1300V, 1,5A, 400ns	BY 228, BY 328, BY 448
54943	RU4DS	1300V, 2,5A, 400ns	BY 228, BY 328
54944	RU4M	RU 4, 400V, 3,5A	BY 398...399, BYW 95B...C, RGP 30G...M



54945	RU4Y	RU 4, 100V	BY 500/100, FE 5B...D, EGP 50B...G
54946	RU4YX	RU 4, 100V, 4A, 200ns	BY 500/100, FE 5B...D, EGP 50B...G
54947	RU4Z	RU 4, 250V	BY 500/400, EGP 50F...G, MR 824...828
54948	RU901	Rb2000hm, R	
54949	1610..1620CT	MUR 1610..1620	MUR 1605...1660CT
54950	RUR-810..860	100..600V, 8A, <35..50ns	BYR 29/..., BYT 12P/..., MUR 810...8100
54951	RUR-D1610..1620	100..200V, 16A, <35ns	-
54952	RUR-D1610..1620	100..200V, 16A, <35ns	-
54953	RUR-D810..860	RUR 810..860	BYR 28/..., BYT 28/...
54954	RV	SM 4T 36A	SM 4T...
54955	RVY	MMST 918S	MMST 918S
54956	RVY	SST 918S	SST 918S
54957	RVZ	SST 4126	SST 4126
54958	RVZ	MMST 4126	MMST 4126
54959	RW	SM 4T 39	SM 4T...
54960	RX	SM 4T 39A	SM 4T...
54961	RX7	SST 6426	SST 6426
54962	RXT2222A	2N2222A, SMD	PXT 2222A
54963	RXT2907A	2N2907A, SMD	PXT 2907A
54964	RXT3904	2N3904, SMD	PXT 3904
54965	RXT3906	2N3906, SMD	PXT 3906
54966	RXTA-14	MPSA 14, SMD	PXTA 14
54967	RXTA-28	MPSA 28, SMD	PXTA 28
54968	RXTA-64	MPSA 64, SMD	PXTA 64
54969	RXTA-76	MPSA 77, SMD	PXTA 77
54970	RY	KTC3879-Y	KTC 3879
54971	RY	2SC3898	2SC3898
54972	RY	2SC2715-Y	2SC2715
54973	RY	KTA1664-Y	KTA 1664
54974	RY	2SJ361	2SJ361
54975	RY	2SA1204-Y	2SA1204
54976	RY23	UR200V, Uz250..400V	-
54977	RY24	UR400V, Uz400..450V	-
54978	RZC	MMST 4124	MMST 4124
54979	RZC	SST 4124	SST 4124
54980	S	HVU 359	HVU 359
54981	S	HVC 359	HVC 359
54982	S	2SD1483	2SD1483
54983	S-1,5-01...-10(FR)	100..1000V, 1..1,3A	BY 126...127, BY 133...134, 1N4002...07
54984	S.4	D 1FS4	D 1FS4
54985	S0	SST 270	SST 270
54986	S0602BH	<0,2/10mA	TAG 623-..., TAG 628-..., TAG 633-...
54987	S0602DH	S 0602BH, 400V	TAG 623-..., TAG 628-..., TAG 633-...
54988	S0602MH	S 0602BH, 600V	TAG 623-..., TAG 628-..., TAG 633-...
54989	S0602NH	S 0602BH, 800V	TAG 623-..., TAG 628-..., TAG 633-...

54990	S0605BH..NH	S 0602BH..NH, Igt/Ih <5/25mA	TAG 626-..., TAG 627-..., T 3,5N...
54991	S0607BH..NH	S 0602BH..NH, Igt/Ih <10/50mA	TAG 626-..., TAG 627-..., T 3,5N...
54992	S0610BH..NH	S 0602BH..NH, Igt/Ih <25/75mA	TAG 625-..., TIC 116-..., CS6-...
54993	S0802BH	<0,2/10mA	-
54994	S0802DH	S 0802BH, 400V	-
54995	S0802MH	S 0802BH, 600V	-
54996	S0802NH	S 0802BH, 800V	-
54997	S0805BH..NH	S 0802BH..NH, Igt/Ih <5/25mA	T 3,5N..., TAG 661-..., TAG 662-...
54998	S0807BH..NH	S 0802BH..NH, Igt/Ih <10/50mA	T 3,5N..., TAG 661-..., TAG 662-...
54999	S0810BH..NH	S 0802BH..NH, Igt/Ih <25/75mA	TIC 116-..., CS6-..., TAG 660-...
55000	S1	FS 2A	FS 2A
55001	S1	HRU 0103A	HRU 0103A
55002	S1	1SS239	1SS239
55003	S1	SST 271	SST 271
55004	S1	BSV 35A	BSV 35A
55005	S1(p)	BBY 31	BBY 31
55006	S10	HRW 0502A	HRW 0502A
55007	S1005BH	<5/15mA	TAG 666-..., TAG 667-...,
55008	S1005DH	S1005BH, 400V	TAG 666-..., TAG 667-...,
55009	S1005MH	S1005BH, 600V	TAG 666-..., TAG 667-...,
55010	S1005NH	S1005BH, 800V	TAG 666-..., TAG 667-...,
55011	S1007BH..NH	S1005BH..NH, Igt/Ih <10/25mA	TAG 666-..., TAG 667-...,
55012	S1010BH..NH	S1005BH..NH, Igt/Ih <25/50mA	TAG 665-..., TIC 126..., T 7,5N...
55013	S1021	2N3702	2N3702
55014	S1042	2N3703	2N3703
55015	S106...	C 106..	C 106...
55016	S107...	C 107..	C 107...
55017	S11	HRW 0302A	HRW 0302A
55018	S12	STPS 120E	STPS 120E
55019	S12	BBY 39	BBY 39
55020	S12	HSM 113WK	HSM 113WK
55021	S1205BH	<5/7,5mA	-
55022	S1205DH	S 1205BH, 400V	-
55023	S1205MH	S 1205BH, 600V	-
55024	S1205NH	S 1205BH, 800V	-
55025	S1207BH..NH	S 1205BH..NH, Igt/Ih <10/25mA	-
55026	S1210BH..NH	S 1205BH..NH, Igt/Ih <25/50mA	TIC 126-..., T 7,5N..., TAG 680-...
55027	S122...	C 122..	C 122...
55028	S1236	100V, 4A, 40W, >3MHz	BD 243C, BD 539C, BD 953, 2SD 712
55029	S1237	100V, 4A, 40W, >3MHz	BD 244C, BD 540C, BD 954, 2SB682
55030	S1238	60V, 1,5A, >50MHz	BD 517, BD 525, BD 527, BD 529
55031	S1239	60V, 1,5A, >50MHz	BD 518, BD 526, BD 528, BD 530
55032	S1298	300V, 0,1A, >75MHz	BF 858...859, BF 382, MPSU 10
55033	S13	STPS 130E	STPS 130E
55034	S13	HSM 125WK	HSM 125WK

55035	S13	BBY 42	BBY 42
55036	S1350	90V, 6A, 50W, 4MHz	BD 243C, BD 543C, BD 801, 2SD613
55037	S1351	90V, 6A, 50W, 4MHz	BD 244C, BD 544C, BD 802, 2SB633
55038	S1375	80V, 0,75A, >50MHz	BD 387, BD 417, BD 519, BD 529
55039	S1376	80V, 0,75A, >50MHz	BD 388, BD 418, BD 520, BD 530
55040	S1377	250V, 0,5A, >20MHz	BF 381...382, BF 757...759, MPSU 10
55041	S1381	100V, 5A, 40W, >3MHz	BD 243C, BD 539C, BD 953, 2SD613
55042	S1382	100V, 5A, 40W, >3MHz	BD 244C, BD 540C, BD 954, 2SB633
55043	S1383	80V, 0,75A, 0,8W, >50MHz	BC 303, BC 461, BCX 60
55044	S14	STPS 140E	STPS 140E
55045	S14	HSM 126S	HSM 126S
55046	S14	BB 901	BB 901
55047	S140Z	ZPY 9,1	ZPY 9,1
55048	S1420	60V, 0,2A, 0,625W, >150MHz	BC 182, BC 174, BC 190, BC 546
55049	S1420	60V, 0,2A, 0,625W, >150MHz	BC 182, BC 174, BC 190, BC 546
55050	S1423	40V, 0,2A, 0,625W, >150MHz	BC 212, BC 256, BC 266, BC 556
55051	S146Z	ZPD 9,1	ZPD 9,1
55052	S15	HRW 0702A	HRW 0702A
55053	S150T	BD 237	BD 237
55054	S153T	BD 139	BD 139
55055	S16	STPS 160E	STPS 160E
55056	S16	HRC 0202A	HRC 0202A
55057	S1610BH	<25/<38mA	T 9,5N..., CS 15-...,
55058	S1610DH	S1610BH, 400V	T 9,5N..., CS 15-...,
55059	S1610MH	S1610BH, 600V	T 9,5N..., CS 15-...,
55060	S1610NH	S1610BH, 800V	T 9,5N..., CS 15-...,
55061	S1612BH..NH	<50/100mA	BStD10...M, BT 152/..., 2N6506...6509
55062	S17	HRW 0202A	HRW 0202A
55063	S1732	200V, 0,8A, 1,5W	BF 466...468, MPSU 04
55064	S18	HRW 0202B	HRW 0202B
55065	S1805	40V, 0,5A, 0,625W	BC 337, BC 635, BC 637, BC 639
55066	S1806	40V, 0,5A, 0,625W	BC 327, BC 636, BC 638, BC 640
55067	S1807	35V, 0,8A, 0,625W	BC 337, BC 635, BC 637, BC 639
55068	S1808	35V, 0,8A, 0,625W	BC 327, BC 636, BC 638, BC 640
55069	S180D	60V, 1,5A	BY 226, BY 251, GP 15B...M, 1N5392...99
55070	S181D	S 180D, 120V	BY 226, BY 251, GP 15D...M, 1N5393...99
55071	S1836	300V, 0,1A, 0,625W, 80MHz	BF 299, BF 393, BF 420A, 2SC3380
55072	S1837	300V, 0,1A, 0,625W, 60MHz	BF 437, BF 493, BF 421A, 2SA1384
55073	S1838	80V, 0,3A, 0,625W, 100MHz	BC 538, BC 639, 2SD1226, 2SD1616A
55074	S1839	80V, 0,3A, 0,625W, 100MHz	BC 528, BC 640, 2SB910, 2SB1116A
55075	S1840	150V, 0,03A, 0,625W, 100MHz	BF 297...299, BF 420(A), BF 422(A)
55076	S1A	SMBT 3904	SMBT 3904
55077	S1A	SXT 3904	SXT 3904
55078	S1A..M	G 1A..M, SMD	D 1F10...F60, U1 BC44...JC44
55079	S1A60...A150	600..1500V, 0,1A, <1,5µs	BY 203/..., RGP 01-..., SHG 1...1,5

55080	s1B	SMBT 2222	SMBT 2222
55081	s1C	SMBTA 20	SMBTA 20
55082	s1D	SMBTA 42	SMBTA 42
55083	S1D	SXTA 42	SXTA 42
55084	s1E	SMBTA 43	SMBTA 43
55085	S1E	SXTA 43	SXTA 43
55086	s1G	SMBTA 06	SMBTA 06
55087	S1G10...G80	100..800V, 1A	BY 126...127, BY 133...134, 1N4002...07
55088	S1G40Z...G80Z	S 1G40..G80	BYW 53...56, 1N4246...49, 1N5060...62
55089	s1H	SMBTA 05	SMBTA 05
55090	s1K	SMBT 6428	SMBT 6428
55091	s1L	SMBT 6429	SMBT 6429
55092	s1M	SMBTA 13	SMBTA 13
55093	s1N	SMBTA 14	SMBTA 14
55094	s1P	SMBT 2222A	SMBT 2222A
55095	S1P20...P200	200..2000V, 0,1A, <1,5µs	BY 203/..., GP 10D...Y, RGP 01-...
55096	S1P20Z...P40Z	S 1P20..P40, , 0,6A	BYW 52...56, 1N4245...49, 1N5060...62
55097	S1R20...R150	200..1500V, 0,1A, <1,5µs	BAY 88...91, BY 203/..., RGP 01-...
55098	S1R20Z...R40Z	S 1R20..R40, , 0,6A	BYW 52...56, 1N4245...49, 1N5060...62
55099	S1RA60...100	600..1000V, 0,1A, <500ns	BA 158...159, BY 204/..., BY 208/...
55100	S1S3M	30V, 1A	BYS 21-45, BYV 10-30, MBR 150, 1N5818
55101	S1S4M	40V, 1A	BYS 21-45, BYV 10-40, MBR 150, 1N5819
55102	S1S6M	60V, 1A	BYS 21-90, BYV 10-60, MBR 160, SB 160
55103	s1V	SMBT 6427	SMBT 6427
55104	S2	1SS242	1SS242
55105	S2	FS 2B	FS 2B
55106	S2	1SS315	1SS315
55107	S2	2SA813-S2	2SA813
55108	S2	BBY 40	BBY 40
55109	S2	BFQ 31	BFQ 31
55110	S2	HSM 112WK	HSM 112WK
55111	S2	BSV 35	BSV 35
55112	S2000	1500V, 8A, 125W	BU 508
55113	S2000A(-1...-3)	S 2000	BU 508A
55114	S2000AF	S 2000, 50W	BU 508AF
55115	S2000AXI	S 2000, 40W	BU 1808 AX
55116	S2000F,FI	S 2000, 50W	BU 508AF
55117	S2000N	S 2000, 50W	BU 508AF
55118	S2012BH	<50/100mA	2N6506...6509
55119	S2012DH	S2012BH, 400V	2N6507...6509
55120	S2012MH	S2012BH, 600V	2N6508...6509
55121	S2012NH	S2012BH, 800V	2N6509
55122	S2014BH..NH	<75/150mA	-
55123	S2048	2N3702	2N3702
55124	S2049	2N3704	2N3704

55125	S2050	2N3710	2N3710
55126	S2054	1500V, 3,5A, 10W(Tc95°)	BU 508D, 2SC3480...82, 2SC3681...82
55127	S2055	S 2000	BU 508D
55128	S2055A	S 2000A	BU 508D
55129	S2055AF(-1)	S 2000AF	BU 508DF
55130	S2055F(-1),FI	S 2000F	BU 508DF
55131	S2055N	S 2000N	BU 508DF
55132	S2056	1500V, 3A, 10W(Tc95°)	BU 508(A), BU 706, 2S3484...3486
55133	S2060A	Igt/Ih<0,2/<3mA	TAG 633-100, TIC 106A, TAG 623-100
55134	S2060B	S 2060 A, 200V	TAG 633-200, TIC 106B, TAG 623-200
55135	S2060C	S 2060 A, 300V	TAG 633-300, TIC 106C, TAG 623-300
55136	S2060D	S 2060 A, 400V	TAG 633-400, TIC 106D, TAG 623-400
55137	S2060E	S 2060 A, 500V	TAG 633-500, TIC 106E, TAG 623-500
55138	S2060F	S 2060 A, 50V	TAG 633-100, TIC 106F, TAG 623-100
55139	S2060M	S 2060 A, 600V	TAG 633-600, TIC 106M, TAG 623-600
55140	S2060Q	S 2060 A, 15V	TAG 633-100, TIC 106Y, TAG 623-100
55141	S2060Y	S 2060 A, 30V	TAG 633-100, TIC 106Y, TAG 623-100
55142	S2061A...Y	S 2060 A..Y, Igt/Ih<0,5/<6mA	TAG 631-...., TIC 106A...Y, TAG 623-...
55143	S2062A...Y	S 2060 A..Y, Igt/Ih<2/<10mA	TAG 625-...., TIC 106A...Y, TIC 108A...Y
55144	S22	HRF 22	HRF 22
55145	S2292	BC 307	BC 307
55146	S2301	BF 245	BF 245
55147	S2318	BF 245	BF 245
55148	S2329	BF 245	BF 245
55149	S2330	BF 245	BF 245
55150	S2340	BF 245	BF 245
55151	S2350	BF 245	BF 245
55152	S2354	BF 245	BF 245
55153	S2355	BF 245	BF 245
55154	S2363	BF 245	BF 245
55155	S2400A	Igt/Ih<15/20mA	S 2620B, TAG 607-100
55156	S2400B	S 2400 A, 200V	S 2620B, TAG 607-200
55157	S2400D	S 2400 A, 400V	S 2620D, TAG 607-400
55158	S2400M	S 2400 A, 600V	S 2620M, TAG 607-600
55159	S2403(A)	BF 245	BF 245
55160	S2422	BF 245	BF 245
55161	S2423	BF 245	BF 245
55162	S2432	BF 245	BF 245
55163	S2440	BF 245	BF 245
55164	S2446	BF 245	BF 245
55165	S2451	BF 246	BF 246
55166	S2530A	BU 626A	BU 626A
55167	S2566		-
55168	S2600B	200V, 1A, Igt/Ih<15/20mA	TAG 612-200, TAG 606-200, TAG 607-200
55169	S2600D	S 2600 B, 400V	TAG 612-400, TAG 606-400, TAG 607-400

55170	S2600M	S 2600 B, 600V	TAG 612-600, TAG 606-600, TAG 607-600
55171	S2600N	S 2600 B, 800V	TAG 612-800, TAG 606-800, TAG 607-800
55172	S2610B...N	S 2600B..N, 2,2A(Ta25°C)	TAG 606-..., TAG 607-...
55173	S2616	BC 546	BC 546
55174	S2620B...N	S 2600 B..N, 4,25A	-
55175	S2683	BSW 83	BSW 83
55176	S2700B	2N3228	2N3228
55177	S2700D	2N3525	2N3525
55178	S2700M	2N4101	2N4101
55179	S2710B	2N3228	2N3228
55180	S2710D	2N3525	2N3525
55181	S2710M	2N4101	2N4101
55182	S2788	2N3404	2N3404
55183	S279T	BC 547	BC 547
55184	S2800A	Igt/Ih<15/<20mA	TAG 665-100, TIC 126A, T 7,5N400
55185	S2800B	S 2800 A, 200V	TAG 665-200, TIC 126B, T 7,5N400
55186	S2800C	S 2800 A, 300V	TAG 665-400, TIC 126C, T 7,5N400
55187	S2800D	S 2800 A, 400V	TAG 665-400, TIC 126D, T 7,5N400
55188	S2800E	S 2800 A, 500V	TAG 665-500, TIC 126E, T 7,5N600
55189	S2800F	S 2800 A, 50V	TAG 665-100, TIC 126F, T 7,5N400
55190	S2800M	S 2800 A, 600V	TAG 665-600, TIC 126M, T 7,5N600
55191	S2800N	S 2800 A, 800V	TAG 665-800, TIC 126N, T 7,5N800
55192	S2800S	S 2800 A, 700V	TAG 665-700, TIC 126S, T 7,5N700
55193	S2801	1400/600V, 10A, 50W	2SD1279
55194	S2802	1000/400V, 12A, 100W	BU 626A, 2SD1094
55195	S280T	BC 557	BC 557
55196	S2818	1500/700V, 5A, 12,5W(Tc95°)	BU 208(A)D
55197	S2818A	S 2818	BU 208AD
55198	S281T	BC 547	BC 547
55199	S2824	1500V, 3,5A, 10W(Tc95°)	BU 208D, BU 508D, 2SC3480, 2SD903...04
55200	S2887	BC 337	BC 337
55201	S2900(G)	BF 900	BF 900
55202	S298T	BU 208(A)	BU 208(A)
55203	s2A	SMBT 3906	SMBT 3906
55204	S2A	SXT 3906	SXT 3906
55205	S2A..M	G 2A..M, 1,5A, SMD	BYG 10D...M
55206	s2B	SMBT 3907	SMBT 3907
55207	s2C	SMBTA 70	SMBTA 70
55208	s2D	SMBTA 92	SMBTA 92
55209	S2D	SXTA 92	SXTA 92
55210	s2E	SMBTA 93	SMBTA 93
55211	S2E	SXTA 93	SXTA 93
55212	s2F	SMBT 2907A	SMBT 2907A
55213	S2F	SXT 2907A	SXT 2907A
55214	s2G	SMBTA 56	SMBTA 56



55215	s2H	SMBTA 55	SMBTA 55
55216	s2O	SMBT 5087	SMBT 5087
55217	s2P	SMBT 5086	SMBT 5086
55218	S2P	SXT 2222A	SXT 2222A
55219	s2U	SMBTA 63	SMBTA 63
55220	s2V	SMBTA 64	SMBTA 64
55221	S3	1SS357	1SS357
55222	S3	FS 2D	FS 2D
55223	S3	1SS369	1SS369
55224	S3	BFQ 31R	BFQ 31R
55225	S3	2SA813-S3	2SA813
55226	S3	BSV 36	BSV 36
55227	S30	BB 804-0	BB 804-0
55228	S30	FP 1A4A	FP 1...
55229	S301T	BC 308	BC 308
55230	S3060A	Igt/Ih<2/<16mA	-
55231	S3060B	S 3060 A, 200V	-
55232	S3060D	S 3060 A, 400V	-
55233	S3060F	S 3060 A, 50V	-
55234	S3060M	S 3060 A, 600V	-
55235	S31	BB 804-1	BB 804-1
55236	S31	FP 1L2Q	FP 1...
55237	S32	HRF 32	HRF 32
55238	S32	FP 1A3M	FP 1...
55239	S32	BB 804-2	BB 804-2
55240	S33	FP 1F3P	FP 1...
55241	S33	BB 804-3	BB 804-3
55242	S331T	BF 440	BF 440
55243	S33805	SE 4020	SE 4020
55244	S34	FP 1L3N	FP 1...
55245	S34	BB 804-4	BB 804-4
55246	S35	FP 1A4M	FP 1...
55247	S3529A	BUT 11AF	BUT 11AF
55248	S3540	2SC4448	2SC4448
55249	S357T	BU 208(A)	BU 208(A)
55250	S36	FP 1J3P	FP 1...
55251	S36478	MPSA 17	MPSA 17
55252	S3700B	Igt/Ih<40/<50mA	T 3S400, TAG 670S-200, BTW 27S/200
55253	S3700D	S 3700 B, 400V	T 3S400, TAG 670S-400, BTW/27S400
55254	S3700M	S 3700 B, 600V	T 3S600, TAG 670S-600, BTW/27S600
55255	S3701M	600V, 5A, Igt/Ih<35/>15mA	-
55256	S3702	2N3702	2N3702
55257	S3702S(SF)	Igt<45mA	S 6080C, BStCC0146R, TD3F700R, TD4F700R
55258	S3703SF	Igt<32mA	TU 3F800H, TD 3F800H, TD 4F800H
55259	S3704A	Igt/Ih<40/<50mA	S 3702S, TD3F400R, TD4F400R, BStCC0126R

55260	S3704B	S 3704 A, 200V	S 3702S, TD3F400R, TD4F400R, BStCC0126R
55261	S3704D	S 3704 A, 400V	S 3702S, TD3F400R, TD4F400R, BStCC0126R
55262	S3704M	S 3704 A, 600V	S 3702S, TD3F600R, TD4F600R, BStCC0140R
55263	S3704S	S 3704 A, 700V	S 3702S, TD3F700R, TD4F700R, BStCC0146R
55264	S3705M	Igt<32mA	TU 3F600H, BStCC0140H, TD 3F600H
55265	S3706E	Igt<45mA	BStCC0133R, TD 3F500R, TD 4F500R
55266	S3706M	S 3706 E, +600V	BStCC0140R, TD 3F600R, TD 4F600R
55267	S3707...	S 3703	TU 3F...H, BStCC01...H, TD3F...H, TD4F...H
55268	S3714...	S 3704..	S 3704...
55269	S3746	180V, 0,3A, >200MHz	-
55270	S3751	250V, 0,15A, 200MHz	-
55271	S3800D	400V, 3,2A, Igt<45mA,<4,2μs	BStCC0126R, S6087A, TD3F400R, TD4F400R
55272	S3800E	500V, 3,2A, Igt<40mA,<2,4μs	BStCC0146H, S6087B, TD3F500H, TD4F500H
55273	S3800E	500V, 3,2A, Igt<40mA,<2,4μs	BStCC0146H, S6087B, TD3F500H, TD4F500H
55274	S3800EF	S 3800 D, 550V	BStCC0140R, S6087A, TD3F600R, TD4F600R
55275	S3800M	S 3800 D, 600V	BStCC0140R, S6087A, TD3F600R, TD4F600R
55276	S3800MF	S 3800 E, 650V	BStCC0146H, S6087B, TD3F700H, TD4F700H
55277	S3800MF	S 3800 E, 650V	BStCC0146H, S6087B, TD3F700H, TD4F700H
55278	S3800S	S 3800 D, 700V	BStCC0146R, S6087A, TD3F700R, TD4F700R
55279	S3800SF	S 3800 E, 750V	BStCC0153H, S6087B, TD3F800H, TD4F800H
55280	S380D	60V, 3A	BY 251...255, MR 501...510, 1N5401...08
55281	S381D	S 380D, 120V	BY 251...255, MR 502...510, 1N5402...08
55282	S38802	SE 4020	SE 4020
55283	S38803	SE 4021	SE 4021
55284	S3900E	5A(Tc60°),Igt<40mA,<2,4μs	BStCC0233H, 17088
55285	S3900MF	S 3900 E, 650V	BStCC0246H, 17088
55286	S3900S	S 3900 E, 700V	BStCC0246H, 17088
55287	S3900SF	S 3900 E, 750V	BStCC0253H, 17088
55288	S3901M	5A(Tc60°),Igt<45mA,<4,2μs	BStCC0240R, 17089
55289	S3901MF	S 3901 M, 650V	BStCC0246R, 17089
55290	S3901S	S 3901 M, 700V	BStCC0246R, 17089
55291	S3902DF	Igt<40mA,<3μs	BStCC0233H, 17088, S 3900E
55292	S3903MF	Igt<45mA,<5μs	BStCC0246R, 17089, S 3901MF
55293	S3930	1500/600V, 16A, 200W	-
55294	S3934	1700/600V, 10A, 200W	2SC4532
55295	S3935	1700/600V, 8A, 200W	S 3934, 2SC4608
55296	S3936	2SC4439	2SC4439
55297	S3937	180V, 0,3A, >200MHz	2SA1801
55298	S3938	100V, 0,5A, 1100MHz	-
55299	S393T	BD 435	BD 435
55300	S394T	BD 436	BD 436
55301	S3974	1700/600V, 6A, 50W	2SC4796
55302	S3L20U,LA20	200V, 3A, <35ns	BYV 28/200, EGP 30D, FE 3D
55303	S3L40,LA40	400V, 3A, <50ns	BYW 178, EGP 30G, FE 3H
55304	S3L60	600V, 2,2A, <50ns	BYW 178, EGP 30G, FE 3H

55305	S4	BBY 62	BBY 62
55306	S4	1SS367	1SS367
55307	S4	1SS373	1SS373
55308	S4	FS 2G	FS 2G
55309	S4	2SA813-S4	2SA813
55310	S4	BFQ 31A	BFQ 31A
55311	S4	SST 174	SST 174
55312	S4	2SC3361-S4	2SC3361
55313	S4	BSV 37	BSV 37
55314	S4000A	2N3668	2N3668
55315	S4000B	2N3669	2N3669
55316	S4000D	2N3670	2N3670
55317	S4000M	2N4103	2N4103
55318	S4001...4007	1N4001..4007	1N4001...4007
55319	S406	50V, 0,2A, <20ns	BAT 13, BAY 95, 1N3600, 1N4148
55320	S4060A	100V, 10A, Igt/Ih<0,2/<6mA	-
55321	S4060B	S 4060A, 200V	-
55322	S4060C	S 4060A, 300V	-
55323	S4060D	S 4060A, 400V	-
55324	S4060E	S 4060A, 500V	-
55325	S4060F	S 4060A, 50V	-
55326	S4060M	S 4060A, 600V	-
55327	S4060N	S 4060A, 800V	-
55328	S4060S	S 4060A, 700V	-
55329	S4060U	S 4060A, 25V	-
55330	S407	40V, 0,05, <15ns	BA 218, BAx 86, 1N3600, 1N4148
55331	S408T	BU 208	BU 208
55332	S416T	BF 440, SMD	BF 550, BF 824, 2SA1256
55333	S431	150V, 0,2A	BA 147/150, BAY 20...21, BA 157...159
55334	S46	BAR 46	BAR 46
55335	S471(T)	BF 471	BF 471
55336	S472(T)	BF 472	BF 472
55337	S473D	BAY 93	BAY 93
55338	S479T	BF 479	BF 479
55339	S483T	BFW 92, 0,45W	BFW 92
55340	S4A	SM-1XSN4A	SM-1XSN4A
55341	S4SC3M	30V, 2A	HRW 34
55342	S4SC4M	S 4SC3M, 40V	HRW 34
55343	S5	FS 2J	FS 2J
55344	S5	HRW 0203A	HRW 0203A
55345	S5	SST 175	SST 175
55346	S5	BFQ 31AR	BFQ 31AR
55347	S5	2SC3361-S5	2SC3361
55348	S518T	BU 208A	BU 208A
55349	S5210B	Igt/Ih<40/<50mA	TAG 15S-200, MCR 1718-4, C 234B

55350	S5210D	S 5210B, 400V	TAG 15S-400, MCR 1718-6, C 234D
55351	S5210M	S 5210B, 600V	TAG 15S-600, MCR 1718-8, C 234M
55352	S5277B..N	100..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
55353	S527T	BU 526	BU 526
55354	S5295B..J	100..600V, 0,5A, <1,5μs	BY 126...127, BY 133...135, 1N4001...07
55355	S5500B..G	100..400V, 1A	BY 126...127, BY 133...135, 1N4001...07
55356	S554T	BU 208	BU 208
55357	S555T	BU 208	BU 208
55358	S5566B..N	100..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
55359	S556T	BU 226	BU 226
55360	S557T	BU 209	BU 209
55361	S559T	BU 526	BU 526
55362	S5688B..N	100..1000V, 1A	BY 126...127, BY 133...135, 1N4001...07
55363	S577T	BU 208D	BU 208D
55364	S5800B	Igt/Ih<50/<50mA	CSF 11-02
55365	S5800C	S 5800B, 300V	CSF 11-04
55366	S5800D	S 5800B, 400V	CSF 11-04
55367	S5800E	S 5800B, 500V	CSF 11-06
55368	S5800M	S 5800B, 600V	CSF 11-06
55369	S5800N	S 5800B, 800V	CSF 11-08
55370	S5800S	S 5800B, 700V	CSF 11-08
55371	S5801B...S	S 5800 B..S	S 5800 B...S
55372	S5802B...S	S 5800 B..S	S 5800 B...S
55373	S587	20V, 0,1A	BA 127, BA 215, BAY 17, 1N4148...49
55374	S5A(s5A)	SMBD 6050	SMBD 6050
55375	S5B(s5B)	SMBD 6100	SMBD 6100
55376	S5C(s5C)	SMBD 7000	SMBD 7000
55377	S5D(s5D)	SMBD 914	SMBD 914
55378	S6	FS 2K	FS 2K
55379	S6	HRW 0503A	HRW 0503A
55380	S6	SST 176	SST 176
55381	S6	2SC3361-S6	2SC3361
55382	S6(p)	BF 510	BF 510
55383	S6000C	2N6397, 300V	2N6397
55384	S6000E	2N6398, 500V	2N6398
55385	S6000S	2N6399, 700V	2N6399
55386	S6002	BC 556	BC 556
55387	S6040	BC 327	BC 327
55388	S6052	BC 231	BC 231
55389	S6054	BC 308	BC 308
55390	S6080A	700V, 3,2A, Igt/Ih<45/<100mA	BStCC0146R, TD 3F 700R, TD 4F 700R
55391	S6080B	750V, 3,2A, Igt/Ih<30/<100mA	BStCC0153H,TD3F800H,TD4F800R
55392	S6080C	800V, 3,2A, Igt/Ih<40/<100mA	BStCC0153R, TD 3F 800R, TD 4F 800R
55393	S6087A(AG)	700V, 5A, Igt/Ih<45/<100mA	BStCC0146R, TD 3F 700R, TD 4F 700R
55394	S6087B	750V, 5A, Igt/Ih<30/<100mA	BStCC0153H, TD 3F 800H, TD 4F 800H

55395	S6087F	S 6087A	BStCC0153H, TD 3F 800H, TD 4F 800H
55396	S6087J	S 6087A	BStCC0153H, TD 3F 800H, TD 4F 800H
55397	S6089	400V, 3A, Igt/Ih<40/<100mA	S 3700D, BTW 27S/400R, T 3S400 MPC
55398	S6090	BC 212	BC 212
55399	S6091	BC 212	BC 212
55400	S6095	400V, 4,7A, Igt/Ih<50/120mA	CSF 0,7-0,4, S 5800D, BT 153
55401	S6098	Igt/Ih<50/<120mA	S 6111
55402	S6100C	2N6403, 300V	2N6403
55403	S6100E	2N6404, 500V	2N6404
55404	S6100S	2N6405, 700V	2N6405
55405	S6111	BC 308	BC 308
55406	S6111	400V, 4A, Igt/Ih<50/<200mA	-
55407	S6117	BC 307	BC 307
55408	S6130	BC 640	BC 640
55409	S6131D	Igt/Ih<60/<30mA	SC 146B, TW 9N400, TIC 236B, MAC 15-4
55410	S6131G	S 6131D, 400V	SC 146D, TW 9N400, TIC 236D, MAC 15-6
55411	S6132A	700V, 3,2A, Igt/Ih<45/<100mA	BStCC0146R, S6087A, TD3F700R, TD4F700R
55412	S6132B	500V, 3,2A, Igt/Ih<30/<100mA	BStCC0133H, S6087B, TD3F500H, TD4F500H
55413	S6134A	700V, 3,2A, Igt/Ih<45/<100mA	S 6080C, BStCC0146R, TD3F700R, TD4F700R
55414	S6134B	500V, 3,2A, Igt/Ih<30/<100mA	TD4F500H
55415	S6146	Igt/Ih<50/100mA	S 6098, S 6111, BStC0726T
55416	S6157	BC 556	BC 556
55417	S6174	BC 307	BC 307
55418	S6175	BC 307	BC 307
55419	S617T	BU 208	BU 208
55420	S6183		-
55421	S6192F	300V, 3A, Igt/Ih<40/<135mA	S 5800C, BT 153, TAG 650S-400
55422	S6192G	S 6192F, 400V	S 5800D, BT 153, TAG 650S-400
55423	S6200A	Igt/Ih<15/<20mA	BStD4026MM, C 232A
55424	S6200B	S 6200A, 200V	BStD4026MM, C 232B
55425	S6200D	S 6200A, 400V	BStD4026MM, C 232D
55426	S6200M	S 6200A, 600V	BStD4040MM, C 232M
55427	S6210	S 6200	BStD41...M, C 230...
55428	S6220	S 6200	C 230...3
55429	S627T	300V, 0,5A, 1W	BF 393, BF 420A, BFP 25, MPSA 42
55430	S628T	S 627T, 350V	2N6517, 2SD1350
55431	S629T	S 627T, 400V	2SD1350
55432	S630T	BU 208A	BU 208A
55433	S637T	-/400V, 15A, 100W, B>100	BUT 51P, 2SC3664
55434	S6400N	2N3870, 800V	MCR 65-10
55435	S6410N	2N3870, 800V	MCR 3935-10, C 35N, 2N5205, TAG 35-800
55436	S6420A	2N3896	2N6171, MCR 65-3
55437	S6420B	2N3897	2N6172, MCR 65-4
55438	S6420D	2N3898	2N6173, MCR 65-6
55439	S6420M	2N3899	2N6174, MCR 65-8

55440	S6420N	2N3899, 800V	MCR 65-10
55441	S6431M	600V, 35A, Igt/Ih<80/<70mA	48/400
55442	S6493M	600V, 35A, Igt/Ih<80/<70mA	48/600
55443	S662T	30V, 20mA, 800MHz	BF 377...378, BF 763, 2SC2570(A)
55444	S668T	BUT 56A	BUT 56A
55445	S671T	BF 871	BF 871
55446	S672T	BF 872	BF 872
55447	S679T	BF 679T	BF 679
55448	S687T	20V, Idss0,5..8mA	BF 960, BF 966, 3SK70, 3SK80
55449	S690T	BFR 90	BFR 90
55450	S691T	BFR 91	BFR 91
55451	S7	FS 2M	FS 2M
55452	S7	HSM 109WK	HSM 109WK
55453	S7	SST 177	SST 177
55454	S7(p)	BF 511	BF 511
55455	S7030	BC 546	BC 546
55456	S7033	BC 168	BC 168
55457	S7040	BC 337	BC 337
55458	S7074	BC 238	BC 238
55459	S7091	BC 182	BC 182
55460	S7100	BC 546	BC 546
55461	S7134	BC 337	BC 337
55462	S7141	BC 546	BC 546
55463	S7150	BC 238	BC 238
55464	S7165	BC 546	BC 546
55465	S7212	BC 337	BC 337
55466	S7213	BC 337	BC 337
55467	S7231	BC 546	BC 546
55468	S7235	BC 182	BC 182
55469	S7239	BC 639	BC 639
55470	S7248	BC 337	BC 337
55471	S7263	BC 238	BC 238
55472	S7310B	Igt/Ih<80/<110mA	T 24F200B, T 24F200C
55473	S7310C	S 7310B, 300V	T 24F400B, T 24F400C
55474	S7310D	S 7310B, 400V	T 24F400B, T 24F400C
55475	S7310E	S 7310B, 500V	T 24F600B, T 24F600C
55476	S7310M	S 7310B, 600V	T 24F600B, T 24F600C
55477	S7310N	S 7310B, 800V	T 24F800B, T 24F800C
55478	S7314	BC 337	BC 337
55479	S7317	BC 337	BC 337
55480	S7502	250V, 0,3A, Igt/Ih<0,2/<5mA	MCR 100-5, BRY 55/300, TAG 70D, TAG 72D
55481	S7503	S 7502, 300V	MCR 100-5, BRY 55/300, TAG 70D, TAG 72D
55482	S779T	BF 779, SMD	-
55483	S790T	BFR 90	BFR 90
55484	S791T	BFR 91	BFR 91



55485	S8	HRW 0703A	HRW 0703A
55486	S8(p)	BF 512	BF 512
55487	S822T	6V, 8mA, 5200MHz	-
55488	S852T	S 822T	BFR 92
55489	S869T	35V, 30mA, 1000MHz	BF 569, BF 579, BF 767
55490	S876T	1200V, 12A, 110W, 7MHz	BUT 76A, BUW 56A, BUW 66A
55491	S879T	BF 779, SMD	BF 569, BF 579, BF 767
55492	S887T	S 687T, SMD	-
55493	S888T	10V, Idss1..12mA	-
55494	S889T	S 888T	BF 960, BF 965, BF 966
55495	S897T	15V, 0,06A, 0,2W, 5GHz	
55496	S9(p)	BF 513	BF 513
55497	S9001	BC 639	BC 639
55498	S9048	BC 546	BC 546
55499	S915T	BU 508A	BU 508A
55500	S920TS	BF 420, 0,46W	BF 420
55501	S921TS	BF 421, 0,46W	BF 421
55502	S922TS	BF 422, 0,46W	BF 422
55503	S923TS	BF 423, 0,46W	BF 423
55504	S979T	BF 979	BF 979
55505	SA	BSS 123	BSS 123
55506	SA	SMBTA 20	SMBTA 20
55507	SA	2SC2982-A	2SC2982
55508	SA	KTC4377-A	KTC 4377
55509	SA-2	1S1916	1S1916
55510	SA-2A	1S1917	1S1917
55511	SA-2B	1S1918	1S1918
55512	SA-2C	1S1919	1S1919
55513	SA-2Z	1S1915	1S1915
55514	SA1015-..	2SA1015-..	2SA1015
55515	SA154	50V, 1A, <150ns	BYM 11-50, BYM 12-50
55516	SA155	SA 154, 100V	BYM 11-100, BYM 12-100
55517	SA156	SA 154, 200V	BYM 11-200, BYM 12-200
55518	SA157	SA 154, 400V	BYM 11-400, BYM 12-400
55519	SA158	SA 154, 600V, <250ns	BYM 11-600
55520	SA159	SA 154, 900V, <500ns	BYM 11-1000
55521	SA160	SA 154, 1000V, <500ns	BYM 11-1000
55522	SA2(sA2)	SMBD 2836	SMBD 2836
55523	SA3(sA3)	SMBD 2835	SMBD 2835
55524	SA4(sA4)	SMBD 2838	SMBD 2838
55525	SA5(A)..170(A)	5..170V, 500W(1ms)	BZW 06/..., BZX 70/..., BZY 93/...
55526	SA5(sA5)	SMBD 2837	SMBD 2837
55527	SA5C(A)..170C(A)		BZW 06/...B
55528	SA733-..	2SA733-..	2SA733
55529	SAs	BSS 123	BSS 123

55530	SAY10	60V, 0,175A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
55531	SAY11	35V, 0,115A, <2ns	BA 318, BAY 38, BAY 95, 1N4148...49
55532	SAY12(B)	75V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
55533	SAY12L2	SAY 12(B)	SAY 12(B)
55534	SAY13	25V, 0,075A, <60ns	BAX 90, BAX 94, BAV 17, 1N4148...49
55535	SAY14	35V, 0,115, <4ns	BA 318, BAY 38, BAY 95, 1N4148...49
55536	SAY15	20V, 0,075A, <4ns	BA 318, BAY 38, BAY 95, 1N4148...49
55537	SAY16(B)	35V, 0,2A, <4ns	BAY 74, BAY 95, 1N4154, 1N4148...49
55538	SAY16L2	SAY 16(B)	SAY 16(B)
55539	SAY17B	60V, 0,115A, <2ns	BAW 62, BAW 76, BAX 95, 1N4148...49
55540	SAY17L2	SAY 17B	SAY 17B
55541	SAY18B	35V, 0,075A, <2ns	BA 318, BAY 38, BAY 95, 1N4148...49
55542	SAY18L2	SAY 18B	SAY 18B
55543	SAY19	25V, 0,075A, <4ns	BA 318, BAY 38, BAY 95, 1N4148...49
55544	SAY20B	20V, 0,075A, <4ns	BA 317, BAY 71, BAY 94, 1N4148...49
55545	SAY20L2	SAY 20B	SAY 20B
55546	SAY30	30V, 0,03A, <65ns	BAX 90, BAX 94, BAV 17, 1N4148...49
55547	SAY32	30V, 0,05A, <65ns	BAX 90, BAX 95, BAV 17, 1N4148...49
55548	SAY40	20V, 0,02A, <10ns	BA 217, BA 317, BAX 87, 1N4148...49
55549	SAY42	20V, 0,03A, <10ns	BA 217, BA 317, BAX 87, 1N4148...49
55550	SAY52	25V, 0,05A, <60ns	-
55551	SAY73	75V, 0,2A, <4ns	BAW 62, BAW 76, BAX 95, 1N4148...49
55552	SB	2SA1121-B	2SA1121
55553	SB	SMBT 2222	SMBT 2222
55554	SB	KTC4377-B	KTC 4377
55555	SB	2SC2982-B	2SC2982
55556	SB-2(B,C)	1S1897..1899	1S1897...1899
55557	SB1100	SB 120, 100V	-
55558	SB120	20V, 1A	BYS 21-45, BYV 10-20, MBR 150, 1N5817
55559	SB130	SB 120, 30V	BYS 21-45, BYV 10-30, MBR 150, 1N5818
55560	SB140	SB 120, 40V	BYS 21-45, BYV 10-40, MBR 150, 1N5819
55561	SB150	SB 120, 50V	BYS 21-90, BYV 10-60, HRP 22, MBR 150
55562	SB160	SB 120, 60V	BYS 21-90, BYV 10-60, HRP 32, MBR 160
55563	SB180	SB 120, 80V	BYS 21-90, HRP 32
55564	SB190	SB 120, 90V	BYS 21-90, HRP 32
55565	SB2100	SB 220, 100V	-
55566	SB220	20V, 2A	BYS 22-45, HRP 24, MBR 320, 1N5820
55567	SB230	SA 220, 30V	BYS 22-45, HRP 24, MBR 330, 1N5821
55568	SB240	SA 220, 40V	BYS 22-45, HRP 24, MBR 340, 1N5822
55569	SB250	SA 220, 50V	BYS 22-90, HRP 34, MBR 350
55570	SB260	SA 220, 60V	BYS 22-90, HRP 34, MBR 360
55571	SB290	SA 220, 90V	BYS 22-90
55572	SB3100	SB 320, 100V	-
55573	SB320	20V, 3A	BYS 26-45, HRP 24, MBR 320, 1N5820
55574	SB330	SB 320, 30V	BYS 26-45, HRP 24, MBR 330, 1N5821

55575	SB340	SB 320, 40V	BYS 26-45, HRP 24, MBR 340, 1N5822
55576	SB350	SB 320, 50V	BYS 26-90, HRP 34, MBR 350
55577	SB360	SB 320, 60V	BYS 26-90, HRP 34, MBR 360
55578	SB380	SB 320, 80V	BYS 26-90
55579	SB390	SB 320, 90V	BYS 26-90
55580	SB5100	SB 520, 100V	-
55581	SB520	20V, 5A	BYS 27-45, 1N5823
55582	SB530	SB 520, 30V	BYS 27-45, 1N5824
55583	SB540	SB 520, 40V	BYS 27-45, 1N5825
55584	SB550	SB 520, 50V	-
55585	SB560	SB 520, 60V	-
55586	SB580	SB 520, 80V	-
55587	SB590	SB 520, 90V	-
55588	SBC119	60V, 0,5A, 0,75W, >40MHz	BC 140...141, BC 300...203, 2N2102
55589	SBD1620..1660T	SBD 1620..1660T	-
55590	M	SBD 3020..3060P/M	-
55591	SBL1030	30V, 10A	BYV 39/30, MBR 1035
55592	SBL1030..1040CT	SBL 1030..1040	BYS 24-45, MBR 2060
55593	SBL1040	SBL 1030, 40A	BYV 39/40, MBR 1045
55594	SBL1630CT	30V, 16A	BYV 33/30, BYV 133/35, MBR 1550
55595	SBL1640CT	SBL 1630, 40V	BYV 33/40, BYV 133/40, MBR 1550
55596	SBL3030PT	30V, 30A(Tc100°)	BYS 28-45, BYV 73/30, MBR 3035PT
55597	SBL3040PT	SBL 3030PT, 40V	BYS 28-45, BYV 73/45, MBR 3045PT
55598	SBL530	30V, 5A	BYV 19/30, MBR 735
55599	SBL530..540CT	SBL 530..540	BYV 18/..., BYV 118/...
55600	SBL540	SBL 530, 40V	BYV 19/40, MBR 745
55601	SBN1020..1045T	SBP 1020..1045T	-
55602	SBN1620..1660T	SBP 1620..1660T	-
55603	SBN2020..2045T	SBP 2020..2045T	-
55604	M	SBP 3020..3060P/M	-
55605	SBP1020T	20V, 10A	BYS 24-45, BYV 33/30, MBR 2060
55606	SBP1030T	SBP 1020T, 30V	BYS 24-45, BYV 33/30, MBR 2060
55607	SBP1035T	SBP 1020T, 35V	BYS 24-45, BYV 33/35, MBR 2060
55608	SBP1040T	SBP 1020T, 40V	BYS 24-45, BYV 33/40, MBR 2060
55609	SBP1045T	SBP 1020T, 45V	BYS 24-45, BYV 33/45, MBR 2060
55610	SBP1620T	20V, 16A	BYV 33/30, BYV 133/35, MBR 1550
55611	SBP1630T	SBP 1620T, 30V	BYV 33/30, BYV 133/35, MBR 1550
55612	SBP1635T	SBP 1620T, 35V	BYV 33/35, BYV 133/35, MBR 1550
55613	SBP1640T	SBP 1620T, 40V	BYV 33/40, BYV 133/40, MBR 1550
55614	SBP1645T	SBP 1620T, 45V	BYV 33/45, BYV 133/45, MBR 1550
55615	SBP1650T	SBP 1620T, 50V	MBR 1550
55616	SBP1660T	SBP 1620T, 60V	MBR 1560
55617	SBP2020T	20V, 20A	BYV 43/30, MBR 2035
55618	SBP2030T	SBP 2020T, 30V	BYV 43/30, MBR 2035
55619	SBP2035T	SBP 2020T, 35V	BYV 43/35, MBR 2035

55620	SBP2040T	SBP 2020T, 40V	BYV 43/40, MBR 2045
55621	SBP2045T	SBP 2020T, 45V	BYV 43/45, MBR 2045
55622	SBP3020..3060M	SBP 3020..3060P	MBR 3020...3045CT
55623	SBP3020P	20V, 30A	BYS 28-45, BYV 73/30, MBR 3020PT
55624	SBP3030P	SBP 3020P, 30V	BYS 28-45, BYV 73/30, MBR 3035PT
55625	SBP3035P	SBP 3020P, 35V	BYS 28-45, BYV 73/35, MBR 3035PT
55626	SBP3040P	SBP 3020P, 40V	BYS 28-45, BYV 73/40, MBR 3045PT
55627	SBP3045P	SBP 3020P, 45V	BYS 28-45, BYV 73/45, MBR 3045PT
55628	SBP3050P	SBP 3020P, 50V	BYS 79-50, MBR 3050PT
55629	SBP3060P	SBP 3020P, 60V	MBR 3060PT
55630	SBR1020..1045T	SBS 1020..1045T	-
55631	SBR1620..1645T	SBS 1620..1645T	-
55632	SBR520..545T	SBS 520..545T	-
55633	SBR820..860T	SBS 820..860T	-
55634	SBs	BSS 145	BSS 145
55635	SBS1020T	20V, 10A	BYV 39/30, MBR 1635
55636	SBS1030T	SBS 1020T, 30V	BYV 39/30, MBR 1635
55637	SBS1035T	SBS 1020T, 35V	BYV 39/35, MBR 1635
55638	SBS1040T	SBS 1020T, 40V	BYV 39/40, MBR 1645
55639	SBS1045T	SBS 1020T, 45V	BYV 39/45, MBR 1645
55640	SBS1620T	20V, 16A	MBR 1635
55641	SBS1630T	SBS 1620T, 30V	MBR 1635
55642	SBS1635T	SBS 1620T, 35V	MBR 1635
55643	SBS1640T	SBS 1620T, 40V	MBR 1645
55644	SBS1645T	SBS 1620T, 45V	MBR 1645
55645	SBS520T	20V, 5A	BYV 19/30, MBR 735
55646	SBS530T	SBS 520T, 30V	BYV 19/30, MBR 735
55647	SBS535T	SBS 520T, 35V	BYV 19/35, MBR 735
55648	SBS540T	SBS 520T, 40V	BYV 19/40, MBR 745
55649	SBS545T	SBS 520T, 45V	BYV 19/45, MBR 745
55650	SBS820T	20V, 8A	BYV 39/30, MBR 1020
55651	SBS830T	SBS 820T, 30V	BYV 39/30, MBR 1035
55652	SBS835T	SBS 820T, 35V	BYV 39/35, MBR 1035
55653	SBS840T	SBS 820T, 40V	BYV 39/40, MBR 1045
55654	SBS845T	SBS 820T, 45V	BYV 39/45, MBR 1045
55655	SBS850T	SBS 820T, 50V	MBR 1050
55656	SBS860T	SBS 820T, 60V	MBR 1060
55657	SC	2SA1121-C	2SA1121
55658	SC	SMBT 2222A	SMBT 2222A
55659	SC	2SC2982-C	2SC2982
55660	SC	KTC4377-C	KTC 4377
55661	SC-15	1S892	1S892
55662	SC-20	1S893	1S893
55663	SC103	-/10V, 0,05A, 0,25W, $\beta > 18$	BC 160...161, BC 303...304, 2N2303
55664	SC104	SC 103, $\beta > 29$	BC 160...161, BC 303...304, 2N2303

55665	SC105	-/6,6V, 0,05A, 0,25W	BC 160...161, BC 303...304, 2N2303
55666	SC106	SC 105, -/10V	BC 160...161, BC 303...304, 2N2303
55667	SC107	SC 105, -/25V	BC 160...161, BC 303...304, 2N2303
55668	SC107[Piher]	BC 107, 0,25W	BC 107
55669	SC108	-/10V, 0,05A, 0,25W	BC 160...161, BC 303...304, 2N2303
55670	SC108[Piher]	BC 108, 0,25W	BC 108
55671	SC109	-/9V, 0,05A, 0,25W	BC 160...161, BC 303...304, 2N2303
55672	SC109[Piher]	BC 109, 0,25W	BC 109
55673	SC110	20V, 0,25A, 0,6W, 40MHz	BC 140...141, BC 300...302, 2N1613
55674	SC111	30V, 0,2A, 0,6W, 60MHz	BC 140...141, BC 300...302, 2N1613
55675	SC112	20V, 0,1A, 0,6W, 60MHz	BC 140...141, BC 300...302, 2N1613
55676	SC116	20V, 0,1A, 0,3W, 90MHz	BC 178, BC 308, BC 558, BC 478
55677	SC117	SC 116, 30V	BC 178, BC 308, BC 558, BC 478
55678	SC118	SC 116, 60V	BC 212, BC 266, BC 556, BC 477
55679	SC119	SC 116, 80V	BC 477, BC 556, 2SA1285(A)
55680	SC136B..F[Nec]	B200V, D	TAG 136-..., TAG 137-...
55681	SC136B[Mot]	200V, 3A, Igt/Ih<25/<50mA	TAG 96B, 2N6071...6075
55682	SC136B[Mot]	200V, 3A, Igt/Ih<25/<50mA	TAG 96B, 2N6071...6075
55683	SC136C	SC 136B, 300V	TAG 96C, 2N6072...6075
55684	SC136C	SC 136B, 300V	TAG 96C, 2N6072...6075
55685	SC136D	SC 136B, 400V	TAG 96D, 2N6073...6075
55686	SC136D	SC 136B, 400V	TAG 96D, 2N6073...6075
55687	SC136E	SC 136B, 500V	TAG 96E, 2N6074...6075
55688	SC136E	SC 136B, 500V	TAG 96E, 2N6074...6075
55689	SC136M	SC 136B, 600V	TAG 96M, 2N6075
55690	SC136M	SC 136B, 600V	TAG 96M, 2N6075
55691	SC141B	200V, 6A, Igt/Ih<50/<50mA	BS7-02A, MAC 216-4, T 2801B, TW 7N400
55692	SC141D	SC 141B, 400V	BS 7-04A,MAC 216-6, T 2801D, TW 7N400
55693	SC141E	SC 141B, 500V	BS 7-05A,MAC 216-7, T 2801E, TW 7N600
55694	SC141M	SC 141B, 600V	BS 7-06A,MAC 216-8, T 2801M, TW 7N600
55695	SC141N	SC 141B, 800V	T 2801N, TW 7N800, BTA 20N, BTA 21N
55696	SC143B	200V, 8A, Igt<50	BT158/400, MAC222-4, T2806B, TIC226B
55697	SC143D	SC 143B, 400V	BT158/400, MAC222-6, T2806D, TIC226D
55698	SC143E	SC 143B, 500V	BT158/600, MAC222-7, T2806E, TIC226E
55699	SC143F	SC 143B, 600V	BT158/600, MAC222-8, T2806M, TIC226M
55700	SC146B	200V, 10A, Igt/Ih<50/<50mA	TXD10K40M, 2N6342...6345, TW 9N400
55701	SC146D	SC 146B, 400V	TXD10K40M, 2N6343...6345, TW 9N400
55702	SC146E	SC 146B, 500V	TXD10K50M, 2N6344...6345, TW 9N600
55703	SC146M	SC 146B, 600V	TXD10K60M, 2N6344...6345, TW 9N600
55704	SC147	BC 147, 0,25W	BC 147
55705	SC148	BC 148, 0,25W	BC 148
55706	SC149	BC 149, 0,25W	BC 149
55707	SC149B	200V, 12A, Igt/Ih<50/<50mA	TIC 236B, TW 11N400, 2N6342...6345A
55708	SC149D	SC 149B, 400V	TIC 236D, TW 11N400, 2N6343...6345A
55709	SC149E	SC 149B, 500V	TIC 236E, TW 11N600, 2N6344...6345A

55710	SC149M	SC 149B, 600V	TIC 236M, TW 11N600, 2N6344...6345A
55711	SC151B	200V, 15A, Igt/Ih<50/<50mA	T 6001B, MAC 15-4, TIC 246B, TXE10L20
55712	SC151D	SC 151B, 400V	T 6001D, MAC 15-6, TIC 246D, TXE10L40
55713	SC151E	SC 151B, 500V	T 6001E, MAC 15-8, TIC 246E, TXE10L60
55714	SC151M	SC 151B, 600V	T 6001M, MAC 15-8, TIC 246M, TXE10L60
55715	SC157	BC 157, 0,25W	BC 157
55716	SC158	BC 158, 0,25W	BC 158
55717	SC159	BC 159, 0,25W	BC 159
55718	SC174	BC 174, 0,25W	BC 174
55719	SC1815..	2SC1815-..	2SC1815
55720	SC206	$\beta > 28$	BC 168, BC 183, BC 238, BC 548
55721	SC207	SC 206, $\beta > 18$	BC 168, BC 183, BC 238, BC 548
55722	SC236	30V, 0,1A, 0,3W, $\beta 56..560$	BC 168, BC 183, BC 238, BC 548
55723	SC237	SC 236, 50V	BC 167, BC 182, BC 237, BC 547
55724	SC238	SC 236, $\beta 56..1120$	BC 168, BC 183, BC 238, BC 548
55725	SC239(s)	SC 236	BC 169, BC 184, BC 239, BC 549
55726	SC245B	200V, 10A, Igt/Ih<50/<50mA	BS 10-02A, TXD 99A20, T 4110E, T4111E
55727	SC245B...M3	SC 245B..M	T 4120..., SC 250...3, SC 260...3, T 6421...
55728	SC245D	SC 245B, 400V	BS 10-04A, TXD99A40, T 4110E, T 4111E
55729	SC245E	SC 245B, 500V	BS 10-05A, TXD99A50, T 4110E, T 4111E
55730	SC245M	SC 245B, 600V	BS 10-06A, TXD99A60, T 4110M, T 4111M
55731	SC246B...M	SC 245B..M	BS 10..., TW 10N...H, T 4100..., TW 12N...H
55732	SC250B	200V, 15A, Igt/Ih<50/<50mA	TXD 98A20, TW 18N400, TXE 99A20
55733	SC250B...M3	SC 250B..M	SC 260...3, T 6421..., 2N6163...6165
55734	SC250D	SC 250B, 400V	TXD 98A40, TW 18N400, TXE 99A40
55735	SC250E	SC 250B, 500V	TXD 98A50, TW 18N500, TXE 99A50
55736	SC250M	SC 250B, 600V	TXD 98A60, TW 18N600, TXE 99A60
55737	SC251B...M	SC 250B..M	SC 261..., T 6405..., 2N6157...6159
55738	SC256	BC 256, 0,25W	BC 256
55739	SC257	BC 257, 0,25W	BC 257
55740	SC258	BC 258, 0,25W	BC 258
55741	SC259	BC 259, 0,25W	BC 259
55742	SC260B	200V, 25A, Igt/Ih<50/<75mA	TXE 99A20, T 6411B, 2N6160...6162
55743	SC260B...M3	SC 260B..M	T 6421..., 2N6163...6165, T 6420...
55744	SC260D	SC 260B, 400V	TXE 99A40, T 6411D, 2N6161...6162
55745	SC260E	SC 260B, 500V	TXE 99A50, T 6411E, 2N6162
55746	SC260M	SC 260B, 600V	TXE 99A60, T 6411M, 2N6162
55747	SC261B...M	SC 260B..M	2N6157...6159, T 6400..., 2N5441...5443
55748	SC3	SMBT 4126	SMBT 4126
55749	SC307	50V, 0,1A, 0,25W, 300MHz	BC 212, BC 257, BC 307, BC 557
55750	SC308	SC 307, 30V	BC 213, BC 258, BC 308, BC 558
55751	SC309	SC 307	BC 214, BC 259, BC 309, BC 559
55752	SC945-..	2SC945-..	2SC945
55753	SCC321	-/60V, 10A, 100W	BD 313, BD 315, BD 317, BD 745B...D
55754	SCC421	-/60V, 10A, 100W	BD 314, BD 316, BD 318, BD 746B...D



55755	SCE237	SC 237, SMD	BC 846...847, BCW 71...72, BCW 81
55756	SCE238	SC 238, SMD	BC 846...848, BCW 31...33, BCW 81
55757	SCE239	SC 239, SMD	BC 849...850, BCF 32...33, BCF 81
55758	SCE307	SC 307, SMD	BC 856...857, BCW 69...70, BCW 89
55759	SCE308	SC 308, SMD	BC 856...858, BCW 29...30, BCW 61
55760	SCE309	SC 309, SMD	BC 859...860, BCF 29...30, BCF 70
55761	SCE535	45V, 1A, >50MHz	-
55762	SCE536	45V, 1A, >50MHz	-
55763	SCE537	SCE 535, 60V	-
55764	SCE538	SCE 536, 60V	-
55765	SCE539	SCE 535, 100V	-
55766	SCE540	SCE 536, 100V	-
55767	SCX	KSC2881	KSC2881
55768	SCZ	SMBT 4124	SMBT 4124
55769	SD	BSS 145	BSS 145
55770	SD	SMBT 2907	SMBT 2907
55771	SD	2SA1121-D	2SA1121
55772	SD	KTC4377-D	KTC 4377
55773	SD	2SC2982-D	2SC2982
55774	1(A..Z)[Sanken]	100..1000V, 0,5A	BA 157...159, BY 204/..., BY 208/...
55775	SD-1[Fujitsu]	600V, 0,375A	BA 158...159, BY 204/..., BY 208/...
55776	SD1...200	ZY 1..200	BZD 23/..., BZX70/...
55777	SD100	20V, 3A, 62W, 15MHz	BD 245, BDV 91, BDX 91, 2N3055
55778	SD101	30V, 3A, 62W, 15MHz	BD 245, BDV 91, BDX 91, 2N3055
55779	SD102	50V, 3A, 62W, 15MHz	BD 245, BDV 91, BDX 91, 2N3055
55780	SD112	BA 102	BA 102
55781	SD113	35..55pF(0V)	FC 52M...53M
55782	SD114		
55783	SD115	10..16pf(4V)	FC 54M
55784	SD116	6..12pF(4V)	FC 54M
55785	SD117	4..8pF(4V)	FC 54M
55786	SD168	-/300V, 3A, 12,5W(Tc95°)	BU 126, BU 326, BUW 11(A), BUX 45...46
55787	SD20	30V, 0,03A	BA 127, BA 147/50, BAY 18, 1N4148...49
55788	SD21	80V, 0,2A	1N270
55789	SD210DE	1,1/8ns	-
55790	SD211DE	SD 210DE, -25+30/30/+25-30V	-
55791	SD212DE	SD 210DE, +-40/10/+40V	-
55792	SD213DE	SD 210DE, -25+15/10/+25-15V	-
55793	SD214DE	SD 210DE, +-40/20/+40V	-
55794	SD215DE	SD 210DE, -30+25/20/+30-25V	-
55795	SD21A	80V, 0,2A	AA 136
55796	SD241	45V, 30A	MBR 3045CT
55797	SD241F	SD 241	BYS 28-45, MBR 3045PT
55798	SD335	45V, 1,5A, 12,5W, 210MHz	BD 135, BD 226, BD 375, 2SD1177...78
55799	SD336	45V, 1,5A, 12,5W, 210MHz	BD 136, BD 227, BD 376, 2SB874...75

55800	SD337	SD 335, 60V	BD 137, BD 228, BD 377, 2SD1177...78
55801	SD338	SD 336, 60V	BD 138, BD 229, BD 378, 2SB874...75
55802	SD339	SD 335, 80V	BD 139, BD 230, BD 379, 2SD1177...78
55803	SD34	75V, 30mA	AA 117...118, AA 132...133
55804	SD340	SD 336, 80V	BD 140, BD 231, BD 380, 2SB874...75
55805	SD345	45V, 3A, 20W, >60MHz	BD 785, BDX 35...37, MJE 240...244
55806	SD346	45V, 3A, 20W, >60MHz	BD 786, MJE 250...254
55807	SD347	SD 345, 60V	BD 785, BDX 35...37, MJE 240...244
55808	SD348	SD 346, 60V	BD 786, MJE 250...254
55809	SD349	SD 345, 80V	BD 789, BDX 35...37, MJE 240...244
55810	SD350	SD 346, 80V	BD 790, MJE 250...254
55811	SD38	120V, 30mA	AA 133
55812	SD4	1N4148	1N4148
55813	SD401	45V, 10A, 90W	BD 705, BD 805, BD 743, BDT 91
55814	SD402	45V, 10A, 90W	BD 706, BD 806, BD 744, BDT 92
55815	SD403	SD 401, 60V	BD 707, BD 807, BD 743A, BDT 91
55816	SD404	SD 402, 60V	BD 708, BD 808, BD 744A, BDT 92
55817	SD405	SD 401, 80V	BD 709, BD 809, BD 743B, BDT 93
55818	SD406	SD 402, 80V	BD 710, BD 810, BD 744B, BDT 94
55819	SD407	SD 401, 100V	BD 711, BD 911, BD 743C, BDT 95
55820	SD408	SD 402, 100V	BD 712, BD 912, BD 744C, BDT 96
55821	SD409	SD 401, 120V	BD 743D, BDT 87
55822	SD41	45V, 30A	BYS 30, BYS 31-50, BYS 32
55823	SD410	SD 402, 120V	BD 744D, BDT 88
55824	SD451	45V, 10A, 90W, B>1000	BDT 63, BDT 65, BDW 93, BDX 33
55825	SD452	45V, 10A, 90W, B>1000	BDT 62, BDT 64, BDW 94, BDX 34
55826	SD453	SD 451, 60V	BDT 63, BDT 65, BDW 93A, BDX 33A
55827	SD454	SD 452, 60V	BDT 62, BDT 64, BDW 94A, BDX 34A
55828	SD455	SD 451, 80V	BDT 63A, BDT 65A, BDW 93B, BDX 33B
55829	SD456	SD 452, 80V	BDT 62A, BDT 64A, BDW 94B, BDX 34B
55830	SD457	SD 451, 100V	BDT 63B, BDT 65B, BDW 93C, BDX 33C
55831	SD458	SD 452, 100V	BDT 62B, BDT 64B, BDW 94C, BDX 34C
55832	SD459	SD 451, 120V	BDT 63C, BDT 65C, BDX 33D
55833	SD46	60V, 30mA	AA 117...118, AA 132...134
55834	SD460	SD 452, 120V	BDT 62C, BDT 64C, BDX 34D
55835	SD51	45V, 60A	BYS 50, BYS 60-45, MBR 6045
55836	SD54	75V, 30mA	AA 117...118, AA 132...133
55837	SD56	50V, 40mA	AA 117...118, AA 132...134, 1N34, 1N54
55838	SD60	50V, 30mA	1N60
55839	SD600	120/80V, 3A, 10W(Tc80°)	BUW 86...87, BUX 16(A)
55840	SD601	60/50V, 3A, 10W(Tc80°)	BUW 86...87, BUX 16(A)
55841	SD602	120/80V, 3A, 10W(Tc80°)	BUW 86...87, BUX 16(A)
55842	SD802	150/100V, 5A, 50W	BUW 86...87, BUX 16(A)
55843	SD812	500/200V, 4A, 50W	BU 326, BU 426(A), BU 526, BUX 45
55844	SDF2060	TIS 88A	TIS 88A

55845	SDX	KSA1201	KSA1201
55846	SE	SMBT 2907A	SMBT 2907A
55847	SE1001	350MHz	BF 199, BF 224, BF 311, BF 373, BF 597
55848	SE1002	350MHz	BF 199, BF 224, BF 311, BF 373, BF 597
55849	SE1010	>200MHz	BF 240...241, BF 254...255, BF 594...595
55850	SE20	BY 251	BY 251
55851	SE2001	B>40	BC 168, BC 183, BC 238, BC 548
55852	SE2002	SE 2001, B>100	BC 168, BC 183, BC 238, BC 548
55853	SE299T	BF 255	BF 255
55854	SE30	1N4001	1N4001
55855	SE3001	900MHz	BF 377...378, BF 689, BF 763, 2N2857
55856	SE3002	900MHz	BF 377...378, BF 689, BF 763, 2N2857
55857	SE3005	>800MHz	BF 377...378, BF 689, BF 763, 2N2857
55858	SE300T	BF 254	BF 254
55859	SE3030	100MHz	BDX 11, 2N3442, 2SD733, 2SD1047
55860	SE3031	100MHz	BDX 11, 2N3442, 2SD733, 2SD1047
55861	SE3032	100MHz	BD 245A...C, BD 311, BDV 93, BDW 21A...C
55862	SE3033	100MHz	BD 245A...C, BD 311, BDV 93, BDW 21A...C
55863	SE3035	40V, 20W(Tc50°)	BD 245A...C, BD 311, BDV 93, BDW 21A...C
55864	SE3036	40V, 15W(Tc75°)	BD 245A...C, BD 311, BDV 93, BDW 21A...C
55865	SE3040	80V, 5A, 15W(Tc75°), 120MHz	BDV 10...12, 2N4233A, 2SC3253, 2SD284
55866	SE3041	SE 3040, 120V	BDV 10...12, BDW 25, 2SD284, 2SD772
55867	SE3100	800MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55868	SE3646	2N3646	
55869	SE4001	B>60	BC 168, BC 183, BC 238, BC 548
55870	SE4002	SE 4001, >60MHz, B>200	BC 168, BC 183, BC 237, BC 548
55871	SE4010	30V, 0.1A, 0.2W, >300MHz	BC 169, BC 184, BC 239, BC 549, 2SC2675
55872	SE4020	60V, 0.05A, 0.2W, 200MHz	BC 174, BC 182, BC 190, BC 546
55873	SE4021	SE 4020, 45V, 260MHz	BC 167, BC 182, BC 237, BC 547
55874	SE4022	SE 4020, 30V,	BC 169, BC 184, BC 239, BC 549
55875	SE4172	20V, 0.31W, >40MHz	BC 168, BC 183, BC 238, BC 548
55876	SE4401	25V, Idss>1mA, Up<8V	BF 244, BF 245, BFW 61, 2N3819
55877	SE5001	>400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55878	SE5002	>400MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55879	SE5003	>400MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55880	SE5006	>400MHz	BF 240, BF 255, BF 495, BF 595
55881	SE5010	500MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55882	SE5015	450MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55883	SE5020	>375MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55884	SE5021	>375MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55885	SE5022	>300MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55886	SE5023	>300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55887	SE5024	>300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55888	SE5029	35V, >500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
55889	SE5030(A,B)	45V, >600MHz	BF 199, BF 224, BF 311, BF 373, BF 597

55890	SE5031	40V, >500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
55891	SE5032	40V, >500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
55892	SE5035	40V, 1000MHz	BF 180...183, BF 689, BF 763, 2N918
55893	SE5036	35V, 800MHz	BF 180...183, BF 689, BF 763, 2N918
55894	SE5037	45V, >600MHz	BF 180...183, BF 689, BF 763, 2N918
55895	SE5040	30V, 25mA, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55896	SE5050	20V, 10mA, >300MHz	BF 240, BF 255, BF 495, BF 595
55897	SE5051	20V, 10mA, >300MHz	BF 240, BF 255, BF 495, BF 595
55898	SE5052	20V, 10mA, >375MHz	BF 225, BF 314, BF 496, BF 502, BF 505
55899	SE5055	20V, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55900	SE5056	20V, >300MHz	BF 198, BF 225, BF 310, BF 367, BF 596
55901	SE6001	40V, 0,3W, >40MHz, B>50	BC 167, BC 183, BC 237, BC 547
55902	SE6002	SE 6001, B>150	BC 167, BC 183, BC 237, BC 547
55903	SE6010	-/30V, 0,35W, >250MHz	BC 167, BC 182, BC 237, BC 547
55904	SE6020(A)	60V, 1A, 0,3..0,5W, >250MHz	BC 637, BC 639, 2SD667
55905	SE6021(A)	SE 6020, 80V	BC 639, 2SD667
55906	SE6022	60V, 1A, 0,22W, >250MHz	BC 637, BC 639, 2SD667
55907	SE6023	SE 6022, 80V	BC 639, 2SD667
55908	SE6062	25V, 1A, 0,75W, >60MHz	BC 337...338, BC 635, BC 637, BC 639
55909	SE6063	SE 6062, 20V	BC 337...338, BC 635, BC 637, BC 639
55910	SE6562	25V, 0,6A, 0,75W, >60MHz	BC 327...328, BC 636, BC 638, BC 640
55911	SE6563	SE 6562, 20V	BC 327...328, BC 636, BC 638, BC 640
55912	SE7001	150V, 0,1A, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...5059
55913	SE7002	SE 7001, 120V	BF 257...259, BF 657...659, 2N5058...5059
55914	SE7005	150V, 0,5A, 5W, 60MHz	BF 380...382, BF 757...759, MPSU 10
55915	SE7006	SE 7005, 12W	2SC1913(A), 2SC2591...2592
55916	SE7010	150V, 0,05A, 0,8W, >40MHz	BF 257...259, BF 657...659, 2N5058...5059
55917	SE7015	100V, 0,05A, 0,45W, >50MHz	BF 257...259, BF 657...659, 2N5058...5059
55918	SE7016	SE 7015, 140V	BF 257...259, BF 657...659, 2N5058...5059
55919	SE7017	SE 7015, 180V	BF 258...259, BF 658...659, 2N5058...5059
55920	SE7020	300V, 0,4A, 10W, 30MHz	2SC1929, 2SD1263(A)
55921	SE7030	300V, 0,4A, 10W, >30MHz	2SC1929, 2SD1263(A)
55922	SE7055	220V, 0,03A, 1W, >50MHz	BF 258...259, BF 658...659, 2N5058...5059
55923	SE7056	SE 7055, 300V	BF 259, BF 659, BFS 89, 2N5058
55924	SE7057	SE 7055, 450V	2SD593, MJE 3439
55925	SE7066	-/300V, 40MHz	-
55926	SE8001	60V, 1A, 0,8W, >40MHz	BC 140...141, BCX 40, 2N1990, 2N2102
55927	SE8002	SE 8001, 80V	BC 140...141, BCX 40, 2N1990, 2N2102
55928	SE8010	100V, 0,5A, >300MHz	-
55929	SE8012	100V, 0,5A, >300MHz	-
55930	SE8040	30V, 1A, 0,5W, >130MHz	BC 140...141, BCX 40, 2N1990, 2N2102
55931	SE8041	SE 8040, 0,8W	BC 140...141, BCX 40, 2N1990, 2N2102
55932	SE8042	SE 8040, 1W	BC 140...141, BCX 40, 2N1990, 2N2102
55933	SE8510	60V, 0,6A, 0,8W, >100MHz	BC 161, BC 303...304, BC 361, BCX 60
55934	SE8520	B>40	BC 161, BC 460...461, BCX 60

55935	SE8521	SE 8520, B>100	BC 161, BC 460...461, BCX 60
55936	SE8540	30V, 1A, 0,5W, >100MHz	BC 160...161, BC 460...461, BCX 60
55937	SE8541	SE 8540, 0,8W	BC 160...161, BC 460...461, BCX 60
55938	SE8542	SE 8540, 1W	BC 160...161, BC 460...461, BCX 60
55939	SE9020	400V, 7A, 62W, 70MHz	BUX 18B,C,S, BUX 43...44, 2SC2305
55940	SE9051	-/275V, 10A, 50W, >20MHz	BUV 28, BUY 65, 2SC3057, 2SC3562
55941	SE9052	SE 9051, -/325V	BUV 28, BUY 65, 2SC3057, 2SC3562
55942	SE9060	80V, 2A, 20W(Tc45°), >50MHz	BDV 10...12, 2SC1398, 2SC2528...2529
55943	SE9061	SE 9060, >60MHz	BDV 10...12, 2SC1398, 2SC2528...2529
55944	SE9062	SE 9060, 100V	BDV 10...12, 2SC2528...2529
55945	SE9063	SE 9060, 100V, >60MHz	BDV 10...12, 2SC2528...2529
55946	SE9300	60V, 10A, 70W, B>100	BDT 63, BDT 65, BDW 93A, BDX 33A
55947	SE9301	SE 9300, 80V	BDT 63A, BDT 65A, BDW 93B, BDX 33B
55948	SE9302	SE 9300, 100V	BDT 63B, BDT 65B, BDW 93C, BDX 33C
55949	SE9303	SE 9300, 100W	BDV 65, BDX 83A, BDX 85A, MJ 3000
55950	SE9304	SE 9301, 100W	BDV 65A, BDX 83B, BDX 85B, MJ 3001
55951	SE9305	SE 9302, 100W	BDV 65B, BDX 83C, BDX 85C, 2SD628...629
55952	SE9331	-/300V, 1A, 20W, >10MHz	BUW 40(A,B), TIP 48...50, 2N4298...99
55953	SE9400	60V, 10A, 70W, B>100	BDT 62, BDT 64, BDW 94A, BDX 34A
55954	SE9401	SE 9400, 80V	BDT 62A, BDT 64A, BDW 94B, BDX 34B
55955	SE9402	SE 9400, 100V	BDT 62B, BDT 64B, BDW 94C, BDX 34C
55956	SE9404	SE 9401, 100W	BDV 64A, BDX 84B, BDX 86B, MJ 2901
55957	SE9405	SE 9401, 100W	BDV 64B, BDX 84C, BDX 86C, 2SB638...639
55958	SE9560	80V, 2A, 20W(Tc45°), >50MHz	2SA748, 2SA1078...1079, 2SA1288
55959	SE9561	SE 9560, >60MHz	2SA748, 2SA1078...1079, 2SA1288
55960	SE9562	SE 9560, 100V	2SA1078...1079, 2SA1288, 2SA1133
55961	SE9563	SE 9560, 100V, >60MHz	2SA1078...1079, 2SA1288, 2SA1133
55962	SE9570	80V, 2A, 25W(Tc45°), >50MHz	2SA1141, 2SA1146, 2SA1186
55963	SE9571	SE 6570, >60MHz	2SA1141, 2SA1146, 2SA1186
55964	SE9572	SE 6570, 100V	2SA1141, 2SA1146, 2SA1186
55965	SE9573	SE 6570, 100V, >60MHz	2SA1141, 2SA1146, 2SA1186
55966	SEL1		
55967	SES3705	45V, 0,2A, 0,3W, 200MHz	BC 167, BC 182, BC 237, BC 547
55968	SES3819	2N3819	
55969	SF	BB 804	BB 804
55970	SF	SMBTA 13	SMBTA 13
55971	SF	U 1FWJ49	U 1FWJ49
55972	SF-1	1500V, 0,03A, <300ns	BY 584, BY 614
55973	SF0	BB 804 0	BB 804 0
55974	SF016	75V, 0,6A, 0,6W, 50MHz	BC 160...161, BSW 40, 2N4031, 2N4033
55975	SF018	75V, 0,6A, 0,6W, 60MHz	BC 160...161, BSW 40, 2N4031, 2N4033
55976	SFOR1B41	<0,2/5mA	MCR 100-..., BRY 55/..., TAG 70...
55977	SFOR1B42..G42	<0,2/3mA	MCR 100-..., BRY 55/..., TAG 70...
55978	SFOR1D41	SF 0R1B41, 200V	MCR 100-..., BRY 55/..., TAG 70...
55979	SFOR1G41	SF 0R1B41, 400V	MCR 100-..., BRY 55/..., TAG 70...

55980	SFOR3B42	<0,2/4mA	MCR 100-..., BRY 55/..., TAG 70...
55981	SFOR3D42	SF 0R3B42, 200V	MCR 100-..., BRY 55/..., TAG 70...
55982	SFOR3G42	SF 0R3B42, 400V	MCR 100-..., BRY 55/..., TAG 70...
55983	SFOR3J42	SF 0R3B42, 600V	MCR 100-..., BRY 55/..., TAG 70...
55984	SF1	BB 804 1	BB 804 1
55985	SF10B14	<27/60mA	2N4101, TAG 676-...
55986	SF10D14	SF 10B14, 200V	2N4101, TAG 676-...
55987	SF10G14	SF 10B14, 400V	2N4101, TAG 676-...
55988	SF115(A...E)	270MHz	BF 240, BF 255, BF 495, BF 595
55989	SF116	20V, 0,5A, 0,5W, >60MHz	BC 160...161, BSW 23, 2N2904...05(A)
55990	SF117	SF 116, 30V	BC 160...161, BSW 23, 2N2904...05(A)
55991	SF118	SF 116, 60V	BC 161, BSW 23, BSW 40, 2N2904...05(A)
55992	SF119	SF 116, 80V	BC 303, BSW 40, 2N4031, 2N4033, 2N4036
55993	SF121	20V, 0,1A, 0,6W, 130MHz	BC 168, BC 183, BC 238, BC 548
55994	SF122	SF 121, 33V	BC 168, BC 183, BC 238, BC 548
55995	SF123	SF 121, 66V	BC 174, BC 182, BC 190, BC 546
55996	SF126	33V, 0,5A, 0,6W, >60MHz	BC 140...141, BSW 51...52, 2N2218...19(A)
55997	SF127	SF 126, 66V	BC 140...141, BSW 51...52, 2N2218...19(A)
55998	SF128	SF 126, 100V	BC 141, BC 300, BSW 39, 2N1889...90
55999	SF129	SF 126, 120V	BC 300, 2N1893(A), 2N2102, 2N2405
56000	SF131	20V, 0,05A, 450MHz, 195/500ns	BF 240...241, BF 254...255, 2N914
56001	SF132	40V, 0,05A, 450MHz, 195/500ns	BF 240...241, BF 254...255, 2N914
56002	SF136	20V, 0,2A, 0,3W, >300MHz	BC 548, BSW 41, BSY 62, 2N708, 2N4123
56003	SF137	SF 136, 40V	BC 547, BSW 41, BSY 63, 2N708, 2N4123
56004	SF138	40V, 0,2A, 0,3W, 200MHz	BC 167, BC 183, BC 237, BC 547
56005	SF140	40V, 25mA, 350MHz	BF 199, BF 224, BF 311, BF 373, BF 596
56006	SF150	160V, 0,05A, 0,68W, >60MHz	BF 257...259, BF 657...659, 2N5058...5059
56007	SF166	500MHz	BF 225, BF 314, BF 496, BF 502, BF 505
56008	SF167	BF 167	
56009	SF16B14	<40/50mA	2N4103
56010	SF16D14	SF 16B14, 200V	2N4103
56011	SF16G14	SF 16B14, 400V	2N4103
56012	SF173	BF 173	
56013	SF180	BF 180	
56014	SF181	BF 181	
56015	SF194(B)	BF 194	
56016	SF195(C,D)	BF 195	
56017	SF196	BF 196	
56018	SF197	BF 197	
56019	SF1B12	100V, 1A, Igt/Ih <1/10mA	TAG 2-..., TAG 614-...
56020	SF1D12	SF 1B12, 200V	TAG 2-..., TAG 614-...
56021	SF1G12	SF 1B12, 400V	TAG 2-..., TAG 614-...
56022	SF1R3...	Igt/Ih<0,2/<10mA	C 106-..., TAG 106-...
56023	SF2	BB 804 2	BB 804 2
56024	SF200	BF 200	



56025	SF215	>100MHz	BF 240...241, BF 254...255, BF 594...595
56026	SF216	>100MHz	BF 240...241, BF 254...255, BF 594...595
56027	SF223	BF 223	
56028	SF225	500MHz	BF 240...241, BF 254...255, BF 594...595
56029	SF235	740MHz	BF 225, BF 314, BF 496, BF 502, BF 505
56030	SF240	430MHz	BF 198, BF 225, BF 310, BF 367, BF 596
56031	SF245	960MHz	BF 199, BF 224, BF 311, BF 373, BF 597
56032	SF294(B)	BF 194	
56033	SF295(C,D)	BF 195	
56034	SF2B41	<0,2/3mA	TIC 106..., TAG 623-..., TAG 633-...
56035	SF2D41	SF 2B41, 200V	TIC 106..., TAG 623-..., TAG 633-...
56036	SF2G41	SF 2B41, 400V	TIC 106..., TAG 623-..., TAG 633-...
56037	SF2J41	SF 2B41, 600V	TIC 106..., TAG 623-..., TAG 633-...
56038	SF3	BB 804 3	BB 804 3
56039	SF310	BF 310	
56040	SF314	BF 314	
56041	SF334(B)	BF 334	
56042	SF335(C,D)	BF 335	
56043	SF357	160V, 0,1A, 6W(Tc90°)	BF 457...459, BF 415, BF 417
56044	SF358	SF 357, 250V	BF 458...459, BF 415, BF 417
56045	SF359	SF 357, 300V	BF 459, BF 417
56046	SF369	250V, 0,03A, 2W(Tc110°)	BF 458...459, BF 415, BF 417, BF 469
56047	SF3B14	<25/30mA	2N4101, BStC05..., TAG 671-..., TAG 676-...
56048	SF3B41	<40/60mA	BT 152/...
56049	SF3D14	SF 3B14, 200V	2N4101, BStC05..., TAG 671-..., TAG 676-...
56050	SF3D41	SF 3B41, 200V	BT 152/...
56051	SF3G14	SF 3B14, 400V	2N4101, BStC05..., TAG 671-..., TAG 676-...
56052	SF3G41	SF 3B41, 400V	BT 152/...
56053	SF3J41	SF 3B41, 600V	BT 152/...
56054	SF4	BB 804 4	BB 804 4
56055	SF5528	BF 245	BF 245
56056	SF5B14	<27/30mA	BStC05..., TAG 671-..., TAG 676-...
56057	SF5B41	<40/60mA	BStD10..., BStD16..., BStD10...M, BT 152/...
56058	SF5D14	SF 5B14, 200V	BStC05..., TAG 671-..., TAG 676-...
56059	SF5D41	SF 5B41, 200V	BStD10..., BStD16..., BStD10...M, BT 152/...
56060	SF5G14	SF 5B14, 400V	BStC05..., TAG 671-..., TAG 676-...
56061	SF5G41	SF 5B41, 400V	BStD10..., BStD16..., BStD10...M, BT 152/...
56062	SF5J41	SF 5B41, 600V	BStD10..., BStD16..., BStD10...M, BT 152/...
56063	SF816	SF 116, 0,735W	BC 327...328, BC 636, BC 638, BC 640
56064	SF817	SF 117, 0,735W	BC 327...328, BC 636, BC 638, BC 640
56065	SF818	SF 118, 0,735W	BC 327A, BC 638, BC 640, 2SB116(A)
56066	SF819	SF 119, 0,735W	BC 640, 2SB647, 2SB910, 2SB116A
56067	SF826	SF 126, 0,735W	BC 337...338, BC 635, BC 637, BC 639
56068	SF827	SF 127, 0,735W	BC 337A, BC 637, BC 639, 2SD1226
56069	SF828	SF 128, 0,735W	BC 639, 2SD667, 2SD774, 2SD1768

56070	SF829	SF 129, 0,735W	2N3700...3701, 2SD667, 2SD1616A
56071	SF8B41	<40/60mA	BStD10..., BStD16..., BStD10...M, BT 152/...
56072	SF8D41	SF 8B41, 200V	BStD10..., BStD16..., BStD10...M, BT 152/...
56073	SF8G41	SF 8B41, 400V	BStD10..., BStD16..., BStD10...M, BT 152/...
56074	SF8J41	SF 8B41, 600V	BStD10..., BStD16..., BStD10...M, BT 152/...
56075	SFD021	20V, 50mA, <300ns	AA Y 27...28
56076	SFD037(A)	15..30V, 30..60mA	AA Y 27...28, 1N43, 1N54, 1N60
56077	SFD104	30V, 30mA	AA 114, AA 116, 1N60
56078	SFD105	30V, 30mA, <160ns	AA Y 27, 1N3592
56079	SFD106	30V, 30mA	AA 114, AA 116, 1N60
56080	SFD107	15V, 20mA	AA 112, AA 114, AA 116, 1N60
56081	SFD108(A,B,BL)	115V, 30mA	AA 117...118, AA 132...133
56082	SFD111	24V, 30mA	AA 113, AA 119, 1N34, 1N54, 1N60
56083	SFD112	40V, 20mA	AA 114, AA 116, 1N60
56084	SFD117	1N147A	1N147A
56085	SFD118(A)	12V, 20..30mA, <6ns	AA Y 21, AA Y 48
56086	SFD119	30V, 30mA	AA 134, AA Y 27, 1N34, 1N54, 1N60
56087	SFD121	15V, 30mA, <400ns	AA 134, AA Y 49, 1N34, 1N54, 1N60
56088	SFD122	30V, 50mA, <400ns	AA 134, AA Y 49, 1N34, 1N54, 1N60
56089	SFD125	100V, 100mA	AA Z 18, 1N270
56090	SFD127	30V, 100mA	AA 135...136, AA Z 18, 1N270
56091	SFD129(A,B)	40V, 150..200mA, <400..500ns	AA 136, AA Y 49, AA Z 15, AA Z 17, 1N270
56092	SFD130	30V, 150mA, <400ns	AA 135...136, AA Y 49, AA Z 15, AA Z 17
56093	SFD135	100V, 150mA	AA Z 15, 1N270
56094	SFD143	70V, 0,075A, <4ns	BA W 62, BA W 76, BA X 95, 1N4148...49
56095	SFD145	50V, 0,2A, <10ns	BA 204, BA W 53, 1N3600, 1N4148...48
56096	SFD180	50V, 0,08A	BA 127, BA 147/50, BA Y 18, 1N4148...49
56097	SFD181	SFD 180, 150V	BA 189...190, BA 147/150, 1N5606...07
56098	SFD183	SFD 143	SFD 143
56099	SFD184	50V, 0,075A	BA 127, BA 147/50, BA Y 18, 1N4148...49
56100	SFD185	SFD 145	SFD 145
56101	SFD186	120V, 0,2A	BA 176, BA 157...159, BA Y 208/...
56102	SFD43	30V, 0,075A, <4ns	BA 217, BA 317, BA Y 71, 1N4148...49
56103	SFD44	30V, 0,075A, <4ns	BA 217, BA 317, BA Y 71, 1N4148...49
56104	SFD46	150V, 0,1A, <75ns	BA 195...198, BA V 20...21, BA Y 80, 1N3070
56105	SFD49	220V, 0,2A, <75ns	BA 198, BA V 21, (BA 157...159
56106	SFD78	1N4148	1N4148
56107	SFD83	SFD 43	SFD 43
56108	SFD84	SFD 44	SFD 44
56109	SFD86	SFD 46	SFD 46
56110	SFD88	BA 157	BA 157
56111	SFD89	SFD 49	SFD 49
56112	SFD95	300V, 0,1A, <50ns	BA 157...159, BA 245, BA Y 206...207
56113	SFE1A..H	FE 1A..H, SMD	BYM 12-...
56114	SFE225	40V, 25mA, 390MHz	BF 799, BF S 20, 2SC3015, 2SC3374

56115	SFE235	40V, 25mA, 750MHz	BF 799, BFS 20, 2SC3015, 2SC3374
56116	SFE245	40V, 25mA, 910MHz	BF 517, BFS 17, 2SC3016, 2SC3161
56117	SFE569	250V, 0,05A, >60MHz	BFN 16, BFN 18, 2SC3380, 2SC4189
56118	SFE570	250V, 0,05A, >60MHz	BFN 17, BFN 19, 2SA1384
56119	SFR151	100V, 0,75A	BY 126...127, BY 133...135, 1N4002...07
56120	SFR152	SFR 151, 200V	BY 126...127, BY 133...134, 1N4003...07
56121	SFR153	SFR 151, 300V	BY 126...127, BY 133...134, 1N4004...07
56122	SFR154	SFR 151, 400V	BY 126...127, BY 133...134, 1N4004...07
56123	SFR155	SFR 151, 500V	BY 126...127, BY 133...134, 1N4005...07
56124	SFR156	SFR 151, 600V	BY 126...127, BY 133...134, 1N4005...07
56125	SFR164	400V, 0,75A	BY 126...127, BY 133...134, 1N4004...07
56126	SFR250	50V, 1A	BY 126...127, BY 133...135, 1N4001...07
56127	SFR251	SFR 250, 100V	BY 126...127, BY 133...135, 1N4002...07
56128	SFR252	SFR 250, 200V	BY 126...127, BY 133...134, 1N4003...07
56129	SFR253	SFR 250, 300V	BY 126...127, BY 133...134, 1N4004...07
56130	SFR254	SFR 250, 400V	BY 126...127, BY 133...134, 1N4004...07
56131	SFR255	SFR 250, 500V	BY 126...127, BY 133...134, 1N4005...07
56132	SFR256	SFR 250, 600V	BY 126...127, BY 133...134, 1N4005...07
56133	SFR257	SFR 250, 700V	BY 127, BY 133, BY 227, 1N4006...07
56134	SFR258	SFR 250, 800V	BY 127, BY 133, BY 227, 1N4006...07
56135	SFR264	500V, 0,8A	BY 126...127, BY 133...134, 1N4005...07
56136	SFR268	SFR 264, 1000V	BY 127, BY 133, BY 227, 1N4007
56137	SFT106	18V, 0,1A, 0,15W, B28	AC 125...126, AC 151
56138	SFT107	SFT 106, B40	AC 125...126, AC 151
56139	SFT108	SFT 106, B70	AC 125...126, AC 151
56140	SFT115	40MHz	AF 124...127, AF 200
56141	SFT116	40MHz	AF 124...127, AF 200
56142	SFT119	>20MHz	AF 124...127, AF 200
56143	SFT120	>20MHz	AF 124...127, AF 200
56144	SFT121	24V, 0,25A, 0,2W, B30	AC 128, AC 153, AC 188
56145	SFT122	SFT 121, B50	AC 128, AC 153, AC 188
56146	SFT123	SFT 121, B85	AC 128, AC 153, AC 188
56147	SFT124(B,C)	12..24V, 0,5A, 0,35W, B>20	AC 128, AC 153, AC 188
56148	SFT125(B,C)	SFT 124, B>40	AC 128, AC 153, AC 188
56149	SFT126	24V, 0,25V, 0,15W, B30	AC 125...126, AC 151
56150	SFT127	SFT 126, B35	AC 125...126, AC 151
56151	SFT128	SFT 126, B55	AC 125...126, AC 151
56152	SFT130(C)	SFT 124	AC 128K, AC 153K, AC 188K
56153	SFT131(C,P)	SFT 125	AC 128K, AC 153K, AC 188K
56154	SFT141	45V, 0,25A, 0,2W, B32	AC 125...126, AC 151
56155	SFT142	SFT 141, B50	AC 125...126, AC 151
56156	SFT143	45V, 0,5A, 0,35W, B>20	ASY 76...77, AC 128, AC 153
56157	SFT144	SFT 143, B>40	ASY 76...77, AC 128, AC 153
56158	SFT145	SFT 143, 0,55W	ASY 76...77, AC 128K, AC 153K
56159	SFT146	SFT 143, 0,55W, B>40	ASY 76...77, AC 128K, AC 153K

56160	SFT151	24V, 0,15A, 0,2W, B30	AC 125...126, AC 151
56161	SFT152	SFT 151, B50	AC 125...126, AC 151
56162	SFT153	SFT 151, B80	AC 125...126, AC 151
56163	SFT155		AF 124...125, AF 200
56164	SFT162	70V, 0,01A, 0,12W, >70MHz	AF 118, 2SA250, 2SA358
56165	SFT163	>120MHz	AF 106, AF 109R, AF 306
56166	SFT170	250MHz	AF 109R, AF 139, AF 239(S)
56167	SFT171	250MHz	AF 106, AF 109R, AF 306
56168	SFT172	250MHz	AF 106, AF 109R, AF 306
56169	SFT173	250MHz	AF 121, AF 200...201
56170	SFT174	250MHz	AF 121, AF 202(S,L)
56171	SFT184	15V, 0,1A, 0,15W	ASY 28...29, ASY 73...75
56172	SFT185	30V, 0,1A, 0,15W	ASY 26, ASY 76...77
56173	SFT186	140V, 0,15A, 0,8W, 180MHz	BF 257...259, BF 657...659, 2N5058...5059
56174	SFT186P	SFT 186, 120V, 0,6W, 210MHz	BF 257...259, BF 657...659, 2N5058...5059
56175	SFT187	135V, 0,8W, 100MHz	BF 257...259, BF 657...659, 2N5058...5059
56176	SFT190	65V, 1A, 20W(Tc45°)	AUY 19...20, 2N2140...41, 2N2145...46
56177	SFT191	SFT 190, 50V	AUY 19...20, 2N2139...41, 2N2144...46
56178	SFT192	-/45V, 3A, 30W	AD 149, AUY 19...20, 2N2144...46
56179	SFT206	18V, 0,25A, 0,15W, 5,5MHz	ASY 26...27, ASY 48, ASY 76...77
56180	SFT207	18V, 0,25A, 0,15W, 7,5MHz	ASY 26...27, ASY 48, ASY 76...77
56181	SFT208	15V, 0,25A, 0,15W, 12MHz	ASY 26...27, ASY 48, ASY 76...77
56182	SFT211	80V, 6A, 45W	AL 102...103, AUY 22(A), 2N2526...27
56183	SFT212	30V, 3A, 30W	AD 149, AUY 19...20, 2N2142...46
56184	SFT213	SFT 212, 40V	AD 149, AUY 19...20, 2N2143...46
56185	SFT214	SFT 212, 60V	AUY 19...20, 2N2139...41, 2N2144...46
56186	SFT221	30V, 0,25A, 0,15W, B>20	ASY 26, ASY 48, ASY 76...77
56187	SFT222	SFT 221, B>40	ASY 26, ASY 48, ASY 76...77
56188	SFT223	SFT 221, B>60	ASY 26, ASY 48, ASY 76...77
56189	SFT226	B>25	ASY 48, ASY 76...77
56190	SFT227	B>35	ASY 26, ASY 48, ASY 76...77
56191	SFT228	B>50	ASY 26...27, ASY 48, ASY 76...77
56192	SFT229	B>75	ASY 26...27, ASY 48, ASY 76...77
56193	SFT232	40V, 1,5A, 0,45W	AC 128, AC 153
56194	SFT233	SFT 232, 60V	-
56195	SFT234	SFT 232, 80V	-
56196	SFT235	100V, 1A, 0,45W	-
56197	SFT237	15V, 0,1A, 0,15W	AC 125...126, AC 151r
56198	SFT238	40V, 6A, 45W	AL 102...103, AUY 22(A), 2N2526...27
56199	SFT239	SFT 238, 60V	AL 102...103, AUY 22(A), 2N2526...27
56200	SFT240	SFT 238, 80V	AL 102...103, AUY 22(A), 2N2526...27
56201	SFT241	45V, 0,5A, 0,225W, B>30	ASY 76...77
56202	SFT242	SFT 241, B>50	ASY 76...77
56203	SFT243	SFT 241, 60V	ASY 77
56204	SFT244	80V, 0,5A, 0,225W	-

56205	SFT245	SFT 244, 100V	-
56206	SFT250	80V, 3A, 45W	AL 102...103, AUY 20, 2N2141, 2N2146
56207	SFT251	30V, 0,15A, 0,225W, $\beta > 20$	AC 125...126, AC 151, ASY 26, ASY 76...77
56208	SFT252	SFT 251, $\beta > 40$	AC 125...126, AC 151, ASY 26, ASY 76...77
56209	SFT253	SFT 251, $\beta > 60$	AC 125...126, AC 151, ASY 26, ASY 76...77
56210	SFT259	24V, 0,25A, 0,15W, 5MHz	ASY 28...29, ASY 73...75
56211	SFT260	24V, 0,25A, 0,15W, 9MHz	ASY 28...29, ASY 73...75
56212	SFT261	24V, 0,25A, 0,15W, $> 11$ MHz	ASY 28...29, ASY 73...75
56213	SFT264	30V, 15A, 50W	2N1980...82, 2N2078...82, 2N2490...93
56214	SFT265	40V, 15A, 87W	2N1980...82, 2N2078...82, 2N2490...93
56215	SFT266	SFT 265, 60V	2N1981...82, 2N2079...80, 2N2490...93
56216	SFT267	SFT 265, 80V	2N1982, 2N2075, 2N2079, 2N2492...93
56217	SFT268	SFT 265, 100V	2N2493
56218	SFT288	24V, 0,5A, 0,15W	ASY 26...27, ASY 48, ASY 76...77
56219	SFT298	30V, 0,5A, 0,15W	ASY 28...29, ASY 73...75
56220	SFT306(A,C)	9..18V, 0,1A, 3MHz, $\beta > 15$	AF 121, AF 124...127, AF 200
56221	SFT307(A,C)	SFT 306, $\beta > 25$	AF 121, AF 124...127, AF 200
56222	SFT308(A,C)	SFT 306, $\beta > 45$	AF 121, AF 124...127, AF 200
56223	SFT315	40V, 10mA, 30MHz	AF 126, AF 200
56224	SFT316	$> 60$ MHz	AF 126, AF 200
56225	SFT317	40MHz	AF 124...125, AF 200
56226	SFT319	20MHz	AF 126, AF 200
56227	SFT320		AF 126, AF 200
56228	SFT321(B,C)	12..32V, 0,5A, 0,2W, $B > 20$	AC 128, AC 153, AC 188
56229	SFT322(B,C)	SFT 321, $B > 40$	AC 128, AC 153, AC 188
56230	SFT323(B,C)	SFT 321, $B > 60$	AC 128, AC 153, AC 188
56231	SFT325	32V, 0,5A, 0,2W	AC 128, AC 153, AC 188
56232	SFT335	32V, 0,15A, 0,2W	AC 125...126, AC 151
56233	SFT337	15V, 0,1A, 0,15W	AC 125...126, AC 151r
56234	SFT337A	24V, 0,15A, 0,185W	AC 125...126, AC 151r
56235	SFT343	70V, 0,15A, 0,25W	2N2042...2043
56236	SFT351(B,C)	12..32V, 0,15A, 0,2W, $\beta > 20$	AC 125...126, AC 151
56237	SFT352(B,C)	SFT 351, $\beta > 40$	AC 125...126, AC 151
56238	SFT353(B,C,D)	SFT 351, $\beta > 60$	AC 125...126, AC 151
56239	SFT354	80MHz	AF 124...125, AF 200
56240	SFT357(P)	80..85MHz	AF 125, AF 200
56241	SFT358	110MHz	AF 124, AF 200
56242	SFT367	32V, 1A, 0,65W	AC 128, AC 153, AC 188
56243	SFT373	12V, 0,3A, 0,25W	AC 127, AC 176, AC 187
56244	SFT377	32V, 1A, 0,65W	AC 176, AC 187
56245	SFT440	80V, 1A, 12W, 200MHz	-
56246	SFT443	80V, 6W( $T_c 100^\circ$ ), 180MHz	-
56247	SFT443A	SFT 443, 12W	-
56248	SFT445	80V, 0,5A, 0,8W, 200MHz	BC 141, BC 300...301, 2N1889...90
56249	SG	2SA1873-GR	2SA1873

56250	SG	2SA1618-GR	2SA1618
56251	SG	2SA1162-GR	2SA1162
56252	SG	SMBTA 14	SMBTA 14
56253	SG	2SA1832-G	2SA1832
56254	SG	2SA1586-G	2SA1586
56255	SG	U 1GWJ49	U 1GWJ49
56256	SG2182	70V, 0,6A, 0,6W, >200MHz	BC 161, BC 303...304, BC 461, BCX 60
56257	SG2183	55V, 1A, 0,8W, 200MHz	BC 140...141, BC 300...302, BCX 40
56258	SGL41-..	20..60V, 1A	BYM 11-..., BYM 12-...
56259	SGS10004..10005	MJ 10004..10005	MJ 10004...10005
56260	P	MJ 10004P..10005P	MJ 10004P...10005P
56261	SGS110..112	TIP 110..112	TIP 110...112
56262	SGS115..117	TIP 115..117	TIP 115...117
56263	SGS120..122	TIP 120..122	TIP 120...122
56264	SGS125..127	TIP 125..127	TIP 125...127
56265	SGS130..132	TIP 130..132	TIP 130...132
56266	SGS13002..13003	MJE 13002..13003	MJE 13002...13003
56267	3T	MJE 13002..13003	BUT 11(A), BUV 36, BUX 84...85, 2SC3531
56268	SGS135..137	TIP 135..137	TIP 135...137
56269	SGS157..159	BD 157..159	BD 157...159
56270	SGS3055	2N3055, 150W	BD 317, 2N5629...5631
56271	SGS340	MJE 340	MJE 340
56272	SGS3439..3440	MJE 3439..3440	MJE 3439...3449
56273	SGS350	MJE 350	MJE 350
56274	SGS520	MJE 520	MJE 520
56275	SGS6386..6388	2N6386..6388	2N6386...6388
56276	SGS910..912	BU 910..912	BU 910...912
56277	SGSD00030	650/400V, 28A, 150W, B>30	BUT 13...14
56278	SGSD00031	SGSD 0030, 125W	BUT 13P
56279	SGSD00032	700/400V, 12A, 175W, B>5	BUS 13(A), BUW 13(A), BUW 76...77
56280	SGSD00033	SGS 00032, 150W	BUV 48(A), BUW 13(A), 2SC3451, 2SC4706
56281	SGSD00034	1000/450V, 12A, 175W, B>5	BUS 13A, BUV 48A, BUW 13A, BUX 48A...C
56282	SGSD00035	SGS 00034, 150W	BUV 48A, BUW 13A, 2SC3552, 2SC3644
56283	SGSD00036	700/400V, 8A, 120W, B>5	BUV 47(A), BUW 12(A), BUW 35...36
56284	SGSD00037	SGSD 00036	BUV 47(A), BUW 12(A), 3SC3090, 2SC3450
56285	SGSD00038	1000/450V, 8A, 120W, B>5	BUS 12A, BUV 47A, BUW 12A, BUX 81
56286	SGSD00039	SGSD 00038	BUV 47A, BUW 12A, 3SC3461, 2SC4237
56287	SGSD00040	700/400V, 8A, 90W, B>5	BUT 12, BUT 56, BUT 76, MJE 13007
56288	SGSD00041	700/400V, 5A, 90W, B>4	BUT 11, BUT 18, BUV 46, MJE 13071
56289	SGSD00041	1000/450V, 8A, 90W, B>5	BUT 12A, BUT 56A, BUT 76A, BUF 405A
56290	SGSD00042	1000/450V, 5A, 90W, B>4	BUT 11A, BUT 18A, BUV 46A, 2SC3050
56291	SGSD00046	700/400V, 2A, 50W, B>5	-
56292	SGSD00048	SGSD 46	-
56293	SGSD00055	1000/400V, 7A, 75W	BUD 47A
56294	SGSD0030FI	SGSD 0030	BUT 13PFI



56295	SGSD0031FI	SGSD 0030, , 60W	BUT 13PFI
56296	SGSD100	80V, 25A, 130W, B600..15000	-
56297	SGSD110	80V, 25A, 130W, B>15	-
56298	SGSD200	80V, 25A, 130W, B600..15000	-
56299	SGSD210	80V, 25A, 130W, B>15	-
56300	SGSD310	600/400V, 28A, 150W, B>30	BUT 13...14
56301	SGSD311	SGSD 310, 125W	BUT 13P
56302	SGSD311FI	SGSD 310, , 60W	BUT 13PFI
56303	SGSD93E	160/140V, 12A, 80W, B1k..20k	-
56304	SGSD93F	SGS 93E, 180/160V	-
56305	SGSD93FFI		-
56306	SGSD93G	SGS 93E, 200/180V	-
56307	SGSD94FFI	180/160V, 12A, 40W, B>1000	2SD2196
56308	SGSF313	1000/450V, 5A, 70W, -/2,8μs	BUF 405A
56309	SGSF313XI	SGSF 313	BUF 405AFI
56310	SGSF321	850/400V, 5A, 70W, <1/2,8μs	BUT 11(A), BUT 18(A), BUV 46(A)
56311	SGSF322	SGSF 321, 850/450V	BUT 11(A), BUT 18(A), BUV 46(A)
56312	SGSF323	1000/450V, 5A, 70W, <1/2,8μs	BUT 11A, BUT 18A, BUT 46A, BUV 46A
56313	SGSF324	1200/600V, 4A, 70W	BU 506, BU 603, MJE 8502...03, 2SC3050
56314	SGSF341	850/400V, 10A, 85W, <1/2,85μs	BUT 76(A), BUV 56(A), BUV 66(A)
56315	SGSF342	SGSF 341, 850/450V	BUT 76(A), BUV 56(A), BUV 66(A)
56316	SGSF343	1000/450V, 8A, 85W, <1/2,85μs	BUT 12A, BUT 56A, BUT 76A, BUV 56A
56317	SGSF344	1200/600V, 7A, 85W, <1/3,8μs	-
56318	SGSF421	SGSF 321, 80W	BUW 11(A), BUW 131(A), BUV 82, 2SD1503
56319	SGSF422	SGSF 321, 850/450V, 80W	BUW 11(A), BUW 131(A), BUV 82, 2SD1503
56320	SGSF423	SGSF 323, 80W	BUW 11A, BUW 131A, BUV 83, 2SC3535
56321	SGSF424	SGSF 324, 80W	BU 508A, BU 706, BU 908, 2SC4236
56322	SGSF425	SGSIF 325, 80W	BU 508A, BU 903, BU 908, 2SD1496...97
56323	SGSF441	SGSF 341, 95W	BUW 12...13(A), BUV 47...48(A), 2SC3637
56324	SGSF442	SGSF 341, 850/450, 95W	BUW 12...13(A), BUV 47...48(A), 2SC3637
56325	SGSF443	SGSF 343, 95W	BUW 12A...13A, BUV 47A...48A, 2SC3461
56326	SGSF444	SGSF 344, 95W	BU 508A, BU 908, BUV 89, 2SC3643
56327	SGSF445	SGSIF 345, 95W	BU 508A, BU 908, BUV 70...71, 2SD1498
56328	SGSF461	<1,7/2,8μs	BUW 13(A), BUV 48(A...C), 2SC3638
56329	SGSF462	SGSF 461, 850/450V	BUW 13(A), BUV 48(A...C), 2SC3638
56330	SGSF463	<1,7/2,8μs	BUW 13A, BUV 48A...C, 2SC3552
56331	SGSF464	1200/600V, 10A, 125W	BU 2520A, BUV 70...71, 2SC3644, 2SC4023
56332	SGSF465	1300/600V, 10A, 125W	BU 2520A, BUV 70...71, 2SC4023
56333	SGSF521	SGSF 321, 85W	BUW 11(A), BUW 131(A), BUV 82, 2SC3535
56334	SGSF522	SGSF 321, 850/450V, 85W	BUW 11(A), BUW 131(A), BUV 82, 2SC3535
56335	SGSF523	SGSF 323, 85W	BUW 11A, BUW 131A, BUV 83, 2SC3535
56336	SGSF524	SGSF 324, 85W	BU 208A, BU 508A, BU 903, 2SC3642
56337	SGSF541	SGSF 341, 115W	BUS 12(A), BUW 36, BUW 12(A), 2SC3637
56338	SGSF542	SGSF 341, 850/450V, 115W	BUS 12(A), BUW 36, BUW 12(A), 2SC3637
56339	SGSF543	SGSF 343, 115W	BUS 12A, BUW 12A, BUX 81, 2SC3215

56340	SGSF544	SGSF 344, 115W	BU 508A, BU 908, 2SC3643, 2SD1279
56341	SGSF545	SGSIF 345, 115W	BU 508A, BU 908, 2SC4284, 2SD1279
56342	SGSF561	SGSF 461, 150W	BUS 97, BUW 13(A), BUW 46, BUX 48
56343	SGSF562	SGSF 461, 850/450V, 150W	BUS 97, BUW 13(A), BUW 46, BUX 48
56344	SGSF563	SGSF 463, 150W	BUS 13A, BUW 13A, BUX 48A...C, 2SC3552
56345	SGSF564	SGSF 464, 150W	BUV70...71
56346	SGSF565	SGSIF 465, 150W	BU 2520A, BU 2522A, BUV 70...71, 2SC4023
56347	SGSF661	<1,7/2,8µs	BUS 14(A), BUS 98(A), BUX 348(A)
56348	SGSF662	SGSF 661, 850/450V	BUS 14(A), BUS 98(A), BUX 348(A)
56349	SGSF663	<1,7/2,8µs	BUS 14A, BUS 98A, BUX 348A, 2SC3593
56350	SGSF664	1200/600V, 20A, 250W	-
56351	SGSF665	1300/600V, 20A, 250W	-
56352	SGSI808D	BU 808DFI, 10A	-
56353	SGSI809D	BU 808DFI, 1300/600V, 10A	-
56354	SGSIF321	SGSF 321, .., 35W	BUT 11(A)F, BUT 18(A)F, BUV 46(A)FI
56355	SGSIF323	SGSF 323, .., 35W	BUT 11AF, BUT 18AF, BUV 46AFI
56356	SGSIF324	SGSF 324, .., 35W	-
56357	SGSIF325	1300/600V, 4A, 35W	-
56358	SGSIF341	SGSF 341, .., 40W	BUT 12(A)F
56359	SGSIF343	SGSF 343, .., 40W	BUT 12AF
56360	SGSIF344	SGSF 344, .., 40W	-
56361	SGSIF345	1300/600V, 7A, 40W	-
56362	SGSIF421	SGSF 321, .., 45W	BUW 11(A)F, 2SC4427...4428
56363	SGSIF422	SGSF 321, .., 850/450V, 45W	BUW 11(A)F, 2SC4427...4428
56364	SGSIF423	SGSF 323, .., 45W	BUW 11AF, 2SC4427...4428
56365	SGSIF424	SGSF 324, .., 45W	BU 508AF, S 2000AF, 2SC3884, 2SC4882
56366	SGSIF425	SGSIF 325, 45W	BU 508AF, S 2000AF, 2SC3884
56367	SGSIF441	SGSF 341, 55W	BUW 12(A)F, BUV 47(A)F, 2SC4430
56368	SGSIF442	SGSF 341, 850/450V, 55W	BUW 12(A)F, BUV 47(A)F, 2SC4430
56369	SGSIF443	SGSF 343, .., 55W	BUW 12AF, BUV 47AF, 2SC4430
56370	SGSIF444	SGSF 344, .., 55W	BU 508AF, S 2000AF, 2SC4584, 2SC4941
56371	SGSIF445	SGSIF 345, 55W	BU 508AF, S 2000AF, 2SC3892, 2SC4199
56372	SGSIF461	SGSF 461, .., 65W	BUV 48(A)FI, BUW 13(A)F
56373	SGSIF462	SGSF 461, .., 850/450V, 65W	BUV 48(A)FI, BUW 13(A)F
56374	SGSIF463	SGSF 463, .., 65W	BUV 48AFI, BUW 13AF, 2SC4430
56375	SGSIF464	SGSF 464, .., 65W	2SC3897, 2SC4199(A), 2SD1548
56376	SGSIF465	SGSF 465, .., 65W	2SC3897, 2SC4199(A), 2SD1548
56377	SGSIP478	SGSP 478	2SK1686
56378	SGSIP479	SGSP 479	2SK1225, 2SK1452, 2SK1523, 2SK1696
56379	SGSIV47(A)	BUV 47(A)FI	BUV 47(A)FI
56380	SGSIV48...	BUV 48..FI	BUV 48...FI
56381	SGSIW32(A)	BUW 32(A)PFI	BUW 32(A)PFI
56382	SGSP201	SGSP 301	SGSP 301
56383	SGSP202	SGSP 302	SGSP 302
56384	SGSP211	SGSP 311, 50W	SGSP 311

56385	SGSP212	SGSP 312, 50W	SGSP 312
56386	SGSP216	SGSP 316, 50W	SGSP 316
56387	SGSP217	SGSP 317, 50W	SGSP 317
56388	SGSP218	SGSP 318, 50W	SGSP 318
56389	SGSP219	SGSP 319, 50W	SGSP 319
56390	SGSP221	SGSP 321, 50W	SGSP 321
56391	SGSP222	SGSP 322, 50W	SGSP 322
56392	SGSP230	SGSP 330, 50W	SGSP 330
56393	SGSP231	SGSP 331, 50W	SGSP 331
56394	SGSP232	SGSP 332, 50W	SGSP 332
56395	SGSP238	SGSP 338, 40W	SGSP 338
56396	SGSP239	SGSP 339, 40W	SGSP 339
56397	SGSP240	SGSP 340, 18W	SGSP 340
56398	SGSP241	SGSP 341, 18W	SGSP 341
56399	SGSP242	SGSP 342, 18W	SGSP 342
56400	SGSP248	SGSP 348, 18W	SGSP 348
56401	SGSP249	SGSP 349, 18W	SGSP 349
56402	SGSP251	SGSP 351, 40W	SGSP 351
56403	SGSP252	SGSP 352, 40W	SGSP 352
56404	SGSP254	SGSP 354, 40W	SGSP 354
56405	SGSP255	SGSP 355, 40W	SGSP 355
56406	SGSP256	SGSP 356, 40W	SGSP 356
56407	SGSP257	SGSP 357, 40W	SGSP 357
56408	SGSP258	SGSP 358, 40W	SGSP 358
56409	SGSP301	<45/40ns	IRF 610...613, 2SK923
56410	SGSP302	SGSP 301, 80V	IRF 610...613, 2SK923
56411	SGSP311	<75/85ns	BUZ 20, BUZ 72, IRF530, IRF532, 2SK918
56412	SGSP312	SGSP 311, 80V	BUZ 20, BUZ 72, IRF530, IRF532, 2SK918
56413	SGSP316	<60/80ns	BUZ 60, IRF 830...833, 2SK358, 2SK924
56414	SGSP317	<60/80ns	BUZ 60, IRF 830...833, 2SK358, 2SK924
56415	SGSP318	<55/100ns	BUZ 80, 2SK858, 2SK1323, 2SK1922
56416	SGSP319	<3,8Ohm,<55/100ns	BUZ 41A...42, IRF 830, IRF 832, 2SK553
56417	SGSP321	<80/90ns	BUZ 21, IRF 540...543, 2SK674, 2SK972
56418	SGSP322	<75/85ns	BUK552-50, IRF 530...533, 2SK673, 2SK971
56419	SGSP330	<50/105ns	BUZ 41A...42, IRF 830...833, 2SK1493...94
56420	SGSP331	<2,5Ohm(1,5A)	BUZ 76, IRF 720, IRF 722, 2SK1493...94
56421	SGSP332	<2,5Ohm(1,5A)	BUZ 76, IRF 720, IRF 722, 2SK1493...94
56422	SGSP338	SGS 339, 550V, <110hm(0,6A)	BUZ 78, BUZ 80, 2SK858, 2SK1922
56423	SGSP339	<8,5Ohm,<50/105ns	BUZ 74, IRF 820, IRF 822, 2SK858
56424	SGSP340	SGSP 341, 450V	BUZ 78, 2SK602, 2SK1053
56425	SGSP341	<35/90ns	BUZ 78, 2SK602, 2SK1053
56426	SGSP342	SGSP 341, 350V	BUZ 78, 2SK602, 2SK1053
56427	SGSP348	SGSP 349, 550V	-
56428	SGSP349	<40Ohm(0,3A)	2SK1052
56429	SGSP351	<50/55ns	BUZ 30, BUZ 73, IRF 520, IRF 522, 2SK470

56430	SGSP352	SGSP 351, 80V	BUZ 30, BUZ 73, IRF 521, IRF 523, 2SK470
56431	SGSP354	<6,50hm(0,75A)	BUZ 78, 2SK602, 2SK1053
56432	SGSP355	<50hm(0,75A)	BUZ 78, 2SK602, 2SK1053
56433	SGSP356	SGSP 355, 350V	BUZ 78, 2SK602, 2SK1053
56434	SGSP357	SGSP 358, 60V	IRF 520...523, 2SK464, 2SK993
56435	SGSP358	<60/50ns	IRF 520...523, 2SK464, 2SK993
56436	SGSP361	<0,150hm(9A)	BUZ 21, IRF 540, IRF 542, 2SK919
56437	SGSP362	80V, 22A, 100W, <0,30hm(9A)	BUZ 21, IRF 540...543, PRF540, PRF542
56438	SGSP363	<0,450hm(5A)	2SK925, 2SK1221, 2SK1393, 2SK1761
56439	SGSP364	<1,50hm(2,5A)	BUZ 41A...42, IRF 830...833, 2SK552...553
56440	SGSP365	SGSP 364, 400V, <10hm(3A)	BUZ 41A...42, IRF 830...833, 2SK552...553
56441	SGSP366	SGSP 364, 350V, <10hm(3A)	BUZ 41A...42, IRF 830...833, 2SK552...553
56442	SGSP367	<0,330hm(6A)	BUZ 31, IRF 640, IRF 642, 2SK459
56443	SGSP368	<2,50hm(2,5A)	BUZ 90, 2SK1117, 2SK1402, 2SK1923...24
56444	SGSP369	SGSP 364, 500V	BUZ 41A...42, IRF 830, IRF 832, 2SK553
56445	SGSP381	<0,060hm(14A)	BUK 555-60, IRF 540...543, 2SK1296
56446	SGSP382	SGSP 381, 50V	BUZ11, BUK555-50, IRF540...543, 2SK1296
56447	SGSP421	SGSP 321	2SK622, 2SK1267
56448	SGSP422	SGSP 322	2SK622, 2SK1267
56449	SGSP461	<0,150hm(10A)	BUZ 350, 2SK622, 2SK1267
56450	SGSP462	<0,10hm(12,5A)	BUZ 349, 2SK850...851, 2SK906, 2SK1433
56451	SGSP463	SGSP 363	BUZ 325, 2SK412, 2SK634
56452	SGSP464	SGSP 364, 125W	BUZ 330...331
56453	SGSP465	SGSP 365, 125W	BUZ 330...331, 2SK2264
56454	SGSP466	SGSP 366, 125W	BUZ 330...331, 2SK2264
56455	SGSP467	SGSP 367, 125W	2SK573, 2SK1135, 2SK1401
56456	SGSP468	SGSP 368, 125W	2SK1213, 2SK1403
56457	SGSP469	SGSP 369, 125W	2SK1213, 2SK1403
56458	SGSP471	<75m0hm(15A)	BUZ 341, BUZ 349, 2SK850...51, 2SK1433
56459	SGSP472	<50m0hm(17,5A)	BUZ 341, BUZ 349, 2SK850...51, 2SK1433
56460	SGSP473	<0,220hm(10A)	2SK901, 2SK944, 2SK1491, 2SK1641
56461	SGSP474	<0,70hm(4,5A)	BUZ 339, 2SK557, 2SK642, 2SK644, 2SK724
56462	SGSP475	<0,550hm(5A)	BUZ 325...326, 2SK634, 2SK896, 2SK1488
56463	SGSP476	<0,550hm(6A)	BUZ 323, 2SK788, 2SK899, 2SK1608
56464	SGSP477	<0,170hm(10A)	BUZ 350, 2SK623, 2SK901, 2SK944
56465	SGSP478	SGSP 479, 550, <1,20hm(5A)	BUZ 334, 2SK1723, 2SK1968
56466	SGSP479	<0,70hm(4,5A)	BUZ 339, 2SK557, 2SK642, 2SK644, 2SK724
56467	SGSP481	<60m0hm(15A)	BUZ 349, 2SK906, 2SK1303, 2SK1433
56468	SGSP482	SGSP 481, 50V	BUZ 349, 2SK906, 2SK1303, 2SK1433
56469	SGSP491	<33m0hm(20A)	BUZ345, 2SK849, 2SK857, 2SK1124, 2SK1297
56470	SGSP492	SGSP 491, 50V	BUZ 347...348, 2SK849, 2SK857, 2SK905
56471	SGSP511	SGSP 311	2SK398...399, 2SK631, 2SK633, 2SK1529
56472	SGSP512	SGSP 312	2SK398...399, 2SK631, 2SK633, 2SK1529
56473	SGSP516	SGSP 316	BUZ 63, BUZ 330...331, 2SK259...260
56474	SGSP517	SGSP 317	BUZ 63, BUZ 330...331, 2SK259...260

56475	SGSP518	SGSP 318	BUZ 308
56476	SGSP519	SGSP 319	2SK635
56477	SGSP521	SGSP 321	BUZ36, 2N6765, 2SK572, 2SK622, 2SK1267
56478	SGSP522	SGSP 322	BUZ36, 2N6765, 2SK572, 2SK622, 2SK1267
56479	SGSP530	SGSP 330	2SK635
56480	SGSP531	SGSP 331	2SK635
56481	SGSP532	SGSP 332	2SK635
56482	SGSP561	SGSP 361, 125W	BUZ 36, BUZ 350, 2SK622, 2SK1267
56483	SGSP562	SGSP 362, 125W	BUZ 36, BUZ 350, 2SK622, 2SK1267
56484	SGSP563	SGSP 363, 125W	BUZ64, BUZ325, 2SK312, 2SK401, 2SK412
56485	SGSP564	SGSP 364, 125W	BUZ 330...331, 2SK1213, 2SK1403
56486	SGSP565	SGSP 365, 125W	BUZ 63, BUZ 330...331, 2SK1213, 2SK1403
56487	SGSP566	SGSP 366, 125W	BUZ 63, BUZ 330...331, 2SK1213, 2SK1403
56488	SGSP567	SGSP 367, 125W	2SK573, 2SK1135, 2SK1401
56489	SGSP568	SGSP 368, 125W	BUZ 332A, 2SK1213, 2SK1403
56490	SGSP569	SGSP 369, 125W	BUZ 330...331, 2SK1213, 2SK1403
56491	SGSP571	SGSP 471	BUZ24, BUZ341, 2N6764, 2SK850, 2SK1433
56492	SGSP572	SGSP 472	BUZ24, BUZ341, 2N6764, 2SK850, 2SK1433
56493	SGSP573	SGSP 473	2SK623, 2SK901, 2SK944, 2SK1491, 2SK1641
56494	SGSP574	<0,70hm(4,5A)	BUZ 45, 2SK512, 2SK642, 2SK644, 2SK724
56495	SGSP575	<0,550hm(5A)	BUZ 45, 2SK512, 2SK642, 2SK644, 2SK724
56496	SGSP576	<0,550hm(6A)	BUZ338, 2SK725, 2SK788, 2SK899, 2SK1610
56497	SGSP577	<0,170hm(10A)	BUZ36, BUZ350, 2N6766, 2SK901, 2SK944
56498	SGSP578	SGSP 579, 550V, <1,20hm(5A)	BUZ 334, 2SK1723, 2SK1968
56499	SGSP579	<0,70hm(4,5A)	BUZ 45, BUZ 339, 2SK512, 2SK644, 2SK724
56500	SGSP581	SGSP 381, 125W	BUZ24, 2N6763, 2SK850, 2SK906, 2SK1303
56501	SGSP582	SGSP 382, 125W	BUZ24, 2N6763, 2SK850, 2SK906, 2SK1303
56502	SGSP591	<33m0hm(20A)	2SK849, 2SK857, 2SK1124, 2SK1665
56503	SGSP592	SGSP 591, 50V	BUZ 15, BUZ 347...348, 2SK849, 2SK857
56504	SGT03U13	33V	-
56505	SGT06U13	60V	-
56506	SGT23U13	230V	-
56507	SGX	KSA1203	KSA1203
56508	SH	BB 814	BB 814
56509	SH-1(A...Z)	200..1400V, 0,15A	BAY 88...91, BY 203/..., SHG 1...1,5
56510	SH1	BB 814-1	BB 814-1
56511	SH2	BB 814-2	BB 814-2
56512	SH2B41	100V, 2A(Tc35°C), Igt<1,5mA	S 2061..., TIC 108...,
56513	SH2D41	SH 2B41, 200V	S 2061..., TIC 108...,
56514	SH2G41	SH 2B41, 400V	S 2061..., TIC 108...,
56515	SHG1	1000V, 0,2A, <500ns	BY 203/12, BY 208/1000, BY 268...269
56516	SHG1,5	SHG 1, 1500V	BY 203/16, BY 231/1500, BY 269
56517	SHG2	SHG 1, 2000V	BY 203/20, HVG 2, MR 250-2, 1N1732
56518	SHG2,5	SHG 1, 2500V	HVG 3, MR 250-3, 1N1733
56519	SHV-10	10kV, 2mA	BY 209, BY 409, BY 509...510, BY 708

56520	SHV-12	SHV-10, 12kV	BY 209, BY 409, BY 509...510, BY 709
56521	SHV-16	SHV-10, 16kV	BY 476, BY 610, BY 620, BY 710...714
56522	SHV-20	SHV-10, 20kV	BY 477...478, BY 712...714
56523	SHV-24	SHV-10, 24kV	BY 478, BY 713...714
56524	SHX	KSC2883	KSC2883
56525	SI	U 1GWJ2C49	U 1GWJ2C49
56526	SI850..856	GI 850..856	GI 850...856
56527	SI910..918	GI 910..918	GI 910...918
56528	SIB01-02...-06	200..600V, 1A	BY 126...127, BY 133...134, 1N4003...07
56529	SIB02	200V, 1A	BY 126...127, BY 133...134, 1N4003...07
56530	SIB02-01B...-06B	100..600V, 1,5A	B80C1500...B400C1500
56531	SIB02-01B...-06B	100..600V, 1,5A	B80C1500...B400C1500
56532	SIB02-01C...-06C	100..600V, 1,8A	-
56533	SIB03-08...-12	800..1200V, 1A	BY 127, BY 133, BY 227, GP 10Q...Y
56534	SIB04	SI B 02, 400V	BY 126...127, BY 133...134, 1N4003...07
56535	SIB06	SI B 02, 600V	BY 126...127, BY 133...134, 1N4003...07
56536	SiD01-01...-12	100..1200V, 9A	BYW 88/..., BYX 42/..., BYX 98/...
56537	SiD01E...N	300..1200V, 4,5A	BY 214/..., MR 750...760, BY 239/...
56538	SiD02E...N	300..1200V, 6A	BY 214/..., MR 750...760, BY 239/...
56539	SiD30/15	GH 3 F	GH 3 F
56540	SiG05/...	BYX 55/..	BYX 55/...
56541	SiG1/...	BYX 55/..	BYX 55/...
56542	SIS20	1N4148	1N4148
56543	SIS32	BA 159	BA 159
56544	SiT0,8/50...400	0,8A(Tc85°C),Igt/Ih<10/<20mA	BTX 30/..., T 1N..., S 2600..., TAG 612-...
56545	SiT14/50...400	Igt/Ih<50/8mA	-
56546	SiT18/50...600	Igt/Ih<50/10mA	-
56547	SiT180/50...600	400/40mA	-
56548	SiT20/50...400	Igt/Ih<50/50mA	BTW 40/..., BStE41...M, T 17N..., CS 16-...
56549	SiT30/50...600	30A(Tc85°C),Igt/Ih<100/20mA	-
56550	SiT4/50...400	4A(Tc85°C),Igt/Ih<20/<25mA	T 6N...C, T 8N...C, BStD41..., C 230...
56551	SiT50/50...600	50A(Tc85°C),Igt/Ih<100/20mA	-
56552	SiT80/50...400	80A(Tc85°C),Igt/Ih<50/<60mA	-
56553	SiT95/50...600	95A(Tc85°C),Igt/Ih<80/25mA	-
56554	SJ	SMBTA 92	SMBTA 92
56555	SJ1499	2N3055	2N3055
56556	SJE210	BD 140	BD 140
56557	SJE211	BD 139	BD 139
56558	SJE212	BD 140	BD 140
56559	SJE213	BD 139	BD 139
56560	SJE293	BD 140	BD 140
56561	SJE294	BD 139	BD 139
56562	SJE5411	BD 180	BD 180
56563	SJE5412	BD 179	BD 179
56564	SJE957	BD 678	BD 678



56565	SK	SMBTA 93	SMBTA 93
56566	SK	2SC3554-SK	2SC3554
56567	SK12	20V, 1A	MBRS 130, MBRS 140
56568	SK13	SK 12, 30V	MBRS 130, MBRS 140
56569	SK14	SK 12, 40V	MBRS 140
56570	SK15	SK 12, 50V	-
56571	SK16	SK 12, 60V	-
56572	SK18	SK 12, 80V	-
56573	SK4F/02...10	200..1000V, 1,2A, <450ns	SKE 4F2/02...10, BY 205/..., BY 229/...
56574	SK4G/02...10	SK 4F/02..10	SK 4F/02...10
56575	SKE1/01...16	120..1600V, 1,3A	SKE 2,5/01...16, BY 329/..., BY 359/...
56576	SKE1/01...16	120..1600V, 1,3A	SKE 2,5/01...16, BY 329/..., BY 359/...
56577	SKE1F/...		BY228, BY400, BY448, BY329/...,BY359/...
56578	SKE1F/...		BY228, BY400, BY448, BY329/...,BY359/...
56579	SKE2,5/01...16	120..1600V, 2,5A	SKE 4F/02...10, BY 329/..., BY 359/...
56580	SKE2,5/01...16	120..1600V, 2,5A	SKE 4F/02...10, BY 329/..., BY 359/...
56581	SKE4F1/01..10	100..1000V, 1,2A, <400ns	SKE 4F2/01...10, BY 205/..., BY 229/...
56582	SKE4F1/01..10	100..1000V, 1,2A, <400ns	SKE 4F2/01...10, BY 205/..., BY 229/...
56583	SKE4F2/01..10	100..1000V, 2A, <400ns	BY 205/..., BY 229/..., RGP 80B...M
56584	SKE4F2/01..10	100..1000V, 2A, <400ns	BY 205/..., BY 229/..., RGP 80B...M
56585	SKE4G1/01..10	SKE 4F1/01..10	SKE 4F1/01...10
56586	SKE4G1/01..10	SKE 4F1/01..10	SKE 4F1/01...10
56587	SKE4G2/01..10	SKE 4F2/01..10	SKE 4F2/01...10
56588	SKE4G2/01..10	SKE 4F2/01..10	SKE 4F2/01...10
56589	SKS1/01..16	120..1600V, 1,4A	BY 226...227, BY 251...255, 1N5393...99
56590	SL	SMBTA 42	SMBTA 42
56591	SL	2SA1571	2SA1571
56592	SL	2SC3554-SL	2SC3554
56593	SL136-2..-7	Igt/Ih<40/50mA	Z 0410...
56594	SLN2020..2045P	SLP 2020..2045P	-
56595	SLN3020..3045P	SLP 3020..3045P	-
56596	SLP2020P	20V, 20A	BYV 73/30, MBR 3020PT
56597	SLP2030P	SLP 2020P, 30V	BYV 73/30, MBR 3035PT
56598	SLP2035P	SLP 2020P, 35V	BYV 73/35, MBR 3035PT
56599	SLP2040P	SLP 2020P, 40V	BYV 73/40, MBR 3045PT
56600	SLP2045P	SLP 2020P, 45V	BYV 73/45, MBR 3045PT
56601	SLP3020P	20V, 30A	BYV 73/30, MBR 3020PT
56602	SLP3030P	SLP 3020P, 30V	BYV 73/30, MBR 3035PT
56603	SLP3035P	SLP 3020P, 35V	BYV 73/35, MBR 3035PT
56604	SLP3040P	SLP 3020P, 40V	BYV 73/40, MBR 3045PT
56605	SLP3045P	SLP 3020P, 45V	BYV 73/45, MBR 3045PT
56606	SLX	KSB798	KSB798
56607	SM	2SC3082K-M	2SC3082K
56608	SM	SMBTA 43	SMBTA 43
56609	SM	2SC4100-M	2SC4100

56610	SM	2SC3554-SM	2SC3554
56611	SM-1,5-02	200V, 1,5A	BYD 34D...M, BYV 13...16, RGP 15D...M
56612	SM-1,5-02FR	200V, 1A, <400ns	BYD 34D...M, BYV 13...16, RGP 15D...M
56613	SM-1,5-04	400V, 1,5A	BYD 34G...M, BYV 13...16, RGP 15G...M
56614	SM-1,5-04FR	400V, 1A, <400ns	BYD 34G...M, BYV 13...16, RGP 15G...M
56615	SM-1,5-08	800V, 1,5A	BYD 34K...M, BYV 15...16, RGP 15K...M
56616	SM-1,5-08FR	800V, 1A, <800ns	BYD 34K...M, BYV 15...16, RGP 15K...M
56617	SM-1,5-10	1000V, 1,5A	BYD 34M, BYV 16, BYV 96E, RGP 15M
56618	SM-1,5-10FR	1000V, 1A, <800ns	BYD 34M, BYV 16, BYV 96E, RGP 15M
56619	SM-1,5P10	1000V, 0,4A, <50ns	BYV 26E
56620	SM-1,5SN4	400V, 1,5A	BYD 34G...M, BYV 13...16, RGP 15G...M
56621	SM-1XF08	800V, 1A, <800ns	BY 231/800...1500, MR 817, RGP 10K...M
56622	SM-1XF16	1600V, 0,5A, <1500ns	BY 269, RGP 15-16, BY 231/1500
56623	SM-1XF20	2000V, 0,5A, <1500ns	BYD 43-20, RGP 15-20
56624	SM-1XH02	200V, 1A, <400ns	BYT 52D...M, BYV 13...16, RGP 10D...M
56625	SM-1XH04	400V, 1A, <400ns	BYT 52G...M, BYV 13...16, RGP 10G...M
56626	SM-1XH06	600V, 1A, <400ns	BYT 52J...M, BYV 14...16, RGP 10J...M
56627	SM-1XH08	800V, 0,8A, <400ns	BYT 52K...M, BYV 15...16, RGP 10K...M
56628	SM-1XH12	1200V, 0,6A, <400ns	BY 231/1200, BYD 33/U...V, RGP 15-12
56629	SM-1XH16	1600V, 0,2A, <400ns	BY 203-16...-20, BY 269, RGP 15-16
56630	SM-1XN02	200V, 1A	BY 126...127, BY 133...134, 1N5614...22
56631	SM-1XN04	SM-1XN02, 400V	BY 126...127, BY 133...134, 1N5616...22
56632	SM-1XN06	SM-1XN02, 600V	BY 126...127, BY 133...134, 1N5618...22
56633	SM-1XN08	SM-1XN02, 800V	BY 127, BY 133, G 1K...M, 1N5620...22
56634	SM-1XN12	SM-1XN02, 1200V	BY 127, BY 133, EM 513, GP 10Q...Y
56635	SM-1XN16	SM-1XN02, 1600V	DM 513, EM 516, GP 10Y, RGP 15-16
56636	SM-1XP10	1000V, 0,2A, <50ns	BYV 26E, MUR 1100
56637	SM-1XP2	200V, 1A, <50ns	MUR120
56638	SM-1XP4	400V, 0,5A, <50ns	BYV 26B...E, EGP 10G, FE 1H, MUR 140
56639	SM-1XP6	600V, 0,5A, <50ns	BYV 26C...E, MUR 160
56640	SM-1XSN4(A)	400V, 1A	-
56641	SM-1XZ02	200V, 1A, Pbr1kW	BYD 13D...M, BYD 33D...M, 1N4245...49
56642	SM-1XZ04	SM-1XZ02, 400V	BYD 13G...M, BYD 33G...M, 1N4246...49
56643	SM-3-02	200V, 3A	BY 251...255, BYW 95A...C, RGP 30D...M
56644	SM-3-02FR	200V, 2,5A, <400ns	BY 397...399, BYW 95A...C, RGP 30D...M
56645	SM-3-04	400V, 3A	BY 252...255, BYW 95B...C, RGP 30G...M
56646	SM-3-04FR	400V, 2,5A, <400ns	BY 398...399, BYW 95B...C, RGP 30G...M
56647	SM-3-06	600V, 3A	BY 253...255, BYW 95C, RGP 30J...M
56648	SM-3-06FR	600V, 2,5A, <400ns	BY 399, BYW 95C, RGP 30J...M
56649	SM-3-08	800V, 3A	BY 254...255, BYW 96D...E, RGP 30K...M
56650	SM-3-08FR	800V, 2,5A, <800ns	BY 399, BYW 96D...E, RGP 30K...M
56651	SM-3-10FR	1000V, 2,5A, <800ns	BY 228, BY 399S, BYW 96E, RGP 30M
56652	SM-3-15FR	1500V, 1,5A, <1000ns	BY 228, BY 448
56653	SM-3P10	1000V, 0,7A, <50ns	BYV 26E
56654	SM-3P2	200V, 3A, <50ns	BYV 28/200, EGP 30D...G, FE 3D...H

56655	SM-3P4	400V, 1,5A, <50ns	BYD 73G, EGP 20G, FE 2H
56656	SM-3P6	600V, 1,5A, <50ns	-
56657	SM104	BD 241C	BD 241C
56658	SM10D10	<75/<50mA	TAG 265-..., T 4700...
56659	SM10D10	<75/<50mA	TAG 265-..., T 4700...
56660	SM10D14..G14	SM 10D10..G10, 10A(Tc70°C)	-
56661	SM10G10	SM 10D10, 400V	TAG 265-..., T 4700...
56662	SM10G10	SM 10D10, 400V	TAG 265-..., T 4700...
56663	SM12D41	<50/<50mA	BTA 23-..., BT 138/..., TAG 255...
56664	SM12G41	SM 12D41, 400V	BTA 23-..., BT 138/..., TAG 255...
56665	SM12J41	SM 12D41, 600V	BTA 23-..., BT 138/..., TAG 255...
56666	)	6,8..220V, 1,5kW(1ms)	-
56667	A)	SM 15 T..(A), bidirecional	-
56668	SM16D14	<50/<50mA	-
56669	SM16D16	<50/<50mA	T 4700...
56670	SM16D16	<50/<50mA	T 4700...
56671	SM16G14	SM 16D14, 400V	-
56672	SM16G16	SM 16D16, 400V	T 4700...
56673	SM16G16	SM 16D16, 400V	T 4700...
56674	SM16J16	SM 16D16, 600V	T 4700...
56675	SM16J16	SM 16D16, 600V	T 4700...
56676	SM200	20V, Idss<10µA	SD 306
56677	SM21	BAV 21	BAV 21
56678	SM2B41	Igt/Ih15/<25mA	TAG 231-..., TAG 220-..., TAG 225-...,
56679	SM2D41	SM 2B41, 200V	TAG 231-..., TAG 220-..., TAG 225-...,
56680	SM2G41	SM 2B41, 400V	TAG 231-..., TAG 220-..., TAG 225-...,
56681	SM3B41	<30/<25mA	TAG 231-..., TAG 220-..., TAG 225-...,
56682	SM3D41	SM 3B41, 200V	TAG 231-..., TAG 220-..., TAG 225-...,
56683	SM3G41	SM 3B41, 400V	TAG 231-..., TAG 220-..., TAG 225-...,
56684	SM3J41	SM 3B41, 600V	TAG 231-..., TAG 220-..., TAG 225-...,
56685	SM400	M 42	M 42
56686	SM4001..4007	1N4001..4007, SMD	LRL 4001...4004
56687	SM4T6V8..220(A)	6,8..220V, 400W(1ms)	-
56688	A)	SM 4 T..(A), bidirecional	-
56689	SM5(c)	BU 100	BU 100
56690	SM513	EM 513, SMD	-
56691	SM516	EM 516, SMD	-
56692	SM518	EM 518, SMD	-
56693	SM5Z3V3..200A	3,3..200V, 5W(Tc25°)	-
56694	SM600	BA 157	BA 157
56695	SM6B14	<75/<30mA	TAG 260-..., TAG 265-..., T 4700...
56696	SM6B14	<75/<30mA	TAG 260-..., TAG 265-..., T 4700...
56697	SM6D14	SM 6B14, 200V	TAG 260-..., TAG 265-..., T 4700...
56698	SM6D14	SM 6B14, 200V	TAG 260-..., TAG 265-..., T 4700...
56699	SM6G14	SM 6B14, 400V	TAG 260-..., TAG 265-..., T 4700...

56700	SM6G14	SM 6B14, 400V	TAG 260-..., TAG 265-..., T 4700...
56701	SM6T6V8..220(A)	6,8..220V, 600W(1ms)	-
56702	A)	SM 6 T..(A), bidirecional	-
56703	SM8D41	<50/<50mA	MAC 222-..., TIC 226..., T 2802...
56704	SM8G41	SM 8D41, 400V	MAC 222-..., TIC 226..., T 2802...
56705	SM8J41	SM 8D41, 600V	MAC 222-..., TIC 226..., T 2802...
56706	SMBT2222(A)	2N2222(A), SMD	MMBT 2222(A)
56707	SMBT2907(A)	2N2907(A), SMD	MMBT 2907(A)
56708	SMBT3904	2N3904, SMD	MMBT 3904
56709	SMBT3906	2N3906, SMD	MMBT 3906
56710	SMBT4124	2N4124, SMD	MMBT 4124
56711	SMBT4126	2N4126, SMD	MMBT 4126
56712	SMBT5086	2N5086, SMD	MMBT 5086
56713	SMBT5087	2N5087, SMD	MMBT 5087
56714	SMBT6427	2N6427, SMD	MMBT 6427
56715	SMBT6428	2N6428, SMD	MMBT 6428
56716	SMBT6429	2N6429, SMD	MMBT 6429
56717	SMBTA05..06	MPSA 05..06, SMD	MMBTA 05...06
56718	SMBTA13..14	MPSA 13..14, SMD	MMBTA 13...14
56719	SMBTA20	MPSA 20, SMD	MMBTA 20
56720	SMBTA42..43	MPSA 42..43, SMD	MMBTA 42...43
56721	SMBTA55..56	MPSA 55..56, SMD	MMBTA 55...56
56722	SMBTA63..64	MPSA 63..64, SMD	MMBTA 63...64
56723	SMBTA70	MPSA 70, SMD	MMBTA 70
56724	SMBTA92..93	MPSA 92..93, SMD	MMBTA 92...93
56725	SMD10P05(L)	50V, 2A, 40W, <0,28Ohm(5A)	2SJ128, 2SJ133, 2SJ191, 2SJ194
56726	SMD10P06(L)	60V, 10A, 42W, <0,28Ohm(3A)	2SJ389
56727	SMD15N05	<0,10Ohm(7,5A)	2SK1113, 2SK1254, 2SK1282, 2SK1950
56728	SMD15N06	60V, 15A, 40W, <0,10Ohm(7,5A)	-
56729	SMD25N05-45L	<45mOhm(12,5A)	2SK1112, 2SK1471, 2SK1719, 2SK1949
56730	SMD30N03-30L	30V, 6A, 50W, <30mOhm(15A)	2SK1472, 2SK1557, 2SK1748, 2SK2415
56731	SME992	BF 992	BF 992
56732	SME994	BF 994	BF 994
56733	SME996	BF 996	BF 996
56734	SMH-08	1S1103	1S1103
56735	SMH-10	1S1104	1S1104
56736	SMH-16	1S1105	1S1105
56737	SMH-20	1S1106	1S1106
56738	SML1Q3..	300V, 1A, <80ns	BYX 92/300, EGP 10F...G, FE 1F...H
56739	SML3Q3..	300V, 3A, <50ns	EGP 30F...G, FE 3F...H
56740	SMM11P20	<0,5Ohm(6A)	2SJ200
56741	SMM20P10	<0,20Ohm(10A)	-
56742	SMM70N06	<18mOhm(35A)	2SK1259, 2SK1426
56743	SMM70N10	<25mOhm(45A)	-
56744	SMP11P20	<0,5Ohm(6A)	IRF 9640

56745	SMP20N20	<0,16Ohm(10A)	BUZ 30A
56746	SMP20P10	<0,2Ohm(12A)	2SJ221
56747	SMP25N05	<60mOhm(12,5A)	BUZ 22, IRF 540...543, 2SK 674, 2SK1417
56748	SMP25N05-45L	<45mOhm(12,5A)	BUK 555-50, 2SK1291, 2SK1296, 2SK2411
56749	SMP25N06	SMP 25N05, 60V	BUZ 22, IRF 540...543, 2SK 674, 2SK1417
56750	SMP2P20	<3Ohm(0,9A)	BUZ 173, IRF 9620, IRF 9622
56751	SMP30N10	<60mOhm(18A)	BUZ 22, BUK 456-100, 2SK1429, 2SK1293
56752	SMP3N50F	500V, 2,5A, 48W, <3Ohm(1,5A)	-
56753	SMP3P10	100V, 3A, 20W, <1,2Ohm(1,5A)	IRF 9510, IRF 9620...23, 2SJ151
56754	SMP40N10	<40mOhm(25A)	-
56755	SMP40P06	<45mOhm(20A)	-
56756	SMP4N60	<2Ohm(2A),<37/95ns	BUZ 90, 2SK1117, 2SK1402, 2SK1923...24
56757	SMP50N06-25	<25mOhm(25A)	BUK 556-60
56758	SMP5N50F	<1,5Ohm(2,5A)	BUZ 215...216, BUK 655-500
56759	SMP60N03-10L	<15mOhm(30A)	BUK 556-60
56760	SMP60N05	<23mOhm(30A)	BUK 556-60, BUZ 100
56761	SMP60N06	SMP 60N05, 60V	BUK 556-60, BUZ 100
56762	SMP60N06-14	<14mOhm(30A)	BUK 556-60, BUZ 100
56763	SMP60N06-18	<18mOhm(30A)	BUK 556-60, BUZ 100
56764	SMP7N60	<1,1Ohm(3,5A)	BUZ 91, BUK 657-600
56765	SMP8N50F	<0,85Ohm(4A)	BUK 657-500
56766	SMS120..1100	SB 120..1100, SMD	TMBYV 10-...
56767	SMS220..2100	SB 220..2100, SMD	-
56768	SMU10P..	SMD 10P..	SMD 10P...
56769	SMU15N..	SMD 15N..	SMD 15N...
56770	SMU25N..	SMD 25N..	SMD 25N...
56771	SMU30N..	SMD 30N..	SMD 30N...
56772	SMV751	BA 124	BA 124
56773	SMW12P20	<0,5Ohm(7,5A)	2SJ201
56774	SMW14N50F	<40mOhm(7A)	BUK 638-500
56775	SMW20P10	<0,2Ohm(13A)	-
56776	SMW45N10	<40mOhm(27A)	BUZ 344, 2SK1381...82, 2SK1434
56777	SMW60N06-18	<18mOhm(30A)	BUK439-60, 2SK1258, 2SK1382, 2SK1422
56778	SMW60N10	<25mOhm(37A)	BUZ 344, 2SK1382, 2SK1434
56779	SMW70N06-14	<14mOhm(35A)	2SK1423, 2SK1259, 2SK1426
56780	SMZ1..200	ZY 1..200, SMD	-
56781	SN	2SC3082K-N	2SC3082K
56782	SN	SMBT 3904	SMBT 3904
56783	SN	2SC4100-N	2SC4100
56784	SN	SM 4T 68	SM 4T...
56785	SN113	1N4007, 1600V	BY 228, BY 448, DM 513, EN 516, GP 10Y
56786	SN4	SM-1,5SN4	SM-1,5SN4
56787	SN4	SM-1XSN4	SM-1XSN4
56788	SN695-16	AF 125	AF 125
56789	SN7000	BS 170, 0,25A	BS 170

56790	SN7002	BS 170, SMD, 0,19A	PMBF 170, BST 82
56791	SO	2SA1162-O	2SA1162
56792	SO	SMBT 3906	SMBT 3906
56793	SO	2SC1832-O	2SA1832
56794	SO	2SA1586-O	2SA1586
56795	SO1613	2N1613, SMD	BCW 66, BCX 41, 2SD1782
56796	SO1613R		-
56797	SO1711	2N1711, SMD	BCW 66, BCX 41, 2SD1782
56798	SO1711R		-
56799	SO1893	2N1893, SMD	BCX 41
56800	SO1893R		-
56801	SO2221..2222(A)	2N2221..2222(A), SMD	BCW 65...66, PMBT 2222(A), SMBT 2222(A)
56802	SO2221..2222(A)R		-
56803	SO2369(A)	2N2369(A), SMD	PMBT 2369(A), 2SC4168
56804	SO2369(A)R		-
56805	SO245(A..C)	BF 245, SMD	-
56806	SO245(A..C)R	BF 245, SMD	BF 545
56807	SO2484	2N2484, SMD	BC 850, 2SC3323...3324
56808	SO2484R		-
56809	SO269	ESM 269, SMD	-
56810	SO269R		-
56811	SO2894	2N2894, SMD	2SA1607
56812	SO2894R		-
56813	SO2906..2907(A)	2N2906..2907(A), SMD	BCW 68, PMBT 2907(A), SMBT 2907(A)
56814	SO2906..2907(A)R		-
56815	SO3570..3572	2N3570..3572, SMD	2SC3014, 2SC3016, 2SC4082
56816	SO3570..3572R		-
56817	SO3903..3904	2N3903..3904, SMD	BC 846, PMBT 3903...04, SMBT 3904
56818	SO3903..3904R		-
56819	SO3905..3906	2N3905..3906, SMD	BC 856, PMBT 3905...06, SMBT 3906
56820	SO3905..3906R		-
56821	SO3966	2N3966, SMD	-
56822	SO3966R		-
56823	SO4091..4093	2N4091..4093, SMD	BSR 56...58
56824	SO4091..4093R		-
56825	SO4391..4393	2N4391..4393, SMD	BSR 56...58, PMBF 4391...4393
56826	SO4391..4393R		-
56827	SO4401	2N4401, SMD	BCW 65...66, PMBT 4401, 2SC3392
56828	SO4403	2N4403, SMD	BCW 68, PMBT 4403, 2SA1338
56829	SO4416	2N4416, SMD	-
56830	SO502S	BF 502S, SMD	BF 599, BF 799, BFS 20, 2SC3015
56831	SO502SR		-
56832	SO506	BF 506, SMD	BF 536, BF 568, BF 660
56833	SO506R		-
56834	SO517	BC 517, SMD	BCV 27, BCV 47



56835	SO5400..5401	2N5400..5401, SMD	-
56836	SO5400..5401R		-
56837	SO5432..5434	2N5432..5434, SMD	-
56838	SO5432..5434R		-
56839	SO5550..5551	2N5550..5551	-
56840	SO5550..5551R		-
56841	SO642	MPSA 42, SMD	MMBTA 42
56842	SO642R		-
56843	SO679	BF 679, SMD	BFS 17, 2SC3161
56844	SO679R		-
56845	SO692	MPSA 92..93, SMD	MMBTA 92...93
56846	SO692R		-
56847	SO918	2N918, SMD	BF 517, BFS 17, 2SC3016, 2SC3161
56848	SO918R		-
56849	SO930	2N930, SMD	BC 850, BCF 81, 2SC3323
56850	SO930R		-
56851	SO960	BF 960, SMD	-
56852	SO961	BF 961, SMD	-
56853	SO970	BF 970, SMD	BF 517, BFS 17, 2SC3016, 2SC3161
56854	SO970R		-
56855	SOA05..06	MPSA 05..06, SMD	MMBTA 05...06
56856	SOA55..56	MPSA 55..56, SMD	MMBTA 55...56
56857	SOBRY55	BRY 55, SMD	-
56858	Sp	BA 582	BA 582
56859	SP	2SC3082K-P	2SC3082K
56860	SP	BSS 84	BSS 84
56861	SP	2SC4100-P	2SC4100
56862	SP	SM 4T 68A	SM 4T...
56863	SP-1(K)	1N4007	1N4007
56864	SP0610L	19/30ns	BST 100, BS 208, BS 212
56865	SP0610T	SP 0610T, SMD	2SJ209...210
56866	SPF2038	TIS 88A	TIS 88A
56867	SPF2060	TIS 88(A)	TIS 88(A)
56868	SPs	BSS 84	BSS 84
56869	SPS5384	BD 529	BD 529
56870	SPS5418	MPSA 13	MPSA 13
56871	SPS5431	MPSA 65	MPSA 65
56872	SPS5491	BC 393	BC 393
56873	SQ	2SC3082K-Q	2SC3082K
56874	SQ	2SC4100-Q	2SC4100
56875	SR	2SC2405-R	2SC2405
56876	SR	BSS 131	BSS 131
56877	SR	2SC3929-R	2SC3929
56878	SRP100A..K	50..800V, 1A, <100..200ns	BYT 11/..., BYV 26/..., BYV 96/...
56879	SRP10A..K	SRP 100A..K	SRP 100A...K

56880	SRP300A..K	50..800V, 3A, <100..200ns	BYT56/..., BYW95/..., BYW96/..., BYW16/...
56881	SRP30A..K	SRP 300A..K	SRP 300A...K
56882	SRP600A..K	50..800V, 6A, <100..200ns	BY 500/..., EGP 50A...G, MR 820...824
56883	SRs	BSS 131	BSS 131
56884	SS	BSS 138	BSS 138
56885	SS	2SC2405-S	2SC2405
56886	SS	2SC3929-S	2SC3929
56887	SS05J25	250V, 0,5A, 200ns	-
56888	SS1.5J4..J5	J440, J5	
56889	SS100	BSS 100	BSS 100
56890	SS100	BC 307	BC 307
56891	SS101	BSS 101	BSS 101
56892	SS101	-/33V, 0,05A, 0,25W	BC 212, BC 257, BC 307, BC 557
56893	SS102	SS 101, -/66V	BC 212, BC 256, BC 266, BC 556
56894	SS106	25V, 0,2A, 0,3W, <40/75ns	BSS 11...12, 2N3011, 2N2368...69(A)
56895	SS108	SS 106, 40V	BSS 11, BSX 19...20, 2N2368...69(A)
56896	SS109	SS 106, 20V	BSS 10...11, 2N3011, 2N2368...69(A)
56897	SS10SJ9	90V, 10A, 150ns	-
56898	SS110	BSS 110	BSS 110
56899	SS120	60V, 0,6A, 0,8W	BC 140...141, 2N2218...2219(A)
56900	SS124	BSS 124	BSS 124
56901	SS125	BSS 125	BSS 125
56902	SS125	30V, 0,5A, 0,6W	BC 140...141, 2N2218...2219(A)
56903	SS126	SS 125, 60V	BC 140...141, 2N2218...2219(A)
56904	SS129	BSS 129	BSS 129
56905	SS135	BSS 135	BSS 135
56906	SS149	BSS 149	BSS 149
56907	SS15SJ4..SJ6	40..60V, 15A, 150ns	-
56908	SS1J2..J9	J220, J3U	BYV 10-20...-60
56909	SS200	70V, 0,03A, 0,15W	BF 297...299, BF 422, BSS 38, BSX 21
56910	SS201	SS 200, 100V	BF 297...299, BF 422, BSS 38, BSX 21
56911	SS202	SS 200, 120V	BF 297...299, BF 422, BSS 38, BSX 21
56912	SS20SJ9	90V, 20A	-
56913	SS216	20V, 0,1A, 0,2W, <100/500ns	BSV 89...92, BSX 92...93, 2N2368...69
56914	SS218	SS 216, <35/60ns	BSV 89...92, BSX 92...93, 2N2368...69
56915	SS219	SS 216, 35/30ns	BSV 89...92, BSX 92...93, 2N2368...69
56916	SS229	BSS 229	BSS 229
56917	SS25JK6	60V, 25A, 150ns	-
56918	SS25JK6	60V, 25A, 150ns	-
56919	SS295	BSS 295	BSS 295
56920	SS296	BSS 296	BSS 296
56921	SS297	BSS 297	BSS 297
56922	SS2J9	90V, 2A, 30ns	-
56923	SS30JK3U..JK4	JK3U30V(-	BYV 73-30...-45, MBR 3035PT...3060PT
56924	SS30JK3U..JK4	JK3U30V(-	BYV 73-30...-45, MBR 3035PT...3060PT

56925	SS30SJ4..SJ6	40..60V, 30A	MBR 4040, 1N5834
56926	SS3J3U..J6	J3U30V(--	
56927	SS60SJ4..SJ6	40..60V, 60A	-
56928	SS8050(B...D)	40V, 1,5A, 1W, 190MHz	MPS 650...651, 2SD1207, 2SD1227, 2SD1331
56929	SS8550(B...D)	40V, 1,5A, 1W, 120MHz	MPS 750...751, 2SB892, 2SB911, 2SB978
56930	SS88	BSS 88	BSS 88
56931	SS89	BSS 89	BSS 89
56932	SS9011(D...I)	50V, 0,03A, 0,4W, 370MHz	BC 237, BC 547, BF 240...41, BF 254...55
56933	SS9012(D...H)	40V, 0,5A, 0,625W	BC 327, BC 636, BC 638, BC 640
56934	SS9013(D...H)	40V, 0,5A, 0,625W	BC 337, BC 635, BC 637, BC 639
56935	SS9014(A...D)	50V, 0,1A, 0,45W, 270MHz	BC 414, BC 550, 2SC2240, 2SC2675
56936	SS9015(A...C)	50V, 0,1A, 0,45W, 190MHz	BC 416, BC 560, 2SA970, 2SA1137
56937	SS9016(D...I)	30V, 25mA, 0,4W, 620MHz	BF 240...241, BF 254...255, BF 594...595
56938	SS9018(D...I)	30V, 0,05A, 0,4W, 1100MHz	BF 225, BF 255, BF 314, BF 505, BF 507
56939	SS92	BSS 92	BSS 92
56940	SS98	BSS 98	BSS 98
56941	SSE200	SS 200, SMD	BC 846, BCV 71...72, BSS 64, BSR 19(A)
56942	SSE201	SS 201, SMD	BSS 64, BSR 19(A), 2SC3340, 2SC4050
56943	SSE202	SS 202, SMD	BSS 64, BSR 19(A), 2SC3340, 2SD4050
56944	SSE216	SS 216, SMD	BSV 52, 2SC3578, 2SC3757
56945	SSE219	SS 219, SMD	BSV 52, 2SC3578, 2SC3757
56946	SSE350	60V, 0,5A, B>2000	BCV 49, BST 51...52, 2SD1625
56947	SSE351	SSE 350, 80V	BCV 49, BST 51...52, 2SD1625
56948	SSE352	SSE 350, 90V	BST 52
56949	SSE360	60V, 0,5A, B>2000	BCV 48, BST 61...62, 2SB1125
56950	SSE361	SSE 360, 80V	BCV 48, BST 61...62, 2SB1125
56951	SSE362	SSE 360, 90V	BST 62
56952	SSH10N05	50V, 10A, 75W, <0,28Ohm(5A)	2SK399, 2SK500, 2SK631
56953	SSH10N06	SSH 10N05, 60V	2SK399, 2SK500, 2SK631
56954	SSH10N08	80V, 10A, 75W, <0,33Ohm(5A)	2SK399, 2SK631
56955	SSH10N10	SSH 10N08, 100V	2SK399, 2SK631
56956	SSH10N70	<0,9Ohm(5A)	2SK1796, 2SK1933
56957	SSH12N05	50V, 12A, 75W, <0,20Ohm(6A)	2SK572
56958	SSH12N06	SSH 12N05, 60V	2SK572
56959	SSH12N08	80V, 12A, 75W, <0,18Ohm(6A)	2SK572
56960	SSH12N10	SSH 12N08, 100V	2SK572
56961	SSH15N55	<0,45Ohm(8A)	2SK1573
56962	SSH15N60	SSH 15N55, 600V	2SK1573
56963	SSH20N45	<0,25Ohm(13A)	2SK1169...70, 2SK1497...1500, 2SK1680
56964	SSH20N50	SSH 20N45, 500V	2SK1170, 2SK1498, 2SK1500, 2SK1680
56965	SSH25N35	<0,20Ohm(13A)	2SK1497...1500
56966	SSH25N40	SSH 25N35, 400V	2SK1497...1500
56967	SSH3N70	700V, 3A, 75W, <5Ohm(1,5A)	BUZ 307, 2SK726, 2SK954, 2SK1339
56968	SSH40N15	<65mOhm(20A)	-
56969	SSH40N20	SSH 40N15, 200V	-

56970	SSH4N45	450V, 4A, 75W, <1,5Ohm(2A)	2SK1213, 2SK1403
56971	SSH4N50	SSH 4N45, 500V	2SK1213, 2SK1403
56972	SSH4N55	550V, 4A, 75W, <2,5Ohm(2A)	2SK1213, 2SK1403
56973	SSH4N60	SSH 4N55, 600V	2SK1213, 2SK1403
56974	SSH4N70	700V, 4A, 125W, <2,5Ohm((2A)	2SK695, 2SK727, 2SK793, 2SK1760
56975	SSH5N35	350V, 5A, 75W, <1Ohm(2,5A)	2SK2264
56976	SSH5N40	SSH 5N35, 400V	2SK2264
56977	SSH60N06	<25mOhm(30A)	BUK 539-60, 2SK1258, 2SK1379, 2SK1422
56978	SSH60N10	SSH 60N06, 100V	2SK1381, 2SK1434
56979	SSH6N55	550V, 6A, 125W, <1,2Ohm(3A)	BUZ 332A, BUZ 305, 2SK684, 2SK1032
56980	SSH6N60	SSH 6N55, 600V	BUZ 332A, BUZ 305, 2SK684, 2SK1032
56981	SSH6N70	700V, 6A, 150W, <1,4Ohm(3A)	BUZ 305, 2SK684, 2SK1032
56982	SSH7N12	120V, 7A, 75W, <0,7Ohm(3,5A)	2SK405, 2SK631, 2SK633, 2SK1529
56983	SSH7N15	SSH 7N12, 150V	2SK405, 2SK631, 2SK633, 2SK1529
56984	SSH7N18	180V, 7A, 75W, <0,7Ohm(3,5A)	2SK400, 2SK633, 2SK1529
56985	SSH7N20	SSH 7N18, 200V	2SK400, 2SK633
56986	SSH8N12	120V, 8A, 75W, <0,5Ohm(4A)	2SK405, 2SK631, 2SK633, 2SK1529
56987	SSH8N15	SSH 8N12, 150V	2SK405, 2SK631, 2SK633, 2SK1529
56988	SSH8N18	180V, 8A, 75W, <0,4Ohm(4A)	2SK400, 2SK633, 2SK1529
56989	SSH8N20	SSH 8N18, 200V	2SK400, 2SK633
56990	SSH8N55	550V, 8A, 150W, <0,5Ohm(4A)	BUZ 332A, BUZ 334, 2SK1968
56991	SSH8N60	SSH 8N55, 600V	BUZ 332A, BUZ 334, 2SK1968
56992	SSiA16-H010	10kV, 14mA	-
56993	SSiA16-H012	SSi A16-H010, 12kV	-
56994	SSiA19-H025	25kV, 7mA	-
56995	SSiA19-H030	SSi A19-H025, 30kV	-
56996	SSiA19-H034	SSi A19-H025, 34kV	-
56997	SSiB0510	150V, 1,1..2,8A	BY 251, BYW 17/200, BYW 82, 1N5402
56998	SSiB0520	SSi B 0510, 300V	BY 252, BYW 17/400, BYW 83, 1N5403
56999	SSiB0540	SSi B 0510, 600V	BY 253, BYW 17/600, BYW 84, 1N5406
57000	SSiB0580	SSi B 0510, 1000V	BY 255, BYW 17/1000, BYW 86, 1N5408
57001	SSiB0810	130V, 0,1A	BA 157...159, BAY 20...21, 1N4003...07
57002	SSiB0830	SSi B 0810, 400V	BA 157...159, BAY 89...91, 1N4004...07
57003	SSiB0850	SSi B 0810, 650V	BA 159, BAY 90...91, 1N4006...07
57004	SSiB0880	SSi B 0810, 1000V	BA 159, BAY 90...91, 1N4007
57005	SSiC0810	150V, 1,9A	BY 251, BY 259/150, GP 20D, 1N5060
57006	SSiC0820	SSi C0810, 300V	BY 252, BY 259/300, GP 20G, 1N5060
57007	SSiC0840	SSi C0810, 600V	BY 253, BY 259/600, GP 20J, 1N5061
57008	SSiC0860	SSi C0810, 900V	BY 255, BY 259/900, BYW 56, GP 20M
57009	SSiC0880	SSi C0810, 1000V	BY 255, BY 259/1000, BYW 56, GP 20M
57010	SSiC1710	150V, 1,45..3,8A	BY 251, BYW 17/200, BYW 82, 1N5402
57011	SSiC1720	SSi C 1710, 300V	BY 252, BYW 17/400, BYW 83, 1N5403
57012	SSiC1740	SSi C 1710, 600V	BY 253, BYW 17/600, BYW 84, 1N5406
57013	SSiC1760	SSi C 1710, 900V	BY 255, BYW 17/1000, BYW 86, 1N5408
57014	SSiC1780	SSi C 1710, 1000V	BY 255, BYW 17/1000, BYW 86, 1N5408

57015	SSiC2620	RGP 30M	RGP 30M
57016	SSiC2630(B)	RGP 30M	RGP 30M
57017	sSJ	BSS 7728	BSS 7728
57018	SSM10N..	SSH 10N..	SSH 10N...
57019	SSM12N..	SSH 12N..	SSH 12N...
57020	SSM15N..	SSH 15N.., 200W	SSH 15N...
57021	SSM20N..	SSH 20N.., 200W	SSH 20N...
57022	SSM25N..	SSH 25N.., 200W	SSH 25N...
57023	SSM3N..	SSH 3N..	SSH 3N...
57024	SSM40N..	SSH 40N.., 200W	SSH 40N...
57025	SSM4N..	SSH 4N..	SSH 4N...
57026	SSM5N..	SSH 5N..	SSH 5N...
57027	SSM60N..	SSH 60N.., 200W	SSH 60N...
57028	SSM6N..	SSH 6N..	SSH 6N...
57029	SSM7N..	SSH 7N..	SSH 7N...
57030	SSM8N..	SSH 8N..	SSH 8N...
57031	SSP10N05..N10	SSH 10N05..10	BUZ 20, BUZ 72, 2SK918, 2SK921, 2SK1300
57032	SSP12N05..N10	SSH 12N05..10	IRF 530, 2SK919, 2SK922, 2SK1301
57033	SSP1N45	<8,5Ohm(0,6A)	BUZ 74, IRF 820, 2SK892, 2SK1053
57034	SSP1N50	SSP 1N45, 500V	BUZ 74, IRF 820, IRF 822, 2SK892
57035	SSP1N55	550V, 1A, 50W, <12Ohm(0,5A)	BUZ 78, 2SK602
57036	SSP1N60	SSP 1N55, 600V	BUZ 78, 2SK602
57037	SSP3N70	SSH 3N70	BUK 456-800, BUZ 81, 2SK513, 2SK1600
57038	SSP4N45..N50	SSH 4N45..50	BUZ 41...42, IRF 830, 2SK1156, 2SK1246
57039	SSP4N55..N60	SSH 4N55..60	BUZ 90, 2SK1117, 2SK1402, 2SK1809
57040	SSP4N70	SSH 4N70	BUZ 81, 2SK1501, 2SK1639, 2SK1809
57041	SSP5N35..N40	SSH 5N35..40	BUZ 60, IRF 830, 2SK1156, 2SK1246
57042	SSP6N55..N60	SSH 6N55..60	BUK 657-600, BUZ 91
57043	SSP7N12..N20	SSH 7N12..20	BUK 554-200, BUZ 30, BUZ 73, IRF 630
57044	SSP8N12..N20	SSH 8N12..20	BUK 554-200, BUZ 30, BUZ 73, IRF 630
57045	SSR1N45..N50	SSP 1N45..50	2SK580, 2SK1152, 2SK1672, 2SK2017
57046	SSR1N55..N60	SSP 1N55..60	2SK1327, 2SK1880
57047	SSs	BSS 138	BSS 138
57048	SSS2N90	900V, 2A	2SK1143, 2SK1174, 2SK1275, 2SK1459
57049	SSS4N55	550V, 2,7A, 35W, <2,5Ohm(2A)	2SK1572, 2SK1767, 2SK2144
57050	SSS4N60	SSS 4 N55, 600V	2SK1572, 2SK1767, 2SK2144
57051	SSS6N55	550V, 3,4A, 40W, <1,8Ohm(3A)	2SK1118, 2SK1404, 2SK1637, 2SK2118
57052	SSS6N60	SSS 6 N55, 600V	2SK1118, 2SK1404, 2SK1637, 2SK2118
57053	SST108	J 108, SMD	PMBFJ 108
57054	SST109	J 109, SMD	PMBFJ 109
57055	SST110	J 110, SMD	PMBFJ 110
57056	SST111	J 111, SMD	BSR 111, PMBFJ 111
57057	SST112	J 112, SMD	BSR 112, PMBFJ 112
57058	SST113	J 113, SMD	BSR 113, PMBFJ 113
57059	SST1130	30V, 0,2A	BCW 60, BCX 70, 2SC4209

57060	SST1139	30V, 30mA, >850MHz	BF 517, BF 547, BFS 17, 2SC3014, 2SC3016
57061	SST174	J 174, SMD	BSR 174, PMBFJ 174
57062	SST175	J 175, SMD	BSR 175, PMBFJ 175
57063	SST176	J 176, SMD	BSR 176, PMBFJ 176
57064	SST177	J 177, SMD	BSR 177, PMBFJ 177
57065	SST201	J 201, SMD	-
57066	SST202	J 202, SMD	-
57067	SST204	J 204, SMD	-
57068	SST213	SD 213DE	-
57069	SST215	SD 215DE	-
57070	SST2222(A)	2N2222(A), SMD	MMBT 2222(A)
57071	SST270	J 270, SMD	-
57072	SST271	J 271, SMD	-
57073	SST2907(A)	2N2907(A), SMD	MMBT 2907(A)
57074	SST308	J 308, SMD	-
57075	SST309	J 309, SMD	-
57076	SST310	J 310, SMD	-
57077	SST3904	2N3904, SMD	MMBT 3904
57078	SST3906	2N3906, SMD	MMBT 3906
57079	SST4117	2N4117, SMD	-
57080	SST4118	2N4118, SMD	-
57081	SST4119	2N4119, SMD	-
57082	SST4124	2N4124, SMD	MMBT 4124
57083	SST4126	2N4126, SMD	MMBT 4126
57084	SST4391	2N4391, SMD	BSR 56, PMBF 4391, SO 4391
57085	SST4392	2N4392, SMD	BSR 57, PMBF 4392, SO 4392
57086	SST4393	2N4393, SMD	BSR 58, PMBF 4393, SO 4393
57087	SST4400	2N4400, SMD	MMBT 4400
57088	SST4401	2N4401, SMD	MMBT 4401
57089	SST4403	2N4403, SMD	MMBT 4403
57090	SST4416	2N4416, SMD	-
57091	SST5086	2N5086, SMD	MMBT 5086
57092	SST5087	2N5087, SMD	MMBT 5087
57093	SST5088	2N5088, SMD	MMBT 5088
57094	SST5089	2N5089, SMD	MMBT 5089
57095	SST5101	60V, 0,2A, >125MHz	MMBT 55...56, 2SA1620
57096	SST5210	2N5210, SMD	MMBT 5210
57097	SST5424	30V, 50mA, >600MHz	BF 517, BF 547, BFS 17, 2SC3014, 2SC3016
57098	SST5484	2N5484, SMD	-
57099	SST5485	2N5485, SMD	-
57100	SST5486	2N5486, SMD	-
57101	SST6426	2N6426, SMD	MMBT 6426
57102	SST6427	2N6427, SMD	MMBT 6427
57103	SST6428	2N6428, SMD	MMBT 6428
57104	SST6838	50V, 0,2A, >50MHz	MMBT 05...06, 2SC4209



57105	SST6839	50V, 0,2A, >50MHz	MMBT 55...56, 2SA1620
57106	SST7157	60V, 0,2A	MMBT 55...56, 2SA1620
57107	SST7208	60V, 0,1A, 180MHz	BC 846, BCV 71...72, 2SC3323...24
57108	SST8245	30V, 50mA, >600MHz	BF 517, BF 547, BFS 17, 2SC3014, 2SC3016
57109	SST8598	MPS 8598, SMD	BCW 68, MMBTA 55...56, 2SB1198
57110	SST918(S)	2N918(S), SMD	MMBT 918
57111	SSTA05	MPSA 05, SMD	MMBTA 05
57112	SSTA06	MPSA 06, SMD	MMBTA 06
57113	SSTA13	MPSA 13, SMD	MMBTA 13
57114	SSTA14	MPSA 14, SMD	MMBTA 14
57115	SSTA20	MPSA 20, SMD	MMBTA 20
57116	SSTA28	MPSA 28, SMD	MMBTA 28
57117	SSTA29	MPSA 29, SMD	MMBTA 29
57118	SSTA55	MPSA 55, SMD	MMBTA 55
57119	SSTA56	MPSA 56, SMD	MMBTA 56
57120	SSTA63	MPSA 63, SMD	MMBTA 63
57121	SSTA64	MPSA 64, SMD	MMBTA 64
57122	SSTA70	MPSA 70, SMD	MMBTA 70
57123	SSTPAD100	30V, 10mA, Ir<100pA(20V)	-
57124	SSTPAD5	30V, 10mA, Ir<5pA(20V)	-
57125	SSTTIS93	TIS 93, SMD	BC 807, BCW 68, MMBTA 55...56, 2SA1313
57126	SSTTIS97	TIS 97, SMD	2SC3323...24
57127	SSU1N45..N50	SSP 1N45..50	2SK580, 2SK1152, 2SK1672, 2SK2017
57128	SSU1N55..N60	SSP 1N55..60	2SK1327, 2SK1880
57129	SSX	KSC2982	KSC2982
57130	SSY20	60V, 0,6A, 0,7W, <50/100ns	BSS 27, BSV 77, BSV 95, 2N5189
57131	ST	2SC4453	2SC4453
57132	ST	2SC2405-T	2SC2405
57133	ST	2SC3929-T	2SC3929
57134	ST	2SC4452	2SC4452
57135	ST(s)	BSS 139	BSS 139
57136	ST2	Ub28..36V, Ib<0,2mA	-
57137	ST3904	2N3904	2N3904
57138	ST3906	2N3906	2N3906
57139	ST4	ST2	-
57140	ST5771(-1,-2)	2N5771	2N5771
57141	STH12N60	<0,6Ohm(6A)	BUZ 334, IRFPC 50, 2SK1723
57142	STH12N60	<0,6Ohm(6A)	BUZ 334, IRFPC 50, 2SK1723
57143	STH12N60FI	STH 12N60, , 7A, 70W	2SK1464, 2SK1685, 2SK1774...75
57144	STH14N50	<0,45Ohm(7,5A)	BUZ 338, 2SK1678, 2SK1745
57145	STH14N50	<0,45Ohm(7,5A)	BUZ 338, 2SK1678, 2SK1745
57146	STH14N50FI	STH 14N50, , 8,8A, 70W	2SK1329, 2SK1523, 2SK1696, 2SK1832
57147	STH15N50	<0,40Ohm(7,5A)	BUZ 338, 2SK1678, 2SK1745
57148	STH15N50FI	STH 15N50, , 9,3A, 70W	2SK1329, 2SK1523, 2SK1696, 2SK1832
57149	STH26N25	<0,11Ohm(13A)	2SK902, 2SK1675...76

57150	STH26N25FI	STH 26N25, , 16A, 70W	2SK820, 2SK822, 2SK1549, 2SK2008
57151	STH33N20	<85mOhm(16A)	2SK851, 2SK902, 2SK1675...76
57152	STH33N20FI	STH 33N20, , 20A, 70W	2SK822, 2SK1549, 2SK2008
57153	STH45N10	<40mOhm(22,5A)	BUZ 344, 2SK1381, 2SK1434
57154	STH45N10FI	STH 45N10, , 27A, 60W	2SK1435
57155	STH4N80	<30hm(1,7A)	2SK534, 2SK604, 2SK695, 2SK793
57156	STH4N80FI	STH 4N80, , 2,8A, 55W	BUK 428-800, 2SK1683
57157	STH4N90	<3,20hm(1,7A)	2SK794, 2SK1341, 2SK1760, 2SK1794
57158	STH4N90FI	STH 4N90, , 2,7A, 55W	2SK1683
57159	STH55N10	<30mOhm(30A)	2SK1382, 2SK1437
57160	STH55N10FI	STH 55N10, , 33A, 70W	2SK1435
57161	STH5N90	<2,40hm(2,5A)	2SK794, 2SK1341, 2SK1760, 2SK1794
57162	STH5N90FI	STH 4N90, , 3,5A, 60W	2SK1175, 2SK1463, 2SK1684, 2SK2147
57163	STH60N10	<25mOhm(30A)	2SK1382, 2SK1437
57164	STH60N10FI	STH 60N10, , 36A, 70W	2SK1149, 2SK1436
57165	STH65N05	<20mOhm(32,5A)	2SK1259, 2SK1426
57166	STH65N06	STH 65N05, 60V	2SK1259, 2SK1426
57167	STH65N06FI	STH 65N05, , 60V, 37A, 60W	2SK1149, 2SK1424, 2SK1436, 2SK2203
57168	STH6N100	1000V, 6A, 180W, <20hm(3A)	2SK1120, 2SK1934
57169	STH6N100FI	STH 6N100, , 3,7A, 70W	2SK1770
57170	STH6NA80	<2,40hm(3A)	BUK 638-800, 2SK1032
57171	STH6NA80FI	STH 6NA80, , 3,7A, 60W	2SK1175, 2SK1463, 2SK1684, 2SK2147
57172	STH75N05	<14mOhm(40A)	2SK1259, 2SK1426
57173	STH75N05FI	STH 75N05, , 48A, 70W	2SK1436, 2SK1666, 2SK2203
57174	STH7N90	<1,40hm(3,5A)	2SK1358, 2SK1462, 2SK1692, 2SK1795
57175	STH7N90FI	STH 7N90, , 4,5A, 70W	2SK1175, 2SK1463, 2SK1684, 2SK2147
57176	STH80N05	<12mOhm(40A)	2SK1259, 2SK1426
57177	STH80N05FI	STH 80N05, , 52A, 70W	2SK1436, 2SK1666, 2SK2203
57178	STH8N80	<1,20hm(4A)	2SK1358, 2SK1462, 2SK1692, 2SK1795
57179	STH8N80FI	STH 8N80, , 5,1A, 70W	2SK1464, 2SK1685, 2SK1774...75
57180	STH9N80	800V, 9A, 180W, <10hm(4,5A)	2SK1796, 2SK1933
57181	STH9N80FI	STH 9N80, , 5,6A, 70W	2SK1464, 2SK1685, 2SK1774...75
57182	STHI07N50	500V, 7A, 100W	GN 6010A, IGT 4 E10...E11
57183	STHI07N50R	STHI 07N50	GT 15J102
57184	STHI10N50	500V, 10A, 100W	GN 6015A, IGT 4 E10...E11
57185	STHI10N50R	STHI 10N50	GT 15J102
57186	STHV102	<3,50hm(2A)	BUZ 357...358, BUZ 312, 2SK1359
57187	STHV102FI	STHV 102, , 2,6A, 60W	2SK1770
57188	STHV102FI	STHV 102, , 2,6A, 60W	2SK1770
57189	STHV82	<20hm(2,5A)	2SK794, 2SK1341, 2SK1760, 2SK1794
57190	STHV82FI	STHV 82, , 3,6A, 60W	2SK1175, 2SK1463, 2SK1684, 2SK2147
57191	STK12N05L	50V, 12A, 50W, <0,150hm(6A)	BUK 552-50, 2SK971, 2SK1301, 2SK1559
57192	STK12N06L	STK 12N05, 60V	BUK 552-60, 2SK971, 2SK1301, 2SK1559
57193	STK14N05	50V, 14A, 50W, <0,120hm(7A)	BUK 552-50, 2SK971, 2SK1416, 2SK1559
57194	STK14N06	STK 14N05, 60V	BUK 552-60, 2SK888, 2SK1301, 2SK1559

57195	STK14N10	<0,14Ohm(7A)	2SK888, 2SK919, 2SK1301, 2SK1559
57196	STK16N10L	<0,12Ohm(8A)	2SK1301, 2SK1559, 2SK1561
57197	STK17N10	<0,11Ohm(8,5A)	BUZ 21, IRF 540, IRF 542, 2SK1428
57198	STK18N05	50V, 18A, 60W, <85mOhm(9A)	BUZ 10, IRF 540...543, 2SK674, 2SK1417
57199	STK18N05L..06L	STK 18N05..06	2SK972, 2SK1115, 2SK1287, 2SK1910
57200	STK18N06	STK 18N05, 60V	BUZ 21, IRF 540...543, 2SK674, 2SK1417
57201	STK22N05	<65mOhm(11A)	BUZ 10, IRF 540...543, 2SK674, 2SK1417
57202	STK22N06	STK 22N05, 60V	BUZ 21, IRF 540...543, 2SK674, 2SK1417
57203	STK23N05L	50V, 23A, 65W, <55mOhm	2SK972, 2SK1115, 2SK1287, 2SK1910
57204	STK23N06L	STK 23N05L, 60V	2SK972, 2SK1115, 2SK1287, 2SK1910
57205	STK2N50	500V, 2A, 50W, <6Ohm(1A)	BUZ 40, BUZ 74, IRF 820...821, 2SK892
57206	STK2N60	600V, 1,7A, 50W, <8Ohm(1A)	BUZ 80, 2SK858, 2SK1323...24, 2SK1922
57207	STK2N80	800V, 2,1A, 70W, <7Ohm(1A)	BUZ 80, 2SK1199, 2SK1323, 2SK1338
57208	STK3055E	60V, 12A, 50W, <0,15Ohm(6A)	MTP 3055V
57209	STK3N50	<3,8Ohm(1,5A)	2SK1154, 2SK1244, 2SK1494
57210	STK4N30	300V, 4,2A, 60W, <1,4Ohm(2A)	BUZ 41, IRF 830, 2SK1246, 2SK1751
57211	STK4N30L	STK 4N30, <1,4Ohm(2,5A)	-
57212	STK4N40	400V, 3,7A, 60W, <2,2Ohm(2A)	BUZ 41, IRF 830, 2SK1246, 2SK1751
57213	STK6N20	200V, 6A, 55W, <0,7Ohm(3A)	BUZ 73, 2SK741, 2SK1319, 2SK1667
57214	STK9N10	100V, 9A, 50W, <0,3Ohm(4,5A)	BUZ 20, BUZ 72, 2SK740, 2SK1427
57215	STLT19	50V, 15A, 75W, 80/75ns	2SK971
57216	STLT19FI	STLT 19	2SK943, 2SK1214
57217	STLT20	STLT 19, 60V	2SK971
57218	STLT20FI	STLT 20	2SK943, 2SK1214
57219	STLT29	50V, 25A, 100W, 235/130ns	-
57220	STLT30	STLT 29, 60V	-
57221	STO5-16	Ur13,6V, Ubr16V, Pbr500W	BZW06/13, BZW70/13, BZX70/13, BZY93/13
57222	STO5-27	Ur23V, Ubr27V, Pbr500W	BZY93/C24
57223	STP15N05..06LFI	STP 15N05L..06L, , 10A, 35W	2SK1093, 2SK1256, 2SK1344, 2SK1895
57224	STP15N05L	50V, 15A, 70W, <0,15Ohm	BUK 552-50, 2SK971, 2SK1555, 2SK2175
57225	STP15N06L	STP 15N05L, 60V	BUK 552-60, 2SK971, 2SK1301, 2SK2175
57226	STP18N10	<0,14Ohm(9A)	BUZ 21, IRF 540, IRF 542, 2SK1428
57227	STP18N10FI	STP 18N10, , 11A, 40W	BUK 545-100, 2SK1230, 2SK1430, 2SK1904
57228	STP20N06	<85mOhm(10A)	IRF 540...43, 2SK600, 2SK674, 2SK1417
57229	STP20N06FI	STP 20N06, , 13A, 35W	BUK 445-100, 2SK1286, 2SK1419, 2SK1896
57230	STP20N10	<0,12Ohm(10A)	BUZ 21, IRF 540, IRF 542, 2SK1116
57231	STP20N10L	STP 20N10	BUK 555-100, 2SK1116, 2SK1302, 2SK1347
57232	STP20N10LFI	STP 20N10	2SK1034, 2SK1288, 2SK1306, 2SK1558
57233	STP21N05..06LFI	STP 21N05L..06L, , 14A, 35W	2SK1094, 2SK1286, 2SK1896
57234	STP21N05L	<85mOhm(10A)	2SK972, 2SK1115, 2SK1287, 2SK1910
57235	STP21N06L	STP 21N05L, 60V	2SK972, 2SK1115, 2SK1287, 2SK1910
57236	STP25N05	<65mOhm(12,5A)	BUK 555-50, 2SK1291, 2SK1296, 2SK2411
57237	STP25N05..06FI	STP 25N05..06, , 16A, 40W	BUK 445-100, 2SK1286, 2SK1419, 2SK1896
57238	STP25N06	STP 25N05, 60V	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
57239	STP2N60	<3,5Ohm(1,5A)	BUK 456/800, 2SK513, 2SK1600

57240	STP2N60FI	STP 2N60, , 2,2A, 35W	BUK 445-600, 2SK1142, 2SK1834, 2SK1953
57241	STP2N80	800V, 2,4A, 90W, <7Ohm(1A)	BUK 456/800, 2SK513, 2SK1600, 2SK1638
57242	STP2N80FI	STP 2N80, , 1,5A, 35W	BUK 446-800, 2SK1142, 2SK1611, 2SK1834
57243	STP30N05	<50mOhm(15A)	BUK 555-50, 2SK1291, 2SK1296, 2SK2411
57244	STP30N05..06FI	STP 30N05..06, , 19A, 40W	2SK943, 2SK1095, 2SK1345, 2SK2232
57245	STP30N06	STP 30N05, 60V	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
57246	STP32N05..06LFI	STP 32N05L..06L, , 19A, 40W	2SK943, 2SK1095, 2SK1345, 2SK2232
57247	STP32N05L	50V, 32A, 105W, <55mOhm	BUK 555-50, 2SK1291, 2SK1296, 2SK2411
57248	STP32N06L	STP 32N05L, 60V	BUK 555-60, 2SK1291, 2SK1296, 2SK2411
57249	STP33N10	<60mOhm(17A)	BUK 456-100, BUZ 22
57250	STP33N10FI	STP 33N10, , 18A, 45W	2SK1307, 2SK1345, 2SK1432, 2SK1906
57251	STP36N05..06LFI	40W	2SK1345, 2SK1882, 2SK2232, 2SK2346
57252	STP36N05L	50V, 36A, 120W, <40mOhm	BUZ 102AL, 2SK1542
57253	STP36N06	<40mOhm(18A)	PRFZ 42, 2SK856, 2SK1542
57254	STP36N06FI	STP 36N05L, , 60V, 21A, 40W	2SK1345, 2SK1420, 2SK1882, 2SK2232
57255	STP36N06L	STP 36N05L, 60V	2SK1542
57256	STP3N100	<5Ohm(1,5A)	-
57257	STP3N50XI	500V, 1,7A, 25W, <4Ohm(1,5A)	BUK 444-500, 2SK1833, 2SK1989
57258	STP3N60FI	<2,2Ohm(1,5A)	BUK 445-600, 2SK1758, 2SK1953, 2SK2043
57259	STP3N60XI	<2,5Ohm(1,5A)	BUK 445-600, 2SK1758, 2SK1953, 2SK2043
57260	STP3N80XI	<4,5Ohm(1,7A)	BUK 446-800, 2SK1142, 2SK1611, 2SK1834
57261	STP3N90	<4,5Ohm(1,7A)	BUK456-1000, 2SK1456, 2SK1601, 2SK1638
57262	STP40N05	<35mOhm(20A)	BUZ 12, BUZ 102, 2SK856, 2SK1542
57263	STP40N05..06FI	STP 40N05..06, , 23A, 40W	2SK1345, 2SK1882, 2SK2232, 2SK2346
57264	STP40N06	STP 40N05, 60V	PRFZ 42, 2SK856, 2SK1542
57265	STP40N10	<40mOhm(20A)	-
57266	STP40N10FI	STP 40N10, , 23A, 40W	2SK1349, 2SK1432
57267	STP4N100	<3,5Ohm(2A)	2SK1119
57268	STP4N100FI	STP 4N100, , 2,2A, 40W	-
57269	STP4N100XI	<4Ohm(2A)	-
57270	STP4N40	400V, 4A, 75W, <2,1Ohm(2A)	BUZ 60, IRF 730, 2SK1246, 2SK1751
57271	STP4N90	<3,5Ohm(1,7A)	2SK1643
57272	STP4N90FI	STP 4N90, , 2,3A, 40W	2SK1143, 2SK1174, 2SK1275, 2SK1459
57273	I	STP 50N05..06(L), , 27A, 45W	2SK1262
57274	STP50N05L	50V, 50A, 150W, <28mOhm	BUK 556-60, BUZ 100L
57275	STP50N06	<28mOhm(25A)	BUK 556-60
57276	STP50N06L	STP 50N05, 60V	BUK 556-60
57277	STP53N05	<25mOhm(26,5A)	BUK 456-50, BUK 556-60, BUZ 100L
57278	STP53N06	STP 53N05, 60V	BUK 556-60, PRFZ 40
57279	STP55N05..06LFI	STP 55N05L..06L, 60V	2SK1262
57280	STP55N05L	50V, 55A, 150W, <23mOhm	BUK 556-60, BUZ 100L
57281	STP55N06L	STP 55N05L, 60V	BUK 556-60
57282	STP5N30	300V, 5A, 75W, <1,4Ohm(2,5A)	BUZ 60, IRF 730, 2SK1246, 2SK1751
57283	STP5N30FI	STP 5N30, , 3,5A, 35W	BUK 445-450, 2SK1444, 2SK1862...63
57284	STP5N30L	STP 5N30	-

57285	STP5N30LFI	STP 5N30, , 3,5A, 35W	-
57286	STP5N50	<1,6Ohm(2,5A)	BUZ 41A...42, IRF840, IRF842, 2SK893
57287	STP5N50FI	STP 5N50, , 3A, 35W	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
57288	STP5N60	<1,5Ohm(2,5A)	BUK 455/600A, IRFBC 40
57289	STP5N60FI	STP 5N60, , 3,2A, 40W	2SK1572, 2SK1767, 2SK2144
57290	STP5N80	<2Ohm(2,5A)	2SK1643
57291	STP5N80FI	STP 5N80, , 3,1A, 40W	2SK1356, 2SK1460, 2SK1995
57292	STP5N80XI	<2,4Ohm(2,5A)	2SK1356, 2SK1460, 2SK1995
57293	STP5N90	<2,4Ohm(2,5A)	2SK1643
57294	STP5N90FI	STP 5N90, , 2,8A, 40W	2SK1356, 2SK1460, 2SK1995
57295	STP5NA50	<1,6Ohm(2,5A)	BUZ 41A...42, IRF840, IRF842, 2SK893
57296	STP5NA50FI	STP 5NA50, , 3,1A, 35W	BUK 445-500, 2SK1572, 2SK1767, 2SK1863
57297	STP5NA80	<2,4Ohm(2,5A)	2SK1643
57298	STP5NA80FI	STP 5NA80, , 2,7A, 40W	2SK1356, 2SK1460, 2SK1995
57299	STP60N05	<20mOhm(30A)	BUK 556-60, BUZ 100L
57300	STP60N05..06FI	STP 60N05..06, 60V	2SK1262
57301	STP60N06	STP 60N05, 60V	BUK 556-60
57302	STP6N25	250V, 6A, 70W, <1Ohm(3A)	2SK1319...20, 2SK1400, 2SK1667
57303	STP6N25FI	STP 6N25, , 4A, 35W	BUK 445-400, 2SK2010, 2SK2108, 2SK2345
57304	STP6N50	500V, 6A, 100W, <1,1Ohm(3A)	BUK 657-500, IRF 840, IRF 842, 2SK894
57305	STP6N50FI	STP 6N50, , 3,8A, 40W	2SK1232, 2SK1351, 2SK1608, 2SK1991
57306	STP6N60FI	600V, 3,8A, 40W, <1,2Ohm(3A)	2SK1118, 2SK2044, 2SK2100, 2SK2118
57307	STP7N20	<0,65Ohm(3,5A)	BUK554-200, BUZ 73, 2SK1319, 2SK1667
57308	STP7N20FI	STP 7N20, , 4A, 30W	BUK 444-200, BUZ 73(A)F, 2SK2010
57309	STP8N50XI	<0,85Ohm(4A)	2SK1232, 2SK1351, 2SK1627, 2SK1993
57310	STP8NA50	<0,85Ohm(4A)	BUK 657-500, IRF 840, 2SK894, 2SK1574
57311	STP8NA50FI	STP 8NA50, , 4,5A, 40W	2SK1232, 2SK1351, 2SK1627, 2SK1993
57312	STPR..CF	STPR 610..620CT, , 6A(Tc120°)	BYQ 28F-..., MA 650
57313	STPR..D	STPR 310..320, 3A(Tc125°)	BYT 85/600
57314	STPR..F	15A(Tc70°)	-
57315	STPR..F	STPR 810..820D, , 8A(Tc100°)	BYW 29-100F...-200F
57316	STPR..F	STPR 510..520D, , 5A(Tc115°)	MA 690
57317	STPR..F	STPR 310..320, , 3A(Tc120°)	MA 690
57318	STPR..F	10A(Tc115°)	BYV 32F-100...-200
57319	STPR..F	12A(Tc80°)	BYV 12PI/600
57320	STPR1010CT	100V, 10A(Tc125°), <30ns	BYP 20-100, BYQ 28-100, BYT 28-300
57321	STPR1020CT	STPR 1010CT, 200V	BYQ 28-200, BYT 28-300
57322	STPR1210D	100V, 12A(Tc115°), <30ns	BYT 79-300, BYV 79-100...-200
57323	STPR1220D	STPR 1210D, 200V	BYT 79-300, BYV 79-200
57324	STPR1510D	100V, 15A(Tc115°), <30ns	BYR 79-500, BYT 87/600, MUR 1510
57325	STPR1520D	STPR 1510D	BYR 79-500, BYT 87/600, MUR 1520
57326	STPR1610CT	100V, 16A(Tc120°), <30ns	BYP 22-100, BYV 44-300, BYW 51/100
57327	STPR1620CT	STPR 1610CT, 200V	BYP 22-200, BYR 34-500, BYV 44-300
57328	STPR2410CT	100V, 24A(Tc115°), <30ns	BYP 22-100, BYV 44-300, BYW 51/100
57329	STPR2420CT	STPR 2410CT, 200V	BYP 22-200, BYR 34-500, BYV 44-300



57330	STPR310	100V, 3A, <30ns	BYV 28/100.../200, EGP 30B...G, FE 3B...H
57331	STPR320	STPR 310, 200V	BYV 28/200, EGP 30D...G, FE 3D...H
57332	STPR510D	100V, 5A(Tc125°), <30ns	BYT 08-200, BYW 29-100, FE 8B...J
57333	STPR520D	STPR 510D, 200V	BYT 08-200, BYW 29-200, FE 8D...J
57334	STPR610CT	100V, 6A(Tc125°), <30ns	MUR 610...620
57335	STPR620CT	STPR 610CT, 200V	MUR 620
57336	STPR810D	100V, 8A(Tc120°), <30ns	BYT 08-100, BYW 29-100, FE 8B...J
57337	STPR820D	STPR 810D, 200V	BYT 08-200, BYW 29-200, FE 8D...J
57338	STPS..CF	STPS 1535D..1545D, , 2x7,5A	BYV 33F/..., BYV 133F/...
57339	STPS..CF	,20A(Tc120°)	BYV 143F/..., MA 752(A)
57340	STPS..CF	STPS 620CT..640CT	BYV 118F/...
57341	STPS..CPI	,60A(Tc105°)	-
57342	STPS..CPI	,30A(Tc125°)	-
57343	STPS..CPI	,60A(Tc105°)	-
57344	STPS..CPI	,30A(Tc125°)	-
57345	STPS..CT	STPS 1535D..1545D, , 2x7,5A	BUV 33/..., BYV 133/...
57346	STPS..F	STPS 1035D..1045D	MBRF 1045
57347	STPS..F	7,5A(Tc120°)	MBRF 745
57348	STPS..F	15A(Tc105°)	MBRF 1545
57349	STPS1035D	35V, 10A(Tc120°)	MBR 1035...1080
57350	STPS1045D	STPS 1035D, 45V	MBR 1045...1080
57351	STPS12035TV	35V, 120A(Tc100°)	-
57352	STPS12045TV	STPS 12035TV, 45V	-
57353	STPS1535D	35V, 15A(Tc135°)	MBR 1635...1645
57354	STPS1545D	STPS 1535D, 45V	MBR 1645
57355	STPS16035TV	35V, 160A(Tc85°)	-
57356	STPS16045TV	STPS 16035TV, 45V	-
57357	STPS20100CT	100V, 20A(Tc110°)	-
57358	STPS2035CT	35V, 20A(Tc135°)	MBR 2035...2045
57359	STPS2045CT	STPS 2035CT, 45V	MBR 2045
57360	STPS220CE	20V, 2x1A	-
57361	STPS230CE	STPS 220CE, 30V	-
57362	STPS24035TV	35V, 240A(Tc105°)	-
57363	STPS24045TV	STPS 24035, 45V	-
57364	STPS240CE	STPS 220CE, 40V	-
57365	STPS260CE	STPS 220CE, 60V	-
57366	STPS3035CP	35V, 30A(Tc135°)	BYS 28-45, BYV 30/35, MBR 3035PT
57367	STPS3035CP	35V, 30A(Tc135°)	BYS 28-45, BYV 30/35, MBR 3035PT
57368	STPS3045CP	STPS 3035CP, 45V	BYS 28-45, BYV 30/45, MBR 3045PT
57369	STPS3045CP	STPS 3035CP, 45V	BYS 28-45, BYV 30/45, MBR 3045PT
57370	STPS4045CP	45V, 40A(Tc125°)	MBR 4035PT...4060PT
57371	STPS4045CP	45V, 40A(Tc125°)	MBR 4035PT...4060PT
57372	STPS6035CP	35V, 60A(Tc125°)	MBR 6045PT
57373	STPS6035CP	35V, 60A(Tc125°)	MBR 6045PT
57374	STPS6045CP	STPS 6035CP, 45V	MBR 6045PT



57375	STPS6045CP	STPS 6035CP, 45V	MBR 6045PT
57376	STPS620CT	20V, 2x3A(Tc135°)	BYV 18/30.../45, BYV 118/35.../45
57377	STPS630CT	STPS 620CT, 30V	BYV 18/30.../45, BYV 118/35.../45
57378	STPS640CT	STPS 620CT, 40V	BYV 18/40.../45, BYV 118/40.../45
57379	STPS735D	35V, 7,4A(Tc135°)	BYV 19/35.../45, MBR 745...760
57380	STPS745D	STPS 735D, 45V	BYV 19/45, MBR 745...760
57381	STPS80100TV	100V, 80A(Tc90°)	-
57382	STT1	30V, Ip<4μA, Iv>7mA	2N2646, 2N4871
57383	STTA12006T1	600V, 2x60A, <80ns	-
57384	STTA12006V1	STTA 12006T1	-
57385	STTA1206D	600V, 12A, <55ns	BYT 12P/600.../1000, FE 16J
57386	STTA1206DI	STTA 1206D	BYT 12PI/600.../1000
57387	STTA1212D	1200V, 12A, <100ns	-
57388	STTA1512P	1200V, 15A, <105ns	-
57389	STTA1512PI	STTA 1512P	-
57390	STTA2006P	600V, 20A, <60ns	BYT 30P/600.../1000
57391	STTA2006PI	STTA 2006P	BYT 30PI/600.../1000
57392	STTA2512P	1200V, 25A, <110ns	-
57393	STTA3006P	600V, 30A, <65ns	BYT 30P/600.../1000
57394	STTA3006PI	STTA 3006P	BYT 30PI/600.../1000
57395	STTA5012T1	1200V, 2x25A, <110ns	-
57396	STTA5012V1	STTA 5012T1	-
57397	STTA506D	600V, 5A, <50ns	BYR 29-600, BYT 86/600, FE 8J
57398	STTA506F	STTA 506D	BYR 29F-600
57399	STTA512D	1200V, 5A, <95ns	BY 329/1200, DTV 64-1200C
57400	STTA512F	STTA 512D	DTV 64F-1200C
57401	STTA6006T1	600V, 2x30A, <65ns	-
57402	STTA6006V1	STTA 6006T1	-
57403	STTA806D	600V, 8A, <52ns	BYR 29-600, MUR 860, FE 8J
57404	STTA806DI	STTA 806D	BYR 29F/600
57405	STTA812D	1200V, 8A, <100ns	BY 329/1200, MUR 10120E
57406	STTA812DI	STTA 812D	-
57407	STTA9012T1	1200V, 2x45A, <115ns	-
57408	STTA9012V1	STTA 9012T1	-
57409	STTB12009T1	600V, 2x60A, <115ns	-
57410	STTB12009V1	STTB 12009T1	-
57411	STTB1206D	600V, 12A, <100ns	BYT 12P/600.../1000, FE 16J, MUR 1560
57412	STTB1206DI	STTB 1206D	BYT 12PI/600.../1000
57413	STTB2006P	600V, 20A, <105ns	BYT 30P/600.../1000
57414	STTB2006PI	STTB 2006D	BYT 30PI/600.../1000
57415	STTB3006P	600V, 30A, <110ns	BYT 30P/600.../1000
57416	STTB3006PI	STTB 3006D	BYT 30PI/600.../1000
57417	STTB506D	600V, 5A, <95ns	BYR 29/600.../1000, FE 8J
57418	STTB506DI	STTB 806D	BYR 29F/600.../1000
57419	STTB506F	STTB 506D	BYR 29F/600.../1000

57420	STTB6006T1	600V, 2x30A, <65ns	-
57421	STTB6006V1	STTB 6006T1	-
57422	STTB806D	600V, 8A, <100ns	BYR 29/600.../1000, FE 8J, MUR 860
57423	STV-3-G	1,72..1,80V(7mA)	-
57424	STV-3-O	1,60..1,68V(7mA)	-
57425	STV-3-Y	1,66..1,74V(7mA)	-
57426	STV102	1000V, 4,2A, 125W, 140/400ns	BUZ 357...358, BUZ 380...381, 2SK685
57427	STV82	800V, 5,5A, 125W, 140/400ns	BUZ 355...356, 2SK685, 2SK695
57428	STVHD90	50V, 52A, 125W, 140/420ns	PRFZ 40
57429	STW12N60	STH 12N60	STH 12N60
57430	STW12N60	STH 12N60	STH 12N60
57431	STW14N50	STH 14N50	STH 14N50
57432	STW15N50	STH 15N50	STH 15N50
57433	STW16N40	<0,3Ohm(8A)	BUZ 323, 2SK1678, 2SK1745
57434	STW33N20	STH 33N20	STH 33N20
57435	STW55N10	STH 55N10	STH 55N10
57436	STW60N10	STH 60N10	STH 60N10
57437	STW75N06	STH 75N06	STH 75N06
57438	STW80N05	STH 80N05	STH 80N05
57439	STW8N80	STH 8N80	STH 8N80
57440	STZ6.8T	6,47..7,14V	-
57441	STZT2222(A)	2N2222(A), SMD	BCX 55, PXT 2222, SXT 2222, 2SD1005...06
57442	STZT2907(A)	2N2907(A), SMD	BCX 52, PXT 2907, SXT 2907, 2SB803...05
57443	STZT3904	2N3904, SMD	PXT 3904, SXT 3904, 2SC3803
57444	STZT3906	2N3906, SMD	PXT 3906, SXT 3906, 2SA1483
57445	STZT5400	2N5400, SMD	2SA1418
57446	STZT5401	2N5401, SMD	2SA1418
57447	STZT5550	2N5550, SMD	2SC3648
57448	STZT5551	2N5551, SMD	2SC3648
57449	STZTA42	MPSA 42, SMD	BST 40, PXTA 42, SXTA 42
57450	STZTA43	MPSA 43, SMD	BST 40, PXTA 43, SXTA 43
57451	STZTA92	MPSA 92, SMD	BST 16, PXTA 92, SXTA 92
57452	STZTA93	MPSA 93, SMD	BST 15...16, PXTA 93, SXTA 93
57453	SU111	450/400V, 10A, 120W	BU 921...922, BU 931...932
57454	SU160	1500/700V, 5A, 12,5W(Tc95°)	BU 208(A), BU 508(A), 2SD 350(A)
57455	SU161	1500/700V, 2,5A, 10W(Tc90°)	BU 205(A), BU 705, 2SC1922, 2SD818
57456	SU165	900/350V, 2,5A, 10W(Tc90°)	BU326, BU205(A), BU208(A), BUW11(A)
57457	SU167	800/325V, 10A, 100W	BU 626A, BUX 80...81, S 2530A, 2SD1094
57458	SU169	1000/400V, 10A, 100W	BU 626A, BUX 81, S 2530A, 2SD1094
57459	SU177	800/400V, 4A, 50W(Tc50°)	BUS 11(A), BUW 11(A), BUX 46(A)
57460	SU178	800/400V, 6A, 60W(Tc50°)	BU 526, BU 536, BUX 47(A), BUX 82...83
57461	SU179	SU 178, 1000/450V	BU 536, BUS 11A, BUX 47A, BUX 83
57462	SU180	1200/400V, 4A, 50W(Tc50°)	BU 546, BU 903, BUV 89, 2SC3059
57463	SU186	160/125V, 15A, 150W	BUV 11...12, BUX 11...12, BUX 40...41
57464	SU187	SU 186, 250/200V	BUV 11...12, BUX 11...12, BUX 41

57465	SU188	SU 186, 300/250V, 20A	BUV 12, BUW 73, BUX 12, 2N6322
57466	SU189	850/400V, 15A, 175W	BUS 13(A), BUS 97(A), BUW 46, BUX 48(A)
57467	SU190	SU 189, 1000/450V	BUS 13A, BUS 97A, BUX 48A, 2SC3216
57468	SU191	120/90V, 30A, 150W	BUW 39, BUW 40, BUX 39
57469	SU192	160/125, 25A, 150W	BUV 10, BUW 57, BUX 10, BUX 40, BUX 70
57470	SU193	300/250, 15A, 150W	BUW 52, BUX 13, MJ 15022
57471	SU310	200/150, 12A, 125W	BU 930...932, BUV 37, 2SD711(A)
57472	SU311	450/400, 12A, 125W	BU 931...932, BUV 37, 2SD711(A)
57473	SU312	450/400, 12A, 125W	BU 931...932, BUV 37, 2SD711(A)
57474	SU377	600/300V, 6A, 85W	BUT 11(A), BUT 56(A), BUV 46(A)
57475	SU378	700/400V, 8A, 85W	BUT 12(A), BUT 56(A), BUT 76(A)
57476	SU379	SU 377, 800/400V	BUT 11(A), BUT 56(A), BUV 46(A)
57477	SU380	SU 378, 850/400V	BUT 12(A), BUT 56(A), BUT 76(A)
57478	SU382	700/450V, 9A, 120W	BUV 47(A), BUW 12(A), 2SC3637
57479	SU383	SU 382, 850/450V	BUV 47(A), BUW 12(A), 2SC3637
57480	SU384	SU 382, 1000/450V	BU 908, BUV 47A, BUW 12A, BUV 71...72
57481	SU386	160/125V, 15/20A, 150W	BUW 50...52, BUX 70, 2SC3263
57482	SU387	250/200V, 15/20A, 150W	BUW 50...52, BUX 70, 2SC3263
57483	SU388	300/250V, 20/25A, 150W	BUW 51...52, 2SC2626, 2SC2307
57484	SU389	850/400V, 15/30A, 150W	BUV 48(A...C), BUW 13(A), BUW 133(A)
57485	SU390	SU 389, 1000/450V	BUV 48A, BUW 13A, BUW 133A, 2SC3552
57486	SU391	125/90V, 30A, 150W	BUW 50...52, BUX 70
57487	SU392	160/125V, 25A, 150W	BUW 50...52, BUX 70
57488	SU393	300/250V, 20A, 150W	BUW 51...52, 2SC2626, 2SC2307
57489	SUB50N06-18	<18mOhm(30A)	-
57490	SUB60N06-14	SUP 60N06-14, 100W	-
57491	SUB60N06-18	<12mOhm(30A)	-
57492	SUB60P06-20	SUP 60P06-20, 150W	-
57493	SUF4001	50V, 1A, <50ns	EGP 10A...G, FE 1A...H
57494	SUF4002	SUF 4001, 100V	EGP 10B...G, FE 1B...H
57495	SUF4003	SUF 4001, 200V	EGP 10C...G, FE 1C...H
57496	SUF4004	SUF 4001, 400V	EGP 10G, FE 1H
57497	SUF5400	50V, 3A, <50ns	BYV 28/50, EGP 30A...G, FE 3A...H
57498	SUF5401	SUF 5400, 100V	BYV 28/100, EGP 30B...G, FE 3B...H
57499	SUF5402	SUF 5400, 200V	BYV 28/200, EGP 30D...G, FE 3D...H
57500	SUF5403	SUF 5400, 300V	EGP 30F...G, FE 3F...H
57501	SUF5404	SUF 5400, 400V	EGP 30G, FE 3H
57502	SUP50N06-18	<18mOhm(30A)	BUK 556-60
57503	SUP60N06-08	<8mOhm(30A)	BUK 556-60
57504	SUP60N06-14	<14mOhm(30A)	BUK 556-60
57505	SUP60P06-20	<20mOhm(30A)	-
57506	SV-9	BA 127	BA 127
57507	SV31	1S188	1S188
57508	SW	SM 4T 100	SM 4T...
57509	SX	SM 4T 100A	SM 4T...

57510	SX3702	2N3702	
57511	SXT2222A	2N2222A, SMD	BCX 55...56, PXT 2222A, 2SD1005...1006
57512	SXT2907A	2N2907A, SMD	BCX 52...53, PXT 2907A, 2SB803...805
57513	SXT3904	2N3904, SMD	PXT 3904, 2SC3803
57514	SXT3906	2N3906, SMD	PXT 3906, 2SA1483
57515	SXTA42	MPSA42, SMD	BST 40, PXTA 42
57516	SXTA43	MPSA43, SMD	BST 40, PXTA 43
57517	SXTA92	MPSA92, SMD	BST 16, PXTA 92
57518	SXTA93	MPSA93, SMD	BST 15...16, PXTA 93
57519	SY	2SA1618-Y	2SA1618
57520	SY	2SA1873-Y	2SA1873
57521	SY	2SC3900	2SC3900
57522	SY	2SA1162-Y	2SA1162
57523	SY	2SA1832-Y	2SA1832
57524	SY	2SA1586-Y	2SA1586
57525	SY100	75V, 1A	BY 205/100, BY 229/200, BY 249/300
57526	SY101	SY 100, 100V	BY 205/100, BY 229/200, BY 249/300
57527	SY102	SY 100, 200V	BY 205/200, BY 229/200, BY 249/300
57528	SY103	SY 100, 300V	BY 205/400, BY 229/400, BY 249/600
57529	SY104	SY 100, 400V	BY 205/400, BY 229/400, BY 249/600
57530	SY105	SY 100, 500V	BY 205/600, BY 229/600, BY 249/600
57531	SY106	SY 100, 600V	BY 205/600, BY 229/600, BY 249/600
57532	SY107	SY 100, 700V	BY 205/800, BY 229/800
57533	SY108	SY 100, 800V	BY 205/800, BY 229/800
57534	SY110	SY 100, 1000V	BY 205/1000, BY 229/1000
57535	SY120	SY 100	BY 205/100, BY 229/200, BY 249/300
57536	SY121	SY 101	BY 205/100, BY 229/200, BY 249/300
57537	SY122	SY 102	BY 205/200, BY 229/200, BY 249/300
57538	SY123	SY 103	BY 205/400, BY 229/400, BY 249/300
57539	SY124	SY 104	BY 205/400, BY 229/400, BY 249/600
57540	SY125	SY 105	BY 205/600, BY 229/600, BY 249/600
57541	SY126	SY 106	BY 205/600, BY 229/600, BY 249/600
57542	SY127	SY 107	BY 205/800, BY 229/800
57543	SY128	SY 108	BY 205/800, BY 229/800
57544	SY130	SY 110	BY 205/1000, BY 229/1000
57545	SY200	75V, 0,95A	BY 126...127, BY 133...135, 1N4002...07
57546	SY201	SY 200, 100V	BY 126...127, BY 133...135, 1N4002...07
57547	SY202	SY 200, 200V	BY 126...127, BY 133...134, 1N4003...07
57548	SY203	SY 200, 300V	BY 126...127, BY 133...134, 1N4004...07
57549	SY204	SY 200, 400V	BY 126...127, BY 133...134, 1N4004...07
57550	SY205	SY 200, 500V	BY 126...127, BY 133...134, 1N4005...07
57551	SY206	SY 200, 600V	BY 126...127, BY 133...134, 1N4005...07
57552	SY207	SY 200, 700V	BY 127, BY 133, BY 227, 1N4006...07
57553	SY208	SY 200, 800V	BY 127, BY 133, BY 227, 1N4006...07
57554	SY210	SY 200, 1000V	BY 127, BY 133, BY 227, 1N4007

57555	SY220	SY 200	SY 200
57556	SY221	SY 201	SY 201
57557	SY222	SY 202	SY 202
57558	SY223	SY 203	SY 203
57559	SY224	SY 204	SY 204
57560	SY225	SY 205	SY 205
57561	SY226	SY 206	SY 206
57562	SY227	SY 207	SY 207
57563	SY228	SY 208	SY 208
57564	SY230	SY 210	SY 210
57565	SY320/0,75..10	75..1000V, 0,95A	BY 126...127, BY 133...135, 1N4002...07
57566	SY330/1...10	100..1000V, 0,27..0,43A, <500ns	BA 157...159, BY 204/..., BY 208/...
57567	SY330/12...20	0,16..0,24A,<500ns	BY 203/...
57568	SY335/05K..8K	50..800V, 1..1,4A, <500ns	BY 258/..., BYV 12...16, RGP 15A...M
57569	SY335/05L...8L	50..800V, 1..1,4A, <1µs	BY 258/..., BYV 12...16, RGP 15A...M
57570	SY345/05K...10K	50..1000V, 1,1..1,4A, <500ns	BY 258/..., BYV 12...16, RGP 15A...M
57571	SY345/05L...10L	50..1000V, 1,1..1,4A, <1µs	BY 258/..., BYV 12...16, RGP 15A...M
57572	SY346/05..10	50..1000V, 0,59..0,81A, 200ns	BYT 52A...M, BYV 12...16, RG 1A...M
57573	SY347/05..10	50..1000V, 0,53..0,73A, 200ns	BYT 52A...M, BYV 12...16, RG 1A...M
57574	SY351/05...14	50..1400V, 3A	BY 251...255, BY 228, BY 448
57575	SY356/05..10	50..1000V, 1,5A, 300ns	BYV 12...16, BYV 36A...E, RG 2A...M
57576	SY360/0,5...10	50..1000V, 0,9A	BY 126...127, BY 133...135, 1N4001...07
57577	SY361/10..13	1000..1300V, 1A	BY 228, BY 231/..., DM 513, GP 10V...Y
57578	SY361/16	SY 361/10..13, 1600V	BY 228, BY 231/1500, DM 516, GP 10Y
57579	SY361/18	SY 361/10..13, 1800V	-
57580	SY400/0,75..10	75..1000V, 2A	BY 251...255, BY 259/..., GP 20A...M
57581	SYX	KSD1621	KSD1621
57582	sZC	SMBT 4124	SMBT 4124
57583	SZX	KSB1121	KSB1121
57584	T	2SK1615	2SK1615
57585	T	HSU 83	HSU 83
57586	T	2SK1065	2SK1065
57587	T0	TN 0610T	TN 0610T
57588	T0,8N/0,6..5[ITT]	0/<20mA	BTX 30/..., T 1N..., S 2600..., TAG 612-...
57589	G]	0/<20mA	BTX 30/..., T 1N..., S 2600..., TAG 612-...
57590	T005..10	50..1000V, 3A	B...C3300
57591	T0505BH	Igt/Ih5/15mA	TXC 18D...M, TAG 222-..., TAG 227-...
57592	T0505DH	T 0505BH, 400V	TXC 18D...M, TAG 222-..., TAG 227-...
57593	T0505MH	T 0505BH, 600V	TXC 18D...M, TAG 222-..., TAG 227-...
57594	T0505NH	T 0505BH, 800V	TXC 18D...M, TAG 222-..., TAG 227-...
57595	T0509BH..NH	T 0505BH..NH, Igt/Ih10/25mA	TAG 232-..., TAG 221-..., MAC 228A-...
57596	T0510BH..NH	T 0505BH..NH, Igt/Ih25/50mA	TAG 231-..., TAG 220-..., TAG 225-...
57597	T0512BH..NH	T 0505BH..NH, Igt/Ih50/100mA	TAG 230-..., TCX 10H...M, TAG 224-...
57598	T0605BH	Igt/Ih<5/<5mA	TCX 18D...M, TAG 222-..., TAG 227-...
57599	T0605DH	T 0605BH, 400V	TCX 18D...M, TAG 222-..., TAG 227-...

57600	T0605MH	T 0605BH, 600V	TCX 18D...M, TAG 222-..., TAG 227-...
57601	T0605NH	T 0605BH, 800V	TCX 18D...M, TAG 222-..., TAG 227-...
57602	T0609BH..NH	T 0605BH..NH, Igt/Ih10/25mA	TCX 18G...M, TAG 221-..., TAG 226-...
57603	T0610BH..NH	T 0605BH..NH, Igt/Ih25/50mA	TAG 220-..., TAG 225-..., TAG 257-...
57604	T0610BJ..NJ	T 0605BH..NH, , Igt/Ih25/50mA	TAG 421-..., TAG 426-..., TAG 452-...
57605	T0612BJ..NJ	T 0610BJ..NJ, , Igt/Ih50/100mA	TAG 420-..., TAG 425-..., TAG 451-...
57606	T0805BH	Igt/Ih5/15mA	TAG 227-...
57607	T0805DH	T 0805BH, 400V	TAG 227-...
57608	T0805MH	T 0805BH, 600V	TAG 227-...
57609	T0805NH	T 0805BH, 800V	TAG 227-...
57610	T0809BH..NH	T 0805BH..NH, Igt/Ih10/25mA	TAG 226-..., MAC 228A-...
57611	T0810BH..NH	T 0805BH..NH, Igt/Ih25/50mA	TAG 225-..., TAG 257-...
57612	T0810BJ..NJ	T 0810BH..NH	TAG 426-..., TAG 452-..., TAG 457-...
57613	T0812BH..NH	T 0805BH..NH, Igt/Ih50/100mA	TAG 224-..., TXD 10H..., TAG 250-...
57614	T0812BJ..NJ	T 0812BH..NH	TAG 425-..., TAG 451-..., TAG 456-...
57615	T0813BJ..NJ	Igt/Ih75/150mA	TAG 425-..., TAG 451-..., TAG 456-...
57616	T1	1SV153	1SV153
57617	T1	1SV254	1SV254
57618	T1	1SV214	1SV214
57619	T1	2SC5136	2SC5136
57620	T1	HVM 89	HVM 89
57621	T1(p)	BCX 17	BCX 17
57622	T1010BH	Igt/Ih25/50mA	TAG 252-..., TAG 257-...
57623	T1010BJ..NJ	T 1010BH..NH	TAG 457-...
57624	T1010DH	T 1010BH, 400V	TAG 252-..., TAG 257-...
57625	T1010MH	T 1010BH, 600V	TAG 252-..., TAG 257-...
57626	T1010NH	T 1010BH, 800V	TAG 252-..., TAG 257-...
57627	T1012BH..NH	T 1010BH..NH, Igt/Ih50/100mA	TAG 250-..., TAG 251-..., TXD10H...M
57628	T1012BJ..NJ	T 1012BH..NH	TAG 456-..., TAG 480-..., TAG 481-...
57629	T1013BH..NH	T 1010BH..NH, Igt/Ih75/150mA	TAG 250-..., TAG 251-..., TXD10H...M
57630	T1013BJ..NJ	T 1013BH..NH	TAG 456-..., TAG 480-..., TAG 481-...
57631	T10A6CI	T 10A6CP	TAG 456-600, TAG 457-600
57632	T10A6CP	600V, 10A, Igt<30mA	BTA 22M, TAG 250...252-600, TXD10H60M
57633	T10N/100...900C..	25/<60mA	-
57634	T10N/100...900H..	T 10N/..C	-
57635	T10N/100...900P..	T 10N/..C	-
57636	T11	HVM 17WA	HVM 17WA
57637	T12	HVM 100	HVM 100
57638	T12	2SC2755-T12	2SC2755-T12
57639	T1210BH	Igt/Ih25/50mA	TAG 257-...
57640	T1210DH	T 1210BH, 400V	TAG 257-...
57641	T1210MH	T 1210BH, 600V	TAG 257-...
57642	T1210NH	T 1210BH, 800V	TAG 257-...
57643	T1212BH..NH	T 1210BH..NH, Igt/Ih50/100mA	BT 138/..., TAG 255-..., TAG 256-...
57644	T1212BJ..NJ	T 1212BH..NH	TAG 480-..., TAG 481-...



57645	T1213BH..NH	T 1210BH..NH, Igt/Ih75/150mA	BT 138/..., TAG 255-..., TAG 256-...
57646	T1213BJ..NJ	T 1213BH..NH	TAG 480-..., TAG 481-...
57647	T12A6CI	T 12A6CP	TAG 480-600, TAG 481-600
57648	T12A6CP	600V, 12A, Igt<50mA	BTA 23M, TAG 255...257-600, TXD 10H60P
57649	T12F/100..1200C..	12A(85°C)Igt/Ih<50/<100mA	-
57650	T12N/100..1200C..	12A(85°C),Igt/Ih<40/<100mA	2N5204...5207
57651	T13	2SC2755-T13	2SC2755-T13
57652	T14	2SC2755-T14	2SC2755-T14
57653	T14F/100..900C..	50/<40mA	-
57654	T14F/100..900E..	T 14F/..C	-
57655	T14N/100..900E..	T 14N/..F	-
57656	T14N/400...800F..	Igt<50mA	-
57657	..	Igt/Ih<50/<100mA	TAG16N..., BTW92/..., CS16..., T17N...
57658	T1512BJ	Igt/Ih50/100mA	-
57659	T1512DJ	T 1512BJ, 400V	-
57660	T1512MJ	T 1512BJ, 600V	-
57661	T1512NJ	T 1512BJ, 800V	-
57662	T1513BJ..NJ	T 1512BJ..NJ, Igt/Ih75/150mA	-
57663	T15F/200..1300B..	0mA,<12µs	T 20F...B, BStF04...
57664	T15F/200..1300C..	T 15F/..B	T 20F...C, BStF04...
57665	T15N/200..1300C..	Igt/Ih<100/<200mA	T 16N...C, T 25N...C, BTV 24/...
57666	T15N/200..1300E..	T 15N/..C	T 16N...B, T 25N...B
57667	T1612BH	Igt/Ih50/100mA	MAC 15A-..., BT 139/..., TAG 280-...
57668	T1612DH	T 1612BH, 400V	MAC 15A-..., BT 139/..., TAG 280-...
57669	T1612MH	T 1612BH, 600V	MAC 15A-..., BT 139/..., TAG 280-...
57670	T1612NH	T 1612BH, 800V	MAC 15A-..., BT 139/..., TAG 280-...
57671	T1613BH..NH	T 1612BH..NH, Igt/Ih75/150mA	MAC 15A-..., BT 139/..., TAG 280-...
57672	T16A6CI	T 16A6CP	-
57673	T16A6CP	600V, 16A, Igt<50mA	BT 139/600, MAC 15A-8, TAG 280...281-600
57674	T16N/400..1600B..	Igt/Ih<120/<200mA	T 25N...B
57675	T16N/400..1600C..	T 16N/..B	T 25N...C
57676	T17F/200..1400B..	17A,Igt/Ih<80/<150mA,<12µs	T 24F...B
57677	T17F/200..1400C..	T 17F/..B	T 24F...C
57678	T17N/200..1400B..	Igt/Ih<80/<150mA	T 24N...B, TAG 24N..., CS 23...
57679	T17N/200..1400C..	T17N/..B	T 24N...C, TAG 24N..., CS 23...
57680	T18F/100..900C..	<12µs	-
57681	T18F/100..900E..	T 18F/..C	-
57682	T18N/100..900E..	Igt/Ih<50/8mA	-
57683	T1A6C	600V, 1A, Igt<10mA	MAC 95A, MAC 96A
57684	T1N/100...600A	1A(Tc85°C),Igt/Ih<10/<25mA	BTX30/..., TAG613-..., S2600..., TAG612-...
57685	T2	1SV215	1SV215
57686	T2	1SV161	1SV161
57687	T2	TN 2460T	TN 2460T
57688	T2	2SK242-T2	2SK242
57689	T2	HVM 15	HVM 15

57690	T2(p)	BCX 18	BCX 18
57691	T2046	2N2904	2N2904
57692	T2047	2N696	2N696
57693	T2096	AF 139	AF 139
57694	T2097	AF 139	AF 139
57695	T20F/200..1200B..	0mA,<12µs	-
57696	T20F/200..1200C..	T 20F/..B	-
57697	T22	STPS 220CE	STPS 220CE
57698	T22	2SC2756-T22	2SC2756
57699	T22N/400..1300C..	Igt/Ih<100/<80mA	T 25N...C, BTV 24/...
57700	T22N/400..1300E..	T 22N/..C	-
57701	T23	STPS 230CE	STPS 230CE
57702	T23	2SC2756-T23	2SC2756
57703	T2300A	Igt/Ih<3/<5mA	T 2320A, Z 0402B, T 2300PA
57704	T2300B	T 2300A, 200V	T 2320B, Z 0402B, T 2300PB
57705	T2300C	T 2300A, 300V	T 2320C, Z 0402D, T 2300PC
57706	T2300D	T 2300A, 400V	T 2320D, Z 0402D, T 2300PD
57707	T2300E	T 2300A, 500V	T 2320E, Z 0402M, T 2300PE
57708	T2300F	T 2300A, 50V	T 2320F, Z 0402B, T 2300PF
57709	T2300M	T 2300A, 600V	T 2320M, Z 0402M, T 2300PM
57710	T2300N	T 2300A, 800V	T 2320N, Z 0402N, T 2300PN
57711	T2300PA...N	T 2300 A..N	Z 0402..., T 2320...
57712	T2300PA...N	T 2300 A..N	Z 0402..., T 2320...
57713	T2301A...N	T 2300A..N, Igt/Ih<4/<5mA	T 2327..., Z 0405..., T 2301P...
57714	T2301PA...N	T 2301 A..N	TXC18D..., TAG222..., Z0405..., TAG233...
57715	T2301PA...N	T 2301 A..N	TXC18D..., TAG222..., Z0405..., TAG233...
57716	T2302A...N	T 2300A..N, Igt/Ih<10/<15mA	T 2322..., Z 0409..., T 2302P...
57717	T2302PA...N	T 2302 A..N	Z0409..., TAG232..., TXC18G..., TAG221...
57718	T2302PA...N	T 2302 A..N	Z0409..., TAG232..., TXC18G..., TAG221...
57719	T2303A	Igt/Ih<40/<35mA	TAG208-100, TAG231-200, TAG220-100
57720	T2303B	T 2303A, 200V	TAG208-200, TAG231-200, TAG220-100
57721	T2303D	T 2303A, 400V	TAG208-400, TAG231-400, TAG220-400
57722	T2303F	T 2303A, 50V	TAG208-100, TAG231-200, TAG220-100
57723	T2303M	T 2303A, 600V	TAG208-600, TAG231-600, TAG220-600
57724	T2304B	Igt/Ih<10/<15mA	TAG201-100, T2302B, TAG202A-100
57725	T2304D	T 2304B, 400V	TAG201-400, T2302D, TAG202A-400
57726	T2305B	T 2304A..B, Igt/Ih<40/<30mA	TAG 200-200, T 2303B, TAG 208-200
57727	T2305D	T 2305B, 400V	TAG 200-400, T 2303D, TAG 208-400
57728	T2306A...N	T 2300A..N, Igt/Ih<45/6mA	TIC201..., TAG231..., TAG220..., TAG225.
57729	T2310A...N	T 2300A..N, 1,9A	T 2300..., T 2320..., Z 0402..., T 2300P...
57730	T2311A...N	T 2301A..N, 1,9A	T 2301..., T 2327..., Z 0405..., T 2301P...
57731	T2312A...N	T 2302A..N, 1,9A	T 2302..., T 2322..., Z 0409..., T 2302P...
57732	T2313A...M	T 2303A..N, 1,9A	T 2303..., T 2323..., Z 0410..., TAG 231...
57733	T2316A...N	Igt/Ih<45/6mA	TIC 201..., TAG 231..., TAG 220...
57734	T2320A	Igt/Ih<3/<30mA	Z 0402B, T 2300PB

57735	T2320B	T 2320A, 200V	Z 0402B, T 2300PB
57736	T2320C	T 2320A, 300V	Z 0402D, T 2300PC
57737	T2320D	T 2320A, 400V	Z 0402D, T 2300PD
57738	T2320E	T 2320A, 500V	Z 0402M, T 2300PE
57739	T2320F	T 2320A, 50V	Z 0402B, T 2300PF
57740	T2320M	T 2320A, 600V	Z 0402M, T 2300PM
57741	T2320N	T 2320A, 800V	Z 0402N, T 2300PN
57742	T2322A...N	T 2320A..N, Igt/Ih<10/<30mA	Z0409..., T2302P..., TAG232..., TXC18G...
57743	T2323A...N	T 2320A..N, Igt/Ih<40/<30mA	Z0410..., TAG231..., TAG220..., TAG225...
57744	T2327A...N	T 2320A..N, Igt/Ih<5/<30mA	Z0405..., TXC18D..., TAG233..., TAG222...
57745	T23xxP..5	T 23xx P..	Z0409..., TAG232..., TXC18G..., TAG221...
57746	T24	STPS 240CE	STPS 240CE
57747	T24	2SC2756-T24	2SC2756
57748	T24F/200..1400B..	mA,<12μs	-
57749	T24F/200..1400C..	T 24F/..B	-
57750	T24N/200..1400B..	Igt/Ih<80/<150mA	CS 23-...
57751	T24N/200..1400C..	T 24N/..B	TAG 24N..., CS 23-...
57752	T2500B	Igt/Ih<60/<30mA	TXC 10H40M, TAG 224-200, MAC 222A-4
57753	T2500D	T 2500B, 400V	TXC 10H40M, TAG 224-400, MAC 222A-6
57754	T2500M	T 2500B, 600V	TXC 10H60M, TAG 224-600, MAC 222A-8
57755	T2500N	T 2500B, 800V	TXC 10H80M, TAG 224-800, MAC 222A-10
57756	T2506B...N	T 2500B..N, Igt/Ih<45/<15mA	TXC10K...M, TW7N..., MAC222..., TIC226...
57757	T2512BH	<50/<100mA	-
57758	T2512BK..NK	T 2512BH..NH	TAG 740-..., TAG 741-...
57759	T2512DH	T 2512BH, 400V	-
57760	T2512MH	T 2512BH, 600V	-
57761	T2512NH	T 2512BH, 800V	-
57762	T2513BH..NH	<75/150mA	-
57763	T2513BK..NK	T 2513BH..NH	TAG 740-..., TAG 741-...
57764	T25N/400..1600B..	Igt/Ih<120/<200mA	-
57765	T25N/400..1600C..	T 25N/..B	-
57766	T25U40	800/400V, 25A, 200W, <1,5/6μs	-
57767	T26	STPS 260CE	STPS 260CE
57768	T2606B	Igt/Ih<45/15mA	TXC 10K40M, TW 7N400, MAC 222-4
57769	T2606D	T 2606B, 400V	TXC 10K40M, TW 7N400, MAC 222-6
57770	T2606DF	T 2606B, 450V	TXC 10K50M, TW 7N600, MAC 222-7
57771	T2616DF	T 2606 DF	T 2606 DF
57772	T2696	AF 139	AF 139
57773	T2697	AF 139	AF 139
57774	T2700B	Igt/Ih<40/<30mA	TAG261-200, TAG266-200, TAG220-200
57775	T2700B	Igt/Ih<40/<30mA	TAG261-200, TAG266-200, TAG220-200
57776	T2700D	T 2700B, 400V	TAG 261-400, TAG 266-400, TAG 220-400
57777	T2700D	T 2700B, 400V	TAG 261-400, TAG 266-400, TAG 220-400
57778	T2700M	T 2700B, 600V	TAG 261-600, TAG 266-600, TAG 220-600
57779	T2700M	T 2700B, 600V	TAG 261-600, TAG 266-600, TAG 220-600

57780	T2700N	T 2700B, 800V	TAG 261-800, TAG 266-800, TAG 220-800
57781	T2700N	T 2700B, 800V	TAG 261-800, TAG 266-800, TAG 220-800
57782	T2706B...N	T 2700B..N, Igt/Ih<45/15mA	T4706..., T2806..., TAG220..., TAG 225...
57783	T2706B...N	T 2700B..N, Igt/Ih<45/15mA	T4706..., T2806..., TAG220..., TAG 225...
57784	T2710B...N	T 2700 B..N	T 2700 B...N
57785	T2716B...N	T 2706 B..N	T 2706 B...N
57786	T2796	AF 139	AF 139
57787	T2797	AF 139	AF 139
57788	T2800A	Igt/Ih<60/<30mA	TAG 224-100, MAC 222A-3, BT 137/500
57789	T2800B	T 2800A, 200V	TAG 224-200, MAC 222A-4, BT 137/500
57790	T2800C	T 2800A, 300V	TAG 224-300, MAC 222A-5, BT 137/500
57791	T2800D	T 2800A, 400V	TAG 224-400, MAC 222A-6, BT 137/500
57792	T2800E	T 2800A, 500V	TAG 224-500, MAC 222A-7, BT 137/500
57793	T2800F	T 2800A, 50V	TAG 224-100, MAC 222A-2, BT 137/500
57794	T2800M	T 2800A, 600V	TAG 224-600, MAC 222A-8, BT 137/600
57795	T2800N	T 2800A, 800V	TAG 224-800, MAC 222A-10, BT 137/800
57796	T2801A	Igt/Ih<80/100mA	BS 7-02A, MAC 216-4, SC 141B
57797	T2801B	T 2801A, 200V	BS 7-02A, MAC 216-4, SC 141B
57798	T2801C	T 2801A, 300V	BS 7-04A, MAC 216-6, SC 141D
57799	T2801D	T 2801A, 400V	BS 7-04A, MAC 216-6, SC 141D
57800	T2801DF	T 2801A, 450V	BS 7-05A, MAC 216-7, SC 141E
57801	T2801E	T 2801A, 500V	BS 7-05A, MAC 216-7, SC 141E
57802	T2801F	T 2801A, 50V	BS 7-02A, MAC 216-4, SC 141B
57803	T2801M	T 2801A, 600V	BS 7-06A, MAC 216-8, SC 141M
57804	T2802A...N	T 2800A..N, Igt/Ih<50/<60mA	MAC 222..., TIC 226..., TXD 10K/L...
57805	T2806A...N	T 2800A..N, Igt/Ih<45/15mA	TAG 225..., TAG 252...
57806	T2850A	Igt/Ih<60/<30mA	TAG 224-100, MAC 222A-3, BT 137/500
57807	T2850B	T 2850A, 200V	TAG 224-200, MAC 222A-4, BT 137/500
57808	T2850D	T 2850A, 400V	TAG 224-400, MAC 222A-6, BT 137/500
57809	T2850E	T 2850A, 500V	TAG 224-500, MAC 222A-7, BT 137/500
57810	T2850F	T 2850A, 50V	TAG 224-100, MAC 222A-2, BT 137/500
57811	T2850M	T 2850A, 600V	TAG 224-600, MAC 222A-8, BT 137/600
57812	T2851B	Igt/Ih<80/100mA	TAG 425-200, TAG 451-200, TAG 456-200
57813	T2851C	T 2851B, 300V	TAG 425-400, TAG 451-400, TAG 456-400
57814	T2851D	T 2851B, 400V	TAG 425-400, TAG 451-400, TAG 456-400
57815	T2851DF	T 2851B, 450V	TAG 425-500, TAG 451-600, TAG 456-600
57816	T2851E	T 2851B, 500V	TAG 425-500, TAG 451-600, TAG 456-600
57817	T2851M	T 2851B, 600V	TAG 425-600, TAG 451-600, TAG 456-600
57818	T2856A...M	T 2850 A..M	TAG 426..., TAG 452..., TAG 457...
57819	T2896	AF 139	AF 139
57820	T3	1SV261	1SV261
57821	T3	1SV186	1SV186
57822	T3	1SV245	1SV245
57823	T3	HVM 16	HVM 16
57824	T3	BSS 63	BSS 63

57825	T3	2SK242-T3	2SK242
57826	T3	2SK1065-3	2SK1065
57827	T3,5N/400..800F..	5A(Tc72°C),Igt/Ih<10/<25mA	TAG 661-..., TAG 662-..., TAG 666-...
57828	T30E45FZ	500/450V, 50A, 300W, B>100	-
57829	T30E45FZ	500/450V, 30A, 300W, B>100	-
57830	T30F/100...900C..	Igt/Ih<100/20mA, <15µs	-
57831	T30F/100...900E..	T 30F/..B	-
57832	T30G40	850/400V, 30A, 200W, <3/4µs	-
57833	T32	2SC2757-T32	2SC2757
57834	T33	2SC2757-T33	2SC2757
57835	T34	2SC2757-T34	2SC2757
57836	T35	BSR 20	BSR 20
57837	T36	BSR 20A	BSR 20A
57838	T3A6CI	T 3A6CP	-
57839	T3A6CP	600V, 3A, Igt<50mA	BT 136/600, TXC 10H60, TAG 230...231-600
57840	T3N/50...600C..	Igt<20mA	T 6N...C, T 8N...C, BStD41..., S 6210...
57841	T3S/400...700M..	5,1A(68°C),Igt/Ih<50/<100mA	TAG 670S-..., TAG 675S-..., TAG 661S-...
57842	T4	1SV204	1SV204
57843	T4	1SV216	1SV216
57844	T4	1SV256	1SV256
57845	T4	HVM 11	HVM 11
57846	T4	BCX 17R	BCX 17R
57847	T4	2SK242-T4	2SK242
57848	T4	2SK1065-4	2SK1065
57849	T4,5N/50...400C..	4,5A(Tc85°C),Igt/Ih<20/25mA	T 6N...C, T 8N...C, BStD41..., S 2610...
57850	T4012BK	Igt/Ih50/100mA	-
57851	T4012DK	T 4012BK, 400V	-
57852	T4012MK	T 4012BK, 600V	-
57853	T4012NK	T 4012BK, 800V	-
57854	T4013BK..NK	T 4012BK..NK, Igt/Ih75/150mA	-
57855	T4100E	Igt/Ih<80/<75mA	2N6159, T 6400E, 2N5443
57856	T4100F	T 4100E, 50V	2N6157...6159, T 6400F, 2N5441...5443
57857	T4100M	T 4100E, 600V	2N6159, T 6400M, 2N5443
57858	T4101E	Igt/Ih<40/<30mA	-
57859	T4101F	T 4101E, 50V	2N5567...5568
57860	T4101M	T 4101E, 600V	-
57861	T4103B	Igt/Ih<80/<75mA	2N6157...6159, T 6400B, 2N5441...5443
57862	T4103D	T 4103B, 400V	2N6158...6159, T 6400D, 2N5442...5443
57863	T4103E	T 4103B, 500V	2N6159, T 6400E, 2N5443
57864	T4103M	T 4103B, 600V	2N6159, T 6400M, 2N5443
57865	T4104B...M	T 4103B..M, 10A(Tc80°)	T 4100..., T 6400..., 2N6157...6159
57866	T4105B...M	T 4103B..M, 6A(Tc90°)	T 4100..., T 6400..., 2N6157...6159
57867	T4106E...M	T 4100E..M, Igt/Ih<45/20mA	T 4101..., T 6406..., T 6407...
57868	T4107E...M	T 4101E..M, Igt/Ih<45/15mA	T 4101..., T 6406..., T 6407...
57869	T4110E...M	T 4100 E..M	T 6411..., 2N6160...6162, T 6410...

57870	T4111E...M	T 4101 E..M	-
57871	T4113B...M	T 4103 B..M	T 6411..., T 6410..., 2N6160...6162
57872	T4114B...M	T 4104 B..M	T 4110..., T 6411..., 2N6160...6162
57873	T4115B...M	T 4105 B..M	T 4110..., T 6411..., 2N6160...6162
57874	T4116E...M	T 4100..., Igt/Ih<45/20mA	T 4111..., T 4117..., T 6417...
57875	T4117E...M	T 4101..., Igt/Ih<45/15mA	T 4111..., T 4116..., T 6417...
57876	T4120E...M	T 4100 E..M	T 6421..., 2N6163...6165, T 6420...
57877	T4121E...M	T 4101 E..M	-
57878	T4126E...M	T 4100E..M, Igt/Ih<45/20mA	T 4127..., T 6427..., T 6426..., T 4121...
57879	T4127E...M	T 4101E..M, Igt/Ih<45/15mA	T 4127..., T 6427..., T 6426..., T 4121...
57880	T4700B	Igt/Ih<80/<60mA	MAC 15A-4, BT 139/500, TAG 280-200
57881	T4700B	Igt/Ih<80/<60mA	MAC 15A-4, BT 139/500, TAG 280-200
57882	T4700D	T 4700B, 400V	MAC 15A-6, BT 139/500, TAG 280-400
57883	T4700D	T 4700B, 400V	MAC 15A-6, BT 139/500, TAG 280-400
57884	T4700E	T 4700B, 500V	MAC 15A-8, BT 139/500, TAG 280-600
57885	T4700E	T 4700B, 500V	MAC 15A-8, BT 139/500, TAG 280-600
57886	T4700F	T 4700B, 50V	MAC 15A-4, BT 139/500, TAG 280-200
57887	T4700F	T 4700B, 50V	MAC 15A-4, BT 139/500, TAG 280-200
57888	T4700M	T 4700B, 600V	MAC 15A-8, BT 139/600, TAG 280-600
57889	T4700M	T 4700B, 600V	MAC 15A-8, BT 139/600, TAG 280-600
57890	T4700N	T 4700B, 800V	MAC 15A-10, BT 139/800, TAG 280-800
57891	T4700N	T 4700B, 800V	MAC 15A-10, BT 139/800, TAG 280-800
57892	T4706B...N	T 4700B..N, Igt/Ih<45/15mA	MAC 15..., TIC 246..., TXE 10...
57893	T4706B...N	T 4700B..N, Igt/Ih<45/15mA	MAC 15..., TIC 246..., TXE 10...
57894	T5	1SV153A	1SV153A
57895	T5	HVM 27WK	HVM 27WK
57896	T5	BCX 18R	BCX 18R
57897	T5	2SK242-T5	2SK242
57898	T5	2SK1065-5	2SK1065
57899	T5058	BC 142	BC 142
57900	T5A6CI	T 5A6CP	TAG 420-600
57901	T5A6CP	600V, 5A, Igt<50mA	TAG 230-600, TAG 231-600, TXC10H60M
57902	T6	1SV217	1SV217
57903	T6	1SV211	1SV211
57904	T6	HVM 17	HVM 17
57905	T6	BSS 63R	BSS 63R
57906	T6000B	Igt/Ih<80/<35mA	MAC 15A-4, BT 139/500, TAG 280-200
57907	T6000C	T 6000B, 300V	MAC 15A-6, BT 139/500, TAG 280-400
57908	T6000D	T 6000B, 400V	MAC 15A-6, BT 139/500, TAG 280-400
57909	T6000E	T 6000B, 500V	MAC 15A-8, BT 139/500, TAG 280-600
57910	T6000F	T 6000B, 50V	MAC 15A-4, BT 139/500, TAG 280-200
57911	T6000M	T 6000B, 600V	MAC 15A-8, BT 139/600, TAG 280-600
57912	T6000N	T 6000B, 800V	MAC 15A-10, BT 139/800, TAG 280-800
57913	T6001B...N	T 6000B..N, Igt/Ih<80/<50mA	MAC 15A..., BT 139/..., TAG 280...
57914	T6006B...N	T 6000B..N, Igt<45mA	MAC 15..., TIC 246..., TXE 10...



57915	T6260B	Igt/Ih<80/<60mA	MAC 525A-4, TAG 725-200, TAG 726-200
57916	T6260C	T 6260B, 300V	MAC 525A-5, TAG 725-400, TAG 726-400
57917	T6260D	T 6260B, 400V	MAC 525A-6, TAG 725-400, TAG 726-400
57918	T6260E	T 6260B, 500V	MAC 525A-7, TAG 725-600, TAG 726-600
57919	T6260M	T 6260B, 600V	MAC 525A-8, TAG 725-600, TAG 726-600
57920	T6261B...M	T 6261B..M, Igt/Ih<80/<60mA	MAC 525..., MAC 25..., MAC 50...
57921	T6400B	200V, 40A, Igt/Ih<80/<60mA	2N5441...5443
57922	T6400D	T 6400B, 400V	2N5442...5443
57923	T6400E	T 6400B, 500V	2N5443
57924	T6400F	T 6400B, 50V	2N5441...5443
57925	T6400M	T 6400B, 600V	2N5443
57926	T6401B	Igt/Ih<80/<60mA	-
57927	T6401D	T 6401B, 400V	-
57928	T6401E	T 6401B, 500V	-
57929	T6401F	T 6401B, 50V	-
57930	T6401M	T 6401B, 600V	-
57931	T6401N	T 6401N, 800V	-
57932	T6404B	Igt/Ih<120/<90mA	T 6400B, 2N5441...5443
57933	T6404D	T 6404B, 400V	T 6400D, 2N5442...5443
57934	T6404E	T 6404B, 500V	T 6400E, 2N5443
57935	T6405B...E	T 6404B..E, 25A(Tc85°)	T 6404..., T 6400..., 2N5441...5443
57936	T6406B...M	T 6400B..M, Igt/Ih<45/25mA	-
57937	T6407B...M	T 6401B..M, Igt/Ih<45/25mA	T 6406...
57938	T6410B...M	T 6400 B..M	2N5444...5446
57939	T6411B...M	T 6401 B..M	T 6410..., 2N6160...6162, 2N5444...5446
57940	T6414B...E	T 6404 B..E	T 6410..., 2N5444...5446
57941	T6415B...E	T 6405 B..E	T 6411..., 2N6160...6162, 2N5444...5446
57942	T6416B...M	T 6400B..M, Igt/Ih<45/25mA	-
57943	T6417B...M	T 6401B..M, Igt/Ih<45/25mA	-
57944	T6420B...M	T 6400 B..M	-
57945	T6421B...M	T 6401 B..M	T 6420...,2N6163...6165
57946	T6426B...M	T 6406 B..M	-
57947	T6427B...M	T 6407 B..M	T 6426...
57948	T6F/100...800C..	6A(Tc85°C),Igt/Ih<40/<60mA	TAG 15S..., T 12F...
57949	T6F/100...800H..	T 6F/..C	-
57950	T6F/100...800P..	T 6F/..C	-
57951	T6N/100...800C..	6A(Tc85°C),Igt/Ih<20/<60mA	T 8N...C, BStD41..., T 10N...C, BStD41...M
57952	T6N/100...800H..	T 6N/..C	T 8N...H, BStD40..., T 10N...H, BStD40...M
57953	T6N/100...800P..	T 6N/..C	T 8N...H, BStD40..., T 10N...H, BStD40...M
57954	T7	1SV230	1SV230
57955	T7	1SV224	1SV224
57956	T7	1SV258	1SV258
57957	T7	SST 4117	SST 4117
57958	T7(p)	BSR 15	BSR 15
57959	T7,5N/400..800F..	Igt<25mA	TIC 126..., T9,5N..., CS 15-...

57960	T71	BSR 15R	BSR 15R
57961	T7N/100...700F..	Igt<20mA	TIC126..., T7,5N..., TAG680-..., TAG681-...
57962	T8	1SV212	1SV212
57963	T8	1SV229	1SV229
57964	T8	1SV257	1SV257
57965	T8	HVM 25	HVM 25
57966	T8	SST 4118	SST 4118
57967	T8(p)	BSR 16	BSR 16
57968	T81	BSR 16R	BSR 16R
57969	T8A6CI	T 8A6CP	TAG 425...426-600, TAG 451...452-600
57970	T8A6CP	600V, 8A, Igt<50mA	BT 137/600, MAC 222A-8, T 2800M
57971	T8F/100...800C..	8A(Tc85°C),Igt/Ih<40/<60mA	TAG 15S..., T 12F...
57972	T8F/100...800H..	T 8F/..C	-
57973	T8F/100...800P..	T 8F/..C	-
57974	T8N/100...800C..	8A(Tc85°C),Igt/Ih<20/<60mA	BStD41..., T 10N...C, BStD41...M
57975	T8N/100...800H..	T 8N/..C	BStD40..., T 10N...H, BStD40...M
57976	T8N/100...800P..	T 8N/..C	BStD40..., T 10N...H, BStD40...M
57977	T9	1SV227	1SV227
57978	T9	1SV259	1SV259
57979	T9	1SV232	1SV232
57980	T9	HVM 306	HVM 306
57981	T9	SST 4119	SST 4119
57982	T9	BSR 18	BSR 18
57983	T9,5N/400..800F..	Igt<25mA	CS 15-...
57984	T91	BSR 18R	BSR 18R
57985	T92	BSR 18A	BSR 18A
57986	T93	BSR 18AR	BSR 18AR
57987	T9N/100...700F..	Igt<20mA	T 9,5N..., CS 15-...
57988	TA	1SV231	1SV231
57989	TA	1SV226	1SV226
57990	TA	KTC3295-A	KTC 3295
57991	TA	2SA1314-A	2SA1314
57992	TA06	Ub26..38V, Ib<0,2mA, Itsm2A	1N5761, N413M, BR100, D3202Y, DO201YR
57993	TA16090	40888	40888
57994	TA16091	40889	40889
57995	TA16092	16092	
57996	TA16093	16093	
57997	TA16094	16094	
57998	TA16422	RGP 30M	RGP 30M
57999	TA16422	RGP 30M	RGP 30M
58000	TA7137	2N5296	2N5296
58001	TA8160	40890	
58002	TA8161	40891	
58003	TA8162	40892	
58004	TA8163	40892	

58005	TA8348	BDX 65A	BDX 65A
58006	TA8350	BDX 64A	BDX 64A
58007	TA8376	40888	40888
58008	TA8377	40889	40889
58009	TAG06A	Igt/Ih<0,2/<5mA	MCR100-3, BRY55/100, TAG70D, TAG72D
58010	TAG06B	TAG 06A, 200V	MCR100-4, BRY55/200, TAG70D, TAG72D
58011	TAG06C	TAG 06A, 300V	MCR100-5, BRY55/300, TAG70D, TAG72D
58012	TAG06D	TAG 06A, 400V	MCR100-6, BRY55/300, TAG70D, TAG72D
58013	TAG06Y	TAG 06A, 30V	MCR100-3, BRY55/30, TAG70D, TAG72D
58014	TAG06YY	TAG 06A, 60V	MCR100-3, BRY55/60, TAG70D
58015	TAG1-50...600	Igt/Ih<10/<25mA	BTX 30/..., T 1N..., S 2600..., TAG 613...
58016	TAG10-50...1000	Igt/Ih<30/<25mA	T 12N..., CS 35..., MCR 64..., TAG 35...
58017	TAG103X	BR 203	TAG 64..., BR 203
58018	TAG106A...M	C 106 A..M	C 106...1, Z 0403..., C 108..., TAG 108...
58019	TAG107A...M	C 107 A..M	C 107..., S 2061..., TIC 108...
58020	TAG108A...M	C 108 A..M	C 108..., TIC 106..., TAG 623..., TAG 628...
58021	TAG10S-50...1000	Igt/Ih<30/<25mA, <12µs	TAG 15S..., T 12F...
58022	TAG122-100...600	C 122 A..M	C 122..., TIC 116..., BStC10...M, CS 6...
58023	TAG12F400...1000	12A(Tc85°)Igt/Ih<75/100mA	TAG 16F..., TAG 19F..., T 17F...C, T 24F...C
58024	TAG136A...M	TAG 96 A..M, 4A(Tc60°)	Z 0410..., TAG 96..., 2N6068...6075
58025	TAG137A...M	TAG 97 A..M, 4A(Tc60°)	Z 0409..., TAG 97..., 2N6068A...75A
58026	TAG138A...M	TAG 98 A..M, 4A(Tc60°)	Z 0405..., TAG 98..., 2N6068B...6075B
58027	0	14A(Tc85°)Igt/Ih<50/<70mA	BTW 39/..., BTW 45/..., T 12N..., CS 13...
58028	TAG15-100...1000	Igt/Ih<50/<50mA	BTW 39/..., BTW 45/..., T 12N..., CS 13...
58029	100...1000	Igt/Ih<50/<50mA, <12µs	T 12F...
58030	TAG16F400...1000	5/<100mA	T 17F...C, TAG 19F..., T 24F...C
58031	0	16A(Tc85°)Igt/Ih<50/<70mA	BTW 92/..., CS 16..., T 17N..., T 24N...
58032	TAG19F400...1000	5/<100mA	T 17F...C, T 24F...C
58033	TAG2,5-100...800	Igt/Ih<20/<25mA	TAG 611..., TAG 605...
58034	100...800	Igt/Ih<20/<25mA, <12µs	S 5801..., S 5802..., TAG 620S-...
58035	TAG2-50...600	Igt/Ih<1/<5mA	TAG 614...
58036	TAG20-50...1000	Igt/Ih<50/<50mA	BTW 92/..., CS 16..., T 17N..., T 24N...
58037	TAG200-100...600	Igt/Ih<25/<25mA	T2303..., TAG208..., TAG630..., TAG620...
58038	TAG201-100...600	Igt/Ih<10/<10mA	T2302..., TAG202A..., TAG203..., TAG209...
58039	TAG202-100...600	Igt/Ih<10/<10mA	TAG 202A..., TAG 203..., TAG 209...
58040	100...600	Igt/Ih<10/<10mA	TAG203..., TAG209..., Z0409..., TXC18G...
58041	TAG203-100...600	Igt/Ih<10/<10mA	TAG203A..., TAG209..., Z0409..., TXC18G...
58042	TAG204-100...600	Igt/Ih<5/<10mA	TAG 204A..., TAG 205..., Z 0405...
58043	100...600	Igt/Ih<5/<10mA	TAG 204A..., TAG 205..., Z 0405...
58044	TAG205-100...600	Igt/Ih<5/<10mA	TAG 204A..., TAG 205..., Z 0405...
58045	TAG206-100...600	Igt/Ih<3/<5mA	TAG 207..., Z 0402...
58046	TAG207-100...600	Igt/Ih<3/<5mA	TAG 207..., Z 0402...
58047	TAG208-100...600	Igt/Ih<25/<25mA	Z0410..., TAG231..., TAG220..., TAG 421...
58048	TAG209-100...600	Igt/Ih<10/<10mA	TAG 202A..., TAG 203..., Z 0409...
58049	TAG20S-50...1000	Igt/Ih<50/50mA, <12µs	-

58050	TAG220-100...800	Igt/Ih<25/<25mA	TAG 225..., TAG 257...
58051	TAG221-100...800	Igt/Ih<10/<10mA	TXC 18G...M, TAG 226..., MAC 228A...
58052	TAG222-100...800	Igt/Ih<5/<10mA	TAG 227...
58053	TAG224-100...800	Igt/Ih<50/<50mA	T2800..., T2850..., MAC222A..., BT137/...
58054	TAG225-100...800	Igt/Ih<25/<25mA	TAG257..., TAG252..., TAG426..., TAG452...
58055	TAG226-100...800	Igt/Ih<10/<10mA	MAC 228A...
58056	TAG227-100...800	Igt/Ih<5/<10mA	-
58057	TAG230-200...800	Igt/Ih<50/<50mA	TAG 224..., MAC 222A..., BT 138/...
58058	TAG231-200...800	Igt/Ih<25/<50mA	TAG 220..., TAG 225..., TAG 257...
58059	TAG232-200...800	Igt/Ih<10/<25mA	TXC 18G...M, TAG 221..., MAC 228A...
58060	TAG233-200...800	Igt/Ih<5/<10mA	TXC 18D...M, TAG 222..., TAG 227...
58061	TAG240-100...800	Igt/Ih<50/<50mA	TW7N..., T2802..., MAC222..., TIC226...
58062	TAG241-100...800	Igt/Ih<25/<25mA	T 2806..., TAG 252..., TAG 257...
58063	TAG245-100...800	Igt/Ih<50/<50mA	T2802..., MAC222..., TIC226..., TAG224...
58064	TAG246-100...800	Igt/Ih<25/<25mA	T 2806..., TAG 225..., TAG 257...
58065	0	Igt/Ih<50/<70mA	T 24N..., CS 23...
58066	100..800	10A(Tc70°),Igt/Ih<75/<50mA	TAG 251..., TXD 10H...M, BT 138/...
58067	TAG251-100...800	10A(Tc70°),Igt/Ih<50/<50mA	TXD 10H...M, BT 138/..., TAG 255...
58068	TAG252-100...800	10A(Tc70°),Igt/Ih<25/<25mA	TAG 257...
58069	100..800	12A(Tc70°),Igt/Ih<75/<50mA	TAG 256..., BT 138/..., TXD 10H...P
58070	TAG256-100...800	12A(Tc70°),Igt/Ih<50/<50mA	BT 138/..., TXD 10H...P, 2N6346A...6349A
58071	TAG257-100...800	12A(Tc70°),Igt/Ih<25/<25mA	-
58072	TAG260-100...800	Igt/Ih<50/<50mA	TAG 265..., T 4700..., TAG 224...
58073	TAG260-100...800	Igt/Ih<50/<50mA	TAG 265..., T 4700..., TAG 224...
58074	TAG261-100...800	Igt/Ih<25/<25mA	TAG 265..., TAG 225..., TAG 252...
58075	TAG261-100...800	Igt/Ih<25/<25mA	TAG 265..., TAG 225..., TAG 252...
58076	TAG265-100...800	12A(Tc61°),Igt/Ih<50/<50mA	T 4700..., BT 138/..., TAG 255...
58077	TAG265-100...800	12A(Tc61°),Igt/Ih<50/<50mA	T 4700..., BT 138/..., TAG 255...
58078	TAG266-100...800	12A(Tc61°),Igt/Ih<25/<25mA	TAG 257...
58079	TAG266-100...800	12A(Tc61°),Igt/Ih<25/<25mA	TAG 257...
58080	TAG270-100...600	Igt/Ih<50/<50mA	SC245..., BS10...A, TXD99..., T4110...
58081	TAG271-100...600	Igt/Ih<25/<25mA	T 4116..., T 4117..., T 4111...
58082	TAG275-100...600	Igt/Ih<50/<50mA	TW12N...C, SC250..., TXD98..., TW18N...
58083	TAG276-100...600	Igt/Ih<25/<25mA	T 6417...
58084	TAG280-200...800	16A(Tc72°),Igt/Ih<75/<50mA	T6000..., BT139/..., MAC15A..., TAG281...
58085	TAG281-200...800	16A(Tc72°),Igt/Ih<50/<50mA	BT 139/..., MAC 223A...
58086	TAG3-50...800R	Igt/Ih<15/<25mA	TAG 671..., TAG 676..., BStC10...,CS 6...
58087	TAG302-50...600	Igt/Ih<15/<15mA	TAG202..., TAG201..., T2302..., TAG203...
58088	TAG306-50...800	Igt/Ih<50/<50mA	TAG260..., TAG265..., T4700...,TXC10H...M
58089	TAG306-50...800	Igt/Ih<50/<50mA	TAG260..., TAG265..., T4700...,TXC10H...M
58090	TAG307-50...800	TAG 307-50..800	TW 12N...C, TW 18N...
58091	TAG310-50...800	Igt/Ih<50/50mA	TW 12N...C, TW 18N...
58092	TAG340-100...600	Igt/Ih<100/<100mA	T 4700..., BT 138/..., T 6000...
58093	TAG340-100...600	Igt/Ih<100/<100mA	T 4700..., BT 138/..., T 6000...
58094	TAG341-100...600	12A(Tc70°),Igt/Ih<50/<50mA	TAG265..., BTA23..., BT138/..., TAG255...

58095	TAG35-100...1000	Igt/Ih<40/<70mA	MCR 64...
58096	TAG350-100...600	Igt/Ih<100/<100mA	TW18N..., T6411..., 2N6160...6162, T6410...
58097	TAG351-100...600	15A(Tc70°),Igt/Ih<50/<50mA	SC250..., TXD98..., TXE99..., SC260...
58098	100...1000	Igt/Ih<40/<70mA,<18µs	-
58099	TAG3S-50...800R	Igt/Ih<15/<25mA, <12µs	TAG 671S..., TAG 676S..., S 5801...
58100	TAG420-100...800	Igt/Ih<50/<50mA	TAG425..., TAG451..., TAG456..., TAG481...
58101	TAG421-100...800	Igt/Ih<25/<25mA	TAG 426..., TAG 452..., TAG 457...
58102	TAG425-100...800	Igt/Ih<50/<50mA	TAG 451..., TAG 456..., TAG 481...
58103	TAG4441...4444	2N4441..4444	2N4441...4444
58104	TAG451-200...800	Igt/Ih<50/<50mA	TAG 456..., TAG 481...
58105	TAG452-200...800	Igt/Ih<25/<25mA	TAG 457...
58106	TAG456-200...800	10A(Tc70°),Igt/Ih<50/<50mA	TAG 481...
58107	TAG457-200...800	10A(Tc70°),Igt/Ih<25/<25mA	-
58108	TAG480-200...800	Igt/Ih<75/<75mA	-
58109	TAG481-200...800	Igt/Ih<50/<50mA	-
58110	TAG5001A...M	Igt/Ih<200/<800mA	-
58111	TAG5002A...M	TAG 5001 A..M, tgq3,5µs	-
58112	TAG5003A...M	TAG 5001 A..M, tgq10µs	-
58113	TAG510B	Igt/Ih<10/<50mA	TAG631-200, TAG621-200, TAG 651-200
58114	TAG510D	TAG 510B, 400V	TAG631-400, TAG621-400, TAG626-400
58115	TAG510E	TAG 510B, 500V	TAG631-500, TAG621-500, TAG626-500
58116	TAG510M	TAG 510B, 600V	TAG631-600, TAG621-600, TAG626-600
58117	TAG511B...M	TAG 510B..M, Igt/Ih<5/<25mA	TAG632..., TAG622..., TAG662..., TAG667...
58118	TAG512B...M	TAG 510B..M, Igt/Ih<2/<8mA	S 2062...
58119	TAG520A	100V, 1,6A, Igt/Ih<10/<25mA	2N1596...1599, BTX 30/100, T 1N100
58120	TAG520B	TAG 520A, 200V	2N1597...1599, BTX 30/200, T 1N200
58121	TAG520C	TAG 520A, 300V	2N1598...1599, BTX 30/300, T 1N300
58122	TAG520D	TAG 520A, 400V	2N1599, BTX 30/400, T 1N400
58123	TAG520F	TAG 520A, 50V	2N1595...1599, BTX 30/50, T 1N100
58124	TAG521A...F	TAG 520A..F, Igt/Ih<0,2/<10mA	2N2322...2329, TAG615..., C106..., X0403...
58125	TAG59A	100V, 1A, Igt/Ih<0,2/<5mA	2N6681...6685, BT 149A, MCR 606-3
58126	TAG59B	TAG 59A, 200V	2N6682...6685, BT 149B, MCR 606-4
58127	TAG59D	TAG 59A, 400V	2N6683...6685, BT 149D, MCR 606-6
58128	TAG59E	TAG 59A, 500V	2N6684...6685, BT 149E, MCR 606-7
58129	TAG59F	TAG 59A, 50V	2N6681...6685, BT 149F, MCR 606-2
58130	TAG59M	TAG 59A, 600V	2N6684...6685, BT 149M, MCR 606-8
58131	TAG59S	TAG 59A, 700V	2N6685
58132	50...1000(R)	Igt/Ih<25/<25mA	-
58133	TAG605-100...800	Igt/Ih<25/<30mA	MCR107..., TAG630..., TAG620..., BS1C10...
58134	TAG606-100...800	Igt/Ih<10/<25mA	S2620..., TAG631..., TAG621..., TAG 626...
58135	TAG607-100...800	Igt/Ih<5/<15mA	TAG632..., TAG622..., TAG627..., TAG662...
58136	TAG60A	<10µs	BRX 46...49, TAG 62A, BRX 51...56
58137	TAG60F	TAG 60A, 50V	BRX 45...49, TAG 62F, BRX 50...56
58138	TAG60Y	TAG 60A, 30V	BRX 44...49, TAG 62Y, BRX 50...56
58139	TAG611-100...800	Igt/Ih<25/<25mA	TAG605..., TAG630..., TAG620..., BS1C10...

58140	TAG612-100...800	Igt/Ih<10/<25mA	TAG606..., TAG631..., TAG621..., TAG626...
58141	TAG613-100...800	Igt/Ih<5/<15mA	TAG607..., TAG632..., TAG622..., TAG627...
58142	TAG614-100...800	Igt/Ih<1/<10mA	TIC 108...
58143	TAG615-100...800	Igt/Ih<0,2/<5mA	TIC106..., TAG633..., TAG623..., TAG628...
58144	TAG6151...6156	2N6151..6156	2N6151...6156
58145	TAG620-100...800	Igt/Ih<25/<25mA	BStC10..., TAG625..., TIC126..., T7,5N...
58146	100...800	TAG 620-100..800, <12µs	TAG625S..., TAG660S..., TAG665S..., BT151...
58147	TAG621-100...800	Igt/Ih<10/<25mA	TAG626..., T3,5N..., TAG661..., TAG666...
58148	100...800	TAG 621-100..800, <12µs	TAG 626S..., TAG 651S..., TAG 666S...
58149	TAG622-100...800	Igt/Ih<5/<15mA	TAG 667...
58150	TAG623-100...800	Igt/Ih<0,2/<5mA	TAG 628..., S 4060...
58151	TAG625-100...800	Igt/Ih<25/<25mA	TIC116..., CS6..., TAG660..., S2800...
58152	100...800	TAG 625-100..800, <12µs	TAG 660S..., TAG 665S..., BT 151/...
58153	TAG626-100...800	Igt/Ih<10/<25mA	T 3,5N..., TAG 661..., TAG 666...
58154	100...800	TAG 626-100..800, <12µs	TAG 661S..., TAG 666S..., BT 151/...
58155	TAG627-100...800	Igt/Ih<5/<15mA	TAG 662..., TAG 667...
58156	TAG628-100...800	Igt/Ih<0,2/<5mA	-
58157	TAG62A...Y	TAG 60 A..Y	TAG 60..., BRX 44...49, BRX 50...56
58158	TAG630-100...800	Igt/Ih<25/<25mA	TAG620..., BStC10..., TAG625..., TIC116...
58159	TAG631-100...800	Igt/Ih<10/<25mA	TAG621..., BStC10..., TAG626..., T3,5N...
58160	TAG632-100...800	Igt/Ih<5/<15mA	TAG622..., TAG627..., TAG662..., TAG667...
58161	TAG633-100...800	Igt/Ih<0,2/<5mA	TIC106..., TAG623..., TAG628..., S4060...
58162	TAG64A...Y	TAG 60 A..Y, 0,65A(Tc90°C)	TAG 60..., BRX 44...49, BRX 50...56
58163	TAG650-100...600	Igt/Ih<50/<50mA	TAG 655...
58164	100...600	TAG 650-100..600, <12µs	TAG 655S...
58165	TAG651-100...600	Igt/Ih<15/<50mA	TAG 656...
58166	100...600	TAG 651-100..600, <12µs	TAG 656S...
58167	TAG655-100...600	Igt/Ih<50/<50mA	TAG 655S..., BStD10..., BT 152/...
58168	100...600	TAG 655-100..600, <12µs	CSF 11...
58169	TAG656-100...600	Igt/Ih<15/<50mA	C122..., TIC116..., BStC10...M, CS6...
58170	100...600	TAG 656-100..600, <12µs	TAG 661S..., TAG 666S..., BT 151/...
58171	TAG660-100...800	Igt/Ih<25/<30mA	S 2800..., 2N6394...6399, TAG 655...
58172	100...800	TAG 660-100..800, <12µs	TAG 665S..., BT 151/...
58173	TAG661-100...800	Igt/Ih<10/<25mA	TAG 666..., BStD16...
58174	100...800	TAG 661-100..800, <12µs	TAG 666S..., BT 151/...
58175	TAG662-100...800	Igt/Ih<5/<15mA	TAG 667..., BStD16...
58176	TAG665-100...800	Igt/Ih<25/<30mA	TIC126..., T7,5N..., TAG680..., BStD10...
58177	100...800	TAG 665-100..800, <12µs	BT 151/...
58178	TAG666-100...800	Igt/Ih<10/<25mA	BStD10..., BStD16...
58179	100...800	TAG 666-100..800, <12µs	BT 151/...
58180	TAG667-100...800	Igt/Ih<5/<15mA	-
58181	TAG66A...Y	TAG 60 A..Y, 0,65A(Tc115°C)	BRX 60...66
58182	TAG670-100...800	Igt/Ih<50/<50mA	TAG 675..., BStD16..., BT 152/...
58183	100...800	TAG 670-100..800, <12µs	TAG 675S..., CSF 11...
58184	TAG671-100...800	Igt/Ih<15/<25mA	TAG 676..., S 2800..., 2N6394...6399



58185	100...800	TAG 671-100..800, <12µs	TAG 676S..., BT 151/...
58186	TAG675-100...800	Igt/Ih<50/<50mA	BStD10...,BStD16...,BT152...2N6504...6509
58187	100...800	TAG 675-100..800, <12µs	CSF 11...
58188	TAG676-100...800	Igt/Ih<15/<25mA	TIC126..., T7,5N..., TAG681..., T9,5N...
58189	100...800	TAG 676-100..800V, <12µs	BT 151/...
58190	TAG680-100...800	Igt/Ih<25/<30mA	2N6400...6405, BStD10...M, T9,5N...,CS 15...
58191	TAG681-100...800	Igt/Ih<15/<30mA	BStD10...M, T 9,5N..., CS 15...
58192	50..1000(R)	Igt/Ih<25/<25mA,<12µs	-
58193	50...1000(R)	Igt/Ih<25/<25mA	T 12N..., C 35..., MCR 64..., TAG 35...
58194	TAG70D	Igt/Ih<0,2/<5mA	BRY 55/400, TAG 72D, 2N6683...6685
58195	TAG70E	TAG 70D, 500V	BRY 55/500, TAG 72E, 2N6684...6685
58196	TAG70M	TAG 70D, 600V	BRY 55/600, TAG 72M, 2N6684...6685
58197	TAG70N	TAG 70D, 800V	BRY 55/800, TAG 72N, 2N6685
58198	TAG70S	TAG 70D, 700V	BRY 55/700, TAG 72S, 2N6685
58199	TAG725-200...800	Igt/Ih<75/<75mA	TAG 740..., MAC 25A..., MAC 50A...
58200	TAG726-200...800	Igt/Ih<50/<50mA	TAG 741...
58201	TAG72D...N	TAG 70 D..N	BRY 55/..., TAG 72..., 2N6681...6685
58202	TAG740-200...800	Igt/Ih<75/<75mA	MAC 50A...
58203	TAG741-200...800	Igt/Ih<50/<50mA	-
58204	50..1000(R)	Igt/Ih<25/<25mA,<12µs	TAG 15S..., T 12F...
58205	TAG825-200...800	Igt/Ih<75/<75mA	TAG 840..., BTW 67/...
58206	TAG826-200...800	Igt/Ih<50/<50mA	TAG 841..., BTW 66/...
58207	TAG840-200...800	Igt/Ih<75/<75mA	BTW 67/...
58208	TAG841-200...800	Igt/Ih<50/<50mA	-
58209	TAG92A,-3	100V, 0,6A, Igt/Ih<10/<10mA	MAC 91-3, MAC 94-3, TAG 94A, Z 0106B
58210	TAG92B,-4	TAG 92A, 200V	MAC 91-4, MAC 94-4, TAG 94B, Z 0106B
58211	TAG92C,-5	TAG 92A, 300V	MAC 91-5, MAC 94-5, TAG 94C, Z 0106D
58212	TAG92D,-6	TAG 92A, 400V	MAC 91-6, MAC 94-6, TAG 94D, Z 0106D
58213	TAG92Y,-1	TAG 92A, 30V	MAC 91-2, MAC 94-2, TAG 94Y, Z 0106B
58214	TAG92YY,-2	TAG 92A, 60V	MAC 91-3, MAC 94-3, TAG 94YY, Z 0106B
58215	TAG93A...YY	TAG 92A..YY, Igt/Ih<5/<10mA	MAC 92(A)..., MAC 95..., Z 0104...
58216	TAG94A...YY	Igt/Ih<10/<10mA	MAC 91A..., MAC 94A..., Z 0106...
58217	TAG96A	Igt/Ih<25/<50mA	2N6070...6075
58218	TAG96B	TAG 96A, 200V	2N6071...6075
58219	TAG96C	TAG 96A, 300V	2N6072...6075
58220	TAG96D	TAG 96A, 400V	2N6073...6075
58221	TAG96E	TAG 96A, 500V	2N6074...6075
58222	TAG96M	TAG 96A, 600V	2N6075
58223	TAG97A...M	TAG 96A..M, Igt/Ih<10/<25mA	2N6070A...6075A
58224	TAG98A...M	TAG 96A..M, Igt/Ih<5/<10mA	2N6070B...6075B
58225	TAG9N400...1000	9A(Tc85°),Igt/Ih<50/<70mA	TAG15..., TAG14N..., BTW39/..., BTW45/...
58226	TAS3707D	S 3703, +400V	TU 3F400H, TD 3F400H,TD 4F400H
58227	TAS3707EF	S 3703, +650V	TU 3F700H, TD 3F700H,TD 4F700H
58228	TAS3900..	S 3900 ..	S 3900 ...
58229	TAS3901..	S 3901 ..	S 3901 ...

58230	TAS7431..	S 7310 ..	S 7310 ...
58231	TB	1SV238	1SV238
58232	TB	KTC3295-B	KTC 3295
58233	TB	2SA1314-B	2SA1314
58234	TBC327	BC 327	BC 327
58235	TBC328	BC 328	BC 328
58236	TBC337	BC 337	BC 337
58237	TBC338	BC 338	BC 338
58238	TBC546	BC 546	BC 546
58239	TBC547	BC 547	BC 547
58240	TBC548	BC 548	BC 548
58241	TBC549	BC 549	BC 549
58242	TBC550	BC 550	BC 550
58243	TBC556	BC 556	BC 556
58244	TBC557	BC 557	BC 557
58245	TBC558	BC 558	BC 558
58246	TBC559	BC 559	BC 559
58247	TBC560	BC 560	BC 560
58248	TBF757	BF 757	BF 757
58249	TBF758	BF 758	BF 758
58250	TBF759	BF 759	BF 759
58251	TBF760	BF 760	BF 760
58252	TBF761	BF 761	BF 761
58253	TBF762	BF 762	BF 762
58254	TBF869	BF 869	BF 869
58255	TBF870	BF 870	BF 870
58256	TBF871	BF 871	BF 871
58257	TBF872	BF 872	BF 872
58258	TC	1SV239	1SV239
58259	TC	1SV260	1SV260
58260	TC	2SC2736	2SC2736
58261	TC	2SA1314-C	2SA1314
58262	TCH98(B)	40V, 0,05A, 15MHz	BC 212, BC 257, BC 307, BC 557
58263	TCH99(B)	TCH 98, 70V	BC 212, BC 256, BC 266, BC 556
58264	TD	1SV262	1SV262
58265	TD	P6 SMB-47C	P6 SMB-47C
58266	TD041	BA 157	BA 157
58267	TD1003	BRY 54/100T	BRY 54/100T
58268	TD1011	BC 556	BC 556
58269	TD1095	35V, 0,05A	BA 127, BA 147/50, BA 215, 1N4148...49
58270	TD129	50V	BA 127, BA 147/50, BA 215, 1N4148...49
58271	TD13002	TE 13002, 20W(Tc60°)	-
58272	SMD	TE 13002..13005, SMD	-
58273	TD13003	TE 13003, 20W(Tc60°)	-
58274	TD13004..	TE 13004.., 30W(Tc60°)	-

58275	TD13005..	TE 13005..., 30W(Tc60°)	-
58276	TD144	BZX 62	BZX 62
58277	TD147	1N4148	1N4148
58278	TD153	50V	BA 127, BA 147/50, BA 215, 1N4148...49
58279	TD175	1N4148	1N4148
58280	TD176	BA 157	BA 157
58281	TD184	BY 127	BY 127
58282	TD190(A...C)	BA 157	BA 157
58283	TD2,8F400...800H	mA	BStCC01...H, TD 3F...H, TD 4F...H
58284	TD2,8F400...800R	mA	BStCC01...R, TD 3F...R, TD 4F...R
58285	TD2003	BRY 54/200T	BRY 54/200T
58286	TD260	BA 157	BA 159
58287	TD300	BA 316	BA 316
58288	TD3003	BRY 54/300T	BRY 54/300T
58289	TD3F400...800H	TD 2,8F ..H, 3,4A	TD 4F...H
58290	TD3F400...800R	TD 2,8F..R, 3,4A	TD 4F...R
58291	TD3FP800H	TD 2,8F ..H, 3,4A	BStCC0253H, 17088
58292	TD3FP800R	TD 2,8F ..R, 3,4A	BStCC0253R, 17089
58293	TD4003	BRY 54/400T	BRY 54/400T
58294	TD469	1N4148	1N4148
58295	TD473	BA 316	BA 316
58296	TD482	1N4148	1N4148
58297	TD490	BAY 21	BAY 21
58298	TD4F400...800H	TD 2,8F..H, 4A	BStCC02...H, 17088
58299	TD4F400...800R	TD 2,8F..R, 4A	BStCC02...R, 17089
58300	TD5	2N1595, 500V	2N1595
58301	TD5001S	2N2322, 500V	2N2322
58302	TD5003	BRY 54/500T	BRY 54/500T
58303	TD503	BRY 54/30T, 50V	BRY 54/30T
58304	TD6	2N1595, 600V	2N1595
58305	TD6001S	2N2322, 600V	2N2322
58306	TD6003	BRY 54/600T	BRY 54/600T
58307	TD702	BAV 19	BAV 19
58308	TD861	1N4148	1N4148
58309	TD960016-1	1S188	1S188
58310	TE	1SV269	1SV269
58311	TE	P6 SMB-47CA	P6 SMB-47CA
58312	TE	2SC3906K-E	2SC3906K
58313	TE	2SC4102-E	2SC4102
58314	TE	2SD1702-TE	2SD1702
58315	TE00671	MJ 900	MJ 900
58316	TE13002	MJ 4360, MJE 13002	MJE 13002
58317	TE13003	MJ 4361, MJE 13003	MJE 13003
58318	TE13004	MJ 4380, MJE 13004	MJE 13004
58319	D		-

58320	TE13005	MJ 4381, MJE 13005	MJE 13005
58321	TE13006	MJE 13006	MJE 13006
58322	TE13007	MJE 13007	MJE 13007
58323	TE13008	MJE 13008	MJE 13008
58324	TE13009	MJE 13009	MJE 13009
58325	TE404	BD 241B	BD 241B
58326	TE404	BD 241B	BD 241B
58327	TE441	BF 459	BF 459
58328	TEC8012	40V, 0,5A, 0,625W, 200MHz	BC 327(A), BC 638, BC 640, 2SB1116(A)
58329	TEC8013	40V, 0,5A, 0,625W, 300MHz	BC 337(A), BC 637, BC 639, 2SD1616(A)
58330	TEC9011	50V, 0,05A, 0,4W, >100MHz	BF 240...241, BF 254...255, BF 594...595
58331	TEC9012	30V, 0,8A, 0,625W	BC 327...328, BC 636, BC 638, BC 640
58332	TEC9013	30V, 0,8A, 0,625W	BC 337...338, BC 635, BC 637, BC 639
58333	TEC9014	60V, 0,15A, 0,625W, >150MHz	BC 414, BC 550, 2SC2675, 2SC2631...32
58334	TEC9015	50V, 0,15A, 0,625W, >100MHz	BC 416, BC 560, 2SA1137, 2SA1123...24
58335	TEC9016	40V, 25mA, 0,4W, 620MHz	BF 240...241, BF 254...255, BF 594...595
58336	TED1402	60V, 0,15A, 0,4W, 175MHz	BC 174, BC 182, BC 546, 2SC3245(A)
58337	TED1502	40V, 0,03A, 0,25W, 550MHz	BF 240...241, BF 254...255, BF 594...595
58338	TED1602	50V, 0,15A, 0,4W, 150MHz	BC 256, BC 212, BC 556, 2SA1285(A)
58339	TED1702	35V, 0,8A, 0,6W, 120MHz	BC 337...338, BC 635, BC 637, BC 639
58340	TED1802	35V, 0,8A, 0,6W, 120MHz	BC 327...328, BC 636, BC 638, BC 640
58341	TEO1088	BDX 33A	BDX 33A
58342	TEO1089	BDX 34A	BDX 34A
58343	TEO1299	BD 313	BD 313
58344	TEO1300	BD 314	BD 314
58345	TF	P6 SMB-51C	P6 SMB-51C
58346	TF	1SV270	1SV270
58347	TF	BAL 99	BAL 99
58348	TF	2SD1702-TF	2SD1702
58349	TF1095	TD 1095	TD 1095
58350	TF286	BC 141	BC 141
58351	TF320M	200V, 3A, Igt/Ih<50/<70mA	TAG 620-200, TAG 621-200, TAG 622-200
58352	TF321M	Igt/Ih<10/4mA	TAG 621-200, TAG 622-200
58353	TF321M-A	Igt/Ih<0,1/1mA	S 0602BH, TAG 623-200, TIC 106B
58354	TF340M	TF 320M 400	TAG 620-400, TAG 621-400, TAG 622-400
58355	TF340M-A	mA, 5µs	-
58356	TF341M	TF 321M, 400V	TAG 621-400, TAG 622-400
58357	TF341M-A	TF 321M-A, 400V	S 0602DH, TAG 623-400, TIC 106D
58358	TF361M	TF 321M, 600V	TAG 621-600, TAG 622-600
58359	TF361M-A	TF 321M-A, 600V	S 0602MH, TAG 623-600, TIC 106M
58360	TF49	15V, 0,2A, 0,06W	AC 125...126, AC 151, ASY 26...27
58361	TF521..561S	TF 521..561M, , 5A	-
58362	TF521M	Igt/Ih<15/4mA	C 122B, TAG 660...662-200, TIC 116B
58363	TF541M	TF 521M, 400V	C 122D, TAG 660...662-400, TIC 116D
58364	TF561M	TF 521M, 600V	C 122M, TAG 660...662-600, TIC 116M

58365	TF620M	200V, 6A, Igt/Ih<30/30mA	S 2800B, TAG 660...661-200, TIC 116B
58366	TF640M	TF 620M, 400V	S 2800D, TAG 660...661-400, TIC 116D
58367	TF65	16V, 0,05A, 0,06W	AC 125...126, AC 151
58368	TF65/30	TF 65, 32V	AC 125...126, AC 151
58369	TF66	16V, 0,3A, 0,1W	AC 128, AC 153, AC 188
58370	TF66/30	TF 66, 32V	AC 128, AC 153
58371	TF66/60	TF 66, 64V	ACY 24, ASY 48, ASY 77
58372	TF78	16V, 0,6A, 3W(Tc45°)	2SB493
58373	TF78/30	TF 78, 32V	2SB493
58374	TF78/60	TF 78, 64V	-
58375	TF821..861S	TF 821..861M	-
58376	TF821M	200V, 8A, Igt/Ih<15/10mA	S1205B, TAG 680...681-200, TIC 122B
58377	TF841M	TF 821M, 400V	S1205D, TAG 680...681-400, TIC 122D
58378	TF861M	TF 821M, 600V	S1205M, TAG 680...681-600, TIC 122M
58379	TFH340M	mA, <5µs	S 5800D...5802D, TAG 620S...621S-400
58380	TFH341S	<3,5µs	TAG 650S-400, TAG 651S-400
58381	TFH361S	TFH 341S, 600V	TAG 650S-600, TAG 651S-600
58382	TFR1L..T	L800, N1	BY 350/1500, GP 10W, DM 513, EM 516
58383	TFR2L..T	800..1500V, 0,5A, <4µs	BY 350/1500, GP 10W, DM 513, EM 516
58384	TFR3L..T	800..1500V, 0,2A, <1,5µs	BY 203/12.../20, SHG 1...2,5
58385	TFR4L..T	800..1500V, 0,3A, <4µs	BY 203/12.../20
58386	TG	P6 SMB-51CA	P6 SMB-51CA
58387	TG	2SK302-GR	2SK302
58388	TG	2SK882-GR	2SK882
58389	TG840M	400V, 8A, Igt/Ih<30/15mA	TIC 122D, TAG 680-400, TAG 681-400
58390	TGH340M	mA, <5µs	S 5800D...5802D, TAG 620S...621S-400
58391	TH	P6 SMB-56C	P6 SMB-56C
58392	TH	SM 4T 150	SM 4T...
58393	TI-	2SC4197	2SC4197
58394	TI-	2SC5136	2SC5136
58395	TI-	2SC4260	2SC4260
58396	TI1131	200V, 7,5A, 80W, >7,5MHz	2N1724A
58397	TI1132	200V, 7,5A, 80W, >7,5MHz	2N1724A
58398	TI1133	150V, 7,5A, 80W, >7,5MHz	2N1724A
58399	TI1134	150V, 7,5A, 80W, >7,5MHz	2N1724A
58400	TI1135	100V, 7,5A, 80W, >7,5MHz	2N1724(A)
58401	TI1136	100V, 7,5A, 80W, >7,5MHz	2N1724(A)
58402	TI1151	200V, 7,5A, 80W, >7,5MHz	2N1724A
58403	TI1152	200V, 7,5A, 80W, >7,5MHz	2N1724A
58404	TI1153	150V, 7,5A, 80W, >7,5MHz	2N1724A
58405	TI1154	150V, 7,5A, 80W, >7,5MHz	2N1724A
58406	TI1155	100V, 7,5A, 80W, >7,5MHz	2N1724(A)
58407	TI1156	100V, 7,5A, 80W, >7,5MHz	2N1724(A)
58408	TI3016	>1700MHz	BFQ 59, BFQ 70, BFR 34, BFT 97
58409	TI3027	45V, 7A, 106W	AL 100...103, AUY 22(A), 2N2526...27

58410	TI3028	TI 3027, 60V	AL 100...103, AUY 22(A), 2N2526...27
58411	TI3029	TI 3027, 80V	AL 100...103, AUY 22(A), 2N2526...27
58412	TI3030	TI 3027, 100V	AL 100...103, ASZ 15, ASZ 18, 2N2527
58413	TI3031	TI 3027, 120V	AL 100...103, AUY 38, 2N2527
58414	TI407	450MHz	BF 240...241, BF 254...255, BF 505
58415	TI408	300MHz	BF 240...241, BF 254...255, BF 505
58416	TI409	300MHz	BF 240...241, BF 254...255, BF 505
58417	TI410	600MHz	BF 225, BF 314, BF 496, BF 502, BF 505
58418	TI411	50V, 0,8A, 0,3W, >100MHz	BC 337, BC 637, BC 639, 2SD667
58419	TI412	2N3704	2N3704
58420	TI413	2N3705	2N3705
58421	TI414	2N3706	2N3706
58422	TI415	2N3707	2N3707
58423	TI416	2N3708	2N3708
58424	TI417	2N3710	2N3710
58425	TI418	2N3711	2N3711
58426	TI419	30V, 0,03A, 0,25W, >300MHz	BC 168, BC 183, BC 238, BC 548
58427	TI420	2N2387	2N2387
58428	TI421	2N2388	2N2388
58429	TI422	2N851	2N851
58430	TI423	2N852	2N852
58431	TI424	2N2389	2N2389
58432	TI425	2N2390	2N2390
58433	TI426	2N2391	2N2391
58434	TI427	2N2392	2N2392
58435	TI428	2N2393	2N2393
58436	TI429	2N2394	2N2394
58437	TI42A	Ub28..36V, Itsm1A	-
58438	TI430	2N849	2N849
58439	TI431	2N850	2N850
58440	TI432	2N2395	2N2395
58441	TI433	2N2396	2N2396
58442	TI43A	Ub28..36V, Itsm1A	-
58443	TI440		AF 109R, AF 139, AF 239(S)
58444	TI442		AF 139, AF 239(S)
58445	TI443		AF 109R, AF 139, AF 239(S)
58446	TI444		AF 109R, AF 139, AF 239(S)
58447	TI445		AF 109R, AF 139, AF 239(S)
58448	TI446	30V, 0,05A, 0,075W	-
58449	TI447	30V, 0,05A, 0,075W	-
58450	TI448	30V, 0,05A, 0,075W	-
58451	TI450	2N849	2N849
58452	TI451	2N850	2N850
58453	TI457	2N2391	2N2391
58454	TI458	2N2392	2N2392



58455	TI459	2N2395	2N2395
58456	TI460	2N2396	2N2396
58457	TI461	2N2393	2N2393
58458	TI462	2N2394	2N2394
58459	TI480	50V, 0,06A, 0,6W, 1MHz	BC 140...141, BC 300...302, 2N1613
58460	TI481	TI 480, 80V	BC 140...141, BC 300...302, 2N1613
58461	TI482	B>20	BC 140...141, BC 300...302, 2N2218...19
58462	TI483	B>20	BC 140...141, BC 300...302, 2N2218...19
58463	TI484	TI 483, B>40	BC 140...141, BC 300...302, 2N2218...19
58464	TI485	20V, 0,05A, 0,3W, >100MHz	BC 168, BC 183, BC 238, BC 548
58465	TI486	80, 1,5A, 1W, >50MHz	BCX 40, BSS 42...43, BSX 45...47
58466	TI487	TI 486, 15W(Tc100°)	BD 139, BD 230, 2SC2275(A), 2SC2528
58467	TI490	2N780	2N780
58468	TI492	40V, 0,025A, 0,15W	BC 167, BC 183, BC 237, BC 547
58469	TI493	40V, 0,02A, 0,125W	BC 167, BC 183, BC 237, BC 547
58470	TI494	40V, 0,02A, 0,125W	BC 167, BC 183, BC 237, BC 547
58471	TI495	40V, 0,02A, 0,125W	BC 167, BC 183, BC 237, BC 547
58472	TI496	70V, 0,06A, 0,6W	BC 174, BC 182, BC 190, BC 546
58473	TI539	60V, 3,5A, 25W	AL 102...103, AUY 20, 2N2137...46
58474	TI540	TI 539, 80V	AL 102...103, AUY 20, 2N2137...46
58475	TI650C	BF 245	BF 245
58476	TI704C	BF 245	BF 245
58477	TI711A	360MHz	AFY 18
58478	TIC101A	100V, 5A, Igt/Ih<0,4/<5mA	TIC 106A, TAG 623-100, TAG 628-100
58479	TIC101B	TIC 101A, 200V	TIC 106B, TAG 623-200, TAG 628-200
58480	TIC101C	TIC 101A, 300V	TIC 106C, TAG 623-300, TAG 628-300
58481	TIC101D	TIC 101A, 400V	TIC 106D, TAG 623-400, TAG 628-400
58482	TIC101E	TIC 101A, 500V	TIC 106E, TAG 623-500, TAG 628-500
58483	TIC101F	TIC 101A, 50V	TIC 106F, TAG 623-100, TAG 628-100
58484	TIC101M	TIC 101A, 600V	TIC 106M, TAG 623-600, TAG 628-600
58485	TIC101Y	TIC 101A, 30V	TIC 106Y, TAG 623-100, TAG 628-100
58486	TIC102A...Y	TIC 101A..Y, Igt/Ih<5/<5mA	TAG622..., TAG627..., T3,5N..., CS3...
58487	TIC106A	Igt/Ih<0,2/<5mA	TAG 623-100, TAG 628-100, S 4060A
58488	TIC106B	TIC 106A, 200V	TAG 623-200, TAG 628-200, S 4060B
58489	TIC106C	TIC 106A, 300V	TAG 623-300, TAG 628-300, S 4060C
58490	TIC106D	TIC 106A, 400V	TAG 623-400, TAG 628-400, S 4060D
58491	TIC106E	TIC 106A, 500V	TAG 623-500, TAG 628-500, S 4060E
58492	TIC106F	TIC 106A, 50V	TAG 623-100, TAG 628-100, S 4060F
58493	TIC106M	TIC 106A, 600V	TAG 623-600, TAG 628-600, S 4060M
58494	TIC106N	TIC 106A, 800V	TAG 623-800, TAG 628-800, S 4060N
58495	TIC106S	TIC 106A, 700V	TAG 623-700, TAG 628-700, S 4060S
58496	TIC106Y	TIC 106A, 30V	TAG 623-100, TAG 628-100, S 4060F
58497	TIC108A...Y	TIC 106A..Y, Igt/Ih<1/<10mA	TIC106..., TAG622..., TAG623..., TAG628...
58498	TIC116A	Igt/Ih<20/<40mA	CS6-02, BStC1026M, TAG660-100, S2800A
58499	TIC116B	TIC 116A, 200V	CS6-02, BStC1026M, TAG660-200, S2800B

58500	TIC116C	TIC 116, 300V	CS6-04, BStC1026M, TAG660-400, S2800C
58501	TIC116D	TIC 116, 400V	CS6-04, BStC1026M, TAG660-400, S2800D
58502	TIC116E	TIC 116, 500V	CS6-06, BStC1033M, TAG660-500, S2800E
58503	TIC116F	TIC 116, 50V	CS6-02, BStC1026M, TAG660-100, S2800F
58504	TIC116M	TIC 116, 600V	CS6-06, BStC1040M, TAG660-600, S2800M
58505	TIC116N	TIC 116, 800V	CS6-08, BStC1053M, TAG660-800, S2800N
58506	TIC116S	TIC 116, 700V	CS6-08, BStC1046M, TAG660-700, S2800S
58507	TIC122B	Igt/Ih<25/<30mA	TIC126B, BStD1026, T7,5N400, TAG680-200
58508	TIC122D	TIC 122, 400V	TIC126D, BStD1026, T7,5N400, TAG680-400
58509	TIC122E	TIC 122, 500V	TIC126E, BStD1033, T7,5N600, TAG680-500
58510	TIC122F	TIC 122, 50V	TIC126F, BStD1026, T7,5N400, TAG680-100
58511	TIC126A...N	TIC 116A..N, 7,5A(Tc70°)	BStD10..., T7,5N..., TAG680..., T9,5N...
58512	TIC163A...F	Igt/Ih<20/<40mA	-
58513	TIC163A...F	Igt/Ih<20/<40mA	-
58514	TIC20	TIC 220 B	TIC 220 B
58515	TIC201A	Igt/Ih<25/<30mA	TAG 231-200, TAG 220-100, TAG 225-100
58516	TIC201B	TIC 201A, 200V	TAG 231-200, TAG 220-200, TAG 225-200
58517	TIC201C	TIC 201A, 300V	TAG 231-400, TAG 220-300, TAG 225-300
58518	TIC201D	TIC 201A, 400V	TAG 231-400, TAG 220-400, TAG 225-400
58519	TIC201E	TIC 201A, 500V	TAG 231-600, TAG 220-500, TAG 225-500
58520	TIC201M	TIC 201A, 600V	TAG 231-600, TAG 220-600, TAG 225-600
58521	TIC201N	TIC 201A, 800V	TAG 231-800, TAG 220-800, TAG 225-800
58522	TIC201S	TIC 201A, 700V	TAG 231-700, TAG 220-700, TAG 225-700
58523	TIC205A	Igt/Ih<10/<30mA	TAG 201-100, TAG 202-100, T 2302A
58524	TIC205B	TIC 205A, 200V	TAG 201-200, TAG 202-200, T 2302B
58525	TIC205D	TIC 205A, 400V	TAG 201-400, TAG 202-400, T 2302D
58526	TIC206A	Igt/Ih<10/<30mA	100
58527	TIC206B	TIC 206A, 200V	200
58528	TIC206C	TIC 206A, 300V	400
58529	TIC206D	TIC 206A, 400V	400
58530	TIC206E	TIC 206A, 500V	600
58531	TIC206M	TIC 206A, 600V	600
58532	TIC206N	TIC 206A, 800V	800
58533	TIC206S	TIC 206A, 700V	800
58534	TIC21	TIC 220 D	TIC 220 D
58535	TIC215A	Igt/Ih<10/<30mA	TAG 202-100, T 2302A, TAG 202A-100
58536	TIC215B	TIC 215A, 200V	TAG 202-200, T 2302B, TAG 202A-200
58537	TIC215D	TIC 215A, 400V	TAG 202-400, T 2302D, TAG 202A-400
58538	TIC216A	Igt/Ih<10/<30mA	TXC 18H40M, TAG 221-100, TAG 226-100
58539	TIC216B	TIC 216A, 200V	TXC 18H40M, TAG 221-200, TAG 226-200
58540	TIC216C	TIC 216A, 300V	TXC 18H40M, TAG 221-300, TAG 226-300
58541	TIC216D	TIC 216A, 400V	TXC 18H40M, TAG 221-400, TAG 226-400
58542	TIC216E	TIC 216A, 500V	TXC 18H50M, TAG 221-500, TAG 226-500
58543	TIC216M	TIC 216A, 600V	TXC 18H60M, TAG 221-600, TAG 226-600
58544	TIC216N	TIC 216A, 800V	TXC 18H80M, TAG 221-800, TAG 226-800

58545	TIC216S	TIC 216A, 700V	TXC 18H70M, TAG 221-700, TAG 226-700
58546	TIC22	TIC 222 B	TIC 222 B
58547	TIC220B	200V, 6A(Tc70°), Igt<50mA	BS602B, TW6N200H, BS802B, T 4100B
58548	TIC220D	TIC 220B, 400V	BS604B, TW 6N400, BS804B, T 4100D
58549	TIC220E	TIC 220B, 500V	BS605B, TW 6N500, BS805B, T 4100E
58550	TIC221B...E	TIC 220 B..E	SC245...3, T4120..., SC250...3, T6421...
58551	TIC222B...E	TIC 220 B..E	BS6...A, TW6N...C, BS8...A, SC 245...
58552	TIC225A	Igt/Ih<5/<30mA	TAG 227-100
58553	TIC225B	TIC 225A, 200V	TAG 227-200
58554	TIC225C	TIC 225A, 300V	TAG 227-300
58555	TIC225D	TIC 225A, 400V	TAG 227-400
58556	TIC225E	TIC 225A, 500V	TAG 227-500
58557	TIC225M	TIC 225A, 600V	TAG 227-600
58558	TIC225N	TIC 225A, 800V	TAG 227-800
58559	TIC225S	TIC 225A, 700V	TAG 227-700
58560	TIC226A...S	TIC 225A..S, Igt/Ih<50/<60mA	T2802..., MAC222..., TAG224..., BT137/...
58561	TIC23	TIC 222 D	TIC 222 D
58562	TIC230B...E	TIC 220B..E, 10A(Tc70°)	SC246..., BS10...B, TW10N...H, T4100...
58563	TIC231B...E	TIC 221B..E, 10A(Tc70°)	SC245...3, T4120..., SC250...3, SC260...3
58564	TIC232B...E	TIC 222B..E, 10A(Tc70°)	SC245..., BS10...A, TXD99..., T4110...
58565	TIC236A	Igt/Ih<50/<50mA	TW 11N400, 2N6342A...6345A, TXD 10K40P
58566	TIC236B	TIC 236A, 200V	TW 11N400, 2N6342A...6345A, TXD 10K40P
58567	TIC236C	TIC 236A, 300V	TW 11N400, 2N6343A...6345A, TXD 10K40P
58568	TIC236D	TIC 236A, 400V	TW 11N400, 2N6343A...6345A, TXD 10K40P
58569	TIC236E	TIC 236A, 500V	TW 11N600, 2N6344A...6345A, TXD 10K50P
58570	TIC236M	TIC 236A, 600V	TW 11N600, 2N6344A...6345A, TXD 10K60P
58571	TIC236N	TIC 236A, 800V	TW 11N800, 2N6345A, TXD 10K80P
58572	TIC236S	TIC 236A, 700V	TW 11N700, 2N6345A, TXD 10K70P
58573	TIC240B...E	TIC 220B..E, 15A(Tc70°)	SC251..., T6405..., 2N6157...6159, T6400...
58574	TIC241B...E	TIC 221B..E, 15A(Tc70°)	SC 250...3, 2N6145...6147, SC 260...3
58575	TIC242B...E	TIC 222B..E, 15A(Tc70°)	SC 250..., TXD 98..., TW 18N..., TXE 99...
58576	TIC246A...S	TIC 236A..S, 16A(Tc70°)	MAC15..., T6001..., TXE10..., MAC223...
58577	TIC250B	200V, 20A(Tc70°), Igt<100mA	SC 261B, T 6405B, 2N6157...6159, T 6400B
58578	TIC250D	TIC 250B, 400V	SC 261D, T 6405D, 2N6158...6159, T 6400D
58579	TIC250E	TIC 250B, 500V	SC 261M, T 6405E, 2N6159, T 6400E
58580	TIC250M	TIC 250B, 600V	SC 261M, 2N6159, T 6400M
58581	TIC252B...M	TIC 250 B..M	TXE99..., SC260..., T6415..., T6411...
58582	TIC253A	Igt/Ih<50/<50mA	TIC 263A, BTA 26A, BTA 41A
58583	TIC253B	TIC 253A, 200V	TIC 263B, BTA 26B, BTA 41B
58584	TIC253C	TIC 253A, 300V	TIC 263C, BTA 26C, BTA 41C
58585	TIC253D	TIC 253A, 400V	TIC 263D, BTA 26D, BTA 41D
58586	TIC253E	TIC 253A, 500V	TIC 263E, BTA 26E, BTA 41E
58587	TIC253M	TIC 253A, 600V	TIC 263M, BTA 26M, BTA 41M
58588	TIC253N	TIC 253A, 800V	TIC 263N, BTA 26N, BTA 41N
58589	TIC253S	TIC 253A, 700V	TIC 263S, BTA 26S, BTA 41S

58590	TIC260B...M	TIC 250B..M, 25A(Tc70°)	SC 261..., T 6405..., T 6404..., T 6400...
58591	TIC262B...M	TIC 252 B..M, 25A(Tc70°)	TXE99..., SC260..., T6415..., T6411...
58592	TIC263A...S	TIC 253A..S, 25A(Tc70°)	BTA 26..., BTA 41...
58593	TIC270B...M	TIC 250B..M, 40A(Tc70°)	T6400..., 2N5441...5443
58594	TIC272B...M	TIC 252B..M, 40A(Tc70°)	T 6414..., T6410..., 2N5444...5446
58595	TIC39A	Igt/Ih<0,2/<5mA	2N6334...6337, TAG 615-100
58596	TIC39B	TIC 39A, 200V	2N6335...6337, TAG 615-200
58597	TIC39C	TIC 39A, 300V	2N6336...6337, TAG 615-400
58598	TIC39D	TIC 39A, 400V	2N6337, TAG 615-400
58599	TIC39F	TIC 39A, 50V	2N6333...6337, TAG 615-100
58600	TIC39Y	TIC 39A, 30V	2N6332...6337, TAG 615-100
58601	TIC44	Igt/Ih<0,2/<5mA	TIC60...64, MCR100..., BRY55/..., TAG 70.
58602	TIC45	TIC 44, 60V	TIC61...64, MCR100..., BRY55/60...800
58603	TIC46	TIC 44, 100V	TIC62...64, MCR100-3, BRY55/100...800
58604	TIC47	TIC 44, 200V	TIC64, MCR100-4...8, BRY55/200...800
58605	TIC54	Ub26..36V, Itsm1A	-
58606	TIC55	Ub22..38V, Itsm1A	-
58607	TIC56	TIC 54	-
58608	TIC57	TIC 55	-
58609	TIC60	2N5060	2N5060
58610	TIC61	2N5061	2N5061
58611	TIC62	2N5062	2N5062
58612	TIC63	2N5063	2N5063
58613	TIC64	2N5064	2N5064
58614	TIP04	400/300V, 2,5A, 65W, >3MHz	BUW 71, BUX 16C, BUX 45, 2SC1463
58615	TIP100	60V, 8A, 80W, B>1000	BD 645, BD 897, BDW 73A...D, BDX 53A...F
58616	TIP101	TIP 100, 80V	BD 647, BD 899, BDW 73B...D, BDX 53B...F
58617	TIP102	TIP 100, 100V	BD 649, BD 901, BDW 73C...D, BDX 53C...F
58618	TIP105	60V, 8A, 80W, B>1000	BD 646, BD 898, BDW 74A...D, BDX 54A...F
58619	TIP106	TIP 105, 80V	BD 648, BD 900, BDW 74B...D, BDX 54B...F
58620	TIP107	TIP 105, 100V	BD 650, BD 902, BDW 74C...D, BDX 54C...F
58621	TIP110	60V, 4A, 50W, B>1000	BD 715, BDW 23A, BDW 53A, BDW 63A
58622	TIP111	TIP 110, 80V	BD 717, BDW 23B, BDW 53B, BDW 63B
58623	TIP112	TIP 110, 100V	BDW 23C, BDW 53C, BDW 63C
58624	TIP115	60V, 2A, 50W, B>1000	BD 716, BDW 24A, BDW 54A, BDW 64A
58625	TIP116	TIP 115, 80V	BD 718, BDW 24B, BDW 54B, BDW 64B
58626	TIP117	TIP 115, 100V	BDW 24C, BDW 54C, BDW 64C
58627	TIP120	60V, 5A, 65W, B>1000	BD 645, BD 897, BDW 23A, BDW 63A
58628	TIP121	TIP 120, 80V	BD 647, BD 899, BDW 23B, BDW 63B
58629	TIP122	TIP 120, 100V	BD 649, BD 901, BDW 23C, BDW 63C
58630	TIP125	60V, 5A, 65W, B>1000	BD 646, BD 898, BDW 24A, BDW 64A
58631	TIP126	TIP 125, 80V	BD 648, BD 900, BDW 24B, BDW 64B
58632	TIP127	TIP 125, 100V	BD 650, BD 902, BDW 24C, BDW 64C
58633	TIP130	60V, 8A, 70W, B>1000	BD 647, BD 897, BDW 73A, BDX 53A
58634	TIP131	TIP 130, 80V	BD 647, BD 899, BDW 73B, BDX 53B

58635	TIP132	TIP 130, 100V	BD 649, BD 901, BDW 73C, BDX 53C
58636	TIP135	60V, 8A, 70W, B>1000	BD 646, BD 898, BDW 74A, BDX 54A
58637	TIP136	TIP 135, 80V	BD 648, BD 900, BDW 74B, BDX 54B
58638	TIP137	TIP 135, 100V	BD 650, BD 902, BDW 74C, BDX 54C
58639	TIP140	60V, 10A, 125W, B>1000	BDV 65, BDV 67, BDW 83A
58640	TIP140FI..142F	TIP 140..142, , 60W	BDV 65...F
58641	TIP140FI..142FI	TIP 140..142, , 50W	BDV 65...F
58642	TIP140T	TIP 140	BDT 63(A...C), BDW 93A...C, BDX 33A...E
58643	TIP141	TIP 140, 80V	BDV 65A, BDV 67, BDW 83B
58644	TIP141T	TIP 141	BDT 63A...C, BDW 93B...C, BDX 33B...E
58645	TIP142	TIP 140, 100V	BDV 65B, BDV 67A, BDW 83C
58646	TIP142T	TIP 142	BDT 63B...C, BDW 93C, BDX 33C...E
58647	TIP145	60V, 10A, 125W, B>1000	BDV 64, BDV 66, BDW 84A
58648	TIP145F..147F	TIP 145..147, , 60W	BDV 64...F
58649	TIP145FI..147FI	TIP 145..147, , 50W	BDV 64...F
58650	TIP145T	TIP 145	BDT 62(A...C), BDW 94A...C, BDX 34A...E
58651	TIP146	TIP 145, 80V	BDV 64A, BDV 66, BDW 84B
58652	TIP146T	TIP 146	BDT 62A...C, BDW 94B...C, BDX 34B...E
58653	TIP147	TIP 145, 100V	BDV 64B, BDV 66A, BDW 84C
58654	TIP147T	TIP 147	BDT 62B...C, BDW 94C, BDX 34C...E
58655	TIP150	B>150	BU 810
58656	TIP151	TIP 151, 350/350V	BU 810
58657	TIP152	TIP 150, 400/400V	BU 810
58658	TIP160	320/320V, 10A, 50W, B>200	BU 920...922, BUW 66, BUW 81(A), 2SD685
58659	TIP161	TIP 160, 350/350V	BU 920...922, BUW 66, BUW 81(A), 2SD695
58660	TIP162	TIP 160, 380/380V	BU 920...922, BUW 66, BUW 81(A), 2SD685
58661	TIP29(A...F)	BD 239(A..F)	BD 239...
58662	TIP29..42(..)F	TIP 29..42(..)F	
58663	TIP2955	100V, 15A, 90W	BD 250C, BD 746C
58664	TIP2955T	70V, 10A, 75W	BD 710, BD 810, BD 744B...F, BDT 96
58665	TIP30(A...F)	BD 240(A..F)	BD 240...
58666	TIP3055	100V, 15A, 90W	BD 249C, BD 745C
58667	TIP3055T	70V, 10A, 75W	BD 709, BD 809, BD 743B...F, BDT 95
58668	TIP31(A...F)	BD 241(A..F)	BD 241...
58669	TIP32(A...F)	BD 242(A..F)	BD 242...
58670	TIP33(A...F)	BD 245(A..F)	BD 245...
58671	TIP34(A...F)	BD 246(A..F)	BD 246...
58672	TIP35(A...F)	BD 249(A..F)	BD 249...
58673	TIP36(A...F)	BD 250(A..F)	BD 250...
58674	TIP41(A...F)	BD 243(A..F)	BD 243...
58675	TIP42(A...F)	BD 244(A..F)	BD 244...
58676	TIP47	350/250V, 1A, 40W, >10MHz	BUW 40(A...B), BUX 84...85, 2SC2333
58677	TIP48	TIP 47, 400/300V	BUW 40(A...B), BUX 84...85, 2SC2333
58678	TIP49	TIP 47, 450/350V	BUW 40(A...B), BUX 84...85, 2SC2333
58679	TIP50	TIP 47, 500/400V	BUW 40A...B, BUX 84...85, 2SC2333

58680	TIP501	40V, 3A, 1W, <100/400ns	2N3506...3507
58681	TIP501	TIP 501, 60V	2N3506...3507
58682	TIP503	>70MHz	BUX 67, 2N3441, 2SC2528...2529, 2SD610
58683	TIP504	TIP 503, 160V	BUX 67, 2N3441, 2SC2529, 2SD610
58684	TIP505	TIP 503	-
58685	TIP506	TIP 504	-
58686	TIP507	>50MHz	-
58687	TIP508	TIP 507, 4W(Tc100°)	-
58688	TIP509	>70MHz	-
58689	TIP51	350/250V, 3A, 100W, >2,5MHz	BU 426(A), BUW 11(A), 2SC3550
58690	TIP510	TIP 509, 160V	-
58691	TIP511	TIP 509	-
58692	TIP512	TIP 510	-
58693	TIP513	>40MHz	-
58694	TIP514	TIP 513, 20W(Tc100°)	BUX 66
58695	TIP515	80W(Tc100°),>70MHz	-
58696	TIP516	TIP 515, 160V	-
58697	TIP517	TIP 515	-
58698	TIP518	TIP 516	-
58699	TIP52	TIP 51, 400/300V	BU 426(A), BUW 11(A), 2SC3550
58700	TIP520	TIP 519	-
58701	TIP521	>50MHz	-
58702	TIP522	TIP 521, 4W(Tc100°)	-
58703	TIP523	>40MHz	-
58704	TIP524	TIP 523, 6W(Tc100°)	-
58705	TIP525	250V, 5A, >40MHz	BUX 16(A...C), 2SC2908
58706	TIP526	TIP 525	-
58707	TIP527	60W(Tc100°),>40MHz	BUW 96, 2SB552, 2SB613
58708	TIP528	TIP 527	-
58709	TIP529	67W(Tc100°),>20MHz	-
58710	TIP53	TIP 51, 450/350V	BU 426(A), BUW 11(A), 2SC3550
58711	TIP530	TIP 529, 20W(Tc100°)	BUY 63...64, 2SC1466, 2SC2929, 2SC2826
58712	TIP531	50MHz	BUV 24...25, BUX 24...25
58713	TIP532	TIP 531, 450/400V	BUV 24...25, BUX 24...25
58714	TIP533	TIP 531	2N6690...6693
58715	TIP534	TIP 532	2N6690...6693
58716	TIP535	300/200V, 7,5A, 100W(Tc100°)	BUW 24...26, BUW 34...36, BUX 15
58717	TIP536	TIP 535, 400/300V	BUW 24...26, BUW 34...36, BUX 15
58718	TIP537	TIP 535, 500/400V	BUW 25...26, BUW 34...36, BUX 15
58719	TIP538	300/200V, 15A, 125W(Tc100°)	BUV 24...25, BUX 24...25
58720	TIP539	TIP 538, 400/300V	BUV 24...25, BUX 24...25
58721	TIP54	TIP 51, 500/400V	BU 426(A), BUW 11(A), 2SC3550
58722	TIP540	TIP 538, 500/400V	BUV 25, BUX 25
58723	TIP541	50V, 2A, 1W, >150MHz	BCX 40, BSS 15...16, 2N4237...39
58724	TIP542	50V, 10A, 40W, >150MHz	2N5002, 2N5004, 2N5284...5285



58725	TIP543	TIP 542, 75V	2N5002, 2N5004, 2N5284...85
58726	TIP544	100V, 6A, 150W, >1MHz	2N6229...6231, 2SB555...556, 2SB817
58727	TIP545	TIP 544, 120V	2N6230...6231, 2SB555...556, 2SB817
58728	TIP546	TIP 544, 140V	2N6231, 2SB556, 2SB681, 2SB817
58729	TIP550	1200/600V, 3A, 60W(Tc80°)	BU 205, BU 208(A), 2SC1875, 2SD819
58730	TIP551	TIP 550, 1400/700V	BU 205, BU 208(A), 2SC1875, 2SD819
58731	TIP552	1200/600V, 5A, 60W(Tc80°)	BU 208(A), 2SC2928, 2SD350(A)
58732	TIP553	TIP 552, 1400/700V	BU 208(A), 2SC2928, 2SD350(A)
58733	TIP5530	100V, 15A, 90W	BD 250C, BD 746C
58734	TIP554	400/300V, 3A, 100W, >2,5MHz	BUX 15, BUX 44...45, TIP 52...54, 2SC3083
58735	TIP555	TIP 554, 450/350V	BUX 15, BUX 44...45, TIP 52...54, 2SC3083
58736	TIP556	TIP 554, 500/400V	BUX 15, BUX 45, TIP 54, 2SC3083
58737	TIP558	350/250V, 7,5A, 100W(Tc100°)	BUW 24...26, BUW 34...36, BUX 15
58738	TIP559	TIP 558, 400/300V	BUW 24...26, BUW 34...36, BUX 15
58739	TIP55A	350/250V, 7,5A, 50W(Tc100°)	BUW 12(A), BUV 47(A), 2SC2536
58740	TIP560	TIP 558, 450/350V	BUW 24...26, BUW 34...36, BUX 15
58741	TIP561	TIP 558, 500/400V	BUW 25...26, BUW34...36, BUX 15
58742	TIP562	300/300V, 10A, 100W(Tc100°)	BUW 74, BUX 14, BUX 17C, BUX 43
58743	TIP563	TIP 562, 400/400V	BUW 74, BUX 14, BUX 17C, BUX 43
58744	TIP564	400/350V, 10A, 150W(Tc100°)	BUV 24...25, BUX 24...25
58745	TIP565	TIP 564, 450/400V	BUV 24...25, BUX 24...25
58746	TIP56A	TIP 55A, 400/300V	BUW 12(A), BUV 47(A), 2SC2536
58747	TIP575	350/200V, 3A, 100W, >10MHz	BUX 15, BUX 45, TIP 51...54, 2SC3041
58748	TIP575A	TIP 575, 400/250V	BUX 15, BUX 45, TIP 52...54, 2SC3041
58749	TIP575B	TIP 575, 450/300V	BUX 15, BUX 45, TIP 53...54, 2SC3041
58750	TIP575C	TIP 575, 500/400V	BUX 15, BUX 45, TIP 54, 2SC3041
58751	TIP57A	TIP 55A, 450/350V	BUW 12(A), BUV 47(A), 2SC2536
58752	TIP58A	TIP 55A, 500/400V	BUW 12(A), BUV 47(A), 2SC2536
58753	TIP59	-/600V, 2,5A	BUW 11(A), BUW 131(A), 2SC3152...53
58754	TIP60	-/600V, 2,5A	BUW 11(A), BUW 131(A), 2SC3152...53
58755	TIP600	60V, 10A, 100W, B>1000	BDV 65, BDW 83A, BDX 85A, BDX 87A
58756	TIP601	TIP 600, 80V	BDV 65A, BDW 83B, BDX 85B, BDX 87B
58757	TIP602	TIP 600, 100V	BDV 65B, BDW 83C, BDX 85C, BDX 87C
58758	TIP605	60V, 10A, 100W, B>1000	BDV 64, BDW 84A, BDX 86A, BDX 88A
58759	TIP606	TIP 605, 80V	BDV 64A, BDW 84B, BDX 86B, BDX 88B
58760	TIP607	TIP 605, 100V	BDV 64B, BDW 84C, BDX 86C, BDX 88C
58761	TIP61	>3MHz	BD 239, BD 241, BD 533, BD 933
58762	TIP61A	TIP 61, 60V	BD 239A, BD 241A, BD 535, BD 935
58763	TIP61B	TIP 61, 80V	BD 239B, BD 241B, BD 537, BD 937
58764	TIP61C	TIP 61, 80V	BD 239C, BD 241C, BD 937, 2SD712
58765	TIP62	>3MHz	BD 240, BD 242, BD 534, BD 934
58766	TIP620	60V, 5A, 65W, B>1000	BDX 63, BDX 85A, TIP 140, 2SD1170
58767	TIP621	TIP 620, 80V	BDX 63A, BDX 85B, TIP 141, 2SD1170
58768	TIP622	TIP 620, 100V	BDX 63B, BDX 85C, TIP 142, 2SD1170
58769	TIP625	60V, 5A, 65W, B>1000	BDX 62, BDX 86A, TIP 145, 2SB897

58770	TIP626	TIP 625, 80V	BDX 62A, BDX 86B, TIP 146, 2SB897
58771	TIP627	TIP 625, 100V	BDX 62B, BDX 86C, TIP 147, 2SB897
58772	TIP62A	TIP 62, 60V	BD 240A, BD 242A, BD 536, BD 936
58773	TIP62B	TIP 62, 80V	BD 240B, BD 242B, BD 538, BD 938
58774	TIP62C	TIP 62, 100V	BD 240C, BD 242C, BD 938, 2SB682
58775	TIP63	350/300V, 0,5A, 20W, >15MHz	BUW 40(A...B), BUX 84...85, 2SC1810
58776	TIP64	TIP 63, 400/350V	BUW 40(A...B), BUX 84...85, 2SC1810
58777	TIP640	60V, 10A, 175W, B>1000	BDX 67, BDX 87A, 2N6057, 2N6282
58778	TIP641	TIP 640, 80V	BDX 67A, BDX 87B, 2N6058, 2N6283
58779	TIP642	TIP 640, 100V	BDX 67B, BDX 87C, 2N6059, 2N6284
58780	TIP645	60V, 10A, 175W, B>1000	BDX 66, BDX 88A, 2N6050, 2N6285
58781	TIP646	TIP 645, 80V	BDX 66A, BDX 88B, 2N6051, 2N6286
58782	TIP647	TIP 645, 100V	BDX 66B, BDX 88C, 2N6052, 2N6287
58783	TIP65	-/600V, 1,5A, 40W	BUW 11(A), 2SC3088, 2SC3151, 2SC3533
58784	TIP66	-/600V, 1,5A, 40W	BUW 11(A), 2SC3088, 2SC3151, 2SC3533
58785	TIP660	320/320V, 10A, 80W, B>500	BU 920...922, BUW 28...29, BUW 81(A)
58786	TIP661	TIP 660, 350/350V	BU 920...922, BUW 28...29, BUW 81(A)
58787	TIP662	TIP 660, 380/380V	BU 920...922, BUW 29, BUW 81(A)
58788	TIP663	400/300V, 20A, 150W(Tc100°)	BUT 13, MJ 10000...01, MJ 10004...05
58789	TIP664	TIP 663, 450/350V	BUT 13, MJ 10000...01, MJ 10004...05
58790	TIP665	TIP 663, 500/400V	BUT 13, MJ 10001, MJ 10005, MJ 10008
58791	TIP666	400/300V, 10A, 150W(Tc100°)	BUT 13, MJ 10001, MJ 10005, MJ 10008
58792	TIP667	TIP 666, 450/350V	BUT 13, MJ 10001, MJ 10005, MJ 10008
58793	TIP668	TIP 666, 550/450V	BUT 13, MJ 10001, MJ 10005, MJ 10008
58794	TIP73	50V, 15A, 80W, 5MHz	BD 743, BD 907
58795	TIP73A	TIP 73, 70V	BD 743A, BD 909
58796	TIP73B	TIP 73, 90V	BD 743B, BD 911
58797	TIP73C	TIP 73, 110V	BD 743C
58798	TIP74	50V, 15A, 80W, 5MHz	BD 744, BD 908
58799	TIP74A	TIP 74, 70V	BD 744A, BD 910
58800	TIP74B	TIP 74, 90V	BD 744B, BD 912
58801	TIP74C	TIP 74, 90V	BD 744C
58802	TIP75	350/200V, 3A, 65W, >10MHz	BUT 11(A), BUT 93, 2SC3038, 2SD841
58803	TIP75A	TIP 75, 400/250V	BUT 11(A), BUT 93, 2SC3038, 2SD841
58804	TIP75B	TIP 75, 450/300V	BUT 11(A), BUT 93, 2SC3038, 2SD841
58805	TIP75C	TIP 75, 500/400V	BUT 11(A), BUT 93, 2SC3038, 2SD841
58806	TIPL13004	700/300V, 5A, 50W	BUT11(A), BUT18(A), BUT46(A), BUV46(A)
58807	TIPL13005	TIPL 13004, 800/400V	BUT11(A), BUT18(A), BUT46(A), BUV46(A)
58808	TIPL751	850/400V, 4A, 120W	BUS 11(A), BUW 11(A), BUX 83, 2SC3343
58809	TIPL751A	TIPL 751, 1000/450V	BUS 11A, BUW 11A, BUX 83, 2SC3343
58810	TIPL752	850/400V, 6A, 150W	BUS 11(A), BUW 11(A), BUX 83, 2SC3343
58811	TIPL752A	TIPL 752, 1000/450V	BUS 11A, BUW 11A, BUX 83, 2SC3343
58812	TIPL753	850/400V, 8A, 150W	BUS 12(A), BUW 12(A), BUX 81, 2SC3461
58813	TIPL753A	TIPL 753, 1000/450V	BUS 12A, BUW 12A, BUX 81, 2SC3461
58814	TIPL755	850/400V, 10A, 180W	BUS 12(A), BUW 12(A), BUX 81, 2SC3461

58815	TIPL755A	TIPL 755, 1000/450V	BUS 12A, BUW 12A, BUX 81, 2SC3461
58816	TIPL757	850/400V, 15W, 200W	BUS13(A), BUS97(A), BUW13(A), BUX48(A)
58817	TIPL757A	TIPL 757, 1000/450V	BUS 13A, BUS 97A, BUW 13A, BUX 48A
58818	TIPL760	850/400V, 4A, 75W	BUT11(A), BUT18(A), BUT46(A), BUV46(A)
58819	TIPL760A	TIPL 760, 1000/400V	BUT 11A, BUT 18A, BUT 46A, BUV 46A
58820	TIPL760B	TIPL 760, 1100/500V	MJE 8502...03, 2SC3050
58821	TIPL760C	TIPL 760, 1200/550V	MJE 8502...03, 2SC3050
58822	TIPL761	TIPL 760, 100W	2SC3535
58823	TIPL761A	TIPL 760A, 100W	BUW 11A, BUV 83, BUW 132A, 2SC3535
58824	TIPL761B	TIPL 760B, 100W	BUV 89, 2SC3466, 2SC3642
58825	TIPL761C	TIPL 760C, 100W	BUV 89, 2SC3466, 2SC3642
58826	TIPL762	TIPL 752, 120W	2SC3535
58827	TIPL762A	TIPL 752A, 120W	BUW 11A, BUV 83, BUW 132A, 2SC3535
58828	TIPL763	TIPL 753, 120W	2SC3535
58829	TIPL763A	TIPL 753A, 120W	BUW 11A, BUV 93, BUW 132A, 2SC3535
58830	TIPL765	TIPL 755, 125W	BUV48(A)
58831	TIPL765A	TIPL 755A, 125W	BUW 12A, BUW 13A, BUV 47A, BUV 48A
58832	TIPL770	850/400V, 2,5A, 50W	BUV 36(A), BUX 84...85, 2SC3531
58833	TIPL773	950/600V, 20A, 180W	-
58834	TIPL773A	TIPL 773, 1050/700V	-
58835	TIPL773B	TIPL 773, 1150/800V	-
58836	TIPL774	550/450V, 20A, 150W	BUT 13, MJ 10008...10009
58837	TIPL775	150/120V, 10A, 100W	-
58838	TIPL775A	TIPL 775, 200/150V	-
58839	TIPL777	950/600V, 20A, 180W	-
58840	TIPL777A	TIPL 777, 1050/700V	-
58841	TIPL777B	TIPL 777, 1150/800V	-
58842	TIPL785	TIPL 775, 80W	-
58843	TIPL785A	TIPL 775A, 80W	-
58844	TIPL790	TIPL 775, 70W	-
58845	TIPL790A	TIPL 775A, 70W	-
58846	TIPL791	TIPL 751, 75W	BUT11(A), BUT18(A), BUT46(A), BUV46(A)
58847	TIPL791A	TIPL 751A, 75W	BUT 11A, BUT 18A, BUT 46A, BUV 46A
58848	TIS03	2N3702	
58849	TIS04	2N3703	
58850	TIS05	2N3993	
58851	TIS06	2N3573	
58852	TIS07	2N3574	
58853	TIS100	180V, 0,1A, 0,625W, 80MHz	BF 298...299, BFR 88...89, 2SC3468
58854	TIS101	TIS 100, 150V	BF 297...299, BFR 87...89, 2SC3468
58855	TIS102	TIS 100, 0,8W	BF 258...259, BF 658...659, 2N5058...5059
58856	TIS103	TIS 100, 150V, 0,8W	BF 257...259, BF 657...659, 2N5058...5059
58857	TIS104	60V, 0,05A, 0,36W, >90MHz	BC 212, BC 256, BC 266, BC 556
58858	TIS105	600MHz, 0,36W, >90MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58859	TIS106	80V, 0,2A, 0,36W, >200MHz	BC 546, 2SC2240, 2SC2459, 2SC3245(A)

58860	TIS107	TIS 106, 60V	BC 174, BC 182, BC 190, BC 546
58861	TIS108	>350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
58862	TIS109	60V, 0,8A, 0,36W, 20/220ns	BC 637, BC 639, 2N2221...2222(A)
58863	TIS11		
58864	TIS110	60V, 0,8A, 0,36W, <35/290ns	BC 637, BC 639, 2N2221...2222(A)
58865	TIS111	60V, 0,8A, 0,36W, <35/290ns	BC 637, BC 639, 2N2221...2222(A)
58866	TIS112	60V, 0,6A, 0,36W, <50/150ns	BC 638, BC 640, 2N2906...2907(A)
58867	TIS113	50V, 0,5A, 0,7W,<40/75ns,B>60	BC 637, BC 639, 2N4013...4014
58868	TIS114	TIS 113, B>50	BC 637, BC 639, 2N4013...4014
58869	TIS115	TIS 113, 80V	BC 639, 2N4014
58870	TIS116	TIS 113, 80V, B>50	BC 639, 2N4014
58871	TIS125	>450MHz	BF 198, BF 225, BF 310, BF 367, BF 596
58872	TIS126	>600MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58873	TIS128	>650MHz	BF 324, BF 414, BF 506, BF 914, BF 936
58874	TIS129	>800MHz	BF 377...378, BF 689, BF 763, 2N2857
58875	TIS130		-
58876	TIS131	300V, 0,05A, 10W, >60MHz	BF 382, BF 461...462,
58877	TIS132	TIS 131, 250V	BF 381, BF 460...462,
58878	TIS133	50V, 0,5A, 0,7W,<40/75ns,B>60	BC 637, BC 639, 2N4013...4014
58879	TIS134	TIS 133, B>50	BC 637, BC 639, 2N4013...4014
58880	TIS135	TIS 133, 80V	BC 639, 2N4014
58881	TIS136	TIS 133, 80V, B>50	BC 639, 2N4014
58882	TIS137	B>45	BC 213, BC 257, BC 307, BC 557
58883	TIS138	TIS 137, B>25	BC 213, BC 257, BC 307, BC 557
58884	TIS139	100V, 1A, 10W, 80MHz	BD 419, BD 529
58885	TIS14		BF 256, BFS 71, BFS 80, 2N4221
58886	TIS140	TIS 139, 120V	-
58887	TIS141	70V, 1,5A, >150MHz	BD 418, BD 420, BD BD 528, BD 530
58888	TIS142	TIS 141, 80V	BD 418, BD 420, BD BD 528, BD 530
58889	TIS143	50V, 1,5A, 10W, B>20000	BD 411...412, MPSU 45
58890	TIS144	TIS 143, 80V, B>10000	-
58891	TIS145	300V, 0,1A, 10W, 85MHz	BF 464...465, MPSU 60
58892	TIS146	TIS 145, 250V, 100MHz	BF 463...465, MPSU 60
58893	TIS148		-
58894	TIS149	>1600MHz	BFQ 78, 2SA1058
58895	TIS15	2N3821	
58896	TIS150	80V, 1A, 1,2W, B>20000	BC 618, BC 877, BC 879, BSR 51...52
58897	TIS151	TIS 150, 50V, B>10000	BC 617...618, BC 877, BC 879, BSR 50...52
58898	TIS152		-
58899	TIS153		-
58900	TIS154	300V, 0,1A, 0,75W, 85MHz	BF 299, BF 420A, BFR 89, 2SC3468
58901	TIS155	TIS 154, 250V, 100MHz	BF 298...299, BFR 88...89, BF 422A
58902	TIS156		-
58903	TIS157		-
58904	TIS158		-

58905	TIS159		-
58906	TIS16	2N3822	
58907	TIS160		-
58908	TIS161		2N5246, 2N5360, 2SK107
58909	TIS162		BF 244...245, BFS 71, 2N3823, 2N4416
58910	TIS163	TIS 161	TIS 161
58911	TIS164	TIS 162	TIS 162
58912	TIS165		-
58913	TIS17	2N3824	
58914	TIS177	300V, 0,1A, 85MHz	BF 464...465, MPSU 60
58915	TIS178	TIS 177, 200V, 100MHz	BF 463...465, MPSU 60
58916	TIS179	TIS 177	BF 437, BF 493, BFP 26, MPSA 92
58917	TIS18	>600MHz	BF 357, BFR 37, BFW 30, BFX 73
58918	TIS180	TIS 177, 200V	BF 436, BF 492, BFP 23, MPSA 93
58919	TIS22	45V, 0,05A, >30MHz, $\beta > 60$	BC 123
58920	TIS23	TIS 22, $\beta > 150$	BC 123
58921	TIS24	TIS 22, 60V, $\beta > 150$	-
58922	TIS34		BF 244, BF 245, BFS 72, 2N3823
58923	TIS37		BF 440...441, BF 450...451, BF 540...542
58924	TIS38		BF 440...441, BF 450...451, BF 540...542
58925	TIS39	30V, 0,2A, >800MHz	BFR 36, 2SC2852
58926	TIS41		BFS 74, BFS 77, BSV 78, 2N4856...59
58927	TIS42		-
58928	TIS43	Iv2mA, Ip5 $\mu$ A	2N4870, 2N4891
58929	TIS44	2N706	
58930	TIS45	2N708	
58931	TIS46	2N914	
58932	TIS47	2N2368	
58933	TIS48	2N2369	
58934	TIS49	2N2369A	
58935	TIS50	2N4423	
58936	TIS51	2N3011	
58937	TIS52	2N4420	
58938	TIS53	2N3639	
58939	TIS54	2N3640	
58940	TIS55	2N4422	
58941	TIS56	30V, 30mA, >500MHz	BF 225, BF 314, BF 496, BF 502, BF 505
58942	TIS57	30V, 30mA, >500MHz	BF 225, BF 413, BF 496, BF 502, BF 505
58943	TIS58		BF 256A, 2N5485, 2SK107
58944	TIS59		BF 244...245, BFW 10, 2N5363...64
58945	TIS60	40V, 0,4A, 0,3W	BC 337, BC 637, BC 639, 2SD667
58946	TIS61	40V, 0,4A, 0,3W	BC 327, BC 638, BC 640, 2SB647
58947	TIS62(A)	>500MHz	BF 225, BF 314, BF 496, BF 502, BF 503
58948	TIS63(A)	>400MHz	BF 225, BF 314, BF 496, BF 502, BF 503
58949	TIS64(A)	>300MHz	BF 225, BF 314, BF 496, BF 502, BF 503

58950	TIS68		-
58951	TIS69		-
58952	TIS70		-
58953	TIS71	25V, 0,05A, PQ>10mW(4GHz)	BFP 96, BFQ 72...73, BFR 96, BFT 65
58954	TIS72	25V, 0,05A, PQ>3mW(4GHz)	BFP 96, BFQ 72...73, BFR 96, BFT 65
58955	TIS73	30V, Idss>50mA, Up<10V	BFS 74, BFS 77, BSV 78, 2N4856, 2N4859
58956	TIS73[Nsc]	TIS 73	TIS 73
58957	TIS73L	TIS 73	TIS 73
58958	TIS74	TIS 73, 20..100mA, Up<6V	BFS 75, BFS 78, BSV 79, 2N4857, 2N4860
58959	TIS74[Nsc]	TIS 74	TIS 74
58960	TIS74L	TIS 74	TIS 74
58961	TIS75		BFS 76, BFS 79, BSV 80, 2N4858, 2N4861
58962	TIS75L	TIS 75	BFS 76, BFS 79, BSV 80, 2N4858, 2N4861
58963	TIS78	300V	2N5543
58964	TIS79	200V	2N5544
58965	TIS82	60V, 1,2A, 1W, <25/30ns	BSS 27, BSV 77, 2N5189, 2SC1386
58966	TIS83	40V, 0,05A, PQ15mW(930MHz)	BF 357, BFR 37, BFW 30, BFX 73
58967	TIS84	650MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58968	TIS85	>350MHz	BF 198, BF 225, BF 310, BF 367, BF 596
58969	TIS86	>500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58970	TIS87	>500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58971	TIS88		BF 256, 2N5397...98, 2N5486
58972	TIS88A	TIS 88	BF 256, 2N5397...98, 2N5486
58973	TIS89	>500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
58974	TIS90(M)	40V, 0,4A, 0,625W	BC 337, BC 637, BC 639, 2SD667
58975	TIS91(M)	40V, 0,4A, 0,625W	BC 327, BC 638, BC 640, 2SB647
58976	TIS92(M)	TIS 90(M)	TIS 90
58977	TIS93(M)	TIS 91(M)	TIS 91
58978	TIS94	60V, 0,2A, 0,36W, >200MHz	2SC2240, 2SC2459
58979	TIS95	80V, 0,2A, 0,36W, >200MHz	2SC2240, 2SC2459
58980	TIS96	80V, 0,2A, 0,36W, >200MHz	2SC2240, 2SC2459
58981	TIS97	TIS 94	TIS 94
58982	TIS98	TIS 95	TIS 95
58983	TIS99	TIS 96	TIS 96
58984	TIX09	1500MHz	BF 377...378, BF 689K, BF 763
58985	TIX10	1500MHz	BF 377...378, BF 689K, BF 763
58986	TIX2000		-
58987	TIX2150	2N2150	
58988	TIX2151	2N2151	
58989	TIX3015	2N3570	
58990	TIX3016	30V, 0,05A, PQ>0,03W(2GHz)	BFQ 72, BFT 65
58991	TIX3023	>2400MHz	-
58992	TIX3024(A)	>1500MHz	-
58993	TIX3032	25V, 0,1A, 500MHz	AFY 18
58994	TIX316	2N2996	



58995	TIX435	15V, 0,1A, 1W	-
58996	TIX608	3N74	
58997	TIX609	3N79	
58998	TIX67		-
58999	TIX690		-
59000	TIX802	2N3037	
59001	TIX803	2N3038	
59002	TIX804	2N3039	
59003	TIX805	2N3040	
59004	TIX895	5V, 0,075A, 0,075W, 5/6ns	-
59005	TIXA01	50V, 0,15A, 0,15W	ACY 24, ASY 48, ASY 77
59006	TIXA02	40V, 0,15A, 0,15W	ACY 24, ASY 48, ASY 77
59007	TIXA03	25V, 0,15A, 0,15W	AC 125...126, AC 151
59008	TIXA04	25V, 0,15A, 0,15W	AC 125...126, AC 151
59009	TIXA05	20V, 0,15A, 0,15W	AC 125...126, AC 151
59010	TIXM01	>355MHz	AF 124, AF 106, AF 109(R)
59011	TIXM02	>282MHz	AF 124...125, AF 106, AF 109(R)
59012	TIXM03	>316MHz	AF 124...125, AF 106, AF 109(R)
59013	TIXM04	>224MHz	AF 124...126, AF 106, AF 109(R)
59014	TIXM05	>450MHz	AF 109(R), AF 139, AF 239(S)
59015	TIXM06	>380MHz	AF 109(R), AF 139, AF 239(S)
59016	TIXM07	>315MHz	AF 109(R), AF 139, AF 239(S)
59017	TIXM08	>380MHz	AF 121, AF 200...202
59018	TIXM10	>630MHz	AF 139, AF 239(S)
59019	TIXM101	1700MHz	AFY 25...26, AF 139, AF 239(S)
59020	TIXM103	>1800MHz	-
59021	TIXM104	>1400MHz	-
59022	TIXM105	>2200MHz	-
59023	TIXM106	>2200MHz	-
59024	TIXM107	>1500MHz	AF 379
59025	TIXM108	>1000MHz	AF 379
59026	TIXM11	>500MHz	AF 139, AF 239(S)
59027	TIXM13	>1000MHz	AFY 25...26, AF 139, AF 239(S)
59028	TIXM14	600MHz	AF 139, AF 239(S)
59029	TIXM15	600MHz	AF 139, AF 239(S)
59030	TIXM16	500MHz	AF 139, AF 239(S)
59031	TIXM17	500MHz	AF 139, AF 239(S)
59032	TIXM18	900MHz	AF 139, AF 239(S)
59033	TIXM19	900MHz	AF 139, AF 239(S)
59034	TIXP39	2N5939	-
59035	TIXP40	2N5940	-
59036	TIXP547	80V, 100A, 200W(Tc100°)	-
59037	TIXP548	TIXP 547, 100V	-
59038	TIXP549	TIXP 547, 120V	-
59039	TIXS09	PQ0,05W(1500MHz)	BFQ 72, BFT 65, BFW 93, 2SC2466

59040	TIXS10	PQ0,05W(1000MHz)	BFQ 72, BFT 65, BFW 93, 2SC2466
59041	TIXS11		-
59042	TIXS28	>630MHz	BF 225, BF 314, BF 496, BF 502, BF 505
59043	TIXS29	>500MHz	BF 199, BF 224, BF 503, BF 505, BF 507
59044	TIXS30	>500MHz	BF 199, BF 224, BF 503, BF 505, BF 507
59045	TIXS31	>500MHz	BF 199, BF 224, BF 311, BF 373, BF 597
59046	TIXS33		2N4091
59047	TIXS35		-
59048	TIXS36		-
59049	TIXS37	80..320MHz	BF 440...441. BF 450...451, BF 540...542
59050	TIXS37	80..320MHz	BF 440...441. BF 450...451, BF 540...542
59051	TIXS38	50..200MHz	BF 440...441. BF 450...451, BF 540...542
59052	TIXS39	30V, 0,2A, 900MHz	BFR 36, BFX 55, 2SC2852
59053	TIXS40	PQ>0,25W(1600MHz)	BFR 36, BFR 95, 2SC2852
59054	TIXS42		2N4093, 2N4858, 2N4861
59055	TIXS67		-
59056	TIXS78	300V	2N5543
59057	TIXS79	200V	2N5544
59058	TIXS80		-
59059	TIXS81		-
59060	TK	P6 SMB-56CA	P6 SMB-56CA
59061	TK	SM 4T 150A	SM 4T...
59062	TK	2SC3617-TK	2SC3617
59063	TL	P6 SMB-62C	P6 SMB-62C
59064	TL	2SA1573	2SA1573
59065	TL	2SC3617-TL	2SC3617
59066	TM	P6 SMB-62CA	P6 SMB-62CA
59067	TM	2SC3617-TM	2SC3617
59068	TM1020	Igt/Ih<50/50mA	T 4700B, T 4706B
59069	TM1020M..1040M	TM 1020..1040	SC 151..., TAG 280...281..., TIC 246...
59070	TM1040	TM 1020, 400V	T 4700D, T 4706D
59071	TM1041..1061S-L	10A(Tc90°)	TAG 457-...
59072	TM1041M-L	Igt/Ih<30/15mA	TAG 252-400, TAG 257-400
59073	TM1061M-L	TM 1041M-L, 600V	TAG 252-600, TAG 257-600
59074	TM1241..1261S-L	12A(Tc85°)	-
59075	TM1241M-L	Igt/Ih<30/15mA	TAG 257-400
59076	TM1261M-L	TM 1241M-L, 600V	TAG 257-600
59077	TM1641M-L	Igt/Ih<30/15mA	TAG 6006-400
59078	TM1661M-L	TM 1641M-L, 600V	TAG 6006-600
59079	TM320M	Igt/Ih<50/50mA	TIC 216B, T 2506B, TAG 232-200
59080	TM340M	TM 320M, 400V	TIC 216D, T 2506D, TAG 232-400
59081	TM340M-A	Igt/Ih<2/10mA	TIC 108D, S 5801D, S 5802D
59082	TM341..361S-L	TM 341..361M-L, , 3A(Tc109°)	TAG 421-...
59083	TM341M-L	Igt/Ih<30/15mA	TAG 232-400, TIC 206D, TXC 18H40
59084	TM361M-L	TM 341M-L, 600V	TAG 232-600, TIC 206M, TXC 18H60

59085	TM541..561S-L	TM 541..561M-L, , 5A(Tc104°)	TAG 421-...
59086	TM541M-L	Igt/Ih<30/15mA	TIC 216D, T 2506D, TAG 232-400
59087	TM561M-L	TM 541M-L, 600V	TIC 216M, T 2506M, TAG 232-600
59088	TM620M	Igt/Ih<50/50mA	SC 146B, TAG 250B...252B, TW 9N400
59089	TM640M	TM 620M, 400V	SC 146D, TAG 250D...252D, TW 9N400
59090	TM841..861S-L	TM 841..861M-L, , 8A(Tc90°)	TAG 426-..., TAG 452-...
59091	TM841M-L	Igt/Ih<30/15mA	BT 158/400, T 2806D, TAG 225-400
59092	TM861M-L	TM 841M-L, 600V	BT 158/600, T 2806M, TAG 225-600
59093	TN	P6 SMB-68C	P6 SMB-68C
59094	TN0201L	20V, 0,64A, <20hm(0,25A)	2SK1727, 2SK1729, 2SK1733
59095	TN0201T	20V, 0,3A, <10hm(0,3A)	BSS 138
59096	TN0401L	TN 0201L, 40V	2SK1727, 2SK1729, 2SK1733
59097	TN0601L	60V, 0,47A, <1,80hm(1A)	2SK1727, 2SK1729, 2SK1733
59098	TN1613	2N1613, 2W(Tc25°)	2SD1733
59099	TN1711	2N1711, 2W(Tc25°)	2SD1733
59100	TN2010T	200V, 85mA, <110hm(0,1A)	BSS 131
59101	TN2102	2N2102, 2W(Tc25°)	2SC4134, 2SD1074...1075
59102	TN2218(A)	2N2218(A)	2SD1733
59103	TN2219(A)	2N2219(A), 2W(Tc25°)	2SD1733
59104	TN2219[Nsc1996]	2N2219(A), 1W(Ta25°C)	2SD1292
59105	TN2270	2N2270	2SD1733
59106	TN2410L	240V, 0,18A, <100hm(0,2A)	BSS 89, BSN 254
59107	TN2460L	240V, 75mA, <600hm(50mA)	BS 109, BSS 101
59108	TN2460T	TN 2460L, SMD	BSS 131
59109	TN2904(A)	2N2904(A)	2SB1181
59110	TN2905(A)	2N2905(A), 2W(Tc25°)	2SB1181
59111	TN2905[Nsc1996]	2N2905(A), 1W(Ta25°C)	2SB647(A)
59112	TN3012L	<120hm(0,18A)	BS 109, BSS 89, BSS 124
59113	TN3019	2N3019, 2W(Tc25°)	2SC2983, 2SD1220, 2SD1918
59114	TN3019A	2N3019, 1W(Ta25°)	2SC2383, 2SC3228
59115	TN3020	2N3020, 2W(Tc25°)	2SC2983, 2SD1220, 2SD1918
59116	TN3053	2N3053, 2W(Tc25°)	2SD1733
59117	TN3244	2N3244	-
59118	TN3245	2N3245	-
59119	TN3252	2N3252	-
59120	TN3253	2N3253	-
59121	TN3440	2N3440	2SC4615, 2SD1053
59122	TN3440A	2N3440, 1W(Ta25°)	2SC4645
59123	TN3444	2N3444	-
59124	TN3467	2N3467	-
59125	TN3467A	2N3467, 1W(Ta25°)	-
59126	TN3724	2N3724	-
59127	TN3725	2N3725	-
59128	TN3725A	2N3725, 1W(Ta25°)	-
59129	TN3742	2N3742	2SC2924, 2SC3408, 2SC3805, 2SC4019

59130	TN4030	2N4030, 2W(Tc25°)	2SB1181
59131	TN4031	2N4031, 2W(Tc25°)	2SB1181
59132	TN4032	2N4032, 2W(Tc25°)	2SB1181
59133	TN4033	2N4033, 2W(Tc25°)	2SB1181
59134	TN4033A	2N4033, 1W(Ta25°)	2SB647(A), 2SB1041
59135	TN4036	2N4036, 2W(Tc25°)	2SA1592, 2SB844...845
59136	TN4037	2N4037, 2W(Tc25°)	2SA1592, 2SB844...845, 2SB1181
59137	TN41A	2N6027	2N6027
59138	TN41A	2N6027	2N6027
59139	TN41B	2N6028	2N6028
59140	TN41B	2N6028	2N6028
59141	TN4234	2N4234	2SA1731, 2SB906, 2SB1184, 2SB1202
59142	TN4235	2N4235	2SB906, 2SB1184, 2SB1202
59143	TN4236	2N4236	2SA1876
59144	TN4314	2N4314	2SA1592, 2SB844...845
59145	TN5022	2N5022	-
59146	TN5023	2N5023	-
59147	TN5320A	2N5320	2SD1015
59148	TN5322A	2N5322	-
59149	TN5415A	2N5415	-
59150	TN6705A	2N6705	2SD863, 2SD667(A), 2SD1292
59151	TN6714A	2N6714, 1W(Ta25°)	2SC3726, 2SD1207, 2SD2069
59152	TN6715A	2N6715, 1W(Ta25°)	2SC3726, 2SD1207, 2SD2069
59153	TN6717A	2N6717, 1W(Ta25°)	2SC3328, 2SD1207, 2SD2069
59154	TN6719A	2N6719	2SC3249, 2SC3468
59155	TN6725A	2N6725	2SD1854, 2SD1929, 2SD1931
59156	TN6726A	2N6726, 1,5A	2SA1382, 2SB892, 2SB1312, 2SB1433
59157	TN6728A	2N6727, 1,2A	2SA1315, 2SB892, 2SB1459
59158	TN6729A	2N6729, 1A	2SB647(A), 2SB1041
59159	TO	2SK302-O	2SK302
59160	TO201	BC 256	BC 256
59161	TP	P6 SMB-68CA	P6 SMB-68CA
59162	TP	2SD1119-P	2SD1119
59163	TP0202T	20V, 0,31A, <1,4Ohm(0,2A)	-
59164	TP0610E	TP 0610L, 0,25A, 1,5W	TP 0610L
59165	TP0610L	<10Ohm(0,5A)	BST 100, 2SJ198, 2SJ228, 2SJ231
59166	TP0610T	TP 0610L, SMD	-
59167	TP107	BC 107	BC 107
59168	TP107	BC 107	BC 107
59169	TP108	BC 108	BC 108
59170	TP108	BC 108	BC 108
59171	TP109	BC 109	BC 109
59172	TP109	BC 109	BC 109
59173	TP1220L	<20Ohm(50mA)	BS 192, BS 208, BS 212
59174	TP2020L	TP 1220L, 200V	BS 192, BS 208

59175	TP251	BC 251	BC 251
59176	TP251	BC 251	BC 251
59177	TP252	BC 252	BC 252
59178	TP252	BC 252	BC 252
59179	TP253	BC 253	BC 253
59180	TP253	BC 253	BC 253
59181	TP3566	2N3566	
59182	TP3638(A)	2N3638(A)	
59183	TP3702...3711	2N3702..3711	
59184	R	2N3702..3711	
59185	TP4058...4062	2N4058..4062	
59186	TP4123...4126	2N4123..4126	
59187	TP4257...4258	2N4257..4258	
59188	TP4274...4275	2N4274..4275	
59189	TPS-A13	MPSA 13	
59190	TPS-A14	MPSA 14	
59191	TPS141	70V, 10A, 75W, >0,8MHz	BD 710, BD 712, BD 808, BD 810
59192	TPS142	TPS 141, 80V	BD 710, BD 712, BD 810
59193	TPS241(A...C)	BD 241(A..C)	
59194	TPS242(A...C)	BD 242(A..C)	
59195	TPS6512...6523	MPS 6512..6523	
59196	TQ	P6 SMB-75C	P6 SMB-75C
59197	TQ	2SA1530-Q	2SA1530
59198	TQ	2SA1603-Q	2SA1603
59199	TQ	2SD1119-Q	2SD1119
59200	TQ	2SD1699-TQ	2SD1699
59201	TR	P6 SMB-75CA	P6 SMB-75CA
59202	TR	2SC2406-R	2SC2406
59203	TR	2SC3906K-R	2SC3906K
59204	TR	2SA1530-R	2SA1530
59205	TR	2SC4102-R	2SC4102
59206	TR	2SC3929A-R	2SC3929A
59207	TR	2SA1603-R	2SA1603
59208	TR	2SD1119-R	2SD1119
59209	TR	2SD1699-TR	2SD1699
59210	TR22	HVT 30S	HVT 30S
59211	TR30	HVT 30E	HVT 30E
59212	TS	P6 SMB-82C	P6 SMB-82C
59213	TS	2SA1530-S	2SA1530
59214	TS	2SC2406-S	2SC2406
59215	TS	2SC3906K-S	2SC3906K
59216	TS	2SC3929A-S	2SC3929A
59217	TS	2SC4102-S	2SC4102
59218	TS	2SA1603-S	2SA1603
59219	TS	SM 4T 200	SM 4T...

59220	TSB3055	-/80V, 10A, 70W, 8MHz	BD 245C, BD 545C, BDV 95, 2SD1840
59221	TSD30100(DV)	1200/1200V, 30A, 310W	-
59222	TSD3080	1000/800V, 30A, 250W	-
59223	TSD5080(DV)	1000/1000V, 50A, 415W	-
59224	TT	P6 SMB-82CA	P6 SMB-82CA
59225	TT	2SC4519	2SC4519
59226	TT	2SA1530-T	2SA1530
59227	TT	2SC2406-T	2SC2406
59228	TT	2SA1603-T	2SA1603
59229	TT	2SC3929A-T	2SC3929A
59230	TT	SM 4T 200A	SM 4T...
59231	TU	P6 SMB-91C	P6 SMB-91C
59232	TU	SM 4T 220	SM 4T...
59233	TU3F400...800H	mA	TD 3F...H, TD 4F...H, BStCC02...H
59234	TUI1(R)	Iv>4mA, Ip<300µA	-
59235	TUP1A	Iv>70µA, Ip<2µA	-
59236	TUP1B	Iv4mA, Ip20µA	-
59237	TUP2A	Iv>25µA, Ip<0,2mA	-
59238	TUP2B	Iv>0,8mA, Ip<2µA	-
59239	TUP3	Iv>70µA, Ip<5µA	2N6027, 2N6116, 2N6119, MPU 131, MPU 231
59240	TUP3S	Iv>25µA, Ip<1µ	2N6028, 2N6120
59241	TUP4	Iv>70µA, Ip<5µA	-
59242	TV	P6 SMB-91CA	P6 SMB-91CA
59243	TV	SM 4T 220A	SM 4T...
59244	TV4	BA 158	BA 158
59245	TV526/100...700	100..700V, 10A, Igt<75mA	TW9N..., TW11N..., T6001..., MAC15...
59246	TV8	BY 156	BA 158
59247	TVR1B..J	B100, D2	BY 126...127, BY 402...405, 1N4002...4007
59248	TVR2B..J	100..600V, 0,5A, <20µs	BY 126...127, BY 402...405, 1N4002...4007
59249	TVR4J..N	J600, L8	BY 226...227, G 1J...M, 1N5397...5399
59250	TVR5B..J	100..600V, 0,5A, <1,5µs	BY 126...127, BY 402...405, 1N4002...4007
59251	TW	P6 SMB-100C	P6 SMB-100C
59252	Z	10A(Tc85°),Igt/Ih<50/<60mA	BS 10...A, TW 12N...C, TW 18N..., TW 25N...
59253	Z	TW 10N..CZ	BS 10...B, TW 12N...H, T 6401...
59254	Z	TW 10N..CZ	BS 10...B, TW 12N...H, T 6401...
59255	Z	Igt<50mA	TIC236..., 2N6342A...6345A, TXD10K/L...P
59256	CT	Igt/Ih<80/<100mA	TW 18N..., TW 25N...
59257	HT	TW 12N..CT	-
59258	CT	Igt/Ih<80/<100mA	TW 25N...
59259	CT	Igt<150mA	-
59260	TW6N100...700CZ	Igt/Ih<50/<60mA	BS 6...A, TW 8N...C, BS 8...A, TW 10N...C
59261	TW6N100...700HZ	TW 6N..CZ	BS 6...B, TW 8N...H, BS 8...B, TW 10N...H
59262	TW6N100...700PZ	TW 6N..CZ	BS 6...B, TW 8N...H, BS 8...B, TW 10N...H
59263	TW7N400...800FZ	Igt<50mA	MAC222..., TIC226..., T2802..., T2800...
59264	TW8N100...700CZ	Igt/Ih<50/<60mA	BS8...A, TW10N...C, BS10...A, TW12N...C



59265	TW8N100...700HZ	TW 8N..CZ	BS 8...B, TW 10N...H, BS 10...B, TW 12N...H
59266	TW8N100...700PZ	TW 8N..CZ	BS 8...B, TW 10N...H, BS 10...B, TW 12N...H
59267	TW9N400...800FZ	Igt<50mA	TAG251..., TXD10H...M, TAG256..., TIC236.
59268	TX	P6SMB-100CA	P6 SMB-100CA
59269	B	TYAL 1110B..3810B	TAG 456-..., TAG 480-..., TAG 481-...
59270	C	<60/<20mA	TAG 456-..., TAG 480-..., TAG 481-...
59271	0M	<100/<50mA	TAG 456-..., TAG 480-..., TAG 481-...
59272	B	TYAL 1115B..3815B	MAC 15-..., TIC 246..., T 6001...
59273	5M	<100/50mA	MAC 15-..., TIC 246..., T 6001...
59274	TXAL116B..386B	TYAL 116B..386B	TAG 425-..., TAG 451-..., TAG 456-...
59275	TXAL116C..386C	<60/<20mA	TAG 425-..., TAG 451-..., TAG 456-...
59276	M	<100/<50mA	TAG 425-..., TAG 451-..., TAG 456-...
59277	TXAL118B..388B	TYAL 118B..388B	TAG 425-..., TAG 451-..., TAG 456-...
59278	TXAL118C..388C	<60/<20mA	TAG 425-..., TAG 451-..., TAG 456-...
59279	M	<100/<50mA	TAG 425-..., TAG 451-..., TAG 456-...
59280	TXC01A10...60	Igt/Ih<75/<80mA	TAG 260..., TAG 265..., T 4700...
59281	TXC01B10...60	TX C01 A10..A60	TAG 260..., TAG 265..., T 4700...
59282	TXC01C10...60	Igt/Ih<50/<50mA	TAG 260..., TAG 265..., MAC 222...
59283	TXC01D10...60	Igt/Ih<50/<50mA	TAG 260..., TAG 265..., MAC 222...
59284	TXC01E10...60	Igt/Ih<15/<20mA	TAG 261..., TAG 266..., TAG 226...
59285	TXC01F10...60	Igt/Ih<15/<20mA	TAG 261..., TAG 266..., TAG 226...
59286	TXC02A10...60	100..600V, 3A, Igt/Ih<75/80mA	TXC10L..., TAG 250..., BT 136/...
59287	TXC02B10...60	TX C02 A10..A60	TXC10L..., TAG 250..., BT 136/...
59288	TXC02C10...60	Igt/Ih<50/<50mA	TXC10K..., TAG 230..., MAC 216...
59289	TXC02D10...60	Igt/Ih<50/<50mA	TXC10K..., TAG 230..., MAC 216...
59290	TXC02E10...60	Igt/Ih<15/<20mA	TAG 137..., TAG 97..., TIC 206...
59291	TXC02F10...60	Igt/Ih<15/<20mA	TAG 137..., TAG 97..., TIC 206...
59292	TXC03A10...60	Igt/Ih<75/<80mA	TXC30L..., TXC10L..., TAG 250...
59293	TXC03B10...60	TX C03 A10..A60	TXC30L..., TXC10L..., TAG 250...
59294	TXC03C10...60	Igt/Ih<50/<50mA	TXC30K..., TXC10K..., TAG 230...
59295	TXC03D10...60	Igt/Ih<50/<50mA	TXC30K..., TXC10K..., TAG 230...
59296	TXC03E10...60	Igt/Ih<15/<20mA	TXC38H..., TXC38G..., TAG201..., T2302...
59297	TXC03F10...60	Igt/Ih<15/<20mA	TXC38H..., TXC38G..., TAG201..., T2302...
59298	TXC10H40...80	Igt/Ih<50/<25mA	BT136/..., TAG230..., T2500..., T2800...
59299	TXC10H40...80M	Igt/Ih<50/<25mA	T2500..., T2800..., TAG224..., MAC222A...
59300	TXC10K40...80	Igt/Ih<50/<50mA	BT136/..., TAG230..., T2500..., T2800...
59301	TXC10K40...80M	Igt/Ih<50/<50mA	T2500..., T2800..., TAG224..., MAC222A...
59302	TXC10L40...80	Igt/Ih<75/<75mA	BT136/..., TAG250..., T2500..., T2800...
59303	TXC10L40...80M	Igt/Ih<75/<75mA	T2500..., T2800..., TAG250..., MAC222A...
59304	TXC18D40...80	400..800V, 4A, Igt/Ih<5/<20mA	TAG227...
59305	TXC18D40...80M	400..800V, 6A, Igt/Ih<5/<20mA	TAG 222..., TAG 227...
59306	TXC18E40...80	TX C18 D40..80	TXC18E...M, TIC225..., MAC228..., TAG223...
59307	TXC18E40...80M	TX C18 D40..80 M	MAC228..., TIC225..., TXC18D...M, TAG222...
59308	TXC18G40...80	Igt/Ih<10/<20mA	226.
59309	TXC18G40...80M	Igt/Ih<10/<20mA	TAG 221..., TAG 226..., MAC 228A...

59310	TXC18H40...80	Igt/Ih<10/<20mA	TIC216..., TXC18H...M, TXC18G...,TAG232...
59311	TXC18H40...80M	Igt/Ih<10/<20mA	TIC216..., TXC18G...M, TAG221..., TAG226...
59312	TXC30H40...80	Igt/Ih<25/<25mA	T2323..., Z0410..., TAG231..., TAG220...
59313	TXC30J40...80	TX C30 H40..800	T2323..., Z0410..., TAG231..., TAG220...
59314	TXC30K40...80	Igt/Ih<50/<50mA	TXC10K..., TW7N..., MAC222..., TIC226...
59315	TXC30L40...80	Igt/Ih<75/<75mA	TXC10L..., TW7N..., TAG250..., TIC226...
59316	TXC30M40...80	Igt/Ih<50/<50mA	TXC10K..., TW7N..., MAC222..., TIC226...
59317	TXC30P40...80	Igt/Ih<75/<75mA	TXC10L..., TW7N..., TAG250..., TIC226...
59318	TXC31H40...80	Igt/Ih<25/<25mA	T2323..., Z0410..., TAG231..., TAG220...
59319	TXC31J40...80	TX C31 H40..80	T2323..., Z0410..., TAG231..., TAG220...
59320	TXC31K40...80	Igt/Ih<50/<50mA	TXC10K..., TW7N..., MAC222..., TIC226...
59321	TXC31L40...80	Igt/Ih<75/<75mA	TXC10L..., TW7N..., TAG250..., TXCD10L...
59322	TXC31M40...80	Igt/Ih<50/<50mA	TXC10K..., TW7N..., MAC222..., TIC226...
59323	TXC31P40...80	Igt/Ih<75/<75mA	TXC10L..., TW7N..., TAG250..., TXCD10L...
59324	TXC38D40...80	400..800V, 1A, Igt/Ih<5/<20mA	T2301..., TXC18D..., TAG233..., TAG222...
59325	TXC38E40...80	TX C38 D40..80	TXC38D..., Z0104..., T2301..., TXC18E...
59326	TXC38G40...80	Igt/Ih<10/<20mA	Z0106..., T2302..., TXC18G..., TAG232...
59327	TXC38H40...80	Igt/Ih<10/<20mA	TXC38G..., Z0106..., T2302..., TXC18H...
59328	TXC39D40...80	Igt/Ih<5/<20mA	T2301..., T2327..., Z0405..., TXC18D...
59329	TXC39E40...80	TX C39 D40..80	TXC39D..., T2327..., Z0405..., TXC18D...
59330	TXC39G40...80	Igt/Ih<10/<20mA	Z0106..., T2302..., TXC18G..., Z0409...
59331	TXC39H40...80	Igt/Ih<10/<20mA	TXC39G..., Z0106..., T2302..., TXC18H...
59332	TXD10H40...80	Igt/Ih<50/<25mA	TAG 224..., MAC 222A..., BT 137/...
59333	TXD10H40...80M	Igt/Ih<50/<25mA	TAG251..., BT138/..., TAG255..., MAC15A...
59334	TXD10H40...80P	Igt/Ih<50/<25mA	BT138/..., TAG255..., TAG256..., MAC15A...
59335	TXD10K40...80	Igt/Ih<50/<50mA	MAC 222..., TIC 226..., 2N6342...6345
59336	TXD10K40...80M	Igt/Ih<50/<50mA	TW9N..., TIC236..., TW11N..., T6001...
59337	TXD10K40...80P	Igt/Ih<50/<50mA	TIC 236..., TW 11N..., 2N6342A...6345A
59338	TXD10L40...80	Igt/Ih<75/<75mA	MAC 222..., TIC 226..., 2N6342...6345
59339	TXD10L40...80M	Igt/Ih<75/<75mA	TW9N..., TIC236..., TW11N..., TXD10L...P
59340	TXD10L40...80P	Igt/Ih<75/<75mA	TIC 236..., TW 11N..., 2N6342A...6345A
59341	TXD98A20...60	Igt/Ih<50/<50mA	SC250..., TW18N..., TXE99..., SC260...
59342	TXD99A20...60	Igt/Ih<50/<50mA	SC245..., TW10N...C, BS10...A, SC250...
59343	TXDV208	Igt/Ih<100/30mA	MAC 222-..., TIC 226..., T 2802...
59344	TXDV212	<100/30mA	TIC 236..., TW 11N..., TXD 10K/L...P
59345	TXDV408	TXDV 208, 400V	MAC 222-..., TIC 226..., T 2802...
59346	TXDV412	TXDV 212, 400V	TIC 236..., TW 11N..., TXD 10K/L...P
59347	TXDV608	TXDV 208, 600V	MAC 222-..., TIC 226..., T 2802...
59348	TXDV612	TXDV 212, 600V	TIC 236..., TW 11N..., TXD 10K/L...P
59349	TXDV808	TXDV 208, 800V	MAC 222-..., TIC 226..., T 2802...
59350	TXDV812	TXDV 212, 800V	TIC 236..., TW 11N..., TXD 10K/L...P
59351	TXE10L20...80	200..800V, 20A, Igt<50mA	MAC 223..., MAC 223A...
59352	TXE99A20...60	200..600V, 25A, Igt<50/<75mA	SC260..., T6411..., 2N6160...6162, T6410...
59353	TXF505..6005	TYF 505..6005	S 5800..., CSF 11-...
59354	TXF508A..6008A	TYF 508A..6008A	CSF 11-...

59355	TXN0510..1010	TYN 0510..1010	S 2800..., TAG 665-..., TIC 126...
59356	TXN0512..1012	TYN 0512..1012	TIC 126..., T 7,5N..., TAG 680-...
59357	TXN0516..616	TYN 0516..616, Isso	TAG 680-..., TAG 681-..., T 9,5N...
59358	TXN054..1004	TYN 054..1004	-
59359	TXN056..1006	TYN 056..1006	TAG 620-..., TIC 116..., CS 6-...,
59360	TXN058..1008	TYN 058..1008	TIC 116..., TAG 660-..., S 2800...
59361	TXN682..690	TYN 682..690	CS 15-...
59362	8	TYS 1006-05..1006-8	S 4060...
59363	8	<0,5/<6mA	S 4060...
59364	TXS406-05..406-8	TYS 406-05..406-8	TAG 633-..., TIC 106..., TAG 623-...
59365	TXS407-05..407-8	,Igt/Ih<0,5/6mA	TIC 108..., TIC 106..., TAG 623-...
59366	TXS606-05..606-8	TYS 606-05..606-8	TAG 623-..., TAG 628-..., S 4060...
59367	TXS607-05..607-8	,Igt/Ih<0,5/6mA	TAG 623-..., TAG 628-..., S 4060...
59368	TXS806-05..806-8	TYS 806-05..806-8	TAG 628-..., S 4060...
59369	TXS807-05..807-8	8,,Igt/Ih<0,5/<6mA	TAG 628-..., S 4060...
59370	TY	1SS371	1SS371
59371	TY	P6 SMB-110C	P6 SMB-110C
59372	TY	1SS241	1SS241
59373	TY	1SS314	1SS314
59374	TY	2SK302-Y	2SK302
59375	TY	2SC3912	2SC3912
59376	TY	2SK882	2SK882
59377	TY	2SK2315	2SK2315
59378	TY1004	TYN 104	TYN 104
59379	TY1005F	TYF 1005	TYF 1005
59380	TY1008	TYN 108	TYN 108
59381	TY1010	TYN 110	TYN 110
59382	TY2004	TYN 204	TYN 204
59383	TY2005F	TYF 2005	TYF 2005
59384	TY2008	TYN 208	TYN 208
59385	TY2010	TYN 210	TYN 210
59386	TY3004	TYN 204, 300V	TYN 204
59387	TY3005F	TYF 3005	TYF 3005
59388	TY3008	TYN 208, 300V	TYN 208
59389	TY3010	TYN 210, 300V	TYN 210
59390	TY4004	TYN 404	TYN 404
59391	TY4005F	TYF 4005	TYF 4005
59392	TY4008	TYN 408	TYN 408
59393	TY4010	TYN 410	TYN 410
59394	TY5004	TYN 404, 500V	TYN 404
59395	TY5005F	TYF 5005	TYF 5005
59396	TY5008	TYN 408, 500V	TYF 408
59397	TY5010	TYN 410, 500V	TYN 410
59398	TY504	TYN 054	TYN 054
59399	TY505F	TYN 505	TYN 505

59400	TY508	TYN 058	TYN 058
59401	TY510	TYN 0510	TYN 0510
59402	TY6004	TYN 604	TYN 604
59403	TY6005F	TYF 6005	TYF 6005
59404	TY6008	TYN 608	TYN 608
59405	TY6010	TYN 610	TYN 610
59406	TYAL1110B	<50/<50mA	TW 9N..., TXD 10K/L...M, TIC 236...
59407	C	<60/<20mA	TAG 250-..., TAG 251-..., BT 138/...
59408	0M	<100/<50mA	TW 9N..., TXD 10K/L...M, TIC 236...
59409	TYAL1115B	<50/<50mA	MAC 15-..., TIC 246..., T 6001...
59410	5M	<100/50mA	MAC 15-..., TIC 246..., T 6001...
59411	TYAL116B	<50/<50mA	TXC 10K/L...M, TW 7N..., MAC 222-...
59412	TYAL116C..386C	<60/<25mA	TXC 10H...M, TAG 224-..., MAC 222A-...
59413	M	<100/<50mA	TXC 10H...M, TAG 224-..., MAC 222A-...
59414	TYAL118B	<50/<50mA	MAC 222-..., TIC 226..., T 2802...
59415	TYAL118C..388C	<60/<20mA	TAG 224-..., MAC 222A-..., BT 137/...
59416	M	<100/<50mA	MAC 222-..., TIC 226..., T 2802...
59417	TYAL2210B	TYAL 1110, 400V	TW 9N..., TXD 10K/L...M, TIC 236...
59418	TYAL2215B	TYAL 1115B, 400V	MAC 15-..., TIC 246..., T 6001...
59419	TYAL226B	TYAL 116B, 400V	TXC 10K/L...M, TW 7N..., MAC 222-...
59420	TYAL228B	TYAL 118B, 400V	MAC 222-..., TIC 226..., T 2802...
59421	TYAL3810B	TYAL 1110, 700V	TW 9N..., TXD 10K/L...M, TIC 236...
59422	TYAL3815B	TYAL 1115B, 700V	MAC 15-..., TIC 246..., T 6001...
59423	TYAL386B	TYAL 116B, 700V	TXC 10K/L...M, TW 7N..., MAC 222-...
59424	TYAL388B	TYAL 118B, 700V	MAC 222-..., TIC 226..., T 2802...
59425	TYF1005	TYF 505, 100V	S 5800..., CSF 11-...
59426	TYF2005	TYF 505, 200V	S 5800..., CSF 11-...
59427	TYF2008A	TYF 508A, 200V	CSF 11-...
59428	TYF3005	TYF 505, 300V	S 5800..., CSF 11-...
59429	TYF4005	TYF 505, 400V	S 5800..., CSF 11-...
59430	TYF4008A	TYF 508A, 400V	CSF 11-...
59431	TYF5005	TYF 505, 500V	S 5800..., CSF 11-...
59432	TYF505	<40/<30mA	S 5800..., CSF 11-...
59433	TYF508A	<30/10mA	CSF 11-...
59434	TYF6005	TYF 505, 600V	S 5800..., CSF 11-...
59435	TYF6008A	TYF 508A, 600V	CSF 11-...
59436	TYN0510	<15/30mA	S 2800..., TAG 665-..., TIC 126...
59437	TYN0512	Igt/Ih<15/30mA	TIC 126..., T 7,5N..., TAG 680-...
59438	TYN0516	<25/40mA	TAG 680-..., TAG 681-..., T 9,5N...
59439	TYN054	<15/30mA	TAG 630-..., TAG 620-..., TAG 625-...
59440	TYN056	<15/30mA	TAG 620-..., TAG 625-..., TIC 116...
59441	TYN058	<15/<30mA	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59442	TYN1004	TYN 054, 1000V	-
59443	TYN1006	TYN 056, 1000V	-
59444	TYN1008	TYN 058, 1000V	-

59445	TYN1010	TYN 0510, 1000V	-
59446	TYN1012	TYN 0512, 1000V	-
59447	TYN104	TYN 054, 100V	TAG 630-..., TAG 620-..., TAG 625-...
59448	TYN106	TYN 056, 100V	TAG 620-..., TAG 625-..., TIC 116...
59449	TYN108	TYN 058, 100V	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59450	TYN110	TYN 0510, 100V	S 2800..., TAG 665-..., TIC 126...
59451	TYN112	TYN 0512, 100V	TIC 126..., T 7,5N..., TAG 680-...
59452	TYN116	TYN 0516, 100V	TAG 680-..., TAG 681-..., T 9,5N...
59453	TYN204	TYN 054, 200V	TAG 630-..., TAG 620-..., TAG 625-...
59454	TYN206	TYN 056, 200V	TAG 620-..., TAG 625-..., TIC 116...
59455	TYN208	TYN 058, 200V	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59456	TYN210	TYN 0510, 200V	S 2800..., TAG 665-..., TIC 126...
59457	TYN212	TYN 0512, 200V	TIC 126..., T 7,5N..., TAG 680-...
59458	TYN216	TYN 0516, 200V	TAG 680-..., TAG 681-..., T 9,5N...
59459	TYN404	TYN 054, 400V	TAG 630-..., TAG 620-..., TAG 625-...
59460	TYN406	TYN 056, 400V	TAG 620-..., TAG 625-..., TIC 116...
59461	TYN408	TYN 058, 400V	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59462	TYN410	TYN 0510, 400V	S 2800..., TAG 665-..., TIC 126...
59463	TYN412	TYN 0512, 400V	TIC 126..., T 7,5N..., TAG 680-...
59464	TYN416	TYN 0516, 400V	TAG 680-..., TAG 681-..., T 9,5N...
59465	TYN604	TYN 054, 600V	TAG 630-..., TAG 620-..., TAG 625-...
59466	TYN606	TYN 056, 600V	TAG 620-..., TAG 625-..., TIC 116...
59467	TYN608	TYN 058, 600V	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59468	TYN610	TYN 0510, 600V	S 2800..., TAG 665-..., TIC 126...
59469	TYN612	TYN 0512, 600V	TIC 126..., T 7,5N..., TAG 680-...
59470	TYN616	TYN 0516, 600V	TAG 680-..., TAG 681-..., T 9,5N...
59471	TYN682	<25/<40mA	CS 15-...
59472	TYN682	<25/<40mA	CS 15-...
59473	TYN683	TYN 682, 100V	CS 15-...
59474	TYN685	TYN 682, 200V	CS 15-...
59475	TYN688	TYN 682, 500V	CS 15-...
59476	TYN690	TYN 682, 600V	CS 15-...
59477	TYN804	TYN 054, 800V	TAG 630-..., TAG 620-..., TAG 625-...
59478	TYN806	TYN 056, 800V	TAG 620-..., TAG 625-..., TIC 116...
59479	TYN808	TYN 058, 800V	TIC 116..., CS 6-..., TAG 660-..., S 2800...
59480	TYN810	TYN 0510, 800V	S 2800..., TAG 665-..., TIC 126...
59481	TYN812	TYN 0512, 800V	TIC 126..., T 7,5N..., TAG 680-...
59482	TYS1006-05	<0,2/<6mA	S 4060...
59483	TYS1006-1	TYS 1006-05, 100V	S 4060...
59484	TYS1006-2	TYS 1006-05, 200V	S 4060...
59485	TYS1006-4	TYS 1006-05, 400V	S 4060...
59486	TYS1006-6	TYS 1006-05, 600V	S 4060...
59487	TYS1006-8	TYS 1006-05, 800V	S 4060...
59488	8	<0,5/<6mA	S 4060...
59489	TYS406-05	<0,2/<6mA	TAG 633-..., TIC 106..., TAG 623-...

59490	TYS406-1	TYS 406-05, 100V	TAG 633-..., TIC 106..., TAG 623-...
59491	TYS406-2	TYS 406-05, 200V	TAG 633-..., TIC 106..., TAG 623-...
59492	TYS406-4	TYS 406-05, 400V	TAG 633-..., TIC 106..., TAG 623-...
59493	TYS406-6	TYS 406-05, 600V	TAG 633-..., TIC 106..., TAG 623-...
59494	TYS406-6	TYS 406-05, 800V	TAG 633-..., TIC 106..., TAG 623-...
59495	TYS407-05..407-8	<0,5/6mA	TIC 108..., TIC 106..., TAG 623-...
59496	TYS606-05	<0,2/6mA	TAG 623-..., TAG 628-..., S 4060...
59497	TYS606-1	TYS 606-05, 100V	TAG 623-..., TAG 628-..., S 4060...
59498	TYS606-2	TYS 606-05, 200V	TAG 623-..., TAG 628-..., S 4060...
59499	TYS606-4	TYS 606-05, 400V	TAG 623-..., TAG 628-..., S 4060...
59500	TYS606-6	TYS 606-05, 600V	TAG 623-..., TAG 628-..., S 4060...
59501	TYS606-8	TYS 606-05, 800V	TAG 623-..., TAG 628-..., S 4060...
59502	TYS607-05..607-8	<0,5/6mA	TAG 623-..., TAG 628-..., S 4060...
59503	TYS806-05	<0,2/<6mA	TAG 628-..., S 4060...
59504	TYS806-1	TYS 806-05, 100V	TAG 628-..., S 4060...
59505	TYS806-2	TYS 806-05, 200V	TAG 628-..., S 4060...
59506	TYS806-4	TYS 806-05, 400V	TAG 628-..., S 4060...
59507	TYS806-6	TYS 806-05, 600V	TAG 628-..., S 4060...
59508	TYS806-8	TYS 806-05, 800V	TAG 628-..., S 4060...
59509	TYS807-05..807-8	<0,5/<6mA	TAG 628-..., S 4060...
59510	TZ	P6SMB-110CA	P6 SMB-110CA
59511	TZ	BZW 20	BZW 20
59512	TZ4,7..24	4,7..24V, 5%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5230...52
59513	TZM/C2V4..75	BZX 55/C..., SMD	BZD27/..., BZV55/..., HZK ..., RLZ ...
59514	B	1N5221B.. 5267B, SMD	BZD27/..., BZV55/..., HZK ..., RLZ ...
59515	U	HVU 355	HVU 355
59516	U	HVE 355	HVE 355
59517	U05B...J	100..800V, 2,5A	BY 251...255, GP 30B...M, 1N5401...08
59518	U06C...J	200..800V, 2A, <600ns	BY 318/..., BY 396...399, RGP 30B...M
59519	U07J...N	800..1500V, 1A, <800ns	BY 228, BY 231/..., BY 448, BY 458
59520	U1	3SK284	3SK284
59521	U1	3SK283	3SK283
59522	U1	FES 1A	FES 1A
59523	U1(p)	BCX 19	BCX 19
59524	U1(s)	BGX 50A	BGX 50A
59525	U10120E	MUR 10120E	MUR 10120E
59526	U10150E	MUR 10150E	MUR 10150E
59527	U12	2SC2758-U12	2SC2758
59528	U120	MUR 120	MUR 120
59529	U13	2SC2758-U13	2SC2758
59530	U13T1	2N6027	2N6027
59531	U13T2	2N6028	2N6028
59532	U13T3	2N6027, 100V	-
59533	U13T4	2N6028, 100V	-
59534	U14	2SC2758-U14	2SC2758



59535	U140	MUR 140	MUR 140
59536	U1520	MUR 1520	MUR 1520
59537	U1540	MUR 1540	MUR 1540
59538	U1560	MUR 1560	MUR 1560
59539	U160	MUR 160	MUR 160
59540	U1620	MURF 1620CT	MURF 1620CT
59541	U1620	MUR 1620CT	MUR 1620CT
59542	U1620R	MUR 1620TR	MUR 1620TR
59543	U1620T	MURB 1620CT	MURB 1620CT
59544	U1640	MUR 1640CT	MUR 1640CT
59545	U1660	MUR 1660CT	MUR 1660CT
59546	U1660	MURF 1660CT	MURF 1660CT
59547	U1660T	MURB 1660CT	MURB 1660CT
59548	U1837(E)	TIS 88A	TIS 88A
59549	U1897	<30Ohm	2N4091
59550	U1897E..1899E	U 1897..1899	U1897...99
59551	U1898	<50Ohm	2N4092
59552	U1899	40V, Idss>8mA, Up<5V, <8Ohm	2N4093
59553	U190E	MUR 190E	MUR 190E
59554	U1981(E)	TIS 88A	TIS 88A
59555	U1BC44..JC44	BC44100,	BYG 10D...M, D 1F10...F60
59556	U1CL49..DL49	150..200V, 1A	-
59557	U1D	MURS 120	MURS 120
59558	U1FWJ49..GWJ49	FWJ4930V,	-
59559	U1GWJ2C49	S, 40V, 1A, 11ns	-
59560	U1J	MURS 160	MURS 160
59561	U1ZB12..390	12..390V	BZG03/..., MA1Z..., RD...FM, PTZ...
59562	U2	FES 1B	FES 1B
59563	U2	2SK613-2	2SK613
59564	U2(p)	BCX 20	BCX 20
59565	U21	2SC2759-U21	2SC2759
59566	U22	2SC2759-U22	2SC2759
59567	U23	2SC2759-U23	2SC2759
59568	U2720	BC 116A	BC 116A
59569	U2734	BC 141	BC 141
59570	U2735	BC 161	BC 161
59571	U290	Up<10V	-
59572	U290	Up<10V	-
59573	U291	U 290, Idss>200mA, Up<4,5V	-
59574	U2GWJ2C42	40V, 2A, 13ns	-
59575	U2TA506	B>1000	BC 618, BC 877, BC 879, 2SD2116
59576	U3	FES 1D	FES 1D
59577	U3	BSS 64	BSS 64
59578	U3	2SK613-3	2SK613
59579	U3020	MUR 3020PT	MUR 3020PT

59580	U3020	MUR 3020WT	MUR 3020WT
59581	U3040	MUR 3040PT	MUR 3040PT
59582	U3040	MUR 3040	MUR 3040
59583	U3040	MUR 3040WT	MUR 3040WT
59584	U3060	MUR 3060PT	MUR 3060PT
59585	U3060	MUR 3060WT	MUR 3060WT
59586	U308		
59587	U308..310-TO-92	U 308..U 310	
59588	U3080	MUR 3080	MUR 3080
59589	U309	U 308, Idss12..30mA, Up<-4V	BF 256C, 2N5397, 2N5485
59590	U310	U 308, Idss24..60mA, Up<-6V	2SK582
59591	U312	Up<6V	BF 256C, 2N5397, 2N5486
59592	U32	3SK132-U32	3SK132
59593	U320	Idss100..500mA,Up<10V	-
59594	U320	MURD 320	MURD 320
59595	U321	Up<4V	-
59596	U322	Idss200..700mA,Up<10V	-
59597	U33	3SK132-U33	3SK132
59598	U35	BSR 19	BSR 19
59599	U36	BSR 19A	BSR 19A
59600	U3GWJ2C42	40V, 3A, 15ns	-
59601	U4	FES 1F	FES 1F
59602	U4	2SK613-4	2SK613
59603	U4	BCX 19R	BCX 19R
59604	U4100E	MUR 4100	MUR 4100(E)
59605	U42	3SK132-U42	3SK132
59606	U420	MUR 420	MUR 420
59607	U43	3SK132-U43	3SK132
59608	U460	MUR 460	MUR 460
59609	U490E	MUR 490E	MUR 490E
59610	U5	FES 1G	FES 1G
59611	U5	BCX 20R	BCX 20R
59612	U5150E	MUR 5150E	MUR 5150E
59613	U6	BSS 64R	BSS 64R
59614	U6040	MUR 6040	MUR 6040
59615	U620	MUR 620CT	MUR 620CT
59616	U620T	MURD 620CT	MURD 620CT
59617	U7(p)	BSR 13	BSR 13
59618	U71	BSR 13R	BSR 13R
59619	U71	2N6027, SMD	2N6027
59620	U72	2N6028, SMD	2N6028
59621	U8(p)	BSR 14	BSR 14
59622	U81	BSR 14R	BSR 14R
59623	U8100E	MUR 8100	MUR 8100(E)
59624	U820	MURF 820	MURF 820

59625	U820	MUR 820	MUR 820
59626	U840	MUR 840	MUR 840
59627	U860	MUR 860	MUR 860
59628	U890E	MUR 890E	MUR 890E
59629	U9	BSR 17	BSR 17
59630	U91	BSR 17R	BSR 17R
59631	U92	BSR 17A	BSR 17A
59632	U93	BSR 17AR	BSR 17AR
59633	UA	2SB852-UA	2SB852
59634	UA	MMBTA 517	MMBTA 517
59635	UA	2SB852K-A	2SB852K
59636	UA	3SK101	3SK101
59637	UA1	2SJ357	2SJ357
59638	UA2	2SJ358	2SJ358
59639	UB	2SC4973-B	2SC4973
59640	UB	2SB852-UB	2SB852
59641	UB	2SK1771	2SK1771
59642	UB	BB 503	BB 503
59643	UB	2SB852K-B	2SB852K
59644	UB	2SC2404-B	2SC2404
59645	UB	2SC4627-B	2SC4627
59646	UB	2SC3931-B	2SC3931
59647	UBS421	50V, 20A, 70W, on<17mOhm	-
59648	UC	2SC4973-C	2SC4973
59649	UC	3SK126	3SK126
59650	UC	2SC4627-C	2SC4627
59651	UC	2SC2404-C	2SC2404
59652	UC	2SC3931-C	2SC3931
59653	UC	3SK114	3SK114
59654	UD	2SC4973-D	2SC4973
59655	UD	3SK127	3SK127
59656	UD	2SC4627-D	2SC4627
59657	UD	BB 504	BB 504
59658	UD	2SC2404-D	2SC2404
59659	UD	2SC2821-D	2SC2821
59660	UD	2SC3931-D	2SC3931
59661	UD	SM 4T 18C	SM 4T...
59662	UD	3SK115	3SK115
59663	UE	3SK146	3SK146
59664	UE	2SC2821-E	2SC2821
59665	UE	SM 4T 18CA	SM 4T...
59666	UE	3SK145	3SK145
59667	UF	BB 801	BB 801
59668	UF	2SC2821-F	2SC2821
59669	UF-1(A...C)	400..1000V, 0,25A, <300ns	BA 157...159, BY 204/..., BY 208/...

59670	UF-2	600V, 1A, <300ns	BY 201/6, BYX 55/600, RGP 10J...M
59671	UF-3	500V, 1,5A, <300ns	BY 318/600, BY 399, RGP 30J...M
59672	UF4001	50V, 1A, <50ns	BYV 26B...E, EGP 10A...F, FE 1A...H
59673	UF4002	UF 4001, 100V	BYV 26B...E, EGP 10B...F, FE 1B...H
59674	UF4003	UF 4001, 200V	BYV 26B...E, EGP 10D...F, FE 1D...H
59675	UF4004	UF 4001, 400V	BYV 26B...E, FE 1H
59676	UF4005	UF 4001, 600V	BYV 26C...E, BYV 36C...E
59677	UF4006	UF 4001, 800V, <75ns	BYV 26D...E, BYV 36D...E
59678	UF4007	UF 4001, 1000V, <75ns	BYV 26E
59679	UF5400	50V, 3A, <50ns	BYV 28/50...200, EGP 30A...G, FE 3A...H
59680	UF5401	UF 5400, 100V	BYV 28/100...200, EGP 30B...G, FE 3B...H
59681	UF5402	UF 5400, 200V	BYV 28/200, EGP 30D...G, FE 3D...H
59682	UF5403	UF 5400, 300V	EGP 30F...G, FE 3F...H
59683	UF5404	UF 5400, 400V	EGP 30G, FE 3H
59684	UF5405	UF 5400, 500V	MUR 450, MUR 460, MUR 480, MUR 4100
59685	UF5406	UF 5400, 600V	MUR 460, MUR 480, MUR 4100
59686	UF5408	UF 5400, 800V	MUR 480, MUR 4100
59687	UFSD-1(A...C)	400..1000V, 0,3A, <300ns	BA 157...159, BY 204/..., BY 208/...
59688	UG	3SK140	3SK140
59689	UG	BBY 31	BBY 31
59690	UG	3SK121	3SK121
59691	UH	3SK151	3SK151
59692	UH	3SK260	3SK260
59693	UH	SM 4T 22C	SM 4T...
59694	UH	3SK150	3SK150
59695	UH840	MURH 840CT	MURH 840CT
59696	UH840	MURHB 840CT	MURHB 840CT
59697	UH860	MURH 860CT	MURH 860CT
59698	UI	3SK153	3SK153
59699	UI	3SK259	3SK259
59700	UI	3SK152	3SK152
59701	UI-	2SC4229	2SC4229
59702	UI-	2SC4259	2SC4259
59703	UJ	3SK195	3SK195
59704	UK	SM 4T 22CA	SM 4T...
59705	UK	2SC3618-UK	2SC3618
59706	UL	3SK160	3SK160
59707	UL	2SB1295	2SB1295
59708	UL	SM 4T 24C	SM 4T...
59709	UL	2SC3618-UL	2SC3618
59710	UL	3SK159	3SK159
59711	UM	3SK199	3SK199
59712	UM	2SC3618-UM	2SC3618
59713	UM	SM 4T 24CA	SM 4T...
59714	UM	3SK198	3SK198

59715	N	FMA 1A..FMA 11A	-
59716	N	FMB 1A..FMB 14A	-
59717	UMC1N..UMC6N	FMC 1A..FMC 6A	-
59718	UMD2N..UMD6N	IMD 2A..IMD 6A	-
59719	N	FMG 1A..FMG 11A	-
59720	N	IMH 1A..IMH 15A	-
59721	UML1N	-/40V, 0,1A	Pin-Code: AEBCK
59722	UML2N	-/40V, 0,1A	Pin-Code: AEBCK
59723	UMS1N	FMS 1A	-
59724	UMS2N	FMS 2A	-
59725	UMT1N..UMT3N	IMT 1A..IMT 3N	-
59726	UMT2222A	2N2222A, SMD	-
59727	UMT2907A	2N2907A, SMD	-
59728	UMT3904	2N3904, SMD	BC 817W, 2SD1820A
59729	UMT3906	2N3906, SMD	BC 807W, 2SB1219A
59730	UMT4401	2N4401, SMD	BC 817W, PMST 4401, 2SD1820A
59731	UMT4403	2N4403, SMD	BC 807W, PMST 4403, 2SB1219A
59732	UMT918	2N918, SMD	BF 517W, BF 547W, BFS 17W, 2SC4780
59733	N	FMW 1..FMW 13	-
59734	N	IMX 1..IMX 13	-
59735	UMY1N..UMY4N	FMY 1A..FMY 4A	-
59736	UMZ1N	IMZ 1A	-
59737	UMZ2N	IMZ 2A	-
59738	UN	3SK240	3SK240
59739	UN	3SK215	3SK215
59740	UN	3SK274	3SK274
59741	UN	3SK274	3SK274
59742	UN	SM 4T 27C	SM 4T...
59743	UN1110	Rb47k, Rbe-, 50V, 0,1A, 0,4W	AN 1L4Z, DTA 144TS, KSR 2012, 2SA1509
59744	UN1111	UN 1110, RbRbe10kOhm	AN 1A4M, DTA 114ES, RN 2002, 2SA1348
59745	UN1112	UN 1110, RbRbe22kOhm	AN 1F4M, DTA 124ES, RN 2003, 2SA1346
59746	UN1113	UN 1110, RbRbe47kOhm	AN 1L4M, DTA 144ES, RN 2004, 2SA1345
59747	UN1114	UN 1110, Rb10k, Rbe47kOhm	AN 1A4P, DTA 114YS, RN 2007, 2SA1564
59748	UN1115	UN 1110, Rb10kOhm, Rbe-	AN 1A4Z, DTA 114TS, RN 2011, 2SA1497
59749	UN1116	UN 1110, Rb4,7kOhm, Rbe-	AN 1L3Z, DTA 143TS, RN 2010, 2SA1511
59750	UN1117	UN 1110, Rb22kOhm, Rbe-	AN 1F4Z, DTA 124TS, KSR 2011, 2SA1590
59751	UN1118	UN 1110, Rb0,51k, Rbe5,1kOhm	-
59752	UN1119	UN 1110, Rb1k, Rbe10kOhm	AN 1A3Q, DTA 113ZS
59753	UN111D	0,4W	DTA 144VS
59754	UN111E	UN 111D, Rb47k, Rbe22kOhm	AN 1L4L, DTA 144WS, RN 2009, 2SA1347
59755	UN111F	UN 111D, Rb4,7k, Rbe10kOhm	AN 1L3N, DTA 143XS, KSR 2005, 2SA1654
59756	UN111H	UN 111D, Rb2,2k, Rbe10kOhm	DTA 123YS, 2SA1503
59757	UN111K	UN 111D, Rb10k, Rbe4,7kOhm	DTA 114WS
59758	UN111L	UN 111D, RbRbe4,7kOhm	AN 1L3M, DTA 143ES, RN 2001, 2SA1656
59759	UN1121	0,6W	DTB 123ES, RN 2222, 2SA1525, 2SA1529

59760	UN1122	UN 1121, RbRbe4,7kOhm	DTB 143ES, RN 2223, 2SA1523, 2SA1527
59761	UN1123	UN 1121, RbRbe10kOhm	DTB 114ES, RN 2224, 2SA1522, 2SA1526
59762	UN1124	UN 1121, Rb2,2k, Rbe10kOhm	DTB 123YS, RN 2227, 2SA1524, 2SA1528
59763	UN112X	0,6W	-
59764	UN112Y	UN 112X, Rb3,1k, Rbe4,6kOhm	-
59765	UN1210	Rb47k, Rbe-, 50V, 0,1A, 0,4W	AA 1L4Z, DTC 144TS, KSR 1012, 2SC3899
59766	UN1211	UN 1210, RbRbe10kOhm	AA 1A4M, DTC 114ES, RN 1002, 2SC3402
59767	UN1212	UN 1210, RbRbe22kOhm	AA 1F4M, DTC 124ES, RN 1003, 2SC3400
59768	UN1213	UN 1210, RbRbe47kOhm	AA 1L4M, DTC 144ES, RN 1004, 2SC3399
59769	UN1214	UN 1210, Rb10k, Rbe47kOhm	AA 1A4P, DTC 114YS, RN 1007, 2SC4048
59770	UN1215	UN 1210, Rb10k, Rbe-	AA 1A4Z, DTC 114TS, RN 1011, 2SC3860
59771	UN1216	UN 1210, Rb4,7k, Rbe-	AA 1L3Z, DTC 143TS, RN 1010, 2SC3901
59772	UN1217	UN 1210, Rb22k, Rbe-	AA 1F4Z, DTC 124TS, KSR 1011, 2SC4121
59773	UN1218	UN 1210, Rb0,51k, Rbe5,1kOhm	-
59774	UN1219	UN 1210, Rb1k, Rbe10kOhm	AA 1A3Q, DTC 113ZS
59775	UN121D	0,4W	DTC 144VS
59776	UN121E	UN 121D, Rb47k, Rbe22kOhm	AA 1L4L, DTC 144WS, RN 1009, 2SC3401
59777	UN121F	UN 121D, Rb4,7k, Rbe10kOhm	AA 1L3N, DTC 143XS, KSR 1005, 2SC3461
59778	UN121H	UN 121D, Rb2,2k, Rbe10kOhm	DTC 123YS, 2SC3864
59779	UN121K	UN 121D, Rb10k, Rbe4,7kOhm	DTC 114WS
59780	UN121L	UN 121D, RbRbe4,7kOhm	AA 1L3M, DTC 143ES, RN 1001, 2SC4363
59781	UN1221	0,6W	DTD 123ES, RN 1222, 2SC3919, 2SC3923
59782	UN1222	UN 1221, RbRbe4,7kOhm	DTD 143ES, RN 1223, 2SC3917, 2SC3921
59783	UN1223	UN 1221, RbRbe10kOhm	DTD 114ES, RN 1224, 2SC3916, 2SC3920
59784	UN1224	UN 1221, Rb2,2k, Rbe10kOhm	DTD 123YS, RN 1227, 2SC3918, 2SC3922
59785	UN1231	Rb1k, Rbe47kOhm, 20V, 0,7A	-
59786	UN1231A	UN 1231, 60V	-
59787	UN2110	UN 1110, SMD	FN 1L4Z, DTA 144TK, KSR 2112, 2SA1508
59788	UN2111	UN 1111, SMD	FN 1A4M, DTA 114EK, RN 2402, 2SA1344
59789	UN2112	UN 1112, SMD	FN 1F4M, DTA 124EK, RN 2403, 2SA1342
59790	UN2113	UN 1113, SMD	FN 1L4M, DTA 144EK, RN 2404, 2SA1341
59791	UN2114	UN 1114, SMD	FN 1A4P, DTA 114YK, RN 2407, 2SA1563
59792	UN2115	UN 1115, SMD	FN 1A4Z, DTA 114TK, RN 2411, 2SA1496
59793	UN2116	UN 1116, SMD	FN 1L3Z, DTA 143TK, RN 2410, 2SA1510
59794	UN2117	UN 1117, SMD	FN 1F4Z, DTA 124TK, KSR 2111, 2SA1589
59795	UN2118	UN 1118, SMD	-
59796	UN2119	UN 1119, SMD	FN 1A3Q, DTA 113ZK
59797	UN211D	UN 111D, SMD	DTA 144VK
59798	UN211E	UN 111E, SMD	FN 1L4L, DTA 144WK, RN 2409, 2SA1343
59799	UN211F	UN 111F, SMD	FN 1L3L, DTA 143XK, KSR 2105, 2SA1653
59800	UN211H	UN 111H, SMD	DTA 123YK, 2SA1502
59801	UN211K	UN 111K, SMD	DTA 114WK
59802	UN211L	UN 111L, SMD	FN 1L3M, DTA 143EK, RN 2401, 2SA1655
59803	UN211M	Rbe47kOhm	DTA 123JK, RN 2405, KSR 2113
59804	UN2121	UN 1121, SMD	DTB 123EK, 2SA1521



59805	UN2122	UN 1122, SMD	DTB 143EK, 2SA1519
59806	UN2123	UN 1123, SMD	DTB 114EK, 2SA1518
59807	UN2124	UN 1124, SMD	DTB 123YK, 2SA1520
59808	UN212X	UN 112X, SMD	-
59809	UN212Y	UN 112Y, SMD	-
59810	UN2210	UN 1210, SMD	FA 1L4Z, DTC 144TK, KSR 1112, 2SC3898
59811	UN2211	UN 1211, SMD	FA 1A4M, DTC 114EK, RN 1402, 2SC3398
59812	UN2212	UN 1212, SMD	FA 1F4M, DTC 124EK, RN 1403, 2SC3396
59813	UN2213	UN 1213, SMD	FA 1L4M, DTC 144EK, RN 1404, 2SC3395
59814	UN2214	UN 1214, SMD	FA 1A4P, DTC 114YK, RN 1407, 2SC4047
59815	UN2215	UN 1215, SMD	FA 1A4Z, DTC 114TK, RN 1411, 2SC3859
59816	UN2216	UN 1216, SMD	FA 1L3Z, DTC 143TK, RN 1410, 2SC3900
59817	UN2217	UN 1217, SMD	FA 1F4Z, DTC 124TK, KSR 1111, 2SC4120
59818	UN2218	UN 1218, SMD	-
59819	UN2219	UN 1219, SMD	FA 1A3Q, DTC 113ZK
59820	UN221D	UN 121D, SMD	DTC 144VK
59821	UN221E	UN 121E, SMD	FA 1L4L, DTC 144WK, RN 1409, 2SC3397
59822	UN221F	UN 121F, SMD	FA 1L3N, DTC 143XK, KSR 1105, 2SC4360
59823	UN221H	UN 121H, SMD	DTC 123YK, 2SC3863
59824	UN221K	UN 121K, SMD	DTC 114WK
59825	UN221L	UN 121L, SMD	FA 1L3M, DTC 143EK, RN1401, 2SC4362
59826	UN221M	Rbe47kOhm	DTC 123JK, KSR 1113, RN1405
59827	UN2221	UN 1221, SMD	DTD 123EK, 2SC3915
59828	UN2222	UN 1222, SMD	DTD 143EK, 2SC3913
59829	UN2223	UN 1223, SMD	DTD 114EK, 2SC3912
59830	UN2224	UN 1224, SMD	DTD 123YK, 2SC3914
59831	UN4110..4119	UN 1110..1119, 0,3W	UN 1110...1119
59832	UN411D..L	UN 111..., 0,3W	UN 111...
59833	UN4121..4124	UN 1121..1124, 0,3W	UN 1121...1124
59834	UN412X..Y	UN 112..., 0,3W	UN 112...
59835	UN4210..4219	UN 1210..1219, 0,3W	UN 1210...1219
59836	UN421D..L	UN 121..., 0,3W	UN 121...
59837	UN4221..4224	UN 1221..1224, 0,3W	UN 1221...1224
59838	UN5101	30mA	-
59839	UN5110	UN 1110, SMD	DTA 144TU
59840	UN5111	UN 1111, SMD	DTA 114EU, RN2302, 2SA1678
59841	UN5112	UN 1112, SMD	DTA 124EU, RN2303, 2SA1677
59842	UN5113	UN 1113, SMD	DTA 144EU, RN2304, 2SA1676
59843	UN5114	UN 1114, SMD	DTA 114YU, RN2307
59844	UN5115	UN 1115, SMD	DTA 114TU, RN2311
59845	UN5116	UN 1116, SMD	DTA 143TU, RN2310
59846	UN5117	UN 1117, SMD	DTA 124TU
59847	UN5118	UN 1118, SMD	-
59848	UN5119	UN 1119, SMD	DTA 113ZU
59849	UN511D	UN 111D, SMD	DTA 144VU

59850	UN511E	UN 111E, SMD	DTA 144WU, RN 2309
59851	UN511F	UN 111F, SMD	DTA 143XU
59852	UN511H	UN 111H, SMD	DTA 123YU, 2SA1722
59853	UN511K	UN 111K, SMD	DTA 114WU
59854	UN511L	UN 111L, SMD	DTA 143EU, RN 2301
59855	UN511M	Rbe47kOhm	DTA 123JU, RN 2305
59856	UN5201	30mA	-
59857	UN5210	UN 1210, SMD	DTC 144TU
59858	UN5211	UN 1211, SMD	DTC 114EU, RN 1302, 2SC4398
59859	UN5212	UN 1212, SMD	DTC 124EU, RN 1303, 2SC4397
59860	UN5213	UN 1213, SMD	DTC 144EU, RN 1304, 2SC4396
59861	UN5214	UN 1214, SMD	DTC 114YU, RN 1307
59862	UN5215	UN 1215, SMD	DTC 114TU, RN 1311
59863	UN5216	UN 1216, SMD	DTC 143TU, RN 1310
59864	UN5217	UN 1217, SMD	DTC 124TU
59865	UN5218	UN 1218, SMD	-
59866	UN5219	UN 1219, SMD	DTC 113ZU
59867	UN521D	UN 121D, SMD	DTC 144VU
59868	UN521E	UN 121E, SMD	DTC 144WU, RN 1309
59869	UN521F	UN 121F, SMD	DTC 143XU
59870	UN521H	UN 121H, SMD	DTC 123YU, 2SC4498
59871	UN521K	UN 121K, SMD	DTC 114WU
59872	UN521L	UN 121L, SMD	DTC 143EU, RN 1301
59873	UN521M	Rbe47kOhm	DTC 123JU, RN 1305
59874	UN6110..6119	UN 1110..1119	UN 1110...1119
59875	UN611D..L	UN 111..	UN 111...
59876	UN6121..6124	UN 1121..1124	UN 1121...1124
59877	UN612X..Y	UN 112..	UN 112...
59878	UN6210..6219	UN 1210..1219	UN 1210...1219
59879	UN621D..L	UN 121..	UN 121...
59880	UN6221..6224	UN 1221..1224	UN 1221...1224
59881	UN7231	UN 1231, SMD	-
59882	UN8231(A)	UN 1231(A)	-
59883	UN9110	UN 1110, SMD	DTA 144TE
59884	UN9111	UN 1111, SMD	DTA 114EE, RN 2102
59885	UN9112	UN 1112, SMD	DTA 124EE, RN 2103
59886	UN9113	UN 1113, SMD	DTA 144EE, RN 2104
59887	UN9114	UN 1114, SMD	DTA 114YE, RN 2107
59888	UN9115	UN 1115, SMD	DTA 114TE, RN 2111
59889	UN9116	UN 1116, SMD	DTA 143TE, RN 2110
59890	UN9117	UN 1117, SMD	DTA 124TE
59891	UN9118	UN 1118, SMD	-
59892	UN9119	UN 1119, SMD	DTA 113ZE
59893	UN911D	UN 111D, SMD	DTA 144VE
59894	UN911E	UN 111E, SMD	DTA 144WE, RN 2109

59895	UN911F	UN 111F, SMD	DTA 143XE
59896	UN911H	UN 111H, SMD	DTA 123YE
59897	UN911K	UN 111K, SMD	DTA 114WE
59898	UN911L	UN 111L, SMD	DTA 143EE, RN 2101
59899	UN9210	UN 1210, SMD	DTC 144TE
59900	UN9211	UN 1211, SMD	DTC 114EE, RN 1102
59901	UN9212	UN 1212, SMD	DTC 124EE, RN 1103
59902	UN9213	UN 1213, SMD	DTC 144EE, RN 1104
59903	UN9214	UN 1214, SMD	DTC 114YE, RN 1107
59904	UN9215	UN 1215, SMD	DTC 114TE, RN 1111
59905	UN9216	UN 1216, SMD	DTC 143TE, RN 1110
59906	UN9217	UN 1217, SMD	DTC 124TE
59907	UN9218	UN 1218, SMD	-
59908	UN9219	UN 1219, SMD	DTC 113ZE
59909	UN921D	UN 121D, SMD	DTC 144VE
59910	UN921E	UN 121E, SMD	DTC 144WE, RN 1109
59911	UN921F	UN 121F, SMD	DTC 143XE
59912	UN921H	UN 121H, SMD	DTC 123YE
59913	UN921K	UN 121K, SMD	DTC 114WE
59914	UN921L	UN 121L, SMD	DTC 143EE, RN 1101
59915	UO	3SK249	3SK249
59916	UO	3SK232	3SK232
59917	UP	3SK216	3SK216
59918	UP	3SK275	3SK275
59919	UP	3SK250	3SK250
59920	UP	SM 4T 27CA	SM 4T...
59921	UQ	SM 4T 30C	SM 4T...
59922	UR	3SK256	3SK256
59923	UR	3SK207	3SK207
59924	UR	SM 4T 30CA	SM 4T...
59925	UR2271	1N4936	1N4936
59926	US	SM 4T 33C	SM 4T...
59927	UT	3SK257	3SK257
59928	UT	3SK225	3SK225
59929	UT	2SC4577	2SC4577
59930	UT	2SC4555	2SC4555
59931	UT	SM 4T 33CA	SM 4T...
59932	UTZJ4.7..39(A..C)	4,7..39V, 0,35W	BZV 39/..., 1N4099...4123
59933	UU	3SK258	3SK258
59934	UU	3SK226	3SK226
59935	UU	SM 4T 36C	SM 4T...
59936	UV	SM 4T 36CA	SM 4T...
59937	UW	SM 4T 39C	SM 4T...
59938	UW0029	BC 239	BC 239
59939	UX	SM 4T 39CA	SM 4T...

59940	UY	2SC3913	2SC3913
59941	UY	2SJ450	2SJ450
59942	UZ-2..40A,B	2..40V, 0,5W, A10%, B5%	BZX55/..., BZX83/..., ZPD..., 1N5221...59
59943	UZP-5,6..33B	5,6..33V, 5%, 1W	BZW22/..., BZX61/..., ZPY..., 1N5919...37
59944	V	HVC 308A	HVC 308A
59945	V	HVU 308A	HVU 308A
59946	V	2SK1332	2SK1332
59947	V0	VP 0610T	VP 0610T
59948	V01	3SK179-V01	3SK179
59949	V01C...L	200..1000V, 1,5A	BY 226...227, BY 251...255, 1N5392...99
59950	V02	3SK179-V02	3SK179
59951	V03	3SK179-V03	3SK179
59952	V03C...G	200..600V, 1,3A	BY 226...227, BY 251...255, 1N5392...99
59953	V06C...G	200..600V, 1,1A	BY 226...227, BY 251...255, 1N5392...99
59954	V07E...J	400..800V, 1,3A	BYW 18/..., BYW 53...56, 1N5060...62
59955	V08E...J	400..800V, 1,1A	BYW 18/..., BYW 53...56, 1N5060...62
59956	V09C...G	200..600V, 0,4A, <800ns	BA 157...159, BY 206...207, BY 406...407
59957	V1	FES 2A	FES 2A
59958	V1	1SV160	1SV160
59959	V1	VN 50300T	VN 50300T
59960	V1	2SD596-V1	2SD596
59961	V1(p)	BFT 25	BFT 25
59962	V10	3SK131-V10	3SK131
59963	V10	BFT 25A	BFT 25A
59964	V11	3SK131-V11	3SK131
59965	V11	BFG 25	BFG 25
59966	V11J,L	800..1000V, 0,4A, <800ns	BA 158...159, BY 204/..., BY 208/...
59967	V12	3SK131-V12	3SK131
59968	V12	BFG 67X	BFG 67X
59969	V13	BFG 197X	BFG 197X
59970	V14	BFG 92AX	BFG 67AX
59971	V15	BFG 93AX	BFG 93AX
59972	V16	BFG 33X	BFG 33X
59973	V2	D 1F20	D 1F20
59974	V2	HVU 362	HVU 362
59975	V2	FES 2B	FES 2B
59976	V2	HVC 362	HVC 362
59977	V2	VN 0605T	VN 0605T
59978	V2	2SD596-V2	2SD596
59979	V2	2SK303-V2	2SK303
59980	V2	BFQ 67W	BFQ 67W
59981	V2(p)	BFQ 67	BFQ 67
59982	V25	PMBT 3640	PMBT 3640
59983	V26	BFG 67XR	BFG 67XR
59984	V27	BFG 67R	BFG 67R

59985	V29	BFG 92A/XR	BFG 92A/XR
59986	V3	BFG 67	BFG 67
59987	V3	HVC 363A	HVC 363A
59988	V3	HVU 363A	HVU 363A
59989	V3	FES 2D	FES 2D
59990	V3	1SV225	1SV225
59991	V3	2SD596-V3	2SD596
59992	V3	2SK303-V3	2SK303
59993	V30	PMBTH 10	PMBTH 10
59994	V31	PMBTH 81	PMBTH 81
59995	V32	BF 750	BF 750
59996	V33	BFG 93A/XR	BFG 93A/XR
59997	V34	BF 749	BF 749
59998	V35	BFG 197XR	BFG 197XR
59999	V38	BF 752	BF 752
60000	V4	FES 2F	FES 2F
60001	V4	D 1F40	D 1F40
60002	V4	BFT 25R	BFT 25R
60003	V4	2SK303-V4	2SK303
60004	V4	2SD780-V4	2SD780
60005	V4	1SV228	1SV228
60006	V413K	Ub26..40V, Ib<0,2mA, Itsm2A	1N5761, N413M, BR100, D3202Y, DO201YR
60007	V413L	V413K, Ub26..32V	1N5760, N413L, D3202U
60008	V413M	V413K, Ub29..37V	1N5761, N413M, BR100, D3202Y, DO201YR
60009	V413N	V413K, Ub34..40V	1N5762, N413N, D3202U
60010	V5	BFG 197	BFG 197
60011	V5	FES 2G	FES 2G
60012	V5	2SD780-V5	2SD780
60013	V5	1SV242	1SV242
60014	V5	2SK303-V5	2SK303
60015	V5B	TVR 5B	TVR 5B...J
60016	V5D	TVR 5D	TVR 5B...J
60017	V5G	TVR 5G	TVR 5B...J
60018	V5J	TVR 5J	TVR 5B...J
60019	V6	BFG 33	BFG 33
60020	V6	HVC 365	HVC 365
60021	V6	HVU 365	HVU 365
60022	V6	D 1F60	D 1F60
60023	V6	2SD780-V6	2SD780
60024	V7005	MV 7005	MV 7005
60025	V7404	MV 7404	MV 7404
60026	VA	RN 4901	RN 4901
60027	VA	RN 4601	RN 4601
60028	VA	KTC 3121	KTC 3121
60029	VA	2SC2776-A	2SC2776

60030	VA	2SC4626-A	2SC4626
60031	VA	2SC2295-A	2SC2295
60032	VA	2SC3930-A	2SC3930
60033	VB	RN 4902	RN 4902
60034	VB	RN 4602	RN 4602
60035	VB	2SC4626-B	2SC4626
60036	VB	2SC2776-B	2SC2776
60037	VB	2SC2295-B	2SC2295
60038	VB	2SC3930-B	2SC3930
60039	VC	RN 4603	RN 4603
60040	VC	RN 4903	RN 4903
60041	VC	2SC4626-C	2SC4626
60042	VC	2SC2295-C	2SC2295
60043	VC	2SC2776-C	2SC2776
60044	VC	2SC3930-C	2SC3930
60045	VCR2N	25V, 0,3W, Up<7V, <60Ohm	-
60046	VCR4N	25V, 0,3W, Up<7V, <600Ohm	-
60047	VCR7N	25V, 0,3W, Up<5V, <8kOhm	-
60048	VD	RN 4604	RN 4604
60049	VD	RN 4904	RN 4904
60050	VD	P6 SMB-130C	P6 SMB-130C
60051	VD	P6 SMB-120C	P6 SMB-120C
60052	VD	1SV268	1SV268
60053	VD	SM 4T 6V8C	SM 4T...
60054	VD1120	0,56..0,61V(1,5mA)	-
60055	VD1121	0,59..0,64V(1,5mA)	-
60056	VD1122	0,62..0,67V(1,5mA)	-
60057	VD1123	0,63..0,69V(10mA)	-
60058	VD1124	0,62..0,67V(1,5mA)	-
60059	VD1210	1,12..1,22V(1,5mA)	-
60060	VD1211	1,18..1,28V(1,5mA)	-
60061	VD1212	1,24..1,34V(1,5mA)	-
60062	VD1213	1,26..1,38V(10mA)	-
60063	VD1220	VD 1210	-
60064	VD1221	VD 1211	-
60065	VD1222	VD 1212	-
60066	VD1223	VD 1213	-
60067	VD1320	1,68..1,83V(1,5mA)	-
60068	VD1321	1,77..1,92V(1,5mA)	-
60069	VD1322	1,86..2,01V(1,5mA)	-
60070	VD1323	1,89..2,07V(10mA)	-
60071	VE	RN 4605	RN 4605
60072	VE	RN 4905	RN 4905
60073	VE	P6SMB-120CA	P6 SMB-120CA
60074	VE	SM 4T 6V8CA	SM 4T...



60075	VF	RN 4606	RN 4606
60076	VF	RN 4906	RN 4906
60077	VF	SM 4T 7V5C	SM 4T...
60078	VG	P6SMB-130CA	P6 SMB-130CA
60079	VG	2SJ106-GR	2SJ106
60080	VG	2SJ144-GR	2SJ144
60081	VG	SM 4T 7V5CA	SM 4T...
60082	VH	RN 4907	RN 4907
60083	VH	RN 4607	RN 4607
60084	VH	P6 SMB-150C	P6 SMB-150C
60085	VI	RN 4908	RN 4908
60086	VI	RN 4608	RN 4608
60087	VI	1SV160	1SV160
60088	VIB	2SA1617-B	2SA1617
60089	VIC	2SA1617-C	2SA1617
60090	VJ	RN 4909	RN 4909
60091	VJ	RN 4609	RN 4609
60092	VK	RN 4610	RN 4610
60093	VK	RN 4910	RN 4910
60094	VK	P6SMB-150CA	P6 SMB-150CA
60095	VK	2SD1950-VK	2SD1950
60096	VL	P6 SMB-160C	P6 SMB-160C
60097	VL	2SA1581	2SA1581
60098	VL	2SJ106-BL	2SJ106
60099	VL	2SJ144-BL	2SJ144
60100	VL	2SD1950-VL	2SD1950
60101	VM	RN 4911	RN 4911
60102	VM	RN 4611	RN 4611
60103	VM	P6SMB-160CA	P6 SMB-160CA
60104	VM	2SD1950-VM	2SD1950
60105	VN	RN 4612	RN 4612
60106	VN	P6 SMB-170C	P6 SMB-170C
60107	VN	SM 4T 10C	SM 4T...
60108	VN0300B	VN 0300L, 1,51A, 5W	BST 95
60109	VN0300L	30V, 0,64A, 0,8W, <3,3Ohm	BST 70, BSS 296, 2SK1727, 2SK1729
60110	VN0300M	VN 0300L, 0,67A, 1W	-
60111	VN0605T	60V, 0,18A, <5Ohm, <20/20ns	BSS 145, BST 82
60112	VN0606L	60V, 0,33A, 0,8W, <3Ohm	BSS 296, 2SK940...941, 2SK1727
60113	VN0606M	VN 0606L, 0,36A, 1W	-
60114	VN0610L	VN 0610LL	2SK1336...1337
60115	VN0610LL	60V, 0,19A, 0,4W, <10/10ns	BS 170, BST 72
60116	VN0610LL	<10/10ns	BS 170, BST 72, 2SK1336...1337
60117	VN0808L	80V, 0,3A, 0,8W, <4Ohm(1A)	BSS 296, 2SK940...941, 2SK1729
60118	VN0808M	VN 0808L, 0,33A, 1W	-
60119	VN10KE	<10/10ns	BS 170, BSS 91, BST 72, 2SK1336

60120	VN10KM	VN 10KE, 0,31A, 1W	-
60121	VN10LE	<10/10ns	BSS 296, BST 70, BST 90, 2SK1484
60122	VN10LM	VN 10KM, 0,32A, 1W	-
60123	VN1206B	VN 1206L, 0,22A, 5W	-
60124	VN1206D	VN 1206L, 0,33A, 20W	-
60125	VN1206L	120V, 0,23A, 0,8W, <6Ohm	BSS 88...89, BSN 254
60126	VN1206M	VN 1206L, 0,26A, 1W	-
60127	VN1210L	VN 1210M, 0,18A, 0,8W	-
60128	VN1210M	120V, 0,2A, 1W, <10Ohm	-
60129	VN1706L	170V, 0,2A, 0,35W, <6Ohm	BSS 88...89, BSN 254
60130	VN2010L	200V, 0,19A, 0,8W, <10Ohm	BSS 88...89, BSN 254
60131	VN2222L	VN 2222LL	2SK1336...1337
60132	VN2222LL	7,5Ohm,<10/10ns	BS 170, BST 72, 2SK1336...1337
60133	VN2222LM	VN 2222LL, 0,26A, 1W	-
60134	VN2406B	VN 2406L, 0,63A, 6,25W	-
60135	VN2406D	VN 2406L, 1,12A, 20W	-
60136	VN2406L	240V, 0,21A, <6Ohm(0,5A)	BSN 254, BSS 88...89
60137	VN2406M	VN 2406L	-
60138	VN2410L	240V, 0,15A, <10Ohm(0,5A)	BSN 254, BSS 88...89
60139	VN2410M	VN 2410L	-
60140	VN3515L	350V, 0,15A, <15Ohm(0,1A)	-
60141	VN4000A	400V, 8A, 100W, 125/125ns	BUZ 210...211, BUZ 330...331, 2SK298
60142	VN4001A	400V, 8A, 100W, 125/125ns	BUZ 210...211, BUZ 330...331, 2SK298
60143	VN4012L	400V, 0,16A, <12Ohm(0,1A)	-
60144	VN50300L	<300Ohm(10mA)	BSS 125
60145	VN50300T	VN 50300L, SMD	-
60146	VN66AFD	60V, 1,46A, 15W, <6Ohm(1A)	-
60147	VN88AFD	80V, 1,29A, 15W, <4Ohm(1A)	-
60148	VNH100N04	42V, 100A, <12mOhm	-
60149	VNH50N04	40V, 50A, <12mOhm	-
60150	VNH70N07	70V, 70A, <15mOhm	-
60151	VNP10N06	VND 10N06	-
60152	VNP10N07	70V, 10A, <0,10Ohm	-
60153	VNP14N04	42V, 14A, <0,07Ohm	-
60154	VNP20N07	70V, 20A, <0,05Ohm	-
60155	VNP28N04	42V, 28A, <35mOhm	-
60156	VNP35N07	70V, 35A, <28mOhm	-
60157	VNP35N07FI	VNP 35N07	-
60158	VNP49N04	42V, 49A, <0,02Ohm	-
60159	VNP5N07	70V, 5A, <0,2Ohm	-
60160	VNP7N04	42V, 7A, <0,14Ohm	-
60161	VO	2SC3803-O	2SC3803
60162	VP	P6SMB-170CA	P6 SMB-170CA
60163	VP	2SD968A-P	2SD968A
60164	VP	SM 4T 10CA	SM 4T...

60165	VP0300B	<2,5Ohm(1A)	IRF 9610...9613
60166	VP0300L	VP 0300B, 0,32A, 0,8W	BS 250, BST 100, 2SJ228
60167	VP0300M	VP 0300B, 0,5A, 1W	-
60168	VP0610E	VP 0610L, 0,25A, 1,5W	-
60169	VP0610L	<10Ohm(0,5A)	BST 100, 2SJ198, 2SJ228, 2SJ231
60170	VP0610T	VP 0610L, SMD, 0,12A	2SJ209...211
60171	VP0808B	80V, 0,88A, 2,5W, <5Ohm(1A)	IRF 9610...9613
60172	VP0808L	VP 0808B, 0,28A, 0,8W	2SJ198, 2SK231
60173	VP0808M	VP 0808B, 0,31A, 1W	-
60174	VP1008B	100V, 0,79A, 2,5W, <5Ohm(1A)	IRF 9610...9613
60175	VP1008L	VP 0808B, 0,28A, 0,8W	2SJ198, 2SJ231
60176	VP1008M	VP 0808B, 0,31A, 1W	-
60177	VP2020E	VP 2020L, 0,17A, 1,5W	-
60178	VP2020L	<20Ohm(0,1A)	BS 192, BS 208, BS 212, BSP 204
60179	VP2410B	VP 2410L, 0,17A, 0,73W	-
60180	VP2410L	<10Ohm(0,1A)	BS 209, BSS 92
60181	VQ	P6 SMB-180C	P6 SMB-180C
60182	VQ	2SD968A-Q	2SD968A
60183	VR	P6SMB-180CA	P6 SMB-180CA
60184	VR	2SD968A-R	2SD968A
60185	VR	2SC3803-R	2SC3803
60186	VR1B	TVR 1B	TVR 1B...J
60187	VR1D	TVR 1D	TVR 1B...J
60188	VR1G	TVR 1G	TVR 1B...J
60189	VR1J	TVR 1J	TVR 1B...J
60190	VR2B	TVR 2B	TVR 2B...J
60191	VR2D	TVR 2D	TVR 2B...J
60192	VR2G	TVR 2G	TVR 2B...J
60193	VR2J	TVR 2J	TVR 2B...J
60194	VR4J	TVR 4J	TVR 4J...N
60195	VR4L	TVR 4L	TVR 4J...N
60196	VR4N	TVR 4N	TVR 4J...N
60197	VS	P6 SMB-200C	P6 SMB-200C
60198	VS	2SD968A-S	2SD968A
60199	VS	SM 4T 12C	SM 4T...
60200	VT	P6SMB-200CA	P6 SMB-200CA
60201	VT	SM 4T 12CA	SM 4T...
60202	VU	P6 SMB-220C	P6 SMB-220C
60203	VV	P6SMB-220CA	P6 SMB-220CA
60204	VW	SM 4T 15C	SM 4T...
60205	VX	SM 4T 15CA	SM 4T...
60206	VY	2SJ106-Y	2SJ106
60207	VY	2SC3914	2SC3914
60208	VY	2SJ144-Y	2SJ144
60209	VY	2SC3803-Y	2SC3803

60210	VY	2SK2788	2SK2788
60211	W	HSU 402J	HSU 402J
60212	W06A...C	50..200V, 0,75A	BY 126...127, BY 133...135, 1N4001...07
60213	W1	BFT 92W	BFT 92W
60214	W1(p)	BFT 92	BFT 92
60215	W1002A	HRW 1002A	HRW 1002A
60216	W1002B	HRW 1002B	HRW 1002B
60217	W2	BZX 84/C0V8	BZX 84/C0V8
60218	W2	BZV 49/C0V8	BZV 49/C0V8
60219	W245CX	BF 245	BF 245
60220	W2502A	HRW 2502A	HRW 2502A
60221	W2502B	HRW 2502B	HRW 2502B
60222	W3	BZX 84/C2V4	BZX 84/C2V4
60223	W3	BZV 49/C2V4	BZV 49/C2V4
60224	W4	BFT 92R	BFT 92R
60225	W4	BZX 84/C2V7	BZW 84/C2V7
60226	W4	BZX 88/C2V7	BZX 88/C2V7
60227	W4	BZV 49/C2V7	BZV 49/C2V7
60228	W4891..4894	2N4891..4894	2N4891...4894
60229	W5	BZX 84/C3V0	BZX 84/C3V0
60230	W5	BZX 88/C3V0	BZX 88/C3V0
60231	W5	BZV 49/C3V0	BZV 49/C3V0
60232	W6	BZX 84/C3V3	BZX 84/C3V3
60233	W6	BZX 88/C3V3	BZX 88/C3V3
60234	W6	BZV 49/C3V3	BZV 49/C3V3
60235	W7	BZX 84/C3V6	BZX 84/C3V6
60236	W7	BZX 88/C3V6	BZX 88/C3V6
60237	W7	BZV 49/C3V6	BZV 49/C3V6
60238	W8	BZX 84/C3V9	BZX 84/C3V9
60239	W8	BZX 88/C3V9	BZX 88/C3V9
60240	W8	BZV 49/C3V9	BZV 49/C3V9
60241	W9	BZX 84/C4V3	BZX 84/C4V3
60242	W9	BZX 88/C4V3	BZX 88/C4V3
60243	W9	BZV 49/C4V3	BZV 49/C4V3
60244	WA	2SD1383-WA	2SD1383
60245	WA	HN 3C01F	HN 3C01F
60246	WA	2SD1383K-A	2SD1383K
60247	WAO	KTC3920-O	KTC 3920
60248	WAY	KTC3920-Y	KTC 3920
60249	WB	2SD1383-WB	2SD1383
60250	WB	HN 3C02F	HN 3C02F
60251	WB	2SD1383K-B	2SD1383K
60252	WC	HN 3C03F	HN 3C03F
60253	WCs	BCR 133	BCR 133
60254	WDs	BCR 141	BCR 141

60255	WE	HN 3C06F	HN 3C06F
60256	WE	2SK322-E	2SK322
60257	WEs	BCR 148	BCR 148
60258	WF	HN 3C07F	HN 3C07F
60259	WF	2SK322-F	2SK322
60260	WFs	BCR 112	BCR 112
60261	WG	HN 3C08F	HN 3C08F
60262	WG	2SK322-G	2SK322
60263	WG1010A	15V, 5mA	BA 127, BA 215, BA 222, 1N4148...49
60264	WG1010A	15V, 5mA	BA 127, BA 215, BA 222, 1N4148...49
60265	WG713	35V, 0,1A, <6ns	BAY 74, BAY 95, 1N4154, 1N4148...49
60266	WH	2SK322-H	2SK322
60267	WHs	BCR 108	BCR 108
60268	WI-	3SK197	3SK197
60269	WJs	BCR 135	BCR 135
60270	WKs	BCR 119	BCR 119
60271	WL	2SA1589	2SA1589
60272	WLs	BCR 146	BCR 146
60273	WMs	BCR 183	BCR 183
60274	WN	SM 4T 68C	SM 4T...
60275	WNs	BCR 185	BCR 185
60276	WO	KTC3876-O	KTC 3876
60277	WO	2SC2859-O	2SC2859
60278	WO	2SC4118-O	2SC4118
60279	WO	2SA1483-O	2SA1483
60280	WOs	BCR 191	BCR 191
60281	WP	2SK322-P	2SK322
60282	WP	SM 4T 68CA	SM 4T...
60283	WP	2SD968-P	2SD968
60284	WPs	BCR 192	BCR 192
60285	WQ	2SD2432-Q	2SD2432
60286	WQ	2PD602Q	2PD602
60287	WQ	2SK322-Q	2SK322
60288	WQ	2SD602-Q	2SD602
60289	WQ	2SD1820-Q	2SD1820
60290	WQ	2SD968-Q	2SD968
60291	WR	2SD2432-R	2SD2432
60292	WR	2SK322-R	2SK322
60293	WR	2PD602R	2PD602
60294	WR	2SD602-R	2SD602
60295	WR	2SD1820-R	2SD1820
60296	WR	2SD968-R	2SD968
60297	WR	2SA1483-R	2SA1483
60298	WRs	BCR 198	BCR 198
60299	WS	2SD2432-S	2SD2432

60300	WS	2SK322-S	2SK322
60301	WS	2SD602-S	2SD602
60302	WS	2PD602S	2PD602
60303	WS	2SD1820-S	2SD1820
60304	WS	2SD968-S	2SD968
60305	WS504A	1200V, 2..4A	-
60306	WS504A	1200V, 2..4A	-
60307	WS604A	WS 504A, 1500V	-
60308	WS604A	WS 504A, 1500V	-
60309	WT	2SK322-T	2SK322
60310	WV-	2SK2752	2SK2752
60311	WW	SM 4T 100C	SM 4T...
60312	WX	SM 4T 100CA	SM 4T...
60313	WY	2SC2859-Y	2SC2859
60314	WY	KTC3876-Y	KTC 3876
60315	WY	2SC3915	2SC3915
60316	WY	2SC4118-Y	2SC4118
60317	WY	2SJ484	2SJ484
60318	WY	2SA1483-Y	2SA1483
60319	WZ-032...-350	3,2..35V, 5%, 0,5W	BZX55/..., BZX83/..., ZPD..., 1N5225...58
60320	WZs	BCR 142	BCR 142
60321	X0100AA	<0,02/5mA	-
60322	B	X 0100AA..0100DA	-
60323	X0100BA	X 0100AA, 200V	-
60324	X0100CA	X 0100AA, 300V	-
60325	X0100DA	X 0100AA, 400V	-
60326	X0101BA	X 0100BA, 0,5A(Tc55°)	-
60327	B	X 0101BA..0101NA	-
60328	D	X 0101BA..0101NA	-
60329	X0101DA	X 0100DA	-
60330	X0101MA	X 0100DA, 600V, 0,5A(Tc55°)	-
60331	X0101NA	X 0100DA, 800V, 0,5A(Tc55°)	-
60332	A	<0,2/5mA	TAG 59-..., BT 149/..., MCR 606...,
60333	B	<0,2/5mA	TAG 59-..., BT 149/..., MCR 606...,
60334	A	<0,2/5mA	2N6681...6685
60335	B	<0,2/5mA	2N6681...6685
60336	D	<0,2/5mA	TAG 651-...
60337	X0301BG	<0,02/5mA	-
60338	X0301DG	X 0301BG, 400V	-
60339	X0301MG	X 0301BG, 600V	-
60340	G	<0,2/5mA	TAG 615-...
60341	G	<0,5/5mA	TAG 615-...
60342	X0403BE	Igt/Ih<0,2/<5mA	TAG 633-200, TIC 106B, TAG 623-200
60343	X0403BF..0403NF	X 0403BE..0403NE	TAG 623-..., TAG 628-..., S 4060...,
60344	X0403DE	X 0403BE, 400V	TAG 633-400, TIC 106D, TAG 623-400



60345	X0403ME	X 0403BE, 600V	TAG 633-600, TIC 106M, TAG 623-600
60346	X0403NE	X 0403BE, 800V	TAG 633-800, TIC 106N, TAG 623-800
60347	X0404BE	Igt/Ih<0,5/<5mA	TIC 108B
60348	X0404BF..0404NF	X 0403BE..0403NE	TIC 108...
60349	X0404DE	X 0404BE, 400V	TIC 108D
60350	X0404ME	X 0404BE, 600V	TIC 108M
60351	X0404NE	X 0404BE, 800V	TIC 108N
60352	X0609BE	Igt/Ih<10/<15mA	TAG 632-200, TAG 621-200,TAG 622-200
60353	X0609BF..0609NF	X 0609BE..0609NE	TAG 627-..., TAG 626-..., T 3,5N...
60354	X0609DE	X 0609BE, 400V	TAG 632-400, TAG 621-400,TAG 622-400
60355	X0609ME	X 0609BE, 600V	TAG 632-600, TAG 621-600,TAG 622-600
60356	X0609NE	X 0609BE, 800V	TAG 632-800, TAG 621-800,TAG 622-800
60357	X0709BG	<10/15mA	TAG 607-...
60358	X0709DG	X 0709BG, 400V	TAG 607-...
60359	X0709MG	X 0709BG, 600V	TAG 607-...
60360	X1	BZX 84/C27	BZX 84/C27
60361	X1	2SK94-1	2SK94
60362	X1	BZX 88/C27	BZX 88/C27
60363	X1	BFT 93W	BFT 93W
60364	X1	2SK852-X1	2SK852
60365	X1	BZV 49/C27	BZV 49/C27
60366	X1(p)	BFT 93	BFT 93
60367	X11	2SK425-X11	2SK425
60368	X12	2SK425-X12	2SK425
60369	X13	2SK425-X13	2SK425
60370	X14	2SK425-X14	2SK425
60371	X15	2SK425-X15	2SK425
60372	X16	2SK425-X16	2SK425
60373	X17	2SK425-X17	2SK425
60374	X18	2SK425-X18	2SK425
60375	X2	2SK94-2	2SK94
60376	X2	BZX 84/C30	BZX 84/C30
60377	X2	BZX 88/C30	BZX 88/C30
60378	X2	2SK852-X2	2SK852
60379	X2	BZV 49/C30	BZV 49/C30
60380	X21	2SK426-X21	2SK426
60381	X22	2SK426-X22	2SK426
60382	X23	2SK426-X23	2SK426
60383	X24	2SK426-X24	2SK426
60384	X25	2SK426-X25	2SK426
60385	X26	2SK426-X26	2SK426
60386	X27	2SK426-X27	2SK426
60387	X28	2SK426-X28	2SK426
60388	X3	2SK94-3	2SK94
60389	X3	BZX 84/C33	BZX 84/C33

60390	X3	BZX 88/C33	BZX 88/C33
60391	X3	2SK852-X3	2SK852
60392	X3	BZV 49/C33	BZV 49/C33
60393	X31	2SK515-X31	2SK515
60394	X32	2SK515-X32	2SK515
60395	X33	2SK515-X33	2SK515
60396	X34	2SK515-X34	2SK515
60397	X35	2SK515-X35	2SK515
60398	X4	BZX 84/C36	BZX 84/C36
60399	X4	2SK94-4	2SK94
60400	X4	BFT 93R	BFT 93R
60401	X4	2SK852-X4	2SK852
60402	X4	BZX 88/C36	BZX 88/C36
60403	X4	BZV 49/C36	BZV 49/C36
60404	X41	2SK1001-X41	2SK1001
60405	X42	2SK1001-X42	2SK1001
60406	X43	2SK1001-X43	2SK1001
60407	X44R224	D 44 R2	
60408	X5	BZX 84/C39	BZX 84/C39
60409	X5	MMBV 409	MMBV 409
60410	X5	BZX 88/C39	BZX 88/C39
60411	X5	BZV 49/C39	BZV 49/C39
60412	X6	2SD1048-X6	2SD1048
60413	X6	BZX 84/C43	BZX 84/C43
60414	X6	BZX 88/C43	BZX 88/C43
60415	X6	BZV 49/C43	BZV 49/C43
60416	X7	BZX 84/C47	BZX 84/C47
60417	X7	2SD1048-X7	2SD1048
60418	X7	BZX 88/C47	BZX 88/C47
60419	X7	BZV 49/C47	BZV 49/C47
60420	X8	2SD1048-X8	2SD1048
60421	XA	RN 1901	RN 1901
60422	XA	RN 1701	RN 1701
60423	XA	RN 1501	RN 1501
60424	XA	RN 1601	RN 1601
60425	XA	RN 1401	RN 1401
60426	XA	RN 1101	RN 1101
60427	XA	RN 1301	RN 1301
60428	XA	RN 5001	RN 5001
60429	XAF	2SK980-F	2SK980
60430	XAG	2SK980-G	2SK980
60431	XB	RN 1602	RN 1602
60432	XB	RN 1702	RN 1702
60433	XB	RN 1502	RN 1502
60434	XB	RN 1902	RN 1902

60435	XB	RN 1402	RN 1402
60436	XB	RN 1102	RN 1102
60437	XB	RN 1302	RN 1302
60438	XB	RN 5002	RN 5002
60439	XB-	2SC4416	2SC4416
60440	XB401	60V, 1A, PQ>2,5W(175MHz)	BFS 23, BLY 34
60441	XB411	BLY 61	BLY 61
60442	XB412	BLY 62	BLY 62
60443	XB413	BLY 63	BLY 63
60444	XC	RN 1603	RN 1603
60445	XC	RN 1903	RN 1903
60446	XC	RN 1503	RN 1503
60447	XC	RN 1703	RN 1703
60448	XC	2SK492-C	2SK492
60449	XC	RN 1403	RN 1403
60450	XC	RN 1103	RN 1103
60451	XC	RN 1303	RN 1303
60452	XC	RN 5003	RN 5003
60453	XC-	2SC4415	2SC4415
60454	XD	RN 1904	RN 1904
60455	XD	RN 1604	RN 1604
60456	XD	RN 1504	RN 1504
60457	XD	RN 1704	RN 1704
60458	XD	RN 1404	RN 1404
60459	XD	2SK492-D	2SK492
60460	XD	RN 1104	RN 1104
60461	XD	RN 1304	RN 1304
60462	XDB	2SK1031-B	2SK1031
60463	XDB	2SK1532-B	2SK1532
60464	XDC	2SK1031-C	2SK1031
60465	XDC	2SK1532-C	2SK1532
60466	XDD	2SK1031-D	2SK1031
60467	XDD	2SK1532-D	2SK1532
60468	XE	RN 1905	RN 1905
60469	XE	RN 1605	RN 1605
60470	XE	RN 1505	RN 1505
60471	XE	RN 1705	RN 1705
60472	XE	2SK492-E	2SK492
60473	XE	RN 1405	RN 1405
60474	XE	RN 1105	RN 1105
60475	XE	RN 1305	RN 1305
60476	XE-	2SK1092	2SK1092
60477	XF	RN 1606	RN 1606
60478	XF	RN 1906	RN 1906
60479	XF	RN 1706	RN 1706

60480	XF	RN 1506	RN 1506
60481	XF	RN 1106	RN 1106
60482	XF	RN 1406	RN 1406
60483	XF	RN 1306	RN 1306
60484	XF	RN 5006	RN 5006
60485	XF-	2SC4464	2SC4464
60486	XG	2SK2145-GR	2SK2145
60487	XG	2SK209-GR	2SK209
60488	XG	KTK 209-G	KTK 209-G
60489	XG	2SK880-GR	2SK880
60490	XH	RN 1607	RN 1607
60491	XH	RN 1907	RN 1907
60492	XH	RN 1507	RN 1507
60493	XH	RN 1707	RN 1707
60494	XH	RN 1107	RN 1107
60495	XH	RN 1407	RN 1407
60496	XH	RN 1307	RN 1307
60497	XH	SM 4T 150C	SM 4T...
60498	XI	RN 1908	RN 1908
60499	XI	RN 1608	RN 1608
60500	XI	RN 1708	RN 1708
60501	XI	RN 1508	RN 1508
60502	XI	RN 1408	RN 1408
60503	XI	RN 1108	RN 1108
60504	XI	RN 1308	RN 1308
60505	XI-	3SK196	3SK196
60506	XJ	RN 1609	RN 1609
60507	XJ	RN 1709	RN 1709
60508	XJ	RN 1509	RN 1509
60509	XJ	RN 1909	RN 1909
60510	XJ	RN 1109	RN 1109
60511	XJ	RN 1409	RN 1409
60512	XJ	RN 1309	RN 1309
60513	XJD	2SK1326-D	2SK1326
60514	XJE	2SK1326-E	2SK1326
60515	XK	RN 1910	RN 1910
60516	XK	RN 1510	RN 1510
60517	XK	RN 1610	RN 1610
60518	XK	RN 1710	RN 1710
60519	XK	RN 1110	RN 1110
60520	XK	RN 1410	RN 1410
60521	XK	RN 1310	RN 1310
60522	XK	SM 4T 150CA	SM 4T...
60523	XK	2SD1614-XK	2SD1614
60524	XL	2SK2145-L	2SK2145

60525	XL	2SK209-BL	2SK209
60526	XL	2SA1597	2SA1597
60527	XL	KTK 209-L	KTK 209-L
60528	XL	2SK880-BL	2SK880
60529	XL	2SD1614-XL	2SD1614
60530	XLA	2SK1479-A	2SK1479
60531	XLB	2SK1479-B	2SK1479
60532	XM	RN 1611	RN 1611
60533	XM	RN 1711	RN 1711
60534	XM	RN 1911	RN 1911
60535	XM	RN 1511	RN 1511
60536	XM	RN 1411	RN 1411
60537	XM	RN 1111	RN 1111
60538	XM	RN 1311	RN 1311
60539	XM	2SD1614-XM	2SD1614
60540	XM-	2SC4591	2SC4591
60541	XM-	2SC4593	2SC4593
60542	XN	2SD1784	2SD1784
60543	XN-	2SC4592	2SC4592
60544	XN1101	UN 5101	-
60545	XN1110..1119	UN 1110..1119	-
60546	XN111F..M	UN 211..	-
60547	XN1201	UN 5201	-
60548	XN1210..1217	UN 1210..1217	-
60549	XN121F..M	UN 221..	-
60550	XN1401	2SB709A, SMD,	-
60551	XN1501	2SD601A, SMD,	-
60552	XN1504	2SD1938, SMD,	-
60553	XN1507	2SD814, SMD,	-
60554	XN1509	2SC4561, SMD,	-
60555	XN1531	2SC3130, SMD,	-
60556	XN1601	2SB709A+2SD601A	-
60557	XN1871	2SK198	-
60558	XN1872	2SK621	-
60559	XN1A312	UN 1212 + UN 1112	-
60560	XN1B301	2SB709A + 2SD601A	-
60561	XN1C301	2SB709A + 2SD601A	-
60562	XN1D873	2SK1103, , 50V, 0,03A	-
60563	XN2210..2216	UN 1210..1216	-
60564	XN2401	2SB709A, SMD,	-
60565	XN2501	2SD601A, SMD,	-
60566	XN2531	2SC3130, SMD,	-
60567	XN4111..4116	UN 1111..1116	-
60568	XN4130	2SB970 + Rbe10kOhm, SMD,	-
60569	XN4210..4216	UN 1210..1216	-

60570	XN421F	UN 221..	-
60571	XN4311	UN 1211 + UN 1111	-
60572	XN4312	UN 1212 + UN 1112	-
60573	XN4314	UN 1214 + UN 1114	-
60574	XN4315	UN 1215 + UN 1115	-
60575	XN4316	UN 1216 + UN 1116	-
60576	XN4322	UN 1222 + UN 1122	-
60577	XN4381	UN 1223 + UN 1122	-
60578	XN4401	2SB709A, SMD,	-
60579	XN4402	2SB710A, SMD,	-
60580	XN4404	2SB970, SMD,	-
60581	XN4482	2SB709A + 2SB710A, SMD	-
60582	XN4501	2SD601A, SMD,	-
60583	XN4502	2SD602A, SMD,	-
60584	XN4503	2SD813, SMD,	-
60585	XN4504	2SD1328, SMD,	-
60586	XN4505	2SD601A + 2SD1328, SMD	-
60587	XN4506	2SD1915, SMD,	-
60588	XN4509	2SC4561, SMD,	-
60589	XN4556	2SD1149, SMD,	-
60590	XN4601	2SD601A + 2SB709A, SMD	-
60591	XN4604	2SD1328 + 2SB970, SMD	-
60592	XN4608	2SD601A + 2SB970, SMD	-
60593	XN4609	2SD1328 + 2SB709A, SMD	-
60594	XN5501	2SD601A, SMD,	-
60595	XN5531	2SC3130, SMD,	-
60596	XN5553	2SD1149, SMD,	-
60597	XN5601	2SB709A + 2SD601A, SMD	-
60598	XN6111..6116	UN 1111..1116	-
60599	XN611FH	UN 111F + UN 611H	-
60600	XN6211..6216	UN 1211..1216	-
60601	XN6401	2SB709A, SMD,	-
60602	XN6435	2SA1022, SMD,	-
60603	XN6501	2SD601A, SMD,	-
60604	XN6534	2SC2404, SMD,	-
60605	XN6537	2SC3110, SMD,	-
60606	XN6542	2SC2480 + 2SC4444, SMD	-
60607	XN6543	2SC3904, SMD,	-
60608	XN6A554	2SC3757	-
60609	XN7651	2SD1328 + 2SB970, SMD	-
60610	XN8081	2SK1103 + UN 1213, SMD	-
60611	XO	KTK 209-O	KTK 209-O
60612	XO	2SK209-O	2SK209
60613	XP	2SD875-P	2SD875
60614	XP1101..2501	XN 1101..2501	-



60615	XP1B301	XN 1B301	-
60616	XP1C301	XN 1C301	-
60617	XP1D873	2SK1103, , 50V, 0,03A	-
60618	XP1D874	2SK1842	-
60619	XP4111..4601	XN 4111..4601	-
60620	XP4654	2SC3757 + 2SA1738, SMD	-
60621	XP4683	2SC2404 + 2SB709A, SMD	-
60622	XP5501..8081	XN 5501..9081	-
60623	XQ	2SD602A-Q	2SD602A
60624	XQ	2PD602AQ	2PD602A
60625	XQ	2SD1820A-Q	2SD1820A
60626	XQ	2SD875-Q	2SD875
60627	XR	3SK239A	3SK239A
60628	XR	2SD602A-R	2SD602A
60629	XR	2PD602AR	2PD602A
60630	XR	2SD1820A-R	2SD1820A
60631	XR	2SD875-R	2SD875
60632	XR-	3SK228	3SK228
60633	XS	2PD602AS	2PD602A
60634	XS	2SD602A-S	2SD602A
60635	XS	2SD1820A-S	2SD1820A
60636	XS	SM 4T 200C	SM 4T...
60637	XS	2SD875-S	2SD875
60638	XS-	3SK229	3SK229
60639	XT	SM 4T 200CA	SM 4T...
60640	XT-	2SC4674	2SC4674
60641	XU-	2SC4680	2SC4680
60642	XV-	3SK309	3SK309
60643	XV-	2SC4702	2SC4702
60644	XW-	3SK238	3SK238
60645	XW-	3SK233	3SK233
60646	XX-	3SK236	3SK236
60647	XX-	3SK234	3SK234
60648	XXA	RN 1961	RN 1961
60649	XXB	RN 1962	RN 1962
60650	XXC	RN 1963	RN 1963
60651	XXD	RN 1964	RN 1964
60652	XXE	RN 1965	RN 1965
60653	XXF	RN 1966	RN 1966
60654	XXH	RN 1967	RN 1967
60655	XXI	RN 1968	RN 1968
60656	XXJ	RN 1969	RN 1969
60657	XXK	RN 1970	RN 1970
60658	XXM	RN 1971	RN 1971
60659	XY	2SK2145-Y	2SK2145

60660	XY	2SK209-Y	2SK209
60661	XY	2SD1851	2SD1851
60662	XY	KTK 209-Y	KTK 209-Y
60663	XY	2SK880-Y	2SK880
60664	XY-	3SK237	3SK237
60665	XY-	3SK235	3SK235
60666	Y	HRU 0203A	HRU 0203A
60667	Y1	BZX 84/C11	BZX 84/C11
60668	Y1	BZX 88/C11	BZX 88/C11
60669	Y1	BZV 49/C11	BZV 49/C11
60670	Y10	BZX 84/C27	BZX 84/C27
60671	Y11	BZX 84/C30	BZX 84/C30
60672	Y12	BZX 84/C33	BZX 84/C33
60673	Y12	2SA1464-Y12	2SA1464
60674	Y12	2SA1608-Y12	2SA1608
60675	Y13	2SA1464-Y13	2SA1464
60676	Y13	BZX 84/C36	BZX 84/C36
60677	Y13	2SA1608-Y13	2SA1608
60678	Y14	BZX 84/C39	BZX 84/C39
60679	Y14	2SA1464-Y14	2SA1464
60680	Y14	2SA1608-Y14	2SA1608
60681	Y15	BZX 84/C43	BZX 84/C43
60682	Y15	NTM 2907A	NTM 2907A
60683	Y16	BZX 84/C47	BZX 84/C47
60684	Y17	BZX 84/C51	BZX 84/C51
60685	Y18	BZX 84/C56	BZX 84/C56
60686	Y19	BZX 84/C62	BZX 84/C62
60687	Y2	BZX 84/C12	BZX 84/C12
60688	Y2	BZX 88/C12	BZX 88/C12
60689	Y2	BZV 49/C12	BZV 49/C12
60690	Y20	BZX 84/C68	BZX 84/C68
60691	Y21	BZX 84/C75	BZX 84/C75
60692	Y22	2SA1461-Y22	2SA1461
60693	Y23	2SA1461-Y23	2SA1461
60694	Y24	2SA1461-Y24	2SA1461
60695	Y25	NTM 3906	NTM 3906
60696	Y3	BZX 84/C13	BZX 84/C13
60697	Y3	BZX 88/C13	BZX 88/C13
60698	Y3	BZV 49/C13	BZV 49/C13
60699	Y33	2SA1462-Y33	2SA1462
60700	Y33	2SA1610-Y33	2SA1610
60701	Y34	2SA1462-Y34	2SA1462
60702	Y34	2SA1610-Y34	2SA1610
60703	Y4	BZX 84/C15	BZX 84/C15
60704	Y4	BZX 88/C15	BZX 88/C15

60705	Y4	BZV 49/C15	BZV 49/C15
60706	Y5	BZX 84/C16	BZX 84/C16
60707	Y5	BZX 88/C16	BZX 88/C16
60708	Y5	BZV 49/C16	BZV 49/C16
60709	Y6	BZX 84/C18	BZX 84/C18
60710	Y6	BZX 88/C18	BZX 88/C18
60711	Y6	BZV 49/C18	BZV 49/C18
60712	Y7	BZX 84/C20	BZX 84/C20
60713	Y7	BZX 88/C20	BZX 88/C20
60714	Y7	BZV 49/C20	BZV 49/C20
60715	Y8	BZX 84/C22	BZX 84/C22
60716	Y8	BZX 88/C22	BZX 88/C22
60717	Y8	BZV 49/C22	BZV 49/C22
60718	Y9	BZX 84/C24	BZX 84/C24
60719	Y9	BZX 88/C24	BZX 88/C24
60720	Y9	BZV 49/C24	BZV 49/C24
60721	YA	RN 2901	RN 2901
60722	YA	RN 2601	RN 2601
60723	YA	RN 2701	RN 2701
60724	YA	RN 2501	RN 2501
60725	YA	RN 2101	RN 2101
60726	YA	RN 2401	RN 2401
60727	YA	BCW 61RA	BCW 61R
60728	YA	RN 2301	RN 2301
60729	YA	RN 6001	RN 6001
60730	YA-	2SC4791	2SC4791
60731	YA-	2SC5137	2SC5137
60732	YA-	2SC5049	2SC5049
60733	YA-	2SC4784	2SC4784
60734	YB	RN 2902	RN 2902
60735	YB	RN 2502	RN 2502
60736	YB	RN 2702	RN 2702
60737	YB	RN 2602	RN 2602
60738	YB	BCW 61RB	BCW 61R
60739	YB	RN 2402	RN 2402
60740	YB	RN 2102	RN 2102
60741	YB	RN 2302	RN 2302
60742	YB	RN 6002	RN 6002
60743	YC	RN 2703	RN 2703
60744	YC	RN 2503	RN 2503
60745	YC	RN 2903	RN 2903
60746	YC	2SC5078	2SC5078
60747	YC	RN 2603	RN 2603
60748	YC	2SC5079	2SC5079
60749	YC	2SK197-C	2SK197

60750	YC	BCW 61RC	BCW 61R
60751	YC	RN 2403	RN 2403
60752	YC	RN 2103	RN 2103
60753	YC	RN 2303	RN 2303
60754	YC	RN 6003	RN 6003
60755	YD	RN 2604	RN 2604
60756	YD	RN 2504	RN 2504
60757	YD	RN 2904	RN 2904
60758	YD	RN 2704	RN 2704
60759	YD	RN 2104	RN 2104
60760	YD	2SK197-D	2SK197
60761	YD	RN 2404	RN 2404
60762	YD	BCW 61RD	BCW 61RD
60763	YD	RN 2304	RN 2304
60764	YD-	2SC4995	2SC4995
60765	YD-	2SC4926	2SC4926
60766	YE	RN 2605	RN 2605
60767	YE	RN 2905	RN 2905
60768	YE	RN 2505	RN 2505
60769	YE	RN 2705	RN 2705
60770	YE	RN 2405	RN 2405
60771	YE	2SK197-E	2SK197
60772	YE	RN 2105	RN 2105
60773	YE	RN 2305	RN 2305
60774	YE	2SC3728-E	2SC3728
60775	YF	RN 2706	RN 2706
60776	YF	RN 2606	RN 2606
60777	YF	RN 2906	RN 2906
60778	YF	RN 2506	RN 2506
60779	YF	RN 2106	RN 2106
60780	YF	RN 2406	RN 2406
60781	YF	RN 2306	RN 2306
60782	YF	2SC3728-F	2SC3728
60783	YF	RN 6006	RN 6006
60784	YFB	2SC4932-B	2SC4932
60785	YFC	2SC4932-C	2SC4932
60786	YFD	2SC4932-D	2SC4932
60787	YG	BCX 71RG	BCX 71R
60788	YG	2SK210-GR	2SK210
60789	YG	2SC3728-G	2SC3728
60790	YH	RN 2507	RN 2507
60791	YH	RN 2707	RN 2707
60792	YH	RN 2607	RN 2607
60793	YH	RN 2907	RN 2907
60794	YH	BCX 71RH	BCX 71R

60795	YH	RN 2107	RN 2107
60796	YH	RN 2407	RN 2407
60797	YH	RN 2307	RN 2307
60798	YH-	2SC5140	2SC5140
60799	YH-	2SC4899	2SC4899
60800	YI	RN 2608	RN 2608
60801	YI	RN 2908	RN 2908
60802	YI	RN 2508	RN 2508
60803	YI	RN 2708	RN 2708
60804	YI	RN 2408	RN 2408
60805	YI	RN 2108	RN 2108
60806	YI	RN 2308	RN 2308
60807	YI-	2SA1666	2SA1666
60808	YJ	RN 2909	RN 2909
60809	YJ	RN 2609	RN 2609
60810	YJ	RN 2509	RN 2509
60811	YJ	RN 2709	RN 2709
60812	YJ	BCX 71RJ	BCX 71R
60813	YJ	RN 2109	RN 2109
60814	YJ	RN 2409	RN 2409
60815	YJ	RN 2309	RN 2309
60816	YJ-	2SC4900	2SC4900
60817	YK	RN 2510	RN 2510
60818	YK	RN 2610	RN 2610
60819	YK	RN 2710	RN 2710
60820	YK	RN 2910	RN 2910
60821	YK	BCX 71RK	BCX 71R
60822	YK	RN 2410	RN 2410
60823	YK	RN 2110	RN 2110
60824	YK	RN 2310	RN 2310
60825	YK	2SB1115-YK	2SB1115
60826	YK-	2SC5218	2SC5218
60827	YK-	2SC4901	2SC4901
60828	YL	2SK210-BL	2SK210
60829	YL	2SA1607	2SA1607
60830	YL	2SA1685	2SA1685
60831	YL	2SB1115-YL	2SB1115
60832	YL-	2SC5138	2SC5138
60833	YL-	2SC4902	2SC4902
60834	YL-	2SC4903	2SC4903
60835	YM	RN 2511	RN 2511
60836	YM	RN 2711	RN 2711
60837	YM	RN 2911	RN 2911
60838	YM	RN 2611	RN 2611
60839	YM	RN 2111	RN 2111

60840	YM	RN 2411	RN 2411
60841	YM	RN 2311	RN 2311
60842	YM	2SB1115-YM	2SB1115
60843	YM-	2SC4904	2SC4904
60844	YM-	2SC4905	2SC4905
60845	YN-	2SC5141	2SC5141
60846	YN-	2SC4906	2SC4906
60847	YP	2SD1484K-P	2SD1484K
60848	YP	2SD1949K-P	2SD1949K
60849	YP	2SB1115A-YP	2SB1115A
60850	YQ	2SD2216-Q	2SD2216
60851	YQ	2SD1484K-Q	2SD1484K
60852	YQ	2PD601Q	2PD601
60853	YQ	2SD601-Q	2SD601
60854	YQ	2SD1949K-Q	2SD1949K
60855	YQ	2SD874A-Q	2SD874A
60856	YQ	2SB1115A-YQ	2SB1115A
60857	YQB	2SA1867-B	2SA1867
60858	YQC	2SA1867-C	2SA1867
60859	YQD	2SA1867-D	2SA1867
60860	YR	2SD2216-R	2SD2216
60861	YR	2SD601-R	2SD601
60862	YR	2SD1484K-R	2SD1484K
60863	YR	2PD601R	2PD601
60864	YR	2SD1949K-R	2SD1949K
60865	YR	2SD874A-R	2SD874A
60866	YR-	2SC4992	2SC4992
60867	YR-	2SC4991	2SC4991
60868	YS	2SD2216-S	2SD2216
60869	YS	2SD601-S	2SD601
60870	YS	2PD601S	2PD601
60871	YS	2SD874A-S	2SD874A
60872	YS-	2SC4993	2SC4993
60873	YS-	2SC4994	2SC4994
60874	YTS2221(A)	2N2221(A), SMD	MMBT 2221(A)
60875	YTS2222(A)	2N2222(A), SMD	MMBT 2222(A)
60876	YTS2906(A)	2N2906(A), SMD	MMBT 2906(A)
60877	YTS2907(A)	2N2907(A), SMD	MMBT 2907(A)
60878	YTS3903	2N3903, SMD	MMBT 3903
60879	YTS3904	2N3904, SMD	MMBT 3904
60880	YTS3905	2N3905, SMD	MMBT 3905
60881	YTS3906	2N3906, SMD	MMBT 3906
60882	YTS4123	2N4123, SMD	MMBT 4123
60883	YTS4124	2N4124, SMD	MMBT 4124
60884	YTS4125	2N4125, SMD	MMBT 4125



60885	YTS4126	2N4126, SMD	MMBT 4126
60886	YTS4400	2N4400, SMD	MMBT 4400
60887	YTS4401	2N4401, SMD	MMBT 4401
60888	YTS4402	2N4402, SMD	MMBT 4402
60889	YTS4403	2N4403, SMD	MMBT 4403
60890	YV	MMBTA 92	MMBTA 92
60891	YV-	2SC4964	2SC4964
60892	YV-	2SC4965	2SC4965
60893	YW	MMBTA 93	MMBTA 93
60894	YW-	2SC4966	2SC4966
60895	YW-	2SC4967	2SC4967
60896	YY	2SC4104	2SC4104
60897	YY	2SK210-Y	2SK210
60898	YY-	2SK2113	2SK2113
60899	YYA	RN 2961	RN 2961
60900	YYB	RN 2962	RN 2962
60901	YYC	RN 2963	RN 2963
60902	YYD	RN 2964	RN 2964
60903	YYE	RN 2965	RN 2965
60904	YYF	RN 2966	RN 2966
60905	YYH	RN 2967	RN 2967
60906	YYI	RN 2968	RN 2968
60907	YYJ	RN 2969	RN 2969
60908	YYK	RN 2970	RN 2970
60909	YYM	RN 2971	RN 2971
60910	YZ-	2SC5139	2SC5139
60911	YZ-	2SC5050	2SC5050
60912	YZ-	2SC5051	2SC5051
60913	Z	HRU 0302A	HRU 0302A
60914	Z0	SST 310	SST 310
60915	Z0101BA	<3/10mA	-
60916	Z0101BB..0101NB	Z 0101BA..0101NA	-
60917	Z0101DA	Z 0101BA, 400V	-
60918	Z0101MA	Z 0101BA, 600V	-
60919	Z0101NA	Z 0101BA, 800V	-
60920	A	<5/10mA	-
60921	Z0104BB..0104NB	<5/10mA	-
60922	A	<10/10mA	-
60923	Z0106BB..0106NB	<10/10mA	-
60924	Z02W4.3..24	4,3...24V, 0,2W	BZX 84/..., HZM ..., RD ...M
60925	Z0302BG	Igt/Ih<3/3mA	TAG 207-...
60926	Z0302DG	Z 0302BG, 400V	TAG 207-...
60927	Z0302MG	Z 0302BG, 600V	TAG 207-...
60928	G	<5/5mA	TAG 204A-..., TAG 205-...
60929	G	<10/10mA	TAG 203A-..., TAG 203-..., TAG 209-...

60930	G	<25/25mA	TAG 208-...
60931	Z0402BE	Igt/Ih<3/<10mA	-
60932	Z0402BF..0402NF	Z 0402BE..0402NE	-
60933	Z0402DE	Z 0402 BE, 400V	-
60934	Z0402ME	Z 0402 BE, 600V	-
60935	Z0402NE	Z 0402 BE, 800V	-
60936	Z0405BE	200V, 4A(Tc75°), Igt/Ih<5/5mA	TXC 18D40, TAG 233-200, TAG 222-200
60937	Z0405BF..0405NF	Z 0405BE..0405NE	TXC 18D..., TAG 233-..., TAG 222-...
60938	Z0405DE	Z 0405BE, 400V	TXC 18D40, TAG 233-400, TAG 222-400
60939	Z0405ME	Z 0405BE, 600V	TXC 18D60, TAG 233-600, TAG 222-600
60940	Z0405NE	Z 0405BE, 800V	TXC 18D80, TAG 233-800, TAG 222-800
60941	Z0409BE	Igt/Ih<10/10mA	TXC 18G40, TAG 232-200, TAG 221-200
60942	Z0409BF..0409NF	Z 0409BE..0409NE	TXC 18G..., TAG 232-..., TAG 221-...
60943	Z0409DE	Z 0409BE, 400V	TXC 18G40, TAG 232-400, TAG 221-400
60944	Z0409ME	Z 0409BE, 600V	TXC 18G60, TAG 232-600, TAG 221-600
60945	Z0409NE	Z 0409BE, 800V	TXC 18G80, TAG 232-800, TAG 221-800
60946	Z0410BE	Igt/Ih<25/25mA	TAG231-200, TAG220-200, TAG225-200
60947	Z0410BF..0410NF	Z 0410BE..0410NE	TAG 231-..., TAG 220-..., TAG 225-...
60948	Z0410DE	Z 0410BE, 400V	TAG231-400, TAG220-400, TAG225-400
60949	Z0410ME	Z 0410BE, 600V	TAG231-600, TAG220-600, TAG225-600
60950	Z0410NE	Z 0410BE, 800V	TAG231-800, TAG220-800, TAG225-800
60951	Z1	BZX 84/C4V7	BZX 84/C4V7
60952	Z1	BZX 88/C4V7	BZX 88/C4V7
60953	Z1	BZV 49/C4V7	BZV 49/C4V7
60954	Z11	BZX 84/C2V4	BZX 84/C2V4
60955	Z12	BZX 84/C2V7	BZX 84/C2V7
60956	Z13	BZX 84/C3V0	BZX 84/C3V0
60957	Z14	BZX 84/C3V3	BZX 84/C3V3
60958	Z15	BZX 84/C3V6	BZX 84/C3V6
60959	Z16	BZX 84/C3V9	BZX 84/C3V9
60960	Z17	BZX 84/C4V3	BZX 84/C4V3
60961	Z1SMB-6V8..-200	BZY 97/C6V8../C200, SMD, 1W	BZG 03/..., MA 1Z ..., PTZ ..., RD ...FM
60962	Z2	BZX 84/C5V1	BZX 84/C5V1
60963	Z2	BZX 88/C5V1	BZX 88/C5V1
60964	Z2	BZV 49/C5V1	BZV 49/C5V1
60965	Z3	BZX 84/C5V6	BZX 84/C5V6
60966	Z3	BZX 88/C5V6	BZX 88/C5V6
60967	Z3	BZV 49/C5V6	BZV 49/C5V6
60968	Z3	2SK1078	2SK1078
60969	Z4	BZX 84/C6V2	BZX 84/C6V2
60970	Z4	BZX 88/C6V2	BZX 88/C6V2
60971	Z4	BZV 49/C6V2	BZV 49/C6V2
60972	Z4	2SK1079	2SK1079
60973	Z5	BZX 84/C6V8	BZX 84/C6V8
60974	Z5	BZX 88/C6V8	BZX 88/C6V8

60975	Z5	BZV 49/C6V8	BZV 49/C6V8
60976	Z5	2SK1717	2SK1717
60977	Z6	BZX 84/C7V5	BZX 84/C7V5
60978	Z6	BZX 88/C7V5	BZX 88/C7V5
60979	Z6	2SJ238	2SJ238
60980	Z6	BZV 49/C7V5	BZV 49/C7V5
60981	Z7	BZX 84/C8V2	BZX 84/C8V2
60982	Z7	BZX 88/C8V2	BZX 88/C8V2
60983	Z7	BZV 49/C8V2	BZV 49/C8V2
60984	Z7	2SK2549	2SK2549
60985	Z8	BZX 84/C9V1	BZX 84/C9V1
60986	Z8	SST 308	SST 308
60987	Z8	BZX 88/C9V1	BZX 88/C9V1
60988	Z8	2SJ360	2SJ360
60989	Z8	BZV 49/C9V1	BZV 49/C9V1
60990	Z9	SST 309	SST 309
60991	Z9	BZX 84/C10	BZX 84/C10
60992	Z9	BZX 88/C10	BZX 88/C10
60993	Z9	BZV 49/C10	BZV 49/C10
60994	Z9	2SJ465	2SJ465
60995	ZA	BCW 60RA	BCW 60RA
60996	ZA	2N3906S	2N3906S
60997	ZA	2SK2615	2SK2615
60998	ZB	KTN2222S	KTN 2222S
60999	ZB	BCW 60RB	BCW 60RB
61000	ZB1-6...-100	6..100V, 1W	BZW22/..., BZX61/..., ZPY..., 1N5920...49
61001	ZC	KST 4124	KST 4124
61002	ZC	YTS 4124	YTS 4124
61003	ZC	2N3904S	2N3904S
61004	ZC	2SK217-C	2SK217
61005	ZC	BCW 60RC	BCW 60RC
61006	ZC	FMMT4124	FMMT4124
61007	ZC	MMBT4124	MMBT4124
61008	ZC-	2SC5078	2SC5078
61009	ZC-	2SC5079	2SC5079
61010	ZC-	2SC5246	2SC5246
61011	ZD	FMMT4125	FMMT4125
61012	ZD	YTS 4125	YTS 4125
61013	ZD	2SK217-D	2SK217
61014	ZD	KST 4125	KST 4125
61015	ZD	KTN2907S	KTN 2907S
61016	ZD	MMBT 4125	MMBT 4125
61017	ZD	BCW 60RD	BCW 60RD
61018	ZD-	2SC5081	2SC5081
61019	ZD-	2SC5080	2SC5080

61020	ZD-	2SC5247	2SC5247
61021	ZD3,9...200	3,9..200V, 5%, 1,32W	BZW22/..., BZX61/..., ZPY..., 1N5915...59
61022	ZDD	SM 5Z 3V3A	SM 5Z...
61023	ZDE	SM 5Z 3V6A	SM 5Z...
61024	ZDF	SM 5Z 3V9A	SM 5Z...
61025	ZDG	SM 5Z 4V3A	SM 5Z...
61026	ZDH	SM 5Z 4V7A	SM 5Z...
61027	ZDK	SM 5Z 5V1A	SM 5Z...
61028	ZDL	SM 5Z 5V6A	SM 5Z...
61029	ZDN	SM 5Z 6V2A	SM 5Z...
61030	ZDP	SM 5Z 6V8A	SM 5Z...
61031	ZDQ	SM 5Z 7V5A	SM 5Z...
61032	ZDR	SM 5Z 8V2A	SM 5Z...
61033	ZDT	SM 5Z 9V1A	SM 5Z...
61034	ZDU	SM 5Z 10A	SM 5Z...
61035	ZDW	SM 5Z 12A	SM 5Z...
61036	ZDX	SM 5Z 13A	SM 5Z...
61037	ZDY	SM 5Z 14A	SM 5Z...
61038	ZDZ	SM 5Z 15A	SM 5Z...
61039	ZE	2SK217-E	2SK217
61040	ZE-	2SK2373	2SK2373
61041	ZE1,5	1,35..1,55V(5mA)	BZ102/1V4, BZX75/C1V4
61042	ZE2	1,9..2,2V(5mA)	BZ102/2V1, BZX75/C2V1
61043	ZED	SM 5Z 16A	SM 5Z...
61044	ZEF	SM 5Z 18A	SM 5Z...
61045	ZEH	SM 5Z 20A	SM 5Z...
61046	ZEK	SM 5Z 22A	SM 5Z...
61047	ZEL	SM 5Z 24A	SM 5Z...
61048	ZEN	SM 5Z 27A	SM 5Z...
61049	ZEP	SM 5Z 28A	SM 5Z...
61050	ZEQ	SM 5Z 30A	SM 5Z...
61051	ZER	SM 5Z 33A	SM 5Z...
61052	ZET	SM 5Z 39A	SM 5Z...
61053	ZEV	SM 5Z 47A	SM 5Z...
61054	ZF	MMBT 4126	MMBT 4126
61055	ZF-	2SJ399	2SJ399
61056	ZF110..191[Japan]	10...91V, 0,75W	BZW22/..., BZX61/..., ZPY, 1N4740...64...
61057	ZF2,7...33[ITT]	2,7..33V, 5%, 0,4W	BZX55/..., BZX83/..., ZPD..., 1N5223...57
61058	ZF210..291[Japan]	10..91V, 0,25W	BZX55/..., BZX83/..., ZPD..., 1N5240...70
61059	ZFD	SM 5Z 62A	SM 5Z...
61060	ZFG	SM 5Z 82A	SM 5Z...
61061	ZFK	SM 5Z 91A	SM 5Z...
61062	ZFL	SM 5Z 100A	SM 5Z...
61063	ZFM	SM 5Z 110A	SM 5Z...
61064	ZFR	SM 5Z 150A	SM 5Z...

61065	ZFS	SM 5Z 160A	SM 5Z...
61066	ZFU	SM 5Z 180A	SM 5Z...
61067	ZFW	SM 5Z 200A	SM 5Z...
61068	ZG	BCX 70RG	BCX 70RG
61069	ZG	KTN2222AS	KTN 2222AS
61070	ZG-	3SK276	3SK276
61071	ZG1	0,65..0,75V(5mA), 0,4W	BA 315, BZ102/0V7, BZX55/0V8, ZPD 1
61072	ZG2,7...33	ZF 2,7..33, 10%	ZF 2,7...33
61073	ZH	KTN2907AS	KTN 2907AS
61074	ZH	BCX 70RH	BCX 70RH
61075	ZH-	3SK288	3SK288
61076	ZI	KTN2369S	KTN 2369S
61077	ZI-	2SC4366	2SC4366
61078	ZJ	BCX 70RJ	BCX 70RJ
61079	ZJ-	3SK290	3SK290
61080	ZK	BCX 70RK	BCX 70RK
61081	ZK	KTN2369AS	KTN 2369AS
61082	ZK	2SB1114-ZK	2SB1114
61083	ZK-	2SJ451	2SJ451
61084	ZL	HN 3G01J	HN 3G01J
61085	ZL	2SA1653	2SC4104
61086	ZL	2SB1114-ZL	2SB1114
61087	ZL-	2SK2570	2SK2570
61088	ZL1	12,5W(Tc25°)	-
61089	ZL3,9...180	ZX 3,9..180, 10%	ZX 3,9...180
61090	ZM	2SB1114-ZM	2SB1114
61091	ZM-	2SJ452	2SJ452
61092	ZM3,9...180	ZD 3,9..180, 10%	ZD 3,9...180
61093	ZMM1..51	ZPD 1..51, SMD, 0,5W	BZD 27/..., BZV 55/..., RLZ ...(J)
61094	ZMM746..759	1N746..759, SMD	BZD 27/..., BZV 55/..., RLZ ...(J)
61095	ZMU100..180	ZPU 100..180, SMD	BZD 27/...
61096	ZMY1..100	ZPY 1..100, SMD	BZD 27/..., BZV 55/..., RLZ ...(J)
61097	ZN-	2SK2569	2SK2569
61098	ZO	2SA1182-O	2SA1182
61099	ZO	2SA1588-O	2SA1588
61100	ZP	2SB1301-ZP	2SB1301
61101	ZP-	3SK297	3SK297
61102	ZP-	3SK298	3SK298
61103	ZP2,7...33	ZF 2,7..33	ZF 2,7...33
61104	ZPD1	0,7..0,8(5mA), 0,5W	BZ102/0V7, BZW22/C1, BZX83/C0V8, ZPY 1
61105	ZPD2,7...51	2,7..51V, 5%, 0,5W	BZX55/..., BZX83/..., BZX97/..., 1N5223...62
61106	ZPE1,5	1,4..1,6V(5mA)	BZ102/1V4, BZX75/C1V4, ZTE1,5
61107	ZPU100...220	100..220V, 10%, 1,3W	BZW22/..., BZX61/..., ZPY..., 1N5949...56
61108	ZPY1	0,65..0,75V(5mA), 1,3W	BZW22/C1, ZY 1
61109	ZPY3,9...200	3,9..200V, 5%, 1,3W	BZW22/..., BZX61/..., ZD..., 2N5915...56

61110	ZQ	2SD2496-Q	2SD2496
61111	ZQ	2PD601AQ	2PD601A
61112	ZQ	2SD601A-Q	2SD601A
61113	ZQ	2PC4081Q	2PC4081
61114	ZQ	2SD1819A-Q	2SD1819A
61115	ZQ	2SB1301-ZQ	2SB1301
61116	ZQ	2SD874-Q	2SD874
61117	ZQ-	3SK295	3SK295
61118	ZQ-	3SK296	3SK296
61119	ZR	2SD2496-R	2SD2496
61120	ZR	2SD601A-R	2SD601A
61121	ZR	2PD601AR	2PD601A
61122	ZR	2PC4081R	2PC4081
61123	ZR	2SD1819A-R	2SD1819A
61124	ZR	2SB1301-ZR	2SB1301
61125	ZR	2SD874-R	2SD874
61126	ZR-	3SK300	3SK300
61127	ZS	2SD2496-S	2SD2496
61128	ZS	2SD601A-S	2SD601A
61129	ZS	2PD601AS	2PD601A
61130	ZS	2SD1819A-S	2SD1819A
61131	ZS	2PC4081S	2PC4081
61132	ZS	2SD874-S	2SD874
61133	ZT-	2SK2685	2SK2685
61134	ZT110	25V, 0,5A, <80/300ns, B>38	BSV 59, BSX 49, 2N2221...2222(A)
61135	ZT111	ZT 110, 45V	BSV 59, BSX 49, 2N2221...2222(A)
61136	ZT112	ZT 110, 45V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61137	ZT113	ZT 110, 60V	BSV 59, BSX 49, 2N2221...2222(A)
61138	ZT114	ZT 110, 60V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61139	ZT116	ZT 110, 100V	BC 639, BCX 22, BCX 24, BSS 59
61140	ZT117	ZT 80, 25V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61141	ZT118	ZT 110, 100V, B>75	BC 639, BCX 22, BCX 24, BSS 59
61142	ZT119	ZT 110, 70V, B>75	BC 639, BCX 22, BCX 24, BSS 59
61143	ZT131	75V, 0,05A, 0,3W, 110MHz	BC 546, 2SC1890(A), 2SC2363, 2SD755
61144	ZT132	ZT 131, 100V	BSS 38, 2SC1890(A), 2SC2363, 2SD755
61145	ZT1487...1490	2N1487..1490	
61146	ZT1511...1514	2N1511..1514	
61147	ZT152	20V, 0,5A, 0,3W, >30MHz	BC 327...328, BC 636, BC 638, BC 640
61148	ZT153	ZT 152, 35V	BC 327(A), BC 636, BC 638, BC 640
61149	ZT154	ZT 152, 45V	BC 327A, BC 636, BC 638, BC 640
61150	ZT1702	2N1702	
61151	ZT1703	2N1703	
61152	ZT180	25V, 0,5A, 120/250ns, B>38	BC 327...328, BSW 24, 2N2906...2907(A)
61153	ZT181	ZT 180, 45V	BC 327(A), BSW 24, 2N2906...2907(A)
61154	ZT182	ZT 180, 45V, B>75	BC 327(A), BSW 24, 2N2906...2907(A)



61155	ZT183	ZT 180, 45V	BC 327(A), BSW 24, 2N2906...2907(A)
61156	ZT184	ZT 180, 45V, B>75	BC 327(A), BSW 24, 2N2906...2907(A)
61157	ZT187	ZT 180, B>75	BC 327(A), BSW 24, 2N2906...2907(A)
61158	ZT189	ZT 180, 70V, B>75	BC 640, 2N4027, 2N4029, 2SB647
61159	ZT190	B>50	BC 238, BC 548, BSW 41, 2N2221...22(A)
61160	ZT191	ZT 190, B>35	BC 238, BC 548, BSW 41, 2N2221...22(A)
61161	ZT192	ZT 190, 40V, B>35	BC 237, BC 547, BSW 41, 2N2221...22(A)
61162	ZT193	ZT 190, 40V, B>75	BC 237, BC 547, BSW 41, 2N2221...22(A)
61163	ZT20	20V, 0,05A, <110/175ns, B>18	BSW 51...54, BSY 58, 2N2218...2219(A)
61164	ZT2015	2N2015	
61165	ZT2016	2N2016	
61166	ZT202	B>18	BC 168, BC 183, BC 238, BC 548
61167	ZT202P	ZT 202, 0,5A	BC 140...141, BC 300...302, 2N3053
61168	ZT203	ZT 202, B>38	BC 168, BC 183, BC 238, BC 548
61169	ZT203P	ZT 203, 0,5A	BC 140...141, BC 300...302, 2N3053
61170	ZT204	ZT 202, B>78	BC 168, BC 183, BC 238, BC 548
61171	ZT204P	ZT 204, 0,5A	BC 140...141, BC 300...302, 2N3053
61172	ZT21	ZT 20, B>38	BSW 51...54, BSY 58, 2N2218...2219(A)
61173	ZT210	60V, 1A, 1W, >60MHz	BC 161, BCX 60, BSV 17, 2N5322...23
61174	ZT211	ZT 210, 90V	BCX 60, BSS 17, BSV 17, 2N5322...23
61175	ZT22	ZT 20, 45V	BSW 51...54, BSY 58, 2N2218...2219(A)
61176	ZT2222	PZT 2222	PZT 2222
61177	ZT2222A	PZT 2222A	PZT 2222A
61178	ZT23	ZT 20, 45V, B>38	BSW 51...54, BSY 58, 2N2218...2219(A)
61179	ZT24	ZT 20, 45V, B>78	BSW 51...54, BSY 58, 2N2218...2219(A)
61180	ZT27	100V, 0,05A, 0,35W, >70MHz	BF 257, 2SC1890A, 2SC2363, 2SD755
61181	ZT2708	2N2708	
61182	ZT280	25V, 0,5A, 120/250ns, B>38	BC 327...328, BSW 24, 2N2906...2907(A)
61183	ZT281	ZT 280, 45V	BC 327(A), BSW 24, 2N2906...2907(A)
61184	ZT282	ZT 280, 45V, B>75	BC 327(A), BSW 24, 2N2906...2907(A)
61185	ZT283	ZT 280, 45V, B>38	BC 327(A), BSW 24, 2N2906...2907(A)
61186	ZT284	ZT 280, 45V, B>75	BC 327(A), BSW 24, 2N2906...2907(A)
61187	ZT2857	2N2857	
61188	ZT287	ZT 280, B>75	BC 327(A), BSW 24, 2N2906...2907(A)
61189	ZT2876	2N2876	
61190	ZT2887	2N2876	
61191	ZT289	ZT 280, 70V, B>75	BC 640, 2N4027, 2N4029, 2SB647
61192	ZT2907	PZT 2907	PZT 2907
61193	ZT2907A	PZT 2907A	PZT 2907A
61194	ZT3229	2N3229	
61195	ZT3375	2N3375	
61196	ZT3441	2N3441	
61197	ZT3442	2N3442	
61198	ZT3600	2N3600	
61199	ZT3904	PZT 3904	PZT 3904

61200	ZT3906	PZT 3906	PZT 3906
61201	ZT40	20V, 0,05A, <110/175ns, B>18	BSW 41, BSY 63, 2N2221...2222(A)
61202	ZT402	B>18	BC 168, BC 183, BC 238, BC 548
61203	ZT402P	ZT 402, 0,5A	BC 337...338, BC 635, BC 637, BC 639
61204	ZT403	ZT 402, B>38	BC 168, BC 183, BC 238, BC 548
61205	ZT403P	ZT 403, 0,5A	BC 337...338, BC 635, BC 637, BC 639
61206	ZT404	ZT 402, B>75	BC 168, BC 183, BC 238, BC 548
61207	ZT404P	ZT 404, 0,5A	BC 337...338, BC 635, BC 637, BC 639
61208	ZT41	ZT 40, B>38	BSW 41, BSY 63, 2N2221...2222(A)
61209	ZT42	ZT 40, 45V	BSW 41, BSY 63, 2N2221...2222(A)
61210	ZT43	ZT 40, 45V, B>38	BSW 41, BSY 63, 2N2221...2222(A)
61211	ZT44	ZT 40, 45V, B>78	BSW 41, BSY 63, 2N2221...2222(A)
61212	ZT50	20V, 120MHz	BD 135, BD 226, 2SC1398, 2SC3419
61213	ZT60	25V, 0,5A, <80/300ns, B>38	BC 140...141, BC 300...302, 2N2218...19(A)
61214	ZT600	24V, 1A, 0,8W, <60/60ns	BSS 27...29, BSV 69, 2N3724A, 2N5189
61215	ZT61	ZT 60, 45V	BC 140...141, BC 300...302, 2N2218...19(A)
61216	ZT62	ZT 60, 45V, B>75	BC 140...141, BC 300...302, 2N2218...19(A)
61217	ZT63	ZT 60, 60V, B>35	BC 140...141, BC 300...302, 2N2218...19(A)
61218	ZT64	ZT 60, 60V, B>75	BC 140...141, BC 300...302, 2N2218...19(A)
61219	ZT66	ZT 60, 100V, B>35	BC 141, BC 300, BSW 39, 2N1889...90
61220	ZT67	ZT 60, 100V, B>75	BC 141, BC 300, BSW 39, 2N1889...90
61221	ZT68	100V, 0,5A, 0,75W, <80/300ns	BC 141, BC 300, BSW 39, 2N1889...90
61222	ZT69	70V, 0,5A, 0,8W, >120MHz	BC 140...141, BC 300...301, 2N2218...19A
61223	ZT80	25V, 0,5A, <80/300ns, B>38	BSV 59, BSX 49, 2N2221...2222(A)
61224	ZT81	ZT 80, 45V	BSV 59, BSX 49, 2N2221...2222(A)
61225	ZT82	ZT 80, 45V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61226	ZT83	ZT 80, 60V	BSV 59, BSX 49, 2N2221...2222(A)
61227	ZT84	ZT 80, 60V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61228	ZT86	ZT 80, 100V	BC 639, BCX 22, BCX 24, BSS 59
61229	ZT87	ZT 80, 25V, B>75	BSV 59, BSX 49, 2N2221...2222(A)
61230	ZT88	ZT 80, 100V, B>75	BC 639, BCX 22, BCX 24, BSS 59
61231	ZT89	ZT 80, 70V, B>75	BC 639, BCX 22, BCX 24, BSS 59
61232	ZT90	60V, 1A, 1W, >60MHz, B>60	BC 140...141, BC 300...302, 2N1711
61233	ZT91	ZT 90, 120V, B>40	BC 300, BSS 42...43, BSX 47, 2N1893(A)
61234	ZT917	2N917	
61235	ZT918	2N918	
61236	ZT92	ZT 90, 120V, B>65	BC 300, BSS 42...43, BSX 47, 2N1893(A)
61237	ZT93	ZT 90, 120V, B>40	BC 300, BSS 42...43, BSX 47, 2N1893(A)
61238	ZT94	ZT 90, B>30	BC 140...141, BC 300...302, 2N1711
61239	ZT95	ZT 90, B>30	BC 140...141, BC 300...302, 2N1711
61240	ZTA96	PZTA 96	PZTA 96
61241	ZTE1,5	1,35..1,55V(5mA), 0,3W	BZ102/1V4, BZX75/C1V4
61242	ZTE2	2,0..2,3V(5mA), 0,3W	BZ102/2V1, BZX75/C2V1
61243	ZTE2,4	2,2..2,56V(5mA), 0,3W	-
61244	ZTE2,7	2,5..2,9V(5mA), 0,3W	-

61245	ZTE3,0	2,8..3,2V(5mA), 0,3W	-
61246	ZTE3,3	3,1..3,5V(5ma), 0,3W	-
61247	ZTE3,6	3,4..3,8V(5mA), 0,3W	-
61248	ZTE3,9	3,7..4,1V(5mA), 0,3W	-
61249	ZTE4,3	4,0..4,6V(5mA), 0,3W	-
61250	ZTE4,7	4,4..5,0V(5mA), 0,3W	-
61251	ZTE5,1	4,8..5,4V(5mA), 0,3W	-
61252	ZTU1	BUY 80	BUY 80
61253	ZTU2	BUY 81	BUY 81
61254	ZTU3	BUY 82	BUY 82
61255	ZTX107	BC 107	
61256	ZTX108	BC 108	
61257	ZTX109	BC 109	
61258	ZTX114	BC 114	
61259	ZTX167	BF 167	
61260	ZTX173	BF 173	
61261	ZTX187(AM)	-/50V, 0,1A, 0,3W, 350MHz	BC 174, BC 182, BC 190, BC 546
61262	ZTX189	-/5V, 0,2A, 0,3W	BC 168, BC 183, BC 238, BC 548
61263	ZTX196	BF 196	
61264	ZTX197	BF 197	
61265	ZTX212	BC 212	
61266	ZTX213	BC 213	
61267	ZTX214	BC 214	
61268	ZTX223	BC 223	
61269	ZTX237	BC 237	
61270	ZTX238	BC 238	
61271	ZTX239	BC 239	
61272	ZTX300	BCW 10	
61273	ZTX301	BCW 12	
61274	ZTX302	BCW 14	
61275	ZTX303	BCW 16	
61276	ZTX304	BCW 18	
61277	ZTX310	BSV 23	
61278	ZTX311	BSV 24	
61279	ZTX312	BSV 25	
61280	ZTX313	BSV 26	
61281	ZTX314	BSV 27	
61282	ZTX320	BFW 97	
61283	ZTX321	BFW 97	
61284	ZTX322	BFW 97	
61285	ZTX323	BFW 97	
61286	ZTX325	BFY 90	
61287	ZTX326	BFY 90	
61288	ZTX327	2N3866	
61289	ZTX330	BCW 20	

61290	ZTX331	BCW 22	
61291	ZTX337	BC 337	
61292	ZTX338	BC 338	
61293	ZTX341	BSV 28	
61294	ZTX342	BSV 29	
61295	ZTX350		-
61296	ZTX360	BSX 59	
61297	ZTX3702...3711	2N3702...3711	
61298	ZTX382	BC 382	
61299	ZTX383	BC 383	
61300	ZTX384	BC 384	
61301	ZTX3903...3906	2N3903..3906	
61302	ZTX4400...4403	2N4400..4403	
61303	ZTX449	50V, 1A, 1W, >150MHz	2SD1207, 2SD1582, 2SD1835, 2SD1616
61304	ZTX450	60V, 1A, 1W, >150MHz	BC 337A, BC 637, BC 639, 2SD1207
61305	ZTX451	ZTX 450, 80V	BC 639, 2N3700...01, 2SD667, 2SD1616A
61306	ZTX452	100V, 1A, 1W, >150MHz	BC 639, 2N3700...01, 2SD667, 2SD1616A
61307	ZTX453	ZTX 452, 120V	2N3700...01, 2SD667, 2SD1616A
61308	ZTX454	140V, 1A, 1W, >100MHz	2N3700...01, 2SC2383, 2SC3228, 2SD1812
61309	ZTX455	ZTX 454, 160V	2SC2383, 2SC3228, 2SD1812
61310	ZTX500	BCW 11	
61311	ZTX501	BCW 13	
61312	ZTX502	BCW 15	
61313	ZTX503	BCW 17	
61314	ZTX504	BCW 19	
61315	ZTX510	BSV 33	
61316	ZTX530	BCW 21	
61317	ZTX531	BCW 23	
61318	ZTX537	BC 327	
61319	ZTX538	BC 328	
61320	ZTX541	100V, 0,1A, 0,5W	BF 423, 2SA893A, 2SB715...716(A)
61321	ZTX542	ZTX 541, 120V	BF 423, 2SA893A, 2SA1019, 2SB716(A)
61322	ZTX549	35V, 1A, 1W, >100MHz	2SA1315, 2SB892, 2SB1229
61323	ZTX550	60V, 1A, 1W, >150MHz	BC 638, BC 640, 2SB647, 2SB1116(A)
61324	ZTX551	ZTX 550, 80V	BC 640, 2SB647, 2SA1013, 2SB1116A
61325	ZTX552	100V, 1A, 1W, >150MHz	BC 640, 2SB647, 2SB984, 2SA1013
61326	ZTX553	ZTX 552, 120V	2SA1013, 2SB647, 2SB984
61327	ZTX600(A,B)	160V, 1A, 1W, >150, B>2000	2SD1579, 2SD1659
61328	ZTX601(A,B)	ZTX 601, 180V	-
61329	ZTX649	35V, 2A, 1W, >150MHz	2SC4486, 2SD1207, 2SD1835, 2SD2177
61330	ZTX650	60V, 2A, 1W, >140MHz	2SC3328, 2SD1207, 2SD1835
61331	ZTX651	ZTX 650, 80V	2SC3328
61332	ZTX652	ZTX 650, 100V	-
61333	ZTX653	ZTX 650, 120V	-
61334	ZTX656	200V, 0,5A, 1W, >30MHz	BF 391...393, BF 420A, BF 422A, MPSA 43

61335	ZTX657	ZTX 656, 300V	BF 393, BF 420A, BFP 25, MPSA 42
61336	ZTX749	35V, 2A, 1W, >100MHz	2SA1315, 2SB892, 2SB1229
61337	ZTX750	60V, 2A, 1W, >100MHz	2SA1315, 2SB892, 2SB1229
61338	ZTX751	ZTX 750, 80V	2SA1315
61339	ZTX752	ZTX 750, 100V	-
61340	ZTX753	ZTX 750, 120V	-
61341	ZTX756	200V, 0,5A, 1A, >30MHz	BF 491...493, BF 421A, BF 423A, MPSA 93
61342	ZTX757	ZTX 756, 300V	BF 493, BF 421A, BFP 26, MPSA 92
61343	ZU-	2SJ486	2SJ486
61344	ZU3,9...180	ZY 3,9..180, 10%	ZY 3,9...180
61345	ZV-	2SK2802	2SK2802
61346	ZW2,7...33	ZF 2,7..33, 0,6W	ZF 2,7...33
61347	ZX	2SB1628-ZX	2SB1628
61348	ZX3,9...200	3,9..200V, 5%, 12,5W(Tc25°)	BZX98/..., BZY93/..., 1M2970...3015
61349	ZY	2SC4047	2SC4047
61350	ZY	2SA1182-Y	2SA1182
61351	ZY	2SA1588-Y	2SA1588
61352	ZY	2SB1628-ZY	2SB1628
61353	ZY1	0,71..0,82V(100mA), 2W	-
61354	ZY3,9...200	ZD 3,9..200, 2W	BZD23/..., BZV47/..., BZX70/...
61355	ZZ	2SB1628-ZZ	2SB1628