

Model: KP-53HS10, KP-61HS10**No.** 504**Subject:** Audio Dropout/Distortion Under Low AC
Conditions.**Date:** September 21, 2000**Symptom:**
(2511)

Audio mutes or distorts under low AC conditions

Solution: If the customer should complain of audio dropout please make the following circuit changes on the "K" Board.

1. Change the value of capacitor C2054 to 10uf/ 50v.
Note: It is possible to use a 16v, or 25v rated capacitor as a substitute.
2. Mount a 10uf/50-volt capacitor from the anode side of diode D2023 with the negative side of the cap to ground.

Ref	Description Former	Description New	Part Number
C2054	470UF/16v	10UF/50V	1-126-964-11
C1	Not Mounted	10UF/50V	1-126-964-11

K Board



