



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:	
310G-1	
Cone Kit:	C4R310G-1
Nom. Impedance:	4 Ohm
Dynamic Test Input V:	5
Sweep Frequency Hz:	30-1200
D.C. Resistance Ohms:	3.6 min/4.5 max
Gap Gauge:	.051"
Notes:	
If Not Serviceable, Replace With:	310G-3
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different.
Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Dome:	61521
Mounting Gasket:	60979
Trim Ring:	61384
MID RANGE DRIVER:	
305G-1	
Cone Kit:	C4R305G-1
Nom. Impedance:	4 Ohm
Dynamic Test Input V:	4
Sweep Frequency Hz:	75-3000
D.C. Resistance Ohms:	3.8 min/4.6 max
Gap Gauge:	.040"
Notes:	Remove Trim Ring
carefully. Replacement Trim Ring 61373-01 no longer available.	
If Not Serviceable, Replace With:	305G-2
visual Change:	res
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different.
Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Dome:	54721
HIGH FREQUENCY DRIVER:	
LE25-2	
Diaphragm Kit:	D8RLE252
Nom. Impedance:	8 Ohm
Dynamic Test Input V:	3
Sweep Frequency Hz:	500-1200

HIGH FREQUENCY DRIVER (Cont'd)

D.C. Resistance Ohms:	3.6 min/4.4 max
Gap Gauge:	.029"
Notes:	Kit includes parts for similar models. Use required parts only.
If Not Serviceable, Replace With:	035TiA
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No. Use as a last resort. Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Trim Ring:	53363
Mounting Gasket:	50949-01
Dome:	21606

PASSIVE RADIATOR:

PR310-1	
Cone Kit:	Kit not available.
Notes:	Defective unit should be replaced.
Replace With:	PR310-3
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Slightly different.
Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Mounting Gasket:	60979
Trim Ring:	61384

SYSTEM SPECIFICATIONS:

Nom. Impedance:	6 Ohm
Rec. Amp Power Range:	10-150 Watts Continuous Sine Wave Per Channel
Crossover Frequencies:	600 Hz, 3000 Hz
Sensitivity:	91dB (1 Watt @ 1 Meter)
Enclosure Dim:	37-3/4" x 16-1/4" x 12-3/4" D 959mm x 413mm x 324mm
Shipping Weight:	57-1/2 lbs. - 26.2 kg.
Additional Parts Currently Available*:	
Binding Posts:	Red: 56131 Black: 56130

*Other parts may also be available. Check with JBL for details.